

Camera Mount Adapters for the Logitech Adaptive Gaming Kit

3D PRINTING GUIDE

3D Printing Summary

Metrics	Entire Set
Total Print Time (min)	9:54
Total Number of Components	12
Typical Total Mass (g)	10
Typical Number of Print Setups	4

3D Printing Settings

Print File Name	Qty	Individual Print Time (hr:min)	Total Print Time (hr:min)	Individual Mass (g)	Total Mass (g)	Infill (%)	Support	Layer Height/ Nozzle Diameter (mm)	Notes (orientation, special settings, etc)
Large.stl	3	1:13	3:39	11	33	20	Support Required	0.2/0.4	- Needs Support - Touching Build plate only - 2 perimeters minimum
Trigger.stl	2	0:47	1:34	6	18	20	Support Required	0.2/0.4	- Needs Support - Touching Build plate only - 2 perimeters minimum
Small.stl	3	0:35	1:45	4	12	20	Support Required	0.2/0.4	- Needs Support - Touching Build plate only - 2 perimeters minimum
Light_Touch.stl	4	0:44	2:56	5	20	20	Support Required	0.2/0.4	- Needs Support - Touching Build plate only - 2 perimeters minimum

Customization Options

- Can be printed in any colour.

Post-Processing

- Remove supports ensuring holes for barbs in T-nuts are uncovered.
- Follow Assembly guide for complete instructions on mounting the Logitech Large Button.



Camera Mount Adapters for the Logitech Adaptive Gaming Kit 3D PRINTING GUIDE

Examples of Quality Prints

