I Can Solder Badge kit

Assembly Instructions

Blinky light and White flashlight

CORNFIELD ELECTRONICS

23-Jun-2023

Learn To Solder

The following photos will
show you how to solder.

But feel free to download
the “Soldering Is Easy” comic book
for free!

(In many different languages.)

download for free at:
http://mightyohm.com/soldercomic

Learn To Solder



download for free at:
http://mightyohm.com/soldercomic

Learn To Solder



Download in the language of your choice for free at:
http://mightyohm.com/soldercomic

Learn To Solder



Download in the language of your choice for free at:
http://mightyohm.com/soldercomic

Learn To Solder

Download in the language of your choice for free at:
http://mightyohm.com/soldercomic

Learn To Solder

Download in the language of your choice for free at:
http://mightyohm.com/soldercomic

All of the parts

The board we'll solder the parts to (front)

The board we'll solder the parts to (back)



<u>Important:</u>
Use solder WITH lead (Pb) !!
Unleaded solder has very poisonous fumes!

<u>The tools you'll need</u>:

- soldering Iron (35W or less)
- solder (60/40 Sn/Pb, rosin core, 0.031" (0.7mm) diameter or less)
- soldering iron stand
- cellulose kitchen sponge *(not plastic!)*
- *small* wire cutter

(63/37 is also good)



These are available at:
https://CornfieldElectronics.com

Learn To Solder



The following photos will
show you how to solder a resistor.

There is no resistor in this kit.
But the soldering procedure is the
same for all of the parts in this kit.

The “I Can Solder Badge” kit has no resistors



(but, the parts in this kit are soldered the same way)

The “I Can Solder Badge” kit has no resistors

this is how a resistor will look *before* inserting it into the board

LEDs for this kit go into the board like this resistor




Push part down
all the way



so that the part won’t fall out while soldering it

How to hold a soldering iron

(Like a pencil – held from underneath)

Important

The perfect kind of solder for electronics:

60/40 rosin core,

(63/37 is also good)

0.031” (0.7mm) diameter (or smaller)

<u>Important</u>:

Use solder WITH lead (Pb) !!
lead-free solder
has very poisonous fumes!

3 Safety Tips…

Safety Tip #1:

Hot !!

(When you touch the tip,
you *will* let go quickly every time!)

Safety Tip #2:

Lead (Pb) is toxic

But it easily washes off your hands with soap and water

Safety Tip #3:

(coming soon)

2 secrets to good soldering…

Secret #1:

Clean the tip!

(before every solder connection)

Bang (lightly) 3 times,

Swipe, Rotate, Swipe (on the sponge):

Keep the tip shiny silver!

knock solder off the tip

Lay clean tip across half of the pad,
touching the pad and lead
for 1 second



Do this quickly (slowly doesn't work well) – solder in & out in about 1 second



Make sure solder melts on the <u>underside</u> of the soldering iron tip
(not the side or top of the soldering iron tip)!

Do this quickly (slowly doesn't work well) – solder in & out in about 1 second



Make sure solder melts on the <u>underside</u> of the soldering iron tip
(not the side or top of the soldering iron tip)!


Pull solder away,
But keep holding soldering iron down
for 1 more second

Secret #2:

Keep hot tip down

1 second
for solder to flow !!


Now
Lift soldering iron



If you can see any of the pad, or the hole, you need more solder – so, just do all the steps again to make it perfect.

The Rhythm !

and speed (about 1 second per step)

The Rhythm !

and speed (about 1 second per step)

Clean the tip

The Rhythm !

and speed (about 1 second per step)

Tip Down

The Rhythm !

and speed (about 1 second per step)

Solder In

The Rhythm !

and speed (about 1 second per step)

Solder Out

The Rhythm !

and speed (about 1 second per step)

WAIT !

The Rhythm !

and speed (about 1 second per step)

Lift Tip

The Rhythm !

and speed (about 1 second per step)

The Rhythm !

and speed (about 1 second per step)

Clean the tip

The Rhythm !

and speed (about 1 second per step)

Tip Down

The Rhythm !

and speed (about 1 second per step)

Solder In

The Rhythm !

and speed (about 1 second per step)

Solder Out

The Rhythm !

and speed (about 1 second per step)

WAIT !

The Rhythm !

and speed (about 1 second per step)

Lift Tip

Solder all of the leads of the part to the board



For this part, there are two leads

Here you can see two good solder connections

Now cut the leads short



Cutting with the tip of the wire cutter gives you more control

Safety Tip #3:

Hold or cover the lead !

(or it will fly into your eye!)

(They like doing that – so please hold or cover the lead when you cut.)

No wires sticking out

One part at a time

Till all the parts are soldered

Then put in the batteries,

Turn it on,

And it works!

(Or you start debugging.)

And it will look like this when you’re done.

Let’s start!

Insert Pin in the front



Solder Pin on the back

Insert Battery Holder in the back



The correct orientation of the battery holder is like this photo

Solder Battery Holder on the front (1st pad)



Solder Battery Holder on the front (2nd pad)



Insert Slide Switch in the front

Orientation does not matter

Solder Slide Switch on the back (1st pad)

Solder Slide Switch on the back (2nd pad)

Solder Slide Switch on the back (3rd pad)

Trim Slide Switch leads (1st lead)

REMEMBER:

Cover the lead with your finger when you cut !

Trim Slide Switch leads (2nd lead)



REMEMBER:

Cover the lead with your finger when you cut !

Trim Slide Switch leads (3rd lead)

REMEMBER:

Cover the lead with your finger when you cut !

Insert Push Button Switch in the front



It fits in two ways, and either way is OK

Solder Push Button Switch on the back (1st pad)

Solder Push Button Switch on the back (2nd pad)

Solder Push Button Switch on the back (3rd pad)

Solder Push Button Switch on the back (4th pad)

Test each LED to see which is the White LED and which is the Blinky LED



White LED

Test each LED to see which is the White LED and which is the Blinky LED



Blinky LED

Insert White LED in the front

Insert White LED in the front



Leads of White LED bent like a “V”



Solder White LED on the back (1st pad)

Solder White LED on the back (2nd pad)



Trim White LED leads (1st lead)

Trim White LED leads (2nd lead)



Insert Blinky LED in the front

Short lead is “-”

Long lead is “+”

Insert Blinky LED in the front



Leads of Blinky LED bent like a “V”

Solder Blinky LED on the back (1st pad)

Solder Blinky LED on the back (2nd pad)



Trim Blinky LED leads (1st lead)



Trim Blinky LED leads (2nd lead)

Insert Battery (+) side up

Insert Battery (+) side up

All done!

Turn on Blinky LED !

Move Slide Switch to the left to turn on the Blinky LED

Turn on White LED !



Press Push Button Switch to turn on the White LED

Turn on both White and Blinky LED !

Wear it !

Use the clasp

Please Remember:

to

Wash your hands

after soldering

I Can Solder Badge kit

Assembly Instructions

Blinky light and White flashlight

CORNFIELD ELECTRONICS

23-Jun-2023