

Network Modules	Compatible Switch	Minimum Required Version
M) ¹		
C9300-NM-2Q (-M)		
C9300-NM-8X (-M)	C9300	
C9300-NM-2Y (-M) ²		
C9300X-NM-4C	C9300X-48HX, C9300X-48TX and C9300X-24Y models.	
C9300X-NM-8M ¹	C9300X	
C9300-NM-4G	C9300	
C9300-NM-4M		
C9200-NM-2Y		17.18.1+
C9200-NM-2Q	Support only on C9200-24PXG, C9200-48PXG	
C9200-NM-4G	C9200 (Not supported on C9200-24PXG, C9200-48PXG)	
C9200-NM-4X	C9200	

1. The number of Network Module ports are limited when C9300X-NM-xx are used with the C9300X-48HXN models. For more details see IOS-XE documentation.
2. The C9300-NM-2Y-M module is supported on C9300-24S/48S with firmware CS16.7. Support for the other C9300 switch models require CS16.8



The C9300X-NM-2C-M modules will operate at 40Gbps with software support in CS17 firmware. For 100G operation, IOS-XE 17.15+ is required.

Cloud Management with IOS XE



Cloud-managed Catalyst switches that are being scheduled for an upgrade from any CS firmware version to the latest Cloud Management with IOS XE version (17.15+) should first meet the minimum CS firmware requirement of CS17 version before upgrading.



Cloud-managed Catalyst switch platforms are now supported in the [Meraki India](#), [Meraki China](#), and [Meraki Canada](#) regional clouds. Both cloud configuration mode and device configuration mode are supported with IOS XE. For more details, see the [Cloud Management with IOS XE Overview](#).

IOS XE 17.18

The new 17.18 release delivers high-scale management with advanced features such as enhanced routing protocols, robust high availability capabilities, expanded cloud visibility and troubleshooting tools like SmartPorts and Intelligent Capture (scheduling). With support for additional switch platforms, including C9200/CX, C9300LM, and C9500, it provides seamless, scalable, and reliable management across multiple sites—all through a single, intuitive dashboard.



Try the new Cloud Management with IOS XE 17.18.2 Release Candidate for additional powerful capabilities, such as BGP, VRF, and Cloud EVPN Fabric. **For in-dash upgrade, please see the "Other Available Versions" tab.**

Refer to feature list and documentation: [Additional Features in 17.18.2](#)

Features in 17.18.1

Feature	Supported Models/Family	Minimum Required License
Expand switching platform supports	C9200/C9300/C9500H	Enterprise
Border Gateway Protocol (BGP)	C9200CX, C9300, MS390, and C9500H	Enterprise
Virtual Routing and Forwarding (VRF)	All supported C9000 and MS390 switches in Cloud Management with Cloud Configuration running IOS XE 17.18.1	Enterprise
Routed Ports		Enterprise
StackWise Virtual		Enterprise
In-Service Software Upgrade (ISSU) ¹	C9500H	Enterprise
Rapid Per-VLAN STP (RPVST+) ²		Enterprise
Cloud value expansion:		
SmartPorts Profiles Intelligent Capture Scheduling Device Uptime Digital Optical Monitoring Radius Caching Additional DHCP options	All supported C9000 and MS390 switches in Cloud Management with Cloud Configuration running IOS XE 17.18.1	Enterprise

1. ISSU will only become available when upgrading to the next release from IOS XE 17.18.1
2. IMPORTANT! Please prune unused VLANs. VLANs greater than the number of supported RPVST Instances will automatically be removed for each switch in the network. For more information, refer to [VLAN Profiles](#) documentation.



- Cisco C9350 Series Smart Switches are running their first IOS XE release. The following advanced Layer 3 features are not supported in this release: BGP, VRF, Rapid Per-VLAN Spanning Tree Protocol (RPVST+), Routed Ports, Digital Optical Monitoring, Radius Caching, Intelligent Capture Scheduling, SmartPort Profiles, Encrypted Traffic Analytics (ETA), detailed traffic analytics(trunk ports, port channels, and uplink modules), and VLAN to SGT mapping. Additionally, certain fields in NetFlow exporters are not supported

Additional Features in 17.18.2

Feature	Supported Models/Family	Minimum Required License
SmartPort Automation (early access)	MS390/ C9200/C9300/C9500H Enterprise	
UAC Uplink Allow List (early access)	MS390/ C9200/C9300/C9500H Enterprise	
Live Tool - Multicast	MS390/ C9200/C9300/C9500H Enterprise	
VRF Enhancements (ARP/TraceRoute/Multicast Live Tool)	MS390/ C9200/C9300/C9500H Enterprise	
VRRP	MS390/ C9200/C9300/C9500H Enterprise	
Configure Allowed VLAN DB on LSP	MS390/ C9200/C9300/C9500H Enterprise	
Cloud EVPN Fabric	C9300X and C9500H	Advanced

Please note, [UAC Automatic Fallback to Preferred Uplink](#) (new with 17.15.4.1+) is also supported in 17.18.2+.

Unsupported Features

The following features are not available in Cloud Management with IOS XE 17.18.1 and will be added in future releases.

- MAC Blocklist
- RSPAN / VLAN SPAN
- IPv6 RA Guard / DHCP Guard
- HTTP Proxy
- Sticky MAC
- Dynamic ARP Inspection (DAI) Auto-Uplink
- Netflow on IPv6
- SecurePort
- Meraki for Government Cloud

IOS XE 17.15

Key Highlights

- Introducing a new onboarding flow including both cloud and device configuration: two powerful ways to manage your Catalyst 9000 switches from the Meraki dashboard. These options give you the flexibility to choose cloud management with cloud configuration in Meraki dashboard or device configuration (previously referred to as cloud monitoring) that offers configuration via an embedded cloud CLI while leveraging the cloud for monitoring and troubleshooting. [Learn more](#).
- Management Interface Architecture Change: a dedicated management interface is no longer required.
- Default Network Module: this enhancement simplifies and consolidates network module configuration into 8 default ports that get applied dynamically to any inserted network module. (Watch [this](#) video to learn more about this change or see the [Cloud Operating Mode for Catalyst Cloud-Managed Switches Overview](#) documentation)
- Standardized Cisco Logging and Interface Naming

Supported Features

- [UAC Automatic Fallback to Preferred Uplink](#) (new with 17.15.4.1+)
- Configuration Templates
- Adaptive Policy
- [Intelligent Capture](#)
- Storm Control

- Radius Multi-Auth (dot1X)
- Device Uptime
- 802.1X Control Direction
- Meraki Authentication (Meraki Auth)
- Alternate Management Interface (AMI)
- Port Schedules
- C9200L Hardware Platform Support (see supported models above)
- SNMPv3
- Encrypted Traffic Analytics
- Energy Efficient Ethernet
- MAC Allow Lists
- Support for regional clouds: [Meraki India](#), [Meraki China](#), and [Meraki Canada](#)

Unsupported Features



The following features are not available in IOS XE 17.15 with cloud configuration and will be added in future releases.

- SmartPorts
- MAC Blocklist
- Digital Optical Monitoring (DOM)
- RSPAN / VLAN SPAN
- IPv6 RA Guard / DHCP Guard
- WarmSpare / VRRP
- HTTP Proxy
- Sticky MAC
- Dynamic ARP Inspection (DAI) Auto-Uplink
- Netflow on IPv6
- SecurePort
- Meraki for Government Cloud

IOS XE 17.15.5 Release Highlights and Important references

Highlights and References

Details

UAC Enhancements

[UAC enhancements and expected behavior](#)

Key UAC Improvements:

- More reliable uplink selection and IP management.
- Uses gateway ARP probes instead of PING for connectivity checks.
- Automatically reverts to the preferred uplink after successful ARP probe.
- Always prioritizes the preferred uplink after a reboot.

Highlights and References

Details

Layer 3 Migration Guide

[L3 Migration guide from CS to IOS XE firmware](#)

For customers migrating their L3 switches from CS to IOS XE firmware, we highly recommended they review the architectural differences as well as the best practices to follow for a smoother transition experience

Expanded Meraki regional cloud support for switches on IOS XE firmware

Cloud Management with IOS XE now available in **Meraki India, China, and Canada** regions.

Firmware Upgrade Optimizations

Numerous enhancements have been made to the CS to IOS XE upgrade process, significantly reducing upgrade times and optimizing firmware upgrade experience. These improvements ensure faster, more reliable upgrades with minimized downtime.