

Exp No: 14

EMBEDDED C PROGRAM TO DISPLAY “HELLO WORLD” MESSAGE

Program:

```
#include <reg51.h>
```

```
#include <stdio.h>
```

```
char putchar(char c)
```

```
{  
    SBUF = c;      // Send character  
    while(TI == 0); // Wait for transmission  
    TI = 0;        // Clear transmit flag  
    return c;  
}
```

```
void main(void)
```

```
{  
    SCON = 0x50;    // UART Mode 1, 8-bit  
    TMOD = 0x20;    // Timer1 Mode2  
  
    TH1 = 0xFD;     // 9600 baud for 11.0592 MHz  
    TL1 = 0xFD;  
  
    TR1 = 1;        // Start Timer1  
  
    while(1)  
    {  
        printf("Hello World!\r\n");  
  
        {
```

```

    unsigned int i, j;

    for(i = 0; i < 200; i++)

        for(j = 0; j < 500; j++)

            }

        }

    }

```

