

SolarPro Global — Technical Guide

Engineering basis, standards, and integration reference

Version: 2026-06-05 (beta) **Audience:** Senior engineers, technical leads, and procurement/IT staff at Ghana installer and supplier companies; internal engineering team. **Companion to:** User Guide (workflow) and Sales Pitch (positioning).

This document explains **how** SolarPro computes its outputs and **which standards** it follows, so an external engineer can defend any value the platform produces to a client or to a financing bank.

1. Engineering principles in one page

SolarPro is built on three rules:

1. **Every output is derivable from the inputs.** No "magic" multipliers — every coefficient is listed in this guide or in **assumptions.md**.
2. **Every output is overridable.** Defaults are conservative; the engineer can replace any value with their own.
3. **Every output is traceable.** The proposal PDF shows the calculation path so a reviewing engineer can validate without re-running the tool.

2. Standards applied

Standard	Where it's applied	Notes
----------	--------------------	-------

BS 7671 (18th Edition, +A2)	AC cable sizing, derating, protective device coordination	UK origin; default standard for Ghana commercial/industrial wiring
IEC 62548	DC string design, MPPT voltage windows, isolation	International PV-array standard
IEC 60364-7-712	PV-specific installation requirements	Used for protective bonding, isolation
IEC 61730	Module safety classification	Determines Class II isolation requirements
NEC Article 690	Fallback for US-style installations	Triggered only when site country = USA
Ghana Energy Commission — Solar PV Code of Practice (2019)	Permitting checklist on the installation report	Drives the EC-certification section
IEC 61724	Performance ratio & yield calculation	Drives the economic analysis

Standards are cited inline in every report so the bank's engineer can verify.

3. Site assessment

3.1 Irradiance

Source: `config/global_solar_data.py` — region-level peak sun hours (PSH) lookup.

For Ghana:

Region	PSH (kWh/m ² /day)	Ambient (°C)
Greater Accra	5.2	28
Ashanti	5.0	26

Northern	5.6	30
Volta	5.1	27
Western	4.8	26

Source data: NASA POWER + Ghana Meteorological Agency monthly means, averaged 2018–2023.

3.2 ECG tariff

Region-tagged residential and commercial tariffs sourced from Public Utilities Regulatory Commission (PURC) quarterly publications. Escalation default = 6%/year (BoG inflation forecast).

The engineer can override tariff and escalation in the economic step.

4. Load analysis

$$\text{Daily energy demand (Wh/day)} = \sum (P_i \times n_i \times h_i \times d_i / 7)$$

Where:

- P_i = nameplate power of load i (W)
- n_i = quantity
- h_i = hours per day
- d_i = days per week (default 7)

A diversity factor is applied to the **peak** load (not the daily energy):

$$\text{Peak (kW)} = \sum (P_i \times n_i) \times DF$$

Where DF = 0.65 for residential, 0.85 for commercial, 1.0 for industrial. The engineer can change DF per project.

Surge load = peak $\times$ 3 (motor start; configurable 2–5 $\times$).

5. PV array sizing

5.1 Required peak power

$$P_{pv} \text{ (kWp)} = E_{\text{daily}} / (PSH \times \eta_{\text{system}} \times \delta_{\text{temp}})$$

Where:

- E_{daily} = daily energy demand (kWh)
- PSH = peak sun hours from §3.1
- η_{system} = 0.80 (default) — combined inverter + wiring + soiling
- $\delta_{\text{temp}} = 1 - \gamma \times (T_{\text{cell}} - 25)$ — temperature derate

Cell temperature: $T_{\text{cell}} = T_{\text{amb}} + 25 \text{ }^{\circ}\text{C}$ (NOCT approximation; configurable). γ (power temperature coefficient) = -0.0034 K^{-1} (Tier-1 mono panel default).

5.2 Module count

$$N_{\text{modules}} = \text{ceil}(P_{pv} \times 1000 / W_{\text{module}})$$

Where $W_{\text{module}} \in \{110, 250, 330, 400, 450, 500, 550\} \text{ Wp}$ (commit [27b2492](#)).

5.3 String design

For each candidate inverter MPPT range $[V_{\text{min}}, V_{\text{max}}]$:

$$\begin{aligned} N_{\text{series_min}} &= \text{ceil}(V_{\text{min}} / (V_{\text{mp}} \times \delta_{T_{\text{hot}}})) \\ N_{\text{series_max}} &= \text{floor}(V_{\text{max}} / (V_{\text{oc}} \times \delta_{T_{\text{cold}}})) \end{aligned}$$

Temperature corrections:

- $\delta_{T_{\text{hot}}} = 1 + \beta_{\text{voc}} \times (T_{\text{cell_hot}} - 25) \approx 0.88$ (V_{mp} shrinks when panel is hot)
- $\delta_{T_{\text{cold}}} = 1 + \beta_{\text{voc}} \times (T_{\text{cold}} - 25) \approx 1.10$ (V_{oc} grows when panel is cold)

$\beta_{\text{voc}} = -0.0029 \text{ K}^{-1}$ default.

If `N_series_min > N_series_max`, the MPPT panel is incompatible → engine flags WARNING and suggests a smaller-Vmp module or a different inverter.

5.4 Mounting derate

Mounting type	Soiling factor	Temperature uplift (°C)
<code>rooftop_pitched</code>	0.95	+5
<code>rooftop_flat</code>	0.90	+10
<code>rooftop_metal</code>	0.95	+12
<code>rooftop_membrane</code>	0.95	+8
<code>ground_fixed</code>	0.92	+3
<code>ground_tracking</code>	0.95	+3

These factors fold into `η_system` and `T_cell` automatically.

6. Battery sizing

$$C_{\text{battery}} \text{ (Wh)} = E_{\text{daily}} \times N_{\text{autonomy}} / (\text{DoD} \times \eta_{\text{inv}} \times \eta_{\text{batt}})$$

Defaults:

- `N_autonomy` = 1 day (residential), 0.5 day (grid-tied), 2 days (off-grid critical)
- `DoD` = 0.80 (lithium), 0.50 (gel/AGM)
- `η_inv` = 0.95
- `η_batt` = 0.95 (lithium), 0.85 (lead acid)

The battery type (lithium / gel / AGM) drives DoD and `η_batt`. The engineer chooses; the engine reflects the math.

Output is rounded up to the nearest stocked battery module size (5 kWh, 10 kWh, 15 kWh, 20

kWh by default — configurable in Settings → ROQ)

7. Inverter sizing

$$P_{inv} \text{ (kW)} = \max(\text{Peak_kW} \times 1.25, P_{pv} \times 0.85)$$

Two-sided constraint:

- Must handle peak load with 25% margin
- Must absorb at least 85% of PV array output (Ghana standard avoids over-clipping under low PSH)

A hybrid inverter is selected by default for off-grid + battery; grid-tied selects a string inverter.

8. Cable sizing

8.1 DC cable (panel → combiner → inverter)

Voltage drop method (IEC 62548):

$$A \text{ (mm}^2\text{)} = (2 \times L \times I \times \rho) / \Delta V_{\max}$$

Where:

- L = one-way length (m)
- I = string current at STC
- ρ = 0.0175 $\Omega \cdot \text{mm}^2/\text{m}$ (Cu @ 20 °C)

- $\Delta V_{\max} = 1.5\% \times V_{\text{array}}$

Round up to the next standard size (4, 6, 10, 16, 25 mm²). Verify the result against ampacity at 70 °C ambient — bump up one size if borderline.

8.2 AC cable (inverter → DB → load)

Per BS 7671 §523, Table 4D5 (PVC SWA):

Cable	Current carrying capacity (A) @ 30 °C ambient
2.5 mm ²	24 A
4 mm ²	32 A
6 mm ²	41 A
10 mm ²	57 A
16 mm ²	76 A
25 mm ²	101 A

Derating applied:

- Ambient temperature factor (BS 7671 Table 4B1) — Ghana ambient 32–35 °C → 0.94
- Grouping factor (Table 4C1) — if more than one cable shares conduit
- Installation method factor (clipped direct vs. conduit)

Final: smallest size whose derated capacity $\geq$ design current $\times$ 1.25.

Voltage drop check: $\leq$ 3% for final circuits, $\leq$ 5% combined (per BS 7671 Appendix 12).

8.3 Earthing

Earth conductor sized per BS 7671 §544 — half the phase conductor's cross-section, minimum 4 mm² Cu.

Earth rod: 1.2 m $\times$ 16 mm Cu — measured resistance $\leq$ 10 Ω per IEC 60364-7-712.

9. Bill of Quantities — how it's built

`calc_boq()` traverses the sized system and emits one line per material category:

Category	Quantity logic
Modules	N_{modules} from §5.2
Mounting rails	$\text{ceil}(N_{\text{modules}} \times 1.05 \text{ m} / 4.2 \text{ m})$ — 4.2 m standard rail
End clamps	$4 \times N_{\text{strings}}$
Mid clamps	$2 \times (N_{\text{modules}} - N_{\text{strings}})$
MC4 connectors	$2 \times N_{\text{strings}}$
DC cable	length from §8.1 with 10% wastage
AC cable	length from §8.2 with 10% wastage
Inverter	N_{inv}
Battery modules	$\text{ceil}(C_{\text{battery}} / W_{\text{battery_unit}})$
Earth rod	1 per system
Earth conductor	length matches AC cable
Surge arrestor (DC)	1 per MPPT input
Surge arrestor (AC)	1 per phase
Isolators (DC)	1 per string
Combiner box	1 per inverter
Ground mount only	steel post (1 per 4 modules), concrete footing (1 per post), purlin beam (4.2 m per row), earth rod (1 per 20 modules)

Pricing:

- Default: blank — engineer types unit cost.
- With supplier integration enabled: pulls live pricing via the supplier's API. Currently

10 Economic analysis

10.1 Energy yield (per IEC 61724)

$$E_{\text{year}} \text{ (kWh)} = P_{\text{pv}} \times \text{PSH} \times 365 \times \text{PR}$$

PR (performance ratio) defaults:

- Rooftop residential: 0.75
- Rooftop commercial: 0.80
- Ground mount fixed: 0.82
- Ground mount tracking: 0.86

10.2 Cash flow

For year $y \in [1, \text{lifetime}]$:

$$\begin{aligned} \text{Savings}_y &= E_{\text{year}} \times (1 - \delta_y) \times \text{Tariff} \times (1 + \text{escalation})^{(y - 1)} \\ \text{OPEX}_y &= \text{OPEX}_0 \times (1 + 0.03)^{(y - 1)} \\ \text{Net}_y &= \text{Savings}_y - \text{OPEX}_y \\ \text{NPV}_y &= \text{Net}_y / (1 + \text{discount})^y \end{aligned}$$

Where:

- δ_y = degradation per year (default 0.5%, lithium battery system; 0.7% pure PV)
- OPEX_0 = annual maintenance estimate (default 1% of CAPEX)

10.3 Headline metrics

- **Payback (years)** — interpolated to the year where cumulative cashflow ≥ 0
- **IRR (%)** — Newton-Raphson on the cashflow vector, tolerance 1e-6
- **NPV (GHS)** — sum of NPV_y over lifetime
- **LCOE (GHS/kWh)** — $\sum \text{Costs} / \sum \text{Energy}$

11. Reports

Every project produces seven PDF reports, all rendered from the same JSON state:

1. **PV Sizing Report** — array, strings, MPPT match, temperature checks
2. **BOQ** — full materials list with prices
3. **Cable Schedule** — every run with gauge, length, derating, voltage drop
4. **Economic Analysis** — charts + IRR/NPV table
5. **Installation Method Statement** — step-by-step, with safety
6. **Energy Yield Report** — month-by-month projection
7. **Bankable Proposal** — combined cover-page + executive summary + sized excerpts of 1–6

Reports embed the assumptions used (PSH, system efficiency, derating factors) so a third-party engineer can validate without re-running the tool.

12. Data model (for IT staff)

12.1 Storage

Each project's full engineering state lives in a single JSON blob: `projects.data_json`. Schema (abbreviated):

```
{
  "site": { "country": "Ghana", "region": "Greater Accra", "psh": 5.2, "ambient": 30.0 },
  "loads": [ { "name": "Fridge", "watts": 250, "qty": 1, "hours": 12, "days_per_year": 365 },
  "totals": { "daily_kwh": 18.3, "peak_kw": 4.1, "surge_kw": 12.3 },
  "results": {
    "pv": { "p_kwp": 6.0, "n_modules": 12, "w_module": 500, "strings": [ ... ] },
    "battery": { "kwh": 10, "type": "lithium" },
    "inverter": { "kw": 5.0, "type": "hybrid" },
    "cable": { "dc_mm2": 6, "ac_mm2": 4 },
    "boq": [ ... ],
    "economics": { "payback_y": 4.2, "irr": 0.27, "npv_25y": 86_200 }
  }
}
```

12.2 Export

- **PDF** — **Generate Proposal** button on the project page.
- **JSON** — **GET /api/project/<id>/export.json** (authenticated; returns the schema above).
- **BOQ** — **GET /api/project/<id>/boq.csv** (BOQ only).

12.3 Re-import

POST a previously exported JSON to **/api/project/import** — recreates the project. Useful for restoring from backup or moving a project between accounts.

13. Integration points

For supplier and installer companies, three integration surfaces are available during beta:

13.1 Pricing API (suppliers)

If you sell panels / inverters / batteries / cables, we'll wire your stock into the BOQ procurement screen. Required from you:

- A REST or GraphQL endpoint returning JSON with { **sku**, **name**, **category**, **unit_price_ghs**, **in_stock**, **lead_time_days** }
- Optional webhook for stock updates

We pull on a 6-hour cadence (configurable). Live unit costs replace blank cells in the BOQ.

13.2 Project handoff (installers)

After a designer signs off a project, a **/installer/handoff** webhook fires to your endpoint with the full JSON state. Your project management system picks it up and creates a work order.

13.3 Single sign-on (SSO)

If your company uses Google Workspace, Microsoft 365, or any OIDC provider — we support SSO on Business+ plans. Required: client ID + client secret + issuer URL.

14. Security & compliance

Control	Implementation
Authentication	Username + password; 5-failed-attempt lockout 15 min
Session management	HttpOnly Lax cookie; CSRF (<code>_csrf</code>) on every POST
Database isolation	Per-tenant row-level filters on all user data tables
Encryption at rest	Hosting platform-managed (currently AES-256)
Encryption in transit	TLS 1.2+ end-to-end
Audit log	<code>audit.log</code> (JSON-line) — login, project edits, exports
Security headers	CSP, X-Content-Type-Options, Referrer-Policy, Frame-Ancestors
Data export	Self-serve from Settings → Export (per GDPR Art. 20)
Data deletion	Self-serve from Settings → Delete Account
Backups	Daily snapshot, 30-day retention

Reference: `SECURITY.md` in the repo for the full Zero-Trust architecture + RBAC matrix.

15. Performance & SLA targets (beta)

Metric	Target	Notes
Sizing calculation latency	< 30 s	p95
Proposal PDF generation	< 60 s	p95

Optimic	99.9%	Free Railway tier, will rise to 99.9% on RGS
Support response (in-app chat)	< 60 s	Rule-based; AI fallback to Claude/Llama
Support response (email)	24 h	Business hours

16. Where to look in the code (internal staff)

Concern	File
Loads → sizing pipeline	<code>web_app.py</code> → <code>calc_loads</code> / <code>calc_pv</code> / <code>calc_battery</code>
AC cable sizing	<code>calculation/ac_cable_sizing.py</code>
DC cable sizing	<code>web_app.py</code> → <code>size_dc_cable</code>
BOQ generation	<code>web_app.py</code> → <code>calc_boq</code>
Economic engine	<code>web_app.py</code> → <code>calc_economics</code>
Global irradiance data	<code>config/global_solar_data.py</code>
AI helpline	<code>web_app.py</code> → <code>/api/assistant/chat</code> + <code>api_manager.py</code>
Email send chain	<code>api_manager.py</code> → <code>_send_email</code>
Structured logging	<code>logging_config/structured_logger.py</code>
Health endpoints	<code>web_app.py</code> → <code>/api/health*</code>

17. Roadmap (next 90 days)

Month	Theme	Highlights
-------	-------	------------

June 2026	Data hardening	Custom domain SSL, multi-tenant edge isolation, screenshots in user guide
July 2026	Procurement	Nocheski + Ozo pricing live in BOQ, supplier directory page
2026	Energy reporting	Month-by-month yield, Excel export of BOQ, mobile-optimised dashboard

Feature requests during beta: send to support@aiappinvent.com or via in-app chat. Top-3 by demand each fortnight ships on the next sprint.

18. Engineering changelog (June 17, 2026)

Four mechanical changes shipped to master today. The first three concern the shading dashboard's mathematical contract; the fourth introduces a mount-aware electrical drawing.

18.1 Sun-position Bézier — single source of truth

The shading dashboard's central viewport draws a dashed yellow sun-path arc as the SVG path

```
M 60 460 Q 500 -340 940 460
```

a quadratic Bézier with horizon endpoints (60, 460) and (940, 460) and control point (500, -340) so the noon peak sits at (500, 60). The same Bézier coefficients now drive the JS animation:

```
function sunXY(hour) {
  var t = (hour - 6) / 12;
  var x = (1 - t) * (1 - t) * 60 + 2 * (1 - t) * t * 500 + t * t * 940;
  var y = (1 - t) * (1 - t) * 460 + 2 * (1 - t) * t * (-340) + t * t * 460;
  return { x: x, y: y };
}
```

with `BASE_X = 700`, `BASE_Y = 70` matching the server-rendered `_sun_x` / `_sun_y` defaults, so the disk's transform `translate(p.x - BASE_X, p.y - BASE_Y)` puts it at `(p.x, p.y)` for every hour. Five visible marker circles sit on the curve at `t = 1/12 3.5/12 6/12 8.5/12 11/12` (07:00 09:30, 12:00, 14:30, 17:00) — pre-computed Jinja constants so they never drift.

Net: the visible curve and the moving disk are guaranteed to share a single mathematical formula

Any client asking "is your simulation accurate?" can be shown both the SVG path string and the JS coefficients side by side.

18.2 Shading-factor precedence chain

The dashboard now reads `_factor` / `_label` / `_loss` from a single ordered precedence:

1. `shading.factor` (the saved value written by `_apply_shading_factor`)
2. `_eng.bucket_factor` (cached engine block, used only when no save exists)
3. `1.00 / ' ' / 0` (no-data defaults)

`_apply_shading_factor` (in `web_app.py`) runs the deterministic geometry engine first, falls back

to the heuristic agent `_compute_shading_factor` when project context is incomplete, and yields to a manual operator override when the gold-pill Save handler fires. All three write the same `data["shading"]["factor"]` field, so the dashboard now displays the actually-applied value regardless of which source produced it.

When `factor_source == "manual"`, a `· MANUAL` suffix is appended to the displayed label, and the AGENT PICK row highlight in the SHADING_FACTORS table tracks the saved factor rather than the cached engine bucket. The engine block remains in `data["shading"]["engine"]` so the 3D scene still has geometry to render against.

18.3 Engine ↔ heuristic snapping parity

Both `engine.shading_engine.SHADING_BUCKETS` and `web_app.SHADING_FACTORS` are the same eight rows (No shading → Very severe shading, 0% → 40% loss, 1.00 → 0.60 factor) with the same conservative snap rule: pick the highest row whose loss% is $\leq$ the computed loss%.

When either path runs alone its output is one of those eight rows, so the visible factor on the dashboard is one of eight discrete values — never a continuous figure. Downstream code (loads / sizing / BOQ) reads only the snapped row.

18.4 Installation drawings — mount-aware string routing (Drawing 1B)

The Installation Drawings report (`/project/<pid>/report/installation/drawings`) carries a new Drawing 1B between the existing PV-panel internal-wiring diagram and the battery-bank diagram. One SVG with three Jinja branches keyed on the project's stored `mounting_type`

Mount class	Topology rendered	Standards cited

rooftop_sloped (default, pitched, hip, gable, metal, rooftop_pitched, rooftop_metal)	Cables clipped to under-tray, EPDM-flashed pitched penetration, IP65 rigid conduit to indoor inverter wall	BS 7671 Method B-1, 0.85 thermal-insulation factor; §712 PV bonding
rooftop_flat (flat, membrane, concrete, rooftop_flat, rooftop_membrane)	Galvanised cable tray on ballast stands, parapet transition to UV-rated rigid conduit, drop to plant room	IEC 60364-5-52 tray fill ≤ 40 %, 70 °C PVC; FM 4474 ballast wind-load
ground_* (ground_fixed, ground_tracking)	IP67 armoured conduit buried ≥ 600 mm, cable draw-pits every 90 m, combiner on equipment shelter	BS 7671 Tab 4D4A buried-cable derating; BS 7499 array frame bonding

The diagram is sized from the project's actual **pps** (panels per string) × **num_strings**, colours each string from an 8-step palette (red → orange → yellow → green → blue → violet → magenta → cyan), and draws DC+ red / DC– blue cable paths from the array to the combiner box (fuse + DC isolator per string, IP65 housing, "{N}-in / 1-out") and out to the inverter (MPPT input ceiling annotated). The notes panel adds string-balance, derating, and combiner-termination guidance with BS 7671 §537 lockout requirement.

Implementation: see **templates/report_installation_drawings.html** block "DRAWING 1B" (≈ 150 LOC SVG + 3-column notes panel). All **mt** branches are derived from the lower-cased **mounting_type** string, so any new raw mount value the form might add ("ground_pole", "rooftop_carport", etc.) defaults to the closest-class topology rather than 500'ing.

19. Screenshots index

The technical guide references the same screens as the user guide:

- **[SCREEN: location-globe]** — for §3 site assessment
- **[SCREEN: loads-input]** — for §4 load analysis
- **[SCREEN: results-pv]** — for §5 PV sizing
- **[SCREEN: boq]** — for §9 BOQ
- **[SCREEN: economics]** — for §10 economics
- **[SCREEN: installation-drawings]** — for §6.4 mounting derate consequences

Capture from the live app, save under **docs/screens/<slug>.png** rerun the PDF build to

embed.

[illegible]

© 2015 Pearson Education, Inc. or its affiliate(s). All rights reserved. No part of this publication may be reproduced, stored in a retrieval system, or transmitted, in any form or by any means, electronic, mechanical, photocopying, recording, or by any information storage or retrieval system, without prior written permission from Pearson Education, Inc. or its affiliate(s).