6.9 Checkpoint Review

Date: 3/15/2026, 2:19:56 PM

Time Spent: 11:46

Score: 70%

Passing Score: 80%

Question 1

Correct

What is the significance of a link-local address in IPv6?

- It is used for routing packets over the Internet.
- It is only necessary for devices acting as routers.
- It must always be configured on an interface. ✓ Correct
- It is an optional configuration for improved network security.

Explanation

In IPv6, every interface must have a link-local address, which is used for local communication on the network segment and for certain protocols like Neighbor Discovery Protocol. It is essential for the operation of an IPv6 network.

Link-local addresses are not routable over the Internet; they are only valid within a network segment.

All devices, not just routers, require a link-local address on their interfaces.

Link-local addresses are not optional; they are a fundamental part of IPv6 configuration for network operation, not specifically for security.

Related Content

resources\questions\q_apipa6_link_local_purpose_n09.question.xml

Question 2 Correct

When installing structured cabling, why is it important to leave a service loop at both ends of the cable run?

- To ensure that the cable can be easily pulled out for recycling
- To provide extra cable length for future reconnections or changes ✓ Correct
- To increase the tension on the cable, ensuring a tighter fit
- To make the installation look more professional and organized

Explanation

Leaving a service loop (extra length of cable) at both ends of the cable run allows for adjustments, reconnections, or changes in the future without the need to install new cabling. This flexibility is crucial for maintaining and upgrading network infrastructure as needs evolve.

While recycling is an important consideration, the primary purpose of a service loop is not to facilitate cable removal for recycling, but to provide flexibility for future adjustments.

Increasing tension on the cable is not desirable. In fact, too much tension can damage the cable and negatively affect its performance. A service loop is meant to provide slack, not tension.

Although a neat and organized installation is important, the main function of a service loop is practical (to allow for future adjustments) rather than aesthetic.

Related Content

- 2.3.1 Structured Cabling System
- 2.3.3 Patch Panels
- 2.3.4 Structured Cable Installation
- 2.3.6 Lab: Explore Multiple Locations in a Lab
- 2.3.8 Lab: Connect Patch Panel Cables 1
- 2.3.9 Lab: Connect Patch Panel Cables 2
- 2.4.4 Fiber Optic Cable Installation
- 2.4.5 Fiber Distribution Panels
- 2.4.8 Wavelength Division Multiplexing
- 2.7.3 Structured Cable Installation

resources\questions\q_struct_cable_service_loop_02_n09.question.xml

Question 3

Correct

Which of the following problems does NAT help address?

- (selected) The shortage of IPv4 addresses ✓ Correct
- Registering IP addresses with an ISP
- The shortage of IPv6 addresses
- IPsec not working properly

Explanation

Network Address Translation helps address the shortage of registered IPv4 addresses. A NAT router translates multiple private addresses into a single registered IP address.

The internet is classified as a public network. All devices on a public network must have a registered IP address assigned by an internet service provider (ISP). NAT does not address any issues in this process.

There is no shortage of IPv6 addresses.

NAT can cause IPsec to malfunction because NAT changes packet headers. IPsec detects changes to packet headers as part of the security process.

Related Content

- 5.3.2 Network Address Translation Types
- 5.3.3 Port Address Translation
- 5.3.4 Lab: Configure NAT

resources\questions\q_nat_ipv4_shortage_n09.question.xml

Question 4 Correct

During the planning phase of a data center upgrade, a network architect decides to implement Wavelength Division Multiplexing (WDM) to increase the data capacity over existing fiber optic links.

Which of the following considerations is MOST critical for ensuring the successful deployment of WDM in the network?

- Ensuring all transceivers operate at the same power level
- Selecting transceivers that support the same Ethernet standard
- Choosing transceivers that can operate on multiple wavelengths ✓ Correct
- Matching the color of the transceiver casings with the fiber optic cables

Explanation

The most critical consideration for the successful deployment of Wavelength Division Multiplexing (WDM) is choosing transceivers that can operate on multiple wavelengths. WDM works by multiplexing multiple optical carrier signals on a single optical fiber by using different wavelengths (colors) of laser light to carry different signals. This allows for a significant increase in capacity without the need for additional physical fibers. Transceivers used in a WDM setup must be capable of transmitting and receiving signals at the specific wavelengths used in the WDM system to ensure compatibility and optimal performance.

While operating power levels are important for overall network performance, the key to WDM deployment success is the ability of transceivers to handle multiple wavelengths, not just power levels.

Supporting the same Ethernet standard is important for ensuring network devices can communicate effectively, but for WDM, the ability to operate on multiple wavelengths is more critical to increase data capacity.

The color of transceiver casings is purely aesthetic and has no impact on the functionality or compatibility of the transceivers with WDM technology or fiber optic cables.

Related Content

- 3.1.3 Transceiver Mismatch Issues
- 3.1.4 Transceiver Signal Strength Issues

resources\questions\q_transceiver_multiple_wavelengths_scenario_n09.question.xml

Question 5 ✕ Incorrect

During a routine inspection of a fiber optic network that services a critical communications infrastructure, you discover that some sections of the network are experiencing higher than normal signal attenuation. You need to quickly identify whether the issue is due to dirty connectors or actual damage to the fiber.

Which tool would be most effective for initially diagnosing the problem?

- ○ Visual Fault Locator (VFL) ✓ Correct
- ○ Fusion Splicer
- ◉ Spectrum Analyzer ✕ Incorrect
- ○ Cable Certifier

Explanation

Visual Fault Locator (VFL) is the correct answer. A Visual Fault Locator (VFL) is a practical tool for quickly identifying breaks, bends, and major issues in fiber optic cables, as well as problems with connectors. It can help determine whether the attenuation is due to dirty connectors (by identifying no faults in the cable itself) or if there is visible damage to the fiber that needs further investigation.

A fusion splicer is used for joining two fiber strands together, not for diagnosing or identifying issues such as dirty connectors or damage.

A spectrum analyzer is used to analyze the frequency spectrum of electrical signals, not for direct inspection or diagnosis of physical issues in fiber optic networks.

Cable certifiers are primarily used for certifying the performance of copper and, in some cases, fiber optic cabling to industry standards, but they are not the best tool for quickly diagnosing the specific cause of signal attenuation like a VFL.

Related Content

2.6.8 Fiber Optic Cable Testing Tools

resources\questions\q_fiber_test_vfl_scenario_n09.question.xml

Question 6 ✕ Incorrect

What does a higher margin value indicate when measuring insertion loss?

- ○ The cable is closer to not meeting acceptable link standards.
- ○ The cable is heavier than standard cables.
- ◉ The cable exceeds the maximum allowed insertion loss. ✕ Incorrect
- ○ The cable is further from reaching the maximum allowed insertion loss. ✓ Correct

Explanation

Margin value is the difference between the actual loss and the maximum value allowed for the cable standard. A higher margin value indicates that the cable is further from reaching the maximum allowed insertion loss, which is desirable.

A higher margin value actually indicates that the cable is further from not meeting acceptable link standards, not closer.

The weight of the cable is unrelated to the margin value of insertion loss.

Exceeding the maximum allowed insertion loss would result in a negative margin, not a higher one.

Related Content

- 2.6.1 Specification and Limitations
- 2.6.6 Attenuation and Interference Issues
- 2.6.7 Crosstalk Issues
- 12.4.2 Insufficient Wireless Coverage Issues

resources\questions\q_attenuation_higher_margin_value_n09.question.xml

Question 7

Correct

What is ARP used for in IPv4 networks?

- [x] To determine the Data Link layer address of the destination interface ✓ Correct
- [ ] To increase the packet's Time to Live (TTL)
- [ ] To encrypt the packet's contents
- [ ] To find the shortest path to the destination

Explanation

The correct answer is to determine the Data Link layer address of the destination interface for packets delivered to a directly connected network. ARP is crucial for mapping IP addresses to their corresponding physical (MAC) addresses in IPv4 networks, facilitating the delivery of packets within the same network segment.

ARP has no relation to TTL; TTL is managed within the IP header to control the packet's lifespan.

ARP is not involved in encryption; it is purely for address resolution.

ARP does not determine paths; it resolves physical addresses for local communication.

Related Content

resources\questions\q_pack_forw_arp_use_n09.question.xml

Question 8 ✕ Incorrect

How is an IPv4 address MOST commonly formatted for readability?

- ○ Hexadecimal notation
- ○ Dotted decimal notation ✓ Correct
- ○ Binary notation
- ◉ Octal notation ✕ Incorrect

Explanation

Dotted decimal notation is used to make IPv4 addresses more readable to humans. In this format, the 32-bit address is divided into four 8-bit octets, each converted to its decimal equivalent and separated by periods. This notation simplifies reading, writing, and communicating IP addresses.

While hexadecimal is used in other contexts (like IPv6 addresses), IPv4 addresses are typically not represented in hexadecimal for everyday use.

Representing an IPv4 address in binary is technically accurate but impractical for human readability due to its length and complexity.

Octal notation is not a standard practice for representing IPv4 addresses. Dotted decimal notation is the preferred and widely used format.

Related Content

resources\questions\q_ipv4_dotted_decimal_notation_n09.question.xml

Question 9 ✕ Incorrect

Which of the following items of information are the MOST critical to include on a troubleshooting ticket? (Select three.)

- [ ] The ticket creator's personal opinion on the cause
- [ ] The favorite troubleshooting tool of the technician
- [ ] Who is responsible ✓ Correct
- [ ] The brand of equipment being used
- [x] A complete description of the problem ✓ Correct
- [x] The customer's contact information ✕ Incorrect
- [x] A complete description of the solution ✓ Correct

Explanation

The following are the most critical items of information to include on a troubleshooting ticket:

- Who is responsible. Including who is responsible for the ticket ensures accountability and clarity on who is handling the problem. This is crucial for follow-ups and for maintaining an organized workflow.
- A complete description of the problem. A thorough description of the problem helps in understanding the issue without needing to ask for more information. It ensures that anyone who reads the ticket can grasp the situation, which is essential for effective troubleshooting and for future reference.
- A complete description of the solution. Documenting the solution in detail is vital for resolving similar issues in the future. It serves as a knowledge base for the team and can save time and resources by preventing the need to rediscover solutions to recurring problems.

While insights can be helpful, personal opinions without evidence can lead to bias and may not be useful for solving the problem. It's important to focus on factual information and findings.

While important for communication, the customer's contact information is not directly related to the troubleshooting process itself. This information should be kept in a separate, secure location due to privacy concerns.

Although the brand of equipment can be relevant in some cases, it is not a mandatory piece of information for every troubleshooting ticket. The focus should be on the problem, solution, and responsible party.

The technician's preferred tools are subjective and not necessary for the ticket. What matters is the actions taken and the outcomes, rather than the personal preferences of the technician.

Related Content

1.4.1 Network Troubleshooting Methodology

1.4.6 Establish a Plan of Action

1.4.9 Document Findings, Actions, and Outcomes

1.4.10 Lab: Troubleshooting Methodology

resources\questions\q_document_troubleshooting_ticket_n09.question.xml

Question 10 Correct

What is the primary purpose of creating logical subnets within an IP network?

- To increase the speed of the internet connection for all users
- To enhance the security of the network by encrypting data
- To allow for more efficient use of IP addresses and improve network management ✓ Correct
- To replace the need for physical network infrastructure

Explanation

The primary purpose of creating logical subnets within an IP network is to allow for more efficient use of IP addresses and improve network management. By dividing a larger network into smaller subnetworks, administrators can better control traffic flow, reduce network congestion, and allocate IP addresses in a manner that matches the specific needs of different parts of the organization. This segmentation also facilitates applying security policies and access controls more granularly.

While subnetting can help manage network traffic more efficiently, it does not directly increase the speed of the internet connection for all users. The speed of an internet connection is influenced by various factors, including the service provider, bandwidth, and the physical infrastructure, rather than the logical division of networks into subnets.

Creating logical subnets can contribute to enhancing network security by allowing for more specific application of security policies. However, subnetting itself does not encrypt data. Encryption is a separate process that involves converting data into a coded format to prevent unauthorized access.

Logical subnets are used to organize and manage IP networks more effectively, but they do not replace the need for physical network infrastructure. Physical components such as routers, switches, and cables are still required to build and operate a network. Logical subnetting works within the framework of this physical infrastructure to optimize its use and management.

Related Content

resources\questions\q_subnets_logical_subnets_n09.question.xml

Question 11 Correct

What does the Start of Authority (SOA) record identify?

- ○ The most frequently visited domain in the zone
- ◉ The primary authoritative name server for the zone ✓ Correct
- ○ The secondary name servers in the zone
- ○ The dynamic resource records in the zone

Explanation

The SOA record identifies the primary authoritative name server that maintains complete resource records for the zone, including modifications.

The SOA record does not track domain visitation frequency.

The SOA record specifies the primary, not secondary, name servers.

The SOA record does not specifically identify dynamic resource records.

Related Content

- 1.3.7 Binary and Hexadecimal
- 6.5.1 Host Names and Domain Names
- 6.5.2 DNS Hierarchy
- 6.5.3 Name Resolution Using DNS
- 6.5.4 Resource Record Types
- 6.5.5 Host Address and Canonical Name Records
- 6.5.6 Mail Exchange, Service, and Text Records
- 6.5.7 Pointer Records
- 6.5.8 DNS Server Configuration
- 6.5.9 Internal vs External DNS
- 6.5.10 DNS Security
- 6.5.11 Lab: Configure DNS Addresses
- 6.5.12 Lab: Create Standard DNS Zones
- 6.5.13 Lab: Create Host Records

6.5.14 Lab: Create CNAME Records

6.5.15 Lab: Troubleshoot DNS Records

6.5.16 Configuring DNS Caching on Linux

6.6.1 Client DNS Issues

6.6.2 Name Resolution Issues

6.6.3 nslookup

6.6.4 dig

6.6.5 Lab: Explore nslookup

6.6.6 Lab: Use nslookup

7.1.1 Transport Layer Security

9.4.4 DNS Attacks

10.1.5 Digital Certificates and PKI

10.4.5 Extensible Authentication Protocol and IEEE 802.1X

13.2.4 Internet Key Exchange

resources\questions\q_dns_resource_soa_record_identifry_n09.question.xml

Question 12 Correct

How many root level servers are there in the DNS hierarchy?

- 7
- 10
- 13 ✓ Correct
- 15

Explanation

There are 13 root level servers, labeled A to M, which are a critical part of the Internet's infrastructure, containing information about top-level domain servers.

7 is incorrect because it underestimates the number of root servers, which is officially 13.

10 is incorrect because it is not the correct number of root level servers.

15 is incorrect because it overestimates the number of root servers, which is officially 13.

Related Content

- 1.3.7 Binary and Hexadecimal
- 6.5.1 Host Names and Domain Names
- 6.5.2 DNS Hierarchy
- 6.5.3 Name Resolution Using DNS
- 6.5.4 Resource Record Types
- 6.5.5 Host Address and Canonical Name Records
- 6.5.6 Mail Exchange, Service, and Text Records
- 6.5.7 Pointer Records
- 6.5.8 DNS Server Configuration
- 6.5.9 Internal vs External DNS
- 6.5.10 DNS Security
- 6.5.11 Lab: Configure DNS Addresses
- 6.5.12 Lab: Create Standard DNS Zones
- 6.5.13 Lab: Create Host Records

6.5.14 Lab: Create CNAME Records

6.5.15 Lab: Troubleshoot DNS Records

6.5.16 Configuring DNS Caching on Linux

6.6.1 Client DNS Issues

6.6.2 Name Resolution Issues

6.6.3 nslookup

6.6.4 dig

6.6.5 Lab: Explore nslookup

6.6.6 Lab: Use nslookup

7.1.1 Transport Layer Security

9.4.4 DNS Attacks

10.1.5 Digital Certificates and PKI

10.4.5 Extensible Authentication Protocol and IEEE 802.1X

13.2.4 Internet Key Exchange

resources\questions\q_dns_structure_root_level_servers_n09.question.xml

Question 13

Correct

In the OSI model, what is the primary function of the Network layer?

- [x] The primary function of the Network layer is to move data around an internetwork using logical network and host IDs. ✓ Correct
- [ ] The primary function of the Network layer is to encode and convert data into signals suitable for transmission over the physical medium.
- [ ] The primary function of the Network layer is to establish, manage, and terminate connections between applications on different hosts.
- [ ] The primary function of the Network layer is to ensure reliable transmission of data across a physical link.

Explanation

The primary function of the Network layer is to move data around an internetwork using logical network and host IDs. The Network layer, or Layer 3 of the OSI model, is responsible for the logical addressing of data and its delivery across different networks, or an internetwork. It uses logical addresses, such as IP addresses, to ensure data packets are routed to the correct destination network and ultimately to the correct host within that network. Routers, which operate at this layer, use the information contained in the packet's network layer header to make forwarding decisions, guiding the packet through the internetwork hop by hop until it reaches its destination.

Encoding and converting data into signals suitable for transmission over the physical medium is the primary function of the Physical layer, or Layer 1 of the OSI model. Layer 1 is responsible for the transmission and reception of raw bit streams over a physical medium. It deals with the electrical, mechanical, procedural, and functional aspects of the physical connection between devices.

Establishing, managing, and terminating connections between applications on different hosts is the primary function of the Session layer, or Layer 5 of the OSI model. The Session layer is responsible for setting up, managing, and then tearing down sessions between presentation layer entities on different hosts. It provides mechanisms for controlling the dialogue between the two hosts, including synchronization and checkpointing.

Ensuring reliable transmission of data across a physical link is the primary function of the Transport layer, or Layer 4 of the OSI model. The Transport layer is responsible for providing reliable data transfer services to the upper layers. This includes the segmentation of data, acknowledgment of receipt, error correction through retransmission, and flow control.

Related Content

- 1.2.1 Open Systems Interconnection Model
- 1.2.5 Layer 3 - Network

- 1.2.8 OSI Model Summary
- 1.3.4 Network Layer Functions
- 1.3.6 The Internet
- 1.3.7 Binary and Hexadecimal
- 1.3.8 Lab: Explore a Single Location in a Lab
- 4.1.2 Layer 2 vs Layer 3 Addressing and Forwarding
- 4.2.3 Subnet Masks
- 6.2.2 DHCP Server Configuration
- 13.1.1 Wide Area Networks and the OSI Model
- 14.3.5 Cloud Firewall Security

resources\questions\q_layer3_description_n09.question.xml

Question 14 Correct

What does the IEEE 802.3af standard specify in terms of PoE?

- (selected) Power is supplied as 350mA@48V and limited to 15.4 W output. ✓ Correct
- Supplies at 30 W, with a maximum current of 600 mA.
- Supplies at 60 W (Type 3) or 90 W (Type 4).
- It is a standard for data encryption over PoE connections.

Explanation

Power is supplied as 350mA@48V and limited to 15.4 W output is correct because the 802.3af standard specifies that power is supplied at 350mA@48V with a maximum output of 15.4 W, suitable for devices requiring up to about 13 W.

Supplies at 30 W, with a maximum current of 600 mA is incorrect because this describes the 802.3at (PoE+) standard, which allows for higher power delivery.

Supplies at 60 W (Type 3) or 90 W (Type 4) is incorrect because this describes the 802.3bt (PoE++) standard, which allows for even higher power delivery.

It is a standard for data encryption over PoE connections is incorrect because the IEEE 802.3 standards relate to physical and data link layers, not data encryption.

Related Content

- 3.1.4 Transceiver Signal Strength Issues
- 3.3.5 Power Over Ethernet
- 3.3.8 Lab: Configure PoE
- 3.4.1 Hardware Failure Issues
- 3.4.7 Power Over Ethernet Issues
- 7.3.7 Lab: Connect VoIP 2
- 12.2.3 Wireless Surveys and Heat Maps

resources\questions\q_poe_ieee_standard_n09.question.xml

Question 15 ✕ Incorrect

What should be checked if the cable and connections are not the issue?

- ○ The power supply to the computer
- ○ The network adapter's functionality in Device Manager ✓ Correct
- ○ The router's firmware version
- ◉ The Ethernet port on the switch ✕ Incorrect

Explanation

The network adapter's functionality in Device Manager is the correct thing to check because it allows you to verify whether the computer is recognizing the network adapter and if it's functioning correctly. Issues here could include the device being disabled, drivers being outdated or corrupted, or the adapter failing. This step is crucial for identifying problems beyond the physical layer of connectivity.

The power supply to the computer is fundamental for the operation of all components, including the network adapter. However, if the computer is on and other functions are working, the power supply is likely not the issue related to network connectivity.

The router's firmware version can impact network performance and connectivity but is typically considered when troubleshooting broader network issues affecting multiple devices, rather than a single computer's connection problem.

The Ethernet port on the switch could be a factor in connectivity issues, especially in environments with multiple networked devices. However, this is usually checked if there's evidence of port-specific issues or after individual device troubleshooting (like checking the network adapter's functionality) does not resolve the problem.

Related Content

resources\questions\q_troubleshooting_strategies_adapter_device_manager_n09.question.xml

Question 16 Correct

What happens to a Windows host configured for dynamic addressing if it fails to obtain a lease?

- It uses a static IP address from the network configuration.
- It selects an address in the 169.254.0.0/16 range. ✓ Correct
- It disconnects from the network.
- It uses the last successful IP address lease.

Explanation

When a Windows host configured for dynamic addressing fails to obtain a lease, it automatically selects an IP address from the APIPA (Automatic Private IP Addressing) range, which is 169.254.0.0/16. This allows the host to communicate with other devices on the same local network, but it may not have access to external networks.

When a DHCP lease cannot be obtained, the host does not revert to a static IP address unless manually configured to do so.

The host does not disconnect from the network; it still maintains a local network connection using an APIPA address.

The host does not reuse the last successful IP address lease if it cannot contact the DHCP server.

Related Content

- 4.5.5 IPv6 Link Local Addressing
- 6.3.1 Automatic Private IP Addressing
- 6.3.2 IPv6 Interface Autoconfiguration and Testing
- 6.3.4 Lab: Explore APIPA Addressing
- 6.3.5 Lab: Explore APIPA Addressing in Network Modeler
- 6.3.6 Set Up Alternate Addressing
- 6.4.2 DHCP Issues

resources\questions\q_dhcp_issues_lease_failure_n09.question.xml

Question 17 Correct

A cybersecurity analyst is investigating a series of suspicious network activities that have been flagged by the intrusion detection system. The analyst notices a pattern of packets that have unusually large sizes, which could indicate an attempt to exploit vulnerabilities through fragmentation attacks.

To further analyze these packets and identify potential threats, the analyst decides to examine the IPv4 datagram headers of the captured packets.

Which field in the IPv4 datagram header should the analyst focus on to determine the size of these packets and assess the risk of fragmentation attacks?

- (●) Total Length field ✓ Correct
- ( ) Identification field
- ( ) Fragment Offset field
- ( ) Time to Live (TTL) field

Explanation

The Total Length field in the IPv4 datagram header specifies the total size of the packet, including the header and the payload. By examining this field, the cybersecurity analyst can determine the size of the packets and assess the risk of fragmentation attacks, as large packet sizes could be indicative of such threats.

The Identification field is used as part of IP fragmentation and reassembly, helping to identify fragments of the original IP datagram that belong together, but it does not indicate the size of the packet.

The Fragment Offset field is used in the fragmentation process to indicate where a fragment fits within the original packet. While it is related to fragmentation, it does not provide information on the total size of the packet.

The Time to Live (TTL) field is used to limit the lifespan of a packet, determining how many hops (routers) the packet can pass through before being discarded. It does not provide information on packet size or fragmentation.

Related Content

resources\questions\q_ipv4_header_total_length_scernario_n09.question.xml

Question 18 ✕ Incorrect

You've implemented a network where hosts are assigned specific roles, such as file sharing and printing roles. Other hosts access those resources, but they don't host services of their own.

Which type of network have you implemented?

- (●) Peer-to-peer ✕ Incorrect
- ( ) Client-server ✓ Correct
- ( ) Intranet
- ( ) Extranet

Explanation

In a client-server network, hosts have specific roles. For example, some hosts are assigned server roles, which allow them to provide network resources to other hosts. Other hosts are assigned client roles, which allow them to consume network resources.

In a peer-to-peer network, each host can provide network resources to other hosts or access resources located on other hosts, and each host is in charge of controlling access to those resources.

An intranet is a private network that uses internet technologies. Services on an intranet are only available to hosts that are connected to the private network.

An extranet is a private network that uses internet technologies, but whose resources are made available to external (but trusted) users. For example, you might create a website on a private network that only users from a partner company can access.

Related Content

- 1.1.1 Networking Concepts
- 1.1.2 Network Types
- 1.1.3 Network Topology
- 1.1.4 Star Topology
- 1.1.8 Lab: Create Network Topologies
- 1.2.3 Layer 1 - Physical
- 3.4.1 Hardware Failure Issues
- 3.4.6 Network Loop and Broadcast Storm Issues

5.5.1 Hybrid Topology

12.2.7 Other Wireless Network Types

14.4.5 Software-Defined WAN

resources\questions\q_net_concepts_client_server_01_n09.question.xml

Question 19 Correct

What actions does the use of Uninterruptible Power Supplies (UPSs) allow for during power anomalies in enterprise sites? (Select two.)

- [ ] Automatically repair damaged network cables.
- [ ] Permanently replace the main power source.
- [x] Shut down the system gracefully. ✓ Correct
- [ ] Increase the processing power of servers.
- [x] Switch to a secondary power source. ✓ Correct

Explanation

The following are actions that UPSs allow for during power anomalies:

- Switching to a secondary power source. UPSs provide temporary power during outages, allowing time to switch to a secondary power source like a generator. This ensures continuity of operations and prevents data loss.
- Shutting down the system gracefully. UPSs also allow for a graceful shutdown of systems in the event of a power failure. This helps in avoiding data corruption and loss by ensuring that all processes are properly closed before the system powers down.

UPSs are designed for temporary power provision during short-term outages, not as a permanent replacement for the main power source. They provide a bridge to more stable solutions or allow for safe shutdowns.

The purpose of UPSs is to maintain power during outages, not to increase the processing power of servers. They have no direct impact on the computational capabilities of network devices.

UPSs provide power backup; they do not have the capability to automatically repair physical damages such as those to network cables. Their function is purely related to power continuity.

Related Content

- 2.5.3 Power Management
- 3.4.1 Hardware Failure Issues
- 7.4.4 Fault Tolerance and Redundancy

resources\questions\q_hard_fail_power_anomaly_actions_n09.question.xml

Question 20 Correct

Where does VLAN ID configuration take place?

- On the end system
- On the switch interface ✓ Correct
- On the router
- On the network firewall

Explanation

VLAN IDs are configured on the switch interfaces to assign ports to specific VLANs. This is essential for managing network segmentation and traffic flow within a network.

End systems are not typically where VLAN configurations are applied. VLAN assignments are done on network devices like switches.

While routers can route traffic between VLANs, the VLAN ID configuration is done on switch interfaces.

Firewalls may enforce policies between VLANs but do not handle the VLAN ID configuration on switch interfaces.

Related Content

resources\questions\q_vlan_id_vlan_id_configuration_n09.question.xml

Copyright © CompTIA, Inc. All rights reserved.