

A Complete Rotor–Router Orbit and Frequency Theorem for Finite Strong Directed Multigraphs

Route-A structural certificate HCS-C181

Abstract

For every finite nonempty strongly connected directed multigraph with distinguished arcs and arbitrary local cyclic rotor orders, we classify the rotor–router permutation on recurrent unicycle states. If t_v counts directed spanning in-arborescences toward v , then $M = \gcd_v t_v$ is the number of recurrent orbits and $L = M^{-1} \sum_v d_v^+ t_v$ is their common exact length. Every orbit visits v exactly $d_v^+ t_v / M$ times and traverses each distinguished outgoing arc at v exactly t_v / M times. We derive every fixed count, $\zeta_{AM} = (1 - z^L)^{-M}$, the finite Koopman determinant and spectrum, and the Eulerian edge-once degeneration. This is a sinkless unicycle theorem, not a sandpile translation. Its natural finite quantization is exact, but the absence of arithmetic labels forces a Route-A stop.

Keywords: rotor–router; directed arborescence; unicycle; Eulerian digraph; dynamical zeta; permutation spectrum.

中文摘要

对任意有限非空强连通有向多重图及任意局部转子循环序，本文完整分类单环 状态上的转子路由置换。若 t_v 是指向顶点 v 的有向生成树数量，则 $M = \gcd_v t_v$ 等于循环轨道数，而 $L = M^{-1} \sum_v d_v^+ t_v$ 是共同精确 周期。每条轨道对顶点及每条可区分弧的访问频率均有闭式公式，并由此得到 全部不动点计数、动力学泽塔、有限置换行列式、谱重数及欧拉图退化。本结果 研究无汇点的单环动力学，不把它改写为沙堆平移；自然有限量子化虽精确，但缺少算术标签仍迫使甲路线停止。

1 Frozen rotor system

Let $G = (V, A)$ be a finite nonempty strongly connected directed multigraph. Loops and parallel arcs are allowed, and every arc is distinguished. At each vertex fix a cyclic order of outgoing arcs. A state consists of a chip vertex and one currently selected outgoing arc at every vertex. One tick first advances the rotor at the chip vertex and then moves the chip along the newly selected arc.

The selected arcs form a functional digraph. A *unicycle state* has exactly one directed cycle and places the chip on that cycle. These are the recurrent states. This classical orbit framework and its spanning-tree connection are prior work; see Pham [1]. We claim no novelty for the classical rotor–router orbit theorem or directed matrix-tree theorem. In particular, Pham’s Theorem 1 supplies the exact common orbit length and orbit count used below; our proof records that imported step before deriving the local distinguished-arc frequencies.

For $v \in V$, let t_v be the number of spanning in-arborescences oriented toward v , equivalently the v -cofactor of the row Laplacian $\Delta = D_{\text{out}} - A$. Put

$$M = \gcd_{v \in V} t_v, \quad L = \frac{1}{M} \sum_{v \in V} d_v^+ t_v. \quad (1)$$

2 Orbit and local-frequency classification

Theorem 1. *For every frozen graph and every choice of cyclic rotor orders, the recurrent permutation has exactly M orbits and every orbit has exact length L . On each orbit,*

$$\#\{\text{departures from } v\} = \frac{d_v^+ t_v}{M}, \quad \#\{\text{uses of each arc out of } v\} = \frac{t_v}{M}. \quad (2)$$

The recurrent phase has $ML = \sum_v d_v^+ t_v$ states.

Proof. On a complete recurrent orbit every rotor returns to its starting arc. Let x_v be the number of full turns made by the rotor at v . Every outgoing arc from v is then used x_v times, so flow balance gives

$$\Delta^T x = 0.$$

Strong connectivity makes this kernel one-dimensional with a positive primitive integer generator. The directed matrix-tree theorem places the cofactor vector $t = (t_v)$ in the same kernel, so its primitive reduction is t/M . Thus $x = q(t/M)$ for some positive integer q . Pham’s exact orbit-size theorem [1, Theorem 1], for the same advance-then-move unicycle model and allowing loops and multiple arcs, gives orbit length L . But the length is also $\sum_v d_v^+ x_v = qM^{-1} \sum_v d_v^+ t_v = qL$, so $q = 1$. This proves (2) and shows how the imported exact-return theorem fixes the otherwise undetermined kernel multiple.

For the state count, fix the chip at v and delete its selected rotor arc. The remaining selected arcs form an in-arborescence toward v . Conversely, an in-arborescence toward v and a choice of one of its d_v^+ outgoing arcs reconstruct a unique unicycle state with chip on the unique cycle. Thus there are $d_v^+ t_v$ states with chip v , and ML in total. Division by Pham's exact common orbit length gives exactly M orbits, consistently recovering the orbit-count clause of the same theorem. $\square$

3 Fixed counts, zeta, and finite quantization

Corollary 2. *For every $n \geq 1$,*

$$\# \text{Fix}(R^n) = \begin{cases} ML, & L \mid n, \\ 0, & L \nmid n, \end{cases} \quad \zeta_{\text{AM}}(z) = (1 - z^L)^{-M}.$$

On ℓ^2 of recurrent states, the permutation Koopman unitary U obeys

$$\det(I - zU) = (1 - z^L)^M,$$

and every L -th root of unity occurs with multiplicity M .

Proof. The recurrent permutation is a disjoint union of M cycles of length L . The trace, logarithmic zeta, and characteristic polynomial statements follow by cycle. $\square$

Corollary 3 (Eulerian degeneration). *If G is Eulerian, all t_v equal a common τ , so $M = \tau$, $L = |A|$, there are τ recurrent orbits, and every orbit traverses every distinguished arc exactly once.*

Proof. For an Eulerian graph, the all-ones vector lies in $\ker \Delta^T$. Uniqueness of its positive ray makes t_v constant. Theorem 1 then gives the claims. $\square$

4 Source boundaries and Route-A decision

The system has no sink and no stabilization. Its proof does not identify unicycles with recurrent sandpiles and does not use a critical-group translation. The finite Koopman operator is a natural quantization, but abstract reversal of each cycle requires a chosen basepoint; the source graph does not canonically provide those basepoints.

This separation is structural rather than terminological. The phase space contains a moving chip and a selected arc at every vertex; recurrence is the single-cycle condition. Deleting the chip rotor is used only as a counting bijection to an arborescence, not as a stabilization map or a group action.

The strict tuple is

$$(\text{AO_FAIL}, \text{A1_WEAK}, \text{A2_FAIL}, \text{A3_FAIL}, \text{A4_NATURAL_QUANTIZATION}).$$

The graph supplies complete primitive orbits and an exact finite unitary, but no rational-prime labels, prime-power weights, target amplitudes, target divisor, functional equation, or Weil compression. A0 failure therefore forces ROUTE_A_REJECTED; A4 cannot override the entry gate.

gate	decisive boundary
A0_FAIL	graph invariants have no rational-prime labels or prime-power weights
A1_WEAK	every recurrent orbit is classified, but no target amplitudes arise
A2_FAIL	the exact divisor consists only of finite-cycle roots of unity
A3_FAIL	there is no target functional equation, counting law, or Weil compression
A4_NATURAL_QUANTIZATION	the recurrent permutation gives a canonical finite Koopman unitary

References

- [1] T. V. Pham, *Orbits of rotor-router operation and stationary distribution of random walks on directed graphs*, Adv. Appl. Math. 70 (2015), 45–53, <https://arxiv.org/abs/1403.5875>.