



13 August 2026

PUBLIC REVIEW DRAFT:

DUNE Interface Document:

Slow Controls – Ground Impedance Monitor (GIZMo)

Manuel Arroyave

Public review copy. This file is not an approved or controlled EDMS revision. Site endpoints, executable fingerprints, access details, and source workbooks are omitted. Use the controlled delivery package for commissioning and acceptance.

Summary

This public review copy describes the interface between DUNE Slow Controls (SC) and the Ground Impedance Monitor (GIZMo). SC supports two hardware implementations: GIZMo Kria, built around an AMD/Xilinx Kria K26 SOM on the KR260 Robotics Starter Kit carrier, and legacy GIZMo, built around the ZedBoard. Both use the common supervisory OPC UA contract while retaining different internal hardware, firmware, operating-system, and control capabilities. The document separates the physical measurement layer, hardware-control layer, internal application protocols, public OPC UA interface, Ignition display and history, Detector Protection boundary, calibration authority, and commissioning gates.

DUNE Doc:	DUNE GIZMo–SC Interface Document	
EDMS Id:	Not a controlled EDMS copy	
Version:	0.8-public	
Last modified:	13 August 2026	
Prepared by:	Checked by:	Approved by:
Manuel Arroyave	TBD: GIZMo owner; SC; DPS	TBD

Distribution List

GIZMo system owner; DUNE Slow Controls; Detector Protection System; detector operations; installation and integration; controls cybersecurity; Ignition support.

History of Changes

Revision	Date	Author	History of changes
0.1	2026-08-12	M. Arroyave	Initial dual-platform draft and companion DCS intake spreadsheets.
0.2	2026-08-12	M. Arroyave	Reorganized as a layered interface-control document following the SC-PDS precedent. Distinguished native controller capability from presently exposed SC control and added the legacy controlled- expansion gates.
0.3	2026-08-12	M. Arroyave	Defined GIZMo Kria and legacy GIZMo as two supported hardware implementations, identified the K26 SOM/KR260 and ZedBoard platforms, and removed platform-precedence requirements.
0.4	2026-08-12	M. Arroyave	Audited all workbook numeric fields against the maintained Kria runtime, recovered legacy behavior, engineering records, and commissioning observations. Defined the then-proposed initial threshold, alarm timing, and removed inherited template example values.
0.5	2026-08-12	M. Arroyave	Set the initial threshold to 100 ohm for both implementations. Used the retained Kria SQLite history and read-only live samples from the connected ZedBoard to populate clearly labelled commissioning values and operating envelopes; confirmed that no OPC UA server currently runs on the ZedBoard.

0.6	2026-08-13	M. Arroyave	Implemented and deployed the initial monitoring-only off-board ZedBoard adapter. Added pinned target identity, hash-locked coherent RUN acquisition, explicit non-good unsupported values, and independent rejection of all OPC UA writes and methods.
0.7	2026-08-13	M. Arroyave	Delivery review synchronized document and workbook revision metadata, reconciled the selected signal attributes with the canonical model, completed identity and health summary rows, and incorporated the partial 27-cycle legacy-adapter pilot without closing its acceptance gate.
0.7-public	2026-08-13	M. Arroyave	Created a clearly labelled public review copy with site endpoints, executable fingerprints, access details, and controlled source workbooks omitted.
0.8-public	2026-08-13	M. Arroyave	Added the public human-facing connection, power-up, and construction-monitoring guide; identified the planned legacy OPC UA server as the production integration dependency while retaining the off-board adapter pilot as commissioning evidence; and aligned history guidance with the version-2 SQLite edge/replica contract.

Contents

1	Introduction	6
1.1	Applicable and reference documents	6
1.2	Definitions and requirement language	7
2	System Architecture	8
2.1	Layered architecture	8
2.2	Implementation topology	8
3	Physical and Electrical Interface	9
3.1	Measurement boundary	9
3.2	External connectors	9
3.3	Kria hardware layer	10

3.4	Legacy hardware layer	10
4	Link, Transport, and Internal Protocols	10
4.1	Controls network	10
4.2	Kria private interfaces	10
4.3	Legacy private interfaces	11
5	Public OPC UA Application Interface	11
5.1	Endpoint and information model	11
5.2	DataValue and quality semantics	12
5.3	Monitoring groups	12
5.4	Numeric-field convention	13
6	Configuration, Control, and Reset Semantics	13
6.1	Control classification	13
6.2	GIZMo Kria controls	14
6.3	Legacy GIZMo controlled expansion	15
7	Detector Control Display, Alarms, and History	16
7.1	Display	16
7.2	Sampling and freshness	16
7.3	Ignition history boundary	16
7.4	Alarms and Detector Protection	16
8	Calibration and Maintenance	19
8.1	GIZMo Kria	19
8.2	Legacy GIZMo	19
9	Security and Access Control	19
10	Responsibilities	20
11	Test Stand, Commissioning, and Acceptance	20
11.1	Physical and common interface acceptance	20
11.2	GIZMo Kria acceptance	21
11.3	Legacy GIZMo monitoring acceptance	21
11.4	Legacy GIZMo control acceptance	21

1 Introduction

The GIZMo monitors the impedance relationship between detector ground and building ground. It applies an AC stimulus, observes the returned signal through the installed current-transformer and analog path, calculates impedance-related quantities, and provides a local alarm indication. SC uses the public machine interface for authorized configuration and operations, operator display, alarms, and history.

The reviewed GIZMo Kria runtime (package version 0.4.5, OPC UA model 1.3.0) provides the native Kria endpoint. The legacy GIZMo runs the preserved 2017 ARM controller on its ZedBoard. SC shall support both implementations. A production legacy OPC UA server is under development for the same canonical namespace. The earlier monitoring-only adapter remains validation evidence, not the production dependency; it validates the controller against a controlled SHA-256 fingerprint before publishing data. The fingerprint is omitted from this public copy and retained in the commissioning record:

`<controlled-executable-sha256>`

This ICD specifies interfaces and ownership; it does not replace electrical schematics, the device software design, a Detector Protection design, or a traceable metrology procedure. In particular, existence of legacy calibrator hardware and a CAL command does not establish a production self- calibration process.

1.1 Applicable and reference documents

Document	Use in this ICD
DUNE-doc 1805 v.12, <i>Ground Impedance Monitor</i> documentation set	Legacy GIZMo engineering and setup documentation, including <i>Ground Impedance Monitor Engineering Note 170621</i> , <i>Impedance Monitor System Setup Instructions 170621</i> , <i>ZMon System Diagram 170616</i> , ZMon Amplifier Board drawing 176962, and the ZedBoard Rev D schematic.
DUNE-doc 27482 v.2, <i>Ground Impedance Monitor</i> test, calibration, and chassis documentation set	Legacy PMod ZMon Calibrator drawing 176971, revised amplifier and chassis drawings, test procedures, SD-card procedure, and recorded characterization data.
DUNE-doc 35392 v.2, <i>ORC Documents for DUNE Impedance Monitor Rack in FNAL HEERC G271</i>	Kria GIZMo rack, power, equipment, safety, and ORC context.

<i>GIZMo-Kria</i> , T. DeLine, 26 June 2025; and <i>GIZMo-Kria System Development/User Manual</i> , T. DeLine, 22 July 2026	Kria hardware, firmware, software, connections, startup, operator access, and calibration guidance.
Maintained GIZMo runtime 0.4.5 documentation, including <code>docs/opcua.md</code> and <code>docs/architecture.md</code>	Implemented GIZMo Kria public OPC UA model, service boundaries, and control behavior.
DUNE-doc 37315 v.1, <i>Communication Architecture for DUNE FD Slow Controls</i>	Current SC bridge-application, OPC UA, Ignition, protocol-hook, and hardware-emulator direction.

1.2 Definitions and requirement language

Term	Definition
GIZMo Kria	GIZMo implementation using an AMD/Xilinx Kria K26 SOM on the KR260 Robotics Starter Kit carrier.
Legacy GIZMo	GIZMo implementation using the ZedBoard and the preserved 2017 controller software.
Native capability	A function present in the platform software or service manager, whether or not it is exposed to SC.
Exposed control	A validated, authorized operation available through the public OPC UA contract.
Reset	An ambiguous word that shall be qualified as <i>clear alarm latch</i> , <i>restart measurement engine</i> , <i>reboot controller</i> , or <i>restore calibrator high-impedance state</i> . These actions are not interchangeable.
Authoritative alarm	Alarm decision produced by the device branch that controls its physical alarm outputs; not a state recreated by SC.
HIGH Z	Resistance outside the validated measurement range. It is a state, not a fabricated numeric endpoint.
CharacterizationOnly	Hardware or historical sweep data exist, but no production calibration has completed validation and controlled activation.

“Shall” denotes a normative requirement. “Should” denotes a recommended implementation.

Open values are marked TBD and shall not be interpreted as zero, disabled, or accepted by omission.

2 System Architecture

2.1 Layered architecture

Layer 0	Detector ground <-> building ground / CT / saturable inductor
Layer 1	GIZMo analog front end, ADC/DAC, FPGA, relays, local display
Layer 2	Platform controller and private application protocols Kria: ZMon :5055, ZMQ :5555, private control socket Zed: GIZMO.elf, FPGA MMIO, VM801P SPI, SysV service
Layer 3	Public interface: OPC UA Binary over UA TCP
Layer 4	Ignition: tags, controls, alarms, trends, and history

Only Layer 3 is the normal SC command/data boundary. Interfaces in Layer 2 are private implementation details and shall not become independent SC control paths. Layer 0 and Layer 1 work is a controlled electrical or calibration activity.

2.2 Implementation topology

Hardware	Acquisition and control path	SC consumers
GIZMo Kria	K26 SOM/KR260 measurement engine → native canonical OPC UA endpoint	Ignition tags, controls, alarms, trends, and history
Legacy GIZMo	ZedBoard GIZMO.elf → planned read-only legacy OPC UA server → canonical OPC UA endpoint	Ignition tags, controls, alarms, trends, and history; mutating controls are enabled only after the gates in Section 6.3

GIZMO-SC-005 SC shall support both GIZMo Kria and legacy GIZMo through the common OPC UA and Ignition interface described in this ICD. Platform-specific capability differences shall be represented explicitly; this ICD defines no precedence relationship between the implementations.

3 Physical and Electrical Interface

3.1 Measurement boundary

The installed measurement path consists of detector ground, building-ground reference, the stimulus path, saturable-inductor assembly, current transformer (CT), analog front end, and the associated cable shields and chassis bonding. The system drawing places the GIZMo, CT, saturable inductor, alarm beacon, and audio indication across the detector/building-ground monitoring boundary.

3.2 External connectors

Connection	Function	Interface rule
Stimulus Out / To Detector	AC stimulus-current driver output	Route only by the approved chassis drawing. Its center and shield are not generic isolated meter terminals.
CT In / From CT	Returned current-transformer signal into the amplifier/ADC	Connect to the CT output with the specified coaxial cable and polarity.
Monitor BNCs	Stimulus-current and CT-output observation	Oscilloscope diagnostics only; loading and grounding shall be controlled.
Detector / building ground	Quantity being monitored	High-current and protective bonding remain governed by the electrical design, not this OPC UA interface.
12-V input	Chassis/control power	Supply, fuse, connector, and power budget shall follow the hardware record.
Ethernet	SC network interface	Copper CAT5e/CAT6 or approved optical path to the restricted controls network.
USB, UART, JTAG	Local commissioning and recovery	Maintenance-only; not a production SC command path.
Beacon/audio	Local physical alarm outputs	Owned by GIZMo/DPS design; SC shall monitor rather than independently drive them unless separately approved.

The legacy rear centers labelled **TODETECTOR** and **FROMCT** are active stimulus/output and signal/input conductors. A powered resistance-mode measurement across them injects meter current into the active loop and is not a passive detector-ground measurement. The observed 50-kohm external-box response is useful characterization evidence but is not a calibration point.

3.3 Kria hardware layer

GIZMo Kria uses an AMD/Xilinx Kria K26 SOM mounted on the KR260 Robotics Starter Kit carrier, the custom control board, FPGA overlay, ADC/DAC signal path, relay drivers, 5-inch EVE display, alarm/audio connections, and two Processing-System Ethernet interfaces. The available records establish the K26/KR260 platform but do not establish the SOM commercial/industrial grade. The maintained software maps the installed FPGA resources at fixed addresses; the overlay identity and expected devices are monitored through the public model.

GIZMO-SC-013 The Kria overlay, control-board revision, calibration tables, and physical cable assignment shall form one controlled device configuration.

3.4 Legacy hardware layer

The legacy platform consists of a ZedBoard, 2017 FPGA bitstream, amplifier board 176962, PMod calibrator 176971, and VM801P/FT801 local display. The calibrator has five populated binary-weighted sections measured during characterization as 8.15, 16.17, 31.60, 63.52, and 127.12 ohm. The R6 footprint is unpopulated and participates in the high-impedance disconnect topology. These DMM readings are as-built engineering observations, not traceable standards.

The relay controller accepts a one-shot set/reset pulse for each latching relay. Finite states select combinations of R1–R5; the restored normal state opens the chain through the unpopulated R6 position. Any diagnostic that owns relay MMIO shall first stop `GIZMO.elf`, guarantee cleanup on normal exit, error, and interruption, verify restoration, and then restart the original controller.

4 Link, Transport, and Internal Protocols

4.1 Controls network

The SC-facing physical network is Ethernet. Each OPC UA server shall use a site-assigned address on the restricted controls network. Final hostname, address, route, switch port, VLAN, and firewall entries are installation data.

4.2 Kria private interfaces

Interface	Default	Purpose and policy
ZMon stream	TCP 5055	Private measurement-engine result stream used by the display and command bridge.

ZeroMQ command API	TCP 5555	Compatibility command API for threshold, averaging, calibration, ADC capture, time, and latch actions. It is not the preferred public SC interface.
Temperature stream	TCP 5005	Private temperature producer.
SDR stream	TCP 5556	Private raw acquisition stream; the OPC UA snapshot is for modest-rate inspection, not continuous waveform distribution.
Privileged helper	Unix socket	Root-owned, allow-listed operations including measurement-engine restart and setting the system/RTC time.
OPC UA	TCP 4840	Supported public monitoring and control interface.
Dashboard	HTTP 8080	Read-only operator/engineering view.

The package target `gizmo.target` is the local service-lifecycle boundary. Systemd starts, stops, supervises, and restarts the owned components. Service state is monitored through OPC UA; arbitrary `systemctl` execution is not an OPC UA capability.

4.3 Legacy private interfaces

The 2017 controller is launched by its SysV service in normal measurement mode. Its command parser has native commands including `RUN`, `CAL`, `set_th`, `read_adc`, `set_time`, `set_res`, and `set_rly`. The SysV wrapper supports start, stop, restart, and status. These facts establish native capability; they do not by themselves authorize remote SC control.

The Zed-to-VM801P display link is a private 16-bit SPI exchange at 4 MHz, mode 0, MSB-first. The controller sends a tagged threshold, tagged resistance, and an untagged comparison value; the display returns alarm bits used by the legacy controller. This SPI link is not an SC interface.

The commissioning adapter reads a coherent completed `RUN` frame from the exact executable through a restricted SSH path. It shall check one PID, the executable hash, coherent finite I/Q/magnitude/resistance, and the recovered transfer function before publishing a new sequence. Repeated polls of the same frame shall not manufacture new measurements.

5 Public OPC UA Application Interface

5.1 Endpoint and information model

The public protocol is OPC UA Binary over UA TCP, normally at:

```
opc.tcp://<assigned-gizmo-host>:4840
```

The namespace URI is `urn:fnal:gizmo`. Clients shall resolve that URI at connection time and shall not hard-code a namespace index. Canonical objects are rooted at `Objects/GIZMo`; deterministic string NodeIds include:

```
GIZMo.Identity.*
GIZMo.Measurement.*
GIZMo.Alarm.*
GIZMo.Configuration.*
GIZMo.Operations.*
GIZMo.Calibration.*
GIZMo.Health.*
```

Model 1.x revisions preserve NodeId, datatype, rank, and physical meaning. A breaking change requires a new major-version namespace. The recovered `SimpleOPCUAServer/CommandObject` tree may remain for migration, but new SC integration shall use the canonical model.

5.2 DataValue and quality semantics

Every variable shall provide its OPC UA datatype, StatusCode, and source timestamp. Unknown numeric values shall not be exposed as plausible zero. Before a first sample, the status is `BadWaitingForInitialData`; a retained sample after loss may be `UncertainLastUsableValue`; an unavailable platform feature is `BadNotSupported` or `BadDataUnavailable`.

GIZMO-SC-020 `Resistance0hm` is a physical value only when `ResistanceRange=InRange`. HIGH Z shall be an explicit range state with a null/NaN resistance and non-good quality, never a fabricated 500- or 999-ohm measurement.

GIZMO-SC-021 `Alarm.Active`, when available, shall come from the device's authoritative alarm branch. SC, the OPC UA producer, and Ignition shall not recompute it from the resistance and threshold readbacks.

5.3 Monitoring groups

The canonical model contains Identity, Measurement, Alarm, Thermal, Time, OperatingSystem, Network, Storage, Firmware, Services, Calibration, SDR, Configuration, Operations, and Health groups. The two platform intake lists are the detailed selected SC integration catalogs: they contain the production-facing variables, controls, command readbacks, and requested model additions defined by this ICD, rather than all native diagnostic leaves. Unsupported legacy fields remain present only when needed for contract compatibility and carry a non-good StatusCode.

5.4 Numeric-field convention

In the companion intake spreadsheets, *Sensor Span* is a verified software bound or documented presentation domain, *Nominal Value* is the requested initial value or a clearly identified current observation, and *Desired Range* is the initial normal or commissioning check band. A wider authorized write range, where one exists, is stated in Notes. The Low/High, delay, deadband, and action columns define Ignition alarm configuration only. A blank cell means that no supported number or action has been established; it is not zero and it is not “not applicable” data copied from the intake template. Notes distinguish implemented bounds, current device/package values, measured observations, and provisional commissioning choices.

6 Configuration, Control, and Reset Semantics

6.1 Control classification

Operation	Kria native / OPC UA	Zed native	Zed initial OPC UA
Set alarm threshold	Yes / read-write	<code>set_thN</code>	Read-only until command-broker gate
Set averaging / reads	Yes / read-write	Fixed RUN implementation; launch argument controls cadence, not the same averaging semantics	Read-only
Clear alarm latch	Yes / <code>ClearLatch</code>	No equivalent latch protocol in the legacy display/controller path	Not supported
Restart measurement engine	Yes / local allow-listed helper; not presently a canonical method	SysV <code>restart</code>	Not exposed initially
Reboot controller	Linux capability / not a canonical method	Linux capability	Not exposed
Capture ADC	Yes / <code>CaptureAdc</code>	<code>read_adc</code>	Not exposed initially
Normalize magnitude	Yes / method supported	No validated equivalent	Not supported

Set system time	Yes / <code>SetSystemTime</code>	<code>set_time</code> ; target clock is historically stale	Not exposed initially
Calibration sweep	Yes / <code>StartCalibration</code>	<code>CALN</code>	Maintenance- only and disabled initially
Direct relay/resistor state	Native maintenance capability	<code>set_res</code> , <code>set_rly</code> , or reviewed diagnostic	Never a routine SC control

Thus the system is not monitor-only: GIZMo Kria already supports configuration and controlled actions. The initial legacy OPC UA production release is deliberately monitor-only, even though its controller and hardware can perform several actions. This is a safety and interface-maturity restriction, not a hardware limitation.

6.2 GIZMo Kria controls

GIZMo Kria exposes two writable UInt32 configuration variables. Their stable NodeIds and ranges are:

<code>GIZMo.Configuration.ThresholdOhm</code>	0 .. 1,000,000 ohm
<code>GIZMo.Configuration.AveragesPerCalculation</code>	1 .. 1,000,000

The Kria package initializes the threshold and averaging count to 100. For initial joint commissioning, SC shall request 100 ohm and verify the live `Measurement.ThresholdOhm` readback. This value matches the sustained setpoint in the retained Kria history; a brief 2-kohm commissioning excursion is test evidence and is not a desired operating value. Although the firmware accepts zero, the initial Ignition operator range is 1–500 ohm because zero effectively disables the resistance-threshold branch. The accepted OPC UA bounds remain unchanged.

It exposes the following typed methods and command-result variable:

```
GIZMo.Operations.ClearLatch()
GIZMo.Operations.StartCalibration(UInt32)
GIZMo.Operations.CaptureAdc()
GIZMo.Operations.NormalizeMagnitude()
GIZMo.Operations.SetSystemTime(DateTime)
GIZMo.Configuration.LastCommandResult
```

GIZMO-SC-030 SC writes and methods shall be bounded, role-authorized, logged, and followed by readback of the resulting state. A transport-level success alone does not prove that the requested physical state was reached.

GIZMO-SC-031 Clearing the latch shall not suppress an active physical alarm. A device restart or reboot shall not be described as “clear latch.”

GIZMO-SC-032 Restarting `gizmo-zmon.service` and rebooting the Kria are local maintenance/recovery actions until separately specified as canonical OPC UA methods.

SC shall not infer those permissions from writable service-status nodes; service-status nodes are read-only.

6.3 Legacy GIZMo controlled expansion

The first ZedBoard OPC UA server release is a read-only validation pilot. Afterwards, controls may be introduced one at a time through an allow-listed broker; SC shall never pass arbitrary shell text or raw MMIO values to the target.

As verified on 12 August 2026, the preserved target had no OPC UA server and TCP port 4840 was closed. On 13 August 2026 a monitoring-only off-board adapter was deployed temporarily to validate coherent acquisition and failure semantics. The production dependency is now the read-only legacy OPC UA server under development. It shall pin or otherwise verify target identity, publish only validated coherent completed RUN frames, keep all variables client read-only, and return **BadNotSupported** for operation methods. No historian or production Ignition binding is enabled until the Stage 0 gate below passes. The legacy controller remains the sole owner of FPGA/MMIO and relay resources.

Stage	Candidate capability	Release gate
0	Monitoring only	100 coherent cycles match the local display; restart, stale, wrong-hash, partial-frame, and network-loss tests pass.
1	Measurement-engine restart/status	Exact target identity; serialized service ownership; timeout; post-restart PID/hash/freshness readback; audit.
2	Threshold write	Exact command grammar and numeric bounds; persisted or restart behavior documented; new threshold returned by the controller/display; authorization and rollback tested.
3	ADC capture and clock correction	Output-file ownership, bounded transfer, timeout, target-time quality, and restoration of normal RUN mode tested.
4	Calibration sweep	Approved isolated fixture; exclusive relay ownership; raw I/Q and state provenance; guaranteed HIGH Z cleanup; independent validation; no automatic activation.

GIZMO-SC-033 A failed, timed-out, or interrupted legacy command shall leave the last verified normal measurement mode or report a latched command-failure state requiring maintenance. It shall not report success from command submission alone.

GIZMO-SC-034 Direct `set_res` and `set_rly` shall remain expert, isolated maintenance operations. They shall not be general-purpose Ignition buttons or writable tag values.

GIZMO-SC-035 A future restart method shall name its scope explicitly, for example `RestartMeasurementEngine`; a generic `Reset` method is prohibited.

7 Detector Control Display, Alarms, and History

7.1 Display

Ignition shall show source identity, endpoint health, sample age, measurement quality, resistance/range, threshold, calibration state, and relevant control capabilities. The hardware implementation shall be labelled *GIZMo Kria (K26/KR260)* or *Legacy GIZMo (ZedBoard)* wherever it could be ambiguous. HIGH Z is rendered as a state, not as a precise endpoint. The local display remains an independent commissioning reference; disagreement creates a diagnostic event and never triggers automatic calibration.

7.2 Sampling and freshness

Kria measurement data update nominally each second; platform data update at 10- or 30-second cadence. Clients should use subscriptions. The legacy server may poll each second but shall increment `Measurement.Sequence` and write to Ignition history only when it detects a new coherent completed RUN result. A stale source becomes non-good within two expected completed cycles.

7.3 Ignition history boundary

Ignition shall subscribe directly to each GIZMo OPC UA endpoint and shall own the production tag history. History shall preserve the reported device identity, OPC UA source timestamp, `StatusCode`, null/HIGH Z gaps, and command audit events. The SC integration requires no intermediate history service between OPC UA and Ignition. Ignition history failure shall not stop local measurement or physical alarm indication.

7.4 Alarms and Detector Protection

SC shall alarm separately on physical ground-impedance alarm, communication loss, stale data, non-good measurement quality, identity mismatch, and command failure. An unavailable legacy `Alarm.Active` remains unknown; it shall not be converted to clear/false.

The following values are the initial SC configuration. A provisional operating envelope is a rounded commissioning check band derived from retained or live observations; it is not automatically an alarm threshold. Such values may be revised through change control without changing the OPC UA contract.

Parameter	GIZMo Kria	Legacy GIZMo	Basis/status
Resistance presentation domain	0–500 ohm; higher values are HIGH Z	0–500 ohm documented display domain; higher values are HIGH Z	Kria implemented; legacy metrology still requires installed-loop validation
Threshold accepted range	Firmware/OPC UA: 0–1,000,000 ohm; initial operator range: 1–500 ohm	Documented operating policy: integer 1–500 ohm	Verified implementation/-documentation bounds
Initial threshold	100 ohm; package default and sustained retained-history value	100 ohm; confirmed in 15 direct controller frames and 27 validation- adapter pilot cycles	Requested initial setpoint
Resistance comparison	Alarm when resistance is strictly less than the live threshold	Alarm-return bits assert when rounded displayed resistance is strictly less than threshold	Recovered device behavior
Additional Kria phase alarm	If resistance is greater than 8 ohm and the absolute interpolated-versus-atan2 phase difference exceeds 1.5 degrees	No validated equivalent	Implemented Kria logic
Ignition physical-alarm trigger	Alarm.Active=True , 0-s on-delay, no additional SC hysteresis	Disabled until actual return-word readback is exposed and validated; then the same Boolean trigger/timing applies	Initial requested SC configuration

Automatic action	Annunciate and direct operator response; no automatic power or protection command	Same	Initial interface scope
------------------	---	------	-------------------------

The Kria measurement engine contains no alarm on-delay or hysteresis in the reviewed decision path. The recovered legacy display comparison likewise has no delay or hysteresis. SC therefore adds neither: the Ignition on-delay is 0 s and the deadband field is blank. Ignition shall alarm on the Boolean **Alarm.Active**; it shall not create a second resistance comparator that could disagree with the phase-aware Kria decision or the legacy rounded-value decision.

The retained Kria SQLite replica covers 27 July through 3 August 2026 and contains 560,762 fast samples, 56,082 platform samples, 9,457 minute rollups, and 227 transition events. It confirms a sustained 100-ohm threshold, a stable 1436-Hz stimulus value, HIGH Z as the predominant normal range state, and both implemented alarm-reason branches. Its steady-state distributions are used to populate provisional Desired Range fields for temperatures, utilization, available memory, phase, and lock-in counts. Commissioning and startup excursions are retained in Notes but are not promoted to desired values. The retained run was captured under model 1.3.0 and the then-installed runtime 0.4.4; the maintained public source baseline reviewed for this ICD is runtime 0.4.5.

A read-only live check of the connected legacy board on 12 August 2026 collected 15 coherent completed RUN frames from the unchanged **GIZMO.elf**. The controller returned a 100-ohm threshold, 15 accumulations, 111.554–111.902 ohm calculated resistance, and a 112-ohm green display. The I, Q, magnitude, and derived **atan2** observations are recorded in the legacy workbook as same-setup commissioning envelopes. They do not validate the missing CT/inductor path or the full detector-loop calibration.

The deployed adapter subsequently captured 27 contiguous cycles (**Sequence 21–47**) on 13 August 2026. Resistance was 111.465703–112.010978 ohm (mean 111.722419 ohm), the threshold remained exactly 100 ohm, and the calculated legacy display-equivalent rounding was 112 ohm in 26 cycles and 111 ohm in one. Target communication was then lost before 100 cycles. The captured values carried **UncertainLastUsableValue** and **Measurement.Quality=Uncertain**, consistent with the unvalidated legacy measurement path; after the loss, the adapter exposed **BadNoCommunication** and **Health.Overall=Failed** rather than fresh data. This adds evidence for the attributes and loss semantics but does not close **OPEN-05**.

No reviewed GIZMo or SC source establishes numerical temperature, CPU, memory, storage, or similar supervisory alarm thresholds. Observed envelopes therefore remain monitor/trend checks and the spreadsheet alarm cells remain intentionally blank. Approved limits can be added without changing the OPC UA NodeIds.

Priority, response ownership, and any Detector Protection action still require joint approval by the GIZMo owner, SC, DPS, and operations. A required hard protective action shall not depend only on Linux, OPC UA, or Ignition.

8 Calibration and Maintenance

8.1 GIZMo Kria

GIZMo Kria calibration is a controlled maintenance method, not an automatic SC reaction. Production tables shall be staged, validated, content-hashed, activated atomically, and rollback-tested. Success, error, timeout, process termination, and power-interruption paths shall restore and verify the normal relay state. Calibration state and the active table identities are published through OPC UA.

8.2 Legacy GIZMo

The legacy **CALN** command selects 32 R1–R5 states and logs lock-in measurements. It does not fit, validate, persist, or activate a transfer function; it does not use the abandoned **calib2.txt**; and it does not guarantee normal-state restoration at completion. Starting **RUN** restores the normal **SetRes(-1)** selection, but an interrupted calibration can leave a finite test resistance selected.

Accordingly, the initial endpoint reports **Calibration.State=CharacterizationOnly** or **Unvalidated**. A future calibration workflow requires the restored CT/saturable-inductor fixture, measured standards, a common runtime/calibration acquisition primitive, raw I/Q and relay-state records, up/down sweeps, blind validation, clipping and hysteresis checks, guaranteed cleanup, atomic model activation, and rollback. Capacitance remains unsupported until mixed R/C characterization establishes a defensible model.

9 Security and Access Control

Both endpoints belong on the restricted controls network or behind approved authenticated transport. Final certificates, trust lists, usernames/roles, and firewall rules are installation data jointly assigned by SC and site cybersecurity.

GIZMo Kria currently supports an explicitly configured insecure OPC UA policy for an isolated network; serialization is not encryption. Production deployment shall document whether that exception is accepted or deploy the site certificate and role policy.

The legacy commissioning transport shall pin the SSH host key and use a restricted identity/command. Unrestricted root SSH is not a production command interface. The control broker shall allow only typed operations with bounds, mutual exclusion, timeout, readback, audit, and failure cleanup. It shall not expose arbitrary command strings, environment values, file paths, shell execution, FPGA MMIO, or relay bit patterns.

Credentials, private keys, and unbounded log text shall not be published as OPC UA values or Ignition history/audit events.

10 Responsibilities

Area	GIZMo system owner	SC / other group
Physical system	Supply, label, install, maintain, and document the chassis, analog chain, CT/inductor, calibrator, display, power, alarms, and cables.	I&I provides approved routing and installation support; SC does not alter the analog or ground wiring.
Device software	Maintain Kria runtime/overlay and the preserved Zed image; define meanings, control effects, safe states, and rollback.	SC supplies the integration framework and endpoint host resources where applicable.
OPC UA	Implement and test the canonical producer/server and readbacks.	SC integrates tags, quality, certificates, roles, alarming, and displays in Ignition.
Controls	Define typed operations, bounds, state transitions, and cleanup.	SC implements role-authorized operator workflow and audit; operations approves production use.
Calibration	Own standards, method, fits, validation, activation, rollback, and relay cleanup.	SC displays state/history and provides authorized workflow; it does not infer validity.
History	Publish device identity, quality, source time, model version, and command audit through OPC UA.	SC configures Ignition tag history, retention, restore, and operational access.
Protection	Define hazards and required physical response.	DPS owns reviewed hard protection; SC owns supervisory alarm presentation.

11 Test Stand, Commissioning, and Acceptance

11.1 Physical and common interface acceptance

Before SC sign-off, the parties shall:

- verify connector labels, power, fusing, shield/ground assignment, CT polarity, and the

approved stimulus path;

- resolve the namespace URI and verify every required NodeId, datatype, access class, EngineeringUnits value, StatusCode, and source timestamp with a generic OPC UA client;
- verify DeviceId, platform, runtime/ELF identity, endpoint, and time;
- force disconnect, stale data, restart, and out-of-range conditions and confirm non-good quality and last-good semantics;
- confirm HIGH Z is never persisted as a fabricated numeric value;
- verify Ignition display, alarm journal, command audit, trends, and history identity separation; and
- demonstrate that OPC UA or Ignition-history failure does not stop local measurement or physical alarm indication.

11.2 GIZMo Kria acceptance

All maintained runtime tests shall pass. Threshold and averaging writes shall enforce type and range; every method shall report a bounded result. Latch clear, time correction, ADC capture, magnitude normalization, and calibration shall be tested with authorization and readback. Calibration testing shall include error/interruption cleanup and rollback. A 24-hour soak and power-interruption recovery test shall complete before production approval.

11.3 Legacy GIZMo monitoring acceptance

At least 100 completed cycles shall match the physical display's rounded resistance, including identical consecutive readings. Wrong hash, multiple or changed PID, target restart, server restart, network outage, partial update, stale frame, and non-finite values shall not produce a false fresh sample. During this pilot, every write/method shall fail explicitly without reaching the controller or relay hardware. Ignition shall retain the ZedBoard samples with their reported device identity, source timestamp, and StatusCode.

11.4 Legacy GIZMo control acceptance

Each control stage in Section 6.3 requires a separate test record. Tests shall cover allowed and rejected values, simultaneous requests, broker/SSH loss, controller crash, timeout, power interruption, command readback, audit completeness, safe-state restoration, and rollback to the monitoring-only release. Calibration and relay tests additionally require an approved isolated electrical setup and independent observation of the restored HIGH Z state.

12 Open Items and Change Control

ID	Open item / release gate	Owner
OPEN-01	Assign EDMS identifier, reviewers, approvers, and controlled distribution.	GIZMo + SC
OPEN-02	Assign production endpoint hostnames/IPs, switch ports, certificate policy, trust lists, roles, and firewall rules.	SC + cybersecurity
OPEN-03	Review the requested 100-ohm threshold and zero added delay/no-hysteresis configuration; approve final priority, response owner, and any DPS action.	GIZMo + SC + DPS
OPEN-04	Add explicit Platform, AcquisitionAdapter, ValidatedResistanceMaximumOhm, and capability nodes in a backward-compatible model revision.	GIZMo software
OPEN-05	Complete the legacy OPC UA server's 100-cycle read-only acceptance.	GIZMo + SC
OPEN-06	Expose and validate off-board readback of the actual legacy alarm-return word used by the controller. The bit meanings and physical SPI exchange have been recovered; the server shall not synthesize this readback from resistance.	GIZMo firmware
OPEN-07	Define, implement, and test the allow-listed legacy command broker beginning with measurement-engine restart and threshold control.	GIZMo software + SC
OPEN-08	Decide whether a canonical RestartMeasurementEngine method is required for both platforms; do not add a generic reset command.	GIZMo + SC + operations
OPEN-09	Restore the CT/saturable-inductor fixture and validate legacy resistance/phase calibration with measured external standards.	GIZMo hardware

Any change to a connector, electrical reference, NodeId, datatype, physical meaning, access class, command effect, alarm ownership, calibration authority, safe state, or historized-field set requires joint review and a new controlled revision, including review of source identity, quality semantics, and retention.