

EGA 64-Colour Hardware Palette

Pick any 16 of these 64 to display at once

Each primary (R/G/B) carries 2 bits → 4 intensity levels (00, 55, AA, FF) → $4^3 = 64$ total. Gold border = boot-default 16.

★ #000000 0,0,0	#000055 0,0,85	★ #0000AA 0,0,170	#0000FF 0,0,255	#005500 0,85,0	#005555 0,85,85	#0055AA 0,85,170	#0055FF 0,85,255
★ #00AA00 0,170,0	#00AA55 0,170,85	★ #00AAAA 0,170,170	#00AAFF 0,170,255	#00FF00 0,255,0	#00FF55 0,255,85	#00FFAA 0,255,170	#00FFFF 0,255,255
#550000 85,0,0	#550055 85,0,85	#5500AA 85,0,170	#5500FF 85,0,255	#555500 85,85,0	★ #555555 85,85,85	#5555AA 85,85,170	★ #5555FF 85,85,255
#55AA00 85,170,0	#55AA55 85,170,85	#55AAAA 85,170,170	#55AAFF 85,170,255	#55FF00 85,255,0	★ #55FF55 85,255,85	#55FFAA 85,255,170	★ #55FFFF 85,255,255
★ #AA0000 170,0,0	#AA0055 170,0,85	★ #AA00AA 170,0,170	#AA00FF 170,0,255	★ #AA5500 170,85,0	#AA5555 170,85,85	#AA55AA 170,85,170	#AA55FF 170,85,255
#AAAA00 170,170,0	#AAAA55 170,170,85	★ #AAAAAA 170,170,170	#AAAAFF 170,170,255	#AAFF00 170,255,0	#AAFF55 170,255,85	#AAFFAA 170,255,170	#AAFFFF 170,255,255
#FF0000 255,0,0	#FF0055 255,0,85	#FF00AA 255,0,170	#FF00FF 255,0,255	#FF5500 255,85,0	★ #FF5555 255,85,85	#FF55AA 255,85,170	★ #FF55FF 255,85,255
#FFAA00 255,170,0	#FFAA55 255,170,85	#FFAAAA 255,170,170	#FFAAFF 255,170,255	#FFFF00 255,255,0	★ #FFFF55 255,255,85	#FFFFAA 255,255,170	★ #FFFFFF 255,255,255

The 4 intensity levels per primary are 0x00, 0x55, 0xAA, 0xFF – i.e. 0%, 33%, 67%, 100%. EGA's monitor cable carries those 6 bits as RGB + rgb (uppercase = high-intensity bit, lowercase = low-intensity bit). The boot-default 16 (gold) match the CGA palette for backwards compatibility; apps could remap any of the 16 palette registers to any of the 64.