FasterCap 3D Input Files

Triangular panel definitions ('T' statement)

```
Syntax: T <condname> <x1> <y1> <z1>   <x2> <y2> <z2>   <x3> <y3> <z3>   [<xref> <yref>
<zref>]
```

The 'T' element at the beginning of a line defines a triangular panel. If the triangular panel belongs to a conductor surface, the `<condname>` parameter is used to associate the panel to a parent conductor named `<condname>`. If the triangular panel belongs to a dielectric surface, the `<condname>` parameter is ignored. The *(x1, y1, z1)*, *(x2, y2, z2)*, *(x3, y3, z3)* 3D points specify the coordinates of the three corners of the panel; the coordinates must be entered in clockwise or counterclockwise order starting from any one corner.
In case the panel is part of a dielectric interface, you can use the optional coordinates *(xref, yref, zref)* to specify a reference point; see 3D Dielectric definitions ('D' statement) for more details about dielectric interfaces.

Example 1:

```
T mypyramid  1.0 1.0 0.0  1.0 0.0 0.0  1.0 0.0 1.0
```

This input file fragments specifies a face of the surface of a conducting pyramid, whose name is `mypyramid`.

Example 2:

```
T onepyramid  0.0 0.0 0.0  1.0 0.0 0.0  0.0 1.0 0.0
T otherpyramid  0.0 1.0 0.0  1.0 1.0 0.0  1.0 1.0 1.0
T onepyramid  0.0 0.0 0.0  1.0 0.0 0.0  0.5 0.5 1.0
```

This input file fragments specifies two face of the surface of a conducting pyramid, whose name is `onepyramid`, and one face of the surface of a second conducting pyramid, whose name is `otherpyramid`.

Example 3:

```
T mypyramid  1.0 1.0 0.0  1.0 0.0 0.0  1.0 0.0 1.0  0.0 0.0 2.0
```

This input file fragments specifies a face of the surface of a dielectric pyramid, whose name is `mypyramid`, with a panel-specific dielectric reference point at (0,0,2).