



BENCHMARK REPORT

Direction-response Benchmark

Matched-state native Nestopia and FCEUmm response measurements.

2026 EDITION / IAIN BENNETT / MIT LICENSE

The **PowerGlove Vision Controller (Arduino UNO Q)** performs the camera, recognition, and send stages measured in this record.

This deterministic headless benchmark compares the same exact Super Glove Ball ROM through its native packet path and its conventional FCEUmm joystick path. Gun.Smoke remains available as an optional positional-FCEUmm reference. This is a software validation tool, not a substitute for camera, display, or physical cabinet testing.

Reproducible inputs

Lane	Core	Exact game image
Native coordinates	Nestopia PowerGlove built from pinned Nestopia revision 5a1cd378cb46ca9ccc2dd6f8b2b6a79ab986052e plus the repository patch	Super Glove Ball (USA), SHA-256 ad60ef1b62cd1b3bc02a9320376067347a8ab2ebbe46e1616693d8379c9d9a7b
Standard joystick	Stock FCEUmm revision 236ccdfc911e84c60feab6b9d0699c2d440a8de14	The same exact Super Glove Ball (USA) image
Optional standard-D-pad reference	The same stock FCEUmm revision	Gun.Smoke (USA), SHA-256 4ad9629a2bacc158a7f50975869c7dfe533567ae399a5bdc5df2240286df259f

ROMs stay outside the project and every result is tied to its digest. Gun.Smoke uses the positional Program G mapping, making it a useful second FCEUmm exercise of the shared camera-direction recognition when supplied.

Method

The runner boots each exact ROM into play and saves one emulator state. For each direction it restores that same state twice: once for the baseline and once with only the candidate input changed. It records the first emulated video frame whose checksum differs. Release uses the same comparison after eight frames of held input: continuing the hold is the baseline and returning to neutral is the sole change.

FCEUmm also records whether the libretro input callback was polled on the first changed frame and which input-device API it requested. For Super Glove Ball it requested only libretro device [1](#), the standard joypad, confirming that the native state file is not part of that lane. The native lane publishes one coherent state immediately before every emulated frame; the custom core's packet trace is the separate evidence that this state is sampled once per frame. The shared recognition check proves all four directions activate at [0.29](#) normalized displacement and release at [0.13](#), on the responsive side of the configured [0.28/0.14](#) boundaries. It also drives the adaptive native coordinate filter directly. A large X/Y change must use the strongest follow rate immediately, reach at least 90% of its target within 150 ms, and preserve the bounded neutral-jitter check.

Results

Three complete executions produced byte-identical reports.

Lane	Directions	First visible activation	First visible release	First-frame input pickup
Super Glove Ball / lr-nestopia-powerglove	Left, right, up, down	Frame 3, about 50.0 ms at 60 Hz	Frame 3, about 50.0 ms at 60 Hz	Native state published before frame; per-frame packet consumption established by the trace runner
The same Super Glove Ball ROM / stock FCEUmm	Left, right, up, down	Frame 3, about 50.0 ms at 60 Hz	Frame 3, about 50.0 ms at 60 Hz	Standard joypad callback polled on frame 1; no native packet input
Gun.Smoke / stock FCEUmm reference	Left, right, up, down	Frame 2, about 33.3 ms at 60 Hz	Frame 2, about 33.3 ms at 60 Hz	Standard joypad callback polled on frame 1

The native positive-X sweep also diverged on frame 3 at every tested magnitude: [1024](#), [2048](#), [4096](#), [8192](#), [16384](#), and [32767](#). The smallest step is about 3.1% of the positive signed coordinate range, so the test demonstrates continuous small-motion response rather than only edge-to-edge movement.

The same-ROM visual comparison exposed and corrected a native Y-axis wrapping error that a checksum-only test had missed. The corrected trace now returns [\\$80](#), [\\$00](#), and [\\$7F](#) for Y minimum, center, and maximum, and the corresponding screens place the Robo-Glove at bottom, center, and top. Conventional FCEUmm directions also reach their matching screen edges, but they do so as held digital commands; native coordinates specify an absolute target position. This is the substantive gameplay difference between the two modes even though their first visible response occurs on the same emulated frame in this ROM.

These numbers are the first input-caused *visible* frame, not a camera-to-screen wall-clock claim. Camera capture cadence, the 75 ms Academy polling interval, display buffering, and physical display latency are intentionally outside this headless core benchmark.

The Dashboard now reports rolling camera-read-to-send and changed-control-to-send p50/p95 measurements. Those cover the PowerGlove Vision Controller software stage for both FCEUmm and native X/Y. Receiver publication and the core's next-frame consumption remain separate stages: the coherent native record timestamps publication on RetroPie after packet validation and virtual-gamepad writes, rather than socket arrival, and the headless core benchmark publishes the changed record immediately before an emulated frame.

Repeatable camera comparison

[scripts/record-vision-benchmark.py](#) records a temporary local 30-second cue sequence containing full-field and short movement, neutral jitter, A/B, rolls, Closed Hand, push, pull, tracking recovery, and near/far poses. The companion [scripts/benchmark-vision-replay.py](#) runs the same full frames through MediaPipe Hands with 1, 2, and 4 inference threads, plus MediaPipe Tasks Video when its model is supplied. Each runs at 640×480 and a full-field 512×384 resize with preview work both closed and open; neither resolution crops the image.

The replay report includes inference p50/p95, detection continuity, cue recognition, first recognition within each cue, neutral false activations, coordinate jitter, and preview cost. Live Dashboard readings remain authoritative for latest-camera-frame age because an offline replay has no live capture queue. The temporary AVI and cue sidecar must be

deleted after aggregate conclusions are retained. The proven 640×480 configuration remains the default unless a candidate improves p95 by at least 15%, introduces no neutral false activation, meets the response targets, and loses no more than one percentage point of labeled recognition.

For a user-paced capture, [scripts/guided-vision-benchmark.py](#) serves a temporary live camera page. Nothing is recorded while the player frames a pose. Selecting **Record this step** starts a two-second countdown and records only that labeled step; the player decides when to continue. The completed camera source remains local and releases the camera automatically. A fixed-duration subset may then be sampled from those confirmed steps for repeatable replay. Guided capture is diagnostic evidence, not training data or an automatic part of Glove Academy.

Preliminary PowerGlove Vision Controller steady-state timing

After deploying 0.3.2-dev on September 5, 2026, two controller-off 300-sample smoke-test windows exercised the current MediaPipe Hands configuration at 640×480. These validate the camera, inference, state calculation, telemetry, and preview isolation; they do not replace the labeled clip or console tests.

Preview state	Recognition rate	Inference p50 / p95	Camera read to decision p50 / p95
Dashboard closed	11.4 Hz	87.9 / 98.4 ms	109.6 / 127.9 ms
Dashboard stream open	11.8 Hz	88.0 / 97.6 ms	108.2 / 125.7 ms

The preview-open window did not materially increase p95. Controller delivery was intentionally stopped, so no changed-control-to-send samples were recorded; that metric requires the authenticated RetroPie receiver during the live test.

Guided replay result - September 5, 2026

A player-confirmed guided session recorded 1,575 frames across 52 seconds at an effective 30.29 fps. A 30-second comparison subset retained the first two seconds of every labeled step at 15 fps, giving all 16 lanes the same 450 source frames and 67 ms temporal resolution. The complete guided source was preserved while the comparison ran.

Backend and full-frame size	Threads	Preview	Inference p50 / p95	Detection continuity	Neutral false frames
MediaPipe Hands, 640×480	1	Closed	96.51 / 207.60 ms	71.33%	14
MediaPipe Hands, 640×480	2	Closed	92.94 / 217.40 ms	71.33%	14
MediaPipe Hands, 640×480	4	Closed	98.60 / 190.18 ms	71.33%	14
MediaPipe Tasks Video, 640×480	1	Closed	184.55 / 403.13 ms	82.89%	44
MediaPipe Hands, 512×384	4	Closed	97.37 / 213.53 ms	72.67%	60
MediaPipe Tasks Video, 512×384	1	Closed	183.85 / 401.05 ms	81.11%	43
MediaPipe Hands, 640×480	4	Open	99.45 / 190.36 ms	71.33%	14

Backend and full-frame size	Threads	Preview	Inference p50 / p95	Detection continuity	Neutral false frames
MediaPipe Tasks Video, 640×480	1	Open	187.21 / 382.52 ms	82.89%	44

Tasks Video recovered difficult A, B, and Closed Hand poses that the proven backend missed in the selected windows, but approximately doubled median inference time and exceeded the gameplay latency target decisively. The 512×384 resize did not improve p95 by the required 15%; it increased neutral false activations and weakened roll recognition. Thread count did not change recognition, and no alternative produced a consistent qualifying latency gain. The deployed choice therefore remains **MediaPipe Hands (proven)** at 640×480 with four inference threads. Preview encoding at that size measured about 9.6 ms p95 and did not materially increase inference p95.

The replay deliberately saturates inference and produced higher tail latency than real-time capture. The live steady-state p95 measurements above remain the authoritative gameplay-stage values. Replay is used for relative comparisons and identical-frame recognition evidence.

The guided source also documented a difficult backlit scene. Mean luma was approximately 77-79 on a 0-255 scale and 34-38% of pixels were below luma 32. The camera was already using automatic exposure. Its hardware backlight compensation made a reversible still-image test slightly darker, while restoring brightness and contrast to factory defaults helped only modestly. No camera control was promoted globally. Front lighting or moving the bright window out of the background is the safer remedy because forced exposure can add motion blur and reduce the stable frame rate.

Collect a live status baseline

Before changing responsiveness settings, measure one stage at a time. Preserve the same camera position, lighting, calibration, recognition settings, and game state between comparisons. The read-only collector does not activate the camera or enable controller delivery; prepare the intended mode on Dashboard first.

For a stationary open-hand window, run from the development checkout:

```
SH
python3 scripts/measure-vision-status.py \
  --status-url http://UNO-Q-NAME.local:8088/status \
  --phase neutral --seconds 30 --output /tmp/powerglove-neutral.json
```

Repeat with `--phase movement` and a new output path while making deliberate short X/Y steps and returns. Use a separate run for preview-open and preview-closed conditions. Neither run records camera images. The neutral report includes observed signed-axis span and standard deviation; those combine physical hand movement with tracker variation and are not an isolated sensor noise measurement. The phase label describes the operator's test, not an automatically verified pose. Do not label ordinary gameplay as a neutral test.

The collector counts each observed inference timestamp/capture-sequence pair once, rejects invalid timings, and separates changing profiles, delivery gates, preview-client counts, and camera/backend settings. It reports p50/p95 over unique observations, not averages of the worker's overlapping rolling windows. Detected-hand and missing-hand inference distributions remain separate, and each segment reports the change in the worker's skipped-capture counter. Public status is cached by the supervisor, so these are sampled distributions, not a complete frame trace. A faster polling interval cannot recover frames that were never exposed by that cache. A direct worker `/status` read inside its container avoids the supervisor cache but still samples results.

Review fresh-sample counts, request errors, detection/calibration counts, and local send-success counts before comparing runs. `sent_sample_age_ms` contains only locally successful sends, whereas ordinary `sample_age_ms` also exists with delivery stopped. Neither proves receiver acceptance. An idle window produces no active samples and exits

with code 2; it must not be presented as a zero-latency result. The report excludes addresses, tokens, images, landmarks, and individual coordinate records. Full options are in the [Configuration Reference](#).

Keep the stage boundaries separate

Stage	Evidence to collect	What it does not establish
Exposure and camera delivery	Physical visual reference plus camera/driver timestamps when available	OpenCV read-completion timestamps do not measure exposure or upstream buffering.
Capture to inference	capture_age_ms , processed capture spacing, negotiated camera mode, and frame skips	Processed-frame spacing is not the spacing of every camera frame.
Inference and recognition	inference_ms , inference spacing, detection continuity, and fixed-input replay	Existing inference timing includes tracking and gesture work; replay is not live capture.
Local send	send_ms , successful-send counts, and sent_sample_age_ms	Successful UDP submission is not a delivery acknowledgement.
Network reception	Controller-to-console round trips as a diagnostic; correlated receive timestamps for actual UDP measurements	ICMP round trips cannot be relabeled as one-way gameplay delivery time.
Receiver publication	Local timestamps at receive, after validation/uinput, and after publishing the even guard	The current record timestamp starts at publication; it hides preceding receiver work.
Native core consumption	Match a published sample to the core callback using the console's monotonic clock	Polling the native file from another process does not prove when the core consumed it.
Game and display	Exact-ROM frame response, active RetroArch video settings, and a high-frame-rate hand/screen recording	The headless frame-3 result excludes presentation buffering and physical display response.

Use durations within one machine's clock domain. Do not subtract independent monotonic clocks across machines, halve an ICMP round trip into a claimed UDP delay, or add independently measured p95 values into an end-to-end percentile. Receiver publication and core-consumption timestamps need additional diagnostic instrumentation before those intervals can be reported as measured. Keep any instrumentation bounded and compare its overhead before using its results.

For the visual test, frame the hand and game display in one 120/240-fps recording. Hold an open hand still for five seconds, then make five short horizontal steps with a pause after each. Count from first physical motion to first corresponding game motion for each step, recording the camera frame rate and uncertainty. Also inspect resting movement and repeats in the reverse direction. This measures the complete visible path; it does not by itself assign delay to one software stage.

September 6 diagnostic preflight

With the cabinet newly booted, a 20-packet Controller-to-RetroPie ICMP probe returned all packets: minimum 0.315 ms, average 0.389 ms, maximum 0.666 ms, and reported deviation 0.088 ms. This short idle-network check is not a gameplay UDP latency measurement. The cabinet reported 1920x1080 at 60 Hz, threaded video enabled in the global configuration, and no reported throttling. Effective per-game settings and live timing must still be checked with the game running. No recognition, smoothing, camera, network, or video defaults were changed.

The subsequent game launch confirmed [lr-nestopia-powerglove](#), device [517](#), and the native-state path. Both active append files were checked for video overrides; they added a 60.00 Hz refresh value and did not override threaded video. The user confirmed the Robo-Glove followed their hand before repeating the two windows below. Measurements came directly from the worker at a 50 ms poll interval, with the proven 640x480 MJPG backend, delivery enabled, and one preview client. Camera metadata reported a requested/negotiated 60 fps; this is not proof of a 60 fps effective capture rate.

Window	Fresh / detected observations	Detected inference p50 / p95	Camera-read-to-send p50 / p95
Requested stationary hold, 10 seconds	91 / 78	91.1 / 109.9 ms	116.6 / 205.4 ms
Short movement, 30 seconds	315 / 315	91.0 / 103.2 ms	112.3 / 132.8 ms

Both windows had zero request errors and locally successful sends for every observed sample. The stationary attempt included 13 tracking misses, whose inference measured 175.7 / 204.5 ms p50/p95. Its X/Y spans were 25,080 / 17,829 signed-axis units, so it is not an accepted stationary-jitter baseline without video review and a repeat. The movement window retained detection throughout. Superseded-capture counter deltas were 205 and 584 respectively; intentional frame replacement is not network packet loss.

A separate 15-second read-only native-file observer saw 128 distinct guarded publications, including 101 detected/calibrated Super Glove Ball samples, and rejected two incoherent reads. For those gameplay samples, observed publication interval p50/p95 was 94.139 / 109.235 ms. Publication-to-observer age p50/p95 was 1.105 / 2.154 ms. This was a different window with a 2 ms polling sleep: it does not measure socket arrival, publication cost, or core pickup, and it can miss overwritten records. It is cadence evidence only.

These results identify inference and tracking recovery as substantial measured costs. They do not yet justify changing stabilization, camera settings, or threaded video. Frame-by-frame video analysis, a reliable stationary window, receiver timing instrumentation, and native-consumption timing remain outstanding. Read-to-send timing also omits the wait for the next inference opportunity when physical motion begins between processed frames.

Run it again

Build the two isolated benchmark cores:

```
SH
scripts/build-nestopia-powerglove.sh
scripts/build-fceumm-benchmark.sh
```

Then supply external paths to the exact ROMs:

```
SH
python3 scripts/benchmark-direction-response.py \
--nestopia-core build/nestopia-powerglove/nestopia_powerglove_libretro.so \
--super-glove-ball-rom "/path/to/Super Glove Ball (USA).nes" \
--fceumm-core build/fceumm-benchmark/fceumm_libretro.so \
--scratch /tmp/powerglove-direction-benchmark \
--output /tmp/powerglove-direction-benchmark/result.json
```

On macOS, use the emitted `.dylib` paths instead of `.so`. Build products, scratch state, reports, and ROMs are not release-package content. The runner's `--fceumm-rom` option adds the optional Gun.Smoke reference lane.

Hostname refresh follow-up - 6 September 2026

Before moving controller hostname refresh out of the send path, twelve isolated `.local` lookups on the Controller cleared only that diagnostic process's resolver cache. Median lookup duration was 2.35 ms; the maximum was 107.54 ms. This is a small lookup sample, not an end-to-end camera-to-game latency measurement.

Controller sends now read a background-refreshed address. A blocked lookup does not block a send call or retain any controller samples; unavailable/expired addresses skip the current send. Deterministic tests stall resolution while attempting 100 states, then verify that only the next new state is sent after resolution completes. Capture, inference, movement thresholds, smoothing, native state publication, and core consumption are unchanged. The stationary-hand and synchronized physical display comparison remain pending.

Signed transport processing - 6 September 2026

An isolated comparison ran on the actual Controller app container and RetroPie with dummy input and no network transmission or gamepad publication. Each column uses 2,000 samples after 100 warm-up iterations. It compares the prior v1 codec/token check against the new v2 signing/challenge validation code loaded in memory; this is not a deployed camera-to-display test.

Stage and machine	Protocol	Median ms	p95 ms	Maximum ms
Packet creation, Controller	v1	0.1550	0.2142	0.4525
Packet creation, Controller	v2	0.2654	0.3364	2.4920
Validation, RetroPie	v1	0.1090	0.1473	0.3143
Validation, RetroPie	v2	0.4488	0.5640	0.7606

The representative released-state packet grew from 505 to 606 bytes, using a dummy 32-character token. Signed packet size no longer depends on token length. Median processing additions were 0.1104 ms for Controller packet creation and 0.3398 ms for RetroPie validation. These microbenchmarks do not include scheduling, network transit, initial handshake, uinput/native publication, core consumption, display latency, or stationary jitter. No movement smoothing or recognition settings changed. The synchronized physical movement baseline remains pending.