



SECURITY POLICY

VirtualGlove Security Policy

Reporting, trust boundaries, network exposure, shutdown, and release integrity.

2026 EDITION / IAIN BENNETT / MIT LICENSE

Use VirtualGlove on a trusted home or workshop network. This policy explains how to report a vulnerability and which protections the project expects pairing, networking, and shutdown code to maintain.

Supported code

Security fixes will be available on the current [main](#) branch and included in the next tagged release. Older snapshots may lack pairing, network, dependency, or shutdown protections and should be upgraded before troubleshooting them.

Reporting a vulnerability

Please do not publish credentials, pairing codes, tokens, private device configuration, or working exploit instructions in a public issue.

1. Open the repository's **Security** tab and look for private vulnerability reporting.
2. Submit a private report with the information below. Remove secrets from every attachment.
3. If private reporting is unavailable, open a minimal public issue asking for a private contact channel; include no exploit details or secrets.

Include these details in the private report:

- the affected commit or release;
- the VirtualGlove Controller, RetroPie, browser, and network environment involved;
- concise reproduction steps and the observed result;
- the security boundary that was crossed;
- logs or screenshots after removing tokens, passwords, pairing codes, local addresses, and unrelated personal information.

This project does not currently offer a bug bounty or a guaranteed response time.

You can report controller-mapping, camera-compatibility, and game-profile problems in public issues after removing sensitive information from the logs.

Security model

The **VirtualGlove Controller** is the Arduino UNO Q device that owns the camera, recognition pipeline, local website, and controller sender.

VirtualGlove is designed for a trusted home or workshop network. The VirtualGlove Controller performs hand tracking and sends virtual-controller state to RetroPie. RetroPie sends per-game profile changes back to the VirtualGlove Controller. Neither device should be treated as an Internet-facing service.

The main protected assets are:

- the shared controller token;
- the VirtualGlove Controller and RetroPie operating systems;
- the privileged `/dev/uinput` receiver;

- the physical pairing display and single-use PIN;
- the fixed-purpose VirtualGlove Controller shutdown and USB-camera recovery helpers;
- the integrity of the App Lab installation ZIP, MediaPipe wheel, bundled or downloaded model, and Arduino dependencies.

The project does not attempt to protect a device after an attacker obtains root access, physical storage access, or control of the trusted local network and both paired hosts.

Pairing boundaries

The VirtualGlove Controller and RetroPie share one random token of at least 16 characters. The active token belongs only in the VirtualGlove Controller's private `data/device.json` and RetroPie's `/etc/powerglove/token`. It must not be committed, placed in a shell argument, stored in `launcher.json`, or included in a screenshot or log.

The supervised vision worker reads its token using `--device-config`, keeping the secret out of process arguments. Device settings are created and replaced atomically with mode `0600`. Legacy `--token` remains a compatibility option for manual commands; prefer `--token-file` or `--device-config` for the worker. Browser mutation routes reject cross-site origins, and connection-setting writes require JSON. These browser protections do not add local-user authentication or change the trusted-network model.

The recommended setup path uses a short-lived one-time code to authenticate the RetroPie pairing server over pinned TLS. Password pairing uses authenticated SSH. After the initial connection establishes trust, subsequent connections verify the saved remote host key. The password is not placed on the process command line.

Each Controller owns a persistent private local certificate authority. It signs the HTTPS leaf for the Controller's stable `.local` name. Secure Setup can download only the public authority certificate; plain HTTP receives no certificate download. A user may explicitly trust that public certificate on each phone or computer to remove later browser warnings. The authority and website private keys remain mode `0600` in the Controller's private data directory and are never served.

Both browser pairing methods still require the user to compare the current website certificate identity with the identifier on the physical VirtualGlove Controller matrix and enter its single-use PIN before a token is released. The first trust download should occur only after this physical comparison. Locally trusting the Controller authority improves repeat visits but does not replace the Matrix ceremony or turn the Controller into a public certificate authority.

Fresh interactive installation proposes `virtualglove.local`, accepts a different validated single-label name, and checks whether that name visibly belongs to another LAN address before changing the host. Unattended installation requires an explicit `--hostname` to rename the board. Upgrades never accept a rename, preventing an update command from silently changing the trusted website identity. Hostname files are included in the installer's recovery backup. The installer also records that approved host label in private application data; the containerized website reads it instead of trusting its transient Docker hostname when issuing the HTTPS leaf.

After installing the token, the Controller sends a signed controller hello and reports success only after RetroPie returns a valid matching challenge. This post-write check confirms that the receiver accepts the newly shared token; it does not arm output or establish that an emulator consumed controller input.

Pairing sessions limit how long a connection handshake can take and how long the pairing service remains available. Reusing a PIN, removing the physical display requirement, accepting pairing credentials over ordinary HTTP, or extending the listener indefinitely weakens the intended boundary and requires explicit security review.

Network exposure

Port	Protocol	Direction	Boundary
55355	UDP	VirtualGlove Controller to RetroPie	Authenticated virtual-controller packets
55356	UDP	RetroPie to VirtualGlove Controller	HMAC-authenticated profile commands and acknowledgements
55357	TCP/TLS	Pairing client to temporary server	Short-lived code-pairing exchange only
8088	HTTP	Browser to VirtualGlove Controller	Local dashboard, Play, public Help guides, diagnostics, and ordinary controls; no pairing credentials accepted
8443	HTTPS	Browser to VirtualGlove Controller	Protected setup and pairing operations

Keep these ports on a trusted LAN. Do not configure router port forwarding, public reverse proxies, cloud tunnels, or Internet firewall exceptions for them. Guest Wi-Fi and untrusted shared networks are inappropriate unless the devices are isolated by firewall rules or a dedicated VLAN.

The profile-control brick publishes UDP 55356 and forwards packets to the worker on the private container network. It has no token or private data mount, runs without elevated privileges, and bounds packet sizes, pending exchanges, and reply lifetime. Authentication remains in the worker; the relay never creates an acknowledgement. A signed acknowledgement confirms queue admission, not completed camera startup or enabled gameplay delivery.

Controller and profile UDP traffic is authenticated but not encrypted. Anyone with access to the local network can observe packet timing and size even when they cannot create accepted input without the token. The dashboard can expose camera imagery and operational status to clients that can reach it, so network access to port 8088 is itself sensitive.

The Help library serves a fixed list of public Markdown guides and images from the installed application. It must not expose `data/`, the machine-specific cheat sheet, arbitrary filesystem paths, or pairing credentials. Markdown HTML is not executed, unsafe link schemes are rejected, and image requests are confined below `docs/images`.

The dynamic **This console** page accepts only a validated hostname or IP from the browser `Host` header and combines it with `public_config()`. It may show local network addresses, ports, profile selection, camera selection, and whether pairing is configured, but it must never return the token value, passwords, private files, or arbitrary Host-header content.

Shutdown and camera-recovery permissions

The web process does not receive general `sudo` permission. A root-owned systemd path unit watches one fixed file in the application data directory. A matching oneshot service deletes that file and requests a non-blocking Linux halt.

The dashboard route requires an explicit confirmation header and only creates the fixed request when the host installer has placed the private `.shutdown-enabled` marker. These checks reduce accidents and prevent command substitution; they do not make the dashboard safe for public network exposure. Anyone able to use the reachable dashboard may still cause a denial of service by shutting down the VirtualGlove Controller.

A root-owned tmpfiles rule recreates only that fixed readiness marker during boot. It grants no command execution and does not change the container's privileges.

Camera recovery follows the same fixed-request pattern with separate path and service units. Installation may occur without a camera. When exactly one UVC camera is healthy, the root-owned helper writes its identity and its actual parent hub's identity and physical USB path to the root-owned `/etc/powerglove-camera-recovery.json` allowlist. A later healthy sighting safely updates that association if the camera has moved. During an outage the helper validates both the

stored path and hub identity and resets only that hub; it never accepts a device path from the web application or guesses among hubs.

The helper consumes the request before acting, permits one request per camera outage, and enforces a root-owned cooldown. Before first enrollment it refuses to reset anything. A client able to activate vision could still cause one brief USB interruption during a real camera outage, so the web interface remains suitable only for a trusted LAN.

Keep both helpers' path units, service units, scripts, and tmpfiles rules owned by root. Unit and rule permissions are [0644](#); the camera helper is [0755](#). Do not replace the fixed [ExecStart](#) commands with user input, a shell string, or an arbitrary command runner. Remove or disable the corresponding helper set if remote shutdown or camera recovery is not wanted.

Dependency and release integrity

- The App Lab installation ZIP is generated and verified; it is not maintained as a changing source-controlled binary.
- The custom MediaPipe wheel's provenance and checksum are recorded in [THIRD_PARTY_NOTICES.md](#) at the repository root.
- Google's Hand Landmarker model is installed from the bundled copy, with its pinned download as a fallback only when that copy is absent. Both paths must match the expected SHA-256 digest before atomic installation; the package verifier also checks the bundled model and license text.
- The optional Nestopia core is built from one pinned upstream commit and one checksum-recorded local patch. Its build rejects changes to Nestopia's original Power Glove license header, and installation keeps the upstream [COPYING](#) file and the local modification ledger beside the separately named core. Stock Nestopia and FCEUmm are not replaced.
- Arduino library versions are pinned in [sketch/sketch.yaml](#).
- GitHub Actions rebuilds and inspects documentation and the App Lab installation ZIP on every pull request and push to [main](#) or [dev](#).

Changing a download URL, checksum, dependency source, pairing primitive, network binding, file permission, or privileged service requires focused review and corresponding tests and documentation.

Paired game editing and gesture tuning

The separate RetroPie Games service listens on TCP [55358](#). Only the paired UNO proxy uses it; browsers call the UNO website. Requests and replies use a distinct HMAC-authenticated protocol. Server challenges expire after fifteen seconds and are consumed once. The shared token never goes to the browser. This protects message integrity; the LAN transport does not encrypt ROM filenames.

The service accepts only registry reads, validated writes, and restoration. File locations come from the administrator's launcher configuration, never from browser input. Writes use revision checks, atomic replacement, and a previous valid backup. The service has bounded document sizes, pending challenges, and socket timeouts; it runs separately from controller input delivery. Its systemd unit confines writes to the configured registry directory and removes device access and capabilities.

The new Games and Tune browser actions require JSON, an explicit action header, and matching Origin when supplied; cross-site browser requests are rejected. They retain the existing trusted-LAN administration model, not per-user accounts. Normal personalization contains numerical thresholds only. Measurements are held briefly in memory, previews expire with the owning session, and camera images are not saved. Tuning suppresses controller delivery even if a game launches or another Dashboard requests input. Saved settings are validated and atomically replaced.

The optional Advanced diagnostic is the only Academy path that records video. It is explicitly started and user-paced, remains on the VirtualGlove Controller, and is deleted immediately after aggregate analysis or cancellation. An abandoned AVI expires after 30 minutes. Its downloadable JSON contains aggregate continuity, latency, confidence, lighting, and recognized-state names only: no frames, landmarks, tokens, addresses, or saved personal thresholds.

Documentation screenshots

Documentation screenshots use isolated sample data and an omitted-camera placeholder. If capturing a live page instead, blur the complete camera image before capture. Keep controls legible, but never publish unblurred camera frames or screenshots that contain passwords, private tokens, or pairing codes. The reference images show the interface; they are not saved gesture recordings.

Personal hand setup and tuning data

Optional hand setup measures all five fingers; gesture tuning measures selected components. Both use three short sets of numerical samples in memory. The version-5 [data/gesture-tuning.json](#) file stores player names, one joystick center-box size, gesture activation/release pairs shared across game profiles for each player, Academy progress, and a required-center flag and separate saved calibration, plus a bounded pending reference during a calibration restore. Internal versions 1-4 migrate with private backups. Portable hand-setup exports use the [virtualglove-hand-setup](#) format at version 4. Legacy [powerglove-hand-setup](#) versions 2 and 3 remain importable, while version 1 is rejected. Exports contain a name, center-box size, personal and complete gesture threshold pairs, software identity, and a neutral reference. They exclude camera images, landmarks, Wi-Fi credentials, pairing tokens, and lesson progress. Restoring calibration requires an explicit same-position confirmation and strict finite field validation. A persisted restore resumes after interruption with output gated; Start controller is still required. The active physical reference remains in [data/calibration.json](#); each player retains a separate saved reference and reuse requires confirmation. The installer never packages a maintainer's neutral reference: camera position, player distance, and wrist pose make it installation-specific. Preserve both files during updates. Expiry or discard removes temporary preview state, not saved settings. Numerical validity and sample separation do not prove a pose was performed correctly; preview feedback and physical testing are still required before release.

Wi-Fi status sampler

The network sampler runs as [arduino](#) and reads physical-link carrier state plus the subnet broadcast address for each connected Wi-Fi/Ethernet interface. It publishes a small expiring record in [data/wifi-status.json](#); it does not collect SSIDs, host unicast addresses, passwords, or scans, and cannot change network settings. The application retains no controller states while hostname resolution runs in the background. Controller version-2 messages use the signed sessions described below.

Controller packet integrity and replay boundaries

Version-2 controller messages use HMAC-SHA256 with a controller-specific domain prefix, separate from profile and registry messages. The secret is never included in these datagrams. All message fields are authenticated; size limits and duplicate-key rejection bound parsing. A receiver-issued random challenge is required for input, is bound to the sender session and UDP peer, and is replaced on session activation or receiver restart. Strictly increasing sequences reject duplicates and reordering within the current session. Old handshakes cannot resurrect recorded state because a fresh challenge needs a fresh authenticated response. Pending challenges are bounded and expire; input states are never queued by the handshake.

This protects message integrity and retired-session replay, not confidentiality or availability. A host holding the shared token can create valid input, and a network attacker can still drop traffic. Input fields remain readable on the LAN. The

existing timeout neutralizes both gamepad and native state even under rejected traffic or repeated handshakes.

Address recovery does not trust a hostname, DHCP lease, or responding IP as the console's identity. When directed delivery or name resolution stops producing authenticated maintenance replies, the Controller may send the signed [hello](#) message to the broadcast address of each connected physical LAN. It accepts a new address only from a correctly signed, request-matched challenge made with the existing pairing key. State messages are never broadcast. Discovery is limited to the local broadcast domain; routers, guest isolation, VLANs, and firewalls may prevent it, which is a safe availability failure rather than an authentication bypass. A copied pairing key can impersonate the console and must be rotated if exposed.

The reverse profile path follows the same identity rule. When RetroPie cannot reach the configured Controller address, it broadcasts a signed discovery request that contains no ROM or requested profile. It accepts only a signed, request-matched acknowledgement, sends the profile command to that authenticated source by unicast, and retains the address only in a bounded 30-second process cache. Neither direction rewrites saved addresses automatically.

The public system-report endpoint is field-allowlisted. It excludes network addresses as well as frames, secrets, ROM names, player identities, calibration, and gesture measurements; adding a new internal status field does not make that field appear in a report automatically.

The [architecture timing table](#) distinguishes gameplay packets, liveness handshakes, profile leases, Setup health checks, and host-link sampling. In particular, handshake or rejected traffic cannot extend the receiver's 250-millisecond valid-state deadline, and background status checks do not run in the camera inference path.

The receiver rejects version 1 by default. `--allow-legacy-controller` is an explicit temporary upgrade option with weaker protections: old packets contain the secret, and receiver restarts lose their legacy replay history. The option stops accepting legacy input once signed input arrives but reopens after a process restart; remove it after migration. Update both computers together and consider re-pairing if the previous token was exposed. The new sender never silently downgrades.