

R.O.B. Vision quick reference

R.O.B. is virtual. The UNO Q app and RetroPie link are running. Both Gyromite gate colors responded in Game A. The camera recognized both games' Test modes. RetroPie's game-frame link sent all six commands from each game to the virtual R.O.B. during live Direct play.

Where	Action	Result
Mission	Select Gyromite, Stack-Up, or Pose Lab	Choose the virtual scene while no game is active.
Mission	Run Demo Sequence	Finite animation; available while paired and idle.
Mission	Home	Reset selected virtual game and pieces.
Mission	Emergency Stop	Live: stop capture and clear game. Preview: cancel local script.
Mission	Fast Gates during live Gyromite	Blue 2, red 1, Release Both 0; press again to release a color. Auto-release after 60 seconds.
Setup	Pair Console / Check Link	Pair RetroPie or refresh its authenticated online status.
Setup	Start Camera Check	Show framing, measured fps, and sampling rectangle.
Setup	Reset & Reconnect	Retry OpenCV capture; USB hub is unaffected.
Setup	Watch Test Signal	Blink R.O.B.'s red light for a detected Test signal; no movement.
Setup	Gyromite / Stack-Up checks	Send manual pad or movement commands to the live model.
Mission	GAME FRAMES LINKED	RetroPie is sending rendered game frames for the selected ROM; automatic movement does not require the camera.

In Stack-Up, press Select on the ROBOT BLOCK screen, choose Test, then press Start. The artwork remains visible while the Test signal plays.

Use [Mission](#) and [Setup](#) on the UNO Q. A local `file://` page is only the preview. The camera requests 60 fps for preview and Test checks; the RetroPie frame link reads complete commands at the game's own frame rate.

The game launch hook identifies an exact ROM name. The receiver applies Gyromite virtual pad states as Controller 2 input and releases both on exit or stale network data. Stack-Up moves modeled blocks and has no gate-button return path. See the [user guide](#) and [troubleshooting](#).