



COMPATIBILITY EVIDENCE

Power Glove Game ROM Input Audit

ROM evidence for native packets and conventional controller mappings.

2026 EDITION / IAIN BENNETT / MIT LICENSE

This audit is limited to the Power Glove game list shipped in the registry. ROMs were read from the user's archive folder for static inspection and were not copied into the repository or release package.

Game	ROM SHA-256	Input finding	Shared profile
Bad Street Brawler (USA)	be2714f072338f2ca7204be750eaa03daadeb12521e1713cfe54d35b65457700	Standard NES button polling; in-game Power Glove program choices change how glove motions become those buttons.	bad_street_brawler
Defender II (USA)	dbc69122c8d84af7f026e2612cbd0713ce371954e2401610f2acb7aa51dd95e0	Standard controller polling.	program_e
Gyruss (USA)	c6aeb2448aea5c3931e63fb9bafa85300acdbe2c59a9ba500863c2041e0fe9d8	Standard controller polling.	program_c
Gun Smoke (USA)	4ad9629a2bacc158a7f50975869c7dfe533567ae399a5bdc5df2240286df259f	Standard controller polling.	program_g
Joust (USA)	083eb550a39b4821dba154111521cd67826f07769ec0b93db0dd6c5b3fe18837	Standard controller bits are consumed selectively; no native multi-byte glove packet was found.	program_b
Knight Rider (USA)	6e822c93f64347032847bcaa46728eb324e8fe7dc8746a6a9e6512bc7ba39cc2	Standard controller polling.	program_i
Sesame Street 123 (USA)	5d2c0a69e65f1e9c6984025407f5a7198cbf5e1774d2f3a87883327520a91793	Standard controller polling.	program_f
Super Glove Ball (USA)	ad60ef1b62cd1b3bc02a9320376067347a8ab2ebbe46e1616693d8379c9d9a7b	Detects and consumes a native ten-byte Power Glove stream; also contains a standard-controller fallback.	super_glove_ball

The broad result supports one global camera calibration and recognition model. FCEUmm receives responsive standard D-pad/button output for seven games and remains the Super Glove Ball fallback. Only Super Glove Ball benefits from bypassing D-pad thresholds and sending continuous X/Y through the custom Nestopia core.

Static inspection establishes which controller path the program reads; it does not replace cabinet play testing. Program labels remain output mappings, not separate recognition or calibration profiles.