POWER SYMBOLS:

NOTE: A COMPLETE LIST OF RECEPTACLE SYMBOLS IS SHOWN FOR THE DUPLEX RECEPTACLE ONLY. OTHER RECEPTACLE SYMBOLS WILL FOLLOW THE SAME SHADING CONVENTION AS THE DUPLEX RECEPTACLE, UNO.

CENTER HATCH: ISOLATED GROUND RECEPTACLE
OUTER HATCH: GFCI RECEPTACLE
RIGHT HATCH: CONTROLLED RECEPTACLE

20A, 125V, RECEPTACLE
(NEMA 520R), WALL MTD
(SIMPLEX LEFT, DUPLEX CENTER, QUAD RIGHT)
D= DUAL SWITCHED
H = HALF SWITCHED
TR = TAMPER RESISTANT
U= USB OUTLET
WP = WEATHERPROOF
WR = WEATHER RESISTANT
SP = SURGE PROTECTIVE
(LEVITON T5380W OR EQUAL)

20A, 125V, IG DUPLEX RECEPTACLE
(NEMA 520R), WALL MTD

20A, 125V, GFCI DUPLEX RECEPTACLE
(NEMA 520R), WALL MTD

20A, 125V, GFCI DUPLEX RECEPTACLE
(NEMA 520R), WALL MTD

20A, 125V, RECEPTACLE ON EMERGENCY
CIRCUIT (NEMA 520R), WALL MTD
(SIMPLEX LEFT, DUPLEX CENTER, QUAD RIGHT)

20A, 125V, RECEPTACLE
(NEMA 520R), FLOOR MTD
(SIMPLEX LEFT, DUPLEX CENTER, QUAD RIGHT)

20A, 125V, RECEPTACLE ON EMERGENCY
CIRCUIT (NEMA 520R), FLOOR MTD
(SIMPLEX LEFT, DUPLEX CENTER, QUAD RIGHT)

20A, 125V, RECEPTACLE
(NEMA 520R), CEILING MTD
(SIMPLEX LEFT, DUPLEX CENTER, QUAD RIGHT)

20A, 125V, RECEPTACLE ON EMERGENCY
CIRCUIT (NEMA 520R), CEILING MTD
(SIMPLEX LEFT, DUPLEX CENTER, QUAD RIGHT)

FB — MULTISERVICE, FLOOR BOX, FLUSH MNT
(SEE SPECS OR NOTES)
FB = FLOOR BOX
FF = FURNITURE FEED

PT — MULTISERVICE, POKE-
THRU, 2 HR. FIRERATED, FLUSH MNT (SEE SPECS OR NOTES)
PT = POKETHRU
FF = FURNITURE FEED

PT — MULTISERVICE, CEILING BOX WITH PROJECTOR MOUNT (SEE SPECS OR NOTES)

WB — MULTISERVICE, WALL BOX, RECESSED MNT
(SEE SPECS OR NOTES)

SPECIAL PURPOSE RECEPTACLE
(SEE EQUIPMENT SCHEDULE OR NOTES)
(WALL MNT LEFT, FLOOR MTD RIGHT)

SPECIAL PURPOSE RECEPTACLE ON
EMERGENCY CIRCUIT
(SEE EQUIPMENT SCHEDULE OR NOTES)
(WALL MNT LEFT, FLOOR MTD RIGHT

60A — 60A, 480V, 3PH, WELDING RECEPTACLE, WALL MTD

DROP CORD (SEE SPECS OR NOTES)

POWER POLE (SEE SPECS OR NOTES)

RECEPTACLE RACEWAY / PLUG MOLD

J — JUNCTION BOX, WALL MTD

WP — JUNCTION BOX
WP = WEATHERPROOF

J — JUNCTION BOX, FLOOR MTD

J — JUNCTION BOX, EXPLOSION PROOF

30/NF — SAFETY SWITCH, 30A, 3POLE, NONFUSED
(FBO - FURNISHED BY OTHERS)

30/20 — SAFETY SWITCH, 30A, 3POLE, FUSED @ 20A
(FBO - FURNISHED BY OTHERS)

STARTER OR MOTOR CONTROLLER

T — STARTER, COMBINATION W/ DISC. SWITCH

TRANSFORMER

ELECTRICAL PANEL / ENCLOSURE AS NOTED ON
PLAN DRAWINGS
(SURFACE MTD LEFT, RECESSED MTD RIGHT)

ELECTRIC UTILITY METER

GROUNDING BUSBAR (SEE SPECS OR NOTES)

PP — UTILITY POWER POLE

LIGHTING SYMBOLS:

NOTE: REFER TO LIGHTING FIXTURE SCHEDULE FOR FIXTURE TYPES AND SENSOR SCHEDULE FOR SENSOR TYPES. REFER TO PLAN DRAWINGS FOR ADDITIONAL SYMBOLS.

A: — CAPITAL LETTER ADJACENT TO FIXTURE = TYPE

a: — LOWERCASE LETTER = SWITCHING GROUP

EM: — EMERGENCY LIGHTING IS DESIGNATED BY AN "EM" ADJACENT TO THE FIXTURE AND/OR A "HALF SHADED" OR "FULL SHADED" FIXTURE SYMBOL

NL: — NIGHT LIGHTING (UNSWITCHED FIXTURE)

$^{x}_{xx} — SWITCH, 20A, 120/277V, TOGGLE TYPE, U.N.O.
a,b,c,... =SWITCHING GROUP
BLANK =SINGLE POLE
2 =DOUBLE POLE
3 =THREEWAY
4 =FOURWAY
D =DIMMER SWITCH
K =SINGLE POLE KEY OPERATED
M =MOTOR RATED
MA =MAINTAINED CONTACT
MO =MOMENTARY CONTACT
P =SINGLE POLE W/ PILOT LIGHT
P2 =DOUBLE POLE W/ PILOT LIGHT
RC =REMOTE CONTROL
T =TIMER OPERATED SWITCH
WP =WEATHERPROOF
2HR =2HOUR OVERRIDE SWITCH

B — BLANK PLATE

O — OCCUPANCY SENSOR, WALL MTD

D^{x}_{xx} — LOW VOLTAGE DIGITAL SWITCH, WALL MTD

DP — LIGHTING CONTROL DEVICE
DP =DIMMABLE POWER PACK (ON/OFF WITH DIMMING)
PP =POWER PACK (ON/OFF)
RP =AUX. RELAY PACK (ON/OFF)
GW =GATEWAY
PS =POWER SUPPLY
BR =BRIDGE
LC =LIGHTING CONTACTOR
TC =TIME CLOCK
MS =MOTION SENSOR
PC =PHOTOCELL

PL — PLUG LOAD CONTROLLER (ON/OFF)

EPC — EMERGENCY POWER CONTROLLER

OCCUPANCY SENSOR, CORNER MTD

OS — OCCUPANCY SENSOR, CEILING MTD

DS — DAYLIGHT SENSOR, CEILING MTD

OS/DS — COMBINATION OCCUPANCY / DAYLIGHT SENSOR, CEILING MTD

2'X4' LAYIN TROFFER

2'X2' LAYIN TROFFER

1'X4' LAYIN TROFFER

STRIP/CHANNEL FIXTURE

DOWNLIGHT, CEILING MTD

WALL WASHER, CEILING MTD

LIGHT FIXTURE, CEILING MTD

LIGHT FIXTURE, WALL MTD

WALL PACK

EMERGENCY WALL PACK (BUG EYE)
(WALL MTD LEFT, CEILING MTD RIGHT)

EXIT SIGN, SINGLE FACE
(ARROW INDICATES DIRECTION OF EGRESS)
(WALL MTD LEFT, CEILING MTD RIGHT)

EXIT SIGN, DOUBLE FACE
(ARROW INDICATES DIRECTION OF EGRESS)
(WALL MTD LEFT, CEILING MTD RIGHT)

EXIT SIGN W/ COMBINATION EMERGENCY LIGHT, SINGLE FACE
(ARROW INDICATES DIRECTION OF EGRESS)
(WALL MTD LEFT, CEILING MTD RIGHT)

SPECIAL SYSTEMS SYMBOLS:

NOTE: UNLESS NOTED OTHERWISE, PROVIDE OVERSIZED JUNCTION BOX AND 1" EMPTY CONDUIT WITH PLASTIC INSULATING BUSHINGS AND PULL STRING STUBBED MIN. 6" INTO ACCESSIBLE CEILING SPACE. COORDINATE WITH LV CONTRACTOR FOR FINAL REQUIREMENTS.

TELEPHONE OUTLET, WALL MTD
1 TELE OUTLET, U.N.O.

COMBINATION TELE/DATA OUTLET, WALL MTD
1 TELE / 1 DATA OUTLET, U.N.O.

COMBINATION TELE/DATA OUTLET, WALL MTD
1 TELE / 2 DATA OUTLETS, U.N.O.

TELEPHONE OUTLET
1 TELE OUTLET, U.N.O.
(FLOOR MTD LEFT, CEILING MTD RIGHT)

COMBINATION TELE/DATA OUTLET
1 TELE / 1 DATA OUTLET, U.N.O.
(FLOOR MTD LEFT, CEILING MTD RIGHT)

COMBINATION TELE/DATA OUTLET
1 TELE / 2 DATA OUTLETS, U.N.O.
(FLOOR MTD LEFT, CEILING MTD RIGHT

TELEPHONE BACKBOARD (TBB)

INTERCOM OUTLET

M / I — INTERCOM STATION
BLANK = REMOTE
M = MASTER

AV AV — AUDIO / VIDEO DEVICE
(WALL MTD LEFT, CEILING MTD RIGHT)
AV = AUDIO / VIDEO OUTLET
M = MICROPHONE OUTLET
SM = SECURITY MONITOR OUTLET
TV = TELEVISION OUTLET
V=VOLUME CONTROL

AMP — SOUND SYSTEM AMPLIFIER

S S — SPEAKER
(WALL MTD LEFT, CEILING MTD RIGHT)

B — AUDIBLE NOTIFICATION DEVICE
B= BELL
C= CHIME
G= GONG

B — BUZZER

B — BELL & BUZZER COMBINATION

H — AUDIBLE NOTIFICATION DEVICE
H= HORN
S= SIREN

BT — AUXILIARY SYSTEM DEVICE
BT= BELL RINGING TRANSFORMER
R= RELAY
D= ELECTRIC DOOR OPENER
LV= LOW VOLTAGE TRANSFORMER

ANNUNCIATOR

BL BL — INDICATOR LIGHT
(WALL MTD LEFT, CEILING MTD RIGHT)
BL = BURGLAR ALARM LIGHT

M — CLOCK
M = MASTER
DF = DOUBLE FACE
S = COMBINATION SPEAKER

DC PVM — SECURITY DEVICES
DC = DOOR CONTACT
GB = GLASS BREAK DETECTOR
HD = HEAT DETECTOR
HU = HOLDUP BUTTON
KP = KEY PAD
MD = MOTION DETECTOR
PB = PANIC BUTTON
PVM = PUBLIC VIEW MONITOR
SD = SOUND DETECTOR
SEC = SECURITY CONTROL PANEL
VS = VIBRATION SENSOR
WC = WINDOW CONTACT

CR ACP — ACCESS CONTROL DEVICE
ACP = ACCESS CONTROL PANEL
CR = CARD READER
ES = ELECTRIC STRIKE
ML = MAGNETIC LOCK
PS = PROXIMITY SENSOR
PWR = POWER SUPPLY
RX = REQUEST EXIT PUSH BUTTON

XX XX — SECURITY CAMERA
(WALL MTD LEFT, CEILING MTD RIGHT)
PTZ = PAN/TILT/ZOOM
BX = BOX
D=MINI DOME
BL = BULLET
WP = WEATHERPROOF

PUSHBUTTON STATION
(BUTTONS REPRESENTED BY SOLID DOTS

NORMAL / EMERGENCY CALL BUTTON

PUSH BUTTON

RACEWAY SYMBOLS:

HOMERUN CIRCUIT TO PANELBOARD

LOW VOLTAGE CABLE

CONDUIT BURIED

CONDUIT CONCEALED

CONDUIT EXPOSED

FLEXIBLE CONDUIT

CONDUIT UP

CONDUIT DOWN

CONDUIT SEALOFF

CONDUIT TEE BODY

CONDUIT EL BODY

CONDUIT CAP

CONDUIT SLEEVE WITH BUSHINGS

PB — PULL BOX

HH — HAND HOLE

FIRE ALARM SYMBOL LEGEND

SYMBOL	DESCRIPTION
F	FIRE ALARM ADA APPROVED WALL MOUNTED HORN/STROBE ALARM. ENTIRE LENS SHALL NOT BE LESS THAN 80" AND NOT GREATER THAN 96" AFF.
V	FIRE ALARM ADA APPROVED WALL MOUNTED VISUAL ALARM. ENTIRE LENS SHALL NOT BE LESS THAN 80" AND NOT GREATER THAN 96" AFF.
FACP	FIRE ALARM CONTROL PANEL
FAA	FIRE ALARM ANNUNCIATOR
D D	FIRE ALARM SMOKE DETECTOR - WALL MTD., CEILING MTD.
F	FIRE ALARM PULL STATION
D	DUCT MOUNTED SMOKE DETECTOR

CODE IN EFFECT(GA):

ALL WORK SHALL BE IN STRICT ACCORDANCE WITH:

- NATIONAL ELECTRICAL CODE - 2020
- GEORGIA BUILDING CODE - 2015 IECC

WORK AND EQUIPMENT UNDER THIS DIVISION SHALL BE IN STRICT COMPLIANCE WITH THE CODES, STANDARDS, AND PRACTICES LISTED HEREIN. THEIR RESPECTIVE DATES ARE FURNISHED AS THE MINIMUM REQUIREMENTS (UNLESS OTHERWISE DETERMINED BY THE LOCAL AUTHORITIES HAVING JURISDICTION).

ABBREVIATIONS:

A	AMPERE
AFC	AVAILABLE FAULT CURRENT
AFCI	ARC FAULT CIRCUIT INTERRUPTER
AFF	ABOVE FINISHED FLOOR
AFG	ABOVE FINISHED GRADE
AHJ	AUTHORITY HAVING JURISDICTION
AIC	AMPERE INTERRUPTING CAPACITY
ATS	AUTOMATIC TRANSFER SWITCH
BLDG	BUILDING
BRKR	BREAKER
C	CONDUIT
CKT	CIRCUIT
CLG	CEILING
CPT	CONTROL POWER TRANSFORMER
CT	CURRENT TRANSFORMER
CU	COPPER
CTR	CENTER
EA	EACH
EG	EQUIPMENT GROUND
EGC	EQUIPMENT GROUNDING CONDUCTOR
EM	EMERGENCY
EOL	ELECTRONIC OVERLOAD
FDR	FEEDER
FLA	FULL LOAD AMPS
GEC	GROUNDING ELECTRODE CONDUCTOR
GFI	GROUND FAULT INTERRUPTER
GFCI	GROUND FAULT CIRCUIT INTERRUPTER
GND	GROUND
GRS	GALVANIZED RIGID STEEL
HTD	HEATED
HOA	HANDOFFAUTO
IG	ISOLATED GROUND
JB	JUNCTION BOX
KVA	KILOVOLTAMPERE
KW	KILOWATT
L.S.I.G.	LONG, SHORT, INSTANTANEOUS, GROUND FAULT TRIP
LTG	LIGHTING
MCA	MINIMUM CIRCUIT AMPS
MCB	MAIN CIRCUIT BREAKER
MCC	MOTOR CONTROL CENTER
MCCB	MOLDED CASE CIRCUIT BREAKER
MCP	MOTOR CIRCUIT PROTECTOR
MDP	MAIN DISTRIBUTION PANEL
MFS	MAXIMUM FUSE SIZE
MGB	MAIN GROUNDING BUSBAR
MLO	MAIN LUG ONLY
MOCP	MAXIMUM OVERCURRENT PROTECTION
MTD	MOUNTED
MTS	MANUAL TRANSFER SWITCH
N.C.	NORMALLY CLOSED
N.O.	NORMALLY OPEN
NL	NIGHT LIGHT
NTS	NOT TO SCALE
OCPD	OVERCURRENT PROTECTION DEVICE
OH	OVERHEAD
P	POLE
PH	PHASE
PNL	PANEL
PWR	POWER
RECEP	RECEPTACLE
RI	REACHIN
RM	ROOM
SC	SECONTAINED
SCCR	SHORT CIRCUIT CURRENT RATING
SOL	SOLENOID
SW	SWITCH
SWBR	SWITCHBOARD
SWGR	SWITCHGEAR
TBB	TELEPHONE BACKBOARD
TD	TIME DELAY
TELCO	TELEPHONE COMPANY
TELE	TELEPHONE
TGB	TELECOMMUNICATIONS GROUNDING BUSBAR
TMGB	TELECOMMUNICATIONS MAIN GROUNDING BUSBAR
TYP	TYPICAL
UG	UNDERGROUND
UNO	UNLESS NOTED OTHERWISE
UPS	UNINTERRUPTIBLE POWER SUPPLY
V	VOLT
VIF	VERIFY IN FIELD
W/	WITH
W	WIRE
WP	WEATHERPROOF
WR	WEATHER RESISTANT
WTOP	WORKTOP
XFMR	TRANSFORMER

ELECTRICAL SHEET INDEX:

E-001	ELECTRICAL LEGEND AND ABBREVIATION
E-002	ELECTRICAL GENERAL NOTES
E-003	ELECTRICAL SPECIFICATIONS
E-004	COMCHECK
E-010	ELECTRICAL SITE PLAN AND REMOTE DRIVE THRU
E-011	ELECTRICAL PHOTOMETRIC SITE PLAN
E-012	ELECTRICAL SITE DETAILS
E-100	ELECTRICAL POWER & AUXILIARY PLAN
E-101	ELECTRICAL POWER ROOF PLAN
E-130	ELECTRICAL LIGHTING PLAN
E-150	ELECTRICAL SECURITY PLAN
E-500	ELECTRICAL DETAILS
E-600	LUMINAIRE AND SENSOR SCHEDULES AND DETAILS
E-601	EXTERIOR LIGHTING CUTSHEETS
E-602	EXTERIOR LIGHTING CUTSHEETS
E-603	EXTERIOR LIGHTING CUTSHEETS
E-610	ELECTRICAL PANEL SCHEDULES
E-700	ELECTRICAL DEVICE PLAN
E-701	ELECTRICAL ELEVATIONS
E-702	ELECTRICAL ELEVATIONS
E-703	ELECTRICAL ELEVATIONS
E-704	ELECTRICAL ELEVATIONS
E-800	ELECTRICAL RISER DIAGRAM

PRAXIS3
100 Peachtree St NW
Suite 1450
Atlanta, GA 30303
404-875-4500 tel
www.praxis3.com

GEORGIA REGISTERED No. 041560 PROFESSIONAL ENGINEER RAHN ONEAL WILLIAMS

Copyright (c) 2024 Praxis3, LLC

All reports, plans, specifications, computer files, field data, notes and other documents and instruments prepared by Praxis3 shall retain all common law, statutory and other reserved rights, including copyright thereto.

This drawing may not be reproduced in whole or in part without written permission of Praxis3. It is to be returned upon request. Scales as stated are valid on the original drawings.

Rev	Date	Comments
	07/02/2026	PERMIT SET

Client:
FIFTH THIRD BANK

Project Number: 26032
Project Name:
FIFTH THIRD BANK WATSON
1,900 SF

2711 WATSON BOULEVARD
WARNER ROBBINS, GA 31093

Key Plan:

Sheet Title:
ELECTRICAL LEGEND AND ABBREVIATION

Sheet Number:
E-001

6/30/2026 2:31:56 PM