Robot Procedure 2016_027

Aug 10th

2016

Procedure for Setting up patch software update in RJ3iB controller for OS144 & OS145 alarm

[Applicable for RJ3i-B controller as per list softwares]

This document shows a procedure to install patch software (for OS144 & OS145 alarm) into following version controller.

Target Version: **V6.10P/A5**
V6.10P/A6
V6.10P/A7
V6.10P/B0
V6.10P/B1
V6.10P/B2
V6.10P/B3

0. Unzip the mc.zip into memory card.
   Confirm that following files are extracted to the root directory of the memory card.
   - a.cm
   - chif.ld1
   - pgu_a5.ld1
   - pgu_b0.ld1
   - pgu_b3.ld1
   - z060_set.pc
   - z060_set.tp

The above file location: T:\Service\Shared\Knowledge Base\Consolidated Data\Technical Support Informations\ROBOT\Software\RJ3iB Alarm OS144 & OS145_Patch Softwares

1. Please save image backup files before installation.(For safety)

2. Insert patch software memory card into memory card socket of controller.

3. Select file menu.
   - [MENUS]
   - FILE

4. Select MC: as memory device and show list of all files.
   - F5[UTIL]
   - 1 Set Device
   - Select "Mem Card (MC:)".
   - F2 [DIR]
   - Select "*.*" and put ENTER

5. Select A.CM and put ENTER key.

6. Question: Execute A.CM? is displayed. Then press F4 (YES).

7. When following message is displayed, installation is succeeded. Go ahead to 8.
   'Patch was loaded successfully.'
   'Please power off/on.'

   If "Version Mismatch" message is displayed, installation is cancelled.
   Because software version is not Target version.

8. Turn OFF/ON the power.

That's all for installation.

If you want to restore state before patch installation, please restore image backup.
If you want to confirm whether patch software is applied or not,
Please refer "Procedure to confirm patch software (R-J3iB controller) ".

Procedure to confirm patch software (R-J3iB controller)

Step 1
Display [STATUS Version ID] screen by pressing following keys.
[Menu] -> [0. –-NEXT--] -> [4. STATUS] -> [F1. TYPE] -> [2. Version ID]
-> [F3. Config]
Screen similar to following is displayed.

```
STATUS Version ID        G1     JOINT 10 %
     FEATURE:              ORD NO:  1/128
  1  FANUC Handling Tool    H542
  2  Japanese Dictionary    H520
  3  Ext. DIO Config        EIOC
  4  External DI BWD        ESET
  5  SSPC error text        ETSS
  6  Kernel + Basic S/W     H510
  7  Robot Servo Code       H930
  8  Host Communications    HOCO
  9  TCP/IP Interface       HTCP
 10  Web Server             HTTP

[ TYPE ] SOFTWARE CONFIG  MOTOR   SERVO
```

Step 2
Move the cursor to last line.

```
STATUS Version ID        G1     JOINT 10 %
     FEATURE:              ORD NO:  1/128
119  ********************** ****
120  ********************** ****
121  ********************** ****
122  ********************** ****
123  ********************** ****
124  ********************** ****
125  ********************** ****
126  ********************** ****
127  ********************** ****
128  FIX DB/TB PROBLEM      Z060

[ TYPE ] SOFTWARE CONFIG  MOTOR   SERVO
```

Step 3
If patch software has been already applied, [FIX DB/DB PROBLEM Z060] is displayed on the last line.

End of document