

EOS Command API Guide

Software Release 4.36.0FX-SRV6

May 16, 2026

http://www.arista.com email:support@arista.com

Contents

1 Arista Command API Fundamentals **2**
- 1.1 Configuring the Command API Agent . . . 4
  - 1.1.1 Configuring a Certificate . . . 4
  - 1.1.2 Configuring multiple VRFs . . . 4
- 1.2 The Spec . . . 5
  - 1.2.1 Exploring the Command API . . . 5
  - 1.2.2 An annotated example . . . 5
  - 1.2.3 Command Specification . . . 9
  - 1.2.4 Error Codes . . . 9
- 1.3 Using the Command API . . . 9
  - 1.3.1 Unsupported commands . . . 10
  - 1.3.2 Unconverted commands . . . 10
  - 1.3.3 Streamed commands . . . 10
  - 1.3.4 Using JSON-RPC . . . 10
- 1.4 On-box Usage of Command API . . . 11
  - 1.4.1 Using EapiClientLib (requires no configuration) . . . 11
  - 1.4.2 Other Methods (requires configuration) . . . 11
- 1.5 Using Websockets with Command API . . . 11
- 1.6 Client-Side Certificates . . . 12
- 1.7 Session Based Authorization . . . 14
  - 1.7.1 User Login . . . 14
  - 1.7.2 Command Requests . . . 14
  - 1.7.3 User Logout . . . 14
  - 1.7.4 Session Validation . . . 14
- 1.8 Versioning . . . 15
  - 1.8.1 Incompatible Model . . . 15
  - 1.8.2 Understanding Revisions And Versions . . . 16
  - 1.8.3 Accessing a Command's Current Revision . . . 16
  - 1.8.4 More Documentation On Revisions . . . 17

2 Command Output **18**
- 2.1 clear security pki certificate rotation ROTATION_ID . . . 19
- 2.2 dir [...] . . . 19
  - 2.2.1 FileUrl . . . 19
- 2.3 export flow tracking cpu-queue tracker TRACKER_NAME buffers FILE_NAME . . . 19
- 2.4 ping adaptive-virtual-topology (vrf VRF) (avt AVT) (destination DEST) [...] . . . 20
  - 2.4.1 AvtPathSummaryModel . . . 20
  - 2.4.2 AvtPingSequenceModel . . . 20
- 2.5 ping mpls bgp labeled-unicast (ip (IP_ADDR_PREFIX | (IP_PREFIX_PREFIX | (IP_PREFIX_PREFIX_ADDR IP_PREFIX_PREFIX_MASK))) | (ipv6 (IP6_ADDR_PREFIX6 | IP6_PREFIX_PREFIX6)) [...] . . . 22
  - 2.5.1 MplsPingHdr . . . 22
- 2.6 ping mpls bgp vpn (vrf (VRF | default)) (ip PREFIX) | (ipv6 PREFIX6) [...] . . . 25

2.7 ping mpls generic ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK)) [...] 26
2.8 ping mpls ldp ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK)) [...] . . 26
2.9 ping mpls p2mp mldp ROOTADDR ((lsp-id OPQVAL) | (multicast ipv4 SOURCEADDR GROUPADDR)) [...] . . . 26
2.10 ping mpls pseudowire ((ldp PW_NAME) | (vpls ldp INSTANCE_NAME group GROUP_NAME NEIGHBOR_ADDRESS)) [...] . . . 26
2.11 ping mpls rsvp session ((id SESSION_ID) | (name SESSION_NAME)) [...] . . . 26
2.12 ping mpls rsvp tunnel TUNNEL_NAME [...] . . . 26
2.13 ping mpls segment-routing ((((ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK))) | (ipv6 IPV6_ADDRESS) | (isis ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK))) | (isis ipv6 IPV6_ADDRESS))) | (ospf ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK)))) [...] . . . 27
2.14 reset management dmf controller sync . . . 27
2.15 security pki certificate generate signing-request rotation ssl profile PROFILE_NAME key generate ((rsa RSA_BIT_LENGTH) | (ecdsa EC_CURVE_NAME)) [...] . . . 27
2.16 security pki certificate rotation commit ROTATION_ID . . . 27
2.17 security pki certificate rotation commit ssl profile PROFILE_NAME [...] . . . 28
2.18 security pki certificate rotation import ROTATION_ID . . . 28
2.19 session peer-supervisor CMD . . . 28
2.20 show ((ip bgp neighbors) | (ipv6 bgp peers)) ((received-routes) | (received-routes ((regex REGEX) | ((community { (AANN_FORMAT | COMMUNITY_ENUM | COMMUNITY_U32) })) | (access-list AS_PATH_LIST_NAME) | ((IPV4_ADDR | IPV6_ADDR)) | ((IPV4_ADDR_MASK | IPV6_ADDR_MASK))))) [...] . . . 29
2.20.1 BgpRouteHeader . . . 29
2.21 show ((ip bgp neighbors IP_PEER) | (ipv6 bgp peers (IP6_PEER | IP6_LL_PEER))) advertised-routes queued-withdrawals [...] . . . 42
2.21.1 BgpQueuedWithdrawals . . . 42
2.22 show ((ip bgp neighbors PEER) | (ipv6 bgp peers ((IP6_PEER | IP6_LL_PEER)))) (((routes | advertised-routes)) | ((routes | advertised-routes) ((regex REGEX) | ((community { (AANN_FORMAT | COMMUNITY_ENUM | COMMUNITY_U32) })) | (access-list AS_PATH_LIST_NAME) | ((IPV4_ADDR | IPV6_ADDR)) | ((IPV4_ADDR_MASK | IPV6_ADDR_MASK))))) [...] . . . 43
2.23 show ((ip bgp neighbors PEER) | (ipv6 bgp peers ((IP6_PEER | IP6_LL_PEER)))) (advertised-routes attribute discard) [...] . . . 43
2.24 show ((ip mroute sparse-mode) | (pim ipv4 sparse-mode route)) IP1 IP2 interface [...] . . . 44
2.24.1 MrouteSmInterface . . . 44
2.25 show ((ip mroute sparse-mode) | (pim ipv4 sparse-mode route)) [...] . . . 46
2.25.1 GroupSm . . . 46
2.26 show ((ip mroute sparse-mode) | (pim ipv4 sparse-mode route)) count [...] . . . 48
2.27 show ((ip pim) | (pim ipv4)) sparse-mode rp [...] . . . 48
2.27.1 PimRpCandidateSet . . . 49
2.28 show ((ip pim sparse-mode rp-hash) | (pim ipv4 sparse-mode rp hash)) GROUP [...] . . . 49
2.29 show ((ip pim sparse-mode upstream joins) | (pim ipv4 sparse-mode join)) [...] . . . 50
2.29.1 JoinPruneNeighbor . . . 50
2.30 show ((mac address-table) | mac-address-table) [...] . . . 51
2.30.1 MulticastMacAddressTable . . . 51
2.30.2 UnicastMacAddressTable . . . 51
2.31 show ((mac address-table) | mac-address-table) count [...] . . . 51
2.31.1 VlanCount . . . 51
2.32 show ((mac address-table) | mac-address-table) dynamic local limit [...] . . . 52
2.32.1 LimitedVlanEntry . . . 52
2.33 show ((mac address-table) | mac-address-table) mlag-peer [...] . . . 52
2.34 show ((mac address-table) | mac-address-table) mlag-peer diff local-only . . . 52
2.35 show ((mac address-table) | mac-address-table) mlag-peer diff peer-only . . . 52
2.36 show ((mac address-table) | mac-address-table) multicast [...] . . . 52

2.36.1 IgmpSnoopingTableEntry . . . 52
2.37 show ((mac address-table) | mac-address-table) multicast brief [...] . . . 53
2.38 show ((mac address-table) | mac-address-table) notification host-flap detection window . . . 53
2.39 show ((mac address-table) | mac-address-table) notification host-flap logging . . . 53
2.40 show (AGENT | (mpls ldp) | (vrf leak)) rcf [...] . . . 54
2.40.1 ShowAgentRcfFunctionModel . . . 54
2.40.2 ShowAgentRcfDetailFunctionModel . . . 54
2.41 show (AGENT | (mpls ldp) | (vrf leak)) rcf detail [...] . . . 55
2.42 show (arp | (ip arp)) [...] . . . 55
2.42.1 IpV4Neighbor . . . 55
2.43 show (arp | (ip arp)) resolve summary total [...] . . . 55
2.44 show (arp | (ip arp)) summary [...] . . . 55
2.45 show (arp | (ip arp)) | (ipv6 neighbors) remote [...] . . . 55
2.45.1 ArpBindingVlan . . . 56
2.46 show (bgp rpki cache) [...] . . . 57
2.46.1 CacheModel . . . 57
2.47 show (bgp rpki cache counters) [...] . . . 59
2.47.1 CacheCounterModel . . . 59
2.48 show (bgp rpki cache counters) errors [...] . . . 60
2.48.1 CacheRxErrorCounterModel . . . 60
2.48.2 CacheTxErrorCounterModel . . . 60
2.49 show (cli | routing-context) vrf . . . 60
2.50 show (ip | ipv6) attached-host route export [...] . . . 60
2.50.1 AttachedHostInterfaces . . . 61
2.51 show (ip | ipv6) bgp summary lldp [...] . . . 62
2.51.1 BgpSummary . . . 62
2.52 show (ip | ipv6) hardware ale routes acknowledgement [...] . . . 64
2.52.1 AcknowledgementRouteEntry . . . 64
2.53 show (ip | ipv6) hardware ale routes drop [...] . . . 64
2.53.1 VrfDropRoute . . . 64
2.54 show (ip | ipv6) hardware ale routes inconsistent [...] . . . 64
2.54.1 VrfRouteEntry . . . 64
2.55 show (ip | ipv6) hardware ale routes summary [...] . . . 66
2.55.1 Ale.Summary.PlatformStatusCounter . . . 66
2.55.2 Ale.Summary.ReviewQueueCounter . . . 66
2.56 show (ip | ipv6) hardware fib fec [...] . . . 67
2.56.1 FibFecInfo . . . 67
2.57 show (ip | ipv6) hardware fib routes compressed [...] . . . 69
2.57.1 ParentPrefixColl . . . 69
2.58 show (ip | ipv6) hardware fib summary . . . 70
2.58.1 AdjResourceOptimization . . . 70
2.59 show (ip | mac) access-lists payload alias . . . 71
2.59.1 PayloadSpec . . . 71
2.60 show (segment-l3 ipv6 address profile) [...] . . . 72
2.60.1 Ip6AddressInterface . . . 72
2.61 show (segment-l3 ipv6 address profile) aggregates . . . 73
2.61.1 AggregateVrfStatus . . . 73
2.62 show ADDR_FAMILY dhcp relay access-list [...] . . . 74
2.62.1 IpAclList . . . 74
2.62.2 Ipv6AclList . . . 76
2.63 show ADDR_FAMILY dhcp relay counters . . . 76
2.63.1 GlobalCounters . . . 76
2.63.2 InterfaceCounter . . . 76
2.64 show ADDR_FAMILY helper-address . . . 77
2.64.1 ConfiguredInterface . . . 78

2.64.2 DefaultServersShowModel . . . 78
2.64.3 Option82SubOptionsModel . . . 78
2.64.4 RemotePDSyncShowModel . . . 78
2.64.5 VssUnsupportedServersModel . . . 79
2.65 show APPLICATION profile . . . 79
2.65.1 FpgaApplicationInstanceInfo . . . 79
2.66 show APPLICATION profile all . . . 79
2.66.1 FpgaApplicationProfile . . . 79
2.67 show GNSS status . . . 80
2.67.1 Gnss . . . 80
2.68 show SYNCE . . . 81
2.68.1 SynceStatusInfo . . . 81
2.69 show aaa . . . 82
2.69.1 Aaa.Cli.AaaUser . . . 82
2.70 show aaa authentication lockout . . . 82
2.70.1 Aaa.Cli.AaaLockedUser . . . 82
2.71 show aaa counters . . . 82
2.72 show aaa methods accounting . . . 83
2.72.1 AaaMethodListsAcctMethods . . . 83
2.73 show aaa methods all . . . 83
2.73.1 AaaMethodListsAuthen . . . 84
2.73.2 AaaMethodListsAuthz . . . 84
2.74 show aaa methods authentication . . . 84
2.75 show aaa methods authorization . . . 84
2.76 show access-lists [...] . . . 84
2.76.1 IpAclList . . . 84
2.76.2 Ipv6AclList . . . 85
2.76.3 MacAclList . . . 85
2.77 show adaptive-virtual-topology application-profile [...] . . . 85
2.77.1 AvtAppProfileByVrfModel . . . 85
2.78 show adaptive-virtual-topology flow [...] . . . 86
2.78.1 AvtFlowInfo . . . 86
2.79 show adaptive-virtual-topology flow ipv6 [...] . . . 86
2.80 show adaptive-virtual-topology next-hop tunnel encapsulation [...] . . . 86
2.80.1 AvtNextHopByVrfModel . . . 87
2.81 show adaptive-virtual-topology path [...] . . . 88
2.81.1 AvtPathsByVrfModel . . . 88
2.82 show adaptive-virtual-topology path counters [...] . . . 89
2.82.1 AvtCountersByVrfModel . . . 89
2.83 show address locking . . . 91
2.83.1 IpLockingIntfEnabled . . . 91
2.84 show address locking counters . . . 93
2.84.1 ClientIntfCounters . . . 93
2.84.2 IntfCounters . . . 93
2.84.3 ServerCounters . . . 93
2.84.4 ServerIntfCounters . . . 94
2.85 show address locking counters detail [...] . . . 95
2.85.1 ActionCounters . . . 95
2.85.2 IntfCountersList . . . 95
2.86 show address locking servers . . . 95
2.86.1 IpLockingProtocol . . . 96
2.87 show address locking table ipv4 [...] . . . 96
2.87.1 IntfLeases . . . 96
2.88 show agent AGENT activity . . . 97
2.89 show agent AGENT memory allocations slab content SLABNAME SLABSIZE partial [...] . . . 98

2.89.1 SlabAllocatorContentPerThreadModel . . . 98
2.90 show agent AGENT memory allocations slab page statistics . . . 98
2.90.1 SlabAllocatorMappedRangeModel . . . 99
2.90.2 SlabAllocatorPageModel . . . 99
2.91 show agent AGENT memory detail . . . 99
2.92 show agent AGENT task scheduler [...] . . . 100
2.92.1 TaskScheduler . . . 100
2.93 show agent AGENT_NAME schanaccel command batch tracking duration . . . 102
2.93.1 AgentStat . . . 102
2.94 show agent StrataLb table ExactMatchClbV4 [...] . . . 103
2.94.1 ExactMatchEntryV4 . . . 103
2.95 show agent StrataLb table ExactMatchClbV4NoCounter [...] . . . 103
2.95.1 ExactMatchEntryV4NoCounter . . . 103
2.96 show agent StrataLb table ExactMatchClbV4Vxlan [...] . . . 103
2.96.1 ExactMatchEntryV4Vxlan . . . 103
2.97 show agent StrataLb table ExactMatchClbV4VxlanNoCounter [...] . . . 104
2.97.1 ExactMatchEntryV4VxlanNoCounter . . . 104
2.98 show agent StrataLb table ExactMatchClbV6 [...] . . . 104
2.98.1 ExactMatchEntryV6 . . . 104
2.99 show agent StrataLb table ExactMatchClbV6LowNoCounter [...] . . . 105
2.99.1 ExactMatchEntryV6LowNoCounter . . . 105
2.100 show agent StrataLb table ExactMatchClbV6NoCounter [...] . . . 105
2.100.1 ExactMatchEntryV6NoCounter . . . 105
2.101 show agent StrataLb table ExactMatchIpfixRoceV4 [...] . . . 105
2.101.1 ExactMatchEntryIpfixRoceV4 . . . 106
2.102 show agent cpu [...] . . . 106
2.102.1 AgentCpuEntry . . . 106
2.103 show agent event history [...] . . . 106
2.103.1 EventHistoryAgent.Cli.EventHistoryFiltersModel . . . 107
2.103.2 EventHistoryAgent.Cli.LogEntryModel . . . 107
2.104 show agent memory [...] . . . 107
2.104.1 AgentMemoryEntry . . . 107
2.105 show agent memory allocations (delta DELTA) [...] . . . 107
2.105.1 ShowAllocsTypeDiffModel . . . 107
2.106 show agent memory allocations [...] . . . 107
2.106.1 ShowAllocsTypeModel . . . 108
2.107 show agent memory allocations heap summary [...] . . . 108
2.107.1 AgentLib.Cli.Mallinfo . . . 108
2.108 show agent memory allocations slab [...] . . . 109
2.108.1 SlabAllocatorAgentModel . . . 109
2.109 show agent memory allocations slab sort ((blocks (in-use | free | percent-free)) | (memory (in-use | free | percent-free | overhead | total | mmap | madvise | dirty))) . . . 110
2.110 show agent names [...] . . . 110
2.111 show agent oom scores [...] . . . 110
2.111.1 AgentOomScoresEntry . . . 110
2.112 show agent ping [...] . . . 110
2.112.1 AgentPingEntry . . . 111
2.113 show agent qtrace event tracking [...] . . . 111
2.113.1 QtEventTrackingEntryModel . . . 111
2.114 show agent qtrace size [...] . . . 111
2.114.1 AgentLib.Cli.AgentQtHandleInfos . . . 111
2.115 show agent runnability [...] . . . 111
2.115.1 AgentRunnability . . . 112
2.116 show agent sfe threads flow cache scan counters . . . 112
2.116.1 WalkerCounter . . . 112

2.117 show agent sfe threads flow cache scan counters detail [...] . . . 112
2.118 show agent sfe threads flow cache scan status [...] . . . 112
2.118.1 WalkerStatus . . . 112
2.119 show agent socket attrlog [...] . . . 113
2.119.1 AgentSocketAttrLogInfo . . . 113
2.120 show agent socket attrlog detail [...] . . . 113
2.121 show agent stages startup log . . . 114
2.121.1 BootClassStagesLogModel . . . 114
2.122 show agent uptime [...] . . . 114
2.122.1 AgentUptimeEntry . . . 114
2.123 show agent warm-restart [...] . . . 114
2.123.1 ShowAgentWarmRestartEntry . . . 114
2.124 show aliases [...] . . . 115
2.124.1 Cli.Model.Alias . . . 115
2.124.2 Cli.Model.RegexAlias . . . 115
2.125 show application traffic recognition [...] . . . 115
2.125.1 ApplicationModel . . . 115
2.126 show application traffic recognition counters [...] . . . 115
2.126.1 ApplicationCountersModel . . . 116
2.127 show arp agent (ipv4 | ipv6) cache capacity [...] . . . 116
2.127.1 Arp.Cli.CapacityKinds . . . 116
2.128 show arp agent (ipv4 | ipv6) input [...] . . . 117
2.128.1 Arp.Cli.ArpInputEntryList . . . 117
2.129 show arp agent (ipv4 | ipv6) output [...] . . . 117
2.130 show arp counters hardware ingress [...] . . . 117
2.130.1 Arp.Cli.ArpCounter . . . 117
2.131 show arp monitor [...] . . . 117
2.131.1 Arp.Cli.MonitoredNexthopEntry . . . 118
2.131.2 Arp.Cli.MonitoredNexthopVrfSummary . . . 118
2.132 show arp monitor summary . . . 118
2.133 show arp | (ipv6 neighbors) bridged [...] . . . 118
2.134 show backplane-channel [...] . . . 119
2.134.1 PortChannel . . . 119
2.135 show backplane-channel limits . . . 120
2.135.1 LagGroupLimits . . . 120
2.136 show banner login . . . 120
2.137 show banner motd . . . 120
2.138 show bfd ((ip access-list) | (ipv6 access-list)) [...] . . . 120
2.139 show bfd hardware acceleration . . . 120
2.140 show bfd hardware utilization [...] . . . 121
2.140.1 BfdHwResource . . . 121
2.141 show bfd peers [...] . . . 122
2.141.1 BfdNeighborVrf . . . 122
2.142 show bfd peers debug [...] . . . 126
2.142.1 Issue . . . 127
2.143 show bfd peers history [...] . . . 128
2.143.1 PeerSnapshot . . . 128
2.144 show bfd peers protocol vxlan mlag primary . . . 130
2.144.1 VxlanVtepBfdStatus . . . 130
2.145 show bfd peers summary [...] . . . 131
2.145.1 SessionCountByType . . . 132
2.146 show bfd rbfd-stats . . . 132
2.147 show bfd sbfd-stats reflectors . . . 133
2.148 show bgp ((vpn-ipv4 | vpn-ipv6)) summary . . . 133
2.149 show bgp (AFI SAFI) ((IP | IP_PREFIX)) [...] . . . 133

2.150 show bgp (AFI SAFI) [...] . . . 134
2.151 show bgp (AFI SAFI) summary [...] . . . 134
2.152 show bgp (AFI SAFI) summary lldp [...] . . . 134
2.153 show bgp AFI unicast field-set FSNAME [...] . . . 134
2.154 show bgp access-list [...] . . . 134
2.155 show bgp auto-aggregation ipv4 [...] . . . 134
2.155.1 AutoAggregation . . . 134
2.156 show bgp auto-aggregation ipv6 [...] . . . 135
2.157 show bgp convergence [...] . . . 136
2.157.1 ShowBgpConvergenceVrfModel . . . 136
2.158 show bgp debug policy export ((((vrf-route filter-rcf ipv4 unicast) | (vpn-ipv4)) PREFIX) | (((vrf-route filter-rcf ipv6 unicast) | (vpn-ipv6)) PREFIX6)) [...] . . . 138
2.158.1 PolicyEvalResult . . . 138
2.158.2 RcfCodeUnitText . . . 146
2.159 show bgp debug policy export evpn (PREFIX | PREFIX6) [...] . . . 147
2.160 show bgp debug policy export evpn vpws VPWS etid ETID route ROUTE [...] . . . 147
2.161 show bgp debug policy import ((((vpn-route filter-rcf vpn-ipv4) | (ipv4 unicast)) PREFIX) | (((vpn-route filter-rcf vpn-ipv6) | (ipv6 unicast)) PREFIX6)) rd RD [...] . . . 147
2.162 show bgp debug policy inbound neighbor (ADDR | ADDR6 | ADDR6LL | all) ((ipv4 unicast PREFIX) | (ipv6 unicast PREFIX6)) [...] . . . 147
2.163 show bgp debug policy inbound neighbor (ADDR | ADDR6 | ADDR6LL | all) (vpn-ipv4 | vpn-ipv6) (PREFIX | PREFIX6) rd RD [...] . . . 147
2.164 show bgp debug policy inbound neighbor (ADDR | ADDR6 | ADDR6LL | all) evpn route-type ip-prefix (PREFIX | PREFIX6) rd RD [...] . . . 148
2.165 show bgp debug policy inbound neighbor (ADDR | ADDR6 | ADDR6LL | all) flow-spec (ipv4 | ipv6) rule FLOWSPEC_RULE [...] . . . 148
2.166 show bgp debug policy inbound neighbor (ADDR | ADDR6 | ADDR6LL | all) flow-spec (vpn-ipv4 | vpn-ipv6) rule FLOWSPEC_RULE [...] . . . 148
2.167 show bgp debug policy inbound neighbor (ADDR | ADDR6 | ADDR6LL | all) rt-membership origin-as (none | AS_PLAIN_NUM | AS_DOT_NUM) route-target ROUTE_TARGET [...] . 148
2.168 show bgp debug policy network (ipv4 unicast PREFIX) | (ipv6 unicast PREFIX6) [...] . . . 148
2.169 show bgp debug policy outbound neighbor (ADDR | ADDR6 | ADDR6LL) (ipv4 unicast PREFIX) | (ipv6 unicast PREFIX6) [...] . . . 148
2.170 show bgp debug policy outbound neighbor (ADDR | ADDR6 | ADDR6LL) (vpn-ipv4 | vpn-ipv6) (PREFIX | PREFIX6) rd RD [...] . . . 149
2.171 show bgp debug policy outbound neighbor (ADDR | ADDR6 | ADDR6LL) evpn route-type ip-prefix (PREFIX | PREFIX6) rd RD [...] . . . 149
2.172 show bgp debug policy outbound neighbor (ADDR | ADDR6 | ADDR6LL) flow-spec (ipv4 | ipv6) rule FLOWSPEC_RULE [...] . . . 149
2.173 show bgp debug policy outbound neighbor (ADDR | ADDR6 | ADDR6LL) flow-spec (vpn-ipv4 | vpn-ipv6) rule FLOWSPEC_RULE [...] . . . 149
2.174 show bgp debug policy outbound neighbor (ADDR | ADDR6 | ADDR6LL) rt-membership origin-as (none | AS_PLAIN_NUM | AS_DOT_NUM) route-target ROUTE_TARGET [...] . 149
2.175 show bgp debug policy redistribute (ipv4 unicast PREFIX) | (ipv6 unicast PREFIX6) [...] . 149
2.176 show bgp debug policy redistribute flow-spec (ipv4 | ipv6) rule FLOWSPEC_RULE [...] . . 150
2.177 show bgp evpn (arp | mac) [...] . . . 151
2.177.1 EvpnRouteL2TableEntry . . . 151
2.178 show bgp evpn (route-type ((auto-discovery) | (mac-ip) | imet | (ethernet-segment) | (ip-prefix) | (smet | join-sync | leave-sync | spmsi))) internal [...] . . . 153
2.178.1 EvpnRouteEntry . . . 153
2.179 show bgp evpn [...] . . . 157
2.180 show bgp evpn host-flap . . . 157
2.180.1 Routing.Bgp.MacPlugin.HostFlapEntry . . . 157
2.181 show bgp evpn instance [...] . . . 158
2.181.1 BgpEvpnInstance . . . 158

2.182 show bgp evpn route-type count . . . 160
2.183 show bgp evpn sanity [...] . . . 161
2.183.1 EvpnSanityCategory . . . 161
2.184 show bgp evpn summary [...] . . . 161
2.185 show bgp flow-spec (ipv4 | ipv6) summary [...] . . . 161
2.186 show bgp flow-spec (vpn-ipv4 | vpn-ipv6) summary . . . 161
2.187 show bgp flow-spec ipv4 [...] . . . 162
2.187.1 BgpFlowspecRules . . . 162
2.188 show bgp flow-spec ipv6 [...] . . . 164
2.189 show bgp flow-spec vpn-ipv4 [...] . . . 164
2.190 show bgp flow-spec vpn-ipv6 [...] . . . 164
2.191 show bgp instance [...] . . . 165
2.191.1 ShowBgpInstanceModel . . . 165
2.192 show bgp instance vpn summary [...] . . . 169
2.192.1 ShowBgpInstanceVpnSummaryModel . . . 169
2.193 show bgp labeled-unicast forwarding [...] . . . 170
2.193.1 BgpLuForwardingTunnelTableEntry . . . 170
2.194 show bgp labeled-unicast forwarding raw [...] . . . 180
2.195 show bgp labeled-unicast tunnel [...] . . . 180
2.195.1 BgpLuTunnelTableEntry . . . 180
2.196 show bgp labeled-unicast tunnel raw [...] . . . 180
2.197 show bgp link-state [...] . . . 181
2.197.1 BgpLsRoutes . . . 181
2.198 show bgp link-state summary . . . 183
2.199 show bgp monitoring AFI neighbors [...] . . . 183
2.199.1 VrfPeersExportStatus . . . 184
2.200 show bgp monitoring [...] . . . 185
2.200.1 BgpAdjRibInExportStatus . . . 185
2.200.2 BgpAdjRibOutExportStatus . . . 185
2.200.3 BgpAllStationGlobalExportStatus . . . 185
2.200.4 BgpLocRibExportStatus . . . 185
2.200.5 BmpGlobalConfig . . . 186
2.200.6 BmpStation . . . 186
2.201 show bgp monitoring active [...] . . . 188
2.201.1 BmpActive . . . 188
2.202 show bgp monitoring active summary . . . 188
2.202.1 BmpActiveSummary . . . 189
2.203 show bgp monitoring internal scheduler [...] . . . 189
2.204 show bgp monitoring passive [...] . . . 189
2.204.1 BmpPassive . . . 189
2.205 show bgp monitoring passive summary . . . 189
2.205.1 BmpPassiveSummary . . . 190
2.206 show bgp monitoring summary . . . 190
2.206.1 BmpStationSummary . . . 190
2.207 show bgp mvpn-ipv4 (vrf VRF) route-type intra-as-ipmsi [...] . . . 191
2.207.1 MvpnRoutes . . . 191
2.208 show bgp mvpn-ipv4 (vrf VRF) route-type selective-pmsi [...] . . . 193
2.209 show bgp mvpn-ipv4 (vrf VRF) route-type shared-tree [...] . . . 193
2.210 show bgp mvpn-ipv4 (vrf VRF) route-type source-active [...] . . . 193
2.211 show bgp mvpn-ipv4 (vrf VRF) route-type source-tree [...] . . . 193
2.212 show bgp mvpn-ipv4 route-type intra-as-ipmsi [...] . . . 193
2.213 show bgp mvpn-ipv4 route-type selective-pmsi [...] . . . 194
2.214 show bgp mvpn-ipv4 route-type shared-tree [...] . . . 194
2.215 show bgp mvpn-ipv4 route-type source-active [...] . . . 194
2.216 show bgp mvpn-ipv4 route-type source-tree [...] . . . 194

2.217 show bgp mvpn-ipv4 rsvp leaf [...] . . . 194
2.217.1 MvpnVrfRsvpLeafStatus . . . 194
2.218 show bgp mvpn-ipv4 summary . . . 195
2.219 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) ((routes | advertised-routes | (received-routes))) ((IP | IP_PREFIX)) [...] . . . 195
2.220 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) ((routes | advertised-routes | (received-routes))) [...] . . . 195
2.221 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) evpn (advertised-routes | routes | received-routes) [...] . . . 195
2.222 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) flow-spec ipv4 (((routes | received-routes | (advertised-routes)))) [...] . . . 195
2.223 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) flow-spec ipv6 (((routes | received-routes | (advertised-routes)))) [...] . . . 195
2.224 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) flow-spec vpn-ipv4 ROUTE_TYPE [...] . . . 196
2.225 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) flow-spec vpn-ipv6 ROUTE_TYPE [...] . . . 196
2.226 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) link-state ((routes | advertised-routes | (received-routes))) [...] . . . 196
2.227 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) path-selection ROUTE_TYPE [...] . . . 197
2.227.1 BgpDpsVrfRoutes . . . 197
2.228 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) rt-membership ROUTE_TYPE 199
2.228.1 RtMembershipRoutes . . . 199
2.229 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) rt-membership filter . . . 202
2.229.1 ShowRtMembershipNeighborFilterVrfModel . . . 202
2.230 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) sr-te POLICY_FILTER [...] . . . 202
2.231 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) vpn-ipv4 ((routes | advertised-routes | (received-routes))) PREFIX (rd RD_VAL) internal [...] . . . 203
2.231.1 MplsVpnRoutes . . . 203
2.232 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) vpn-ipv4 ((routes | advertised-routes | (received-routes))) [...] . . . 205
2.233 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) vpn-ipv6 ((routes | advertised-routes | (received-routes))) PREFIX (rd RD_VAL) internal [...] . . . 206
2.234 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) vpn-ipv6 ((routes | advertised-routes | (received-routes))) [...] . . . 206
2.235 show bgp neighbors PEER vpls (advertised-routes | received-routes | routes) [...] . . . 207
2.235.1 BgpVplsRoute . . . 207
2.236 show bgp neighbors [...] . . . 209
2.237 show bgp neighbors history [...] . . . 209
2.237.1 NeighborHistoryVrfModel . . . 209
2.238 show bgp neighbors history socket . . . 211
2.238.1 NeighborHistorySocketVrfModel . . . 211
2.239 show bgp optimal-route-reflection position . . . 212
2.239.1 BgpOrrPosition . . . 212
2.240 show bgp path-selection [...] . . . 212
2.241 show bgp path-selection community { (AANN_FORMAT | COMMUNITY_ENUM | COMMUNITY_U32) } [...] . . . 212
2.242 show bgp path-selection community-list COMM_LIST_NAME [...] . . . 212
2.243 show bgp path-selection summary . . . 212
2.244 show bgp peer-group [...] . . . 213
2.244.1 BgpPeerGroups . . . 213
2.245 show bgp rcf [...] . . . 214
2.246 show bgp rcf detail [...] . . . 214
2.247 show bgp route-flap-damping (AFI unicast) [...] . . . 215

2.247.1 BgpRfdVrfModel . . . 215
2.248 show bgp route-flap-damping policy [...] . . . 215
2.248.1 BgpRfdPolicy . . . 216
2.249 show bgp rpki roa ipv4 | ipv6 [...] . . . 216
2.249.1 Roa . . . 216
2.250 show bgp rpki roa summary . . . 216
2.250.1 CacheRoaSummaryModel . . . 216
2.250.2 TableRoaSummaryModel . . . 217
2.251 show bgp rpki roa table summary . . . 217
2.251.1 RoaTableSummaryModel . . . 217
2.252 show bgp rt-membership [...] . . . 217
2.253 show bgp rt-membership floodlist [...] . . . 217
2.253.1 ShowRtMembershipFloodlistVrfModel . . . 217
2.254 show bgp rt-membership origin-as (none | AS_PLAIN_NUM | AS_DOT_NUM) [...] . . . 218
2.255 show bgp rt-membership route-target ROUTE_TARGET [...] . . . 218
2.256 show bgp rt-membership summary . . . 218
2.257 show bgp scheduler [...] . . . 218
2.258 show bgp segment-routing prefix-segments . . . 218
2.258.1 PrefixSegment . . . 218
2.259 show bgp session tracker [...] . . . 218
2.259.1 BgpSessionTrackerEntry . . . 218
2.260 show bgp sr-te [...] . . . 219
2.261 show bgp sr-te community { (AANN_FORMAT | COMMUNITY_ENUM | COMMUNITY_U32) } [...] . . . 219
2.262 show bgp sr-te community-list COMM_LIST_NAME [...] . . . 219
2.263 show bgp sr-te endpoint ENDPOINT_VALUE color COLOR_VALUE distinguisher DISTINGUISHER_VALUE [...] . . . 219
2.264 show bgp sr-te endpoint ENDPOINT_VALUE path-selection color-vrf COLOR_VRF (avt AVT) router ROUTER_ID [...] . . . 219
2.265 show bgp sr-te summary [...] . . . 220
2.266 show bgp statistics [...] . . . 221
2.266.1 BgpStatistics . . . 221
2.266.2 BgpStatisticsGlobal . . . 223
2.267 show bgp summary [...] . . . 224
2.267.1 BgpSummaryAll . . . 224
2.268 show bgp traffic-policy field-set mappings [...] . . . 225
2.268.1 ShowTrafficPolicyFieldSetCommunityMappingsModel . . . 226
2.269 show bgp tunnel udp . . . 226
2.269.1 BgpUdpTunnelTableEntry . . . 226
2.270 show bgp update-group [...] . . . 227
2.270.1 BgpUpdateGroups . . . 227
2.271 show bgp vpls [...] . . . 230
2.272 show bgp vpls auto-discovery [...] . . . 230
2.272.1 BgpVplsAdInstance . . . 230
2.273 show bgp vpls signaling [...] . . . 231
2.273.1 BgpVplsVeInstance . . . 231
2.274 show bgp vpls summary [...] . . . 232
2.275 show bgp vpn-ipv4 PREFIX (rd RD_VAL) internal . . . 232
2.276 show bgp vpn-ipv4 [...] . . . 232
2.277 show bgp vpn-ipv6 PREFIX (rd RD_VAL) internal . . . 232
2.278 show bgp vpn-ipv6 [...] . . . 232
2.279 show bgp vrf selection policy field-set mappings . . . 233
2.279.1 ShowVrfSelectionPolicyFieldSetCommunityMappingsModel . . . 233
2.280 show boot stages log . . . 233
2.281 show boot stages verification sso . . . 233

2.281.1 Stage . . . 233
2.282 show boot stages verification ssu . . . 233
2.283 show boot-config . . . 234
2.283.1 PcrBank . . . 235
2.284 show boot-extensions . . . 235
2.285 show bridge ((mac address-table) | mac-address-table) aging timeout . . . 235
2.286 show cbf nexthop-group override [...] . . . 235
2.286.1 CbfNhgOverride . . . 235
2.287 show cdp neighbors . . . 237
2.287.1 CdpInterface . . . 237
2.288 show cfm alarm indication [...] . . . 238
2.288.1 MdAisModel . . . 238
2.289 show cfm continuity-check counters [...] . . . 239
2.289.1 MdCcCountersModel . . . 239
2.290 show cfm continuity-check counters detail [...] . . . 241
2.290.1 IntfCcCountersModel . . . 241
2.291 show cfm continuity-check end-point [...] . . . 243
2.291.1 MdCcModel . . . 243
2.292 show cfm continuity-check end-point remote-defect [...] . . . 245
2.292.1 MdRdiModel . . . 245
2.293 show cfm counters [...] . . . 246
2.293.1 CfmIntfCounter . . . 246
2.294 show cfm end-point [...] . . . 247
2.294.1 MdModel . . . 247
2.295 show cfm intermediate-point . . . 248
2.296 show cfm measurement delay proactive [...] . . . 249
2.296.1 MdDmModel . . . 249
2.297 show cfm measurement loss proactive [...] . . . 251
2.297.1 MdLmModel . . . 251
2.298 show cfm measurement loss synthetic proactive [...] . . . 253
2.298.1 MdSlmModel . . . 253
2.299 show cfm summary . . . 255
2.299.1 CcSummaryLocActionModel . . . 255
2.299.2 CcSummaryRdiActionModel . . . 255
2.299.3 CfmSummaryProfileModel . . . 255
2.300 show class-map [...] . . . 257
2.300.1 ClassMapModel . . . 257
2.301 show class-map type control-plane [...] . . . 258
2.302 show class-map type pbr [...] . . . 259
2.302.1 ClassMapModel . . . 259
2.303 show class-map type tapagg [...] . . . 267
2.304 show cli commands [({ hidden | functions | (truncate LENGTH) | verbatim })] . . . 267
2.305 show cli commands all-modes [({ hidden | functions | (truncate LENGTH) | verbatim })] . . . 268
2.306 show cli pid . . . 268
2.307 show clock [...] . . . 269
2.307.1 ClockSourceModel . . . 269
2.307.2 LocalTimeModel . . . 269
2.308 show cluster voq attached-host adjacency remote | local [...] . . . 269
2.308.1 ShowClusterVoqAttachedHostAdjacencyDevice . . . 269
2.309 show cluster voq attached-host route local . . . 270
2.309.1 ShowClusterVoqAttachedHostRoute . . . 270
2.310 show cluster voq counters queue remote [...] . . . 270
2.310.1 IngressVoqCounters . . . 270
2.311 show cluster voq device [...] . . . 272
2.311.1 ShowClusterVoqDeviceLeaf . . . 272

2.311.2 ShowClusterVoqDeviceSpine . . . 272
2.311.3 ShowClusterVoqDeviceSpineStage2 . . . 272
2.312 show cluster voq fabric audit [...] . . . 273
2.312.1 FabricAuditIteration . . . 273
2.312.2 FabricAuditDeviceStats . . . 274
2.312.3 FabricAuditPathStats . . . 274
2.313 show cluster voq fabric audit detail [...] . . . 274
2.314 show cluster voq fabric audit history . . . 274
2.315 show cluster voq interfaces . . . 274
2.315.1 ShowClusterVoqInterfacesDevice . . . 274
2.316 show cluster voq qos interfaces ecn [...] . . . 276
2.316.1 IntfEcnModel . . . 276
2.317 show cluster voq summary . . . 277
2.318 show command-tag [...] . . . 278
2.318.1 CommandTagStatus . . . 278
2.319 show configuration checkpoints . . . 278
2.319.1 ConfigSession.Cli.Checkpoint . . . 278
2.320 show configuration consistency igmp snooping . . . 278
2.320.1 ConfigConsistencyTableModel . . . 278
2.321 show configuration consistency nat [...] . . . 279
2.322 show configuration consistency switch ({ aggregation }) . . . 279
2.323 show configuration fragments . . . 279
2.323.1 Fragment . . . 279
2.324 show configuration fragments (all | (named FRAGMENT)) [...] . . . 279
2.324.1 FragmentContent . . . 279
2.325 show configuration fragments combined [...] . . . 280
2.326 show configuration lock . . . 280
2.326.1 Cli.Model.ConfigureLockModelUser . . . 280
2.327 show configuration lock history . . . 280
2.327.1 Cli.Model.ConfigureLockModelHistoryInfo . . . 281
2.328 show configuration sessions [...] . . . 281
2.328.1 ConfigSession.Cli.Session . . . 281
2.329 show configuration sessions history . . . 282
2.329.1 ConfigSession.Cli.Commit . . . 282
2.330 show configuration sessions memory . . . 282
2.330.1 ConfigSession.Cli.SessionMemory . . . 282
2.331 show container-manager backup . . . 282
2.331.1 ContainerMgrBackupFiles . . . 282
2.332 show container-manager containers [...] . . . 283
2.332.1 ContainerMgrContainer . . . 283
2.333 show container-manager images [...] . . . 283
2.333.1 ContainerMgrImage . . . 283
2.334 show container-manager info . . . 284
2.335 show container-manager log CONTAINER_NAME . . . 284
2.336 show container-manager registry [...] . . . 284
2.336.1 ContainerMgrRegistry . . . 284
2.337 show cpu counters queue . . . 284
2.337.1 MakoCpuCountersQueueCoppClassCounts . . . 285
2.338 show cpu counters queue [...] . . . 285
2.338.1 EgressCpuCounters . . . 285
2.338.2 IngressCpuCounters . . . 285
2.339 show cvx [...] . . . 287
2.339.1 ClusterStatus . . . 287
2.339.2 ClusterStatusDebug . . . 288
2.339.3 SslProfileStatus . . . 288

2.340 show cvx connections [...] . . . 288
2.340.1 CvxConnection . . . 288
2.341 show cvx connections client (SYSTEMID | HOSTNAME) . . . 289
2.342 show cvx connections client (SYSTEMID | HOSTNAME) brief . . . 289
2.343 show cvx debug dirs [...] . . . 289
2.343.1 DirStatus . . . 289
2.344 show cvx debug pingpong . . . 289
2.345 show cvx file-replication . . . 290
2.345.1 Status . . . 290
2.346 show cvx file-replication NAME . . . 290
2.347 show cvx mounts . . . 290
2.347.1 CvxMounts . . . 290
2.348 show cvx mounts (HOSTNAME | SYSTEMID) . . . 291
2.349 show cvx service . . . 291
2.349.1 CvxService . . . 291
2.350 show cvx service NAME . . . 292
2.351 show cvx service peer [...] . . . 292
2.351.1 CvxPeerServiceStatus . . . 292
2.352 show daemon DAEMON_NAME ((ip access-list) | (ipv6 access-list) | (access-list)) [...] . . . 292
2.353 show daemon [...] . . . 293
2.353.1 DaemonCli.Cli.DaemonAgent . . . 293
2.354 show dcbx [...] . . . 294
2.354.1 InterfaceDescription . . . 294
2.354.2 EtsTlvModel . . . 295
2.355 show debugging counter { COUNTERS } . . . 295
2.356 show debugging counters [...] . . . 295
2.357 show debugging inotify (QUERY | all) . . . 295
2.357.1 InotifyPids . . . 295
2.357.2 InotifyProc . . . 296
2.358 show debugging inotify file pid PID . . . 296
2.359 show debugging shark clients all . . . 296
2.360 show debugging smash clients all . . . 296
2.360.1 TableInfo . . . 296
2.361 show deep-inspection summary . . . 297
2.362 show dhcp server ((ipv4 leases) | (ipv6 leases) | leases) [...] . . . 298
2.362.1 DhcpServerShowLeasesModel . . . 298
2.363 show dhcp server [...] . . . 299
2.363.1 DhcpServerShowModel . . . 299
2.364 show directflow . . . 303
2.365 show directflow counters [...] . . . 304
2.365.1 Flows . . . 304
2.366 show directflow detail [...] . . . 309
2.366.1 Details . . . 309
2.367 show directflow field-set . . . 309
2.367.1 DirectFlowEndPointList . . . 310
2.368 show directflow flows [...] . . . 310
2.369 show dns cache counters . . . 310
2.370 show dns domain [...] . . . 310
2.371 show dot1q-tunnel [...] . . . 310
2.372 show dot1x all . . . 311
2.372.1 Dot1xInterfaceInformation . . . 311
2.372.2 Dot1xInterfaceDetails . . . 312
2.373 show dot1x all brief . . . 313
2.374 show dot1x all details . . . 314
2.375 show dot1x all statistics . . . 315

2.375.1 Dot1xDroppedCounterStats . . . 315
2.375.2 Dot1xInterfaceStats . . . 315
2.376 show dot1x captive-portal bypass [...] . . . 315
2.376.1 Dot1xCaptivePortalBypassIpMatch . . . 315
2.377 show dot1x captive-portal counters [...] . . . 315
2.377.1 CaptivePortalCountersInterface . . . 316
2.378 show dot1x captive-portal resolutions [...] . . . 316
2.378.1 Dot1xCaptivePortalResolutionsEntry . . . 316
2.379 show dot1x hosts [...] . . . 316
2.379.1 Dot1xHosts . . . 316
2.380 show dot1x hosts blocked . . . 317
2.380.1 Dot1xBlockedMacEntry . . . 317
2.381 show dot1x hosts interface INTFS detail . . . 318
2.381.1 Dot1xIntfHosts . . . 318
2.382 show dot1x hosts mac MAC [...] . . . 320
2.383 show dot1x hosts mac MAC accounting . . . 321
2.384 show dot1x interface INTFS . . . 321
2.385 show dot1x interface INTFS details . . . 321
2.386 show dot1x interface INTFS statistics . . . 322
2.387 show dot1x radius . . . 322
2.387.1 ServerInfo . . . 322
2.388 show dot1x statistics hosts [...] . . . 323
2.388.1 Dot1xHostStats . . . 323
2.388.2 Dot1xInterfaceHostStats . . . 323
2.388.3 Dot1xVlanHostStats . . . 324
2.389 show dot1x supplicant [...] . . . 324
2.389.1 Dot1xSupplicant . . . 324
2.390 show dot1x vlan assignment group [...] . . . 324
2.391 show drop notification trim . . . 325
2.392 show drop notification trim counters . . . 325
2.392.1 PacketTrimming.Cli.PacketTrimmingCountersModel . . . 325
2.393 show dynamic prefix-list [...] . . . 326
2.393.1 DynamicPrefixLists . . . 326
2.394 show e-tree vlan . . . 327
2.394.1 EtreeRoleModel . . . 327
2.395 show environment power . . . 328
2.395.1 Details . . . 328
2.395.2 PowerSupply . . . 328
2.396 show environment power detail . . . 329
2.397 show environment power voltage . . . 330
2.397.1 FruSlot . . . 330
2.398 show event-handler [...] . . . 332
2.398.1 EventHandler . . . 332
2.399 show event-handler trigger counters [...] . . . 334
2.399.1 EventHandlerTriggerCounters . . . 334
2.400 show event-monitor backup status . . . 335
2.400.1 TableBackupStatus . . . 335
2.401 show event-monitor lacp [...] . . . 335
2.401.1 LacpEventMonReasonDetails . . . 335
2.402 show event-monitor row-limit [...] . . . 335
2.402.1 TableRowLimit . . . 335
2.403 show event-monitor status [...] . . . 336
2.403.1 TableStatus . . . 336
2.404 show extensions [...] . . . 337
2.404.1 Extension . . . 337

2.405 show fabric counters [...] . . . 338
2.405.1 FabricCells . . . 338
2.406 show fabric counters detail [...] . . . 339
2.406.1 FabricDetail . . . 339
2.407 show fabric counters errors [...] . . . 339
2.407.1 FabricErrors . . . 339
2.408 show fabric counters rates [...] . . . 339
2.408.1 FabricRates . . . 340
2.409 show fabric peers [...] . . . 340
2.409.1 DeviceFabricConnectivityInfo . . . 340
2.410 show feature-toggle [...] . . . 340
2.410.1 ArToggleEntry . . . 340
2.411 show feature-toggle override status . . . 341
2.412 show fib (ipv4 | ipv6) route limit suppressed [...] . . . 341
2.412.1 FibRouteLimitSuppressedRouteInfo . . . 341
2.413 show file digest HASHTYPE URL . . . 341
2.414 show file information URL . . . 341
2.415 show file systems . . . 342
2.415.1 FileSystem . . . 342
2.416 show firewall distributed instance session-table [...] . . . 343
2.416.1 TrackerModel . . . 343
2.417 show firewall distributed instance session-table archive [...] . . . 345
2.417.1 MonitorSessionModel . . . 345
2.418 show firewall distributed instance status . . . 346
2.419 show firewall distributed interceptor counters . . . 346
2.420 show firewall distributed interceptor flow-table . . . 346
2.420.1 DfwOffloadClientInterceptFlowTableValuesModel . . . 346
2.421 show firewall distributed interceptor status . . . 346
2.421.1 DfwOffloadClientStatus . . . 347
2.422 show firewall distributed offload requests [...] . . . 347
2.422.1 DfwOffloadServer.Cli.FlowOffloadRequestList . . . 347
2.423 show firewall distributed offload status . . . 347
2.423.1 DfwOffloadServer.Cli.ClientStatus . . . 347
2.424 show firewall distributed service-leaf redundancy . . . 348
2.424.1 DfwServiceClusterRedundancy . . . 348
2.425 show firewall distributed service-leaf status . . . 348
2.425.1 DfwServiceClusterStatus . . . 348
2.426 show flow telemetry ipfix counters . . . 350
2.426.1 IpfixExporterCounter . . . 350
2.427 show flow telemetry ipfix flow-table . . . 350
2.427.1 IpfixExporterFlow . . . 350
2.428 show flow telemetry ipfix option-data . . . 351
2.428.1 IpfixExporterOptionData . . . 351
2.429 show flow telemetry ipfix template . . . 352
2.429.1 IpfixExporterTemplate . . . 352
2.430 show flow telemetry postcard counters . . . 352
2.431 show flow telemetry postcard flow-table . . . 352
2.432 show flow telemetry postcard option-data . . . 352
2.433 show flow telemetry sflow counters . . . 353
2.434 show flow telemetry sflow flow-table . . . 353
2.435 show flow telemetry sflow option-data . . . 353
2.436 show flow tracking (cpu-queue | sampled | hardware | mirror-on-drop | (telemetry inband) | (firewall distributed)) [...] . . . 354
2.436.1 EncapTypeModel . . . 354
2.436.2 FilterTypeModel . . . 354

2.436.3 FtModel . . . 355
2.436.4 FtrTrafficTypeModel . . . 358
2.436.5 PacketBufferModel . . . 358
2.436.6 TrapSuppressionModel . . . 358
2.437 show flow tracking (sampled | hardware | (firewall distributed) | (telemetry inband)) ipfix options-table [...] . . . 359
2.437.1 TrackerOptTableModel . . . 359
2.438 show flow tracking (sampled | hardware | (firewall distributed) | (telemetry inband)) ipfix template [...] . . . 360
2.438.1 TrackerTemplateModel . . . 360
2.439 show flow tracking cpu-queue counters . . . 362
2.439.1 CpuQueueCountersModel . . . 362
2.440 show flow tracking hardware counters [...] . . . 363
2.440.1 TrackerCounters . . . 363
2.441 show flow tracking hardware flow-table [...] . . . 365
2.441.1 TrackerModel . . . 365
2.442 show flow tracking hardware flow-table [...]_1 . . . 367
2.442.1 TrackerModel . . . 367
2.443 show flow tracking hardware | (firewall distributed) counters [...] . . . 369
2.444 show flow tracking mirror-on-drop counters [...] . . . 370
2.444.1 TrackerModel . . . 370
2.445 show flow tracking mirror-on-drop counters drop-reason [...] . . . 372
2.446 show flow tracking mirror-on-drop flow-table [...] . . . 372
2.447 show flow tracking sampled counters [...] . . . 373
2.447.1 HardwareOffloadCounters . . . 373
2.447.2 SampleCounters . . . 374
2.447.3 TrackerCounters . . . 374
2.448 show flow tracking sampled counters debug [...] . . . 375
2.448.1 PacketErrorCounter . . . 375
2.449 show flow tracking sampled counters interface errors [...] . . . 376
2.449.1 PerInterfaceFlowErrCounters . . . 376
2.450 show flow tracking sampled flow-table [...] . . . 377
2.450.1 TrackerModel . . . 377
2.451 show flow tracking sampled flow-table hardware [...] . . . 382
2.451.1 HoTrackerModel . . . 382
2.452 show flow tracking sampled flow-table hardware counters [...] . . . 383
2.452.1 HoTrackerCounterModel . . . 383
2.453 show flow tracking sampled statistics [...] . . . 383
2.453.1 FtStatisticsPerTracker . . . 384
2.454 show flow tracking telemetry inband counters [...] . . . 384
2.455 show flow tracking telemetry inband flow-table [...] . . . 384
2.456 show flow-spec (ipv4 | ipv6) summary [...] . . . 384
2.456.1 VrfFlowspecRuleSummary . . . 385
2.457 show flow-spec ipv4 [...] . . . 386
2.457.1 VrfFlowspecRule . . . 386
2.458 show flow-spec ipv6 [...] . . . 389
2.459 show flowcontrol [...] . . . 390
2.459.1 FlowControlData . . . 390
2.460 show forwarding destination [...] . . . 390
2.460.1 EgressInterface . . . 390
2.460.2 PacketDestinationDetailModel . . . 390
2.461 show forwarding destination ingress-interface <ingressIntf> raw <rawPacket> [...] . . . 390
2.462 show fpga applications [...] . . . 391
2.463 show fpga applications compatibility . . . 391
2.463.1 FpgaApplicationsCompatibility . . . 391

2.464 show fpga applications profile [...] . . . 391
2.465 show fpga metawatch buffers [...] . . . 391
2.465.1 MetaWatchInstanceBuffers . . . 391
2.466 show fpga metawatch device-id [...] . . . 392
2.466.1 InstanceDeviceId . . . 392
2.467 show fpga metawatch interfaces counters [...] . . . 393
2.467.1 FpgaMetaWatchInterfaceCountersBase . . . 393
2.467.2 FpgaMetaWatchInIntfCounters . . . 393
2.467.3 FpgaMetaWatchOutIntfCounters . . . 393
2.467.4 FpgaMetaWatchPassIntfCounters . . . 393
2.468 show fpga metawatch interfaces counters deduplication [...] . . . 394
2.468.1 MetaWatchInstanceCountersDedup . . . 394
2.469 show fpga metawatch ptp . . . 395
2.469.1 PtpClockSummary . . . 395
2.469.2 PtpIntfVlanSummary . . . 396
2.470 show fpga metawatch status [...] . . . 397
2.470.1 InstanceStatus . . . 397
2.471 show fpga multiaccess interfaces counters access-list [...] . . . 399
2.471.1 MultiAccessInterfaceCountersAccessList . . . 399
2.472 show fpga multiaccess interfaces counters buffer [...] . . . 399
2.472.1 MultiAccess.Cli.MultiAccessInterfaceCountersBuffer . . . 399
2.473 show fpga multiaccess interfaces counters queue [...] . . . 399
2.473.1 MetaMuxApplicationInterfaceQueueStats . . . 399
2.474 show fpga multiaccess interfaces counters vlan [...] . . . 400
2.474.1 MultiAccess.Cli.MultiAccessInterfaceCountersVlan . . . 400
2.475 show fpga multiaccess interfaces storm-control [...] . . . 400
2.475.1 InterfaceStormControlStatus . . . 400
2.476 show fpga multiaccess status [...] . . . 400
2.476.1 MultiAccessInstanceStatus . . . 400
2.477 show fpga switch ((mac address-table) | mac-address-table) multicast [...] . . . 401
2.477.1 EthGroup . . . 401
2.478 show fpga switch [...] . . . 401
2.478.1 FpgaSwitchCore . . . 402
2.479 show fpga switch counters [...] . . . 402
2.479.1 MakoDebugCounterValue . . . 402
2.480 show fpga switch counters cpu queue . . . 402
2.481 show fpga switch ip route [...] . . . 403
2.481.1 FpgaSwitchCoreRoutes . . . 403
2.482 show fpga switch mapping [...] . . . 404
2.482.1 PortMappings . . . 404
2.483 show fpga switch multicast ip route [...] . . . 404
2.483.1 FpgaSwitchMulticastCoreRoutes . . . 404
2.484 show fpga switch parity event [...] . . . 405
2.484.1 ParityEvent . . . 405
2.485 show gre tunnel static [...] . . . 406
2.485.1 L3IntfTunnelTableEntry . . . 406
2.486 show hardware asset-tag [...] . . . 406
2.486.1 Asset . . . 406
2.486.2 Missing . . . 406
2.487 show hardware capacity [...] . . . 406
2.487.1 TableEntry . . . 406
2.488 show hardware capacity alert threshold . . . 407
2.488.1 TableThreshold . . . 407
2.489 show hardware clock frequency sink . . . 407
2.489.1 FreqSinkInfo . . . 407

2.490 show hardware clock frequency source . . . 408
2.490.1 FreqSourceInfo . . . 408
2.491 show hardware clock frequency topology . . . 408
2.491.1 SinkInfo . . . 408
2.492 show hardware clocking . . . 408
2.492.1 ClockPortStatus . . . 408
2.493 show hardware clocking time-sync . . . 408
2.494 show hardware clocking time-sync offset statistics . . . 409
2.494.1 TimesyncOffsetStatisticsRecord . . . 409
2.495 show hardware counter drop [...] . . . 410
2.495.1 DropEvents . . . 410
2.496 show hardware counter events . . . 410
2.496.1 CounterEvent . . . 411
2.497 show hardware counter feature . . . 412
2.497.1 CounterFeatureInfo . . . 416
2.498 show hardware eeprom [...] . . . 417
2.498.1 Component . . . 417
2.499 show hardware external alarm-input . . . 418
2.499.1 ExternalAlarm . . . 418
2.500 show hardware external alarm-input ALARM_ID . . . 418
2.501 show hardware fabric ejector-handle . . . 418
2.502 show hardware forwarding profile . . . 418
2.503 show hardware fpga detail . . . 418
2.503.1 FpgaHardwareDetails . . . 419
2.504 show hardware fpga error . . . 420
2.504.1 FpgaCrcErrorDetails . . . 420
2.505 show hardware license tpm . . . 421
2.506 show hardware logical-port (pool | POOL_RANGE) status . . . 421
2.506.1 PoolStatus . . . 421
2.507 show hardware pll [...] . . . 421
2.507.1 ClockModel . . . 421
2.508 show hardware resource [...] . . . 421
2.508.1 AgentName . . . 422
2.509 show hardware resource hitbit [...] . . . 423
2.509.1 StrataCounters.HitBits.Cli.FlexibleHitbitRequest . . . 423
2.510 show hardware resource hitbit tables . . . 424
2.511 show hardware resource l3 interface . . . 424
2.512 show hardware resource l3 mgroups [...] . . . 424
2.512.1 MGroupModel . . . 425
2.513 show hardware resource l3 mroutes . . . 425
2.513.1 HardwareResourceMroutesEntry . . . 425
2.514 show hardware resource l3 mroutes_1 . . . 426
2.514.1 StrataMcast.CliModel.ShowHwResL3MroutesEntry . . . 426
2.515 show hardware resource l3 nexthops NEXTHOP_TYPE . . . 426
2.516 show hardware resource l3 summary . . . 427
2.517 show hardware resource mapping table TABLE [...] . . . 429
2.517.1 Table . . . 429
2.518 show hardware resource tcam [...] . . . 430
2.519 show hardware resource vlan . . . 430
2.519.1 HwResourceVlan . . . 430
2.520 show hardware resource vxlan mac [...] . . . 430
2.520.1 VxlanVlanInfo . . . 431
2.521 show hardware speed-group | SPEED-GROUP configurations . . . 431
2.521.1 SpeedGroupCap . . . 431
2.522 show hardware speed-group | SPEED-GROUP status . . . 431

2.522.1 SpeedGroupStatus . . . 431
2.523 show hardware system forwarding-chips . . . 432
2.523.1 ForwardingChip . . . 432
2.524 show hardware system spi-chips . . . 432
2.524.1 SpiChip . . . 432
2.525 show hardware tcam profile ((PROFILE ((feature (((acl vlan ip) | (acl vlan ipv6) | (acl vlan ipv6 egress) | (acl subintf ip) | (acl subintf ipv6) | (acl subintf mac) | (acl port ip) | (acl port ipv6) | (acl port mac) | (acl gre tunnel interface ip) | (acl port ip egress) | (acl port ip egress disabled) | (acl port ip egress mpls-tunnelled-match) | (acl port ipv6 egress) | (acl port ipv6 egress no-recirculation) | (acl port ipv6 source-only egress) | (acl vlan ipv6 source-only egress) | (acl port mac egress) | (acl vlan ip egress) | (acl port ip ingress) | (acl vlan ip ingress) | (acl port ipv6 ingress) | (acl vlan ipv6 ingress) | (acl port mac ingress) | (acl port ipv6 source-only ingress) | (acl tunnel interface ip) | (acl tunnel interface ipv6) | (adaptive-copp ipv4) | (pbr ip) | (pbr ipv6) | (pbr mpls) | (pbr subintf ip) | (pbr subintf ipv6) | (pbr tunnel interface ip) | (tunnel ipv4) | (tunnel vxlan) | (tunnel vxlan multicast mlag) | (tunnel vxlan multi-homing multicast) | (tunnel vxlan multi-homing multicast peg) | (tunnel vxlan multi-homing) | (tunnel vxlan multi-homing domain remote) | (tunnel vxlan routing) | (tunnel vxlan routing v6-underlay) | (tunnel vxlan vni policing) | (qos ip) | (qos ipv6) | (qos subintf ip) | (qos subintf ipv6) | (qos port ip) | (qos port ipv6) | (qos vlan ip) | (qos vlan ipv6) | (qos port ip egress) | (qos vlan ip egress) | (qos vlan ipv6 egress) | (qos mac) | (tapagg port) | (tapagg ip) | (tapagg ipv6) | (tapagg mac) | (tapagg tunnel termination) | (mirror ip) | (mirror ip egress) | (mirror ipv6) | (mirror ipv6 egress) | (mirror mac) | (mirror1 ip ingress) | (mirror1 ipv6 ingress) | (mirror1 mac ingress) | (mirror2 ip ingress) | (mirror2 ipv6 ingress) | (mirror2 mac ingress) | (mirror3 ip ingress) | (mirror3 ipv6 ingress) | (mirror3 mac ingress) | (mirror4 ip ingress) | (mirror4 ipv6 ingress) | (mirror4 mac ingress) | (mirror mpls-over-gre ip) | (mirror mpls-over-gre ipv6) | (mirror port egress rate-limit) | (mirror congestion) | (hash mpls-over-gre inner ipv4) | (hash mpls-over-gre inner ipv6) | (evpn mpls irb) | (evpn mpls multi-homing) | flow | (flow mac) | (flow mac vlan-rewrite) | (flow http) | (flow mac-ipv4-l4) | (flow ipv6) | (flow ipv6 l4) | (flow ipv6 vlan-tag) | cbf | (flex-route) | (counter multicast ipv4) | mpls | (mpls fallback ipv4 preserve dscp) | (mpls fallback ipv6 preserve dscp) | (mpls pop ingress) | (mpls pop ingress multicast) | (counter fabric audit) | (counter lfib) | (counter vlan-interface ingress) | (counter vlan traffic-class) | (counter vtep decap) | dot1x | (flow-spec port ipv4) | (flow-spec port ipv6) | (l2-protocol forwarding) | ipsec | (ipsec egress padding-removal) | (traffic-policy cpu ipv4) | (traffic-policy cpu ipv6) | (traffic-policy cross-field-summarization ipv4) | (traffic-policy cross-field-summarization ipv6) | (traffic-policy port ipv4) | (traffic-policy port ipv6) | (traffic-policy port ipv4 egress) | (traffic-policy port ipv6 egress) | (traffic-policy tapagg ipv6) | (traffic-policy tapagg non-ipv6) | (traffic-policy vlan-bridged ipv4) | (traffic-policy vlan-bridged ipv6) | (traffic-policy vlan-interface ipv4) | (traffic-policy vlan-interface ipv6) | (traffic-policy vrf ipv4) | (traffic-policy vrf ipv6) | (segment-security ipv4) | (segment-security ipv6) | (forwarding-destination) | (forwarding-destination mpls) | (tcp-mss-ceiling ip) | (macsec-proxy) | (interface-policing) | (telemetry postcard policy ipv4) | (telemetry postcard policy ipv6) | (flow tracking sampled accelerated) | (flow tracking sampled ipv4) | (flow tracking sampled ipv4 rocev2) | (ptp e2etransparent one-step) | (vlan editing extended-64) | (vrf selection) | (vrf selection extended) | cfm | (cfm mlag egress) | rfc2544 | (mlag egress filter disabled) | (unicast rpf lookup-vrf) | (srv6 classic) | (sflow filtered-sampling) | (sflow subintf) | (vpls irb) | (private-vlan) | (storm-control subintf) | (load-balance hash extended) | (load-balance hash replacement ipv4 symmetric) | (load-balance hash replacement ipv6 symmetric) | (load-balance dynamic ipv4) | (load-balance dynamic ipv6) | (system ipv6 augment) | (srv6 usid f3216) | (srv6 usid f3216 psp) | eapol))) | detail)) | detail) . . . 434
2.525.1 ProfileModel . . . 435
2.526 show hardware tcam profile PROFILE . . . 436
2.527 show hostname . . . 436
2.528 show hosts . . . 436
2.528.1 IpAddresses . . . 436

2.528.2 NameServerConfig . . . 436
2.529 show icmp error extensions [...] . . . 437
2.529.1 ErrorResponderVrfModel . . . 437
2.530 show icmp error extensions counters [...] . . . 437
2.530.1 ErrorResponderAfCountersModel . . . 437
2.531 show icmp probe . . . 439
2.531.1 ProbeResponderModel . . . 439
2.532 show idprom (transceiver | interface) [...] . . . 440
2.532.1 InterfacesTransceiverIdpromPages . . . 440
2.533 show igmp snooping querier [...] . . . 440
2.533.1 IgmpSnooping.Cli.IgmpSnoopingVlanQuerier . . . 440
2.534 show igmp snooping querier counters [...] . . . 441
2.534.1 IgmpSnoopingVlanQuerierCounters . . . 441
2.535 show igmp snooping querier membership [...] . . . 442
2.535.1 IgmpSnoopingVlanQuerierMembership . . . 442
2.536 show igmp snooping querier membership vlan VLAN_ID group IPADDR . . . 443
2.537 show igmp snooping querier status [...] . . . 443
2.538 show installed-extensions . . . 444
2.538.1 InstallationStatus . . . 444
2.539 show interfaces (counters bins) | (counters bins (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 444
2.539.1 InterfaceInOutBinsCounters . . . 444
2.540 show interfaces (counters errors) | (counters errors (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 445
2.540.1 ErrorCounters . . . 445
2.541 show interfaces (counters half-duplex) | (counters half-duplex (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 445
2.541.1 HalfDuplexErrorCounters . . . 445
2.542 show interfaces (counters ingress acl drop) | (counters ingress acl drop (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 445
2.542.1 InterfacesCounterAclDrop . . . 446
2.543 show interfaces (error-correction) | (error-correction (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 447
2.543.1 InterfaceErrorCorrectionStatus . . . 447
2.544 show interfaces (flow-control) | (flow-control (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 448
2.545 show interfaces (hardware default) | (hardware default (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 449
2.545.1 InterfaceCapabilitiesDefaultData . . . 449
2.546 show interfaces (l2 mtu) | (l2 mtu (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 451
2.546.1 L2Mtu . . . 451
2.547 show interfaces (link-flap damping) | (link-flap damping (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 451
2.547.1 LinkFlapDampingIntfData . . . 452

2.548 show interfaces (phy detail) | (phy detail (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] 453
2.548.1 InterfacePhyStatusesDetailed 453
2.549 show interfaces (phy diag error-correction histogram) | (phy diag error-correction histogram (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . 544
2.549.1 IntfFecHistogramPhy 544
2.550 show interfaces (phy diag test pattern) | (phy diag test pattern (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] 548
2.550.1 IntfTestPatternStatus 548
2.551 show interfaces (phy diag test pattern counters) | (phy diag test pattern counters (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . 549
2.551.1 IntfTestPatternCounters 549
2.552 show interfaces (phy diag test pattern counters detail) | (phy diag test pattern counters detail (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] 550
2.552.1 IntfTestPatternDetail 550
2.553 show interfaces (phy diag test pattern histogram) | (phy diag test pattern histogram (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . 550
2.553.1 PrbsHistogramLane 550
2.554 show interfaces (phy modulation) | (phy modulation (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] 551
2.554.1 InterfacePhyLineRate 551
2.554.2 InterfacePhyModulation 551
2.555 show interfaces (phy precoding) | (phy precoding (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] 552
2.555.1 InterfacePrecoding 552
2.556 show interfaces (phy skew) | (phy skew (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] 552
2.556.1 InterfacesPhySkew 553
2.557 show interfaces (phy skew persistent) | (phy skew persistent (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] 553
2.557.1 InterfacesPhySkewPstore 553
2.558 show interfaces (priority-flow-control) | (priority-flow-control (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] 554
2.558.1 PfcFrameCountersModel 554
2.558.2 PfcIntfStatusModel 554
2.558.3 PfcStatusModel 555
2.558.4 PfcWatchdogStatusModel 555
2.559 show interfaces (priority-flow-control buffer counters) | (priority-flow-control buffer counters (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] 557
2.559.1 PfcIntfBufferCountersModel 557
2.559.2 PfcIntfBufferBytesCountersModel 558

2.559.3 PfcIntfBufferOnChipCountersModel . . . 558
2.559.4 PfcIntfPacketDescriptorCountersModel . . . 558
2.560 show interfaces (priority-flow-control buffer on-chip counters) | (priority-flow-control buffer on-chip counters (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 559
2.561 show interfaces (priority-flow-control counters) | (priority-flow-control counters (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 559
2.562 show interfaces (priority-flow-control counters detail) | (priority-flow-control counters detail (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 559
2.562.1 PfcIntfDetailedCountersModel . . . 560
2.563 show interfaces (priority-flow-control counters watchdog) | (priority-flow-control counters watchdog (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 560
2.563.1 PfcWatchdogIntfCountersModel . . . 560
2.564 show interfaces (priority-flow-control counters watchdog drop) | (priority-flow-control counters watchdog drop (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 561
2.564.1 PfcWatchdogIntfEgressDropCountersModel . . . 561
2.565 show interfaces (priority-flow-control packet descriptor counters) | (priority-flow-control packet descriptor counters (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 562
2.566 show interfaces (priority-flow-control status) | (priority-flow-control status (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 562
2.567 show interfaces (status detail) | (status detail (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 562
2.567.1 InterfaceStatusDetailEntry . . . 562
2.568 show interfaces (status errdisabled) | (status errdisabled (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 563
2.568.1 InterfaceCauseModel . . . 563
2.569 show interfaces (tap | tool) | (tap | tool (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 564
2.569.1 TapProperty . . . 564
2.569.2 ToolProperty . . . 565
2.570 show interfaces Fabric priority-flow-control . . . 566
2.571 show interfaces [...] . . . 567
2.571.1 InterfaceStatus . . . 567
2.571.2 ApplicationInterfaceStatus . . . 570
2.571.3 EthInterfaceStatus . . . 572
2.571.4 EthPhyInterfaceStatus . . . 575
2.571.5 InternalRecircInterfaceStatus . . . 577
2.571.6 LagEthInterfaceStatus . . . 579
2.571.7 InterfaceConfigSanity . . . 581
2.571.8 SubInterfaceStatus . . . 583
2.571.9 TunnelIntfConfigSanity . . . 585

2.571.10 TunnelIntfStatus . . . 586
2.571.11 VlanInterfaceStatus . . . 588
2.571.12 VxlanInterfaceStatus . . . 590
2.572 show interfaces all hardware default . . . 595
2.572.1 InterfaceCapabilitiesData . . . 595
2.573 show interfaces attached nic counters [...] . . . 596
2.573.1 InterfaceCountersBase . . . 596
2.573.2 InterfaceFastCounters . . . 596
2.573.3 VirtualInterfaceCountersBase . . . 596
2.573.4 VxlanInterfaceCounters . . . 596
2.574 show interfaces attached nic counters discards [...] . . . 596
2.574.1 InterfaceCounterDiscards . . . 597
2.575 show interfaces attached nic counters errors [...] . . . 597
2.576 show interfaces cable detail [...] . . . 598
2.576.1 BaseTCableTestStatus . . . 598
2.577 show interfaces config-sanity [...] . . . 599
2.578 show interfaces counters discards [...] . . . 599
2.579 show interfaces counters drop-precedence [...] . . . 599
2.579.1 IntfDropPrecedenceCounters . . . 599
2.580 show interfaces counters egress acl drop [...] . . . 599
2.580.1 EgressAclDropCounters . . . 599
2.581 show interfaces counters egress mtu [...] . . . 600
2.581.1 EgressMtuCounters . . . 600
2.582 show interfaces counters ip [...] . . . 600
2.582.1 InterfaceIpv4Ipv6Counters . . . 600
2.583 show interfaces counters ip rates [...] . . . 600
2.583.1 InterfaceIpv4Ipv6CounterRates . . . 600
2.584 show interfaces counters queue [...] . . . 602
2.584.1 EgressQueueCounters . . . 602
2.584.2 IngressQueueCounters . . . 603
2.585 show interfaces counters queue drop-precedence [...] . . . 603
2.585.1 IntfDropPrecedenceCounters . . . 603
2.586 show interfaces counters queue drops [...] . . . 603
2.586.1 QueueTrafficClassDropsCounters . . . 603
2.587 show interfaces counters queue drops unicast [...] . . . 604
2.587.1 EgressQueueDropCounters . . . 604
2.588 show interfaces counters queue ingress [...] . . . 605
2.589 show interfaces counters queue rates [...] . . . 605
2.590 show interfaces counters rates [...] . . . 606
2.590.1 InterfaceCountersRateBase . . . 606
2.590.2 FabricIntfCountersRateModel . . . 606
2.590.3 FabricPairCountersRateModel . . . 606
2.590.4 InterfaceCountersRate . . . 607
2.590.5 VlanInterfaceCountersRate . . . 607
2.590.6 VxlanInterfaceCountersRate . . . 607
2.591 show interfaces counters rates watermark [...] . . . 607
2.591.1 InterfaceRateWatermark . . . 608
2.592 show interfaces counters traffic-class [...] . . . 608
2.592.1 InterfaceTrafficClassesCounters . . . 608
2.593 show interfaces counters vni [...] . . . 609
2.594 show interfaces counters vni rates [...] . . . 609
2.595 show interfaces counters | (counters (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 609

2.596 show interfaces debounce | (debounce (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 609
2.596.1 InterfaceDebounceTime . . . 609
2.597 show interfaces description [...] . . . 609
2.597.1 InterfaceDescription . . . 610
2.598 show interfaces encapsulation dot1q vlan [...] . . . 610
2.598.1 InterfaceEncapsulations . . . 610
2.599 show interfaces encapsulation vlan [...] . . . 610
2.599.1 FlexibleEncapsulations . . . 610
2.600 show interfaces hardware | (hardware (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 611
2.601 show interfaces interactions | (interactions (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 612
2.601.1 InterfacesInteractionsDataBySpeed . . . 612
2.602 show interfaces mac [...] . . . 614
2.602.1 InterfaceMacData . . . 614
2.603 show interfaces mac security capabilities [...] . . . 615
2.603.1 Macsec.Cli.MacsecCapableInterface . . . 615
2.604 show interfaces queue length [...] . . . 615
2.604.1 QueueTypeQueueInfo . . . 615
2.604.2 SandQueueTypeQueueInfo . . . 615
2.605 show interfaces single INTF . . . 616
2.606 show interfaces status | (status (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 617
2.606.1 InterfaceStatusEntry . . . 617
2.607 show interfaces switchport configuration source [...] . . . 618
2.607.1 ConfigSource . . . 618
2.608 show interfaces switchport vlan mapping [...] . . . 619
2.608.1 InterfaceVlanMappings . . . 619
2.609 show interfaces switchport | (switchport (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 620
2.609.1 SwitchPort . . . 620
2.610 show interfaces transceiver [...] . . . 622
2.610.1 InterfaceTransceiverBase . . . 622
2.610.2 InterfaceTransceiver . . . 622
2.611 show interfaces transceiver channels [...] . . . 623
2.611.1 InterfaceTransceiverChannels . . . 623
2.612 show interfaces transceiver diag test pattern [...] . . . 624
2.612.1 InterfacesTransceiverTestPatternConfiguration . . . 624
2.613 show interfaces transceiver diag test pattern capabilities [...] . . . 624
2.613.1 InterfacesTransceiverTestPatternCapabilities . . . 625
2.614 show interfaces transceiver diag test pattern counters [...] . . . 625
2.614.1 InterfacesTransceiverTestPatternCounters . . . 625
2.615 show interfaces transceiver dom [...] . . . 626
2.615.1 InterfaceTransceiverDomBase . . . 626
2.615.2 InterfaceTransceiverDom . . . 626
2.616 show interfaces transceiver eeprom [...] . . . 628
2.616.1 InterfacesTransceiverEepromIntf . . . 628
2.617 show interfaces transceiver hardware [...] . . . 630
2.617.1 InterfacesTransceiverHardware . . . 630

2.618 show interfaces transceiver performance-monitoring [...] . . . 631
2.618.1 InterfaceTransceiverPerformanceMonitoring . . . 631
2.619 show interfaces transceiver properties [...] . . . 631
2.619.1 TransceiverProperties . . . 631
2.620 show interfaces transceiver tuning [...] . . . 632
2.620.1 InterfaceTransceiverTuning . . . 632
2.621 show interfaces trunk | (trunk (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 633
2.621.1 InterfaceTrunk . . . 633
2.622 show interfaces unidirectional | (unidirectional (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...] . . . 634
2.622.1 InterfaceUnidirectional . . . 634
2.623 show interfaces vlans [...] . . . 634
2.623.1 InterfaceVlansModel . . . 635
2.624 show internet-exit policy [...] . . . 636
2.624.1 SfeIePolicyStatusModel . . . 636
2.625 show inventory . . . 637
2.625.1 CardSlot . . . 637
2.625.2 Clock . . . 638
2.625.3 FanTraySlot . . . 638
2.625.4 Fpga . . . 638
2.625.5 PowerSupplySlot . . . 638
2.625.6 StorageDevice . . . 638
2.625.7 SystemInformation . . . 638
2.625.8 XcvrSlot . . . 638
2.626 show ip . . . 639
2.626.1 IpMulticastRouting . . . 639
2.626.2 V6EcmpModel . . . 639
2.627 show ip access-lists [...] . . . 639
2.628 show ip address virtual source-nat sourceNatAddr . . . 639
2.629 show ip arp inspection interface [...] . . . 639
2.629.1 ArpInspectionInterfaceConfig . . . 640
2.630 show ip arp inspection statistics vlan | interface [...] . . . 641
2.630.1 ArpInspectionStatistics . . . 641
2.630.2 IntfArpInspectionStatistics . . . 641
2.630.3 VlanArpInspectionStatistics . . . 641
2.631 show ip arp inspection vlan [...] . . . 642
2.631.1 VlanArpInspectionStatus . . . 642
2.632 show ip as-path access-list NAME detail . . . 642
2.632.1 IpAsPathList . . . 642
2.633 show ip as-path access-list NAME summary . . . 642
2.634 show ip as-path access-list [...] . . . 643
2.635 show ip bgp ((community regex COMMREGEX as-path regex ASPREGEX) | (regex ASPREGEX community regex COMMREGEX)) [...] . . . 643
2.636 show ip bgp (IP | PREFIX) [...] . . . 643
2.637 show ip bgp [...] . . . 643
2.638 show ip bgp access-list AS_PATH_LIST_NAME [...] . . . 643
2.639 show ip bgp community regex REGEX [...] . . . 643
2.640 show ip bgp field-set FSNAME [...] . . . 643
2.641 show ip bgp large-community { LARGE_COMM_VALUE } detail exact [...] . . . 644
2.642 show ip bgp neighbors [...] . . . 645
2.642.1 BgpPeerList . . . 645
2.643 show ip bgp neighbors update errors [...] . . . 669

2.643.1 BgpNeighborUpdateError . . . 669
2.644 show ip bgp regex REGEX [...] . . . 670
2.645 show ip bgp summary [...] . . . 670
2.646 show ip community-list [...] . . . 670
2.646.1 IpCommunityList . . . 670
2.647 show ip decap-group [...] . . . 671
2.647.1 DecapGroupModelBase . . . 671
2.647.2 DecapGroupGreModel . . . 671
2.647.3 DecapGroupIpIpModel . . . 672
2.647.4 DecapGroupQosTcModel . . . 672
2.647.5 DecapGroupUdpModel . . . 672
2.648 show ip decap-group gre keys [...] . . . 673
2.648.1 DecapGroupWithOnlyGreKeyToVrfMapModel . . . 673
2.649 show ip decap-group qos [...] . . . 673
2.650 show ip dhcp relay . . . 673
2.651 show ip dhcp snooping . . . 673
2.651.1 CircuitIdModel . . . 673
2.652 show ip dhcp snooping counters [...] . . . 675
2.652.1 VlanCounters . . . 675
2.653 show ip dhcp snooping counters debug . . . 675
2.653.1 SnoopingRelayCounters . . . 676
2.654 show ip dhcp snooping hardware . . . 676
2.654.1 VlanList . . . 676
2.655 show ip extcommunity-list [...] . . . 676
2.655.1 IpExtCommunityList . . . 676
2.656 show ip hardware ale adj [...] . . . 677
2.656.1 AleL3AdjInfo . . . 677
2.657 show ip hardware ale adj acknowledgement [...] . . . 679
2.657.1 AcknowledgementFecEntry . . . 679
2.658 show ip hardware ale adj export [...] . . . 679
2.658.1 AleOpenConfigExportedFec . . . 680
2.659 show ip hardware ale adj platform-api [...] . . . 681
2.659.1 AleShmemAdjInfo . . . 681
2.660 show ip hardware ale adj proxy [...] . . . 685
2.660.1 FecProxyInfo . . . 685
2.661 show ip hardware ale counters egress bindings l2-adj [...] . . . 685
2.661.1 AleL2AdjCounterBindingsInfo . . . 685
2.662 show ip hardware ale counters egress bindings platform-key [...] . . . 686
2.662.1 AlePdckCounterBindingsInfo . . . 686
2.663 show ip hardware ale event counters (summary | (counter COUNTERNAME)) [...] . . . 686
2.663.1 Ale.Model.AleDebugCountersEntryList . . . 686
2.664 show ip hardware ale event statistics [...] . . . 687
2.664.1 AleEventStatInfo . . . 687
2.665 show ip hardware ale l2-adj [...] . . . 688
2.665.1 AleL2AdjInfo . . . 688
2.666 show ip hardware ale mac-address router gateway . . . 689
2.666.1 VlanListType . . . 689
2.667 show ip hardware ale routes [...] . . . 689
2.667.1 AleRouteInfo . . . 689
2.668 show ip hardware ale routes diff [...] . . . 690
2.668.1 AleRouteDiffDisplayDataEntryList . . . 690
2.669 show ip hardware ale routes platform-api [...] . . . 690
2.669.1 AleShmemRoutes . . . 690
2.670 show ip hardware ale routes vrf all [...] . . . 692
2.671 show ip hardware ale vrf . . . 692

2.671.1 VrfStatus . . . 692
2.672 show ip hardware fib ecmp resilience [...] . . . 692
2.672.1 AleResEcmpRouteInfos . . . 692
2.673 show ip hardware fib ecmp resilience summary [...] . . . 693
2.674 show ip hardware fib load-balance distribution . . . 694
2.675 show ip hardware fib load-balance distribution dynamic group RANGE flows . . . 694
2.675.1 FlowsetTableEntry . . . 695
2.676 show ip hardware fib load-balance distribution dynamic group flows . . . 695
2.677 show ip hardware fib load-balance distribution dynamic interfaces . . . 695
2.677.1 DlbInterface . . . 695
2.678 show ip hardware fib routes [...] . . . 695
2.679 show ip igmp access-list [...] . . . 695
2.680 show ip igmp groups GROUPADDR [...] . . . 695
2.680.1 IgmpGroup . . . 696
2.681 show ip igmp groups [...] . . . 696
2.682 show ip igmp groups count [...] . . . 696
2.683 show ip igmp groups interface INTF [...] . . . 696
2.684 show ip igmp groups interface INTF count [...] . . . 696
2.685 show ip igmp host-proxy (debug | interface) [...] . . . 697
2.685.1 IgmpHostProxyInterface . . . 697
2.686 show ip igmp host-proxy config-sanity . . . 698
2.686.1 IHPPotentialMisconfigs . . . 698
2.687 show ip igmp interface [...] . . . 699
2.687.1 IgmpInterface . . . 699
2.688 show ip igmp membership [...] . . . 699
2.688.1 IgmpMemGrpList . . . 699
2.689 show ip igmp profile [...] . . . 700
2.689.1 ProfileInfo . . . 700
2.690 show ip igmp snooping [...] . . . 701
2.690.1 IgmpSnoopingVlanInfo . . . 701
2.691 show ip igmp snooping counters [...] . . . 702
2.691.1 IgmpSnooping.Cli.IgmpSnoopingCountersInterface . . . 702
2.692 show ip igmp snooping groups [...] . . . 702
2.692.1 VlanMembershipInfo . . . 703
2.693 show ip igmp snooping groups count [...] . . . 703
2.694 show ip igmp snooping groups detail [...] . . . 703
2.694.1 VlanMembershipDetailInfo . . . 704
2.695 show ip igmp snooping groups proxy [...] . . . 704
2.695.1 IgmpSnoopingProxyPorts . . . 705
2.696 show ip igmp snooping mrouter [...] . . . 705
2.696.1 IgmpSnoopingMrouterVlan . . . 705
2.697 show ip igmp snooping report-flooding [...] . . . 706
2.697.1 IgmpSnoopingVlanReportFlooding . . . 706
2.698 show ip igmp static-groups [...] . . . 706
2.698.1 IgmpStaticGroupsInterface . . . 706
2.699 show ip igmp static-groups group [...] . . . 707
2.699.1 IgmpInterfacesList . . . 707
2.700 show ip igmp statistics [...] . . . 708
2.700.1 IgmpStatisticsInterface . . . 708
2.701 show ip interface [...] . . . 709
2.701.1 IpStatus . . . 709
2.702 show ip interface brief [...] . . . 710
2.702.1 IpStatusBrief . . . 710
2.703 show ip large-community-list [...] . . . 711
2.703.1 IpLargeCommunityList . . . 711

2.704 show ip load-sharing trident fields . . . 712
2.704.1 EcmpHashFieldsCommon . . . 712
2.704.2 EcmpHashFieldsGtp . . . 712
2.704.3 EcmpHashFieldsIp . . . 712
2.704.4 EcmpHashFieldsIpv6 . . . 712
2.705 show ip mroute GROUP_OR_SOURCE1 interface [...] . . . 712
2.705.1 MrouteInterfaceDetails . . . 713
2.706 show ip mroute [...] . . . 714
2.706.1 Groups . . . 714
2.707 show ip mroute bidirectional GROUP_ADDR interface [...] . . . 715
2.708 show ip mroute bidirectional [...] . . . 715
2.709 show ip mroute bidirectional count [...] . . . 715
2.710 show ip mroute count [...] . . . 715
2.711 show ip mroute sparse-mode (sources | groups) [...] . . . 715
2.711.1 SourceGroupCollection . . . 715
2.712 show ip mroute vrf all [...] . . . 715
2.713 show ip msdp peer [...] . . . 716
2.713.1 PeerInfo . . . 716
2.714 show ip msdp peer authentication [...] . . . 716
2.714.1 Routing.Msdp.Model.PeerAuthentication.TcpAoInfo . . . 717
2.715 show ip msdp pim sa-cache [...] . . . 717
2.716 show ip msdp sa-cache [...] . . . 717
2.717 show ip msdp summary [...] . . . 717
2.717.1 PeerSummary . . . 717
2.718 show ip multicast boundary [...] . . . 718
2.718.1 McastBoundaryInterface . . . 718
2.719 show ip name-server [...] . . . 718
2.720 show ip nat ((access-list | acl)) [...] . . . 718
2.720.1 NatAcl . . . 718
2.721 show ip nat counters [...] . . . 720
2.721.1 NatCounters . . . 720
2.722 show ip nat dynamic counters [...] . . . 721
2.722.1 NatDynamicCountersProfileModel . . . 721
2.723 show ip nat flow action [...] . . . 722
2.723.1 NatFlowActionPolicy . . . 722
2.724 show ip nat flow match [...] . . . 723
2.724.1 NatFlowMatchPolicy . . . 723
2.725 show ip nat flow profile [...] . . . 723
2.725.1 NatFlowProfilePolicy . . . 724
2.726 show ip nat logging . . . 724
2.727 show ip nat pool [...] . . . 724
2.727.1 NatPool . . . 724
2.728 show ip nat profile [...] . . . 725
2.728.1 NatProfile . . . 725
2.729 show ip nat service-list [...] . . . 725
2.729.1 NatServiceList . . . 725
2.730 show ip nat synchronization . . . 726
2.730.1 Version . . . 726
2.730.2 NatSyncFwdToPeer . . . 726
2.731 show ip nat synchronization advertised-translations [...] . . . 727
2.731.1 Translation . . . 727
2.732 show ip nat synchronization discovered-translations [...] . . . 728
2.733 show ip nat synchronization peer . . . 728
2.734 show ip nat translation (address-only | full-cone) flows [...] . . . 729
2.734.1 IntfTranslationFlows . . . 729

2.735 show ip nat translation DYNAMIC_TYPE [...] . . . 730
2.735.1 Translation . . . 730
2.736 show ip nat translation STATIC_TYPE [...] . . . 731
2.737 show ip nat translation [...] . . . 731
2.738 show ip nat translation address-only mapping [...] . . . 731
2.738.1 SrcIpTranslations . . . 731
2.739 show ip nat translation connection limit drop [...] . . . 732
2.739.1 DropRuleCounter . . . 732
2.739.2 DropTable . . . 732
2.739.3 PoolDropCounter . . . 732
2.740 show ip nat translation dynamic summary . . . 732
2.740.1 DynamicTranslationSummary . . . 732
2.741 show ip nat translation max-entries . . . 734
2.741.1 NatHostConnectionLimit . . . 734
2.741.2 NatPoolConnectionLimit . . . 735
2.742 show ip nat translation max-entries IPADDR . . . 735
2.743 show ip nat translation max-entries pool POOL . . . 735
2.744 show ip nat translation rates . . . 735
2.744.1 NatTranslationRates . . . 735
2.745 show ip nat translation summary [...] . . . 735
2.745.1 TranslationSummary . . . 736
2.746 show ip nat translation twice [...] . . . 737
2.746.1 Translation . . . 737
2.747 show ip nat translation vrf [...] . . . 737
2.747.1 Translation . . . 738
2.748 show ip ospf [...] . . . 739
2.748.1 InstListOspfShowInstModel . . . 739
2.749 show ip ospf access-list [...] . . . 744
2.750 show ip ospf border-routers [...] . . . 744
2.750.1 InstListOspfBorderRoutersInstance . . . 744
2.751 show ip ospf counters [...] . . . 745
2.751.1 InstListOspfCountersInstance . . . 745
2.752 show ip ospf counters interface [...] . . . 746
2.752.1 InstListOspfCountersInterface . . . 746
2.753 show ip ospf counters interface rates [...] . . . 748
2.753.1 InstListOspfCountersInterfaceRates . . . 748
2.754 show ip ospf counters neighbor [...] . . . 750
2.754.1 InstListOspfCountersNeighbor . . . 750
2.755 show ip ospf database [...] . . . 751
2.755.1 InstListOspfDatabaseInstance . . . 751
2.756 show ip ospf database database-summary [...] . . . 759
2.756.1 InstListOspfDatabaseSummary . . . 759
2.757 show ip ospf interface [...] . . . 760
2.757.1 InstListOspfInterface . . . 760
2.758 show ip ospf local-convergence-delay [...] . . . 762
2.758.1 InstListOspfConvergenceDelayInstanceModel . . . 762
2.759 show ip ospf lsa-log [...] . . . 763
2.759.1 InstListOspfLsaLogModel . . . 763
2.760 show ip ospf mpls ldp sync [...] . . . 764
2.760.1 InstListOspfMplsLdpSyncModel . . . 764
2.761 show ip ospf neighbor [...] . . . 765
2.761.1 InstListOspfNeighborsInstance . . . 765
2.762 show ip ospf neighbor adjacency-changes [...] . . . 766
2.762.1 InstListOspfNeighborAdjChanges . . . 767
2.763 show ip ospf neighbor summary [...] . . . 767

2.763.1 InstListOspfNeighborSummaryInstance . . . 767
2.764 show ip ospf request queue [...] . . . 768
2.764.1 InstListOspfLsaRequestList . . . 768
2.765 show ip ospf retransmission queue [...] . . . 769
2.765.1 InstListOspfLsaRetransmissionList . . . 769
2.766 show ip ospf segment-routing . . . 769
2.766.1 InstListOspfShowSrModel . . . 769
2.767 show ip ospf segment-routing adjacency-segments . . . 771
2.767.1 InstListOspfShowSrAdjacencySegmentSummaryModel . . . 771
2.768 show ip ospf segment-routing bindings [...] . . . 772
2.768.1 MplsLabelBinding . . . 772
2.768.2 MplsLdpBindingAdvertisements . . . 773
2.769 show ip ospf segment-routing global-blocks . . . 773
2.769.1 InstListOspfShowSrGlobalBlocksSummaryModel . . . 773
2.770 show ip ospf segment-routing prefix-segments [...] . . . 774
2.770.1 InstListOspfShowSrPrefixSegmentSummaryModel . . . 774
2.771 show ip ospf segment-routing tunnel [...] . . . 775
2.771.1 OspfSrTunnelTableEntry . . . 775
2.772 show ip ospf sham-link [...] . . . 775
2.773 show ip ospf sham-link route [...] . . . 776
2.773.1 RibRoutesByProtocol . . . 776
2.774 show ip ospf spf-log [...] . . . 779
2.774.1 InstListOspfSpfLog . . . 779
2.775 show ip ospf summary [...] . . . 780
2.775.1 InstListOspfShowSummaryModel . . . 780
2.776 show ip ospf ti-lfa path [...] . . . 782
2.776.1 TilfaPathOspfVrfModel . . . 782
2.777 show ip pim access-list [...] . . . 784
2.778 show ip pim anycast-rp [...] . . . 784
2.779 show ip pim bidirectional df [...] . . . 784
2.779.1 Rpas . . . 784
2.780 show ip pim bidirectional rp [...] . . . 784
2.781 show ip pim bidirectional rp-hash GROUP_ADDR [...] . . . 785
2.782 show ip pim bidirectional upstream joins [...] . . . 785
2.783 show ip pim bsr [...] . . . 785
2.783.1 ElectedBsr . . . 785
2.784 show ip pim bsr counters [...] . . . 786
2.784.1 PimBsrErrorCounters . . . 786
2.785 show ip pim bsr debug . . . 787
2.785.1 PimBsrBorder . . . 787
2.785.2 PimBsrCandidate . . . 787
2.785.3 PimBsrRpCandidate . . . 788
2.785.4 PimBsrRpCandidateStatus . . . 788
2.785.5 ZoneAcl . . . 788
2.785.6 ZoneGroup . . . 788
2.786 show ip pim bsr rp [...] . . . 788
2.787 show ip pim bsr rp-hash GROUP [...] . . . 788
2.788 show ip pim config-sanity anycast-rp [...] . . . 788
2.788.1 RouteCheck . . . 789
2.789 show ip pim config-sanity bidirectional [...] . . . 790
2.789.1 MrtConfigCheck . . . 790
2.789.2 StaticRpSet . . . 790
2.790 show ip pim config-sanity igmp [...] . . . 791
2.790.1 InvalidBoundaryGroup . . . 791
2.790.2 NotDefinedBAcl . . . 791

2.790.3 NotStandardBAcl . . . 791
2.791 show ip pim config-sanity interface [...] . . . 791
2.792 show ip pim config-sanity neighbor [...] . . . 792
2.792.1 InvalidHello . . . 792
2.793 show ip pim config-sanity sparse-mode [...] . . . 792
2.794 show ip pim interface [...] . . . 793
2.794.1 PimInterface . . . 793
2.795 show ip pim neighbor [...] . . . 795
2.795.1 VrfPimNeighbors . . . 795
2.796 show ip pim neighbor bfd [...] . . . 796
2.796.1 VrfPimBfdNeighbors . . . 796
2.797 show ip pim protocol counters [...] . . . 796
2.797.1 PimMessageCounter . . . 796
2.797.2 PimMessageCountersDetails . . . 796
2.798 show ip pim register-source [...] . . . 796
2.799 show ip pim rp [...] . . . 797
2.800 show ip pim rp-candidate [...] . . . 797
2.800.1 PimRpCandidate . . . 797
2.801 show ip pim rp-hash GROUP_ADDR [...] . . . 797
2.802 show ip pim upstream joins [...] . . . 797
2.803 show ip prefix-list NAME detail . . . 798
2.803.1 IpPrefixList . . . 798
2.804 show ip prefix-list NAME summary . . . 798
2.805 show ip prefix-list [...] . . . 798
2.806 show ip rip access-list [...] . . . 799
2.807 show ip route (PREFIX | ADDR) longer-prefixes [...] . . . 800
2.807.1 IpRoutes . . . 800
2.808 show ip route [...] . . . 804
2.809 show ip route fec [...] . . . 805
2.809.1 FecRoutesModel . . . 805
2.810 show ip route fec protocol summary . . . 806
2.810.1 FecTypeBreakdown . . . 806
2.811 show ip route fec summary [...] . . . 807
2.811.1 FecBreakdown . . . 807
2.812 show ip route host [...] . . . 807
2.812.1 IpRoutesHost . . . 807
2.813 show ip route kernel unprogrammed [...] . . . 808
2.813.1 UnprogrammedRoutes . . . 808
2.814 show ip route multicast [...] . . . 808
2.814.1 MulticastRibRoute . . . 808
2.815 show ip route next-hop nexthop-group [...] . . . 808
2.816 show ip route next-hop vxlan [...] . . . 808
2.817 show ip route priority summary [...] . . . 809
2.817.1 IpRoutePrioritySummaryForVrf . . . 809
2.818 show ip route rpf unicast [...] . . . 810
2.818.1 UrpfInterface . . . 810
2.819 show ip route static not-installed bfd [...] . . . 810
2.819.1 NotInstalledBfd . . . 811
2.820 show ip route summary [...] . . . 812
2.820.1 IpRouteSummaryForVrf . . . 812
2.820.2 ServiceRoutingProtoModelStatus . . . 813
2.821 show ip route vrf all summary brief [...] . . . 813
2.822 show ip security applied-profile [...] . . . 814
2.822.1 IpsecAppliedProfile . . . 814
2.823 show ip security connection [...] . . . 815

2.823.1 IpsecConnection . . . 815
2.824 show ip security connection policy [...] . . . 819
2.825 show ip security daemon [...] . . . 820
2.826 show ip security daemon log [...] . . . 820
2.827 show ip security encryption status . . . 820
2.828 show ip security fips status . . . 820
2.829 show ip security key controller local . . . 820
2.829.1 IpsecLocalKey . . . 820
2.830 show ip security key controller peer [...] . . . 821
2.830.1 IpsecPeer . . . 821
2.831 show ip security policy [...] . . . 821
2.831.1 IpsecPolicy . . . 822
2.832 show ip security profile [...] . . . 822
2.832.1 IpsecProfile . . . 822
2.833 show ip security security-association [...] . . . 822
2.833.1 IpsecSecurityAssociation . . . 823
2.834 show ip source binding static [...] . . . 823
2.834.1 IpMacBindingEntry . . . 823
2.835 show ip user route [...] . . . 823
2.835.1 IpRibRoutes . . . 824
2.836 show ip verify source . . . 824
2.836.1 IpsgInterfaceOperationalState . . . 824
2.837 show ip verify source detail . . . 824
2.837.1 IpsgBindingDetailStateList . . . 825
2.838 show ip verify source vlan . . . 825
2.838.1 IpsgVlanOperationalState . . . 825
2.839 show ip virtual-router [...] . . . 826
2.839.1 VarpRouterBase . . . 826
2.839.2 VarpRouterV4 . . . 826
2.839.3 VarpRouterV6 . . . 827
2.839.4 VirtualRouterMacModel . . . 827
2.839.5 MlagPeerRouterMac . . . 827
2.839.6 VarpRouterMac . . . 827
2.840 show ipv6 access-lists [...] . . . 827
2.841 show ipv6 address virtual source-nat sourceNatAddr . . . 828
2.842 show ipv6 bgp (IP | PREFIX) [...] . . . 828
2.843 show ipv6 bgp [...] . . . 828
2.844 show ipv6 bgp access-list AS_PATH_LIST_NAME [...] . . . 828
2.845 show ipv6 bgp field-set FSNAME [...] . . . 828
2.846 show ipv6 bgp large-community { LARGE_COMM_VALUE } detail exact [...] . . . 828
2.847 show ipv6 bgp peers [...] . . . 828
2.848 show ipv6 bgp peers update errors [...] . . . 829
2.849 show ipv6 bgp regex REGEX [...] . . . 829
2.850 show ipv6 bgp summary [...] . . . 829
2.851 show ipv6 dhcp relay installed routes [...] . . . 829
2.851.1 Dhcp6InstalledRoutesPerVrf . . . 829
2.852 show ipv6 dhcp relay routes sync . . . 829
2.852.1 Ip.Helper.DhcpRelay.Cli.RemoteNeighborSyncStatus . . . 830
2.853 show ipv6 dhcp snooping . . . 830
2.854 show ipv6 dhcp snooping counters [...] . . . 830
2.855 show ipv6 dhcp snooping counters debug . . . 830
2.856 show ipv6 dhcp snooping hardware . . . 831
2.857 show ipv6 hardware ale routes [...] . . . 831
2.858 show ipv6 hardware ale routes platform-api [...] . . . 831
2.859 show ipv6 hardware ale routes vrf all [...] . . . 831

2.860 show ipv6 hardware fib ecmp resilience [...] . . . 831
2.861 show ipv6 hardware fib ecmp resilience summary [...] . . . 831
2.862 show ipv6 hardware fib routes [...] . . . 831
2.863 show ipv6 interface [...] . . . 832
2.863.1 Ip6Status . . . 832
2.864 show ipv6 interface brief [...] . . . 834
2.864.1 Ip6StatusBrief . . . 834
2.865 show ipv6 nd proxy [...] . . . 834
2.865.1 Arp.Cli.NdProxyPrefixInterface . . . 834
2.866 show ipv6 nd ra internal state [...] . . . 836
2.866.1 Interface . . . 836
2.866.2 VrfGlobalCounters . . . 837
2.867 show ipv6 nd ra neighbors [...] . . . 837
2.867.1 InterfaceNeighbors . . . 837
2.868 show ipv6 neighbor [...] . . . 838
2.868.1 IpV6Neighbor . . . 838
2.869 show ipv6 ospf [...] . . . 839
2.869.1 InstListOspf3ShowInstModel . . . 839
2.870 show ipv6 ospf access-list [...] . . . 842
2.871 show ipv6 ospf border-routers [...] . . . 842
2.871.1 InstListOspf3BorderRoutersInstance . . . 842
2.872 show ipv6 ospf database [...] . . . 844
2.872.1 InstListOspf3DatabaseInstance . . . 844
2.873 show ipv6 ospf database database-summary [...] . . . 847
2.873.1 InstListOspf3DatabaseSummary . . . 847
2.874 show ipv6 ospf interface [...] . . . 849
2.874.1 InstListOspf3Interface . . . 849
2.875 show ipv6 ospf lsa-log [...] . . . 850
2.875.1 InstListOspf3LsaLogInst . . . 850
2.876 show ipv6 ospf neighbor [...] . . . 852
2.876.1 InstListOspf3NeighborsInstance . . . 852
2.877 show ipv6 ospf request-list [...] . . . 853
2.877.1 InstListOspf3LsaRequestList . . . 854
2.878 show ipv6 ospf retransmission-list [...] . . . 854
2.878.1 InstListOspf3LsaRetransmissionList . . . 854
2.879 show ipv6 ospf spf-log [...] . . . 855
2.879.1 InstListOspf3SpfLogInst . . . 855
2.880 show ipv6 prefix-list NAME detail . . . 855
2.881 show ipv6 prefix-list NAME summary . . . 855
2.882 show ipv6 prefix-list [...] . . . 856
2.883 show ipv6 route (PREFIX | ADDR) longer-prefixes [...] . . . 857
2.883.1 Ip6Routes . . . 857
2.884 show ipv6 route [...] . . . 858
2.885 show ipv6 route fec [...] . . . 858
2.886 show ipv6 route fec summary [...] . . . 858
2.887 show ipv6 route host [...] . . . 858
2.887.1 Ip6RoutesHost . . . 858
2.888 show ipv6 route kernel unprogrammed [...] . . . 859
2.889 show ipv6 route multicast [...] . . . 859
2.890 show ipv6 route next-hop nexthop-group [...] . . . 859
2.891 show ipv6 route priority summary [...] . . . 859
2.892 show ipv6 route rpf unicast [...] . . . 859
2.892.1 Ip6UrpfInterface . . . 860
2.893 show ipv6 route static not-installed bfd [...] . . . 860
2.894 show ipv6 route summary [...] . . . 861

2.894.1 Ip6RouteSummaryForVrf . . . 861
2.895 show ipv6 route vrf all summary brief [...] . . . 862
2.896 show ipv6 user route [...] . . . 862
2.897 show ipv6 virtual-router [...] . . . 862
2.898 show isis (area proxy) | (INSTANCE area proxy) | (area proxy vrf VRFNAME) . . . 862
2.898.1 InstancesIsisShowAreaProxyModel . . . 863
2.899 show isis (database (detail | traffic-engineering)) | (INSTANCE database (detail | traffic-engineering)) | (database (detail | traffic-engineering) vrf VRFNAME) [...] . . . 864
2.899.1 InstancesIsisLsdbDetailModel . . . 864
2.900 show isis (database detail tlv) | (INSTANCE database detail tlv) | (database detail tlv vrf VRFNAME) [...] . . . 877
2.900.1 InstancesIsisLsdbDetailTlvModel . . . 877
2.901 show isis (dynamic flooding interfaces) | (INSTANCE dynamic flooding interfaces) | (dynamic flooding interfaces vrf VRFNAME) [...] . . . 888
2.901.1 InstancesIsisDynFloodInterfacesModel . . . 888
2.902 show isis (dynamic flooding nodes) | (INSTANCE dynamic flooding nodes) | (dynamic flooding nodes vrf VRFNAME) [...] . . . 888
2.902.1 InstancesIsisDynFloodNodeModel . . . 888
2.903 show isis (dynamic flooding paths) | (INSTANCE dynamic flooding paths) | (dynamic flooding paths vrf VRFNAME) [...] . . . 889
2.903.1 InstancesIsisDynFloodPathsModel . . . 889
2.904 show isis (dynamic flooding topology) | (INSTANCE dynamic flooding topology) | (dynamic flooding topology vrf VRFNAME) [...] . . . 889
2.904.1 InstancesIsisDynFloodTopologyModel . . . 890
2.905 show isis (flex-algo) | (INSTANCE flex-algo) | (flex-algo vrf VRFNAME) [...] . . . 891
2.905.1 InstancesIsisShowFlexAlgoModel . . . 891
2.906 show isis (graceful-restart) | (INSTANCE graceful-restart) | (graceful-restart vrf VRFNAME) 893
2.906.1 InstancesIsisGracefulRestartModel . . . 893
2.907 show isis (local-convergence-delay) | (INSTANCE local-convergence-delay) | (local-convergence-delay vrf VRFNAME) [...] . . . 895
2.907.1 InstancesIsisUloopModel . . . 895
2.908 show isis (lsp log) | (INSTANCE lsp log) | (lsp log vrf VRFNAME) . . . 896
2.908.1 InstancesIsisLspLogTableModel . . . 896
2.909 show isis (lsp purges) | (INSTANCE lsp purges) | (lsp purges vrf VRFNAME) [...] . . . 897
2.909.1 InstancesIsisLspPurgesModel . . . 897
2.910 show isis (network topology) | (INSTANCE network topology) | (network topology vrf VRFNAME) [...] . . . 898
2.910.1 InstancesIsisTopologyModel . . . 898
2.911 show isis (segment-routing) | (INSTANCE segment-routing) | (segment-routing vrf VRFNAME) . . . 900
2.911.1 InstancesSrSummaryModel . . . 900
2.912 show isis (segment-routing adjacency-segments) | (INSTANCE segment-routing adjacency-segments) | (segment-routing adjacency-segments vrf VRFNAME) . . . 902
2.912.1 InstancesAdjacencySegmentSummaryModel . . . 902
2.913 show isis (segment-routing global-blocks) | (INSTANCE segment-routing global-blocks) | (segment-routing global-blocks vrf VRFNAME) . . . 904
2.913.1 InstancesGlobalBlockSummaryModel . . . 904
2.914 show isis (segment-routing prefix-segments) | (INSTANCE segment-routing prefix-segments) | (segment-routing prefix-segments vrf VRFNAME) [...] . . . 905
2.914.1 InstancesPrefixSegmentSummaryModel . . . 905
2.915 show isis (spf log) | (INSTANCE spf log) | (spf log vrf VRFNAME) [...] . . . 907
2.915.1 InstancesIsisSpfLogTableModel . . . 907
2.916 show isis (srv6 locators detail) | (INSTANCE srv6 locators detail) | (srv6 locators detail vrf VRFNAME) . . . 907
2.916.1 InstancesIsisInstanceSrv6Locators . . . 907

2.917 show isis (summary-address) | (INSTANCE summary-address) | (summary-address vrf VRF-NAME) [...] . . . 908
2.917.1 InstancesIsisLeakedRouteSumAddrInstanceModel . . . 908
2.918 show isis counters | (INSTANCE counters) | (counters vrf VRFNAME) [...] . . . 910
2.918.1 InstancesIsisInstanceCounters . . . 910
2.919 show isis database | (INSTANCE database) | (database vrf VRFNAME) [...] . . . 924
2.919.1 InstancesIsisLsdbSummaryModel . . . 924
2.920 show isis flex-algo path [...] . . . 925
2.920.1 FlexAlgoPathVrfModel . . . 925
2.921 show isis hostname | (INSTANCE hostname) | (hostname vrf VRFNAME) . . . 926
2.921.1 InstancesIsisHostnameInstanceModel . . . 926
2.922 show isis interface | (INSTANCE interface) | (interface vrf VRFNAME) | (interface intf) [...] 928
2.922.1 InstancesIsisInterfaceModel . . . 928
2.923 show isis mpls ldp sync [...] . . . 932
2.923.1 InstancesIsisMplsLdpSyncModel . . . 932
2.924 show isis neighbors | (INSTANCE neighbors) | (neighbors vrf VRFNAME) [...] . . . 933
2.924.1 InstancesIsisInstanceNeighbors . . . 933
2.925 show isis segment-routing tunnel [...] . . . 935
2.925.1 IsisSrTunnelTableEntry . . . 935
2.926 show isis summary | (INSTANCE summary) | (summary vrf VRFNAME) . . . 936
2.926.1 InstancesIsisInstanceSummaryModel . . . 936
2.927 show isis ti-lfa path [...] . . . 939
2.927.1 TilfaPathVrfModel . . . 939
2.928 show isis ti-lfa tunnel [...] . . . 940
2.928.1 TilfaTunnelTableEntry . . . 940
2.929 show kernel interface addr [...] . . . 941
2.929.1 ShowKernelInterfaceAddrVrf . . . 941
2.930 show kernel interface counters [...] . . . 942
2.930.1 ShowKernelInterfaceCountersVrf . . . 942
2.931 show kernel ip acl [...] . . . 944
2.931.1 ShowKernelIpAclVrf . . . 944
2.932 show kernel ip arp [...] . . . 945
2.932.1 ShowKernelIpArpVrf . . . 945
2.933 show kernel ip counters [...] . . . 946
2.933.1 ShowKernelIpCountersVrfDetails . . . 946
2.934 show kernel ip interface addr [...] . . . 946
2.935 show kernel ip route [...] . . . 947
2.935.1 ShowKernelIpRouteVrf . . . 947
2.936 show kernel ipsec [...] . . . 948
2.936.1 ShowKernelIpsecConnections . . . 948
2.936.2 ShowKernelIpsecSecurityAssociations . . . 948
2.936.3 ShowKernelIpsecStrongSwan . . . 948
2.937 show kernel ipv6 acl [...] . . . 949
2.938 show kernel ipv6 counters [...] . . . 949
2.939 show kernel ipv6 interface addr [...] . . . 949
2.940 show kernel ipv6 neighbors [...] . . . 949
2.941 show kernel ipv6 route [...] . . . 949
2.942 show kernel ports in-use [...] . . . 949
2.942.1 ShowKernelInUsePorts . . . 949
2.943 show kernel software forwarding hardware offload config-sanity [...] . . . 950
2.943.1 Fwd0EthTypeConfigSanityEntries . . . 950
2.944 show kernel software forwarding hardware offload summary [...] . . . 950
2.944.1 Fwd0EthTypeEntries . . . 950
2.945 show kernelFib scheduler [...] . . . 951
2.946 show l1 counters status [...] . . . 951

2.946.1 L1CounterStatus . . . 951
2.947 show l1 destination [...] . . . 951
2.947.1 L1Destination . . . 952
2.947.2 PhysicalIntfs . . . 952
2.947.3 VirtualIntfs . . . 952
2.948 show l1 matrix [...] . . . 952
2.948.1 L1MatrixEntry . . . 952
2.949 show l1 modules profile configuration [...] . . . 952
2.949.1 Enumeration . . . 952
2.950 show l1 modules profile status [...] . . . 953
2.950.1 Status . . . 953
2.951 show l1 path [...] . . . 953
2.951.1 L1Source . . . 953
2.952 show l1 port breakout status [...] . . . 953
2.952.1 PortBreakoutStatus . . . 953
2.953 show l1 port phy polarity [...] . . . 953
2.953.1 PhyPolaritySetting . . . 954
2.954 show l1 port status [...] . . . 954
2.954.1 L1PortStatus . . . 954
2.955 show l1 source [...] . . . 954
2.956 show l1 source capabilities [...] . . . 954
2.956.1 SourceableIntfs . . . 955
2.957 show l2-protocol forwarding interfaces [...] . . . 955
2.957.1 L2ProtocolForwardingInterface . . . 955
2.958 show l2-protocol forwarding profile [...] . . . 955
2.958.1 L2ProtocolForwardingProfile . . . 955
2.959 show l2-protocol forwarding profile summary [...] . . . 956
2.959.1 L2ProtocolForwardingProfileSummary . . . 956
2.960 show l2Rib (input SOURCE) [...] . . . 957
2.960.1 HostEntry . . . 957
2.960.2 HostEntryAndSource . . . 958
2.961 show l2Rib (input SOURCE) destination [...] . . . 958
2.961.1 DestsFromHostTable . . . 958
2.962 show l2Rib (input SOURCE) destination floodset [...] . . . 959
2.962.1 DestFloodSetSummary . . . 959
2.963 show l2Rib (input SOURCE) floodset [...] . . . 959
2.963.1 FloodSetSummary . . . 959
2.964 show l2Rib output [...] . . . 959
2.965 show l2Rib output destination [...] . . . 959
2.966 show l2Rib output destination floodset [...] . . . 959
2.967 show l2Rib output floodset [...] . . . 960
2.968 show l2Rib summary . . . 960
2.968.1 TableSummary . . . 960
2.969 show lacp aggregates [...] . . . 960
2.969.1 LacpMarkerMessages . . . 960
2.969.2 PortChannelAggregate . . . 960
2.970 show lacp counters [...] . . . 962
2.970.1 InterfaceLacpCounters . . . 962
2.970.2 PortChannelLacpCounters . . . 962
2.971 show lacp interface [...] . . . 963
2.971.1 InterfaceLacp . . . 963
2.971.2 PortChannelLacp . . . 964
2.972 show lacp interface counters [...] . . . 964
2.973 show lacp interface internal [...] . . . 965
2.973.1 InterfaceLacpInternal . . . 965

2.973.2 LacpSysIdBase . . . 966
2.973.3 MlagLacpSysId . . . 966
2.973.4 PortChannelLacpInternal . . . 966
2.974 show lacp interface peer [...] . . . 967
2.974.1 InterfaceLacpNeighbors . . . 967
2.974.2 PortChannelLacpNeighbors . . . 967
2.975 show lacp internal [...] . . . 967
2.976 show lacp internal events [...] . . . 968
2.976.1 LacpInternalEventRecord . . . 968
2.977 show lacp peer [...] . . . 968
2.978 show lacp sys-id [...] . . . 968
2.978.1 Details . . . 969
2.979 show led [...] . . . 969
2.979.1 LedSetting . . . 969
2.980 show led palette [...] . . . 969
2.980.1 LedCapability . . . 969
2.981 show led state [...] . . . 969
2.981.1 LedStateDict . . . 970
2.982 show led theme . . . 970
2.982.1 LightSettingTheme . . . 970
2.983 show led theme interface [...] . . . 970
2.984 show license [...] . . . 970
2.984.1 FeatureModel . . . 970
2.985 show license features . . . 971
2.986 show license files [...] . . . 971
2.987 show line system dom [...] . . . 971
2.988 show line system eeprom [...] . . . 971
2.989 show line system idprom [...] . . . 971
2.990 show line system status [...] . . . 972
2.990.1 InterfacesTransceiverStatusValues . . . 972
2.991 show lldp [...] . . . 991
2.991.1 LldpInterface . . . 991
2.991.2 TlvType . . . 992
2.992 show lldp counters [...] . . . 992
2.992.1 LldpInterfaceTraffic . . . 992
2.993 show lldp local-info [...] . . . 993
2.993.1 LocalInterfaceInfo . . . 993
2.993.2 ManagementAddr . . . 998
2.993.3 SystemCapabilities . . . 998
2.994 show lldp neighbors [...] . . . 1000
2.994.1 LldpNeighbor . . . 1000
2.994.2 LldpSwagNeighbor . . . 1000
2.995 show lldp neighbors detail [...] . . . 1001
2.995.1 LldpNeighborsList . . . 1001
2.995.2 LldpSwagMemberDetail . . . 1005
2.996 show load-balance destination ip ingress-interface INTF dst-mac-address DST_MAC { ((src-ip-address SRC_IP) | (dst-ip-address DST_IP) | (ip-ttl IP_TTL) | (ip-protocol IP_PROTO)) | ((src-l4-port SRC_L4_PORT) | (dst-l4-port DST_L4_PORT)) } | { ((src-ipv6-address SRC_IPV6) | (dst-ipv6-address DST_IPV6) | (hop-limit HOP_LIMIT) | (next-header NEXT_HDR) | (flow-label FLOW_LABEL)) | ((src-l4-port SRC_L4_PORT) | (dst-l4-port DST_L4_PORT)) } [...] . . . 1006
2.997 show load-balance destination ip ingress-interface INTF src-ipv4-address SRC_IPV4ADDR dst-ipv4-address DST_IPV4ADDR ip-protocol PROTO [...] . . . 1006
2.998 show load-balance destination ip ingress-interface INTF src-ipv6-address SRC_IPV6ADDR dst-ipv6-address DST_IPV6ADDR ip-protocol PROTO [...] . . . 1006

2.999 show load-balance destination mac ingress-interface INTF src-mac-address SRC_MAC dst-mac-address DST_MAC (ether-type ETH_TYPE) | { ((src-ip-address SRC_IP) | (dst-ip-address DST_IP) | (ip-ttl IP_TTL) | (ip-protocol IP_PROTO)) | ((src-l4-port SRC_L4_PORT) | (dst-l4-port DST_L4_PORT)) } | { ((src-ipv6-address SRC_IPV6) | (dst-ipv6-address DST_IPV6) | (hop-limit HOP_LIMIT) | (next-header NEXT_HDR) | (flow-label FLOW_LABEL)) | ((src-l4-port SRC_L4_PORT) | (dst-l4-port DST_L4_PORT)) } [...] 1006
2.1000 show load-balance destination port-channel PORT_CHANNEL (bridged ((vlan-id VLAN) (src-mac-address SRC_MAC) (dst-mac-address DST_MAC))) | (routed ((vlan-id VLAN) (src-mac-address SRC_MAC) (dst-mac-address DST_MAC)) ((src-ip-address SRC_IP) (dst-ip-address DST_IP) (ip-protocol IP_PROTO))) [...] 1007
2.1001 show load-balance destination port-channel PORT_CHANNEL { ((ingress-interface ING_INTF) | (vlan-id VLAN) | non-unicast) | ((src-mac-address SRC_MAC) | (dst-mac-address DST_MAC) | (eth-type ETH_TYPE)) } | { ((ingress-interface ING_INTF) | (vlan-id VLAN) | non-unicast) | ((src-ip-address SRC_IP) | (dst-ip-address DST_IP) | (ip-ttl IP_TTL) | (ip-protocol IP_PROTO)) | ((src-l4-port SRC_L4_PORT) | (dst-l4-port DST_L4_PORT)) } | { ((ingress-interface ING_INTF) | (vlan-id VLAN) | non-unicast) | ((src-ipv6-address SRC_IPV6) | (dst-ipv6-address DST_IPV6) | (hop-limit HOP_LIMIT) | (next-header NEXT_HDR) | (flow-label FLOW_LABEL)) | ((src-l4-port SRC_L4_PORT) | (dst-l4-port DST_L4_PORT)) } 1007
2.1002 show load-balance ecmp sand fields [...] 1008
2.1002.1 Module 1008
2.1003 show load-balance port-channel sand fields [...] 1012
2.1003.1 Module 1012
2.1003.2 AradProfile 1013
2.1004 show load-balance profile [...] 1014
2.1005 show logging counters 1015
2.1005.1 LogCounterStat 1015
2.1006 show logging group server [...] 1015
2.1006.1 LogGroupStatus 1015
2.1007 show loop-protection [...] 1016
2.1007.1 LoopProtectShowDetail 1016
2.1008 show loop-protection counters 1016
2.1008.1 LoopProtectCounter 1016
2.1009 show loop-protection vlan VLANSET 1017
2.1009.1 LoopProtectVlanIntfList 1017
2.1010 show mac access-lists [...] 1017
2.1011 show mac pause-frame 1017
2.1012 show mac security counters [...] 1018
2.1012.1 MacSecCountersInterface 1018
2.1013 show mac security interface [...] 1020
2.1013.1 MacsecInterface 1020
2.1014 show mac security mka counters [...] 1022
2.1014.1 MacsecMessageCountersInterface 1022
2.1015 show mac security participants [...] 1023
2.1015.1 MacsecParticipantsInterface 1023
2.1016 show mac security profile [...] 1024
2.1016.1 MacsecProfiles 1024
2.1017 show mac security ptp bypass 1025
2.1017.1 MacsecPtpBypassInterface 1025
2.1018 show mac security sak [...] 1025
2.1018.1 MacsecSak 1026
2.1019 show mac security status 1026
2.1020 show mac source-check invalid 1027
2.1021 show mac source-check system-mac 1027
2.1022 show mac timestamp keyframe profile [...] 1027

2.1022.1 Profile . . . 1027
2.1023 show mac traffic-policy field-set [...] . . . 1027
2.1023.1 MacTrafficPolicyMacFieldSetSource . . . 1027
2.1024 show mac traffic-policy summary . . . 1028
2.1024.1 MacTrafficPolicySourceSummary . . . 1028
2.1025 show maintenance . . . 1028
2.1025.1 MaintenanceProtocolInfo . . . 1029
2.1026 show maintenance bgp (IP_PEER | IP6_PEER | IP6_LL_PEER) [...] . . . 1030
2.1026.1 BgpPeerMaintenanceInfo . . . 1030
2.1027 show maintenance bgp ip all [...] . . . 1032
2.1027.1 BgpMaintenanceStatus . . . 1032
2.1028 show maintenance bgp ipv6 all [...] . . . 1032
2.1029 show maintenance bgp receiver route-map . . . 1032
2.1030 show maintenance debug [...] . . . 1032
2.1030.1 MaintenanceEventInfo . . . 1032
2.1031 show maintenance debug bgp . . . 1033
2.1032 show maintenance debug bgp (GROUP | IP_PEER | IP6_PEER | IP6_LL_PEER) [...] . . . 1033
2.1033 show maintenance groups . . . 1033
2.1033.1 BgpGroup . . . 1033
2.1033.2 InterfaceGroup . . . 1033
2.1034 show maintenance groups bgp [...] . . . 1034
2.1035 show maintenance groups interface [...] . . . 1034
2.1036 show maintenance interface [...] . . . 1034
2.1036.1 MaintenanceInterfaceBrief . . . 1034
2.1037 show maintenance interface detail [...] . . . 1035
2.1037.1 MaintenanceInterfaceStatus . . . 1035
2.1038 show maintenance profiles . . . 1036
2.1038.1 BgpProfile . . . 1037
2.1038.2 InterfaceProfile . . . 1037
2.1038.3 UnitProfile . . . 1037
2.1039 show maintenance profiles bgp [...] . . . 1037
2.1040 show maintenance profiles bgp default . . . 1037
2.1041 show maintenance profiles interface [...] . . . 1038
2.1042 show maintenance profiles interface default . . . 1038
2.1043 show maintenance profiles unit [...] . . . 1038
2.1044 show maintenance profiles unit default . . . 1038
2.1045 show maintenance stages [...] . . . 1038
2.1045.1 MaintenanceStage . . . 1038
2.1046 show maintenance summary . . . 1039
2.1046.1 MaintenanceRateMonSummary . . . 1039
2.1047 show maintenance units [...] . . . 1039
2.1047.1 MaintenanceUnit . . . 1039
2.1048 show management api eos-sdk-rpc . . . 1041
2.1048.1 EosSdkRpcTransportStatus . . . 1041
2.1049 show management api gnmi . . . 1044
2.1049.1 GnmiEndpointStatus . . . 1044
2.1049.2 GrpctunnelClientStatus . . . 1044
2.1050 show management api gnmi access-list [...] . . . 1045
2.1051 show management api gnpsi . . . 1046
2.1051.1 GnpsiTransportStatus . . . 1046
2.1052 show management api gnsi . . . 1047
2.1052.1 GnsiEndpointStatus . . . 1047
2.1053 show management api gribi . . . 1048
2.1053.1 GribiRpcStatus . . . 1048
2.1054 show management api gribi access-list [...] . . . 1049

2.1055 show management api http-commands . . . 1050
2.1055.1 HttpProtocolStatus . . . 1051
2.1055.2 SslProfile . . . 1051
2.1055.3 UnixProtocolStatus . . . 1051
2.1055.4 UserStatistics . . . 1051
2.1056 show management api http-commands ((ip access-list) | (ipv6 access-list)) [...] . . . 1051
2.1057 show management api http-commands https certificate . . . 1051
2.1058 show management api http-commands https cipher . . . 1052
2.1058.1 CipherSuite . . . 1054
2.1059 show management api http-commands https diffie-hellman . . . 1055
2.1060 show management api models . . . 1056
2.1060.1 AclOptions . . . 1056
2.1060.2 IpfixOptions . . . 1056
2.1060.3 IsisOptions . . . 1057
2.1060.4 SflowOptions . . . 1057
2.1060.5 SysdbExcludesStatus . . . 1057
2.1061 show management api netconf . . . 1057
2.1062 show management api restconf . . . 1057
2.1063 show management api restconf access-list [...] . . . 1057
2.1064 show management archive . . . 1058
2.1065 show management cvx . . . 1059
2.1065.1 MgmtCvxClusterStatus . . . 1059
2.1066 show management cvx debug pingpong . . . 1060
2.1067 show management cvx mounts . . . 1060
2.1068 show management cvx service . . . 1060
2.1068.1 MgmtCvxService . . . 1060
2.1069 show management cvx service NAME . . . 1060
2.1070 show management data sources . . . 1060
2.1070.1 SensorClient.SensorStatusModel . . . 1060
2.1071 show management data sources sensors . . . 1061
2.1071.1 SensorClient.ConnectionStatusModel . . . 1061
2.1072 show management dmf controller zerotouch . . . 1061
2.1073 show management dmf controller zerotouch detail . . . 1062
2.1073.1 LogMsg . . . 1062
2.1074 show management dmf dynamic configuration . . . 1062
2.1075 show management dmf version . . . 1062
2.1076 show management http-server . . . 1063
2.1076.1 HttpServiceVrf . . . 1063
2.1077 show management http-server ((ip access-list) | (ipv6 access-list)) [...] . . . 1063
2.1078 show management http-server counters . . . 1063
2.1078.1 VrfStats . . . 1063
2.1079 show management ldap . . . 1065
2.1079.1 LdapStatsModel . . . 1065
2.1079.2 LdapStatusModel . . . 1065
2.1079.3 ServerGroupModel . . . 1065
2.1080 show management package [...] . . . 1066
2.1081 show management package repository [...] . . . 1066
2.1081.1 RepositoryEntry . . . 1066
2.1082 show management security . . . 1066
2.1083 show management security auto-certificate profile [...] . . . 1067
2.1083.1 AutoCertMgmt.Cli.CertProfile . . . 1067
2.1084 show management security auto-certificate protocol est [...] . . . 1067
2.1084.1 AutoCertMgmt.Cli.EstProfile . . . 1067
2.1085 show management security certificate [...] . . . 1069
2.1085.1 Certificate . . . 1069

2.1086 show management security session shared-secret profile NAME [...] . . . 1071
2.1086.1 SecretModel . . . 1071
2.1087 show management security session shared-secret profile [...] . . . 1072
2.1088 show management security ssl crl [...] . . . 1072
2.1088.1 Crl . . . 1072
2.1089 show management security ssl diffie-hellman [...] . . . 1072
2.1089.1 DiffieHellmanParameters . . . 1072
2.1090 show management security ssl key [...] . . . 1073
2.1091 show management security ssl profile [...] . . . 1074
2.1091.1 ProfileStatus . . . 1074
2.1092 show management security ssl profile cipher [...] . . . 1075
2.1092.1 ProfileCipher . . . 1075
2.1093 show management security ssl profile key-establishment-group [...] . . . 1075
2.1093.1 ProfileKexGroup . . . 1075
2.1094 show management security ssl profile signature algorithms [...] . . . 1076
2.1094.1 ProfileSignatureAlgorithm . . . 1076
2.1095 show management security tpm measured-boot version . . . 1076
2.1095.1 MeasuredBootVersion . . . 1076
2.1096 show management security tpm pcr PCR_RANGE [...] . . . 1076
2.1096.1 PcrValueList . . . 1076
2.1097 show management security tpm pcr event revision . . . 1077
2.1098 show management security tpm pcr log [...] . . . 1077
2.1098.1 PcrLog . . . 1077
2.1099 show management ssh ((ip access-list) | (ipv6 access-list)) [...] . . . 1078
2.1100 show management ssh authorized-principals [...] . . . 1078
2.1100.1 SshUserConfig . . . 1078
2.1101 show management ssh key ((KEYALGO | hidden_alias) | FILENAME) public . . . 1078
2.1102 show management ssh key server cert [...] . . . 1078
2.1103 show management ssh trusted-ca key public [...] . . . 1079
2.1104 show management ssh user-keys authorized-keys [...] . . . 1079
2.1105 show management ssh user-keys revoke-list [...] . . . 1079
2.1106 show management telnet ((ip access-list) | (ipv6 access-list)) [...] . . . 1079
2.1107 show management telnet [...] . . . 1079
2.1108 show match-list prefix-ipv4 [...] . . . 1079
2.1108.1 MatchList . . . 1079
2.1109 show match-list prefix-ipv6 [...] . . . 1079
2.1110 show mdns counters . . . 1080
2.1111 show mdns links . . . 1080
2.1111.1 MdnsLinkList . . . 1080
2.1112 show mdns service name NAME [...] . . . 1081
2.1112.1 MdnsServiceInfo . . . 1081
2.1113 show mdns service record name NAME . . . 1082
2.1113.1 MdnsRecordEntryList . . . 1082
2.1114 show mdns service rule NAME [...] . . . 1082
2.1114.1 MdnsServiceList . . . 1083
2.1115 show mdns service type [...] . . . 1083
2.1115.1 MdnsServiceTypeList . . . 1083
2.1116 show mdns status . . . 1083
2.1116.1 MdnsServerGatewayStatus . . . 1084
2.1117 show metamux counters . . . 1084
2.1117.1 FpgaMetaMuxBaseInterfaceCounters . . . 1084
2.1117.2 FpgaMetaMuxInInterfaceCounters . . . 1084
2.1117.3 FpgaMetaMuxOutInterfaceCounters . . . 1084
2.1118 show metamux counters queue . . . 1084
2.1119 show metamux interfaces [...] . . . 1084

2.1119.1 FpgaMetaMuxInterfacesBaseStatus . . . 1085
2.1119.2 FpgaMetaMuxInInterfacesStatus . . . 1085
2.1119.3 FpgaMetaMuxOutInterfacesStatus . . . 1085
2.1120 show metamux mux status [...] . . . 1085
2.1120.1 MetaMux.Cli.MetaMuxMuxInstanceStatus . . . 1085
2.1121 show metamux status [...] . . . 1085
2.1121.1 FpgaMetaMuxStatus . . . 1085
2.1122 show metamux storm-control [...] . . . 1086
2.1123 show metawatch counters [...] . . . 1086
2.1124 show metawatch counters deduplication [...] . . . 1086
2.1125 show metawatch device-id [...] . . . 1086
2.1126 show metawatch ptp . . . 1086
2.1127 show metawatch status [...] . . . 1086
2.1128 show mlag [...] . . . 1087
2.1128.1 Detail . . . 1088
2.1129 show mlag config-sanity [...] . . . 1089
2.1129.1 GlobalFeatureParam . . . 1090
2.1129.2 IntfFeatureParam . . . 1090
2.1130 show mlag interfaces [...] . . . 1091
2.1130.1 MlagInterface . . . 1091
2.1131 show mlag interfaces ignored [...] . . . 1092
2.1132 show mlag interfaces interlock filter egress [...] . . . 1092
2.1133 show mlag interfaces members [...] . . . 1092
2.1134 show mlag issu compatibility URL . . . 1092
2.1135 show mlag issu warnings . . . 1092
2.1136 show mlag subinterfaces [...] . . . 1092
2.1136.1 MlagToSubIntf . . . 1092
2.1137 show mld membership [...] . . . 1093
2.1137.1 MldMembershipInterface . . . 1093
2.1138 show mld querier [...] . . . 1094
2.1138.1 MldQuerierInterface . . . 1094
2.1139 show mld snooping [...] . . . 1094
2.1139.1 MldSnoopingVlanInfo . . . 1094
2.1140 show mld snooping counters [...] . . . 1096
2.1140.1 MldSnoopingCountersInterface . . . 1096
2.1141 show mld snooping groups [...] . . . 1096
2.1142 show mld snooping groups count [...] . . . 1096
2.1143 show mld snooping groups detail [...] . . . 1096
2.1144 show mld snooping mrouter [...] . . . 1097
2.1145 show mld snooping querier [...] . . . 1097
2.1145.1 MldSnoopingVlanQuerier . . . 1097
2.1146 show mld snooping querier counters [...] . . . 1097
2.1146.1 MldSnoopingPacketCounters . . . 1097
2.1147 show mld snooping querier detail [...] . . . 1098
2.1148 show mld snooping querier membership [...] . . . 1098
2.1148.1 VlanMembership . . . 1098
2.1149 show mld static-group access-list ACL_NAME [...] . . . 1098
2.1149.1 RuleInfo . . . 1099
2.1150 show mld statistics [...] . . . 1100
2.1150.1 MldStatisticsInterface . . . 1100
2.1151 show mld summary [...] . . . 1100
2.1151.1 MldSummaryInterface . . . 1101
2.1152 show module [...] . . . 1101
2.1152.1 Module . . . 1101
2.1153 show module power [...] . . . 1103

2.1153.1 Module . . . 1103
2.1154 show module power budget . . . 1104
2.1155 show monitor connectivity [...] . . . 1105
2.1155.1 ConnMonitorVrf . . . 1105
2.1156 show monitor dataplane integrity profiles . . . 1106
2.1156.1 IpicProfileModel . . . 1106
2.1157 show monitor dataplane integrity test . . . 1108
2.1158 show monitor device-health . . . 1108
2.1158.1 HealthCategoryModel . . . 1108
2.1159 show monitor ethernet reflectors [...] . . . 1109
2.1159.1 ReflectorInterfaceModel . . . 1109
2.1160 show monitor fail-to-wire status [...] . . . 1109
2.1160.1 FailToWireAgentMonitoredModel . . . 1109
2.1161 show monitor latency measurement end-to-end status . . . 1109
2.1161.1 LatencyFeatureStatus . . . 1109
2.1162 show monitor link qualification generators [...] . . . 1111
2.1162.1 LinkQualificationGeneratorIntfModel . . . 1111
2.1163 show monitor link qualification generators profiles [...] . . . 1111
2.1163.1 LinkQualificationProfileModel . . . 1112
2.1164 show monitor rfc2544 generators profiles [...] . . . 1112
2.1164.1 Rfc2544ProfileModel . . . 1112
2.1165 show monitor rfc2544 generators test-report [...] . . . 1113
2.1165.1 IntfTestReportModel . . . 1113
2.1166 show monitor security awake [...] . . . 1118
2.1166.1 MsaNucleus . . . 1118
2.1166.2 MsaStatus . . . 1118
2.1167 show monitor security awake counters [...] . . . 1120
2.1167.1 FlowCounters . . . 1120
2.1167.2 IpfixCounters . . . 1120
2.1167.3 NucleusCounters . . . 1121
2.1168 show monitor security awake dpi memory . . . 1122
2.1168.1 MsaDpiMemoryDetails . . . 1122
2.1169 show monitor security awake dpi memory allocations [...] . . . 1122
2.1169.1 MsaDpiCtxMemoryAllocations . . . 1122
2.1170 show monitor security awake dpi memory pools . . . 1122
2.1170.1 MsaDpiMemoryPoolDetails . . . 1123
2.1171 show monitor security awake flow-table [...] . . . 1124
2.1171.1 FlowGroup . . . 1124
2.1172 show monitor server PROTOCOL [...] . . . 1126
2.1172.1 ServerProbeStats . . . 1126
2.1173 show monitor server-failure . . . 1126
2.1174 show monitor server-failure history . . . 1126
2.1174.1 Server . . . 1127
2.1175 show monitor server-failure servers IP_ADDR . . . 1127
2.1176 show monitor server-failure servers [...] . . . 1127
2.1177 show monitor session [...] . . . 1128
2.1177.1 MirrorSession . . . 1128
2.1178 show monitor system . . . 1132
2.1179 show monitor telemetry inband . . . 1133
2.1179.1 InbandTelemetryProfiles . . . 1133
2.1179.2 SamplePolicyModel . . . 1134
2.1180 show monitor telemetry inband profile [...] . . . 1146
2.1181 show monitor telemetry inband profile summary [...] . . . 1146
2.1181.1 IntfList . . . 1146
2.1182 show monitor telemetry influx . . . 1146

2.1182.1 InfluxTelemetry.Cli.DestinationInfluxdb . . . 1146
2.1182.2 InfluxTelemetry.Cli.SourceSocket . . . 1147
2.1183 show monitor telemetry path characteristics [...] . . . 1148
2.1183.1 ItsPeer . . . 1148
2.1184 show monitor telemetry path counters [...] . . . 1149
2.1185 show monitor telemetry postcard counters . . . 1149
2.1186 show monitor telemetry postcard policy . . . 1149
2.1186.1 Collection . . . 1150
2.1186.2 SampleTcpUdpChecksum . . . 1150
2.1187 show monitor telemetry postcard policy profile [...] . . . 1150
2.1187.1 ProfileModel . . . 1150
2.1188 show monitor telemetry postcard sample policy [...] . . . 1150
2.1188.1 SamplePolicyModel . . . 1150
2.1189 show monitor twamp-light ((ip IP) | (interface INTF)) raw [...] . . . 1151
2.1189.1 TwampLightDelaysModel . . . 1151
2.1190 show monitor twamp-light [...] . . . 1151
2.1190.1 Result . . . 1151
2.1191 show monitor twamp-light counters [...] . . . 1151
2.1191.1 TwampLightCountersPerInterface . . . 1151
2.1192 show monitor twamp-light detail [...] . . . 1153
2.1192.1 ResultDetailed . . . 1153
2.1193 show mpls bgp labeled-unicast bindings [...] . . . 1153
2.1194 show mpls bgp link-state bindings [...] . . . 1153
2.1195 show mpls config route [...] . . . 1154
2.1195.1 MplsRoute . . . 1154
2.1196 show mpls hardware ale adj [...] . . . 1160
2.1196.1 MplsFecRequestTableEntry . . . 1160
2.1197 show mpls hardware ale routes acknowledgement [...] . . . 1160
2.1197.1 MplsRouteAckTableEntry . . . 1160
2.1198 show mpls interface [...] . . . 1160
2.1198.1 MplsInterfaceInfo . . . 1161
2.1198.2 MplsInterfaceIngressCounters . . . 1161
2.1199 show mpls interface counters [...] . . . 1161
2.1200 show mpls label ranges . . . 1161
2.1200.1 MplsLabelRange . . . 1161
2.1201 show mpls ldp [...] . . . 1162
2.1201.1 MplsLdpStatus . . . 1162
2.1202 show mpls ldp access-list [...] . . . 1164
2.1203 show mpls ldp bindings [...] . . . 1164
2.1204 show mpls ldp bindings mldp [...] . . . 1164
2.1205 show mpls ldp discovery [...] . . . 1164
2.1205.1 MplsLdpDiscovery . . . 1164
2.1206 show mpls ldp neighbor [...] . . . 1166
2.1206.1 MplsLdpNeighborList . . . 1166
2.1207 show mpls ldp tunnel [...] . . . 1173
2.1207.1 LdpTunnelTableEntry . . . 1173
2.1208 show mpls ldp tunnel mldp [...] . . . 1173
2.1208.1 MldpTunnelTableEntry . . . 1173
2.1209 show mpls lfib counters [...] . . . 1173
2.1209.1 MplsLfibCounterLabelEntry . . . 1174
2.1210 show mpls lfib counters no-resource . . . 1174
2.1211 show mpls lfib counters summary . . . 1174
2.1212 show mpls lfib input bgp labeled-unicast . . . 1175
2.1213 show mpls lfib route [...] . . . 1175
2.1214 show mpls lfib stitching preferences [...] . . . 1175

2.1214.1 MplsDestinationProtocolStitchingPreferences . . . 1175
2.1215 show mpls parsing speculative . . . 1175
2.1216 show mpls ping access-list [...] . . . 1175
2.1217 show mpls route [...] . . . 1176
2.1217.1 MplsHwRoute . . . 1176
2.1218 show mpls route summary . . . 1178
2.1219 show mpls rsvp . . . 1179
2.1219.1 GrHelper . . . 1180
2.1219.2 GrSpeaker . . . 1180
2.1219.3 HitlessRestart . . . 1180
2.1219.4 LspCount . . . 1180
2.1219.5 P2mpLspCount . . . 1180
2.1219.6 P2mpSubLspCount . . . 1180
2.1220 show mpls rsvp ((ip access-list) | (ipv6 access-list)) [...] . . . 1181
2.1221 show mpls rsvp bandwidth [...] . . . 1181
2.1221.1 RsvpBandwidthIntfModel . . . 1181
2.1222 show mpls rsvp bandwidth summary [...] . . . 1181
2.1222.1 RsvpBandwidthIntfSummaryModel . . . 1181
2.1223 show mpls rsvp counters [...] . . . 1181
2.1223.1 RsvpErrorCounter . . . 1181
2.1223.2 RsvpInterfaceCounter . . . 1182
2.1224 show mpls rsvp neighbor [...] . . . 1183
2.1224.1 RsvpNeighbor . . . 1183
2.1225 show mpls rsvp neighbor summary . . . 1184
2.1225.1 RsvpNeighborStatistics . . . 1184
2.1226 show mpls rsvp session [...] . . . 1185
2.1226.1 RsvpP2mpSession . . . 1185
2.1226.2 RsvpSession . . . 1187
2.1227 show mpls segment-routing bindings [...] . . . 1189
2.1228 show mpls tunnel counters [...] . . . 1189
2.1228.1 MplsTunnelCountersEntry . . . 1189
2.1229 show mpls tunnel fib . . . 1190
2.1229.1 MplsTunnelFibEntry . . . 1190
2.1230 show mpls tunnel static [...] . . . 1191
2.1230.1 StaticTunnelTableEntry . . . 1191
2.1231 show mpls tunnel termination qos maps [...] . . . 1191
2.1232 show msdp mesh-group [...] . . . 1192
2.1232.1 Group . . . 1192
2.1233 show msdp rpf-peer RP [...] . . . 1192
2.1234 show msrp [...] . . . 1193
2.1234.1 Intf . . . 1193
2.1234.2 SrClassGlobal . . . 1193
2.1235 show msrp counters [...] . . . 1194
2.1235.1 Intf . . . 1194
2.1236 show msrp interfaces (streams | listeners | talkers) [...] . . . 1194
2.1236.1 Intf . . . 1194
2.1237 show msrp mrp [...] . . . 1195
2.1237.1 IntfDatabase . . . 1195
2.1238 show msrp streams [...] . . . 1196
2.1238.1 Stream . . . 1196
2.1239 show msrp streams count . . . 1197
2.1240 show msrp streams propagation [...] . . . 1198
2.1240.1 Stream . . . 1198
2.1241 show multicast (ipv4 | ipv6) evpn decap joined [...] . . . 1199
2.1241.1 MrouteVxlanDecapInterface . . . 1199

2.1242 show multicast (ipv4 | ipv6) source route export [...] . . . 1199
2.1243 show multicast AF evpn decap received . . . 1199
2.1243.1 MulticastTunnelVlan . . . 1199
2.1243.2 UnderlayReplicationModel . . . 1200
2.1244 show multicast AF evpn decap received flood . . . 1200
2.1244.1 MulticastFloodVlan . . . 1200
2.1245 show multicast AF evpn encap . . . 1200
2.1246 show multicast AF evpn encap flood . . . 1200
2.1247 show multicast fib ipv4 PIM_MODE [...] . . . 1201
2.1247.1 MfibGroup . . . 1201
2.1248 show multicast fib ipv4 [...] . . . 1202
2.1249 show multicast fib ipv4 df [...] . . . 1202
2.1250 show multicast fib ipv4 rpa [...] . . . 1202
2.1251 show multicast fib ipv6 PIM_MODE [...] . . . 1202
2.1252 show multicast fib ipv6 [...] . . . 1202
2.1253 show multicast ipv4 boundary [...] . . . 1202
2.1254 show multicast ipv4 evpn config-sanity [...] . . . 1202
2.1254.1 EvpnVlanVniCheck . . . 1203
2.1254.2 VrfCheck . . . 1203
2.1255 show multicast ipv4 evpn encap mapping (vrf VRF) OVERLAY_GRP . . . 1203
2.1256 show multicast ipv4 evpn mpls vrf . . . 1203
2.1256.1 MvpnVrfPmsis . . . 1203
2.1257 show multicast ipv6 boundary [...] . . . 1203
2.1258 show multicast oifset hardware [...] . . . 1204
2.1258.1 McastCommon.CliModel.OifsetInfo . . . 1204
2.1259 show multicast tunnel counters (rsvp | static) . . . 1204
2.1259.1 McastMplsTunnelCounterEntry . . . 1205
2.1260 show mvpn ipv4 decapsulation [...] . . . 1205
2.1260.1 PmsiTunnelDecapModel . . . 1205
2.1261 show mvpn ipv4 encapsulation [...] . . . 1206
2.1261.1 EncapVrfModel . . . 1206
2.1262 show mvpn ipv4 vrf . . . 1207
2.1263 show mvrp [...] . . . 1207
2.1263.1 Intf . . . 1207
2.1264 show mvrp mrp [...] . . . 1207
2.1264.1 IntfDatabase . . . 1207
2.1265 show mvrp vlans [...] . . . 1208
2.1265.1 Vlan . . . 1208
2.1266 show nat map-t domain [...] . . . 1208
2.1266.1 Domain . . . 1208
2.1267 show nat map-t domain counters [...] . . . 1209
2.1267.1 DomainCountersSummary . . . 1209
2.1268 show nat map-t domain counters drop [...] . . . 1209
2.1268.1 DomainDropCounters . . . 1210
2.1269 show nat map-t domain counters exception [...] . . . 1210
2.1269.1 DomainExceptionCounters . . . 1210
2.1270 show nat map-t domain counters offload [...] . . . 1210
2.1270.1 DomainOffloadCounters . . . 1211
2.1271 show nat map-t domain counters rule [...] . . . 1211
2.1271.1 DomainRuleCounters . . . 1211
2.1272 show nat map-t summary . . . 1211
2.1272.1 DomainSummary . . . 1211
2.1273 show neighbor classification [...] . . . 1212
2.1273.1 NbrClassificationModel . . . 1212
2.1274 show neighbor classification summary [...] . . . 1212

2.1274.1 NbrClassificationSummaryModel . . . 1212
2.1275 show network physical-topology hosts [...] . . . 1212
2.1275.1 Host . . . 1212
2.1276 show network physical-topology neighbors [...] . . . 1213
2.1276.1 DirectedEdge . . . 1213
2.1277 show nexthop-group [...] . . . 1214
2.1277.1 NexthopGroup . . . 1214
2.1278 show nexthop-group id [...] . . . 1216
2.1279 show nexthop-group id mapping . . . 1216
2.1280 show nexthop-group summary . . . 1216
2.1281 show nexthop-group tunnel [...] . . . 1216
2.1281.1 NexthopGroupTunnelTableEntry . . . 1216
2.1282 show ntp ((ip access-list) | (ipv6 access-list)) [...] . . . 1217
2.1283 show ntp associations . . . 1217
2.1283.1 NtpPeer . . . 1217
2.1284 show ntp status . . . 1218
2.1284.1 NtpComponentInfo . . . 1218
2.1284.2 NtsKeClientInfo . . . 1218
2.1284.3 NtsKeServerInfo . . . 1218
2.1285 show openflow . . . 1219
2.1285.1 BindModeEntries . . . 1219
2.1285.2 ConnectedController . . . 1219
2.1285.3 ControllerConfig . . . 1220
2.1285.4 RvlanEntries . . . 1220
2.1286 show openflow flows [...] . . . 1220
2.1287 show openflow groups [...] . . . 1220
2.1287.1 Group . . . 1220
2.1288 show openflow ports . . . 1221
2.1288.1 Entry . . . 1221
2.1289 show openflow profiles . . . 1222
2.1289.1 OpenFlowTableProfile . . . 1222
2.1290 show openflow queues . . . 1223
2.1290.1 OpenFlowQStats . . . 1223
2.1290.2 PortQ . . . 1223
2.1291 show openflow statistics . . . 1223
2.1291.1 Stats . . . 1223
2.1292 show openstack (ip | ipv6) access-list [...] . . . 1224
2.1293 show openstack agent uuid . . . 1224
2.1294 show openstack config all-regions . . . 1225
2.1294.1 RegionConfig . . . 1225
2.1295 show openstack config networks vni mapping . . . 1226
2.1295.1 VlanToVniMap . . . 1227
2.1296 show openstack config region REGION_NAME . . . 1227
2.1297 show openstack config region REGION_NAME timestamp . . . 1227
2.1298 show openstack features . . . 1227
2.1299 show openstack grace-period . . . 1227
2.1300 show openstack instances [...] . . . 1228
2.1300.1 Region . . . 1228
2.1301 show openstack networks [...] . . . 1230
2.1302 show openstack physical-network [...] . . . 1231
2.1302.1 Switch . . . 1231
2.1303 show openstack regions [...] . . . 1231
2.1304 show openstack resource-pool vlan region REGION_NAME uuid . . . 1231
2.1305 show openstack resource-pools [...] . . . 1232
2.1305.1 PhysicalNetworkVlanPool . . . 1232

2.1306 show openstack segments { (host HOSTNAME) | (network NETWORK_NAME_OR_ID) | (port PORT_NAME_OR_ID) | (instance INSTANCE_NAME_OR_ID) | (region REGION_NAME) | (switch SWITCH) | (tenant TENANT_NAME_OR_ID) } . . . 1232
2.1306.1 RegionInstanceBinding . . . 1232
2.1307 show openstack sync-timeout . . . 1233
2.1308 show openstack tenants [...] . . . 1233
2.1309 show openstack vlans . . . 1233
2.1310 show openstack vms [...] . . . 1233
2.1311 show ospfv3 [...] . . . 1234
2.1311.1 AddressFamilyOspf3MultiAfShowInstModel . . . 1234
2.1312 show ospfv3 access-list [...] . . . 1235
2.1313 show ospfv3 border-routers [...] . . . 1236
2.1313.1 AddressFamilyOspf3MultiAfBorderRoutersInstance . . . 1236
2.1314 show ospfv3 counters [...] . . . 1237
2.1314.1 AddressFamilyOspf3CountersInstance . . . 1237
2.1315 show ospfv3 counters interface [...] . . . 1237
2.1315.1 AddressFamilyOspf3CountersInterface . . . 1237
2.1316 show ospfv3 counters neighbor [...] . . . 1239
2.1316.1 AddressFamilyOspf3MultiAfCountersNeighor . . . 1239
2.1317 show ospfv3 database [...] . . . 1240
2.1317.1 AddressFamilyOspf3MultiAfDatabaseInstance . . . 1240
2.1318 show ospfv3 database database-summary [...] . . . 1241
2.1318.1 AddressFamilyOspf3MultiAfDatabaseSummary . . . 1241
2.1319 show ospfv3 interface [...] . . . 1241
2.1319.1 AddressFamilyOspf3MultiAfInterface . . . 1242
2.1320 show ospfv3 ipv6 sham-link [...] . . . 1242
2.1321 show ospfv3 ipv6 sham-link route [...] . . . 1242
2.1322 show ospfv3 lsa-log [...] . . . 1242
2.1322.1 AddressFamilyOspf3MultiAfLsaLogInst . . . 1242
2.1323 show ospfv3 neighbor [...] . . . 1243
2.1323.1 AddressFamilyOspf3MultiAfNeighborsInstance . . . 1243
2.1324 show ospfv3 request-list [...] . . . 1243
2.1324.1 AddressFamilyOspf3MultiAfLsaRequestList . . . 1243
2.1325 show ospfv3 retransmission-list [...] . . . 1243
2.1325.1 AddressFamilyOspf3MultiAfLsaRetransmissionList . . . 1243
2.1326 show ospfv3 spf-log [...] . . . 1244
2.1326.1 AddressFamilyOspf3MultiAfSpfLogInst . . . 1244
2.1327 show p4-runtime . . . 1245
2.1327.1 P4RtDeviceStatusEntry . . . 1245
2.1327.2 P4RtTransport . . . 1245
2.1328 show p4-runtime device . . . 1245
2.1328.1 P4RtDeviceStatusEntryDetail . . . 1245
2.1329 show p4-runtime device counters packet-io . . . 1246
2.1329.1 P4RtDeviceCounterEntry . . . 1246
2.1330 show patch panel [...] . . . 1247
2.1330.1 Patch . . . 1247
2.1331 show patch panel forwarding . . . 1253
2.1331.1 LabelForwardingInfoTable . . . 1253
2.1331.2 PortForwardingInfoTable . . . 1255
2.1331.3 TaggedForwardingInfoTable . . . 1256
2.1332 show patch panel summary . . . 1257
2.1333 show path-selection application counters [...] . . . 1257
2.1333.1 Dps.Cli.DpsLbCountersProfiles . . . 1257
2.1334 show path-selection load-balance counters [...] . . . 1258
2.1335 show path-selection mtu [...] . . . 1259

2.1335.1 DpsPeer . . . 1259
2.1336 show path-selection paths [...] . . . 1260
2.1337 show path-selection paths export . . . 1261
2.1337.1 Dps.Cli.DpsExport . . . 1261
2.1338 show pci . . . 1261
2.1338.1 PciErrorSum . . . 1261
2.1339 show pci detail . . . 1262
2.1339.1 PciDetailError . . . 1262
2.1340 show pci errors rates . . . 1262
2.1340.1 PciErrorsStats . . . 1262
2.1341 show pci errors rates detail . . . 1263
2.1341.1 PciErrorsStatsDetail . . . 1263
2.1342 show pci tree . . . 1263
2.1343 show peer-filter [...] . . . 1263
2.1343.1 PeerFilter . . . 1263
2.1344 show phy transmitter equalization profile [...] . . . 1264
2.1344.1 PhyTxEqPort . . . 1264
2.1345 show pim (ipv4 | ipv6) anycast-rp [...] . . . 1264
2.1346 show pim (ipv4 | ipv6) bsr [...] . . . 1264
2.1347 show pim (ipv4 | ipv6) bsr counters [...] . . . 1264
2.1348 show pim (ipv4 | ipv6) bsr debug . . . 1265
2.1349 show pim (ipv4 | ipv6) bsr rp [...] . . . 1265
2.1350 show pim (ipv4 | ipv6) bsr rp-hash GROUP [...] . . . 1265
2.1351 show pim (ipv4 | ipv6) config-sanity anycast-rp [...] . . . 1265
2.1351.1 GenRouteCheck . . . 1265
2.1352 show pim (ipv4 | ipv6) interface [...] . . . 1265
2.1353 show pim (ipv4 | ipv6) neighbor [...] . . . 1265
2.1354 show pim (ipv4 | ipv6) neighbor bfd [...] . . . 1266
2.1355 show pim (ipv4 | ipv6) register-source [...] . . . 1266
2.1356 show pim (ipv4 | ipv6) rp [...] . . . 1266
2.1357 show pim (ipv4 | ipv6) rp-candidate [...] . . . 1266
2.1358 show pim evpn gateway dr [...] . . . 1266
2.1358.1 EvpnGatewayDr . . . 1266
2.1359 show pim ipv4 sparse-mode non-dr drop-rules [...] . . . 1267
2.1359.1 NonDrDropRuleInterface . . . 1267
2.1360 show pim ipv6 sparse-mode join [...] . . . 1267
2.1361 show pim ipv6 sparse-mode route IP1 IP2 interface [...] . . . 1267
2.1362 show pim ipv6 sparse-mode route [...] . . . 1267
2.1363 show pim ipv6 sparse-mode route count [...] . . . 1267
2.1364 show pim ipv6 sparse-mode rp [...] . . . 1268
2.1365 show pim ipv6 sparse-mode rp hash GROUP [...] . . . 1268
2.1366 show pim protocol counters [...] . . . 1268
2.1367 show pim sparse-mode evpn cli membership [...] . . . 1268
2.1367.1 VlanMembership . . . 1268
2.1368 show pim sparse-mode evpn gateway [...] . . . 1268
2.1368.1 EvpnGatewayVrf . . . 1268
2.1369 show pim sparse-mode evpn pim membership [...] . . . 1269
2.1370 show pim sparse-mode pim evpn membership [...] . . . 1269
2.1371 show platform (fap | arad) eci hardware-sync [...] . . . 1269
2.1371.1 AradEciTimeSyncInfo . . . 1269
2.1372 show platform (fap | arad) zuma [...] . . . 1269
2.1372.1 ZumaMapping . . . 1269
2.1373 show platform (fap | arad) zuma detail [...] . . . 1269
2.1373.1 ZumaDetails . . . 1270
2.1374 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) [...] . . . 1270

2.1374.1 FapInfo . . . 1270
2.1375 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) cint [...] . . . 1270
2.1375.1 CintFap . . . 1270
2.1376 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) copp mapping [...] . . . 1271
2.1376.1 AradGenericCoppClassStats . . . 1271
2.1376.2 AradPolicerCoppClassStats . . . 1271
2.1377 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) eedb outac [...] . . . 1272
2.1377.1 EedbOutAcPoolMap . . . 1272
2.1378 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) evpn mpls decap [...] . . . 1273
2.1378.1 L2EvpnMplsDecapMapping . . . 1273
2.1378.2 L3EvpnMplsDecapMapping . . . 1273
2.1379 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) evpn mpls encap [...] . . . 1274
2.1379.1 VlanEvpnMplsEncapMap . . . 1274
2.1380 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) fabric load distribution [...] 1275
2.1380.1 WfdConfigNumSerdes . . . 1275
2.1381 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) fabric load distribution destination (fap | arad | jericho | jericho2 | jericho3 | jericho4) [...] . . . 1275
2.1381.1 FapWfdSerdesWeights . . . 1275
2.1382 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) flow tracking sampled flow-table hw [...] . . . 1276
2.1382.1 FlowTableFapLevelInfo . . . 1276
2.1383 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) ip route prefix compression tcam [...] . . . 1276
2.1383.1 PrefixCompressionTcamEntries . . . 1276
2.1384 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) label sharing inlif shadow [...] 1277
2.1384.1 LabelSharingInLifEntriesForFap . . . 1277
2.1385 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) label sharing isem (shadow | hardware | diff) [...] . . . 1281
2.1385.1 LabelSharingIsemForFap . . . 1281
2.1386 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) label sharing ppmc l2 shadow [...] . . . 1282
2.1386.1 PpmcLabelSharingEntries . . . 1282
2.1387 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) label sharing ppmc l3 shadow [...] . . . 1282
2.1388 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) lag [...] . . . 1282
2.1388.1 AradLags . . . 1283
2.1389 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) mac-address-table [...] . . . 1283
2.1389.1 FapMacAddressTable . . . 1283
2.1389.2 PollerFapInfo . . . 1284
2.1390 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) mac-address-table diff [...] . 1284
2.1390.1 FapMacAddressTableDiff . . . 1284
2.1391 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) mapping [...] . . . 1285
2.1391.1 PortMappings . . . 1285
2.1392 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) mroute [...] . . . 1286
2.1392.1 FapToIpv4MroutesMapping . . . 1286
2.1392.2 FapToIpv6MroutesMapping . . . 1287
2.1393 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) mroute ipv4 [...] . . . 1287
2.1394 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) mroute ipv6 [...] . . . 1287
2.1395 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) mvpn decap [...] . . . 1288
2.1395.1 MvpnDecapEntry . . . 1288
2.1396 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) phy PHY_FROM_PORT dump [...] . . . 1288
2.1396.1 PhysicalInfo . . . 1288
2.1397 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) phy PHY_FROM_PORT register mmd PHY_REG_START [...] . . . 1288

2.1397.1 PhysicalRegister . . . 1288
2.1398 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) pim bidirectional df [...] . . 1288
2.1398.1 DfEntryListModel . . . 1289
2.1399 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) pim bidirectional rpa [...] . 1289
2.1399.1 RpaEntryModel . . . 1289
2.1400 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) pmf [...] . . . 1290
2.1400.1 ProfileInstance . . . 1290
2.1401 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) pmf dbinfo [...] . . . 1312
2.1401.1 TcamDbInfoTable . . . 1312
2.1402 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) ppmc multicast [...] . . . 1313
2.1402.1 PpmcEntries . . . 1313
2.1403 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) priority-flow-control buffer profile [...] . . . 1314
2.1403.1 FapConfig . . . 1314
2.1403.2 GlobalConfig . . . 1314
2.1404 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) ptp hardware-sync [...] . . . 1315
2.1404.1 SlaveModel . . . 1315
2.1405 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) qos policy mapping [...] . . 1316
2.1405.1 FapQosPolicyMapping . . . 1316
2.1406 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) qos tcam mapping [...] . . . 1318
2.1406.1 FapQosAclTcamMappingModel . . . 1318
2.1407 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) qos tcam mapping bank BANK ENTRY [...] . . . 1320
2.1407.1 FapQosAclTcamEntryModel . . . 1320
2.1408 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) qos tcam mapping policy-map PMAP [...] . . . 1320
2.1409 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) sflow accel [...] . . . 1321
2.1409.1 PlatformSflowAccelResourceInfo . . . 1321
2.1410 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) sflow accel counters [...] . . 1321
2.1410.1 PlatformSflowAccelCountersInfo . . . 1321
2.1411 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) split-horizon group [...] . . 1322
2.1411.1 VlanSplitHorizonGroup . . . 1322
2.1412 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) subinterface mapping [...] . 1322
2.1412.1 SubInterfaceMap . . . 1322
2.1413 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) subinterface mapping l2 [...] 1323
2.1413.1 SubInterfaceL2Map . . . 1323
2.1414 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) subinterface mapping l3 [...] 1323
2.1414.1 SubInterfaceL3Map . . . 1323
2.1415 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) tcam action-priority [...] . . 1324
2.1415.1 TcamFapActionPriorityInfo . . . 1324
2.1416 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) tcam port qualifiers [...] . . 1325
2.1416.1 TcamFapPortQualifiersInfo . . . 1325
2.1417 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) tcam summary [...] 1326
2.1417.1 TcamFapInfo . . . 1326
2.1418 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) tpid [...] . . . 1326
2.1418.1 PlatformTpid . . . 1326
2.1419 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) voq credit rates [...] 1327
2.1419.1 FapStatus . . . 1327
2.1420 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) vpls pseudowire decap [...] 1327
2.1420.1 VplsPseudowireDetails . . . 1327
2.1421 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) vrf selection inlif [...] . . . 1328
2.1421.1 VrfSelectionInLifBank . . . 1328
2.1422 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) vrf selection tcam shadow [...] 1329
2.1422.1 VrfSelectionExtendedV6TcamEntries . . . 1329
2.1422.2 VrfSelectionV4TcamEntries . . . 1329

2.1422.3 VrfSelectionV6TcamEntries . . . 1329
2.1423 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) vxlan egress filter multihoming [...] . . . 1330
2.1423.1 EthernetSegmentToMultihomeInfo . . . 1330
2.1424 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) vxlan multicast route underlay [...] . . . 1330
2.1424.1 VxlanUnderlayMrouteBase . . . 1330
2.1424.2 VxlanUnderlayMrouteV4Entry . . . 1330
2.1424.3 VxlanUnderlayMrouteV6Entry . . . 1330
2.1425 show platform (fap | fe | arad | jericho | jericho2 | jericho3 | jericho4 | fe1600 | fe3600 | ramon | ramon3) fabric [...] . . . 1331
2.1425.1 FapFeSerdesInfo . . . 1331
2.1426 show platform (fap | fe | arad | jericho | jericho2 | jericho3 | jericho4 | fe1600 | fe3600 | ramon | ramon3) fabric detail [...] . . . 1332
2.1427 show platform (fap | fe | arad | jericho | jericho2 | jericho3 | jericho4 | fe1600 | fe3600 | ramon | ramon3) fabric interface mapping [...] . . . 1332
2.1427.1 FabricIntfToSerdesMapping . . . 1332
2.1428 show platform (fap | fe | arad | jericho | jericho2 | jericho3 | jericho4 | fe1600 | fe3600 | ramon | ramon3) fabric rates mbps [...] . . . 1333
2.1429 show platform (fap | jericho2) mac security [...] . . . 1334
2.1429.1 MacSecTableFap . . . 1334
2.1430 show platform (fap | jericho2) mac security counters default [...] . . . 1334
2.1430.1 DefaultEntCounterTableDirection . . . 1335
2.1431 show platform (fap | jericho2) policer fairness [...] . . . 1335
2.1431.1 MeterToFairnessLevelMapping . . . 1335
2.1432 show platform (fe | fe1600 | fe3600 | ramon | ramon3) [...] . . . 1335
2.1432.1 FeInfo . . . 1335
2.1433 show platform (fe | fe1600 | fe3600 | ramon | ramon3) dcs mapping [...] . . . 1336
2.1433.1 DcsBlock . . . 1336
2.1434 show platform aegisalgo stage [...] . . . 1337
2.1434.1 Batch . . . 1337
2.1435 show platform agent-state verify (AGENT | all) . . . 1338
2.1435.1 PerAgentVerifyResultDict . . . 1338
2.1436 show platform arad lag mode . . . 1338
2.1437 show platform bios . . . 1339
2.1437.1 BiosVersion . . . 1339
2.1437.2 BiosVersions . . . 1339
2.1438 show platform bios history [...] . . . 1340
2.1438.1 BiosHistory . . . 1340
2.1439 show platform cortina INTF diag counters . . . 1340
2.1439.1 CountersModel . . . 1340
2.1440 show platform etba counters [...] . . . 1341
2.1440.1 HandlerCounter . . . 1341
2.1441 show platform fap ecmp hash [...] . . . 1341
2.1441.1 HashInfoFap . . . 1341
2.1442 show platform fap interfaces INTFS profile latency . . . 1342
2.1442.1 Sand.Cli.Model.LatencyDetails . . . 1342
2.1443 show platform fap interfaces INTFS profile rate-class . . . 1342
2.1443.1 VoqDetailsDict . . . 1342
2.1444 show platform fap ip security counters [...] . . . 1343
2.1444.1 AleTunnelsec.Counters.TunnelsecIntfCounterCliTable . . . 1343
2.1445 show platform fap port-channel hash [...] . . . 1344
2.1446 show platform fap voq delete . . . 1345
2.1446.1 VoqDeleteEntry . . . 1345
2.1447 show platform ip igmp snooping groups [...] . . . 1345

2.1447.1 VlanStatus . . . 1345
2.1448 show platform module [...] . . . 1346
2.1448.1 PlatformModuleStatus . . . 1346
2.1449 show platform power controller . . . 1346
2.1449.1 PowerController . . . 1346
2.1450 show platform power isl [...] . . . 1347
2.1450.1 IslController . . . 1347
2.1451 show platform power isl current phase [...] . . . 1347
2.1452 show platform power isl current phase histogram [...] . . . 1348
2.1453 show platform ptp hardware-sync . . . 1348
2.1453.1 MasterModel . . . 1348
2.1454 show platform ptp hardware-sync master SCD_NAME . . . 1348
2.1455 show platform ptp hardware-sync slave SWITCH_NAME . . . 1348
2.1456 show platform sand capabilities . . . 1349
2.1457 show platform sand counters mac-address-table flush . . . 1350
2.1458 show platform sand fabric monitor capacity . . . 1351
2.1458.1 FapFabricCapacityInfo . . . 1351
2.1459 show platform sand health . . . 1352
2.1459.1 EventLogModel . . . 1352
2.1459.2 FabricInterruptDataModel . . . 1352
2.1459.3 FapDataModel . . . 1353
2.1459.4 PeerFapListModel . . . 1353
2.1459.5 PeerLinkId . . . 1353
2.1460 show platform sand lag id reserved . . . 1353
2.1460.1 SandLagIdReservationByPartition . . . 1353
2.1461 show platform sand lag interlock [...] . . . 1353
2.1461.1 SandLagInterlockPortChannel . . . 1353
2.1462 show platform sand lag mode . . . 1354
2.1463 show platform sand mcast replication ingress maximum . . . 1354
2.1464 show platform sand mdb profile [...] . . . 1354
2.1464.1 MdbFapProfile . . . 1354
2.1465 show platform sand pmf qualifier warnings . . . 1355
2.1465.1 FeatureWarningsModel . . . 1355
2.1466 show platform sand qos map cpu traffic-class to cos [...] . . . 1356
2.1467 show platform sand recirculation mapping . . . 1356
2.1467.1 RecirculationMappingInfo . . . 1356
2.1468 show platform sand scheduler copp COPP_PORT_NAME (fap | arad | jericho | jericho2 | jericho3 | jericho4) [...] . . . 1357
2.1468.1 PrintFlowUpModel . . . 1357
2.1469 show platform sand scheduler interface INTF . . . 1358
2.1470 show platform sand srv6 endpoint [...] . . . 1359
2.1471 show platform sand srv6 endpoint detail [...] . . . 1359
2.1472 show platform sand subinterface anchor [...] . . . 1359
2.1473 show platform sand subinterface capabilities . . . 1359
2.1474 show platform sand subinterface load-balancing [...] . . . 1359
2.1474.1 InterfaceLoadBalancingModel . . . 1359
2.1475 show platform sand tapagg [...] . . . 1360
2.1475.1 TapAggGroup . . . 1360
2.1475.2 TapAggNexthopGroup . . . 1360
2.1475.3 TapPort . . . 1361
2.1475.4 ToolPort . . . 1361
2.1476 show platform sand tapagg truncation-profile . . . 1361
2.1476.1 TruncationProfileFapModel . . . 1361
2.1477 show platform sand traffic-class to network-qos map . . . 1362
2.1478 show platform sand voq tail-drop . . . 1363

2.1478.1 IngressThresholds . . . 1363
2.1479 show platform sand voq tail-drop fadt . . . 1364
2.1480 show platform sand voq tail-drop fadt status . . . 1364
2.1481 show platform sand voq tail-drop subinterface . . . 1364
2.1482 show platform sand voq tail-drop subinterface fadt . . . 1364
2.1483 show platform scd satellite debug [...] . . . 1364
2.1483.1 SatelliteScd . . . 1364
2.1484 show platform schanaccel command batch tracking duration . . . 1365
2.1485 show platform sfe counters [...] . . . 1365
2.1485.1 Counter . . . 1365
2.1486 show platform sfe flow tracking counters . . . 1366
2.1487 show platform sfe high availability . . . 1367
2.1488 show platform sfe interface profile PROFILE_NAME detail . . . 1367
2.1488.1 InterfaceProfileIntfParams . . . 1367
2.1489 show platform sfe interface profile [...] . . . 1368
2.1489.1 InterfaceProfileEntry . . . 1368
2.1490 show platform sfe ip route [...] . . . 1368
2.1490.1 AsyncGate . . . 1368
2.1490.2 AsyncPrefix . . . 1368
2.1491 show platform sfe ip route diff . . . 1369
2.1491.1 FibFecInfo . . . 1369
2.1491.2 Gates . . . 1369
2.1491.3 ModuleTable . . . 1369
2.1491.4 PModStatusTable . . . 1370
2.1491.5 Fec . . . 1370
2.1492 show platform sfe ip route multicast . . . 1370
2.1492.1 McastGates . . . 1370
2.1493 show platform sfe ipv6 route [...] . . . 1370
2.1494 show platform sfe l3 next-hops [...] . . . 1371
2.1494.1 AsyncFecInfo . . . 1371
2.1495 show platform sfe l3 next-hops diff . . . 1371
2.1495.1 FecInfo . . . 1372
2.1496 show platform sfe l3 peer-group . . . 1372
2.1497 show platform sfe l3 software summary . . . 1372
2.1498 show platform sfe l3 unicast summary . . . 1373
2.1499 show platform sfe licensing . . . 1373
2.1500 show platform sfe memory counters . . . 1373
2.1500.1 BessdCounterBlock . . . 1374
2.1501 show platform sfe memory counters free . . . 1374
2.1501.1 BessdCounterInfo . . . 1374
2.1502 show platform sfe memory pool . . . 1374
2.1502.1 MempoolStatsModel . . . 1374
2.1503 show platform sfe mirroring . . . 1376
2.1503.1 MirrorSession . . . 1376
2.1504 show platform sfe mroute AF [...] . . . 1377
2.1504.1 MfibMrouteGroup . . . 1377
2.1505 show platform sfe multicast interface counter AF [...] . . . 1377
2.1505.1 McastIntfCounter . . . 1377
2.1506 show platform sfe nat counters . . . 1379
2.1507 show platform sfe nat module pool-mgr . . . 1382
2.1508 show platform sfe nat pool [...] . . . 1384
2.1508.1 PoolRange . . . 1384
2.1509 show platform sfe network-accelerator counters [...] . . . 1385
2.1509.1 InterfaceCounters . . . 1385
2.1510 show platform sfe network-accelerator flows . . . 1385

2.1510.1 NacIesSaFlowParams . . . 1385
2.1511 show platform sfe network-accelerator mac address-table . . . 1385
2.1511.1 NacIesMacTableParams . . . 1385
2.1512 show platform sfe network-accelerator status . . . 1386
2.1512.1 InterfaceState . . . 1386
2.1513 show platform sfe qos . . . 1386
2.1514 show platform sfe route-cache ip hitbit (vrf VRF) . . . 1387
2.1514.1 HitbitEntry . . . 1387
2.1515 show platform sfe route-cache ip hitbit summary . . . 1387
2.1516 show platform sfe route-cache summary . . . 1387
2.1517 show platform sfe status . . . 1388
2.1517.1 FlowCacheInsertionModel . . . 1388
2.1517.2 NicInfo . . . 1388
2.1518 show platform sfe worker summary [...] . . . 1389
2.1518.1 TopDpiFlowsModel . . . 1389
2.1518.2 TopIpsecFlowsModel . . . 1389
2.1518.3 WorkerInfoModel . . . 1389
2.1519 show platform smbus counters . . . 1390
2.1519.1 DeviceModel . . . 1390
2.1520 show platform smbus counters errors . . . 1390
2.1520.1 DeviceErrorModel . . . 1390
2.1521 show platform tfa counters flow . . . 1390
2.1521.1 ArfaRateCounterDirections . . . 1391
2.1522 show platform tfa counters kernel interfaces . . . 1391
2.1522.1 PamCollectionEntry . . . 1391
2.1523 show platform tfa interface mode . . . 1391
2.1524 show platform tfa kernel interfaces path . . . 1392
2.1524.1 EosLabKernelInterfaceSortingInfo . . . 1392
2.1525 show platform tfa lookups . . . 1392
2.1525.1 GenericLookups . . . 1392
2.1526 show platform tfa pbr nexthops . . . 1392
2.1526.1 ArfaPbrNexthopModel . . . 1392
2.1527 show platform tfa rates mac security . . . 1393
2.1527.1 MacsecSingleFlowRateModel . . . 1393
2.1528 show platform trident ((counters raw) | (counters raw (interface INTERFACE) | (all (interface INTERFACE)))) [...] . . . 1393
2.1528.1 PlatformCounterInterfaceRawModel . . . 1393
2.1529 show platform trident acl [...] . . . 1394
2.1529.1 StrataAclRequestModel . . . 1394
2.1530 show platform trident agent [...] . . . 1397
2.1530.1 TridentAgentModel . . . 1397
2.1531 show platform trident agent port [...] . . . 1398
2.1531.1 ChipPortsModel . . . 1398
2.1532 show platform trident agent role [...] . . . 1398
2.1532.1 RoleModel . . . 1398
2.1533 show platform trident ces connection [...] . . . 1398
2.1533.1 ConnectionsModel . . . 1398
2.1534 show platform trident ces queue-mapping . . . 1399
2.1534.1 PortQueueMapsModel . . . 1399
2.1535 show platform trident counters [...] . . . 1400
2.1535.1 PlatformCountTypeCountersModel . . . 1400
2.1536 show platform trident counters fast-polling [...] . . . 1414
2.1536.1 FastPollInfoDetail . . . 1414
2.1537 show platform trident counters fast-polling interface [...] . . . 1415
2.1538 show platform trident counters interface (FABRIC | ETH | UETH | INTERNALRECIRC) . . . 1415

2.1539 show platform trident counters polling [...] . . . 1415
2.1540 show platform trident counters sampling . . . 1415
2.1540.1 SampledCounterChipModel . . . 1415
2.1541 show platform trident cpu-queue mapping [...] . . . 1416
2.1541.1 CpuQueueMap . . . 1416
2.1542 show platform trident directflow [...] . . . 1417
2.1542.1 StrataSliceInfo . . . 1417
2.1543 show platform trident ecmp-lag (software | shadow) [...] . . . 1418
2.1543.1 EcmpLagStatus . . . 1418
2.1544 show platform trident egress event debug [...] . . . 1418
2.1544.1 EgrEventListModel . . . 1418
2.1545 show platform trident exact-match [...] . . . 1419
2.1545.1 StrataEmCliModelEntry . . . 1419
2.1546 show platform trident exact-match keygen-mask . . . 1420
2.1546.1 StrataEmAppInfo . . . 1420
2.1546.2 StrataEmKeyGenMaskEntry . . . 1420
2.1547 show platform trident exact-match summary . . . 1421
2.1547.1 StrataEmCliSummaryModelEntry . . . 1421
2.1547.2 StrataEmHitbitIntervalSummary . . . 1421
2.1548 show platform trident fabric counters fec [...] . . . 1421
2.1548.1 PlatformSliceFecCounterModel . . . 1421
2.1549 show platform trident fabric counters queue [...] . . . 1422
2.1549.1 StrataFabricQueueCounterDropModel . . . 1422
2.1550 show platform trident fabric counters queue detail [...] . . . 1422
2.1550.1 StrataFabricInterfaceCounterModel . . . 1422
2.1551 show platform trident fabric counters rate . . . 1423
2.1552 show platform trident fabric fib shadow [...] . . . 1423
2.1552.1 StrataFabricFibLinecardShadowModel . . . 1423
2.1553 show platform trident fabric fib software [...] . . . 1423
2.1553.1 StrataFabricFibMemberModel . . . 1423
2.1554 show platform trident fabric fib-mirror shadow [...] . . . 1424
2.1555 show platform trident fabric fib-mirror software [...] . . . 1424
2.1556 show platform trident fifo-dma . . . 1425
2.1556.1 FifoDriverStateModel . . . 1425
2.1557 show platform trident flexcounters l3intf in summary . . . 1426
2.1557.1 L3IntfInFlexCounterInfo . . . 1426
2.1558 show platform trident flexcounters l3intf in values . . . 1427
2.1558.1 FlexCounterValuesColl . . . 1427
2.1559 show platform trident flexcounters l3intf out summary . . . 1427
2.1560 show platform trident flexcounters l3intf out values . . . 1427
2.1561 show platform trident flexcounters multicast summary . . . 1427
2.1561.1 McastSources . . . 1427
2.1562 show platform trident flexcounters multicast values . . . 1428
2.1562.1 McastSources . . . 1428
2.1563 show platform trident flexcounters requests . . . 1430
2.1563.1 FlexRequest . . . 1430
2.1564 show platform trident flexcounters requests summary . . . 1431
2.1564.1 FlexRequestSummary . . . 1431
2.1565 show platform trident flexcounters summary . . . 1431
2.1565.1 PoolInfoList . . . 1431
2.1566 show platform trident flexcounters vni egress summary . . . 1432
2.1566.1 VniFlexCounterInfo . . . 1432
2.1567 show platform trident flexcounters vni egress values . . . 1432
2.1568 show platform trident flexcounters vni ingress summary . . . 1432
2.1569 show platform trident flexcounters vni ingress values . . . 1432

2.1570 show platform trident flexcounters vtep decap summary . . . 1432
2.1570.1 VtepDecapFlexCounterInfo . . . 1432
2.1571 show platform trident flexcounters vtep decap values . . . 1433
2.1572 show platform trident flexcounters vtep encap summary . . . 1433
2.1572.1 VtepFlexCounterInfo . . . 1433
2.1573 show platform trident flexcounters vtep encap values . . . 1433
2.1574 show platform trident flow tracker counters [...] . . . 1433
2.1574.1 StftOneLinecardCounter . . . 1433
2.1575 show platform trident flow tracker summary . . . 1434
2.1575.1 OneLinecardFlowTracker . . . 1434
2.1576 show platform trident forwarding-table partition . . . 1434
2.1577 show platform trident forwarding-table partition flexible . . . 1436
2.1578 show platform trident forwardingplane featureagents . . . 1437
2.1578.1 AgentModel . . . 1437
2.1579 show platform trident ingress event debug [...] . . . 1437
2.1579.1 IngEventListModel . . . 1437
2.1580 show platform trident interface map [...] . . . 1438
2.1580.1 ChipEntry . . . 1438
2.1581 show platform trident l2 hardware mac-address-table [...] . . . 1438
2.1581.1 MacAddressTable . . . 1438
2.1582 show platform trident l2 hardware mac-address-table diff [...] . . . 1439
2.1582.1 MacTableDiffEntry . . . 1439
2.1583 show platform trident l2 hardware mac-address-table missing [...] . . . 1439
2.1583.1 MacTableMissingEntry . . . 1439
2.1584 show platform trident l2 shadow egr-vlan-xlate [...] . . . 1441
2.1584.1 EgrVlanXlateHwTable . . . 1441
2.1585 show platform trident l2 shadow egr-vlan-xlate-2 [...] . . . 1443
2.1585.1 EgrVlanXlate2HwTable . . . 1443
2.1586 show platform trident l2 shadow vlan-xlate [...] . . . 1445
2.1586.1 VlanXlateHwTable . . . 1445
2.1587 show platform trident l2 shadow vlan-xlate-2 [...] . . . 1446
2.1587.1 VlanXlate2HwTable . . . 1446
2.1588 show platform trident l2 software ingress-vlan-range . . . 1446
2.1588.1 VlanRangeEntry . . . 1447
2.1589 show platform trident l2 software mac-address-table . . . 1447
2.1589.1 L2SwMacAddrTableEntry . . . 1447
2.1590 show platform trident l2 software mac-address-table count . . . 1448
2.1591 show platform trident l2 software mac-address-table remote count . . . 1448
2.1592 show platform trident l2 software multicast-group-table count . . . 1449
2.1593 show platform trident l2 status [...] . . . 1450
2.1593.1 L2StatusMacProgrammerStatus . . . 1450
2.1593.2 L2StatusMcastStatus . . . 1451
2.1594 show platform trident l3 cmdring . . . 1452
2.1594.1 CmdRing . . . 1452
2.1594.2 L3AgentStatus . . . 1456
2.1595 show platform trident l3 shadow (my-station | my-station-2) [...] . . . 1458
2.1595.1 L3MyStationEntry . . . 1458
2.1596 show platform trident l3 shadow counter [...] . . . 1458
2.1596.1 CounterTable . . . 1458
2.1597 show platform trident l3 shadow dlb-ecmp-group-control [...] . . . 1459
2.1597.1 L3ShwDlbEcmpGroupControlEntry . . . 1459
2.1598 show platform trident l3 shadow dlb-ecmp-group-membership [...] . . . 1459
2.1598.1 L3ShwDlbEcmpGroupMembershipEntry . . . 1459
2.1599 show platform trident l3 shadow dlb-ecmp-group-port-to-member [...] . . . 1459
2.1599.1 L3ShwDlbEcmpGroupPortToMemberEntry . . . 1459

2.1600 show platform trident l3 shadow ecmp-dlb-control [...] . . . 1460
2.1600.1 L3ShwEcmpDlbControlEntry . . . 1460
2.1601 show platform trident l3 shadow interfaces [...] . . . 1460
2.1601.1 L3ShwIntfEntry . . . 1460
2.1602 show platform trident l3 shadow l3-iif-profile [...] . . . 1460
2.1602.1 L3ShwIifProfileEntry . . . 1460
2.1603 show platform trident l3 shadow l3-tunnel [...] . . . 1461
2.1603.1 L3ShwL3TunnelEntry . . . 1461
2.1604 show platform trident l3 shadow mroutes [...] . . . 1461
2.1604.1 L3ShwMroutesEntry . . . 1461
2.1605 show platform trident l3 shadow mtu [...] . . . 1462
2.1605.1 L3ShwMtuEntry . . . 1462
2.1606 show platform trident l3 shadow next-hops her . . . 1462
2.1606.1 L3ShwNextHopsHerEntry . . . 1462
2.1607 show platform trident l3 shadow next-hops multipath [...] . . . 1462
2.1607.1 L3NextHopsEcmp . . . 1462
2.1608 show platform trident l3 shadow next-hops multipath ecmp [...] . . . 1462
2.1609 show platform trident l3 shadow next-hops multipath hfec [...] . . . 1463
2.1609.1 L3NextHopsEcmpHierarchicalList . . . 1463
2.1610 show platform trident l3 shadow next-hops simple [...] . . . 1463
2.1610.1 L3ShwNextHopsSimpleEntry . . . 1463
2.1611 show platform trident l3 shadow routes defip [...] . . . 1464
2.1611.1 L3ShwRoutesDefipEntry . . . 1464
2.1612 show platform trident l3 shadow routes host [...] . . . 1464
2.1612.1 L3ShwRoutesHostEntry . . . 1464
2.1613 show platform trident l3 shadow routes lpm [...] . . . 1466
2.1613.1 L3ShwRoutesLpmEntry . . . 1466
2.1614 show platform trident l3 shadow routes-v6 defip [...] . . . 1466
2.1615 show platform trident l3 shadow routes-v6 host [...] . . . 1466
2.1616 show platform trident l3 shadow routes-v6 lpm [...] . . . 1466
2.1617 show platform trident l3 shadow tunnel TYPE [...] . . . 1467
2.1617.1 L3ShwEgrIpTunnelEntry . . . 1467
2.1617.2 L3ShwEgrIpTunnelEntryVxlanIpv6 . . . 1467
2.1618 show platform trident l3 shadow unified-tcam . . . 1467
2.1618.1 UnifiedTcamEntry . . . 1467
2.1619 show platform trident l3 shadow unified-tcam map . . . 1467
2.1619.1 UnifiedTcamMapEntry . . . 1468
2.1620 show platform trident l3 software alpm-table [...] . . . 1469
2.1620.1 AlpmTableState . . . 1469
2.1620.2 L3AlpmRouteLpm . . . 1470
2.1620.3 L3AlpmRoutes . . . 1470
2.1620.4 L3AlpmTableBuckets . . . 1470
2.1620.5 L3AlpmThreeLevelTableStats . . . 1471
2.1620.6 L3AlpmTwoLevelTableStats . . . 1472
2.1621 show platform trident l3 software alpm-table routes-v6 [...] . . . 1474
2.1622 show platform trident l3 software ecmp . . . 1474
2.1622.1 simpleUcastEcmpBlocks . . . 1474
2.1623 show platform trident l3 software host-table [...] . . . 1475
2.1623.1 HostBankBucketInfo . . . 1475
2.1623.2 HostBankInfo . . . 1475
2.1624 show platform trident l3 software interfaces tunnel decap [...] . . . 1476
2.1624.1 L3ShwL3IntfTunnelEntry . . . 1476
2.1625 show platform trident l3 software interfaces tunnel encap [...] . . . 1476
2.1625.1 L3ShwEgrIpIntfTunnelEntry . . . 1476
2.1626 show platform trident l3 software l3-iif-profile . . . 1476

2.1626.1 IifTableRow . . . 1477
2.1627 show platform trident l3 software lpm-table [...] . . . 1478
2.1627.1 L3LpmTableIndexRanges . . . 1478
2.1627.2 L3LpmTableRoutes . . . 1478
2.1627.3 L3LpmTableSummary . . . 1479
2.1628 show platform trident l3 software mgroups [...] . . . 1480
2.1628.1 MGroupModel . . . 1480
2.1629 show platform trident l3 software next-hops [...] . . . 1482
2.1629.1 L3SoftwareNextHopsHwHer . . . 1482
2.1629.2 L3SoftwareNextHopsMcast . . . 1483
2.1629.3 L3SoftwareNextHopsSdTag . . . 1483
2.1629.4 L3SoftwareNextHopsUcast . . . 1483
2.1630 show platform trident l3 software routes [...] . . . 1487
2.1630.1 StrataL3Vrfs . . . 1487
2.1631 show platform trident l3 software routes-v6 [...] . . . 1487
2.1632 show platform trident l3 software routing-vlan [...] . . . 1487
2.1632.1 PerVlanEntry . . . 1488
2.1633 show platform trident l3 software urpf exception-list [...] . . . 1488
2.1633.1 UnsupportedAclRule . . . 1488
2.1633.2 UrpfException . . . 1488
2.1634 show platform trident l3 summary . . . 1489
2.1634.1 McastModule . . . 1492
2.1635 show platform trident lag [...] . . . 1492
2.1635.1 LagDetailSingleEntry . . . 1492
2.1636 show platform trident lag detail [...] . . . 1493
2.1637 show platform trident lag nonucast-trunk-block-mask l3mc [...] . . . 1493
2.1637.1 NonUcastTrunkBlockMaskTbl . . . 1493
2.1638 show platform trident lag software . . . 1493
2.1639 show platform trident lanz coprocessor status . . . 1494
2.1639.1 CopStatusEntry . . . 1494
2.1640 show platform trident lanz hardware status . . . 1496
2.1640.1 HwStatusEntry . . . 1496
2.1641 show platform trident mac-address-table [...] . . . 1496
2.1642 show platform trident mac-address-table diff [...] . . . 1496
2.1643 show platform trident mac-address-table missing [...] . . . 1496
2.1644 show platform trident mac-traffic-policy hardware-id summary . . . 1497
2.1644.1 MatchRuleHardwareSummary . . . 1497
2.1645 show platform trident mac-traffic-policy rules status [...] . . . 1497
2.1645.1 MacTrafficPolicyRulesChipStatus . . . 1497
2.1646 show platform trident mirror index [...] . . . 1497
2.1646.1 IndexTable . . . 1497
2.1647 show platform trident mirror session [...] . . . 1498
2.1647.1 SessionInfo . . . 1498
2.1648 show platform trident mmu buffers status . . . 1498
2.1648.1 StrataMmuBufferModel . . . 1498
2.1649 show platform trident mmu queue cpu-profile [...] . . . 1498
2.1649.1 CpuQueueConfig . . . 1499
2.1650 show platform trident mmu queue dcn . . . 1499
2.1651 show platform trident mmu queue headroom . . . 1499
2.1652 show platform trident mmu queue mirror-on-drop . . . 1499
2.1653 show platform trident mmu queue mirror-on-drop counters [...] . . . 1499
2.1653.1 StrataMmu.Cli.StrataMmuPoolCountersModel . . . 1499
2.1654 show platform trident mmu queue mirror-on-drop status [...] . . . 1500
2.1654.1 StrataMmu.Cli.InterfaceListOccupancyModel . . . 1500
2.1655 show platform trident mmu queue mirror-on-drop watermarks [...] . . . 1500

2.1655.1 StrataMmu.Cli.StrataMmuPoolWatermarksModel . . . 1500
2.1656 show platform trident mmu queue status [...] . . . 1501
2.1656.1 PlatformInterfaceMmuStatusModel . . . 1501
2.1657 show platform trident mmu queue status cpu [...] . . . 1501
2.1657.1 PlatformCpuStatusModel . . . 1502
2.1658 show platform trident mmu queue watermark [...] . . . 1503
2.1658.1 StrataInterfaceMmuIngressWatermarkModel . . . 1503
2.1658.2 StrataInterfaceMmuMulticastSharedWatermarkModel . . . 1503
2.1658.3 StrataInterfaceMmuUnicastSharedWatermarkModel . . . 1504
2.1658.4 StrataMmuIngressHeadroomPoolWatermarkModel . . . 1504
2.1659 show platform trident mmu queue watermark cpu [...] . . . 1504
2.1659.1 StrataCpuMmuQueueWatermarkModel . . . 1505
2.1660 show platform trident mmu replication watermark [...] . . . 1505
2.1660.1 StrataUnitMmuRqeWatermarkModel . . . 1505
2.1661 show platform trident obm counters [...] . . . 1505
2.1661.1 ObmIntfs . . . 1505
2.1662 show platform trident parity-event [...] . . . 1506
2.1662.1 ChipParityInformation . . . 1506
2.1663 show platform trident priority-flow-control watchdog snapshot [...] . . . 1507
2.1663.1 IntfSnapshotModel . . . 1507
2.1663.2 SnapshotSummaryModel . . . 1507
2.1664 show platform trident profile [...] . . . 1509
2.1664.1 ChipProfileModel . . . 1509
2.1664.2 TileScale . . . 1509
2.1665 show platform trident ptp hardware-sync [...] . . . 1510
2.1666 show platform trident security . . . 1510
2.1666.1 CommonStatusModel . . . 1510
2.1666.2 EgressStatusModel . . . 1510
2.1666.3 IngressStatusModel . . . 1510
2.1667 show platform trident security interfaces [...] . . . 1511
2.1667.1 ShowSecIntfStatusModel . . . 1511
2.1668 show platform trident switch-extender counters queue egress . . . 1512
2.1668.1 SwitchExtenderInterfaceModel . . . 1512
2.1669 show platform trident switch-extender counters queue ingress [...] . . . 1512
2.1669.1 SwitchExtenderInterfaceBackplaneModel . . . 1512
2.1670 show platform trident tcam [...] . . . 1513
2.1670.1 TcamChipInformation . . . 1513
2.1671 show platform trident tcam counter object [...] . . . 1514
2.1671.1 TcamCounterObjectStageModel . . . 1514
2.1672 show platform trident tcam cpu-bound [...] . . . 1515
2.1672.1 PoliciesModel . . . 1515
2.1673 show platform trident tcam directed-broadcast [...] . . . 1518
2.1673.1 TcamDirectedBroadcastPipeModel . . . 1519
2.1674 show platform trident tcam group id [...] . . . 1519
2.1674.1 TridentTcamGroupIdSliceFeatures . . . 1519
2.1675 show platform trident tcam profile [...] . . . 1519
2.1675.1 TcamChipInfo . . . 1520
2.1676 show platform trident tcam qos [...] . . . 1520
2.1677 show platform trident tcam summary [...] . . . 1520
2.1677.1 StrataTcamSummaryChip . . . 1520
2.1678 show platform trident vfi mc-index . . . 1521
2.1678.1 L3VfiMcIndexInfo . . . 1521
2.1679 show platform trident vfi virtual-ports . . . 1521
2.1679.1 L3VfiPhysicalInterfaceVp . . . 1521
2.1679.2 L3VfiSystemInterfaceVp . . . 1522

2.1680 show platform trident vfi vlan map . . . 1522
2.1681 show platform trident vlan membership egr-vp . . . 1522
2.1681.1 VpVlanMembershipEntry . . . 1522
2.1682 show platform trident vlan membership egr-vp unprogrammed . . . 1522
2.1683 show platform trident vlan membership ing-vp . . . 1523
2.1684 show platform trident vlan membership ing-vp unprogrammed . . . 1523
2.1685 show platform trident vlan profile . . . 1523
2.1685.1 VlanProfileEntry . . . 1523
2.1686 show platform trident vlan setting . . . 1523
2.1686.1 VlanSettingEntry . . . 1523
2.1687 show platform trident vlan status . . . 1524
2.1687.1 VlanStatusEntry . . . 1524
2.1688 show platform trident vlan stg . . . 1524
2.1688.1 VlanStgEntry . . . 1524
2.1689 show platform trident vxlan local-vtep . . . 1525
2.1689.1 VxlanLocalVtepV4V6InterfaceModel . . . 1525
2.1690 show platform trident vxlan multicast route underlay [...] . . . 1525
2.1690.1 MrouteKeyToEMEntryModel . . . 1525
2.1691 show platform trident vxlan multicast tunnel [...] . . . 1525
2.1691.1 McastTunnelEntryModel . . . 1525
2.1692 show platform trident vxlan multihoming groups non-peering . . . 1526
2.1692.1 FilteredGroupRow . . . 1526
2.1693 show platform trident vxlan multihoming groups peering . . . 1526
2.1693.1 PeeringGroupRow . . . 1526
2.1694 show platform trident vxlan next-hop . . . 1526
2.1694.1 HerVtepNextHopsModel . . . 1527
2.1694.2 VfiNextHopsModel . . . 1527
2.1695 show platform trident vxlan port-to-next-hop . . . 1527
2.1695.1 VxlanPortToNhTable . . . 1527
2.1696 show platform trident vxlan port-to-next-hop overflow . . . 1527
2.1697 show platform trident vxlan routing-info . . . 1528
2.1697.1 VlanToSvpEntry . . . 1528
2.1698 show platform trident vxlan vlan [...] . . . 1528
2.1698.1 VxlanVlanEntry . . . 1528
2.1699 show platform trident vxlan vlan summary . . . 1528
2.1700 show platform trident vxlan vp-usage . . . 1529
2.1701 show platform trident vxlan vtep [...] . . . 1529
2.1701.1 VxlanRemoteVtepInfoModel . . . 1529
2.1702 show poe [...] . . . 1530
2.1702.1 PoePort . . . 1530
2.1703 show poe histogram [...] . . . 1531
2.1703.1 PoePortHistory . . . 1531
2.1704 show poe neighbor [...] . . . 1531
2.1704.1 PoePortNbrInfo . . . 1531
2.1705 show poe statistics [...] . . . 1532
2.1706 show policing [...] . . . 1533
2.1706.1 ProfileModel . . . 1533
2.1706.2 PolicerInstanceModel . . . 1535
2.1706.3 PolicerPktSizeAdjProfileModel . . . 1535
2.1706.4 PriorityGroupsInstanceModel . . . 1535
2.1707 show policing interfaces [...] . . . 1535
2.1707.1 InterfacePolicerModel . . . 1536
2.1708 show policing interfaces counters [...] . . . 1536
2.1708.1 InterfacePolicingCounterModel . . . 1536
2.1709 show policing policy-map type qos [...] . . . 1536

2.1709.1 Qos.Model.PriorityGroupPmapCmapAttachmentModel . . . 1537
2.1710 show policing priority-group [...] . . . 1537
2.1711 show policy-map PMAP class CMAP [...] . . . 1538
2.1711.1 ClassMap . . . 1538
2.1712 show policy-map PMAP counters [...] . . . 1541
2.1712.1 PolicyMapModel . . . 1541
2.1713 show policy-map [...] . . . 1542
2.1714 show policy-map copp PMAP . . . 1542
2.1715 show policy-map copp copp-system-policy . . . 1542
2.1716 show policy-map counters [...] . . . 1542
2.1717 show policy-map interface (INTF | SVI_INTF | VTI_INTF) [...] . . . 1542
2.1718 show policy-map interface INTF type control-plane . . . 1542
2.1719 show policy-map type copp (copp-system-policy | PMAP) class CMAP . . . 1542
2.1720 show policy-map type copp [...] . . . 1542
2.1721 show policy-map type copp counters [...] . . . 1543
2.1722 show policy-map type pbr [...] . . . 1544
2.1722.1 PolicyMapModel . . . 1544
2.1723 show policy-map type tapagg [...] . . . 1556
2.1724 show port numbering . . . 1556
2.1725 show port-channel [...] . . . 1556
2.1726 show port-channel dense . . . 1557
2.1726.1 PortChannelSummary . . . 1557
2.1727 show port-channel limits . . . 1558
2.1728 show port-channel load-balance (jericho | jericho2 | jericho3 | jericho4) fields [...] . . . 1558
2.1729 show port-channel load-balance [...] . . . 1558
2.1729.1 PortChannelTraffic . . . 1558
2.1730 show port-channel load-balance distribution . . . 1558
2.1731 show port-channel load-balance trident fields . . . 1559
2.1731.1 LagHashFieldsCommon . . . 1559
2.1731.2 LagHashFieldsGre . . . 1559
2.1731.3 LagHashFieldsGtp . . . 1559
2.1731.4 LagHashFieldsIp . . . 1559
2.1731.5 LagHashFieldsIpv6 . . . 1560
2.1731.6 LagHashFieldsMac . . . 1560
2.1731.7 LagHashFieldsMim . . . 1560
2.1731.8 LagHashFieldsMpls . . . 1560
2.1732 show port-channel load-balance trident udf . . . 1561
2.1732.1 StrataLagUdfHashLoadBalanceModel . . . 1561
2.1733 show port-security . . . 1561
2.1733.1 PortStatistic . . . 1561
2.1734 show port-security interface [...] . . . 1563
2.1734.1 Interface . . . 1563
2.1735 show port-security mac-address . . . 1564
2.1735.1 Address . . . 1564
2.1736 show port-security vlan [...] . . . 1564
2.1736.1 VlanDict . . . 1564
2.1737 show priority-flow-control [...] . . . 1565
2.1738 show priority-flow-control buffer counters [...] . . . 1565
2.1739 show priority-flow-control buffer on-chip counters [...] . . . 1565
2.1740 show priority-flow-control counters [...] . . . 1565
2.1741 show priority-flow-control counters detail [...] . . . 1565
2.1742 show priority-flow-control counters history [...] . . . 1565
2.1742.1 PfcIntfHistoryCountersModel . . . 1565
2.1743 show priority-flow-control counters watchdog [...] . . . 1566
2.1744 show priority-flow-control counters watchdog drop [...] . . . 1566

2.1745 show priority-flow-control interfaces Fabric status . . . 1566
2.1746 show priority-flow-control interfaces packet-buffer profile [...] . . . 1566
2.1746.1 PfcIntfPacketBufferProfileModel . . . 1566
2.1747 show priority-flow-control packet descriptor counters [...] . . . 1566
2.1748 show priority-flow-control packet-buffer profile [...] . . . 1566
2.1748.1 PfcPacketBufferProfileModel . . . 1567
2.1749 show priority-flow-control status [...] . . . 1567
2.1750 show privilege . . . 1567
2.1751 show processes . . . 1567
2.1751.1 ProcessInfo . . . 1567
2.1751.2 SystemTimeInfo . . . 1568
2.1752 show processes top once [...] . . . 1569
2.1752.1 CpuInfo . . . 1569
2.1752.2 ProcessActivityInfo . . . 1569
2.1752.3 SystemMemSum . . . 1570
2.1752.4 ThreadsInfo . . . 1570
2.1753 show ptp . . . 1570
2.1754 show ptp foreign-master-record . . . 1570
2.1754.1 PtpIntfVlanForeignMasterRecords . . . 1570
2.1755 show ptp hardware-sync . . . 1571
2.1756 show ptp hold-ptp-time . . . 1571
2.1757 show ptp interface INTFS vlan VLAN_ID . . . 1573
2.1757.1 PtpIntfVlans . . . 1573
2.1758 show ptp interface [...] . . . 1577
2.1759 show ptp interface counters [...] . . . 1577
2.1759.1 PtpIntfVlansCounters . . . 1577
2.1760 show ptp interface counters drop [...] . . . 1577
2.1760.1 PtpDebugIntfCounters . . . 1577
2.1761 show ptp interface vlans [...] . . . 1580
2.1761.1 PtpVlansExtendedWrapper . . . 1580
2.1762 show ptp ip access-list . . . 1580
2.1763 show ptp local-clock . . . 1581
2.1763.1 PtpOrdinaryOrBoundaryClock . . . 1581
2.1764 show ptp local-clock time-properties . . . 1582
2.1764.1 PtpTimeProperty . . . 1582
2.1765 show ptp management-plane . . . 1582
2.1766 show ptp masters . . . 1582
2.1766.1 PtpParent . . . 1583
2.1767 show ptp monitor . . . 1583
2.1767.1 PtpMonitorDataEntry . . . 1583
2.1768 show ptp mpass . . . 1584
2.1769 show ptp mpass interface [...] . . . 1584
2.1770 show ptp mpass interface counters [...] . . . 1584
2.1771 show ptp region domain-number [...] . . . 1584
2.1771.1 DomainNumbersVlans . . . 1584
2.1772 show ptp source . . . 1585
2.1773 show ptp source ip . . . 1585
2.1774 show ptp unicast-negotiation candidate-grantor . . . 1585
2.1774.1 UcastNegCandidateGrantorEntry . . . 1585
2.1775 show ptp unicast-negotiation granted . . . 1585
2.1775.1 UcastNegMessages . . . 1585
2.1776 show ptp unicast-negotiation profile [...] . . . 1586
2.1776.1 UcastNegProfile . . . 1586
2.1777 show ptp unicast-negotiation remote-grantee . . . 1586
2.1777.1 UcastNegRemoteGranteeEntry . . . 1587

2.1778 show ptp unicast-negotiation requested . . . 1587
2.1779 show qos ecn [...] . . . 1587
2.1780 show qos ecn counters . . . 1587
2.1781 show qos ecn delay [...] . . . 1587
2.1782 show qos interfaces [...] . . . 1588
2.1782.1 IntfQosAllModel . . . 1588
2.1783 show qos interfaces drop-thresholds [...] . . . 1593
2.1783.1 IntfDropThresholdsModel . . . 1593
2.1784 show qos interfaces dscp mpls encapsulation disabled [...] . . . 1593
2.1785 show qos interfaces ecn [...] . . . 1594
2.1786 show qos interfaces ecn counters queue [...] . . . 1594
2.1786.1 EcnQueueCounterModel . . . 1594
2.1787 show qos interfaces ecn dynamic [...] . . . 1594
2.1787.1 IntfBufferBasedDecnModel . . . 1594
2.1788 show qos interfaces fabric [...] . . . 1594
2.1789 show qos interfaces latency maximum [...] . . . 1595
2.1789.1 IntfLatencyThresholdModel . . . 1595
2.1790 show qos interfaces random-detect drop [...] . . . 1595
2.1790.1 IntfWredModel . . . 1595
2.1791 show qos interfaces random-detect ecn [...] . . . 1596
2.1792 show qos interfaces scheduler profile [...] . . . 1596
2.1792.1 TxQueueSchedulerMapModel . . . 1596
2.1793 show qos interfaces trust [...] . . . 1596
2.1793.1 IntfTrustModeModel . . . 1596
2.1794 show qos interfaces wred counters queue [...] . . . 1597
2.1794.1 WredQueueCounterModel . . . 1597
2.1795 show qos map cos to traffic-class [...] . . . 1597
2.1795.1 CosToTcProfileModel . . . 1597
2.1796 show qos map dscp to outDscp [...] . . . 1597
2.1796.1 DscpToDscpMapModel . . . 1598
2.1797 show qos map dscp to traffic-class [...] . . . 1598
2.1797.1 DscpToTcMapModel . . . 1598
2.1798 show qos map exp to traffic-class [...] . . . 1598
2.1798.1 ExpToTcProfileModel . . . 1598
2.1799 show qos map traffic-class to cos [...] . . . 1598
2.1799.1 TcToCosMapModel . . . 1598
2.1800 show qos map traffic-class to dscp [...] . . . 1599
2.1800.1 DscpRewriteMapModel . . . 1599
2.1801 show qos map traffic-class to exp [...] . . . 1599
2.1801.1 TcDpToExpMapModel . . . 1599
2.1802 show qos maps [...] . . . 1600
2.1803 show qos profile [...] . . . 1602
2.1803.1 QosProfileModel . . . 1602
2.1804 show qos profile summary [...] . . . 1605
2.1804.1 QosProfileConfiguredIntfs . . . 1605
2.1805 show qos random-detect ecn [...] . . . 1605
2.1806 show qos scheduler profile [...] . . . 1607
2.1806.1 QosSchedulerProfilePerSpeedAdjacencyModel . . . 1607
2.1807 show qos scheduler profile summary . . . 1608
2.1808 show qos scheduling group [...] . . . 1608
2.1808.1 IntfSchedulingGroupWithMembersModel . . . 1608
2.1809 show qos scheduling hierarchy [...] . . . 1608
2.1809.1 QosSchedulingHierarchyModel . . . 1608
2.1810 show qos subinterface port-channel load-balancing . . . 1608
2.1811 show qos tx-queue . . . 1609

2.1812 show qos tx-queue shape rate precision . . . 1609
2.1813 show queue-monitor length (all | global-buffer | statistics) . . . 1610
2.1813.1 CongestionRecordModel . . . 1610
2.1813.2 BarefootCongestionRecord . . . 1610
2.1813.3 BarefootStatisticsRecord . . . 1610
2.1813.4 MakoCongestionRecord . . . 1611
2.1813.5 MakoStatisticsRecord . . . 1611
2.1813.6 SandCongestionRecord . . . 1611
2.1813.7 SandLatencyRecord . . . 1611
2.1813.8 StrataCommonRecord . . . 1612
2.1813.9 StrataCongestionRecord . . . 1612
2.1813.10 StrataDropsRecord . . . 1613
2.1813.11 StrataLatencyRecord . . . 1613
2.1813.12 StrataStatisticsRecord . . . 1614
2.1813.13 XpCongestionRecord . . . 1614
2.1813.14 XpStatisticsRecord . . . 1614
2.1814 show queue-monitor length [...] . . . 1615
2.1815 show queue-monitor length csv [...] . . . 1615
2.1816 show queue-monitor length status . . . 1616
2.1816.1 InterfaceStatusModel . . . 1617
2.1816.2 MakoQueueMonitorLengthStatusModel . . . 1617
2.1817 show queue-monitor streaming ((ip access-list) | (ipv6 access-list)) [...] . . . 1617
2.1818 show queue-monitor streaming clients [...] . . . 1617
2.1818.1 ListOfHostnames . . . 1618
2.1819 show radius . . . 1619
2.1819.1 RadiusStats . . . 1619
2.1819.2 ServerGroup . . . 1620
2.1820 show radius proxy client group [...] . . . 1621
2.1820.1 ClientGroupInfo . . . 1621
2.1821 show radius proxy server group [...] . . . 1622
2.1821.1 ServerGroupInfo . . . 1622
2.1822 show recirc-channel [...] . . . 1622
2.1823 show recirc-channel limits . . . 1622
2.1824 show recirc-channel traffic [...] . . . 1623
2.1825 show redundancy file-replication . . . 1623
2.1826 show redundancy status . . . 1624
2.1827 show redundancy switchover sso . . . 1624
2.1827.1 SwitchoverLog . . . 1625
2.1828 show redundancy time-sync . . . 1625
2.1829 show reload . . . 1625
2.1830 show reload cause [...] . . . 1625
2.1830.1 ReloadCause . . . 1625
2.1831 show reload cause history . . . 1625
2.1831.1 ReloadCauseList . . . 1626
2.1832 show reload cause module (((MODNAME | (Supervisor MODNAME_SUPERVISOR) | (Linecard MODNAME_LINECARD) | (Fabric MODNAME_FABRIC) | (Switchcard MODNAME_SWITCHCARD))) | history) [...] . . . 1626
2.1832.1 Cli.Model.ModularReloadCauseModule . . . 1626
2.1833 show reload console logs [...] . . . 1627
2.1834 show reload console status . . . 1627
2.1834.1 ConsoleLogFile . . . 1627
2.1835 show reload fast-boot . . . 1627
2.1835.1 ReloadHitlessBlockingReason . . . 1628
2.1835.2 ReloadHitlessWarningReason . . . 1629
2.1836 show reload hitless . . . 1630

2.1837 show rib loop (ip | ipv6) route [...] . . . 1630
2.1837.1 LoopedRoute . . . 1630
2.1838 show rib multicast route (ip | ipv6) [...] . . . 1630
2.1839 show rib next-hop (ip | ipv6) [...] . . . 1630
2.1839.1 RibNextHop . . . 1630
2.1840 show rib next-hop (ip | ipv6) dependency . . . 1631
2.1840.1 RecursiveNhDependencyByProtocol . . . 1631
2.1841 show rib next-hop resolution route (ipv4 | ipv6) [...] . . . 1632
2.1841.1 ResolutionRoute . . . 1632
2.1842 show rib ready [...] . . . 1633
2.1842.1 RibReadyModel . . . 1633
2.1843 show rib route (ip | ipv6) [...] . . . 1634
2.1844 show rib route (ip | ipv6) internal [...] . . . 1634
2.1845 show rib route (ip | ipv6) tag TAG [...] . . . 1635
2.1846 show rib route summary [...] . . . 1635
2.1846.1 RibRouteSummaryForVrf . . . 1635
2.1847 show rib route summary brief [...] . . . 1635
2.1848 show rib system-tunneling-ldp-rib route ipv4 [...] . . . 1635
2.1849 show route (ipv4 | ipv6) counters [...] . . . 1635
2.1849.1 RouteCounters . . . 1635
2.1850 show route cache (vrf (VRF | all)) [...] . . . 1636
2.1850.1 Prefix . . . 1636
2.1851 show route cache (vrf (VRF | all)) ipv6 [...] . . . 1636
2.1852 show route cache summary [...] . . . 1636
2.1852.1 RouteCacheSummary . . . 1637
2.1853 show route cache threshold . . . 1637
2.1853.1 ThresholdParams . . . 1637
2.1854 show route-map [...] . . . 1637
2.1855 show route-map config-sanity . . . 1637
2.1856 show route-map expanded [...] . . . 1637
2.1856.1 ExpandedRouteMap . . . 1638
2.1857 show router igp topology [...] . . . 1639
2.1857.1 VrfModel . . . 1639
2.1858 show router rcf code [...] . . . 1641
2.1859 show router rcf errors [...] . . . 1641
2.1860 show router rcf function FUNC_NAME . . . 1641
2.1860.1 FunctionLocationModel . . . 1641
2.1861 show router rcf function location [...] . . . 1641
2.1862 show router rcf pending . . . 1641
2.1862.1 RcfPendingCodeUnitModel . . . 1642
2.1862.2 RcfPendingOpenConfigFunctionModel . . . 1642
2.1863 show running-config [...] . . . 1642
2.1864 show running-config all [...] . . . 1642
2.1865 show running-config digest [...] . . . 1642
2.1866 show schedule NAME | summary . . . 1643
2.1866.1 ScheduleJobModels . . . 1643
2.1867 show security first-instruction . . . 1643
2.1867.1 AmdStatus . . . 1643
2.1867.2 IntelStatus . . . 1644
2.1868 show security pki certificate rotation ROTATION_ID . . . 1644
2.1868.1 CertificateSigningRequest . . . 1644
2.1869 show security pki certificate rotation [...] . . . 1644
2.1870 show segment-security [...] . . . 1645
2.1870.1 Vrf . . . 1645
2.1871 show segment-security application [...] . . . 1645

2.1871.1 Service . . . 1646
2.1872 show segment-security counters [...] . . . 1646
2.1872.1 DestSegment . . . 1646
2.1872.2 PolicyCounter . . . 1647
2.1873 show segment-security errors [...] . . . 1647
2.1873.1 Vrf . . . 1647
2.1874 show segment-security hardware counters [...] . . . 1647
2.1874.1 VrfHardwareCounters . . . 1647
2.1875 show segment-security hardware detail [...] . . . 1648
2.1875.1 VrfHardwareDetail . . . 1648
2.1876 show segment-security hardware routes [...] . . . 1648
2.1876.1 VrfHardwareRoutes . . . 1649
2.1877 show segment-security hardware summary [...] . . . 1649
2.1877.1 VrfHardwareSummary . . . 1649
2.1878 show segment-security policy [...] . . . 1649
2.1878.1 Policy . . . 1649
2.1879 show segment-security status [...] . . . 1650
2.1879.1 Vrf . . . 1650
2.1880 show segment-security to (DST_IP | DST_IPV6) [...] . . . 1650
2.1880.1 FwPolicyToInfoSourceSegments . . . 1650
2.1881 show service mss status . . . 1651
2.1881.1 MssPolicyEnforcementModel . . . 1651
2.1882 show service vxlan address-table advertised [...] . . . 1651
2.1882.1 VxlanVniStatus . . . 1651
2.1883 show service vxlan address-table received [...] . . . 1652
2.1884 show service vxlan arp advertised [...] . . . 1652
2.1884.1 VxlanArpTable . . . 1652
2.1885 show service vxlan arp received [...] . . . 1652
2.1885.1 VxlanVtep . . . 1652
2.1886 show service vxlan nd advertised [...] . . . 1653
2.1887 show service vxlan nd received [...] . . . 1653
2.1888 show service vxlan status . . . 1653
2.1888.1 VxlanControllerCapability . . . 1653
2.1889 show service vxlan vni advertised [...] . . . 1654
2.1889.1 VniList . . . 1654
2.1890 show service vxlan vni received [...] . . . 1654
2.1890.1 SwitchList . . . 1654
2.1891 show service-insertion connection [...] . . . 1654
2.1891.1 SfeSiConnStatusModel . . . 1654
2.1892 show session-config [...] . . . 1655
2.1893 show session-config digest [...] . . . 1655
2.1894 show sflow [...] . . . 1656
2.1894.1 BgpExport . . . 1657
2.1894.2 GnpsiDestination . . . 1657
2.1894.3 Ipv4Destination . . . 1658
2.1894.4 Ipv4Source . . . 1658
2.1894.5 Ipv6Destination . . . 1658
2.1894.6 Ipv6Source . . . 1658
2.1894.7 SendingDatagram . . . 1658
2.1894.8 Details . . . 1659
2.1895 show sflow hardware accelerators . . . 1660
2.1895.1 SflowAcceleratorInfo . . . 1660
2.1896 show sflow hardware counters . . . 1660
2.1896.1 HardwareSflowCountersInfo . . . 1660
2.1897 show sflow hardware mapping . . . 1660

2.1897.1 SflowAcceleratorMappingInfo . . . 1660
2.1898 show sflow hardware mapping lag . . . 1661
2.1898.1 SflowAcceleratorMappingLagInfo . . . 1661
2.1899 show sflow hardware status . . . 1662
2.1899.1 AgentIpAddress . . . 1662
2.1899.2 Vrf . . . 1662
2.1899.3 SflowAccelModuleStatus . . . 1662
2.1900 show sflow interfaces [...] . . . 1663
2.1900.1 LagMemberSflowTypeStatus . . . 1663
2.1901 show sflow interfaces counters . . . 1663
2.1901.1 IntfSampleCounterMap . . . 1664
2.1902 show snapshot counters ecmp detail . . . 1664
2.1903 show snapshot counters ecmp history . . . 1664
2.1903.1 StrataEcmpSnapshotModel . . . 1664
2.1904 show snapshot counters ecmp polling . . . 1664
2.1904.1 EcmpMonitorPollingModel . . . 1665
2.1905 show snmp . . . 1666
2.1905.1 Contact . . . 1666
2.1905.2 SnmpChassis . . . 1666
2.1905.3 SnmpCounters . . . 1666
2.1905.4 SnmpInterface . . . 1667
2.1905.5 SnmpLocation . . . 1667
2.1905.6 SnmpLogging . . . 1667
2.1905.7 SnmpMiscConfig . . . 1667
2.1905.8 SnmpVrfs . . . 1667
2.1906 show snmp ((ipv4 access-list) | (ipv6 access-list)) [...] . . . 1667
2.1907 show snmp community . . . 1667
2.1907.1 SnmpCommunityDetailModel . . . 1668
2.1908 show snmp debug counters table (TABLE | all) [...] . . . 1668
2.1908.1 SnmpTableIteratorCounterModel . . . 1668
2.1909 show snmp debug identifier hashed . . . 1668
2.1910 show snmp engineID . . . 1668
2.1910.1 SnmpRemoteEngineIdHostToPortModel . . . 1669
2.1911 show snmp group [...] . . . 1669
2.1911.1 SnmpGroupVerToDetailModel . . . 1669
2.1912 show snmp local-interface . . . 1669
2.1913 show snmp mib . . . 1669
2.1913.1 SnmpOidsModel . . . 1670
2.1914 show snmp mib bridgemib portid [...] . . . 1670
2.1915 show snmp mib ifmib ifindex [...] . . . 1670
2.1916 show snmp mib notifications [...] . . . 1670
2.1916.1 SnmpSentNotification . . . 1670
2.1917 show snmp mib qosmib counter-interval . . . 1670
2.1918 show snmp mib translate OID . . . 1671
2.1919 show snmp net-snmp buffer . . . 1671
2.1920 show snmp notification . . . 1671
2.1920.1 SnmpNotification . . . 1671
2.1921 show snmp notification host . . . 1671
2.1921.1 HostModel . . . 1671
2.1922 show snmp scheduler [...] . . . 1672
2.1923 show snmp user [...] . . . 1672
2.1923.1 UserCollectionModel . . . 1672
2.1924 show snmp v2-mib chassis . . . 1672
2.1925 show snmp v2-mib contact . . . 1672
2.1926 show snmp v2-mib location . . . 1673

2.1927 show snmp view [...] . . . 1673
2.1927.1 SnmpView . . . 1673
2.1928 show spanning-tree [...] . . . 1674
2.1928.1 SpanningTreeInstance . . . 1674
2.1929 show spanning-tree blockedports . . . 1677
2.1929.1 SpanningTreeBlockedPortsList . . . 1677
2.1930 show spanning-tree counters . . . 1677
2.1931 show spanning-tree instance [...] . . . 1678
2.1931.1 SpanningTreeBridgesDetail . . . 1678
2.1932 show spanning-tree interface ETHINTF [...] . . . 1678
2.1933 show spanning-tree mst [...] . . . 1679
2.1933.1 SpanningTreeMstInstance . . . 1679
2.1934 show spanning-tree mst configuration [...] . . . 1679
2.1935 show spanning-tree mst interface ETHINTF [...] . . . 1679
2.1935.1 SpanningTreeMstInterface . . . 1680
2.1936 show spanning-tree mst test information . . . 1681
2.1936.1 BridgeStpiInfo . . . 1681
2.1937 show spanning-tree root [...] . . . 1682
2.1937.1 SpanningTreeRoot . . . 1682
2.1938 show spanning-tree topology status [...] . . . 1682
2.1938.1 Topology . . . 1682
2.1939 show spanning-tree transmit active [...] . . . 1683
2.1939.1 SpanningTreeBridgeAssuranceInterfaces . . . 1683
2.1940 show spanning-tree vlan [...] . . . 1683
2.1940.1 SpanningTreeVlanInstance . . . 1683
2.1941 show split-horizon group [...] . . . 1683
2.1941.1 VlanWithGroups . . . 1683
2.1942 show srv6 adjacency-segments [...] . . . 1685
2.1942.1 AdjacencySegments . . . 1685
2.1943 show srv6 capabilities . . . 1687
2.1943.1 OtherCapabilitiesModel . . . 1687
2.1943.2 Srv6EndBehaviorsModel . . . 1687
2.1943.3 Srv6EndFlavorsModel . . . 1687
2.1943.4 Srv6HeadendBehaviorsModel . . . 1687
2.1944 show srv6 domain [...] . . . 1688
2.1944.1 Srv6DomainVrfModel . . . 1688
2.1945 show srv6 hardware ale adj [...] . . . 1688
2.1945.1 Ale.Srv6FecRequestTableEntry . . . 1688
2.1946 show srv6 locator [...] . . . 1690
2.1946.1 Srv6ConfigVrfModel . . . 1690
2.1947 show srv6 route [...] . . . 1690
2.1947.1 Srv6RouteEntry . . . 1691
2.1948 show srv6 route counters [...] . . . 1691
2.1948.1 Srv6.Cli.Srv6RouteCountersEntry . . . 1691
2.1949 show storm-control [...] . . . 1693
2.1949.1 GlobalStormControlType . . . 1693
2.1949.2 IntfStormControlStatus . . . 1693
2.1950 show stun client counters [...] . . . 1694
2.1950.1 StunServerProfileCountersModel . . . 1694
2.1951 show stun client translations [...] . . . 1694
2.1951.1 StunClientBindingModel . . . 1694
2.1952 show stun server bindings [...] . . . 1695
2.1952.1 StunServerBindingModel . . . 1695
2.1953 show stun server status . . . 1695
2.1954 show switch aggregation backplane floodset [...] . . . 1696

2.1954.1 SwagFloodsetForIntf . . . 1696
2.1955 show switch aggregation onboarding [...] . . . 1696
2.1955.1 SwagOnboardingMember . . . 1696
2.1956 show switch aggregation onboarding configuration [...] . . . 1697
2.1956.1 SwagMemberConfig . . . 1697
2.1957 show switch aggregation reachability [...] . . . 1697
2.1957.1 ReachabilityState . . . 1697
2.1958 show switch aggregation summary . . . 1698
2.1958.1 MemberStatus . . . 1698
2.1959 show switch forwarding-mode . . . 1698
2.1959.1 SupportedMode . . . 1698
2.1960 show switch scheduler . . . 1699
2.1961 show sync-e esmc counters . . . 1700
2.1961.1 SynceEsmcCountersInfo . . . 1700
2.1962 show sync-e esmc detail [...] . . . 1702
2.1962.1 SynceEsmcDetailInfo . . . 1702
2.1963 show sync-e selection . . . 1703
2.1963.1 SynceSelectionStatus . . . 1704
2.1964 show system bmc status . . . 1704
2.1965 show system coredump . . . 1704
2.1966 show system environment all . . . 1705
2.1966.1 SystemCooling . . . 1705
2.1966.2 SystemEnvAllExtra . . . 1706
2.1966.3 SystemTemperature . . . 1707
2.1966.4 SystemXcvrTemperature . . . 1708
2.1967 show system environment cooling [...] . . . 1708
2.1968 show system environment power . . . 1709
2.1969 show system environment power budget . . . 1709
2.1969.1 PowerConsumer . . . 1709
2.1969.2 PowerDomainStatus . . . 1709
2.1970 show system environment power current . . . 1709
2.1971 show system environment power current detail . . . 1709
2.1971.1 CurrentSensorDetail . . . 1709
2.1972 show system environment power detail . . . 1710
2.1973 show system environment power domain . . . 1710
2.1973.1 PowerDomain . . . 1710
2.1974 show system environment power histogram . . . 1710
2.1975 show system environment power histogram detail . . . 1710
2.1976 show system environment power pmbus . . . 1711
2.1977 show system environment power voltage . . . 1711
2.1978 show system environment temperature [...] . . . 1711
2.1979 show system environment temperature pid-drivers . . . 1711
2.1980 show system environment temperature transceiver [...] . . . 1711
2.1981 show system health storage . . . 1711
2.1981.1 StorageHealth . . . 1711
2.1982 show system memory detail . . . 1712
2.1982.1 MemoryControllerDetailModel . . . 1712
2.1983 show system memory errors . . . 1712
2.1983.1 MemoryControllerErrorsModel . . . 1713
2.1984 show system storage health . . . 1713
2.1985 show system storage health smart . . . 1713
2.1985.1 DeviceSmartAttrs . . . 1713
2.1986 show system storage health smart detail . . . 1713
2.1986.1 DeviceSmartAttrDetails . . . 1713
2.1987 show system storage statistics . . . 1714

2.1987.1 IOStat . . . 1714
2.1988 show system storage statistics last day . . . 1714
2.1989 show system storage statistics rates . . . 1714
2.1990 show system systemd [...] . . . 1714
2.1990.1 SystemdUnitStatus . . . 1715
2.1991 show system systemd detail . . . 1716
2.1991.1 SystemdMountpointsDetail . . . 1716
2.1991.2 SystemdServicesDetail . . . 1716
2.1991.3 SystemdSocketsDetail . . . 1717
2.1992 show system systemd mountpoints detail . . . 1718
2.1993 show system systemd services detail . . . 1718
2.1994 show system systemd sockets detail . . . 1718
2.1995 show tacacs . . . 1719
2.1995.1 ServerGroup . . . 1719
2.1995.2 TacacsStats . . . 1719
2.1996 show tap aggregation counters default-forwarding . . . 1720
2.1996.1 CounterValue . . . 1720
2.1997 show tap aggregation counters tunnel termination gre . . . 1720
2.1998 show tap aggregation groups [...] . . . 1720
2.1998.1 TapAggGroup . . . 1720
2.1999 show tap aggregation groups map TAPPORT [...] . . . 1721
2.1999.1 MapPropertyList . . . 1721
2.2000 show tap aggregation groups map TOOLPORT [...] . . . 1721
2.2001 show tap aggregation nexthop-groups [...] . . . 1721
2.2001.1 FecNexthopGroup . . . 1721
2.2001.2 McgNexthopGroup . . . 1722
2.2002 show tcpdump . . . 1722
2.2002.1 SessionModel . . . 1722
2.2003 show terminal . . . 1722
2.2004 show trace AGENT . . . 1724
2.2004.1 StateAndLevel . . . 1724
2.2005 show traffic generators status [...] . . . 1724
2.2005.1 TrafficGenModel . . . 1724
2.2006 show traffic-engineering adaptive-virtual-topology area . . . 1725
2.2007 show traffic-engineering adaptive-virtual-topology database . . . 1726
2.2007.1 AvtNode . . . 1726
2.2008 show traffic-engineering adaptive-virtual-topology paths [...] . . . 1727
2.2008.1 AvtPathsFromSource . . . 1727
2.2009 show traffic-engineering adaptive-virtual-topology paths history [...] . . . 1728
2.2009.1 AvtPathEventsFromSource . . . 1728
2.2010 show traffic-engineering cbf fec [...] . . . 1729
2.2010.1 CbfFecModel . . . 1729
2.2011 show traffic-engineering cbf mpls [...] . . . 1729
2.2011.1 Cbf.Cli.CbfMplsModel . . . 1730
2.2012 show traffic-engineering cspf path IP_ADDR links . . . 1731
2.2012.1 CspfPathLinksVrfModel . . . 1731
2.2013 show traffic-engineering cspf path PATH_ID [...] . . . 1734
2.2013.1 CspfPathByIdVrfModel . . . 1734
2.2014 show traffic-engineering cspf path PATH_ID links . . . 1735
2.2014.1 CspfPathByIdLinksVrfModel . . . 1736
2.2015 show traffic-engineering cspf path [...] . . . 1737
2.2015.1 CspfPathVrfModel . . . 1737
2.2016 show traffic-engineering cspf path p2mp [...] . . . 1739
2.2016.1 CspfPathVrfP2mpModel . . . 1739
2.2017 show traffic-engineering cspf path p2mp tunnel-name TUNNEL_NAME [...] . . . 1741

2.2018 show traffic-engineering cspf path tunnel-name TUNNEL_NAME [...] . . . 1741
2.2019 show traffic-engineering cspf path tunnel-name TUNNEL_NAME links . . . 1741
2.2020 show traffic-engineering database . . . 1742
2.2020.1 TeVrfDbModel . . . 1742
2.2021 show traffic-engineering database duplicate interface-address . . . 1744
2.2021.1 InterfaceIpInfoModel . . . 1744
2.2022 show traffic-engineering database router-id IP . . . 1744
2.2023 show traffic-engineering gribi ipv4-aft [...] . . . 1744
2.2023.1 GribiIpAft . . . 1744
2.2024 show traffic-engineering gribi ipv4-aft failed [...] . . . 1745
2.2025 show traffic-engineering gribi ipv4-aft unacknowledged [...] . . . 1745
2.2025.1 GribiPendingIpAft . . . 1745
2.2026 show traffic-engineering gribi ipv6-aft [...] . . . 1745
2.2027 show traffic-engineering gribi ipv6-aft failed [...] . . . 1745
2.2028 show traffic-engineering gribi ipv6-aft unacknowledged [...] . . . 1745
2.2029 show traffic-engineering gribi mpls-aft [...] . . . 1745
2.2029.1 GribiMplsAftType . . . 1745
2.2030 show traffic-engineering gribi nexthop-aft [...] . . . 1747
2.2030.1 GribiNhAftType . . . 1747
2.2031 show traffic-engineering gribi nexthop-aft unacknowledged [...] . . . 1748
2.2031.1 GribiNhAftVersionType . . . 1748
2.2032 show traffic-engineering gribi nexthop-group-aft [...] . . . 1749
2.2032.1 GribiNhgAftType . . . 1749
2.2033 show traffic-engineering gribi nexthop-group-aft failed [...] . . . 1750
2.2034 show traffic-engineering gribi nexthop-group-aft unacknowledged [...] . . . 1750
2.2034.1 GribiNhgAftVersionType . . . 1750
2.2035 show traffic-engineering interfaces [...] . . . 1751
2.2035.1 TeIntfModel . . . 1751
2.2036 show traffic-engineering interfaces bandwidth [...] . . . 1752
2.2036.1 TeInterfaceBwModel . . . 1752
2.2037 show traffic-engineering rsvp . . . 1753
2.2038 show traffic-engineering rsvp tunnel [...] . . . 1754
2.2038.1 RsvpLerTunnel . . . 1754
2.2039 show traffic-engineering segment-routing cbf fec [...] . . . 1759
2.2039.1 Cbf.Cli.SrTePolicyCbfFecModel . . . 1759
2.2040 show traffic-engineering segment-routing policy [...] . . . 1760
2.2040.1 SrTePolicyCandidatesModel . . . 1760
2.2041 show traffic-engineering segment-routing policy active [...] . . . 1763
2.2041.1 SrTePolicyActiveModel . . . 1763
2.2042 show traffic-engineering segment-routing policy fec [...] . . . 1763
2.2042.1 SrTePolicyFecInfo . . . 1763
2.2043 show traffic-engineering segment-routing policy segment-list [...] . . . 1764
2.2043.1 SrTePolicySegmentLists . . . 1764
2.2044 show traffic-engineering segment-routing policy segment-list counters [...] . . . 1765
2.2044.1 SrTePolicySegmentListsCounters . . . 1765
2.2045 show traffic-engineering segment-routing policy summary . . . 1766
2.2045.1 SrTePolicySummaryModel . . . 1766
2.2046 show traffic-engineering segment-routing replication-segment [...] . . . 1769
2.2046.1 SrP2mpCandidatesModel . . . 1769
2.2047 show traffic-engineering segment-routing replication-segment summary . . . 1771
2.2047.1 ReplicationSegmentSummaryModel . . . 1771
2.2048 show traffic-policy (cpu | vlan | interface) [...] . . . 1773
2.2048.1 TrafficPolicy . . . 1773
2.2049 show traffic-policy (cpu | vlan | interface) counters [...] . . . 1775
2.2049.1 TrafficPolicyCounters . . . 1775

2.2050 show traffic-policy (cpu | vlan | interface) errors [...] . . . 1776
2.2050.1 TrafficPolicyErrors . . . 1776
2.2051 show traffic-policy (cpu | vlan | interface) summary [...] . . . 1778
2.2051.1 TrafficPolicySummary . . . 1778
2.2052 show traffic-policy field-set integer [...] . . . 1779
2.2052.1 TrafficPolicyIntegerFieldSet . . . 1779
2.2053 show traffic-policy field-set ipv4 prefix [...] . . . 1779
2.2053.1 IpPrefixFieldSet . . . 1780
2.2054 show traffic-policy field-set ipv6 prefix [...] . . . 1780
2.2055 show traffic-policy field-set l4-port [...] . . . 1780
2.2055.1 TrafficPolicyL4PortFieldSet . . . 1780
2.2056 show traffic-policy field-set mac [...] . . . 1781
2.2056.1 TrafficPolicyMacFieldSet . . . 1781
2.2057 show traffic-policy field-set service [...] . . . 1781
2.2057.1 TrafficPolicyServiceFieldSet . . . 1781
2.2058 show traffic-policy field-set vlan [...] . . . 1782
2.2058.1 TrafficPolicyVlanFieldSet . . . 1782
2.2059 show traffic-policy interface vrf detail [...] . . . 1782
2.2059.1 VrfIntfOverrideInput . . . 1782
2.2060 show traffic-policy protocol neighbors bgp . . . 1782
2.2060.1 ProtocolNeighbor . . . 1782
2.2061 show transceiver application [...] . . . 1783
2.2061.1 TransceiverApplications . . . 1783
2.2062 show transceiver cdb capabilities [...] . . . 1784
2.2062.1 TransceiverCdbCapabilitiesSlotDetail . . . 1784
2.2063 show transceiver cdb operation [...] . . . 1786
2.2063.1 TransceiverCdbOperationSlotDetail . . . 1786
2.2064 show transceiver controller state [...] . . . 1787
2.2064.1 Xcvr.XcvrCliModels.ControllerState . . . 1787
2.2065 show transceiver error [...] . . . 1787
2.2065.1 TransceiverErrorValues . . . 1787
2.2066 show transceiver error-correction coherent degrade [...] . . . 1788
2.2066.1 TransceiverCoherentFecDegradeSlot . . . 1788
2.2067 show transceiver squelch [...] . . . 1789
2.2067.1 TransceiverSquelchTypes . . . 1789
2.2068 show transceiver status [...] . . . 1789
2.2069 show transceiver status electrical tuning file . . . 1790
2.2070 show transceiver status firmware update [...] . . . 1791
2.2070.1 TransceiverFirmwareUpdateSlotDetail . . . 1791
2.2071 show transceiver status firmware version [...] . . . 1792
2.2071.1 TransceiverFirmwareCollection . . . 1792
2.2072 show transceiver traffic-loopback capabilities [...] . . . 1792
2.2072.1 Capabilities . . . 1792
2.2073 show transceiver traffic-loopback status [...] . . . 1793
2.2073.1 SlotInfo . . . 1793
2.2074 show tunnel counters ip-in-ip [...] . . . 1793
2.2074.1 TunnelCountersEntry . . . 1793
2.2075 show tunnel counters mpls rate [...] . . . 1794
2.2075.1 MplsTunnelCountersRateEntry . . . 1794
2.2076 show tunnel counters udp [...] . . . 1794
2.2077 show tunnel fib [...] . . . 1795
2.2077.1 TunnelFibCategory . . . 1795
2.2078 show tunnel fib multicast [...] . . . 1796

2.2079 show tunnel rib (system-tunneling-ldp-tunnel-rib | system-igp-shortcut-tunnel-rib | system-tunnel-rib | (colored (system-colored-tunnel-rib | system-colored-tunneling-ldp-tunnel-rib | system-colored-igp-shortcut-tunnel-rib)) | TUNNEL_RIB_NAME) summary . . . 1796
2.2080 show tunnel rib brief [...] . . . 1796
2.2080.1 TunnelRibEntriesByTunnelType . . . 1796
2.2081 show tunnel rib candidates [...] . . . 1797
2.2081.1 InternalTunnelRibCandidates . . . 1797
2.2082 show tunnel rib colored brief [...] . . . 1798
2.2082.1 TunnelRibColors . . . 1798
2.2083 show tunnel rib multicast (mldp | rsvp | static) . . . 1798
2.2083.1 MulticastTunnelRibEntry . . . 1799
2.2084 show tunnel rib summary . . . 1799
2.2085 show twserver [...] . . . 1799
2.2086 show twserver summary . . . 1799
2.2087 show uptime . . . 1800
2.2088 show users . . . 1800
2.2088.1 Aaa.Cli.ShowAaaUserInfo . . . 1800
2.2089 show users accounts . . . 1800
2.2089.1 Aaa.Cli.User . . . 1800
2.2090 show users detail . . . 1800
2.2090.1 Aaa.Cli.AaaSession . . . 1801
2.2091 show users roles [...] . . . 1801
2.2091.1 Aaa.Cli.Rules . . . 1801
2.2092 show version [...] . . . 1802
2.2092.1 Details . . . 1802
2.2093 show version compatibility SWI . . . 1803
2.2094 show version firmware . . . 1803
2.2095 show version license . . . 1803
2.2096 show vlan [...] . . . 1804
2.2096.1 Status . . . 1804
2.2097 show vlan brief [...] . . . 1804
2.2098 show vlan brief count . . . 1804
2.2099 show vlan counters [...] . . . 1805
2.2099.1 VlanStats . . . 1805
2.2100 show vlan dynamic . . . 1805
2.2101 show vlan floodset expanded [...] . . . 1805
2.2101.1 FloodsetExpandedVlanModel . . . 1805
2.2102 show vlan interface dynamic . . . 1805
2.2102.1 VlanIntfs . . . 1805
2.2103 show vlan internal allocation policy . . . 1806
2.2104 show vlan internal usage . . . 1806
2.2105 show vlan internal usage reserved . . . 1806
2.2106 show vlan private-vlan . . . 1806
2.2106.1 PrivateVlans . . . 1806
2.2107 show vlan trunk group [...] . . . 1806
2.2107.1 GroupNames . . . 1807
2.2108 show vmtracer all [...] . . . 1808
2.2108.1 VmTracerSwitches . . . 1808
2.2109 show vmtracer interface INTFS vm VMNAME . . . 1809
2.2109.1 VmTracerGenericInterface . . . 1809
2.2109.2 VmTracerLagInterface . . . 1809
2.2110 show vmtracer interface [...] . . . 1809
2.2111 show vmtracer logical-switch [...] . . . 1809
2.2111.1 NetworkScope . . . 1810
2.2112 show vmtracer session SESSION (vcenter | vsm) [...] . . . 1811

2.2112.1 VmTracerSessionStatus . . . 1811
2.2113 show vmtracer session [...] . . . 1812
2.2114 show vmtracer vm VM_NAME . . . 1812
2.2115 show vmtracer vm [...] . . . 1812
2.2116 show vmtracer vxlan segment [...] . . . 1812
2.2117 show vmtracer vxlan segment range . . . 1812
2.2117.1 McastRange . . . 1812
2.2117.2 VniRange . . . 1813
2.2118 show vpls [...] . . . 1814
2.2118.1 VplsInstance . . . 1814
2.2119 show vpls pseudowire brief (all | { (neighbor NEIGHBOR) | (pseudowire-type PW_TYPE) }) [...] . . . 1816
2.2120 show vrf [...] . . . 1816
2.2120.1 VrfEntry . . . 1816
2.2121 show vrf leak connected (ipv4 | ipv6) . . . 1817
2.2121.1 LeakedConnectedRoutes . . . 1817
2.2122 show vrf leak id . . . 1817
2.2123 show vrf reserved-ports [...] . . . 1818
2.2123.1 VrfReservedPortsEntry . . . 1818
2.2124 show vrf selection policy . . . 1818
2.2125 show vrf selection policy errors . . . 1818
2.2126 show vrf selection policy field-set ipv4 prefix [...] . . . 1818
2.2127 show vrf selection policy field-set ipv6 prefix [...] . . . 1818
2.2128 show vrf summary . . . 1818
2.2129 show vrrp [...] . . . 1819
2.2129.1 VrrpRouterDetailBase . . . 1819
2.2129.2 VrrpRouterDetailV4 . . . 1820
2.2129.3 VrrpRouterDetailV6 . . . 1821
2.2130 show vrrp brief [...] . . . 1823
2.2130.1 VrrpRouterBriefBase . . . 1823
2.2130.2 VrrpRouterBriefV4 . . . 1823
2.2130.3 VrrpRouterBriefV6 . . . 1823
2.2131 show vxlan address-table [...] . . . 1824
2.2131.1 VxlanMacAddrListing . . . 1824
2.2132 show vxlan address-table count [...] . . . 1824
2.2133 show vxlan config-sanity [...] . . . 1824
2.2133.1 ConfigCheckCategory . . . 1824
2.2134 show vxlan control-plane [...] . . . 1825
2.2134.1 VlanControlPlaneConfigModel . . . 1825
2.2135 show vxlan controller address-table advertised [...] . . . 1825
2.2136 show vxlan controller address-table received [...] . . . 1825
2.2137 show vxlan controller arp advertised [...] . . . 1826
2.2138 show vxlan controller arp received [...] . . . 1826
2.2139 show vxlan controller nd advertised [...] . . . 1826
2.2140 show vxlan controller nd received [...] . . . 1826
2.2141 show vxlan controller status . . . 1826
2.2142 show vxlan counters learn-restrict COUNTER [...] . . . 1826
2.2142.1 VxlanPrefixStatusModel . . . 1827
2.2143 show vxlan counters software . . . 1828
2.2144 show vxlan counters varp . . . 1834
2.2145 show vxlan counters vni [...] . . . 1839
2.2145.1 VxlanVniCounters . . . 1839
2.2146 show vxlan counters vtep [...] . . . 1839
2.2146.1 VxlanVtepCounters . . . 1839
2.2147 show vxlan counters vtep vni [...] . . . 1840

2.2147.1 PerVtepVniCounters . . . 1840
2.2148 show vxlan flood traffic . . . 1840
2.2149 show vxlan flood vtep [...] . . . 1840
2.2149.1 VxlanVtepListModel . . . 1840
2.2150 show vxlan learn-restrict vtep [...] . . . 1841
2.2150.1 VxlanPrefixListModel . . . 1841
2.2151 show vxlan policers vni [...] . . . 1841
2.2151.1 VxlanConfigModel . . . 1841
2.2152 show vxlan policers vni counters [...] . . . 1842
2.2152.1 VxlanVniPolicersAllCountersInfoModel . . . 1842
2.2153 show vxlan qos . . . 1842
2.2154 show vxlan security profile . . . 1843
2.2155 show vxlan vni [...] . . . 1843
2.2155.1 VxlanVniVlanCollection . . . 1843
2.2156 show vxlan vni summary . . . 1843
2.2157 show vxlan vtep [...] . . . 1844
2.2157.1 RemoteVtepConfig . . . 1844
2.2157.2 TunnelTypeList . . . 1844
2.2157.3 VxlanInterface . . . 1844
2.2158 show vxlan vtep encapsulation [...] . . . 1844
2.2158.1 VxlanEncapSourceIpRewriteModelList . . . 1844
2.2159 show vxlan vtep summary . . . 1845
2.2160 show world . . . 1845
2.2160.1 Country . . . 1845
2.2161 show world bad . . . 1845
2.2162 show world stream [...] . . . 1845
2.2163 show zerotouch . . . 1845
2.2164 traceroute adaptive-virtual-topology (vrf VRF) (avt AVT) (destination DEST) [...] . . . 1847
2.2164.1 AvtPathTraceModel . . . 1847
2.2165 traceroute mpls generic ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK)) [...] . . . 1848
2.2165.1 MplsTracerouteHdr . . . 1848
2.2166 traceroute mpls ldp ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK)) [...] 1851
2.2167 traceroute mpls p2mp mldp ROOTADDR ((lsp-id OPQVAL) | (multicast ipv4 SOURCEADDR GROUPADDR)) [...] . . . 1851
2.2168 traceroute mpls rsvp session ((id SESSION_ID lsp LSP) | (name SESSION_NAME)) [...] 1851
2.2169 traceroute mpls rsvp tunnel TUNNEL_NAME [...] . . . 1851
2.2170 traceroute mpls segment-routing ((((ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK))) | (ipv6 IPV6_ADDRESS) | (isis ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK))) | (isis ipv6 IPV6_ADDRESS))) | (ospf ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK)))) [...] . . . 1851
2.2171 who . . . 1852

Chapter 1

Arista Command API Fundamentals

The Arista Command API is a simple and complete API that allows you to configure and monitor your Arista switches. Once the API is enabled, the switch accepts commands using the industry standard CLI syntax, and responds with machine readable output and errors serialized in JSON, served over HTTP.

The Command API is easy to use...

```
from jsonrpclib import Server
import ssl

# -- Configuration --
CA_CERT_PATH = "/path/to/your/custom_ca.pem"

# 1.  Create a default SSL Context
context = ssl.create_default_context()

# 2.  Load the CA certificate file that verifies the server's certificate
try:
    context.load_verify_locations( CA_CERT_PATH )
except FileNotFoundError:
    print( f"Error:  CA certificate not found at {CA_CERT_PATH}")
    # Handle error or fall back

# 3.  Instantiate the Server, passing the configured context
switch = Server( "https://username:passw0rd@myswitch/command-api", context=context )
response = switch.runCmds( 1, ["show version"] )
print( "The switch's system MAC addess is", response[0]["systemMacAddress"] )
```

... and easy to configure!

```
bash$ ssh username@myswitch
Password:  ⟨passw0rd⟩
myswitch⟩ enable
myswitch# configure terminal
myswitch(config)# management api http-commands
myswitch(config-mgmt-api-http-cmds)# no shutdown
myswitch(config-mgmt-api-http-cmds)# show management api http-commands
Enabled:            Yes
HTTPS server:       running, set to use port 443
HTTP server:        shutdown, set to use port 80
Local HTTP server:  shutdown, no authentication, set to use port 8080
Unix Socket server: shutdown, no authentication
VRFs:               default
...
```

1.1 Configuring the Command API Agent

Although disabled by default, it is very simple to get the Command API server running on your switch. To modify its configuration, from `configure` mode, enter `management api http-commands` mode. In this submode, you can turn on or off the server by typing `[no] shutdown`.
The configuration of the protocol itself in done in HttpServer mode. From `configure` mode, enter `management http-server` mode. In this submode, you can switch between accepting HTTP or HTTPS traffic via `[no] protocol http[s]`, and adjust the ports the server should listen on using `protocol http[s] port` ⟨portNumber⟩.
You can also configure the API to only accept connections from scripts running on the switch itself. To enable this feature, see 1.4.
In any CLI mode, you can issue the `show management api http-commands` command to view the status of the agent, including server information, attached users, last request time and other details.

```
myswitch⟩ enable
myswitch# configure terminal
myswitch(config)# management api http-commands
myswitch(config-mgmt-api-http-cmds)# [no] shutdown
myswitch(config-mgmt-api-http-cmds)# management http-server
myswitch(config-mgmt-http-server)# [no] protocol https [port <portNumber>]
myswitch(config-mgmt-http-server)# [no] protocol http [port <portNumber>]
myswitch(config-mgmt-http-server)# [no] protocol http localhost [port <portNumber>]
myswitch(config-mgmt-http-server)# [no] protocol unix-socket
```

1.1.1 Configuring a Certificate

Because clients use HTTP basic authentication to send usernames and passwords to the switch, we recommend using HTTPS so no passwords are sent in the clear over the network. HTTPS certificates and key can be changed with `[no] protocol https certificate`. By default a self-signed certificate will be used.

```
myswitch⟩ enable
myswitch# configure terminal
myswitch(config)# management http-server
myswitch(config-mgmt-http-server)# protocol https certificate
Enter TEXT certificate.  Type 'EOF' on its own line to end.
...
EOF

Enter TEXT private key.  Type 'EOF' on its own line to end.
...
EOF
```

1.1.2 Configuring multiple VRFs

Since release 4.20, you can configure multiple VRFs in `management api http-commands` mode. By entering submode `vrf` ⟨vrfName⟩, you can enable or disable Command API server in multiple VRFs by typing `[no] shutdown` inside each VRF submode. If no VRF specified and Command API server is enabled, it will start in default VRF automatically. When you enable Command API server in the first user VRF, it will be removed from default VRF. You can run Command API server in default VRF by explicitly configuring in submode `vrf default` with `no shutdown` (this behavior is for reasons of backwards compatibility).

```
myswitch⟩ enable
myswitch# configure terminal
myswitch(config)# management api http-commands
myswitch(config-mgmt-api-http-cmds)# vrf foo
myswitch(config-mgmt-api-http-cmds-vrf-foo)# no shutdown
myswitch(config-mgmt-api-http-cmds-vrf-foo)# exit
myswitch(config-mgmt-api-http-cmds)# vrf bar
myswitch(config-mgmt-api-http-cmds-vrf-bar)# no shutdown
myswitch(config-mgmt-api-http-cmds-vrf-bar)# exit
myswitch(config-mgmt-api-http-cmds)# vrf default
myswitch(config-mgmt-api-http-cmds-vrf-default)# no shutdown
myswitch(config-mgmt-api-http-cmds-vrf-default)# exit
myswitch(config-mgmt-api-http-cmds)# show management api http-commands
Enabled:            Yes
HTTPS server:       running, set to use port 443
HTTP server:        shutdown, set to use port 80
Local HTTP server:  shutdown, no authentication, set to use port 8080
Unix Socket server: shutdown, no authentication
VRFs:               bar,default,foo
...
```

1.2 The Spec

The Command API uses the lightweight, standardized JSON-RPC protocol to communicate between your program (the client) and the switch (the server), see http://www.jsonrpc.org/specification. Although most languages have client libraries which abstract away the JSON-RPC internals, it is useful to understand the communication mechanism between the client and the switch.

1.2.1 Exploring the Command API

To explore the API, point your web browser to `http[s]://myswitch/`, after enabling Command API. This web-app lets you interactively explore the protocol, return values, and model documentation. Please note that if you visit the tool using HTTPS, your browser may emit a warning; this is because by default the agent uses a locally signed certificate for encryption purposes and can be ignored. You may always set a certificate and key issued by your own CA for enhanced security.

1.2.2 An annotated example

The client starts by sending a JSON-RPC request via an HTTP POST request to http://⟨your-switch⟩/command-api, which encapsulates a list of CLI commands it wishes to run, and the switch replies with a JSON-RPC response containing the result of each CLI command that was executed. The commands in the request are run in order on the switch. After the switch has executed all commands, it exits back to unprivileged mode. If any of the commands emit an error, no further commands from that request are executed, and the response from the switch will contain an `error` object containing the details of the error that occurred.

To illustrate, here are annotated versions of the underlying Request and Response messages sent between the client and switch.

1.2.2.1 The Request

```
{
 "jsonrpc": "2.0",
 "method": "runCmds",
 "params": {
   "version": 1,
   "cmds": [
     "enable",
     "configure",
     "interface Ethernet1",
     "switchport access vlan 3",
     "show vlan 3",
   ],
   "format": "json",
 },
 "id": 1
}
```

`jsonrpc`: The protocol version. Always `2.0`, and usually set by a client library.

`method`: The method to run on the switch. At this time `runCmds` is the only method supported.

`version` is a mandatory parameter representing the API version. Currently always has the value `1`.

`cmds` is a mandatory parameter which contains a list of CLI commands. Commands may either be a string or a complex object type. For more details, see the command specification

`format` is an optional parameter specifying response format. Can be `text` or `json`, and defaults to `json`.

`id`: A unique identifier that will be echoed back by the switch. May be a string or number.

1.2.2.2 The Response: success case

This response is returned by the switch after receiving the above request. All responses conform JSON-RPC 2.0 specifications.

```
{
 "jsonrpc": "2.0",
 "result": [
   {},
   {},
   {},
   { "warnings": [
       "Access VLAN does not exist.  Creating vlan 3"
     ]
   },
   { "sourceDetail": "",
     "vlans": {
       "3": {
         "status": "active",
         "name": "VLAN0003",
         "interfaces": {
           "Ethernet1": {
              "annotation": null,
              "privatePromoted": false
           }
         },
         "dynamic": false
       }
     }
   }
 ],
 "id": 1
}
```

The protocol version. Always `"2.0"`.

The result list. Contains one object for each CLI command executed, and the position of the result corresponds to the original command list. If the request specified a `text` format, however, `result` will contain a list of strings.

Most non-show commands produce no output and thus return an empty JSON object. However, in some cases, a command may produce `warnings` or `errors` which will be stored in arrays of the same name.

show commands will return formatted JSON objects containing all information seen in the ASCII output in the normal CLI. In this case, `show vlan 3` will give you a mapping from VLAN id to VLAN model.

The same id (string/number) that was provided by the request.

1.2.2.3 The Response: failure case

In this case, let's assume our account does not have the appropriate AAA permissions to enter `configure` mode.

```
{
   "jsonrpc": "2.0",
   "error": {
```

On an `error`, no result object is present, only an error object, which is guaranteed to have the following attributes: `code`, `messages`, and `data`.

```
     "code": 1005,
```

Command API `error code`.

```
     "message": "CLI command 2 of 5 'configure' failed:
                 permission to run command denied",
```

General high-level error message.

```
     "data": [
```

Similar to the `result` object in the successful response, the `data` object is a list of objects corresponding to the results of all commands up to, and including, the failed command. If there was a an error before any commands were executed (e.g. bad credentials), `data`, will be empty.

```
         {},
```

The `enable` command passed without incident.

```
         { "errors": [
           "Authorization denied for command 'configure'"
         ] }
     ]
   },
   "id": 1
}
```

In this case, we failed on the second command. The last object in the `data` array will always correspond to the failed command. The command failure details are always stored in the `errors` array.

1.2.3 Command Specification

In most cases, the client will use a simple string to specify the CLI command in the `cmds` parameter in the request. In certain cases, however, clients may wish to specify additional parameters during the command's execution. To use complex commands, pass a JSON object in lieu of a string, with the following attributes:

`cmd`	(mandatory) specify the CLI command to run.
`input`	(optional) specify a string to be provided as standard input while running the `cmd`
`revision`	(optional) in the case of 'show' commands that have been modified over the course of different EOS releases, this parameter allows clients to request an old model format. At this time, all models are at revision 1, and this attribute will be ignored.

For example, to set the message of the day to `Hello World!`, the client should set `cmds` to

```
[ "enable", "configure", { "cmd":  "banner motd", "input":  "Hello World!\nEOF" } ]
```

Similarly, if the switch requires an enable password, the following `cmds` value would let you enter exec mode and clear interface counters

```
[  "cmd":  "enable", "input":  "hunter2" , "clear counters" ]
```

1.2.4 Error Codes

The following errors are generated if there is an issue with the request. Do note that new error codes may be introduced in future releases.

JSON-RPC 2.0 Defined Errors

Code	Description
32700	Parse Error
32600	Invalid Request
32601	Method not found
32602	Invalid params
32603	Internal server error

Command API Errors

Code	Description
1000	General error
1001	Command caused internal exception
1002	Invalid command: the string does not match any command
1003	Command not ready: attempted to get json from a show command, however the command has not been converted to be compatible with the Command API yet. Use format = text to run this command and get ASCII output.
1004	Command incompatible: cannot run command over the Command API
1005	Command unauthorized: user has insufficient permissions to run the command
1006	Configuration locked: another CLI session has the configuration lock

1.3 Using the Command API

In practice, most libraries hide the JSON-RPC version, id and protocol details. Instead you only need to call the `runCmds` method with the `version` and `cmds` parameters and, optionally, the `format` parameter. The responses generated by the client library usually follow language conventions. For example, in Python, an error response results in

an Exception being thrown, while Javascript expects an error handler callback.

1.3.1 Unsupported commands

Certain commands are not permitted and will always return an error. The largest class of such commands are interactive commands; `watch` is a prime example. Other commands, like `reload` must use their non-interactive versions: such as `reload now`. The `bash` command is only allowed with the `timeout <seconds>` argument, ie. `bash timeout <seconds> <bash-command>`.

Commands that attempt to use CLI pipes (e.g. `show interfaces | grep Ethernet1`) are also not allowed. In addition, no abbreviations are allowed in commands. This is necessary because future versions of EOS may add more commands, rendering previous abbreviations ambiguous.

1.3.2 Unconverted commands

Although you can access almost any CLI command via the Command API, not all `show` commands have been converted to return formatted data, and trying to run the command with the `format` parameter set to `json` will result in an error. However, you can still get the CLI ASCII output for the unconverted command by setting the `format` parameter to `text`. With this parameter set, the response will contain an array of strings (rather than an array of objects), each representing the text output of the corresponding command. When operating with `format` set to `text`, no errors will be generated; rather they will be included in the ASCII output, the same way they are printed in a standard CLI session. To view converted commands visit the `documentation.html` on a switch.

1.3.3 Streamed commands

eAPI maintains a buffer that can be exhausted if the return value is too large. eAPI offers a special streaming mode that does not buffer any of the results. The benefits of using streaming is it uses less memory and less CPU. However errors are not handled in the standard JSON-RPC fashion. According to the JSON-RPC spec an `error` object must appear at the top level of the response. However in the streaming case the `error` object appears within the `result` object. Additionally valid JSON may not be produced in an error case. To use streaming please use `streaming=true`

1.3.4 Using JSON-RPC

The JSON-RPC spec is well documented at `http://www.jsonrpc.org/specification`, and there are libraries in almost every language that make dealing with JSON-RPC a breeze. Here are a list of some recommended client libraries:

Python : `https://github.com/joshmarshall/jsonrpclib`

Perl : `http://search.cpan.org/~powerman/JSON-RPC2-0.1.1/lib/JSON/RPC2/Client.pm`

Javascript : `https://github.com/gimmi/jsonrpcjs`

And many more `http://en.wikipedia.org/wiki/JSON-RPC#Implementations`

1.4 On-box Usage of Command API

It is often useful to run scripts that use Command API directly on the switch itself, without configuring them with AAA credentials. EOS provides three mechanisms to accomplish this. The preferred way is to use the EapiClientLib library, however other methods are also supported.

1.4.1 Using EapiClientLib (requires no configuration)

```
from EapiClientLib import EapiClient

switch = Server( disableAaa=True, privLevel=15 )
response = switch.runCmds( 1, ["show version"] )
print( "The switch's system MAC addess is", response["result"][0]["systemMacAddress"] )
```

1.4.2 Other Methods (requires configuration)

The first is an HTTP server bound to localhost (on port 8080 by default), which only accepts connections arriving from the same machine. The other solution is a Unix domain socket. To enable one or both, use the following commands:

```
myswitch⟩ enable
myswitch# configure terminal
myswitch(config)# management api http-commands
myswitch(config-mgmt-api-http-cmds)# protocol http localhost
myswitch(config-mgmt-api-http-cmds)# protocol unix-socket
myswitch(config-mgmt-api-http-cmds)# no shutdown
```

Once Command API is enabled then you access via the local domain socket `unix:/var/run/command-api.sock`

```
switch = Server( "unix:/var/run/command-api.sock" )
```

If configured to use HTTP over localhost, your script can access the API as follows:

```
switch = Server( "http://localhost:8080/command-api" )
```

1.5 Using Websockets with Command API

Command API can also be used over Websockets, allowing for a stateful approach, which jsonrpc does not provide on its own. Commands executed over Websockets do not create a new session for each request. One use case is if multiple requests needs to be performed while holding the configuration lock. There is a reference implementation of the protocol in the python site-packages named EapiWebsocketLib.py. This is an example usage if it were done on-box:

```
import websocket
from EapiWebsocketLib import EapiWebsocketClient

ws = websocket.WebSocket()
with EapiWebsocketClient( ws, "127.0.0.1", username, password ) as switch:
    response = switch.runCmds( 1, ["show version"] )
    print( "The switch's system MAC addess is", response["result"][0]["systemMacAddress"]
 )
```

1.6 Client-Side Certificates

Client authentication can be accomplished via X.509 public key certificates.

What is this good for? Imagine you have a general purpose script that does some operations on an Arista switch using eAPI. That script will need your EOS username/password. Since the various users of that script might have their own EOS usernames/passwords, putting them into the script makes little sense; having the script collect them from a well-known password file relative to $HOME makes more sense. The public key certificates is simply the standard way of dealing with such a well-known password file.

Public key certificates are digitally signed by a Certificate Authority (CA). If you trust that CA, then you must trust the certificates it signed. The trusted CA(s) has to be configured into the Arista switch. Then any client certificate signed by that trusted CA will be accepted by eAPI, but only if the CA directly signed it, that is, a client cannot create "sub-clients" (the CA plays the role of the admin that creates the account for which the certificate stands). Client certificates can also be self-signed, in which case each client certificate has to be configured into the Arista switch as trusted.

The certificate will need to contain the username and its privilege level (a number between 1 and 15) in the "common name" field of the certificate's "subject" field (see openssl command syntax below for more exact details). If a connection with this certificate is accepted, then on the switch it will be accounted against that username and given specified privilege level. Note that this will bypass RADIUS/TACACS+.

If you configure trusted CA/clients, then you also need to configure the HTTPS server's certificate/privateKey using the `management security ssl profile` commands as illustrated below (server keys are no longer auto-generated in this case – once you generate the client's certificate, you might as well generate the server certificate and key). Those certificates/keys are stored in bootflash under `/persist/secure/ssl`, not in the startup-config.

```
myswitch⟩ enable
myswitch# configure
myswitch(config)# !  download the client certificates and server certificate/key
myswitch(config)# copy scp:<username>@<server>//<certificate1-filename> certificate:ca1
myswitch(config)# copy scp:<username>@<server>//<certificate2-filename> certificate:user1
myswitch(config)# copy scp:<username>@<server>//<certificate3-filename> certificate:httpServer
myswitch(config)# copy scp:<username>@<server>//<privateKey3-filename> sslkey:httpServer
myswitch(config)# !  create an ssl profile and add those certs/keys into it
myswitch(config)# management security
myswitch(config-mgmt-security)# ssl profile capi
myswitch(config-mgmt-sec-ssl-profile-eapi)# certificate httpServer key httpServer
myswitch(config-mgmt-sec-ssl-profile-eapi)# trust certificate ca1
myswitch(config-mgmt-sec-ssl-profile-eapi)# trust certificate user1
myswitch(config)# !  now configure eAPI to use that ssl profile
myswitch(config)# management api http-commands
myswitch(config-mgmt-api-http-cmds)# protocol https
myswitch(config-mgmt-api-http-cmds)# protocol https ssl profile capi
myswitch# !  some show commands
myswitch# show management security ssl certificate
myswitch# show management security ssl profile
myswitch# show management security ssl key
myswitch# !  find more commands with:
myswitch# show cli commands all | grep ssl
```

Above we first downloaded certificates and a private key (key is for the https server). Certificates (that contain the public key) go to the `certificate:` filesystem, (private) keys go to the `sslkey:` filesystem. Then we add those certificates/keys into an ssl profile called `capi`, then make command-api use that profile.

A self signed certificate and associated private key (a "pair") can be generated with the `openssl` tool like so: (re-

place the ⟨fields⟩ with actual values)

```
openssl req -new -nodes -x509 -days <number-of-days>
   -subj '/CN=<username> <privilege> <optional-stuff>'
   -out <certificate-filename>
   -keyout <key-filename>
```

You can use the above for generating the `certificate:httpServer` and `sslkey:httpServer` or the `certificate:user1/ca1` used in the example above. In case of the client/user, the key-file is for the client to install in his account for access by tools like wget/browsers (in the same way as a username/password would be). In case of the CA, you (the admin), would keep that key to sign client certificates with.

You can create a self signed certificate per user, and have EOS trust each one, or you can create a CA, have EOS trust just that CA, then sign the user certificates you generate with the (private) key of the CA. In that case, creating the certificate is a 2 step process: you first create a "signing-request" (similar to creating a cert/key pair, but without the "-x509 -days" options), which is then signed in the second step.

```
openssl req -new -nodes
   -subj '/CN=<username> <privilege>'
   -out <signing-request-filename>
   -keyout <user-key-filename>

openssl x509 -req -sha256 -days <valid-for-days>
   -in <signing-request-filename>
   -CA <ca-certificate-filename> -CAkey <ca-key-filename>
   -set_serial <serial-number>
   -out <user-certificate-filename>
```

An eAPI request can be generated like so by using the wget utility: (the –no-check-certificate is required if the server uses a self-signed certificate)

```
wget -no-check-certificate
   -private-key=<key-filename>
   -certificate=<certificate-filename>
   -q -O - https://<server>/command-api -post-data="$(cat <file-with-json-request>)"
```

A simple `<file-with-json-request>` could have this content:

```
{
   "jsonrpc": "2.0",
   "method": "runCmds",
   "params": {
     "version": 1,
     "cmds": [ "show clock" ],
     "format": "json"
   },
   "id": "1"
}
```

1.7 Session Based Authorization

Some systems use 2-factor authentication where RSA is implemented and keys rotate every 30 seconds. It is cumbersome to authenticate using username and password in these systems. Command API requests use basic authentication by default. This results in high overhead on the switch to verify user credentials for each command request. HTTP sessions can be used to reduce the overhead in the above use cases by caching user authentication. Usage of the session mechanism is explained below.

1.7.1 User Login

A user logs in by sending an HTTP POST request to `http[s]://<yourswitch>/login` with an encapsulated JSON user credential.

```
{
   "username":  <user>,
   "password":  <password>,
}
```

The switch will authenticate the user credentials in the request and if successful, send a set cookie response containing a `Session=<sessionId>` field and an expiry of 24 hours. The sessionId is an unique session identifier. On failure, a "401 Unauthorized" HTTP response will be sent in lieu of a cookie.

1.7.2 Command Requests

Subsequent command requests to `http[s]://<yourswitch>/command-api` need to include `Session=<sessionId>` in the cookie header. The format of the command request as well as its response is same as the one using the basic authentication scheme. If the session is invalid, a "401 Unauthorized" response will be sent.

1.7.3 User Logout

A user may logout by sending an HTTP POST request to `http[s]://<yourswitch>/logout` with `Session=<sessionId>` in the cookie header. On success, a "200 OK" response will be sent, otherwise a "400 Bad Request" response will be sent.

1.7.4 Session Validation

Browser-based applications may find it useful to check if a valid session already exists, thereby avoiding a prompt. To do this, send a POST request to `http[s]://<yourswitch>/login` with an empty JSON body: `{}`. If the cookie included in your request exists and contains a valid sessionId, the server will send a "200 OK" HTTP response, otherwise it will reply with a "401 Unauthorized" response.

1.8 Versioning

eAPI models are now revisioned.
This means that if a model is modified in a non-backwards compatible way, then its revision will be bumped up (revisions are numbers, default value is 1).
By default an eAPI request will return revision 1 of the model instance, this ensures that older management software will not suddenly stop working when a switch is upgraded.
If a specific revision is required, then that revision must be specified in the json rpc, like illustrated in this example json request below:

```
{
  "jsonrpc": "2.0",
  "method": "runCmds",
  "params": {
    "version": 1,
    "cmds": [
      "enable",
      { "cmd": "show aliases", "revision": 2 },
      { "cmd": "show interfaces", "revision": 3 },
      "show clock"
    ],
   "format": "json"
  },
  "id": "1"
}
```

1.8.1 Incompatible Model

The following list contains changes that will result in a new revision of a model. In the list below, the term "element" refers to an attribute or submodel.

- Changing the type/format of an element (say, from integer to string)
- Removing mandatory elements
- Adding mandatory elements
- Changing the optionality of an element

Looking at it from the other side, the model changes that can happen without a revision bump can be summed up as:

- Changing help text
- Using a stronger type (from string to any, i.e. number, is compatible)
- Adding/removing optional elements
- Adding/removing an enumerated value
- Obviously: adding a new cli command

Normally, in TLV/schema-less systems (like JSON is), adding new key-value pairs is considered a compatible change, as long as the new pairs are just an "enhancement" that does not affect the meaning of the remaining pairs, since older system will be oblivious to them (they naturally skip over them).
So why is adding a mandatory element non-backwards compatible? Because we are talking from the perspective of the published model.
If a network management developer looks at the latest model and sees that model X is at revision 1 and attribute Y is mandatory, then he will assume Y to be always present, then get a key error when discovering a switch running an older release! The downside is that you need extra effort to get the newer attributes (specify a later revision), but

unless you add code to deal with that extra data, you might as well just continue receiving only the older attributes. If your application can deal with "fuzzy models", then look for "Get Current Revision" further below.

1.8.2 Understanding Revisions And Versions

Do not confuse "revisions" and "versions" as they are not the same. A "revision" applies to a particular CLI command whereas a "version" is global and is internally translated to a specific "revision" for each CLI command in the rpc. At this time, the API remains at version 1, and will do so until many models have progressed to later revisions. Until the version gets a bump, in order to access newer revisions of CLI output, you have to name the revision you desire, per command, or use the "latest" version as documented in the "Accessing a Command's Current Revision" section below. Note that an explicit revision value attached to a command always takes precedence over the version.

Here is how revisions and versions play together.
Assume commands C1 and C2 have shipped with those changes across EOS releases (C3 is new and has no revisions yet – still at revision=1):

Versioning Examples

Command	EOS-Release	eAPI-Version	Command-Revision
C1	4.13.1	1	1
C1	4.13.2	2	2
C1	4.13.3	2	3
C1	4.13.4	3	3
C1	4.13.5	3	4
C2	4.13.1	1	1
C2	4.13.4	3	2
C3	4.13.5	1	1

Then, if querying a switch running Eos-release 4.13.5, we get:

Returned Models

Command	Version-Requested	Revision-Returned
C1	1	1
C1	2	2
C1	3-*	3
C2	1-2	1
C2	3-*	2
C3	1-*	1

If a revision bump occurs without version bump, then, for a given version, you are stuck at the initial revision level: no matter the version, you will never get revision 4 for C1. The only way to see a more up-to-date output (for example C1 at revision 4) is to explicitely ask for that revision of the command, or to request the current revision (see next chapter), which could return anything from the distant future, thus unpredictable.

Note that requiring a version higher than the command knows about will simply return the latest available one.

1.8.3 Accessing a Command's Current Revision

If your code can deal with new output naturally, then you may want to always get output according to the latest revision a switch can provide (its current revision), which is possible by providing the special version value 'latest' (in that case only, the version is a string). For example:

```
{
  "jsonrpc": "2.0",
  "method": "runCmds",
  "params": {
     "version": "latest",
     "cmds": [
        "enable",
        "show ip interfaces",
     ],
     "format": "json"
  },
  "id": "1"
}
```

1.8.4 More Documentation On Revisions

Since there is now infrastructure in place during the software development cycle to detect changes to models and force the bumping up of revision numbers, thus ensuring that eAPI is a stable and predictable API, we eventually could also publish our per revision "Reference Models", as those are a python structures and thus more formally usable than a web-page or pdf.

Chapter 2

Command Output

All commands are guaranteed to have structured response format, documented here. If an attribute is marked as optional (name enclosed in `[]` brackets), its presence is not guaranteed in the resulting JSON respones.

Config and exec commands, standard response fields (all optional)

`[errors]`	List of strings	If running this command produced any configuration errors, this field will be populated with a list of strings, each representing a discrete error.
`[warnings]`	List of strings	If running this command produced any warnings, this field will be populated with a list of strings, each representing a discrete warning.
`[messages]`	List of strings	Occasionally a non-show command will produce an informative message upon completion. If this happens, this field will be populated with a list of strings, each representing a discrete message.

Each following sub-chapter defines a cli command output, potentially followed by sub-sub-chapters that define the complex types used in the just described cli output (the title of those sub-sub-chapters are the complex type's name). The leftmost column is the attribute name, the middle column is its type, and the rightmost column is its description. Attributes can be of those basic types:

- string
- integer (any length)
- floating point number
- boolean (True or False)
- IPv4 address
- IPv6 address
- MAC address
- interface name
- enumeration (list of names)

and those complex types:

- list: ordered list
- table: unordered key/value list

Enumerations are represented like this: `enum: red | blue | green`. Tables are represented as `table(key)=type`, meaning the table is indexed by `key` and contains rows of type `type`.

2.1 clear security pki certificate rotation ROTATION_ID

[errorMessage]	*string*	Error message if not successful.
rotationId	*string*	Unique rotation ID.
statusCode	*enum: success | invalidRotationId*	Status code.

2.2 dir [...]

revision 2

[urls]	*table(string) = FileUrl* see 2.2.1	File url information.

2.2.1 FileUrl

[entries]	*table(string) = FileEntries* see 2.2.1.1	File entries.
[errorMsg]	*string*	File error message.
[filesystem]	*FileSystemInfo* see 2.2.1.2	File system information.

2.2.1.1 FileEntries

[entries]	*table(string) = FileEntries* see 2.2.1.1	File entries of the current directory.
[errorMsg]	*string*	File error message.
[link]	*string*	File path to which link points to.
[mtime]	*floating point number*	File modification time.
[permissions]	*string*	Permissions for files and directories as 'drwx'.
[size]	*integer*	File size in bytes.

2.2.1.2 FileSystemInfo

freeBytes	*integer*	File system size available.
name	*string*	File system name.
totalBytes	*integer*	File system size.

2.3 export flow tracking cpu-queue tracker TRACKER_NAME buffers FILE_NAME

filePath	*string*	Location of PCAP file containing the buffer contents. Empty on failure.

2.4 ping adaptive-virtual-topology (vrf VRF) (avt AVT) (destination DEST) [...]

avt	*string*	AVT name in which the ping command is being executed.
destVtep	*string*	Destination VTEP IP.
[errorCode] **	*integer*	Error code if any while sending ping requests. **Since: 4.32.2
[errorMessage]	*string*	Error in sending ping requests.
repeat	*integer*	Number of times ping is repeated.
[sequences]	*table(string) = AvtPingSequenceModel* see 2.4.2	Sequence wise detail for every path.
[summary]	*table(string) = AvtPathSummaryModel* see 2.4.1	summary of every ping across every path.
vrf	*string*	VRF name in which the ping command is being executed.

2.4.1 AvtPathSummaryModel

[labelStack]	*list of integer*	LabelStack of the multihop path.
lossRate	*floating point number*	loss rate for the path.
onewayTimeAvg	*floating point number*	Average oneway time for packets along the path.
onewayTimeMax	*floating point number*	Maximum oneway time for a packet along the path.
onewayTimeMdev	*floating point number*	Standard deviation of oneway times for packets along the path.
onewayTimeMin	*floating point number*	Minimum oneway time for a packet along the path.
pktsRx	*integer*	Packets received along the path.
pktsTx	*integer*	Packets sent along the path.
rttAvg	*floating point number*	Average RTT for each packet along the path.
rttMax	*floating point number*	Maximum RTT for a packet along the path.
rttMdev	*floating point number*	Standard deviation of RTT for packets along the path.
rttMin	*floating point number*	Minimum RTT for a packet along the path.
totalTime	*floating point number*	Total time taken to ping along the path.

2.4.2 AvtPingSequenceModel

paths	*list of AvtPathSequenceModel* see 2.4.2.1	Avt ping details for a sequence on a path.

2.4.2.1 AvtPathSequenceModel

[errorCode]	*integer*	Error code if any error happens along the path.
[errorMessage]	*string*	Error message, if any error happens along the path.
onewayTime	*floating point number*	oneway time for the packet to reach destination.
pathId	*string*	Path ID.
rtt	*floating point number*	RTT for the packet.
ttlRemaining	*integer*	TTL remaining in the request packet before it was received at the destination.

2.5 ping mpls bgp labeled-unicast (ip (IP_ADDR_PREFIX | (IP_PREFIX_PREFIX | (IP_PREFIX_PREFIX_ADDR IP_PREFIX_PREFIX_MASK))) | (ipv6 (IP6_ADDR_PREFIX6 | IP6_PREFIX_PREFIX6)) [...]

revision 2

`ping`	*MplsPingHdr* see 2.5.1	Ping request.

2.5.1 MplsPingHdr

`[bgpLuModel]` **	*BgpLuModel* see 2.5.1.1	MPLS BGP LU ping model. **Since: 4.30.0
`[errInfo]`	*list of ErrInfo* see 2.5.1.2	Errors.
`[genericModel]` **	*GenericModel* see 2.5.1.3	MPLS generic ping model. **Since: 4.30.0
`interval`	*integer*	Ping intervals.
`[p2mpLspStats]` **	*table(string) = MplsPingP2mpLspModel* see 2.5.1.4	MPLS P2MP ping stats for LSPs keyed by string representation of each LSP ID. **Since: 4.33.2
`[p2mpLspVia]` **	*table(string) = MplsPingP2mpLspModel* see 2.5.1.4	MPLS P2MP ping LSPs keyed by string representation of each LSP ID. **Since: 4.33.2
`protocol`	*enum: raw | ldp | segment-routing | mldp | pwLdp | rsvp | vpn | bgpLu | generic | nexthop-group-tunnel | static | nexthop-group | SrTePolicy | rsvp-p2mp | segment-routing-ospf*	Protocol.
`[pwLdpModel]` **	*PwLdpModel* see 2.5.1.5	MPLS PW LDP ping model. **Since: 4.30.1
`[rsvpModel]` **	*RsvpModel* see 2.5.1.6	MPLS RSVP ping model. **Since: 4.30.0
`[rsvpP2mpPing]` **	*RsvpP2mpPingModel* see 2.5.1.7	MPLS RSVP P2MP ping model. **Since: 4.33.2
`[srModel]` **	*SrModel* see 2.5.1.8	MPLS SR ping model. **Since: 4.30.0
`statsModel`	*list of MplsPingVia* see 2.5.1.4.1	MPLS ping statistics.
`timeout`	*integer*	Timeout for ping.
`viaModel`	*list of MplsPingVia* see 2.5.1.4.1	MPLS ping vias.
`[vpnModel]`	*VpnModel* see 2.5.1.9	MPLS VPN ping model.

2.5.1.1 BgpLuModel

`prefix`	*string*	Destination.

2.5.1.2 ErrInfo

error	*string*	Error encountered when cmd issued.

2.5.1.3 GenericModel

prefix	*string*	Destination.

2.5.1.4 MplsPingP2mpLspModel

[extTunnelId]	*string*	Extended Tunnel ID for P2MP LSP.
[lspId]	*integer*	LSP ID for P2MP LSP.
[p2mpId]	*integer*	P2MP ID for P2MP LSP.
[tunnelId]	*integer*	Tunnel ID for P2MP LSP.
[tunnelSenderAddr]	*string*	Address of pinging node.
[vias]	*table(string) = MplsPingVia* see 2.5.1.4.1	MPLS P2MP ping vias keyed by string representation of each via.
[viasStats]	*table(string) = MplsPingVia* see 2.5.1.4.1	MPLS P2MP ping statistics for vias keyed by string representation of each via.

2.5.1.4.1 MplsPingVia

[interface]	*string*	Interface name.
[labelStack]	*list of integer*	Label stack.
[lspId] **	*integer*	RSVP tunnel LSP ID. **Since: 4.30.0
[nextHopIp]	*string*	NextHop IP.
[nhgTunnelEntryIndex]	*integer*	Nexthop tunnel entry index.
[p2mpPingReply] **	*table(string) = MplsPingReply or NULL* see 2.5.1.4.1.1	MPLS ping replies keyed by destination. **Since: 4.33.2
[p2mpPingStats] **	*MplsPingStatisticsSummary* see 2.5.1.4.1.2	MPLS ping statistics. **Since: 4.33.2
[pingReply]	*MplsPingReply* see 2.5.1.4.1.1	MPLS reply packet details.
[pingStats]	*MplsPingStatisticsSummary* see 2.5.1.4.1.2	MPLS ping statistics.
resolved	*boolean*	Resolution status of tunnel/via.
[subTunnelId] **	*integer*	RSVP sub tunnel ID. **Since: 4.30.0

2.5.1.4.1.1 MplsPingReply

[errorSubTlvMap] **	*list of integer*	Error sub Tlv Map. **Since: 4.29.2
[errorTlvMap] **	*list of integer*	Error Tlv Map. **Since: 4.29.2
oneWayDelay **	*integer*	One way delay time for packet in microseconds. **Since: 4.29.1
replyHost	*string*	Reply host address.

retCode	*enum: premTermination* | *usIntfUnknown* | *reservedRetCode* | *labelMappingMismatch* | *lblSwitchedFecChange* | *seeDdmTlv* | *labelSwitchedAtStackDep* | *noMappingForFec* | *dsMappingMismatch* | *noLabelEntryAtStackDep* | *labelSwitchedNoMplsFwd* | *protocolIntfMismatch* | *malFormEchoRequest* | *repRouterEgress* | *tlvNotUnderstood* | *noRetCode*	Return code.
roundTripTime	*integer*	RoundTrip time for packet in milliseconds.
roundTripTimeUs **	*integer*	Round Trip time for packet in microseconds. **Since: 4.29.1
sequence	*integer*	Sequence number.

2.5.1.4.1.2 MplsPingStatisticsSummary

[mplsStatistics]	*list of MplsPingStatistics* see 2.5.1.4.1.3	MPLS ping statistics details.
[mplsStatisticsP2mp] **	*table(string) = MplsPingStatistics or NULL* see 2.5.1.4.1.3	MPLS P2MP ping statistics details keyed by destination. **Since: 4.33.2
packetLoss	*integer*	Percentage of packets lost.
packetsReceived	*integer*	Packets received.
packetsTransmitted	*integer*	Packets transmitted.
replyTime	*integer*	Reply timestamp time.

2.5.1.4.1.3 MplsPingStatistics

destination	*string*	Reply host address.
oneWayDelayAvg **	*integer*	Average one way delay in microseconds. **Since: 4.29.1
oneWayDelayMax **	*integer*	Maximum one way delay in microseconds. **Since: 4.29.1
oneWayDelayMin **	*integer*	Minimum one way delay in microseconds. **Since: 4.29.1
packetsReceived	*integer*	Packets received from destination.
roundTripTimeAvg	*integer*	Average round trip time in milliseconds.
roundTripTimeAvgUs **	*integer*	Average round trip time in microseconds. **Since: 4.29.1
roundTripTimeMax	*integer*	Maximum round trip time in milliseconds.
roundTripTimeMaxUs **	*integer*	Maximum round trip time in microseconds. **Since: 4.29.1

roundTripTimeMin	*integer*	Minimum round trip time in milliseconds.
roundTripTimeMinUs **	*integer*	Minimum round trip time in microseconds. **Since: 4.29.1

2.5.1.5 PwLdpModel

pwCCType	*enum: ra | ccTypeUnset | ttlExp | cw*	Pseudowire CC types.
pwId	*string*	Pseudowire ID.
pwLabel	*integer*	Pseudowire VC label.
pwLdpName	*string*	Pseudowire LDP name.
pwNeighbor	*string*	Neighbor IP address.

2.5.1.6 RsvpModel

[lspId]	*integer*	LSP Id.
[prefix]	*string*	Destination.
[session]	*string*	Rsvp session name or session Id.
[subTunnelId]	*integer*	Rsvp subtunnel Id.
[tunnel]	*string*	Rsvp tunnel name.

2.5.1.7 RsvpP2mpPingModel

[extTunnelId]	*string*	Extended Tunnel ID for P2MP session.
[lspId]	*integer*	LSP ID.
[p2mpId]	*integer*	P2MP ID for P2MP session.
[responderAddr]	*string*	Node Responder Address.
[sessionName]	*string*	RSVP P2MP session name or session ID.
[tunnel]	*string*	RSVP P2MP tunnel name.
[tunnelId]	*integer*	Tunnel ID for P2MP session.

2.5.1.8 SrModel

[algorithm]	*string*	Algorithm.
[igpProtocolType] **	*string*	Segment Routing IGP Protocol. **Since: 4.30.2
prefix	*string*	Destination.

2.5.1.9 VpnModel

prefix	*string*	Destination.
rd	*string*	Route Distinguisher.

2.6 ping mpls bgp vpn (vrf (VRF | default)) (ip PREFIX) | (ipv6 PREFIX6) [...]

revision 2

see 2.5

2.7 ping mpls generic ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK)) [...]

revision 2

see 2.5

2.8 ping mpls ldp ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK)) [...]

revision 2

see 2.5

2.9 ping mpls p2mp mldp ROOTADDR ((lsp-id OPQVAL) | (multicast ipv4 SOURCEADDR GROUPADDR)) [...]

revision 2

see 2.5

2.10 ping mpls pseudowire ((ldp PW_NAME) | (vpls ldp INSTANCE_NAME group GROUP_NAME NEIGHBOR_ADDRESS)) [...]

revision 2

see 2.5

2.11 ping mpls rsvp session ((id SESSION_ID) | (name SESSION_NAME)) [...]

revision 2

see 2.5

2.12 ping mpls rsvp tunnel TUNNEL_NAME [...]

revision 2

see 2.5

2.13 ping mpls segment-routing ((((ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK))) | (ipv6 IPV6_ADDRESS) | (isis ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK))) | (isis ipv6 IPV6_ADDRESS))) | (ospf ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK))))) [...]

revision 2

see 2.5

2.14 reset management dmf controller sync

controllerDigest	*string*	SHA-256 digest of the config received from the controller.
runningConfigDigest	*string*	SHA-1 digest of the running-config of the switch.

2.15 security pki certificate generate signing-request rotation ssl profile PROFILE_NAME key generate ((rsa RSA_BIT_LENGTH) | (ecdsa EC_CURVE_NA)) [...]

[csr]	*string*	PEM encoded CSR.
[errorMessage]	*string*	Error message if not successful.
[rotationId]	*string*	Unique rotation ID.
statusCode	*enum: success* | *requestFailed*	Status code.

2.16 security pki certificate rotation commit ROTATION_ID

[errorMessage]	*string*	Error message if not successful.
rotationId	*string*	Unique rotation ID.
statusCode	*enum: success* | *certDoesNotExist* | *requestFailed* | *certExpired* | *certNotYetValid* | *invalidRotationId* | *invalidSslProfile*	Status code.

2.17 security pki certificate rotation commit ssl profile PROFILE_NAME [...]

[errorMessage]	*string*	Error message if not successful.
statusCode	*enum: success* | *invalidCert* | *invalidKey* | *requestFailed* | *certDoesNotMatchKey* | *certExpired* | *certNotYetValid* | *invalidSslProfile*	Status code.

2.18 security pki certificate rotation import ROTATION_ID

[errorMessage]	*string*	Error message if not successful.
rotationId	*string*	Unique rotation ID.
statusCode	*enum: success* | *invalidCert* | *requestFailed* | *certExpired* | *certDoesNotMatchKey* | *invalidRotationId*	Status code.

2.19 session peer-supervisor CMD

[output]	*string*	Output of the CLI command ran on the peer supervisor.

2.20 show ((ip bgp neighbors) | (ipv6 bgp peers)) ((received-routes) | (received-routes ((regex REGEX) | ((community { (AANN_FORMAT | COMMUNITY_ENUM | COMMUNITY_U32) })) | (access-list AS_PATH_LIST_NAME) | ((IPV4_ADDR | IPV6_ADDR)) | ((IPV4_ADDR_MASK | IPV6_ADDR_MASK))))) [...]

revision 3

vrfs	*table(string) = BgpRouteHeader* see 2.20.1	Per VRF BGP route summary.

2.20.1 BgpRouteHeader

asn	*string*	Autonomous System Number.
bgpRouteEntries	*table(string) = BgpRouteEntry* see 2.20.1.1	Dictionary of BGP route entries indexed by the route prefix. For SR-TE SAFI, the index is in the format: 'Endpoint|Color|Distinguisher'.
[currentSeqNum]	*integer*	Current route sequence number.
[lastProcessedSeqNum]	*integer*	Last route sequence number acknowledged.
routerId	*IPv4 address*	BGP Router Identity.
vrf	*string*	VRF name.

2.20.1.1 BgpRouteEntry

address	*IP address*	Route address; For SR-TE SAFI, this is same as srTeEndpoint.
[bgpAdvertisedPeerGroups]	*table(string) = BgpRouteAdvertisedPeerListEntry* see 2.20.1.1.1	List of peers this route is advertised to indexed by peer-group name.
[bgpAdvertisedPeers]	*BgpRouteAdvertisedPeerListEntry* see 2.20.1.1.1	List of peers this route is advertised to.
bgpRoutePaths	*list of BgpRoutePath* see 2.20.1.1.2	List of BGP route ECMP paths.
[dpsAvtId] **	*integer*	Adaptive virtual topology ID of DPS policy. **Since: 4.28.2
[dpsAvtName] **	*string*	Adaptive virtual topology of DPS policy. **Since: 4.28.2
[dpsRouter] **	*IPv4 address*	Source router of DPS policy. **Since: 4.28.2
[dpsVni] **	*integer*	VNI of DPS policy. **Since: 4.28.2
[dpsVrf] **	*string*	VRF of DPS policy. **Since: 4.28.2
maskLength	*integer*	Route mask length.

[notUcmpEligibleReason]	*enum: noLinkBWOnAllPaths | maxUcmpExceeded*	Used when ECMP could be converted to UCMP. NoLinkBWOnAllPaths - All contributing paths do not have link bandwidth available maxUcmpExceeded - Max UCMP configuration is less than or equal to the number of nexthops preventing UCMP application effectively.
[routePriority] **	*enum: medium | high | low*	Route processing priority. **Since: 4.32.1
[srTeColor]	*integer*	Color of SR TE policy.
[srTeDistinguisher]	*integer*	Distinguisher of SR TE policy.
[srTeEndpoint]	*IP address*	Endpoint address of SR TE policy.
[totalAdvertisedPeers]	*integer*	Number of peers this route is advertised to.
[totalPaths]	*integer*	Total number of paths for this route.

2.20.1.1.1 BgpRouteAdvertisedPeerListEntry

peerList	*list of string*	List of peers the route is advertised to.

2.20.1.1.2 BgpRoutePath

[aigpDistance] **	*integer*	Accumulated IGP Distance for the route. **Since: 4.24.1
[aigpMetric] **	*integer*	Accumulated IGP metric for the route. **Since: 4.24.1
asPathEntry	*BgpRouteASPathEntry* see 2.20.1.1.2.1	AS path information.
[localPreference]	*integer*	I-BGP Local preference indicator.
[med]	*integer*	Multi Exit Discriminator for the route.
[nextHop]	*string*	Route next hop address.
[orrWinners] **	*list of string*	List of ORR positions for which this path is best. **Since: 4.27.0
[peerEntry] **	*BgpRoutePeerEntry* see 2.20.1.1.2.43	Peer information for the route. **Since: 4.21.3

reasonNotBestpath	*enum: clusterlistLenTB* | *ebgp* | *localPath* | *macMobilityEsi* | *rtMembershipDefault-Originate* | *peerAddress* | *rrClient* | *igpDomainType* | *nexthopVrf* | *weight* | *igpPreference* | *routerId* | *neighborMultipath* | *macMobilityStickyMac* | *origin* | *age* | *noBest* | *macMobilitySeqNum* | *igpMetric* | *macMobilityRemoteDomain* | *originAsValidity* | *routeUnusable* | *noLocalLabel* | *med* | *ageTB* | *aspathLength* | *originatorIdOrRouterId* | *macMobilityTep-AddrdomainPathLength* | *noReason* | *infMed* | *ecmpFast* | *routeNotReady* | *localpref* | *originatorIdTB* | *pathId* | *invalid* | *clusterlistLen* | *routerIdTB* | *aigp* | *redist* | *nhgTunnelEcmpDisabled* | *aspathDetails* | *preference* | *originatorId*	Reason route was not selected as BGP best path.
[routeDetail]	*BgpRouteDetailEntry* see 2.20.1.1.2.2	Route details.
routeType	*BgpRouteTypeEntry* see 2.20.1.1.2.44	Route type.
[tag] **	*integer*	Tag for this route. **Since: 4.26.0
[timestamp]	*integer*	UTC seconds since epoch when the route was received. Only returned with 'show ip bgp detail'.
[weight]	*integer*	Weight for the route.

2.20.1.1.2.1 BgpRouteASPathEntry

[asPath]	*string*	AS path string (if absent, then the route was originated locally).
asPathType	*enum: Internal* | *Local* | *Confed-External* | *Invalid* | *External*	AS path type: Internal - originated by I-BGP External - originated by E-BGP Confed-External - originated by a E-BGP confederation Local - originated locally Invalid - AS path is invalid.

2.20.1.1.2.2 BgpRouteDetailEntry

[aggregator]	*string*	Aggregator of the route.
[aigpDistance] **	*integer*	Accumulated IGP Distance for the route. **Since: 4.24.1
[aigpMetric] **	*integer*	Accumulated IGP metric for the route. **Since: 4.24.1
[bgpContributors]	*list of BgpRouteContributor* see 2.20.1.1.2.28	List of contributors to this aggregated route.
[bgpLsLinkAttributes] **	*BgpLsLinkAttributes* see 2.20.1.1.2.3	Attributes a BGP Link State link. **Since: 4.24.2
[bgpLsNodeAttributes] **	*BgpLsNodeAttributes* see 2.20.1.1.2.10	Attributes of a BGP Link State node. **Since: 4.24.2
[bgpLsPrefixAttributes] **	*BgpLsPrefixAttributes* see 2.20.1.1.2.22	Attributes of a BGP Link State prefix. **Since: 4.24.2
[clusterList]	*string*	Cluster list for the route.
communityList	*list of string*	List of communities for this route.
[domainPath] **	*list of string*	Domain path attribute. **Since: 4.23.0
extCommunityList	*list of string*	List of extended communities for this route.
[extCommunityListRaw] **	*list of integer*	List of raw extended communities for this route. **Since: 4.25.2
[fieldSetName] **	*string*	Field Set assigned to the route. **Since: 4.27.1
[igpMetric]	*integer*	IGP metric.
[isLeaked] **	*boolean*	Route leaked from a different VRF. **Since: 4.23.2
[labelStack]	*list of integer*	MPLS label stack information.
largeCommunityList **	*list of string*	List of large communities for this route. **Since: 4.21.3
[localLabel]	*integer*	Local MPLS label.
[nextHopVrfName] **	*string*	VRF Name of the nexthop for the route. **Since: 4.21.3
origin	*enum: Incomplete | Igp | Egp*	Route origin.
[originator]	*string*	Router ID of the originator of this route.
[pendingTimeToAdv]	*floating point number*	Timestamp of route advertisement.
[pmsiTunnel] **	*PmsiTunnel* see 2.20.1.1.2.38	P-Multicast Service Interface Tunnel Attribute. **Since: 4.23.2
[recmpEligible] **	*boolean*	The route is RECMP eligible. **Since: 4.29.1
recvdFromRRClient	*boolean*	Route received from route reflector client.
[redistributionProtocol]	*enum: Is-Is-Sr | BGP-Aggregate | Eos-Sdk | Connected | Static | unknown | Bgp | Ldp | Dynamic | Rip | Ospf | Ospf3 | Is-Is*	Protocol from which the route was redistributed into BGP.
[remoteLabel]	*EncapLabel* see 2.20.1.1.2.34	Remote label.

[rfdFlaps] **	*integer*	Number of path flaps. **Since: 4.29.2
[rfdPenalty] **	*integer*	Route flap damping penalty. **Since: 4.29.2
[rxPathId]	*integer*	Received path ID of this route.
[rxSafi]	*string*	Received SAFI of this route.
[seqNumber]	*integer*	Route sequence number.
[srLabelIndex]	*integer*	Prefix SID Label Index.
[srTeTunnelEncap]	*BgpSrTePolicyTunnelEncap* see 2.20.1.1.2.29	Bgp Segment Routing Policy Tunnel Encapsulation Attribute.
tunnelRibEligible	*boolean*	Route eligible to be installed in Tunnel RIB.
[txPathId]	*integer*	Advertised path ID for this route.

2.20.1.1.2.3 BgpLsLinkAttributes

[administrativeGroup]	*integer*	Administrative Group(color) of link.
[administrativeGroups-Extended] **	*list of integer*	Extended Administrative Group (color) of Link. **Since: 4.33.2
[bgpPeerNodeSid] **	*BgpLsSrPeerNodeSid* see 2.20.1.1.2.6	SR Peer Node SID. **Since: 4.33.0
[dpsLinkAttributes] **	*DpsLinkAttributes* see 2.20.1.1.2.9	DPS Link Attributes Information. **Since: 4.28.2
igpMetric	*integer*	IGP metric of link.
[localIpv4RouterId]	*IPv4 address*	IPv4 Router ID of local node.
[localIpv6RouterId]	*IPv6 address*	IPv6 Router ID of local node.
[maxLinkBw]	*integer*	Maximum link bandwidth (bps).
[maxReservableLinkBw]	*integer*	Maximum bandwidth (bps) that can be reserved on link.
[remoteIpv4RouterId]	*IPv4 address*	IPv4 Router ID of remote node.
[remoteIpv6RouterId]	*IPv6 address*	IPv6 Router ID of remote node.
[srAdjacencySids]	*list of BgpLsSrAdjacencySid* see 2.20.1.1.2.4	List of SR Adjacency SIDs.
[srlgIds]	*list of integer*	Link SRLG values.
[teDefaultMetric]	*integer*	Traffic engineering metric of link.
unknownTlvs **	*list of BgpLsUnknownTlv* see 2.20.1.1.2.8	List of unknown Link Path Attribute TLVs. **Since: 4.30.1
[unreservedBw]	*table(string) = integer*	Unreserved bandwith(bps) keyed by priority.

2.20.1.1.2.4 BgpLsSrAdjacencySid

flags	*BgpLsSrAdjSidFlags* see 2.20.1.1.2.5	SR Adjacency SID Flags.
sid	*integer*	SR Adjacency Index/Label SID.
weight	*integer*	Weight of the Adj-SID for load balancing.

2.20.1.1.2.5 BgpLsSrAdjSidFlags

adjacencySet	*boolean*	SID refers to set of adjacencies and may also be assigned to other adjacencies.
backup	*boolean*	SID is eligible for protection such as using IPFRR or MPLS-FRR.
ipv6	*boolean*	SID is used for forwarding IPv6 traffic.
local	*boolean*	Value/index carried by SID has local significance.
persistent	*boolean*	SID is persistent across router restart/interface flap.
value	*boolean*	SID carries a value instead of an index.

2.20.1.1.2.6 BgpLsSrPeerNodeSid

flags	*BgpLsSrPeerNodeSidFlags* see 2.20.1.1.2.7	SR Peer Node SID Flags.
sid	*integer*	SR Peer Node Index/Label SID.
weight	*integer*	Weight of the Peer Node SID for load balancing.

2.20.1.1.2.7 BgpLsSrPeerNodeSidFlags

backup	*boolean*	SID is eligible for protection such as using IPFRR or MPLS-FRR.
local	*boolean*	Value/index carried by the SID has local significance.
persistent	*boolean*	SID is persistent across router restart or BGP session flap.
value	*boolean*	SID carries a value instead of an index.

2.20.1.1.2.8 BgpLsUnknownTlv

tlvLen	*integer*	Unknown TLV Length.
tlvType	*integer*	Unknown TLV Type.
tlvValue **	*string*	Unknown TLV Value. **Since: 4.31.0

2.20.1.1.2.9 DpsLinkAttributes

[pathAvailableCapacity] **	*integer*	DPS Path available capacity (mbps). **Since: 4.33.0
[pathJitter]	*integer*	DPS Path Jitter (microseconds).
[pathLatency]	*integer*	DPS Path Latency (microseconds).
[pathLossRate]	*integer*	DPS Path Loss Rate (percentage).
[pathMtu]	*integer*	DPS Path MTU.
[pathTotalCapacity] **	*integer*	DPS Path total capacity (mbps). **Since: 4.33.0
[segmentLabel]	*integer*	DPS Segment Label.

2.20.1.1.2.10 BgpLsNodeAttributes

[dpsNodeAttributes] **	*DpsNodeAttributes* see 2.20.1.1.2.13	DPS Node Attributes Information. **Since: 4.28.2
flags	*BgpLsNodeFlags* see 2.20.1.1.2.12	Node flags.
flexAlgoDefinitions **	*table(numeric string) = FlexAlgoModel* see 2.20.1.1.2.15	Dictionary of flexible algorithm definitions keyed by flex algo number. **Since: 4.31.1
[ipv4RouterId]	*IPv4 address*	IPv4 router ID of node.
[ipv6RouterId]	*IPv6 address*	IPv6 router ID of node.
isisAreaIds	*list of string*	List of IS-IS area identifiers.
multiTopologies **	*list of BgpLsMultiTopologyId* see 2.20.1.1.2.11	List of MultiToplogy IDs. **Since: 4.31.2
nodeMsds **	*list of MsdModel* see 2.20.1.1.2.16	List of Node MSDs. **Since: 4.28.1
[nodeName]	*string*	Symbolic name of node.
[srCapabilities]	*SrCapabilityModel* see 2.20.1.1.2.17	SR Capabilities.
[srlb]	*SrlbModel* see 2.20.1.1.2.20	SR Local Block Information.
unknownTlvs **	*list of BgpLsUnknownTlv* see 2.20.1.1.2.8	List of unknown Node Path Attribute TLVs. **Since: 4.30.1

2.20.1.1.2.11 BgpLsMultiTopologyId

attached	*boolean*	Topology is attached to another IS-IS area.
overloaded	*boolean*	Topology is overloaded.
topologyId	*integer*	Multi-Topology ID.
[topologyName]	*string*	String representation of the Multi-Topology ID.

2.20.1.1.2.12 BgpLsNodeFlags

isisAttached	*boolean*	IS-IS node is attached to L2 node in a different area.
isisOverload	*boolean*	IS-IS node is overloaded.

2.20.1.1.2.13 DpsNodeAttributes

[avtIds]	*list of DpsAvtIdsModel* see 2.20.1.1.2.14	DPS AVT ID.
[regionId]	*integer*	DPS Region ID.
role	*enum: region transit | unknown | edge | zone transit | pathfinder*	DPS Role.
[siteId]	*integer*	DPS Site ID.
[zoneId] **	*integer*	DPS Zone ID. **Since: 4.29.0

2.20.1.1.2.14 DpsAvtIdsModel

dpsAvtId	*integer*	DPS AVT ID.
dpsAvtVni	*integer*	DPS AVT VNI.

2.20.1.1.2.15 FlexAlgoModel

[calcType]	*enum: sspf | spf*	FAD calculation type.
calcTypeValue	*integer*	FAD calc type value.
excludeGroups	*list of integer*	FAD exclude admin groups.
excludeSrlgs	*list of integer*	FAD exclude shared risk link groups.
includeAllGroups	*list of integer*	FAD include all admin groups.
includeAnyGroups	*list of integer*	FAD include any admin groups.
[metricType]	*enum: minDelay | igpMetric | teMetric*	FAD metric type.
metricTypeValue	*integer*	FAD metric type value.
priority	*integer*	FAD priority.

2.20.1.1.2.16 MsdModel

msdType	*integer*	MSD type.
msdValue	*integer*	MSD value.

2.20.1.1.2.17 SrCapabilityModel

flags	*SrCapabilityFlags* see 2.20.1.1.2.18	SR Capability Flags.
srCapabilitySrgb	*list of SrCapabilitySrgb* see 2.20.1.1.2.19	Segment Routing Global Blocks.

2.20.1.1.2.18 SrCapabilityFlags

mplsV4	*boolean*	SR capability MPLS IPv4 Flag.
mplsV6	*boolean*	SR capability MPLS IPv6 Flag.

2.20.1.1.2.19 SrCapabilitySrgb

srgbBase	*integer*	SRGB base.
srgbRange	*integer*	SRGB range.

2.20.1.1.2.20 SrlbModel

srlbRanges	*list of SrlbRange* see 2.20.1.1.2.21	Segment Routing Local Blocks.

2.20.1.1.2.21 SrlbRange

srlbBase	*integer*	SRLB base.
srlbRange	*integer*	SRLB range.

2.20.1.1.2.22 BgpLsPrefixAttributes

flags	*BgpLsPrefixFlags* see 2.20.1.1.2.23	Prefix flags.
[metric]	*integer*	Metric of prefix as known in the IGP topology.
[srPrefixSid]	*BgpLsSrPrefixSid* see 2.20.1.1.2.24	SR Prefix SID.
[srRange] **	*BgpLsSrRange* see 2.20.1.1.2.26	SR Range TLV. **Since: 4.32.0
unknownTlvs **	*list of BgpLsUnknownTlv* see 2.20.1.1.2.8	List of unknown Prefix Path Attribute TLVs. **Since: 4.30.1

2.20.1.1.2.23 BgpLsPrefixFlags

isisDown	*boolean*	A prefix has been leaked from a higher level to a lower level.

2.20.1.1.2.24 BgpLsSrPrefixSid

algorithm	*integer*	Algorithm identifier to compute reachability of prefix.
flags	*BgpLsSrPrefixFlags* see 2.20.1.1.2.25	SR Prefix SID Flags.
sid	*integer*	SR Prefix Index/Label SID.

2.20.1.1.2.25 BgpLsSrPrefixFlags

explicitNull	*boolean*	Upstream neighbor must replace with an Explicit NULL value SID before sending packet.
local	*boolean*	Value/index carried by SID has local significance.
noPhp	*boolean*	Penultimate hop must not pop SID before sending packet to advertising node.
nodeSid	*boolean*	SID refers to the router identified by the prefix, typically attached to router loopback address.
readvertised	*boolean*	Corresponding prefix has been re-advertised from another level or redistribution.
value	*boolean*	SID carries a value instead of an index.

2.20.1.1.2.26 BgpLsSrRange

baseSrPrefixSid	*BgpLsSrPrefixSid* see 2.20.1.1.2.24	Prefix SID mapping information.
flags	*BgpLsSrRangeFlags* see 2.20.1.1.2.27	SR Range TLV flags.
prefixCount	*integer*	Range size, carry the number of prefixes that are covered by the advertisement.

2.20.1.1.2.27 BgpLsSrRangeFlags

isisAddressFamily	*boolean*	The prefix SIDs in the range refer to IPv6 prefixes, otherwise they refer to IPv4 prefixes.
isisAttached	*boolean*	The prefix SIDs in the range are directly connected to their originators.
isisFlood	*boolean*	The prefix SIDs in the range should be flooded across the entire routing domain.
isisLeaked	*boolean*	The prefix SIDs in the range have been leaked from Level-2 to Level-1, and must not be leaked from Level-1 to Level-2.
isisMirrorContext	*boolean*	The prefix SIDs in the range correspond to a mirrored context.

2.20.1.1.2.28 BgpRouteContributor

[asPath]	*string*	AS path string (if absent, then the route was originated locally).
communities	*list of string*	List of communities for the contributor.
contributorAddr	*IP address*	Contributor address.
contributorMaskLen	*integer*	Contributor mask length.
extCommunities	*list of string*	List of extended communities for the contributor.
[extCommunityListRaw] **	*list of integer*	List of raw extended communities for the contributor. **Since: 4.26.0
largeCommunities **	*list of string*	List of large communities for the contributor. **Since: 4.21.3
[nlri] **	*IP address prefix*	Contributor prefix. **Since: 4.26.0
origin	*enum: Incomplete* | *Igp* | *Egp*	Contributor Route origin.
[redistProtocol]	*enum: Is-Is-Sr* | *BGP-Aggregate* | *unknown* | *Connected* | *Static* | *Bgp* | *Ldp* | *Dynamic* | *Rip* | *Ospf* | *Ospf3* | *Is-Is*	Protocol from which the contributor was learned.

2.20.1.1.2.29 BgpSrTePolicyTunnelEncap

[bindingSid]	*BgpSrTePolicyBindingSid* see 2.20.1.1.2.30	Binding Segment Identifier.
[enlp] **	*BgpSrTePolicyEnlp* see 2.20.1.1.2.31	Explicit null label policy. **Since: 4.23.0
[preference]	*integer*	Preference of the SR Policy.
segmentLists	*list of BgpSrTePolicySegmentList* see 2.20.1.1.2.32	Segment lists.

2.20.1.1.2.30 BgpSrTePolicyBindingSid

bindingSidType	*enum: mpls | ipv6*	Binding Segment Identifier Type.
[mplsLabelSid]	*integer*	Binding Segment Identifier Value in the form of MPLS Label.

2.20.1.1.2.31 BgpSrTePolicyEnlp

enlpType	*enum: unknown | ipv4 | none | ipv4AndIpv6 | ipv6*	Explicit null label policy type.
value	*integer*	Explicit null label policy value.

2.20.1.1.2.32 BgpSrTePolicySegmentList

[availableCapacity] **	*integer*	Available capacity of the path in Mbps. **Since: 4.32.1
[jitter] **	*floating point number*	Jitter of the path in msecs. **Since: 4.28.2
[latency] **	*floating point number*	Latency of the path in msecs. **Since: 4.28.2
[load] **	*floating point number*	load of the path in percentage. **Since: 4.32.1
[lossRate] **	*floating point number*	Loss rate of the path in percentage. **Since: 4.28.2
[mtu] **	*integer*	Maximum transmission unit of the path in bytes. **Since: 4.28.2
[priority] **	*integer*	Priority of the path. **Since: 4.29.0
segments	*list of BgpSrTePolicySegment* see 2.20.1.1.2.33	Segments that make up the segment list.
[totalCapacity] **	*integer*	Total capacity of the path in Mbps. **Since: 4.32.1
[weight]	*integer*	Weight of the segment list.

2.20.1.1.2.33 BgpSrTePolicySegment

[mplsLabelSid]	*integer*	Segment Identifier in the form of MPLS Label.

2.20.1.1.2.34 EncapLabel

Could also be an instance of:
LocalEncapLabel 2.20.1.1.2.37

encapType	*enum: VXLAN | SRv6 | MPLS*	Encapsulation type.
[srv6Sid] **	*Srv6Sid* see 2.20.1.1.2.35	SRv6 SID. **Since: 4.28.2
value	*string*	Label value.

2.20.1.1.2.35 Srv6Sid

behavior	*enum: endDt6 | unknown | endDt4 | endDx4 | end | endDx6 | endX | endDt46*	SID behavior.
[flavors]	*Srv6SidFlavorFlags* see 2.20.1.1.2.36	SID flavors.
sid	*IP address prefix*	SID value (IPv6 prefix).

2.20.1.1.2.36 Srv6SidFlavorFlags

[nextCsid]	*boolean*	NEXT-CSID flavor.
[nextOnlyCsid] **	*boolean*	NEXT-ONLY-CSID flavor. **Since: 4.30.0
[psp]	*boolean*	Penultimate Segment Pop (PSP) of the SRH flavor.
[usd]	*boolean*	Ultimate Segment Decapsulation (USD) flavor.
[usp]	*boolean*	Ultimate Segment Pop (USP) of the SRH flavor.

2.20.1.1.2.37 LocalEncapLabel

encapType	*enum: VXLAN | SRv6 | MPLS*	Encapsulation type.
labelAllocationMode **	*enum: vrfLabelAllocation | nexthopLabelAllocation | receivedVpnRoute-Allocation*	Label allocation scheme. **Since: 4.34.2
[srv6Sid] **	*Srv6Sid* see 2.20.1.1.2.35	SRv6 SID. **Since: 4.28.2
value	*string*	Label value.

2.20.1.1.2.38 PmsiTunnel

leafInformationRequired	*boolean*	Leaf information required.
mplsLabel	*integer*	MPLS label.
[tunnelId]	*PmsiTunnelId* see 2.20.1.1.2.39	Tunnel information.

tunnelType	*enum: bidirPimTree* | *ingressReplication* | *unknown* | *bier* | *transportTunnel* | *wildcardTransport* | *mLdpP2mpLsp* | *rsvpTeP2mpLsp* | *pimSmTree* | *pimSsmTree* | *noInfo* | *assistedReplication* | *mLdpMp2mpLsp*	Tunnel technology used to establish PMSI tunnel.

2.20.1.1.2.39 PmsiTunnelId

[ingressReplication]	*IP address*	Replication address.
[mldpP2mp] **	*PmsiMldpTunnelId* see 2.20.1.1.2.40	MLDP P2MP tree information. **Since: 4.27.0
[pim] **	*PmsiPimTunnelId* see 2.20.1.1.2.41	PIM tree information. **Since: 4.24.2
[rsvpP2mp] **	*PmsiRsvpTunnelId* see 2.20.1.1.2.42	RSVP P2MP tree information. **Since: 4.32.1

2.20.1.1.2.40 PmsiMldpTunnelId

[invalidOpaqueValue] **	*boolean*	Opaque value has invalid type. **Since: 4.33.0
opaqueValue	*string*	FEC opaque value.
rootAddress	*IP address*	FEC root address.

2.20.1.1.2.41 PmsiPimTunnelId

group	*IP address*	Destination address used in tunnel encapsulation.
source	*IP address*	Source address used in tunnel encapsulation.

2.20.1.1.2.42 PmsiRsvpTunnelId

extTunnelId	*IP address*	Extended Tunnel ID (Originator IP).
p2mpId	*integer*	P2MP ID (VRF ID).
tunnelId	*integer*	Tunnel ID.

2.20.1.1.2.43 BgpRoutePeerEntry

peerAddr	*string*	Peer address for the route.
peerRouterId	*IPv4 address*	Peer router Identity.

2.20.1.1.2.44 BgpRouteTypeEntry

active	*boolean*	Route is active.

[asPathValidity] **	*enum: notValidated* | *valid* | *unknown* | *invalid*	Result of validating AS path. **Since: 4.36.0
atomicAggregator	*boolean*	Route is an atomic-aggregate.
backup	*boolean*	Route is backup.
ecmp	*boolean*	Route is an ECMP route.
ecmpContributor	*boolean*	Route contributes to ECMP.
ecmpHead	*boolean*	Route is the ECMP head.
[localAgg]	*boolean*	Route is locally aggregated.
luRoute	*boolean*	Route is an LU route.
[notInstalledReason]	*enum: routeInstallDenied* | *labeledRoutePresent* | *routeBestInactive*	Reason for route not being installed.
[origin]	*enum: Incomplete* | *Igp* | *Egp*	Route origin.
[originValidity] **	*enum: notValidated* | *valid* | *notFound* | *invalid*	Result of validating origin AS. **Since: 4.26.0
queued	*boolean*	Route is queued for advertisement.
[rfdSuppressed] **	*boolean*	Path is suppressed as it exceeded route flap damping suppression threshold. **Since: 4.29.2
[sixPeRoute] **	*boolean*	Route is an IPv6 provider edge (6PE) route. **Since: 4.22.1
stale	*boolean*	Route is stale.
suppressed	*boolean*	Route is suppressed by a covering aggregate.
ucmp	*boolean*	Route is an UCMP route.
[unknownMetric] **	*boolean*	Route is pending resolution. **Since: 4.24.1
valid	*boolean*	Route is valid.
[waitForConvergence]	*boolean*	Route is pending best path selection.

2.21 show ((ip bgp neighbors IP_PEER) | (ipv6 bgp peers (IP6_PEER | IP6_LL_PEER))) advertised-routes queued-withdrawals [...]

vrfs	*table(string) = BgpQueuedWithdrawals* see 2.21.1	Per VRF BGP queued withdrawals.

2.21.1 BgpQueuedWithdrawals

bgpQueuedWithdrawals	*list of BgpQueuedWithdrawal* see 2.21.1.1	List of paths pending withdrawal due to out-delay.
localAsn	*string*	Local Autonomous System Number.
localRouterId	*IPv4 address*	Local BGP Router Identity.
peerAddress	*string*	BGP peer address.
vrf	*string*	VRF name.

2.21.1.1 BgpQueuedWithdrawal

address	*IP address*	Address of route being withdrawn.
[localLabel] **	*integer*	Local MPLS label of route being withdrawn. **Since: 4.23.1
maskLength	*integer*	Mask length of route being withdrawn.
[pathId]	*integer*	Path ID of route being withdrawn.
rxAfiSafi **	*string*	Received AFI SAFI of route being withdrawn. **Since: 4.23.1
secondsRemaining	*integer*	Seconds remaining until route is withdrawn.

2.22 show ((ip bgp neighbors PEER) | (ipv6 bgp peers ((IP6_PEER | IP6_LL_PEER)))) (((routes | advertised-routes)) | ((routes | advertised-routes) ((regex REGEX) | ((community { (AANN_FORMAT | COMMUNITY_ENUM | COMMUNITY_U32) })) | (access-list AS_PATH_LIST_NAME) | ((IPV4_ADDR | IPV6_ADDR)) | ((IPV4_ADDR_MASK | IPV6_ADDR_MASK))))) [...]

revision 3

see 2.20

2.23 show ((ip bgp neighbors PEER) | (ipv6 bgp peers ((IP6_PEER | IP6_LL_PEER)))) (advertised-routes attribute discard) [...]

revision 3

see 2.20

2.24 show ((ip mroute sparse-mode) | (pim ipv4 sparse-mode route)) IP1 IP2 interface [...]

group	*IP address*	Group address of multicast route.
interfaces	*table(Interface name) = MrouteSmInterface* see 2.24.1	Map of interfaces for multicast route.
source	*IP address*	Source address of multicast route.

2.24.1 MrouteSmInterface

[address]	*IP address*	Interface IP address.
assertState	*enum: iAmAssertLoser | iAmAssertWinner | assertNoInfo*	Assert state.
[details]	*MrouteSmInterfaceDetails* see 2.24.1.1	Detailed mroute interface information.
downstreamJoinState	*enum: joined | noInfo | prunePending*	Downstream join state.
forward	*boolean*	Member of outgoing interface set.
iAmDr	*boolean*	This Pim router is the designated router on this interface.
[lastJoinReceived]	*floating point number*	UTC time at which the last downstream join was received.
[lastRptPruneReceived]	*floating point number*	UTC time at which the last downstream RPT prune was received.
markedForDeletion	*boolean*	If true, this interface has no (S,G,I)/(*,G,I) state and is scheduled to be removed from the route's interface list.
rptState	*enum: rptPruned | rptNoInfo | rptPrunePending | rptPrunePendingTemp | rptPruneTemp*	Downstream RPT state.

2.24.1.1 MrouteSmInterfaceDetails

[assertWinnerMetric]	*AssertMetric* see 2.24.1.1.1	Assert winner metric.
[evpnInfo] **	*EvpnInfo* see 2.24.1.1.2	EVPN Information. **Since: 4.25.0
[lastAssertAction]	*integer*	Last assert action.
[sgState]	*SgMrouteInterface* see 2.24.1.1.3	Interface state specific to (S,G) routes.
[wcState]	*WcMrouteInterface* see 2.24.1.1.4	Interface state specific to (*,G) routes.

2.24.1.1.1 AssertMetric

address	*IP address*	Address of router that generated the assert.
metric	*integer*	Route metric to the source/RP.

preference	*integer*	Route preference to the source/RP.
rptBit	*boolean*	Assert metric is for the RP tree.

2.24.1.1.2 EvpnInfo

[pegDr]	*boolean*	This interface is PEG DR.
[sbdVlan]	*boolean*	This is SBD VLAN interface.
[vni]	*integer*	VNI of the interface.
[vrf]	*string*	VRF the interface belongs to.

2.24.1.1.3 SgMrouteInterface

assertTrackingDesiredSg	*boolean*	Assert tracking desired (S,G,I).
couldAssertSg	*boolean*	Could assert (S,G,I).
excludeSg	*boolean*	Member of pim exclude (S,G).
immediateOlistSg	*boolean*	Member of immediate olist (S,G).
includeSg	*boolean*	Member of pim include (S,G).
inheritedOlistSg	*boolean*	Member of inherited olist (S,G).
inheritedOlistSgRpt	*boolean*	Member of inherited olist (S,G,Rpt).
joinsSg	*boolean*	Member of joins (S,G).
localReceiverExcludeSg	*boolean*	Local receiver exclude (S,G,I).
localReceiverIncludeSg	*boolean*	Local receiver include (S,G,I).
lostAssertSg	*boolean*	Member of lost assert (S,G).
lostAssertSgRpt	*boolean*	Member of lost assert (S,G,Rpt).
[myAssertMetricSg]	*AssertMetric* see 2.24.1.1.1	My assert metric (S,G,I).
prunesSgRpt	*boolean*	Member of prunes (S,G,Rpt).
[sptAssertMetric]	*AssertMetric* see 2.24.1.1.1	SPT assert metric (S,I).

2.24.1.1.4 WcMrouteInterface

assertTrackingDesiredWc	*boolean*	Assert tracking desired (*,G,I).
couldAssertWc	*boolean*	Could assert (*,G,I).
immediateOlistWc	*boolean*	Member of immediate olist (*,G).
immediateOlistWcRp	*boolean*	Member of immediate olist (*,*,G).
includeWc	*boolean*	Member of pim include (*,G).
joinsWc	*boolean*	Member of joins (*,G).
joinsWcRp	*boolean*	Member of joins (*,*,G).
localReceiverIncludeWc	*boolean*	Local receiver include (*,G,I).
lostAssertWc	*boolean*	Member of lost assert (*,G).
[myAssertMetricWc]	*AssertMetric* see 2.24.1.1.1	My assert metric (*,G,I).
[rptAssertMetric]	*AssertMetric* see 2.24.1.1.1	RPT assert metric (G,I).

2.25 show ((ip mroute sparse-mode) | (pim ipv4 sparse-mode route)) [...]

groups	*table(IPv4 or IPv6 address) = GroupSm* see 2.25.1	Map of sparse-mode Pim multicast groups.

2.25.1 GroupSm

groupSources	*table(IPv4 or IPv6 address) = MrouteSm* see 2.25.1.1	Map of multicast routes for this group.

2.25.1.1 MrouteSm

creationTime	*floating point number*	UTC time at which the route was created.
[details]	*MrouteDetails* see 2.25.1.1.1	Detailed information for this multicast route.
[nonDrOifList] **	*list of Interface name*	List of outgoing interfaces with egress drop rule in effect on non-DR. **Since: 4.22.1
oifList	*list of Interface name*	Outgoing interface list.
[registerInOifList]	*boolean*	If true, the register tunnel is part of the outgoing interface list.
routeFlags	*string*	Route flags.
[rp]	*IP address*	RP(G): The Rendezvous Point for this group.
[rpf]	*RpfSm* see 2.25.1.1.2	Reverse path forwarding information.
[rpfFrr] **	*RpfSm* see 2.25.1.1.2	Reverse path forwarding information for MoFrr. **Since: 4.20.0
[rpfFrrInterface] **	*interface name*	Reverse path forwarding interface for MoFRR. **Since: 4.20.0
[rpfInterface]	*interface name*	Reverse path forwarding interface, packets for this mroute must arrive on this interface to be accepted/forwarded. If this value is set to 'Register', the RPF interface is the register tunnel.
sourceAddress	*IP address*	Source address.

2.25.1.1.1 MrouteDetails

[evpnInfo] **	*EvpnInfo* see 2.24.1.1.2	EVPN Information. **Since: 4.25.0
[fastFailovers] **	*list of string*	This field is not used. **Since: 4.22.0
oifPrimes	*table(string) = OifPrime* see 2.25.1.1.1.1	Map of interfaces not in OIF set.
[sgState]	*SgMroute* see 2.25.1.1.1.2	State specific to (S,G) routes.

upstreamJoinState	*enum: upJoined | upNotJoined*	Upstream joined state.
upstreamRptState	*enum: upRptNotPruned | upRptNotJoined | upRptPruned*	Upstream RPT joined state.
[wcState]	*WcMroute* see 2.25.1.1.1.3	State specific to (*,G) routes.

2.25.1.1.1.1 OifPrime

assertLoser	*boolean*	Assert loser on this interface.
incomingInterface	*boolean*	The incoming interface for the route.
interface	*interface name*	Name of this interface.
locallyExcluded	*boolean*	Locally excluded.
notDr	*boolean*	Not a designated router on this interface.
rptPruned	*boolean*	Pruned from the RP tree.

2.25.1.1.1.2 SgMroute

couldRegisterSg	*boolean*	CouldRegister(S,G): If true, we may send register messages for this (S,G).
joinDesiredSg	*boolean*	Join Desired (S,G), if true we should send joins for this source if a valid upstream neighbor exists.
nullImmediateOlistSg	*boolean*	No interfaces in immediate olist (S,G).
nullInheritedOlistSg	*boolean*	No interfaces in immediate olist (S,G).
pruneDesiredSgRpt	*boolean*	Prune Desired (S,G,Rpt), if true, we should prune ourselves from the RP tree for this source. This is to avoid receiving traffic both from the RP tree and source tree.
registerStopSg	*boolean*	If true, we should send a register stop for this (S,G) in response to a register message.
sourceActive **	*boolean*	If true, there is active traffic for the source. **Since: 4.33.0

2.25.1.1.1.3 WcMroute

joinDesiredWc	*boolean*	Join Desired (*,G).
joinDesiredWcRp	*boolean*	Join Desired (*,*,G).
nullImmediateOlistWc	*boolean*	No interfaces in immediate olist (*,G).
nullImmediateOlistWcRp	*boolean*	No interfaces in immediate olist (*,*,G).
rptJoinDesiredWc	*boolean*	RPT Join Desired (*,G).

2.25.1.1.2 RpfSm

rpfAttached	*boolean*	If true, the source/RP is directly connected to this router.

[rpfEvpnTenantDomain] **	*boolean*	If true, the source/RP is inside EVPN Tenant Domain. **Since: 4.23.1
rpfMetric	*integer*	RPF route metric.
[rpfMvpn] **	*boolean*	If true, the source/RP is inside MVPN Domain. **Since: 4.27.1
[rpfNeighbor]	*IP address*	RPF neighbor.
rpfPreference	*integer*	RPF route preference.
rpfPrefix	*IP address prefix*	RPF route prefix.
rpfRib	*enum: M | U | none*	RPF routing table.

2.26 show ((ip mroute sparse-mode) | (pim ipv4 sparse-mode route)) count [...]

anycastRpDiscovered	*integer*	Number of routes discovered on the RP from from an anycast RP via a register message.
couldRegister	*integer*	Number of (S,G)s for which CouldRegister(S,G) is True.
drDiscovered	*integer*	Number of routes discovered on the RP from a DR via aa register message.
groups	*integer*	Number of groups.
mbrDiscovered	*integer*	Number of (S,G)s discovered via MBR.
msdpDiscovered	*integer*	Number of routes discovered on the RP via an MSDP source advertisement.
registerOif	*integer*	Number of (S,G)s with the register tunnel in the OIF set.
registerStop	*integer*	Number of (S,G)s for which the RP should generate register stops on receipt of a register/null register.
sgRoutes	*integer*	Number of (S,G) routes.
sources	*integer*	Number of sources.
switching	*integer*	Number of (S,G)s currently in the midst of switching from the RP tree to the SP tree.
toBeDeleted	*integer*	Number of routes currently scheduled for deletion.
unresolved	*integer*	Number of routes for which RPF information has not beendetermined.
wcRoutes	*integer*	Number of (*,G) routes.

2.27 show ((ip pim) | (pim ipv4)) sparse-mode rp [...]

crpSet	*table(IPv4 or IPv6 address prefix) = PimRpCandidateSet* see 2.27.1	Map of Candidate RP Set belonging to this group prefix.
detail	*boolean*	ShowDetails.

2.27.1 PimRpCandidateSet

crp	*table(IPv4 or IPv6 address) = PimRpCandidate* see 2.27.1.1	Map of candidate RP information for this RP.
[mode]	*enum: Sparse/Bidir | Bidir | None | Sparse*	PIM mode.
prefix	*IP address prefix*	Group Prefix.

2.27.1.1 PimRpCandidate

creationTime	*floating point number*	UTC time at which the entry was created.
[expires]	*floating point number*	Number of seconds after which the entry will expire.
hashMaskLen	*integer*	Hash Mask Length.
[hashMaskValue]	*integer*	Hash Mask Length.
[holdTime]	*integer*	Number of seconds for which this entry is set to be held.
[mode]	*enum: Sparse/Bidir | Bidir | None | Sparse*	PIM mode.
[override]	*boolean*	Entry is set to override BSR provided RP.
priority	*integer*	Rp Priority.
rpAddress	*IP address*	IP address of RP.
rpType	*string*	Type of RP candidate.

2.28 show ((ip pim sparse-mode rp-hash) | (pim ipv4 sparse-mode rp hash)) GROUP [...]

[crp]	*table(IPv4 or IPv6 address) = PimRpCandidate* see 2.27.1.1	Map of candidate RP info related to the RP Hash.
detail	*boolean*	Show details.
[mode]	*enum: modePimNone | modePimSm | modePimBidir*	PIM mode.
prefix	*IP address prefix*	Group Prefix.
[rp]	*IP address*	Rendezvous Point Router's IP address.
[rpHashAlgorithm] **	*enum: rpHashAlgorithmDefault | rpHashAlgorithmModulo*	Rp Hash Algorithm. **Since: 4.17.0
[rpHashMaskLen]	*integer*	Hash Mask Length.
[rpPriority]	*integer*	RP Priority.

2.29 show ((ip pim sparse-mode upstream joins) | (pim ipv4 sparse-mode join)) [...]

neighbors	*table(IPv4 or IPv6 address) = JoinPruneNeighbor* see 2.29.1	Map of upstream neighbors to which periodic join/prunes are being sent.

2.29.1 JoinPruneNeighbor

groups	*table(IPv4 or IPv6 address) = JoinPruneGroup* see 2.29.1.1	Map of groups for which periodic joins/prunes are being sent to this neighbor.
interface	*interface name*	Interface via which joins/prunes are being sent to this neighbor.
interfaceAddress	*IP address*	The join/prune interface's address.

2.29.1.1 JoinPruneGroup

joinedSources	*table(IPv4 or IPv6 address prefix) = JoinPruneSource* see 2.29.1.1.1	Map of sources for this group for which periodic joins are being sent.
[mode]	*enum: Sparse/Bidir | Bidir | None | Sparse*	PIM mode.
prunedSources	*table(IPv4 or IPv6 address prefix) = JoinPruneSource* see 2.29.1.1.1	Map of sources for this group for which periodic prunes are being sent.

2.29.1.1.1 JoinPruneSource

joinPruneFlagList	*list of JoinPruneFlag* see 2.29.1.1.1.1	Join/prune flags.
joinSuppressed	*boolean*	The upstream join for this source is currently suppressed.

2.29.1.1.1.1 JoinPruneFlag

flag	*enum: WC | RPT | SPT*	Type of join/prune, can be WC => (*,G), RPT => (S,G,Rpt) or SPT => (S,G).

2.30 show ((mac address-table) | mac-address-table) [...]

revision 2

disabledMacLearningVlans	*list of integer*	VLANs with disabled MAC learning.
[multicastTable]	*MulticastMacAddressTable* see 2.30.1	Multicast MAC address table.
unicastTable	*UnicastMacAddressTable* see 2.30.2	Unicast MAC address table.

2.30.1 MulticastMacAddressTable

tableEntries	*list of MulticastTableEntry* see 2.30.1.1	List of all of the Multicast entries.

2.30.1.1 MulticastTableEntry

entryType	*static*	Type.
interfaces	*list of Interface name*	Interfaces of the MAC Address.
macAddress	*MAC address*	MAC Address.
vlanId	*integer*	VLAN Id of MAC address.

2.30.2 UnicastMacAddressTable

tableEntries	*list of UnicastTableEntry* see 2.30.2.1	List of all of the Unicast entries.

2.30.2.1 UnicastTableEntry

entryType	*enum: static | dynamic*	MAC Address creation type.
interface	*interface name*	Interface of the MAC Address.
[interfaceFunction] **	*string*	MAC address interface function. **Since: 4.26.2
[lastMove]	*floating point number*	Timestamp of last move.
macAddress	*MAC address*	MAC Address.
[moves]	*integer*	Number of moves.
vlanId	*integer*	VLAN Id of MAC address.

2.31 show ((mac address-table) | mac-address-table) count [...]

vlanCounts	*table(numeric string) = VlanCount* see 2.31.1	Mapping between a VLAN Id and it's counters.

2.31.1 VlanCount

dynamic	*integer*	Number of dynamic address MAC entries.
multicast	*integer*	Number of multicast address MAC entries.
unicast	*integer*	Number of unicast address MAC entries.

2.32 show ((mac address-table) | mac-address-table) dynamic local limit [...]

revision 2

limitedVlans	*table(numeric string) = LimitedVlanEntry* see 2.32.1	Limited VLANs, keyed by their ID.

2.32.1 LimitedVlanEntry

appliedLimit	*integer*	Limit programmed in the hardware.
currentAddresses	*integer*	Current number of locally learned MACs.
limit	*integer*	Maximum number of locally learned MACs.

2.33 show ((mac address-table) | mac-address-table) mlag-peer [...]

see 2.30.2

2.34 show ((mac address-table) | mac-address-table) mlag-peer diff local-only

see 2.30.2

2.35 show ((mac address-table) | mac-address-table) mlag-peer diff peer-only

see 2.30.2

2.36 show ((mac address-table) | mac-address-table) multicast [...]

igmpMacEntries	*list of IgmpSnoopingTableEntry* see 2.36.1	All IGMP Snooping MAC entries.
multicastMacTable	*MulticastMacAddressTable* see 2.30.1	Multicast MAC entries.

2.36.1 IgmpSnoopingTableEntry

interfaces	*list of Interface name*	Interfaces of the MAC address.
macAddr	*MAC address*	MAC address.
macType	*igmp*	Type of MAC address.
vlanId	*integer*	VLAN ID of MAC address.

2.37 show ((mac address-table) | mac-address-table) multicast brief [...]

see 2.36

2.38 show ((mac address-table) | mac-address-table) notification host-flap detection window

`detectionWindow`	*integer*	The detection window for MAC Flapping, in seconds.

2.39 show ((mac address-table) | mac-address-table) notification host-flap logging

`status`	*boolean*	The current configuration of MAC Flap logging.

2.40 show (AGENT | (mpls ldp) | (vrf leak)) rcf [...]

functions	*table(string) = ShowAgentRcfFunctionModel* see 2.40.1	Routing control function information, keyed by function name.

2.40.1 ShowAgentRcfFunctionModel

Could also be an instance of:
ShowAgentRcfDetailFunctionModel 2.40.2

[missingReferenceDetails] **	*ShowAgentRcfMissingRefModel* see 2.40.1.1	Detail of missing reference lists. **Since: 4.29.2
status	*enum: missingSymbol | active | missingReference*	Routing control function state. active - Routing control function is valid missingReference - Routing control function is missing an external reference missingSymbol - Routing control function symbol is missing.

2.40.1.1 ShowAgentRcfMissingRefModel

[asPathList]	*list of string*	Missing reference to an ASN list.
[communityList]	*list of string*	Missing reference to a community list.
[extCommunityList]	*list of string*	Missing reference to an extended community list.
[largeCommunityList]	*list of string*	Missing reference to a large community list.
[prefixListV4]	*list of string*	Missing reference to an IPv4 prefix list.
[prefixListV6]	*list of string*	Missing reference to an IPv6 prefix list.
[roaTable]	*list of string*	Missing reference to a ROA table.
[srLabelRangeMissing]	*boolean*	Indicate if SR label range is missing.
[tagSet] **	*list of string*	Missing reference to a tag set. **Since: 4.34.0

2.40.2 ShowAgentRcfDetailFunctionModel

lastUpdateReason	*enum: functionDefinitionChange | externalReferenceChange*	Reason for most recent update.
lastUpdated	*floating point number*	Timestamp of most recent update.
[missingReferenceDetails]	*ShowAgentRcfMissingRefModel* see 2.40.1.1	Detail of missing reference lists.
status	*enum: missingSymbol | active | missingReference*	Routing control function state. active - Routing control function is valid missingReference - Routing control function is missing an external reference missingSymbol - Routing control function symbol is missing.
updateCount	*integer*	Number of function updates.

2.41 show (AGENT | (mpls ldp) | (vrf leak)) rcf detail [...]

functions	*table(string) = ShowAgentRcfDetailFunctionModel* see 2.40.2	Detailed routing control function information, keyed by function name.

2.42 show (arp | (ip arp)) [...]

[defaultArpAgingTimeout] **	*integer*	Default ARP aging timeout in seconds. **Since: 4.33.0
dynamicEntries	*integer*	Number of dynamically learnt addresses in ARP table.
ipV4Neighbors	*list of IpV4Neighbor* see 2.42.1	IPv4 neighbors discovered by the Address Resolution Protocol.
notLearnedEntries	*integer*	Number of addresses in ARP table not due to learning.
staticEntries	*integer*	Number of statically configured addresses in ARP table.
totalEntries	*integer*	Total number of addresses in ARP table.

2.42.1 IpV4Neighbor

address	*string*	IPv4 address or hostname.
[age]	*integer*	How many minutes ago the neighbor entry was learned.
[extra]	*string*	Extra metadata about this neighbor's discovery.
hwAddress	*string*	Hardware (layer 2) address learnt for the corresponding network (layer 3) address.
interface	*string*	Interface name the neighbor was learned on.

2.43 show (arp | (ip arp)) resolve summary total [...]

see 2.42

2.44 show (arp | (ip arp)) summary [...]

see 2.42

2.45 show (arp | (ip arp)) | (ipv6 neighbors) remote [...]

vlans	*table(numeric string) = ArpBindingVlan* see 2.45.1	A mapping of VLAN to its ARP bindings.

2.45.1 ArpBindingVlan

`attributes` **	*table(IPv4 or IPv6 address) = ArpBindingType* see 2.45.1.1	A mapping of IP address to its MAC address attributes. **Since: 4.26.2
`ipAddresses`	*table(IPv4 or IPv6 address) = MAC address*	A mapping of IP address to its MAC address.

2.45.1.1 ArpBindingType

`evpnMultihomed`	*boolean*	The IP address is EVPN multihomed.
`evpnRemoteMultihomed` **	*boolean*	The IP address is EVPN remote multihomed. **Since: 4.35.0
`vcsRemote` **	*boolean*	The IP address is received from VCS. **Since: 4.29.1

2.46 show (bgp rpki cache) [...]

caches	*table(string) = CacheModel* see 2.46.1	Collection of cache server information indexed by cache server's name.

2.46.1 CacheModel

activeSince	*floating point number*	Time the connection became active in UTC.
aspaTables **	*list of string*	RPKI ASPA tables populated by the cache server. **Since: 4.36.0
deleted	*boolean*	The config for this cache has been deleted.
[detail]	*CacheDetailModel* see 2.46.1.1	Detail information.
entries	*integer*	Number of Route Origin Authorization and ASPA entries.
expireInterval	*integer*	Number of seconds to retain data synced from cache server.
host	*string*	IP address or hostname of cache server.
lastFullSync	*floating point number*	Time of last reset sync with cache server in UTC.
lastResetQuery	*floating point number*	Time of last reset query sent to cache server in UTC.
lastSerialQuery	*floating point number*	Time of last serial query sent to cache server in UTC.
lastUpdateSync	*floating point number*	Time of last serial sync with cache server in UTC.
port	*integer*	Transport port of cache server.
preference	*integer*	Cache server preference. Lower value means higher preference.
protocolVersion	*enum: version1 | version2 | version0 | notNegotiatedYet*	RPKI-RTR protocol version.
[reasonInactive]	*string*	Reason the connection is not active.
refreshInterval	*integer*	Number of seconds between cache server polls.
retryInterval	*integer*	Number of seconds between poll error and cache server poll.
roaTables **	*list of string*	RPKI ROA tables populated by the cache server. **Since: 4.27.1
serialNumber **	*integer*	Serial number for the last successful sync. **Since: 4.24.2
sessionId **	*integer*	Session ID for this cache instance. **Since: 4.24.2
state	*enum: connected | disconnected | awaitingRoaData | requestRoaReset | requestRoaUpdate | idle | misconfigured | synced | disabled | syncing*	Cache server current state.

[transportInformation] **	*CacheTransport-InformationModel* see 2.46.1.2	Transport information. **Since: 4.26.2
transportProtocol **	*enum: tcp | tls*	Transport protocol for connection to RPKI cache server. **Since: 4.25.0
vrf	*string*	VRF where the cache server is configured.

2.46.1.1 CacheDetailModel

lastConfigChange	*floating point number*	Time when the host, port, VRF or local interface was changed in the config in UTC.
lastConnectionError	*floating point number*	Time of last connection error to cache server in UTC.
lastProtocolError	*floating point number*	Time of sending/receiving protocol error to/from cache server in UTC.
overrideConfiguredInterval-Values	*boolean*	Cache suggested or default interval values will be used.
[tcpInformation]	*TcpInformationModel* see 2.46.1.1.1	TCP information.
tcpKeepaliveIdleTime **	*integer*	Idle time (seconds) before TCP keepalive. **Since: 4.25.1
tcpKeepaliveProbeCount **	*integer*	Number of keepalive probes before closing connection. **Since: 4.25.1
tcpKeepaliveProbeInterval **	*integer*	Interval (seconds) between TCP keepalive probes. **Since: 4.25.1

2.46.1.1.1 TcpInformationModel

congestionWindow	*integer*	TCP send congestion window (bytes).
delayedAckTimeout	*integer*	TCP socket delayed ack timeout (microseconds).
inputQueueLength	*integer*	TCP input queue length.
inputQueueMaxLength	*integer*	TCP input queue max length.
localTcpAddress	*IP address*	TCP local address.
localTcpPort	*integer*	TCP local port.
maxSegmentSize	*integer*	TCP outgoing maximum segment size (bytes).
options	*TcpOptionsModel* see 2.46.1.1.1.1	TCP socket options.
outputQueueLength	*integer*	TCP output queue length.
outputQueueMaxLength	*integer*	TCP output queue max length.
recvRtt	*integer*	TCP receive round-trip time (microseconds).
recvWindow	*integer*	TCP advertised receive window (bytes).
recvWindowScale	*integer*	TCP socket receive window scale factor.
retransmitTimeout	*integer*	TCP socket retransmission timeout (microseconds).
sendRtt	*integer*	TCP round-trip time (microseconds).

sendRttVariance	*integer*	TCP round-trip time variance (microseconds).
sendWindowScale	*integer*	TCP socket send window scale factor.
slowStartThreshold	*integer*	TCP send slow start size threshold (bytes).
state	*enum: CLOSED | TIME-WAIT | CLOSE-WAIT | FIN-WAIT-1 | SYN-RECEIVED | ESTABLISHED | LISTEN | SYN-SENT | NOTUSED | CLOSING | FIN-WAIT-2 | LAST-ACK*	TCP Socket current state.
totalRetrans	*integer*	Total number of TCP retransmissions.

2.46.1.1.1.1 TcpOptionsModel

ecn	*boolean*	Explicit Congestion Notification enabled.
selectiveAcks	*boolean*	Selective Acknowledgments enabled.
timestamps	*boolean*	Timestamps enabled.
windowScale	*boolean*	Window Scale enabled.

2.46.1.2 CacheTransportInformationModel

[sslProfileName]	*string*	Configured SSL profile name.

2.47 show (bgp rpki cache counters) [...]

caches	*table(string) = CacheCounterModel* see 2.47.1	A mapping of cache names to their counters.

2.47.1 CacheCounterModel

cacheReset	*integer*	Count of Cache Reset PDU.
cacheResponse	*integer*	Count of Cache Response PDU.
endOfData	*integer*	Count of End of Data PDU.
ipv4Prefix	*integer*	Count of IPv4 Prefix PDU.
ipv6Prefix	*integer*	Count of IPv6 Prefix PDU.
resetQuery	*integer*	Count of Reset Query PDU.
serialNotify	*integer*	Count of Serial Notify PDU.
serialQuery	*integer*	Count of Serial Query PDU.

2.48 show (bgp rpki cache counters) errors [...]

cachesRx	*table(string) = CacheRxErrorCounterModel* see 2.48.1	A mapping of cache names to their received error counters.
cachesTx	*table(string) = CacheTxErrorCounterModel* see 2.48.2	A mapping of cache names to their sent error counters.

2.48.1 CacheRxErrorCounterModel

corruptData	*integer*	Count of Corrupt Data PDU.
internalError	*integer*	Count of Internal Error PDU.
invalidRequest	*integer*	Count of Invalid Request PDU.
noData	*integer*	Count of No Data PDU.
other	*integer*	Count of Other PDU.
pduTimeout	*integer*	Count of timeouts waiting for PDU.
unexpectedProtocol **	*integer*	Count of Unexpected Protocol PDU. **Since: 4.24.1
unsupportedPdu	*integer*	Count of Unsupported PDU.
unsupportedProtocol	*integer*	Count of Unsupported Protocol PDU.

2.48.2 CacheTxErrorCounterModel

corruptData	*integer*	Count of Corrupt Data PDU.
duplicateAnnouncement	*integer*	Count of Duplicate Announcement PDU.
internalError	*integer*	Count of Internal Error PDU.
other	*integer*	Count of Other PDU.
unexpectedProtocol **	*integer*	Count of Unexpected Protocol PDU. **Since: 4.24.1
unsupportedPdu	*integer*	Count of Unsupported PDU.
unsupportedProtocol	*integer*	Count of Unsupported Protocol PDU.
withdrawalUnknown	*integer*	Count of Withdrawal Unknown PDU.

2.49 show (cli | routing-context) vrf

vrfRoutingContext	*string*	Name of VRF for the current routing-context.

2.50 show (ip | ipv6) attached-host route export [...]

revision 3

vrfs	*table(string) = AttachedHostInterfaces* see 2.50.1	A dictionary of VRF to corresponding L3 interfaces.

2.50.1 AttachedHostInterfaces

l3Interfaces	*table(string) = AttachedHostInterfaceEntry* see 2.50.1.1	A dictionary of L3 interface to hosts learnt.

2.50.1.1 AttachedHostInterfaceEntry

hosts	*list of AttachedHostPrefix* see 2.50.1.1.1	List of all hosts learnt on the L3 interface.

2.50.1.1.1 AttachedHostPrefix

address	*IP address*	IP Address.
[l2Interface]	*interface name*	L2 interface on which host is learnt on.
prefix	*IP address prefix*	Prefix added corresponding to attached host routes.

2.51 show (ip | ipv6) bgp summary lldp [...]

revision 3

vrfs	*table(string) = BgpSummary* see 2.51.1	Per VRF BGP summary.

2.51.1 BgpSummary

asn	*string*	Autonomous System Number.
peers	*table(string) = BgpSummaryPeerEntry* see 2.51.1.1	Dictionary of BGP peer entries indexed by the peer address.
routerId	*IPv4 address*	BGP Router Identity.
vrf	*string*	VRF Name.

2.51.1.1 BgpSummaryPeerEntry

asn	*string*	Autonomous System Number.
[description] **	*string*	Peer Description. **Since: 4.21.3
inMsgQueue	*integer*	Number of messages waiting to be processed.
[lldpNeighbors] **	*list of string*	LLDP Neighbor list (only multi-agent mode). **Since: 4.27.2
msgReceived	*integer*	Number of messages received.
msgSent	*integer*	Number of messages sent.
outMsgQueue	*integer*	Number of messages waiting to be sent.
peerState	*enum: NotNegotiated | OpenConfirm | Active | Established | Connect | OpenSent | Idle*	Current peer state. Idle - Ignoring everything Connect - Trying to connect Active - Waiting for a connection OpenSent - Open packet has been sent OpenConfirm - Waiting for a keepalive or notify Established - Connection has been established.

[peerStateIdleReason]	*enum: PendingNotification | OrrPositionIncomplete | MaxPath | IbgpLinkLocalUnsupported | Damping | OrrAndAddPathBackup | MinHoldTime | NoInterface | EbgpLinkLocalMultihopUnsupported | GroupAdmin | MaxAdvertisedPath | NoLocalNexthops | UnsupportedTcpAuthConfig | OrrPositionCountExceedsMaximum | NoActivate | AsuShutdown | Deleted | UnsupportedCaps | Other | NoRemoteAs | OrrLinkLocalPeer | Admin | SendFailureHoldTime | OrrPositionPeerAddressDynamicPeer | MaxAcceptedPath*	Used when peer state is "Idle". NoInterface - The peer's interface is down Admin - The peer is disabled GroupAdmin - The peer's group is disabled MaxPath - The peer has exceeded its max route limit Deleted - The peer is deleted and waiting for deferred cleanup NoActivate - The peer is not activated in any address-family mode NoLocalNexthops - The peer is missing local addresses for activated AFI/SAFIs UnsupportedCaps - The peer has not negotiated required capabilities NoRemoteAs - Missing remote-as for peer AsuShutdown - ASU2 shutdown in progress IbgpLinkLocalUnsupported - IBGP peering over IPv6 link-local address not supported MaxAcceptedPath - The peer has exceeded its max accepted route limit Other - The peer is idled for some other reason PeerNotification - The peer is pending notification message to be sent EbgpLinkLocalMultihopUnsupported - EBGP multihop session over IPv6 link-local addresses not supported MaxAdvertisedPath - The peer has exceeded its max advertised route limit Damping - The peer is waiting for BFD connection to be stable UnsupportedTcpAuthConfig - The peer has not negotiated required TcpAuth config.
prefixAccepted	*integer*	Number of prefixes accepted.
[prefixAdvertised] **	*integer*	Number of prefixes advertised (multi-agent mode). **Since: 4.34.1
[prefixInBest] **	*integer*	Number of paths select as best. **Since: 4.22.0
[prefixInBestEcmp] **	*integer*	Number of paths end in best ecmp group. **Since: 4.22.0
prefixReceived	*integer*	Number of prefixes received from peer.
[rulesAccepted] **	*integer*	Number of flowspec rules accepted from peer. **Since: 4.21.3
[rulesAdvertised] **	*integer*	Number of flowspec rules advertised (multi-agent mode). **Since: 4.34.1
[rulesReceived] **	*integer*	Number of flowspec rules received from peer. **Since: 4.21.3
[underMaintenance]	*boolean*	Peering under maintenance.
upDownTime	*floating point number*	Timestamp of last up/down transition.
version	*integer*	BGP version.

2.52 show (ip | ipv6) hardware ale routes acknowledgement [...]

[cmdErr]	*string*	Error Message.
fibRoutes	*table(IPv4 or IPv6 address prefix) = AcknowledgementRouteEntry* see 2.52.1	Mapping prefix to its FibRoute Info.
[vrfName]	*string*	VRF name.

2.52.1 AcknowledgementRouteEntry

[acknowledged]	*AcknowledgementRouteVersionId* see 2.52.1.1	Acknowledged Route Version Id.
[requested]	*AcknowledgementRouteVersionId* see 2.52.1.1	Requested Route Version Id.

2.52.1.1 AcknowledgementRouteVersionId

failed **	*boolean*	Route install failed. **Since: 4.28.0
requestedDelete	*boolean*	Route due to be deleted.
versionId	*integer*	Route Version Id to be acknowledged.

2.53 show (ip | ipv6) hardware ale routes drop [...]

routingTelemetry **	*enum: enabled | disabled*	Routing telemetry status. **Since: 4.29.2
[vrfDropRoutes]	*list of VrfDropRoute* see 2.53.1	List of all drop routes.

2.53.1 VrfDropRoute

insertTime	*floating point number*	Drop route creation time.
prefix	*IP address prefix*	The route's prefix.
vrfName	*string*	Name of a VRF.

2.54 show (ip | ipv6) hardware ale routes inconsistent [...]

routingTelemetry **	*enum: enabled | disabled*	Routing telemetry status. **Since: 4.29.2
[vrfInconsistentRoutes]	*list of VrfRouteEntry* see 2.54.1	List of all inconsistent routes.

2.54.1 VrfRouteEntry

insertTime	*floating point number*	Route entry creation time.
prefix	*IP address prefix*	The route's prefix.

`vrfName`	*string*	Name of a VRF.

2.55 show (ip | ipv6) hardware ale routes summary [...]

addressFamily	*enum: afIpv6 | afIpv4*	IP Version of the Routes Summary Counter.
compressedRoutes	*integer*	Counts of compressed routes.
fibRouteAllocations	*integer*	Total number of FIB routes.
[platformStatus]	*Ale.Summary.PlatformStatusCounter* see 2.55.1	Counts of routes by their platform programming status.
reviewQueue	*Ale.Summary.ReviewQueueCounter* see 2.55.2	Detailed counts of routes within review queue states.

2.55.1 Ale.Summary.PlatformStatusCounter

[dropProgrammed]	*integer*	Number of routes pointing to drop FEC.
[forwardingProgrammed]	*integer*	Number of routes actively forwarding traffic.
[inconsistent]	*integer*	Number of routes whose forwarding state is inconsistent with FIB.
[pendingAck]	*integer*	Number of routes pending acknowledgement from platform.

2.55.2 Ale.Summary.ReviewQueueCounter

absolutePriority	*integer*	Number of routes in absolute priority review.
[deferred]	*integer*	Number of routes currently waiting for adjacency to install.
delayed	*integer*	Number of routes in delayed review.
highPriority	*integer*	Number of routes in high priority review.
lowPriority	*integer*	Number of routes in low priority review.
mediumPriority	*integer*	Number of routes in medium priority review.
retry	*integer*	Number of routes in retry queue.

2.56 show (ip | ipv6) hardware fib fec [...]

[cmdErr]	*string*	Error flag.
[compressedByRoute] **	*IP address prefix*	IP Address of the parent route. **Since: 4.22.0
[fec]	*table(numeric string) = FibFecInfo* see 2.56.1	Mapping fecId to its FEC Info.
[routeCompressed] **	*boolean*	Route is compressed. **Since: 4.22.0
[routeType]	*enum: routeCacheForward | multicast | unknown | attached | ebgp | ospfv3AseE1 | ibgpLu | ospfAseE1 | isisL1 | ebgpLu | ospfAggregate | ospf | ospfInterArea | vcs | lbgp | receive | isisL2 | bgpAggregate | receiveAndHostRoute | ospfAseE2 | ospfv3NssaE1 | policy | receiveBcast | ospfv3NssaE2 | rip | connected | cbfLeaked | kernel | bgp | ospfv3 | drop | redirect | ibgp | ospfv3IntraArea | ospfNssaE1 | routeCacheConnected | nexthopGroup | invalid | staticConfig | directedBcast | ospfNssaE2 | gribi | dynamicPolicy | ospfv3AseE2 | martian | staticEosSdk | dhcp | ospfIntraArea | ospfv3InterArea | l2NexthopGroup*	Route type.

2.56.1 FibFecInfo

[backupFecVias] **	*list of AleL3AdjVia* see 2.56.1.1	Backup Via list. **Since: 4.23.2
[cmdErr]	*string*	Error flag.

[fecType]	*enum: dropRoute | fecInfoUnavailable | bcastReceiveRoute | routeCacheConnectedRoute | nexthopGroupRoute | evpnRoute | forwardRoute | tunnelFibRoute | routeCacheForwardRoute | policyRoute | pwRoute | mplsFloodSetRoute | directedBcastRoute | srv6Route | usedByTunnelRoute | vplsL2UcastRoute | mplsMcastRoute | greMcastRoute | slowReceiveRoute | routeTypeUnknown | receiveRoute | mplsRoute | vplsMcastRoute | invalidRoute | nexthopRoute | attachedRoute*	FEC type.
[fecVias]	*list of AleL3AdjVia* see 2.56.1.1	Via list.
[vias]	*integer*	Number of vias for the route.

2.56.1.1 AleL3AdjVia

[decapInfo] **	*DecapInfo* see 2.56.1.1.2	Decapsulation information. **Since: 4.27.0
[fallbackInfo] **	*FallbackInfo* see 2.56.1.1.3	Fallback information. **Since: 4.27.2
forwardingAction **	*enum: forwarding | setForwardingVrf | encap | decapEncap | decap | decapSetForwardingVrf*	Forwarding action. **Since: 4.31.2
l3IntfId	*interface name*	L3 Interface Id.
nextHopIp	*IP address prefix*	Ip Address of Next Hop.
[tunnelDescriptor] **	*AleL3AdjViaTunnel* see 2.56.1.1.1	Tunnel information. **Since: 4.21.0
weight	*integer*	Metric representing the hop cost.

2.56.1.1.1 AleL3AdjViaTunnel

[tunnelAddressFamily]	*enum: IPv6 | IPv4*	Address family.
tunnelIndex	*integer*	Tunnel table index.
tunnelType	*string*	Tunnel type.

2.56.1.1.2 DecapInfo

actionType	*ipip*	Decapsulation type.

2.56.1.1.3 FallbackInfo

actionType	*enum: none | ipip*	Decapsulation type.
fallbackVrf	*string*	Fallback VRF name.

2.57 show (ip | ipv6) hardware fib routes compressed [...]

[cmdErr]	*string*	Error message.
[vrfs]	*table(string) = ParentPrefixColl* see 2.57.1	Mapping of vrfName to parentPrefixes in that vrf.

2.57.1 ParentPrefixColl

parentPrefixes	*table(IPv4 or IPv6 address prefix) = CompressedRouteColl* see 2.57.1.1	Mapping of parent Prefixes and compressedRoutes.

2.57.1.1 CompressedRouteColl

compressedRoutes	*list of IP address prefix*	List of compressed Routes.

2.58 show (ip | ipv6) hardware fib summary

revision 2

[adjResourceOptimization] **	*AdjResourceOptimization* see 2.58.1	Adjacency resource optimization. **Since: 4.23.2
[adjShare]	*enum: enabled | disabled*	Adjacency sharing status.
[adjShareAttachedRoute] **	*boolean*	Selective adjacency sharing for attached routes. **Since: 4.35.0
[bfdEvent]	*enum: enabled | disabled*	BFD peer event.
deletionDelay	*floating point number*	Deletion delay.
[ecmpExpansionSupported] **	*enum: supported | notSupported*	ECMP expansion supported. **Since: 4.35.2
fibCompression **	*enum: enabled | disabled*	FIB compression status. **Since: 4.22.0
icmpStatus	*enum: enabled | disabled*	ICMP status.
[maxAleEcmp] **	*integer*	Max Ale ECMP. **Since: 4.21.3
[maxEcmpFecSize] **	*integer*	Max ECMP FEC size. **Since: 4.35.2
maxFecHierarchyLevels **	*integer*	Maximum FEC hierarchy levels. **Since: 4.29.1
maxRoutes	*integer*	Maximum number of routes.
[pbrSupport]	*enum: supported | notSupported*	PBR support.
protectDefaultRoute	*enum: enabled | disabled*	Protect default route status.
[ucmpWeightDeviation] **	*floating point number*	UCMP weight deviation. **Since: 4.21.3
urpfSupport	*enum: supported | notSupported*	URPF support.

2.58.1 AdjResourceOptimization

[enabled]	*enum: enabled | disabled*	Adjacency resource optimization enabled.
supported	*enum: supported | notSupported*	Adjacency resource optimization support.
[thresholds]	*AdjResourceOptimization-Thresholds* see 2.58.1.1	Adjacency resource optimization thresholds.

2.58.1.1 AdjResourceOptimizationThresholds

high	*integer*	Threshold for stopping resource optimization.
low	*integer*	Threshold for starting resource optimization.

2.59 show (ip | mac) access-lists payload alias

udfAliases	*table(string) = PayloadSpec* see 2.59.1	Mapping of alias name to payload.

2.59.1 PayloadSpec

headerStart **	*boolean*	True, if offset is from header start. **Since: 4.15.3
headerType **	*enum: l4Header | l3Header*	payload header type. **Since: 4.32.1
payload	*list of PayloadElement* see 2.59.1.1	List of offset,pattern,mask tuple.

2.59.1.1 PayloadElement

alias **	*string*	Alias of payload. **Since: 4.20.0
maskOverride **	*boolean*	True, if mask is overridden in alias. **Since: 4.21.0
offset	*integer*	Offset inside payload for DPI.
pattern	*integer*	Pattern to match at offset inside payload.
patternMask	*integer*	Mask for the pattern to match at offset inside payload.
patternOverride **	*boolean*	True, if pattern is overridden in alias. **Since: 4.21.0

2.60 show (segment-l3 ipv6 address profile) [...]

interfaces	*table(Interface name) = Ip6AddressInterface* see 2.60.1	IPV6 address profile segmentation interface.

2.60.1 Ip6AddressInterface

[addresses]	*table(IPv4 or IPv6 address address and mask length) = Address* see 2.60.1.1	Status of the segmenation addresses for this interface.
[isolationDenyState]	*enum: denyOkay | denyFailed | denyPending*	Status of the segmentation isolation deny request.
[isolationPermitState]	*table(IPv4 or IPv6 address with netmask) = IsolationPermitState* see 2.60.1.3	Status of the segmenation isolation permit request.
[profileError]	*string*	Error message generated when applying the profile.
profileName	*string*	Name of the IPv6 address profile for the interface.
[segmentationPortNumber]	*integer*	Value of the segmentation port number for the interface.
status **	*enum: inactive | connected | unconfigured | disabled*	Connection status of the interface. **Since: 4.35.0
[tenants]	*table(numeric string) = Tenant* see 2.60.1.2	Status of the tenants for this interface.

2.60.1.1 Address

[isolationRequest]	*IsolationRequest* see 2.60.1.1.1	Isolation criteria of the interface.
state	*enum: pending | assigned | conflict*	State of the IPv6 segmenation address on the interface.

2.60.1.1.1 IsolationRequest

description	*string*	Description of the isolation criteria.
isolationCriteria	*IP address and netmask*	IPv6 address bits that must match in order to pass traffic.

2.60.1.2 Tenant

[error]	*string*	Error message generated when the tenant is invalid.

2.60.1.3 IsolationPermitState

description	*string*	Description of the isolation state.
state	*enum: permitPending | permitFailed | permitOkay*	Status of the segmentation isolation permit request.

2.61 show (segment-l3 ipv6 address profile) aggregates

`vrfStatus`	*table(string) = AggregateVrfStatus* see 2.61.1	Aggregates generated from IPv6 address profiles.

2.61.1 AggregateVrfStatus

`contributorStatus`	*table(IPv4 or IPv6 address prefix) = AggregateContributorStatus* see 2.61.1.1	IPv6 address profile aggregates.

2.61.1.1 AggregateContributorStatus

`contributorInterface`	*list of Interface name*	List of contributor interfaces.

2.62 show ADDR_FAMILY dhcp relay access-list [...]

[ipAclList]	*IpAclList* see 2.62.1	IP access list.
[ipv6AclList]	*Ipv6AclList* see 2.62.2	IPv6 access list.

2.62.1 IpAclList

aclList	*list of _AclBase* see 2.62.1.1	List of ACLs.

2.62.1.1 _AclBase

Could also be an instance of:
AclSummary 2.62.1.2
ServiceAclSummary 2.62.1.3

countersEnabled	*boolean*	True if counters are enabled.
countersIncomplete	*boolean*	True if the hardware could not allocate counters for every rule.
dynamic **	*boolean*	True if a dynamic (non-persistent) access control list. **Since: 4.21.3
name	*string*	Name.
permitResponse **	*enum: natTraffic | unused*	Type of ACL permit response traffic. **Since: 4.32.1
readonly	*boolean*	True if read-only.
standard	*boolean*	True if a standard access control list - standard ACLs filter only on the source address.
type	*enum: Ip4Acl | MacAcl | Ip6Acl*	Type of ACL.

2.62.1.2 AclSummary

activeEgressIntfs	*list of IntfSummary* see 2.62.1.2.2	Active egress interfaces.
activeFieldset **	*list of string*	Active field set. **Since: 4.33.1
activeIngressIntfs	*list of IntfSummary* see 2.62.1.2.2	Active ingress interfaces.
configuredEgressIntfs	*list of IntfSummary* see 2.62.1.2.2	Configured egress interfaces.
configuredIngressIntfs	*list of IntfSummary* see 2.62.1.2.2	Configured ingress interfaces.
countersEnabled	*boolean*	True if counters are enabled.
countersIncomplete	*boolean*	True if the hardware could not allocate counters for every rule.
dot1x **	*Dot1x* see 2.62.1.2.1	Dot1x specifications. **Since: 4.33.1

dynamic **	*boolean*	True if a dynamic (non-persistent) access control list. **Since: 4.21.3
name	*string*	Name.
notFullySupportedByHardware	*boolean*	Some rules are not fully supported by hardware.
permitResponse **	*enum: natTraffic | unused*	Type of ACL permit response traffic. **Since: 4.32.1
readonly	*boolean*	True if read-only.
sequenceLength	*integer*	Total number of rules and remarks in the list.
standard	*boolean*	True if a standard access control list - standard ACLs filter only on the source address.
type	*enum: Ip4Acl | MacAcl | Ip6Acl*	Type of ACL.

2.62.1.2.1 Dot1x

interfaceAclMode	*list of Dot1xInterface* see 2.62.1.2.1.1	Interface ACL mode information.
perMacAclMode	*list of Dot1xInterface* see 2.62.1.2.1.1	Per-MAC ACL mode information.

2.62.1.2.1.1 Dot1xInterface

name	*string*	Name of the interface.
supplicants	*list of Dot1xSupplicantInfo* see 2.62.1.2.1.2	Supplicant information.

2.62.1.2.1.2 Dot1xSupplicantInfo

macAddr	*MAC address*	Supplicant MAC.
username	*string*	Supplicant username.

2.62.1.2.2 IntfSummary

name	*string*	Name of interface.
[target] **	*string*	Where the ACL is applied. **Since: 4.18.0
[vrf]	*string*	VRF name, since the summary is per vrf.

2.62.1.3 ServiceAclSummary

activeVrfs	*list of string*	Active on vrfs.
configuredVrfs	*list of string*	Configured on vrfs.
countersEnabled	*boolean*	True if counters are enabled.
countersIncomplete	*boolean*	True if the hardware could not allocate counters for every rule.

dynamic **	*boolean*	True if a dynamic (non-persistent) access control list. **Since: 4.21.3
name	*string*	Name.
permitResponse **	*enum: natTraffic | unused*	Type of ACL permit response traffic. **Since: 4.32.1
readonly	*boolean*	True if read-only.
sequenceLength	*integer*	Total number of rules and remarks in the list.
standard	*boolean*	True if a standard access control list - standard ACLs filter only on the source address.
type	*enum: Ip4Acl | MacAcl | Ip6Acl*	Type of ACL.

2.62.2 Ipv6AclList

aclList	*list of _AclBase* see 2.62.1.1	List of ACLs.

2.63 show ADDR_FAMILY dhcp relay counters

globalCounters	*GlobalCounters* see 2.63.1	DHCP relay global counters.
[interfaceCounters]	*table(Interface name) = InterfaceCounter* see 2.63.2	A mapping of interface to its counters.

2.63.1 GlobalCounters

allRequests	*Counters* see 2.63.1.1	Global counter for requests.
allResponses	*Counters* see 2.63.1.1	Global counter for responses.
lastResetTime	*floating point number*	Last reset time for global counters.

2.63.1.1 Counters

dropped	*integer*	Dropped packets.
forwarded	*integer*	Forwarded packets.
received	*integer*	Received packets.

2.63.2 InterfaceCounter

lastResetTime	*floating point number*	Last reset time for interface counter.
replies	*Counters* see 2.63.1.1	Interface counter for replies.
requests	*Counters* see 2.63.1.1	Interface counter requests.

2.64 show ADDR_FAMILY helper-address

revision 2

activeState	*boolean*	DHCP relay is active.
allSubnets	*boolean*	DHCP all-subnets relaying is enabled.
allSubnetsV6	*boolean*	DHCPv6 all-subnets relaying is enabled.
alwaysOn	*boolean*	DHCP relay alwaysOn state.
configuredInterfaces	*table(Interface name) = ConfiguredInterface* see 2.64.1	A mapping of interface to its DHCP configuration.
crossVrfServerIdPreserve **	*boolean*	DHCP relay preserves server ID option 54 with cross vrf DHCP servers. **Since: 4.34.1
[defaultServers]	*DefaultServersShowModel* see 2.64.2	DHCP Relay mode default addresses/hostnames.
dhcpReqFloodRestrict-DisabledDueToSnooping **	*boolean*	DHCP client request flooding suppression disbled due to DHCP snooping configuration. **Since: 4.30.1
linkLayerAddrOpt	*boolean*	DHCPv6 relay link-layer address option (79) is enabled.
mlagPeerLinkReqDisable **	*boolean*	DHCP requests received over MLAG peer link are suppressed. **Since: 4.27.2
option82	*boolean*	DHCP relay information option (82) is enabled.
[option82SubOpts] **	*Option82SubOptionsModel* see 2.64.3	Enabled suboptions under DHCP relay information option (82). **Since: 4.33.0
remoteIdEncodingFormat	*string*	DHCPv6 relay remote ID option (37) encoding format.
[remotePDSync] **	*RemotePDSyncShowModel* see 2.64.4	DHCPv6 PD remote sync information. **Since: 4.35.2
reqFloodSuppressionVlan-Config **	*list of integer*	DHCP client request flooding suppressed VLANs configured. **Since: 4.30.1
reqFloodSuppressionVlan-Operational **	*list of integer*	DHCP client request flooding suppressed VLANs operational. **Since: 4.30.1
tunnelRepEncapped **	*boolean*	DHCP replies to tunnel requests are encapsulated. **Since: 4.35.2
tunnelReqDisable	*boolean*	DHCP tunnel requests are disabled.
vssControlDisable **	*boolean*	DHCP VSS control sub-option (152) is disabled. **Since: 4.31.2
[vssSubOptUnsupported-Servers] **	*VssUnsupportedServers-Model* see 2.64.5	DHCP VSS control sub-option (152) and DHCPv6 VSS option (68) unsupported servers. **Since: 4.29.0

2.64.1 ConfiguredInterface

allSubnets	*boolean*	DHCP all-subnets relaying enabled interface.
allSubnetsV6	*boolean*	DHCPv6 all-subnets relaying enabled interface.
circuitId	*string*	Circuit ID enabled interface.
disabledV4	*boolean*	DHCPv4 relay is disabled.
disabledV6	*boolean*	DHCPv6 relay is disabled.
[helpers]	*list of Helper* see 2.64.1.1	Helper addresses/hostnames for an interface.
remoteId **	*string*	Remote ID enabled interface. **Since: 4.32.2
usingGlobalModeServersV4	*boolean*	Using DHCPv4 Relay mode configurations.
usingGlobalModeServersV6	*boolean*	Using DHCPv6 Relay mode configurations.

2.64.1.1 Helper

[linkAddr]	*IPv6 address*	Link address.
[serverAddr]	*IP address*	Helper address.
[serverHostname]	*string*	Helper hostname.
[srcAddr]	*IP address*	Source address.
[srcIntf]	*interface name*	Source interface.
vrf	*string*	Server VRF.

2.64.2 DefaultServersShowModel

helpersV4	*list of Helper* see 2.64.1.1	DHCP Relay mode default IPv4 addresses/hostnames.
helpersV6	*list of Helper* see 2.64.1.1	DHCP Relay mode default IPv6 addresses.

2.64.3 Option82SubOptionsModel

circuitIdOpt	*boolean*	DHCP relay circuit-id suboption (1) under information option (82) is enabled.
remoteIdOpt	*boolean*	DHCP relay remote-id suboption (2) under information option (82) is enabled.
vendorSpecificSubOpt	*boolean*	DHCP relay vendor-specific suboption (9) under information option (82) is enabled.

2.64.4 RemotePDSyncShowModel

[inactiveReason]	*string*	Reason that PD remote sync is inactive.
localPort	*integer*	PD remote sync local listening port number.
remoteAddr	*list of IP address*	PD remote sync addresses.

2.64.5 VssUnsupportedServersModel

vssHelpersV4	*list of Helper* see 2.64.1.1	IPv4 DHCP Servers not supporting VSS sub-option.
vssHelpersV6	*list of Helper* see 2.64.1.1	IPv6 DHCP Servers not supporting VSS sub-option.

2.65 show APPLICATION profile

instances	*table(string) = FpgaApplicationInstanceInfo* see 2.65.1	A mapping of FPGA application instance to information specific to each application instance.

2.65.1 FpgaApplicationInstanceInfo

attributes **	*table(string) = string*	Profile attributes. **Since: 4.30.1
fpgaId	*string*	FPGA ID running the application.
[profile]	*string*	Profile Name.
[reason]	*string*	Reason for the error (if in error state).
state	*enum: applied | applying | unknown | error*	State of this profile instance.

2.66 show APPLICATION profile all

profiles	*table(string) = FpgaApplicationProfile* see 2.66.1	Profiles available for the application on the FPGA.

2.66.1 FpgaApplicationProfile

attributes **	*table(string) = string*	Profile attributes. **Since: 4.30.1
compatibleFpgas	*list of string*	FPGAs that this profile is compatible with.
description	*string*	Profile description.
name	*string*	Profile name.

2.67 show GNSS status

gnss	*table(string) = Gnss* see 2.67.1	Map GNSS names to their specifications.

2.67.1 Gnss

altitude	*floating point number*	Altitude.
altitudeOffset	*floating point number*	Offset of Altitude.
clockNsec	*integer*	Nanoseconds from the system clock.
clockSec	*integer*	Seconds from the system clock.
latitude	*floating point number*	Latitude.
latitudeOffset	*floating point number*	Offset of Latitude.
longitude	*floating point number*	Longitude.
longitudeOffset	*floating point number*	Offset of Longitude.
mode	*enum: unknownMode | noFix | twoD | threeD*	Specification for GNSS positioning and grading.
ppsAvailable	*boolean*	PPS available.
ppsNsec	*integer*	Nanoseconds from the PPS source.
ppsSec	*integer*	Seconds from the PPS source.
quantizationErr	*integer*	Quantization error.
satellites	*table(string) = Satellite* see 2.67.1.1	Map satellite names to their specifications.
timeOffset	*floating point number*	Offset of unix time seconds.
unixTimeNsec	*integer*	Nano Seconds past the most recent Seconds since epoch.
unixTimeSec	*integer*	Seconds since epoch.
version	*Version* see 2.67.1.2	Versions of GNSS.

2.67.1.1 Satellite

azimuth	*floating point number*	Rotation (degrees) of the whole antenna around a vertical axis.
elevation	*floating point number*	Angle (degrees) between satellite and horizontal plane.
frequencyId	*integer*	Frequency Id of Satellite 0-13.
gnssId	*integer*	Type of GNSS.
health	*enum: unhealthy | unknownHealth | healthy*	Specification for the health of the satellite.
inUse	*boolean*	Whether the current satellite is in use.
name	*string*	Name of Satellite.
pseudorandomNoiseId	*integer*	Signal that looks as if it is a random noise signal, but actually repeats after a certain length.
snr	*floating point number*	Signal to noise ratio.
spaceVehicleId	*integer*	Serial number assigned to each GPS satellite.

2.67.1.2 Version

`firmwareRevision`	*string*	Name of the firmware revision of GNSS.
`firmwareVersion`	*string*	Name of the firmware version of GNSS.
`modelName`	*string*	Model name of the GNSS.
`serialNumber`	*string*	Serial Number of GNSS.

2.68 show SYNCE

`[info]`	*SynceStatusInfo* see 2.68.1	Synchronous Ethernet status.

2.68.1 SynceStatusInfo

`[cascadedEecCount]` **	*integer*	Number of cascaded EECs. **Since: 4.29.1
`[cascadedEeecCount]` **	*integer*	Number of cascaded eEECs. **Since: 4.29.1
`[etlvFlag]` **	*integer*	EEC/eEEC flag. **Since: 4.29.1
`[freeRunningAndHoldover-QualityLevel]` **	*enum: QL-DNU* | *QL-EEEC* | *QL-FAILED* | *QL-EPRC* | *QL-ST2* | *QL-TNC* | *QL-ST3E* | *QL-SSU-B* | *QL-DUS* | *QL-INV* | *QL-SSU-A* | *QL-NSUPP* | *QL-EEC1* | *QL-PRC* | *QL-EPRTC* | *QL-SMC* | *QL-PRTC* | *QL-INVX* | *QL-EEC2* | *QL-UNC* | *QL-PROV* | *QL-STU* | *QL-PRS*	Quality level of the device when operating in either free-running or holdover state. **Since: 4.28.1
`holdoffDuration` **	*floating point number*	Duration of holdoff timer in seconds. **Since: 4.28.1
`[localClockIdentity]` **	*string*	SyncE clockIdentity of the originator of the extended TLV. **Since: 4.33.2
`[networkOption]`	*enum: 1* | *2*	Network option.
`operState`	*enum: freeRunning* | *holdover* | *lockedAnd-HoldoverAcquired* | *locked*	Operational state of the device.
`qualityLevelEnabled` **	*boolean*	Quality level processing enabled. **Since: 4.28.1
`[selectedClock]`	*ClockSource* see 2.68.1.1	Selected clock source to which the deviced is synchronized.

[selectedQualityLevel]	*enum: QL-DNU | QL-EEEC | QL-FAILED | QL-EPRC | QL-ST2 | QL-TNC | QL-ST3E | QL-SSU-B | QL-DUS | QL-INV | QL-SSU-A | QL-NSUPP | QL-EEC1 | QL-PRC | QL-EPRTC | QL-SMC | QL-PRTC | QL-INVX | QL-EEC2 | QL-UNC | QL-PROV | QL-STU | QL-PRS*	Quality level of the selected clock source.
waitToRestoreDuration **	*floating point number*	Duration of wait-to-restore timer in seconds. **Since: 4.28.1

2.68.1.1 ClockSource

[clockIdentity] **	*string*	SyncE clockIdentity for this clock source. **Since: 4.33.2
[ethernet] **	*interface name*	Ethernet interface providing this clock. **Since: 4.28.1

2.69 show aaa

[enablePassword]	*string*	The encrypted enable password.
users	*table(string) = Aaa.Cli.AaaUser* see 2.69.1	Maps a username to details for this user.

2.69.1 Aaa.Cli.AaaUser

password	*string*	The encrypted password of this account.

2.70 show aaa authentication lockout

lockedUsers	*table(string) = Aaa.Cli.AaaLockedUser* see 2.70.1	Maps a username to details for this user.

2.70.1 Aaa.Cli.AaaLockedUser

lockoutEndTime	*floating point number*	Time that user's account will be unlocked.
lockoutStartTime	*floating point number*	Time that user's account was locked.

2.71 show aaa counters

accountingError	*integer*	Number of error accounting requests.
accountingSuccess	*integer*	Number of successful accounting requests.
authenticationFail	*integer*	Number of failed authentication requests.

authenticationSuccess	*integer*	Number of successful authentication requests.
authenticationUnavailable	*integer*	Number of unavailable authentication requests.
authorizationAborted **	*integer*	Number of aborted authorization requests. **Since: 4.34.0
authorizationAllowed	*integer*	Number of allowed authorization requests.
authorizationDenied	*integer*	Number of denied authorization requests.
authorizationUnavailable	*integer*	Number of unavailable authorization requests.
[counterResetTimestamp]	*floating point number*	Timestamp of last counter reset.
pendingAccountingRequests	*integer*	Number of pending accounting requests.
sessionClosed **	*integer*	Number of times a session is closed. **Since: 4.34.0
sessionOpened **	*integer*	Number of times a session is opened. **Since: 4.34.0

2.72 show aaa methods accounting

commandsAcctMethods	*table(string) = AaaMethodListsAcctMethods* see 2.72.1	A Mapping between command accounting type and methods configured.
dot1xAcctMethods	*table(string) = AaaMethodListsAcctMethods* see 2.72.1	A Mapping between dot1x accounting type and methods configured.
execAcctMethods	*table(string) = AaaMethodListsAcctMethods* see 2.72.1	A Mapping between exec accounting type and methods configured.
systemAcctMethods	*table(string) = AaaMethodListsAcctMethods* see 2.72.1	A Mapping between system accounting type and methods configured.

2.72.1 AaaMethodListsAcctMethods

[consoleAction]	*string*	Present if accounting for console actions is enabled.
consoleMethods	*list of string*	List of methods for a console accounting.
[defaultAction]	*string*	Present if accounting for default actions is enabled.
defaultMethods	*list of string*	List of methods for default accounting.

2.73 show aaa methods all

accounting	*AaaMethodListsAcct* see 2.72	AAA Accounting information.
authentication	*AaaMethodListsAuthen* see 2.73.1	AAA Authentication information.
authorization	*AaaMethodListsAuthz* see 2.73.2	AAA Authorization information.

2.73.1 AaaMethodListsAuthen

dot1xAuthenMethods	*table(string) = AaaMethodListsMethods* see 2.73.1.1	A Mapping between dot1x authentication type and methods configured.
enableAuthenMethods	*table(string) = AaaMethodListsMethods* see 2.73.1.1	A Mapping between enable authentication type and methods configured.
loginAuthenMethods	*table(string) = AaaMethodListsMethods* see 2.73.1.1	A Mapping between login authentication type and methods configured.

2.73.1.1 AaaMethodListsMethods

methods	*list of string*	List of methods for a particular mode.

2.73.2 AaaMethodListsAuthz

commandsAuthzMethods	*table(string) = AaaMethodListsMethods* see 2.73.1.1	A Mapping between command authorization type and methods configured.
execAuthzMethods	*table(string) = AaaMethodListsMethods* see 2.73.1.1	A Mapping between exec authorization type and methods configured.

2.74 show aaa methods authentication

see 2.73.1

2.75 show aaa methods authorization

see 2.73.2

2.76 show access-lists [...]

[ipAclList]	*IpAclList* see 2.76.1	IP access list.
[ipv6AclList]	*Ipv6AclList* see 2.76.2	IPv6 access list.
[macAclList]	*MacAclList* see 2.76.3	MAC access list.
phoneAclBypass	*boolean*	Phone acl bypass enabled.

2.76.1 IpAclList

aclList	*list of _AclBase* see 2.62.1.1	List of ACLs.
phoneAclBypass	*boolean*	Phone ACL bypass enabled.

2.76.2 Ipv6AclList

aclList	*list of _AclBase* see 2.62.1.1	List of ACLs.
phoneAclBypass	*boolean*	Phone ACL bypass enabled.

2.76.3 MacAclList

aclList	*list of _AclBase* see 2.62.1.1	List of ACLs.
phoneAclBypass **	*boolean*	Phone ACL bypass enabled. **Since: 4.33.1

2.77 show adaptive-virtual-topology application-profile [...]

vrfs	*table(string) = AvtAppProfileByVrfModel* see 2.77.1	Application profile information for a VRF.

2.77.1 AvtAppProfileByVrfModel

appProfiles	*table(string) = AvtProfileByAvtModel* see 2.77.1.1	Application Profile information for an adaptive topolgy.
vni	*integer*	VxLAN network identifier for VRF.
vrf	*string*	VRF name.

2.77.1.1 AvtProfileByAvtModel

appProfileId	*integer*	Application profile ID.
appProfileName	*string*	Application profile name.
avtId	*integer*	Adaptive virtual topology service id.
avtName	*string*	Adaptive virtual topology service name.
state	*string*	If the setting is active in status.

2.78 show adaptive-virtual-topology flow [...]

flows	*list of AvtFlowInfo* see 2.78.1	List of flows.

2.78.1 AvtFlowInfo

avtId	*integer*	Adaptive virtual topology identifier.
[avtName]	*string*	Name of adaptive virtual topology.
[directPathId]	*integer*	Direct path ID.
[egressIntf]	*interface name*	Flow egress interface.
[egressPathName]	*string*	Name of the egress path.
key	*AvtFlowKey* see 2.78.1.1	Flow key.
[labelStack]	*list of AvtSegmentLabel* see 2.78.1.2	Label stack of the multihop path.
[lanPathId] **	*integer*	LAN path ID. **Since: 4.32.1
[multihopPathId]	*integer*	Multihop path ID.
[nexthopVtepAddr]	*IP address*	Nexthop VTEP IP address.
transit	*boolean*	Transit node.

2.78.1.1 AvtFlowKey

dstAddr	*IP address*	Destination IP address.
dstPort	*integer*	Destination port.
ipProtocolNumber	*integer*	IP protocol number.
srcAddr	*IP address*	Source IP address.
srcPort	*integer*	Source port.
vrf	*string*	VRF name.

2.78.1.2 AvtSegmentLabel

label	*integer*	Segment label.

2.79 show adaptive-virtual-topology flow ipv6 [...]

see 2.78

2.80 show adaptive-virtual-topology next-hop tunnel encapsulation [...]

vrfs	*table(string) = AvtNextHopByVrfModel* see 2.80.1	Next hop VTEPs per VRF.

2.80.1 AvtNextHopByVrfModel

dpsNextHops	*list of IP address*	List of next hop VTEPs with dynamic path selection encapsulation.
[unknownNextHops] **	*list of IP address*	List of next hop VTEPs with unsupported encapsulation. **Since: 4.35.0
vxlanNextHops	*list of IP address*	List of next hop VTEPs with VXLAN encapsulation.

2.81 show adaptive-virtual-topology path [...]

[regionId] **	*integer*	Adaptive virtual topology region ID. **Since: 4.30.1
[regionName] **	*string*	Adaptive virtual topology region name. **Since: 4.30.1
role **	*enum: region transit | unknown | edge | zone transit | pathfinder*	Role of the node. **Since: 4.30.1
[routerId] **	*IP address*	Router address. **Since: 4.30.1
[siteId] **	*integer*	Adaptive virtual topology site ID. **Since: 4.30.1
[siteName] **	*string*	Adaptive virtual topology site name. **Since: 4.30.1
vrfs	*table(string) = AvtPathsByVrfModel* see 2.81.1	Adaptive virtual topology path information for a VRF.
[zoneId] **	*integer*	Adaptive virtual topology zone ID. **Since: 4.30.1
[zoneName] **	*string*	Adaptive vurtual topology zone name. **Since: 4.30.1

2.81.1 AvtPathsByVrfModel

avts	*table(string) = AvtPathsByAvtModel* see 2.81.1.1	Path information for an adaptive virtual topology.
vni	*integer*	VxLAN network identifier for VRF.
vrf	*string*	VRF name.

2.81.1.1 AvtPathsByAvtModel

avtApplicationProfiles	*list of string*	Adaptive virtual topology application profiles.
avtId	*integer*	Adaptive virtual topology identifier.
avtPaths	*table(string) = AvtPath* see 2.81.1.1.1	Adaptive virtual topology paths, keyed by path type and ID.

2.81.1.1.1 AvtPath

[availableCapacity] **	*integer*	Available capacity in path in Mbps. **Since: 4.33.0
destination	*IP address*	Destination VTEP address.
[directPathId]	*integer*	Direct path ID.
[egressPathName]	*string*	Name of the egress multihop path.
flags	*AvtPathsFlags* see 2.81.1.1.1.1	Path flags.
[jitter]	*floating point number*	Jitter of path in msecs.
[labelStack]	*list of AvtSegmentLabel* see 2.78.1.2	Label stack of the multihop path.

[latency]	*floating point number*	Latency of path in msecs.
[load] **	*floating point number*	Load in path in percentage. **Since: 4.33.0
[loss]	*floating point number*	Loss in path in percentage.
[multihopPathId]	*integer*	Multihop path ID.
[nexthopAddr]	*IP address*	Immediate nexthop VTEP address.
[pathMtu]	*integer*	Maximum transmission unit of path in bytes.
[priority]	*integer*	Priority of path.
[totalCapacity] **	*integer*	Total capacity in path in Mbps. **Since: 4.33.0

2.81.1.1.1.1 AvtPathsFlags

active	*boolean*	Active path used by forwarding engine.
constraintNotMet **	*boolean*	Avt constraint not met for the path. **Since: 4.33.0
directPath	*boolean*	Direct path.
outlier **	*boolean*	Outlier path, not programmed in forwarding engine. **Since: 4.33.0
valid	*boolean*	Valid path processed by forwarding engine.

2.82 show adaptive-virtual-topology path counters [...]

vrfs	*table(string) = AvtCountersByVrfModel* see 2.82.1	Summary of packet distribution on a VRF.

2.82.1 AvtCountersByVrfModel

avts	*table(string) = AvtCountersByAvtModel* see 2.82.1.1	Summary of packet distribution on an AVT.

2.82.1.1 AvtCountersByAvtModel

vteps	*table(IPv4 or IPv6 address) = AvtCountersByVtepModel* see 2.82.1.1.1	Summary of packet distribution on a VTEP IP.

2.82.1.1.1 AvtCountersByVtepModel

paths	*table(string) = AvtCounterEntryModel* see 2.82.1.1.1.1	Summary of packet distribution on a path.

2.82.1.1.1.1 AvtCounterEntryModel

flows	*integer*	Number of flows following the same path.

intf	*interface name*	Local interface name for outgoing traffic.
outBytes	*integer*	Number of out bytes following the same path.
outPkts	*integer*	Number of out pkts following the same path.
rate	*floating point number*	Throughput of the outgoing traffic.

2.83 show address locking

`active`	*boolean*	IP Locking active state.
`configuredIpv4Intfs` **	*list of Interface name*	List of interfaces configured with address locking IPv4. **Since: 4.23.1
`configuredIpv4Vlans` **	*list of integer*	List of VLANs configured with address locking IPv4. **Since: 4.31.0
`configuredIpv6Intfs` **	*list of Interface name*	List of interfaces configured with address locking IPv6. **Since: 4.23.1
`configuredIpv6Vlans` **	*list of integer*	List of VLANs configured with address locking IPv6. **Since: 4.31.0
`enabledIntfs`	*table(Interface name) = IpLockingIntfEnabled* see 2.83.1	A mapping of interfaces to their IPv4 and IPv6 address locking enabled status.
`enabledVlans` **	*table(numeric string) = IpLockingVlanEnabled* see 2.83.1.1	A mapping of VLANs to their IPv4 and IPv6 address locking enabled status. **Since: 4.31.0
`[inactiveReason]`	*string*	Reason that IP Locking is inactive.
`ipv4Enforced` **	*boolean*	Locked-address enforcement is enabled for IPv4. **Since: 4.26.2
`ipv6Enforced` **	*boolean*	Locked-address enforcement is enabled for IPv6. **Since: 4.25.1
`leaseSource` **	*list of string*	How the leases are getting learned. **Since: 4.36.0
`retryInterval` **	*integer*	Configured Lease Query Retry Interval. **Since: 4.30.1
`timeout` **	*integer*	Configured Lease Query Timeout. **Since: 4.30.1

2.83.1 IpLockingIntfEnabled

`assignedVlans` **	*table(numeric string) = IpLockingVlanEnabled* see 2.83.1.1	Mapping of VLANs to which the interface is assigned, to the mode in which they are enabled for address locking. **Since: 4.31.0
`ipv4Enabled`	*boolean*	Address Locking is enabled on interface for IPv4.
`[ipv4InactiveReason]` **	*string*	Reason that Address Locking is not enabled for IPv4. **Since: 4.23.1
`[ipv4Mode]` **	*string*	IPv4 address locking mode. **Since: 4.29.2
`ipv6Enabled`	*boolean*	Address Locking is enabled on interface for IPv6.
`[ipv6InactiveReason]` **	*string*	Reason that Address Locking is not enabled for IPv6. **Since: 4.23.1

[ipv6Mode] **	*string*	IPv6 address locking mode. **Since: 4.29.2

2.83.1.1 IpLockingVlanEnabled

ipv4Enabled	*boolean*	Address Locking is enabled on VLAN for IPv4.
[ipv4InactiveReason]	*string*	Reason that Address Locking is not enabled for IPv4.
[ipv4Mode]	*string*	IPv4 address locking mode.
ipv6Enabled	*boolean*	Address Locking is enabled on VLAN for IPv6.
[ipv6InactiveReason]	*string*	Reason that Address Locking is not enabled for IPv6.
[ipv6Mode]	*string*	IPv6 address locking mode.

2.84 show address locking counters

clientIntfCounters **	*table(Interface name) = ClientIntfCounters* see 2.84.1	A mapping of client interfaces to their counters. **Since: 4.36.0
intfCounters	*table(Interface name) = IntfCounters* see 2.84.2	A mapping of interfaces to their counters.
serverCounters	*table(IPv4 or IPv6 address) = ServerCounters* see 2.84.3	A mapping of server addresses to their counters.
serverIntfCounters **	*table(Interface name) = ServerIntfCounters* see 2.84.4	A mapping of server interfaces to their counters. **Since: 4.36.0

2.84.1 ClientIntfCounters

dhcpDecline	*integer*	Number of DHCPDECLINE packets.
dhcpDiscover	*integer*	Number of DHCPDISCOVER packets.
dhcpRelease	*integer*	Number of DHCPRELEASE packets.
dhcpRequest	*integer*	Number of DHCPREQUEST packets.

2.84.2 IntfCounters

leaseActive	*integer*	Number of lease active packets.
leaseQuery	*integer*	Number of lease query packets.
leaseUnassigned	*integer*	Number of lease unassigned packets.
leaseUnknown	*integer*	Number of lease unknown packets.

2.84.3 ServerCounters

leaseActiveDropped	*integer*	Number of lease active packets that were dropped.
leaseActiveReceived	*integer*	Number of lease active packets that were received.
leaseQuery	*integer*	Number of lease query packets.
leaseUnassignedDropped	*integer*	Number of lease unassigned packets that were dropped.
leaseUnassignedReceived	*integer*	Number of lease unassigned packets that were received.
leaseUnknownDropped	*integer*	Number of lease unknown packets that were dropped.
leaseUnknownReceived	*integer*	Number of lease unknown packets that were received.
unknown	*integer*	Number of packets dropped due to unrecognized packet type.

2.84.4 ServerIntfCounters

dhcpAck	*integer*	Number of DHCPACK packets.
dhcpAckUnknownServer	*integer*	Number of DHCPACK packets from a server IP that is not confugured.
dhcpNak	*integer*	Number of DHCPNAK packets.
dhcpOffer	*integer*	Number of DHCPOFFER packets.

2.85 show address locking counters detail [...]

[actions]	*list of ActionCounters* see 2.85.1	A list of TCAM rules and number of hits.
[interfaces]	*table(Interface name) = IntfCountersList* see 2.85.2	A mapping of interfaces to action counters.

2.85.1 ActionCounters

action	*Action* see 2.85.1.1	Action on the ingressing packet.
[host]	*Host* see 2.85.1.2	The host that has sent the packet.
[senderIp]	*IP address*	IP of the host that sent ARP packet.
[sourceIp]	*IP address*	Source IP of the IPv4 packet.
totalHits	*integer*	Number of packets of a given type.

2.85.1.1 Action

[direction]	*enum: fromServer | toClient | fromClientToServer | toServer*	Direction of the DHCP / DHCP6 packet.
pktAction	*enum: permit | drop*	Action to be taken on ingressing packet.
protocol	*enum: ip | dhcp | dhcp6 | arp | ndp*	Protocol of packet ingressing on IpLocking interface.
[senderIp]	*enum: 0.0.0.0 | any*	IP of the host that sent ARP packet.
[sourceIp]	*enum: 0.0.0.0 | any*	Source IP of the IPv4 packet.
[subType]	*enum: routerSolicitation | routerAdvertisement | routerRedirect*	Neighbor discovery packet type.
[vlan]	*boolean*	Installed over VLAN.

2.85.1.2 Host

ipAddr	*IP address*	IP address of the host.
macAddr	*MAC address*	MAC address of the host.

2.85.2 IntfCountersList

actions	*list of ActionCounters* see 2.85.1	List of actions for an interface.

2.86 show address locking servers

dhcpV4Servers	*table(IPv4 or IPv6 address) = IpLockingProtocol* see 2.86.1	Mapping of servers queried for DHCP v4 leases to the protocol used to query them.
dhcpV6Servers **	*table(IPv4 or IPv6 address) = IpLockingProtocol* see 2.86.1	Mapping of servers queried for DHCP v6 leases to the protocol used to query them. **Since: 4.25.2

2.86.1 IpLockingProtocol

protocol	*enum: arIpQuery | leaseQuery | dhcpPacket | arIpv6Query*	Protocol used to query server.

2.87 show address locking table ipv4 [...]

denyLeases **	*table(Interface name) = IntfLeases* see 2.87.1	A mapping of an interface to its denied leases. **Since: 4.31.0
intfLeases	*table(Interface name) = IntfLeases* see 2.87.1	A mapping of an interface to its leases.

2.87.1 IntfLeases

leases	*table(IPv4 or IPv6 address) = Lease* see 2.87.1.1	A mapping of a lease's IP address to its information.

2.87.1.1 Lease

clientMac	*MAC address*	Client's MAC address.
expirationTime	*integer*	Lease expiration time in UTC.
installed	*boolean*	This lease is installed in hardware.
[overwritten] **	*boolean*	Lease overwritten as IP is denied on interface. **Since: 4.31.0
source **	*enum: server | config*	lease source type. **Since: 4.23.2

2.88 show agent AGENT activity

activityLoopExecNsTime	*integer*	UTC time in nanoseconds at which the current activity loop started.
activityMgrLoopCounter	*integer*	Number of activity loops executed.
attrlogNotEnoughWritable-Bytes	*integer*	Number of times FlowOut could not be processed due to no space left in write buffer or FlowOut Quantum is reached.
avgClockNotifTime	*floating point number*	Average clock notification time in seconds.
avgCombinedFlowOutRunTime	*floating point number*	Average run time spent for all FlowOuts in one activity loop in seconds.
avgFdsPerCycle	*floating point number*	Average file descriptors processed per activity loop.
avgFlowOutRunTime	*floating point number*	Average run time spent for an individual FlowOut in one activity loop in seconds.
avgIOWaitTime	*floating point number*	Average IO wait time in seconds.
avgMountTime	*floating point number*	Average mount time in seconds.
avgRemoteMountTime	*floating point number*	Average remote mount time in seconds.
avgTimeBetweenActivityLoops	*floating point number*	Average time between activity loops in seconds.
currentFlowOutCount	*integer*	Current number of FlowOut.
maxClockNotifTime	*floating point number*	Maximum clock notification time in seconds.
maxCombinedFlowOutRunTime	*floating point number*	Maximum run time spent for all FlowOuts in one activity loop in seconds.
maxFdsPerCycle	*integer*	Maximum file descriptors processed per activity loop.
maxFlowOutCount	*integer*	Maximum number of FlowOut in one activity loop.
maxFlowOutRunTime	*floating point number*	Maximum run time spent for an individual FlowOut in one activity loop in seconds.
maxIOWaitTime	*floating point number*	Maximum IO wait time in seconds.
maxMountStatMountName	*string*	Mount name of mount that took longest to process.
maxMountStatPeerName	*string*	Peer name of mount that took longest to process.
maxMountStatTime	*floating point number*	Maximum time spent processing a mount in seconds.
maxRemoteMountStatMountName	*string*	Mount name of remote mount that took longest to process.
maxRemoteMountStatPeerName	*string*	Peer name of remote mount that took longest to process.
maxRemoteMountStatTime	*floating point number*	Maximum time spent processing a remote mount in seconds.
maxTimeBetweenActivityLoops	*floating point number*	Maximum time between activity loops in seconds.
mountCompleteCount	*integer*	Number of mounts complete.
mountFlowOutOnNonSchedConn-Count	*integer*	Number of mount FlowOut on non-scheduled connection.
mountRemoteCompleteCount	*integer*	Number of remote mounts complete.
mountRemoteRequestCount	*integer*	Number of remote mounts requested.
mountRequestCount	*integer*	Number of mounts requested.

tacElEntityRefCount	*integer*	TAC entity log reference count.
totalFlowOutCount	*integer*	Total number of FlowOut.

2.89 show agent AGENT memory allocations slab content SLABNAME SLABSIZE partial [...]

blockSize	*integer*	The size of blocks allocated from this allocator.
maxBlocksPerPage	*integer*	The maximum number of blocks we can allocate from a single page.
name	*string*	The name of the allocator, "normal", "transient" or custom name assigned.
perThread	*list of SlabAllocatorContentPerThreadModel* see 2.89.1	Per thread statistics for this allocator.
uniqueName	*string*	Unique name of the allocator.

2.89.1 SlabAllocatorContentPerThreadModel

blocks	*list of SlabAllocatorBlockModel* see 2.89.1.1	Blocks in partially filled pages.
threadName	*string*	The name of the thread the statistics pertains to.

2.89.1.1 SlabAllocatorBlockModel

count	*integer*	Number of blocks seen with this data & onFreeList.
data	*integer*	One pointers worth of data from the block, for blocks in use it is from the start of the block, for free blocks it starts 8 bytes into the block. For blocks not large enough this is always zero.
dataSymbolName	*string*	The symbol name corresponding to key.data.
onFreeList	*boolean*	Is the block free.

2.90 show agent AGENT memory allocations slab page statistics

mappedRanges	*list of SlabAllocatorMappedRangeModel* see 2.90.1	List of all mapped memory ranges used by the SlabAllocator.
mappedRangesCoalesced **	*list of SlabAllocatorMappedRangeModel* see 2.90.1	Coalesced list of all mapped memory ranges used by the SlabAllocator. **Since: 4.33.0
pages	*list of SlabAllocatorPageModel* see 2.90.2	List of all pages touched by the SlabAllocator.

2.90.1 SlabAllocatorMappedRangeModel

rangeEnd	*integer*	Memory address of the end of the mapped range.
rangeStart	*integer*	Memory address of the start of the mapped range.

2.90.2 SlabAllocatorPageModel

[blockSize]	*integer*	Size of blocks allocated from this page. Only populated in full and partiallyFull pages.
[blocksPerPage]	*integer*	The number of blocks that fit in one page. Only populated in full and partiallyFull pages.
[freeBlockCount]	*integer*	The number of blocks that are free in the page. Only populated in full and partially-Full pages.
[name]	*string*	Name of the thread and/or allocator the page belongs to, not populated for empty and madvised.
pageStart	*integer*	Memory address of the start of the page.
pageState	*enum: emptyThreadCache2 | full | emptyThreadCache1 | empty | partiallyFull | madvised*	The state of the page.

2.91 show agent AGENT memory detail

memory	*integer*	Memory usage in kB.
mostCommonObjects	*table(string) = integer*	Counts for the 100 most common objects, keyed by their type.
threads	*integer*	Number of threads in agent.

2.92 show agent AGENT task scheduler [...]

schedulers	*table(string) = TaskScheduler* see 2.92.1	Root schedulers indexed by name.

2.92.1 TaskScheduler

[completedTasks]	*TaskList* see 2.92.1.3	List of completed tasks.
[displayOrder]	*integer*	Rendered text output sorts multiple schedulers in ascending order of (displayOrder, schdulerName).
[generalError] **	*string*	Error encountered running show command. **Since: 4.28.1
[history]	*History* see 2.92.1.1	History of task actions.
isRootScheduler	*boolean*	This is a root scheduler.
maxSchedulerSlip	*floating point number*	Max. scheduler slip, in seconds.
priorityStats	*table(string) = PriorityStats* see 2.92.1.2	Task counts and statistics indexed by priority.
schedulerName	*string*	Name of the scheduler.
subSchedulers	*table(string) = TaskScheduler* see 2.92.1	Nested hierarchical subschedulers indexed by a unique key.
[taskNameRegex] **	*string*	Regular expression used to filter task names. **Since: 4.28.0
[taskNameRegexError] **	*string*	If 'taskNameRegex' is supplied and is not a valid regular expression, this will contain an error message for diagnostic purposes. **Since: 4.28.0
tasks	*TaskList* see 2.92.1.3	List of active tasks.

2.92.1.1 History

history	*list of HistoryEvent* see 2.92.1.1.1	History events.
historyEntryCount	*integer*	Max number of entries in circular history.
historyEventCount **	*integer*	The number of events in circular history. **Since: 4.28.0

2.92.1.1.1 HistoryEvent

[eventId]	*string*	The object associated with the event.
eventType	*string*	Which type of event.
nsSinceBoot	*integer*	Event time, in nanoseconds since system boot.

2.92.1.2 PriorityStats

completedTasks	*integer*	Completed tasks with this priority.
idleTasks	*integer*	Idle tasks with this priority.
runnableTasks	*integer*	Runnable tasks with this priority.
totalRunCount	*integer*	Total run count.

2.92.1.3 TaskList

purged **	*integer*	Number of tasks purged due to overflow. **Since: 4.33.2
skipped	*integer*	Skipped tasks with no runs.
tasks	*list of Task* see 2.92.1.3.1	List of tasks.

2.92.1.3.1 Task

[address]	*string*	Memory address of live task.
[completedCount]	*integer*	The number of tasks by this name that have completed.
currentlyRunning	*boolean*	Task is currently running.
firstTaskRunTimestamp **	*integer*	Timestamp of the first time the task ran, in nanoseconds since system boot. If the task has not run it will be zero. **Since: 4.28.0
hasTimer	*boolean*	Task has an associated timer.
lastSchedulingLatency	*floating point number*	Tasks's last scheduling latency, in seconds.
lastTaskRunTimestamp **	*integer*	Timestamp of the most recent time the task ran, in nanoseconds since system boot. If the task as not run it will be zero. **Since: 4.28.0
maxMs	*integer*	Maximum task run time (in ms).
name	*string*	Task name.
onRunQueue	*boolean*	Task is on run queue.
priority	*enum: low | scavenge | high | absolute | critical | normal*	Task priority.
qv200	*integer*	Number of times task used 200% of quantum.
qv500	*integer*	Number of times task used 500% of quantum.
runCount	*integer*	Number of times the Task has run.
[schedulerSuspended] **	*boolean*	Direct or indirect parent scheduler is suspended. **Since: 4.28.0
schedulingLatencyHighWaterMark	*floating point number*	Tasks's scheduling latency high water mark, in seconds.
[subScheduler]	*string*	If the task is a nested hierarchical scheduler, this is identifier in the TaskScheduler.subSchedulers collection.
suspended	*boolean*	Task is suspended.
timerRunning	*boolean*	Task's associated timer is running.
totalRunTime	*floating point number*	Task total run time, in seconds.

[workCount]	*WorkCount* see 2.92.1.3.1.1	Work count.
[workPending]	*WorkPending* see 2.92.1.3.1.2	Pending work.

2.92.1.3.1.1 WorkCount

decayingAvg	*floating point number*	Work count decaying average.
highwater	*integer*	Work count high water mark.
total	*integer*	Total work done.

2.92.1.3.1.2 WorkPending

highwater	*integer*	Pending work high water mark.
pending	*integer*	Pending work.

2.93 show agent AGENT_NAME schanaccel command batch tracking duration

agents	*table(string) = AgentStat* see 2.93.1	Agents using SchanAccel keyed by agent name.

2.93.1 AgentStat

agentName	*string*	Agent that uses SchanAccel.
cmdRings	*table(string) = CmdRingStat* see 2.93.1.1	Command rings using SchanAccel keyed by command ring name.

2.93.1.1 CmdRingStat

stats	*table(numeric string) = TimesliceStat* see 2.93.1.1.1	Histogram for each command ring keyed by UTC timestamp.

2.93.1.1.1 TimesliceStat

countbins	*table(string) = integer*	Number of command batches that finished categorized by time ranges: 'Bin 0': Batches finished within the time range <= 10us, 'Bin 1': Batches finished within the time range 10us <X <= 100us, 'Bin 2': Batches finished within the time range 100us <X <= 1ms, 'Bin 3': Batches finished within the time range 1ms <X <= 10ms, 'Bin 4': Batches finished within the time range 10ms <X <= 100ms, 'Bin 5': Batches finished within the time range 100ms <X <= 1s, 'Bin 6': Batches finished beyond the time range > 1s.

2.94 show agent StrataLb table ExactMatchClbV4 [...]

flow	*table(numeric string) = ExactMatchEntryV4* see 2.94.1	A mapping of flowId to its entry.

2.94.1 ExactMatchEntryV4

dstIp	*IP address*	Destination Ip address.
dstL4Port	*integer*	Destination port.
dstQPair	*integer*	Destination Q pair.
flexCtrAction	*integer*	Flex Control action.
flexCtrObjBusContainerId	*integer*	Flex Control object bus container id.
flexCtrObject	*integer*	Flex Control object.
flowId	*integer*	flowId.
ipProtocol	*integer*	Ip protocol.
nextHop	*integer*	nextHop.
[packetPipeInstance]	*integer*	Packet pipe instance.
rxPort	*integer*	Rx port.

2.95 show agent StrataLb table ExactMatchClbV4NoCounter [...]

flow	*table(numeric string) = ExactMatchEntryV4NoCounter* see 2.95.1	A mapping of flowId to its entry.

2.95.1 ExactMatchEntryV4NoCounter

dstIp	*IP address*	Destination Ip address.
dstL4Port	*integer*	Destination port.
dstQPair	*integer*	Destination Q pair.
flowId	*integer*	flowId.
ipProtocol	*integer*	Ip protocol.
nextHop	*integer*	nextHop.
[packetPipeInstance]	*integer*	Packet pipe instance.
rxPort	*integer*	Rx port.

2.96 show agent StrataLb table ExactMatchClbV4Vxlan [...]

flow	*table(numeric string) = ExactMatchEntryV4Vxlan* see 2.96.1	A mapping of flowId to its entry.

2.96.1 ExactMatchEntryV4Vxlan

dstIp	*IP address*	Destination Ip address.
dstL4Port	*integer*	Destination port.
dstQPair	*integer*	Destination Q pair.

flexCtrAction	*integer*	Flex Control action.
flexCtrObjBusContainerId	*integer*	Flex Control object bus container id.
flexCtrObject	*integer*	Flex Control object.
flowId	*integer*	flowId.
ipProtocol	*integer*	Ip protocol.
nextHop	*integer*	nextHop.
outerDstL4Port	*integer*	Outer destination port.
[packetPipeInstance]	*integer*	Packet pipe instance.
rxPort	*integer*	Rx port.

2.97 show agent StrataLb table ExactMatchClbV4VxlanNoCounter [...]

flow	*table(numeric string) = ExactMatchEntryV4Vxlan-NoCounter* see 2.97.1	A mapping of flowId to its entry.

2.97.1 ExactMatchEntryV4VxlanNoCounter

dstIp	*IP address*	Destination Ip address.
dstL4Port	*integer*	Destination port.
dstQPair	*integer*	Destination Q pair.
flowId	*integer*	flowId.
ipProtocol	*integer*	Ip protocol.
nextHop	*integer*	nextHop.
outerDstL4Port	*integer*	Outer destination port.
[packetPipeInstance]	*integer*	Packet pipe instance.
rxPort	*integer*	Rx port.

2.98 show agent StrataLb table ExactMatchClbV6 [...]

flow	*table(numeric string) = ExactMatchEntryV6* see 2.98.1	A mapping of flowId to its entry.

2.98.1 ExactMatchEntryV6

dstIp6	*IP address*	Destination Ip6 address.
dstL4Port	*integer*	Destination port.
dstQPair	*integer*	Destination Q pair.
flexCtrAction	*integer*	Flex Control action.
flexCtrObjBusContainerId	*integer*	Flex Control object bus container id.
flexCtrObject	*integer*	Flex Control object.
flowId	*integer*	flowId.
ipProtocol	*integer*	Ip protocol.
nextHop	*integer*	nextHop.
[packetPipeInstance] **	*integer*	Packet pipe instance. **Since: 4.35.2

[rxPort] **	*integer*	Receiving port. **Since: 4.35.2

2.99 show agent StrataLb table ExactMatchClbV6LowNoCounter [...]

flow	*table(numeric string) = ExactMatchEntryV6LowNoCounter* see 2.99.1	A mapping of flowId to its entry.

2.99.1 ExactMatchEntryV6LowNoCounter

dstIp6Low	*IP address*	Destination Ip6 Low address.
dstL4Port	*integer*	Destination port.
dstQPair	*integer*	Destination Q pair.
flowId	*integer*	flowId.
ipProtocol	*integer*	Ip protocol.
nextHop	*integer*	nextHop.
[packetPipeInstance]	*integer*	Packet pipe instance.
[rxPort]	*integer*	Receiving port.

2.100 show agent StrataLb table ExactMatchClbV6NoCounter [...]

flow	*table(numeric string) = ExactMatchEntryV6NoCounter* see 2.100.1	A mapping of flowId to its entry.

2.100.1 ExactMatchEntryV6NoCounter

dstIp6	*IP address*	Destination Ip6 address.
dstL4Port	*integer*	Destination port.
dstQPair	*integer*	Destination Q pair.
flowId	*integer*	flowId.
ipProtocol	*integer*	Ip protocol.
nextHop	*integer*	nextHop.
[packetPipeInstance]	*integer*	Packet pipe instance.
[rxPort]	*integer*	Receiving port.

2.101 show agent StrataLb table ExactMatchIpfixRoceV4 [...]

flow	*table(numeric string) = ExactMatchEntryIpfixRoceV4* see 2.101.1	A mapping of entry index to its entry.

2.101.1 ExactMatchEntryIpfixRoceV4

dstIp	*IP address*	Destination IP address.
flexCtrObject	*integer*	Flex Counter object.
[packetPipeInstance]	*integer*	Packet pipe instance.
[rxPort]	*integer*	Receiving port.
srcIp	*IP address*	Source IP address.
srcL4Port	*integer*	Source L4 port.
vrf	*integer*	VRF ID.

2.102 show agent cpu [...]

agents	*table(string) = AgentCpuEntry* see 2.102.1	Mapping from Agent name to Agent CPU statistics.

2.102.1 AgentCpuEntry

lastCpuPct	*integer*	Agent current CPU usage (percent).
maxCpuDuration	*integer*	Duration of agent peak CPU usage (seconds).
maxCpuPct	*integer*	Agent peak CPU usage (percent).
pid **	*integer*	Agent process ID. **Since: 4.29.1
threads **	*table(numeric string) = AgentThreadCpuEntry* see 2.102.1.1	Mapping from thread ID to thread CPU statistics. **Since: 4.29.1
totalCpuTime **	*floating point number*	Agent total CPU usage (seconds). **Since: 4.29.1

2.102.1.1 AgentThreadCpuEntry

lastCpuPct	*integer*	Thread current CPU usage (percent).
maxCpuDuration	*integer*	Duration of thread peak CPU usage (seconds).
maxCpuPct	*integer*	Thread peak CPU usage (percent).
name	*string*	Thread name.
totalCpuTime	*floating point number*	Thread total CPU usage (seconds).

2.103 show agent event history [...]

events	*list of EventHistoryAgent.Cli.LogEntryModel* see 2.103.2	List of EventHistory events.
filters	*EventHistoryAgent.Cli.EventHistoryFiltersModel* see 2.103.1	Regular expression filters to get a subset of EventHistory.

2.103.1 EventHistoryAgent.Cli.EventHistoryFiltersModel

agent	*string*	Agent filter.
group	*string*	Group filter.

2.103.2 EventHistoryAgent.Cli.LogEntryModel

agentName	*string*	Agent name.
category **	*string*	EventHistory category. **Since: 4.21.0
message	*string*	Log message.
messageGroup	*string*	Message group.
timestamp	*floating point number*	Timestamp when the event was logged.

2.104 show agent memory [...]

agents	*table(string) = AgentMemoryEntry* see 2.104.1	Mapping from Agent name to Agent memory statistics.

2.104.1 AgentMemoryEntry

lastVmRss	*integer*	Agent current resident set size (KiB).
lastVmSize	*integer*	Agent current virtual memory usage (KiB).
maxVmRss	*integer*	Agent peak resident set size (KiB).
maxVmSize	*integer*	Agent peak virtual memory usage (KiB).

2.105 show agent memory allocations (delta DELTA) [...]

types	*table(string) = ShowAllocsTypeDiffModel* see 2.105.1	A mapping of type name to its memory usage information.

2.105.1 ShowAllocsTypeDiffModel

currentAllocations	*integer*	Number of objects currently allocated.
deltaAllocations	*integer*	Difference in Number of object allocations.
memoryAllocationOverhead	*integer*	Memory allocation overhead in bytes.
prevAllocations	*integer*	Number of objects allocated when the command was run previously.
size	*integer*	Size of type in bytes.

2.106 show agent memory allocations [...]

types	*table(string) = ShowAllocsTypeModel* see 2.106.1	A mapping of type name to its memory usage information.

2.106.1 ShowAllocsTypeModel

currentAllocations	*integer*	Number of objects currently allocated.
highestAllocations	*integer*	High watermark of currentAllocations.
memoryAllocationOverhead	*integer*	Memory allocation overhead in bytes.
size	*integer*	Size of type in bytes.
totalAllocations	*integer*	Total number of allocations (calls to new).

2.107 show agent memory allocations heap summary [...]

agents	*table(string) = AgentLib.Cli.Mallinfo* see 2.107.1	Heap summary by agent.

2.107.1 AgentLib.Cli.Mallinfo

[arena]	*integer*	Non-mmapped space allocated (bytes).
[fordblks]	*integer*	Total free space (bytes).
[fsmblks]	*integer*	Space in freed fastbin blocks (bytes).
[hblkhd]	*integer*	Space allocated in mmapped regions (bytes).
[hblks]	*integer*	Number of mmapped regions.
[keepcost]	*integer*	Top-most, releasable space (bytes).
[ordblks]	*integer*	Number of free chunks.
[smblks]	*integer*	Number of free fastbin blocks.
status	*string*	Heap summary query status (anything other than 'success' indicates an error).
[uordblks]	*integer*	Total allocated space (bytes).
[usmblks]	*integer*	Maximum total allocated space (bytes).

2.108 show agent memory allocations slab [...]

agents	*table(string) = SlabAllocatorAgentModel* see 2.108.1	Per agent statistics, keyed by agent name.
errorAgents	*table(string) = string*	Errors encountered, keyed by agent name.

2.108.1 SlabAllocatorAgentModel

allocatedPages	*integer*	Number of pages allocated to individual allocators or held in per thread free caches.
allocators	*table(string) = SlabAllocatorStatsModel* see 2.108.1.2	Per allocator statistics, keyed by unique name of the allocator.
emptyPages	*integer*	Number of pages that are empty, but dirty.
emptyPagesPerThread	*list of SlabAllocatorEmptyPagesPerThreadModel* see 2.108.1.1	Number of empty pages in the per thread empty page cache.
mmapPages	*integer*	Number of pages of virtual address mmap'd by the slab allocator.
pageSize	*integer*	Size of the internal pages in bytes.
releasedPages	*integer*	Number of pages that were used in the past, but released back to the kernel, these do not consume physical memory.
touchedPages	*integer*	Number of pages touched by the slab allocator.

2.108.1.1 SlabAllocatorEmptyPagesPerThreadModel

emptyPages	*integer*	Number of empty pages.
threadName	*string*	The name of the thread the statistics pertains to.

2.108.1.2 SlabAllocatorStatsModel

blockSize	*integer*	The size of blocks allocated from this allocator.
maxBlocksPerPage	*integer*	The maximum number of blocks we can allocate from a single page.
name	*string*	The name of the allocator, "normal", "transient" or custom name assigned.
perThread	*list of SlabAllocatorStatsPerThreadModel* see 2.108.1.2.1	Per thread statistics for this allocator.

2.108.1.2.1 SlabAllocatorStatsPerThreadModel

blocksFree	*integer*	Number of blocks free.
blocksInUse	*integer*	Number of blocks in use.
fragmentationScore **	*floating point number*	Fragmentation score: pages*free/used. **Since: 4.30.2

pages	*integer*	Number of pages used by this allocator in this thread.
pagesHighWaterMark **	*integer*	Largest number of pages used by this allocator in this thread. **Since: 4.31.1
pagesWithBlocksFreeCount	*table(numeric string) = integer*	Key is number of blocks in a page that is free, value is the number of pages with that number of blocks free.
threadName	*string*	The name of the thread the statistics pertains to.

2.109 show agent memory allocations slab sort ((blocks (in-use | free | percent-free)) | (memory (in-use | free | percent-free | overhead | total | mmap | madvise | dirty)))

see 2.108

2.110 show agent names [...]

agentNames	*list of string*	List of Agent names in Sysdb's launcher config.

2.111 show agent oom scores [...]

agents	*table(string) = AgentOomScoresEntry* see 2.111.1	Mapping from Agent name to Agent OOM scores information.

2.111.1 AgentOomScoresEntry

maxVmSize	*integer*	Agent peak virtual memory size.
oomScore	*integer*	Out-of-memory score of agent: -1000 (least likely to be a victim when system needs to find memory) to 1000.
oomScoreAdj	*integer*	Adjustment up or down (1000 to -1000) to apply to the computed OOM-score of the agent in order to make it more or less likely to become a target/victim of out-of-memory killer).
rssAnon	*integer*	Agent resident anonymous memory size.
vmSize	*integer*	Agent virtual memory size.

2.112 show agent ping [...]

agents	*table(string) = AgentPingEntry* see 2.112.1	Mapping from Agent name to Agent ping statistics.

2.112.1 AgentPingEntry

[lastPingRtt]	*floating point number*	RTT in seconds of the most recent agent ping event.
[lastPingTimestamp]	*integer*	Epoch timestamp in seconds of the most recent agent ping event.
[maxPingRtt]	*floating point number*	Max RTT in seconds observed for agent ping event.
[maxPingTimestamp]	*integer*	Epoch timestamp in seconds when max RTT value was recorded.

2.113 show agent qtrace event tracking [...]

[events]	*list of QtEventTracking-EntryModel* see 2.113.1	List of wall-clock events from qt file.

2.113.1 QtEventTrackingEntryModel

eventData	*string*	Qt wall-clock event data.
eventKey	*string*	Qt wall-clock event message.
eventType	*string*	Qt wall-clock event type.
timestamp	*floating point number*	UTC timestamp when the event occured.

2.114 show agent qtrace size [...]

agents	*table(string) = AgentLib.-Cli.AgentQtHandleInfos* see 2.114.1	Map an agent's name to its set of HandleInfos.

2.114.1 AgentLib.Cli.AgentQtHandleInfos

handles	*table(string) = AgentLib.-Cli.AgentQtHandleInfo* see 2.114.1.1	Map a qt handle name to its HandleInfo in an agent.

2.114.1.1 AgentLib.Cli.AgentQtHandleInfo

multithreaded	*boolean*	Whether this is a multithreaded QuickTrace handle.
sizes	*list of integer*	List of sizes in KiB for each trace level in a quicktrace handle.

2.115 show agent runnability [...]

agents	*table(string) = AgentRunnability* see 2.115.1	Mapping from agent name to agent runnability status.

2.115.1 AgentRunnability

agentName	*string*	Agent name.
reason	*list of string*	The reasons the agent is or is not runnable.
role	*string*	The redundancy role the agent is expected to run in.
status	*boolean*	True if this agent is runnable.

2.116 show agent sfe threads flow cache scan counters

counter	*WalkerCounter* see 2.116.1	Flow cache walker counters per feature.

2.116.1 WalkerCounter

walkerCounters	*table(string) = Counter* see 2.116.1.1	Flow cache walker counters per feature.

2.116.1.1 Counter

counters	*table(string) = integer*	Key and value map.

2.117 show agent sfe threads flow cache scan counters detail [...]

counterDetail	*table(numeric string) = WalkerCounter* see 2.116.1	Flow cache walker counters per thread.

2.118 show agent sfe threads flow cache scan status [...]

status	*table(numeric string) = WalkerStatus* see 2.118.1	Flow cache walker status per thread.

2.118.1 WalkerStatus

bucketEnd	*integer*	Bucket end index.
bucketStart	*integer*	Bucket start index.
lastScanDuration	*integer*	Last scan duration in milliseconds.
scanCount	*integer*	Scan count.

2.119 show agent socket attrlog [...]

agentErrors **	*table(string) = string*	Errors encountered (keyed by agent name). **Since: 4.35.2
agents	*table(string) = AgentSocketAttrLogInfo* see 2.119.1	Socket buffer stats for the agent's outbound (TX) AttrLog sockets.

2.119.1 AgentSocketAttrLogInfo

connectedPeers	*list of AgentSocketAttrLogPeerInfo* see 2.119.1.1	Socket buffer stats for the outbound (TX) AttrLog socket buffer toward a specific connected peer.

2.119.1.1 AgentSocketAttrLogPeerInfo

congestionActive	*boolean*	Congestion status of the socket, indicating that the socket buffer's utilization is above a normal/healthy level.
[congestionCount]	*integer*	Number of times congestion was triggered on the socket.
[congestionEndTime]	*floating point number*	Time when congestion last ended on this connection.
[congestionMaxDuration]	*floating point number*	Length of the longest congestion event on this connection.
congestionStartTime	*floating point number*	Time when congestion last started on this connection.
[congestionTotalDuration]	*floating point number*	Total time spent congested on this connection (across all congestions).
[depthKb]	*integer*	Socket buffer current queue depth (in kB).
highWatermarkKb	*integer*	Socket buffer fill high watermark (in kB).
highWatermarkTime	*floating point number*	Time when the socket buffer fill high watermark was encountered.
limitKb	*integer*	Socket buffer absolute fill limit (in kB).
peerName	*string*	Name of the peer on the other end of the connection.
peerPid **	*integer*	Process ID of the peer on the other end of the connection. **Since: 4.36.0
[starvationCount]	*integer*	Number of times data transmissions was delayed for an excessively long time due to congestion, causing the socket buffer to fully drain while buffered data is waiting for transmission.

2.120 show agent socket attrlog detail [...]

see 2.119

2.121 show agent stages startup log

stagesClassLog **	*list of BootClassStagesLogModel* see 2.121.1	List of stage class logs. **Since: 4.34.1

2.121.1 BootClassStagesLogModel

logs	*list of BootStagesLogEntryModel* see 2.121.1.1	List of boot stage logs.

2.121.1.1 BootStagesLogEntryModel

deltaTime	*floating point number*	Time of the log relative to stage start.
msg	*string*	Log message.
timestamp	*floating point number*	Switch time when the log event occured.
utcTimestamp **	*floating point number*	UTC Timestamp when the log event occured. **Since: 4.36.0

2.122 show agent uptime [...]

agents	*table(string) = AgentUptimeEntry* see 2.122.1	Mapping from Agent name to Agent restart statistics.

2.122.1 AgentUptimeEntry

agentRunning **	*boolean*	Whether agent is currently running. **Since: 4.28.2
agentStartTime	*integer*	Agent start time in UTC seconds since epoch.
restartCount	*integer*	Number of agent restarts.

2.123 show agent warm-restart [...]

agents	*table(string) = ShowAgentWarmRestartEntry* see 2.123.1	Mapping from Agent name to Agent warm restart configurations.

2.123.1 ShowAgentWarmRestartEntry

allowedCount	*integer*	Number of warm restarts allowed.
windowLength	*floating point number*	Window length in seconds for warm restarts.

2.124 show aliases [...]

aliases	*table(string) = Cli.Model.Alias* see 2.124.1	Maps alias names to their corresponding commands.
commandsPath **	*string*	Directory of scripts to be converted to aliases. **Since: 4.18.1
dynamicAliases **	*table(string) = Cli.Model.Alias* see 2.124.1	Maps aliases of scripts in commandsPath to their corresponding commands. **Since: 4.18.1
regexAliases **	*list of Cli.Model.RegexAlias* see 2.124.2	Regular expression aliases. **Since: 4.24.0

2.124.1 Cli.Model.Alias

commands	*table(numeric string) = string*	Map a sequence number to a command.

2.124.2 Cli.Model.RegexAlias

commands	*table(numeric string) = string*	Map a sequence number to a command.
regex	*string*	A Python-compatible regular expression.

2.125 show application traffic recognition [...]

applications	*table(string) = ApplicationModel* see 2.125.1	Applications configured on the switch, keyed by application name.

2.125.1 ApplicationModel

classifier	*enum: customDpi | ipv4 | dpi*	The classifier used for the application.
services	*table(string) = ServiceModel* see 2.125.1.1	Services available for the application, keyed by service name.

2.125.1.1 ServiceModel

category	*string*	Category assigned to the application service.

2.126 show application traffic recognition counters [...]

applications	*table(string) = ApplicationCountersModel* see 2.126.1	Applications configured on the switch, keyed by application name.

2.126.1 ApplicationCountersModel

appId	*integer*	Application identifier.
services	*table(string) = ServiceVrfsModel* see 2.126.1.1	Services available for the application, keyed by service name.

2.126.1.1 ServiceVrfsModel

serviceId	*integer*	Service identifier.
vrfs	*table(string) = VrfApplicationCountersModel* see 2.126.1.1.1	Application service data keyed by VRF name.

2.126.1.1.1 VrfApplicationCountersModel

categories	*table(string) = integer*	A mapping of category names to ids.
counters	*ApplicationDataModel* see 2.126.1.1.1.1	Counters for an application service.
profiles	*table(string) = integer*	A mapping of profile names to ids.
vrfId	*integer*	VRF identifier.

2.126.1.1.1.1 ApplicationDataModel

classifierPackets	*integer*	Number of packets processed by the classifier.
totalBytes	*integer*	Number of bytes received for an application service.
totalFlows	*integer*	Number of flows received for an application service.
totalPackets	*integer*	Number of packets received for an application service.

2.127 show arp agent (ipv4 | ipv6) cache capacity [...]

capacityKinds	*table(string) = Arp.Cli.CapacityKinds* see 2.127.1	Mapping from cache entry kind to neighbor cache capacity kind.

2.127.1 Arp.Cli.CapacityKinds

interfaces	*table(Interface name) = Arp.Cli.Capacity* see 2.127.1.1	Mapping from interface to neighbor cache capacity.

2.127.1.1 Arp.Cli.Capacity

cacheEntries	*list of IP address*	List of IP addresses of the neighbor cache entries.
capacity	*integer*	Capacity of the neighbor cache.
count	*integer*	Count of the neighbor cache entries.

linkLocalExcluded **	*boolean*	Exclude link local from Cache Capacity. **Since: 4.33.2

2.128 show arp agent (ipv4 | ipv6) input [...]

entryMap	*table(string) = Arp.Cli.ArpInputEntryList* see 2.128.1	Mapping of VRF name to list of ARP entries.

2.128.1 Arp.Cli.ArpInputEntryList

entrys	*list of Arp.Cli.ArpInputEntry* see 2.128.1.1	ARP input entry list.

2.128.1.1 Arp.Cli.ArpInputEntry

entryType	*string*	Type of entry (Either static or dynamic).
ethAddr	*string*	MAC address.
genId	*string*	Gen ID of dynamic entries.
intfId	*interface name*	Name of the interface.
ipAddr	*IP address*	Ip or Ipv6 address.
refreshTime	*string*	Quick Refresh time.
source	*string*	Source of the ARP entries.

2.129 show arp agent (ipv4 | ipv6) output [...]

see 2.128

2.130 show arp counters hardware ingress [...]

interfaces	*table(Interface name) = Arp.Cli.ArpCounter* see 2.130.1	Mapping of interface to ARP hardware counters.

2.130.1 Arp.Cli.ArpCounter

replies	*integer*	ARP replies.
requests	*integer*	ARP requests.

2.131 show arp monitor [...]

entryList	*list of Arp.Cli.MonitoredNexthopEntry* see 2.131.1	Monitored nexthop entry.
totalEntries	*integer*	Total number of monitored nexthop entries.

vrfList	*list of Arp.Cli.Monitored-NexthopVrfSummary* see 2.131.2	Monitored nexthop entry count.

2.131.1 Arp.Cli.MonitoredNexthopEntry

intf	*interface name*	Name of the interface.
ipAddr	*string*	Nexthop Ip or Ipv6 address.

2.131.2 Arp.Cli.MonitoredNexthopVrfSummary

entries	*integer*	Total number of monitored nexthop entries for the Vrf.
vrfname	*string*	Name of the Vrf.

2.132 show arp monitor summary

see 2.131

2.133 show arp | (ipv6 neighbors) bridged [...]

see 2.45

2.134 show backplane-channel [...]

portChannels	*table(Interface name) = PortChannel* see 2.134.1	Map port-channels to their member information.

2.134.1 PortChannel

activePorts	*table(Interface name) = ActivePort* see 2.134.1.1	Map active ports to time they became active, protocol, and mode.
[currWeight] **	*integer*	Port channel active ports total weight. **Since: 4.26.2
[fallbackState]	*enum: monitoring | configured | unconfigured | passive | enabled | initialized | locallyOnly*	Port Channel fallback state.
inactiveLag **	*boolean*	Exceeds the port channel config limit. **Since: 4.25.0
inactivePorts	*table(Interface name) = InactivePort* see 2.134.1.2	Map inactive ports to time and reason they became inactive.
[maxLinks] **	*integer*	Port channel configured maximum links. **Since: 4.34.0
[maxWeight] **	*integer*	Port channel active ports maximum total weight allowed. **Since: 4.26.2
[minLinks] **	*integer*	Port channel configured minimum links. **Since: 4.26.2
[minSpeed] **	*string*	Port channel configured minimum speed (gbps or mbps). **Since: 4.26.2
recircFeature	*list of string*	Contains a list of features that uses recirc-channel.
rxPorts **	*table(Interface name) = RxPort* see 2.134.1.3	Map receive-only ports to time they start receiving and reason they don't transmit. **Since: 4.27.0

2.134.1.1 ActivePort

[collecting] **	*boolean*	Member port is capable of receiving packets. **Since: 4.31.0
[distributing] **	*boolean*	Member port is capable of transmitting packets. **Since: 4.31.0
[lacpMode]	*enum: passive | active | off*	LACP active or passive mode.
[protocol]	*enum: static | lacp | unconfigured*	Lag mode configuration.
[timeBecameActive]	*floating point number*	UTC time the port became active.
[weight] **	*integer*	Member port weight. **Since: 4.26.2

2.134.1.2 InactivePort

[reasonUnconfigured]	*string*	Reason interface is not part of the LAG.
[timeBecameInactive]	*floating point number*	UTC time the interface was no longer active.

2.134.1.3 RxPort

[reason]	*string*	Reason port is receiving but not transmitting.
[time]	*floating point number*	UTC time the port started receiving.

2.135 show backplane-channel limits

backplaneChannelLimits	*table(string) = LagGroupLimits* see 2.135.1	Map a LAG Group name to the ports it applies to, and the hardware lag limits applicable to them.

2.135.1 LagGroupLimits

[lagFeature] **	*enum: Backplane channel | lag | unknown | round-robin ordered*	Port-Channel feature limits. **Since: 4.34.2
maxPortChannels	*integer*	Maximum number of active port-channels.
maxPortsPerPortChannel	*integer*	Maximum number of active ports allowed in a port-channel.
portList	*list of Interface name*	Compatible ports based on hardware limits.

2.136 show banner login

loginBanner	*string*	Login banner for the switch.

2.137 show banner motd

motd	*string*	Message of the day for the switch.

2.138 show bfd ((ip access-list) | (ipv6 access-list)) [...]

see 2.62

2.139 show bfd hardware acceleration

reasons **	*list of string*	List of reasons why hardware acceleration is not running. **Since: 4.23.0
running	*boolean*	Hardware acceleration is running.

supported	*boolean*	Hardware acceleration is supported by platform.

2.140 show bfd hardware utilization [...]

resources	*table(string) = BfdHwResource* see 2.140.1	Hardware resource information keyed by the resource's name.

2.140.1 BfdHwResource

maxSessions	*integer*	Maximum number of sessions configured of the chip.
[numSessions]	*integer*	Number of sessions configured on a chip.
[sessions]	*list of BfdHwResourceSession* see 2.140.1.1	List of sessions configured on the chip.
ssoSupported **	*boolean*	HW BFD SSO is supported. **Since: 4.32.1

2.140.1.1 BfdHwResourceSession

intf	*interface name*	Local egress interface.
ip	*IP address*	IP address of peer.
localDisc	*integer*	Local discriminator of BFD session.
sessType	*enum: sessionTypeLagLegacy | sessionTypeVxlanTunnel | sessionTypeVxlanTunnel echo | sessionTypeSbfdInitiator | sessionTypeMicroLegacy | sessionTypeMultihop | sessionTypeMultihop echo | sessionTypeNormal | sessionTypeLagRfc7130 echo | sessionTypeMicroLegacy echo | sessionTypeLagRfc7130 | sessionTypeMicroRfc7130 | sessionTypeNormal echo | sessionTypeSbfdReflector | sessionTypeLagLegacy echo | sessionTypeMicroRfc7130 echo*	BFD session type.
vrf	*string*	VRF that peer is configured in.

2.141 show bfd peers [...]

revision 4

vrfs	*table(string) = BfdNeighborVrf* see 2.141.1	A mapping between vrf and peer stats.

2.141.1 BfdNeighborVrf

ipv4InitiatorNeighbors	*table(IPv4 or IPv6 address) = SbfdInitiatorTunnel* see 2.141.1.2	A mapping between IPv4 peer address and tunnel ID.
ipv4Neighbors	*table(IPv4 or IPv6 address) = BfdNeighborInterface* see 2.141.1.1	A mapping between IPv4 peer address and interface.
ipv4ReflectorNeighbors	*table(IPv4 or IPv6 address) = SbfdReflector* see 2.141.1.3	A mapping between IPv4 peer address and remote discriminators.
ipv6InitiatorNeighbors	*table(IPv4 or IPv6 address) = SbfdInitiatorTunnel* see 2.141.1.2	A mapping between IPv6 peer address and tunnel ID.
ipv6Neighbors	*table(IPv4 or IPv6 address) = BfdNeighborInterface* see 2.141.1.1	A mapping between IPv6 peer address and interface.
ipv6ReflectorNeighbors	*table(IPv4 or IPv6 address) = SbfdReflector* see 2.141.1.3	A mapping between IPv6 peer address and remote discriminators.

2.141.1.1 BfdNeighborInterface

peers	*table(Interface name) = BfdNeighborIntfPeer* see 2.141.1.1.1	A mapping between interface and peer type.

2.141.1.1.1 BfdNeighborIntfPeer

types	*table(string) = BfdNeighborSrcAddr* see 2.141.1.1.1.1	A mapping between peer type and source address.

2.141.1.1.1.1 BfdNeighborSrcAddr

peerStats	*table(IPv4 or IPv6 address) = PeerStats* see 2.141.1.1.1.2	A mapping between source address and peer stats.

2.141.1.1.1.2 PeerStats

authProfileName	*string*	Configured authentication profile.

authType	*enum: Keyed Sha1 | Meticulous Sha1 | Password | Meticulous Md5 | None | Keyed Md5*	Authentication mode.
[description] **	*string*	Peer description provided by the app. **Since: 4.35.0
[destPort]	*integer*	Destination Port of SBFD Reflector.
[echoRxStats]	*RxStats* see 2.141.1.1.1.7	Echo Rx statistics for peer.
[echoTxStats]	*TxStats* see 2.141.1.1.1.8	Echo Tx statistics for peer.
[kernelIfIndex]	*integer*	Kernel interface.
l3intf	*interface name*	Local egress interface.
lastDiag	*enum: diagCtrlTimeout | diagRevConcatPathDown | diagConcatPathDown | diagNeighDown | diagPathDown | diagForwardingReset | diagAdminDown | diagNone | diagEchoFail*	Last diagnostic for reason of change to Down state.
lastDown	*floating point number*	Last time peer session went down in seconds, 0.0 if never down.
lastUp	*floating point number*	Last time peer session came up in seconds, 0.0 if never up.
localDisc	*integer*	Local discriminator of BFD session.
[peerStatsDetail]	*PeerStatsDetail* see 2.141.1.1.1.3	Detailed peer stats.
proxy	*boolean*	S-BFD proxy Enabled.
remoteDisc	*integer*	Remote discriminator BFD session.
[rttStats]	*RttStats* see 2.141.1.1.1.6	RTT statistics for peer.
[rxStats]	*RxStats* see 2.141.1.1.1.7	Rx statistics for peer.

sessType	*enum: sessionTypeLagLegacy | sessionTypeVxlanTunnel | sessionTypeVxlanTunnel echo | sessionTypeSbfdInitiator | sessionTypeMicroLegacy | sessionTypeMultihop | sessionTypeMultihop echo | sessionTypeNormal | sessionTypeLagRfc7130 echo | sessionTypeMicroLegacy echo | sessionTypeLagRfc7130 | sessionTypeMicroRfc7130 | sessionTypeNormal echo | sessionTypeSbfdReflector | sessionTypeLagLegacy echo | sessionTypeMicroRfc7130 echo*	BFD session type.
status	*enum: down | up | adminDown | init*	State of the peer.
[tunnelId]	*integer*	TunnelID of SBFD Initiator.
[tunnelIdx]	*integer*	Tunnel index of SBFD Initiator.
[tunnelType]	*enum: srTeSegmentListTunnel | eosSdkSbfdSessionTunnel*	Tunnel type of SBFD Initiator.
[txStats]	*TxStats* see 2.141.1.1.1.8	Tx statistics for peer.

2.141.1.1.1.3 PeerStatsDetail

apps	*list of string*	Registered protocols.
detectMult	*integer*	Number of consecutive BFD packets missed before failure.
detectTime	*integer*	Detection timeout in microseconds.
echoActive	*boolean*	Active echo session with both tx and rx session.
echoDisc	*integer*	Discriminator of BFD Echo session.
echoOn	*boolean*	Echo turned on.
hwAcceleratedStates	*table(string) = boolean*	Mapping of session type to hw acceleration state.
lastDemand	*boolean*	Last received Peer demand bit.
lastDetectMult	*integer*	Last received Peer detection multiplier.
lastDiag	*integer*	Last received Peer diagnostic code between values 0-8.
lastEchoRxIntv	*integer*	Last received Echo Rx interval in microseconds.
lastFinal	*boolean*	Last received Peer final bit.
lastLength	*integer*	Last received packet length.
lastMinRxIntv	*integer*	Last received minimum Rx interval in microseconds.

lastMinTxIntv	*integer*	Last received minimum Tx interval in microseconds.
lastMyDiscU32	*integer*	Last received Peer discriminator.
lastPoll	*boolean*	Last received Peer poll bit.
lastState	*enum: down* | *up* | *adminDown* | *init*	Last received Peer BFD session state.
lastVersion	*integer*	Last received Peer BFD version.
lastYourDiscU32	*integer*	Last received local discriminator.
localIpAddr	*IP address*	Local IP.
operEchoTxRxInterval	*integer*	Operational rate in microseconds at which Bfd echo packets are sent and received.
operRxInterval	*integer*	Operational rate in microseconds at which BFD control pckets are received.
operTxInterval	*integer*	Operational rate in microseconds at which BFD control packets are sent.
remoteDetectMult	*integer*	Receive multiplier of peer.
remoteMinRxInterval	*integer*	Minimum rate in microseconds at which BFD packets can be received by the peer.
role	*enum: active* | *passive*	BFD role.
segmentType	*enum: ipNexthop* | *mplsLabel* | *invalid*	Segment type.
segments	*list of integer*	Proxy segment list.
[tunnelInfo]	*TunnelInfo* see 2.141.1.1.1.4	Tunnel information of tunnelId.

2.141.1.1.1.4 TunnelInfo

ipDscp	*integer*	IP DSCP value.
mplsExp	*integer*	MPLS EXP value.
mplsLabels	*list of integer*	MPLS label stack.
[sbfdReturnPathLabelStack]	*list of integer*	MPLS label stack of SBFD return path.
[via]	*Via* see 2.141.1.1.1.5	Via next hop.

2.141.1.1.1.5 Via

interface	*interface name*	Egress L3 interface of the next hop.
nextHop	*IP address*	Next hop IP address.

2.141.1.1.1.6 RttStats

avgRtt	*integer*	Average RTT in microseconds.
lastRtt	*integer*	Last RTT in microseconds.
maxRtt	*integer*	Maximum RTT in microseconds.
minRtt	*integer*	Minimum RTT in microseconds.

2.141.1.1.1.7 RxStats

[avgPeriod]	*integer*	Average time between received packets in microseconds.
[lastRxState]	*enum: down | up | adminDown | init*	Last Rx state of the peer.
[lastRxStateChg]	*floating point number*	Time of last Rx packet of state change received in seconds.
[lastRxTime]	*floating point number*	Time of last successfully authenticated and validated packet received in seconds.
[maxPeriod]	*integer*	Maximum time between received packets in microseconds.
[minPeriod]	*integer*	Minimum time between received packets in microseconds.
numReceived	*integer*	Number of packets received.

2.141.1.1.1.8 TxStats

[avgLateness]	*integer*	Average number of microseconds messages sent after its configured period.
[lastTxTime]	*floating point number*	Time of last successfully transmitted packet in seconds.
[maxLateness]	*integer*	Max number of microseconds a message sent after its configured period.
[minLateness]	*integer*	Minimum number of microseconds a message sent after its configured period.
numSent	*integer*	Number of packets sent since last Tx config change.
[sentAfter3p]	*integer*	Number of packets sent later than three periods of last packet.
[sentWithin1p]	*integer*	Number of packets sent within configured period since last packet.
[sentWithin2p]	*integer*	Number of packets sent later than one period but before two periods of last packet.
[sentWithin3p]	*integer*	Number of packets sent later than two periods but before three periods of last packet.

2.141.1.2 SbfdInitiatorTunnel

peerStats	*table(numeric string) = PeerStats* see 2.141.1.1.1.2	A mapping between tunnel ID and peer stats.

2.141.1.3 SbfdReflector

peerStats	*table(numeric string) = PeerStats* see 2.141.1.1.1.2	A mapping between remote discriminator and peer stats.

2.142 show bfd peers debug [...]

downSessions	*table(string) = integer*	Mapping of diag to number of down sessions.
echoRxIntervals	*table(string) = string*	Mapping of peer to echo rx interval.

issues	*table(string) = Issue* see 2.142.1	Mapping of issue type to issue detail.
rxIntervals	*table(string) = string*	Mapping of peer to rx interval.
slowEchoTxs	*table(string) = integer*	Mapping of peer to number of slow echo tx.
slowTxs	*table(string) = integer*	Mapping of peer to number of slow tx.

2.142.1 Issue

issueList	*list of string*	List of issues.

2.143 show bfd peers history [...]

peerSnapshots	*list of PeerSnapshot* see 2.143.1	List of BFD peer history.

2.143.1 PeerSnapshot

authProfileName **	*string*	Configured authentication profile. **Since: 4.22.0
authType **	*enum: Keyed Sha1 | Meticulous Sha1 | Password | Meticulous Md5 | None | Keyed Md5*	Authentication mode. **Since: 4.22.0
[avgLateness] **	*integer*	Average number of microseconds messages sent after its configured period. **Since: 4.29.2
[avgPeriod] **	*integer*	Average time between received packets in microseconds. **Since: 4.29.2
detectTime	*integer*	Detection timeout in microseconds.
[echoAvgLateness] **	*integer*	Average number of microseconds messages sent after its configured period for echo. **Since: 4.29.2
[echoAvgPeriod] **	*integer*	Average time between received packets in microsecondsfor echo. **Since: 4.29.2
echoDetectTime **	*integer*	Detection timeout in microseconds for echo. **Since: 4.22.0
[echoLastRxTime] **	*floating point number*	Time of last successfully authenticated and validated packet received in seconds for echo. **Since: 4.29.2
[echoLastTxTime] **	*floating point number*	Time of last successfully transmitted packet in seconds for echo. **Since: 4.29.2
[echoMaxLateness] **	*integer*	Max number of microseconds a message sent after its configured period for echo. **Since: 4.29.2
[echoMaxPeriod] **	*integer*	Maximum time between received packets in microsecondsfor echo. **Since: 4.29.2
[echoMinLateness] **	*integer*	Minimum number of microseconds a message sent after its configured period for echo. **Since: 4.29.2
[echoMinPeriod] **	*integer*	Minimum time between received packets in microseconds for echo. **Since: 4.29.2
echoOn **	*boolean*	Echo turned on. **Since: 4.22.0

`echoRxCount` **	*integer*	Number of echo packets received. **Since: 4.22.0
`echoRxInterval` **	*integer*	Rate in microseconds at which BFD echo packets are received. **Since: 4.22.0
`echoSentAfter3p` **	*integer*	Number of echo packets sent later than three periods of last echo packet. **Since: 4.22.0
`echoSentWithin1p` **	*integer*	Number of echo packets sent within configured period since last echo packets. **Since: 4.22.0
`echoSentWithin2p` **	*integer*	Number of echo packets sent later than one period but before two periods of last echo packet. **Since: 4.22.0
`echoSentWithin3p` **	*integer*	Number of echo packets sent later than two periods but before three periods of last echo packet. **Since: 4.22.0
`echoTxCount` **	*integer*	Number of echo packets sent. **Since: 4.22.0
`echoTxInterval` **	*integer*	Rate in microseconds at which BFD echo packets are sent. **Since: 4.22.0
`event`	*enum: sessionNoEvent* | *sessionDelete* | *sessionDown* | *sessionPeerAdminDown* | *sessionPeerDown* | *sessionAdminDown*	BFD session event.
`eventTime`	*floating point number*	Time of BFD session event in seconds.
`intf`	*interface name*	Local egress interface.
`ip`	*IP address*	IP address of peer.
`lastDiag`	*enum: diagCtrlTimeout* | *diagRevConcatPathDown* | *diagConcatPathDown* | *diagNeighDown* | *diagPathDown* | *diagForwardingReset* | *diagAdminDown* | *diagNone* | *diagEchoFail*	Last diagnostic for reason of change to Down state.
`lastDown`	*floating point number*	Last time peer session went down in seconds, 0.0 if never down.
`[lastRxTime]` **	*floating point number*	Time of last successfully authenticated and validated packet received in seconds. **Since: 4.29.2
`[lastTxTime]` **	*floating point number*	Time of last successfully transmitted packet in seconds. **Since: 4.29.2
`lastUp`	*floating point number*	Last time peer session went up in seconds, 0.0 if never up.
`localDisc` **	*integer*	Local discriminator of BFD session. **Since: 4.29.2

localIpAddr **	*IP address*	Local IP. **Since: 4.29.2
[maxLateness] **	*integer*	Max number of microseconds a message sent after its configured period. **Since: 4.29.2
[maxPeriod] **	*integer*	Maximum time between received packets in microseconds. **Since: 4.29.2
[minLateness] **	*integer*	Minimum number of microseconds a message sent after its configured period. **Since: 4.29.2
[minPeriod] **	*integer*	Minimum time between received packets in microseconds. **Since: 4.29.2
prevState **	*enum: down | up | adminDown | init*	previous state. **Since: 4.29.0
remoteDisc **	*integer*	Remote discriminator BFD session. **Since: 4.29.2
rxCount	*integer*	Number of packets received.
rxInterval	*integer*	Rate in microseconds at which BFD control packets are received.
sentAfter3p	*integer*	Number of packets sent later than three periods of last packet.
sentWithin1p	*integer*	Number of packets sent within configured period since last packet.
sentWithin2p	*integer*	Number of packets sent later than one period but before two periods of last packet.
sentWithin3p	*integer*	Number of packets sent later than two periods but before three periods of last packet.
status	*enum: down | up | adminDown | init*	State of peer session.
[tunnelId] **	*integer*	TunnelID of SBFD Initiator. **Since: 4.24.0
txCount	*integer*	Number of packets sent.
txInterval	*integer*	Rate in microseconds at which BFD control packets are sent.
vrf	*string*	Vrf that peer is configured in.

2.144 show bfd peers protocol vxlan mlag primary

interfaces	*table(Interface name) = VxlanVtepBfdStatus* see 2.144.1	Mapping from VXLAN interface to its VTEP addresses.

2.144.1 VxlanVtepBfdStatus

vteps	*table(IPv4 or IPv6 address) = string*	A mapping of VXLAN VTEP to its BFD status.

2.145 show bfd peers summary [...]

`adminDown` **	*boolean*	BFD has been shut down administratively. **Since: 4.23.0
`dscpValue` **	*integer*	DSCP value. **Since: 4.32.0
`initiatorMinTx` **	*integer*	Operational rate in microseconds at which SBFD control packets are sent on initiator. **Since: 4.24.2
`initiatorMult` **	*integer*	Number of consecutive SBFD packets missed before failure. **Since: 4.24.2
`[localIntf]` **	*interface name*	SBFD local interface. **Since: 4.24.1
`[localIntfIp6]` **	*interface name*	SBFD IPv6 local interface. **Since: 4.31.0
`localIntfIp6Add` **	*IP address*	Local interface IPv6 address. **Since: 4.31.0
`localIntfIpAdd` **	*IP address*	Local interface IP address. **Since: 4.24.2
`mhMinRx` **	*integer*	Operational rate in microseconds at which BFD control pckets are received on multi-hop BFD session. **Since: 4.23.0
`mhMinTx` **	*integer*	Operational rate in microseconds at which BFD control packets are sent on multihop BFD session. **Since: 4.23.0
`mhMult` **	*integer*	Number of consecutive BFD packets missed before failure onmultihop BFD session. **Since: 4.23.0
`minRx` **	*integer*	Operational rate in microseconds at which BFD control pckets are received. **Since: 4.23.0
`minTx` **	*integer*	Operational rate in microseconds at which BFD control packets are sent. **Since: 4.23.0
`mult` **	*integer*	Number of consecutive BFD packets missed before failure. **Since: 4.23.0
`reflectorLocalDisc` **	*integer*	Local discriminator of SBFD session. **Since: 4.24.2
`reflectorMinRx` **	*integer*	Operational rate in microseconds at which SBFD control pckets are received on reflector. **Since: 4.24.2
`sessionStatsInterval` **	*integer*	Interval in seconds between unsolicited per-session statistics from BFD acclerators. **Since: 4.25.2

sessions	*table(string) = SessionCountByType* see 2.145.1	Mapping of addressing to session count by type.
slowTimer **	*integer*	Operation rate in microseconds at which BFD control packets are received on async sessions when echo is enabled. **Since: 4.23.0

2.145.1 SessionCountByType

types	*table(string) = SessionCountByState* see 2.145.1.1	Mapping of session type to session count by state.

2.145.1.1 SessionCountByState

states	*table(string) = SessionCount* see 2.145.1.1.1	Mapping of session state to number of sessions.

2.145.1.1.1 SessionCount

async	*integer*	Number of async sessions.
echo	*integer*	Number of echo sessions.

2.146 show bfd rbfd-stats

netlinkFailureFail	*integer*	Number of times session failure sent but broadcast failed.
netlinkPacketChangeFail	*integer*	Number of times packet change sent but broadcast failed.
numInvalidSessions	*integer*	Number of packets without session in Rx.
numPassupDisc0	*integer*	Number of packets passed up with discriminator zero.
pskbExpandFail	*integer*	Number of times pskb needed to be expanded but failed for packets without a session.
rfcDrops	*integer*	Number of packets dropped on receive before processing.
rxPacketMissing	*integer*	Number of times packet missing upon Rx trigger.
rxSessionCount **	*integer*	Number of active Rx Sessions. **Since: 4.34.0
txSessionCount **	*integer*	Number of active Tx Sessions. **Since: 4.34.0
vrfCount **	*integer*	Number of active vrfs. **Since: 4.36.0

2.147 show bfd sbfd-stats reflectors

rxDemandUnset	*integer*	Number of packets with demand mode unset on receive.
rxDrop	*integer*	Number of packets dropped on receive.
rxHashHit	*integer*	Number of session cache lookup hit.
rxHashMiss	*integer*	Number of session cache lookup miss.
rxHashTrim	*integer*	Number of session cache lookup trim.
rxInvalidBfdState	*integer*	Number of packets with invalid bfd state on receive.
rxInvalidLen	*integer*	Number of packets with invalid length on receive.
rxInvalidMulti	*integer*	Number of packets with invalid multiple detect on receive.
rxInvalidMyDisc	*integer*	Number of packets with invalid my discriminator on receive.
rxInvalidPktFormat	*integer*	Number of packets with invalid packet format on receive.
rxInvalidSrcPort	*integer*	Number of packets with invalid source port on receive.
rxInvalidTlv **	*integer*	Number of packets with invalid TLVs on receive. **Since: 4.28.2
rxInvalidVer	*integer*	Number of packets with invalid version on receive.
rxTruncated	*integer*	Number of packets truncated on receive.
rxUnsupported	*integer*	Number of packets unsupported on receive.
rxValid	*integer*	Number of valid packets received.
rxYourDiscUnmatch	*integer*	Number of packets with unmatched your discriminator on receive.
txInvalidLen	*integer*	Number of packets with invalid length.
txSend	*integer*	Number of packets sent.
txSendToFail	*integer*	Number of packets failed to send.

2.148 show bgp ((vpn-ipv4 | vpn-ipv6)) summary

revision 3

see 2.51

2.149 show bgp (AFI SAFI) ((IP | IP_PREFIX)) [...]

revision 3

see 2.20

2.150 show bgp (AFI SAFI) [...]

revision 3

see 2.20

2.151 show bgp (AFI SAFI) summary [...]

revision 3

see 2.51

2.152 show bgp (AFI SAFI) summary lldp [...]

revision 3

see 2.51

2.153 show bgp AFI unicast field-set FSNAME [...]

revision 3

see 2.20

2.154 show bgp access-list [...]

see 2.62

2.155 show bgp auto-aggregation ipv4 [...]

`vrfs`	*table(string) = AutoAggregation* see 2.155.1	Per VRF auto aggregation summary.

2.155.1 AutoAggregation

`domains`	*list of Domain* see 2.155.1.1	Auto aggregation domains.

2.155.1.1 Domain

`address`	*IP address*	Domain address.
`contiguousPrefixBlocks`	*list of PrefixBlock* see 2.155.1.1.1	List of contiguous prefix blocks.
`maskLength`	*integer*	Domain mask length.

2.155.1.1.1 PrefixBlock

firstAddress	*IP address*	Block first address.
lastAddress	*IP address*	Block last address.
prefixes	*list of Prefix* see 2.155.1.1.1.1	Prefixes that are active in the RIB and eligible for auto aggregation.

2.155.1.1.1.1 Prefix

address	*IP address*	Prefix address.
autoAggregate	*boolean*	Whether this prefix is an auto aggregate.
contributors	*list of Contributor* see 2.155.1.1.1.2	Auto aggregate contributors.
maskLength	*integer*	Prefix mask length.
[notAggregatedReason]	*noComplement*	Reason this prefix is not auto aggregated.

2.155.1.1.1.2 Contributor

address	*IP address*	Contributor address.
maskLength	*integer*	Contributor mask length.

2.156 show bgp auto-aggregation ipv6 [...]

see 2.155

2.157 show bgp convergence [...]

vrfs	*table(string) = ShowBgpConvergenceVrfModel* see 2.157.1	Per VRF BGP convergence information.

2.157.1 ShowBgpConvergenceVrfModel

[bgpProcessingState] **	*table(string) = BgpVrfAfiSafiRouteProcessingState* see 2.157.1.1	BGP route processing status in VRF, keyed by AFI/SAFI. **Since: 4.31.0
config	*ShowBgpConvergenceVrfConfigModel* see 2.157.1.2	Convergence configuration for VRF.
peersNotConverged	*table(IP address and interface name (for IPv6 link local peers only)) = string*	Current state of peers that still haven't converged in VRF, keyed by peer address.
status	*ShowBgpConvergenceVrfStatusModel* see 2.157.1.3	Current convergence status for VRF.

2.157.1.1 BgpVrfAfiSafiRouteProcessingState

[processedTime]	*floating point number*	Time when BGP best path selection completed.
processingState	*enum: complete | inProgress*	BGP best path selection state.

2.157.1.2 ShowBgpConvergenceVrfConfigModel

afiSafiWaitForConvergence	*table(string) = boolean*	Wait for convergence enabled for each AFI/SAFI.
convergenceTimeout	*integer*	Convergence timeout in seconds.
[convergenceUpdateSyncEnabled]	*boolean*	Convergence based update synchronisation is enabled.
slowPeerTimeout	*integer*	Slow peer timeout in seconds.

2.157.1.3 ShowBgpConvergenceVrfStatusModel

[afiSafiConvergenceStates]	*table(string) = string*	Convergence state per AFI/SAFI type.
[allIgpConverged]	*boolean*	All IGP protocols have converged.
convergenceState	*enum: convergenceActive | timeout | converged | convergenceIdle | notInitialized*	BGP convergence states.
[convergenceTimeout]	*floating point number*	Convergence timeout in seconds.
[convergenceTimer]	*boolean*	Convergence timer is running.
[convergenceTimerExpires]	*floating point number*	Time since epoch when timer expires.
[dynamicPeerGroups]	*boolean*	Dynamic peering is configured.
[expectedPeersUp]	*boolean*	Expected peers are up.
[firstPeerUp]	*boolean*	First peer is up.

[firstPeerUpTime]	*floating point number*	Timestamp since epoch when first peer came up.
[lastEventTime]	*floating point number*	Timestamp of last event since epoch.
[outstandingEors]	*integer*	Number of outstanding EORs.
[outstandingKeepalives]	*integer*	Number of outstanding keepalives.
[outstandingRpkis] **	*integer*	Number of outstanding RPKIs. **Since: 4.32.1
peers	*ShowBgpConvergenceVrfPeerStatsModel* see 2.157.1.3.1	Convergence statistics.
[previouslyEstablishedPeers]	*integer*	Number of previously established peers.
[slowPeerTimeout]	*floating point number*	Slow peer timeout in seconds.
[timeToConverge]	*floating point number*	Seconds taken to converge.

2.157.1.3.1 ShowBgpConvergenceVrfPeerStatsModel

disabledPeers	*integer*	Number of disabled peers.
establishedPeers	*integer*	Number of established peers.
pendingPeers	*integer*	Number of pending peers.
totalPeers	*integer*	Number of total peers.

2.158 show bgp debug policy export ((((vrf-route filter-rcf ipv4 unicast) | (vpn-ipv4)) PREFIX) | (((vrf-route filter-rcf ipv6 unicast) | (vpn-ipv6)) PREFIX6)) [...]

revision 2

evalResults	*list of PolicyEvalResult* see 2.158.1	Evaluation result for each NLRI.
[rcfCodeUnits]	*table(string) = RcfCodeUnitText* see 2.158.2	Reference to the text of RCF functions where evaluation occurred in each code unit, keyed by code unit name.

2.158.1 PolicyEvalResult

[messages]	*list of string*	Message describing why policy evaluation was not returned.
nlri	*NlriModel* see 2.158.1.1	NLRI of the evaluated path.
pointOfApplication	*PolicyEvalPointOf-Application* see 2.158.1.2	Point of application evaluated.
[rcfEval]	*RcfDebugEvaluation* see 2.158.1.4	Debug information for an RCF evaluation.
[routeMapEval]	*PolicyEvalRouteMap* see 2.158.1.3	Route map evaluated.

2.158.1.1 NlriModel

[esi] **	*string*	Ethernet segment identifier. **Since: 4.34.2
[etid] **	*integer*	Ethernet Tag ID. **Since: 4.34.2
[flowspecRule] **	*string*	Bgp flowspec rule. **Since: 4.30.1
[ipPrefix]	*IP address prefix*	IPv4 or IPv6 prefix.
nlriType	*enum: mplsVpnIpv6Unicast | evpnType5Ipv6 | ipv6FlowspecVpn | macSegment | ipv4Unicast | ipv6Unicast | ipv4FlowspecVpn | rtMembership | evpnType5Ipv4 | mplsVpnIpv4Unicast | ipv4Flowspec | ipv6Flowspec*	Type of BGP NLRI.
[originAs] **	*string*	Rt membership origin as. **Since: 4.32.2
[pathId] **	*integer*	Path ID of the route. **Since: 4.30.1
[rd] **	*string*	Route distinguisher. **Since: 4.29.2

[routeDomain] **	*enum: local | remote*	Local or remote domain. **Since: 4.34.2
[routeTarget] **	*string*	Rt membership route-target prefix. **Since: 4.32.2
[routeType] **	*enum: local | remote*	Local or remote route. **Since: 4.34.2

2.158.1.2 PolicyEvalPointOfApplication

[evpnDomain] **	*enum: local | remote*	Evpn Domain. **Since: 4.36.0
name	*enum: import | export | inbound | network | outbound | redistribute*	Name of the point of application.
[networkSource] **	*string*	Source of routes injected with Network statement. **Since: 4.32.1
[peerAddr]	*IP address and interface name (for IPv6 link local peers only)*	Peer address of application.
[redistributionSource]	*string*	Source of redistributed routes.
[sourcePeerAddr] **	*IP address*	Source peer for the route. **Since: 4.34.2
[sourceProtocol] **	*string*	Source protocol for the route. **Since: 4.34.2
[vpnAfiSafi] **	*enum: evpn | ipv4MplsVpn | ipv6MplsVpn*	AfiSafi of VPN routes. **Since: 4.30.0

2.158.1.3 PolicyEvalRouteMap

[notFound]	*boolean*	Route map is not configured.
[routeMapCycleDetected]	*boolean*	Route map is part of a cycle.
routeMapName	*string*	Name of the route map.
routeMapResult	*PolicyEvalRouteMapResult* see 2.158.1.3.1	Result of the route map.
[sequences]	*table(numeric string) = PolicyEvalSequence* see 2.158.1.3.2	Evaluated sequences.

2.158.1.3.1 PolicyEvalRouteMapResult

[permittingSeqnos]	*list of integer*	Sequences resulting in permit.
result	*enum: explicitDeny | permit | noMatchingSequenceDeny*	Route map result.

2.158.1.3.2 PolicyEvalSequence

[continueNextSequence]	*boolean*	Continue to next sequence.
[continueSeqno]	*integer*	Continue to sequence number.
[descriptions]	*list of string*	Route map sequence description.
filterType	*enum: deny | permit*	Filter type.

[matcherResults]	*list of MatchRules* see 2.158.1.3.2.1	Evaluated matcher results.
[missingContinueTarget]	*boolean*	Sequence contains a continue statement to a target which is not configured.
sequenceResult	*PolicyEvalSequenceResult* see 2.158.1.3.2.7	Sequence result.
[setRules]	*SetRules* see 2.158.1.3.2.8	Applied set rules.
[subRouteMap]	*PolicyEvalRouteMap* see 2.158.1.3	Sub route map evaluation.
[subRouteMapInvertResult]	*boolean*	Invert result of the sub route map.

2.158.1.3.2.1 MatchRules

[accessList]	*string*	IPv4 address filtered by access control list.
[aggregation]	*AggregateContributor* see 2.158.1.3.2.2	Match contributors to BGP aggregates.
[aggregationInvertResult]	*boolean*	Invert match contributors to BGP aggregates.
[asNumber]	*string*	BGP autonomous system number.
[asPathLength]	*AsPathLengthRange* see 2.158.1.3.2.3	Match on as-path length.
[asPathLengthInvertResult]	*boolean*	Invert of as-path length match.
[asPathList]	*string*	BGP autonomous system path access list.
[community]	*string*	BGP community.
[communityExactMatch]	*boolean*	Exact match of communities.
[communityInstances]	*CommInstancesRange* see 2.158.1.3.2.4	Match on the number of community instances.
[communityInstancesInvertResult]	*boolean*	Invert match community instances result.
[communityInvertResult]	*boolean*	Invert match community result.
[communityOrResults] **	*boolean*	Or results of community lists. **Since: 4.23.1
[debugInfo] **	*DebugInfo* see 2.158.1.3.2.5	Debugging information for match rules. **Since: 4.22.1
[extCommunity]	*string*	BGP extended community.
[extCommunityInvertResult]	*boolean*	Invert match extcommunity result.
[interface]	*interface name*	Interface name.
[ipAddrDynamicPrefixList]	*string*	Ip address dynamic prefix list name.
[ipv6AddrDynamicPrefixList]	*string*	Ipv6 address dynamic prefix list name.
[ipv6NextHop]	*IPv6 address*	IPv6 next hop filtered by IPv6 address.
[ipv6NextHopPrefixList]	*string*	IPv6 next hop filtered by IPv6 prefix list.
[ipv6PrefixList]	*string*	IPv6 address filtered by IPv6 prefix list.
[ipv6PrefixListInvertResult] **	*boolean*	Invert IPv6 prefix list match result. **Since: 4.33.0
[ipv6ResolvedNextHopPrefixList]	*string*	IPv6 resolved nexthop filtered by IPv6 prefix list.
[isisInstance] **	*integer*	IS-IS route instance. **Since: 4.24.2
[isisLevel]	*enum: level-1 | level-2*	IS-IS route level.

[largeCommunity]	*string*	BGP large community.
[largeCommunityInvert-Result]	*boolean*	Invert match large community result.
[localPref]	*integer*	Bgp local preference metric.
[nextHop]	*IPv4 address*	IPv4 next hop filtered by IP address.
[nextHopPrefixList]	*string*	IPv4 next hop filtered by IP prefix list.
[originAs] **	*string*	Route origin AS number. **Since: 4.23.1
[originAsValidity] **	*enum: invalid* | *valid* | *notFound*	AS Origin validation state. **Since: 4.23.2
[originAsValidityInvert-Result] **	*boolean*	Invert match AS Origin validation state. **Since: 4.24.0
[ospfInstance] **	*integer*	OSPF route instance. **Since: 4.25.0
[ospfMetricType]	*enum: type-1* | *type-2*	OSPF external LSA metric type.
[prefixList]	*string*	IPv4 address filtered by IP prefix list.
[prefixListInvertResult] **	*boolean*	Invert IPv4 prefix list match result. **Since: 4.33.0
[protocol]	*enum: rip* | *dynamic* | *connected* | *ospf* | *bgp* | *static* | *ospfv3* | *attached-host* | *isis*	Routing protocol of route's source.
[resolvedNextHopPrefixList]	*string*	IPv4 resolved nexthop filtered by IP prefix list.
[routeMetric]	*integer*	Route metric.
[routeTag]	*integer*	Route tag.
[routeTagSet] **	*string*	Route tag set name. **Since: 4.33.0
[routeType]	*enum: internal* | *vpn* | *external* | *local* | *confederation-external*	Route type.
[routerIdPrefixList]	*string*	Router ID filtered by prefix list.

2.158.1.3.2.2 AggregateContributor

[aggregateAttributes]	*string*	Route map against which to evalute the aggregate route.
aggregateRole	*contributor*	Role in contributor-aggregate relation.

2.158.1.3.2.3 AsPathLengthRange

end	*integer*	The maximum length of the as-path.
start	*integer*	The minimum length of the as-path.

2.158.1.3.2.4 CommInstancesRange

end	*integer*	The maximum number of communities.
start	*integer*	The minimum number of communities.

2.158.1.3.2.5 DebugInfo

[community]	*AttributeDebug* see 2.158.1.3.2.6	Debugging information for match community lists.
[communityAddOrReplace] **	*AttributeDebug* see 2.158.1.3.2.6	Debugging information for add/replace community lists. **Since: 4.25.1
[communityDelete] **	*AttributeDebug* see 2.158.1.3.2.6	Debugging information for delete community lists. **Since: 4.25.1
[communityFilter] **	*AttributeDebug* see 2.158.1.3.2.6	Debugging information for filter community lists. **Since: 4.25.1
[extCommunity]	*AttributeDebug* see 2.158.1.3.2.6	Debugging information for extended community lists.
[extCommunityFilter] **	*AttributeDebug* see 2.158.1.3.2.6	Debugging information for filter extended community lists. **Since: 4.25.1
[largeCommunity]	*AttributeDebug* see 2.158.1.3.2.6	Debugging information for large community lists.
[largeCommunityFilter] **	*AttributeDebug* see 2.158.1.3.2.6	Debugging information for filter large community lists. **Since: 4.25.1
[matchResult]	*enum: matched* | *failed* | *unsupported*	Result of the matcher.

2.158.1.3.2.6 AttributeDebug

[ignored] **	*string*	String representation of element that may be ignored. **Since: 4.23.0
[undefined]	*string*	String representation of undefined element.

2.158.1.3.2.7 PolicyEvalSequenceResult

[continueSeqno]	*integer*	Continue to sequence number.
result	*enum: deny* | *permit* | *fallThrough*	Route map sequence result.

2.158.1.3.2.8 SetRules

[aigpMetric] **	*AigpMetric* see 2.158.1.3.2.9	AIGP Metric. **Since: 4.24.0
[asPathPrepend]	*string*	BGP AS path to prepend.
[asPathPrependLastAs]	*integer*	Number of times to prepend the last AS number.
[asPathReplace]	*string*	BGP AS path to replace.
[bpAsPathWeight] **	*integer*	BGP bestpath AS path weight parameter. **Since: 4.23.0
[communityAddOrReplace]	*CommunitySet* see 2.158.1.3.2.10	Community addor replace modifications.

[communityDelete]	*CommunitySet* see 2.158.1.3.2.10	Community deletemodifications.
[communityFilter] **	*CommunitySet* see 2.158.1.3.2.10	Community filtermodifications. **Since: 4.25.1
[debugInfo] **	*DebugInfo* see 2.158.1.3.2.5	Debugging information for set rules. **Since: 4.22.1
[distance]	*integer*	Protocol independent administrative distance.
[extCommunity]	*CommunitySet* see 2.158.1.3.2.10	Extended communitymodifications.
[extCommunityFilter] **	*CommunitySet* see 2.158.1.3.2.10	Extended communityfilter modifications. **Since: 4.25.1
[igpMetric]	*integer*	IGP metric.
[isisLevel]	*enum: level-1 | level-1-2 | level-2*	IS-IS route level.
[isisMetricStyle] **	*wide*	IS-IS metric style. **Since: 4.32.2
[largeCommunity]	*CommunitySet* see 2.158.1.3.2.10	Large communitymodifications.
[largeCommunityFilter] **	*CommunitySet* see 2.158.1.3.2.10	Large communityfilter modifications. **Since: 4.25.1
[localPref]	*integer*	BGP local preference metric.
[nextHop]	*NextHop* see 2.158.1.3.2.11	Next hop information.
[origin]	*enum: bgpEGP | bgpIGP | bgpIncomplete*	BGP origin of path information.
[originAsValidity] **	*enum: invalid | valid | notFound*	AS Origin validation state. **Since: 4.23.2
[ospfBitDn] **	*OspfBit* see 2.158.1.3.2.12	DN bit to prevent routing loops. **Since: 4.25.1
[ospfExternalForwarding-AddressZero] **	*boolean*	External lsa forwarding address 0.0.0.0. **Since: 4.36.0
[ospfMetricType]	*enum: type-1 | type-2*	OSPF external LSA metric type.
[ospfv3BitDn] **	*Ospfv3Bit* see 2.158.1.3.2.13	DN bit to prevent routing loops in OSPFv3. **Since: 4.30.2
[resolutionRibProfile-Config] **	*ResolutionRibProfileConfig* see 2.158.1.3.2.14	Resolution RIBs. **Since: 4.25.1
[routeMetric]	*RouteMetric* see 2.158.1.3.2.16	Route Metric.
[routeTag]	*integer*	Route tag.
[segmentIndex]	*integer*	MPLS Segment Routing Index.
[weight]	*integer*	BGP weight parameter.

2.158.1.3.2.9 AigpMetric

[metricType]	*enum: igp-metric | metric | additive | igp-next-hop-cost | subtractive*	AIGP metric from IGP metric or IGP next-hop-cost.
value	*integer*	AIGP metric value.

2.158.1.3.2.10 CommunitySet

[communityFilterTypes] **	*list of string*	Community filter type values. **Since: 4.25.1
[communityLists]	*list of string*	Community list names.
[communityValues]	*list of string*	Community list values.
operationType	*enum: default | none | add | delete | filter*	Community set operation type.

2.158.1.3.2.11 NextHop

[ipAddress]	*IP address*	Next hop IP address.
nextHopType	*enum: ipAddress | unchanged | ipv6PeerAddress | peerAddress | ipv6Unchanged | evpnUnchanged*	Next hop type.

2.158.1.3.2.12 OspfBit

ospfBitType	*dn*	Set an OSPF protocol bit.

2.158.1.3.2.13 Ospfv3Bit

ospfv3BitType	*dn*	Set an OSPFv3 protocol bit.

2.158.1.3.2.14 ResolutionRibProfileConfig

resolutionMethods	*list of ResolutionRib* see 2.158.1.3.2.15	List of resolution methods.
[systemDefault]	*boolean*	System default profile is set for next-hop.

2.158.1.3.2.15 ResolutionRib

[colored]	*boolean*	The tunnel RIB is colored.
name	*string*	Name of the resolution RIB.
ribType	*enum: tunnel | ip*	Type of the resolution RIB.

2.158.1.3.2.16 RouteMetric

[metricType]	*enum: add-igp-nexthop-cost | igp-metric | multiplicative | value-add-igp-metric | additive | add-igp-metric | igp-nexthop-cost | metric | value-add-igp-nexthop-cost | subtractive*	Additive or subtractive metric value.

value	*integer*	Route metric value.

2.158.1.4 RcfDebugEvaluation

entryPoint	*string*	The initial RCF expression that was invoked.
functionEvaluations	*table(string) = RcfDebugFunction* see 2.158.1.4.1	Evaluation information for each function invoked during the RCF evaluation keyed by function name.
result	*RcfDebugResult* see 2.158.1.4.1.5	The overall result of the RCF evaluation.

2.158.1.4.1 RcfDebugFunction

[codeUnitName]	*string*	Code unit containing the function definition.
functionDomain **	*enum: USER_DEFINED | POA_WRAPPER | OPEN_CONFIG | BUILTIN*	Source of this RCF function. **Since: 4.33.1
invocations	*list of RcfDebugFunctionInvocation* see 2.158.1.4.1.1	A function can be invoked multiple times during RCF evaluation. The evaluation of the called function may differ each time. This is a list of all of the invocationsthat occurred.

2.158.1.4.1.1 RcfDebugFunctionInvocation

callStackDepth	*integer*	How deep in the call stack this invocation was evaluated.
fragments	*list of RcfDebugFragment* see 2.158.1.4.1.2	Fragments representing pieces of code relevant to the evaluation of the invoked function. Sorted first by their location (line and column number) and then by the order they occurred.
result	*RcfDebugResult* see 2.158.1.4.1.5	Result of the function invocations evaluation.

2.158.1.4.1.2 RcfDebugFragment

continuation	*boolean*	Whether this fragment is for an expression continuing from a previous line.

fragmentType	*enum: logicalOperator* | *openExplicitBracket* | *closeExplicitBracket* | *openStatementExpression* | *openImplicitBracket* | *closeStatementExpression* | *statement* | *openBlock* | *functionCall* | *closeImplicitBracket* | *elseStatement* | *assignment* | *definition* | *closeBlock* | *condition* | *ifStatement*	Type of code the fragment represents.
[invocation]	*RcfDebugFunctionInvocationReference* see 2.158.1.4.1.4	Reference to the RCF invocation that occurred in the code fragment.
location	*RcfDebugFragmentLocation* see 2.158.1.4.1.3	Location the fragment occurred at in the RCF code.
[result]	*RcfDebugResult* see 2.158.1.4.1.5	Result of the code fragments evaluation.

2.158.1.4.1.3 RcfDebugFragmentLocation

column	*integer*	Column number of the location on a line.
[length]	*integer*	Length of the fragment in bytes.
line	*integer*	Line number of the location within a code unit.

2.158.1.4.1.4 RcfDebugFunctionInvocationReference

functionName	*string*	Name of the RCF function that was invoked.
invocationIndex	*integer*	A function can be invoked multiple times during RCF evaluation. The evaluation of the called function may differ each time. This index is used to indicate the particular invocation being referenced.

2.158.1.4.1.5 RcfDebugResult

[reason]	*string*	Explanation of the result.
[termination] **	*enum: returnToCaller* | *exitToPoa* | *noTermination*	Trilean termination flag. **Since: 4.33.0
value	*enum: true* | *false* | *unknown*	Trilean result value.

2.158.2 RcfCodeUnitText

functions	*table(string) = RcfFunctionText* see 2.158.2.1	Reference to the text of RCF functions where evaluation occurred, keyed by the RCF function name.

2.158.2.1 RcfFunctionText

`lines`	*table(numeric string) = string*	Lines of RCF text. Keyed by line number.

2.159 show bgp debug policy export evpn (PREFIX | PREFIX6) [...]

revision 2

see 2.158

2.160 show bgp debug policy export evpn vpws VPWS etid ETID route ROUTE [...]

revision 2

see 2.158

2.161 show bgp debug policy import ((((vpn-route filter-rcf vpn-ipv4) | (ipv4 unicast)) PREFIX) | (((vpn-route filter-rcf vpn-ipv6) | (ipv6 unicast)) PREFIX6)) rd RD [...]

revision 2

see 2.158

2.162 show bgp debug policy inbound neighbor (ADDR | ADDR6 | ADDR6LL | all) ((ipv4 unicast PREFIX) | (ipv6 unicast PREFIX6)) [...]

revision 2

see 2.158

2.163 show bgp debug policy inbound neighbor (ADDR | ADDR6 | ADDR6LL | all) (vpn-ipv4 | vpn-ipv6) (PREFIX | PREFIX6) rd RD [...]

revision 2

see 2.158

2.164 show bgp debug policy inbound neighbor (ADDR | ADDR6 | ADDR6LL | all) evpn route-type ip-prefix (PREFIX | PREFIX6) rd RD [...]

revision 2

see 2.158

2.165 show bgp debug policy inbound neighbor (ADDR | ADDR6 | ADDR6LL | all) flow-spec (ipv4 | ipv6) rule FLOWSPEC_RULE [...]

revision 2

see 2.158

2.166 show bgp debug policy inbound neighbor (ADDR | ADDR6 | ADDR6LL | all) flow-spec (vpn-ipv4 | vpn-ipv6) rule FLOWSPEC_RULE [...]

revision 2

see 2.158

2.167 show bgp debug policy inbound neighbor (ADDR | ADDR6 | ADDR6LL | all) rt-membership origin-as (none | AS_PLAIN_NUM | AS_DOT_NUM) route-target ROUTE_TARGET [...]

revision 2

see 2.158

2.168 show bgp debug policy network (ipv4 unicast PREFIX) | (ipv6 unicast PREFIX6) [...]

revision 2

see 2.158

2.169 show bgp debug policy outbound neighbor (ADDR | ADDR6 | ADDR6LL) (ipv4 unicast PREFIX) | (ipv6 unicast PREFIX6) [...]

revision 2

see 2.158

2.170 show bgp debug policy outbound neighbor (ADDR | ADDR6 | ADDR6LL) (vpn-ipv4 | vpn-ipv6) (PREFIX | PREFIX6) rd RD [...]

revision 2

see 2.158

2.171 show bgp debug policy outbound neighbor (ADDR | ADDR6 | ADDR6LL) evpn route-type ip-prefix (PREFIX | PREFIX6) rd RD [...]

revision 2

see 2.158

2.172 show bgp debug policy outbound neighbor (ADDR | ADDR6 | ADDR6LL) flow-spec (ipv4 | ipv6) rule FLOWSPEC_RULE [...]

revision 2

see 2.158

2.173 show bgp debug policy outbound neighbor (ADDR | ADDR6 | ADDR6LL) flow-spec (vpn-ipv4 | vpn-ipv6) rule FLOWSPEC_RULE [...]

revision 2

see 2.158

2.174 show bgp debug policy outbound neighbor (ADDR | ADDR6 | ADDR6LL) rt-membership origin-as (none | AS_PLAIN_NUM | AS_DOT_NUM) route-target ROUTE_TARGET [...]

revision 2

see 2.158

2.175 show bgp debug policy redistribute (ipv4 unicast PREFIX) | (ipv6 unicast PREFIX6) [...]

revision 2

see 2.158

2.176 show bgp debug policy redistribute flow-spec (ipv4 | ipv6) rule FLOWSPEC_RUL [...]

revision 2

see 2.158

2.177 show bgp evpn (arp | mac) [...]

asn	*integer*	Autonomous System Number.
evpnRoutes	*table(string) = EvpnRouteL2TableEntry* see 2.177.1	Dictionary of BGP EVPN route entries indexed by the route key.
routerId	*IPv4 address*	BGP Router Identity.
vrf	*string*	VRF name.

2.177.1 EvpnRouteL2TableEntry

evpnRoutePaths	*list of EvpnPathL2TableEntry* see 2.177.1.1	List of BGP EVPN route ECMP paths.
routeKeyDetail	*EvpnRouteKeyDetail* see 2.177.1.2	NLRI details.
[routePriority] **	*enum: medium | high | low*	Route processing priority. **Since: 4.32.1
[totalPaths]	*integer*	Total number of paths for this route.

2.177.1.1 EvpnPathL2TableEntry

[labelMpls]	*EncapLabel* see 2.20.1.1.2.34	Local or remote MPLS label.
[labelVxlan]	*EncapLabel* see 2.20.1.1.2.34	Local or remote VXLAN label.
nextHop	*string*	Route next hop address.
[seqNum]	*integer*	EVPN MAC mobility extended community.
vlan	*integer*	VLAN that the path was imported into.

2.177.1.2 EvpnRouteKeyDetail

[domain] **	*enum: local | remote*	BGP route domain. **Since: 4.26.0
[esi]	*string*	For auto-discovery and ethernet-segment routes, the ethernet segment identifier.
[eti]	*integer*	For auto-discovery, mac-ip, imet, and ip-prefix routes, the ethernet tag identifier.
[eti2] **	*integer*	For dual-encap mac-ip and imet routes, the second ethernet tag identifier. **Since: 4.27.1
[group] **	*IP address*	Multicast group address. **Since: 4.23.0
[ipGenAddr]	*IP address*	For mac-ip routes, the IP address corresponding to the ethernet address. For imet and ethernet-segment routes, the originating router IP address.
[ipGenAddr2] **	*IP address*	For dual-encap imet routes, the second originating router IP address. **Since: 4.27.1

[ipGenPrefix]	*IP address prefix*	For ip-prefix routes, the IPv4 or IPv6 address prefix.
[mac]	*string*	For mac-ip routes, the ethernet address.
nlriType	*enum: auto-discovery* | *mac-address* | *mac-arp* | *imet* | *smet* | *spmsi* | *join-sync* | *leave-sync* | *ethernet-segment* | *ip-prefix* | *mac-ip*	NLRI type.
[rd]	*string*	Route distinguisher.
[source] **	*IP address*	Multicast source address. **Since: 4.23.0
[syncnum] **	*integer*	Leave group synchronization number. **Since: 4.23.0

2.178 show bgp evpn (route-type ((auto-discovery) | (mac-ip) | imet | (ethernet-segment) | (ip-prefix) | (smet | join-sync | leave-sync | spmsi))) internal [...]

revision 2

asn	*integer*	Autonomous System Number.
[count] **	*integer*	Number of filtered EVPN routes. **Since: 4.35.2
[currentSeqNum]	*integer*	Current route sequence number.
evpnRoutes	*table(string) = EvpnRouteEntry* see 2.178.1	Dictionary of BGP EVPN route entries indexed by the route key.
[lastProcessedSeqNum]	*integer*	Last route sequence number acknowledged.
routerId	*IPv4 address*	BGP Router Identity.
vrf	*string*	VRF name.

2.178.1 EvpnRouteEntry

evpnRoutePaths	*list of EvpnRoutePath* see 2.178.1.1	List of BGP EVPN route ECMP paths.
routeKeyDetail	*EvpnRouteKeyDetail* see 2.177.1.2	NLRI details.
[routePriority] **	*enum: medium | high | low*	Route processing priority. **Since: 4.32.1
[totalPaths]	*integer*	Total number of paths for this route.

2.178.1.1 EvpnRoutePath

asPathEntry	*EvpnRouteASPathEntry* see 2.178.1.1.2	AS path information.
[importedEvpnPathRd]	*string*	Imported EVPN path RouteDistinguisher.
[localPreference]	*integer*	I-BGP Local preference indicator.
[med]	*integer*	Multi Exit Discriminator for the route.
[nextHop]	*string*	Route next hop address.

reasonNotBestpath	*enum: clusterlistLenTB* | *ebgp* | *localPath* | *macMobilityEsi* | *rtMembershipDefault-Originate* | *peerAddress* | *rrClient* | *igpDomainType* | *nexthopVrf* | *weight* | *igpPreference* | *routerId* | *neighborMultipath* | *macMobilityStickyMac* | *origin* | *age* | *noBest* | *macMobilitySeqNum* | *igpMetric* | *macMobilityRemoteDomain* | *originAsValidity* | *routeUnusable* | *noLocalLabel* | *med* | *ageTB* | *aspathLength* | *originatorIdOrRouterId* | *macMobilityTep-AddrdomainPathLength* | *noReason* | *infMed* | *ecmpFast* | *routeNotReady* | *localpref* | *originatorIdTB* | *pathId* | *invalid* | *clusterlistLen* | *routerIdTB* | *aigp* | *redist* | *nhgTunnelEcmpDisabled* | *aspathDetails* | *preference* | *originatorId*	Reason route was not selected as BGP best path.
[routeDetail]	*EvpnRouteDetailEntry* see 2.178.1.1.3	Route details.
routeType	*BgpVpnRouteTypeEntry* see 2.178.1.1.1	Route type.
[tag] **	*integer*	Tag for the route. **Since: 4.29.1
[timestamp]	*integer*	UTC seconds since epoch when the route was received. Only returned with 'show bgp evpn detail'.
[weight]	*integer*	Weight for the route.

2.178.1.1.1 BgpVpnRouteTypeEntry

active	*boolean*	Route is active.
atomicAggregator	*boolean*	Route is an atomic-aggregate.
backup	*boolean*	Route is backup.
ecmp	*boolean*	Route is an ECMP route.
ecmpContributor	*boolean*	Route contributes to ECMP.
ecmpHead	*boolean*	Route is the ECMP head.
[localAgg]	*boolean*	Route is locally aggregated.
[notInstalledReason]	*enum: routeInstallDenied* | *labeledRoutePresent* | *routeBestInactive*	Reason for route not being installed.

[origin]	*enum: Incomplete | Igp | Egp*	Route origin.
queued	*boolean*	Route is queued for advertisement.
stale	*boolean*	Route is stale.
suppressed	*boolean*	Route is suppressed from entering the RIB.
[ucmp]	*boolean*	Route is an UCMP route.
[unknownMetric]	*boolean*	Route is pending resolution.
valid	*boolean*	Route is valid.
[waitForConvergence]	*boolean*	Route is pending best path selection.

2.178.1.1.2 EvpnRouteASPathEntry

[asPath]	*string*	AS path string (if absent, then the route was originated locally).
asPathType	*enum: Internal | Local | Confed-External | Invalid | External*	AS path type: Internal - originated by I-BGP External - originated by E-BGP Confed-External - originated by a E-BGP confederation Local - originated locally Invalid - AS path is invalid.

2.178.1.1.3 EvpnRouteDetailEntry

[aggregator]	*string*	Aggregator of the route.
[clusterList]	*string*	Cluster list for the route.
communities	*list of string*	List of communities for this route.
[customerAttributeSet]	*CustomerAttributesDetailEntry* see 2.178.1.1.3.1	Customer Attributes.
[domainPath] **	*list of string*	Domain path attribute. **Since: 4.23.0
[esi]	*string*	Ethernet segment identifier.
extCommunities	*list of string*	List of extended communities for this route.
extCommunityListRaw **	*list of integer*	List of raw extended communities for this route. **Since: 4.26.0
fromRRClient	*boolean*	Route received from route reflector client.
[gatewayIpAddr] **	*IP address*	Route gateway IP address. **Since: 4.29.0
[l3Label]	*EncapLabel* see 2.20.1.1.2.34	Local or remote L3 label.
[l3LabelMpls] **	*EncapLabel* see 2.20.1.1.2.34	Local or remote L3 MPLS label. **Since: 4.28.0
[l3LabelVxlan] **	*EncapLabel* see 2.20.1.1.2.34	Local or remote L3 VXLAN label. **Since: 4.28.0
[label]	*EncapLabel* see 2.20.1.1.2.34	Local or remote label.
[labelMpls] **	*EncapLabel* see 2.20.1.1.2.34	Local or remote MPLS label. **Since: 4.26.0
[labelSrv6] **	*EncapLabel* see 2.20.1.1.2.34	Local or remote SRv6 SID (label). **Since: 4.28.2

[labelStack]	*list of integer*	MPLS label stack information.
[labelVxlan] **	*EncapLabel* see 2.20.1.1.2.34	Local or remote VXLAN label. **Since: 4.26.0
largeCommunities **	*list of string*	List of large communities for route. **Since: 4.22.1
[multicastFlags] **	*MulticastFlags* see 2.178.1.1.3.2	Multicast flags for route-type smet, join-sync, and leave-sync. **Since: 4.26.2
origin	*enum: Incomplete | Igp | Egp*	Route origin.
[originator]	*IPv4 address*	Router ID of the originator of this route.
[peerEntry]	*BgpRoutePeerEntry* see 2.20.1.1.2.43	Peer information for the route.
[pendingTimeToAdv]	*floating point number*	Timestamp of route advertisement.
[pmsiTunnel] **	*PmsiTunnel* see 2.20.1.1.2.38	P-Multicast Serivce Interface Tunnel Attribute. **Since: 4.23.2
[redistributionProtocol]	*enum: unknown | Connected | Static | Rip | Ospf | Ospf3 | Is-Is*	Protocol from which route got redistributed into BGP.
[rxPathId]	*integer*	Received path ID of this route.
[rxSafi]	*string*	Received SAFI of this route.
[seqNumber]	*integer*	Route sequence number.
[tunnelEncap] **	*table(string) = TunnelEncap* see 2.178.1.1.3.3	Tunnel encapsulation attribute. **Since: 4.25.0
tunnelRibEligible	*boolean*	Route eligible to be installed in Tunnel RIB.
[txPathId]	*integer*	Advertised path ID for this route.

2.178.1.1.3.1 CustomerAttributesDetailEntry

[aggregator]	*string*	Aggregator of the route.
[clusterList]	*string*	Cluster list for the route.
communities	*list of string*	Standard community attributes.
[domainPath]	*list of string*	Domain path attribute.
extCommunities	*list of string*	Extended community attributes.
extCommunityListRaw	*list of integer*	Raw extended community attributes.
largeCommunities	*list of string*	Large community attributes.
[localPreference]	*integer*	I-BGP Local preference indicator.
[med]	*integer*	Multi Exit Discriminator for the route.
origin	*enum: Incomplete | Igp | Egp*	Route origin.
originAsn	*integer*	Origin AS number.
[originator]	*IPv4 address*	Router ID of the originator of this route.

2.178.1.1.3.2 MulticastFlags

[filterMode]	*enum: include | exclude*	Group membership filter mode.

2.178.1.1.3.3 TunnelEncap

asn	*integer*	Autonomous System Number.
endpoint	*IP address*	Tunnel egress endpoint.

2.179 show bgp evpn [...]

revision 2

see 2.178

2.180 show bgp evpn host-flap

duplicationBlacklistedMacs	*list of Routing.Bgp.MacPlugin.HostFlapEntry* see 2.180.1	List of suppressed MAC addresses.

2.180.1 Routing.Bgp.MacPlugin.HostFlapEntry

macAddr	*string*	Suppressed MAC Address due to duplication.
time	*floating point number*	Timestamp when MAC was suppressed (UTC epoch seconds).
vlan	*integer*	VLAN ID of suppressed MAC Address.

2.181 show bgp evpn instance [...]

revision 2

bgpEvpnInstances	*table(string) = BgpEvpnInstance* see 2.181.1	BGP EVPN instances indexed by instance name.

2.181.1 BgpEvpnInstance

[adLabel]	*integer*	MPLS label used in auto-discovery routes.
[afiSafiConfig] **	*table(string) = InstanceAfiSafiConfigs* see 2.181.1.3	Route targets for an address family type. **Since: 4.30.0
[ethernetSegments]	*table(string) = EthernetSegment* see 2.181.1.2	Local ethernet segments indexed by ESI.
[evpnVpwsDetail]	*BgpEvpnVpwsDetail* see 2.181.1.1	EVPN virtual private wire service (VPWS) detailed information.
[exportRemoteRts]	*list of integer*	Remote route targets to export.
[exportRtRcf] **	*string*	RCF function to apply on route target export. **Since: 4.31.0
[exportRts]	*list of integer*	Route targets to export.
[imetLabel]	*integer*	MPLS label used in imet routes.
[importRemoteRts]	*list of integer*	Remote route targets to import.
[importRts]	*list of integer*	Route targets to import.
[labelAllocMode]	*enum: perInstance | perPseudowire | perVlan*	Label allocation mode.
[localMplsIp]	*IP address*	Local MPLS IP.
[localVxlanIp]	*IP address*	Local VXLAN IP.
[macLabel]	*integer*	MPLS label used in mac-ip routes.
[mplsEnabled]	*boolean*	MPLS Enabled.
rd	*string*	EVPN instance route distinguisher.
[remoteEthernetSegments] **	*table(string) = RemoteEthernetSegment* see 2.181.1.4	Remote ethernet segments. **Since: 4.30.0
[remoteRd]	*string*	EVPN instance remote route distinguisher.
[serviceIntf]	*enum: vlanBased | vlanAwareBundle*	EVPN instance service interface.
[vxlanEnabled]	*boolean*	VXLAN Enabled.

2.181.1.1 BgpEvpnVpwsDetail

controlWord	*boolean*	Control word required when sending EVPN packets to this device.
[fxcNormalizedVlanTagSignaling]	*enum: all | none*	Flexible cross connect normalized VLAN tag signaling.
[l2Mtu]	*integer*	L2 MTU value used for validation, if enabled.

pseudowires	*table(string) = BgpEvpnVpwsPseudowire* see 2.181.1.1.1	Mapping of pseudowire name to detailed information.

2.181.1.1.1 BgpEvpnVpwsPseudowire

[color] **	*integer*	Color. **Since: 4.30.2
status	*enum: pending | noRemoteId | localIdConflict | up | noLocalId | noRequest | remoteIdConflict | noLocalLabel*	Pseudowire status.
[vlanTagNormalization]	*enum: single | double*	Flexible cross connect VLAN tag normalization.
[vpwsIdLocal]	*integer*	Advertised virtual private wire service (VPWS) instance identifier.
[vpwsIdRemote]	*integer*	Peer's virtual private wire service (VPWS) instance identifier.
[vpwsLabel]	*integer*	Advertised pseudowire label.

2.181.1.2 EthernetSegment

[backupDFPeers] **	*list of EsiPeer* see 2.181.1.2.1	Backup designated forwarder. **Since: 4.36.0
[dFElectionAlgorithm]	*enum: modulus | hrw | preference*	DF election algorithm.
[dFElectionState]	*enum: pending | started | finished*	DF election state.
dFPeer	*EsiPeer* see 2.181.1.2.1	Designated forwarder.
[downReason] **	*string*	Reason the ES is currently down. **Since: 4.34.1
[esiLabel]	*integer*	MPLS ESI label used for split-horizon filtering.
forwardingPeers	*list of EsiPeer* see 2.181.1.2.1	All forwarding peers.
[frrAnycastSrcIp] **	*IP address*	Fast reroute anycast source IP address. **Since: 4.36.0
[frrDuration] **	*integer*	Duration after a failure for which traffic will be ' 'rerouted using the backup tunnel. **Since: 4.36.0
[frrMode] **	*string*	Fast reroute mode. **Since: 4.36.0
[frrRedirectLabel] **	*integer*	Fast reroute redirect label. **Since: 4.36.0
[frrState] **	*string*	Fast reroute state. **Since: 4.36.0
importRT	*string*	ES import route target (now obsolete as this field is included in importRTs).

importRTs **	*list of string*	ES import route target(s). **Since: 4.33.1
intf	*interface name*	Interface name.
nonDFPeers	*list of EsiPeer* see 2.181.1.2.1	Non-designated forwarders.
[pseudowires]	*table(string) = EthernetSegmentPseudowire* see 2.181.1.2.2	Mapping of pseudowire name to detailed information.
redundancyMode	*enum: allActive | singleActive*	Redundancy mode.
[sharedEsiLabel]	*boolean*	MPLS ESI label shared with other PEs.
state	*enum: down | up*	Ethernet segment state.

2.181.1.2.1 EsiPeer

[esiLabel]	*integer*	MPLS ESI label advertised by peer.
ip	*IP address*	IP address of peer.

2.181.1.2.2 EthernetSegmentPseudowire

[backup]	*IP address*	IP address of the backup peer.
[primary]	*IP address*	IP address of the primary peer.

2.181.1.3 InstanceAfiSafiConfigs

[routeTargetExports]	*list of string*	Route targets to export.
[routeTargetExportsRemote] **	*list of string*	Route targets to export remote. **Since: 4.35.0
[routeTargetImports]	*list of string*	Route targets to import.
[routeTargetImportsRemote] **	*list of string*	Route targets to import remote. **Since: 4.35.0

2.181.1.4 RemoteEthernetSegment

activeTEPs	*list of IP address*	IP addresses of the remote peers that has the Ethernet segment.

2.182 show bgp evpn route-type count

[autoDiscovery]	*integer*	Number of Ethernet auto-discovery (A-D) route (type 1) paths.
[ethernetSegment]	*integer*	Number of Ethernet segment route (type 4) paths.
[imet]	*integer*	Number of inclusive multicast Ethernet tag route (type 3) paths.
[ipPrefixIpv4]	*integer*	Number of IPv4 prefix route (type 5) paths.
[ipPrefixIpv6]	*integer*	Number of IPv6 prefix route (type 5) paths.
[macIp]	*integer*	Number of MAC/IP advertisement route (type 2) paths.

2.183 show bgp evpn sanity [...]

Could also be an instance of:
EvpnSanityModelBrief 2.183.1.1
EvpnSanityModelDetail 2.183.1.1

categories	*table(string) = EvpnSanityCategory* see 2.183.1	EVPN sanity categories to verify, keyed by their name.

2.183.1 EvpnSanityCategory

description	*string*	Description of category.
items	*list of EvpnSanityItem* see 2.183.1.1	Items to verify in this category.

2.183.1.1 EvpnSanityItem

name	*string*	Name of item.
[reasonNotOk]	*string*	Reason why this check was not successful.
status	*enum: warn | ok | fail*	Status of verification of item.
categories	*table(string) = EvpnSanityCategory* see 2.183.1	EVPN sanity categories to verify, keyed by their name.
categories	*table(string) = EvpnSanityCategory* see 2.183.1	EVPN sanity categories to verify, keyed by their name.

2.184 show bgp evpn summary [...]

revision 3

see 2.51.1

2.185 show bgp flow-spec (ipv4 | ipv6) summary [...]

revision 3

see 2.51

2.186 show bgp flow-spec (vpn-ipv4 | vpn-ipv6) summary

revision 3

see 2.51

2.187 show bgp flow-spec ipv4 [...]

vrfs	*table(string) = BgpFlowspecRules* see 2.187.1	Bgp Flowspec rule summary.

2.187.1 BgpFlowspecRules

asn	*integer*	Autonomous System Number.
routerId	*IPv4 address*	BGP Router Identity.
rules	*table(string) = BgpFlowspecRuleEntry* see 2.187.1.1	Dictionary of BGP Flowspec rule entries indexed by the route key.
vrf	*string*	VRF name.

2.187.1.1 BgpFlowspecRuleEntry

[matchDetails]	*list of string*	Descriptions of matching conditions.
paths	*list of BgpFlowspecRulePath* see 2.187.1.1.1	BGP flowspec rule paths.
ruleId	*integer*	Unique identifier of this rule.
totalPaths	*integer*	Total number of paths for this rule.
[unsupportedReason] **	*list of string*	Reasons why the flowspec nlri for the rule is unsupported. **Since: 4.33.1

2.187.1.1.1 BgpFlowspecRulePath

actions	*list of BgpFlowspecAction* see 2.187.1.1.1.1	Actions that are performed for this rule.
asPathEntry	*BgpRouteASPathEntry* see 2.20.1.1.2.1	AS path information.
[localPreference]	*integer*	I-BGP Local preference indicator.
[med]	*integer*	Multi Exit Discriminator for the route.
[peerEntry] **	*BgpRoutePeerEntry* see 2.20.1.1.2.43	Peer information for the route. **Since: 4.22.1

reasonNotBestpath	*enum: clusterlistLenTB | ebgp | localPath | macMobilityEsi | rtMembershipDefault-Originate | peerAddress | rrClient | igpDomainType | nexthopVrf | weight | igpPreference | routerId | neighborMultipath | macMobilityStickyMac | origin | age | noBest | macMobilitySeqNum | igpMetric | macMobilityRemoteDomain | originAsValidity | routeUnusable | noLocalLabel | med | ageTB | aspathLength | originatorIdOrRouterId | macMobilityTep-AddrdomainPathLength | noReason | infMed | ecmpFast | routeNotReady | localpref | originatorIdTB | pathId | invalid | clusterlistLen | routerIdTB | aigp | redist | nhgTunnelEcmpDisabled | aspathDetails | preference | originatorId*	Reason route was not selected as BGP best path.
[redirectVrf]	*BgpFlowspecRedirectVrf* see 2.187.1.1.1.2	VRF being used by a traffic redirect action.
[redistPolicy] **	*string*	Name of the redistributed flowspec policy. **Since: 4.32.2
[routeDetail]	*BgpRouteDetailEntry* see 2.20.1.1.2.2	Route details.
routeType	*BgpRouteTypeEntry* see 2.20.1.1.2.44	Route type.
[unsupportedReason] **	*list of string*	Reasons why this rule path is unsupported. **Since: 4.33.1
[weight]	*integer*	Weight for the route.

2.187.1.1.1.1 BgpFlowspecAction

action	*enum: redirectIp | markDscp | trafficAction | police | drop | redirectVrf | mirrorIp*	Type of action that is performed.
[value]	*string*	Value associated with the action.

2.187.1.1.1.2 BgpFlowspecRedirectVrf

routeTarget	*string*	Route target that was used to select a VRF.
vrf	*string*	Name of the VRF traffic is being redirected to.

2.188 show bgp flow-spec ipv6 [...]

see 2.187

2.189 show bgp flow-spec vpn-ipv4 [...]

see 2.187

2.190 show bgp flow-spec vpn-ipv6 [...]

see 2.187

2.191 show bgp instance [...]

revision 5

vrfs	*table(string) = ShowBgpInstanceModel* see 2.191.1	per VRF bgp instance information models.

2.191.1 ShowBgpInstanceModel

adjRibInsAwaitingCleanup	*integer*	Number of Adj-RIB-Ins awaiting cleanup.
afiSafiConfig	*table(string) = ShowBgpInstanceAfiSafiConfigModel* see 2.191.1.1	Configuration keyed by AFI/SAFI name.
[afiSafiConvergence]	*table(string) = ShowBgpInstanceAfiSafiConvergenceModel* see 2.191.1.2	Convergence status keyed by AFI/SAFI name.
[afiSafiState]	*table(string) = ShowBgpInstanceAfiSafiStatusModel* see 2.191.1.3	Status keyed by AFI/SAFI name.
[bgpIpv4ListenPort]	*integer*	Port BGP is listening on IPv4.
bgpIpv4Listening	*boolean*	BGP is listening on IPv4.
[bgpIpv6ListenPort]	*integer*	Port BGP is listening on IPv6.
bgpIpv6Listening	*boolean*	BGP is listening on IPv6.
converged	*boolean*	BGP has converged.
[convergenceTimeout]	*integer*	Convergence timeout in seconds.
convergenceTimer	*boolean*	Convergence timer enabled.
[convergenceTimerExpires]	*floating point number*	Convergence expiration time since epoch.
eorTimeout	*integer*	End-of-RIB timeout in seconds.
fourByteAsn	*boolean*	four-byte ASN enabled.
gracefulRestart	*boolean*	Graceful restart mode enabled.
gracefulRestartHelper	*boolean*	Graceful restart helper mode.
gracefulRestartTimeout	*integer*	Graceful restart timeout in seconds.
lbwInherit	*boolean*	Link-bandwidth inheritance is enabled.
[lbwInheritProtocols]	*table(string) = ShowBgpInstanceLbwInheritProtocolsModel* see 2.191.1.4	Attribute for LBW inheritance enabled in effective config for each source protocol.
localAs	*integer*	Local AS number.
[nexthopLuOriginateLfibUninstallDelay]	*integer*	Next hop labeled unicast origination LFIB uninstall delay timer in seconds.
outstandingEors	*integer*	Number of outstanding End-of-RIB's.
outstandingKeepalives	*integer*	Number of outstanding keepalives.
peerMacResolutionTimeout	*integer*	Peer MAC resolution in seconds.
peers	*ShowBgpInstancePeersModel* see 2.191.1.5	Peer statistics.
reflectedRoutesAttributesState	*enum: preserved | alwaysPreserved | unknown | notPreserved*	State of attributes of the reflected routes.
routerId	*IPv4 address*	Router ID.

slowPeerTimeout	*integer*	Slow peer timeout in seconds.
[timeToConverge]	*floating point number*	Time taken to BGP convergence in seconds.
[ucmpDeviation]	*floating point number*	UCMP deviation.
[ucmpLinkBwDelay]	*integer*	Link-bandwidth delay.
[ucmpLinkBwRegeneration-Limit]	*boolean*	Link-bandwidth regeneration limit is enabled.
[ucmpMaximumPaths]	*integer*	UCMP maximum paths.
ucmpMode	*enum: ucmpDisabled | ucmpMode1*	UCMP mode.

2.191.1.1 ShowBgpInstanceAfiSafiConfigModel

[additionalPaths-Installation]	*boolean*	Additional paths installation enabled.
[additionalPaths-InstallationEcmpPrimary]	*boolean*	Allow additional path with ECMP primary path.
[aigpSessionConfed]	*boolean*	AIGP session is enabled for confed peers.
[aigpSessionEbgp]	*boolean*	AIGP session is enabled for eBGP peers.
[aigpSessionIbgp]	*boolean*	AIGP session is enabled for iBGP peers.
[bgpLsProtoRoles]	*list of BgpLsProtoRole* see 2.191.1.1.2	Link State roles and protocols.
[extendedNextHopCapability]	*boolean*	Extended next-hop capability.
[importedDatabases]	*table(string) = BgpLsImportDbEntry* see 2.191.1.1.1	Dictionary of BGP Link State imported LSDBs keyed by IGP instance name.
[ipLookupLocalLabel]	*string*	Local IP lookup MPLS VRF label.
[ipLookupLocalSid]	*Srv6Sid* see 2.20.1.1.2.35	Local IP lookup SRv6 VRF SID.
[ipLuRibRouteMap]	*string*	IP LU RIB route map.
[ipLuTargetRibs]	*string*	IP LU Target RIBs.
[ipLuTunnelRibRouteMap]	*string*	IP LU tunnel RIB route map.
[lfibInstall]	*boolean*	LFIB entry installation is enabled.
[luOriginateEnabled-Nexthops]	*list of string*	Labeled unicast originate enabled next hops.
[mplsResolutionRibs]	*NhResolutionRibProfile* see 2.191.1.1.3	MPLS resolution RIBs.
[nexthopTunnelType]	*udp*	Next-hop tunnel type.
[rcfExports]	*table(string) = string*	RCF function to apply on export, keyed by AFI/SAFI name.
[rcfImports]	*table(string) = string*	RCF function to apply on import, keyed by AFI/SAFI name.
[redistributedRoutes]	*list of ShowBgpInstance-RedistProtoModel* see 2.191.1.1.5	Redistributed routes into BGP.
[resolutionRibs]	*NhResolutionRibProfile* see 2.191.1.1.3	Resolution RIBs.
[routeDistinguisher]	*integer*	Route distinguisher.
[routeDistinguisherRemote-Domain]	*integer*	Remote domain route distinguisher.

[routeMapExports]	*table(string) = string*	Route maps to apply on export, keyed by AFI/SAFI name. (overridden if RCF is configured).
[routeMapImports]	*table(string) = string*	Route maps to apply on import, keyed by AFI/SAFI name. (overridden if RCF is configured).
[routeTargetExportRemote-Domain]	*ShowBgpInstanceAfiSafi-RouteLists* see 2.191.1.1.4	Remote domain route targets to export.
[routeTargetExports]	*ShowBgpInstanceAfiSafi-RouteLists* see 2.191.1.1.4	Route targets to export.
[routeTargetImportRemote-Domain]	*ShowBgpInstanceAfiSafi-RouteLists* see 2.191.1.1.4	Remote domain route targets to import.
[routeTargetImports]	*ShowBgpInstanceAfiSafi-RouteLists* see 2.191.1.1.4	Route targets to import.
[sixPeResolutionRibs]	*NhResolutionRibProfile* see 2.191.1.1.3	6PE resolution RIBs.
[tunnelProfilePolicyName]	*string*	Name of configured tunnel profile policy.
[vxlanResolutionRibs]	*NhResolutionRibProfile* see 2.191.1.1.3	VXLAN resolution RIBs.
[waitForConvergence]	*boolean*	Convergence based update synchronization enable.

2.191.1.1.1 BgpLsImportDbEntry

source	*enum: bgp | isis | dps*	Source protocol.
status	*enum: active | notActive | idConflict*	Status of source protocol's instance.
vrf	*string*	VRF of source protocol's instance.

2.191.1.1.2 BgpLsProtoRole

protocol	*enum: bgp | isis | dps*	Link State protocols.
role	*enum: producer | propagator | consumer*	Link State roles.

2.191.1.1.3 NhResolutionRibProfile

[defaults]	*list of ResolutionRib* see 2.158.1.3.2.15	List of default resolution methods.
[error]	*string*	Invalid resolution profile reason.
[resolutionMethods]	*list of ResolutionRib* see 2.158.1.3.2.15	List of resolution methods.
[routeMap]	*string*	Route map to determine resolution profile.

2.191.1.1.4 ShowBgpInstanceAfiSafiRouteLists

[dps]	*list of string*	List of routes for dynamic path selection.
[evpn]	*list of ShowEvpnRouteTargetDetail* see 2.191.1.1.4.1	List of route-targets for EVPN.
[linkState]	*list of string*	List of routes for BGP Link State.
[mplsVpnV4u]	*list of string*	List of routes for IPv4 MPLS VPN.
[mplsVpnV6u]	*list of string*	List of routes for IPv6 MPLS VPN.
[v4Flowspec]	*list of string*	List of routes for IPv4 Flowspec.
[v4FlowspecVpn]	*list of string*	List of routes for IPv4 Flowspec VPN.
[v4SrTe]	*list of string*	List of routes for IPv4 SR-TE.
[v4lu]	*list of string*	List of routes for IPv4 Labeled Unicast.
[v4m]	*list of string*	List of routes for IPv4 Multicast.
[v4u]	*list of string*	List of routes for IPv4 Unicast.
[v6Flowspec]	*list of string*	List of routes for IPv6 Flowspec.
[v6FlowspecVpn]	*list of string*	List of routes for IPv6 Flowspec VPN.
[v6SrTe]	*list of string*	List of routes for IPv6 SR-TE.
[v6lu]	*list of string*	List of routes for IPv6 Labeled Unicast.
[v6m]	*list of string*	List of routes for IPv6 Multicast.
[v6u]	*list of string*	List of routes for IPv6 Unicast.

2.191.1.1.4.1 ShowEvpnRouteTargetDetail

autoDerived	*boolean*	Whether the route target has been auto-derived or not.
routeTarget	*string*	An EVPN route target.
[serviceId]	*integer*	The identifier from which this route target was derived (e.g., VNI).
[serviceIdType]	*vxlan*	Type of service identifier used to auto-derive the route target (e.g., VXLAN).

2.191.1.1.5 ShowBgpInstanceRedistProtoModel

[includeLeaked]	*boolean*	Include leaked routes in redistribution.
proto	*string*	Source protocol name.
[routeMap]	*string*	Route map name.

2.191.1.2 ShowBgpInstanceAfiSafiConvergenceModel

converged	*boolean*	AFI/SAFI converged.
outstandingEors	*integer*	Number of outstanding End-of-RIB's.
outstandingKeepalives	*integer*	Number of outstanding Keepalives.
[timeToConverge]	*floating point number*	Time taken to converge.

2.191.1.3 ShowBgpInstanceAfiSafiStatusModel

[producerStats]	*ShowBgpInstanceProducerStatsModel* see 2.191.1.3.1	Producer statistics.

2.191.1.3.1 ShowBgpInstanceProducerStatsModel

numIpv4Prefixes	*integer*	Number of LSDB IPv4 prefixes.
numIpv6Prefixes	*integer*	Number of LSDB IPv6 prefixes.
numLinks	*integer*	Number of LSDB links.
numNodes	*integer*	Number of LSDB nodes.

2.191.1.4 ShowBgpInstanceLbwInheritProtocolsModel

inheritedAttribute	*weight*	Attribute of the resolving route that is inherited as link-bandwidth.

2.191.1.5 ShowBgpInstancePeersModel

dynamicPeers	*integer*	Number of dynamic peers.
establishedPeers	*integer*	Number of established peers.
staticPeers	*integer*	Number of static peers.
totalPeers	*integer*	Number of peers.

2.192 show bgp instance vpn summary [...]

vrfs	*table(string) = ShowBgpInstanceVpnSummaryModel* see 2.192.1	per VRF bgp instance information models.

2.192.1 ShowBgpInstanceVpnSummaryModel

[routeDistinguisher]	*integer*	Route distinguisher.

2.193 show bgp labeled-unicast forwarding [...]

entries	*table(numeric string) = BgpLuForwardingTunnelTableEntry* see 2.193.1	BGP LU Forwarding entries keyed by tunnel index.

2.193.1 BgpLuForwardingTunnelTableEntry

labels	*list of string*	Label stack.
vias	*list of Via* see 2.193.1.1	List of nexthops.

2.193.1.1 Via

Could also be an instance of:
IpVia 2.193.1.3
MplsTunnelVia 2.193.1.5
MplsVia 2.193.1.4
TunnelVia 2.193.1.6
GreFibVia 2.193.1.2
IpInIpFibVia 2.193.1.2.6.5
IpsecFibVia 2.193.1.2.6.6
IpsecGreFibVia 2.193.1.2.6.7
MplsFibVia 2.193.1.2.6.8
Srv6FibVia 2.193.1.2.6.9
TunnelFibVia 2.193.1.2.6.1
VoqFibVia 2.193.1.2.6.10

type	*enum: tunnel | ip*	Type of via, indicating the expected attributes.

2.193.1.2 GreFibVia

[encapId]	*integer*	Encapsulation identifier.
[greEncap]	*GreTunnelInfo* see 2.193.1.2.1	Encapsulation parameters for GRE tunnel.
interface	*interface name*	Egress L3 interface of the next-hop.
[ipInIpEncap]	*IpInIpTunnelInfo* see 2.193.1.2.3	Encapsulation parameters for IP-in-IP tunnel.
[ipsecEncap]	*IpsecTunnelInfo* see 2.193.1.2.4	Encapsulation parameters for IPsec tunnel.
[ipsecGreEncap]	*IpsecGreTunnelInfo* see 2.193.1.2.2	Encapsulation parameters for GRE over IPsec tunnel.
[mplsEncap]	*MplsTunnelInfo* see 2.193.1.2.5	Encapsulation parameters for MPLS tunnel.
nexthop	*IP address*	Nexthop IP address.
[nhgId]	*integer*	Nexthop Group Id for NHG tunnel.
[nhgName]	*string*	Nexthop Group name for NHG tunnel.
[resolvingTunnel]	*TunnelId* see 2.193.1.2.6.4	Resolving tunnel Information.
[resolvingTunnelInfo] **	*ResolvingTunnelInfo* see 2.193.1.2.6	Resolving tunnel detailed inforamtion. **Since: 4.34.0

[srTePolicyId]	*SrTePolicyId* see 2.193.1.2.6.2	SR-TE policy information.
[srv6Encap]	*Srv6TransportTunnelInfo* see 2.193.1.2.6.3	Encapsulation parameters for SRv6 transport tunnel.
type	*enum: tunnel | ip*	Type of via, indicating the expected attributes.
[ucmpGenerationMode] **	*linkBandwidth*	UCMP mode. **Since: 4.32.0

2.193.1.2.1 GreTunnelInfo

Could also be an instance of:
IpsecGreTunnelInfo 2.193.1.2.2

checksum	*boolean*	Checksum in use.
[dscp]	*integer*	Differentiated services code point.
dstAddr	*IP address*	Location in the IP network where the tunnel terminates.
[hoplimit]	*integer*	Hop limit.
[key]	*integer*	GRE key.
sequence	*boolean*	Sequence numbers in use.
srcAddr	*IP address*	Location in the IP network where the tunnel starts.
[tos]	*integer*	Type of service.
[ttl]	*integer*	Time to live.

2.193.1.2.2 IpsecGreTunnelInfo

checksum	*boolean*	Checksum in use.
[dscp]	*integer*	Differentiated services code point.
dstAddr	*IP address*	Location in the IP network where the tunnel terminates.
[hoplimit]	*integer*	Hop limit.
[key]	*integer*	GRE key.
sequence	*boolean*	Sequence numbers in use.
srcAddr	*IP address*	Location in the IP network where the tunnel starts.
[tos]	*integer*	Type of service.
[ttl]	*integer*	Time to live.

2.193.1.2.3 IpInIpTunnelInfo

[dscp]	*integer*	Differentiated services code point.
dstAddr	*IP address*	Location in the IP network where the tunnel terminates.
[hoplimit]	*integer*	Hop limit.
srcAddr	*IP address*	Location in the IP network where the tunnel starts.
[tos]	*integer*	Type of service.
[ttl]	*integer*	Time to live.

2.193.1.2.4 IpsecTunnelInfo

[dscp]	*integer*	Differentiated services code point.
dstAddr	*IP address*	Location in the IP network where the tunnel terminates.
[hoplimit]	*integer*	Hop limit.
srcAddr	*IP address*	Location in the IP network where the tunnel starts.
[tos]	*integer*	Type of service.
[ttl]	*integer*	Time to live.

2.193.1.2.5 MplsTunnelInfo

labelStack	*list of string*	MPLS label stack.

2.193.1.2.6 ResolvingTunnelInfo

backupVias	*list of TunnelFibVia* see 2.193.1.2.6.1	List of resolving tunnel backup vias.
vias	*list of TunnelFibVia* see 2.193.1.2.6.1	List of resolving tunnel vias.

2.193.1.2.6.1 TunnelFibVia

Could also be an instance of:
GreFibVia 2.193.1.2
IpInIpFibVia 2.193.1.2.6.5
IpsecFibVia 2.193.1.2.6.6
IpsecGreFibVia 2.193.1.2.6.7
MplsFibVia 2.193.1.2.6.8
Srv6FibVia 2.193.1.2.6.9
VoqFibVia 2.193.1.2.6.10

[encapId] **	*integer*	Encapsulation identifier. **Since: 4.21.3
[greEncap]	*GreTunnelInfo* see 2.193.1.2.1	Encapsulation parameters for GRE tunnel.
interface	*interface name*	Egress L3 interface of the next-hop.
[ipInIpEncap] **	*IpInIpTunnelInfo* see 2.193.1.2.3	Encapsulation parameters for IP-in-IP tunnel. **Since: 4.29.1
[ipsecEncap]	*IpsecTunnelInfo* see 2.193.1.2.4	Encapsulation parameters for IPsec tunnel.
[ipsecGreEncap] **	*IpsecGreTunnelInfo* see 2.193.1.2.2	Encapsulation parameters for GRE over IPsec tunnel. **Since: 4.21.3
[mplsEncap]	*MplsTunnelInfo* see 2.193.1.2.5	Encapsulation parameters for MPLS tunnel.
nexthop	*IP address*	Nexthop IP address.

[nhgId] **	*integer*	Nexthop Group Id for NHG tunnel. **Since: 4.26.2
[nhgName] **	*string*	Nexthop Group name for NHG tunnel. **Since: 4.22.0
[resolvingTunnel] **	*TunnelId* see 2.193.1.2.6.4	Resolving tunnel Information. **Since: 4.23.1
[resolvingTunnelInfo] **	*ResolvingTunnelInfo* see 2.193.1.2.6	Resolving tunnel detailed inforamtion. **Since: 4.34.0
[srTePolicyId] **	*SrTePolicyId* see 2.193.1.2.6.2	SR-TE policy information. **Since: 4.26.0
[srv6Encap] **	*Srv6TransportTunnelInfo* see 2.193.1.2.6.3	Encapsulation parameters for SRv6 transport tunnel. **Since: 4.29.0
type	*enum: tunnel | ip*	Type of via, indicating the expected attributes.
[ucmpGenerationMode] **	*linkBandwidth*	UCMP mode. **Since: 4.32.0

2.193.1.2.6.2 SrTePolicyId

color	*integer*	Color of SR-TE policy tunnel.
endpoint	*IP address*	IP address of the SR-TE policy tunnel endpoint.

2.193.1.2.6.3 Srv6TransportTunnelInfo

[sid] **	*list of IP address*	SRv6 sid. **Since: 4.36.0
srcAddr	*IP address*	Location in the IP network where the tunnel starts.

2.193.1.2.6.4 TunnelId

index	*integer*	Tunnel index per tunnel type.

type	*enum: BGP LU Forwarding | maxTunnelType | IP-in-IP | MLDP P2MP | IS-IS SR IPv6 | invalidTunnel | IS-IS SR IPv4 | VXLAN VTEP Encap | IS-IS SRv6 | Nexthop | Static MPLS | SR-TE Policy | SR-TE | OSPF SR | IS-IS SRv6 TI-LFA | IS-IS FlexAlgo | Static IPv6 | Static MPLS Multicast | Nexthop Group | TI-LFA | LDP | RSVP LER SUB | SRv6 SR-TE SL | RSVP P2MP | RSVP LER | EosSdk sBFD | UDP | SRv6 Transport | EVPN VXLAN | VXLAN | RSVP FRR | IS-IS Remote TI-LFA | BGP LU | RSVP | IS-IS SR | Static | Static Interface*	Tunnel type.

2.193.1.2.6.5 IpInIpFibVia

[encapId]	*integer*	Encapsulation identifier.
[greEncap]	*GreTunnelInfo* see 2.193.1.2.1	Encapsulation parameters for GRE tunnel.
interface	*interface name*	Egress L3 interface of the next-hop.
[ipInIpEncap]	*IpInIpTunnelInfo* see 2.193.1.2.3	Encapsulation parameters for IP-in-IP tunnel.
[ipsecEncap]	*IpsecTunnelInfo* see 2.193.1.2.4	Encapsulation parameters for IPsec tunnel.
[ipsecGreEncap]	*IpsecGreTunnelInfo* see 2.193.1.2.2	Encapsulation parameters for GRE over IPsec tunnel.
[mplsEncap]	*MplsTunnelInfo* see 2.193.1.2.5	Encapsulation parameters for MPLS tunnel.
nexthop	*IP address*	Nexthop IP address.
[nhgId]	*integer*	Nexthop Group Id for NHG tunnel.
[nhgName]	*string*	Nexthop Group name for NHG tunnel.
[resolvingTunnel]	*TunnelId* see 2.193.1.2.6.4	Resolving tunnel Information.
[resolvingTunnelInfo] **	*ResolvingTunnelInfo* see 2.193.1.2.6	Resolving tunnel detailed inforamtion. **Since: 4.34.0
[srTePolicyId]	*SrTePolicyId* see 2.193.1.2.6.2	SR-TE policy information.
[srv6Encap]	*Srv6TransportTunnelInfo* see 2.193.1.2.6.3	Encapsulation parameters for SRv6 transport tunnel.
type	*enum: tunnel | ip*	Type of via, indicating the expected attributes.
[ucmpGenerationMode] **	*linkBandwidth*	UCMP mode. **Since: 4.32.0

2.193.1.2.6.6 IpsecFibVia

[encapId]	*integer*	Encapsulation identifier.
[greEncap]	*GreTunnelInfo* see 2.193.1.2.1	Encapsulation parameters for GRE tunnel.
interface	*interface name*	Egress L3 interface of the next-hop.
[ipInIpEncap]	*IpInIpTunnelInfo* see 2.193.1.2.3	Encapsulation parameters for IP-in-IP tunnel.
[ipsecEncap]	*IpsecTunnelInfo* see 2.193.1.2.4	Encapsulation parameters for IPsec tunnel.
[ipsecGreEncap]	*IpsecGreTunnelInfo* see 2.193.1.2.2	Encapsulation parameters for GRE over IPsec tunnel.
[mplsEncap]	*MplsTunnelInfo* see 2.193.1.2.5	Encapsulation parameters for MPLS tunnel.
nexthop	*IP address*	Nexthop IP address.
[nhgId]	*integer*	Nexthop Group Id for NHG tunnel.
[nhgName]	*string*	Nexthop Group name for NHG tunnel.
[resolvingTunnel]	*TunnelId* see 2.193.1.2.6.4	Resolving tunnel Information.
[resolvingTunnelInfo] **	*ResolvingTunnelInfo* see 2.193.1.2.6	Resolving tunnel detailed inforamtion. **Since: 4.34.0
[srTePolicyId]	*SrTePolicyId* see 2.193.1.2.6.2	SR-TE policy information.
[srv6Encap]	*Srv6TransportTunnelInfo* see 2.193.1.2.6.3	Encapsulation parameters for SRv6 transport tunnel.
type	*enum: tunnel | ip*	Type of via, indicating the expected attributes.
[ucmpGenerationMode] **	*linkBandwidth*	UCMP mode. **Since: 4.32.0

2.193.1.2.6.7 IpsecGreFibVia

[encapId]	*integer*	Encapsulation identifier.
[greEncap]	*GreTunnelInfo* see 2.193.1.2.1	Encapsulation parameters for GRE tunnel.
interface	*interface name*	Egress L3 interface of the next-hop.
[ipInIpEncap]	*IpInIpTunnelInfo* see 2.193.1.2.3	Encapsulation parameters for IP-in-IP tunnel.
[ipsecEncap]	*IpsecTunnelInfo* see 2.193.1.2.4	Encapsulation parameters for IPsec tunnel.
[ipsecGreEncap]	*IpsecGreTunnelInfo* see 2.193.1.2.2	Encapsulation parameters for GRE over IPsec tunnel.
[mplsEncap]	*MplsTunnelInfo* see 2.193.1.2.5	Encapsulation parameters for MPLS tunnel.
nexthop	*IP address*	Nexthop IP address.
[nhgId]	*integer*	Nexthop Group Id for NHG tunnel.
[nhgName]	*string*	Nexthop Group name for NHG tunnel.
[resolvingTunnel]	*TunnelId* see 2.193.1.2.6.4	Resolving tunnel Information.
[resolvingTunnelInfo] **	*ResolvingTunnelInfo* see 2.193.1.2.6	Resolving tunnel detailed inforamtion. **Since: 4.34.0

[srTePolicyId]	*SrTePolicyId* see 2.193.1.2.6.2	SR-TE policy information.
[srv6Encap]	*Srv6TransportTunnelInfo* see 2.193.1.2.6.3	Encapsulation parameters for SRv6 transport tunnel.
type	*enum: tunnel | ip*	Type of via, indicating the expected attributes.
[ucmpGenerationMode] **	*linkBandwidth*	UCMP mode. **Since: 4.32.0

2.193.1.2.6.8 MplsFibVia

[encapId]	*integer*	Encapsulation identifier.
[greEncap]	*GreTunnelInfo* see 2.193.1.2.1	Encapsulation parameters for GRE tunnel.
interface	*interface name*	Egress L3 interface of the next-hop.
[ipInIpEncap]	*IpInIpTunnelInfo* see 2.193.1.2.3	Encapsulation parameters for IP-in-IP tunnel.
[ipsecEncap]	*IpsecTunnelInfo* see 2.193.1.2.4	Encapsulation parameters for IPsec tunnel.
[ipsecGreEncap]	*IpsecGreTunnelInfo* see 2.193.1.2.2	Encapsulation parameters for GRE over IPsec tunnel.
[mplsEncap]	*MplsTunnelInfo* see 2.193.1.2.5	Encapsulation parameters for MPLS tunnel.
nexthop	*IP address*	Nexthop IP address.
[nhgId]	*integer*	Nexthop Group Id for NHG tunnel.
[nhgName]	*string*	Nexthop Group name for NHG tunnel.
[resolvingTunnel]	*TunnelId* see 2.193.1.2.6.4	Resolving tunnel Information.
[resolvingTunnelInfo] **	*ResolvingTunnelInfo* see 2.193.1.2.6	Resolving tunnel detailed inforamtion. **Since: 4.34.0
[srTePolicyId]	*SrTePolicyId* see 2.193.1.2.6.2	SR-TE policy information.
[srv6Encap]	*Srv6TransportTunnelInfo* see 2.193.1.2.6.3	Encapsulation parameters for SRv6 transport tunnel.
type	*enum: tunnel | ip*	Type of via, indicating the expected attributes.
[ucmpGenerationMode] **	*linkBandwidth*	UCMP mode. **Since: 4.32.0

2.193.1.2.6.9 Srv6FibVia

[encapId]	*integer*	Encapsulation identifier.
[greEncap]	*GreTunnelInfo* see 2.193.1.2.1	Encapsulation parameters for GRE tunnel.
interface	*interface name*	Egress L3 interface of the next-hop.
[ipInIpEncap]	*IpInIpTunnelInfo* see 2.193.1.2.3	Encapsulation parameters for IP-in-IP tunnel.
[ipsecEncap]	*IpsecTunnelInfo* see 2.193.1.2.4	Encapsulation parameters for IPsec tunnel.
[ipsecGreEncap]	*IpsecGreTunnelInfo* see 2.193.1.2.2	Encapsulation parameters for GRE over IPsec tunnel.

[mplsEncap]	*MplsTunnelInfo* see 2.193.1.2.5	Encapsulation parameters for MPLS tunnel.
nexthop	*IP address*	Nexthop IP address.
[nhgId]	*integer*	Nexthop Group Id for NHG tunnel.
[nhgName]	*string*	Nexthop Group name for NHG tunnel.
[resolvingTunnel]	*TunnelId* see 2.193.1.2.6.4	Resolving tunnel Information.
[resolvingTunnelInfo] **	*ResolvingTunnelInfo* see 2.193.1.2.6	Resolving tunnel detailed inforamtion. **Since: 4.34.0
[srTePolicyId]	*SrTePolicyId* see 2.193.1.2.6.2	SR-TE policy information.
[srv6Encap]	*Srv6TransportTunnelInfo* see 2.193.1.2.6.3	Encapsulation parameters for SRv6 transport tunnel.
type	*enum: tunnel | ip*	Type of via, indicating the expected attributes.
[ucmpGenerationMode] **	*linkBandwidth*	UCMP mode. **Since: 4.32.0

2.193.1.2.6.10 VoqFibVia

[encapId]	*integer*	Encapsulation identifier.
[greEncap]	*GreTunnelInfo* see 2.193.1.2.1	Encapsulation parameters for GRE tunnel.
interface	*interface name*	Egress L3 interface of the next-hop.
interfaceDescription	*string*	Interface description.
[ipInIpEncap]	*IpInIpTunnelInfo* see 2.193.1.2.3	Encapsulation parameters for IP-in-IP tunnel.
[ipsecEncap]	*IpsecTunnelInfo* see 2.193.1.2.4	Encapsulation parameters for IPsec tunnel.
[ipsecGreEncap]	*IpsecGreTunnelInfo* see 2.193.1.2.2	Encapsulation parameters for GRE over IPsec tunnel.
[mplsEncap]	*MplsTunnelInfo* see 2.193.1.2.5	Encapsulation parameters for MPLS tunnel.
nexthop	*IP address*	Nexthop IP address.
[nhgId]	*integer*	Nexthop Group Id for NHG tunnel.
[nhgName]	*string*	Nexthop Group name for NHG tunnel.
[resolvingTunnel]	*TunnelId* see 2.193.1.2.6.4	Resolving tunnel Information.
[resolvingTunnelInfo] **	*ResolvingTunnelInfo* see 2.193.1.2.6	Resolving tunnel detailed inforamtion. **Since: 4.34.0
[srTePolicyId]	*SrTePolicyId* see 2.193.1.2.6.2	SR-TE policy information.
[srv6Encap]	*Srv6TransportTunnelInfo* see 2.193.1.2.6.3	Encapsulation parameters for SRv6 transport tunnel.
type	*enum: tunnel | ip*	Type of via, indicating the expected attributes.
[ucmpGenerationMode] **	*linkBandwidth*	UCMP mode. **Since: 4.32.0

2.193.1.3 IpVia

interface	*interface name*	Egress L3 interface of the next-hop.
nexthop	*IP address*	Nexthop IP address.
type	*enum: tunnel* | *ip*	Type of via, indicating the expected attributes.

2.193.1.4 MplsVia

[backupTunnelInfo] **	*TunnelInfo* see 2.193.1.4.1	Backup Tunnel Information. **Since: 4.23.0
interface	*interface name*	Egress L3 interface of the next-hop.
labels	*list of string*	Label stack.
nexthop	*IP address*	Nexthop IP address.
type	*enum: tunnel* | *ip*	Type of via, indicating the expected attributes.

2.193.1.4.1 TunnelInfo

[staticInterfaceTunnelInfo] **	*IpTunnelInfo* see 2.193.1.4.1.1	Tunnel encap information for a static interface tunnel. **Since: 4.21.0
[tunnelAddressFamily]	*enum: IPv6* | *IPv4*	Address family for MPLS tunnels.
[tunnelAlgorithm] **	*string*	Flexible algorithm of the tunnel. **Since: 4.26.2
[tunnelColor] **	*integer*	Tunnel color. **Since: 4.29.2
[tunnelEndPoint]	*IP address prefix*	Route prefix for MPLS underlay nexthop resolution.
tunnelIndex	*integer*	Tunnel table index.
[tunnelName] **	*string*	Tunnel name. **Since: 4.26.2
tunnelType	*enum: BGP LU Forwarding* | *maxTunnelType* | *IP-in-IP* | *MLDP P2MP* | *invalidTunnel* | *VXLAN VTEP Encap* | *IS-IS SRv6* | *Nexthop* | *Static MPLS* | *SR-TE Policy* | *SR-TE* | *OSPF SR* | *IS-IS SRv6 TI-LFA* | *IS-IS FlexAlgo* | *Static MPLS Multicast* | *Nexthop Group* | *TI-LFA* | *LDP* | *RSVP LER SUB* | *SRv6 SR-TE SL* | *RSVP P2MP* | *RSVP LER* | *EosSdk sBFD* | *UDP* | *SRv6 Transport* | *EVPN VXLAN* | *VXLAN* | *RSVP FRR* | *IS-IS Remote TI-LFA* | *BGP LU* | *RSVP* | *IS-IS SR* | *Static Interface*	Tunnel type.

[tunnelVias] **	*list of TunnelViaInfo* see 2.193.1.4.1.2	List of tunnel vias. **Since: 4.22.0

2.193.1.4.1.1 IpTunnelInfo

tunnelDestination	*IP address*	Location in the IP network where the IP tunnel terminates.
[tunnelDscp]	*integer*	Differentiated services code point.
tunnelEncap	*enum: UDP | MPLS | GREoverIPsec | SRv6 | IP-in-IP | GRE | Invalid | VOQ | IPsec*	Tunnel encapsulation type.
[tunnelHoplimit]	*integer*	Hop limit.
[tunnelKey]	*integer*	GRE IP tunnel key.
tunnelSource	*IP address*	Location in the IP network where the IP tunnel starts.
[tunnelTos]	*integer*	Type of service.
[tunnelTtl]	*integer*	Time to live.

2.193.1.4.1.2 TunnelViaInfo

[interface]	*interface name*	Egress L3 interface of next hop.
[interfaceDescription]	*string*	Interface description.
[labelStack]	*list of integer*	MPLS label stack (top-of-stack label first).
[nextHop] **	*string*	Next-Hop name. **Since: 4.22.0
[nexthopAddr]	*IP address*	Next hop IP address.
[nhgName] **	*string*	Next-Hop-Group name. **Since: 4.22.0
[resolvingTunnel] **	*TunnelId* see 2.193.1.2.6.4	Resolving tunnel information. **Since: 4.23.1
[srTePolicyId] **	*SrTePolicyId* see 2.193.1.2.6.2	SR-TE policy id. **Since: 4.26.0
[srv6SegmentList] **	*list of IP address*	SRv6 segment list. **Since: 4.36.0
[ucmpGenerationMode] **	*linkBandwidth*	UCMP mode. **Since: 4.35.2

2.193.1.5 MplsTunnelVia

labels	*list of string*	Label stack.
tunnelId	*TunnelId* see 2.193.1.2.6.4	Tunnel Identifier.
type	*enum: tunnel | ip*	Type of via, indicating the expected attributes.

2.193.1.6 TunnelVia

tunnelId	*TunnelId* see 2.193.1.2.6.4	Tunnel Identifier.
type	*enum: tunnel | ip*	Type of via, indicating the expected attributes.

2.194 show bgp labeled-unicast forwarding raw [...]

see 2.193

2.195 show bgp labeled-unicast tunnel [...]

revision 2

entries	*table(numeric string) = BgpLuTunnelTableEntry* see 2.195.1	BGP LU tunnel table entries keyed by tunnel index.

2.195.1 BgpLuTunnelTableEntry

bgpMetric	*integer*	BGP Metric for tunnel entry.
bgpMetric2	*integer*	BGP Metric 2 for tunnel entry.
[bgpMetricType] **	*enum: AIGP | MED | metric*	BGP Metric Type for tunnel entry. **Since: 4.26.0
bgpPref	*integer*	BGP Preference for tunnel entry.
bgpPref2	*integer*	BGP Preference 2 for tunnel entry.
contribution	*string*	Contribution of tunnel entry to Tunnel RIB.
endpoint	*IP address prefix*	Endpoint of the tunnel.
labels	*list of string*	Label stack.
vias	*list of Via* see 2.193.1.1	List of nexthops.

2.196 show bgp labeled-unicast tunnel raw [...]

revision 2

see 2.195

2.197 show bgp link-state [...]

revision 2

vrfs	*table(string) = BgpLsRoutes* see 2.197.1	BGP Link State routes.

2.197.1 BgpLsRoutes

asn	*string*	Autonomous System Number.
bgpLsRoutes	*table(string) = BgpLsRouteEntry* see 2.197.1.1	Dictionary of BGP Link State route entries keyed by a string representation of the NLRI.
routerId	*IPv4 address*	BGP Router Identity.
vrf	*string*	VRF name.

2.197.1.1 BgpLsRouteEntry

identifier	*integer*	IGP Instance Identifier.
[linkDescriptor]	*BgpLsLinkDescriptor* see 2.197.1.1.1	Identity of link for link NLRIs.
localNodeDescriptor	*BgpLsNodeDescriptor* see 2.197.1.1.2	Identity of local node.
nlriType	*enum: node | ipv4Prefix | link | ipv6Prefix*	NLRI type.
paths	*list of BgpLsRoutePath* see 2.197.1.1.4	BGP-LS paths.
[prefixDescriptor]	*BgpLsPrefixDescriptor* see 2.197.1.1.3	Identity of prefix for IPv4 and IPv6 prefix NLRIs.
protocolId	*enum: isisLevel1 | isisLevel2 | bgp | bgpDps*	IGP source protocol.
[remoteNodeDescriptor]	*BgpLsNodeDescriptor* see 2.197.1.1.2	Identity of remote node for link NLRIs.
totalPaths	*integer*	Total number of paths for this BGP-LS route.

2.197.1.1.1 BgpLsLinkDescriptor

localIpv4Addrs	*list of IPv4 address*	List of local IPv4 interface addresses.
localIpv6Addrs	*list of IPv6 address*	List of local IPv6 interface addresses.
[localWanGroupId] **	*integer*	Local WAN group Identifier. **Since: 4.28.1
[localWanId] **	*integer*	Local WAN Identifier. **Since: 4.28.1
[multiTopology] **	*BgpLsMultiTopologyId* see 2.197.1.1.1.1	Multi-Topology ID. **Since: 4.31.2
remoteIpv4Addrs	*list of IPv4 address*	List of remote IPv4 interface addresses.
remoteIpv6Addrs	*list of IPv6 address*	List of remote IPv6 interface addresses.
[remoteWanId] **	*integer*	Remote WAN Identifier. **Since: 4.28.1

unknownTlvs **	*list of BgpLsUnknownTlv* see 2.20.1.1.2.8	List of unknown Link Descriptor Sub TLVs. **Since: 4.30.1

2.197.1.1.1.1 BgpLsMultiTopologyId

topologyId	*integer*	Multi-Topology ID.
[topologyName]	*string*	String representation of Multi-Topology ID.

2.197.1.1.2 BgpLsNodeDescriptor

[asn]	*string*	Autonomous System Number of BGP-LS producer.
[bgpRouterId] **	*IPv4 address*	BGP router Identifier. **Since: 4.28.1
igpRouterIdType	*enum: bgpRouterId* | *isisSystemId* | *isisPseudoNodeId* | *invalid*	Type of IGP router identifier.
[isisPnodeId]	*string*	IS-IS pseudonode Identifier.
[isisSystemId]	*string*	IS-IS system Identifier.
unknownTlvs **	*list of BgpLsUnknownTlv* see 2.20.1.1.2.8	List of unknown Node Descriptor Sub TLVs. **Since: 4.30.1

2.197.1.1.3 BgpLsPrefixDescriptor

[multiTopology] **	*BgpLsMultiTopologyId* see 2.197.1.1.1	Multi-Topology ID. **Since: 4.31.2
prefix	*IP address prefix*	Prefix originated in IGP.
unknownTlvs **	*list of BgpLsUnknownTlv* see 2.20.1.1.2.8	List of unknown Prefix Descriptor Sub TLVs. **Since: 4.30.1

2.197.1.1.4 BgpLsRoutePath

asPathEntry	*BgpRouteASPathEntry* see 2.20.1.1.2.1	AS path information.
[localPreference] **	*integer*	I-BGP Local preference indicator. **Since: 4.30.0
[med]	*integer*	Multi Exit Discriminator.
[nextHop]	*string*	Next hop address.
[peerEntry]	*BgpRoutePeerEntry* see 2.20.1.1.2.43	Peer information.

reasonNotBestpath	*enum: clusterlistLenTB* | *ebgp* | *localPath* | *macMobilityEsi* | *rtMembershipDefault-Originate* | *peerAddress* | *rrClient* | *igpDomainType* | *nexthopVrf* | *weight* | *igpPreference* | *routerId* | *neighborMultipath* | *macMobilityStickyMac* | *origin* | *age* | *noBest* | *macMobilitySeqNum* | *igpMetric* | *macMobilityRemoteDomain* | *originAsValidity* | *routeUnusable* | *noLocalLabel* | *med* | *ageTB* | *aspathLength* | *originatorIdOrRouterId* | *macMobilityTep-AddrdomainPathLength* | *noReason* | *infMed* | *ecmpFast* | *routeNotReady* | *localpref* | *originatorIdTB* | *pathId* | *invalid* | *clusterlistLen* | *routerIdTB* | *aigp* | *redist* | *nhgTunnelEcmpDisabled* | *aspathDetails* | *preference* | *originatorId*	Reason route was not selected as BGP best path.
[routeDetail]	*BgpRouteDetailEntry* see 2.20.1.1.2.2	Route details.
routeType	*BgpRouteTypeEntry* see 2.20.1.1.2.44	Route type.
[timestamp]	*integer*	UTC seconds since epoch when the path was received.
[weight]	*integer*	Weight for the path.

2.198 show bgp link-state summary

revision 3

see 2.51.1

2.199 show bgp monitoring AFI neighbors [...]

vrfs	*table(string) = VrfPeersExportStatus* see 2.199.1	Per-VRF, per-peer BGP monitoring status, keyed by VRF name.

2.199.1 VrfPeersExportStatus

`peers`	*table(IPv4 or IPv6 address) = PeerExportStatus* see 2.199.1.1	Per-peer BGP monitoring status, keyed by peer address.

2.199.1.1 PeerExportStatus

`adjRibInExport`	*boolean*	BGP received route export status.
`adjRibOutExport` **	*boolean*	BGP advertised route export status. **Since: 4.35.2
`[description]`	*string*	BGP peer description.

2.200 show bgp monitoring [...]

bgpAdjRibInExportStatus	*BgpAdjRibInExportStatus* see 2.200.1	Global BGP monitoring status.
bgpAdjRibOutExportStatus **	*BgpAdjRibOutExportStatus* see 2.200.2	Status of advertised routes export for BMP. **Since: 4.35.2
bgpAllStationGlobalExport-Status **	*BgpAllStationGlobal-ExportStatus* see 2.200.3	All stations global export status for BMP. **Since: 4.35.2
bgpLocRibExportStatus **	*BgpLocRibExportStatus* see 2.200.4	Status of BGP rib bestpaths export for BMP. **Since: 4.35.2
bmpGlobalConfig **	*BmpGlobalConfig* see 2.200.5	Status of BGP received routes export and global BMP timestamp configuration. **Since: 4.21.3
stations	*table(string) = BmpStation* see 2.200.6	Collection of station information indexed by the station's name.

2.200.1 BgpAdjRibInExportStatus

monitoringEnabled	*boolean*	BGP monitoring is enabled.

2.200.2 BgpAdjRibOutExportStatus

afiSafiExport	*table(string) = boolean*	Address family export enabled flag, keyed by address family name string.

2.200.3 BgpAllStationGlobalExportStatus

adjRibInPostPolicyExport	*boolean*	Export received post-policy routes.
adjRibInPrePolicyExport	*boolean*	Export received pre-policy routes.
locRibExport	*boolean*	Export rib bestpaths.

2.200.4 BgpLocRibExportStatus

afiSafiExport	*table(string) = boolean*	Address family export enabled flag, keyed by address family name string.
allVrfsExport	*boolean*	Global rib bestpaths export configuration inherited by VRFs.
[selectivelyDisabledVrfs]	*list of string*	List of VRFs with rib bestpaths export selectively disabled.
[selectivelyEnabledVrfs]	*list of string*	List of VRFs with rib bestpaths export selectively enabled.

2.200.5 BmpGlobalConfig

adjRibinExportVrfFilter **	*list of string*	List of VRFs filtered for exporting receiving routes. **Since: 4.33.2
afiSafiExport **	*table(string) = boolean*	Address family export enabled flag, keyed by address family name string. **Since: 4.23.0
exportIpv6LuTunnel **	*boolean*	Export IPv6 LU tunnel paths. **Since: 4.23.0
exportSixPe **	*boolean*	Export 6PE paths. **Since: 4.23.0
postPolicyExport	*boolean*	Export received post-policy routes.
prePolicyExport	*boolean*	Export received pre-policy routes.
timestampMode	*enum: none | sendTime*	BMP Timestamp setting: none - No timestamp set in BGP monitoring protocol message sendTime - Time when BGP monitoring protocol message is sent.

2.200.6 BmpStation

[address]	*StationHostnameOrAddress* see 2.200.6.5	The hostname or address of the station.
adjRibOutExport **	*BmpStationRibOutPolicies* see 2.200.6.3	BMP station BGP advertised routes export configuration. **Since: 4.35.2
connected	*boolean*	The state of the connection to the station.
connectionMode	*enum: active | unknown | passive*	The mode used to connect to the station: unknown - No mode is configured, passive - Router listens for station to connect, active - Router initiates the connection to the station.
[description]	*string*	Station description.
[exportPolicyStationConfig] **	*BmpStationPolicies* see 2.200.6.2	BMP station received routes export configuration. **Since: 4.27.1
flapCount	*integer*	Number station disconnects from the router.
locRibExport **	*BmpStationLocRibPolicies* see 2.200.6.1	BMP station BGP rib bestpaths export configuration. **Since: 4.35.2
[remotePort]	*integer*	The port of the station used for active connection mode.
state	*enum: up | connecting | idle*	The state of the station: idle - Station is stopped due to invalid config, connecting - Station is awaiting for the connection or attempting to connect, up - Station connection is established.
[tcpSocketStatistics] **	*BmpTcpStatistics* see 2.200.6.4	Peer TCP information. **Since: 4.20.5
[upTime]	*floating point number*	The timestamp in UTC when station transitioned to up.
vrfName	*string*	The VRF the station will be connected in.

2.200.6.1 BmpStationLocRibPolicies

exportStatus	*boolean*	This station exports BGP rib bestpaths.

2.200.6.2 BmpStationPolicies

postPolicyExport	*boolean*	This station exports received post-policy routes.
prePolicyExport	*boolean*	This station exports received pre-policy routes.

2.200.6.3 BmpStationRibOutPolicies

exportStatus	*boolean*	This station exports advertised rotues.

2.200.6.4 BmpTcpStatistics

congestionWindow	*integer*	TCP send congestion window (bytes).
delayedAckTimeout	*integer*	TCP socket delayed ack timeout (micro secions).
maxSegmentSize	*integer*	TCP outgoing maximum segment size (bytes).
options	*TcpOptions* see 2.200.6.4.1	TCP socket options.
outputQueueLength	*integer*	TCP output queue length.
outputQueueMaxLength	*integer*	TCP output queue max length.
recvRtt	*integer*	TCP receive round-trip time (micro seconds).
recvWindow	*integer*	TCP advertised receive window (bytes).
recvWindowScale	*integer*	TCP socket receive window scale factor.
retransmitTimeout	*integer*	TCP socket retransmission timeout (micro seconds).
sendRtt	*integer*	TCP round-trip time (micro seconds).
sendRttVariance	*integer*	TCP round-trip time variance (micro seconds).
sendWindowScale	*integer*	TCP socket send window scale factor.
slowStartThreshold	*integer*	TCP send slow start size threshold (bytes).
state	*enum: CLOSED* | *TIME-WAIT* | *CLOSE-WAIT* | *FIN-WAIT-1* | *SYN-RECEIVED* | *ESTABLISHED* | *LISTEN* | *SYN-SENT* | *NOTUSED* | *CLOSING* | *FIN-WAIT-2* | *LAST-ACK*	TCP Socket current state.
totalRetrans	*integer*	Total number of TCP retransmissions.

2.200.6.4.1 TcpOptions

ecn	*boolean*	Explicit Congestion Notification enabled.
selectiveAcks	*boolean*	Selective Acknowledgments enabled.
timestamps	*boolean*	Timestamps enabled.
windowScale	*boolean*	Window Scale enabled.

2.200.6.5 StationHostnameOrAddress

[hostName]	*string*	The hostname of the station.
[ip]	*IP address*	The IP address of the station.

2.201 show bgp monitoring active [...]

bgpAdjRibInExportStatus	*BgpAdjRibInExportStatus* see 2.200.1	Global BGP monitoring status.
stations	*table(string) = BmpActive* see 2.201.1	The collection of stations that are using active mode.

2.201.1 BmpActive

address	*StationHostnameOrAddress* see 2.200.6.5	The hostname or address of the station.
connected	*boolean*	The state of the connection to the station.
connectionAttempts	*integer*	The number of times the router has attempted to connect to the station.
connectionErrors	*integer*	The number of times the router has failed to connect to the station.
connectionSuccesses	*integer*	The number of times the router has successfully connected to the station.
[reason]	*string*	The reason why the connection is False.
remotePort	*integer*	The port of the station used for active connection mode.
retryInterval	*integer*	The interval in seconds which the connection will be retried if an attempt fails.
[retryTime]	*floating point number*	The timestamp in UTC of when the router will initiate a connection to the station.
vrfName	*string*	The VRF the station will be connected in.

2.202 show bgp monitoring active summary

bgpAdjRibInExportStatus	*BgpAdjRibInExportStatus* see 2.200.1	Global BGP monitoring status.
stations	*table(string) = BmpActiveSummary* see 2.202.1	The collection of stations that are using active mode.

2.202.1 BmpActiveSummary

connected	*boolean*	The state of the connection to the station.
[retryTime]	*floating point number*	The timestamp in UTC of when the router will initiate a connection to the station.

2.203 show bgp monitoring internal scheduler [...]

see 2.92

2.204 show bgp monitoring passive [...]

revision 2

bgpAdjRibInExportStatus	*BgpAdjRibInExportStatus* see 2.200.1	Global BGP monitoring status.
listenersV4	*table(string) = BmpPassive* see 2.204.1	Collection of IPv4 BMP listeners indexed by VRF name.
listenersV6	*table(string) = BmpPassive* see 2.204.1	Collection of IPv6 BMP listeners indexed by VRF name.

2.204.1 BmpPassive

connectionsAccepted	*integer*	Number of connections accepted.
connectionsRejected	*integer*	Number of connections rejected.
listening	*boolean*	The state of the listener for when the listener is ready to accept connections.
port	*integer*	Port number that is listening for connections.
[reason]	*string*	The reason why listening is False.
stations	*table(string) = StationHostnameOrAddress* see 2.200.6.5	The collection of stations and their hostname this listener will accept when a new connection is made indexed by the station's name.

2.205 show bgp monitoring passive summary

revision 2

bgpAdjRibInExportStatus	*BgpAdjRibInExportStatus* see 2.200.1	Global BGP monitoring status.
listenersV4	*table(string) = BmpPassiveSummary* see 2.205.1	Collection of IPv4 BMP listeners indexed by VRF name.
listenersV6	*table(string) = BmpPassiveSummary* see 2.205.1	Collection of IPv6 BMP listeners indexed by VRF name.

2.205.1 BmpPassiveSummary

listening	*boolean*	Listener is ready to accept connections.
port	*integer*	Port number that is listening for connections.
stationCount	*integer*	Number of stations configured for this listener.

2.206 show bgp monitoring summary

bgpAdjRibInExportStatus	*BgpAdjRibInExportStatus* see 2.200.1	Global BGP monitoring status.
bmpGlobalConfig **	*BmpGlobalConfig* see 2.200.5	Bmp export policy and timestamp configuration. **Since: 4.21.3
stations	*table(string) = BmpStationSummary* see 2.206.1	Collection of station information indexed by the station's name.

2.206.1 BmpStationSummary

state	*enum: up | connecting | idle*	The state of the station: idle - Station is stopped due to invalid config, connecting - Station is awaiting for the connection or attempting to connect, up - Station connection is established.
[upTime]	*floating point number*	The timestamp in UTC when station transitioned to up.

2.207 show bgp mvpn-ipv4 (vrf VRF) route-type intra-as-ipmsi [...]

vrfs	*table(string) = MvpnRoutes* see 2.207.1	MVPN route summary.

2.207.1 MvpnRoutes

asn	*integer*	Autonomous System Number.
mvpnRoutes	*table(string) = MvpnRouteEntry* see 2.207.1.1	Dictionary of MVPN route entries indexed by the route key.
routerId	*IPv4 address*	BGP Router Identity.
vrf	*string*	VRF name.

2.207.1.1 MvpnRouteEntry

mvpnRoutePaths	*list of MvpnRoutePath* see 2.207.1.1.2	List of MVPN route ECMP paths.
routeKeyDetail	*MvpnRouteKeyDetail* see 2.207.1.1.1	NLRI details.
[totalPaths]	*integer*	Total number of paths for this route.

2.207.1.1.1 MvpnRouteKeyDetail

[group]	*IP address*	Multicast group address.
nlriType	*enum: sourceTree | intraAsIpmsi | sourceActive | sharedTree | selectivePmsi*	NLRI type.
[originator]	*IP address*	The originating routers IP address in intra-as-ipmsi routes.
[rd]	*string*	Route distinguisher. For locally sourced source-tree and shared-tree routes, set to the RD of the UMH.
[source]	*IP address*	Multicast source or RP address.
[sourceAs]	*string*	The originating routers Autonomous System in shared-tree and source-tree routes.

2.207.1.1.2 MvpnRoutePath

asPathEntry	*MvpnRouteAsPathEntry* see 2.207.1.1.2.1	AS path information.
[localPreference]	*integer*	I-BGP Local preference indicator.
[med]	*integer*	Multi Exit Discriminator for the route.
[nextHop]	*string*	Route next hop address.

reasonNotBestpath	*enum: clusterlistLenTB* | *ebgp* | *localPath* | *macMobilityEsi* | *rtMembershipDefault-Originate* | *peerAddress* | *rrClient* | *igpDomainType* | *nexthopVrf* | *weight* | *igpPreference* | *routerId* | *neighborMultipath* | *macMobilityStickyMac* | *origin* | *age* | *noBest* | *macMobilitySeqNum* | *igpMetric* | *macMobilityRemoteDomain* | *originAsValidity* | *routeUnusable* | *noLocalLabel* | *med* | *ageTB* | *aspathLength* | *originatorIdOrRouterId* | *macMobilityTep-AddrdomainPathLength* | *noReason* | *infMed* | *ecmpFast* | *routeNotReady* | *localpref* | *originatorIdTB* | *pathId* | *invalid* | *clusterlistLen* | *routerIdTB* | *aigp* | *redist* | *nhgTunnelEcmpDisabled* | *aspathDetails* | *preference* | *originatorId*	Reason route was not selected as BGP best path.
[routeDetail]	*MvpnRouteDetailEntry* see 2.207.1.1.2.2	Route details.
routeType	*BgpVpnRouteTypeEntry* see 2.178.1.1.1	Route type.
[tag] **	*integer*	Tag for the route. **Since: 4.29.1
[timestamp]	*integer*	UTC seconds since epoch when the route was received.Only returned with detail output.
[weight]	*integer*	Weight for the route.

2.207.1.1.2.1 MvpnRouteAsPathEntry

[asPath]	*string*	AS path string (if absent, then the route was originated locally).
asPathType	*enum: Internal* | *Local* | *Confed-External* | *Invalid* | *External*	AS path type: Internal: originated by I-BGP, External: originated by E-BGP, Confed-External: originated by a E-BGP confederation, Local: originated locally, Invalid: AS path is invalid.

2.207.1.1.2.2 MvpnRouteDetailEntry

[clusterList]	*string*	Cluster list for the route.
communities	*list of string*	List of communities for this route.
[customerAttributeSet]	*CustomerAttributesDetail-Entry* see 2.178.1.1.3.1	Customer Attributes.
extCommunities	*list of string*	List of extended communities for this route.
extCommunityListRaw	*list of integer*	List of raw extended communities for this route.
fromRRClient	*boolean*	Route received from route reflector client.
largeCommunities	*list of string*	List of large communities for route.
origin	*enum: Incomplete | Igp | Egp*	Route origin.
[originator]	*IPv4 address*	Router ID of the originator of this route.
[peerEntry]	*BgpRoutePeerEntry* see 2.20.1.1.2.43	Peer information for the route.
[pmsiTunnel]	*PmsiTunnel* see 2.20.1.1.2.38	P-Multicast Serivce Interface Tunnel Attribute.
[rxSafi]	*string*	Received SAFI of this route.
tunnelRibEligible	*boolean*	Route eligible to be installed in Tunnel RIB.

2.208 show bgp mvpn-ipv4 (vrf VRF) route-type selective-pmsi [...]

see 2.207

2.209 show bgp mvpn-ipv4 (vrf VRF) route-type shared-tree [...]

see 2.207

2.210 show bgp mvpn-ipv4 (vrf VRF) route-type source-active [...]

see 2.207

2.211 show bgp mvpn-ipv4 (vrf VRF) route-type source-tree [...]

see 2.207

2.212 show bgp mvpn-ipv4 route-type intra-as-ipmsi [...]

see 2.207

2.213 show bgp mvpn-ipv4 route-type selective-pmsi [...]

see 2.207

2.214 show bgp mvpn-ipv4 route-type shared-tree [...]

see 2.207

2.215 show bgp mvpn-ipv4 route-type source-active [...]

see 2.207

2.216 show bgp mvpn-ipv4 route-type source-tree [...]

see 2.207

2.217 show bgp mvpn-ipv4 rsvp leaf [...]

`vrfs`	*table(string) = MvpnVrfRsvpLeafStatus* see 2.217.1	Dictionary of MVPN RSVP VRF leaf status indexed by VRF ID.

2.217.1 MvpnVrfRsvpLeafStatus

`extendedTunnel`	*IP address*	Extended tunnel ID.
`p2mpIds`	*table(numeric string) = MvpnVrfRsvpLeafTunnelIdModel* see 2.217.1.1	Dictionary of MVPN RSVP tunnel models indexed by P2MP ID.
`[tunnelProfile]`	*string*	Tunnel profile name.
`vrfId`	*integer*	VRF ID.

2.217.1.1 MvpnVrfRsvpLeafTunnelIdModel

`tunnelIds`	*table(numeric string) = MvpnRsvpSessionIdLeafSet* see 2.217.1.1.1	Dictionary of MVPN RSVP leaf sets indexed by tunnel ID.

2.217.1.1.1 MvpnRsvpSessionIdLeafSet

`leafNodes`	*list of IP address*	A set of leaf nodes in a VRF with the same SessionId.

2.218 show bgp mvpn-ipv4 summary

revision 3

see 2.51

2.219 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) ((routes | advertised-routes | (received-routes))) ((IP | IP_PREFIX)) [...]

revision 3

see 2.20

2.220 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) ((routes | advertised-routes | (received-routes))) [...]

revision 3

see 2.20

2.221 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) evpn (advertised-routes | routes | received-routes) [...]

revision 2

see 2.178

2.222 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) flow-spec ipv4 (((routes | received-routes | (advertised-routes)))) [...]

see 2.187

2.223 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) flow-spec ipv6 (((routes | received-routes | (advertised-routes)))) [...]

see 2.187

2.224 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) flow-spec vpn-ipv4 ROUTE_TYPE [...]

see 2.187

2.225 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) flow-spec vpn-ipv6 ROUTE_TYPE [...]

see 2.187

2.226 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) link-state ((routes | advertised-routes | (received-routes))) [...]

revision 2

see 2.197

2.227 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) path-selection ROUTE_TYPE [...]

vrfs	*table(string) = BgpDpsVrfRoutes* see 2.227.1	BGP path selection routes keyed by VRF.

2.227.1 BgpDpsVrfRoutes

asn	*string*	Autonomous system number.
nlris	*table(string) = BgpDpsVrfNlriRoutes* see 2.227.1.1	BGP path selection routes keyed by NLRI.
routerId	*IPv4 address*	BGP router identity.

2.227.1.1 BgpDpsVrfNlriRoutes

vteps	*table(IPv4 or IPv6 address prefix) = BgpDpsRouteEntry* see 2.227.1.1.1	BGP path selection routes keyed by VTEP address.

2.227.1.1.1 BgpDpsRouteEntry

dpsRoutePaths	*list of BgpDpsRoutePath* see 2.227.1.1.1.1	List of BGP path selection route ECMP paths.
[totalPaths]	*integer*	Total number of paths for this route.

2.227.1.1.1.1 BgpDpsRoutePath

[asPathEntry]	*BgpRouteASPathEntry* see 2.20.1.1.2.1	AS path information.
[avtNodeInfo]	*BgpDpsAvtNodeInfo* see 2.227.1.1.1.2	Adaptive virtual topology information.
[endpointAddr]	*IP address*	DPS endpoint address.
[ipSecurityInfo]	*IpSecurityInfo* see 2.227.1.1.1.4	IP security tunnel encapsulation information.
[localPreference]	*integer*	I-BGP Local preference indicator.
[med]	*integer*	Multi Exit Discriminator.
[nextHop]	*string*	Next hop address.
[pathGroupName]	*string*	DPS path group name.
[peerEntry]	*BgpRoutePeerEntry* see 2.20.1.1.2.43	Peer information.
routeState	*BgpDpsRouteState* see 2.227.1.1.1.3	Route state.
[timestamp]	*floating point number*	UTC seconds since epoch when the path was received.
[udpPort]	*integer*	DPS endpoint UDP port.
[wanId]	*integer*	DPS endpoint WAN ID.
[weight]	*integer*	Weight for the path.

2.227.1.1.1.2 BgpDpsAvtNodeInfo

[regionId]	*integer*	Adaptive virtual topology region ID.
[role]	*enum: region transit* | *unknown* | *edge* | *zone transit* | *pathfinder*	Adaptive virtual topology role.
[siteId]	*integer*	Adaptive virtual topology site ID.
[zoneId]	*integer*	Adaptive virtual topology zone ID.

2.227.1.1.1.3 BgpDpsRouteState

queued	*boolean*	Route is queued for advertisement.
stale	*boolean*	Route is stale.
valid	*boolean*	Route is valid.

2.227.1.1.1.4 IpSecurityInfo

algorithms	*list of IpSecurityAlgorithmInfo* see 2.227.1.1.1.5	Algorithm information.
[initialContact]	*boolean*	A flag to indicate whether this is an initial contact.
keyExchanges	*list of IpSecurityKeyExchangeInfo* see 2.227.1.1.1.6	Key exchange information.
[nonceLength]	*integer*	Length of nonce data in bytes.
[rekeyCounter]	*integer*	Rekey counter.

2.227.1.1.1.5 IpSecurityAlgorithmInfo

[authenticationAlgo]	*enum: sha256* | *sha384* | *md5* | *nonehash* | *sha1* | *nullhash* | *sha512*	Authentication algorithm.
[encryptionAlgo]	*enum: aes256gcm128* | *nullesp* | *aes128gcm64* | *aes256* | *aes128gcm128* | *aes128* | *des3* | *aes192*	Encryption algorithm.

2.227.1.1.1.6 IpSecurityKeyExchangeInfo

[dhGroup]	*integer*	Diffie-Hellman group number.
[dhKeyLength]	*integer*	Length of Diffie-Hellman public value in bytes.

2.228 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) rt-membership ROUTE_TYPE

revision 2

vrfs	*table(string) = RtMembershipRoutes* see 2.228.1	RT MEMBERSHIP route summary.

2.228.1 RtMembershipRoutes

asn	*integer*	Autonomous System Number.
routerId	*IPv4 address*	BGP Router Identity.
rtMembershipRoutes	*table(string) = RtMembershipRouteEntry* see 2.228.1.1	Dictionary of BGP RT MEMBERSHIP route entries indexed by the route key.
vrf	*string*	VRF name.

2.228.1.1 RtMembershipRouteEntry

routeKeyDetail	*RtMembershipRouteKeyDetail* see 2.228.1.1.1	NLRI details.
rtMembershipRoutePaths	*list of RtMembershipRoutePath* see 2.228.1.1.2	List of BGP RT MEMBERSHIP route ECMP paths.
[totalPaths]	*integer*	Total number of paths for this route.

2.228.1.1.1 RtMembershipRouteKeyDetail

nlriLength	*integer*	The number of bits (0-96) in the overall Route Target membership NLRI.
originAs	*string*	The ASN of the Autonomous System that originated the Route Target prefix.
routeTargetPrefix	*RtMembershipRouteTargetPrefix* see 2.228.1.1.1.1	The Route Target prefix.

2.228.1.1.1.1 RtMembershipRouteTargetPrefix

maskLength	*integer*	The number of bits (0-64) in the Route Target prefix.
routeTarget	*integer*	The Route Target prefix value.

2.228.1.1.2 RtMembershipRoutePath

asPathEntry	*RtMembershipRouteASPathEntry* see 2.228.1.1.2.1	AS path information.
[localPreference]	*integer*	I-BGP Local preference indicator.

[med]	*integer*	Multi Exit Discriminator for the route.
[nextHop]	*string*	Route next hop address.
[routeDetail]	*RtMembershipRouteDetail-Entry* see 2.228.1.1.2.2	Route details.
routeType	*RtMembershipRouteType-Entry* see 2.228.1.1.2.3	Route type.
[tag]	*integer*	Tag for the route.
[timestamp]	*integer*	UTC seconds since epoch when the route was received.Only returned with detail output.
[weight]	*integer*	Weight for the route.

2.228.1.1.2.1 RtMembershipRouteASPathEntry

[asPath]	*string*	AS path string (if absent, then the route was originated locally).
asPathType	*enum: Internal | Local | Confed-External | Invalid | External*	AS path type: Internal - originated by I-BGP External - originated by E-BGP Confed-External - originated by a E-BGP confederation Local - originated locally Invalid - AS path is invalid.

2.228.1.1.2.2 RtMembershipRouteDetailEntry

communities	*list of string*	List of communities for this route.
extCommunities	*list of string*	List of extended communities for this route.
extCommunityListRaw	*list of integer*	List of raw extended communities for this route.
fromRRClient	*boolean*	Route received from route reflector client.
largeCommunities	*list of string*	List of large communities for this route.
origin	*enum: Incomplete | Igp | Egp*	Route origin.
[originator]	*IPv4 address*	Router ID of the originator of this route.
[peerEntry]	*BgpRoutePeerEntry* see 2.20.1.1.2.43	Peer information for the route.

[reasonNotBestpath]	*enum: clusterlistLenTB* | *ebgp* | *localPath* | *macMobilityEsi* | *rtMembershipDefault-Originate* | *peerAddress* | *rrClient* | *igpDomainType* | *nexthopVrf* | *weight* | *igpPreference* | *routerId* | *neighborMultipath* | *macMobilityStickyMac* | *origin* | *age* | *noBest* | *macMobilitySeqNum* | *igpMetric* | *macMobilityRemoteDomain* | *originAsValidity* | *routeUnusable* | *noLocalLabel* | *med* | *ageTB* | *aspathLength* | *originatorIdOrRouterId* | *macMobilityTep-AddrdomainPathLength* | *noReason* | *infMed* | *ecmpFast* | *routeNotReady* | *localpref* | *originatorIdTB* | *pathId* | *invalid* | *clusterlistLen* | *routerIdTB* | *aigp* | *redist* | *nhgTunnelEcmpDisabled* | *aspathDetails* | *preference* | *originatorId*	Reason route was not selected as BGP best path.
[rxSafi]	*string*	Received SAFI of this route.

2.228.1.1.2.3 RtMembershipRouteTypeEntry

active	*boolean*	Route is active.
atomicAggregator	*boolean*	Route is an atomic-aggregate.
backup	*boolean*	Route is backup.
ecmp	*boolean*	Route is an ECMP route.
ecmpContributor	*boolean*	Route contributes to ECMP.
ecmpHead	*boolean*	Route is the ECMP head.
[localAgg]	*boolean*	Route is locally aggregated.
[origin]	*enum: Incomplete* | *Igp* | *Egp*	Route origin.
queued	*boolean*	Route is queued for advertisement.
stale	*boolean*	Route is stale.
suppressed	*boolean*	Route is suppressed from entering the Rib.
[ucmp]	*boolean*	Route is an UCMP route.
valid	*boolean*	Route is valid.
[waitForConvergence]	*boolean*	Route is pending best path selection.

2.229 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) rt-membership filter

`vrfs`	*table(string) = ShowRtMembership-NeighborFilterVrfModel* see 2.229.1	RT membership neighbor filter information, keyed by VRF name.

2.229.1 ShowRtMembershipNeighborFilterVrfModel

`peers`	*table(IP address and interface name (for IPv6 link local peers only)) = ShowRtMembership-NeighborFilterPeerModel* see 2.229.1.1	RT membership VRF neighbor filter information, keyed by peer address.

2.229.1.1 ShowRtMembershipNeighborFilterPeerModel

`routeTargets`	*list of route target*	RT membership VRF and neighbor route target filter.

2.230 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) sr-te POLICY_FILTER [...]

revision 3

see 2.20

2.231 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) vpn-ipv4 ((routes | advertised-routes | (received-routes))) PREFIX (rd RD_VAL) internal [...]

revision 2

vrfs	*table(string) = MplsVpnRoutes* see 2.231.1	MPLS VPN route summary.

2.231.1 MplsVpnRoutes

asn	*integer*	Autonomous System Number.
[currentSeqNum]	*integer*	Current route sequence number.
[lastProcessedSeqNum]	*integer*	Last route sequence number acknowledged.
mplsVpnRoutes	*table(string) = MplsVpnRouteEntry* see 2.231.1.1	Dictionary of BGP MPLS VPN route entries indexed by the route key.
routerId	*IPv4 address*	BGP Router Identity.
vrf	*string*	VRF name.

2.231.1.1 MplsVpnRouteEntry

mplsVpnRoutePaths	*list of MplsVpnRoutePath* see 2.231.1.1.2	List of BGP MPLS VPN route ECMP paths.
routeKeyDetail	*MplsVpnRouteKeyDetail* see 2.231.1.1.1	NLRI details.
[routePriority] **	*enum: medium | high | low*	Route processing priority. **Since: 4.32.1
[totalPaths]	*integer*	Total number of paths for this route.

2.231.1.1.1 MplsVpnRouteKeyDetail

[ipGenPrefix]	*IP address prefix*	IPv4 or IPv6 address prefix.
nlriType	*enum: IPv4 prefix | IPv6 prefix*	NLRI type.
[rd]	*string*	Route distinguisher.

2.231.1.1.2 MplsVpnRoutePath

asPathEntry	*MplsVpnRouteASPathEntry* see 2.231.1.1.2.1	AS path information.
[importedMplsVpnPathRd]	*string*	Imported MPLS VPN path RouteDistinguisher.
[localPreference]	*integer*	I-BGP Local preference indicator.
[med]	*integer*	Multi Exit Discriminator for the route.
[nextHop]	*string*	Route next hop address.

reasonNotBestpath	*enum: clusterlistLenTB* | *ebgp* | *localPath* | *macMobilityEsi* | *rtMembershipDefault-Originate* | *peerAddress* | *rrClient* | *igpDomainType* | *nexthopVrf* | *weight* | *igpPreference* | *routerId* | *neighborMultipath* | *macMobilityStickyMac* | *origin* | *age* | *noBest* | *macMobilitySeqNum* | *igpMetric* | *macMobilityRemoteDomain* | *originAsValidity* | *routeUnusable* | *noLocalLabel* | *med* | *ageTB* | *aspathLength* | *originatorIdOrRouterId* | *macMobilityTep-AddrdomainPathLength* | *noReason* | *infMed* | *ecmpFast* | *routeNotReady* | *localpref* | *originatorIdTB* | *pathId* | *invalid* | *clusterlistLen* | *routerIdTB* | *aigp* | *redist* | *nhgTunnelEcmpDisabled* | *aspathDetails* | *preference* | *originatorId*	Reason route was not selected as BGP best path.
[routeDetail]	*MplsVpnRouteDetailEntry* see 2.231.1.1.2.2	Route details.
routeType	*BgpVpnRouteTypeEntry* see 2.178.1.1.1	Route type.
[tag] **	*integer*	Tag for the route. **Since: 4.29.1
[timestamp]	*integer*	UTC seconds since epoch when the route was received.Only returned with detail output.
[weight]	*integer*	Weight for the route.

2.231.1.1.2.1 MplsVpnRouteASPathEntry

[asPath]	*string*	AS path string (if absent, then the route was originated locally).
asPathType	*enum: Internal* | *Local* | *Confed-External* | *Invalid* | *External*	AS path type: Internal - originated by I-BGP External - originated by E-BGP Confed-External - originated by a E-BGP confederation Local - originated locally Invalid - AS path is invalid.

2.231.1.1.2.2 MplsVpnRouteDetailEntry

[aggregator]	*string*	Aggregator of the route.
[clusterList]	*string*	Cluster list for the route.
communities	*list of string*	List of communities for this route.
[customerAttributeSet]	*CustomerAttributesDetail-Entry* see 2.178.1.1.3.1	Customer Attributes.
[domainPath]	*list of string*	Domain path attribute.
extCommunities	*list of string*	List of extended communities for this route.
extCommunityListRaw	*list of integer*	List of raw extended communities for this route.
fromRRClient	*boolean*	Route received from route reflector client.
[labelStack]	*list of integer*	MPLS label stack information.
largeCommunities	*list of string*	List of large communities for route.
[localLabel]	*LocalEncapLabel* see 2.20.1.1.2.37	Local MPLS label.
[localSrv6Sid] **	*EncapLabel* see 2.20.1.1.2.34	Local SRv6 SID. **Since: 4.30.1
origin	*enum: Incomplete | Igp | Egp*	Route origin.
[originator]	*IPv4 address*	Router ID of the originator of this route.
[peerEntry]	*BgpRoutePeerEntry* see 2.20.1.1.2.43	Peer information for the route.
[pendingTimeToAdv]	*floating point number*	Timestamp of route advertisement.
[redistributionProtocol]	*enum: unknown | Connected | Static | Rip | Ospf | Ospf3 | Is-Is*	Protocol from which route got redistributed into BGP.
[remoteLabel]	*EncapLabel* see 2.20.1.1.2.34	Remote MPLS label.
[remoteSrv6Sid] **	*EncapLabel* see 2.20.1.1.2.34	Remote SRv6 SID. **Since: 4.30.1
[rxPathId]	*integer*	Received path ID of this route.
[rxSafi]	*string*	Received SAFI of this route.
[seqNumber]	*integer*	Route sequence number.
tunnelRibEligible	*boolean*	Route eligible to be installed in Tunnel RIB.
[txPathId]	*integer*	Advertised path ID for this route.

2.232 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) vpn-ipv4 ((routes | advertised-routes | (received-routes))) [...]

revision 2

see 2.231

2.233 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) vpn-ipv6 ((routes | advertised-routes | (received-routes))) PREFIX (rd RD_VAL) internal [...]

revision 2

see 2.231

2.234 show bgp neighbors (IP_PEER | IP6_PEER | IP6_LL_PEER) vpn-ipv6 ((routes | advertised-routes | (received-routes))) [...]

revision 2

see 2.231

2.235 show bgp neighbors PEER vpls (advertised-routes | received-routes | routes) [...]

asn	*integer*	Autonomous System Number.
routerId	*IPv4 address*	BGP Router Identity.
routes	*table(string) = BgpVplsRoute* see 2.235.1	BGP VPLS routes indexed by route key.
vrf	*string*	VRF name.

2.235.1 BgpVplsRoute

paths	*list of BgpVplsPath* see 2.235.1.1	BGP VPLS route paths.
routeKeyDetail	*BgpVplsRouteKeyDetail* see 2.235.1.2	NLRI details.
totalPaths	*integer*	Total number of paths for this route.

2.235.1.1 BgpVplsPath

asPathEntry	*BgpRouteASPathEntry* see 2.20.1.1.2.1	AS path information.
[localPreference]	*integer*	Local preference.
[med]	*integer*	Multi exit discriminator.
[nextHop]	*IP address*	Next hop address.

reasonNotBestpath	*enum: clusterlistLenTB | ebgp | localPath | macMobilityEsi | rtMembershipDefault-Originate | peerAddress | rrClient | igpDomainType | nexthopVrf | weight | igpPreference | routerId | neighborMultipath | macMobilityStickyMac | origin | age | noBest | macMobilitySeqNum | igpMetric | macMobilityRemoteDomain | originAsValidity | routeUnusable | noLocalLabel | med | ageTB | aspathLength | originatorIdOrRouterId | macMobilityTep-AddrdomainPathLength | noReason | infMed | ecmpFast | routeNotReady | localpref | originatorIdTB | pathId | invalid | clusterlistLen | routerIdTB | aigp | redist | nhgTunnelEcmpDisabled | aspathDetails | preference | originatorId*	Reason route was not selected as BGP best path.
[routeDetail]	*BgpVplsRouteDetailEntry* see 2.235.1.1.1	Route details.
routeType	*BgpVpnRouteTypeEntry* see 2.178.1.1.1	Route type.
[tag] **	*integer*	Tag. **Since: 4.29.1
[timestamp]	*integer*	UTC seconds since epoch when the route was received.
[weight]	*integer*	Weight.

2.235.1.1.1 BgpVplsRouteDetailEntry

[clusterList]	*string*	Cluster list for the route.
communities	*list of string*	List of communities for this route.
[customerAttributeSet] **	*CustomerAttributesDetail-Entry* see 2.178.1.1.3.1	Customer Attributes. **Since: 4.33.0
extCommunities	*list of string*	List of extended communities for this route.
extCommunityListRaw	*list of integer*	List of raw extended communities for this route.
fromRRClient	*boolean*	Route received from route reflector client.
largeCommunities	*list of string*	List of large communities for route.

origin	*enum: Incomplete | Igp | Egp*	Route origin.
[originator]	*IPv4 address*	Router ID of the originator of this route.
[peerEntry]	*BgpRoutePeerEntry* see 2.20.1.1.2.43	Peer information for the route.
[rxPathId] **	*integer*	Received path ID of this route. **Since: 4.32.2
[rxSafi]	*string*	Received SAFI of this route.
tunnelRibEligible	*boolean*	Route eligible to be installed in Tunnel RIB.
[txPathId] **	*integer*	Advertised path ID of this route. **Since: 4.32.2
[vplsVeBlockSize]	*integer*	The number of labels in the VPLS VE block.
[vplsVeLabelBase]	*integer*	The first label in the VPLS VE block.

2.235.1.2 BgpVplsRouteKeyDetail

nlriType	*enum: autoDiscovery | signaling*	NLRI type.
[peAddr]	*integer*	PE address.
[rd]	*string*	Route distinguisher.
[vplsVeBlockOffset] **	*integer*	The VE ID of the first PE that can use a label from the block. **Since: 4.33.0
[vplsVeId] **	*integer*	VPLS Edge identifier. **Since: 4.33.0

2.236 show bgp neighbors [...]

revision 3

see 2.20

2.237 show bgp neighbors history [...]

vrfs	*table(string) = NeighborHistoryVrfModel* see 2.237.1	A dictionary of peer event histories keyed by VRF name.

2.237.1 NeighborHistoryVrfModel

peers	*table(IP address and interface name (for IPv6 link local peers only)) = NeighborHistoryPeerModel* see 2.237.1.1	A dictionary of peer event histories keyed by peer address.

2.237.1.1 NeighborHistoryPeerModel

events	*list of NeighborHistory-RecordModel* see 2.237.1.1.1	Peer event history records.

2.237.1.1.1 NeighborHistoryRecordModel

asn	*integer*	Peer remote AS number.
connectionType	*enum: static | dynamic | interface*	Type of peer connection.
event	*connectFailure*	Type of recorded event.
message	*string*	Event description.
time	*floating point number*	UTC timestamp of event.

2.238 show bgp neighbors history socket

vrfs	*table(string) = NeighborHistorySocketVrfModel* see 2.238.1	A dictionary of peer socket statistics histories keyed by VRF name.

2.238.1 NeighborHistorySocketVrfModel

peers	*table(IP address and interface name (for IPv6 link local peers only)) = NeighborHistorySocketPeerModel* see 2.238.1.1	A dictionary of peer socket statistics histories keyed by peer address.

2.238.1.1 NeighborHistorySocketPeerModel

localAddr	*IP address*	Peer local address.
localPort	*integer*	Peer local port.
records	*list of NeighborHistorySocketRecordModel* see 2.238.1.1.1	Peer socket statistics history records.
remotePort	*integer*	Peer remote port.

2.238.1.1.1 NeighborHistorySocketRecordModel

congestionWindow	*integer*	TCP send congestion window.
delayedAckTimeout	*integer*	TCP socket delayed ACK timeout (microseconds).
maxSegmentSize	*integer*	TCP outgoing maximum segment size.
rcvWindow	*integer*	TCP advertised receive window.
rcvWindowScale	*integer*	TCP socket receive window scale.
retransTimeout	*integer*	TCP socket retransmission timeout (microseconds).
sendWindowScale	*integer*	TCP socket send window scale.
sndRtt	*integer*	TCP round-trip time (microseconds).
sndRttVariance	*integer*	TCP round-trip time variance (microseconds).
state	*enum: CLOSED | TIME-WAIT | CLOSE-WAIT | FIN-WAIT-1 | SYN-RECEIVED | ESTABLISHED | LISTEN | SYN-SENT | NOTUSED | CLOSING | FIN-WAIT-2 | LAST-ACK*	TCP socket state.
throughput	*floating point number*	TCP throughput (megabit per second).
time	*floating point number*	UTC timestamp of record.

2.239 show bgp optimal-route-reflection position

[position]	*list of BgpOrrPosition* see 2.239.1	BGP optimal route reflection positions configured.
[vrfName]	*string*	VRF name that BGP optimal route reflection positions belong to.

2.239.1 BgpOrrPosition

active	*boolean*	The position is active.
[inactiveReason]	*string*	Reason the position is not active.
name	*string*	Name of BGP optimal route reflection position.
[nlriTypes] **	*list of string*	List of supported NLRI types. **Since: 4.31.1
[numericId]	*integer*	Internal numeric identifier of position, assigned to active positions only.
[sources] **	*list of BgpOrrPositionSource* see 2.239.1.1	List of source nodes in IGP topologies. **Since: 4.27.1

2.239.1.1 BgpOrrPositionSource

instance	*integer*	Instance-id of the source.
[isisLevel]	*integer*	Isis level of the source.
protocol	*isis*	protocol advertising the source.
source	*string*	IGP source node id.

2.240 show bgp path-selection [...]

see 2.227

2.241 show bgp path-selection community { (AANN_FORMAT | COMMUNITY_ENUM | COMMUNITY_U32) } [...]

see 2.227

2.242 show bgp path-selection community-list COMM_LIST_NAME [...]

see 2.227

2.243 show bgp path-selection summary

revision 3

see 2.51

2.244 show bgp peer-group [...]

Could also be an instance of:
AllBgpPeerGroups 2.244.1.1.2

vrfs	*table(string) = BgpPeerGroups* see 2.244.1	Per-VRF BGP peer groups.

2.244.1 BgpPeerGroups

peerGroups	*table(string) = BgpPeerGroup* see 2.244.1.1	A dictionary of peer groups keyed by name.

2.244.1.1 BgpPeerGroup

[ancestorPeerGroups] **	*list of string*	Ancestor peer group list. **Since: 4.29.1
dynamicPeers	*table(string) = BgpPeerGroupEntry* see 2.244.1.1.1	A dictionary of dynamic peers keyed by IP address.
[interfacePeers] **	*table(string) = BgpPeerGroupEntry* see 2.244.1.1.1	A dictionary of interface peers keyed by IP address. **Since: 4.28.1
listenRangeSubnets	*table(string) = BgpPeerGroupListenRangeSubnet* see 2.244.1.1.2	A dictionary of listen-range subnets keyed by IP prefix.
staticPeers	*table(string) = BgpPeerGroupEntry* see 2.244.1.1.1	A dictionary of static peers keyed by IP address.

2.244.1.1.1 BgpPeerGroupEntry

negotiatedMpCapabilities	*NegotiatedMpCapabilities* see 2.244.1.1.1.1	Negotiated MP capabilities.
peerState	*enum: NotNegotiated | OpenConfirm | Active | Established | Connect | OpenSent | Idle*	Current peer state. Idle - Ignoring everything Connect - Trying to connect Active - Waiting for a connection OpenSent - Open packet has been sent OpenConfirm - Waiting for a keepalive or notify Established - Connection has been established.
vrf	*string*	VRF name.

2.244.1.1.1.1 NegotiatedMpCapabilities

dps **	*boolean*	Has Dynamic Path Selection capability. **Since: 4.24.1
ipv4FlowSpec	*boolean*	Has IPv4 flow specification capability.
[ipv4FlowSpecVpn] **	*boolean*	Has VPN-IPv4 flow specification capability. **Since: 4.30.0
ipv4MplsLabels	*boolean*	Has IPv4 labeled-unicast capability.

ipv4MplsVpn	*boolean*	Has VPN-IPv4 capability.
ipv4Multicast	*boolean*	Has IPv4 multicast capability.
[ipv4Mvpn] **	*boolean*	Has IPv4 MVPN capability. **Since: 4.28.1
ipv4SrTe	*boolean*	Has IPv4 SR-TE capability.
ipv4Unicast	*boolean*	Has IPv4 unicast capability.
ipv6FlowSpec	*boolean*	Has IPv6 flow specification capability.
[ipv6FlowSpecVpn] **	*boolean*	Has VPN-IPv6 flow specification capability. **Since: 4.30.0
ipv6MplsLabels	*boolean*	Has IPv6 labeled-unicast capability.
ipv6MplsVpn	*boolean*	Has VPN-IPv6 capability.
ipv6Multicast	*boolean*	Has IPv6 multicast capability.
ipv6SrTe	*boolean*	Has IPv6 SR-TE capability.
ipv6Unicast	*boolean*	Has IPv6 unicast capability.
l2VpnEvpn	*boolean*	Has L2VPN EVPN capability.
[l2VpnVpls] **	*boolean*	Has L2VPN VPLS capability. **Since: 4.28.1
linkState **	*boolean*	Has BGP Link State capability. **Since: 4.23.2
rtMembership **	*boolean*	Has RT Membership capability. **Since: 4.25.0

2.244.1.1.2 BgpPeerGroupListenRangeSubnet

asNumber	*string*	AS number.
peerFilter	*string*	Peer filter.
vrf	*string*	VRF name.
[emptyPeerGroups]	*list of string*	List of peer group names with no active members.
vrfs	*table(string) = BgpPeerGroups* see 2.244.1	Per-VRF BGP peer groups.

2.245 show bgp rcf [...]

see 2.40

2.246 show bgp rcf detail [...]

see 2.41

2.247 show bgp route-flap-damping (AFI unicast) [...]

vrfs	*table(string) = BgpRfdVrfModel* see 2.247.1	Per VRF BGP route rfd information.

2.247.1 BgpRfdVrfModel

rfdRouteEntries	*table(string) = BgpRfdRouteEntry* see 2.247.1.1	Route flap damping route entries keyed by prefix.
vrf	*string*	VRF name.

2.247.1.1 BgpRfdRouteEntry

address	*IP address*	Route address.
bgpRfdRoutePaths	*list of BgpRfdRoutePath* see 2.247.1.1.1	List of Bgp route paths.
maskLength	*integer*	Route mask length.
[totalPaths]	*integer*	Total number of paths for this route.

2.247.1.1.1 BgpRfdRoutePath

[asPathEntry]	*BgpRouteASPathEntry* see 2.20.1.1.2.1	AS path information.
dampingState	*enum: stateSuppressed | stateIgnored | stateTracked*	Route flap damping state.
[discardAt]	*floating point number*	Time until which path will be tracked.
flaps	*integer*	Number of path flaps.
nlri	*NlriModel* see 2.158.1.1	NLRI of the path.
[peerEntry]	*BgpRoutePeerEntry* see 2.20.1.1.2.43	Peer information for the route.
penalty	*integer*	Route flap damping penalty.
[reuseAt]	*floating point number*	Time at which suppressed path will be reused.
rfdPolicyName	*string*	Route flap damping policy name.
[suppressedAt]	*floating point number*	Time at which path was suppressed.
[withdrawn]	*boolean*	Path is withdrawn.

2.248 show bgp route-flap-damping policy [...]

policies	*table(string) = BgpRfdPolicy* see 2.248.1	Dictionary of route flap damping policies keyed by policy name.

2.248.1 BgpRfdPolicy

attributeChangePenalty	*integer*	Penalty for path attribute change.
maximumPenaltyThreshold	*integer*	Maximum value of penalty imposed on a path.
maximumSuppressionTime	*integer*	Maximum time a path is suppressed after it is stable in seconds.
minimumSuppressionTime	*integer*	Minimum time a path is suppressed after it is stable in seconds.
penaltyDecayHalfLife	*integer*	Penalty decay half life in seconds.
readvertisementAfter-WithdrawalPenalty	*integer*	Penalty for path readvertisement after it is withdrawn.
reusePenaltyThreshold	*integer*	Value of penalty below which suppressed path would be reused.
[suppressionIgnorePrefix-ListV4Unicast]	*string*	Prefix list of IPv4 unicast prefixes ignored from suppression.
[suppressionIgnorePrefix-ListV6Unicast]	*string*	Prefix list of IPv6 unicast prefixes ignored from suppression.
suppressionPenaltyThreshold	*integer*	Value of penalty above which path would be suppressed.
withdrawalPenalty	*integer*	Penalty for path withdrawal.

2.249 show bgp rpki roa ipv4 | ipv6 [...]

roas	*list of Roa* see 2.249.1	Resource Public Key Infrastructure (RPKI) Route Origin Authorizations (ROAs).

2.249.1 Roa

asn	*integer*	Autonomous System Number.
caches **	*list of string*	Cache servers. **Since: 4.26.2
maxLength	*integer*	Max prefix length.
prefix	*IP address prefix*	Prefix.

2.250 show bgp rpki roa summary

caches	*table(string) = CacheRoaSummaryModel* see 2.250.1	A mapping of cache names to the count of ROAs.
tables **	*table(string) = TableRoaSummaryModel* see 2.250.2	A mapping of ROA table names to the count of ROAs. **Since: 4.27.1
total	*CacheRoaSummaryModel* see 2.250.1	Total number of ROAs in the local database.

2.250.1 CacheRoaSummaryModel

ipv4RoaCount	*integer*	Count of IPv4 ROAs.
ipv6RoaCount	*integer*	Count of IPv6 ROAs.

2.250.2 TableRoaSummaryModel

ipv4RoaCount	*integer*	Count of IPv4 ROAs.
ipv6RoaCount	*integer*	Count of IPv6 ROAs.

2.251 show bgp rpki roa table summary

roaTables	*table(string) = RoaTableSummaryModel* see 2.251.1	A mapping of RPKI ROA table names to caches and status.

2.251.1 RoaTableSummaryModel

caches	*list of string*	Caches within the respective ROA table.
status	*enum: inactive | active*	State of the respective ROA table.

2.252 show bgp rt-membership [...]

revision 2

see 2.228

2.253 show bgp rt-membership floodlist [...]

vrfs	*table(string) = ShowRtMembership-FloodlistVrfModel* see 2.253.1	RT membership floodlist information, keyed by VRF name.

2.253.1 ShowRtMembershipFloodlistVrfModel

routeTargets	*table(route target) = ShowRtMembership-FloodlistRouteTargetModel* see 2.253.1.1	RT membership VRF floodlist information, keyed by route target.

2.253.1.1 ShowRtMembershipFloodlistRouteTargetModel

peers	*list of IP address and interface name (for IPv6 link local peers only)*	RT membership VRF and route target peer floodlist.

2.254 show bgp rt-membership origin-as (none | AS_PLAIN_NUM | AS_DOT_NUM) [...]

revision 2

see 2.228

2.255 show bgp rt-membership route-target ROUTE_TARGET [...]

revision 2

see 2.228

2.256 show bgp rt-membership summary

revision 3

see 2.51

2.257 show bgp scheduler [...]

see 2.92

2.258 show bgp segment-routing prefix-segments

`[prefixSegments]`	*table(IPv4 or IPv6 address prefix) = PrefixSegment* see 2.258.1	Mapping of IPv4 or IPv6 prefixes to corresponding route segments.

2.258.1 PrefixSegment

`localLabel`	*integer*	The generated local label of the route.
`sid`	*integer*	The segment ID of the route.

2.259 show bgp session tracker [...]

`[trackers]`	*table(string) = BgpSessionTrackerEntry* see 2.259.1	Dictionary of session trackers keyed by tracker name.

2.259.1 BgpSessionTrackerEntry

`establishedSessions`	*integer*	Established BGP sessions this tracker tracks.
`interfaces`	*list of Interface name*	Interfaces.

peers	*list of IP address*	Peer addresses.
recoveryDelay	*integer*	Delay for session recovery in seconds.
remainingRecoveryDelay	*integer*	Remaining delay for session recovery in seconds.
state	*enum: down | up | recovery | init*	Tracker state.
stateUpCondition **	*enum: anyPeerEstablished | allPeersEstablished*	Condition for state to be up. **Since: 4.33.2
totalSessions	*integer*	Total BGP sessions this tracker tracks.

2.260 show bgp sr-te [...]

revision 3

see 2.20

2.261 show bgp sr-te community { (AANN_FORMAT | COMMUNITY_ENUM | COMMUNITY_U32) } [...]

revision 3

see 2.20

2.262 show bgp sr-te community-list COMM_LIST_NAME [...]

revision 3

see 2.20

2.263 show bgp sr-te endpoint ENDPOINT_VALUE color COLOR_VALUE distinguisher DISTINGUISHER_VALUE [...]

revision 3

see 2.20

2.264 show bgp sr-te endpoint ENDPOINT_VALUE path-selection color-vrf COLOR_VRF (avt AVT) router ROUTER_ID [...]

revision 3

see 2.20

2.265 show bgp sr-te summary [...]

revision 3

see 2.51

2.266 show bgp statistics [...]

[globalBgpStats] **	*BgpStatisticsGlobal* see 2.266.2	Global BGP statistics information. **Since: 4.25.2
vrfs	*table(string) = BgpStatistics* see 2.266.1	Per VRF BGP Statistics.

2.266.1 BgpStatistics

asn	*string*	Autonomous System Number.
numOfPeersByState	*PeerStateModel* see 2.266.1.1	Number of peers in each state.
routerId	*IPv4 address*	Bgp Router Identity.

2.266.1.1 PeerStateModel

[active]	*integer*	Number of peers in Active state.
[connect]	*integer*	Number of peers in connect state.
[established]	*integer*	Number of peers in Established state.
[idle]	*PeerIdleStateModel* see 2.266.1.1.1	Number of peers in idle state for different idle reasons.
[notNegotiated]	*integer*	Number of peers in NotNegotiated state.
[openConfirm]	*integer*	Number of peers in OpenConfirm state.
[openSent]	*integer*	Number of peers in OpenSent state.

2.266.1.1.1 PeerIdleStateModel

[admin]	*integer*	Number of peers in idle state because the peer is disabled.
[asuShutdown]	*integer*	Number of peers in idle state because ASU2 shutdown is in progress.
[damping] **	*integer*	Number of peers in idle state because of BFD flap damping. **Since: 4.25.1
[deleted]	*integer*	Number of peers in idle state because the peer is deleted and waiting for deferred cleanup.
[ebgpLinkLocalMultihop-Unsupported] **	*integer*	Number of EBGP ipv6 link local peers in idle state because multihop is configured. **Since: 4.22.0
[grpAdmin]	*integer*	Number of peers in idle state because the peer's group is disabled.
[ibgpLinkLocalUnsupported] **	*integer*	Number of peers in idle state because IBGP peering over IPv6 link-local address is not supported. **Since: 4.26.0
[maxAcceptedPath]	*integer*	Number of peers in idle state because the peer has exceeded its max accepted route limit.

[maxAdvertisedPath] **	*integer*	Number of peers in idle state because the peer has exceeded its max advertised route limit. **Since: 4.24.0
[maxPath]	*integer*	Number of peers in idle state because the peer has exceeded its max route limit.
[minHoldTime] **	*integer*	Number of peers in idle state because peer hold time received in open message is less than minimum hold time required. **Since: 4.29.0
[noActivate]	*integer*	Number of peers in idle state because the peer is not activated in any address-family mode.
[noIf]	*integer*	Number of peers in idle state because the peer's interface is down.
[noLocalNexthops]	*integer*	Number of peers in idle state because the peer is missing local addresses for activated AFI/SAFIs.
[noRemoteAs]	*integer*	Number of peers in idle state because remote-as for peer is missing.
[orrAndAddPathBackup] **	*integer*	Number of peers in idle state because they are configured with both ORR and add-path backup, they are not supported together. **Since: 4.27.2
[orrLinkLocalPeer] **	*integer*	Number of peers in idle state because they are link-local peers configured with ORR that is not supported. **Since: 4.26.2
[orrPositionCountExceeds-Maximum] **	*integer*	Number of peers in idle state because they are configured with an ORR position we could not assign a numeric ID to, as the total number of configured ORR positions exceeds the maximum number supported. **Since: 4.26.2
[orrPositionIncomplete] **	*integer*	Number of peers in idle state because they are configured with ORR positions that either does not exist, or does not have at least one IGP prefix configured. **Since: 4.26.2
[orrPositionPeerAddress-DynamicPeer] **	*integer*	Number of peers in idle state because they are dynamic peers configured with ORR peer-address position that is not supported. **Since: 4.26.2
[other]	*integer*	Number of peers in idle state because of some unknown reason.
[pendingNotification] **	*integer*	Number of peers in idle state because the peer is pending notification message to be sent. **Since: 4.21.0
[sendFailureHoldTime] **	*integer*	Number of peers in idle state because tx is stucked for a long time. **Since: 4.31.0

[unsupportedCaps]	*integer*	Number of peers in idle state because the peer has not negotiated required capabilities.
[unsupportedTcpAuthConfig] **	*integer*	Number of peers in idle state because the peer has not negotiated required TcpAuth config. **Since: 4.31.0

2.266.2 BgpStatisticsGlobal

policyAcceptedPaths	*integer*	Number of policy accepted paths in BGP.

2.267 show bgp summary [...]

vrfs	*table(string) = BgpSummaryAll* see 2.267.1	Per VRF BGP summary.

2.267.1 BgpSummaryAll

asn	*string*	Autonomous System Number.
peers	*table(string) = BgpSummaryAllPeerEntry* see 2.267.1.1	Dictionary of BGP peer entries indexed by the peer address.
routerId	*IPv4 address*	BGP Router Identity.
vrf	*string*	VRF Name.

2.267.1.1 BgpSummaryAllPeerEntry

[dps]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for Dynamic Path Selection.
[ipv4FlowSpec]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for IPv4 flow specification.
[ipv4FlowSpecVpn] **	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for VPN-IPv4 flow specification. **Since: 4.30.0
[ipv4MplsLabels]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for IPv4 labeled-unicast.
[ipv4MplsVpn]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for VPN-IPv4.
[ipv4Multicast]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for IPv4 multicast.
[ipv4Mvpn] **	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for IPv4 MVPN. **Since: 4.28.2
[ipv4SrTe]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for IPv4 SR-TE.
[ipv4Unicast]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for IPv4 unicast.
[ipv6FlowSpec]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for IPv6 flow specification.
[ipv6FlowSpecVpn] **	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for VPN-IPv6 flow specification. **Since: 4.30.0
[ipv6MplsLabels]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for IPv6 labeled-unicast.

[ipv6MplsVpn]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for VPN-IPv6.
[ipv6Multicast]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for IPv6 multicast.
[ipv6SrTe]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for IPv6 SR-TE.
[ipv6Unicast]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for IPv6 unicast.
[l2VpnEvpn]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for L2VPN EVPN.
[l2VpnVpls] **	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for L2VPN VPLS. **Since: 4.28.0
[linkState]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for BGP Link State.
peerAsn	*string*	Autonomous System Number.
peerState	*enum: NotNegotiated* | *OpenConfirm* | *Active* | *Established* | *Connect* | *OpenSent* | *Idle*	Current peer state. Idle - Ignoring everything Connect - Trying to connect Active - Waiting for a connection OpenSent - Open packet has been sent OpenConfirm - Waiting for a keepalive or notify Established - Connection has been established.
[rtMembership]	*BgpSummaryAllPeerAfiSafiEntry* see 2.267.1.1.1	Peer information for RT Membership.

2.267.1.1.1 BgpSummaryAllPeerAfiSafiEntry

afiSafiState	*enum: configured* | *advertised* | *negotiated* | *received*	current afiSafi state.
nlrisAccepted	*integer*	Number of nlris accepted from the peer.
nlrisAdvertised **	*integer*	Number of nlris advertised to the peer. **Since: 4.34.1
nlrisReceived	*integer*	Number of nlris receieved from the peer.

2.268 show bgp traffic-policy field-set mappings [...]

vrfs	*table(string) = ShowTrafficPolicyFieldSetCommunityMappingsModel* see 2.268.1	Per VRF BGP traffic-policy field-set mappings.

2.268.1 ShowTrafficPolicyFieldSetCommunityMappingsModel

vrfs	*table(string) = FieldSetCommunity-MappingsVrfModel* see 2.268.1.1	A dictionary of traffic-policy field-set mappings keyed by VRF name.

2.268.1.1 FieldSetCommunityMappingsVrfModel

fieldSetMapping	*boolean*	Dynamic mapping of IP prefixes to field sets is enabled.
[ipv4Bindings]	*table(string) = Traffic-PolicyFieldSetBindings* see 2.268.1.1.1	Dictionary of IPv4 prefix field set bindings indexed by the field set name.
[ipv6Bindings]	*table(string) = Traffic-PolicyFieldSetBindings* see 2.268.1.1.1	Dictionary of IPv6 prefix field set bindings indexed by the field set name.
vrf	*string*	VRF name.

2.268.1.1.1 TrafficPolicyFieldSetBindings

[communities]	*list of string*	Associated standard BGP communities.
[extCommunities] **	*list of string*	Associated extended BGP communities. **Since: 4.34.1
[largeCommunities] **	*list of string*	Associated large BGP communities. **Since: 4.34.1
[peerGroups] **	*list of string*	Peer groups included in field-set. **Since: 4.29.2
[peerType] **	*enum: ibgp | ebgp*	Type of peers included in field-set. **Since: 4.29.2

2.269 show bgp tunnel udp

entries	*table(numeric string) = BgpUdpTunnelTableEntry* see 2.269.1	BGP UDP tunnel entries keyed by tunnel index.

2.269.1 BgpUdpTunnelTableEntry

endpoint	*IP address*	Destination address for tunnel entry.
payloadType	*enum: mpls | ipv4 | ipv6 | ipvx*	Payload type for tunnel entry.
sourceAddr	*IP address*	Source address for tunnel entry.
tos	*integer*	TOS of tunnel entry.
vias	*list of Via* see 2.193.1.1	List of nexthops.

2.270 show bgp update-group [...]

revision 2

vrfs	*table(string) = BgpUpdateGroups* see 2.270.1	Per VRF BGP update group.

2.270.1 BgpUpdateGroups

updateGroups	*table(numeric string) = BgpUpdateGroup* see 2.270.1.1	Dictionary of Bgp update groups by update group index.

2.270.1.1 BgpUpdateGroup

advRoutes	*integer*	Number of advertised routes.
[apSendCap]	*boolean*	Additional path send capability.
[apSendV4UniCap]	*boolean*	IPv4 Unicast additional path send capability.
[apSendV6UniCap]	*boolean*	IPv6 Unicast additional path send capability.
[confedExternalPeer]	*boolean*	eBGP confederation peer.
[defaultMed]	*integer*	Default MED.
[defaultOriginate]	*enum: enabled | always*	Advertise a default route to the neighbor.
[exportLocalPref]	*integer*	Local preference to send.
[extendedNextHop]	*enum: enabled | disabled | enabledWithOriginate*	Extended next hop capability.
[localAs]	*integer*	Local as number.
membersInSync	*integer*	Number of in-sync members.
membersTotal	*integer*	Number of members.
[metricOut]	*integer*	Metric to send.
[missingPolicyAction]	*enum: deny | permit*	Missing policy action.
[mpBgpAfiSafiCap]	*enum: ipv4MplsLabels | ipv6MplsLabels | ipv4Mvpn | ipv6MplsVpn | l2VpnVpls | ipv4FlowSpecVpn | dps | ipv6FlowSpec | ipv4MplsVpn | ipv6FlowSpecVpn | ipv4SrTe | ipv6SrTe | ipv6Unicast | ipv4FlowSpec | l2VpnEvpn | ipv4Unicast | rtMembership | linkState | ipv4Multicast | ipv6Multicast*	MPBGP AFI SAFI capability.
[mpBgpV4LabelCap]	*boolean*	MPBGP capability IPv4 Label Unicast.
[mpBgpV4UniCap]	*boolean*	MPBGP capability IPv4 Unicast.
[mpBgpV4Vpn4Cap]	*boolean*	MPBGP capability IPv4 VPN4.
[mpBgpV6LabelCap]	*boolean*	MPBGP capability IPv6 Label Unicast.
[mpBgpV6UniCap]	*boolean*	MPBGP capability IPv6 Unicast.
[negotiated4byteAs]	*boolean*	Four-byte ASN negotiated.
[neighborAs]	*integer*	Neighbor AS number.

[nexthopSelf]	*boolean*	Export self as nexthop.
[nexthopUnchanged]	*boolean*	Preserve original next hop while advertising routes to eBGP peers.
[orrPositionId]	*integer*	ORR position ID.
[orrPositionName]	*string*	ORR position name.
[outDelay]	*integer*	Out delay time.
[outDelayApply]	*enum: newRoutesChanges-Withdrawals* | *newRoutes* | *newRoutesChanges*	Announcement types to which out delay is applied. newRoutes - Out delay is applied only to new routes newRoutesChanges - Out delay is applied to to new routes and changes newRoutesChangesWithdrawals - Out delay is applied to new routes, changes, and withdrawals.
[outdelayLbw]	*integer*	Out delay time for linkband width.
[peerTagOut]	*string*	Peer-tag name.
[peerTagOutAction]	*string*	Peer-tag action.
peerType	*enum: internal* | *external*	Peer type.
peers	*table(string) = BgpUpdateGroupPeerEntry* see 2.270.1.1.2	Dictionary of BGP Update Group entries indexed by peer address.
[policyGroupId]	*integer*	RibOut policy group ID.
[policyStats]	*BgpUpdateGroupPolicy-Stats* see 2.270.1.1.3	Policy application statistics (multi-agent mode).
[prefixList]	*string*	Prefix list (present if configured in ribd mode, only present if configured and defined in multi-agent mode).
[prefixListV4Multicast]	*string*	Prefix List for IPv4 Multicast (present if configured in ribd mode, only present if configured and defined in multi-agent mode).
[prefixListV4Uni]	*string*	Prefix List for IPv4 Unicast (present if configured in ribd mode, only present if configured and defined in multi-agent mode).
[prefixListV6Multicast]	*string*	Prefix List for IPv6 Multicast (present if configured in ribd mode, only present if configured and defined in multi-agent mode).
[prefixListV6Uni]	*string*	Prefix List for IPv6 Unicast (present if configured in ribd mode, only present if configured and defined in multi-agent mode).
[prependOwnDisabled]	*boolean*	Do not prepend own AS number.
queuedAdv	*integer*	Number of queued route advertisements.
[rcfOutDefOri]	*string*	Outbound RCF function of default originate.
[reflectedRoutesAttributes-State]	*enum: preserved* | *alwaysPreserved* | *notPreserved*	State of attributes of the reflected routes.
[removePrivateAs]	*boolean*	Remove private as numbers.
[removePrivateAsAlways]	*boolean*	Always remove private AS numbers.

[removePrivateAsReplace]	*boolean*	Replace private AS number with local AS number.
[replaceAs]	*integer*	Replace AS number.
[routeMapOut]	*string*	Outbound policy (present if configured in ribd mode, only present if configured and defined in multi-agent mode).
[routeMapOutDefOri]	*string*	Outbound policy of default originate (present if configured in ribd mode, only present if configured and defined in multi-agent mode).
[routeMapOutDefOriV4Uni]	*string*	Outbound policy of default originate for IPv4 Unicast (present if configured in ribd mode, only present if configured and defined in multi-agent mode).
[routeMapOutDefOriV6Uni]	*string*	Outbound policy of default originate for IPv6 Unicast (present if configured in ribd mode, only present if configured and defined in multi-agent mode).
[routeMapOutMaint]	*string*	Outbound policy for maintenance mode (present if configured in ribd mode, only present if configured and defined in multi-agent mode).
[routeMapOutV4Uni]	*string*	Outbound policy for IPv4 Unicast (present if configured in ribd mode, only present if configured and defined in multi-agent mode).
[routeMapOutV6Uni]	*string*	Outbound policy for IPv6 Unicast (present if configured in ribd mode, only present if configured and defined in multi-agent mode).
[routeMapOutVpn4]	*string*	Outbound policy for VPN4 (present if configured in ribd mode, only present if configured and defined in multi-agent mode).
[routeRefreshCap]	*boolean*	Route refresh capability.
[routerIdGroup] **	*BgpRouterIdGroup* see 2.270.1.1.1	Router ID Group. **Since: 4.35.2
[rrClient]	*boolean*	Route Reflector Client.
[rrClusterId]	*IPv4 address*	Cluster ID assigned to route reflector client.
[rtMembershipConstrain]	*boolean*	Constrain route distribution based on peer RT membership.
[sendCommunity]	*boolean*	Send community attribute.
[sendExtendedCommunity]	*boolean*	Send extended community attribute.
[sendLargeCommunity]	*boolean*	Send large community attribute.
[sendOriginAsValidity]	*boolean*	Send origin AS validation state.
[sixPe]	*boolean*	6PE activated for the neighbor.

2.270.1.1.1 BgpRouterIdGroup

remoteRouterId	*IPv4 address*	Remote router ID.

[totalBandwidth]	*integer*	Total bandwidth (bps) of peers in router ID group.

2.270.1.1.2 BgpUpdateGroupPeerEntry

[inSync]	*boolean*	Peer is in-sync.
[queuedAdv]	*integer*	Number of queued advertisements.

2.270.1.1.3 BgpUpdateGroupPolicyStats

extendedNextHopMismatch-Reject	*integer*	Paths rejected due to extended next hop mismatch.
nextHopSelfNoLocalLabel-Reject	*integer*	Paths rejected due to next hop self no local label.
peerTagOutReject	*integer*	Paths rejected due to outbound peer-tag.
policyReject	*integer*	Paths rejected by update group policy.
receivedLinkLocalNextHop-Reject	*integer*	Paths rejected due to received link-local next hop.
wellKnownCommunityReject	*integer*	Paths rejected due to NO_EXPORT / NO_ADVERTISE community.

2.271 show bgp vpls [...]

see 2.235

2.272 show bgp vpls auto-discovery [...]

instances	*table(string) = BgpVplsAdInstance* see 2.272.1	BGP VPLS auto discovered instances indexed by instance name.

2.272.1 BgpVplsAdInstance

groups	*table(string) = BgpVplsAdGroup* see 2.272.1.1	BGP VPLS auto discovered groups indexed by group name.

2.272.1.1 BgpVplsAdGroup

exportRts	*list of integer*	Route targets to export.
importRts	*list of integer*	Route targets to import.
l2VpnId	*integer*	L2 VPN identifier.
[localPeAddr]	*integer*	Local PE address.
rd	*string*	VPLS group route distinguisher.
remotePeers	*table(string) = BgpVplsAdGroupMember* see 2.272.1.1.1	Remote peers indexed by PE address.

2.272.1.1.1 BgpVplsAdGroupMember

nextHop	*IP address*	Remote PE next hop.

2.273 show bgp vpls signaling [...]

instances	*table(string) = BgpVplsVeInstance* see 2.273.1	BGP VPLS signaling instances indexed by instance name.

2.273.1 BgpVplsVeInstance

groups	*table(string) = BgpVplsVeGroup* see 2.273.1.1	BGP VPLS signaling groups indexed by group name.

2.273.1.1 BgpVplsVeGroup

exportRts	*list of integer*	Route targets to export.
importRts	*list of integer*	Route targets to import.
[rcfExports]	*string*	RCF function to apply on export.
[rcfImports]	*string*	RCF function to apply on import.
rd	*string*	VPLS group route distinguisher.
vplsVeIdLocal	*integer*	Local VPLS Edge identifier.
vplsVeIdsRemote	*table(numeric string) = BgpVplsVeGroupRemoteVeId* see 2.273.1.1.1	Remote VE-IDs advertised by the remote peers.

2.273.1.1.1 BgpVplsVeGroupRemoteVeId

remotePeers	*table(string) = BgpVplsVeGroupMember* see 2.273.1.1.1.1	Remote peers indexed by PE address.

2.273.1.1.1.1 BgpVplsVeGroupMember

[decapLabel]	*integer*	Decapsulation label.
[encapLabel]	*integer*	Encapsulation label.

[error]	*enum: encapTypeNotSupported* | *overlappingRemoteLabel-Blocks* | *multipleRemoteVeIds* | *invalidRemoteVeId* | *unknownPeStatus* | *validPeStatus* | *invalidRemoteLabelBlock* | *missingLayer2InfoExt-Comm* | *featureNotSupported* | *duplicatedRemoteVeIds* | *missingRemoteLabelBlock* | *missingLocalLabelBlock* | *tooManyLayer2InfoExt-Comms*	Remote peer negotiation error.
vplsVeId	*integer*	VPLS Edge identifier.

2.274 show bgp vpls summary [...]

revision 3

see 2.51

2.275 show bgp vpn-ipv4 PREFIX (rd RD_VAL) internal

revision 2

see 2.231

2.276 show bgp vpn-ipv4 [...]

revision 2

see 2.231

2.277 show bgp vpn-ipv6 PREFIX (rd RD_VAL) internal

revision 2

see 2.231

2.278 show bgp vpn-ipv6 [...]

revision 2

see 2.231

2.279 show bgp vrf selection policy field-set mappings

`vrfs`	*table(string) = ShowVrfSelectionPolicyFieldSetCommunityMappingsModel* see 2.279.1	BGP VRF selection policy field-set mappings.

2.279.1 ShowVrfSelectionPolicyFieldSetCommunityMappingsModel

`vrfs`	*table(string) = FieldSetCommunityMappingsVrfModel* see 2.268.1.1	A dictionary of VRF selection policy field-set mappings keyed by VRF name.

2.280 show boot stages log

see 2.121.1

2.281 show boot stages verification sso

`stages`	*list of Stage* see 2.281.1	List of stage information.

2.281.1 Stage

`agentsWithStageVerification`	*table(string) = string*	Agents with stage verification.
`agentsWithViolations`	*list of string*	Agents that detected violations.
`agentsWithoutStageVerification`	*list of string*	Agents without stage verification.
`stageName`	*string*	Stage name.

2.282 show boot stages verification ssu

see 2.281

2.283 show boot-config

`abootPassword`	*string*	Encrypted aboot password.
`aristaCert` **	*string*	Arista certificate. **Since: 4.22.0
`aristaCert2` **	*string*	Arista certificate #2. **Since: 4.29.0
`aristaCert3` **	*string*	Arista certificate #3. **Since: 4.29.0
`aristaCertEnabled` **	*boolean*	SWIs signed by Arista Networks are authorized to boot. **Since: 4.22.0
`certsLoaded` **	*boolean*	Certificates were successfully loaded. **Since: 4.22.0
`[consoleSpeed]`	*integer*	Baud rate of console.
`fileChecksum` **	*string*	Checksum of the underlying boot-config file. **Since: 4.28.1
`fileChecksumAlg` **	*string*	Algorithm used to hash the underlying boot-config file. **Since: 4.28.1
`firstInstruction-MeasuredbootEnabled` **	*boolean*	Measured boot is enabled with First Instruction Security. **Since: 4.32.1
`firstInstruction-MeasuredbootSupported` **	*boolean*	Measured boot is supported with First Instruction Security. **Since: 4.32.1
`firstInstructionSecurity` **	*enum: enabled* | *unsupported* | *disabled*	First instruction security status. **Since: 4.35.2
`[firstInstruction-Technology]` **	*enum: amdPlatformSecureBoot* | *intelBootGuard*	First instruction technology by CPU. **Since: 4.35.2
`firstInstruction-VerifiedbootEnabled` **	*boolean*	Verified boot is enabled with First Instruction Security. **Since: 4.32.1
`firstInstruction-VerifiedbootSupported` **	*boolean*	Verified boot is supported with First Instruction Security. **Since: 4.32.1
`measuredbootEnabled` **	*boolean*	Measuring boot components via TPM PCRs is enabled. **Since: 4.27.0
`measuredbootSupported` **	*boolean*	Measuring boot components via TPM PCRs is supported. **Since: 4.35.2
`memTestIterations`	*integer*	Iterations of Memtest to perform at boot time.
`pcrBanksConfigured` **	*list of PcrBank* see 2.283.1	PCR banks configured. **Since: 4.35.2
`pcrBanksEnabled` **	*list of PcrBank* see 2.283.1	PCR banks enabled in TPM. **Since: 4.35.2
`[personalityOnReboot]` **	*enum: cpu* | *bmc*	The personality on reboot. **Since: 4.22.1

`secureBootEnabled` **	*boolean*	Secure boot is enabled. **Since: 4.22.0
`secureBootSupported` **	*boolean*	Secure boot is supported. **Since: 4.22.0
`softwareImage`	*string*	Location of software image.
`spiFlashWriteProtected` **	*boolean*	SPI flash is physically protected against writes. **Since: 4.22.0
`spiUpdateEnabled` **	*boolean*	Updating the SPI flash from Aboot is supported and enabled. **Since: 4.26.0
`tpmPassword` **	*boolean*	Aboot password is stored in the TPM. **Since: 4.22.0
`upgradeCert` **	*string*	SPI upgrade certificate. **Since: 4.27.0
`[useMgmtPortAsDataPort]` **	*boolean*	Use management port as data port. **Since: 4.34.0
`userCert` **	*string*	User certficate. **Since: 4.22.0

2.283.1 PcrBank

`hashAlgorithm`	*enum: sha256 | unknown | sha384 | sha3_256 | sha1 | sha3_384*	Name of hash algorithm.

2.284 show boot-extensions

`extensions`	*list of string*	List of extensions that will be installed and run at startup.

2.285 show bridge ((mac address-table) | mac-address-table) aging time-out

`hostAgingTime`	*floating point number*	Host Aging Time.

2.286 show cbf nexthop-group override [...]

`overrides`	*list of CbfNhgOverride* see 2.286.1	CBF nexthop group FEC overrides.

2.286.1 CbfNhgOverride

`addressFamily`	*enum: IPv6 | IPv4*	Address family.
`[defaultFecId]`	*integer*	Default nexthop group FEC ID.
`defaultNhg`	*string*	Default nexthop group name.
`dscp`	*integer*	DSCP value.
`[ecmp]`	*boolean*	ECMP group.
`[inOctets]`	*integer*	Ingress octet count.

[inPackets]	*integer*	Ingress packet count.
[overrideFecId]	*integer*	Overriding nexthop group FEC ID.
overrideNhg	*string*	Override nexthop group name.
[status]	*enum: hwNotReady* | *hwRequestPending* | *outOfResource* | *fecNotFound* | *programmed* | *unknownStatus*	TCAM programming status for this FEC override.

2.287 show cdp neighbors

cdpInterfaces	*table(Interface name) = CdpInterface* see 2.287.1	CDP enabled interfaces.
[lastRxTime]	*floating point number*	The last time CDP Agent received packet.
nbrDeletes	*integer*	The total numer of removed neighbors.
nbrInserts	*integer*	The total numer of added neighbors.
rxEnabled **	*boolean*	True if CDP packets are parsed. **Since: 4.30.1
rxFrameErrorsTotal	*integer*	The total numer of frames received by the CDP Agent that were discarded because of invalid frame.
rxFramesTotal	*integer*	The total number of packets that CDP Agent received.
rxFramesValidTotal	*integer*	The total number of valid frames received by the CDP Agent.
rxProtocolErrorsTotal	*integer*	The total numer of frames received by the CDP Agent that were discarded because of errors in CDP protocol decoding.
rxTLVsDiscardedTotal	*integer*	The total numer of discarded TLVs received by the CDP Agent.
rxTLVsUnrecognizedTotal	*integer*	The total numer of unknown TLVs received by the CDP Agent.

2.287.1 CdpInterface

cdpNeighbors	*list of CdpNeighbor* see 2.287.1.1	CDP neighbors.

2.287.1.1 CdpNeighbor

localPort	*interface name*	Name of the interface.
[neighborDevice]	*string*	Name of the neighbor device.
[neighborPort]	*string*	Name of the neighbor port.
ttl	*integer*	The Time To Live value (in seconds) advertised by the neighbor.

2.288 show cfm alarm indication [...]

domains	*table(string) = MdAisModel* see 2.288.1	A mapping between MD name and MD AIS.

2.288.1 MdAisModel

associations	*table(string) = MaAisModel* see 2.288.1.1	A mapping between MA name and MA AIS.
level	*integer*	MD level.

2.288.1.1 MaAisModel

direction	*enum: down | up | unconfigured*	MEP direction.
localMeps	*table(numeric string) = LocalMepAisModel* see 2.288.1.1.1	Local MEPs, keyed by local MEP ID.

2.288.1.1.1 LocalMepAisModel

aisCondition	*AisDefectTimeChange-Model* see 2.288.1.1.1.1	Local MEP AIS defect condition and its last change timestamp.
aisDefects	*table(string) = AisDefect-TimeChangeModel* see 2.288.1.1.1.1	AIS defects keyed by their name.
[aisTxInterval]	*integer*	AIS transmission interval in seconds.
[clientDomainLevel]	*integer*	Client MD level for AIS transmission.
[clientDomainLevelError]	*enum: notConfigured | invalid*	Reason for client domain level configuration error.
intf	*interface name*	Local maintenance end point interface.
remoteAisRxEntries	*list of RemoteAisRxEntryModel* see 2.288.1.1.1.2	List of AIS information received from remote MEPs in order of last received.

2.288.1.1.1.1 AisDefectTimeChangeModel

detected	*boolean*	End point has an AIS defect.
lastClearedTime	*floating point number*	UTC time of last AIS state cleared.
lastDetectedTime	*floating point number*	UTC time of last AIS state detected.

2.288.1.1.1.2 RemoteAisRxEntryModel

count	*integer*	Number of AIS PDUs that were received.
lastReceivedTime	*floating point number*	UTC time of last received AIS PDU.
remoteMac	*MAC address*	MAC address of remote MEP that detected a fault.
txInterval	*integer*	AIS transmission interval in seconds.

2.289 show cfm continuity-check counters [...]

domains	*table(string) = MdCcCountersModel* see 2.289.1	Maintenance domains, keyed by their name.

2.289.1 MdCcCountersModel

associations	*table(string) = MaCcCountersModel* see 2.289.1.1	MAs, keyed by their name.
level	*integer*	MD level.

2.289.1.1 MaCcCountersModel

localMeps	*table(numeric string) = LocalMepCcCountersModel* see 2.289.1.1.1	Local MEPs, keyed by their ID.

2.289.1.1.1 LocalMepCcCountersModel

ccmIntervalMismatch	*integer*	Number of CCM packets that were dropped due to a CCM interval mismatch.
ccmPacketParseError	*integer*	Number of CCM packets that were dropped due to an error in packet parsing.
directionMismatch	*integer*	Number of CCM packets that were dropped due to a direction mismatch.
[dot1qEncap] **	*Dot1qEncapModel* see 2.289.1.1.1.1	802.1Q tags of received packet. **Since: 4.35.2
duplicateRemoteMep	*integer*	Number of CCM packets that were dropped due to a duplicate remote MEP.
intfId	*string*	The interface ID.
invalidMaName	*integer*	Number of CCM packets that were dropped due to an invalid MA name.
invalidMdName	*integer*	Number of CCM packets that were dropped due to an invalid MD name.
invalidRemoteMepId	*integer*	Number of CCM packets that were dropped due to an invalid remote MEP ID.
rxCount	*integer*	Number of CCM packets received.
rxCounters **	*list of LocalMepCcCounterModel* see 2.289.1.1.1.2	List of counters for received packets. **Since: 4.35.2
rxDropCount	*integer*	Number of CCM packets that were dropped.
txCount	*integer*	Number of CCM packets sent.
txFailureCount	*integer*	Number of CCM packets that failed to send.
unconfiguredRemoteMep	*integer*	Number of CCM packets that were dropped due to an unconfigured remote MEP.
vlanId	*integer*	The VLAN ID.

2.289.1.1.1.1 Dot1qEncapModel

innerTag	*integer*	Inner 802.1Q VLAN tag.
outerTag	*integer*	Outer 802.1Q VLAN tag.

2.289.1.1.1.2 LocalMepCcCounterModel

Could also be an instance of:
LocalMepCcCountersModel 2.289.1.1.1

ccmIntervalMismatch	*integer*	Number of CCM packets that were dropped due to a CCM interval mismatch.
ccmPacketParseError	*integer*	Number of CCM packets that were dropped due to an error in packet parsing.
directionMismatch	*integer*	Number of CCM packets that were dropped due to a direction mismatch.
[dot1qEncap]	*Dot1qEncapModel* see 2.289.1.1.1.1	802.1Q tags of received packet.
duplicateRemoteMep	*integer*	Number of CCM packets that were dropped due to a duplicate remote MEP.
invalidMaName	*integer*	Number of CCM packets that were dropped due to an invalid MA name.
invalidMdName	*integer*	Number of CCM packets that were dropped due to an invalid MD name.
invalidRemoteMepId	*integer*	Number of CCM packets that were dropped due to an invalid remote MEP ID.
rxCount	*integer*	Number of CCM packets received.
rxDropCount	*integer*	Number of CCM packets that were dropped.
unconfiguredRemoteMep	*integer*	Number of CCM packets that were dropped due to an unconfigured remote MEP.

2.290 show cfm continuity-check counters detail [...]

interfaces	*table(Interface name) = IntfCcCountersModel* see 2.290.1	CC counters, keyed by interface.
[noIntfVlanMapping]	*CcCountersModel* see 2.289	CC counters without interface VLAN mapping.

2.290.1 IntfCcCountersModel

vlans	*table(numeric string) = IntfVlanCcCountersModel* see 2.290.1.1	CC counters, keyed by VLAN ID.

2.290.1.1 IntfVlanCcCountersModel

cfmHeaderParseError	*integer*	Number of CCM packets that were dropped due to an error in CFM header parsing.
domains	*table(string) = MdCcCountersModel* see 2.289.1	Maintenance domains, keyed by their name.
[dot1qEncap] **	*Dot1qEncapModel* see 2.289.1.1.1.1	802.1Q tags of received packet. **Since: 4.35.2
ethHeaderParseError	*integer*	Number of CCM packets that were dropped due to an error in ethernet header parsing.
firstTlvOffsetInvalid	*integer*	Number of CCM packets that were dropped due to an invalid first TLV offset.
mdLevelMismatch	*integer*	Number of CCM packets that were dropped due to an error in MD level mismatch.
noMepConfigured	*integer*	Number of CCM packets that were dropped due to no MEP being configured.
rxCount	*integer*	Number of CCM packets that were received.
rxCounters **	*list of IntfVlanCcCounterModel* see 2.290.1.1.1	List of counters for received packets. **Since: 4.35.2
rxDropCount	*integer*	Number of CCM packets that were dropped.
txCount	*integer*	Number of CCM packets that were sent.
txFailureCount	*integer*	Number of CCM packets that failed to send.

2.290.1.1.1 IntfVlanCcCounterModel

Could also be an instance of:
IntfVlanCcCountersModel 2.290.1.1

cfmHeaderParseError	*integer*	Number of CCM packets that were dropped due to an error in CFM header parsing.

[dot1qEncap]	*Dot1qEncapModel* see 2.289.1.1.1.1	802.1Q tags of received packet.
ethHeaderParseError	*integer*	Number of CCM packets that were dropped due to an error in ethernet header parsing.
firstTlvOffsetInvalid	*integer*	Number of CCM packets that were dropped due to an invalid first TLV offset.
mdLevelMismatch	*integer*	Number of CCM packets that were dropped due to an error in MD level mismatch.
noMepConfigured	*integer*	Number of CCM packets that were dropped due to no MEP being configured.
rxCount	*integer*	Number of CCM packets that were received.
rxDropCount	*integer*	Number of CCM packets that were dropped.

2.291 show cfm continuity-check end-point [...]

domains	*table(string) = MdCcModel* see 2.291.1	A mapping between MD name and MD continuity check.

2.291.1 MdCcModel

associations	*table(string) = MaCcModel* see 2.291.1.1	A mapping between MA name and MA continuity check.
level **	*integer*	MD level. **Since: 4.28.1

2.291.1.1 MaCcModel

[ccmTimeoutMultiplier] **	*floating point number*	Continuity check timeout multiplier. **Since: 4.34.1
ccmTxInterval	*floating point number*	Continuity check transmission interval in seconds.
direction	*enum: down | up | unconfigured*	MEP direction.
localMeps	*table(numeric string) = LocalMepCcModel* see 2.291.1.1.1	Local MEPs, keyed by local MEP ID.

2.291.1.1.1 LocalMepCcModel

[ccmDefects] **	*list of CcmDefectModel* see 2.291.1.1.1.1	CCM defects. **Since: 4.29.1
[ccmPduSent] **	*integer*	Number of CCM PDUs transmitted. **Since: 4.31.0
intf	*interface name*	Local maintenance end point interface.
[intfAction] **	*LocalMepIntfActionModel* see 2.291.1.1.1.2	Action taken on local MEP interface and its reason. **Since: 4.34.1
rdiTxCondition **	*RdiAndTimeChangeModel* see 2.291.1.1.1.6	Local MEP Tx RDI Bit status and its last change timestamp. **Since: 4.29.1
remoteMeps	*table(numeric string) = RemoteMepCcModel* see 2.291.1.1.1.7	Remote MEPs, keyed by remote MEP ID.

2.291.1.1.1.1 CcmDefectModel

cfmDefectPkts	*integer*	Number of defective CFM packets received on the interface.

defectId	*enum: defectCodeCcmTxMismatch | defectCodeMdlMismatch | defectCodeCcmNot-Received | defectCodeUnconfigured-Mep | defectCodeDuplicateMep | defectCodeRdiRecieved | defectCodeMaidMismatch | defectCodeNone*	Defect ID.
firstSeenTime	*floating point number*	UTC time of first time the defect was detected.
lastSeenTime	*floating point number*	UTC time of last time the defect was detected.
level	*integer*	MD level.
maName	*string*	Maintenance association.
maNameFormat **	*enum: maNameFormat-Rfc2685VpnId | maNameFormatShortInt | maNameFormatCharString | maNameFormatPrimaryVid | maNameFormatReserved*	MA name format. **Since: 4.33.1
mdName **	*string*	Maintenance domain. **Since: 4.33.1
mdNameFormat **	*enum: mdNameFormatMac-AddrPlusShortInt | mdNameFormatReserved | mdNameFormatDnsName | mdNameFormatNoName | mdNameFormatCharString*	MD name format. **Since: 4.33.1
remoteMepId	*integer*	Remote MEP ID.

2.291.1.1.1.2 LocalMepIntfActionModel

[actionRouting]	*LocalMepIntfAction-RoutingModel* see 2.291.1.1.1.3	disable routing action for local MEP interface.
[actionTx]	*LocalMepIntfActionTx-Model* see 2.291.1.1.1.5	disable Tx action for local MEP interface.

2.291.1.1.1.3 LocalMepIntfActionRoutingModel

[actionReason]	*list of LocalMepIntfAction-ReasonModel* see 2.291.1.1.1.4	Reason for taking routing action on local MEP interface.

2.291.1.1.1.4 LocalMepIntfActionReasonModel

reason	*enum: RDI | LOC*	Reason for action on local MEP interface.

2.291.1.1.1.5 LocalMepIntfActionTxModel

[actionReason]	*list of LocalMepIntfActionReasonModel* see 2.291.1.1.1.4	Reason for taking transmit action on local MEP interface.

2.291.1.1.1.6 RdiAndTimeChangeModel

lastClearedTime	*floating point number*	UTC time of last RDI state cleared.
lastDetectedTime	*floating point number*	UTC time of last RDI state detected.
rdi	*boolean*	End point remote defect indication.

2.291.1.1.1.7 RemoteMepCcModel

[ccmPduReceived] **	*integer*	Number of CCM PDUs received. **Since: 4.31.0
locState	*LocAndTimeChangeModel* see 2.291.1.1.1.8	End point connectivity state and its last change timestamp.
[mismatchCcmTxInterval] **	*floating point number*	Mismatching Continuity check transmission interval from remote MEP. **Since: 4.29.2

2.291.1.1.1.8 LocAndTimeChangeModel

lastClearedTime	*floating point number*	UTC time of last LOC state cleared.
lastDetectedTime	*floating point number*	UTC time of last LOC state detected.
loc	*boolean*	End point connectivity state.

2.292 show cfm continuity-check end-point remote-defect [...]

domains	*table(string) = MdRdiModel* see 2.292.1	A mapping between MD name and MD RDI.

2.292.1 MdRdiModel

associations	*table(string) = MaRdiModel* see 2.292.1.1	A mapping between MA name and MA RDI.
level **	*integer*	MD level. **Since: 4.28.1

2.292.1.1 MaRdiModel

direction	*enum: down | up | unconfigured*	MEP direction.
localMeps	*table(numeric string) = LocalMepRdiModel* see 2.292.1.1.1	Local MEPs, keyed by local MEP ID.

2.292.1.1.1 LocalMepRdiModel

intf	*interface name*	Local maintenance end point interface.
[intfAction] **	*LocalMepIntfActionModel* see 2.291.1.1.1.2	Action taken on local MEP interface and its reason. **Since: 4.34.1
rdiCondition	*RdiAndTimeChangeModel* see 2.291.1.1.1.6	Local MEP remote defect condition and its last change timestamp.
rdiTxCondition **	*RdiAndTimeChangeModel* see 2.291.1.1.1.6	Local MEP Tx RDI bit status and its last change timestamp. **Since: 4.29.1
remoteMeps	*table(numeric string) = RemoteMepRdiModel* see 2.292.1.1.1.1	Remote MEPs, keyed by remote MEP ID.

2.292.1.1.1.1 RemoteMepRdiModel

rdiState	*RdiAndTimeChangeModel* see 2.291.1.1.1.6	End point remote defect state and its last change timestamp.

2.293 show cfm counters [...]

interfaces	*table(Interface name) = CfmIntfCounter* see 2.293.1	Maps CFM counters to the corresponding interfaces.

2.293.1 CfmIntfCounter

errorPkts	*integer*	Number of invalid CFM packets received on the interface.
inPkts	*integer*	Number of CFM packets received on the interface.
outPkts	*integer*	Number of CFM packets sent from the interface.

2.294 show cfm end-point [...]

domains	*table(string) = MdModel* see 2.294.1	A mapping between MD name and MD.

2.294.1 MdModel

associations	*table(string) = MaModel* see 2.294.1.1	A mapping between MA name and MA.
level **	*integer*	MD level. **Since: 4.28.1

2.294.1.1 MaModel

[ccmTimeoutMultiplier] **	*floating point number*	Continuity check timeout multiplier. **Since: 4.34.1
ccmTxInterval	*floating point number*	Continuity check transmission interval in seconds.
direction	*enum: down | up | unconfigured*	MEP direction.
localMeps	*table(numeric string) = LocalMepModel* see 2.294.1.1.1	Local MEPs, keyed by local MEP ID.

2.294.1.1.1 LocalMepModel

[aisStatus] **	*LocalMepDetailModel* see 2.294.1.1.1.1	Local maintenance end point detailed AIS status. **Since: 4.35.2
[ccStatus] **	*LocalMepDetailModel* see 2.294.1.1.1.1	Local maintenance end point detailed CC status. **Since: 4.35.2
intf	*interface name*	Local maintenance end point interface.
remoteMeps	*table(numeric string) = RemoteMepModel* see 2.294.1.1.1.3	Remote MEPs, keyed by remote MEP ID.
status	*enum: inactive | active*	Local maintenance end point status.
[vlanStatus] **	*LocalMepVlanModel* see 2.294.1.1.1.2	Local maintenance end point VLAN information. **Since: 4.30.1

2.294.1.1.1.1 LocalMepDetailModel

[rxProgrammed]	*boolean*	Programmed as receiver.
[rxReason]	*enum: programmingFailed | waiting*	Reason for receiver programming state.
[txProgrammed]	*boolean*	Programmed as transmitter.
[txReason]	*enum: programmingFailed | waiting*	Reason for transmitter programming state.

2.294.1.1.1.2 LocalMepVlanModel

[activeVlans]	*list of integer*	Active VLANs.
[inactiveVlans]	*list of integer*	Inactive VLANs.
[primaryVlan]	*integer*	Primary VLAN.

2.294.1.1.1.3 RemoteMepModel

[ccStatus] **	*RemoteMepDetailModel* see 2.294.1.1.1.4	Remote maintenance end point detailed CC status. **Since: 4.35.2
[dmStatus] **	*RemoteMepDetailModel* see 2.294.1.1.1.4	Remote maintenance end point detailed DM status. **Since: 4.35.2
[lmStatus] **	*RemoteMepDetailModel* see 2.294.1.1.1.4	Remote maintenance end point detailed LM status. **Since: 4.35.2
[reason]	*string*	Reason for remote MEP status.
[slmStatus] **	*RemoteMepDetailModel* see 2.294.1.1.1.4	Remote maintenance end point detailed SLM status. **Since: 4.35.2
status	*enum: inactive | active*	Remote maintenance end point status.

2.294.1.1.1.4 RemoteMepDetailModel

[activeSessions]	*integer*	Total number of active SLM sessions.
[reason]	*enum: programmingFailed | waiting*	Reason for remote maintenance end point status.
[status]	*enum: inactive | active*	Remote maintenance end point status.
[totalSessions]	*integer*	Total number of SLM sessions.

2.295 show cfm intermediate-point

intermediatePoint	*table(string) = boolean*	Maps maintenance domains to intermediate point.

2.296 show cfm measurement delay proactive [...]

domains	*table(string) = MdDmModel* see 2.296.1	A mapping between MD name and MD.

2.296.1 MdDmModel

associations	*table(string) = MaDmModel* see 2.296.1.1	A mapping between MA name and MA.
level	*integer*	MD level.

2.296.1.1 MaDmModel

direction	*enum: down | up | unconfigured*	MEP direction.
localMeps	*table(numeric string) = LocalMepDmModel* see 2.296.1.1.1	Local MEPs, keyed by local MEP ID.
operMode	*enum: on-demand | proactive*	Delay measurement type.
txInterval	*floating point number*	Delay measurement frame transmission interval in milliseconds.

2.296.1.1.1 LocalMepDmModel

intf	*interface name*	Local maintenance end point interface.
remoteMeps	*table(numeric string) = RemoteMepDmModel* see 2.296.1.1.1.1	Remote MEPs, keyed by remote MEP ID.

2.296.1.1.1.1 RemoteMepDmModel

[avgDelay]	*floating point number*	Average measured delay.
[avgJitter]	*floating point number*	Average measured jitter.
[bestDelay]	*floating point number*	Best measured delay.
[bestDelayTime]	*floating point number*	UTC time when best delay was observed.
[currentMiStats] **	*DmMiStatsModel* see 2.296.1.1.1.2	Current measurement interval statistics for delay measurement. **Since: 4.33.1
[delayHistory]	*list of DmStatsModel* see 2.296.1.1.1.3	Measured delay in the recent delay measurement frames.
enabled	*boolean*	Delay measurement is enabled.
[historicMiStats] **	*list of DmMiStatsModel* see 2.296.1.1.1.2	Historic measurement interval statistics for delay measurement. **Since: 4.33.1
miEnabled **	*boolean*	Measurement interval is configured. **Since: 4.33.1
[numSamples]	*integer*	Number of delay measurement frames.

[reason]	*enum: suspendedForLoc | failed | inProgress | notConfigured*	Reason for delay measurement failure.
[startTime]	*floating point number*	UTC start time of delay measurement.
[worstDelay]	*floating point number*	Worst measured delay.
[worstDelayTime]	*floating point number*	UTC time when worst delay was observed.

2.296.1.1.1.2 DmMiStatsModel

avgDelay	*floating point number*	Average measured delay in measurement interval.
avgVariation	*floating point number*	Average measured variation in measurement interval.
[endTime]	*floating point number*	UTC end time of measurement.
maxDelay	*floating point number*	Maximum measured delay in measurement interval.
maxVariation	*floating point number*	Maximum measured variation in measurement interval.
[measurementInterval]	*integer*	Measurement interval in minutes.
minDelay	*floating point number*	Minimum measured delay in measurement interval.
minVariation	*floating point number*	Minimum measured variation in measurement interval.
numSamples	*integer*	Number of delay measurement frames in measurement interval.
startTime	*floating point number*	UTC start time of measurement.
[suspect]	*enum: incomplete | none | loc*	Suspect status of measurement.

2.296.1.1.1.3 DmStatsModel

delay	*floating point number*	Measured delay in this delay measurement frame.
updateTime	*floating point number*	UTC time when this DM stat entry was updated.

2.297 show cfm measurement loss proactive [...]

domains	*table(string) = MdLmModel* see 2.297.1	A mapping between MD name and MD.

2.297.1 MdLmModel

associations	*table(string) = MaLmModel* see 2.297.1.1	A mapping between MA name and MA.
level	*integer*	MD level.

2.297.1.1 MaLmModel

direction	*enum: down | up | unconfigured*	MEP direction.
localMeps	*table(numeric string) = LocalMepLmModel* see 2.297.1.1.1	Local MEPs, keyed by local MEP ID.
operMode	*enum: on-demand | proactive*	Loss measurement type.
txInterval	*floating point number*	Loss measurement frame transmission interval in milliseconds.

2.297.1.1.1 LocalMepLmModel

intf	*interface name*	Local maintenance end point interface.
remoteMeps	*table(numeric string) = RemoteMepLmModel* see 2.297.1.1.1.1	Remote MEPs, keyed by remote MEP ID.

2.297.1.1.1.1 RemoteMepLmModel

[avgFarEndFrameLoss]	*integer*	Average far-end frame loss.
[avgNearEndFrameLoss]	*integer*	Average near-end frame loss.
[currentMiStats] **	*LmMiStatsModel* see 2.297.1.1.1.2	Current measurement interval statistics for loss measurement. **Since: 4.34.1
enabled	*boolean*	Loss measurement is enabled.
[historicMiStats] **	*list of LmMiStatsModel* see 2.297.1.1.1.2	Historic measurement interval statistics for loss measurement. **Since: 4.34.1
[lmHistory]	*list of LmStatsModel* see 2.297.1.1.1.3	Measurement stats from recent loss measurement frames.
miEnabled **	*boolean*	Measurement interval is configured. **Since: 4.34.1
[numSamples]	*integer*	Number of loss measurement frames.
[reason]	*enum: suspendedForLoc | failed | inProgress | notConfigured*	Reason for loss measurement failure.
[startTime]	*floating point number*	UTC start time of loss measurement.

2.297.1.1.1.2 LmMiStatsModel

avgFarEndFrameLoss-Percentage	*floating point number*	Average far-end frame loss percentage.
avgNearEndFrameLoss-Percentage	*floating point number*	Average near-end frame loss percentage.
[endTime]	*floating point number*	UTC end time of measurement.
maxFarEndFrameLoss-Percentage	*floating point number*	Maximum far-end frame loss percentage.
maxNearEndFrameLoss-Percentage	*floating point number*	Maximum near-end frame loss percentage.
[measurementInterval]	*integer*	Measurement interval in minutes.
minFarEndFrameLoss-Percentage	*floating point number*	Minimum far-end frame loss percentage.
minNearEndFrameLoss-Percentage	*floating point number*	Minimum near-end frame loss percentage.
numSamples	*integer*	Number of loss measurement frames taken in measurement interval.
startTime	*floating point number*	UTC start time of measurement.
[suspect]	*enum: incomplete | none | loc*	Suspect status of measurement.

2.297.1.1.1.3 LmStatsModel

farEndLoss	*integer*	Packets lost on remote MEP.
localRx	*integer*	Packets received on local MEP.
localTx	*integer*	Packets sent from local MEP.
nearEndLoss	*integer*	Packets lost on local MEP.
remoteRx	*integer*	Packets received on remote MEP.
remoteTx	*integer*	Packets sent from remote MEP.
updateTime	*floating point number*	UTC time when this LM stat entry was updated.

2.298 show cfm measurement loss synthetic proactive [...]

domains	*table(string) = MdSlmModel* see 2.298.1	A mapping between MD name and MD.

2.298.1 MdSlmModel

associations	*table(string) = MaSlmModel* see 2.298.1.1	A mapping between MA name and MA.
level	*integer*	MD level.

2.298.1.1 MaSlmModel

direction	*enum: down | up | unconfigured*	MEP direction.
localMeps	*list of LocalMepSlmModel* see 2.298.1.1.1	List of Local MEPs and their COS value.
operMode	*enum: on-demand | proactive*	Synthetic Loss measurement type.
txInterval	*floating point number*	Synthetic Loss measurement frame transmission interval in milliseconds.

2.298.1.1.1 LocalMepSlmModel

cos	*integer*	COS value used for Synthetic Loss measurement frames.
intf	*interface name*	Local MEP interface.
mepId	*integer*	Local MEP ID.
remoteMeps	*table(numeric string) = RemoteMepSlmModel* see 2.298.1.1.1.1	Remote MEPs, keyed by remote MEP ID.
testId **	*integer*	Test ID value used for Synthetic Loss measurement frames. **Since: 4.36.0

2.298.1.1.1.1 RemoteMepSlmModel

[avgFarEndFrameLoss]	*floating point number*	Average far-end synthetic frame loss.
[avgNearEndFrameLoss]	*floating point number*	Average near-end synthetic frame loss.
[currentMiStats] **	*SlmMiStatsModel* see 2.298.1.1.1.2	Current measurement interval statistics for synthetic loss measurement. **Since: 4.33.1
enabled	*boolean*	Synthetic loss measurement is enabled.
[historicMiStats] **	*list of SlmMiStatsModel* see 2.298.1.1.1.2	Historic measurement interval statistics for synthetic loss measurement. **Since: 4.33.1
[measurementPeriod]	*floating point number*	Synthetic loss measurement period in milliseconds.
miEnabled **	*boolean*	Measurement interval is configured. **Since: 4.33.1

[numMeasurements]	*integer*	Number of measurements taken.
[reason]	*enum: suspendedForLoc* | *failed* | *inProgress* | *notConfigured*	Reason for synthetic loss measurement failure.
[slmHistory]	*list of SlmStatsModel* see 2.298.1.1.1.3	Measurement stats from recent synthetic loss measurement frames.
[startTime]	*floating point number*	UTC start time of synthetic loss measurement.

2.298.1.1.1.2 SlmMiStatsModel

avgFarEndFrameLoss-Percentage	*floating point number*	Average far-end frame loss percentage.
avgNearEndFrameLoss-Percentage	*floating point number*	Average near-end frame loss percentage.
[endTime]	*floating point number*	UTC end time of measurement.
maxFarEndFrameLoss-Percentage	*floating point number*	Maximum far-end frame loss percentage.
maxNearEndFrameLoss-Percentage	*floating point number*	Maximum near-end frame loss percentage.
[measurementInterval]	*integer*	Measurement interval in minutes.
minFarEndFrameLoss-Percentage	*floating point number*	Minimum far-end frame loss percentage.
minNearEndFrameLoss-Percentage	*floating point number*	Minimum near-end frame loss percentage.
numMeasurements	*integer*	Number of measurements taken in measurement interval.
startTime	*floating point number*	UTC start time of measurement.
[suspect]	*enum: incomplete* | *none* | *loc*	Suspect status of measurement.

2.298.1.1.1.3 SlmStatsModel

localRx	*integer*	Packets received on local MEP.
localTx	*integer*	Packets sent from local MEP.
remoteRx	*integer*	Packets received on remote MEP.
updateTime	*floating point number*	UTC time of the measurement period.

2.299 show cfm summary

ccActive	*boolean*	Continuity check is active.
ccHwOffloadActive	*boolean*	CCM hardware offload is active.
[ccHwOffloadInactiveReason]	*unsupported*	Reason for inactive CCM hardware offload.
[ccInactiveReason]	*unsupported*	Reason for inactive continuity check.
[inactiveLocActions]	*list of CcSummaryLocActionModel* see 2.299.1	Actions not taken on loss of connectivity.
[inactiveRdiActions] **	*list of CcSummaryRdiActionModel* see 2.299.2	Actions not taken on receiving remote defect indication. **Since: 4.34.1
[locActions]	*list of CcSummaryLocActionModel* see 2.299.1	Actions taken on loss of connectivity.
maCount	*integer*	Number of MAs.
mdCount	*integer*	Number of MDs.
mepCount	*integer*	Number of MEPs.
profiles	*table(string) = CfmSummaryProfileModel* see 2.299.3	Mapping between profile name and its status.
[rdiActions] **	*list of CcSummaryRdiActionModel* see 2.299.2	Actions taken on receiving remote defect indication. **Since: 4.34.1

2.299.1 CcSummaryLocActionModel

action	*enum: logging | interfaceRoutingDisable | interfaceTransmitDisable*	Action on loss of connectivity.
[reason]	*unsupported*	Reason for inactive action on loss of continuity action.

2.299.2 CcSummaryRdiActionModel

action	*enum: logging | interfaceTransmitDisable*	Action on receiving remote defect indication.
[reason]	*unsupported*	Reason remote defect indication action is inactive.

2.299.3 CfmSummaryProfileModel

[activeDefectAlarms]	*list of CcSummaryDefectAlarmModel* see 2.299.3.1	Continuity check defects that will raise an alarm.
[ccmTxInterval]	*floating point number*	Operational CCM TX interval in seconds.
[inactiveDefectAlarms]	*list of CcSummaryDefectAlarmModel* see 2.299.3.1	Continuity check defects that will not raise an alarm.
maCount	*integer*	Number of MAs associated with this profile.

2.299.3.1 CcSummaryDefectAlarmModel

defectAlarm	*enum: ccmDefectAlarmXconCcm | ccmDefectAlarmMacStatus | ccmDefectAlarmRdiCcm | ccmDefectAlarmErrorCcm | ccmDefectAlarmRemote-Ccm*	CCM defect.
[reason]	*unsupported*	Reason for inactive CCM defect.

2.300 show class-map [...]

classMaps	*table(string) = ClassMapModel* see 2.300.1	List of all class maps.

2.300.1 ClassMapModel

classPrio	*integer*	Class priority.
[match]	*table(string) = Match* see 2.300.1.1	Matching access groups.
matchCondition	*enum: matchConditionAny | unspecified*	Match condition.

2.300.1.1 Match

[dscpValue] **	*integer*	DSCP equivalent value in digits. **Since: 4.20.0
[l2ParamsValue] **	*MatchL2Params* see 2.300.1.1.1	L2 Params values configured. **Since: 4.23.2
[matchDscpNameValid] **	*boolean*	Flag to identify if string value of DSCP is used or numeric value. **Since: 4.20.0
[matchEcnValue] **	*enum: dontCare | ect-ce | ect | non-ect | ce*	ECN value configured. **Since: 4.20.0
matchRule	*enum: matchMacAccessGroup | matchIpv6AccessGroup | matchDscpEcn | matchMplsTrafficClass | matchL2Params | matchIpAccessGroup*	Matching rule for the type.

2.300.1.1.1 MatchL2Params

[cosValue]	*string*	COS value configured.
[deiValue] **	*string*	DEI value configured. **Since: 4.29.0
[innerCosValue] **	*string*	Inner COS value configured. **Since: 4.26.2
[innerVlanMask]	*integer*	Inner VLAN mask used.
[innerVlanMaskValid]	*boolean*	Flag to identify if inner vlan range type is used or (innervlan id, mask) is used.
[innerVlanValue]	*string*	Inner VLAN match value configured.
[vlanMask]	*integer*	VLAN mask used.
[vlanMaskValid]	*boolean*	Flag to identify if vlan range type is used or (vlan id, mask).
[vlanValue]	*string*	VLAN match value configured.

2.301 show class-map type control-plane [...]

see 2.300

2.302 show class-map type pbr [...]

classMaps	*table(string) = ClassMapModel* see 2.302.1	List of all class maps.
mapType	*enum: mapTrafficPolicy | mapTapAgg | mapSamplePolicy | mapQos | mapServerLoadBalancer | mapFlowspec | mapPbr*	Map type.

2.302.1 ClassMapModel

[counterData]	*ClassMapCounter* see 2.302.1.1	Number of packets that matched this class-map.
[match]	*table(string) = ClassMatchModel* see 2.302.1.2	Matching rule for class map.
matchCondition	*enum: matchConditionAny | matchConditionAll*	Class map match condition.
name	*string*	Class map name.

2.302.1.1 ClassMapCounter

[byteCount] **	*integer*	Number of bytes matching the rule. **Since: 4.31.2
[checkpointByteCount] **	*integer*	Number of bytes matching the rule since last checkpoint. **Since: 4.31.2
[checkpointPacketCount]	*integer*	Number of packets matching the rule since last checkpoint.
[lastChangedTime]	*floating point number*	Last time (uptime) the counters changed.
[lastChangedTimeUtc] **	*floating point number*	UTC time the counters were last updated. **Since: 4.35.0
[packetCount]	*integer*	Number of packets matching the rule.

2.302.1.2 ClassMatchModel

[acl]	*table(numeric string) = ClassMatchAclModel* see 2.302.1.2.1	Matching acl rule for class map.
[ip6Rule]	*table(numeric string) = Ipv6Rule* see 2.302.1.2.3	Matching IPv6 rule config.
[ipRule]	*table(numeric string) = IpRule* see 2.302.1.2.2	Matching IP rule config.
[macRule]	*table(numeric string) = MacRule* see 2.302.1.2.4	Matching MAC rule config.
[mplsRule]	*MplsRule* see 2.302.1.2.5	Matching MPLS rule config.

option	*enum: matchMacAccessGroup | matchIpv6AccessGroup | matchMplsAccessGroup | matchIpAccessGroup*	class match protocol options.

2.302.1.2.1 ClassMatchAclModel

[ipAclList]	*IpAclList* see 2.62.1	IP Acl list.
[ipv6AclList]	*Ipv6AclList* see 2.62.2	IPv6 Acl list.
[macAclList]	*MacAclList* see 2.302.1.2.1.1	MAC Acl list.
name	*string*	acl name.

2.302.1.2.1.1 MacAclList

aclList	*list of _AclBase* see 2.62.1.1	List of ACLs.

2.302.1.2.2 IpRule

[action]	*enum: deny | permit*	Action to take when the filter matches.
convertSymbols **	*boolean*	Auto-conversion from subnet and port numbers to words in show commands. **Since: 4.20.5
[copyToCpuDst] **	*enum: none | captive-portal*	Copy packet to CPU when this rule is matched. **Since: 4.25.1
[counterData]	*AclCounter* see 2.302.1.2.2.1	Rx counter data for packets matching this rule.
[counterDataTx] **	*AclCounter* see 2.302.1.2.2.1	Rx counter data for packets matching this rule. **Since: 4.33.2
[log]	*boolean*	Log when this rule is matched.
[mirrorSession] **	*string*	Target mirror session if this rule is matched. **Since: 4.23.0
[payload]	*PayloadSpec* see 2.59.1	DPI based payload filter specification.
[ruleFilter]	*IpFilter* see 2.302.1.2.2.2	The filter criteria to match this rule. Unset for remarks. When an optional filter attribute is not present in the output, this implies that there was no specification configured for that attribute, and any valid value is permitted.
sequenceNumber	*integer*	Numeric sequence number.
text	*string*	A textual representation of the rule, sans sequence number. If this rule is a remark, this field will contain the remark text.

2.302.1.2.2.1 AclCounter

[byteCount] **	*integer*	Number of bytes matching the rule. **Since: 4.29.1
[checkpointByteCount] **	*integer*	Number of bytes matching the rule since last checkpoint. **Since: 4.29.1
[checkpointConnCount] **	*integer*	Number of connections matching the rule since last checkpoint. **Since: 4.20.0
[checkpointPacketCount]	*integer*	Number of packets matching the rule since last checkpoint.
[connCount] **	*integer*	Number of connections matching the rule. **Since: 4.20.0
[lastChangedTime]	*floating point number*	Last time (uptime) the counters changed.
[lastChangedTimeUtc] **	*floating point number*	UTC time the counters were last updated. **Since: 4.35.0
[packetCount]	*integer*	Number of packets matching the rule.

2.302.1.2.2.2 IpFilter

destination	*IpAddrAndMask* see 2.302.1.2.2.9	Destination IPv4 address and mask.
[dscp]	*DscpSpec* see 2.302.1.2.2.3	DSCP filter specification.
[dstPort]	*PortSpec* see 2.302.1.2.2.12	Destination port number filter specification.
[ecn] **	*EcnSpec* see 2.302.1.2.2.4	ECN filter specification. **Since: 4.17.0
[established]	*boolean*	True if filtered by established TCP connection.
[etherType] **	*integer*	Ethernet header's Ethernet type. **Since: 4.27.2
fragments	*boolean*	Match only fragmented packets.
gre	*GreSpec* see 2.302.1.2.2.5	GRE filter speciication.
gtp	*GtpSpec* see 2.302.1.2.2.6	GTP filter specification.
[icmp]	*IcmpSpec* see 2.302.1.2.2.7	ICMP specification.
[innerDest] **	*IpAddrAndMask* see 2.302.1.2.2.9	Inner destination IPv4 address and mask. **Since: 4.20.0
[innerDest6] **	*Ip6AddrAndMask* see 2.302.1.2.2.8	Inner destination IPv6 address and mask length. **Since: 4.20.0
[innerProtocol] **	*integer*	IP inner protocol number. **Since: 4.22.0
[innerSource] **	*IpAddrAndMask* see 2.302.1.2.2.9	Inner source IPv4 address and mask. **Since: 4.20.0
[innerSource6] **	*Ip6AddrAndMask* see 2.302.1.2.2.8	Inner source IPv6 address and mask length. **Since: 4.20.0

ipLen **	*IpLenSpec* see 2.302.1.2.2.10	IP packet length specification. **Since: 4.17.0
nexthopGroup **	*string*	Nexthop-group name. **Since: 4.17.0
nvgre	*NvgreSpec* see 2.302.1.2.2.11	NVGRE filter speciication.
protoMask **	*integer*	IP protocol mask. **Since: 4.27.2
protocol	*integer*	IP protocol number.
source	*IpAddrAndMask* see 2.302.1.2.2.9	Source IPv4 address and mask.
[srcPort]	*PortSpec* see 2.302.1.2.2.12	Source port number filter specification.
standard	*boolean*	True if this is an ACL in standard form.
[tcpFlags]	*integer*	TCP flags.
tracked	*boolean*	Connection tracked.
[ttl]	*TtlSpec* see 2.302.1.2.2.13	TTL specification.
userL4	*UserL4Spec* see 2.302.1.2.2.14	DPI based first word payload filter for unknown L4.
[vlan]	*VlanSpec* see 2.302.1.2.2.15	VLAN specification.
vxlan	*VxlanSpec* see 2.302.1.2.2.16	VXLAN filter specification.

2.302.1.2.2.3 DscpSpec

mask **	*integer*	DSCP mask. **Since: 4.23.2
match	*boolean*	True if filtered by DSCP value or name.
[name]	*string*	DSCP filter name.
value	*integer*	DSCP filter value.

2.302.1.2.2.4 EcnSpec

match	*boolean*	True if filtered by ECN value or name.
name	*enum: dontCare | ect-ce | ect | non-ect | ce*	ECN filter value.

2.302.1.2.2.5 GreSpec

protoMask	*integer*	GRE protocol mask.
protocol	*integer*	GRE protocol.

2.302.1.2.2.6 GtpSpec

[protocol]	*enum: gtp-prime | gtp-c | gtp-u*	GTP protocol type.
teid	*integer*	Tunnel Endpoint Id.
teidMask	*integer*	TEID Mask.

[version]	*integer*	GTP version.

2.302.1.2.2.7 IcmpSpec

code	*integer*	ICMP code.
type	*integer*	ICMP type.

2.302.1.2.2.8 Ip6AddrAndMask

[fullMask] **	*IPv6 address*	Ipv6 address full mask, used only when maskcannot be represented as a length. **Since: 4.20.5
ip	*IPv6 address*	Ipv6 address.
[mask]	*integer*	Ipv6 address mask len.

2.302.1.2.2.9 IpAddrAndMask

ip	*IPv4 address*	Ip address.
mask	*integer*	Ip address mask len.

2.302.1.2.2.10 IpLenSpec

ipLens	*list of integer*	IP packet lengths.
oper	*enum: neq | lt | gt | range | eq | any*	IP packet length range operator.

2.302.1.2.2.11 NvgreSpec

protoMask	*integer*	NVGRE protocol mask.
protocol	*integer*	NVGRE protocol.
tni	*integer*	Tenant Network Id.
tniMask	*integer*	TNI mask.

2.302.1.2.2.12 PortSpec

maxPorts	*integer*	Maximum number of ports.
oper	*enum: neq | lt | gt | range | eq | any*	Port number range operator.
ports	*list of integer*	Port numbers.

2.302.1.2.2.13 TtlSpec

oper	*enum: neq | lt | gt | range | eq | any*	TTL range operator.
value	*integer*	TTL value.

2.302.1.2.2.14 UserL4Spec

pattern	*integer*	Pattern to match into first word payload for IP packet.
patternMask	*integer*	Mask for pattern to match.

2.302.1.2.2.15 VlanSpec

id	*integer*	VLAN id.
innerId	*integer*	Inner VLAN id.
innerMask	*integer*	Inner VLAN mask.
mask	*integer*	VLAN mask.

2.302.1.2.2.16 VxlanSpec

vni	*integer*	Virtual Network Id.
vniMask	*integer*	VNI mask.
vxlanValid	*boolean*	True if valid VXLAN packet.

2.302.1.2.3 Ipv6Rule

[action]	*enum: deny | permit*	Action to take when the filter matches.
convertSymbols **	*boolean*	Auto-conversion from subnet and port numbers to words in show commands. **Since: 4.20.5
[copyToCpuDst] **	*enum: none | captive-portal*	Copy packet to CPU when this rule is matched. **Since: 4.25.1
[counterData]	*AclCounter* see 2.302.1.2.2.1	Rx counter data for packets matching this rule.
[counterDataTx] **	*AclCounter* see 2.302.1.2.2.1	Rx counter data for packets matching this rule. **Since: 4.33.2
[log]	*boolean*	Log when this rule is matched.
[mirrorSession] **	*string*	Target mirror session if this rule is matched. **Since: 4.23.0
[payload]	*PayloadSpec* see 2.59.1	DPI based payload filter specification.
[ruleFilter]	*Ipv6Filter* see 2.302.1.2.3.1	The filter criteria to match this rule. Unset for remarks. When an optional filter attribute is not present in the output, this implies that there was no specification configured for that attribute, and any valid value is permitted.
sequenceNumber	*integer*	Numeric sequence number.
text	*string*	A textual representation of the rule, sans sequence number. If this rule is a remark, this field will contain the remark text.

2.302.1.2.3.1 Ipv6Filter

destination	*Ip6AddrAndMask* see 2.302.1.2.2.8	Destination IPv6 address and mask.
[dscp]	*DscpSpec* see 2.302.1.2.2.3	DSCP filter specification.
[dstPort]	*PortSpec* see 2.302.1.2.2.12	Destination port number filter specification.
[ecn] **	*EcnSpec* see 2.302.1.2.2.4	ECN filter specification. **Since: 4.17.0
[established]	*boolean*	True if filtered by established TCP connection.
[etherType] **	*integer*	Ethernet header's Ethernet type. **Since: 4.27.2
[flowLabel] **	*FlowLabelSpec* see 2.302.1.2.3.2	IPv6 flow-label filter specification. **Since: 4.27.1
gre	*GreSpec* see 2.302.1.2.2.5	GRE filter speciication.
gtp	*GtpSpec* see 2.302.1.2.2.6	GTP filter specification.
[icmp]	*IcmpSpec* see 2.302.1.2.2.7	ICMP specification.
[innerDest] **	*IpAddrAndMask* see 2.302.1.2.2.9	Inner destination IPv4 address and mask. **Since: 4.20.0
[innerDest6] **	*Ip6AddrAndMask* see 2.302.1.2.2.8	Inner destination IPv6 address and mask length. **Since: 4.20.0
[innerProtocol] **	*integer*	IP inner protocol number. **Since: 4.22.0
[innerSource] **	*IpAddrAndMask* see 2.302.1.2.2.9	Inner source IPv4 address and mask. **Since: 4.20.0
[innerSource6] **	*Ip6AddrAndMask* see 2.302.1.2.2.8	Inner source IPv6 address and mask length. **Since: 4.20.0
ipLen **	*IpLenSpec* see 2.302.1.2.2.10	IP packet length specification. **Since: 4.17.0
nexthopGroup **	*string*	Nexthop-group name. **Since: 4.17.0
nvgre	*NvgreSpec* see 2.302.1.2.2.11	NVGRE filter speciication.
protoMask **	*integer*	IP protocol mask. **Since: 4.27.2
protocol	*integer*	IP protocol number.
source	*Ip6AddrAndMask* see 2.302.1.2.2.8	Source IPv6 address and mask.
[srcPort]	*PortSpec* see 2.302.1.2.2.12	Source port number filter specification.
standard	*boolean*	True if this is an ACL in standard form.
[tcpFlags]	*integer*	TCP flags.
tracked	*boolean*	Connection tracked.
[ttl]	*TtlSpec* see 2.302.1.2.2.13	TTL specification.

userL4	*UserL4Spec* see 2.302.1.2.2.14	DPI based first word payload filter for unknown L4.
[vlan]	*VlanSpec* see 2.302.1.2.2.15	VLAN specification.
vxlan	*VxlanSpec* see 2.302.1.2.2.16	VXLAN filter specification.

2.302.1.2.3.2 FlowLabelSpec

[mask] **	*integer*	IPv6 flow label mask. **Since: 4.27.2
oper	*enum: neq | lt | gt | range | eq | mask | any*	IPv6 flow-label range operator.
value	*integer*	IPv6 flow-label value.

2.302.1.2.4 MacRule

[action]	*enum: deny | permit*	Action to take when the filter matches.
convertSymbols **	*boolean*	Auto-conversion from subnet and port numbers to words in show commands. **Since: 4.20.5
[copyToCpuDst] **	*enum: none | captive-portal*	Copy packet to CPU when this rule is matched. **Since: 4.25.1
[counterData]	*AclCounter* see 2.302.1.2.2.1	Rx counter data for packets matching this rule.
[counterDataTx] **	*AclCounter* see 2.302.1.2.2.1	Rx counter data for packets matching this rule. **Since: 4.33.2
[log]	*boolean*	Log when this rule is matched.
[mirrorSession] **	*string*	Target mirror session if this rule is matched. **Since: 4.23.0
[payload]	*PayloadSpec* see 2.59.1	DPI based payload filter specification.
[ruleFilter]	*MacFilter* see 2.302.1.2.4.1	The filter criteria to match this rule. Unset for remarks. When an optional filter attribute is not present in the output, this implies that there was no specification configured for that attribute, and any valid value is permitted.
sequenceNumber	*integer*	Numeric sequence number.
text	*string*	A textual representation of the rule, sans sequence number. If this rule is a remark, this field will contain the remark text.

2.302.1.2.4.1 MacFilter

destinationAddr	*MAC address*	Destination address.
destinationMask	*MAC address*	Destination mask.

mpls	*MplsSpec* see 2.302.1.2.4.4	Two-label syntax MPLS filter specification.
[mplsFilter] **	*MplsFilter* see 2.302.1.2.4.2	MPLS filter specification. **Since: 4.20.0
protocol	*integer*	Ethernet protocol.
sourceAddr	*MAC address*	Source address.
sourceMask	*MAC address*	Source mask.
[vlan]	*VlanSpec* see 2.302.1.2.2.15	VLAN specification.

2.302.1.2.4.2 MplsFilter

[bos]	*integer*	MPLS BOS (Bottom Of Stack) bit of the largest specified label.
labels	*table(numeric string) = MplsLabelFilter* see 2.302.1.2.4.3	MPLS labels filter.

2.302.1.2.4.3 MplsLabelFilter

mask	*integer*	MPLS label mask.
value	*integer*	MPLS label value.

2.302.1.2.4.4 MplsSpec

innerLabel	*integer*	MPLS inner label id.
innerLabelMask	*integer*	MPLS inner label mask.
label	*integer*	MPLS label id.
labelMask	*integer*	MPLS label mask.

2.302.1.2.5 MplsRule

[counterData]	*ClassMapCounter* see 2.302.1.1	Number of packets that matched this class-map.

2.303 show class-map type tapagg [...]

see 2.302

2.304 show cli commands [({ hidden | functions | (truncate LENGTH) | verbatim })]

clis	*list of string*	CLI commands in the current mode.

2.305 show cli commands all-modes [({ hidden | functions | (truncate LENGTH) | verbatim })]

`allClis`	*table(string) = Clis* see 2.304	CLI commands in all modes, keyed by mode name.

2.306 show cli pid

`pid`	*integer*	PID of the current CLI.

2.307 show clock [...]

clockSource	*ClockSourceModel* see 2.307.1	Clock source.
localTime	*LocalTimeModel* see 2.307.2	Local time components.
timezone	*string*	Local timezone in use.
utcTime	*floating point number*	The current timestamp (UTC).

2.307.1 ClockSourceModel

local	*boolean*	Clock source is local.
[ntpServer]	*IP address*	NTP server address.
[ptpGrandmaster] **	*string*	PTP grandmaster clock identity. **Since: 4.26.2

2.307.2 LocalTimeModel

dayOfMonth	*integer*	Day of month (1 - 31).
dayOfWeek	*integer*	Day of week (0 - 6, Monday is 0).
dayOfYear	*integer*	Day of year (1 - 366).
daylightSavingsAdjust	*integer*	Daylight savings time (-1 - 1, -1 unknown).
hour	*integer*	Hour (0 - 23).
min	*integer*	Minute (0 - 59).
month	*integer*	Month (1 - 12).
sec	*integer*	Second ((0 - 61, 60 for leap secs, 61 for double leap secs).
year	*integer*	Year (for example, 2019).

2.308 show cluster voq attached-host adjacency remote | local [...]

leafDevices	*table(string) = ShowClusterVoqAttached-HostAdjacencyDevice* see 2.308.1	Leaf devices, keyed by their system name.

2.308.1 ShowClusterVoqAttachedHostAdjacencyDevice

deviceAdjacencies	*table(numeric string) = ShowClusterVoqTunnelInfo* see 2.308.1.1	Tunnel info keyed by adjacency ID.
memberId **	*integer*	Device member ID within a pod. **Since: 4.34.2
podId **	*integer*	Device pod ID. **Since: 4.34.2

2.308.1.1 ShowClusterVoqTunnelInfo

destinationId	*VoqTunnelDestinationId* see 2.308.1.1.1	Tunnel destination ID.
rewriteIndex	*integer*	Rewrite index.
tunnelId	*integer*	Tunnel ID.

2.308.1.1.1 VoqTunnelDestinationId

[lagId]	*integer*	LAG ID.
[lagPartition]	*enum: ? | A | B*	LAG partition.
[systemPortId]	*integer*	System port ID.
[voqId] **	*integer*	VOQ ID. **Since: 4.35.2

2.309 show cluster voq attached-host route local

vrfs	*table(string) = ShowClusterVoqAttachedHostRoute* see 2.309.1	Attached host route information keyed by VRF.

2.309.1 ShowClusterVoqAttachedHostRoute

adjacencyInfo	*table(string) = ShowClusterVoqAdjacencyInfo* see 2.309.1.1	Adjacency info keyed by prefix.

2.309.1.1 ShowClusterVoqAdjacencyInfo

adjacencyId	*integer*	Adjacency ID.

2.310 show cluster voq counters queue remote [...]

sources	*table(string) = IngressVoqCounters* see 2.310.1	Mapping between traffic source and VOQ counters.

2.310.1 IngressVoqCounters

interfaces	*table(Interface name) = IngressVoqTrafficClassCounters* see 2.310.1.1	Mapping between egress interface and traffic class counter data.

2.310.1.1 IngressVoqTrafficClassCounters

trafficClasses	*table(string) = Counters* see 2.310.1.1.1	Mapping between traffic class and counter data.

2.310.1.1.1 Counters

[droppedBitsRate] **	*floating point number*	Bits dropped per second. **Since: 4.22.0
[droppedBytes]	*integer*	Octets (bytes) dropped.
[droppedPackets]	*integer*	Packets dropped.
[droppedPacketsRate] **	*floating point number*	Packets dropped per second. **Since: 4.22.0
[enqueuedBitsRate] **	*floating point number*	Bits enqueued per second. **Since: 4.22.0
[enqueuedBytes]	*integer*	Octets (bytes) enqueued.
[enqueuedPackets]	*integer*	Packets enqueued.
[enqueuedPacketsRate] **	*floating point number*	Packets enqueued per second. **Since: 4.22.0

2.311 show cluster voq device [...]

[leafDevices]	*table(string) = ShowClusterVoqDeviceLeaf* see 2.311.1	Leaf information keyed by system name.
[spineDevices]	*table(string) = ShowClusterVoqDeviceSpine* see 2.311.2	Device name keyed by system name.
[spineStage2Devices] **	*table(string) = ShowClusterVoqDeviceSpineStage2* see 2.311.3	Device name keyed by system name. **Since: 4.34.1

2.311.1 ShowClusterVoqDeviceLeaf

[errorList]	*list of string*	Cluster VOQ errors.
[ip4Address]	*IPv4 address*	CPU interface IPv4 address.
[ip6Address]	*IPv6 address*	CPU interface IPv6 address.
memberId **	*integer*	Device member ID within a pod. **Since: 4.34.2
podId **	*integer*	Device pod ID. **Since: 4.34.2
systemId **	*integer*	Cluster-wide ID for the leaf device. **Since: 4.34.2
[systemPortIdRange]	*ShowClusterVoqSystemPortIdRange* see 2.311.1.1	System port ID range.

2.311.1.1 ShowClusterVoqSystemPortIdRange

end	*integer*	System port ID range end.
start	*integer*	System port ID range start.

2.311.2 ShowClusterVoqDeviceSpine

memberId **	*integer*	Device member ID within a pod. **Since: 4.34.2
podId **	*integer*	Device pod ID. **Since: 4.34.2
systemId **	*integer*	Cluster-wide ID for the spine device. **Since: 4.34.2

2.311.3 ShowClusterVoqDeviceSpineStage2

memberId **	*integer*	Cluster-wide ID for the stage 2 spine device. **Since: 4.34.2
systemId **	*integer*	Cluster-wide ID for the stage 2 spine device. **Since: 4.34.2

2.312 show cluster voq fabric audit [...]

Could also be an instance of:
FabricAuditDetail 2.312.1

auditId	*integer*	Fabric audit ID.
[currentIteration]	*integer*	Current iteration.
[error]	*enum: noDropsSeen* | *aborted* | *deviceTimeout* | *inconsistentPacketCount* | *deviceConnectivityChange*	Fabric audit error.
[fabricAuditEndTime]	*floating point number*	UTC timestamp of fabric audit end time.
[fabricAuditStartTime]	*floating point number*	UTC timestamp of fabric audit start time.
faultyDevices	*list of string*	Faulty devices analyzed by fabric audit.
[firstCrcErrTime]	*floating point number*	UTC timestamp of first CRC error time.
[iterations]	*list of FabricAuditIteration* see 2.312.1	Iterations of fabric audit.
state	*enum: done* | *running* | *initializing* | *analyzing*	State of fabric audit.

2.312.1 FabricAuditIteration

[dropsResolved]	*boolean*	Drops resolved during the iteration.
[endTime]	*floating point number*	UTC timestamp of iteration end time.
[excludedSpine]	*string*	Excluded spine in iteration.
iterationId	*integer*	Iteration ID.
[startTime]	*floating point number*	UTC timestamp of iteration start time.
state auditId	*enum: done* | *running* *integer*	State of fabric audit iteration. Fabric audit ID.
crcErrDevices	*list of string*	Devices that detected initial CRC errors.
[currentIteration]	*integer*	Current iteration.
droppedPathStats	*list of FabricAuditPathStats* see 2.312.3	Traffic paths with packet drops.
[error]	*enum: noDropsSeen* | *aborted* | *deviceTimeout* | *inconsistentPacketCount* | *deviceConnectivityChange*	Fabric audit error.
[fabricAuditEndTime]	*floating point number*	UTC timestamp of fabric audit end time.
[fabricAuditStartTime]	*floating point number*	UTC timestamp of fabric audit start time.
faultyDevices	*list of string*	Faulty devices analyzed by fabric audit.
[firstCrcErrTime]	*floating point number*	UTC timestamp of first CRC error time.
[iterations]	*list of FabricAuditIteration* see 2.312.1	Iterations of fabric audit.
noDropsSeenSpines	*list of string*	Spine devices that observed no packet drops when excluded.
receiverDropStats	*table(string) = FabricAuditDeviceStats* see 2.312.2	Receivers with packet drops.
senderDropStats	*table(string) = FabricAuditDeviceStats* see 2.312.2	Senders with packet drops.
state	*enum: done* | *running* | *initializing* | *analyzing*	State of fabric audit.

2.312.2 FabricAuditDeviceStats

impactedIterationCount	*integer*	Number of iterations with packet drops that involve this device.
impactedPathCount	*integer*	Number of dropped paths with this device.
totalIterationCount	*integer*	Total number of iterations with this device.
totalPathCount	*integer*	Total number of paths with this device.

2.312.3 FabricAuditPathStats

impactedIterationCount	*integer*	Number of iterations where this traffic path saw packet drops.
receiver	*string*	Receiver device.
sender	*string*	Sender device.
totalIterationCount	*integer*	Total number of iterations with this traffic path.

2.313 show cluster voq fabric audit detail [...]

see 2.312.1

2.314 show cluster voq fabric audit history

history	*list of FabricAuditStatus* see 2.312	History of fabric audit runs.

2.315 show cluster voq interfaces

leafDevices	*table(string) = ShowClusterVoqInterfacesDevice* see 2.315.1	Leaf devices, keyed by their system name.

2.315.1 ShowClusterVoqInterfacesDevice

interfaces	*table(Interface name) = ShowClusterVoqInterfacesInterface* see 2.315.1.1	Interface information, keyed by interface name.
memberId **	*integer*	Device member ID within a pod. **Since: 4.34.1
podId **	*integer*	Device pod ID. **Since: 4.34.1

2.315.1.1 ShowClusterVoqInterfacesInterface

systemPortId	*integer*	System port ID.
virtualOutputInterfaceName **	*interface name*	Cluster-wide representation of the interface. **Since: 4.34.1

2.316 show cluster voq qos interfaces ecn [...]

dsfIntfEcnParameters	*table(string) = IntfEcnModel* see 2.316.1	A mapping of DSF cluster interface to ECN parameters.

2.316.1 IntfEcnModel

txQueueEcnList	*list of TxQueueEcnModel* see 2.316.1.1	List of Transmit Queue ECN Settings.
txQueueNonEctList **	*list of TxQueueNonEctModel* see 2.316.1.2	List of Transmit Queue NON-ECT Settings. **Since: 4.28.0

2.316.1.1 TxQueueEcnModel

ecnMarkProbSupported **	*boolean*	ECN mark-probability supported. **Since: 4.21.3
ecnWeightSupported **	*boolean*	ECN Weight Supported. **Since: 4.21.3
txQueue	*string*	Name of Egress Queue.
[txQueueEcnDelayParameters] **	*EcnDelayParametersModel* see 2.316.1.1.1	Transmit Queue Delay based ECN Parameters. Not Applicable if Transmit Queue delay ECN is disabled. **Since: 4.17.0
txQueueEcnDelaySupported **	*boolean*	Trasmit Queue delay ECN supported. **Since: 4.17.0
[txQueueEcnParameters]	*EcnParametersModel* see 2.316.1.1.2	Transmit Queue ECN Parameters. Not Applicable if Transmit Queue buffer ECN is disabled.

2.316.1.1.1 EcnDelayParametersModel

[configuredMarkProb] **	*floating point number*	Configured Mark Probability value in percentage. **Since: 4.35.0
[configuredMinThreshold] **	*floating point number*	Configured Minimum Threshold value in microseconds. **Since: 4.35.0
[configuredThreshold] **	*floating point number*	Configured Threshold value in microseconds. **Since: 4.17.0
maxMarkProbability **	*floating point number*	Actual Ecn Mark Probability in percentage. **Since: 4.35.0
minThreshold **	*floating point number*	Actual Minimum Threshold value in microseconds. **Since: 4.35.0
[source] **	*enum: local | none | global*	Configuration source. **Since: 4.17.0
threshold	*floating point number*	Actual Threshold value in microseconds.
unit **	*string*	Threshold Unit. **Since: 4.35.0

2.316.1.1.2 EcnParametersModel

[maxDroprate] **	*integer*	Mark probability rate. **Since: 4.21.3
maxThreshold	*integer*	Maximum Threshold for ECN.
minThreshold	*integer*	Minimum Threshold for ECN.
[operationalMaxDroprate] **	*integer*	Operational Mark probability rate. **Since: 4.27.0
[segmentSizeInBytes]	*integer*	Size of segment unit in bytes.
unit	*enum: percent* | *mbytes* | *bytes* | *segments* | *kbytes* | *microseconds* | *milliseconds*	Threshold unit for ECN.
[weight] **	*integer*	Weight for averaging queue size. **Since: 4.21.3

2.316.1.2 TxQueueNonEctModel

nonEctWeightSupported	*boolean*	NON-ECT Weight Supported.
txQueue	*string*	Name of Egress Queue.
[txQueueNonEctParameters]	*EcnParametersModel* see 2.316.1.1.2	Transmit Queue NON-ECT Parameters. Not Applicable if Transmit Queue NON-ECT is disabled.

2.317 show cluster voq summary

[configuredVoqCount] **	*integer*	Configured number of VOQs per interface. **Since: 4.35.2
[cpuInterface]	*interface name*	Local CPU interface.
[deviceRole]	*enum: spine* | *spineStage2* | *leaf*	Local device role.
leafDeviceCount	*integer*	Number of leaf devices.
[memberId] **	*integer*	Local member ID. **Since: 4.34.2
[name] **	*string*	Local device name. **Since: 4.34.2
[podId] **	*integer*	Local pod ID. **Since: 4.34.2
[reason] **	*string*	Reason of inactive cluster status. **Since: 4.34.1
rebootRequired	*boolean*	Device has configuration changes that require a reboot to take effect.
spineDeviceCount	*integer*	Number of spine devices.
[spineStage2DeviceCount] **	*integer*	Number of stage 2 spine devices. **Since: 4.34.1
status	*enum: inactive* | *active*	Status of cluster VOQ.
[voqCount] **	*integer*	Number of VOQs per interface. **Since: 4.35.2

2.318 show command-tag [...]

commandTags	*table(string) = CommandTagStatus* see 2.318.1	A mapping of command tags with their current operational status.

2.318.1 CommandTagStatus

operState	*enum: removing | disassociating | disassociated | removed | enabled | disabled*	Command tag operational state.

2.319 show configuration checkpoints

checkpoints	*table(string) = ConfigSession.Cli.Checkpoint* see 2.319.1	A mapping between the checkpoint name and info.
maxCheckpoints	*integer*	Maximum number of checkpoints.

2.319.1 ConfigSession.Cli.Checkpoint

fileDate	*floating point number*	The utc timestamp of when the checkpoint file was created.
fileUser	*string*	The user who created the checkpoint file.
[name] **	*string*	A name given to this checkpoint. **Since: 4.32.2

2.320 show configuration consistency igmp snooping

tables	*table(string) = ConfigConsistencyTableModel* see 2.320.1	Config check result tables, keyed by table names.

2.320.1 ConfigConsistencyTableModel

headings	*list of string*	Table header fot this table.
items	*table(string) = ConfigConsistencyItemModel* see 2.320.1.1	Config consistency items, keyed by item names.
name	*string*	Name of table.
status	*enum: warn | ok | fail*	Table consistency level.

2.320.1.1 ConfigConsistencyItemModel

description	*string*	Description about the consistency item.
name	*string*	Name of item.
status	*enum: warn | ok | fail*	Item consistency level.

2.321 show configuration consistency nat [...]

see 2.320

2.322 show configuration consistency switch ({ aggregation })

see 2.320

2.323 show configuration fragments

fragmentConfigStatus **	*enum: completed | incomplete | notLoaded | inProgress*	State of process of loading fragment config files from disk. **Since: 4.33.0
fragments	*table(string) = Fragment* see 2.323.1	A mapping between the Fragment name and its state.

2.323.1 Fragment

[commitGroupId]	*integer*	Identity of commit group, if part of commit in progress.
[committedSession]	*string*	Name of committed session.
[description]	*string*	Description of the fragment.
[pendingSession]	*string*	Name of pending session.

2.324 show configuration fragments (all | (named FRAGMENT)) [...]

contents	*table(string) = FragmentContent or NULL* see 2.324.1	A mapping between the Fragment name and its config.
[versionName]	*enum: pending | committed*	Display only contents of committed sessions, or prefer 'pending' when both exist.

2.324.1 FragmentContent

[config]	*Mode* see 2.324.1.1	Dictionary of config commands in this fragment. The key is a config command. The config command might be: - a simple command and in this case the value is NULL. Example: 'cmds': { 'no ip routing' : NULL } - a command leading to a sub-mode and in this case the value is a new Mode consisting of potential new config commands. Example: 'cmds': { 'interface Ethernet2' : { 'cmds': { } }.
[pending]	*boolean*	True if the config for this fragment comes from the pending session, False if from the committed session.

2.324.1.1 Mode

cmds	*table(string) = _Mode or NULL* see 2.324.1.1.1	Dictionary of config commands in this mode. The key is a config command. The config command might be: - a simple command and in this case the value is NULL. Example: 'cmds': { 'no ip routing' : NULL } - a command leading to a sub-mode and in this case the value is a new Mode consisting of potential new config commands. Example: 'cmds': { 'interface Ethernet2' : { 'cmds': { } }.
[comments]	*list of string*	Mode comments.
[header]	*list of string*	Header messages. Present only on the Global config mode.

2.324.1.1.1 _Mode

Could also be an instance of:
Mode 2.324.1.1

2.325 show configuration fragments combined [...]

see 2.324.1.1

2.326 show configuration lock

[userInfo]	*Cli.Model.ConfigureLockModelUser* see 2.326.1	Information for the user who holds the Configuration Lock.

2.326.1 Cli.Model.ConfigureLockModelUser

[lockAcquireReason]	*string*	Reason why the lock was acquired.
lockAcquireTime	*floating point number*	UTC timestamp of when the lock was acquired.
[transactionName] **	*string*	Transaction name if a transaction lock. **Since: 4.28.1
[userLocation]	*string*	Source IP address or hostname for VTY sessions and absent for serial connections.
userTty	*string*	TTY for the user who acquired the lock.
username	*string*	The username of who acquired the lock.

2.327 show configuration lock history

history	*list of Cli.Model.ConfigureLockModelHistoryInfo* see 2.327.1	Information for the previous users who held the Configuration Lock.

2.327.1 Cli.Model.ConfigureLockModelHistoryInfo

lockAcquireTime	*floating point number*	UTC timestamp of when the lock was acquired.
[lockReleaseReason]	*string*	Reason why the lock was released.
[lockReleaseTime]	*floating point number*	UTC timestamp of when the lock was released.
[transactionName] **	*string*	Transaction name if a transaction lock. **Since: 4.28.1
[userLocation]	*string*	Source IP address or hostname for VTY sessions and absent for serial connections.
userTty	*string*	TTY for the user who held the lock.
username	*string*	The username of who held the lock.

2.328 show configuration sessions [...]

[commitTimerExpireTime]	*floating point number*	Timestamp of when pending commit timer expires.
[commitTimerSessionName] **	*string*	Config session name with pending commit timer. **Since: 4.32.0
maxOpenSessions	*integer*	Maximum number of open sessions.
maxSavedSessions	*integer*	Maximum number of saved sessions.
mergeOnCommit **	*boolean*	New sessions will perform a commit merge. **Since: 4.29.1
saveToStartupConfigOnCommit **	*boolean*	Successfully committed session will autosave to startup-config. **Since: 4.31.2
sessions	*table(string) = ConfigSession.Cli.Session* see 2.328.1	A mapping between the Session name and information.

2.328.1 ConfigSession.Cli.Session

[commitUser] **	*string*	The user that committed this session. **Since: 4.26.2
[completedTime] **	*floating point number*	Timestamp of when the session completed. **Since: 4.26.2
description	*string*	Description of the session.
instances	*table(numeric string) = ConfigSession.Cli.Instance* see 2.328.1.1	Instances where the session is open, indexed by process ID.
state	*enum: pending | closed | committed | aborted*	State of the session.

2.328.1.1 ConfigSession.Cli.Instance

currentTerminal	*boolean*	The session corresponds to the current terminal.
terminal	*string*	Terminal where the session is open.

user	*string*	User that opened the session.

2.329 show configuration sessions history

commits	*list of ConfigSession.Cli.Commit* see 2.329.1	In order list of commits.

2.329.1 ConfigSession.Cli.Commit

authorName	*string*	The user that committed this session.
commitHash	*string*	Commit Hash.
commitTime	*floating point number*	Timestamp of when the commit was completed.
[commitTimerExpireTime]	*floating point number*	Timestamp of when the commit timer expires.
[description]	*string*	User description of the session.
sessionName	*string*	Name of the session.

2.330 show configuration sessions memory

sessions	*table(string) = ConfigSession.Cli.SessionMemory* see 2.330.1	A mapping between the Session name and information.
totalMemory	*integer*	Memory in bytes used by all sessions.

2.330.1 ConfigSession.Cli.SessionMemory

memory	*integer*	Memory in bytes used by the session.

2.331 show container-manager backup

backup	*table(string) = ContainerMgrBackupFiles* see 2.331.1	Container manager backup keyed by persistent directory.

2.331.1 ContainerMgrBackupFiles

backupFiles	*list of string*	Backup files.

2.332 show container-manager containers [...]

revision 2

containerMgrContainers	*table(string) = ContainerMgrContainer* see 2.332.1	Container Manager containers keyed by containerName.

2.332.1 ContainerMgrContainer

[command]	*string*	Command for the container.
[containerId]	*string*	Container id.
[imageId]	*string*	Image id in sha256 format.
[imageName]	*string*	Image name with tag.
managed	*boolean*	If managed/configured through EOS.
[ports]	*list of ContainerMgrPort* see 2.332.1.1	List of all the ports for this container.
[profileName]	*string*	Profile name configured for container.
[startAttempts]	*integer*	Number of attempts made to start a failing container.
[startAttemptsAllowed]	*integer*	Maximum number of attempts thats will be made to start a failing container before giving up.
state	*enum: paused | shutdown | unknown | created | exited | restarting | removing | dead | failed | waiting | incomplete | running*	State of the container.
[timeOfCreation]	*integer*	Timestamp of container creation.
[timeOfStart]	*integer*	Timestamp of container start.

2.332.1.1 ContainerMgrPort

[ip]	*IP address*	IP address of the port.
portType	*enum: tcp | udp*	Port type.
privatePort	*integer*	Private port number.
[publicPort]	*integer*	Public port number.

2.333 show container-manager images [...]

containerMgrImages	*table(string) = ContainerMgrImage* see 2.333.1	Container Manager images keyed by imageName:tag.

2.333.1 ContainerMgrImage

imageId	*string*	Image id in sha256 format.
imageSize	*integer*	Size of the image.
timeOfCreation	*integer*	Time of image creation.

2.334 show container-manager info

backingFilesystem	*string*	backing Filesystem.
cgroupDriver	*string*	cgroup Driver.
containerMgrEngineId	*string*	Container-manager engine ID.
containerMgrRootDir	*string*	Container-manager root dir.
containerNum	*integer*	Total number of Containers.
cpuNum	*integer*	Total number of CPUs.
hostName	*string*	hostname.
imagesNum	*integer*	Total number of images.
loggingDriver	*string*	logging Driver.
memory	*integer*	Total Memory.
networkType	*list of string*	Network types.
pausedContainerNum	*integer*	Total number of paused Containers.
runningContainerNum	*integer*	Total number of running Containers.
stoppedContainerNum	*integer*	Total number of stopped Containers.
storageDriver	*string*	storage Driver.
volumeType	*list of string*	Volume types.

2.335 show container-manager log CONTAINER_NAME

containerMgrLogs	*string*	Log of a container.

2.336 show container-manager registry [...]

containerMgrRegistries	*table(string) = ContainerMgrRegistry* see 2.336.1	Container Manager registry keyed by registryName.

2.336.1 ContainerMgrRegistry

insecure	*boolean*	Insecure registry.
serverName	*string*	Registry server name.
status	*enum: Success | Failed*	Registry status.
username	*string*	Username for registry.

2.337 show cpu counters queue

classes	*table(string) = MakoCpuCountersQueue-CoppClassCounts* see 2.337.1	Mapping between Copp class and total counts.

2.337.1 MakoCpuCountersQueueCoppClassCounts

packetsDropped	*integer*	Number of packets dropped belonging to this Copp class.
packetsTotal **	*integer*	Number of packets received (both admitted and dropped) belonging to this Copp class. **Since: 4.29.2

2.338 show cpu counters queue [...]

egressQueues	*EgressCpuCounters* see 2.338.1	CPU queue counters on the egress chip.
[ingressVoqs]	*IngressCpuCounters* see 2.338.2	CPU VOQ counters on the ingress source.

2.338.1 EgressCpuCounters

sources	*table(string) = EgressCpuPortCounters* see 2.338.1.1	Mapping between sources and CPU queue counters.

2.338.1.1 EgressCpuPortCounters

cpuPorts	*table(string) = EgressCpuDestinationTypeCounters* see 2.338.1.1.1	Mapping between CPU ports and queues.

2.338.1.1.1 EgressCpuDestinationTypeCounters

mcastQueues	*EgressCpuQueueCounters* see 2.338.1.1.1.1	Multicast CPU traffic class counters.
[ucastQueues]	*EgressCpuQueueCounters* see 2.338.1.1.1.1	Unicast CPU traffic class counters.

2.338.1.1.1.1 EgressCpuQueueCounters

queues	*table(string) = Counters* see 2.310.1.1.1	Mapping between CPU queue and counter data.

2.338.2 IngressCpuCounters

sources	*table(string) = IngressCpuClassCounters* see 2.338.2.1	Mapping between source and CPU class.

2.338.2.1 IngressCpuClassCounters

cpuClasses	*table(string) = IngressCpuPortCounters* see 2.338.2.1.1	Mapping between CPU classes and ingress port.

2.338.2.1.1 IngressCpuPortCounters

ports	*table(string) = Counters* see 2.310.1.1.1	Mapping between ingress port and corresponding counter data.

2.339 show cvx [...]

revision 2

clusterMode	*boolean*	CVX server in cluster mode.
[clusterStatus]	*ClusterStatus* see 2.339.1	Cluster status.
connectionPreserved **	*boolean*	Client connection state preserving is enabled. **Since: 4.22.0
controllerUUID	*string*	Controller UUID.
enabled	*boolean*	Status of the CVX server.
heartbeatInterval	*floating point number*	Heartbeat interval in seconds.
heartbeatTimeout	*floating point number*	Heartbeat timeout in seconds.
[sslProfileStatus]	*SslProfileStatus* see 2.339.3	SSL profile status.

2.339.1 ClusterStatus

Could also be an instance of:
ClusterStatusDebug 2.339.2

clusterName	*string*	Name.
[currLeader]	*string*	Leader.
lastLeaderChangeTs	*floating point number*	Cluster's last leadership change timestamp.
peerStatus	*table(string) = PeerStatus* see 2.339.1.1	Cluster's peer status.
peerTimeout	*floating point number*	Heartbeat timeout in seconds for intra cluster communication.
role	*enum: Disconnected | Standby | Master*	Controller Role.

2.339.1.1 PeerStatus

Could also be an instance of:
PeerStatusDebug 2.339.1.2

peerIp	*IPv4 address*	Peer IP address.
peerName	*string*	Peer name.
[peerSystemId]	*string*	Peer Id.
[registrationErrorStatus]	*string*	Peer registration error description.
registrationState	*string*	Peer registration state.
[serviceVersionStatus]	*string*	Peer service version compatibility.

2.339.1.2 PeerStatusDebug

peerIp	*IPv4 address*	Peer IP address.
peerName	*string*	Peer name.
[peerSystemId]	*string*	Peer Id.
[registrationErrorStatus]	*string*	Peer registration error description.
registrationState	*string*	Peer registration state.
[serviceVersionStatus]	*string*	Peer service version compatibility.

sshKeyCopyStatus	*string*	Ssh key copy status.

2.339.2 ClusterStatusDebug

clusterName	*string*	Name.
[currLeader]	*string*	Leader.
currState	*string*	Election State.
currTerm	*string*	Cluster's current term.
lastLeaderChangeTerm	*string*	Cluster's last leadership change term.
lastLeaderChangeTs	*floating point number*	Cluster's last leadership change timestamp.
peerStatus	*table(string) = PeerStatus* see 2.339.1.1	Cluster's peer status.
peerTimeout	*floating point number*	Heartbeat timeout in seconds for intra cluster communication.
role	*enum: Disconnected | Standby | Master*	Controller Role.

2.339.3 SslProfileStatus

[disableReason]	*enum: profileNotExist | noError | certNotConfigured | profileInvalid | trustedCertNotConfigured | dhparamsNotReady*	Reason for disabled SSL profile.
enabled	*boolean*	Whether SSL profile is enabled.
sslProfileName	*string*	SSL profile name.

2.340 show cvx connections [...]

revision 2

brief **	*boolean*	Show brief status only. **Since: 4.22.0
connections	*list of CvxConnection* see 2.340.1	Cvx connections.

2.340.1 CvxConnection

[connectionTime] **	*floating point number*	Connection establishment UTC timestamp. **Since: 4.18.0
heartbeatStatus	*HeartbeatStatus* see 2.340.1.1	Heartbeat status of the switch.
hostname	*string*	Switch hostname.
[ibConnectionSecured]	*boolean*	Whether in-band connection is SSL secured.
oobConnectionActive **	*boolean*	Connection state. **Since: 4.22.0
[oobConnectionSecured]	*boolean*	Whether out-of-band connection is SSL secured.

oobState **	*enum: negotiating | disconnecting | established | connecting*	Out-of-band state. **Since: 4.15.4
switchId	*MAC address*	Switch Id.

2.340.1.1 HeartbeatStatus

lastHeartbeatReceived	*floating point number*	Last heartbeat.
lastHeartbeatSent	*floating point number*	Last heartbeat sent.

2.341 show cvx connections client (SYSTEMID | HOSTNAME)

revision 2

see 2.340.1

2.342 show cvx connections client (SYSTEMID | HOSTNAME) brief

revision 2

see 2.340

2.343 show cvx debug dirs [...]

[dirChurnCount]	*integer*	Dir churn count.
[dirStatus]	*table(string) = DirStatus* see 2.343.1	Mapping from dir name to status.
[entityChurnCount]	*integer*	Entity churn count.

2.343.1 DirStatus

entityChurnCount	*integer*	Entity churn count.
[entityStatus]	*table(string) = EntityStatus* see 2.343.1.1	Mapping from entity name to status.
entryCount	*integer*	Entry count.

2.343.1.1 EntityStatus

stringBufChurnCount	*integer*	Strung buffer churn count.
stringBufCount	*integer*	String buffer count.

2.344 show cvx debug pingpong

addsPerSecond	*integer*	Adds per second.
addsPerSecondSnapshot	*integer*	Last adds per second snapshot.

[delsPerSecond]	*integer*	Last deletes per second snapshot.
[dirChangeCount]	*integer*	Number of reactor fires on pingpong directories.
[downtimeCount]	*integer*	Number of downtime periods.
enabled	*boolean*	Ping test is enabled.
[longestDowntime]	*floating point number*	Longest downtime (seconds).
runTime	*floating point number*	Total run time (seconds).
[totalDataChangeCount]	*integer*	Number of reactor fires on entities in pingpong directories.
[totalDowntime]	*floating point number*	Total downtime (seconds).
totalPings	*integer*	Total pings.

2.345 show cvx file-replication

services	*table(string) = Status* see 2.345.1	A mapping from service name to sets of replicated files.

2.345.1 Status

requesters	*table(string) = RequesterStatus* see 2.345.1.1	A mapping from replicated file set names to the the replication status of the file set.

2.345.1.1 RequesterStatus

files	*table(string) = FileStatus* see 2.345.1.1.1	A mapping of file names to the replication status of each file.

2.345.1.1.1 FileStatus

[lastSyncTime]	*floating point number*	Last synchronized time.
status	*enum: synchronized | failed | unsynchronized*	Status of file synchronization.

2.346 show cvx file-replication NAME

see 2.345.1

2.347 show cvx mounts

connections	*list of CvxMounts* see 2.347.1	Cvx mounts for all connections.

2.347.1 CvxMounts

hostname **	*string*	Switch hostname. **Since: 4.23.2
mounts	*list of ServiceMountStates* see 2.347.1.1	CVX service mount states.

switchId	*MAC address*	Switch Id.

2.347.1.1 ServiceMountStates

mountStates	*list of GroupMountStates* see 2.347.1.1.1	States of groups of mounts.
service	*string*	Service.

2.347.1.1.1 GroupMountStates

group	*string*	Group.
pathStates	*list of MountState* see 2.347.1.1.1.1	Publish states of paths within a group.
state	*string*	Publish state of group.
systemWhitelist	*list of string*	System whitelist.
versionWhitelist	*list of integer*	Version whitelist.

2.347.1.1.1.1 MountState

path	*string*	Mount path.
state	*string*	Mount state.
type	*string*	Mount type.

2.348 show cvx mounts (HOSTNAME | SYSTEMID)

see 2.347.1

2.349 show cvx service

revision 2

services	*list of CvxService* see 2.349.1	Status of all services running on the controller.

2.349.1 CvxService

name	*string*	Service name.
status	*boolean*	Service status.
switches	*table(string) = ServiceStatus* see 2.349.1.1	Status of all the switches running the service.
versions	*list of integer*	Supported versions.

2.349.1.1 ServiceStatus

enabled	*boolean*	If the service is enabled.
negotiatedVersion	*integer*	Negotiated version.
versionCompatible	*boolean*	Version compatibility.
versionNegotiationComplete	*boolean*	Status of negotiation process.

2.350 show cvx service NAME

revision 2

see 2.349.1

2.351 show cvx service peer [...]

clusterPeers	*table(string) = CvxPeerServiceStatus* see 2.351.1	A mapping of peer name to its service status.

2.351.1 CvxPeerServiceStatus

isLeader	*boolean*	Peer is leader.
overallCompatibility	*enum: unknown | partial | ok | mismatch*	Overall service compatibility for peer.
services	*table(string) = CvxPeerServiceCompatibility* see 2.351.1.1	A mapping of service name to its compatibility information.

2.351.1.1 CvxPeerServiceCompatibility

compatibility	*enum: compatible | unknownLocal | disabledBoth | disabledLocal | disabledPeer | unknownPeer | versionMismatch*	Service compatibility status.
[details]	*string*	Service compatibility details.

2.352 show daemon DAEMON_NAME ((ip access-list) | (ipv6 access-list) | (access-list)) [...]

see 2.62

2.353 show daemon [...]

daemons	*table(string) = DaemonCli.Cli.DaemonAgent* see 2.353.1	A mapping from the daemon process name to its configuration.

2.353.1 DaemonCli.Cli.DaemonAgent

data	*table(string) = string*	A string/string map of status data published by the process.
enabled	*boolean*	Whether the daemon process is configured to run.
[isSdkAgent]	*boolean*	True if this process contains an executable that uses EOS SDK to run a third-party agent. This field will be omitted if the agent is not running.
option	*table(string) = string*	A string/string map of options configured for the process.
[pid] **	*integer*	The PID of the process, if the agent is running. **Since: 4.20.5
running	*boolean*	True if this process is actively running.
[starttime] **	*floating point number*	The start time of the process, if the agent is running. **Since: 4.21.0
[uptime] **	*floating point number*	The uptime of the process, if the agent is running. **Since: 4.21.0

2.354 show dcbx [...]

etsConfig **	*EtsTlvModel* see 2.354.2	ETS configuration TLV. **Since: 4.30.0
etsRecommendation **	*EtsTlvModel* see 2.354.2	ETS recommendation TLV. **Since: 4.30.0
interfaces	*table(Interface name) = InterfaceDescription* see 2.354.1	Map to interface class which holds all of the interface metadata.

2.354.1 InterfaceDescription

apcTlvMalformed	*integer*	Number of Application priority configuration TLVs that are malformed.
apcTlvReceived	*integer*	Number of Application priority configuration TLVs received.
apciEntries	*table(string) = ApplicationPriorityEntryData* see 2.354.1.1	Application priority configuration(apci) object. This object contains metadata for every apci entry. There is a one-to-one mapping between each entry protocol ID and the enabled priorities stored within each value.
dcbxEnabled	*boolean*	Interface exists in the DCBX configuration scheme.
ieeeTlvReceived	*boolean*	Ieee TLVs(Type-Lengh-Values) have been received.
lastLldpduTimestamp	*floating point number*	Unix time stamp taken whenever an LLDPDU is received.
macSecBypassCapability	*boolean*	Capable of bypassing MACsec.
pfcPortConfigEnabled	*boolean*	Port PFC configured.
pfcPortConfigPriorities	*integer*	Number of PFC configuration priorities.
pfcTlvMalformed	*integer*	Number of PFC(priority flow control) TlVs that are malformed.
pfcTlvReceived	*integer*	Number of PFC(priority flow control) TlVs received.
pfcWilling	*boolean*	PFC configuration.
pfcciPfcCapability	*integer*	PFC capabilities.
pfcciPfcEnable	*integer*	PFC enabled priorities.
rxEnabled	*boolean*	LLDP adminstatus is enabled for receive.
txEnabled	*boolean*	LLDP(Link Layer Discovery Protocol) adminstatus is enabled for transmit.

2.354.1.1 ApplicationPriorityEntryData

priority	*list of integer*	Corresponding protocol ID enabled priority.
protocolId	*list of integer*	Protocol ID that maps to the protocol's priority.

2.354.2 EtsTlvModel

trafficClasses	*list of TrafficClassModel* see 2.354.2.1	Traffic classes data.

2.354.2.1 TrafficClassModel

algorithm	*integer*	Algorithm identifier.
bandwidth	*integer*	Bandwidth value.
priority	*integer*	Traffic class priority.

2.355 show debugging counter { COUNTERS }

counters	*table(string) = integer*	A mapping between counter name and counter value.
timestamp	*floating point number*	Pulse Counter timestamp.

2.356 show debugging counters [...]

see 2.355

2.357 show debugging inotify (QUERY | all)

[count]	*integer*	Count of total inotify FDs currently allocated.
[limits]	*table(string) = integer*	A mapping of the inotify limit to its value.
[ps]	*table(string) = InotifyProc* see 2.357.2	A mapping of the /proc/PID/fd of each process using inotify to its process information.
[user]	*table(numeric string) = InotifyProc* see 2.357.2	A mapping of the number of inotify FDs in use by each user.
[watch] **	*InotifyPids* see 2.357.1	Inotify watches grouped by PID. **Since: 4.29.2

2.357.1 InotifyPids

pids	*table(numeric string) = InotifyPid* see 2.357.1.1	A mapping from a process ID to its inotify instances.

2.357.1.1 InotifyPid

[cmdline]	*string*	The /proc/PID/cmdline of the process.
fds	*table(numeric string) = InotifyFiles* see 2.357.1.1.1	A mapping from an inotify instance file descriptor to its watched files.

2.357.1.1.1 InotifyFiles

files	*list of InotifyFile* see 2.357.1.1.1.1	Filepaths and corresponding watch descriptors.

2.357.1.1.1.1 InotifyFile

filepath	*string*	The path of the file being watched.
watchDescriptor	*integer*	The watch descriptor associated with the watch.

2.357.2 InotifyProc

[cmdline]	*string*	The /proc/PID/cmdline of the process.
count	*integer*	The number of inotify FDs owned by the process.
[owner]	*string*	The owner of the process.

2.358 show debugging inotify file pid PID

files	*list of InotifyFile* see 2.357.1.1.1.1	Files in var/shmem being watched by the process using inotify.

2.359 show debugging shark clients all

2.360 show debugging smash clients all

[paths]	*table(string) = TableInfo* see 2.360.1	A mapping of the absolute path of the Smash table to information about this table.

2.360.1 TableInfo

headerInfo	*HeaderInfo* see 2.360.1.1	Header information of this Smash table.
[keyshadow]	*list of string*	All keyshadows of this Smash table.
[reader]	*list of string*	All readers of this Smash table.
[shadow]	*list of string*	All shadows of this Smash table.
[writer]	*string*	The writer of this Smash table.

2.360.1.1 HeaderInfo

[capacity]	*CapacityInfo* see 2.360.1.1.1	Current capacity information.
[occupiedSlots]	*integer*	Current number of occupied slots.

2.360.1.1.1 CapacityInfo

[buckets]	*integer*	Current buckets capacity.
[primaryNotifications]	*integer*	Current capacity of the primary conquer queue.
[secondaryNotifications]	*integer*	Current capacity of the secondary conquer queue.
[slots]	*integer*	Current slots capacity.

2.361 show deep-inspection summary

l2SkipValue	*integer*	deep-inspection payload skip value for L2.
l4SkipValue	*integer*	deep-inspection payload skip value for L4.

2.362 show dhcp server ((ipv4 leases) | (ipv6 leases) | leases) [...]

vrfs	*table(string) = DhcpServerShowLeasesModel* see 2.362.1	DHCP server lease information for all vrfs.

2.362.1 DhcpServerShowLeasesModel

ipv4ActiveLeases	*list of Ipv4Leases* see 2.362.1.1	Active IPv4 Leases.
ipv4LeaseError **	*boolean*	There was an error grabbing IPv4 leases. **Since: 4.29.2
ipv6ActiveLeases **	*list of Ipv6Leases* see 2.362.1.2	Active IPv6 Leases. **Since: 4.23.0
ipv6LeaseError **	*boolean*	There was an error grabbing IPv4 leases. **Since: 4.29.2

2.362.1.1 Ipv4Leases

endLeaseTime	*floating point number*	End time of lease.
ipAddress	*IPv4 address*	IP address.
lastTransaction	*floating point number*	Last transaction time with client.
macAddress	*MAC address*	MAC address of client.
[option82] **	*Option82* see 2.362.1.1.1	Information Option. **Since: 4.28.2

2.362.1.1.1 Option82

[circuitIds]	*list of string*	Circuit ID in hex.
[remoteIds]	*list of string*	Remote ID in hex.
[unknownSubOpts]	*list of Option82SubOption* see 2.362.1.1.1.1	Unknown sub-options.

2.362.1.1.1.1 Option82SubOption

typeCode	*integer*	Unknown sub-option type code.
value	*string*	Unknown sub-option value in hex.

2.362.1.2 Ipv6Leases

endLeaseTime	*floating point number*	End time of lease.
ipAddress	*IPv6 address*	Ipv6 Address.
lastTransaction	*floating point number*	Last transaction time with client.
macAddress	*MAC address*	MAC address of client.

2.363 show dhcp server [...]

vrfs	*table(string) = DhcpServerShowModel* see 2.363.1	DHCP server information for all vrfs.

2.363.1 DhcpServerShowModel

[addressFamily] **	*string*	IP version of the server called. **Since: 4.23.0
ipv4Server	*DhcpServerIpv4ShowModel* see 2.363.1.1	IPv4 DHCP server information.
ipv6Server **	*DhcpServerIpv6ShowModel* see 2.363.1.2	IPv6 DHCP server information. **Since: 4.23.0

2.363.1.1 DhcpServerIpv4ShowModel

[clientClasses] **	*table(string) = DhcpServerClientClassModel* see 2.363.1.1.1	Dictionary of Client Class names to inactive reasons. **Since: 4.28.0
[debugLog] **	*boolean*	Debug log is enabled. **Since: 4.23.0
[debugLogPath] **	*string*	Path to the debug log file. **Since: 4.35.0
ipv4ActiveLeases	*integer*	Number of active leases.
[ipv4DisabledMessage]	*string*	Why IPv4 DHCP server is disabled if configured.
ipv4DnsServers	*list of IPv4 address*	DNS servers.
ipv4DomainName **	*string*	DNS domain name. **Since: 4.23.0
ipv4EchoClientId **	*boolean*	IPv4 DHCP server will send back client-id. **Since: 4.31.2
ipv4Interfaces **	*table(Interface name) = DhcpServerInterfaceStatusShowModel* see 2.363.1.1.2	A mapping of IPv4 DHCP interfaces to their status. **Since: 4.22.1
ipv4LeaseDuration	*floating point number*	Duration of leases (seconds).
ipv4ServerActive	*boolean*	IPv4 DHCP server is active.
ipv4Subnets	*table(IPv4 or IPv6 address prefix) = DhcpServerIpv4SubnetModel* see 2.363.1.1.3	Dictionary of IPv4 subnets configured.
[ipv4TftpBootFile] **	*string*	TFTP boot file. **Since: 4.23.1
[ipv4TftpServerOption150] **	*list of IPv4 address*	TFTP Server option 150. **Since: 4.23.2
[ipv4TftpServerOption66] **	*string*	TFTP Server option 66. **Since: 4.23.1
[ipv4VendorOptions] **	*table(string) = DhcpServerIpv4VendorOptionModel* see 2.363.1.1.4	Dictionary of IPv4 vendor-options configured, mapping vendor-option to sub-options. **Since: 4.24.1

2.363.1.1.1 DhcpServerClientClassModel

inactiveReason	*string*	Inactive Reason.

2.363.1.1.2 DhcpServerInterfaceStatusShowModel

active	*boolean*	This interface is active.
[detail]	*string*	Details of interface activity.

2.363.1.1.3 DhcpServerIpv4SubnetModel

activeLeases	*integer*	Number of active leases for this subnet.
[clientClasses] **	*table(string) = DhcpServerClientClassModel* see 2.363.1.1.1	Dictionary of Client Class names to inactive reasons. **Since: 4.28.0
defaultGateway	*IPv4 address*	Default gateway address.
[disabledMessage]	*string*	Why IPv4 subnet is disabled if configured.
dnsServers	*list of IPv4 address*	DNS servers.
[duplicateReservedIp] **	*IPv4 address*	Duplicate reserved IPv4 address. **Since: 4.25.2
[invalidRange] **	*DhcpServerIpv4Range* see 2.363.1.1.3.1	Invalid ranges. **Since: 4.25.2
[leaseDuration] **	*floating point number*	Duration of leases (seconds). **Since: 4.23.1
name **	*string*	Subnet name. **Since: 4.23.0
[overlappingRange] **	*DhcpServerIpv4Range* see 2.363.1.1.3.1	Overlapping ranges. **Since: 4.25.2
[overlappingSubnets] **	*list of IP address prefix*	Overlapping subnets. **Since: 4.25.0
ranges	*list of DhcpServerIpv4Range* see 2.363.1.1.3.1	Ranges configured.
[reservationsMacAddress] **	*table(MAC address) = DhcpServerIpv4ReservationsMacAddressModel* see 2.363.1.1.3.2	Dictionary of MAC addresses to reserved IPv4 addresses. **Since: 4.24.1
subnet	*IP address prefix*	Subnet.
[tftpBootFile] **	*string*	TFTP boot file. **Since: 4.23.1
[tftpServerOption150] **	*list of IPv4 address*	TFTP server option 150. **Since: 4.23.2
[tftpServerOption66] **	*string*	TFTP server option 66. **Since: 4.23.1
[unknownSubnet] **	*boolean*	Subnet is unknown. **Since: 4.25.2

2.363.1.1.3.1 DhcpServerIpv4Range

[assignedLeases] **	*integer*	Number of assigned leases in range. **Since: 4.28.2
[clientClasses] **	*table(string) = DhcpServerClientClassModel* see 2.363.1.1.1	Dictionary of Client Class names to inactive reasons. **Since: 4.28.0
endRangeAddress	*IPv4 address*	End address.
startRangeAddress	*IPv4 address*	Start address.
[totalLeases] **	*integer*	Number of total leases in range. **Since: 4.28.2

2.363.1.1.3.2 DhcpServerIpv4ReservationsMacAddressModel

[hostname] **	*string*	Reserved hostname. **Since: 4.29.0
[ipv4Address]	*IPv4 address*	Reserved IPv4 address.
macAddress	*MAC address*	MAC address of client.

2.363.1.1.4 DhcpServerIpv4VendorOptionModel

subOptions	*list of DhcpServerSubOptionModel* see 2.363.1.1.4.1	Sub-options configured.

2.363.1.1.4.1 DhcpServerSubOptionModel

optionCode	*integer*	Sub-option code.
[optionDataIpAddresses]	*list of IPv4 address*	IPv4 addresses for sub-option type 'ipv4-address'.
[optionDataString]	*string*	String for sub-option type 'string'.
optionType	*enum: ipAddress | string*	Sub-option type.

2.363.1.2 DhcpServerIpv6ShowModel

[clientClasses] **	*table(string) = DhcpServerClientClassModel* see 2.363.1.1.1	Dictionary of Client Class names to inactive reasons. **Since: 4.28.0
[debugLog]	*boolean*	Debug log is enabled.
[debugLogPath] **	*string*	Path to the debug log file. **Since: 4.35.0
ipv6ActiveLeases	*integer*	Number of active leases.
[ipv6DisabledMessage]	*string*	Why IPv6 DHCP server is disabled if configured.
ipv6DnsServers	*list of IPv6 address*	DNS servers.
ipv6DomainName	*string*	DNS domain name.
ipv6Interfaces	*table(Interface name) = DhcpServerInterfaceStatusShowModel* see 2.363.1.1.2	A mapping of IPv4 DHCP interfaces to their status.
ipv6LeaseDuration	*floating point number*	Duration of leases (seconds).
ipv6ServerActive	*boolean*	IPv6 DHCP server is active.

ipv6Subnets	*table(IPv4 or IPv6 address prefix) = DhcpServerIpv6-SubnetModel* see 2.363.1.2.1	Dictionary of IPv6 subnets configured.
[ipv6TftpBootFile] **	*string*	TFTP boot file. **Since: 4.35.0

2.363.1.2.1 DhcpServerIpv6SubnetModel

activeLeases	*integer*	Number of active leases for this subnet.
[clientClasses] **	*table(string) = DhcpServer-ClientClassModel* see 2.363.1.1.1	Dictionary of Client Class names to inactive reasons. **Since: 4.28.0
directActive	*boolean*	IPv6 server responds to direct requests.
[directActiveDetail]	*string*	Details of direct status.
[disabledMessage]	*string*	Why IPv6 subnet is disabled if configured.
dnsServers	*list of IPv6 address*	DNS servers.
[duplicateReservedIp] **	*IPv6 address*	Duplicate reserved IPv6 address. **Since: 4.27.2
[invalidRange] **	*DhcpServerIpv6Range* see 2.363.1.2.1.1	Invalid ranges. **Since: 4.25.2
[leaseDuration] **	*floating point number*	Duration of leases (seconds). **Since: 4.23.1
name	*string*	Subnet name.
[overlappingPrefix-Delegation] **	*DhcpServerIpv6Range* see 2.363.1.2.1.1	Overlapping prefix delegation's range. **Since: 4.35.2
[overlappingRange] **	*DhcpServerIpv6Range* see 2.363.1.2.1.1	Overlapping ranges. **Since: 4.25.2
[overlappingSubnets] **	*list of IP address prefix*	Overlapping subnets. **Since: 4.25.0
[prefixDelegation] **	*table(IPv4 or IPv6 address prefix) = DhcpServerPrefix-DelegationModel* see 2.363.1.2.1.3	IPv6 prefix to delegate. **Since: 4.35.2
ranges	*list of DhcpServerIpv6Range* see 2.363.1.2.1.1	Ranges configured.
relayActive	*boolean*	IPv6 server responds to relay requests.
[relayActiveDetail]	*string*	Details of relay status.
[reservationsMacAddress] **	*table(MAC address) = DhcpServerIpv6-ReservationsMacAddress-Model* see 2.363.1.2.1.2	Dictionary of MAC addresses to reserved IPv6 addresses. **Since: 4.27.2
subnet	*IP address prefix*	Subnet.
[unknownSubnet] **	*boolean*	Subnet is unknown. **Since: 4.25.2

2.363.1.2.1.1 DhcpServerIpv6Range

[assignedLeases] **	*integer*	Number of assigned leases in range. **Since: 4.28.2

[clientClasses] **	*table(string) = DhcpServerClientClassModel* see 2.363.1.1.1	Dictionary of Client Class names to inactive reasons. **Since: 4.28.0
endRangeAddress	*IPv6 address*	End address.
startRangeAddress	*IPv6 address*	Start address.
[totalLeases] **	*integer*	Number of total leases in range. **Since: 4.28.2

2.363.1.2.1.2 DhcpServerIpv6ReservationsMacAddressModel

[hostname] **	*string*	Reserved hostname. **Since: 4.29.0
[ipv6Address]	*IPv6 address*	Reserved IPv6 address.
macAddress	*MAC address*	MAC address of client.

2.363.1.2.1.3 DhcpServerPrefixDelegationModel

[clientClassNameScope]	*string*	Prefix delegation client class name and scope.
[clientClasses]	*table(string) = DhcpServerClientClassModel* see 2.363.1.1.1	Dictionary of Client Class names to inactive reasons.
delegatedLen	*integer*	Delegated length.
[excludedPrefix]	*IP address prefix*	Excluded prefix.
prefix	*IP address prefix*	IPv6 prefix to delegate.

2.364 show directflow

configuredFlows **	*integer*	Total configured flows. **Since: 4.26.0
enabled	*boolean*	DirectFlow enabled.
pendingFlows **	*integer*	Pending flows. **Since: 4.26.0
rejectedFlows **	*integer*	Rejected flows. **Since: 4.26.0
totalFlows **	*integer*	Programmed flows. **Since: 4.20.5
totalPacketCount	*integer*	Matched packets.

2.365 show directflow counters [...]

revision 2

enabled	*boolean*	DirectFlow enabled.
sources	*table(string) = Flows* see 2.365.1	Mapping between Dynamic flow source and Flows.
totalCounters	*boolean*	Total Counters to be printed.
totalPacketCount	*integer*	Total Matched packets.

2.365.1 Flows

flows	*list of Flow* see 2.365.1.1	Flows.

2.365.1.1 Flow

[action]	*Action* see 2.365.1.1.1	Action set values.
[bridgeMacAddr]	*string*	Bridge MAC Address.
[cookie]	*integer*	flow cookie.
[countersAvailable] **	*boolean*	Hardware counters available. **Since: 4.20.5
countersPerSlice **	*table(string) = Counter* see 2.365.1.1.2	Dictionary of counters keyed with slice name. **Since: 4.18.0
[hardTimeout]	*integer*	Hard timeout.
[idleTimeout]	*integer*	Idle timeout.
[installation] **	*boolean*	Install flow after resource allocation. **Since: 4.24.2
[match]	*Match* see 2.365.1.1.3	Match values.
[matchBytes]	*integer*	Number of bytes that matched flow.
[matchPackets]	*integer*	Number of packets that matched flow.
name	*string*	Flow name.
[persistent]	*boolean*	Flow persistence.
priority	*integer*	Flow priority.
[priorityGroupType] **	*enum: ipv6Fib | low | ethsrc | flood | default | portacl | vlanacl | vip | high | ethdst | ipv4Fib | ethdstHairpin | vlan*	Flow priority Group. **Since: 4.18.0
statusPerSlice **	*table(string) = Status* see 2.365.1.1.4	Dictionary of status's keyed with slice name. **Since: 4.18.0
[tableId] **	*integer*	Table Id. **Since: 4.25.0
[tableName] **	*string*	Flow name. **Since: 4.25.0
[tableType] **	*string*	Flow table type. **Since: 4.18.0

2.365.1.1.1 Action

[addVlanInner] **	*integer*	Add inner Vlan ID. **Since: 4.22.1
[addVlanInnerPCP] **	*integer*	Add inner Vlan PCP. **Since: 4.22.1
[addVlanOuter] **	*integer*	Add outer Vlan ID. **Since: 4.23.1
[addVlanOuterPCP] **	*integer*	Add outer Vlan PCP. **Since: 4.23.1
[allowCopyToCpu] **	*boolean*	Allow copy to CPU. **Since: 4.32.1
[debugCapture] **	*boolean*	Debug Capture. **Since: 4.18.0
[dropTag] **	*boolean*	Drop Outer Tag. **Since: 4.20.0
[egrMirrorInterfaces]	*list of Interface name*	Copy egress to mirror destination interfaces.
[goto] **	*boolean*	Goto Action. **Since: 4.23.0
[group]	*integer*	Forward to group.
[icmpCode] **	*integer*	Set ICMP code. **Since: 4.23.1
[icmpType] **	*integer*	Set ICMP type. **Since: 4.23.1
[ingrMirrorInterfaces]	*list of Interface name*	Copy ingress to mirror destination interfaces.
[ipDst] **	*IpAddr* see 2.365.1.1.1.4	Set destination IP address. **Since: 4.25.1
[ipPortDst]	*integer*	Set TCP/UDP destination port.
[ipPortSrc]	*integer*	Set TCP/UDP source port.
[ipSrc] **	*IpAddr* see 2.365.1.1.1.4	Set source IP address. **Since: 4.25.1
[ipTos]	*integer*	Set Ipv4 Tos (as received).
[localIntf] **	*string*	Local intf. **Since: 4.20.5
[loopback]	*boolean*	Output to ingress interface.
[macDst]	*MacAddr* see 2.365.1.1.1.3	Set destination Mac address.
[macDstBr]	*MacAddr* see 2.365.1.1.1.3	Set destination Mac address to router-address.
[macSrc]	*MacAddr* see 2.365.1.1.1.3	Set source Mac address.
[macSrcBr]	*MacAddr* see 2.365.1.1.1.3	Set source Mac address to router-address.
[metaData] **	*integer*	Set meta data. **Since: 4.25.0
[nextTblName] **	*string*	Next Table Name. **Since: 4.25.0
[outInterfaces]	*list of Interface name*	Output interfaces.
outputAll	*boolean*	Flood to all interfaces except ingress.
outputController	*boolean*	Send to controller.

outputDrop	*boolean*	Drop packet.
outputFlood	*boolean*	Flood to all non-blocked interfaces except ingress.
[outputInternalLoopback] **	*boolean*	Output to hardware loopback. **Since: 4.20.0
outputLocal	*boolean*	Send to switch CPU.
[outputNexthop]	*list of IpGenericAddr* see 2.365.1.1.1.1	Output nexthop IP address.
[outputNexthopRec]	*boolean*	Recursive resolution of nexthop IP address.
[outputNexthopVrfName] **	*string*	VRF name. **Since: 4.22.1
outputNormal	*boolean*	Process normally.
[outputQ]	*integer*	Output queue.
[outputTrafficClass]	*integer*	Output traffic class.
[pktLog] **	*boolean*	Log packet. **Since: 4.26.2
[popVlan] **	*boolean*	Push Vlanid. **Since: 4.23.0
[pushVlan] **	*boolean*	Push Vlanid. **Since: 4.23.0
[removeVlanInner] **	*boolean*	Remove Inner Vlan header. **Since: 4.22.1
[ttlDec]	*boolean*	Decrement TTL.
[vlan]	*integer*	Set Vlan ID.
[vlanPCP]	*integer*	Set Vlan PCP.

2.365.1.1.1.1 IpGenericAddr

Could also be an instance of:
IpGenericAddrAndPort 2.365.1.1.1.2

ip	*IP address*	IPv4 or IPv6 address.

2.365.1.1.1.2 IpGenericAddrAndPort

ip	*IP address*	IPv4 or IPv6 address.
port	*integer*	Port.

2.365.1.1.1.3 MacAddr

mac	*MAC address*	Mac address.

2.365.1.1.1.4 IpAddr

ip	*IPv4 address*	Ip address.

2.365.1.1.2 Counter

[matchBytes]	*integer*	Number of bytes that matched flow.
[matchPackets]	*integer*	Number of packets that matched flow.

2.365.1.1.3 Match

[arpSenderProtoAddr] **	*IpAddrAndBitMask* see 2.365.1.1.3.2	Match ARP sender IP address and mask. **Since: 4.28.0
[arpTargetProtoAddr] **	*IpAddrAndBitMask* see 2.365.1.1.3.2	Match ARP target IP address and mask. **Since: 4.28.0
[encapDot1q] **	*boolean*	Match 802.1Q encapsulation. **Since: 4.22.1
[ethType]	*integer*	Match ethernet type.
[ethTypeMask]	*integer*	Match Ethertype Mask.
[fecId] **	*integer*	FEC ID. **Since: 4.32.1
[fieldSetDst] **	*string*	Match destination field-Set. **Since: 4.22.1
[fieldSetSrc] **	*string*	Match source field-Set. **Since: 4.22.1
[httpMethod] **	*enum: HttpPut | HttpHead | HttpPatch | HttpPost | HttpDelete | HttpGet | HttpOptions*	Match HTTP method. **Since: 4.26.2
[icmpCode] **	*integer*	Match ICMP code. **Since: 4.23.1
[icmpType] **	*integer*	Match ICMP type. **Since: 4.23.1
[inInterfaceCpu]	*boolean*	Match input interface CPU.
[inInterfaces]	*list of Interface name*	Match input interfaces.
[inputInternalLoopback] **	*boolean*	Match hardware loopback. **Since: 4.20.0
[ip6Dst]	*Ip6AddrAndBitMask* see 2.365.1.1.3.1	Match destination IP6 address and mask.
[ip6Src]	*Ip6AddrAndBitMask* see 2.365.1.1.3.1	Match source IP6 address and mask.
[ipDst]	*IpAddrAndBitMask* see 2.365.1.1.3.2	Match destination IP address and mask.
[ipPortDst]	*integer*	Match TCP/UDP destination port.
[ipPortDstMask] **	*integer*	Match TCP/UDP destination port Mask. **Since: 4.27.1
[ipPortSrc]	*integer*	Match TCP/UDP source port.
[ipPortSrcMask] **	*integer*	Match TCP/UDP source port Mask. **Since: 4.27.1
[ipProto]	*integer*	Match IP protocol.
[ipSrc]	*IpAddrAndBitMask* see 2.365.1.1.3.2	Match source IP address and mask.
[ipTos]	*integer*	Match Ip Tos (as received).
[macDst]	*MacAddrAndBitMask* see 2.365.1.1.3.3	Match destination Mac address.

[macDstBr]	*MacAddrAndBitMask* see 2.365.1.1.3.3	Match destination Mac address with router-address.
[macSrc]	*MacAddrAndBitMask* see 2.365.1.1.3.3	Match source Mac address.
[macSrcBr]	*MacAddrAndBitMask* see 2.365.1.1.3.3	Match source Mac address with router-address.
[metaData] **	*integer*	Match metaData. **Since: 4.25.0
[packetRes] **	*enum: L2BC* | *L3McUnknown* | *L2McUnknown* | *L3UcUnknown* | *L2McKnown* | *L2UcUnknown* | *L3UcKnown* | *L3McKnown* | *L2UcKnown*	Match Packet Resolution. **Since: 4.18.0
[tcpAck]	*boolean*	Tcp flag Ack.
[tcpFin]	*boolean*	Tcp flag Fin.
[tcpHLen] **	*integer*	Tcp header length. **Since: 4.31.1
[tcpPsh]	*boolean*	Tcp flag Psh.
[tcpRst]	*boolean*	Tcp flag Rst.
[tcpSyn]	*boolean*	Tcp flag Syn.
[tcpUrg]	*boolean*	Tcp flag Urg.
[ttl]	*integer*	Match Time to Live value.
[ttlMask]	*integer*	Match Time to Live mask.
[unknownL2V4Multicast-Address]	*boolean*	Unknown IPV4 multicastaddress. Match on the L2 field.
[unknownL3V4Multicast-Address]	*boolean*	Unknown IPV4 multicastaddress. Match on the L3 field.
[vlan]	*integer*	Match Vlan 'ID.
[vlanInner] **	*integer*	Match inner Vlan 'ID. **Since: 4.22.1
[vlanInnerMask] **	*integer*	Match inner Vlan ID Mask. **Since: 4.22.1
[vlanMask]	*integer*	Match Vlan ID Mask.
[vlanPCP]	*integer*	Match Vlan PCP.
[vlanUnTagged] **	*boolean*	Match untagged packets. **Since: 4.20.0
[vrfName] **	*string*	Match VRF. **Since: 4.23.0

2.365.1.1.3.1 Ip6AddrAndBitMask

ip	*IPv6 address*	Ip6 address.
mask	*IPv6 address*	Ip6 address mask.

2.365.1.1.3.2 IpAddrAndBitMask

ip	*IPv4 address*	Ip address.
mask	*IPv4 address*	Ip address mask.

2.365.1.1.3.3 MacAddrAndBitMask

mac	*MAC address*	Mac address.
mask	*MAC address*	Mac address mask.

2.365.1.1.4 Status

status	*enum: flowDeleted* | *flowRejectedHwTableFull* | *flowPending* | *flowDeletedGroupRemoved* | *flowRejectedBadMatch* | *flowUnknown* | *flowExpiredHard* | *flowRemovedIntfDown* | *flowCreated* | *flowActionsUnsupported* | *flowRejectedOther* | *flowRejectedBadAction* | *flowRejectedTimeoutNot-Supported* | *flowExpiredIdle*	Flow status per slice.

2.366 show directflow detail [...]

revision 2

[details]	*Details* see 2.366.1	Details of flows.
sources	*table(string) = Flows* see 2.365.1	Mapping between Dynamic flow source and Flows.

2.366.1 Details

[numFlowsProgrammed]	*integer*	Number of programmed flows.
sources	*table(string) = FlowStatus* see 2.366.1.1	Mapping between Dynamic flow source and FlowStatus.

2.366.1.1 FlowStatus

status	*table(string) = string*	Mapping of flow name to flow status.

2.367 show directflow field-set

enabled	*boolean*	DirectFlow enabled.
[endPoints]	*DirectFlowEndPointList* see 2.367.1	endpoint list.
fieldSetName	*string*	FieldSet.

status	*enum: success | pending | rejectedOther | failed*	FieldSet status.

2.367.1 DirectFlowEndPointList

endPoints	*list of DirectFlowEndPoint* see 2.367.1.1	endpoints.

2.367.1.1 DirectFlowEndPoint

fieldSetName	*string*	FieldSet.
ipAddr	*IpGenericAddr* see 2.365.1.1.1.1	IP address of endpoint.
macAddr	*MacAddr* see 2.365.1.1.1.3	MAC address of endpoint.
status	*enum: success | pending | rejectedOther | failed*	Endpoint status.
vlanId	*integer*	vlan of endpoint.
[vrfName]	*string*	Vrf Name.

2.368 show directflow flows [...]

revision 2

see 2.366

2.369 show dns cache counters

evictions	*integer*	Evictions.
hits	*integer*	Queries answered locally.
insertions	*integer*	Insertions.
misses	*integer*	Queries forwarded.
size	*integer*	Cache size.

2.370 show dns domain [...]

[domainName]	*string*	The domain name of the switch.

2.371 show dot1q-tunnel [...]

interfaces	*list of Interface name*	List of interfaces in dot1q-tunnel mode.

2.372 show dot1x all

aaaServerLoadBalancing **	*enum: loadBalanceRoundRobin | loadBalanceDisabled*	AaaServer load-balancing. **Since: 4.35.2
bpduBypass **	*boolean*	Dot1X BPDU Bypass is enabled. **Since: 4.31.2
[configuredDot1xOverriding-Features] **	*list of string*	List of features conflicting with Dot1x. **Since: 4.34.0
dynAuth	*boolean*	Dot1X Dynamic Authorization is enabled.
interfaces	*table(Interface name) = Dot1xInterfaceInformation* see 2.372.1	A mapping of interface to its Dot1X information.
lacpBypass **	*boolean*	Dot1X LACP Bypass is enabled. **Since: 4.33.0
lldpBypass	*boolean*	Dot1X LLDP Bypass is enabled.
sendIdentityReqLoggedOffMac **	*boolean*	Send unicast identity request when a MAC is logged off. **Since: 4.27.2
sendIdentityReqNewMac **	*boolean*	Send unicast identity request on a new MAC. **Since: 4.27.2
sessionMoveEapol **	*boolean*	Dot1x EAPOL session move is enabled. **Since: 4.29.0
sessionReplaceDetection-Action **	*enum: detectionDisabled | errdisable | logOnly*	Action to take when frequent session replacements detected. **Since: 4.29.2
sessionReplaceDetection-Enabled **	*boolean*	Detect frequent session replacements in single host mode. **Since: 4.29.1
systemAuthControl	*boolean*	System Authentication Control is enabled.
version	*integer*	Dot1X protocol version.

2.372.1 Dot1xInterfaceInformation

Could also be an instance of:
Dot1xInterfaceDetails 2.372.2

authFailVlan	*integer*	Authentication failure VLAN.
eapolDisabled	*boolean*	EAPOL is disabled.
forceAuthPhone **	*boolean*	Forced authorization of phone devices. **Since: 4.26.2
hostMode	*enum: authAllHost | singleHost | multiHost*	singleHost – Allow only one supplicant on an authorized port. multiHost – Allow multiple clients on an authorized port. authAllHost – Allow multiple dot1x-authenticated clients on an authorized port.
[idleTimeout] **	*integer*	Idle-Timeout for supplicants in seconds. **Since: 4.26.2
maxReauthReq	*integer*	Maximum number of reauthentication attempts.

mbaAuthAlways **	*boolean*	Retain MAC authentication session when EAPOL is in progress. **Since: 4.27.2
mbaEnabled	*boolean*	MAC-based authentication is enabled.
mbaFallback	*boolean*	MBA fallback for EAPOL authentication failure.
mbaHostMode **	*boolean*	MAC based authentication host mode is enabled. **Since: 4.25.1
mbaTimeout	*floating point number*	Timeout for starting MAC based authentication in seconds.
portControl	*enum: forceAuth | controlled | forceUnauth*	Controlled – enable 802.1X for the interface. ForceAuth – disable 802.1X and put the interface into authorized state. ForceUnauth – disable 802.1X and put the interface into unauthorized state.
quietPeriod	*floating point number*	Waiting period in seconds after a failed authentication.
reauthTimeoutIgnore	*boolean*	Retain current port auth status on reauth server or supplicant timeouts or new reauth requests.
sessionReplaceEnabled **	*boolean*	Dot1x session replace in single-host mode is enabled. **Since: 4.28.1
txPeriod	*floating point number*	Waiting period in seconds before retrying a message to supplicant.
unauthorizedAccessVlan-Egress	*boolean*	Give unauthorized access port egress membership of access VLAN.
unauthorizedNativeVlan-Egress	*boolean*	Give unauthorized trunk port egress membership of native VLAN.

2.372.2 Dot1xInterfaceDetails

authFailVlan	*integer*	Authentication failure VLAN.
eapolDisabled	*boolean*	EAPOL is disabled.
forceAuthPhone **	*boolean*	Forced authorization of phone devices. **Since: 4.26.2
hostMode	*enum: authAllHost | singleHost | multiHost*	singleHost – Allow only one supplicant on an authorized port. multiHost – Allow multiple clients on an authorized port. authAllHost – Allow multiple dot1x-authenticated clients on an authorized port.
[idleTimeout] **	*integer*	Idle-Timeout for supplicants in seconds. **Since: 4.26.2
maxReauthReq	*integer*	Maximum number of reauthentication attempts.
mbaAuthAlways **	*boolean*	Retain MAC authentication session when EAPOL is in progress. **Since: 4.27.2
mbaEnabled	*boolean*	MAC-based authentication is enabled.
mbaFallback	*boolean*	MBA fallback for EAPOL authentication failure.

mbaHostMode **	*boolean*	MAC based authentication host mode is enabled. **Since: 4.25.1
mbaTimeout	*floating point number*	Timeout for starting MAC based authentication in seconds.
[portAuthorizationState]	*enum: authorized | restrictedVlan | blocked | guestVlan*	Blocked – port is unauthorized. Authorized – port is authorized. GuestVlan – port is authorized through guest VLANRestrictedVlan – port is authorized through restricted VLAN.
portControl	*enum: forceAuth | controlled | forceUnauth*	Controlled – enable 802.1X for the interface. ForceAuth – disable 802.1X and put the interface into authorized state. ForceUnauth – disable 802.1X and put the interface into unauthorized state.
[portShutdownStatus] **	*string*	Port shutdown by AAA server. **Since: 4.32.2
quietPeriod	*floating point number*	Waiting period in seconds after a failed authentication.
reauthTimeoutIgnore	*boolean*	Retain current port auth status on reauth server or supplicant timeouts or new reauth requests.
sessionReplaceEnabled **	*boolean*	Dot1x session replace in single-host mode is enabled. **Since: 4.28.1
supplicantMacs	*table(MAC address) = integer*	Mapping of supplicant MAC address to its reauthentication period in seconds.
txPeriod	*floating point number*	Waiting period in seconds before retrying a message to supplicant.
unauthorizedAccessVlan-Egress	*boolean*	Give unauthorized access port egress membership of access VLAN.
unauthorizedNativeVlan-Egress	*boolean*	Give unauthorized trunk port egress membership of native VLAN.

2.373 show dot1x all brief

aaaServerLoadBalancing **	*enum: loadBalanceRoundRobin | loadBalanceDisabled*	AaaServer load-balancing. **Since: 4.35.2
bpduBypass **	*boolean*	Dot1X BPDU Bypass is enabled. **Since: 4.31.2
[configuredDot1xOverriding-Features] **	*list of string*	List of features conflicting with Dot1x. **Since: 4.34.0
dynAuth	*boolean*	Dot1X Dynamic Authorization is enabled.
interfaces	*table(Interface name) = Dot1xInterfaceDetails* see 2.372.2	A mapping of interface to its Dot1X detailed information.
lacpBypass **	*boolean*	Dot1X LACP Bypass is enabled. **Since: 4.33.0
lldpBypass	*boolean*	Dot1X LLDP Bypass is enabled.

`sendIdentityReqLoggedOffMac` **	*boolean*	Send unicast identity request when a MAC is logged off. **Since: 4.27.2
`sendIdentityReqNewMac` **	*boolean*	Send unicast identity request on a new MAC. **Since: 4.27.2
`sessionMoveEapol` **	*boolean*	Dot1x EAPOL session move is enabled. **Since: 4.29.0
`sessionReplaceDetection-Action` **	*enum: detectionDisabled* | *errdisable* | *logOnly*	Action to take when frequent session replacements detected. **Since: 4.29.2
`sessionReplaceDetection-Enabled` **	*boolean*	Detect frequent session replacements in single host mode. **Since: 4.29.1
`systemAuthControl`	*boolean*	System Authentication Control is enabled.
`version`	*integer*	Dot1X protocol version.

2.374 show dot1x all details

see 2.373

2.375 show dot1x all statistics

dropCounters **	*table(Interface name) = Dot1xDroppedCounterStats* see 2.375.1	A mapping between interfaces and 802.1X interface dropped counter statistics. **Since: 4.25.2
interfaces	*table(Interface name) = Dot1xInterfaceStats* see 2.375.2	A mapping between interfaces and 802.1X interface statistics.

2.375.1 Dot1xDroppedCounterStats

unauthEapolHost	*integer*	EAPOL unauthorized host.
unauthEapolPort	*integer*	EAPOL unauthorized port.
unauthMbaHost	*integer*	MBA unauthorized host.

2.375.2 Dot1xInterfaceStats

lastRxSrcMac	*MAC address*	Last EAPOL frame source.
rxInvalid	*integer*	Invalid EAPOL frames received.
rxLogoff	*integer*	EAPOL Logoff frames received.
rxResp	*integer*	EAP Response frames received.
rxRespId	*integer*	EAPOL Resp/Id frames received.
rxStart	*integer*	EAPOL Start frames received.
rxTotal	*integer*	EAPOL frames received.
rxVersion	*integer*	Last EAPOL frame version.
txReq	*integer*	EAP Request frames transmitted.
txReqId	*integer*	EAP Initial Request frames transmitted.
txTotal	*integer*	EAPOL frames transmitted.

2.376 show dot1x captive-portal bypass [...]

fqdns	*table(string) = Dot1xCaptivePortalBypass-IpMatch* see 2.376.1	A mapping of the configured bypass FQDNs to the matching addresses.

2.376.1 Dot1xCaptivePortalBypassIpMatch

addresses	*list of IP address*	Addresses matching the FQDN.

2.377 show dot1x captive-portal counters [...]

interfaces	*table(Interface name) = CaptivePortalCounters-Interface* see 2.377.1	A mapping from interface to its counters.

2.377.1 CaptivePortalCountersInterface

`httpInvalid`	*integer*	HTTP errors/dropped.
`httpRedirect`	*integer*	HTTP redirections to captive portal.
`httpRequest`	*integer*	HTTP requests to dot1x web server.
`httpTimeout` **	*integer*	HTTP timeouts. **Since: 4.34.0
`httpsInvalid`	*integer*	HTTPS errors/dropped.
`httpsRedirect`	*integer*	HTTPS redirections to captive portal.
`httpsRequest`	*integer*	HTTPS requests to dot1x web server.
`httpsTimeout` **	*integer*	HTTPS timeouts. **Since: 4.34.0
`lastClearTime`	*floating point number*	Last cleared time for counters.

2.378 show dot1x captive-portal resolutions [...]

`addresses`	*table(IPv4 or IPv6 address) = Dot1xCaptivePortalResolutionsEntry* see 2.378.1	A mapping of addresses to resolutions.

2.378.1 Dot1xCaptivePortalResolutionsEntry

`[expiration]`	*floating point number*	Expiration time of the hostnames.
`hostnames`	*list of string*	Hostnames returned by DNS.
`ready`	*boolean*	Resolution result is ready.

2.379 show dot1x hosts [...]

`intfSupplicantsDict`	*table(Interface name) = Dot1xHosts* see 2.379.1	A mapping between the interfaces and all the MBA or Dot1X supplicants for that interface.

2.379.1 Dot1xHosts

`supplicants`	*table(MAC address) = Dot1xHost* see 2.379.1.1	A mapping betweeen MAC addresses and Dot1X or MBA supplicant information.

2.379.1.1 Dot1xHost

`authMethod`	*string*	Authentication method used by the supplicant.
`authStage`	*string*	Supplicant state.
`cachedAuthAtLinkDown` **	*boolean*	Cache supplicant on link down. **Since: 4.24.2
`fallback` **	*string*	Fallback applied. **Since: 4.25.2
`internalVlan` **	*boolean*	Internally configured VLAN. **Since: 4.33.1

reauthTimeoutSeen **	*boolean*	Reauth timeout seen. **Since: 4.24.2
sessionCached **	*boolean*	Supplicant software-cached. **Since: 4.31.1
staticVlan **	*boolean*	Statically configured VLAN. **Since: 4.32.0
supplicantMac	*MAC address*	supplicant MAC address.
username **	*string*	EAP identity in use on this interface. **Since: 4.32.0
vlanId	*string*	VLAN ID.
[vlanName] **	*string*	VLAN Name. **Since: 4.32.0

2.380 show dot1x hosts blocked

macAddresses	*table(MAC address) = Dot1xBlockedMacEntry* see 2.380.1	A mapping between blocked MAC address and list of intferace and VLAN pair on which the MAC is blocked through dynamic authorization.

2.380.1 Dot1xBlockedMacEntry

interfaces	*table(Interface name) = integer*	A mapping between interface and VLAN.

2.381 show dot1x hosts interface INTFS detail

interfaces	*table(Interface name) = Dot1xIntfHosts* see 2.381.1	A mapping between interfaces and their host details.

2.381.1 Dot1xIntfHosts

supplicants	*table(MAC address) = Dot1XSupplicantExtended-Attr* see 2.381.1.1	A mapping betweeen MAC addresses and Dot1X or MBA supplicant attributes.

2.381.1.1 Dot1XSupplicantExtendedAttr

deviceDomain	*enum: data | phone*	data - 802.1X supplicant is a data device-phone - 802.1X supplicant is a phone device.
internalVlan **	*boolean*	Internally configured VLAN. **Since: 4.33.1
staticVlan	*boolean*	Statically configured VLAN.
supplicantAttr	*Dot1XSupplicantAttr* see 2.381.1.1.1	Supplicant operational and AAA returned attributes.
[vlanName]	*string*	VLAN Name.

2.381.1.1.1 Dot1XSupplicantAttr

accountingSessionId	*string*	Supplicant Accounting-Session-Id.
[aristaConfigVlan] **	*string*	Supplicant Arista-Config-Vlan. **Since: 4.35.0
[aristaDynamicHostMode] **	*string*	Supplicant Arista-Dynamic-HostMode. **Since: 4.36.0
[aristaInterfaceProfile] **	*string*	Supplicant Arista-Interface-Profile. **Since: 4.33.2
[aristaMvrp] **	*string*	Supplicant Arista-Mvrp. **Since: 4.33.0
[aristaPeriodicIdentity] **	*string*	Supplicant Arista-PeriodicIdentity. **Since: 4.27.2
[aristaSegmentId] **	*string*	Supplicant Arista-Segment-Id. **Since: 4.26.2
[aristaTenantId] **	*string*	Supplicant Arista-Tenant-Id. **Since: 4.33.1
[aristaWebAuth]	*string*	Supplicant Arista-WebAuth.
authMethod	*string*	Authentication method used by the supplicant.
authStage	*string*	Supplicant state.
cacheConfTime **	*integer*	Cached-results configuration interval in seconds. **Since: 4.32.0
cachedAuthAtLinkDown	*boolean*	Cache supplicant on link down.
callingStationId	*string*	Supplicant Calling-Station-Id.
[captivePortal]	*string*	Supplicant Captive portal.

[captivePortalSource]	*string*	Supplicant Captive portal source.
detail_	*boolean*	Print details.
[deviceType] **	*string*	Device Type classification received from AAA. **Since: 4.30.0
fallback **	*string*	Fallback applied. **Since: 4.30.2
[filterId]	*string*	Supplicant Filter-Id.
[framedIpAddrSource]	*string*	Supplicant Framed-IP-Address source.
[framedIpAddress]	*IPv4 address*	Supplicant Framed-IP-Address.
[framedIpv6AddrSource] **	*enum: sourceLldp* | *sourceIpLocking* | *sourceAaaAccept* | *sourceArp* | *sourceNone* | *sourceL3NbrByGnmi*	Supplicant Framed-IPv6-Address source. **Since: 4.34.1
[framedIpv6Address] **	*IPv6 address*	Supplicant Framed-IPv6-Address. **Since: 4.34.1
identity	*string*	EAP identity in use on this interface.
[idleTimeout] **	*integer*	Supplicant Idle-Timeout in seconds. **Since: 4.27.0
interface	*interface name*	Supplicant interface.
internalVlan **	*boolean*	Internally configured VLAN. **Since: 4.33.2
[nasFilterRules] **	*list of string*	The list of supplicant NAS-Filter-Rule. **Since: 4.26.2
[quietPeriod] **	*integer*	Quiet period in seconds for fallback VLAN scenarios. **Since: 4.36.0
reauthBehavior	*string*	Supplicant re-authentication behavior.
reauthInterval	*integer*	Supplicant re-authentication interval in seconds.
reauthTimeoutSeen	*boolean*	Reauth timeout seen.
[serviceType]	*string*	Supplicant Service-Type.
sessionCached **	*boolean*	Supplicant software-cached. **Since: 4.31.1
[sessionTimeout]	*integer*	Supplicant Session-Timeout.
staticVlan **	*boolean*	Statically configured VLAN. **Since: 4.33.2
[supplicantClass]	*string*	Supplicant Class.
supplicantMac	*MAC address*	Supplicant MAC address.
[terminationAction]	*string*	Supplicant Termination-Action.
[timeToCacheExpiry] **	*integer*	Time remaining for cached-results in seconds. **Since: 4.32.0
[timeToReauth] **	*integer*	Time remaining for next reauthentication in seconds. **Since: 4.27.2
[tunnelPrivateGroupId]	*string*	Supplicant Tunnel-Private-GroupId.
[tunnelPrivateGroupIdAuth-Sent] **	*string*	Supplicant Tunnel-Private-GroupId sent in Access Request. **Since: 4.35.0
vlanId	*string*	VLAN ID.

`[vlanName]` **	*string*	VLAN Name. **Since: 4.33.2

2.382 show dot1x hosts mac MAC [...]

see 2.381.1.1.1

2.383 show dot1x hosts mac MAC accounting

[calledStationId]	*string*	Supplicant Called-Station-Id.
[callingStationId]	*string*	Supplicant Calling-Station-Id.
[framedIpAddrSource] **	*string*	Supplicant Framed-IP-Address source. **Since: 4.33.0
[framedIpAddress]	*IPv4 address*	Supplicant Framed-IP-Address.
[framedIpv6AddrSource] **	*enum: sourceLldp* | *sourceIpLocking* | *sourceAaaAccept* | *sourceArp* | *sourceNone* | *sourceL3NbrByGnmi*	Supplicant Framed-IPv6-Address source. **Since: 4.34.1
[framedIpv6Address] **	*IPv6 address*	Supplicant Framed-IPv6-Address. **Since: 4.34.1
[hostname]	*string*	Supplicant DHCP hostname from DHCP option 12.
[identity]	*string*	EAP identity in use on this interface.
[interface]	*interface name*	Supplicant interface.
[lldpSysDesc]	*string*	Supplicant LLDP system description from LLDP TLV 6.
[lldpSysName]	*string*	Supplicant LLDP system name from LLDP TLV 5.
[nasIdentifier]	*string*	Supplicant NAS-Identifier.
[nasPortType]	*enum: virtual* | *ethernet*	ethernet – Ethernet portvirtual – Virtual port.
[paramReqList]	*string*	Supplicant DHCP parameter request list from DHCP option 55.
[serviceType]	*string*	Supplicant Service-Type.
[supplicantClass]	*string*	Supplicant Class.
supplicantMac	*MAC address*	Supplicant MAC address.
[tunnelPrivateGroupIdAcct-Sent] **	*string*	Supplicant Tunnel-Private-GroupId sent in Accounting Request. **Since: 4.35.0
[vendorClassId]	*string*	Supplicant DHCP vendor class identifier from DHCP option 60.

2.384 show dot1x interface INTFS

interfaces	*table(Interface name) = Dot1xInterfaceInformation* see 2.372.1	A mapping between interfaces and 802.1X interface information.

2.385 show dot1x interface INTFS details

interfaces	*table(Interface name) = Dot1xInterfaceDetails* see 2.372.2	A mapping between interfaces and 802.1X interface detailed information.

2.386 show dot1x interface INTFS statistics

see 2.375

2.387 show dot1x radius

revision 2

hosts	*list of ServerInfo* see 2.387.1	List of servers configured for 802.1x.

2.387.1 ServerInfo

[acctPort]	*integer*	Specifies accounting port number.
[authPort]	*integer*	Specifies authorization port number.
deadTime	*floating point number*	Configured RADIUS deadtime.
[dtlsPort] **	*integer*	RADIUS server DTLS port number. **Since: 4.36.0
hostName	*string*	IP address or hostname of the RADIUS server.
lastStatusChange	*floating point number*	Switch time of the most recent server status update.
lastStatusChangeTime **	*floating point number*	UTC time of the most recent server status update. **Since: 4.36.0
status	*enum: failed | active*	Status of the RADIUS server.
[tlsPort]	*integer*	RADIUS server TLS port number.
vrf	*string*	The VRF over which this server is reachable.

2.388 show dot1x statistics hosts [...]

hostStats	*Dot1xHostStats* see 2.388.1	Aggregate supplicant counts.
interfaceFiltered_	*boolean*	Filtered by Interface.
interfaces	*table(string) = Dot1xInterfaceHostStats* see 2.388.2	A mapping between interfaces and their host statistics.
systemAuthControl	*boolean*	Dot1x is enabled globally.
vlanFiltered_	*boolean*	Filtered by VLAN.
vlans	*table(numeric string) = Dot1xVlanHostStats* see 2.388.3	A mapping between VLANs and their host statistics.

2.388.1 Dot1xHostStats

eapolCached	*integer*	Count of EAPOL supplicants in cached state.
eapolFailed	*integer*	Count of EAPOL supplicants in failed state.
eapolFallbackTotal	*integer*	Count of EAPOL supplicants in all fallback states.
eapolSuccess	*integer*	Count of EAPOL supplicants in success state.
mbaCached	*integer*	Count of MBA supplicants in cached state.
mbaFailed	*integer*	Count of MBA supplicants in failed state.
mbaFallbackTotal	*integer*	Count of MBA supplicants in all fallback states.
mbaSuccess	*integer*	Count of MBA supplicants in success state.
totalSupplicant	*integer*	Count of all supplicants.
webAuth	*integer*	Count of web-auth supplicants.

2.388.2 Dot1xInterfaceHostStats

aaaUnrespConfigured	*boolean*	AAA unresponsive agnostic VLAN is configured.
aaaUnrespCount	*integer*	Count of supplicants in AAA unresponsive VLAN.
aaaUnrespPhoneConfigured	*boolean*	AAA unresponsive phone VLAN is configured.
aaaUnrespPhoneCount	*integer*	Count of supplicants in AAA unresponsive phone VLAN.
authFailConfigured	*boolean*	Auth fail vlan is configured.
authFailCount	*integer*	Count of supplicants in auth-fail VLAN.
dot1xEnabled	*boolean*	Dot1x is enabled on the port.
eapolToMbaFallbackCount	*integer*	Count of supplicants in EAPOL to MBA fallback.
guestCount	*integer*	Count of supplicants in guest VLAN.
guestVlanConfigured	*boolean*	Guest vlan is configured.
hostStats	*Dot1xHostStats* see 2.388.1	Aggregate supplicant counts.
mbaFallbackConfigured	*boolean*	EAPOL to MBA fallback is configured.

portControl	*enum: forceAuth* | *controlled* | *forceUnauth*	Controlled – enable 802.1X for the interface. ForceAuth – disable 802.1X and put the interface into authorized state. ForceUnauth – disable 802.1X and put the interface into unauthorized state.

2.388.3 Dot1xVlanHostStats

eapol	*integer*	Count of EAPOL supplicants in VLAN.
mba	*integer*	Count of MBA supplicants in VLAN.

2.389 show dot1x supplicant [...]

interfaces	*table(Interface name)* = *Dot1xSupplicant* see 2.389.1	A mapping between interfaces and 802.1X supplicant interface information.

2.389.1 Dot1xSupplicant

authenticatorMac	*MAC address*	802.1X authenticator MAC address for the interface.
eapMethod	*enum: unset* | *pwd* | *tls* | *fast*	unset – EAP method is currently unset.fast – EAP method in use is EAP FAST.tls – EAP method in use is TLS.pwd – EAP method in use is EAP PWD.
eapTlsCipher **	*string*	EAP TLS cipher. **Since: 4.27.1
eapTlsVersion **	*string*	EAP TLS version. **Since: 4.27.1
[fipsMode] **	*boolean*	FIPS restrictions enabled. **Since: 4.28.1
identity	*string*	EAP identity in use on this interface.
sslProfileName **	*string*	SSL profile name. **Since: 4.26.0
status	*enum: success* | *unused* | *down* | *failed* | *connecting*	unused – 802.1X supplicant is uninitializeddown – 802.1X supplicant is down.connecting – 802.1X supplicant is connecting.failed – 802.1X supplicant has failed.success – 802.1X supplicant has succeeded.
supplicantMac	*MAC address*	802.1X supplicant MAC address for the interface.

2.390 show dot1x vlan assignment group [...]

vlanGroupNameDict	*table(string)* = *string*	A mapping of group name to that group's VLANs.

2.391 show drop notification trim

enabled	*boolean*	Packet Trimming is enabled.
rewriteDscp	*integer*	Rewrite DSCP value.

2.392 show drop notification trim counters

slices	*table(string) = PacketTrimming.Cli.PacketTrimmingCountersModel* see 2.392.1	Mapping from linecard to associated mirror-on-drop pool statistics.

2.392.1 PacketTrimming.Cli.PacketTrimmingCountersModel

itmCounters	*table(string) = PacketTrimming.Cli.ItmCountersModel* see 2.392.1.1	Mapping from pool resource to pool statistics.
slice	*string*	Slice name.

2.392.1.1 PacketTrimming.Cli.ItmCountersModel

droppedPackets	*integer*	Packets not admitted due to pool being full.
highWaterMarks	*integer*	High watermarks of the pool.
occupancy	*integer*	Pool occupancy.
sampledPackets	*integer*	Packets admitted to the pool.
xpe	*string*	MMU Ingress XPE key.

2.393 show dynamic prefix-list [...]

vrfs	*table(string) = DynamicPrefixLists* see 2.393.1	Dynamic prefix list information for VRFs.

2.393.1 DynamicPrefixLists

dynamicPrefixLists	*table(string) = DynamicPrefixListModel* see 2.393.1.1	Table of dynamic prefix lists by name.

2.393.1.1 DynamicPrefixListModel

[bgpSession] **	*BgpSession* see 2.393.1.1.1	BGP session activated dynamic prefix list information. **Since: 4.30.1
[contributingRoutes] **	*list of DynamicPrefixListContributingRoutes* see 2.393.1.1.2	Capped list of contributing routes (a sample of contributing routes), current cap is 10. **Since: 4.21.0
[ipv4PrefixList]	*string*	IPv4 prefix list name.
[ipv6PrefixList]	*string*	IPv6 prefix list name.
[matchProtocol] **	*string*	Source protocol. **Since: 4.35.2
[matchRcfFunction] **	*string*	Match RCF expression name. **Since: 4.30.2
[matchRouteMap]	*string*	Match route map name.
[matchVrf] **	*string*	Match VRF name. **Since: 4.35.2
[numContributingRoutes] **	*integer*	Number of contributing routes. **Since: 4.21.0
state	*enum: inactive | notApplicableToRoutingInstance | active*	State of the dynamic prefix list.

2.393.1.1.1 BgpSession

peers	*table(string) = PeerSpecification* see 2.393.1.1.1.1	Peer specifications.

2.393.1.1.1.1 PeerSpecification

originatePeerAddress	*boolean*	Originate peer-address.
sessionState	*enum: OpenConfirm | Active | Established | Connect | Unknown | OpenSent | Idle*	The state of BGP session.

2.393.1.1.2 DynamicPrefixListContributingRoutes

`prefix`	*IP address prefix*	Route Prefix.

2.394 show e-tree vlan

`vlans`	*table(numeric string) = EtreeRoleModel* see 2.394.1	A VLAN's E-Tree role, keyed by VLAN ID.

2.394.1 EtreeRoleModel

`etreeRoleLeaf`	*boolean*	True if this VLAN has the E-Tree leaf role.
`[remoteLeafInstallMode]` **	*enum: dontinstall | installdrop*	How to treat remote leaf hosts in this VLAN. **Since: 4.33.0

2.395 show environment power

[details]	*Details* see 2.395.1	Details about the power supplies.
powerSupplies	*table(string) = PowerSupply* see 2.395.2	Power supplies status.

2.395.1 Details

pollInterval	*floating point number*	Polling interval (seconds).

2.395.2 PowerSupply

[blackBoxLog] **	*string*	Debugging log. **Since: 4.21.0
[capacity]	*floating point number*	Capacity (watts).
[details]	*boolean*	Details available.
[dominant] **	*boolean*	dominant power supply. **Since: 4.27.2
fans	*table(string) = Fan* see 2.395.2.1	Power supply fans.
[inputBCurrent] **	*floating point number*	Input B current (amps). **Since: 4.22.1
[inputBVoltage] **	*floating point number*	Input B voltage (volts). **Since: 4.22.1
[inputCurrent]	*floating point number*	Input current (amps).
[inputPower]	*floating point number*	Input power (watts).
[inputVoltage]	*floating point number*	Input voltage (volts).
[managed]	*boolean*	Power supply is managed.
[mfrId] **	*string*	Manufacturer ID of power supply. **Since: 4.18.0
[mfrModel] **	*string*	Manufacturer model of power supply. **Since: 4.18.0
[mfrRevision] **	*string*	Manufacturer revision of power supply. **Since: 4.18.0
modelName	*string*	Type of power supply.
[outputBCurrent] **	*floating point number*	Output B current (amps). **Since: 4.31.0
[outputBVoltage] **	*floating point number*	Output B voltage (volts). **Since: 4.31.0
[outputCurrent]	*floating point number*	Output current (amps).
[outputPower]	*floating point number*	Output power (watts).
[outputVoltage]	*floating point number*	Output voltage (volts).
[priFirmware] **	*string*	Primary firmware of power supply. **Since: 4.18.0
[secFirmware] **	*string*	Secondary firmware of power supply. **Since: 4.18.0
[specificInfo]	*string*	Power supply model-specific information.
[state]	*enum: unknown | offline | failed | ok | powerLoss*	State of the power supply.

`tempSensors`	*table(string) = TempSensor* see 2.395.2.2	Power supply temperature sensors.
`[uptime]` **	*floating point number*	Timestamp in UTC (in seconds) when the last change in PowerSupply's state occurred. **Since: 4.20.0

2.395.2.1 Fan

`speed`	*integer*	Fan speed (percentage).
`status`	*enum: unknownHwStatus* | *failed* | *ok*	Fan status.

2.395.2.2 TempSensor

`status`	*enum: failed* | *ok* | *unknownHwStatus* | *disabled* | *invalidReading*	Temp sensor status.
`[temperature]`	*floating point number*	Fan temperature (celsius).

2.396 show environment power detail

see 2.395

2.397 show environment power voltage

revision 2

cardSlots	*table(string) = FruSlot* see 2.397.1	A mapping of labels to card slots.
powerSupplySlots	*table(string) = FruSlot* see 2.397.1	A mapping of labels to power supply slots.
voltageSensors	*table(string) = VoltageSensor* see 2.397.1.3	A mapping of labels to voltage sensors.

2.397.1 FruSlot

[currentSensors] **	*table(string) = CurrentSensor* see 2.397.1.1	A mapping of labels to current sensors. **Since: 4.27.1
entPhysicalClass	*string*	Physical entity class of the slot.
label	*string*	Label of the slot.
pmbusDevices **	*table(string) = PmbusDevice* see 2.397.1.2	A mapping of lables to Pmbus devices. **Since: 4.35.2
voltageSensors	*table(string) = VoltageSensor* see 2.397.1.3	A mapping of labels to voltage sensors.

2.397.1.1 CurrentSensor

[current]	*floating point number*	Measured sensor current (amps).
[name]	*string*	The current sensor's hardware label.
status	*enum: unknownHwStatus | failed | ok | offline*	Current sensor status.

2.397.1.2 PmbusDevice

[cardName]	*string*	PMBus device's owning card.
chipType	*string*	PMBus device type.
name	*string*	PMBus device's hardware label.
pages	*table(numeric string) = PmbusDevicePage* see 2.397.1.2.1	A mapping of labels to Pmbus device pages.

2.397.1.2.1 PmbusDevicePage

[cardName]	*string*	Current device's owning card.
name	*string*	Current device's hardware label.
page	*integer*	Current device's current page.
[statusByte]	*integer*	STATUS_BYTE.
[statusCml]	*integer*	STATUS_CML.
[statusInput]	*integer*	STATUS_INPUT.
[statusIout]	*integer*	STATUS_IOUT.
[statusMfr]	*integer*	STATUS_MFR_SPECIFIC.

[statusMfr2]	*integer*	STATUS_MFR_SPECIFIC2.
[statusOther]	*integer*	STATUS_OTHER.
[statusTemp]	*integer*	STATUS_TEMPERATURE.
[statusVout]	*integer*	STATUS_VOUT.
[statusWord]	*integer*	STATUS_WORD.

2.397.1.3 VoltageSensor

[description]	*string*	Hardware label describing the voltage sensor.
[expectedVoltage]	*floating point number*	Expected sensor voltage (volts).
status	*enum: unknownHwStatus | failed | ok*	Voltage sensor status.
[voltage]	*floating point number*	Measured sensor voltage (volts).

2.398 show event-handler [...]

revision 2

eventHandlers	*table(string) = EventHandler* see 2.398.1	A mapping between a handler and hander information.

2.398.1 EventHandler

action	*string*	The action to take when a trigger occurs.
actionCount	*integer*	The number of actions that have occured.
actionKind **	*string*	Type of action to take when a trigger occurs. **Since: 4.22.1
asynchronous	*boolean*	Indicates if action is non-blocking.
builtinHandler	*boolean*	Indicates that this handler is built-in, not user configured.
builtinHandlerDisabled	*boolean*	Indicates that this built-in handler ismanually disabled by the user.
delay	*floating point number*	The configured event-handler delay in seconds.
detectionCount	*integer*	The number of trigger detections that have occured.
disabledManually **	*boolean*	Indicates that this handler is manually disabled. **Since: 4.35.2
eventSubhandlers **	*table(string) = EventSubhandler* see 2.398.1.1	A mapping between a subhandler for this handler and its status information. **Since: 4.22.1
hasSubhandlers **	*boolean*	The handler has per-source granularity. **Since: 4.22.1
[healthAction]	*string*	The health action to take when a trigger occurs.
[lastActionTime]	*floating point number*	UTC timestamp of last action.
[lastDetectionTime]	*floating point number*	UTC timestamp of last trigger detection.
[lastTriggerTime]	*floating point number*	UTC timestamp of last trigger activation.
maxActionDuration	*floating point number*	The maximum time in seconds the action is allowed to execute before being aborted.
maxRepeatActionCount **	*integer*	Maximum actions permitted in the repeat interval window. **Since: 4.30.0
pollingCount	*integer*	The number of times the event-handler has been polled.
repeatInterval **	*floating point number*	The period in seconds for which repeating events are ignored. **Since: 4.24.2
runUponConfig **	*boolean*	Indicates if action is to carried out when this handler is configured. **Since: 4.26.0
terminateActionOnTimeout **	*boolean*	Indicates that the action should be terminated if it times out. **Since: 4.33.1

thresholdCount	*integer*	The number of events that must occur within the threshold window.
thresholdWindow	*integer*	The window in seconds where the number of events must match or exceed the threshold count.
[trigger]	*Trigger* see 2.398.1.2	The condition that causes a trigger.
triggerCount	*integer*	The number of triggers that have occured.

2.398.1.1 EventSubhandler

actionCount	*integer*	The number of actions that have occured.
detectionCount	*integer*	The number of trigger detections that have occured.
[lastActionTime]	*floating point number*	UTC timestamp of last action.
[lastDetectionTime]	*floating point number*	UTC timetamp of last trigger detection.
[lastTriggerTime]	*floating point number*	UTC timestamp of last trigger activation.
pollingCount	*integer*	The number of times the event-handler has been polled.
triggerCount	*integer*	The number of triggers that have occured.

2.398.1.2 Trigger

[onCounters]	*OnCounters* see 2.398.1.2.1	Trigger on counters.
[onCustomCondition] **	*onCustomCondition* see 2.398.1.2.5	Trigger on Custom Condition. **Since: 4.33.0
[onIntf]	*OnIntf* see 2.398.1.2.2	Trigger on interface.
[onLogging]	*OnLogging* see 2.398.1.2.3	Trigger on logging.
[onMaintenance]	*OnMaintenance* see 2.398.1.2.4	Trigger on maintenance.
triggerType	*enum: onCounters* | *onCustomCondition* | *onLogging* | *vmTracerVm* | *onStartupConfig* | *onIntf* | *onMaintenance* | *onBoot*	Configured event trigger condition.

2.398.1.2.1 OnCounters

condition	*string*	The counter condition expression.
pollInterval	*floating point number*	The counter polling interval in seconds.

2.398.1.2.2 OnIntf

interface	*list of Interface name*	List of monitored interfaces.
onChangeOf	*list of string*	Action is triggered upon these changes to the interface.

2.398.1.2.3 OnLogging

logRegex	*string*	Regular expression to use for searching log messages.
pollInterval	*floating point number*	The poll interval in seconds.

2.398.1.2.4 OnMaintenance

[bgp]	*Bgp* see 2.398.1.2.4.1	BGP peer whose maintenance causes a trigger.
[interface]	*interface name*	Name of interface.
onMaintenanceType	*enum: intf | unit | bgp*	The type of maintenance interface.
onMode	*enum: exit | enter*	Maintenance operation that causes a trigger.
onStage	*enum: all | beforeLinkdown | afterMlag | begin | beforeRatemon | beforeBgp | beforeMlag | end | afterRatemon | afterLinkdown | afterBgp*	Trigger condition occurs on maintenance stage.
[unit]	*string*	The unit whose maintenance causes a trigger.

2.398.1.2.4.1 Bgp

[groupName]	*string*	Name of peer group.
[ip4Neighbor]	*IPv4 address*	Neighbor address.
[ip6Neighbor]	*IPv6 address*	Neighbor address.
[vrfName]	*string*	Configured BGP VRF.

2.398.1.2.5 onCustomCondition

pollInterval	*floating point number*	The poll interval in seconds.
scriptTrigger	*string*	Multi-line script to evaluate.

2.399 show event-handler trigger counters [...]

[eventHandlerTrigger-CounterSources]	*list of string*	The list of counter sources supported by the on-counters event handler.
[eventHandlerTrigger-Counters]	*table(string) = EventHandlerTriggerCounters* see 2.399.1	A mapping of counter sources to counters.

2.399.1 EventHandlerTriggerCounters

counters	*list of string*	The list of counters supported by this on-counters event handler counter source.

2.400 show event-monitor backup status

backupTotal	*integer*	Total count of all backup files.
bufferSize	*integer*	Configured Quicktrace buffer size.
maxSize	*integer*	Maximum number of backup files.
tableStatuses	*table(string) = TableBackupStatus* see 2.400.1	Map an event name to its backup status.

2.400.1 TableBackupStatus

backupEnabled	*string*	Backup files enabled/disabled for this event.
enabled	*string*	Event monitoring enabled/disabled for this event.
event	*string*	Event name.
fileCount	*integer*	Current number of backup files.
path	*string*	Backup path for the event.

2.401 show event-monitor lacp [...]

eventMonReasons	*list of LacpEventMonReasonDetails* see 2.401.1	LACP event monitor reason.

2.401.1 LacpEventMonReasonDetails

lag	*interface name*	Port channel name.
member	*interface name*	Port channel member interface name.
reason	*string*	Reason for the port channel member state transition.
state	*string*	Port Channel member state.
time	*floating point number*	UTC timestamp of the state transition.

2.402 show event-monitor row-limit [...]

events	*table(string) = TableRowLimit* see 2.402.1	Map an event name to its row limit status.

2.402.1 TableRowLimit

limitedCol	*string*	Name of the row limited column.
rowLimit	*integer*	Row limit per unique value in limited column.

2.403 show event-monitor status [...]

`events`	*table(string) = TableStatus* see 2.403.1	Map an event name to its table status.
`[totalCurSize]`	*integer*	Sum of current table sizes.
`[totalMaxSize]`	*integer*	Sum of max table sizes.

2.403.1 TableStatus

`enabled`	*boolean*	Event monitoring enabled/disabled for this event.
`eventCount`	*integer*	Number of events stored in its table.
`maxTableSize`	*integer*	Maximum size of the event's table.
`tableSize`	*integer*	Current size of the event's table.

2.404 show extensions [...]

revision 2

extensionStoredDir **	*string*	The filesystem that extensions are actually stored in. **Since: 4.24.1
extensions	*table(string) = Extension* see 2.404.1	Maps filenames to extension details.
pastErrors **	*list of MemberStatusEntry* see 2.404.1.1	Global past errors encountered. **Since: 4.34.2

2.404.1 Extension

[affectedAgents] **	*list of string*	Agents that are affected by this extension in the sense that they need to be restarted for the extension to take effect (static info). **Since: 4.25.1
[agentsToRestart] **	*list of string*	Agents that are pending a restart to finalize the extension; will be reset after restart. **Since: 4.25.1
boot **	*boolean*	Install at boot. **Since: 4.29.2
[description]	*string*	Description to the extension.
error	*boolean*	Indicates that the extension is in an error state, for instance if the system believes the extension was installed but one or more of its packages got manually uninstalled.
[installedSize]	*integer*	Installed size (in bytes) of the extension.
[memberStatus] **	*MemberStatusEntry* see 2.404.1.1	Extension member status and error information. **Since: 4.34.2
[numPackages]	*integer*	How many packages are installed.
[packages]	*table(string) = PackageInfo* see 2.404.1.2	Info about the extension keyed by names of the extensions.
presence	*enum: present | absent*	Whether or not the extension is still present on the switch. An extension can be installed and then removed, which would cause it to remain installed and become absent.
[presenceDetail]	*string*	Contains an error string explaining the presence of the extension. For instance the extension may be corrupted or otherwise unusable, which would cause the system to consider the extension is absent because it cannot be used.
release	*string*	Release of the extension.
[signed] **	*boolean*	The extension has a valid signature. **Since: 4.24.0
[signedDetail] **	*string*	Contains an error string explaining why the extension is signed incorrectly. **Since: 4.24.0

status	*enum: notInstalled* | *installed* | *forceInstalled*	Whether the extension is installed.
[statusDetail]	*string*	Contains an error string explaining the status of the extensions. For instance the extension may have failed to be (un)installed on the system, and this string would contain additional information explaining why.
[summary]	*string*	Summary to this extension.
[vendor]	*string*	Vendor of this extension.
version	*string*	Version of the extension.

2.404.1.1 MemberStatusEntry

[errorDescription]	*string*	Error description.
status	*enum: uninstallExtensionFailed* | *bootExtensionFailed* | *createStatusFailed* | *copyExtensionFailed* | *invalid* | *restartAgentDone* | *recreateStatusFailed* | *restartAgentFailed* | *bootExtensionRemoveFailed* | *bootExtensionDone* | *installExtensionFailed*	Status of the extension operation on member.
updateTime	*string*	Last status update timestamp.
updateTimestamp **	*integer*	Last status update timestamp in epoch time. **Since: 4.35.2

2.404.1.2 PackageInfo

release	*string*	Release of this particular extension.
version	*string*	Version of this particular extension.

2.405 show fabric counters [...]

interfaces	*table(string) = FabricCells* see 2.405.1	Maps interface name to cell counters.

2.405.1 FabricCells

pollLastOccurred	*floating point number*	Time fabric counters were last polled in UTC.
rxCells	*integer*	Received cells.
txCells	*integer*	Transmitted cells.

2.406 show fabric counters detail [...]

interfaces	*table(string) = FabricDetail* see 2.406.1	Maps interface name to detailed information.

2.406.1 FabricDetail

crcErrorCells	*integer*	Cells received with CRC errors.
crcErrorCellsChanges	*integer*	Times CRC errors has changed.
crcErrorsLastOccurred	*floating point number*	Time CRC errors last occurred in UTC.
fecCorrectedBits	*integer*	FEC corrected bits.
fecCorrectedCodewords	*integer*	FEC corrected codewords.
fecCorrectedCodewordsLast-Occurred	*floating point number*	Time FEC corrected codewords last occurred in UTC.
fecCorrectedSymbols	*integer*	FEC corrected symbols.
fecUncorrectedCodewords	*integer*	FEC uncorrected codewords.
fecUncorrectedCodewords-LastOccurred	*floating point number*	Time FEC uncorrected codewords last occurred in UTC.
leakyBucketTokens	*integer*	Tokens in Leaky Bucket which monitors serdes health.
pollLastOccurred	*floating point number*	Time fabric counters were last polled in UTC.
rxCells	*integer*	Received cells.
rxControlCells	*integer*	Received control cells.
rxDataRate	*integer*	Receive data rate in Mbps.
txCells	*integer*	Transmitted cells.
txDataRate	*integer*	Transmit data rate in Mbps.

2.407 show fabric counters errors [...]

interfaces	*table(string) = FabricErrors* see 2.407.1	Maps interface name to error counters.

2.407.1 FabricErrors

crcErrorCells	*integer*	Cells received with CRC errors.
fecUncorrectedCodewords	*integer*	FEC uncorrected codewords.
pollLastOccurred	*floating point number*	Time fabric counters were last polled in UTC.

2.408 show fabric counters rates [...]

interfaces	*table(string) = FabricRates* see 2.408.1	Maps interface name to rate counters.

2.408.1 FabricRates

pollLastOccurred	*floating point number*	Time fabric counters were last polled in UTC.
rxDataRate	*integer*	Receive data rate in Mbps.
txDataRate	*integer*	Transmit data rate in Mbps.

2.409 show fabric peers [...]

devices	*table(string) = DeviceFabricConnectivityInfo* see 2.409.1	Maps device name to its fabric connectivity info.

2.409.1 DeviceFabricConnectivityInfo

deviceId	*integer*	ID for host device.
interfaces	*table(string) = InterfaceFabricConnectivityInfo* see 2.409.1.1	Maps interface name to its peer connectivity info.
memberId **	*integer*	Member ID for host device. **Since: 4.34.2
[podId] **	*integer*	Pod ID for host device. **Since: 4.34.2

2.409.1.1 InterfaceFabricConnectivityInfo

cableDelay **	*floating point number*	Signal delay for the fabric connection (ns). **Since: 4.36.0
peerDeviceId	*integer*	ID for the peer device.
peerDeviceName	*string*	Name of the peer device.
peerInterface	*string*	Peer interface name.
peerMemberId **	*integer*	Member ID for the peer device. **Since: 4.34.2
[peerPodId] **	*integer*	Pod ID for the peer device. **Since: 4.34.2

2.410 show feature-toggle [...]

toggleInfo	*table(string) = ArToggleEntry* see 2.410.1	Collection of feature toggles.

2.410.1 ArToggleEntry

default	*integer*	Is this toggle enabled by default.
enabled	*integer*	Is this toggle enabled.

2.411 show feature-toggle override status

name	*string*	Describes this status attribute.
status	*enum: OK | NA | ERROR*	Status of toggle override file parse.

2.412 show fib (ipv4 | ipv6) route limit suppressed [...]

revision 3

[routes]	*list of FibRouteLimitSuppressedRouteInfo* see 2.412.1	List of routes, corresponding protocols and eviction orders.

2.412.1 FibRouteLimitSuppressedRouteInfo

[evictionOrder]	*integer*	Route's eviction order.
protocol	*string*	Route protocol.
route	*string*	Route prefix.

2.413 show file digest HASHTYPE URL

[hashType]	*enum: md5 | sha512*	Hash name which is specified by the given flag.
[hashValue]	*string*	Hash value for the given file path.
path	*string*	File path for which this information is under verification.

2.414 show file information URL

[fileName]	*string*	File name if path is a local file else empty.
[fileType]	*enum: script | elf | pythonScript | swix | zip | swi*	File types are: elf: ELF binary swi: Arista software image with version in version field swix: Arista EOS extension zip: Zip archive data script: A script file pythonScript: A Python script file.
isDir	*boolean*	When this flag is set to True it signifiesthat the given path is a directory. All other fields are empty and not relevant when this flag is set.
[isEmpty]	*boolean*	A flag when set to True signifies that the given path is an empty file.
[isExecutable]	*boolean*	A flag when set to True signifies that the given file path is executable.
path	*string*	Path name for which this information is generated.
[version]	*string*	When fileType is swi this field is the Arista EOS version.

2.415 show file systems

`fileSystems`	*list of FileSystem* see 2.415.1	List of file systems.

2.415.1 FileSystem

`currentFs`	*boolean*	When set it signifies this file system is the current one.
`free`	*integer*	Free space in the file system in KB.
`fsType`	*enum: flash* | *system* | *snapshot* | *checkpoint* | *session* | *ssh* | *peer* | *simple* | *network* | *ssl* | *alert-base* | *extension*	file system type.
`[linuxFs]` **	*enum: vfat* | *ext4*	Actual filesystem type used on the physical medium. It will be omitted if there's no physical medium attached to the filesystem. **Since: 4.20.5
`permission`	*enum: rw* | *r* | *w*	File permissions of read-only, write-only and read-write.
`prefix`	*enum: http:* | *checkpoint:* | *scp:* | *certificate:* | *platform:* | *ftp:* | *ssh-key:* | *usb1:* | *usb2:* | *nvme0:* | *drive:* | *ssh-revoke-list:* | *sslkey:* | *snapshot:* | *file:* | *alert-base:* | *drive2:* | *simple:* | *tftp:* | *ssh-ca-key:* | *https:* | *session:* | *sftp:* | *sdcard:* | *ssh-auth-principals-cmd:* | *supervisor-peer:* | *system:* | *crash:* | *flash:* | *extension:* | *nvme1:* | *ssh-host-cert:*	file system prefix.
`size`	*integer*	Size of the file system in KB.

2.416 show firewall distributed instance session-table [...]

running	*boolean*	Is running.
softwareFlowTable	*boolean*	Software flow table is available.
trackers	*table(string) = TrackerModel* see 2.416.1	A mapping between tracker name and tracker.

2.416.1 TrackerModel

groups	*table(string) = GroupModel* see 2.416.1.1	A mapping bewteen group name and group.
numFlows	*integer*	Total number of flows.

2.416.1.1 GroupModel

flows	*list of SessionModel* see 2.416.1.1.1	List of flows.

2.416.1.1.1 SessionModel

[appService]	*string*	Name of service of the application.
[application]	*string*	Name of application.
bytesReceived	*integer*	Number of bytes received in forward direction.
[complete]	*integer*	The number of fully established flows. Meaning handshake complete for TCP, or bidirectional flow seen for other protocols.
exportedBytes	*integer*	Number of bytes exported to collector.
exportedPkts	*integer*	Number of packet exported to collector.
exportedTime	*floating point number*	Time last exported to collector.
[flowDetail]	*SessionDetailModel* see 2.416.1.1.1.2	Flow detailed information.
[fwAction]	*string*	Action by firewall.
[halfOpen]	*integer*	The number of half-open flows. Meaning handshake incomplete for TCP, or only one direction of flow seen for other protocols.
key	*FlowKeyModel* see 2.416.1.1.1.1	Flow key.
pktsReceived	*integer*	Number of packets received in forward direction.
[revBytesReceived]	*integer*	Number of bytes received in reverse direction.
[revPktsReceived]	*integer*	Number of packets received in reverse direction.
revSrcVtep	*IP address*	Source VTEP IP address for the reverse direction.
srcVtep	*IP address*	Source VTEP IP address.
startTime	*floating point number*	Flow start time.

2.416.1.1.1.1 FlowKeyModel

direction	*enum: right* | *left*	Combined flow key direction.
dstAddr	*IP address*	Destination IP address.
dstPort	*integer*	Destination port.
[ipProtocol]	*enum: ipProtoTcp* | *ipProtoOspf* | *ipProtoUdp* | *ipProtoIpv6Frag* | *ipProtoExperiment1* | *ipProtoIgmp* | *ipProtoIpv6NoNxt* | *ipProtoIpip6* | *ipProtoSctp* | *ipProtoIpv6HopByHop* | *ipProtoIsis* | *ipProtoGre* | *ipProtoIpip* | *ipProtoVrrp* | *ipProtoAh* | *ipProtoUnknown* | *ipProtoRsvp* | *ipProtoIpv6Opts* | *ipProtoL2tp* | *ipProtoEsp* | *ipProtoExperiment2* | *ipProtoIcmpv6* | *ipProtoIcmp* | *ipProtoPim* | *ipProtoIpv6Route*	IP protocol.
ipProtocolNumber	*integer*	IP protocol number.
sessionId	*integer*	Session ID.
srcAddr	*IP address*	Source IP address.
srcPort	*integer*	Source port.
vrfName	*string*	VRF name.

2.416.1.1.1.2 SessionDetailModel

[appCategory]	*string*	Name of category of the application.
[fwPolicyId]	*integer*	ID of the firewall policy that is applied.
[fwRuleId]	*integer*	ID of the firewall rule that is applied.
[haStatus]	*string*	High Availability status.
[kvFlags]	*integer*	Flags of the KV Container.
lastPktTime	*floating point number*	Last packet received time.
sessionState	*string*	Session state.
tcpFlags	*string*	Flow TCP flags.

2.417 show firewall distributed instance session-table archive [...]

flows	*list of MonitorSessionModel* see 2.417.1	List of Ipv4 flows.

2.417.1 MonitorSessionModel

bytesReceived	*integer*	Number of bytes received in forward direction.
[completeSessions]	*integer*	Number of established sessions.
dstFragmented	*boolean*	Destination packet is fragmented.
dstLastPktTime	*floating point number*	Time last packet was received from the destination.
dstStartTime	*floating point number*	Time first packet was received from the destination.
[halfOpenSessions]	*integer*	Number of half-open sessions.
isEphemeral	*boolean*	Ephemeral flow.
key	*FlowKeyModel* see 2.417.1.1	Flow key.
pktsReceived	*integer*	Number of packets received in forward direction.
[revBytesReceived]	*integer*	Number of bytes received in reverse direction.
[revPktsReceived]	*integer*	Number of packets received in reverse direction.
[revSrcGretepIp] **	*IP address*	Source GRE tunnel address in the reverse direction. **Since: 4.35.2
sessionId	*integer*	Session ID.
sessionState	*string*	Session state.
srcFragmented	*boolean*	Source packet is fragmented.
[srcGretepIp] **	*IP address*	Source GRE tunnel address. **Since: 4.35.2
srcLastPktTime	*floating point number*	Time last packet was received from the source.

2.417.1.1 FlowKeyModel

dstAddr	*IP address*	Destination IP address.
dstPort	*integer*	Destination port.
ipProtocolNumber	*integer*	IP protocol number.
srcAddr	*IP address*	Source IP address.
srcPort	*integer*	Source port.
startTime	*floating point number*	Time first packet was received from the source.
vrfName	*string*	VRF name.

2.418 show firewall distributed instance status

enforcementMode	*enum: monitor* | *enforcement*	Operational mode.
running	*boolean*	Firewall running status.

2.419 show firewall distributed interceptor counters

hbTxCounter	*integer*	Heartbeat packet transmissions.
hbTxErr	*integer*	Heartbeat packet transmission errors.
offloadReqFailed	*integer*	Failed offload requests.
offloadReqInstalled	*integer*	Installed offload requests.

2.420 show firewall distributed interceptor flow-table

numActiveRecords	*integer*	Number of active records.
records	*list of DfwOffloadClientIntercept-FlowTableValuesModel* see 2.420.1	List of flow records.

2.420.1 DfwOffloadClientInterceptFlowTableValuesModel

action	*enum: deny* | *allow*	Flow action.
bytesCount	*integer*	Bytes count.
dstIp	*IP address*	Destination IP.
dstPort	*integer*	Destination Port.
flowStartTime	*floating point number*	Flow start time.
packetsCount	*integer*	Packets count.
policy	*integer*	Applicable policy.
protocol	*integer*	Flow Protocol.
ruleId **	*integer*	Applicable ruleId. **Since: 4.33.1
srcIp	*IP address*	Source IP.
srcPort	*integer*	Source Port.
vni	*integer*	Flow VNI.
vrf **	*string*	VRF of local device. **Since: 4.33.2

2.421 show firewall distributed interceptor status

connectionStatus	*table(string) = DfwOffloadClientStatus* see 2.421.1	Firewall status list.
offloadReady **	*boolean*	Offload Hardware status. **Since: 4.33.1
running **	*boolean*	Client running status. **Since: 4.33.1

2.421.1 DfwOffloadClientStatus

address	*string*	Firewall IP address.
connStatus	*string*	Firewall connection status.
port	*integer*	Firewall port.
threadId	*integer*	sfe threadId of the connection.

2.422 show firewall distributed offload requests [...]

interceptors	*table(IPv4 or IPv6 address) = DfwOffloadServer.Cli.-FlowOffloadRequestList* see 2.422.1	Flow offload reqests per interceptor.

2.422.1 DfwOffloadServer.Cli.FlowOffloadRequestList

flowOffloadRequests	*list of DfwOffloadServer.-Cli.FlowOffloadRequest* see 2.422.1.1	List of flow offload reqests.

2.422.1.1 DfwOffloadServer.Cli.FlowOffloadRequest

action	*enum: reject | deny | unprovision | allow*	Policy action.
destinationIp	*IP address*	Destination IP address.
destinationPort	*integer*	Destination port.
ipProtocol	*integer*	IP Protocol.
policyId	*integer*	Policy ID.
priority	*integer*	Offload request priority.
sourceIp	*IP address*	Source IP address.
sourcePort	*integer*	Source port.
startTime	*floating point number*	Seconds from epoch.
vni	*integer*	VNI.

2.423 show firewall distributed offload status

active	*boolean*	Server is active.
clientStatus	*table(IPv4 or IPv6 address) = DfwOffloadServer.Cli.-ClientStatus* see 2.423.1	Status of client connections.
[detail]	*string*	Detail of listening status.
listening	*boolean*	Server is listening for clients.
[serverPort]	*integer*	Port that server is listening on.

2.423.1 DfwOffloadServer.Cli.ClientStatus

connectionStatus	*string*	Status of connection.
detail	*string*	Detail of connection status.

port	*integer*	Source port that clients are connecting from.

2.424 show firewall distributed service-leaf redundancy

revision 2

clusters	*table(string) = DfwServiceClusterRedundancy* see 2.424.1	A mapping from a cluster name to the cluster redundancy status.

2.424.1 DfwServiceClusterRedundancy

[cluster]	*string*	Cluster name.
enforcementMode **	*boolean*	Cluster mode. **Since: 4.35.2
layoutEntries	*table(string) = DfwServiceSwLayout* see 2.424.1.1	FW active and backup layout table indexed by entry ID.

2.424.1.1 DfwServiceSwLayout

[active]	*string*	Active Firewall.
[activeIntf]	*string*	Active Firewall interface.
[backup]	*string*	Backup Firewall.
[backupIntf]	*string*	Backup Firewall interface.

2.425 show firewall distributed service-leaf status

revision 2

clusters	*table(string) = DfwServiceClusterStatus* see 2.425.1	A mapping from a cluster name to the cluster status.

2.425.1 DfwServiceClusterStatus

[cluster]	*string*	Cluster name.
configured	*boolean*	Service leaf is active.
enforcementMode **	*boolean*	Cluster mode. **Since: 4.35.2
firewalls	*table(string) = DfwServiceFwStatus* see 2.425.1.1	A mapping of firewall name to its status.
[flowSyncVlan]	*integer*	Flow Sync vlan.
[nexthopGroup]	*string*	Nexthop Group.
[redundancyMode]	*enum: activeActive | activeStandby*	Redundancy mode.
[selectionVlan]	*integer*	Firewall selection vlan.

[tepIp] **	*IP address*	TEP IP address of Firewall cluster. **Since: 4.35.2

2.425.1.1 DfwServiceFwStatus

[mlag]	*integer*	MLAG.
status	*enum: offline* | *online* | *notConfigured* | *maintenance* | *disabled*	Firewall status.

2.426 show flow telemetry ipfix counters

exporters	*list of IpfixExporterCounter* see 2.426.1	Counters for all exporters.
[receivedMessages]	*integer*	Number of IPFIX/sFlow/Postcard messages received.
[sentMessages]	*integer*	Number of flow information sent.

2.426.1 IpfixExporterCounter

exporterId	*IpfixExporterId* see 2.426.1.1	Exporter ID.
interpretFieldErrors	*integer*	Interpret data record field errors.
invalidFieldErrors	*integer*	Invalid data record field errors.
invalidFlowKeyErrors **	*integer*	Invalid flow key in data record errors. **Since: 4.23.1
invalidMsgHdrErrors	*integer*	Invalid message header errors.
invalidOtrErrors	*integer*	Invalid options template record errors.
invalidSetHdrErrors	*integer*	Invalid set header errors.
invalidSetIdErrors	*integer*	Invalid set ID errors.
invalidSetLenErrors	*integer*	Invalid set length errors.
invalidTrErrors	*integer*	Invalid template record errors.
receivedDrs	*integer*	Received IPFIX data records or sFlow/Postcard flow samples.
receivedMessages	*integer*	Received messages.
receivedOdrs	*integer*	Received options data records.
receivedOtrs	*integer*	Received options template records.
receivedTrs	*integer*	Received template records.
unknownTidErrors	*integer*	Unknown template ID errors.
unsupportedOdrErrors	*integer*	Unsupported options data record errors.

2.426.1.1 IpfixExporterId

address	*IP address*	Exporter IP address.
observationDomainId	*integer*	Observation domain ID.
protocol	*enum: greent | ipfix | sflow*	Exporter flow exporting protocol.
sourcePort	*integer*	Exporter source port number.

2.427 show flow telemetry ipfix flow-table

exporters	*list of IpfixExporterFlow* see 2.427.1	Flows for all exporters.

2.427.1 IpfixExporterFlow

exporterId	*IpfixExporterId* see 2.426.1.1	Exporter ID.
v4Flows	*list of IpfixFlow* see 2.427.1.1	IP flows for this exporter.

v6Flows	*list of IpfixFlow* see 2.427.1.1	IPv6 flows for this exporter.

2.427.1.1 IpfixFlow

flowData	*table(string) = string*	Mapping of Information Element name to value in Flow Data part.
flowKey	*table(string) = string*	Mapping of Information Element name to value in Flow Key part.
[intNodes] **	*list of IpfixIntNode* see 2.427.1.1.1	All Inband Telemetry path nodes for this flow. **Since: 4.24.0
lastUpdateTime	*integer*	UTC timestamp in nano second of the last hostname resolution.

2.427.1.1.1 IpfixIntNode

intIntervals	*list of IpfixIntInterval* see 2.427.1.1.1.1	All intervals for this Inband Telemetry path node.
nodeData	*table(string) = string*	Mapping of Information Element name to Information Element value for an Inband Telemetry path node.

2.427.1.1.1.1 IpfixIntInterval

intervalData	*table(string) = string*	Mapping of Information Element name to Information Element value for an interval in an Inband Telemetry path node.

2.428 show flow telemetry ipfix option-data

exporters	*list of IpfixExporterOptionData* see 2.428.1	Option data for all exporters.

2.428.1 IpfixExporterOptionData

exporterId	*IpfixExporterId* see 2.426.1.1	Exporter ID.
interfaces	*table(string) = string*	Interface ID to interface name mapping.
observationDomains	*table(string) = IpfixDataFields* see 2.428.1.1	Observation domain options data.
templates	*table(string) = IpfixDataFields* see 2.428.1.1	Template options data.
vrfs	*table(string) = string*	VRF ID to interface name mapping.

2.428.1.1 IpfixDataFields

fields	*table(string) = string*	Information Element name to value mapping.

2.429 show flow telemetry ipfix template

exporters	*list of IpfixExporterTemplate* see 2.429.1	Templates for all exporters.

2.429.1 IpfixExporterTemplate

exporterId	*IpfixExporterId* see 2.426.1.1	Exporter ID.
templateInfos	*list of IpfixTemplateInfo* see 2.429.1.1	Templates for this exporter.

2.429.1.1 IpfixTemplateInfo

fields	*list of IpfixTemplateField* see 2.429.1.1.1	List of fields.
scopeFields	*list of IpfixTemplateField* see 2.429.1.1.1	List of scope fields.
templateId	*integer*	Template ID.
timeReceived	*integer*	Unix epoch time when template was last received.

2.429.1.1.1 IpfixTemplateField

enterpriseNumber	*integer*	IANA Enterprise number.
informationElementId	*integer*	Information Element ID.
informationElementName	*string*	Information Element name.
length	*integer*	Field length.

2.430 show flow telemetry postcard counters

see 2.426

2.431 show flow telemetry postcard flow-table

see 2.427

2.432 show flow telemetry postcard option-data

see 2.428

2.433 show flow telemetry sflow counters

see 2.426

2.434 show flow telemetry sflow flow-table

see 2.427

2.435 show flow telemetry sflow option-data

see 2.428

2.436 show flow tracking (cpu-queue | sampled | hardware | mirror-on-drop | (telemetry inband) | (firewall distributed)) [...]

revision 2

[bgpElementsExported] **	*boolean*	BGP Export in SFT. **Since: 4.33.2
[enabledBy]	*string*	The command that enables flow tracking.
[encapTypes]	*list of EncapTypeModel* see 2.436.1	List of encapsulations.
[filterTypes] **	*list of FilterTypeModel* see 2.436.2	List of encapsulation filters. **Since: 4.31.1
[ftrTrafficGroups]	*table(string) = FtrTrafficTypeModel* see 2.436.4	Flow tracking traffic types.
ftrType	*enum: cpuQueue | none | hardware | inbandTelemetry | sampled | mirrorOnDrop | dfw*	Flow tracking type.
[packetBuffer] **	*PacketBufferModel* see 2.436.5	Packet buffer status. **Since: 4.31.2
running	*boolean*	Flow tracking is running.
[sampleLimit] **	*integer*	Maximum sample rate in packets per second per interface. **Since: 4.30.1
[sampleSize] **	*integer*	Number of bytes used when sampling. **Since: 4.33.0
[sftAgentCount] **	*integer*	Number of SFT Agent instances. **Since: 4.35.2
[standardFormatForCounters]	*boolean*	Flow tracking standard record format for counters.
[standardFormatForTimeStamps]	*boolean*	Flow tracking standard record format for timestamps.
trackers	*table(string) = FtModel* see 2.436.3	A mapping between tracker name and tracker.
[trapSuppressionDetails] **	*TrapSuppressionModel* see 2.436.6	Trap suppression status. **Since: 4.32.2

2.436.1 EncapTypeModel

encapType	*enum: encapIpv4 | encapNone | encapVxlan | encapIpv6 | encapRoCEv2 | encapMpls | encapGre*	Encapsulation.

2.436.2 FilterTypeModel

filterType	*filterRpf*	Encapsulation filters.

2.436.3 FtModel

active	*boolean*	Tracker is active.
activeEgressIntfs	*list of IntfModel* see 2.436.3.4	Active Egress Interfaces.
activeInterval	*integer*	Active interval in ms.
activeIntfs	*list of IntfModel* see 2.436.3.4	Active Ingress Interfaces.
[congestionInterval] **	*CongestionIntervalModel* see 2.436.3.1	Number of seconds of data to report. **Since: 4.33.0
[dampingTimeout] **	*integer*	Seconds to wait between reports. **Since: 4.33.0
[exportTriggers] **	*list of string*	Causes of exporter being used. **Since: 4.33.0
exporters	*table(string) = ExpModel* see 2.436.3.2	A mapping between exporter name and exporter.
groups	*table(string) = FgModel* see 2.436.3.3	Flow groups.
inactiveEgressIntfs	*list of IntfModel* see 2.436.3.4	Inactive Egress Interfaces.
inactiveIntfs	*list of IntfModel* see 2.436.3.4	Inactive Ingress Interfaces.
[inactiveReason]	*enum: trackerNotProcessed | maxTrackersLimit | trackerInactiveReason-Unknown*	Tracker inactive reason.
inactiveTimeout	*integer*	Inactive timeout in ms.
[monitoredCpuQueueStatus] **	*table(string) = MonitoredCpuQueueModel* see 2.436.3.5	CPU Queues that are being monitored. **Since: 4.34.0
[monitoredCpuQueues] **	*list of string*	CPU Queues that are being monitored. **Since: 4.33.0

2.436.3.1 CongestionIntervalModel

after	*integer*	Number of seconds of data after event to report.
before	*integer*	Number of seconds of data before event to report.

2.436.3.2 ExpModel

active	*boolean*	Exporter is ready for transmission.
collectors	*table(string) = CollectorModel* see 2.436.3.2.1	A mapping between collector address and collector port.
[dscpValue]	*integer*	DSCP value in IP header.
exportFormat	*ExpFormatModel* see 2.436.3.2.2	Export format information.
[inactiveReasons]	*table(string) = ExpReasonModel* see 2.436.3.2.3	A mapping between type of reason and list of reasons for inactive exporter.

localIntf	*interface name*	Local interface to be used for IPFIX source IP4/6 addr.
srcIp6Addr	*IPv6 address*	Local IPv6 address to be used for IPFIX source addr.
srcIpAddr	*IPv4 address*	Local IPv4 address to be used for IPFIX source addr.
[templateInterval]	*integer*	Template interval in ms.
[useSflowCollectorConfig]	*boolean*	Use the configured sFlow collectors.
[vrfName]	*string*	VRF name.

2.436.3.2.1 CollectorModel

active	*boolean*	Collector is ready for transmission.
[inactiveReason]	*enum: collectorInactiveReasonUnknown | collectorNotProcessed | maxCollectorsLimit*	Collector inactive reason.
port	*integer*	Collector port.

2.436.3.2.2 ExpFormatModel

[mtu]	*integer*	MTU of the export format.
name	*string*	Export format name.
[version]	*integer*	Version of the export format.

2.436.3.2.3 ExpReasonModel

expReasons	*list of ExpReason* see 2.436.3.2.3.1	List of reasons for inactive exporter.

2.436.3.2.3.1 ExpReason

expReason	*enum: invalidLocalIntf | exporterInactiveReasonUnknown | invalidVrf | waitingForUDPPort | invalidCollector | maxExportersLimit | exporterNotProcessed | invalidExportFormat*	Exporter inactive reason.

2.436.3.3 FgModel

[encapTypes]	*list of EncapTypeModel* see 2.436.1	List of encapsulations.
[expNames]	*table(string) = GroupExpModel* see 2.436.3.3.2	Exporters, keyed by exporter name.

[hwGroups]	*table(numeric string) = HwFgModel* see 2.436.3.3.3	Flow groups programmed in hardware, keyed by their sequence number.
[ip6AccessLists]	*table(numeric string) = AccessListModel* see 2.436.3.3.1	IPv6 ACLs, keyed by their sequence number.
[ipAccessLists]	*table(numeric string) = AccessListModel* see 2.436.3.3.1	IPv4 ACLs, keyed by their sequence number.
[mirroring]	*MirrorModel* see 2.436.3.3.4	Mirroring details.
[seqno]	*integer*	Flow group sequence number.

2.436.3.3.1 AccessListModel

aclName	*string*	Access list name.

2.436.3.3.2 GroupExpModel

expName	*string*	Exporter name.

2.436.3.3.3 HwFgModel

[active]	*boolean*	Hardware flow group is active.
hwFgName	*string*	Hardware flow group name.

2.436.3.3.4 MirrorModel

[initialCopy]	*integer*	Initial packets to be mirrored.
[mirrorInterval]	*integer*	Sampling interval for packets to be mirrored.
[mirrorSelectorAlgorithm]	*enum: random | sampleModeNone | fixed*	Mirror sampling algorithm.
sessionName	*string*	Mirror session name.

2.436.3.4 IntfModel

interface	*interface name*	Name of the interface.
[reason]	*string*	Reason for interface inactive.
[sampleMode] **	*enum: all | filtered*	Sampling mode for the interface. **Since: 4.31.0

2.436.3.5 MonitoredCpuQueueModel

cpuQueueName	*string*	cpu-queue name.
status	*enum: monitoredCpuQueueActive | monitoredCpuQueue-InactiveUnknown*	Monitored cpu-queue status.

2.436.4 FtrTrafficTypeModel

[egressHwOffloadStatus] **	*FtrHoStatusModel* see 2.436.4.1	Flow tracking egress hardware offload status. **Since: 4.31.1
[hwOffloadStatus]	*FtrHoStatusModel* see 2.436.4.1	Flow tracking ingress hardware offload status.
[sampleRate]	*integer*	Flow tracking sample every x packets.

2.436.4.1 FtrHoStatusModel

[inactiveReasons]	*list of HoInactiveReasonModel* see 2.436.4.1.1	List of hardware offload inactive reasons.
[status]	*enum: inactive* | *active* | *unconfigured*	Flow tracking hardware offload status.

2.436.4.1.1 HoInactiveReasonModel

inactiveReason	*enum: invalidTcamProfile* | *multiSftAgentInstances* | *counterFeatureDisabled*	Hardware offload inactive reason.

2.436.5 PacketBufferModel

[prob100]	*integer*	Configured percent probability of sampling dropped packets.
[prob25]	*integer*	Configured percent probability of sampling dropped packets.
[prob50]	*integer*	Configured percent probability of sampling dropped packets.
[prob75]	*integer*	Configured percent probability of sampling dropped packets.
[shaperBurst]	*integer*	Packet buffer drop shaper burst in packets.
[shaperRate]	*integer*	Packet buffer drop shaper rate in kbps.
status	*enum: enabled* | *insufficientBufferSpace* | *disabled*	Packet buffer hardware status.

2.436.6 TrapSuppressionModel

[active]	*boolean*	Trap Suppression operational value.
[reason]	*string*	Reason for inactive trap suppression.
[trapSuppression]	*boolean*	Trap suppression configured value.

2.437 show flow tracking (sampled | hardware | (firewall distributed) | (telemetry inband)) ipfix options-table [...]

trackers	*table(string) = TrackerOptTableModel* see 2.437.1	A mapping between tracker name and tracker options table.

2.437.1 TrackerOptTableModel

[tables]	*table(string) = OptTableModel* see 2.437.1.1	A mapping between table name and options table.
[trackerInfo]	*TrackerInfoModel* see 2.437.1.2	Tracker info options table.

2.437.1.1 OptTableModel

entries	*table(numeric string) = string*	A mapping between table entry ID and entry value.
scopeFields	*list of string*	List of options table scope fields.
templateId	*integer*	Options template ID.

2.437.1.2 TrackerInfoModel

activeInterval	*integer*	Flow active interval in seconds.
flowTrackingType	*enum: cpuQueue | none | hardware | inbandTelemetry | sampled | mirrorOnDrop | dfw*	Flow tracking type.
inactiveTimeout	*integer*	Flow inactive timeout in seconds.
instances **	*list of InstanceInfoModel* see 2.437.1.2.1	Instance ID and corresponding observation domain ID of all SftAgent instances. **Since: 4.35.2
observationDomain	*string*	Observation domain name.
observationDomainId	*integer*	Observation domain ID for the instance specified in the show command or instance 0 by default.
sampleRate	*integer*	Flow tracking sample every x packets.
selectorAlgorithm	*randomNofNSampling*	Flow selector algorithm.

2.437.1.2.1 InstanceInfoModel

instanceId	*integer*	Instance ID.
observationDomainId	*integer*	Observation domain ID.

2.438 show flow tracking (sampled | hardware | (firewall distributed) | (telemetry inband)) ipfix template [...]

trackers	*table(string) = TrackerTemplateModel* see 2.438.1	A mapping between tracker name and tracker templates.

2.438.1 TrackerTemplateModel

dataTemplates	*table(numeric string) = TemplateModel* see 2.438.1.1	A mapping between template ID and data template.
optionsTemplates	*table(numeric string) = TemplateModel* see 2.438.1.1	A mapping between template ID and options template.

2.438.1.1 TemplateModel

fields	*list of TemplateEntryModel* see 2.438.1.1.1	Ordered list of template fields.
[groups] **	*list of string*	List of flow groups using the template. **Since: 4.28.1
name	*string*	Template name.
[scopeFields]	*list of TemplateEntryModel* see 2.438.1.1.1	Ordered list of template scope fields.
templateId	*integer*	Template ID.

2.438.1.1.1 TemplateEntryModel

[entNum] **	*integer*	Ipfix Enterprise Number. **Since: 4.32.1
[enterpriseIe]	*boolean*	IPFIX template filed is enterprise IE.

`fieldId`	*enum: flowIdleTimeout* | *aristaDpsPathLossRate* | *mplsLabelStackSection10* | *flowActiveTimeout* | *srcIpv6PrefixLen* | *mplsLabelStackSection8* | *samplingSize* | *inbandTelemetryNode-EgressQueueId* | *inbandTelemetryNode-AverageLatency* | *dstVlan* | *aristaBscanTagControl* | *inbandTelemetryPath-NumberOfBytes* | *srcIpPrefixLen* | *bgpSrcAs* | *dstIp* | *flowLabelIpv6* | *opaqueOctets* | *inbandTelemetryNode-MinimumLatency* | *inbandTelemetryInterval-NumberOfPackets* | *aristaBscanFlowGroupId* | *forwardingStatus* | *byteCount* | *inband-TelemetryNodeIngressPort* | *dstL4Port* | *ingressInterfaceName* | *tunnelEncap* | *applicationId* | *innerIpProtocol* | *ip6NextHop* | *inband-TelemetryNodeEgressPort* | *srcMac* | *srcIntf* | *inbandTelemetryLastPacket-Congestion* | *dot1qVlanId* | *dstIpPrefixLen* | *inbandTelemetryTTL* | *flowTrackingType* | *inbandTelemetryNode-MaximumLatency* | *dstIpv6PrefixLen* | *mplsLabelStackSection6* | *ipNextHop* | *flowEndSeconds* | *layer2SegmentId* | *paddingOctets* | *mplsLabelStackSection9* | *egressVrfId* | *inbandTelemetryDeviceId* | *inbandTelemetryNode-Congestion* | *srcIp* | *srcL4Port* | *inbandTelemetryLastPacket-Latency* | *rocev2AckPacketCount* | *vrfId* | *securityRuleId* | *ingressPhysicalInterface* | *mplsTopLabelStackSection* | *ingressInterfaceType* | *aristaDpsPathLatency* | *flowEndReason* | *innerDstIp6* |	IPFIX template field ID.

fieldLen	*integer*	IPFIX template field length (in bytes).
fieldType	*string*	IPFIX template field data type.

2.439 show flow tracking cpu-queue counters

cpuQueueCounters	*list of CpuQueueCountersModel* see 2.439.1	Counters for each CPU queue.

2.439.1 CpuQueueCountersModel

congestionEvents	*integer*	Number of congestion events for the cpu-queue.
cpuQueueId	*integer*	Identifier of the the CPU queue.
cpuQueueName	*string*	Possibly truncated CPU queue name, empty if not known.
sampledPackets	*integer*	Number of sampled packets for the CPU queue.

2.440 show flow tracking hardware counters [...]

[activeFlows]	*integer*	Cumulative active flow count.
[clearTime]	*floating point number*	UTC time when total counters were last cleared.
[expiredFlows]	*integer*	Cumulative expired flow count.
[flows]	*integer*	Cumulative flow count.
[ipfixExportShaping-Supported] **	*boolean*	Ipfix export shaping is supported. **Since: 4.35.2
ipfixFlowExportRates **	*table(numeric string) = integer*	A mapping of time interval to flows exported per second. **Since: 4.35.2
[packets]	*integer*	Cumulative count of packets.
running	*boolean*	Flow tracking agent is running.
softwareFlowTable **	*boolean*	Software flow table is available. **Since: 4.23.2
trackers	*table(string) = TrackerCounters* see 2.440.1	A mapping of tracker name to counters.

2.440.1 TrackerCounters

[activeFlows]	*integer*	Number of active flows.
[clearTime]	*floating point number*	UTC time when counters were last cleared.
[expiredFlows]	*integer*	Cumulative expired flow count.
exporters	*table(string) = ExporterCounters* see 2.440.1.1	A mapping of exporter name to counters.
flowGroups	*table(string) = FlowGroupCounters* see 2.440.1.2	A mapping of flow group name to counters.
[flows]	*integer*	Cumulative flow count.
[packets]	*integer*	Cumulative count of packets.

2.440.1.1 ExporterCounters

[clearTime]	*floating point number*	UTC time when counters were last cleared.
collectors	*list of CollectorCounters* see 2.440.1.1.1	A list of per-collector counters.
exporterType	*ipfix*	Exporter type.

2.440.1.1.1 CollectorCounters

addrAndPort	*IpGenericAddrAndPort* see 2.365.1.1.1.2	Collector IP address and port number.
[exportedFlowRecordTotal-Count]	*integer*	The total number of flow records sent to the collector.
[exportedMessageTotalCount]	*integer*	The total number of messages sent to the collector.
[exportedOctetTotalCount]	*integer*	The total number of bytes sent to the collector.

lastUpdates	*CollectorTimestamp* see 2.440.1.1.1.3	UTC time of last events.
sets	*table(numeric string) = CollectorSetCounters* see 2.440.1.1.1.1	A mapping of IPFIX template ID (set ID) to per-set-id counters.
templates	*list of CollectorTemplateCounters* see 2.440.1.1.1.2	A list of per-template counters.

2.440.1.1.1.1 CollectorSetCounters

flowRecords	*integer*	Number of flow records sent to the collector.

2.440.1.1.1.2 CollectorTemplateCounters

templateType	*enum: template | optionsTemplate*	IPFIX template type.
templates	*integer*	Number of templates sent to the collector.

2.440.1.1.1.3 CollectorTimestamp

[dataRecord]	*floating point number*	UTC time of last exported data record.
[message]	*floating point number*	UTC time of last exported message.
[optionsData]	*floating point number*	UTC time of last exported options data record.
[template]	*floating point number*	UTC time of last exported template.

2.440.1.2 FlowGroupCounters

activeFlows	*integer*	Number of active flows.
expiredFlows	*integer*	Cumulative expired flow count.
flows	*integer*	Cumulative flow count.
packets	*integer*	Cumulative count of packets.

2.441 show flow tracking hardware flow-table [...]

running	*boolean*	Flow tracking is active.
softwareFlowTable **	*boolean*	Software flow table is available. **Since: 4.23.2
trackers	*table(string) = TrackerModel* see 2.441.1	A mapping between tracker name and tracker.

2.441.1 TrackerModel

groups	*table(string) = GroupModel* see 2.441.1.1	A mapping between hardware group name and group.
numFlows	*integer*	Total number of flows.

2.441.1.1 GroupModel

flows	*list of FlowModel* see 2.441.1.1.1	List of flows.

2.441.1.1.1 FlowModel

bytesReceived	*integer*	Number of bytes received.
[flowDetail]	*FlowDetailModel* see 2.441.1.1.1.1	Flow detailed information.
key	*FlowKeyModel* see 2.441.1.1.1.2	Flow key.
pktsReceived	*integer*	Number of packets received.
startTime	*floating point number*	Flow start time.

2.441.1.1.1.1 FlowDetailModel

dot1qVlanId	*integer*	Flow Dot1q VLAN ID.
[hwFgId] **	*integer*	Hardware flow group ID. **Since: 4.25.1
lastPktTime	*floating point number*	Last packet received time.
tcpFlags	*string*	Flow TCP flags.
[vlanId] **	*integer*	Flow ingress VLAN ID. **Since: 4.25.0

2.441.1.1.1.2 FlowKeyModel

dstAddr	*IP address*	Destination IP address.
dstPort	*integer*	Destination port.

[ipProtocol]	*enum: ipProtoTcp* | *ipProtoOspf* | *ipProtoUdp* | *ipProtoIpv6Frag* | *ipProtoExperiment1* | *ipProtoIgmp* | *ipProtoIpv6NoNxt* | *ipProtoIpip6* | *ipProtoSctp* | *ipProtoIpv6HopByHop* | *ipProtoIsis* | *ipProtoGre* | *ipProtoIpip* | *ipProtoVrrp* | *ipProtoAh* | *ipProtoUnknown* | *ipProtoRsvp* | *ipProtoIpv6Opts* | *ipProtoL2tp* | *ipProtoEsp* | *ipProtoExperiment2* | *ipProtoIcmpv6* | *ipProtoIcmp* | *ipProtoPim* | *ipProtoIpv6Route*	IP protocol.
ipProtocolNumber	*integer*	IP protocol number.
srcAddr	*IP address*	Source IP address.
srcPort	*integer*	Source port.
vrfName	*string*	VRF name.

2.442 show flow tracking hardware flow-table [...]_1

running	*boolean*	Flow tracking is active.
softwareFlowTable	*boolean*	Software flow table is available.
trackers	*table(string) = TrackerModel* see 2.442.1	A mapping between tracker name and tracker.

2.442.1 TrackerModel

groups	*table(string) = GroupModel* see 2.442.1.1	A mapping bewteen group name and group.
numFlows	*integer*	Total number of flows.

2.442.1.1 GroupModel

flows	*list of FlowModel* see 2.442.1.1.1	List of flows.

2.442.1.1.1 FlowModel

[appService] **	*string*	Name of service of the application. **Since: 4.28.1
[application] **	*string*	Name of application. **Since: 4.28.1
bytesReceived	*integer*	Number of bytes received in forward direction.
[complete] **	*integer*	The number of fully established flows. Meaning handshake complete for TCP, or bidirectional flow seen for other protocols. **Since: 4.33.1
[flowDetail]	*FlowDetailModel* see 2.442.1.1.1.1	Flow detailed information.
[fwAction] **	*string*	Action by firewall. **Since: 4.34.0
[halfOpen] **	*integer*	The number of half-open flows. Meaning handshake incomplete for TCP, or only one direction of flow seen for other protocols. **Since: 4.33.1
key	*FlowKeyModel* see 2.442.1.1.1.2	Flow key.
pktsReceived	*integer*	Number of packets received in forward direction.
[revBytesReceived] **	*integer*	Number of bytes received in reverse direction. **Since: 4.33.1
[revPktsReceived] **	*integer*	Number of packets received in reverse direction. **Since: 4.33.1
[revSrcVtep] **	*IP address*	Source VTEP IP address for the reverse direction. **Since: 4.34.0

`[srcVtep]` **	*IP address*	Source VTEP IP address. **Since: 4.34.0
`startTime`	*floating point number*	Flow start time.

2.442.1.1.1.1 FlowDetailModel

`[appCategory]` **	*string*	Name of category of the application. **Since: 4.28.1
`[avtName]` **	*string*	Name of AVT profile. **Since: 4.28.1
`[dpsPathLatency]` **	*floating point number*	Latency of DPS path in msecs. **Since: 4.30.2
`[dpsPathLossRate]` **	*floating point number*	Loss in DPS path in percentage. **Since: 4.30.2
`[dpsPathName]` **	*string*	Name of a DPS path. **Since: 4.28.1
`[dpsSourceDevice]` **	*boolean*	Device is the source device selecting the DPS path to destination. **Since: 4.30.2
`egressIntf` **	*string*	Flow egress interface. **Since: 4.25.2
`[fwPolicyId]` **	*integer*	ID of the firewall policy that is applied. **Since: 4.34.0
`[fwRuleId]` **	*integer*	ID of the firewall rule that is applied. **Since: 4.34.0
`[haStatus]` **	*string*	High Availability status. **Since: 4.34.0
`[ingressIntf]` **	*interface name*	Flow ingress interface. **Since: 4.25.2
`[kvFlags]` **	*integer*	Flags of the KV Container. **Since: 4.33.2
`lastPktTime`	*floating point number*	Last packet received time.
`[sessionState]` **	*string*	Session state. **Since: 4.34.0
`tcpFlags`	*string*	Flow TCP flags.

2.442.1.1.1.2 FlowKeyModel

`dstAddr`	*IP address*	Destination IP address.
`dstPort`	*integer*	Destination port.

[ipProtocol]	*enum: ipProtoTcp* | *ipProtoOspf* | *ipProtoUdp* | *ipProtoIpv6Frag* | *ipProtoExperiment1* | *ipProtoIgmp* | *ipProtoIpv6NoNxt* | *ipProtoIpip6* | *ipProtoSctp* | *ipProtoIpv6HopByHop* | *ipProtoIsis* | *ipProtoGre* | *ipProtoIpip* | *ipProtoVrrp* | *ipProtoAh* | *ipProtoUnknown* | *ipProtoRsvp* | *ipProtoIpv6Opts* | *ipProtoL2tp* | *ipProtoEsp* | *ipProtoExperiment2* | *ipProtoIcmpv6* | *ipProtoIcmp* | *ipProtoPim* | *ipProtoIpv6Route*	IP protocol.
ipProtocolNumber	*integer*	IP protocol number.
srcAddr	*IP address*	Source IP address.
srcPort	*integer*	Source port.
vrfName	*string*	VRF name.

2.443 show flow tracking hardware | (firewall distributed) counters [...]

see 2.440

2.444 show flow tracking mirror-on-drop counters [...]

running	*boolean*	Mirror-on-Drop flow tracking is active.
trackers	*table(string) = TrackerModel* see 2.444.1	A mapping between tracker name and tracker information.

2.444.1 TrackerModel

dropReasonCounters **	*table(Interface name) = DropReasonModel* see 2.444.1.2	A mapping between interface and drop reason counters. **Since: 4.30.1
exporters	*table(string) = ExporterModel* see 2.444.1.3	A dictionary of exporters.
groups	*table(string) = GroupModel* see 2.444.1.1	A mapping between group name and group.
intfs	*table(Interface name) = integer*	A mapping between ingress interface and flow count.
numFlows	*integer*	Total number of flows.

2.444.1.1 GroupModel

flows	*list of FlowModel* see 2.444.1.1.1	List of flows.

2.444.1.1.1 FlowModel

age	*integer*	Time in seconds since flow detection.
dropReason	*string*	Reason for drop.
dstAddr	*IP address*	Destination IP address.
dstPort	*integer*	Destination port.
emtStatus	*string*	Exact match entry programming status.
ingressIntf	*string*	Flow ingress interface.
[ipProtocol]	*enum: ipProtoTcp | ipProtoOspf | ipProtoUdp | ipProtoIpv6Frag | ipProtoExperiment1 | ipProtoIgmp | ipProtoIpv6NoNxt | ipProtoIpip6 | ipProtoSctp | ipProtoIpv6HopByHop | ipProtoIsis | ipProtoGre | ipProtoIpip | ipProtoVrrp | ipProtoAh | ipProtoUnknown | ipProtoRsvp | ipProtoIpv6Opts | ipProtoL2tp | ipProtoEsp | ipProtoExperiment2 | ipProtoIcmpv6 | ipProtoIcmp | ipProtoPim | ipProtoIpv6Route*	IP protocol.

ipProtocolNumber	*integer*	IP protocol number.
srcAddr	*IP address*	Source IP address.
srcPort	*integer*	Source port.

2.444.1.2 DropReasonModel

[dstPbmZeroDrop] **	*integer*	Destination port bitmap zero. **Since: 4.34.1
[hardwareError]	*integer*	Hardware error.
[ingressSourcePortFilter]	*integer*	Ingress source port filter.
[ingressSpanningTreeFilter] **	*integer*	Ingress spanning tree filter. **Since: 4.31.2
[ipForwardingLookupMiss]	*integer*	IP forwarding lookup miss.
[ipForwardingLookupMiss-PostMplsDecap]	*integer*	IP forwarding lookup miss after MPLS decap.
[ipMissingArp]	*integer*	ARP unresolved.
[ipMissingArpPostMplsDecap]	*integer*	ARP unresolved after MPLS decap.
[ipMissingRoute]	*integer*	IP missing route.
[ipMissingRoutePostMpls-Decap]	*integer*	IP missing route after MPLS decap.
[ipTtl01]	*integer*	IP TTL 0/1.
[ipTtl01PostMplsDecap]	*integer*	IP TTL 0/1 after MPLS decap.
[ipVersionError]	*integer*	IP version error.
[ipVersionErrorPostMpls-Decap]	*integer*	IP version error after MPLS decap.
[ipv4ChecksumError]	*integer*	IPv4 checksum error.
[ipv4ChecksumErrorPostMpls-Decap]	*integer*	IPv4 checksum error after MPLS decap.
[ipv6MulticastSource]	*integer*	IPv6 multicast source.
[ipv6MulticastSourcePost-MplsDecap]	*integer*	IPv6 multicast source after MPLS decap.
[ipv6Unspecified-Destination]	*integer*	IPv6 unspecified destination.
[ipv6Unspecified-DestinationPostMplsDecap]	*integer*	IPv6 unspecified destination after MPLS decap.
[mplsDisabled]	*integer*	MPLS disabled.
[mplsLabelLookupMiss]	*integer*	MPLS label lookup miss.
[mplsTtl01]	*integer*	MPLS TTL 0/1.
[mtuExceeded]	*integer*	MTU exceeded.
[noForwardingAction]	*integer*	No forwarding action.
[packetBufferEgrPortSp-SharedLimit] **	*integer*	Packet buffer egress port shared limit. **Since: 4.31.2
[packetBufferEgrQueue-SharedLimit] **	*integer*	Packet buffer egress queue shared limit. **Since: 4.31.2
[packetBufferEgrWred] **	*integer*	Packet buffer egress WRED. **Since: 4.31.2
[packetBufferGlobalRejects] **	*integer*	Packet buffer global reject. **Since: 4.31.2
[packetBufferIngressLimit] **	*integer*	Packet buffer ingress limit. **Since: 4.31.2

[packetBufferQueueError] **	*integer*	Packet buffer queue error. **Since: 4.31.2
[packetBufferSharedPool-Limit] **	*integer*	Packet buffer shared pool limit. **Since: 4.31.2
[packetBufferUnknown] **	*integer*	Packet buffer unknown. **Since: 4.31.2
[packetBufferVoqLatency] **	*integer*	Packet buffer VOQ latency. **Since: 4.31.2
[packetBufferVoqShared-Reject] **	*integer*	Packet buffer VOQ shared reject. **Since: 4.31.2
[packetBufferVoqWredReject] **	*integer*	Packet buffer VOQ WRED reject. **Since: 4.31.2
[packetBufferVsqShared-Reject] **	*integer*	Packet buffer VSQ shared reject. **Since: 4.31.2
[packetBufferVsqWredReject] **	*integer*	Packet buffer VSQ WRED reject. **Since: 4.31.2
[portNotVlanMember]	*integer*	Port not VLAN member.
[rpf]	*integer*	reverse path forwarding.
[saEqualsDa]	*integer*	Source address equals destination address.
[saMulticast]	*integer*	Source address is multicast.
[saNotFound]	*integer*	Source Address not found.
[unknownReason]	*integer*	Unkown reason.

2.444.1.3 ExporterModel

collectors	*table(string) = CollectorModel* see 2.444.1.3.1	A mapping between collector and its statistics.

2.444.1.3.1 CollectorModel

addrAndPort	*IpGenericAddrAndPort* see 2.365.1.1.1.2	Collector IP address and port number.
byteCount	*integer*	Total bytes sent.
packetCount	*integer*	Total packets sent.
startCount	*integer*	Total start reports sent.
stopCount	*integer*	Total stop reports sent.

2.445 show flow tracking mirror-on-drop counters drop-reason [...]

see 2.444

2.446 show flow tracking mirror-on-drop flow-table [...]

see 2.444

2.447 show flow tracking sampled counters [...]

[activeFlows] **	*integer*	Cumulative active flow count. **Since: 4.23.1
[clearTime] **	*floating point number*	UTC time when total counters were last cleared. **Since: 4.23.1
[expiredFlows] **	*integer*	Cumulative expired flow count. **Since: 4.23.1
[flows]	*integer*	Cumulative flow count.
ftrType **	*enum: cpuQueue | none | hardware | inbandTelemetry | sampled | mirrorOnDrop | dfw*	Flow tracker type. **Since: 4.24.1
[hardwareOffload] **	*HardwareOffloadCounters* see 2.447.1	Hardware flow group counters. **Since: 4.25.2
[instanceId] **	*integer*	Instance identifier. **Since: 4.34.2
[packets] **	*integer*	Cumulative count of sampled packets. **Since: 4.23.1
running	*boolean*	Flow tracking agent is running.
[sampleCounters] **	*SampleCounters* see 2.447.2	Sample counters. **Since: 4.25.2
trackers	*table(string) = TrackerCounters* see 2.447.3	A mapping of tracker name to counters.

2.447.1 HardwareOffloadCounters

[clearTime]	*floating point number*	UTC time when counters were last cleared.
[flowsActive]	*integer*	Number of active flows in hardware.
[flowsCreated]	*integer*	Number of flows created in hardware.
[flowsDeleted]	*integer*	Number of flows deleted from hardware.
[flowsPending]	*integer*	Number of flows pending to be created in hardware.
[hoLimitIpv4] **	*integer*	Maximum number of IPv4 flows to try to offload. **Since: 4.31.1
[hoLimitIpv6] **	*integer*	Maximum number of IPv6 flows to try to offload. **Since: 4.31.1
[pktsDiscarded]	*integer*	Number of packets discarded in CPU for hardware flows.
[pktsHardwareFailed]	*integer*	Number of packets that failed to create hardware flow.
[pktsHardwareMiss]	*integer*	Number of packets that didn't hit hardware flows.
[pktsReceived]	*integer*	Number of packets received for hardware flows.

2.447.2 SampleCounters

[discarded]	*integer*	Number of samples discared.
[hardwareReceived]	*integer*	Number of hardware samples.
[poolSize]	*integer*	Sample pool size.
received	*integer*	Number of samples received.

2.447.3 TrackerCounters

activeFlows	*integer*	Number of active flows.
[clearTime]	*floating point number*	UTC time when counters were last cleared.
expiredFlows	*integer*	Cumulative expired flow count.
exporters	*table(string) = ExporterCounters* see 2.447.3.1	A mapping of exporter name to counters.
flowGroups	*table(string) = FlowGroupCounters* see 2.447.3.2	A mapping of flow group name to counters.
flows	*integer*	Cumulative flow count.
packets	*integer*	Cumulative count of sampled packets.

2.447.3.1 ExporterCounters

[clearTime] **	*floating point number*	UTC time when counters were last cleared. **Since: 4.22.1
collectors	*list of CollectorCounters* see 2.447.3.1.1	A list of per-collector counters.
exporterType	*ipfix*	Exporter type.

2.447.3.1.1 CollectorCounters

addrAndPort	*IpGenericAddrAndPort* see 2.365.1.1.1.2	Collector IP address and port number.
exportedFlowRecordTotal-Count	*integer*	The total number of flow records sent to the collector.
exportedMessageTotalCount	*integer*	The total number of messages sent to the collector.
exportedOctetTotalCount	*integer*	The total number of bytes sent to the collector.
lastUpdates	*CollectorTimestamp* see 2.447.3.1.1.3	UTC time of last events.
sets	*table(numeric string) = CollectorSetCounters* see 2.447.3.1.1.1	A mapping of IPFIX template ID (set ID) to per-set-id counters.
templates	*list of CollectorTemplateCounters* see 2.447.3.1.1.2	A list of per-template counters.

2.447.3.1.1.1 CollectorSetCounters

flowRecords	*integer*	Number of flow records sent to the collector.

2.447.3.1.1.2 CollectorTemplateCounters

templateType	*enum: template | optionsTemplate*	IPFIX template type.
templates	*integer*	Number of templates sent to the collector.

2.447.3.1.1.3 CollectorTimestamp

[dataRecord]	*floating point number*	UTC time of last exported data record.
[message]	*floating point number*	UTC time of last exported message.
[optionsData]	*floating point number*	UTC time of last exported options data record.
[template]	*floating point number*	UTC time of last exported template.

2.447.3.2 FlowGroupCounters

activeFlows	*integer*	Number of active flows.
expiredFlows	*integer*	Cumulative expired flow count.
flows	*integer*	Cumulative flow count.
[hardwareOffload] **	*HardwareOffloadCounters* see 2.447.1	Hardware flow group counters. **Since: 4.25.2
packets	*integer*	Cumulative count of sampled packets.

2.448 show flow tracking sampled counters debug [...]

revision 2

ftrType	*enum: cpuQueue | none | hardware | inbandTelemetry | sampled | mirrorOnDrop | dfw*	Flow tracker type.
[instanceId] **	*integer*	Instance identifier. **Since: 4.34.2
[packetErrorCounters]	*PacketErrorCounter* see 2.448.1	Packet error counters debug.
running	*boolean*	Flow tracking agent is running.

2.448.1 PacketErrorCounter

flowTableLimit	*integer*	Number of packets dropped due to flow table limit.
ftInputQueueFull	*integer*	Number of packets dropped due to flow table manager input queue full.
fttSimReqQueueFull	*integer*	Number of packets dropped due to simulation request queue full.

fttSimRespQueueFull	*integer*	Number of packets dropped due to simulation response queue full.
kernelPktDrops **	*integer*	Number of packets dropped due to socket being full. **Since: 4.34.2
lastUpdatedTimeKernelPktDrops **	*floating point number*	UTC time when kernel drop counters were last incremented. **Since: 4.34.2
routeInfoQueueFull	*integer*	Number of times route information queue is full.

2.449 show flow tracking sampled counters interface errors [...]

[egressCounters]	*table(Interface name) = PerInterfaceFlowErrCounters* see 2.449.1	Egress counters per interface.
ftrType	*enum: cpuQueue | none | hardware | inbandTelemetry | sampled | mirrorOnDrop | dfw*	Flow tracker type.
[ingressCounters]	*table(Interface name) = PerInterfaceFlowErrCounters* see 2.449.1	Ingress counters per interface.
[instanceId] **	*integer*	Instance identifier. **Since: 4.34.2
running	*boolean*	Sampled flow tracking is active.

2.449.1 PerInterfaceFlowErrCounters

other	*integer*	Packets dropped for other reasons.
parseFail	*integer*	Packets that could not be parsed.
unknownProtocol	*integer*	Packets with unsuppored protocol type.

2.450 show flow tracking sampled flow-table [...]

Could also be an instance of:
IntTrackingModel 2.450.1.1.1.7

ftrType **	*enum: cpuQueue | none | hardware | inbandTelemetry | sampled | mirrorOnDrop | dfw*	Flow tracker type. **Since: 4.23.1
running	*boolean*	Sampled flow tracking is active.
trackers	*table(string) = TrackerModel* see 2.450.1	A mapping between tracker name and tracker.

2.450.1 TrackerModel

groups	*table(string) = GroupModel* see 2.450.1.1	A mapping bewteen group name and group.
numFlows	*integer*	Total number of flows.

2.450.1.1 GroupModel

flows	*list of FlowModel* see 2.450.1.1.1	List of flows.

2.450.1.1.1 FlowModel

bytesReceived	*integer*	Number of bytes received.
[flowDetail]	*FlowDetailModel* see 2.450.1.1.1.1	Flow detailed information.
key	*FlowKeyModel* see 2.450.1.1.1.7	Flow key.
pktsReceived	*integer*	Number of packets received.
startTime	*floating point number*	Flow start time.

2.450.1.1.1.1 FlowDetailModel

Could also be an instance of:
IntFlowDetailModel 2.450.1.1.1.4

bgpNextHopIp	*IP address*	BGP next hop IP address.
[dot1qCustomerVlanId] **	*integer*	IEEE 802.1Q inner tag VLAN ID. **Since: 4.27.0
[dot1qVlanId] **	*integer*	IEEE 802.1Q tag VLAN ID. **Since: 4.27.0
dstAs	*integer*	BGP destination AS.
dstEthAddr	*MAC address*	Flow destination MAC address.
dstPrefixLen	*integer*	Destination prefix length.
egressIntf	*string*	Flow egress interface.
egressVlanId	*integer*	Flow egress VLAN ID.
[flowLabel] **	*integer*	IPv6 flow label. **Since: 4.25.0

[hwBytesReceived] **	*integer*	Number of bytes received in hardware. **Since: 4.25.2
[hwPktsReceived] **	*integer*	Number of packets received in hardware. **Since: 4.25.2
ingressIntf	*interface name*	Flow ingress interface.
ingressVlanId **	*integer*	Flow ingress VLAN ID. **Since: 4.30.0
lastPktTime	*floating point number*	Last packet received time.
[mpls] **	*MplsFlowDetail* see 2.450.1.1.1.2	MPLS flow details. **Since: 4.26.2
nextHopIp	*IP address*	Next hop IP address.
[rocev2] **	*Rocev2FlowDetail* see 2.450.1.1.1.3	RoCEv2 flow details. **Since: 4.34.0
[sampledBytesReceived] **	*integer*	Number of sampled bytes received. **Since: 4.25.2
[sampledPktsReceived] **	*integer*	Number of sampled packets received. **Since: 4.25.2
srcAs	*integer*	BGP source AS.
srcEthAddr	*MAC address*	Flow source MAC address.
srcPrefixLen	*integer*	Source prefix length.
tcpFlags	*string*	Flow TCP flags.
tos	*integer*	TOS in IP header.
vni **	*string*	VXLAN Network Identifier. **Since: 4.23.1

2.450.1.1.1.2 MplsFlowDetail

[fec]	*IP address prefix*	Forwarding equivalence class assignment.
ingressLabelStack **	*list of integer*	Ingress MPLS label stack. **Since: 4.34.1
labelStack	*list of integer*	Egress MPLS label stack.
labelStackTruncated	*boolean*	The actual flow had labels beyond 'labelStack'.
[topLabel]	*integer*	Ingress MPLS top label.
[topLabelType]	*enum: ldp | pseudowire | isis-sr | vpn | teMidpt | bgp*	Control protocol that allocated 'topLabel'.

2.450.1.1.1.3 Rocev2FlowDetail

hwRocev2AckPktsReceived	*integer*	Number of RoCEv2 ACK packets received in hardware.
hwRocev2CnpPktsReceived	*integer*	Number of RoCEv2 CNP packets received in hardware.
hwRocev2NackPktsReceived	*integer*	Number of RoCEv2 NACK packets received in hardware.
hwRocev2OtherPktsReceived	*integer*	Number of RoCEv2 other packets received in hardware.
rocev2QueuePairDstList	*list of integer*	RoCEv2 Queue Pair (QP) destinations.
sampledRocev2AckPkts-Received	*integer*	Number of sampled RoCEv2 ACK packets received.

sampledRocev2CnpPkts-Received	*integer*	Number of sampled RoCEv2 CNP packets received.
sampledRocev2NackPkts-Received	*integer*	Number of sampled RoCEv2 NACK packets received.
sampledRocev2OtherPkts-Received	*integer*	Number of sampled RoCEv2 other packets received.

2.450.1.1.1.4 IntFlowDetailModel

bgpNextHopIp	*IP address*	BGP next hop IP address.
devicesInPath	*integer*	Devices in path.
devicesInformation	*list of IntFlowDetailNodeInfo* see 2.450.1.1.1.6	List of inband telemetry device information.
[dot1qCustomerVlanId] **	*integer*	IEEE 802.1Q inner tag VLAN ID. **Since: 4.27.0
[dot1qVlanId] **	*integer*	IEEE 802.1Q tag VLAN ID. **Since: 4.27.0
dstAs	*integer*	BGP destination AS.
dstEthAddr	*MAC address*	Flow destination MAC address.
dstPrefixLen	*integer*	Destination prefix length.
egressIntf	*string*	Flow egress interface.
egressVlanId	*integer*	Flow egress VLAN ID.
flowIntervalStats	*list of IntFlowDetailIntervalStats* see 2.450.1.1.1.5	List of inband telemetry interval statistics.
flowIntervals	*integer*	Flow intervals.
[flowLabel] **	*integer*	IPv6 flow label. **Since: 4.25.0
hopCountExceeded	*boolean*	Hop count exceeded.
[hwBytesReceived] **	*integer*	Number of bytes received in hardware. **Since: 4.25.2
[hwPktsReceived] **	*integer*	Number of packets received in hardware. **Since: 4.25.2
ingressIntf	*interface name*	Flow ingress interface.
ingressVlanId **	*integer*	Flow ingress VLAN ID. **Since: 4.30.0
lastPktTime	*floating point number*	Last packet received time.
[mpls] **	*MplsFlowDetail* see 2.450.1.1.1.2	MPLS flow details. **Since: 4.26.2
nextHopIp	*IP address*	Next hop IP address.
pathPackets	*integer*	Path packets.
pathTransistions	*integer*	Path transistions.
[rocev2] **	*Rocev2FlowDetail* see 2.450.1.1.1.3	RoCEv2 flow details. **Since: 4.34.0
[sampledBytesReceived] **	*integer*	Number of sampled bytes received. **Since: 4.25.2
[sampledPktsReceived] **	*integer*	Number of sampled packets received. **Since: 4.25.2
srcAs	*integer*	BGP source AS.
srcEthAddr	*MAC address*	Flow source MAC address.

srcPrefixLen	*integer*	Source prefix length.
tcpFlags	*string*	Flow TCP flags.
tos	*integer*	TOS in IP header.
vni	*string*	VXLAN Network Identifier.

2.450.1.1.1.5 IntFlowDetailIntervalStats

avgLatencies	*list of integer*	Average latency per device in path (ns).
congestions	*list of boolean*	Congestion per device in path.
maxLatencies	*list of integer*	Maximum latency per device in path (ns).
minLatencies	*list of integer*	Minimum latency per device in path (ns).
pkts	*integer*	Number of packets.
timestamp	*floating point number*	Interval start time.

2.450.1.1.1.6 IntFlowDetailNodeInfo

deviceId	*integer*	Device ID.
egressPortId	*integer*	Egress port ID.
egressQueueId	*integer*	Egress queue ID.
ingressPortId	*integer*	Ingress port.
lastPacketCongestion	*boolean*	Congestion detected in the last sampled packet.
lastPacketLatency	*integer*	Last packet latency (ns).
ttl	*integer*	Inband telemetry TTL (hop count).

2.450.1.1.1.7 FlowKeyModel

direction **	*enum: ingress* | *ingressAndEgress* | *egress*	Packet Direction. **Since: 4.29.0
dstAddr	*IP address*	Destination IP address.
dstPort	*integer*	Destination port.
[ipProtocol]	*enum: ipProtoTcp* | *ipProtoOspf* | *ipProtoUdp* | *ipProtoIpv6Frag* | *ipProtoExperiment1* | *ipProtoIgmp* | *ipProtoIpv6NoNxt* | *ipProtoIpip6* | *ipProtoSctp* | *ipProtoIpv6HopByHop* | *ipProtoIsis* | *ipProtoGre* | *ipProtoIpip* | *ipProtoVrrp* | *ipProtoAh* | *ipProtoUnknown* | *ipProtoRsvp* | *ipProtoIpv6Opts* | *ipProtoL2tp* | *ipProtoEsp* | *ipProtoExperiment2* | *ipProtoIcmpv6* | *ipProtoIcmp* | *ipProtoPim* | *ipProtoIpv6Route*	IP protocol.

ipProtocolNumber	*integer*	IP protocol number.
srcAddr	*IP address*	Source IP address.
srcPort	*integer*	Source port.
vlanId	*integer*	Flow VLAN ID.
vrfName	*string*	VRF name.
ftrType	*enum: cpuQueue | none | hardware | inbandTelemetry | sampled | mirrorOnDrop | dfw*	Flow tracker type.
running	*boolean*	Sampled flow tracking is active.
trackers	*table(string) = TrackerModel* see 2.450.1	A mapping between tracker name and tracker.

2.451 show flow tracking sampled flow-table hardware [...]

ftrType	*enum: cpuQueue | none | hardware | inbandTelemetry | sampled | mirrorOnDrop | dfw*	Flow tracker type.
running	*boolean*	Sampled flow tracking is active.
trackers	*table(string) = HoTrackerModel* see 2.451.1	A mapping between tracker name and tracker.

2.451.1 HoTrackerModel

groups	*table(string) = HoGroupModel* see 2.451.1.1	A mapping bewteen group name and group.
numFlows	*integer*	Total number of flows.

2.451.1.1 HoGroupModel

flows	*list of HoFlowEntryModel* see 2.451.1.1.1	List of flows.

2.451.1.1.1 HoFlowEntryModel

[egressIntf] **	*interface name*	Flow egress interface. **Since: 4.28.2
[flowDetail]	*HoFlowDetailModel* see 2.451.1.1.1.1	Hardware offload flow detailed information.
hwCreateTime	*floating point number*	Hardware offload flow status entry create time.
[ingressIntf]	*interface name*	Flow ingress interface.
key	*FlowKeyModel* see 2.450.1.1.1.7	Hardware offload flow Status key.
state	*enum: inProgress | outOfResources | hoFlowStateUnknown | inHardware*	Hardware offload flow state.

2.451.1.1.1.1 HoFlowDetailModel

[dstEthAddr]	*MAC address*	Flow destination MAC address.
hwUpdateTime	*floating point number*	Hardware offload flow status entry update time.
[srcEthAddr]	*MAC address*	Flow source MAC address.
[swCreateTime]	*floating point number*	Hardware offload flow config entry create time.

2.452 show flow tracking sampled flow-table hardware counters [...]

ftrType	*enum: cpuQueue | none | hardware | inbandTelemetry | sampled | mirrorOnDrop | dfw*	Flow tracker type.
running	*boolean*	Sampled flow tracking is active.
trackers	*table(string) = HoTrackerCounterModel* see 2.452.1	A mapping between tracker name and tracker.

2.452.1 HoTrackerCounterModel

groups	*table(string) = HoGroupCounterModel* see 2.452.1.1	A mapping bewteen group name and group.
numFlows	*integer*	Total number of flows.

2.452.1.1 HoGroupCounterModel

flows	*list of HoFlowCounterEntryModel* see 2.452.1.1.1	List of flows.

2.452.1.1.1 HoFlowCounterEntryModel

bytesReceived	*integer*	Number of bytes received.
createTime	*floating point number*	Hardware offload flow counter entry create time.
[egressIntf] **	*interface name*	Flow egress interface. **Since: 4.28.2
[ingressIntf]	*interface name*	Flow ingress interface.
key	*FlowKeyModel* see 2.450.1.1.1.7	Hardware offload flow counter key.
pktsReceived	*integer*	Number of packets received.
updateTime	*floating point number*	Hardware offload flow counter entry update time.

2.453 show flow tracking sampled statistics [...]

[instanceId] **	*integer*	Instance identifier. **Since: 4.35.2
running	*boolean*	Sampled flow tracking is active.
trackers	*table(string) = FtStatisticsPerTracker* see 2.453.1	A mapping between flow tracker name and FtStatistics.

2.453.1 FtStatisticsPerTracker

counts	*list of FlowCountAtSample-AndDuration* see 2.453.1.2	List of flow count by sample ranges index and duration ranges index.
durations	*list of DurationRange* see 2.453.1.1	List of duration ranges.
samples	*list of SampleRange* see 2.453.1.3	List of sample ranges.

2.453.1.1 DurationRange

greaterThanEqual	*integer*	Minimum duration for current bucket.
lessThan	*integer*	Maximum duration for current bucket.

2.453.1.2 FlowCountAtSampleAndDuration

durationIndex	*integer*	Index to lookup duration this count is for.
flowCount	*integer*	Flow count for current bucket at sample and duration.
sampleIndex	*integer*	Index to lookup sample this count is for.

2.453.1.3 SampleRange

greaterThanEqual	*integer*	Minimum samples for current bucket.
lessThan	*integer*	Maximum samples for current bucket.

2.454 show flow tracking telemetry inband counters [...]

see 2.447

2.455 show flow tracking telemetry inband flow-table [...]

see 2.450.1.1.1.7

2.456 show flow-spec (ipv4 | ipv6) summary [...]

allVrfInstalledCount	*integer*	Number of flow-spec rules installed in hardware across all VRFs.
allVrfTotalCount	*integer*	Total number of flow-spec rules across all VRFs.
vrfs	*table(string) = VrfFlowspecRuleSummary* see 2.456.1	Flow-spec rule summary indexed by VRF name.

2.456.1 VrfFlowspecRuleSummary

`installedCount`	*integer*	Number of flow-spec rules installed in hardware.
`totalCount`	*integer*	Total number of flow-spec rules.
`unInstalledCount`	*integer*	Number of flow-spec rules not installed in hardware.

2.457 show flow-spec ipv4 [...]

vrfs	*table(string) = VrfFlowspecRule* see 2.457.1	Flow-spec rules indexed by VRF name.

2.457.1 VrfFlowspecRule

activeIntfs	*list of Interface name*	List of interfaces applied with flow-spec.
[activeVrfRedirectIntfs] **	*list of Interface name*	List of interfaces applied with vrf redirect rules. **Since: 4.34.1
configuredIntfs **	*list of Interface name*	List of interfaces configured with flow-spec. **Since: 4.22.0
[configuredVrfRedirect-Intfs] **	*list of Interface name*	List of interfaces configured with vrf redirect rules. **Since: 4.34.1
feasibleRules	*list of FeasibleFlowspecRule* see 2.457.1.1	Feasible flow-spec rules indexed by rule string.
[feasibleVrfRedirectRules] **	*list of FeasibleFlowspecRule* see 2.457.1.1	Feasible vrf redirect rules indexed by rule string. **Since: 4.34.1
infeasibleRules	*list of InfeasibleFlowspecRule* see 2.457.1.3	Infeasible flow-spec rules indexed by rule string.
[infeasibleVrfRedirect-Rules] **	*list of InfeasibleFlowspecRule* see 2.457.1.3	Infeasible vrf redirect rules indexed by rule string. **Since: 4.34.1
[interfaceSets] **	*table(string) = FlowspecInterfaceSet* see 2.457.1.2	Flow-spec interface-sets indexed by set identifier. **Since: 4.31.1

2.457.1.1 FeasibleFlowspecRule

actions	*Actions* see 2.457.1.1.1	Actions for the rule.
[interfaceSets] **	*list of integer*	List of interface-sets for the rule. **Since: 4.31.1
matches	*Matches* see 2.457.1.1.2	Matches for the rule.
ruleId	*integer*	Flow-spec rule identifier.
ruleString	*string*	Flow-spec rule string representation.
status	*Status* see 2.457.1.1.3	Status for the rule.
[unsupportedActions] **	*Actions* see 2.457.1.1.1	Unsupported actions. **Since: 4.30.2

2.457.1.1.1 Actions

[trafficAction] **	*TrafficAction* see 2.457.1.1.1.1	Traffic action to sample or stop traffic filtering. **Since: 4.30.2
[trafficDrop]	*boolean*	Drop action.
[trafficMarking] **	*integer*	Mark DSCP action. **Since: 4.23.1
[trafficRate] **	*floating point number*	Police traffic based on bits per second (bps). **Since: 4.22.0
[trafficRatePkt] **	*floating point number*	Police traffic based on packets per second (pps). **Since: 4.30.2
[trafficRedirect]	*TrafficRedirect* see 2.457.1.1.1.2	Traffic redirect action.

2.457.1.1.1.1 TrafficAction

nonTerminal	*boolean*	Traffic-filtering engine may evaluate or stops filtering based on this bit.
sample	*boolean*	Traffic sampling and logging is enabled.

2.457.1.1.1.2 TrafficRedirect

mirror	*boolean*	Mirror the packet instead of redirecting it.
[nexthop]	*IP address*	IP address of nexthop for redirect.
viaNexthop	*list of ViaNexthop* see 2.457.1.1.1.3	Redirect via the nexthop.
vrf	*string*	VRF name.

2.457.1.1.1.3 ViaNexthop

[mplsLabel] **	*integer*	MPLS label. **Since: 4.22.0
nexthopIp	*IP address*	IP address of nexthop for redirect.
[tunnelIndex] **	*integer*	Tunnel index within tunnel type. **Since: 4.22.0

[tunnelType] **	*enum: BGP LU Forwarding | maxTunnelType | IP-in-IP | MLDP P2MP | invalidTunnel | VXLAN VTEP Encap | IS-IS SRv6 | Nexthop | Static MPLS | SR-TE Policy | SR-TE | OSPF SR | IS-IS SRv6 TI-LFA | IS-IS FlexAlgo | Static MPLS Multicast | Nexthop Group | TI-LFA | LDP | RSVP LER SUB | SRv6 SR-TE SL | RSVP P2MP | RSVP LER | EosSdk sBFD | UDP | SRv6 Transport | EVPN VXLAN | VXLAN | RSVP FRR | IS-IS Remote TI-LFA | BGP LU | RSVP | IS-IS SR | Static Interface*	Tunnel type. **Since: 4.22.0

2.457.1.1.2 Matches

[destPort]	*list of NumericalRange* see 2.457.1.1.2.2	Destination port.
[destPrefix]	*IP address prefix*	Destination prefix.
[dscp]	*list of NumericalRange* see 2.457.1.1.2.2	DSCP.
[flowLabels]	*list of NumericalRange* see 2.457.1.1.2.2	Flow label.
[fragmentFlags]	*list of BitMask* see 2.457.1.1.2.1	Fragment flags.
[icmpCode]	*list of NumericalRange* see 2.457.1.1.2.2	ICMP code.
[icmpType]	*list of NumericalRange* see 2.457.1.1.2.2	ICMP type.
[nextProtocol]	*list of NumericalRange* see 2.457.1.1.2.2	Next protocol.
[packetLength]	*list of NumericalRange* see 2.457.1.1.2.2	Packet length.
[port]	*list of NumericalRange* see 2.457.1.1.2.2	Port.
[srcPort]	*list of NumericalRange* see 2.457.1.1.2.2	Source port.
[srcPrefix]	*IP address prefix*	Source prefix.
[tcpFlags]	*list of BitMask* see 2.457.1.1.2.1	TCP flags.

2.457.1.1.2.1 BitMask

mask	*integer*	Mask.
value	*integer*	Value.

2.457.1.1.2.2 NumericalRange

maxVal	*integer*	Maximum value.
minVal	*integer*	Minimum value.

2.457.1.1.3 Status

[byteCount] **	*integer*	Number of bytes hitting the rule. **Since: 4.30.2
installed	*boolean*	Rule installed in hardware.
[packetCount]	*integer*	Number of packets hitting the rule.
[policeCount] **	*PoliceCount* see 2.457.1.1.3.1	Descriptive count for police. **Since: 4.29.2
[reason]	*string*	Reason for not programmed in hardware.

2.457.1.1.3.1 PoliceCount

[aboveCount]	*CounterInfo* see 2.457.1.1.3.2	Number of packets above police rate.
[belowCount]	*CounterInfo* see 2.457.1.1.3.2	Number of packets below police rate.

2.457.1.1.3.2 CounterInfo

[byteCount]	*integer*	Number of bytes.
[packetCount]	*integer*	Number of packets.

2.457.1.2 FlowspecInterfaceSet

activeIntfs	*list of Interface name*	List of interface-set active interfaces.

2.457.1.3 InfeasibleFlowspecRule

infeasibleMatch	*string*	Infeasible match.
ruleId	*string*	Flow-spec rule identier.
ruleString	*string*	Flow-spec rule string representation.

2.458 show flow-spec ipv6 [...]

see 2.457

2.459 show flowcontrol [...]

interfaceFlowControls	*table(Interface name) = FlowControlData* see 2.459.1	Mapping between an interface and it's flow control data.
[syslogInterval] **	*floating point number*	Syslog interval for flow control pasuse frames in seconds. **Since: 4.26.2

2.459.1 FlowControlData

rxAdminState	*enum: unsupported | unknown | desired | on | off*	Receive Flowcontrol admin state.
rxOperState	*enum: unsupported | unknown | on | off | disagree*	Receive Flowcontrol operational state.
rxPause	*integer*	Pause packets received.
txAdminState	*enum: unsupported | unknown | desired | on | off*	Send Flowcontrol admin state.
txOperState	*enum: unsupported | unknown | on | off | disagree*	Send Flowcontrol operational state.
txPause	*integer*	Pause packets sent.

2.460 show forwarding destination [...]

revision 2

details **	*table(string) = PacketDestinationDetailModel* see 2.460.2	Platform specific details on forwarding destination. **Since: 4.28.1
egressInterfaces	*list of EgressInterface* see 2.460.1	List of egress interfaces.
status	*enum: success | timeout*	Status of the request.

2.460.1 EgressInterface

logical	*interface name*	Logical egress interface.
physical	*interface name*	Physical egress interface.

2.460.2 PacketDestinationDetailModel

[fields]	*table(string) = string*	A mapping of detail field name to its value.

2.461 show forwarding destination ingress-interface <ingressIntf> raw <rawPacket> [...]

revision 2

see 2.460

2.462 show fpga applications [...]

applications	*table(string) = FpgaApplicationInstances* see 2.65	A mapping of FPGA application name to information specific to each application.

2.463 show fpga applications compatibility

applications	*table(string) = FpgaApplicationsCompatibility* see 2.463.1	A mapping of FPGA application name to what is compatible with this verison of EOS.

2.463.1 FpgaApplicationsCompatibility

maxHardwareApi	*string*	Maximum hardware API version.
minHardwareApi	*string*	Minimum hardware API version.

2.464 show fpga applications profile [...]

applications	*table(string) = FpgaApplicationProfiles* see 2.66	A mapping of FPGA application name to information specific to each application.

2.465 show fpga metawatch buffers [...]

instances	*table(string) = MetaWatchInstanceBuffers* see 2.465.1	MetaWatch instance buffer information, keyed by instance name.

2.465.1 MetaWatchInstanceBuffers

buffers	*list of MetaWatchCoreBuffer* see 2.465.1.1	MetaWatch buffer information.

2.465.1.1 MetaWatchCoreBuffer

bufferFree	*integer*	Buffer free in bytes.
bufferUsed	*integer*	Buffer used in bytes.
coreId	*integer*	Core ID.
errorMultiEcc **	*integer*	The number of multi-bit ECC errors detected on this core. **Since: 4.33.2
errorSingleEcc **	*integer*	The number of single-bit ECC errors detected on this core. **Since: 4.33.2

2.466 show fpga metawatch device-id [...]

`instances`	*table(string) = InstanceDeviceId* see 2.466.1	MetaWatch instance device IDs, keyed by instance name.

2.466.1 InstanceDeviceId

`[deviceId]`	*integer*	Value placed in device-id trailer field.

2.467 show fpga metawatch interfaces counters [...]

interfaces	*table(Interface name)* = *FpgaMetaWatchInterface-CountersBase* see 2.467.1	MetaWatch interface counters, keyed by interface name.

2.467.1 FpgaMetaWatchInterfaceCountersBase

Could also be an instance of:
FpgaMetaWatchInIntfCounters 2.467.2
FpgaMetaWatchOutIntfCounters 2.467.3
FpgaMetaWatchPassIntfCounters 2.467.4

2.467.2 FpgaMetaWatchInIntfCounters

dropped	*integer*	Received packets dropped.
errorBadframe	*integer*	Received packets with frame error.
errorFcs	*integer*	Received packets with FCS error.
errorInternal	*integer*	Dropped packets due to internal metawatch errors.
errorLength	*integer*	Received packets exceeding size limit.
errorOctets **	*integer*	Received octets from undersized or oversized packets. **Since: 4.33.0
errorPcs	*integer*	Received packets with PCS error.
filtered	*integer*	Multicast packets filtered.
totalPkts	*integer*	Received packets.

2.467.3 FpgaMetaWatchOutIntfCounters

errorLength **	*integer*	Transmitted packets exceeding size limit. **Since: 4.32.2
errorOctets **	*integer*	Transmitted octets from undersized or oversized packets. **Since: 4.33.0
errorOther	*integer*	Packets dropped due to transmission errors.
errorRunts **	*integer*	Transmitted packets below base size. **Since: 4.32.2
errorUnderrun	*integer*	Packets dropped due to underrun errors.
totalPkts	*integer*	Transmitted packets.

2.467.4 FpgaMetaWatchPassIntfCounters

dropped	*integer*	Packets dropped.
errorFcs	*integer*	Packets dropped due to FCS errors.
errorInternal	*integer*	Packets dropped due to transmission errors.

errorOctets **	*integer*	Transmitted octets from undersized or oversized packets. **Since: 4.33.1
errorUnderrun **	*integer*	Packets dropped due to underrun errors. **Since: 4.32.2
padded **	*integer*	Packets padded before transmission. **Since: 4.32.2
totalPkts	*integer*	Transmitted packets.

2.468 show fpga metawatch interfaces counters deduplication [...]

instances	*table(string) = MetaWatchInstanceCountersDedup* see 2.468.1	MetaWatch instance counters, keyed by instance name.

2.468.1 MetaWatchInstanceCountersDedup

interfaces	*table(Interface name) = MetaWatchTxDedupCounters* see 2.468.1.1	WatchOut deduplication counters, keyed by interface name.

2.468.1.1 MetaWatchTxDedupCounters

dropPkts	*integer*	Number of duplicate packets dropped.
fcsPkts **	*integer*	Number of duplicate packets with FCS error. **Since: 4.32.2
pkts	*integer*	Number of duplicate packets detected.
truncatePkts	*integer*	Number of duplicate packets truncated.

2.469 show fpga metawatch ptp

revision 2

[ptpClockSummary]	*PtpClockSummary* see 2.469.1	Summary Information for boundary clocks.
ptpIntfSummaries	*table(Interface name) = PtpIntfVlanSummary* see 2.469.2	Collection of summaries of PTP enabled interfaces to display.
[ptpMode]	*enum: ptpEndToEndTransparentClock | ptpPeerToPeerTransparentClock | ptpBoundaryClock | ptpGeneralized | ptpOneStepEndToEndTransparentClock | ptpOneStepBoundaryClock | ptpOneStepPeerToPeerTransparentClock | ptpDisabled | ptpOrdinaryMasterClock*	PTP mode.
[ptpProfile]	*enum: ptpG8275_1 | ptpDefaultProfile | ptpG8275_2*	PTP profile.
[ptpSelectedProfile] **	*enum: ptpG8275_1 | ptpDefaultProfile | ptpG8275_2*	Selected (but not applied) PTP profile. **Since: 4.28.0

2.469.1 PtpClockSummary

clockIdentity	*string*	DefaultDS clock identity.
[currentPtpSystemTime]	*integer*	Current sytem time measured with PTP.
gmClockIdentity	*string*	Grandmaster clock identity. See IEEE 1588-2008 for more information.
[gptpRateRatio]	*floating point number*	Estimated gptp rate ratio.
[lastSyncTime]	*integer*	Last time local clock synced from master.
meanPathDelay	*integer*	CurrentDS mean path delay to master in nanoseconds.
[neighborRateRatio]	*floating point number*	Estimated gptp neighbor rate ratio.
numberOfMasterPorts	*integer*	Number of master ports.
numberOfSlavePorts	*integer*	Number of slave ports.
[offsetFromMaster]	*integer*	CurrentDS offset from master in nanoseconds.
[skew]	*floating point number*	Ratio of master's seconds to local seconds.
[slavePort]	*string*	Interface name of slave port.
[slaveVlanId] **	*integer*	VLAN ID of slave port. **Since: 4.23.1
stepsRemoved	*integer*	CurrentDS steps removed from GM.
[systemClockOffset] **	*integer*	Current offset between system clock and PTP clock in nanoseconds. **Since: 4.26.2

2.469.2 PtpIntfVlanSummary

interface	*interface name*	PTP interface name.
ptpIntfVlanSummaries	*list of PtpIntfSummary* see 2.469.2.1	List of summaries of PTP enabled interface on different VLAN to display. There can be several of them when PTP is configured to run on multiple VLANs on a trunk interface.

2.469.2.1 PtpIntfSummary

[asCapable]	*boolean*	Interface is GPTP capable.
[delayMechanism]	*string*	PTP delay mechanism. See IEEE 1588-2008 for more information.
[lastGptpResidenceTime]	*integer*	Minimum measured GPTP residence time.
[mpassEnabled] **	*boolean*	PTP MPASS operational state. **Since: 4.26.0
[mpassStatus] **	*enum: inactive* | *active*	PTP MPASS status. **Since: 4.26.0
[neighborRateRatio]	*floating point number*	Estimated gptp neighbor rate ratio.
[peerPathDelay]	*integer*	Peer mean path delay in nanoseconds. See IEEE 1588-2008 for more information.
[portState]	*enum: psFaulty* | *psListening* | *psPreMaster* | *psPassive* | *psMaster* | *psDisabled* | *psInitializing* | *psIsolatedSlave* | *psUncalibrated* | *psSlave*	PTP port state. See IEEE 1588-2008 for more information.
[timeSinceAsCapableLastChanged]	*string*	Time elasped since AS capable state of the port last changed.
transportMode	*enum: layer2* | *ipv4* | *ipv6*	Type of packet used to send PTP messages.
[vlanId]	*integer*	VLAN on which the PTP trunk interface is configured.

2.470 show fpga metawatch status [...]

instances	*table(string) = InstanceStatus or NULL* see 2.470.1	MetaWatch instance status, keyed by name.

2.470.1 InstanceStatus

[deviceId]	*integer*	Value placed in device-id trailer field.
enabled	*boolean*	MetaWatch is enabled.
[fpgaName]	*string*	FPGA name of where MetaWatch is running.
interfaces	*table(Interface name) = MetaWatchIntfBase* see 2.470.1.1	MetaWatch interface status, keyed by interface name.
[profile]	*string*	Applied profile.
[sdramTestComplete]	*boolean*	SDRAM self test complete.
[timesyncReady]	*boolean*	Timesync initialization complete.

2.470.1.1 MetaWatchIntfBase

Could also be an instance of:
MetaWatchPxIntf 2.470.1.2
MetaWatchRxIntf 2.470.1.3
MetaWatchTxIntf 2.470.1.4

2.470.1.2 MetaWatchPxIntf

2.470.1.3 MetaWatchRxIntf

[dot1adVlanTag]	*integer*	Dot1ad VLAN Tag.
[dot1qVlanTag]	*integer*	Dot1q VLAN Tag.
[egressTimestampPoint] **	*interface name*	Configured egress timestamp point for this port. **Since: 4.34.1
pcsEncapsulationPreserve **	*boolean*	PCS encapsulation is preserved in captured packets. **Since: 4.34.2
portId	*integer*	Value placed in port-id trailer field.
rxEnabled	*boolean*	Rx port is enabled.
timestampOffset	*floating point number*	Offset configured for this port in nanoseconds.
[timestampPointOffset] **	*floating point number*	Configured timestamp point offset for this port in nanoseconds. **Since: 4.34.1
totalOffset	*floating point number*	Total calibrated offsets in nanoseconds.
trafficFilterMulticastDrop	*boolean*	Multicast traffic should be filtered and dropped.
trailerDisabled	*boolean*	All trailers are disabled.
trailerExtensionSequenceNum	*boolean*	Sequence number trailer extension is present.
trailerExtensionSubNano	*boolean*	Subnano trailer extension is present.

[truncationBytes]	*integer*	Number of bytes to truncate packets to.

2.470.1.4 MetaWatchTxIntf

aggregationCores	*list of integer*	Core number that this interface is sourcing.
[bandwidthRateShape]	*integer*	Output bandwidth limit in Kbps.
[bandwidthRateShapeMax]	*integer*	Maximum output bandwidth limit in Kbps.
[bandwidthRateShapeMin]	*integer*	Minimum output bandwidth limit in Kbps.
[deduplication]	*MetaWatchDedup* see 2.470.1.4.1	Deduplication information (if supported).
[packetRateShape]	*integer*	Output packet rate limit in pps.
[packetRateShapeMax]	*integer*	Maximum output packet rate limit in pps.
[packetRateShapeMin]	*integer*	Minimum output packet rate limit in pps.
rxFlowControl	*boolean*	Receive flow control enabled.
[rxPriorityFlowControl-Class]	*integer*	Receive priority flow control class (if enabled).
speed	*integer*	Line rate in Kbps.
trailerExtensionDedupHash	*boolean*	Deduplication hash trailer extension is present.
trailerExtensionSequenceNum	*boolean*	Sequence number trailer extension is present.
[truncationBytes]	*integer*	Number of bytes to truncate packets to.

2.470.1.4.1 MetaWatchDedup

[entryMaxAge]	*floating point number*	Max age for an entry in seconds.
hashFields	*MetaWatchDedupHash-Fields* see 2.470.1.4.1.1	Fields that can be ignored for hashing packets.
matchActions	*MetaWatchDedupMatch-Action* see 2.470.1.4.1.2	Actions taken when a duplicate is seen.

2.470.1.4.1.1 MetaWatchDedupHashFields

ipv4TtlDisabled	*boolean*	IPv4 TTL ignored.
macAddrsDisabled	*boolean*	MAC addresses ignored.
[trailingBytesDisabled]	*integer*	Number of trailing bytes of the payload that are ignored.
vlanDisabled	*boolean*	VLAN field ignored.

2.470.1.4.1.2 MetaWatchDedupMatchAction

drop	*boolean*	Drop packet.
trailerExtensionDedupHash	*boolean*	Add deduplication hash trailer extension.
[truncateBytes]	*integer*	Number of bytes to truncate packets to.

2.471 show fpga multiaccess interfaces counters access-list [...]

revision 2

interfaces	*table(Interface name) = MultiAccessInterface-CountersAccessList* see 2.471.1	A mapping of interface names to their ACL counters.

2.471.1 MultiAccessInterfaceCountersAccessList

[inDropped]	*integer*	Packets denied by the ingress ACL.
[inPermitted]	*integer*	Packets permitted by the ingress ACL.
[outDropped]	*integer*	Packets denied by the egress ACL.

2.472 show fpga multiaccess interfaces counters buffer [...]

interfaces	*table(Interface name) = MultiAccess.Cli.Multi-AccessInterfaceCounters-Buffer* see 2.472.1	A mapping of interface names to their buffer counters.

2.472.1 MultiAccess.Cli.MultiAccessInterfaceCountersBuffer

inBuffer	*integer*	Number of packets that reached the input buffer.

2.473 show fpga multiaccess interfaces counters queue [...]

interfaces	*table(Interface name) = MetaMuxApplication-InterfaceQueueStats* see 2.473.1	A mapping of interface names to their queueing statistics.

2.473.1 MetaMuxApplicationInterfaceQueueStats

averageQueueTime	*integer*	Average queue time (ns) of packets measured in the last 1-second.
maxQueueTime	*integer*	Largest measured queue time (ns) in the last 1-second interval.
totalPkts	*integer*	Number of packets queued in the last 1-second interval.
[underflowOverflowError-Status]	*enum: layer2 | layer1 | layer1and2*	Underflow/Overflow error status.

2.474 show fpga multiaccess interfaces counters vlan [...]

interfaces	*table(Interface name) = MultiAccess.Cli.MultiAccessInterfaceCountersVlan* see 2.474.1	A mapping of interface names to their VLAN counters.

2.474.1 MultiAccess.Cli.MultiAccessInterfaceCountersVlan

[outDropped]	*integer*	Packets dropped due to not matching client VLAN.

2.475 show fpga multiaccess interfaces storm-control [...]

interfaces	*table(Interface name) = InterfaceStormControlStatus* see 2.475.1	A mapping of interface name to their storm-control status information.

2.475.1 InterfaceStormControlStatus

[anyPacketsPerInterval]	*integer*	Threshold for any packet type.
[broadcastPacketsPerInterval]	*integer*	Threshold for broadcast packets.
dropCount	*integer*	Storm control packet drop count.
intervalns	*integer*	Interval in nanoseconds.
[multicastPacketsPerInterval]	*integer*	Threshold for multicast packets.
portDisabled	*boolean*	Interface is currently disabled due to storm control.
portDisabledOnOverRate	*boolean*	Interface is configured to stay disabled after threshold is breached.
[unicastPacketsPerInterval]	*integer*	Threshold for unicast packets.

2.476 show fpga multiaccess status [...]

instances	*table(string) = MultiAccessInstanceStatus or NULL* see 2.476.1	MultiAccess instance status, keyed by name.

2.476.1 MultiAccessInstanceStatus

aclDropDelay	*boolean*	Delayed cut-through mode.
downstreamInterfaces	*table(Interface name) = MultiAccessDownstreamIntf* see 2.476.1.1	Downstream interface status, keyed by interface name.
enabled	*boolean*	Instance is enabled and running.

fpgaFunctionInterfaces **	*list of Interface name*	FpgaFunction interface status, keyed by interface name. **Since: 4.34.2
[fpgaName]	*string*	FPGA name of where MultiAccess is running.
ports **	*integer*	Number of ports used by the profile. **Since: 4.34.1
[profile]	*string*	Applied profile.
upstreamInterfaces	*table(Interface name)* = *MultiAccessUpstreamIntf* see 2.476.1.2	Upstream interface status, keyed by interface name.

2.476.1.1 MultiAccessDownstreamIntf

[accessVlanId]	*integer*	Access VLAN ID.
ingressFilterSupported	*boolean*	If this interface supports ingress filters.
vlanSupported	*boolean*	If VLAN tagging is supported.

2.476.1.2 MultiAccessUpstreamIntf

lowLatencySupported	*boolean*	Interface is low latency.
schedulerType	*enum: orderOfArrival | roundRobin | profileDefault*	Scheduler type.
[vlanTpid]	*integer*	Dot1q ethertype/Tag protocol ID.

2.477 show fpga switch ((mac address-table) | mac-address-table) multicast [...]

[groups]	*list of EthGroup* see 2.477.1	A list of EthGroups.

2.477.1 EthGroup

igmpFlooding	*boolean*	Overflood IGMP packets in hardware.
igmpToCpu	*boolean*	Copy IGMP packets to CPU.
interfaces	*list of Interface name*	Interfaces of the EthGroup.
macAddress	*MAC address*	EthGroup MAC address.
vlanId	*integer*	VLAN identifier.

2.478 show fpga switch [...]

switchCores	*table(numeric string)* = *FpgaSwitchCore* see 2.478.1	A mapping of FPGA Switch core ID to information specific to the FPGA Switch core instance.

2.478.1 FpgaSwitchCore

application	*ApplicationInfo* see 2.478.1.1	FPGA Application information.
featureProfile	*string*	Feature Profile Name.
hardwareApi **	*HardwareApiInfo* see 2.478.1.2	Hardware API version. **Since: 4.28.0
numPipelines **	*integer*	Number of pipelines. **Since: 4.28.0
portProfile	*string*	Port Profile Name.

2.478.1.1 ApplicationInfo

instance	*string*	FPGA Application Instance.
name	*string*	FPGA Application Name.

2.478.1.2 HardwareApiInfo

major	*integer*	Hardware API major revision number.
minor	*integer*	Hardware API minor revision number.

2.479 show fpga switch counters [...]

counters	*table(string) = MakoDebugCounterValue* see 2.479.1	Mapping between counter name and counter info.

2.479.1 MakoDebugCounterValue

firstSeen	*floating point number*	Time when counter was first incremented.
lastSeen	*floating point number*	Time when counter was most recently incremented.
value	*integer*	Value of counter.

2.480 show fpga switch counters cpu queue

see 2.337

2.481 show fpga switch ip route [...]

switchCores	*table(numeric string) = FpgaSwitchCoreRoutes* see 2.481.1	A mapping of FPGA Switch coreID to its programmed routes.

2.481.1 FpgaSwitchCoreRoutes

lastHit **	*floating point number*	Timestamp of the last hit of any of the routes were used for routing a packet. A value of 0 means never hit. **Since: 4.32.0
routes	*list of Route* see 2.481.1.1	List of programmed routes.

2.481.1.1 Route

action	*enum: DROP | ROUTE | CPU_LOW | FLOOD | ECMP | CPU_HIGH*	Action to perform.
consistent	*boolean*	Whether the route and associated rewrite entries are all consistently programmed across the FPGA core.
destIntfs	*table(Interface name) = DestinationInterface* see 2.481.1.1.1	L2 rewrite info keyed by egress L2 port.
[ecmpNhs] **	*list of EcmpNh* see 2.481.1.1.2	Equal Cost Multi Path Choices. **Since: 4.31.2
inHw **	*boolean*	Whether the route and associated rewrite entries are programmed into the FPGA. **Since: 4.32.1
lastHit **	*floating point number*	Timestamp of the last hit of any of the contributing LPM entries were used for routing a packet. A value of 0 means never hit. **Since: 4.32.0
[lpmEntries]	*list of string*	Hardware LPM entries that contribute to this route.
[lpmLastHit] **	*list of floating point number*	Last time the same index LPM entry was used to route a packet. A value of 0 means never hit. **Since: 4.32.0
numEntries	*integer*	Number of hardware LPM entries that contribute to this route.
prefix	*IP address prefix*	Logical IPv4 destination subnet.
vrfId	*integer*	VRF ID.
vrfName **	*string*	VRF name. **Since: 4.29.0

2.481.1.1.1 DestinationInterface

ethAddr	*MAC address*	Rewrite MAC address.
vlanId	*integer*	Rewrite VLAN ID.

2.481.1.1.2 EcmpNh

destIntfs	*table(Interface name) = DestinationInterface* see 2.481.1.1.1	L2 rewrite info keyed by egress L2 port.

2.482 show fpga switch mapping [...]

switchCores	*table(numeric string) = PortMappings* see 2.482.1	A mapping of FPGA Switch core ID to its switch port mapping.

2.482.1 PortMappings

cpuInterfaces	*table(Interface name) = CpuPortMapping* see 2.482.1.1	The mapping of CPU ports to their internal ID.
interfaces	*table(Interface name) = PortMapping* see 2.482.1.2	The mapping of switch ports to their internal IDs.

2.482.1.1 CpuPortMapping

portId	*integer*	Internal port ID.

2.482.1.2 PortMapping

egressId	*integer*	Egress processor ID.
pipeId	*integer*	Ingress pipeline ID.
pipePortId	*integer*	Port ID within the pipeline.
portId	*integer*	Internal port ID.

2.483 show fpga switch multicast ip route [...]

switchCores	*table(numeric string) = FpgaSwitchMulticastCoreRoutes* see 2.483.1	A mapping of FPGA Switch coreID to its programmed multicast routes.

2.483.1 FpgaSwitchMulticastCoreRoutes

lastHit **	*floating point number*	Latest time any of the routes were used for routing a packet. A value of 0 means never hit. **Since: 4.32.2
routes	*list of MulticastRoute* see 2.483.1.1	Programmed multicast routes.

2.483.1.1 MulticastRoute

consistent	*boolean*	Whether the route and associated rewrite entries are all consistently programmed across the FPGA core.
dmac	*MAC address*	Destination MAC address of the route.
group	*IP address*	Logical IP multicast group address.
ingressVlanId	*integer*	Ingress VLAN ID of the route.
interfaces	*table(Interface name) = MulticastDestination* see 2.483.1.1.1	A mapping of destination interface to its egress VLANs.
lastHit **	*floating point number*	Latest time this route was used. A value of 0 means never hit. **Since: 4.32.2
natEnabled **	*boolean*	Whether NAT is enabled for this route. **Since: 4.33.2
natSessionId **	*integer*	NAT session id of this route. **Since: 4.33.2
natType **	*enum: INVALID | DNAT | TNAT | SNAT*	Type of NAT enabled for this route. **Since: 4.33.2
source	*IP address*	Logical IP multicast source address.
vlanGroupId	*integer*	VLAN group ID of the route.

2.483.1.1.1 MulticastDestination

egressVlanIds	*list of integer*	Egress VLAN IDs used for the interface.

2.484 show fpga switch parity event [...]

[events]	*list of ParityEvent* see 2.484.1	A list of parity events.
parityEventCount	*integer*	Number of parity events.

2.484.1 ParityEvent

address	*integer*	Address affected by the event.
count	*integer*	Number of times an event has occurred at this address.
impact	*enum: critical | none | unknown | temporary*	The impact of the event.
lastReportedTime	*floating point number*	Last time an event was reported in at this address in UTC.
sourceId	*integer*	ID of the event source.
sourceName	*string*	Name of the event source.
sourceType	*enum: register | unknown | table | other*	The type of the event source.
switchId	*integer*	ID of the switch instance where event occurred.

2.485 show gre tunnel static [...]

greTunnels	*table(numeric string) = L3IntfTunnelTableEntry* see 2.485.1	Collection of GRE tunnels.

2.485.1 L3IntfTunnelTableEntry

dstAddr	*IP address*	Location in the IP network where the tunnel terminates.
index	*integer*	Tunnel index.
name	*string*	Tunnel name.
srcAddr	*IP address*	Location in the IP network where the tunnel starts.
vias	*list of IpVia* see 2.193.1.3	List of tunnel vias.

2.486 show hardware asset-tag [...]

revision 2

assets	*table(string) = Asset* see 2.486.1	Assets for this system.
missing	*table(string) = Missing* see 2.486.2	Missing assets.

2.486.1 Asset

serial	*string*	Factory-set serial number.
tag	*string*	Customer-supplied asset tag.

2.486.2 Missing

fruType	*string*	Type of the missing FRU.
tag	*string*	Customer-supplied asset tag.

2.487 show hardware capacity [...]

tables	*list of TableEntry* see 2.487.1	A list of tables and utilization.

2.487.1 TableEntry

chip	*string*	Name of chip. Populated only for divergent (per-chip) features.
committed	*integer*	Block of entries dedicated to this feature, but may or may not be in use now. This value is applicable only to those tables which allocate a block of resources (like Bank) to a given feature.

feature	*string*	Name of feature using the given hardware table. When this column is empty, it is an aggregate of the usage by all features using this table.
free	*integer*	Number of free entries: 'Max entries available now - Used entries', where maximum available entries exclude entries used by and committed to other features.
highWatermark	*integer*	The maximum number of entries used by this feature so far. This value may get reset after agent restart or SSO switchover.
maxLimit	*integer*	Best case maximum entries available for this feature, considering no other feature is using them. This is the theoretical maximum resource utilization possible for this feature.
sharedFeatures **	*list of string*	Feature Groups programmed in the TCAM Bank. **Since: 4.32.2
table	*string*	Name of hardware resource / table.
used	*integer*	Number of entries currently in use for the table by given feature.
usedPercent	*integer*	Used percent (%) calculated as 'Number of entries in use by the given feature / (Number of entries in use by the given feature + Number of free entries) * 100'.

2.488 show hardware capacity alert threshold

thresholds	*table(string) = TableThreshold* see 2.488.1	A mapping from table name to thresholds.

2.488.1 TableThreshold

configClearThreshold **	*integer*	Configured Clear Threshold in percent (%). **Since: 4.31.0
configThreshold	*integer*	Configured Threshold in percent (%).
defaultThreshold	*integer*	Default Threshold in percent (%).

2.489 show hardware clock frequency sink

frequencySinks	*table(string) = FreqSinkInfo* see 2.489.1	Frequency sinks indexed by their name.

2.489.1 FreqSinkInfo

description	*string*	Description of the component.
source	*string*	Name of the frequency source the sink is using.

2.490 show hardware clock frequency source

`frequencySources`	*table(string) = FreqSourceInfo* see 2.490.1	Frequency sources indexed by their name.

2.490.1 FreqSourceInfo

`adjustment`	*floating point number*	Configured adjustment to frequency as pulse per billion.
`description`	*string*	Description of the component.
`frequency`	*integer*	Frequency in Hertz of the source.

2.491 show hardware clock frequency topology

`sinks`	*table(string) = SinkInfo* see 2.491.1	Sinks indexed by their name.

2.491.1 SinkInfo

`availableSources`	*list of string*	Available sources that the sink could use.
`source`	*string*	Name of the source the sink is using.

2.492 show hardware clocking

`ports`	*table(string) = ClockPortStatus* see 2.492.1	Clock ports indexed by their name.

2.492.1 ClockPortStatus

`[cableDelay]`	*floating point number*	Cable delay in nanoseconds unit.
`signal`	*enum: gnssAntennaActive | pps | none | gnssAntenna*	Port signal type.
`[source]` **	*enum: local-clock | none | metawatch | pps-in1*	Port signal source. **Since: 4.34.0
`[status]` **	*enum: down | up*	Port signal status. **Since: 4.30.1

2.493 show hardware clocking time-sync

`[configReference]`	*string*	Configured time-sync reference.
`[leaderId]` **	*integer*	Current leader. **Since: 4.32.2
`[offsetFromReference]`	*floating point number*	Difference in nanoseconds between clock and reference time.

[reference] **	*string*	Current time-sync reference. **Since: 4.31.2
[syncStatus]	*string*	Current sync status.

2.494 show hardware clocking time-sync offset statistics

hourStatistics	*TimesyncOffsetStatistics-Record* see 2.494.1	Error statistics for the last hour.
minuteStatistics	*TimesyncOffsetStatistics-Record* see 2.494.1	Error statistics for the last minute.
timestamp	*floating point number*	Time at which the command was executed.
utcTimestamp **	*floating point number*	Time at which the command was executed. **Since: 4.36.0

2.494.1 TimesyncOffsetStatisticsRecord

[average]	*floating point number*	Average sample in nanoseconds.
[maximum]	*floating point number*	Maximum sample in nanoseconds.
[minimum]	*floating point number*	Minimum sample in nanoseconds.
samples	*integer*	Number of samples.
[stdev]	*floating point number*	Sample standard deviation in nanoseconds.

2.495 show hardware counter drop [...]

dropEvents	*table(string) = DropEvents* see 2.495.1	Mapping from chipName to drop events.
totalAdverseDrops	*integer*	Total count of adverse drop counters.
totalCongestionDrops	*integer*	Total count of congestion drop counters.
totalPacketProcessorDrops	*integer*	Total count of packet processor drop counters.

2.495.1 DropEvents

dropEvent	*list of DropEvent* see 2.495.1.1	List of drop events.

2.495.1.1 DropEvent

counterId	*integer*	Counter ID.
counterName	*string*	Counter name.
counterType	*string*	Counter type.
dropCount	*integer*	Drop count.
[dropInLastMinute]	*integer*	The number of drops that happend in the last minute.
[dropInLastOneDay]	*integer*	The number of drops that happend in the last one day.
[dropInLastOneHour]	*integer*	The number of drops that happend in the last one hour.
[dropInLastOneWeek]	*integer*	The number of drops that happend in the last one week.
[dropInLastTenMinute]	*integer*	The number of drops that happend in the last ten minutes.
eventCount	*integer*	Drop event count.
initialEventTime	*string*	UTC timestamp of first occurrence.
[initialThresholdEventTime]	*string*	UTC timestamp of first occurrence above configured threshold.
lastEventTime	*string*	UTC timestamp of most recent occurrence.
[lastSyslogTime]	*string*	UTC timestamp of most recent syslog.
[lastThresholdEventTime]	*string*	UTC timestamp of most recent occurrence above configured threshold.
[thresholdEventCount]	*integer*	Drop count above configured threshold count.

2.496 show hardware counter events

counterEvents	*table(numeric string) = CounterEvent* see 2.496.1	Mapping between counter Id and information for events for a counter.

2.496.1 CounterEvent

counterEventName	*string*	Name of the counter causing the event.
fiveMinuteEvents	*table(string) = ChipEvent* see 2.496.1.1	Mapping between chip name and the events over five minutes for a chip.
oneDayEvents	*table(string) = ChipEvent* see 2.496.1.1	Mapping between chip name and the events over one day for a chip.
oneHourEvents	*table(string) = ChipEvent* see 2.496.1.1	Mapping between chip name and the events over one hour for a chip.
oneWeekEvents	*table(string) = ChipEvent* see 2.496.1.1	Mapping between chip name and the events over one week for a chip.
tenMinuteEvents	*table(string) = ChipEvent* see 2.496.1.1	Mapping between chip name and the events over ten minutes for a chip.

2.496.1.1 ChipEvent

eventCount	*integer*	Number of times the event has occurred.
firstOccurrence	*floating point number*	Time of first occurrence.
firstOccurrenceTime **	*floating point number*	UTC Time of first occurrence. **Since: 4.36.0
lastOccurrence	*floating point number*	Time of last occurrence.
lastOccurrenceTime **	*floating point number*	UTC Time of last occurrence. **Since: 4.36.0
zScore	*floating point number*	Number of standard deviations away from mean the current counter event value is.

2.497 show hardware counter feature

[aclEgressIpv4]	*CounterFeatureInfo* see 2.497.1	Resource and status information for egress IPv4 ACL counters.
[aclEgressIpv6]	*CounterFeatureInfo* see 2.497.1	Resource and status information for egress IPv6 ACL counters.
[aclEgressMac] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for egress MAC ACL counters. **Since: 4.24.0
[aclIngress]	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress ACL counters.
[coppFlowPolicingMeterIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for CoPP flow policing meters. **Since: 4.35.0
[cpuTrafficPolicyIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for CPU traffic policy counters. **Since: 4.23.0
[decapGroup]	*CounterFeatureInfo* see 2.497.1	Resource and status information for decap group counters.
[directFlow] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for DirectFlow counters. **Since: 4.24.1
[ecn] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for egress ECN counters. **Since: 4.22.1
[encryptedPfcIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress encrypted PFC counters. **Since: 4.31.1
[fabricAudit] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for fabric audit counters. **Since: 4.34.2
[flowspec]	*CounterFeatureInfo* see 2.497.1	Resource and status information for Flowspec counters.
[flowspecTwoColor] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for Flowspec two-color counters. **Since: 4.29.2
[greTunnelInterfaceEgress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for egress GRE tunnel interface counters. **Since: 4.22.0
[greTunnelInterfaceIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress GRE tunnel interface counters. **Since: 4.22.0
[intfPolicingIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress interface policing counters. **Since: 4.27.0
[intfPolicingMeterIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress interface policing meters. **Since: 4.27.0
[intfPolicingTrTcmIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress interface policing trTCM counters. **Since: 4.36.0

[intfTrafficPolicyEgress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for egress interface traffic policy counters. **Since: 4.27.0
[intfTrafficPolicyIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress interface traffic policy counters. **Since: 4.23.1
[intfTrafficPolicySvi-Ingress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress SVI traffic policy counters. **Since: 4.31.0
[intfTrafficPolicyTwoColor-Ingress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress interface traffic policy two-color counters. **Since: 4.31.1
[ipInIpEncap] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for IP-in-IP encap counters. **Since: 4.29.1
[ipv4v6Egress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for egress IP counters. **Since: 4.23.0
[ipv4v6Ingress]	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress IP counters.
[l2SubInterfaceEgress]	*CounterFeatureInfo* see 2.497.1	Resource and status information for egress layer 2 subinterface bridged packet counters.
[l2SubInterfaceIngress]	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress layer 2 subinterface counters.
[l2SubInterfaceRouted-Egress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for egress layer 2 subinterface routed packet counters. **Since: 4.28.1
[l3Ipv4v6Egress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for layer 3 egress IPv4, IPv6 counters. **Since: 4.23.1
[l3Ipv4v6Ingress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for layer 3 ingress IPv4, IPv6 counters. **Since: 4.23.1
[latencyEndToEndHistogram] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for latency end to end histogram counters. **Since: 4.33.1
[latencyEndToEndMax] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for latency end to end max counters. **Since: 4.33.1
[maxQueueSize]	*CounterFeatureInfo* see 2.497.1	Resource and status information for LANZ counters.
[mplsInterfaceIngress]	*CounterFeatureInfo* see 2.497.1	Resource and status information for MPLS interface ingress counters.
[mplsLfib]	*CounterFeatureInfo* see 2.497.1	Resource and status information for MPLS LFIB counters.
[mplsTunnel]	*CounterFeatureInfo* see 2.497.1	Resource and status information for MPLS tunnel counters.
[multicastIpv4]	*CounterFeatureInfo* see 2.497.1	Resource and status information for IPv4 multicast counters.

[multicastIpv6] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for IPv6 multicast counters. **Since: 4.23.2
[nexthop]	*CounterFeatureInfo* see 2.497.1	Resource and status information for nexthop group counters.
[nexthopCbf] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for nexthop group CBF counters. **Since: 4.32.2
[oamLmEgress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for egress OAM loss measurement. **Since: 4.27.2
[oamLmIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress OAM loss measurement. **Since: 4.27.2
[oamSyntheticLm] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for OAM synthetic loss measurement. **Since: 4.28.0
[pbrIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress PBR counters. **Since: 4.23.2
[pdp]	*CounterFeatureInfo* see 2.497.1	Resource and status information for PDP counters.
[qosIngress]	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress QoS counters.
[qosMeterIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress QoS meters. **Since: 4.23.1
[qosTrTcmIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress QoS trTCM counters. **Since: 4.24.0
[queueEgress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for egress queue counters. **Since: 4.23.0
[realTimeTrafficBasedWfq] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for real-time traffic-based weighted fair queueing counters. **Since: 4.25.0
[rfc2544NetworkBenchmarks] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for RFC2544 counters. **Since: 4.28.1
[routeIpv4]	*CounterFeatureInfo* see 2.497.1	Resource and status information for IPv4 route counters.
[routeIpv6]	*CounterFeatureInfo* see 2.497.1	Resource and status information for IPv6 route counters.
[routedPortIngress]	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress routed port counters.
[sampledFlowTracking] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for sampled flow tracking counters. **Since: 4.24.2
[segmentSecurity] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for segment security counters. **Since: 4.29.2

[sflowAccel] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for sFlow accel counters. **Since: 4.23.2
[srv6Endpoint] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for SRv6 endpoint counters. **Since: 4.35.2
[stormControlIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for storm control counters. **Since: 4.31.2
[stormControlMeterIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress storm control metering. **Since: 4.25.1
[subInterfaceEgress]	*CounterFeatureInfo* see 2.497.1	Resource and status information for egress layer 3 subinterface counters.
[subInterfaceIngress]	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress layer 3 subinterface counters.
[subInterfaceStormControl-MeterIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress storm control metering on subinterfaces. **Since: 4.30.1
[sviEgress]	*CounterFeatureInfo* see 2.497.1	Resource and status information for egress SVI counters.
[sviIngress]	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress SVI counters.
[tapAggIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress Tap Aggregation counters. **Since: 4.24.2
[tcIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress traffic-class counters. **Since: 4.30.0
[udpTunnel] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for UDP tunnel counters. **Since: 4.33.2
[vlanEgress]	*CounterFeatureInfo* see 2.497.1	Resource and status information for egress VLAN counters.
[vlanIngress]	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress VLAN counters.
[vlanTcIngress]	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress layer 3 interface traffic-class counters.
[vniDecap]	*CounterFeatureInfo* see 2.497.1	Resource and status information for VNI decapsulation counters.
[vniEncap]	*CounterFeatureInfo* see 2.497.1	Resource and status information for VNI encapsulation counters.
[vniPolicingDecap] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for VNI policing decapsulation counters. **Since: 4.32.0
[vniPolicingEncap] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for VNI policing encapsulation counters. **Since: 4.32.0
[voqIngress] **	*CounterFeatureInfo* see 2.497.1	Resource and status information for ingress VOQ counters. **Since: 4.23.0

[vtepDecap]	*CounterFeatureInfo* see 2.497.1	Resource and status information for VTEP decapsulation counters.
[vtepEncap]	*CounterFeatureInfo* see 2.497.1	Resource and status information for VTEP encapsulation counters.

2.497.1 CounterFeatureInfo

[resourceTypes]	*table(string) = CounterFeatureResource* see 2.497.1.1	A mapping between a resource type and counter resources.
[status]	*enum: down | up | unknown | degraded*	Functional status of the counter feature.
[statusDetail]	*string*	Detailed description of the counter feature status.

2.497.1.1 CounterFeatureResource

resourceIds	*list of integer*	Counter resource list.

2.498 show hardware eeprom [...]

components **	*table(string) = Component* see 2.498.1	Mapping of component names to their PreFDL fields. **Since: 4.26.0

2.498.1 Component

[asy]	*string*	Assembly number.
[certificate]	*string*	ASCII readable PEM format (Base64 encoded) certificate.
[cpuFdlVariables]	*table(string) = string*	FDL variables for CPU card.
[cpuHwApi]	*string*	HwApi for CPU card.
[cpuKvn]	*string*	KVN for CPU card.
[cpuMfgTime]	*string*	MfgTime for CPU card.
[cpuPca]	*string*	PCA for CPU card.
[cpuSerialNumber]	*string*	Serial Number for CPU card.
[cpuSid] **	*string*	SID for CPU card. **Since: 4.30.2
[cpuSku]	*string*	SKU for CPU card.
[crc]	*string*	Last four bytes of the PreFDL. This is a CRC-32 checksum.
[dataFormat]	*string*	First four bytes of the PreFDL. This self-describes the PreFDL format.
[deviation]	*list of string*	Defines an action that was taken that was not part of theoriginal build instructions.
[fdlVariables]	*table(string) = string*	Python code (a dictionary) allowing for arbitrary variables to be set.
[hwApi]	*string*	Hardware API.
[hwEpoch]	*string*	Hardware epoch.
[hwRev]	*string*	Hardware revision. This field is used to display the hardware revision to the user.
[kvn]	*string*	The KVN verification field is no longer used. Because it is a required field in formats 0000, 0001, and 0002, the default value 111 is stored as a placeholder.
[macAddrBase]	*MAC address*	The first MAC address allocated to the board.
[mfgTime]	*string*	When the PreFDL was generated.
[mfgTime2] **	*string*	The system clock when the PreFDL was generated, deprecates MfgTime. **Since: 4.28.2
[other]	*list of string*	Present fields which are uncommon.
[pca]	*string*	Printed circuit assembly number.
[prototype] **	*boolean*	This is prototype hardware. **Since: 4.31.1
[serialNumber]	*string*	Board serial number.
[sid]	*string*	System ID. Used by run-time software (along with the HwAPI) to identify the system and choose a FDL.
[signature]	*string*	ASCII readable PEM format (Base64 encoded) signature.

[signatureList]	*list of string*	PreFDL values that should be used in validating the signature.
[sku]	*string*	Software-display SKU.
[ztpToken]	*string*	JWT token to validate the switch in SecureZTP.

2.499 show hardware external alarm-input

alarms	*list of ExternalAlarm* see 2.499.1	List of alarm statuses.

2.499.1 ExternalAlarm

action	*string*	Alarm action.
alarmId	*integer*	Alarm ID number.
asserted	*boolean*	Alarm asserted.
count **	*integer*	Number of times alarm has asserted. **Since: 4.21.3
description	*string*	Alarm description.
lastAssertTime	*floating point number*	Time of last assertion.
lastDeassertTime	*floating point number*	Time of last deassertion.
polarity	*string*	Alarm polarity.

2.500 show hardware external alarm-input ALARM_ID

see 2.499.1

2.501 show hardware fabric ejector-handle

[ejectorHandleOpenAction]	*enum: log | power-off*	Action performed when ejector handle is opened.

2.502 show hardware forwarding profile

linecards	*table(string) = string*	A mapping between a linecard and its forwarding profile.
systemProfile	*string*	Configured system default forwarding profile.

2.503 show hardware fpga detail

revision 2

systemComponents	*table(string) = FpgaHardwareDetails* see 2.503.1	A mapping of system devices to its FPGAs.

2.503.1 FpgaHardwareDetails

`fpgas`	*table(string) = FpgaHardwareDetail* see 2.503.1.1	Detailed information for the FPGAs in the system.

2.503.1.1 FpgaHardwareDetail

`fpgaClassName`	*string*	Name of FPGA.
`isHitlessResetSupported`	*enum: N/A | True | False*	FPGA support for hitless resets.
`majorVersion`	*integer*	Major version number of FPGA.
`minorVersion`	*integer*	Minor version number of FPGA.

2.504 show hardware fpga error

Could also be an instance of:
FpgaCrcErrorsFixed 2.504.1
FpgaCrcErrorsModular 2.504.1

correctableCrcs	*table(string) = FpgaCrcErrorDetails* see 2.504.1	Maps FPGA name to its correctable CRC-Error details. On modular systems the FPGA name contains the slot number.
fpgaCrcRecoveryMode	*enum: powerCycle | log | autoRepair*	System action on FPGA CRC-Error.
[linecardFpgaCrcRecovery-Mode]	*enum: powerCycle | log*	Linecard action on FPGA CRC-Error.
softwareCorrectedCrcs **	*table(string) = FpgaCrcErrorDetails* see 2.504.1	Maps FPGA name to its software-repaired CRC-Error details. On modular systems the FPGA name contains the slot number. **Since: 4.21.3
uncorrectableCrcs	*table(string) = FpgaCrcErrorDetails* see 2.504.1	Maps FPGA name to its uncorrectable CRC-Error details. On modular systems the FPGA name contains the slot number.

2.504.1 FpgaCrcErrorDetails

count	*integer*	Number of CRC-Error occurrences.
[firstOccurrence]	*floating point number*	First CRC-Error occurrence.
[lastOccurrence]	*floating point number*	Last CRC-Error occurrence.
correctableCrcs	*table(string) = FpgaCrcErrorDetails* see 2.504.1	Maps FPGA name to its correctable CRC-Error details. On modular systems the FPGA name contains the slot number.
fpgaCrcRecoveryMode	*enum: powerCycle | log | autoRepair*	System action on FPGA CRC-Error.
[linecardFpgaCrcRecovery-Mode]	*enum: powerCycle | log*	Linecard action on FPGA CRC-Error.
softwareCorrectedCrcs	*table(string) = FpgaCrcErrorDetails* see 2.504.1	Maps FPGA name to its software-repaired CRC-Error details. On modular systems the FPGA name contains the slot number.
uncorrectableCrcs	*table(string) = FpgaCrcErrorDetails* see 2.504.1	Maps FPGA name to its uncorrectable CRC-Error details. On modular systems the FPGA name contains the slot number.
correctableCrcs	*table(string) = FpgaCrcErrorDetails* see 2.504.1	Maps FPGA name to its correctable CRC-Error details. On modular systems the FPGA name contains the slot number.
fpgaCrcRecoveryMode	*enum: powerCycle | log | autoRepair*	System action on FPGA CRC-Error.
[linecardFpgaCrcRecovery-Mode]	*enum: powerCycle | log*	Linecard action on FPGA CRC-Error.
softwareCorrectedCrcs	*table(string) = FpgaCrcErrorDetails* see 2.504.1	Maps FPGA name to its software-repaired CRC-Error details. On modular systems the FPGA name contains the slot number.
uncorrectableCrcs	*table(string) = FpgaCrcErrorDetails* see 2.504.1	Maps FPGA name to its uncorrectable CRC-Error details. On modular systems the FPGA name contains the slot number.

2.505 show hardware license tpm

family	*string*	The main type/version of the TPM.
firmwareVersion **	*string*	The firmware version of the TPM. **Since: 4.35.2
specDate	*string*	The month, day, and year in which the TPM specification was published.
specLevel	*integer*	The specification level.
specRevision	*floating point number*	The specification revision.
specRevisionStr	*string*	The specification revision.
vendorId	*string*	A vendor identifier that is unique to each TPM manufacturer.
vendorStr	*string*	The vendor id string of the TPM manufacturer.

2.506 show hardware logical-port (pool | POOL_RANGE) status

pools	*table(string) = PoolStatus* see 2.506.1	Mapping between a logical port pool's name and its status.

2.506.1 PoolStatus

allocatedInterfaces **	*list of Interface name*	Interfaces allocated a logical port. **Since: 4.34.1
configured	*integer*	Number of configured ports in the pool.
free	*integer*	Number of free logical ports in the pool.
interfaces	*list of Interface name*	Member interfaces.
maximum	*integer*	Maximum logical ports in the pool.

2.507 show hardware pll [...]

clocks	*table(string) = ClockModel* see 2.507.1	Clock name to clock information.

2.507.1 ClockModel

description	*string*	PLL description.
model	*string*	PLL manufacturer and model.
role	*enum: system | timeSyncFreeRun | phy | timeSync | servo*	PLL function.
state	*enum: initializing | failed | freeRunning | disabled | active*	Current state of the PLL.

2.508 show hardware resource [...]

Could also be an instance of:
TcamHardwareResourceModel 2.508.1.1.1.2

tables	*table(string) = AgentName* see 2.508.1	A mapping of table name to its agents.

2.508.1 AgentName

agents	*table(string) = Unit* see 2.508.1.1	A mapping of agent name to its units.

2.508.1.1 Unit

units	*table(string) = View* see 2.508.1.1.1	A mapping of unit to its views.

2.508.1.1.1 View

views	*table(string) = Table* see 2.508.1.1.1.1	A mapping of view to its hardware table entries.

2.508.1.1.1.1 Table

entries	*list of TableEntry* see 2.508.1.1.1.2	Hardware table entries.

2.508.1.1.1.2 TableEntry

dataFields	*table(string) = string*	A mapping of entry data field attr to field val.
keyFields	*table(string) = string*	A mapping of entry key field attr to field val.
tables	*table(string) = AgentName* see 2.508.1	A mapping of table name to its agents.

2.509 show hardware resource hitbit [...]

requests	*table(string) = StrataCounters.HitBits.Cli.-FlexibleHitbitRequest* see 2.509.1	Mapping from request name to request config.

2.509.1 StrataCounters.HitBits.Cli.FlexibleHitbitRequest

entries	*integer*	Number of requested entries.
[index]	*StrataCounters.HitBits.Cli.-HitBitIndex* see 2.509.1.1	Operation used to calculate which bit should be updated.
[indexObject]	*enum: invalidObj | mcast2HitIndex | l2DstHitIndex | l2SrcHitIndex | mcast1HitIndex | noObj | alpmDstHitIndex*	Value used to compute the index.
requestName	*string*	Name of the request.
status	*enum: pending | invalid | noResources | allocatedUnifiedHitbit | allocatedFlexCounter*	Status of the request.
tables	*list of StrataCounters.HitBits.Cli.-UnifiedHitbitBankInfo* see 2.509.1.3	List of tables used to hold hitbit values.
[trigger]	*StrataCounters.HitBits.Cli.-HitBitTrigger* see 2.509.1.2	Operation used to indicate that hitbit should trigger.

2.509.1.1 StrataCounters.HitBits.Cli.HitBitIndex

index	*StrataCounters.HitBits.Cli.-ValueSource* see 2.509.1.1.1	Operation used to compute bucket for hitbit.
value	*StrataCounters.HitBits.Cli.-ValueSource* see 2.509.1.1.1	Operation used to compute specific bit in bucket.

2.509.1.1.1 StrataCounters.HitBits.Cli.ValueSource

valueA	*StrataCounters.HitBits.Cli.-ObjectSelector* see 2.509.1.1.1.1	Value A.
valueB	*StrataCounters.HitBits.Cli.-ObjectSelector* see 2.509.1.1.1.1	Value B.
valueC	*StrataCounters.HitBits.Cli.-ObjectSelector* see 2.509.1.1.1.1	Value C.

2.509.1.1.1.1 StrataCounters.HitBits.Cli.ObjectSelector

maskSize	*integer*	Size of mask in bits (actual size is this value + 1).
shiftLeft	*integer*	Bits to shift value left indicated by srcField.
shiftRight	*integer*	Bits to shift value right indicated by srcField.
source	*enum: noObj | indexHi | indexLo*	Part of object used to compure bucket or bit index.

2.509.1.2 StrataCounters.HitBits.Cli.HitBitTrigger

mask	*integer*	Mask applied to index before checking trigger.
match	*integer*	Value to trigger hitbit hit.

2.509.1.3 StrataCounters.HitBits.Cli.UnifiedHitbitBankInfo

[request]	*string*	Request name.
[startIndex]	*integer*	Start hitbit index.
tableId	*integer*	Table ID.
tableType	*enum: large | small*	Table type.

2.510 show hardware resource hitbit tables

largeTables	*list of StrataCounters.HitBits.Cli.UnifiedHitbitBankInfo* see 2.509.1.3	Status of large unified hitbit tables.
smallTables	*list of StrataCounters.HitBits.Cli.UnifiedHitbitBankInfo* see 2.509.1.3	Status of large unified hitbit tables.

2.511 show hardware resource l3 interface

see 2.508

2.512 show hardware resource l3 mgroups [...]

groups	*table(numeric string) = MGroupModel* see 2.512.1	A mapping of group ID to multicast groups.

2.512.1 MGroupModel

l2Ports	*list of Interface name*	L2 Ports per multicast group.
l3Ports **	*list of L3PortModel* see 2.512.1.1	L3 Ports per multicast group. **Since: 4.35.2
[vxlanTunnels]	*VxlanTunnelsInfo* see 2.512.1.2	VXLAN Tunnels.

2.512.1.1 L3PortModel

interfaces	*list of Interface name*	L3 replication interfaces this port belongs to.
port	*interface name*	L3 port.

2.512.1.2 VxlanTunnelsInfo

[udpPort]	*integer*	VXLAN UDP Port.
vxlanPresent	*boolean*	VXLAN Tunnel is present.
[vxlanVlans]	*table(numeric string) = VxlanVlanInfo* see 2.512.1.2.1	A mapping of VLAN and list of associated VXLAN Tunnels.

2.512.1.2.1 VxlanVlanInfo

vxlanTunnels	*list of Tunnel* see 2.512.1.2.1.1	List of VXLAN Tunnels.

2.512.1.2.1.1 Tunnel

destinationIp	*IP address*	Tunnel destination IP.
egressInterface	*interface name*	Egress interface.
nexthopDmac	*MAC address*	Underlay nextHop destination MAC address.
nexthopSmac	*MAC address*	Underlay nextHop source MAC address.
sourceIp	*IP address*	Tunnel source IP.

2.513 show hardware resource l3 mroutes

mRoutes	*list of HardwareResourceMroutesEntry* see 2.513.1	Defip routing table, indexed by the entry ID.

2.513.1 HardwareResourceMroutesEntry

group	*IP address*	Multicast group address.
ipmcIndex	*integer*	L3 Multicast index.
l3Iif	*integer*	L3 IIF of the entry.
level1Index	*integer*	Level 1 table entry index.
[level2Index]	*integer*	Level 2 table cell index.
[level2Offset]	*integer*	Level 2 table cell offset in bucket.

[level3Index]	*integer*	Level 3 table cell index.
[level3Offset]	*integer*	Level 3 table cell offset in bucket.
sip	*IP address*	Multicast source address.
vrf	*integer*	VRF of the entry.

2.514 show hardware resource l3 mroutes_1

entries	*list of StrataMcast.CliModel.ShowHwResL3MroutesEntry* see 2.514.1	Multicast routes in ALPM table.

2.514.1 StrataMcast.CliModel.ShowHwResL3MroutesEntry

group	*IP address*	Multicast group address.
ipmcIndex	*integer*	L3 Multicast group index.
l3Iif	*integer*	L3 IIF of the entry.
level1Index	*integer*	Level 1 table entry index.
level2Index	*StrataMcast.CliModel.IndexAndSlot* see 2.514.1.1	Level 2 table index.
level3Index	*StrataMcast.CliModel.IndexAndSlot* see 2.514.1.1	Level 3 table index.
routeHit	*boolean*	Route is hit (identical to route hitbit).
srcIp	*IP address*	Multicast source address.
vrf	*integer*	VRF of the entry.

2.514.1.1 StrataMcast.CliModel.IndexAndSlot

index	*integer*	table cell index.
offset	*integer*	table cell offset in bucket.

2.515 show hardware resource l3 nexthops NEXTHOP_TYPE

see 2.508

2.516 show hardware resource l3 summary

adjSharing	*boolean*	Status of adjacency sharing.
alpmL2BucketsUsed	*integer*	Number of buckets used in L2 ALPM memory.
alpmL2CellsMax	*integer*	Maximum number of cells in L2 ALPM memory.
alpmL2CellsUsed	*integer*	Number of cells used in L2 ALPM memory.
alpmL3BucketsUsed	*integer*	Number of buckets used in L3 ALPM memory.
alpmL3CellsMax	*integer*	Maximum number of cells in L3 ALPM memory.
alpmL3CellsUsed	*integer*	Number of cells used in L3 ALPM memory.
alpmSupported	*boolean*	Whether the ALPM table is supported.
alpmV4Pivots	*integer*	Number of IPv4 pivots.
alpmV4Routes	*integer*	Number of IPv4 routes in ALPM.
alpmV4SubPivots	*integer*	Number of IPv4 sub pivots.
alpmV6Pivots	*integer*	Number of IPv6 pivots.
alpmV6Routes	*integer*	Number of IPv6 routes in ALPM.
alpmV6SubPivots	*integer*	Number of IPv6 sub pivots.
dlbEcmpFlowSetSize **	*integer*	DLB flowset size. **Since: 4.35.2
dlbEnabled **	*boolean*	Whether DLB(Dynamic Load Balancing) is enabled. **Since: 4.35.2
dlbSupported **	*boolean*	Whether DLB(Dynamic Load Balancing) is supported. **Since: 4.35.2
hostTableSupported	*boolean*	Whether a host table is supported.
hostV4Entries	*integer*	Number of /32 IPv4 routes.
hostV4EntriesMax	*integer*	Maximum possible number of /32 IPv4 routes.
hostV4Mcast1Entries	*integer*	Number of IPv4 multicast(*,G) routes.
hostV4Mcast1EntriesMax	*integer*	Maximum possible number of IPv4 multicast(*,G) routes.
hostV4Mcast2Entries	*integer*	Number of IPv4 multicast(S,G) routes.
hostV4Mcast2EntriesMax	*integer*	Maximum possible number of IPv4 multicast(S,G) routes.
hostV6Entries	*integer*	Number of /128 IPv6 routes.
hostV6EntriesMax	*integer*	Maximum possible number of /128 IPv6 routes.
hostV6Mcast1Entries	*integer*	Number of IPv6 multicast(*,G) routes.
hostV6Mcast1EntriesMax	*integer*	Maximum possible number of IPv6 multicast(*,G) routes.
hostV6Mcast2Entries	*integer*	Number of IPv6 multicast(S,G) routes.
hostV6Mcast2EntriesMax	*integer*	Maximum possible number of IPv6 multicast(S,G) routes.
ipV4Routes	*integer*	Number of IPv4 routes.
ipV6Routes	*integer*	Number of IPv6 routes.

l3Intf	*integer*	Number of L3 interfaces.
maxDlbEcmpGroups **	*integer*	Maximum possible DLB ECMP groups. **Since: 4.35.2
maxHosts	*integer*	Maximum possible number of entries in host table.
maxL3Intf	*integer*	Maximum possible number of L3 interfaces.
maxVpEntries	*integer*	Maximum possible number of virtual ports.
mcastGroups	*integer*	Number of multicast replication groups.
mcastGroupsMax	*integer*	Maximum possible number of multicast replication groups.
mcastTableSupported **	*boolean*	Whether the multicast Host table is supported. **Since: 4.34.0
memberTablesShareResource **	*boolean*	Whether underlay and overlay ecmp tables are shared. **Since: 4.34.0
myStnEntries	*integer*	Number of Mystation TCAM entries.
myStnEntriesMax	*integer*	Maximum possible number of Mystation TCAM entries.
narrowMode	*boolean*	status of L2,L3 ALPM banks format.
nhEntries	*integer*	Total number of nexthops.
nhEntriesMax	*integer*	Maximum possible number of nexthops.
nhEntriesShared **	*boolean*	Whether underlay and overlay next hop tables are shared. **Since: 4.34.0
numDlbEnabledEcmpGroups **	*integer*	Number of DLB enabled ECMP groups. **Since: 4.35.2
numOfL2Banks	*integer*	Number of banks in L2 ALPM memory.
numOfL2Buckets	*integer*	Number of buckets in L2 ALPM memory.
numOfL3Banks	*integer*	Number of banks in L3 ALPM memory.
numOfL3Buckets	*integer*	Number of buckets in L3 ALPM memory.
overlayEcmpGroupEntries	*integer*	Number of overlay ECMP groups.
overlayEcmpGroupMax	*integer*	Maximum possible number of overlay ECMP groups.
overlayEcmpMemberEntries	*integer*	Number of overlay ECMP members.
overlayEcmpMemberMax	*integer*	Maximum possible number of overlay ECMP members.
overlayEntries	*integer*	Number of overlay nexthops.
overlayEntriesMax	*integer*	Maximum possible number of overlay nexthops.
replHeadEntries	*integer*	Number of MMU repl head entries.
replHeadEntriesMax	*integer*	Maximum possible number of MMU repl head entries.
replListEntries	*integer*	Number of MMU repl list entries.
replListEntriesMax	*integer*	Maximum possible number of MMU repl list entries.
routeDeletionDelay	*floating point number*	Route deletion delay.
tcamEntries	*integer*	Number of entries in TCAM.

tcamEntriesMax	*integer*	Maximum possible number of entries in TCAM.
threeLevelAlpm	*boolean*	status of 3-Level ALPM.
tunnelEcmpGroupEntries **	*integer*	Number of Vxlan Overlay ECMP groups. **Since: 4.35.0
tunnelEcmpGroupMax **	*integer*	Maximum possible number of Vxlan Overlay ECMP groups. **Since: 4.35.0
tunnelEcmpMemberEntries **	*integer*	Number of Vxlan Overlay ECMP members. **Since: 4.35.0
tunnelEcmpMemberMax **	*integer*	Maximum possible number of Vxlan Overlay ECMP members. **Since: 4.35.0
tunnelNhEntries **	*integer*	Number of tunnel nexthops. **Since: 4.34.0
tunnelNhEntriesMax **	*integer*	Maximum possible number of tunnel nexthops. **Since: 4.34.0
tunnelNhSummaryEnabled **	*boolean*	Whether tunnel nexthops summariesare enabled. **Since: 4.34.0
underlayEcmpGroupEntries	*integer*	Number of underlay ECMP groups.
underlayEcmpGroupMax	*integer*	Maximum possible number of underlay ECMP groups.
underlayEcmpMemberEntries	*integer*	Number of underlay ECMP members.
underlayEcmpMemberMax	*integer*	Maximum possible number of underlay ECMP members.
underlayEntries	*integer*	Number of underlay nexthops.
underlayEntriesMax	*integer*	Maximum possible number of underlay nexthops.
unprogrammedV4Routes	*integer*	Number of unprogrammed IPv4 routes.
unprogrammedV6Routes	*integer*	Number of unprogrammed IPv6 routes.
urpfEnabled	*boolean*	Status of source lookup.
usedHosts	*integer*	Number of entries in host table.
vpEntries	*integer*	Number of virtual ports.

2.517 show hardware resource mapping table TABLE [...]

tables	*table(string) = Table* see 2.517.1	Hardware mapping tables, keyed by their name.

2.517.1 Table

groupFormation	*list of TableGroup* see 2.517.1.1	Table groups.
[instances]	*list of integer*	Instance ids.
uniformity	*enum: divergent | uniform*	Value of instance programming.

2.517.1.1 TableGroup

[depth]	*integer*	Depth of the table.
physicalTable	*list of MemoryData* see 2.517.1.1.1	Memories/Registers within the table.

2.517.1.1.1 MemoryData

[maxIndex]	*integer*	Maximum entry index of the depth of the memory/register.
memName	*string*	Name of the memory/register.
[minIndex]	*integer*	Mininum entry index of the depth of the memory/register.
[width]	*integer*	Width of the memory/register in bytes.

2.518 show hardware resource tcam [...]

see 2.508.1.1.1.2

2.519 show hardware resource vlan

units	*table(numeric string) = HwResourceVlan* see 2.519.1	A mapping between a Unit ID and its VLAN resources.

2.519.1 HwResourceVlan

vlans	*table(numeric string) = VlanHwTableInfo* see 2.519.1.1	A mapping between a VLAN ID and its resources.

2.519.1.1 VlanHwTableInfo

classId	*integer*	Opaque control identifier assigned for IFP key generation.
floodId	*integer*	Unicast/broadcast destination.
[l3Interface]	*integer*	L3 Incoming Interface, allowing VXLAN bridging.
membership	*list of Interface name*	Interfaces belonging to the VLAN.
stg	*integer*	Spanning Tree Protocol identifier to prevent routing loops.
[vni]	*integer*	24-bit VXLAN VNI that determines which VLAN the packet is mapped to for bridging.

2.520 show hardware resource vxlan mac [...]

vlans	*table(numeric string) = VxlanVlanInfo* see 2.520.1	Collection of Vxlan VLANs, keyed by VLAN.

2.520.1 VxlanVlanInfo

macs	*table(MAC address) = VxlanMacInfo* see 2.520.1.1	Collection of Vxlan Mac Info, keyed by remote VTEP Mac.
vni	*integer*	Vxlan Network Identifier.

2.520.1.1 VxlanMacInfo

nexthops	*list of NexthopInfo* see 2.520.1.1.1	Collection of Next Hop Info.
sourceIp	*IP address*	IP address of source VTEP.
udpDstPort	*integer*	Remote VTEP UDP Port number.
[vtepGroupId]	*integer*	Optional ECMP Group ID, n/a if single VTEP.

2.520.1.1.1 NexthopInfo

destinationIp	*IP address*	IP address of remote VTEP.
destinationVirtualPort	*integer*	Destination virtual port (DVP).
egressInterface	*interface name*	Core port interface name.
nexthopDstMac	*MAC address*	Nexthop destination MAC address.
nexthopSrcMac	*MAC address*	Nexthop source MAC address.

2.521 show hardware speed-group | SPEED-GROUP configurations

groups	*table(string) = SpeedGroupCap* see 2.521.1	Mapping between a speed group's name and its capabilities.

2.521.1 SpeedGroupCap

availableSpeed-Configurations	*table(string) = string*	Mapping between a SerDes speed and available speed configurations.
interfaces	*list of Interface name*	Group member interfaces.

2.522 show hardware speed-group | SPEED-GROUP status

groups	*table(string) = SpeedGroupStatus* see 2.522.1	Mapping between a speed group's name and its status.

2.522.1 SpeedGroupStatus

activeSerdesSpeeds	*list of SerdesSpeed* see 2.522.1.1	Active serdes speeds.
configuredSerdesSpeeds	*list of SerdesSpeed* see 2.522.1.1	Configured serdes speeds.

defaultSerdesSpeeds	*list of SerdesSpeed* see 2.522.1.1	Default serdes speeds.
interfaces	*list of Interface name*	Group member interfaces.
masterInterface	*interface name*	Master interface of the group.
[speedGroupAutoMode] **	*boolean*	Auto-configure speed-group setting. **Since: 4.28.0
supportedSerdesSpeeds	*list of SerdesSpeed* see 2.522.1.1	Supported serdes speeds.

2.522.1.1 SerdesSpeed

speed	*enum: 200g | 25g | 10g | 50g | 100g | auto*	SerDes speed.

2.523 show hardware system forwarding-chips

chips	*table(string) = ForwardingChip* see 2.523.1	Forwarding chips on this system, keyed by slot and chip label.

2.523.1 ForwardingChip

chipLabel	*string*	Chip label.
chipName	*string*	Chip name.
chipVer	*string*	Chip version.
forwardingAgent	*string*	Forwarding agent.
slotLabel	*string*	Slot label.

2.524 show hardware system spi-chips

chips	*table(string) = SpiChip* see 2.524.1	SPI flash chips on this system, keyed by slot and chip name.

2.524.1 SpiChip

[chipId]	*integer*	Chip JEDEC ID.
[chipModel]	*string*	Chip model.
chipName	*string*	Chip name.
[chipSize]	*integer*	Chip capacity in megabits.
[chipVendor]	*string*	Chip vendor.
slot	*string*	Slot containing chip.

2.525 show hardware tcam profile ((PROFILE ((feature (((acl vlan ip) | (acl vlan ipv6) | (acl vlan ipv6 egress) | (acl subintf ip) | (acl subintf ipv6) | (acl subintf mac) | (acl port ip) | (acl port ipv6) | (acl port mac) | (acl gre tunnel interface ip) | (acl port ip egress) | (acl port ip egress disabled) | (acl port ip egress mpls-tunnelled-match) | (acl port ipv6 egress) | (acl port ipv6 egress no-recirculation) | (acl port ipv6 source-only egress) | (acl vlan ipv6 source-only egress) | (acl port mac egress) | (acl vlan ip egress) | (acl port ip ingress) | (acl vlan ip ingress) | (acl port ipv6 ingress) | (acl vlan ipv6 ingress) | (acl port mac ingress) | (acl port ipv6 source-only ingress) | (acl tunnel interface ip) | (acl tunnel interface ipv6) | (adaptive-copp ipv4) | (pbr ip) | (pbr ipv6) | (pbr mpls) | (pbr subintf ip) | (pbr subintf ipv6) | (pbr tunnel interface ip) | (tunnel ipv4) | (tunnel vxlan) | (tunnel vxlan multicast mlag) | (tunnel vxlan multi-homing multicast) | (tunnel vxlan multi-homing multicast peg) | (tunnel vxlan multi-homing) | (tunnel vxlan multi-homing domain remote) | (tunnel vxlan routing) | (tunnel vxlan routing v6-underlay) | (tunnel vxlan vni policing) | (qos ip) | (qos ipv6) | (qos subintf ip) | (qos subintf ipv6) | (qos port ip) | (qos port ipv6) | (qos vlan ip) | (qos vlan ipv6) | (qos port ip egress) | (qos vlan ip egress) | (qos vlan ipv6 egress) | (qos mac) | (tapagg port) | (tapagg ip) | (tapagg ipv6) | (tapagg mac) | (tapagg tunnel termination) | (mirror ip) | (mirror ip egress) | (mirror ipv6) | (mirror ipv6 egress) | (mirror mac) | (mirror1 ip ingress) | (mirror1 ipv6 ingress) | (mirror1 mac ingress) | (mirror2 ip ingress) | (mirror2 ipv6 ingress) | (mirror2 mac ingress) | (mirror3 ip ingress) | (mirror3 ipv6 ingress) | (mirror3 mac ingress) | (mirror4 ip ingress) | (mirror4 ipv6 ingress) | (mirror4 mac ingress) | (mirror mpls-over-gre ip) | (mirror mpls-over-gre ipv6) | (mirror port egress rate-limit) | (mirror congestion) | (hash mpls-over-gre inner ipv4) | (hash mpls-over-gre inner ipv6) | (evpn mpls irb) | (evpn mpls multi-homing) | flow | (flow mac) | (flow mac vlan-rewrite) | (flow http) | (flow mac-ipv4-l4) | (flow ipv6) | (flow ipv6 l4) | (flow ipv6 vlan-tag) | cbf | (flex-route) | (counter multicast ipv4) | mpls | (mpls fallback ipv4 preserve dscp) | (mpls fallback ipv6 preserve dscp) | (mpls pop ingress) | (mpls pop ingress multicast) | (counter fabric audit) | (counter lfib) | (counter vlan-interface ingress) | (counter vlan traffic-class) | (counter vtep decap) | dot1x | (flow-spec port ipv4) | (flow-spec port ipv6) | (l2-protocol forwarding) | ipsec | (ipsec egress padding-removal) | (traffic-policy cpu ipv4) | (traffic-policy cpu ipv6) | (traffic-policy cross-field-summarization ipv4) |

2.525.1 ProfileModel

[actionOverridesSystemRule] **	*list of string*	Enable action to override system rules. **Since: 4.28.0
[associatedLinecards]	*list of string*	A mapping between TCAM profile and linecards.
counterObjectConfigStages **	*list of string*	List of TCAM counter object configuration per stage. **Since: 4.34.1
features	*table(string) = FeatureModel* see 2.525.1.1	List of features in current TCAM profile.
[globalFieldSizes] **	*table(string) = integer*	List of global key field size configurations. **Since: 4.30.2

2.525.1.1 FeatureModel

actionPriority **	*integer*	Relative action priority of current feature. **Since: 4.27.1
actions	*list of string*	List of actions configured in current feature.
actionsExcluded **	*list of string*	List of implicit actions excluded from the current feature. **Since: 4.34.2
counterObjectReservationStages **	*list of string*	List of TCAM counter object reservation configuration per stage. **Since: 4.34.1
keyFields	*list of string*	List of key fields configured in current feature.
keyFieldsExcluded **	*list of string*	List of implicit key fields excluded from the current feature. **Since: 4.34.2
[keyPolicerUnsharedActionSize] **	*integer*	Numeric policy policer unshared action size for current feature. **Since: 4.27.1
[keyPolicerUnsharedQualSize] **	*integer*	Numeric policy policer unshared qualifier size for current feature. **Since: 4.27.1
keyPortQualSize **	*integer*	Numeric port qualifier size for current feature. **Since: 4.23.0
[keyPrefixLabelSize] **	*integer*	Numeric IP prefix lookup label size for current feature. **Since: 4.26.2
[keyPrefixLpmLabelSize] **	*integer*	Numeric IP prefix longest prefix match lookup label size for current feature. **Since: 4.26.2
keySizeLimit	*integer*	Maximum number of bits used as key.
packetTypes **	*list of string*	List of packet types in current TCAM profile. **Since: 4.20.5
sequence	*integer*	Numeric sequence of current feature.

sliceReservationStages **	*list of string*	List of TCAM slice reservation configuration per stage. **Since: 4.29.0

2.526 show hardware tcam profile PROFILE

[actionOverridesSystemRule] **	*list of string*	Enable action to override system rules. **Since: 4.28.1
[associatedLinecards]	*list of string*	List of TCAM profile associated linecards.
counterObjectConfigStages **	*list of string*	List of TCAM counter object configuration per stage. **Since: 4.34.1
features	*table(string) = FeatureModel* see 2.525.1.1	A mapping of features in current TCAM profile.
profileName	*string*	Name of the profile.

2.527 show hostname

fqdn	*string*	The fully qualified domain name of the switch.
hostname	*string*	The current hostname of the switch.

2.528 show hosts

domainList	*list of string*	List of additional domains to lookup domains with.
[domainName]	*string*	The domain name that the listed hosts are associated with.
hosts	*table(string) = IpAddresses* see 2.528.1	A mapping between host names and their IP addresses.
nameServerConfigs **	*list of NameServerConfig* see 2.528.2	List of configured name servers. **Since: 4.26.0
nameServers	*list of string*	List of domain name servers used to resolve names.

2.528.1 IpAddresses

ipv4Addresses	*list of IPv4 address*	List of IPV4 addresses.
ipv6Addresses	*list of IPv6 address*	List of IPV6 addresses.

2.528.2 NameServerConfig

ipAddr	*IP address*	Name server IP address.
priority	*integer*	Name server priority.
vrf	*string*	Name server VRF.

2.529 show icmp error extensions [...]

v4Active	*boolean*	Active for IPv4 address family.
v6Active	*boolean*	Active for IPv6 address family.
vrfs	*table(string) = ErrorResponderVrfModel* see 2.529.1	ICMP Error responder information for each enabled VRF.

2.529.1 ErrorResponderVrfModel

[v4AclActive]	*boolean*	IPv4 ACL active on VRF.
[v4AclName]	*string*	Name of ACL configured for IPv4 traffic.
[v4ExtensionsActive]	*boolean*	Extensions active for IPv4 address family.
v4Responding	*boolean*	Responding for IPv4 address family.
[v6AclActive]	*boolean*	IPv6 ACL active on VRF.
[v6AclName]	*string*	Name of ACL configured for IPv6 traffic.
[v6ExtensionsActive]	*boolean*	Extensions active for IPv6 address family.
v6Responding	*boolean*	Responding for IPv6 address family.

2.530 show icmp error extensions counters [...]

[ipv4Counters]	*ErrorResponderAfCountersModel* see 2.530.1	ICMPv4 Error responder counters.
[ipv6Counters]	*ErrorResponderAfCountersModel* see 2.530.1	ICMPv6 Error responder counters.

2.530.1 ErrorResponderAfCountersModel

dequeued	*integer*	Total packet objects dequeued by IcmpResponder.
enqueued	*integer*	Packet objects enqueued by kernel.
invalidPktObj	*integer*	Invalid packet objects dequeued by IcmpResponder.
invalidVrfInPktObj	*integer*	Packet info object could not be mapped to a valid VRF.
originalDatagramInPktObj-TooShort	*integer*	Original datagaram too short in the dequeued packet object.
packetsProcessed	*integer*	Packet info objects that pass all checks.
queueDropped	*integer*	Packet objects queue-dropped by kernel.
vrfs	*table(string) = ErrorResponderVrfCountersModel* see 2.530.1.1	ICMP Error responder counters for each enabled VRF.

2.530.1.1 ErrorResponderVrfCountersModel

extendedIcmpErrorsSent	*integer*	ICMP errors sent out with extensions.
icmpErrorsSent	*integer*	ICMP errors sent out without extensions.

packetsProcessed	*integer*	Valid packet objects received from kernel on this VRF.
socketErrors	*integer*	ICMP error packets dropped by the socket.
socketNotFound **	*integer*	Packet objects dropped because socket was not yet initialized. **Since: 4.33.1

2.531 show icmp probe

vrfs	*table(string) = ProbeResponderModel* see 2.531.1	Probe responder information for each VRF.

2.531.1 ProbeResponderModel

allowAddr	*boolean*	Allow query by interface address.
allowIfindex	*boolean*	Allow query by interface index.
allowIfname	*boolean*	Allow query by interface name.
allowRemote	*boolean*	Allow query by remote node address.
badExtensionHeader	*integer*	PROBE requests received with a malformed ICMP extension header.
badExtensionObject	*integer*	PROBE requests received with a bad ICMP extension object.
codes	*table(numeric string) = ProbeResponderCodeModel* see 2.531.1.1	Counts of response packets per error or non-error code.
enabled	*boolean*	Enabled.
incorrectExtensionChecksum	*integer*	PROBE requests received with an incorrect ICMP extension checksum.
incorrectIcmpChecksum	*integer*	PROBE requests received with an incorrect ICMP checksum.
interfaceLookupFailed	*integer*	PROBE requests for which we could not determine the interface.
lastTxError	*string*	The most recent socket error when sending a response.
pktTooShort	*integer*	PROBE requests received but too short.
queueTooLong	*integer*	PROBE requests dropped due to size of queue.
remoteRequestMalformed	*integer*	PROBE requests for a remote node but specify an interface name or index.
requestTypeNotAllowed	*integer*	PROBE requests received with a request type that is not allowed.
requestsReceived	*integer*	PROBE requests received.
responsesSent	*integer*	PROBE responses sent.
txErrors	*integer*	PROBE responses that could not be sent due to a socket error.
wrongVrfRequested	*integer*	PROBE requests which requested an interface in a different VRF.

2.531.1.1 ProbeResponderCodeModel

count	*integer*	Number of packets with this code.
description	*string*	Description of code.

2.532 show idprom (transceiver | interface) [...]

interfaces	*table(Interface name) = InterfacesTransceiver-IdpromPages* see 2.532.1	Mapping between interface name and the eeprom.

2.532.1 InterfacesTransceiverIdpromPages

pages	*table(string) = Interfaces-TransceiverIdpromData* see 2.532.1.1	Mapping of page name to register.
[partialIdpromDumpError] **	*boolean*	Flag indicating error while reading some Idprom pages. **Since: 4.33.1

2.532.1.1 InterfacesTransceiverIdpromData

regWidth	*integer*	Eeprom register width in bits.
registers	*list of integer*	Eeprom data as an integer.

2.533 show igmp snooping querier [...]

vlans	*table(numeric string) = IgmpSnooping.Cli.Igmp-SnoopingVlanQuerier* see 2.533.1	Mapping VLAN ID to the vlan querier info.

2.533.1 IgmpSnooping.Cli.IgmpSnoopingVlanQuerier

igmpVersion	*enum: v1 | v3 | unknown | v2*	Version of IGMP snooping querier in the VLAN.
querierAddress	*IPv4 address*	Address of IGMP querier in the VLAN.
querierInterface	*interface name*	Interface where the querier is located.
queryResponseInterval	*floating point number*	Effective maximum period a recipient can wait before responding with a membership report in seconds.

2.534 show igmp snooping querier counters [...]

vlans	*table(numeric string) = IgmpSnoopingVlanQuerier-Counters* see 2.534.1	Map Vlan id to Vlan counter info.

2.534.1 IgmpSnoopingVlanQuerierCounters

errorPacketReceived	*integer*	Number of error packets received.
igmpVersion	*enum: v1 | unknown | v3 | v2*	Version of IGMP snooping querier in the vlan.
operationalState	*enum: querier | non-querier*	Operational state of querier in the vlan.
otherPacketReceived	*integer*	Number of other packets received.
querierAddress	*IPv4 address*	Address of IGMP querier in the Vlan.
totalGeneralQueriesSent	*integer*	Total number of general queries sent.
v1QueriesReceived	*integer*	Number of v1 queries received.
v1QueriesSent	*integer*	Number of v1 general queries sent.
v1ReportReceived	*integer*	Number of v1 reports received.
v2LeaveReceived	*integer*	Number of v2 leaves received.
v2QueriesReceived	*integer*	Number of v2 queries received.
v2QueriesSent	*integer*	Number of v2 general queries sent.
v2ReportReceived	*integer*	Number of v2 reports received.
v3GSQueriesSent	*integer*	Number of v3 group specific queries sent.
v3GSSQueriesSent	*integer*	Number of v3 group and source specific queries sent.
v3QueriesReceived	*integer*	Number of v3 queries received.
v3QueriesSent	*integer*	Number of v3 general queries sent.
v3ReportReceived	*integer*	Number of v3 reports received.

2.535 show igmp snooping querier membership [...]

vlans	*table(numeric string) = IgmpSnoopingVlanQuerierMembership* see 2.535.1	Mapping vlan id with querier membership info.

2.535.1 IgmpSnoopingVlanQuerierMembership

addRandomDelayToTimer	*boolean*	True if random delay added to expiry timers.
[generalQueryExpiryTime]	*floating point number*	IGMP general query timer expiry in seconds.
[groupMembershipInterval]	*floating point number*	Period after which multicast group membership expires in seconds.
groups	*list of MulticastGroupInfo* see 2.535.1.2	Multicast group information.
[lastMemberQueryTime]	*floating point number*	Total time to send last member query messages in seconds.
[olderHostPresentInterval]	*floating point number*	Time-out for transitioning a group back to IGMPv3 mode once an older version report is received in seconds.
[otherQuerierExpiryTime]	*floating point number*	Other querier present timer expiry in seconds.
[otherQuerierPresentInterval]	*floating point number*	Period for which multicast router waits before becoming a querier in seconds.
querierStatus	*IgmpQuerierStatusVlan* see 2.535.1.1	Querier status information in the vlan.
robustness	*integer*	Number of queries sent to age out a port's membership in group.

2.535.1.1 IgmpQuerierStatusVlan

adminState	*enum: enabled | disabled*	State of IGMP querier in the Vlan.
[lastMemberQueryCount]	*integer*	Number of query messages that are sent before removing from group state and discontinue multicast transmissions in the vlan.
[lastMemberQueryInterval]	*floating point number*	Transmission frequency set for query messages to the group when last member on a particular group sends leave message in seconds.
operationalState	*enum: querier | non-querier*	Operational state of querier in the Vlan.
querierAddress	*IP address*	Ip Address of querier on the vlan.
querierExpiryTime	*floating point number*	Querier's expiry time in seconds.
queryInterval	*floating point number*	Period between IGMP Membership Query messages in seconds.
queryResponseInterval	*floating point number*	Effective maximum period a recipient can wait before responding with a Membership Report in seconds.
[startupQueryCount]	*integer*	Number of query messages that querier in the vlan sends during the startup query interval.

[startupQueryInterval]	*floating point number*	Period between query messages that querier in the vlan sends upon startup in seconds.
version	*enum: v1 | unknown | v3 | v2*	Version of IGMP querier on the Vlan.

2.535.1.2 MulticastGroupInfo

[creationTime]	*floating point number*	UTC time at which the group was created.
[expiryTime]	*floating point number*	UTC time at which the group will expire.
filterMode	*enum: include | exclude*	Filter mode of multicast group.
groupAddress	*IPv4 address*	Address of the multicast group.
igmpVersion	*enum: v1 | unknown | v3 | v2*	Version of IGMP snooping querier.
lastReporter	*IPv4 address*	The IP Address of the latest host who joined this group.
[sources]	*list of GroupSourceInfo* see 2.535.1.2.1	Sources belong to the group and its information.

2.535.1.2.1 GroupSourceInfo

[creationTime]	*floating point number*	UTC time at which this source was created.
expired	*boolean*	True if the source address expires.
[expiryTime]	*floating point number*	UTC time at which this source will expire.
sourceAddress	*IPv4 address*	Source address for multicast group.

2.536 show igmp snooping querier membership vlan VLAN_ID group IPADDR

sources	*list of GroupSourceInfo* see 2.535.1.2.1	Sources belong to the group and its information.

2.537 show igmp snooping querier status [...]

[adminState]	*enum: enabled | disabled*	State of global IGMP querier.
[lastMemberQueryCount]	*integer*	Number of query messages that are sent before removing from group state and discontinue multicast transmissions.
[lastMemberQueryInterval]	*floating point number*	Transmission frequency set for query messages to the group when last member on a particular group sends leave message in seconds.
[querierAddress]	*IPv4 address*	Address of global IGMP querier.
[querierExpiryTime]	*floating point number*	Querier's expiry time in seconds.
[queryInterval]	*floating point number*	Period between IGMP Membership Query messages sent from the global querier in seconds.
[queryResponseInterval]	*floating point number*	Effective maximum period a recipient can wait before responding with a Membership Report in seconds.

[robustness]	*integer*	Number of queries sent to age out a port's membership in group.
[startupQueryCount]	*integer*	Number of query messages that the querier sends during the startup query interval.
[startupQueryInterval]	*floating point number*	Period between query messages that the querier sends upon startup in seconds.
vlans	*table(numeric string) = IgmpQuerierStatusVlan* see 2.535.1.1	Map the vlan id with its querier info.

2.538 show installed-extensions

extensions	*table(string) = InstallationStatus* see 2.538.1	Maps the extension names to their statuses.

2.538.1 InstallationStatus

forced	*boolean*	Whether the installed extension is forced.

2.539 show interfaces (counters bins) | (counters bins (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

interfaces	*table(Interface name) = InterfaceInOutBinsCounters* see 2.539.1	Mapping between an interface and counter bins.

2.539.1 InterfaceInOutBinsCounters

[inBinsCounters]	*InterfaceBinsCounters* see 2.539.1.1	counter bins for in frames.
[outBinsCounters]	*InterfaceBinsCounters* see 2.539.1.1	counter bins for out frames.

2.539.1.1 InterfaceBinsCounters

frames1024To1522Octet	*integer*	counter bin 1024-1522 bytes.
frames128To255Octet	*integer*	counter bin 128-255 bytes.
frames1523ToMaxOctet	*integer*	counter bin 1524-Max bytes.
frames256To511Octet	*integer*	counter bin 256-511 bytes.
frames512To1023Octet	*integer*	counter bin 512-1023 bytes.
frames64Octet	*integer*	counter bin 64 bytes.
frames65To127Octet	*integer*	counter bin 65-127 bytes.

2.540 show interfaces (counters errors) | (counters errors (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

interfaceErrorCounters	*table(Interface name) = ErrorCounters* see 2.540.1	Mapping between an interface and error counters.

2.540.1 ErrorCounters

alignmentErrors	*integer*	Alignment errors.
fcsErrors	*integer*	FCS errors.
frameTooLongs	*integer*	Frame too long errors.
frameTooShorts	*integer*	Frame too short errors.
inErrors	*integer*	Input errors.
outErrors	*integer*	Output errors.
symbolErrors	*integer*	Symbol Errors.

2.541 show interfaces (counters half-duplex) | (counters half-duplex (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

intfHalfDuplexErrorCounters	*table(Interface name) = HalfDuplexErrorCounters* see 2.541.1	Mapping between an interface and half-duplex error counters.

2.541.1 HalfDuplexErrorCounters

deferredTransmissions	*integer*	Deferred transmissions.
excessiveCollisions	*integer*	Excessive collisions.
lateCollisions	*integer*	Late collisions.
multipleCollisionFrames	*integer*	Multiple collision frames.
singleCollisionFrames	*integer*	Single collision frames.

2.542 show interfaces (counters ingress acl drop) | (counters ingress acl drop (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

interfaces	*table(Interface name) = InterfacesCounterAclDrop* see 2.542.1	Mapping between an interface and ACL drop counters.

2.542.1 InterfacesCounterAclDrop

`aclDrops`	*integer*	Packets denied by an ACL.

2.543 show interfaces (error-correction) | (error-correction (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switch-card MODSLOT_SWITCHCARD)))) [...]

interfaceErrCorrStatuses	*table(Interface name)* = *InterfaceErrorCorrection-Status* see 2.543.1	Mapping between an interface and error correction information.

2.543.1 InterfaceErrorCorrectionStatus

[coherentEncoding-Configured] **	*enum: openFec* | *staircaseOverhead7Percent* | *softDecisionOverhead25-PercentBch* | *default* | *reedSolomonG709* | *softDecisionOverhead15-Percent* | *softDecisionOverhead20-Percent* | *concatenatedFec* | *softDecisionOverhead25-Percent*	Configured coherent error-correction encoding. **Since: 4.21.0
[concatenatedFecAvailable] **	*boolean*	True if C-FEC is available. **Since: 4.26.0
errCorrEncodingStatus	*enum: openFec* | *softDecisionOverhead25-Percent* | *unknown* | *staircaseOverhead7Percent* | *softDecisionOverhead25-PercentBch* | *none* | *fireCode* | *reedSolomonG709* | *softDecisionOverhead15-Percent* | *softDecisionOverhead20-Percent* | *passthrough* | *concatenatedFec* | *disabled* | *reedSolomon*	Current error correction encoding state.
fecEncodingConfigDisabled	*boolean*	True if error correction is disabled. When set, all other configured encoding values are ignored and should be False.
fecEncodingConfigFireCode-Enabled	*boolean*	True if Fire code (BASE-R) FEC, is enabled.
fecEncodingConfigReed-Solomon544Enabled **	*boolean*	True if Reed-Solomon FEC (544), is enabled. **Since: 4.21.0
fecEncodingConfigReed-SolomonEnabled	*boolean*	True if Reed-Solomon FEC (528), is enabled.
fecEncodingFireCode-Available	*boolean*	True if Fire code (BASE-R) FEC, is available.
fecEncodingPassthrough-Available **	*boolean*	True if FEC passthrough is available. **Since: 4.35.2

fecEncodingReedSolomon544-Available **	*boolean*	True if RS-FEC-544 is available. **Since: 4.21.0
fecEncodingReedSolomon-Available	*boolean*	True if RS-FEC-528 is available.
[openFecAvailable] **	*boolean*	True if Open FEC is available. **Since: 4.25.1
[reedSolomonG709Available] **	*boolean*	G.709 Reed-Solomon FEC. **Since: 4.21.0
[softDecisionOverhead15-PercentAvailable] **	*boolean*	True if Soft Decision 15% overhead FEC is available. **Since: 4.21.0
[softDecisionOverhead20-PercentAvailable] **	*boolean*	True if Soft Decision 20% overhead FEC is available. **Since: 4.21.0
[softDecisionOverhead25-PercentAvailable] **	*boolean*	True if Soft Decision 25% overhead FEC is available. **Since: 4.21.0
[softDecisionOverhead25-PercentBchAvailable] **	*boolean*	True if Soft Decision 25% overhead BCH FEC is available. **Since: 4.21.0
[staircaseOverhead7Percent-Available] **	*boolean*	True if Staircase 7% overhead FEC is available. **Since: 4.21.0

2.544 show interfaces (flow-control) | (flow-control (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

see 2.459

2.545 show interfaces (hardware default) | (hardware default (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switch-card MODSLOT_SWITCHCARD)))) [...]

interfaces	*table(Interface name) = InterfaceCapabilities-DefaultData* see 2.545.1	A mapping of interfaces to their capabilities defaults information.

2.545.1 InterfaceCapabilitiesDefaultData

[autoNegotiationClause28]	*list of EthSpeedLanesDuplex* see 2.545.1.1.1	List of speed/lane count/duplex triplets at which this interface can perform clause 28 auto negotiation. A missing entry indicates auto negotiation capabilities are unknown.
[autoNegotiationClause37]	*list of EthSpeedLanesDuplex* see 2.545.1.1.1	List of speed/lane count/duplex triplets at which this interface can perform clause 37 auto negotiation. A missing entry indicates auto negotiation capabilities are unknown.
[autoNegotiationClause73]	*AutonegClause73-Capabilities* see 2.545.1.1	List of speed/lane count/duplex triplets at which this interface can perform clause 73 auto negotiation. A missing entry indicates auto negotiation capabilities are unknown.
[coherentModes]	*list of CoherentMode* see 2.545.1.2	List of modulation and coherent error-correction capabilities for this interface.
[coherentTributaries] **	*list of CoherentTributary* see 2.545.1.3	List of tributaries which may be mapped at each line rate. **Since: 4.26.2
[hasAutoneg] **	*boolean*	This interface supports speed auto negotiated. **Since: 4.23.1
modes	*list of EthIntfMode* see 2.545.1.4	List of link-mode capabilities for this interface.
rxFlowControl	*FlowControlCapabilities* see 2.545.1.5	The rx flow control capabilities of this interface.
[speedGroup]	*SpeedGroup* see 2.545.1.6	Speed Group Id and range of member interfaces.
switchModelName	*string*	Model name of the switch.
transceiverType	*string*	Type of the inserted transceiver.
txFlowControl	*FlowControlCapabilities* see 2.545.1.5	The tx flow control capabilities of this interface.

2.545.1.1 AutonegClause73Capabilities

consortium	*list of EthSpeedLanesDuplex* see 2.545.1.1.1	List of speed/lane count/duplex triplets capable of Consortium defined Clause 73 auto negotiation.
ieee	*list of EthSpeedLanesDuplex* see 2.545.1.1.1	List of speed/lane count/duplex triplets capable of IEEE defined Clause 73 auto negotiation.

2.545.1.1.1 EthSpeedLanesDuplex

[auto] **	*boolean*	This speed is auto negotiated. **Since: 4.23.1
[duplex]	*enum: full | half | unknown*	Duplex communication capabilities with this speed.
[laneCount]	*integer*	Number of lanes on the interface.
[speed]	*enum: 2p5Gbps | 400Gbps | 40Gbps | 1p6Tbps | Hg21Gbps | 10Mbps | 1Gbps | 5Gbps | 200Gbps | Hg11Gbps | Hg106Gbps | Hg27Gbps | 100Gbps | 10Gbps | 20Gbps | Hg42Gbps | 800Gbps | 25Gbps | Hg53Gbps | Unknown | 100Mbps | 50Gbps*	Interface speed.

2.545.1.2 CoherentMode

[defaultErrorCorrection]	*enum: C-FEC | O-FEC | RS G.709 | SD 25% BCH | SC 7% | SD 20% | SD 25% | SD 15%*	Default error correction.
[defaultLineRate] **	*enum: 300G | 100G | 200G | 400G*	Default line rate. **Since: 4.26.0
[defaultModulation]	*enum: 8QAM | 16QAM | none | DP-QPSK*	Default modulation type.
errorCorrections	*list of string*	List of coherent error-correction types available while using the corresponding modulation.
lineRates **	*list of string*	List of coherent line rate types available while using the corresponding modulation. **Since: 4.26.0
modulation	*enum: 8QAM | 16QAM | none | DP-QPSK*	Modulation type.

2.545.1.3 CoherentTributary

[defaultTributary]	*integer*	Default tributary.
[lineRate]	*enum: 300G | 100G | 200G | 400G*	Data rate of coherent optical link.
tributaries	*list of integer*	List of tributaries available while using the corresponding line rate.

2.545.1.4 EthIntfMode

[defaultErrorCorrection]	*enum: Passthrough | ReedSolomon544 | FireCode | Disabled | ReedSolomon*	Default error correction.
[defaultLinkMode]	*boolean*	This is the default link mode for this interface.

[errorCorrections]	*list of string*	List of error-correction types capable of running with this speed.
[link]	*EthSpeedLanesDuplex* see 2.545.1.1.1	Interface speed and communication mode.
[pllIncompatible] **	*boolean*	This link mode is incompatible for this interface. **Since: 4.23.1

2.545.1.5 FlowControlCapabilities

autoNegotiationPause	*boolean*	True if we have pause capability for auto negotiation.
flowControl	*enum: Capable | Unknown | Incapable*	Flow control capability.

2.545.1.6 SpeedGroup

groupId	*string*	Speed group Id.
intfList	*list of Interface name*	List of speed group interface members.

2.546 show interfaces (l2 mtu) | (l2 mtu (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

interfaceL2Mtus	*table(Interface name) = L2Mtu* see 2.546.1	Mapping between an interface and errors.

2.546.1 L2Mtu

l2MtuCfg	*integer*	Configured L2 MTU (bytes).
l2MtuStatus	*integer*	L2 MTU Status (bytes).

2.547 show interfaces (link-flap damping) | (link-flap damping (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

interfaces	*table(Interface name) = LinkFlapDampingIntfData* see 2.547.1	Mapping between interfaces and profiles active on them.

2.547.1 LinkFlapDampingIntfData

`profiles`	*table(string) = LinkFlapDampingProfileData* see 2.547.1.1	Mapping between profile names and profile statuses.

2.547.1.1 LinkFlapDampingProfileData

`demerit`	*integer*	Current penalty value.
`reuse`	*floating point number*	Expected reuse time.
`suppressed`	*floating point number*	Last suppression time.

2.548 show interfaces (phy detail) | (phy detail (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

revision 2

interfacePhyStatuses	*table(Interface name) = InterfacePhyStatuses-Detailed* see 2.548.1	Collection of phy information, keyed by interface name.

2.548.1 InterfacePhyStatusesDetailed

[interfaceState]	*InterfaceState* see 2.548.1.1	State of the interface.
[macFaults]	*RsBaseR* see 2.548.1.2.42	MAC local/remote fault information.
[operSpeed]	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
phyStatuses	*list of PhyStatus* see 2.548.1.2	List of phy information for this interface.
[transceiver]	*Transceiver* see 2.548.1.76	Transceiver information.

2.548.1.1 InterfaceState

changes	*integer*	Number of interface state changes.
current	*enum: down | up | adminDown*	Current interface state.
lastChange	*floating point number*	Last time interface state changed.

2.548.1.2 PhyStatus

Could also be an instance of:
InternalGen2PhyIntfStatus 2.548.1.52
InternalGen3PhyIntfStatus 2.548.1.53
InternalPhyIntfStatus 2.548.1.62
RawPhyStatus 2.548.1.71
SwitchAsic1p6tPhyIntfStatus 2.548.1.58
SwitchAsic400gPhyIntfStatus 2.548.1.59
SwitchAsic800gPhyIntfStatus 2.548.1.60
B52ChipPhyStatus 2.548.1.5
B52LinePhyStatus 2.548.1.6
B52PhyStatus 2.548.1.7

B52SystemPhyStatus 2.548.1.8
BabbageChipPhyStatus 2.548.1.9
BabbageLinePhyStatus 2.548.1.10
BabbageSystemPhyStatus 2.548.1.11
CrosspointLineStatus 2.548.1.42
CrosspointPhyStatus 2.548.1.43
DenaliLinePhyStatus 2.548.1.45
DenaliSystemPhyStatus 2.548.1.46
EnigmaLinePhyStatus 2.548.1.47
EnigmaSystemPhyStatus 2.548.1.48
EvoraLinePhyStatus 2.548.1.49
EvoraSystemPhyStatus 2.548.1.50
MakoFpgaPhyIntfStatus 2.548.1.63
AlaskaLinePhyModel 2.548.1.3
AlaskaSystemPhyModel 2.548.1.4
CortinaHostPhyModel 2.548.1.36
CortinaLinePhyModel 2.548.1.37
PhyDs280ChipStatus 2.548.1.67
PhyDs280IntfStatus 2.548.1.68
PhyDs280LineIntfStatus 2.548.1.69
PhyDs280SystemIntfStatus 2.548.1.70
MillenioLinePhyStatus 2.548.1.65
MillenioSystemPhyStatus 2.548.1.66
BlackhawkPhyIntfStatus 2.548.1.24
D5PhyIntfStatus 2.548.1.44
FalconPhyIntfStatus 2.548.1.51
PeregrinePhyIntfStatus 2.548.1.55
TalonPhyIntfStatus 2.548.1.61
SfePhyGen3IntfStatus 2.548.1.56
SfePhyNacIntfStatus 2.548.1.57
IntfStatus 2.548.1.54
Bcm87728ChipPhyStatus 2.548.1.20
Bcm87728LinePhyStatus 2.548.1.21
Bcm87728PhyStatus 2.548.1.22
Bcm87728SystemPhyStatus 2.548.1.23
IntfStatus 2.548.1.26
ShortfinLinePhyModel 2.548.1.72
ShortfinPhyModel 2.548.1.73
ShortfinSystemPhyModel 2.548.1.74
IntfStatus 2.548.1.25
LineStatus 2.548.1.64
SystemStatus 2.548.1.75
Bcm541x2LinePhyModel 2.548.1.17
Bcm541x2PhyModel 2.548.1.18
Bcm54185LinePhyModel 2.548.1.15
Bcm54185PhyModel 2.548.1.16
IntfStatus 2.548.1.28
IntfStatus 2.548.1.33
IntfStatus 2.548.1.32
IntfStatus 2.548.1.34
CredoChipPhyStatus 2.548.1.38
CredoLinePhyStatus 2.548.1.39
CredoPhyStatus 2.548.1.40
CredoSystemPhyStatus 2.548.1.41
IntfStatus 2.548.1.35

IntfStatus 2.548.1.31
IntfStatus 2.548.1.29
IntfStatus 2.548.1.30
IntfStatus 2.548.1.27
Bcm1338PhyStatus 2.548.1.12
Bcm81338ChipPhyStatus 2.548.1.19
Bcm81338LinePhyStatus 2.548.1.13
Bcm81338SystemPhyStatus 2.548.1.14

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.2.1 Fec

Could also be an instance of:
FcFec 2.548.1.2.5
RsFec 2.548.1.2.6
RsFec544 2.548.1.2.7
BabbageRsFec 2.548.1.2.2
CredoRsFec 2.548.1.2.3
CredoRsFec544 2.548.1.2.4

encoding	*enum: fireCode | reedSolomon*	The FEC encoding.

2.548.1.2.2 BabbageRsFec

[alignmentLock]	*RsFecAlignmentLock* see 2.548.1.2.2.22	FEC alignment lock status.
[codewordSize]	*enum: 528 | 544*	FEC codeword size.
[correctedCodewords]	*RsFecCorrectedCodewords* see 2.548.1.2.2.19	Number of corrected FEC codewords.
[correctedSymbolRate]	*floating point number*	FEC corrected symbol rate.
[correctedSymbols]	*table(numeric string) = RsFecCorrectedSymbols* see 2.548.1.2.2.20	Count of FEC corrected symbols per lane.
encoding	*enum: fireCode | reedSolomon*	The FEC encoding.
[fifoStatus]	*FecFifoStatus* see 2.548.1.2.2.1	RS-FEC FIFO status.

[hiSer]	*RsFecHiSer* see 2.548.1.2.2.24	FEC high symbol error rate indication.
[laneAlignmentMarkerLock]	*table(numeric string) = RsFecAlignmentMarkerLock* see 2.548.1.2.2.23	FEC lane alignment marker lock.
[laneMap]	*table(numeric string) = integer*	FEC lane to PMA lane map.
[pmaLaneCorrectedSymbolRate] **	*table(numeric string) = floating point number*	Rate of FEC corrected symbols per PMA lane. **Since: 4.36.0
[uncorrectedCodewords]	*RsFecUnCorrectedCodewords* see 2.548.1.2.2.21	Number of uncorrected FEC codewords.

2.548.1.2.2.1 FecFifoStatus

rxCnt	*integer*	FEC RX FIFO count value.
rxMax	*CountAndChangedStat* see 2.548.1.2.2.2	FEC RX FIFO max value.
rxMin	*CountAndChangedStat* see 2.548.1.2.2.2	FEC RX FIFO min value.
txCnt	*integer*	FEC TX FIFO count value.
txMax	*CountAndChangedStat* see 2.548.1.2.2.2	FEC TX FIFO max value.
txMin	*CountAndChangedStat* see 2.548.1.2.2.2	FEC TX FIFO min value.

2.548.1.2.2.2 CountAndChangedStat

Could also be an instance of:
PcsBipErrors 2.548.1.2.2.14
PcsLastErroredBlockCount 2.548.1.2.2.15
PcsLastHighBerCount 2.548.1.2.2.16
RsFecCorrectedCodewords 2.548.1.2.2.19
RsFecCorrectedSymbols 2.548.1.2.2.20
RsFecUnCorrectedCodewords 2.548.1.2.2.21
FecHistoBin 2.548.1.2.2.7
CredoPhyAdaptCnt 2.548.1.2.2.3
CredoPhyLinkLostCnt 2.548.1.2.2.4
CredoPhyLossOfSignalCnt 2.548.1.2.2.5
CredoPhyReAdaptCnt 2.548.1.2.2.6
FifoStatusEntry 2.548.1.2.2.8
PcsRxCodeGroupErrors 2.548.1.2.2.17
PcsRxFrameErrors 2.548.1.2.2.18
IdleErrorCount 2.548.1.2.2.9
PCSRXErrorCount 2.548.1.2.2.10
PCSRXGoodCount 2.548.1.2.2.11
PCSTXErrorCount 2.548.1.2.2.12
PCSTXGoodCount 2.548.1.2.2.13

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.3 CredoPhyAdaptCnt

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.4 CredoPhyLinkLostCnt

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.5 CredoPhyLossOfSignalCnt

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.6 CredoPhyReAdaptCnt

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.7 FecHistoBin

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.8 FifoStatusEntry

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.9 IdleErrorCount

changes	*integer*	The number of times the count was non-zero.

lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.10 PCSRXErrorCount

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.11 PCSRXGoodCount

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.12 PCSTXErrorCount

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.13 PCSTXGoodCount

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.14 PcsBipErrors

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.15 PcsLastErroredBlockCount

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.16 PcsLastHighBerCount

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.17 PcsRxCodeGroupErrors

changes **	*integer*	The number of times the count was non-zero. **Since: 4.33.2
lastChange **	*floating point number*	The last time the count was non-zero. **Since: 4.33.2
lastRead	*floating point number*	(Deprecated - use lastChange instead) The last time we read the counter.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.18 PcsRxFrameErrors

changes **	*integer*	The number of times the count was non-zero. **Since: 4.33.2
lastChange **	*floating point number*	The last time the count was non-zero. **Since: 4.33.2
lastRead	*floating point number*	(Deprecated - use lastChange instead) The last time we read the counter.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.19 RsFecCorrectedCodewords

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.20 RsFecCorrectedSymbols

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.
value	*integer*	Last non-zero counter value.

2.548.1.2.2.21 RsFecUnCorrectedCodewords

changes	*integer*	The number of times the count was non-zero.
lastChange	*floating point number*	The last time the count was non-zero.

value	*integer*	Last non-zero counter value.

2.548.1.2.2.22 RsFecAlignmentLock

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.2.23 RsFecAlignmentMarkerLock

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.2.24 RsFecHiSer

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.3 CredoRsFec

[alignmentLock]	*RsFecAlignmentLock* see 2.548.1.2.2.22	FEC alignment lock status.
[codewordSize]	*enum: 528 | 544*	FEC codeword size.
[correctedCodewords]	*RsFecCorrectedCodewords* see 2.548.1.2.2.19	Number of corrected FEC codewords.
[correctedSymbolRate]	*floating point number*	FEC corrected symbol rate.
[correctedSymbols]	*table(numeric string) = RsFecCorrectedSymbols* see 2.548.1.2.2.20	Count of FEC corrected symbols per lane.
encoding	*enum: fireCode | reedSolomon*	The FEC encoding.
[fifoStatus]	*CredoFecFifoStatus* see 2.548.1.2.3.1	RS-FEC FIFO status.
[hiSer]	*RsFecHiSer* see 2.548.1.2.2.24	FEC high symbol error rate indication.
[laneAlignmentMarkerLock]	*table(numeric string) = RsFecAlignmentMarkerLock* see 2.548.1.2.2.23	FEC lane alignment marker lock.
[laneMap]	*table(numeric string) = integer*	FEC lane to PMA lane map.
[pmaLaneCorrectedSymbolRate] **	*table(numeric string) = floating point number*	Rate of FEC corrected symbols per PMA lane. **Since: 4.36.0

[uncorrectedCodewords]	*RsFecUnCorrected-Codewords* see 2.548.1.2.2.21	Number of uncorrected FEC codewords.

2.548.1.2.3.1 CredoFecFifoStatus

rxCnt	*integer*	FEC RX FIFO count value.
rxMax	*CountAndChangedStat* see 2.548.1.2.2.2	FEC RX FIFO max value.
rxMin	*CountAndChangedStat* see 2.548.1.2.2.2	FEC RX FIFO min value.
txCnt	*integer*	FEC TX FIFO count value.
txMax	*CountAndChangedStat* see 2.548.1.2.2.2	FEC TX FIFO max value.
txMin	*CountAndChangedStat* see 2.548.1.2.2.2	FEC TX FIFO min value.

2.548.1.2.4 CredoRsFec544

[alignmentLock]	*RsFecAlignmentLock* see 2.548.1.2.2.22	FEC alignment lock status.
[codewordSize]	*enum: 528 | 544*	FEC codeword size.
[correctedCodewords]	*RsFecCorrectedCodewords* see 2.548.1.2.2.19	Number of corrected FEC codewords.
[correctedSymbolRate]	*floating point number*	FEC corrected symbol rate.
[correctedSymbols]	*table(numeric string) = RsFecCorrectedSymbols* see 2.548.1.2.2.20	Count of FEC corrected symbols per lane.
encoding	*enum: fireCode | reedSolomon*	The FEC encoding.
[fifoStatus]	*CredoFecFifoStatus* see 2.548.1.2.3.1	RS-FEC FIFO status.
[hiSer]	*RsFecHiSer* see 2.548.1.2.2.24	FEC high symbol error rate indication.
[laneAlignmentMarkerLock]	*table(numeric string) = RsFecAlignmentMarkerLock* see 2.548.1.2.2.23	FEC lane alignment marker lock.
[laneMap]	*table(numeric string) = integer*	FEC lane to PMA lane map.
[pmaLaneCorrectedSymbol-Rate] **	*table(numeric string) = floating point number*	Rate of FEC corrected symbols per PMA lane. **Since: 4.36.0
[uncorrectedCodewords]	*RsFecUnCorrected-Codewords* see 2.548.1.2.2.21	Number of uncorrected FEC codewords.

2.548.1.2.5 FcFec

encoding	*enum: fireCode | reedSolomon*	The FEC encoding.

perLaneCorrectedFecBlocks	*table(numeric string) = CountAndChangedStat* see 2.548.1.2.2.2	Count of corrected FEC blocks per FEC lane.
perLaneUncorrectedFecBlocks	*table(numeric string) = CountAndChangedStat* see 2.548.1.2.2.2	Count of uncorrected FEC blocks per FEC lane.

2.548.1.2.6 RsFec

[alignmentLock]	*RsFecAlignmentLock* see 2.548.1.2.2.22	FEC alignment lock status.
[codewordSize]	*enum: 528 | 544*	FEC codeword size.
[correctedCodewords]	*RsFecCorrectedCodewords* see 2.548.1.2.2.19	Number of corrected FEC codewords.
[correctedSymbolRate] **	*floating point number*	FEC corrected symbol rate. **Since: 4.24.1
[correctedSymbols]	*table(numeric string) = RsFecCorrectedSymbols* see 2.548.1.2.2.20	Count of FEC corrected symbols per lane.
encoding	*enum: fireCode | reedSolomon*	The FEC encoding.
[hiSer]	*RsFecHiSer* see 2.548.1.2.2.24	FEC high symbol error rate indication.
[laneAlignmentMarkerLock]	*table(numeric string) = RsFecAlignmentMarkerLock* see 2.548.1.2.2.23	FEC lane alignment marker lock.
[laneMap]	*table(numeric string) = integer*	FEC lane to PMA lane map.
[pmaLaneCorrectedSymbolRate] **	*table(numeric string) = floating point number*	Rate of FEC corrected symbols per PMA lane. **Since: 4.36.0
[uncorrectedCodewords]	*RsFecUnCorrectedCodewords* see 2.548.1.2.2.21	Number of uncorrected FEC codewords.

2.548.1.2.7 RsFec544

[alignmentLock]	*RsFecAlignmentLock* see 2.548.1.2.2.22	FEC alignment lock status.
[codewordSize]	*enum: 528 | 544*	FEC codeword size.
[correctedCodewords]	*RsFecCorrectedCodewords* see 2.548.1.2.2.19	Number of corrected FEC codewords.
[correctedSymbolRate] **	*floating point number*	FEC corrected symbol rate. **Since: 4.24.1
[correctedSymbols]	*table(numeric string) = RsFecCorrectedSymbols* see 2.548.1.2.2.20	Count of FEC corrected symbols per lane.
encoding	*enum: fireCode | reedSolomon*	The FEC encoding.
[hiSer]	*RsFecHiSer* see 2.548.1.2.2.24	FEC high symbol error rate indication.

[laneAlignmentMarkerLock]	*table(numeric string) = RsFecAlignmentMarkerLock* see 2.548.1.2.2.23	FEC lane alignment marker lock.
[laneMap]	*table(numeric string) = integer*	FEC lane to PMA lane map.
[pmaLaneCorrectedSymbolRate] **	*table(numeric string) = floating point number*	Rate of FEC corrected symbols per PMA lane. **Since: 4.36.0
[uncorrectedCodewords]	*RsFecUnCorrectedCodewords* see 2.548.1.2.2.21	Number of uncorrected FEC codewords.

2.548.1.2.8 Pcs

Could also be an instance of:
MultiLanePcsBaseR 2.548.1.2.17
PcsBaseR 2.548.1.2.18
PcsClause45 2.548.1.2.19
B52MultiLanePcs 2.548.1.2.9
DenaliPcs 2.548.1.2.13
EnigmaMultiLanePcs 2.548.1.2.14
EvoraMultiLanePcs 2.548.1.2.15
MakoPcs 2.548.1.2.16
CortinaPcsModel 2.548.1.2.12
ShortfinPcsModel 2.548.1.2.21
Bcm541x2PcsModel 2.548.1.2.11
Bcm54185PcsModel 2.548.1.2.10
PcsModel 2.548.1.2.20

2.548.1.2.9 B52MultiLanePcs

[bipErrors]	*table(numeric string) = PcsBipErrors* see 2.548.1.2.2.14	PCS BIP errors.
[blockLock]	*PcsBlockLock* see 2.548.1.2.9.2	PCS block lock.
[deskew]	*PcsDeskew* see 2.548.1.2.9.3	PCS deskew status.
[highBer]	*PcsHighBer* see 2.548.1.2.9.4	PCS high BER status.
[laneAlignmentMarkerLock]	*table(numeric string) = PcsAlignmentMarkerLock* see 2.548.1.2.9.1	PCS lane alignment marker lock.
[laneBlockLock]	*table(numeric string) = PcsBlockLock* see 2.548.1.2.9.2	PCS lane block lock.
[laneDeskew]	*table(numeric string) = PcsDeskew* see 2.548.1.2.9.3	PCS lane deskew status.
[laneMap]	*table(numeric string) = integer*	Local PCS lane to peer PCS lane map.
[lastErroredBlockCount]	*PcsLastErroredBlockCount* see 2.548.1.2.2.15	PCS last errored block count.

[lastHighBerCount]	*PcsLastHighBerCount* see 2.548.1.2.2.16	PCS last high BER count.
[linkStatus]	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
[rxFault]	*PcsRxFault* see 2.548.1.2.9.6	PCS receive fault.
[rxLpi]	*PcsRxLpi* see 2.548.1.2.9.7	PCS has received LPI signaling.
[txFault]	*PcsTxFault* see 2.548.1.2.9.8	PCS transmit fault.

2.548.1.2.9.1 PcsAlignmentMarkerLock

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.9.2 PcsBlockLock

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.9.3 PcsDeskew

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.9.4 PcsHighBer

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.9.5 PcsLinkStatus

changes	*integer*	The number of times the link status changed.
lastChange	*floating point number*	The last time the link status changed.
value	*enum: down | up*	The status of the link.

2.548.1.2.9.6 PcsRxFault

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.9.7 PcsRxLpi

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.9.8 PcsTxFault

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.10 Bcm54185PcsModel

[blockLock]	*PcsBlockLock* see 2.548.1.2.9.2	PCS block lock.
[highBer]	*PcsHighBer* see 2.548.1.2.9.4	PCS high BER status.
[lastErroredBlockCount]	*PcsLastErroredBlockCount* see 2.548.1.2.2.15	PCS last errored block count.
[lastHighBerCount]	*PcsLastHighBerCount* see 2.548.1.2.2.16	PCS last high BER count.
[linkStatus]	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
[rxFault]	*PcsRxFault* see 2.548.1.2.9.6	PCS receive fault.
[rxLpi]	*PcsRxLpi* see 2.548.1.2.9.7	PCS has received LPI signaling.
[txFault]	*PcsTxFault* see 2.548.1.2.9.8	PCS transmit fault.

2.548.1.2.11 Bcm541x2PcsModel

[blockLock]	*PcsBlockLock* see 2.548.1.2.9.2	PCS block lock.
[highBer]	*PcsHighBer* see 2.548.1.2.9.4	PCS high BER status.
[lastErroredBlockCount]	*PcsLastErroredBlockCount* see 2.548.1.2.2.15	PCS last errored block count.

[lastHighBerCount]	*PcsLastHighBerCount* see 2.548.1.2.2.16	PCS last high BER count.
[linkStatus]	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
[rxFault]	*PcsRxFault* see 2.548.1.2.9.6	PCS receive fault.
[rxLpi]	*PcsRxLpi* see 2.548.1.2.9.7	PCS has received LPI signaling.
[txFault]	*PcsTxFault* see 2.548.1.2.9.8	PCS transmit fault.

2.548.1.2.12 CortinaPcsModel

[blockLock]	*PcsBlockLock* see 2.548.1.2.9.2	PCS block lock.
[deskew]	*PcsDeskew* see 2.548.1.2.9.3	PCS deskew status.
[highBer]	*PcsHighBer* see 2.548.1.2.9.4	PCS high BER status.
[lastErroredBlockCount]	*PcsLastErroredBlockCount* see 2.548.1.2.2.15	PCS last errored block count.
[lastHighBerCount]	*PcsLastHighBerCount* see 2.548.1.2.2.16	PCS last high BER count.
[linkStatus]	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
[rxFault]	*PcsRxFault* see 2.548.1.2.9.6	PCS receive fault.
[rxLpi]	*PcsRxLpi* see 2.548.1.2.9.7	PCS has received LPI signaling.
[txFault]	*PcsTxFault* see 2.548.1.2.9.8	PCS transmit fault.

2.548.1.2.13 DenaliPcs

alignmentMarkerLock	*PcsAlignmentMarkerLock* see 2.548.1.2.9.1	PCS alignment marker lock.
bipErrorsDetected	*PcsBipErrorsDetected* see 2.548.1.2.13.1	PCS BIP error detected.
[blockLock]	*PcsBlockLock* see 2.548.1.2.9.2	PCS block lock.
[deskew]	*PcsDeskew* see 2.548.1.2.9.3	PCS deskew status.
[highBer]	*PcsHighBer* see 2.548.1.2.9.4	PCS high BER status.
[lastErroredBlockCount]	*PcsLastErroredBlockCount* see 2.548.1.2.2.15	PCS last errored block count.
[lastHighBerCount]	*PcsLastHighBerCount* see 2.548.1.2.2.16	PCS last high BER count.
[linkStatus]	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
lossOfAlignment	*PcsLossOfAlignment* see 2.548.1.2.13.3	PCS loss of alignment.

pcsErroredBlocksDetected	*PcsErroredBlocksDetected* see 2.548.1.2.13.2	PCS errored blocks detected.
[rxFault]	*PcsRxFault* see 2.548.1.2.9.6	PCS receive fault.
[rxLpi]	*PcsRxLpi* see 2.548.1.2.9.7	PCS has received LPI signaling.
[txFault]	*PcsTxFault* see 2.548.1.2.9.8	PCS transmit fault.

2.548.1.2.13.1 PcsBipErrorsDetected

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.13.2 PcsErroredBlocksDetected

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.13.3 PcsLossOfAlignment

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.14 EnigmaMultiLanePcs

[bipErrors]	*table(numeric string) = PcsBipErrors* see 2.548.1.2.2.14	PCS BIP errors.
[blockLock]	*PcsBlockLock* see 2.548.1.2.9.2	PCS block lock.
[deskew]	*PcsDeskew* see 2.548.1.2.9.3	PCS deskew status.
[highBer]	*PcsHighBer* see 2.548.1.2.9.4	PCS high BER status.
[laneAlignmentMarkerLock]	*table(numeric string) = PcsAlignmentMarkerLock* see 2.548.1.2.9.1	PCS lane alignment marker lock.
[laneBlockLock]	*table(numeric string) = PcsBlockLock* see 2.548.1.2.9.2	PCS lane block lock.

[laneDeskew]	*table(numeric string) = PcsDeskew* see 2.548.1.2.9.3	PCS lane deskew status.
[laneMap]	*table(numeric string) = integer*	Local PCS lane to peer PCS lane map.
[lastErroredBlockCount]	*PcsLastErroredBlockCount* see 2.548.1.2.2.15	PCS last errored block count.
[lastHighBerCount]	*PcsLastHighBerCount* see 2.548.1.2.2.16	PCS last high BER count.
[linkStatus]	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
[rxFault]	*PcsRxFault* see 2.548.1.2.9.6	PCS receive fault.
[rxLpi]	*PcsRxLpi* see 2.548.1.2.9.7	PCS has received LPI signaling.
[txFault]	*PcsTxFault* see 2.548.1.2.9.8	PCS transmit fault.

2.548.1.2.15 EvoraMultiLanePcs

[bipErrors]	*table(numeric string) = PcsBipErrors* see 2.548.1.2.2.14	PCS BIP errors.
[blockLock]	*PcsBlockLock* see 2.548.1.2.9.2	PCS block lock.
[deskew]	*PcsDeskew* see 2.548.1.2.9.3	PCS deskew status.
deskewAchieved	*PcsDeskewAchieved* see 2.548.1.2.15.1	Whether or not deskew has been achieved.
[highBer]	*PcsHighBer* see 2.548.1.2.9.4	PCS high BER status.
[laneAlignmentMarkerLock]	*table(numeric string) = PcsAlignmentMarkerLock* see 2.548.1.2.9.1	PCS lane alignment marker lock.
[laneBlockLock]	*table(numeric string) = PcsBlockLock* see 2.548.1.2.9.2	PCS lane block lock.
[laneDeskew]	*table(numeric string) = PcsDeskew* see 2.548.1.2.9.3	PCS lane deskew status.
[laneMap]	*table(numeric string) = integer*	Local PCS lane to peer PCS lane map.
[lastErroredBlockCount]	*PcsLastErroredBlockCount* see 2.548.1.2.2.15	PCS last errored block count.
[lastHighBerCount]	*PcsLastHighBerCount* see 2.548.1.2.2.16	PCS last high BER count.
linkInterrupted	*PcsLinkInterrupted* see 2.548.1.2.15.2	Whether or not link has been interrupted.
[linkStatus]	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
[rxFault]	*PcsRxFault* see 2.548.1.2.9.6	PCS receive fault.

[rxLpi]	*PcsRxLpi* see 2.548.1.2.9.7	PCS has received LPI signaling.
[txFault]	*PcsTxFault* see 2.548.1.2.9.8	PCS transmit fault.

2.548.1.2.15.1 PcsDeskewAchieved

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.15.2 PcsLinkInterrupted

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.16 MakoPcs

[bipErrors]	*table(numeric string) = PcsBipErrors* see 2.548.1.2.2.14	PCS BIP errors.
[blockLock]	*PcsBlockLock* see 2.548.1.2.9.2	PCS block lock.
[deskew]	*PcsDeskew* see 2.548.1.2.9.3	PCS deskew status.
[highBer]	*PcsHighBer* see 2.548.1.2.9.4	PCS high BER status.
[laneAlignmentMarkerLock]	*table(numeric string) = PcsAlignmentMarkerLock* see 2.548.1.2.9.1	PCS lane alignment marker lock.
[laneBlockLock]	*table(numeric string) = PcsBlockLock* see 2.548.1.2.9.2	PCS lane block lock.
[laneDeskew]	*table(numeric string) = PcsDeskew* see 2.548.1.2.9.3	PCS lane deskew status.
[laneMap]	*table(numeric string) = integer*	Local PCS lane to peer PCS lane map.
[lastErroredBlockCount]	*PcsLastErroredBlockCount* see 2.548.1.2.2.15	PCS last errored block count.
[lastHighBerCount]	*PcsLastHighBerCount* see 2.548.1.2.2.16	PCS last high BER count.
[linkStatus]	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
[rxCodeGroupErrors]	*PcsRxCodeGroupErrors* see 2.548.1.2.2.17	The number of PCS 8B/10B code-group decoding errors.

[rxFault]	*PcsRxFault* see 2.548.1.2.9.6	PCS receive fault.
[rxFrameErrors]	*PcsRxFrameErrors* see 2.548.1.2.2.18	The number of PCS error blocks during a frame.
[rxLinkStateChanges] **	*PcsRxLinkStateChanges* see 2.548.1.2.16.1	Counter that increments on link up and link down. **Since: 4.33.2
[rxLpi]	*PcsRxLpi* see 2.548.1.2.9.7	PCS has received LPI signaling.
[rxStartBlocks] **	*PcsRxStartBlocks* see 2.548.1.2.16.2	The number of PCS blocks containing a start /S/ block type field. **Since: 4.35.0
[txFault]	*PcsTxFault* see 2.548.1.2.9.8	PCS transmit fault.

2.548.1.2.16.1 PcsRxLinkStateChanges

lastRead	*floating point number*	The last time we read the counter.
value	*integer*	The counter value.

2.548.1.2.16.2 PcsRxStartBlocks

lastRead	*floating point number*	The last time we read the counter.
value	*integer*	The counter value.

2.548.1.2.17 MultiLanePcsBaseR

[bipErrors]	*table(numeric string) = PcsBipErrors* see 2.548.1.2.2.14	PCS BIP errors.
[blockLock]	*PcsBlockLock* see 2.548.1.2.9.2	PCS block lock.
[deskew]	*PcsDeskew* see 2.548.1.2.9.3	PCS deskew status.
[highBer]	*PcsHighBer* see 2.548.1.2.9.4	PCS high BER status.
[laneAlignmentMarkerLock]	*table(numeric string) = PcsAlignmentMarkerLock* see 2.548.1.2.9.1	PCS lane alignment marker lock.
[laneBlockLock]	*table(numeric string) = PcsBlockLock* see 2.548.1.2.9.2	PCS lane block lock.
[laneDeskew]	*table(numeric string) = PcsDeskew* see 2.548.1.2.9.3	PCS lane deskew status.
[laneMap]	*table(numeric string) = integer*	Local PCS lane to peer PCS lane map.
[lastErroredBlockCount]	*PcsLastErroredBlockCount* see 2.548.1.2.2.15	PCS last errored block count.
[lastHighBerCount]	*PcsLastHighBerCount* see 2.548.1.2.2.16	PCS last high BER count.

[linkStatus]	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
[rxFault]	*PcsRxFault* see 2.548.1.2.9.6	PCS receive fault.
[rxLpi]	*PcsRxLpi* see 2.548.1.2.9.7	PCS has received LPI signaling.
[txFault]	*PcsTxFault* see 2.548.1.2.9.8	PCS transmit fault.

2.548.1.2.18 PcsBaseR

[blockLock]	*PcsBlockLock* see 2.548.1.2.9.2	PCS block lock.
[deskew]	*PcsDeskew* see 2.548.1.2.9.3	PCS deskew status.
[highBer]	*PcsHighBer* see 2.548.1.2.9.4	PCS high BER status.
[lastErroredBlockCount]	*PcsLastErroredBlockCount* see 2.548.1.2.2.15	PCS last errored block count.
[lastHighBerCount]	*PcsLastHighBerCount* see 2.548.1.2.2.16	PCS last high BER count.
[linkStatus]	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
[rxFault]	*PcsRxFault* see 2.548.1.2.9.6	PCS receive fault.
[rxLpi]	*PcsRxLpi* see 2.548.1.2.9.7	PCS has received LPI signaling.
[txFault]	*PcsTxFault* see 2.548.1.2.9.8	PCS transmit fault.

2.548.1.2.19 PcsClause45

[blockLock]	*PcsBlockLock* see 2.548.1.2.9.2	PCS block lock.
[highBer]	*PcsHighBer* see 2.548.1.2.9.4	PCS high BER status.
[lastErroredBlockCount]	*PcsLastErroredBlockCount* see 2.548.1.2.2.15	PCS last errored block count.
[lastHighBerCount]	*PcsLastHighBerCount* see 2.548.1.2.2.16	PCS last high BER count.
[linkStatus]	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
[rxFault]	*PcsRxFault* see 2.548.1.2.9.6	PCS receive fault.
[rxLpi]	*PcsRxLpi* see 2.548.1.2.9.7	PCS has received LPI signaling.
[txFault]	*PcsTxFault* see 2.548.1.2.9.8	PCS transmit fault.

2.548.1.2.20 PcsModel

[blockLock]	*PcsBlockLock* see 2.548.1.2.9.2	PCS block lock.
[highBer]	*PcsHighBer* see 2.548.1.2.9.4	PCS high BER status.
[lastErroredBlockCount]	*PcsLastErroredBlockCount* see 2.548.1.2.2.15	PCS last errored block count.
[lastHighBerCount]	*PcsLastHighBerCount* see 2.548.1.2.2.16	PCS last high BER count.
[linkStatus]	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
[rxFault]	*PcsRxFault* see 2.548.1.2.9.6	PCS receive fault.
[rxLpi]	*PcsRxLpi* see 2.548.1.2.9.7	PCS has received LPI signaling.
[txFault]	*PcsTxFault* see 2.548.1.2.9.8	PCS transmit fault.

2.548.1.2.21 ShortfinPcsModel

[blockLock]	*PcsBlockLock* see 2.548.1.2.9.2	PCS block lock.
[highBer]	*PcsHighBer* see 2.548.1.2.9.4	PCS high BER status.
[lastErroredBlockCount]	*PcsLastErroredBlockCount* see 2.548.1.2.2.15	PCS last errored block count.
[lastHighBerCount]	*PcsLastHighBerCount* see 2.548.1.2.2.16	PCS last high BER count.
[linkStatus]	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
[rxFault]	*PcsRxFault* see 2.548.1.2.9.6	PCS receive fault.
[rxLpi]	*PcsRxLpi* see 2.548.1.2.9.7	PCS has received LPI signaling.
[txFault]	*PcsTxFault* see 2.548.1.2.9.8	PCS transmit fault.

2.548.1.2.22 PhyChipStatus

Could also be an instance of:
ChipStatus 2.548.1.2.23
ChipStatus 2.548.1.2.24

[hwRev]	*string*	PHY hardware revision.
model	*integer*	Model number.
[modelName]	*string*	PHY model name.
oui	*integer*	Organizationally Unique Identifier (OUI).
rev	*integer*	Revision number.

2.548.1.2.23 ChipStatus

[firmwareRev]	*string*	PHY firmware revision.

[hwRev]	*string*	PHY hardware revision.
model	*integer*	Model number.
[modelName]	*string*	PHY model name.
oui	*integer*	Organizationally Unique Identifier (OUI).
rev	*integer*	Revision number.

2.548.1.2.24 ChipStatus

[availableFirmwareRev] **	*string*	PHY firmware revision available in current EOS image. **Since: 4.23.1
[firmwareRev] **	*string*	PHY firmware revision. **Since: 4.23.1
[firmwareStatus] **	*PhyFirmwareStatus* see 2.548.1.2.24.1	PHY firmware status information. **Since: 4.27.2
[hwRev]	*string*	PHY hardware revision.
model	*integer*	Model number.
[modelName]	*string*	PHY model name.
oui	*integer*	Organizationally Unique Identifier (OUI).
rev	*integer*	Revision number.

2.548.1.2.24.1 PhyFirmwareStatus

changes	*integer*	Number of PHY firmware status changes.
lastChange	*floating point number*	Last time PHY firmware status changed.
value	*enum: ok | unknown | error*	Current PHY firmware status.

2.548.1.2.25 PhyDescription

[lane] **	*integer*	phy lane number. **Since: 4.34.0
[location]	*enum: system | line*	Location of phy within phy chip.
phyChipName	*string*	Name of the phy chip.
[position] **	*integer*	Position of the phy chip in topology. **Since: 4.29.1

2.548.1.2.26 Pma

Could also be an instance of:
PmaBaseR 2.548.1.2.35
PmaBaseT 2.548.1.2.37
PmaClause45 2.548.1.2.39
PmaGen2 2.548.1.2.36
DenaliPma 2.548.1.2.31
EnigmaPma 2.548.1.2.32
EvoraPma 2.548.1.2.33
MakoPma 2.548.1.2.34
CortinaPmaModel 2.548.1.2.30
ShortfinPmaModel 2.548.1.2.40

PmaModel 2.548.1.2.38
Bcm541x2PmaModel 2.548.1.2.28
Bcm54185PmaModel 2.548.1.2.27
PmaModel 2.548.1.2.29

2.548.1.2.27 Bcm54185PmaModel

[laneSignalDetect]	*table(numeric string) = PmaSignalDetect* see 2.548.1.2.27.3	PMA lane signal detect.
[linkStatus]	*PmaLinkStatus* see 2.548.1.2.27.1	PMA link status.
[rxFault]	*PmaRxFault* see 2.548.1.2.27.2	PMA receive fault.
[signalDetect]	*PmaSignalDetect* see 2.548.1.2.27.3	PMA signal detect.
[txFault]	*PmaTxFault* see 2.548.1.2.27.4	PMA transmit fault.

2.548.1.2.27.1 PmaLinkStatus

changes	*integer*	The number of times the link status changed.
lastChange	*floating point number*	The last time the link status changed.
value	*enum: down | up*	The status of the link.

2.548.1.2.27.2 PmaRxFault

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.27.3 PmaSignalDetect

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.27.4 PmaTxFault

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.28 Bcm541x2PmaModel

[laneSignalDetect]	*table(numeric string) = PmaSignalDetect* see 2.548.1.2.27.3	PMA lane signal detect.
[linkStatus]	*PmaLinkStatus* see 2.548.1.2.27.1	PMA link status.
[rxFault]	*PmaRxFault* see 2.548.1.2.27.2	PMA receive fault.
[signalDetect]	*PmaSignalDetect* see 2.548.1.2.27.3	PMA signal detect.
[txFault]	*PmaTxFault* see 2.548.1.2.27.4	PMA transmit fault.

2.548.1.2.29 PmaModel

[laneSignalDetect]	*table(numeric string) = PmaSignalDetect* see 2.548.1.2.27.3	PMA lane signal detect.
[linkStatus]	*PmaLinkStatus* see 2.548.1.2.27.1	PMA link status.
[rxFault]	*PmaRxFault* see 2.548.1.2.27.2	PMA receive fault.
[signalDetect]	*PmaSignalDetect* see 2.548.1.2.27.3	PMA signal detect.
[txFault]	*PmaTxFault* see 2.548.1.2.27.4	PMA transmit fault.

2.548.1.2.30 CortinaPmaModel

[laneLinkStatus]	*table(numeric string) = PmaLinkStatus* see 2.548.1.2.27.1	PMA lane link status.
[laneSignalDetect]	*table(numeric string) = PmaSignalDetect* see 2.548.1.2.27.3	PMA lane signal detect.
[linkStatus]	*PmaLinkStatus* see 2.548.1.2.27.1	PMA link status.
[rxFault]	*PmaRxFault* see 2.548.1.2.27.2	PMA receive fault.
[signalDetect]	*PmaSignalDetect* see 2.548.1.2.27.3	PMA signal detect.
[txFault]	*PmaTxFault* see 2.548.1.2.27.4	PMA transmit fault.

2.548.1.2.31 DenaliPma

adcOutput	*AdcOutput* see 2.548.1.2.31.1	Whether or not ADC output is set.
adcReady	*AdcReady* see 2.548.1.2.31.2	Whether or not ADC is ready.

carrierFrequencyOffset	*CarrierFrequencyOffset* see 2.548.1.2.31.3	Receiver carrier frequency offset in MHz.
chromaticDispersion	*ChromaticDispersion* see 2.548.1.2.31.4	Chromatic dispersion in ps/nm.
dacReady	*DacReady* see 2.548.1.2.31.5	Whether or not DAC is ready.
differentialGroupDelay	*DifferentialGroupDelay* see 2.548.1.2.31.6	Differential group delay in ps.
dispersionLockSet	*DispersionLockSet* see 2.548.1.2.31.7	Whether or not the DSP found a good dispersion compensation setting.
hiAgcError	*HiAgcError* see 2.548.1.2.31.9	Sampled HI quad error filter AGC error.
hqAgcError	*HqAgcError* see 2.548.1.2.31.10	Sampled HQ quad error filter AGC error.
linkQFactor	*LinkQFactor* see 2.548.1.2.31.11	Link Q-factor in dB.
preFecBitErrorRate	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
rollOff	*RollOff* see 2.548.1.2.31.13	Amount of excess bandwidth of the filter, as a fraction of frequency.
rxAsicSubsystemConfigured	*RxAsicSubsystemsConfigured* see 2.548.1.2.31.14	Whether or not the RX ASIC subsystems has been configured.
rxClockConfigured	*RxClockConfigured* see 2.548.1.2.31.15	Whether or not the RX clock has been configured.
rxDelayH	*RxDelayH* see 2.548.1.2.31.16	HQ delay in ps.
rxDelayV	*RxDelayV* see 2.548.1.2.31.17	VQ delay in ps.
rxDemodLockSet	*RxDemodLockSet* see 2.548.1.2.31.18	Whether or not there is RX demodulator lock.
signalNoiseRatio	*SignalNoiseRatio* see 2.548.1.2.31.19	Signal-to-noise ratio in dB.
txAsicSubsystemConfigured	*TxAsicSubsystemsConfigured* see 2.548.1.2.31.20	Whether or not the TX ASIC subsystems has been configured.
txClockConfigured	*TxClockConfigured* see 2.548.1.2.31.21	Whether or not the TX clock has been configured.
txDelayH	*TxDelayH* see 2.548.1.2.31.22	Delay for launching the signal on HQ.
txDelayV	*TxDelayV* see 2.548.1.2.31.23	Delay for launching the signal on VQ.
uncorrectedCodewords	*FecUnCorrectedCodewords* see 2.548.1.2.31.8	Number of uncorrected FEC code words.
viAgcError	*ViAgcError* see 2.548.1.2.31.24	Sampled VI quad error filter AGC error.
vqAgcError	*VqAgcError* see 2.548.1.2.31.25	Sampled VQ quad error filter AGC error.

2.548.1.2.31.1 AdcOutput

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.31.2 AdcReady

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.31.3 CarrierFrequencyOffset

value	*integer*	The value of the attribute.

2.548.1.2.31.4 ChromaticDispersion

value	*integer*	The value of the attribute.

2.548.1.2.31.5 DacReady

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.31.6 DifferentialGroupDelay

value	*integer*	The value of the attribute.

2.548.1.2.31.7 DispersionLockSet

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.31.8 FecUnCorrectedCodewords

changes	*integer*	The number of times the value changed.
lastChange	*floating point number*	The last time the value changed.
value	*integer*	The value of the attribute.

2.548.1.2.31.9 HiAgcError

value	*integer*	The value of the attribute.

2.548.1.2.31.10 HqAgcError

value	*integer*	The value of the attribute.

2.548.1.2.31.11 LinkQFactor

value	*floating point number*	The value of the attribute.

2.548.1.2.31.12 PreFecBitError

value	*floating point number*	Pre-FEC bit error rate.

2.548.1.2.31.13 RollOff

value	*floating point number*	The value of the attribute.

2.548.1.2.31.14 RxAsicSubsystemsConfigured

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.31.15 RxClockConfigured

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.31.16 RxDelayH

value	*floating point number*	The value of the attribute.

2.548.1.2.31.17 RxDelayV

value	*floating point number*	The value of the attribute.

2.548.1.2.31.18 RxDemodLockSet

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.31.19 SignalNoiseRatio

value	*floating point number*	The value of the attribute.

2.548.1.2.31.20 TxAsicSubsystemsConfigured

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.31.21 TxClockConfigured

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.31.22 TxDelayH

value	*floating point number*	The value of the attribute.

2.548.1.2.31.23 TxDelayV

value	*floating point number*	The value of the attribute.

2.548.1.2.31.24 ViAgcError

value	*integer*	The value of the attribute.

2.548.1.2.31.25 VqAgcError

value	*integer*	The value of the attribute.

2.548.1.2.32 EnigmaPma

[laneLinkStatus]	*table(numeric string) = PmaLinkStatus* see 2.548.1.2.27.1	PMA lane link status.
[laneSignalDetect]	*table(numeric string) = PmaSignalDetect* see 2.548.1.2.27.3	PMA lane signal detect.
[linkStatus]	*PmaLinkStatus* see 2.548.1.2.27.1	PMA link status.
[rxFault]	*PmaRxFault* see 2.548.1.2.27.2	PMA receive fault.
[signalDetect]	*PmaSignalDetect* see 2.548.1.2.27.3	PMA signal detect.
[txFault]	*PmaTxFault* see 2.548.1.2.27.4	PMA transmit fault.

2.548.1.2.33 EvoraPma

[laneLinkStatus]	*table(numeric string) = PmaLinkStatus* see 2.548.1.2.27.1	PMA lane link status.
[laneSignalDetect]	*table(numeric string) = PmaSignalDetect* see 2.548.1.2.27.3	PMA lane signal detect.
[linkStatus]	*PmaLinkStatus* see 2.548.1.2.27.1	PMA link status.
[rxFault]	*PmaRxFault* see 2.548.1.2.27.2	PMA receive fault.
[signalDetect]	*PmaSignalDetect* see 2.548.1.2.27.3	PMA signal detect.
[txFault]	*PmaTxFault* see 2.548.1.2.27.4	PMA transmit fault.

2.548.1.2.34 MakoPma

[laneLinkStatus]	*table(numeric string) = PmaLinkStatus* see 2.548.1.2.27.1	PMA lane link status.
[laneSignalDetect]	*table(numeric string) = PmaSignalDetect* see 2.548.1.2.27.3	PMA lane signal detect.
[laneTxStatus]	*table(numeric string) = PmaTxStatus* see 2.548.1.2.34.1	PMA per lane transmit status.
[linkStatus]	*PmaLinkStatus* see 2.548.1.2.27.1	PMA link status.
[rxFault]	*PmaRxFault* see 2.548.1.2.27.2	PMA receive fault.
[signalDetect]	*PmaSignalDetect* see 2.548.1.2.27.3	PMA signal detect.
[txFault]	*PmaTxFault* see 2.548.1.2.27.4	PMA transmit fault.

[txStatus]	*PmaTxStatus* see 2.548.1.2.34.1	PMA lane aggregate transmit status.

2.548.1.2.34.1 PmaTxStatus

changes	*integer*	The number of times the transmit status changed.
lastChange	*floating point number*	The last time the transmit status changed.
value	*enum: on | off*	The transmit status.

2.548.1.2.35 PmaBaseR

[laneLinkStatus]	*table(numeric string) = PmaLinkStatus* see 2.548.1.2.27.1	PMA lane link status.
[laneSignalDetect]	*table(numeric string) = PmaSignalDetect* see 2.548.1.2.27.3	PMA lane signal detect.
[linkStatus]	*PmaLinkStatus* see 2.548.1.2.27.1	PMA link status.
[rxFault]	*PmaRxFault* see 2.548.1.2.27.2	PMA receive fault.
[signalDetect]	*PmaSignalDetect* see 2.548.1.2.27.3	PMA signal detect.
[txFault]	*PmaTxFault* see 2.548.1.2.27.4	PMA transmit fault.

2.548.1.2.36 PmaGen2

[laneLinkStatus]	*table(numeric string) = PmaLinkStatus* see 2.548.1.2.27.1	PMA lane link status.
[laneSignalDetect]	*table(numeric string) = PmaSignalDetect* see 2.548.1.2.27.3	PMA lane signal detect.
[laneTxStatus]	*table(numeric string) = PmaTxStatus* see 2.548.1.2.34.1	PMA per lane transmit status.
[linkStatus]	*PmaLinkStatus* see 2.548.1.2.27.1	PMA link status.
[rxFault]	*PmaRxFault* see 2.548.1.2.27.2	PMA receive fault.
[signalDetect]	*PmaSignalDetect* see 2.548.1.2.27.3	PMA signal detect.
[txFault]	*PmaTxFault* see 2.548.1.2.27.4	PMA transmit fault.
[txStatus]	*PmaTxStatus* see 2.548.1.2.34.1	PMA lane aggregate transmit status.

2.548.1.2.37 PmaBaseT

[laneSignalDetect]	*table(numeric string) = PmaSignalDetect* see 2.548.1.2.27.3	PMA lane signal detect.
[linkPartnerInfoValid]	*LpInformationValid* see 2.548.1.2.37.1	Whether or not link partner information is valid.
[linkStatus]	*PmaLinkStatus* see 2.548.1.2.27.1	PMA link status.
[rxFault]	*PmaRxFault* see 2.548.1.2.27.2	PMA receive fault.
[signalDetect]	*PmaSignalDetect* see 2.548.1.2.27.3	PMA signal detect.
[txFault]	*PmaTxFault* see 2.548.1.2.27.4	PMA transmit fault.

2.548.1.2.37.1 LpInformationValid

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.38 PmaModel

[laneSignalDetect]	*table(numeric string) = PmaSignalDetect* see 2.548.1.2.27.3	PMA lane signal detect.
[linkPartnerInfoValid]	*LpInformationValid* see 2.548.1.2.37.1	Whether or not link partner information is valid.
[linkStatus]	*PmaLinkStatus* see 2.548.1.2.27.1	PMA link status.
[rxFault]	*PmaRxFault* see 2.548.1.2.27.2	PMA receive fault.
[signalDetect]	*PmaSignalDetect* see 2.548.1.2.27.3	PMA signal detect.
[txFault]	*PmaTxFault* see 2.548.1.2.27.4	PMA transmit fault.

2.548.1.2.39 PmaClause45

[laneSignalDetect]	*table(numeric string) = PmaSignalDetect* see 2.548.1.2.27.3	PMA lane signal detect.
[linkStatus]	*PmaLinkStatus* see 2.548.1.2.27.1	PMA link status.
[rxFault]	*PmaRxFault* see 2.548.1.2.27.2	PMA receive fault.
[signalDetect]	*PmaSignalDetect* see 2.548.1.2.27.3	PMA signal detect.
[txFault]	*PmaTxFault* see 2.548.1.2.27.4	PMA transmit fault.

2.548.1.2.40 ShortfinPmaModel

[laneSignalDetect]	*table(numeric string) = PmaSignalDetect* see 2.548.1.2.27.3	PMA lane signal detect.
[linkStatus]	*PmaLinkStatus* see 2.548.1.2.27.1	PMA link status.
[rxFault]	*PmaRxFault* see 2.548.1.2.27.2	PMA receive fault.
[signalDetect]	*PmaSignalDetect* see 2.548.1.2.27.3	PMA signal detect.
[txFault]	*PmaTxFault* see 2.548.1.2.27.4	PMA transmit fault.

2.548.1.2.41 Rs

Could also be an instance of:
RsBaseR 2.548.1.2.42

2.548.1.2.42 RsBaseR

[localFault]	*RsLocalFault* see 2.548.1.2.42.1	MAC Local fault.
[remoteFault]	*RsRemoteFault* see 2.548.1.2.42.2	MAC remote fault.

2.548.1.2.42.1 RsLocalFault

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.2.42.2 RsRemoteFault

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.3 AlaskaLinePhyModel

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
downShift	*DownShift* see 2.548.1.3.1	Downshift.

dtePower	*DtePower* see 2.548.1.3.2	DTE Power.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
fifoIdleDeleted	*FifoIdleDeleted* see 2.548.1.3.3	FifoIdleDeleted.
fifoIdleInserted	*FifoIdleInserted* see 2.548.1.3.4	FifoIdleInserted.
fifoUnderflow	*FifoUnderflow* see 2.548.1.3.5	FifoUnderflow.
[idleErrorCount]	*IdleErrorCount* see 2.548.1.2.2.9	IdleErrorCount.
jabber	*Jabber* see 2.548.1.3.6	Jabber.
linkStatus	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
[localReceiverOk]	*LocalReceiverOk* see 2.548.1.3.7	LocalReceiverOk.
[masterSlaveFault]	*MasterSlaveFault* see 2.548.1.3.8	MasterSlaveFault.
mdi	*Mdi* see 2.548.1.3.9	MDI.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
polarity	*Polarity* see 2.548.1.3.10	Polarity.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[remoteReceiverOk]	*RemoteReceiverOk* see 2.548.1.3.11	RemoteReceiverOk.
resolved	*Resolved* see 2.548.1.3.12	Speed/duplex resolution.
[resolvedToMaster]	*ResolvedToMaster* see 2.548.1.3.13	ResolvedToMaster.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.3.1 DownShift

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.3.2 DtePower

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.3.3 FifoIdleDeleted

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.3.4 FifoIdleInserted

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.3.5 FifoUnderflow

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.3.6 Jabber

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.3.7 LocalReceiverOk

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.3.8 MasterSlaveFault

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.

value	*boolean*	Whether or not a condition is true or present.

2.548.1.3.9 Mdi

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.3.10 Polarity

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.3.11 RemoteReceiverOk

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.3.12 Resolved

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.3.13 ResolvedToMaster

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.4 AlaskaSystemPhyModel

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.

linkStatus	*PcsLinkStatus* see 2.548.1.2.9.5	PCS link status.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
qsgmiiAnegBypass	*QsgmiiAnegBypass* see 2.548.1.4.1	QsgmiiAnegBypass.
qsgmiiSyncStatus	*QsgmiiSyncStatus* see 2.548.1.4.2	QsgmiiSyncStatus.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.4.1 QsgmiiAnegBypass

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.4.2 QsgmiiSyncStatus

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.5 B52ChipPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
firmwareRev	*string*	PHY firmware revision.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.6 B52LinePhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
lanes	*table(numeric string) = CredoPhySerdes* see 2.548.1.6.2	A mapping of SerDes lane to SerDes diagnostic information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.
[topPllVcoCap]	*CredoPhyPllVcoCap* see 2.548.1.6.1	Maximum voltage control oscillator capacitor of phase locked loop over all lanes.

2.548.1.6.1 CredoPhyPllVcoCap

[rxPllCap]	*integer*	Rx VcoCap of Pll, encoded as 0 to 127.
[txPllCap]	*integer*	Tx VcoCap of Pll, encoded as 0 to 127.

2.548.1.6.2 CredoPhySerdes

[adaptCnt]	*CredoPhyAdaptCnt* see 2.548.1.2.2.3	Firmware adaptation counter.
[adaptCompleted]	*CredoPhyAdaptCompleted* see 2.548.1.6.2.1	Firmware adaptation completed.
[channelEst]	*floating point number*	Channel estimation.
[ctleGain]	*list of integer*	SerDes lane Continuous Time Linear Equalizer gain values.
[ctlePeaking]	*list of integer*	SerDes lane Continuous Time Linear Equalizer peaking values.
[dfeTaps]	*list of floating point number*	SerDes lane Decision Feedback Equalizer taps, ordered as main tap first tap, second tap, ... , last tap and initial tap.
[eyeMargins]	*list of floating point number*	Eye margin in mV, in case of multi-bit encodings, ordered by top to bottom.
[highFreqTrans]	*integer*	High frequency transition count after equalization.
[linkLostCnt]	*CredoPhyLinkLostCnt* see 2.548.1.2.2.4	Firmware link lost counter.
linkTrainingEnable **	*boolean*	Tx link training enable. **Since: 4.24.2

linkTrainingStatus **	*enum: invalid | link-ready | train-remote | init | failed | train-local | in-training | complete*	Link training Status. **Since: 4.24.2
[losCnt] **	*CredoPhyLossOfSignalCnt* see 2.548.1.2.2.5	Firmware lost of signal counter. **Since: 4.26.2
[pllVcoCap]	*CredoPhyPllVcoCap* see 2.548.1.6.1	Voltage control oscillator capacitor of phase locked loop.
[reAdaptCnt]	*CredoPhyReAdaptCnt* see 2.548.1.2.2.6	Firmware re-adaptation counter.
[rxDacGain]	*integer*	RX digital sampler gain value.
rxFreqPPM	*integer*	Frequency offset of local reference clock with respect to the frequency of received data in parts per million of Hz.
[signalAmplitude]	*integer*	Signal envelope to represent the amplitude of signal after equalization, encoded as 0 to 63.
[txTaps]	*CredoPhyTxTaps* see 2.548.1.6.2.2	SerDes lane TX pre-emphasis taps.

2.548.1.6.2.1 CredoPhyAdaptCompleted

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.6.2.2 CredoPhyTxTaps

main	*integer*	The main cursor tap.
post1	*integer*	The first post cursor tap.
post2	*integer*	The second post cursor tap.
pre1	*integer*	The first pre cursor tap.
pre2	*integer*	The second pre cursor tap.

2.548.1.7 B52PhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
lanes	*table(numeric string) = CredoPhySerdes* see 2.548.1.6.2	A mapping of SerDes lane to SerDes diagnostic information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.

[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.
[topPllVcoCap]	*CredoPhyPllVcoCap* see 2.548.1.6.1	Maximum voltage control oscillator capacitor of phase locked loop over all lanes.

2.548.1.8 B52SystemPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
lanes	*table(numeric string) = CredoPhySerdes* see 2.548.1.6.2	A mapping of SerDes lane to SerDes diagnostic information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.
[topPllVcoCap]	*CredoPhyPllVcoCap* see 2.548.1.6.1	Maximum voltage control oscillator capacitor of phase locked loop over all lanes.

2.548.1.9 BabbageChipPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
firmwareRev	*string*	PHY firmware revision.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.10 BabbageLinePhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
lanes	*table(numeric string) = CredoPhySerdes* see 2.548.1.6.2	A mapping of SerDes network lane to CRT50216/CRT55321 SerDes info.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.
[topPllVcoCap]	*CredoPhyPllVcoCap* see 2.548.1.6.1	Maximum voltage control oscillator capacitor of phase locked loop over all lanes.

2.548.1.11 BabbageSystemPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
lanes	*table(numeric string) = CredoPhySerdes* see 2.548.1.6.2	A mapping of SerDes system lane to CRT50216/CRT55321 SerDes info.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.
[topPllVcoCap]	*CredoPhyPllVcoCap* see 2.548.1.6.1	Maximum voltage control oscillator capacitor of phase locked loop over all lanes.

2.548.1.12 Bcm1338PhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.

[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*BlackhawkLtOptionalPhySerdesModel* see 2.548.1.12.1	The SerDes statistics.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.12.1 BlackhawkLtOptionalPhySerdesModel

serdesStats	*table(numeric string) = BlackhawkPhySerdesLaneModelBase* see 2.548.1.12.1.1	The serdes statistics.
sortedSerdesStats	*list of integer*	Sorted Serdes statistics.

2.548.1.12.1.1 BlackhawkPhySerdesLaneModelBase

Could also be an instance of:
BlackhawkLtOptionalPhySerdesLaneModel 2.548.1.12.1.2
BlackhawkPhySerdesLaneModel 2.548.1.12.1.3

brPdEnable	*enum: OS | BR*	Baud rate phase detector enable.
[brPdForced] **	*boolean*	Whether the BR CDR is forced. **Since: 4.30.2
[dfeTaps]	*table(numeric string) = integer*	Serdes lane Decision Feedback Equalizer (DFE) taps.
[eyeLeft]	*integer*	Horizontal left eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI.
[eyeLower]	*integer*	Vertical lower eye margin @ 1e-5 as seen by internal diagnostic slicer in mV.
[eyeRight]	*integer*	Horizontal right eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI.
[eyeUpper]	*integer*	Vertical upper eye margin @ 1e-5 as seen by internal diagnostic slicer in mV.
highFrequencyPeakingFilter	*integer*	High frequency peaking filter control.
lowFrequncyPeakingFilter	*integer*	Low frequency peaking filter control.
m1SlicerThreshold	*integer*	Vertical threshold voltage of m1 slicer (mV), 'channel loss hint' in PAM4 mode should always be 0.
mainPeakingFilter	*integer*	Peaking filter main settings.
[osPdForced] **	*boolean*	Whether the OS CDR is forced. **Since: 4.30.2
p1SlicerThreshold	*integer*	Vertical threshold voltage of p1 slicer (mV).

rxPamMode	*enum: PAM4_ES | PAM4_NS | NRZ*	Receiver PAM4 mode.
[rxPpm]	*integer*	Frequency offset of local reference clock with respect to the frequency of received data in ppm.
[txPpm]	*integer*	Frequency offset of local reference clock with respect to the transmit data in ppm.
[txTaps]	*table(numeric string) = integer*	Serdes lane TX pre-emphasis taps.
[vga]	*integer*	Variable gain amplifier value.

2.548.1.12.1.2 BlackhawkLtOptionalPhySerdesLaneModel

brPdEnable	*enum: OS | BR*	Baud rate phase detector enable.
[brPdForced] **	*boolean*	Whether the BR CDR is forced. **Since: 4.30.2
[dfeTaps]	*table(numeric string) = integer*	Serdes lane Decision Feedback Equalizer (DFE) taps.
[eyeLeft]	*integer*	Horizontal left eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI.
[eyeLower]	*integer*	Vertical lower eye margin @ 1e-5 as seen by internal diagnostic slicer in mV.
[eyeRight]	*integer*	Horizontal right eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI.
[eyeUpper]	*integer*	Vertical upper eye margin @ 1e-5 as seen by internal diagnostic slicer in mV.
highFrequencyPeakingFilter	*integer*	High frequency peaking filter control.
[linkTrainingEnable]	*boolean*	Tx link training enable.
[linkTrainingStatus]	*enum: invalid | link-ready | train-remote | init | failed | train-local | in-training | complete*	Link training status.
lowFrequncyPeakingFilter	*integer*	Low frequency peaking filter control.
m1SlicerThreshold	*integer*	Vertical threshold voltage of m1 slicer (mV), 'channel loss hint' in PAM4 mode should always be 0.
mainPeakingFilter	*integer*	Peaking filter main settings.
[osPdForced] **	*boolean*	Whether the OS CDR is forced. **Since: 4.30.2
p1SlicerThreshold	*integer*	Vertical threshold voltage of p1 slicer (mV).
[rxDecoderEnable]	*boolean*	Rx decode enable.
rxPamMode	*enum: PAM4_ES | PAM4_NS | NRZ*	Receiver PAM4 mode.
[rxPpm]	*integer*	Frequency offset of local reference clock with respect to the frequency of received data in ppm.
[txPpm]	*integer*	Frequency offset of local reference clock with respect to the transmit data in ppm.
[txPrecoderEnable]	*boolean*	Tx precoder enable.

[txTaps]	*table(numeric string) = integer*	Serdes lane TX pre-emphasis taps.
[vga]	*integer*	Variable gain amplifier value.

2.548.1.12.1.3 BlackhawkPhySerdesLaneModel

brPdEnable	*enum: OS | BR*	Baud rate phase detector enable.
[brPdForced] **	*boolean*	Whether the BR CDR is forced. **Since: 4.30.2
[dfeTaps]	*table(numeric string) = integer*	Serdes lane Decision Feedback Equalizer (DFE) taps.
[eyeLeft]	*integer*	Horizontal left eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI.
[eyeLower]	*integer*	Vertical lower eye margin @ 1e-5 as seen by internal diagnostic slicer in mV.
[eyeRight]	*integer*	Horizontal right eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI.
[eyeUpper]	*integer*	Vertical upper eye margin @ 1e-5 as seen by internal diagnostic slicer in mV.
highFrequencyPeakingFilter	*integer*	High frequency peaking filter control.
linkTrainingEnable	*boolean*	Tx link training enable.
linkTrainingStatus	*enum: invalid | link-ready | train-remote | init | failed | train-local | in-training | complete*	Link training status.
lowFrequncyPeakingFilter	*integer*	Low frequency peaking filter control.
m1SlicerThreshold	*integer*	Vertical threshold voltage of m1 slicer (mV), 'channel loss hint' in PAM4 mode should always be 0.
mainPeakingFilter	*integer*	Peaking filter main settings.
[osPdForced] **	*boolean*	Whether the OS CDR is forced. **Since: 4.30.2
p1SlicerThreshold	*integer*	Vertical threshold voltage of p1 slicer (mV).
rxDecoderEnable	*boolean*	Rx decode enable.
rxPamMode	*enum: PAM4_ES | PAM4_NS | NRZ*	Receiver PAM4 mode.
[rxPpm]	*integer*	Frequency offset of local reference clock with respect to the frequency of received data in ppm.
[txPpm]	*integer*	Frequency offset of local reference clock with respect to the transmit data in ppm.
txPrecoderEnable	*boolean*	Tx precoder enable.
[txTaps]	*table(numeric string) = integer*	Serdes lane TX pre-emphasis taps.
[vga]	*integer*	Variable gain amplifier value.

2.548.1.13 Bcm81338LinePhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*BlackhawkLtOptionalPhy-SerdesModel* see 2.548.1.12.1	The SerDes statistics.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.14 Bcm81338SystemPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*BlackhawkLtOptionalPhy-SerdesModel* see 2.548.1.12.1	The SerDes statistics.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.15 Bcm54185LinePhyModel

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.

[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.16 Bcm54185PhyModel

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
chipStatus	*PhyChipStatus* see 2.548.1.2.22	Bcm54185 chip status.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
speed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.17 Bcm541x2LinePhyModel

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
mdiStatus **	*MdiCrossoverModel* see 2.548.1.17.1	MDI/MDI-X status. **Since: 4.30.0
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.

[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.17.1 MdiCrossoverModel

changes	*integer*	Number of MDI state changes.
lastChange	*floating point number*	Last time MDI state changed.
mdiState	*enum: mdix | mdi*	MDI/MDI-X layout.

2.548.1.18 Bcm541x2PhyModel

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
chipStatus	*PhyChipStatus* see 2.548.1.2.22	Bcm541x2 chip status.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
speed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.19 Bcm81338ChipPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
firmwareRev	*string*	PHY firmware revision.

[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.20 Bcm87728ChipPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
firmwareRev **	*string*	PHY firmware revision. **Since: 4.30.1
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.21 Bcm87728LinePhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes **	*BlackhawkLtOptionalPhySerdesModel* see 2.548.1.12.1	The SerDes statistics. **Since: 4.30.1
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.22 Bcm87728PhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes **	*BlackhawkLtOptionalPhySerdesModel* see 2.548.1.12.1	The SerDes statistics. **Since: 4.30.1
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.23 Bcm87728SystemPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes **	*BlackhawkLtOptionalPhySerdesModel* see 2.548.1.12.1	The SerDes statistics. **Since: 4.30.1
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.24 BlackhawkPhyIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.

[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*BlackhawkPhySerdes* see 2.548.1.24.1	The serdes stats.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.24.1 BlackhawkPhySerdes

serdesStats	*table(numeric string) = BlackhawkPhySerdesLaneModelBase* see 2.548.1.12.1.1	The serdes statistics.
sortedSerdesStats	*list of integer*	Sorted Serdes statistics.

2.548.1.24.2 PhyState

changes	*integer*	Number of PHY state changes.
lastChange	*floating point number*	Last time PHY state changed.
value	*enum: unknown | autonegotiating | linkUp | detectingXcvr | linkDown | init | errDisabled*	Current PHY state.

2.548.1.25 IntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
configStrap	*integer*	Config strap pins register.
description	*PhyDescription* see 2.548.1.2.25	Phy description.

[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyLinkState	*integer*	Link status register.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.26 IntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.

[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*CellBasedPeregrinePhySerdesModel* see 2.548.1.26.1	The SerDes stats.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.26.1 CellBasedPeregrinePhySerdesModel

serdesStats	*table(numeric string) = PeregrinePhySerdesLaneModel* see 2.548.1.26.1.1	A mapping of lanes to SerDes statistics.

2.548.1.26.1.1 PeregrinePhySerdesLaneModel

Could also be an instance of:
CondorPhySerdesLaneModel 2.548.1.26.1.2

brForced	*boolean*	Whether the BR CDR is forced.
cdrMode	*enum: OS | BR*	Baud Rate Phase Detector enable.
[dfeTaps]	*table(numeric string) = integer*	Serdes lane Decision Feedback Equalizer (DFE) taps.
[eyeLower]	*integer*	Lower Eye margin @ 1e-5 (NRZ) or 1e-3 (PAM4) as seen by internal diagnostic slicer in mV.
[eyeMiddle]	*integer*	Middle Eye margin @ 1e-5 (NRZ) or 1e-3 (PAM4) as seen by internal diagnostic slicer in mV.
[eyeUpper]	*integer*	Upper Eye margin @ 1e-5 (NRZ) or 1e-3 (PAM4) as seen by internal diagnostic slicer in mV.
floatingTapMax	*integer*	Max magnitude of all floating taps.
floatingTapSum	*integer*	Absolute sum of magnitudes of all taps.
highFrequencyPeakingFilter	*integer*	High frequency peaking filter control.
linkTrainingStatus	*enum: timeout | invalid | link-ready | train-remote | init | failed | train-local | in-training | complete | off*	Link training Status.
lowFrequencyPeakingFilter	*integer*	Low frequency peaking filter control.
midFrequencyPeakingFilter	*integer*	Mid frequency peaking filter control.
osForced	*boolean*	Whether the OS CDR is forced.
rxFfe	*table(numeric string) = integer*	A mapping of RX feed-forward equalizer (FFE) tap indices to their values.
rxPamMode	*enum: PAM4_ES | PAM4_NS | NRZ*	Receiver PAM4 mode.
[rxPpm]	*integer*	Frequency offset of local reference clock with respect to the frequency of received data in ppm.

snrDfe	*floating point number*	SNR in db. (20.42, 19.46, 18.26 corresponding roughly to 1e-6,1e-5,1e-4 PAM4 BER).
tp0	*integer*	Echos 'RX_Channel_Loss_hint' provided by user in both PAM4 and NRZ modes.
tp1	*integer*	Initial Channel Loss Estimate from 0-50:Range corresponds with short to long channels.
tp2	*enum: LinkCAT | 2 | 0 | HalfRate | 10GRate | 1*	AFE Static BW setting. 0 to 2 - Used for 100G, tuned at link startup on short channels.
txPiEn	*boolean*	TX phase interpolator enable.
[txPpm]	*integer*	Frequency offset of local reference clock with respect to the transmit data in ppm.
txPrecoderEnable	*boolean*	TX precoder enable.
[txTaps]	*table(numeric string) = integer*	Serdes lane TX pre-emphasis taps.
[vga]	*integer*	Variable gain amplifier value.

2.548.1.26.1.2 CondorPhySerdesLaneModel

brForced	*boolean*	Whether the BR CDR is forced.
cdrMode	*enum: OS | BR*	Baud Rate Phase Detector enable.
[dfeTaps]	*table(numeric string) = integer*	Serdes lane Decision Feedback Equalizer (DFE) taps.
[eyeLower]	*integer*	Lower Eye margin @ 1e-5 (NRZ) or 1e-3 (PAM4) as seen by internal diagnostic slicer in mV.
[eyeMiddle]	*integer*	Middle Eye margin @ 1e-5 (NRZ) or 1e-3 (PAM4) as seen by internal diagnostic slicer in mV.
[eyeUpper]	*integer*	Upper Eye margin @ 1e-5 (NRZ) or 1e-3 (PAM4) as seen by internal diagnostic slicer in mV.
floatingTapMax	*integer*	Max magnitude of all floating taps.
floatingTapSum	*integer*	Absolute sum of magnitudes of all taps.
highFrequencyPeakingFilter	*integer*	High frequency peaking filter control.
linkTrainingStatus	*enum: timeout | invalid | link-ready | train-remote | init | failed | train-local | in-training | complete | off*	Link training Status.
lowFrequencyPeakingFilter	*integer*	Low frequency peaking filter control.
midFrequencyPeakingFilter	*integer*	Mid frequency peaking filter control.
osForced	*boolean*	Whether the OS CDR is forced.
rxFfe	*table(numeric string) = integer*	A mapping of RX feed-forward equalizer (FFE) tap indices to their values.
rxPamMode	*enum: PAM4_ES | PAM4_NS | NRZ*	Receiver PAM4 mode.
[rxPpm]	*integer*	Frequency offset of local reference clock with respect to the frequency of received data in ppm.

snrDfe	*floating point number*	SNR in db. (20.42, 19.46, 18.26 corresponding roughly to 1e-6,1e-5,1e-4 PAM4 BER).
tp0	*integer*	Echos 'RX_Channel_Loss_hint' provided by user in both PAM4 and NRZ modes.
tp1	*integer*	Initial Channel Loss Estimate from 0-50:Range corresponds with short to long channels.
tp2	*enum: LinkCAT | 2 | 0 | HalfRate | 10GRate | 1*	AFE Static BW setting. 0 to 2 - Used for 100G, tuned at link startup on short channels.
txPiEn	*boolean*	TX phase interpolator enable.
[txPpm]	*integer*	Frequency offset of local reference clock with respect to the transmit data in ppm.
txPrecoderEnable	*boolean*	TX precoder enable.
[txTaps]	*table(numeric string) = integer*	Serdes lane TX pre-emphasis taps.
[vga]	*integer*	Variable gain amplifier value.

2.548.1.27 IntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.

serdes	*D5PhySerdesModel* see 2.548.1.27.1	SerDes information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.27.1 D5PhySerdesModel

serdesStats	*table(numeric string) = D5PhySerdesLaneModel* see 2.548.1.27.1.1	A mapping of lanes to SerDes statistics.

2.548.1.27.1.1 D5PhySerdesLaneModel

aeq	*integer*	High frequency gain.
[dfeTaps]	*table(numeric string) = integer*	Serdes lane Decision Feedback Equalizer (DFE) taps.
dlevEven	*integer*	Arista internal.
dlevOdd	*integer*	Arista internal.
eyeLeft **	*integer*	Horizontal left eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI. **Since: 4.35.2
eyeLower **	*integer*	Vertical lower eye margin @ 1e-5 as seen by internal diagnostic slicer in mV. **Since: 4.35.2
eyeRight **	*integer*	Horizontal right eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI. **Since: 4.35.2
eyeUpper **	*integer*	Vertical upper eye margin @ 1e-5 as seen by internal diagnostic slicer in mV. **Since: 4.35.2
h1n0	*integer*	DFE Tap 1 n0.
h1n1	*integer*	DFE Tap 1 n1.
h1p0	*integer*	DFE Tap 1 p0.
h1p1	*integer*	DFE Tap 1 p1.
passEq	*integer*	Arista internal.
[rxPpm]	*integer*	Frequency offset of local reference clock with respect to the frequency of received data in ppm.
[txPpm]	*integer*	Frequency offset of local reference clock with respect to the transmit data in ppm.
[txTaps]	*table(numeric string) = integer*	Serdes lane TX pre-emphasis taps.
[vga]	*integer*	Variable gain amplifier value.

2.548.1.28 IntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.

[interruptCount]	*integer*	PHY interrupt counter.
[jabberDetect]	*JabberDetect* see 2.548.1.28.2	Jabber status.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[mdiStatus]	*MdiCrossoverModel* see 2.548.1.17.1	MDI/MDI-X status.
[miiRemoteFault]	*MiiRemoteFault* see 2.548.1.28.1	MII remote fault status.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[speedDownshifted]	*SpeedDownshifted* see 2.548.1.28.3	Ethernet@Wirespeed downgrade status (due to unstable link).
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.28.1 MiiRemoteFault

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.28.2 JabberDetect

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.28.3 SpeedDownshifted

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.29 IntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*OspreyPhySerdesModel* see 2.548.1.29.1	SerDes information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.29.1 OspreyPhySerdesModel

serdesStats	*table(numeric string) = OspreyPhySerdesLaneModel* see 2.548.1.29.1.1	The SerDes statistics.

2.548.1.29.1.1 OspreyPhySerdesLaneModel

brPdEnable **	*enum: OS | BR*	Baud rate phase detector enable. **Since: 4.30.0
[brPdForced] **	*boolean*	Whether the BR CDR is forced. **Since: 4.35.2
dfeSIdx	*integer*	Total DFE activity Index.
[dfeTaps]	*table(numeric string) = integer*	Serdes lane Decision Feedback Equalizer (DFE) taps.
disableEyeDisplay	*boolean*	Whether eye values are to be displayed.
enable6Taps	*boolean*	6 tap TX equalization enabled.
eyeLeft	*integer*	Horizontal left eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI.
eyeLower	*integer*	Vertical lower eye margin @ 1e-5 as seen by internal diagnostic slicer in mV.
eyeRight	*integer*	Horizontal right eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI.
eyeUpper	*integer*	Vertical upper eye margin @ 1e-5 as seen by internal diagnostic slicer in mV.
fga	*integer*	Fixed Gain Amplifier gain.
highFrequencyPeakingFilter	*integer*	High frequency peaking filter control.
linkTrainingEnable	*boolean*	TX link training enable.
linkTrainingStatus	*enum: invalid | link-ready | train-remote | init | failed | train-local | in-training | complete*	Link training Status.
lowFrequencyPeakingFilter	*integer*	Low frequency peaking filter control.
mid1PeakingFilter	*integer*	Peaking filter mid1 settings.
mid2PeakingFilter	*integer*	Peaking filter mid2 settings.
[osPdForced] **	*boolean*	Whether the OS CDR is forced. **Since: 4.35.2
p1mV	*integer*	Vertical threshold voltage of p1 slicer (mV).
rxFfeEnabled	*boolean*	RX feed-forward equalizer enabled.
rxFfeGain	*integer*	RX feed-forward equalizer gain.
rxFfeN1	*integer*	RX feed-forward equalizer pre1.
rxFfeP1	*integer*	RX feed-forward equalizer post1.
rxPamMode	*enum: PAM4_ES | PAM4_NS | NRZ*	Receiver PAM4 mode.
[rxPpm]	*integer*	Frequency offset of local reference clock with respect to the frequency of received data in ppm.
tp0	*integer*	Tuning parameter 0. Vertical threshold voltage of m1 slicer (mV), 'channel loss hint' in PAM4 mode should always be 0.
tp1	*integer*	AFE Initial Channel Loss Estimate from 0 to 31, a negative value is an indicator of over-equalization.
tp2	*integer*	Feedback to optimize TX pre-emphasis tap pre2, suboptimal outside +/- 20.
tp3	*integer*	Feedback to optimize TX pre-emphasis tap pre3, suboptimal outside +/- 20.

txPiEn	*enum: Disabled | Enabled*	TX phase interpolator enable.
[txPpm]	*integer*	Frequency offset of local reference clock with respect to the transmit data in ppm.
txPrecoderEnable	*boolean*	TX precoder enable.
[txTaps]	*table(numeric string) = integer*	Serdes lane TX pre-emphasis taps.
[vga]	*integer*	Variable gain amplifier value.

2.548.1.30 IntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*PeregrinePhySerdesModel* see 2.548.1.30.1	SerDes information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.30.1 PeregrinePhySerdesModel

Could also be an instance of:
CondorPhySerdesModel 2.548.1.30.2
CellBasedPeregrinePhySerdesModel 2.548.1.26.1

serdesStats	*table(numeric string) = PeregrinePhySerdesLaneModel* see 2.548.1.26.1.1	A mapping of lanes to SerDes statistics.

2.548.1.30.2 CondorPhySerdesModel

serdesStats	*table(numeric string) = PeregrinePhySerdesLaneModel* see 2.548.1.26.1.1	A mapping of lanes to SerDes statistics.

2.548.1.31 IntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*TalonPhySerdesModel* see 2.548.1.31.1	SerDes information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.31.1 TalonPhySerdesModel

Could also be an instance of:
TalonPhySerdes 2.548.1.31.2

serdesStats	*table(numeric string) = TalonPhySerdesLaneModel* see 2.548.1.31.1.1	A mapping of lanes to SerDes statistics.

2.548.1.31.1.1 TalonPhySerdesLaneModel

aeq **	*integer*	AFE boost. **Since: 4.35.2
bga **	*enum: ena | frz*	Background RX adaptation. **Since: 4.35.2
[dfeTaps]	*table(numeric string) = integer*	Serdes lane Decision Feedback Equalizer (DFE) taps.
[eyeLower] **	*integer*	Lower eye vertical opening @ 1e-6 (NRZ) or 1e-3 (PAM4) as seen by internal diagnostic slicer in mV. **Since: 4.35.2
[eyeMiddle] **	*integer*	Middle eye vertical opening @ 1e-6 (NRZ) or 1e-3 (PAM4) as seen by internal diagnostic slicer in mV. **Since: 4.35.2
[eyeUpper] **	*integer*	Upper eye vertical opening @ 1e-6 (NRZ) or 1e-3 (PAM4) as seen by internal diagnostic slicer in mV. **Since: 4.35.2
fldAcc **	*integer*	False lock detection accumulator. **Since: 4.35.2
fldCnt **	*integer*	False lock detection count. **Since: 4.35.2
fldEn **	*boolean*	False lock detection enabled. **Since: 4.35.2
linkTrainingStatus **	*enum: invalid | link-ready | train-remote | init | failed | train-local | in-training | complete | off*	Link training Status. **Since: 4.35.2
pllDiv **	*floating point number*	RX PLL divider. **Since: 4.35.2
pllLock **	*boolean*	RX PLL locked. **Since: 4.35.2
rxFfe **	*table(numeric string) = integer*	A mapping of RX feed-forward equalizer (FFE) tap indices to their values. **Since: 4.35.2
rxPamMode **	*enum: PAM4_ES | PAM4_NS | NRZ*	Receiver PAM4 mode. **Since: 4.35.2
[rxPpm]	*integer*	Frequency offset of local reference clock with respect to the frequency of received data in ppm.
[txPpm]	*integer*	Frequency offset of local reference clock with respect to the transmit data in ppm.
[txTaps]	*table(numeric string) = integer*	Serdes lane TX pre-emphasis taps.
vcoA **	*integer*	VCO band A calibration value. **Since: 4.35.2
[vga]	*integer*	Variable gain amplifier value.

2.548.1.31.2 TalonPhySerdes

serdesStats	*table(numeric string) = TalonPhySerdesLaneModel* see 2.548.1.31.1.1	A mapping of lanes to SerDes statistics.

2.548.1.32 IntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*BlackhawkPhySerdesModel* see 2.548.1.32.1	SerDes information keyed by serdes lanes number (starting at 0).
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.32.1 BlackhawkPhySerdesModel

Could also be an instance of:
BlackhawkPhySerdes 2.548.1.24.1
MerlinPhySerdesModel 2.548.1.32.2

serdesStats	*table(numeric string) = BlackhawkPhySerdesLaneModelBase* see 2.548.1.12.1.1	The serdes statistics.
sortedSerdesStats	*list of integer*	Sorted Serdes statistics.

2.548.1.32.2 MerlinPhySerdesModel

serdesStats	*table(numeric string) = BlackhawkPhySerdesLaneModelBase* see 2.548.1.12.1.1	The serdes statistics.
sortedSerdesStats	*list of integer*	Sorted Serdes statistics.

2.548.1.33 IntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*table(numeric string) = TscfSerdesLaneStatus* see 2.548.1.33.1	SerDes information keyed by serdes lanes number (starting at 0).
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.33.1 TscfSerdesLaneStatus

Could also be an instance of:
TsceSerdesLaneStatus 2.548.1.33.2

[dfeTaps]	*table(numeric string) = integer*	Serdes lane Decision Feedback Equalizer (DFE) taps.
eyeLeft	*integer*	Horizontal left eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI.
eyeLower	*integer*	Vertical lower eye margin @ 1e-5 as seen by internal diagnostic slicer in mV.
eyeRight	*integer*	Horizontal right eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI.
eyeUpper	*integer*	Vertical upper eye margin @ 1e-5 as seen by internal diagnostic slicer in mV.
lowFrequncyPeakingFilter	*integer*	Low frequency peaking filter control.
mainPeakingFilter	*integer*	Peaking filter main settings.
[rxPpm]	*integer*	Frequency offset of local reference clock with respect to the frequency of received data in ppm.
[txPpm]	*integer*	Frequency offset of local reference clock with respect to the transmit data in ppm.
[txTaps]	*table(numeric string) = integer*	Serdes lane TX pre-emphasis taps.
[vga]	*integer*	Variable gain amplifier value.

2.548.1.33.2 TsceSerdesLaneStatus

[dfeDcd]	*table(numeric string) = integer*	A mapping from SerDes lane to DFE Duty Cycle Distortion (DCD).
[dfeTaps]	*table(numeric string) = integer*	Serdes lane Decision Feedback Equalizer (DFE) taps.
eyeLeft	*integer*	Horizontal left eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI.
eyeLower	*integer*	Vertical lower eye margin @ 1e-5 as seen by internal diagnostic slicer in mV.
eyeRight	*integer*	Horizontal right eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI.
eyeUpper	*integer*	Vertical upper eye margin @ 1e-5 as seen by internal diagnostic slicer in mV.
lowFrequncyPeakingFilter	*integer*	Low frequency peaking filter control.
mainPeakingFilter	*integer*	Peaking filter main settings.
[rxPpm]	*integer*	Frequency offset of local reference clock with respect to the frequency of received data in ppm.
[txPpm]	*integer*	Frequency offset of local reference clock with respect to the transmit data in ppm.
[txTaps]	*table(numeric string) = integer*	Serdes lane TX pre-emphasis taps.
[vga]	*integer*	Variable gain amplifier value.

2.548.1.34 IntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*table(numeric string) = Wc40SerdesLaneStatus* see 2.548.1.34.1	A mapping from serdes lane ID to serdes statistics.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.34.1 Wc40SerdesLaneStatus

analogPllLock	*ConditionAndChangedStat* see 2.548.1.34.1.1	Serdes PLL lock.
[dfeTaps]	*table(numeric string) = integer*	Serdes lane Decision Feedback Equalizer (DFE) taps.
integRegXfer	*integer*	Serdes lane PPM transfer.
pfCtrl	*integer*	Serdes lane peaking filter control.
pllRange	*integer*	Serdes PLL range in Hz.
postcMetric	*integer*	Serdes lane post cursor metric.
rxLosSdkEnabled	*integer*	SDK RX los enabled state.
[rxPpm]	*integer*	Frequency offset of local reference clock with respect to the frequency of received data in ppm.
slicerTarget	*integer*	Serdes lane slicer target.

[txPpm]	*integer*	Frequency offset of local reference clock with respect to the transmit data in ppm.
[txTaps]	*table(numeric string) = integer*	Serdes lane TX pre-emphasis taps.
[vga]	*integer*	Variable gain amplifier value.

2.548.1.34.1.1 ConditionAndChangedStat

Could also be an instance of:
LpInformationValid 2.548.1.2.37.1
PcsAlignmentMarkerLock 2.548.1.2.9.1
PcsBlockLock 2.548.1.2.9.2
PcsDeskew 2.548.1.2.9.3
PcsHighBer 2.548.1.2.9.4
PcsRxFault 2.548.1.2.9.6
PcsRxLpi 2.548.1.2.9.7
PcsTxFault 2.548.1.2.9.8
PmaRxFault 2.548.1.2.27.2
PmaSignalDetect 2.548.1.2.27.3
PmaTxFault 2.548.1.2.27.4
RsLocalFault 2.548.1.2.42.1
RsRemoteFault 2.548.1.2.42.2
RsFecAlignmentLock 2.548.1.2.2.22
RsFecAlignmentMarkerLock 2.548.1.2.2.23
RsFecHiSer 2.548.1.2.2.24
CredoPhyAdaptCompleted 2.548.1.6.2.1
AdcOutput 2.548.1.2.31.1
AdcReady 2.548.1.2.31.2
DacReady 2.548.1.2.31.5
DispersionLockSet 2.548.1.2.31.7
PcsBipErrorsDetected 2.548.1.2.13.1
PcsErroredBlocksDetected 2.548.1.2.13.2
PcsLossOfAlignment 2.548.1.2.13.3
RxAsicSubsystemsConfigured 2.548.1.2.31.14
RxClockConfigured 2.548.1.2.31.15
RxDemodLockSet 2.548.1.2.31.18
TxAsicSubsystemsConfigured 2.548.1.2.31.20
TxClockConfigured 2.548.1.2.31.21
PcsDeskewAchieved 2.548.1.2.15.1
PcsLinkInterrupted 2.548.1.2.15.2
DownShift 2.548.1.3.1
DtePower 2.548.1.3.2
FifoIdleDeleted 2.548.1.3.3
FifoIdleInserted 2.548.1.3.4
FifoUnderflow 2.548.1.3.5
Jabber 2.548.1.3.6
LocalReceiverOk 2.548.1.3.7
MasterSlaveFault 2.548.1.3.8
Mdi 2.548.1.3.9
Polarity 2.548.1.3.10
QsgmiiAnegBypass 2.548.1.4.1
QsgmiiSyncStatus 2.548.1.4.2
RemoteReceiverOk 2.548.1.3.11
Resolved 2.548.1.3.12

ResolvedToMaster 2.548.1.3.13
MarvellAutonegComplete 2.548.1.34.1.2
MarvellRemoteFault 2.548.1.34.1.3
MiiLinkStatus 2.548.1.34.1.4
MiiRemoteFault 2.548.1.34.1.5
JabberDetect 2.548.1.28.2
MiiRemoteFault 2.548.1.28.1
SpeedDownshifted 2.548.1.28.3
PllLock 2.548.1.34.1.6

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.34.1.2 MarvellAutonegComplete

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.34.1.3 MarvellRemoteFault

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.34.1.4 MiiLinkStatus

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.34.1.5 MiiRemoteFault

changes	*integer*	The number of times the condition changed.
lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.34.1.6 PllLock

changes	*integer*	The number of times the condition changed.

lastChange	*floating point number*	The last time the condition changed.
value	*boolean*	Whether or not a condition is true or present.

2.548.1.35 IntfStatus

[anSmState]	*AutonegSmStatus* see 2.548.1.35.1	Autoneg SM status.
[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
pllLock	*PllLock* see 2.548.1.34.1.6	PLL Lock.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
qsgmiiEnabled	*boolean*	QSGMII (Quad Serial Gigabit Media Independent Interface) is enabled.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
sgmiiEnabled	*boolean*	SGMII (Serial Gigabit Media Independent Interface) is enabled.
[stale]	*boolean*	Status of this phy might be stale.
[txSmState]	*PcsTxSmStatus* see 2.548.1.35.2	PCS TX SM status.
usxgmiiEnabled	*boolean*	USXGMII (Universal Serial 10G Media Independent Interface) is enabled.

2.548.1.35.1 AutonegSmStatus

changes	*integer*	Number of autoneg SM state changes.
lastChange	*floating point number*	Last time autoneg SM state changed.
state	*enum: ok | error*	Current autoneg SM state.

2.548.1.35.2 PcsTxSmStatus

changes	*integer*	Number of clause 49 TX SM state changes.
lastChange	*floating point number*	Last time clause 49 TX SM state changed.
state	*enum: ok | error | init*	Current clause 49 TX SM state.

2.548.1.36 CortinaHostPhyModel

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.
stats	*CortinaXGPCSStatsModel* see 2.548.1.36.1	Additional PHY statistics.
tuningValues **	*TXEqualization* see 2.548.1.36.2	Tuning values. **Since: 4.28.1

2.548.1.36.1 CortinaXGPCSStatsModel

pcsRXErr	*PCSRXErrorCount* see 2.548.1.2.2.10	PCS RX Error Count.
pcsRXGood	*PCSRXGoodCount* see 2.548.1.2.2.11	PCS RX Good Count.
pcsTXErr	*PCSTXErrorCount* see 2.548.1.2.2.12	PCS TX Error Count.
pcsTXGood	*PCSTXGoodCount* see 2.548.1.2.2.13	PCS TX Good Count.

2.548.1.36.2 TXEqualization

main	*integer*	Main tuning value.
post	*integer*	Post tuning value.

2.548.1.37 CortinaLinePhyModel

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.
stats	*CortinaXGPCSStatsModel* see 2.548.1.36.1	Additional PHY statistics.

2.548.1.38 CredoChipPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[firmwareRev]	*string*	PHY firmware revision.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.39 CredoLinePhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
lanes	*table(numeric string) = CredoPhySerdes* see 2.548.1.6.2	A mapping of SerDes lane to Sparrow SerDes info.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.

[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.
[topPllVcoCap]	*CredoPhyPllVcoCap* see 2.548.1.6.1	Maximum voltage control oscillator capacitor of phase locked loop over all lanes.

2.548.1.40 CredoPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
lanes	*table(numeric string) = CredoPhySerdes* see 2.548.1.6.2	A mapping of SerDes lane to Sparrow SerDes info.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.
[topPllVcoCap]	*CredoPhyPllVcoCap* see 2.548.1.6.1	Maximum voltage control oscillator capacitor of phase locked loop over all lanes.

2.548.1.41 CredoSystemPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
lanes	*table(numeric string) = CredoPhySerdes* see 2.548.1.6.2	A mapping of SerDes lane to Sparrow SerDes info.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.

[stale]	*boolean*	Status of this phy might be stale.
[topPllVcoCap]	*CredoPhyPllVcoCap* see 2.548.1.6.1	Maximum voltage control oscillator capacitor of phase locked loop over all lanes.

2.548.1.42 CrosspointLineStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
chipId	*integer*	Chip Id.
chipName	*string*	Chip Name.
coreId	*integer*	Core Id.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
egressSerdesMappings	*list of SerdesMapping* see 2.548.1.42.3	Egress SerDes Mappings.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
ingressSerdesMappings	*list of SerdesMapping* see 2.548.1.42.3	Ingress SerDes Mappings.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
polarities	*list of Polarity* see 2.548.1.42.1	Polarity Values.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
rxEqualizations	*list of RXEqualization* see 2.548.1.42.2	Rx Equalization Values.
[stale]	*boolean*	Status of this phy might be stale.
txEqualizations	*list of TXEqualization* see 2.548.1.42.4	Tx Equalization Values.

2.548.1.42.1 Polarity

lane	*integer*	Lane Id.
rxPolarity	*string*	Rx Polarity Value.
rxPolarityLastChange	*floating point number*	Last change timestamp for Rx Polarity.
txPolarity	*string*	Tx Polarity Value.
txPolarityLastChange	*floating point number*	Last change timestamp for Tx Polarity.

2.548.1.42.2 RXEqualization

afe	*integer*	Rx Afe Equlization Value.
lane	*integer*	Lane Id.

2.548.1.42.3 SerdesMapping

destination	*integer*	Destination Lane Id.
[source]	*integer*	Source Lane Id.

2.548.1.42.4 TXEqualization

lane	*integer*	Lane Id.
[main]	*integer*	Main tuning value.
[post]	*integer*	Post tuning value.
[pre]	*integer*	Pre tuning value.

2.548.1.43 CrosspointPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
chipId	*integer*	Chip Id.
chipName	*string*	Chip Name.
coreId	*integer*	Core Id.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
egressSerdesMappings	*list of SerdesMapping* see 2.548.1.42.3	Egress SerDes Mappings.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
ingressSerdesMappings	*list of SerdesMapping* see 2.548.1.42.3	Ingress SerDes Mappings.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
polarities	*list of Polarity* see 2.548.1.42.1	Polarity Values.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
rxEqualizations	*list of RXEqualization* see 2.548.1.42.2	Rx Equalization Values.
[stale]	*boolean*	Status of this phy might be stale.
txEqualizations	*list of TXEqualization* see 2.548.1.42.4	Tx Equalization Values.

2.548.1.44 D5PhyIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.

[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*D5PhySerdesModel* see 2.548.1.27.1	The serdes stats.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.45 DenaliLinePhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
coherentPma	*table(numeric string) = Pma* see 2.548.1.2.26	Coherent PMA information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.46 DenaliSystemPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.47 EnigmaLinePhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.48 EnigmaSystemPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.

[stale]	*boolean*	Status of this phy might be stale.

2.548.1.49 EvoraLinePhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.50 EvoraSystemPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.51 FalconPhyIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.

operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*FalconPhySerdes* see 2.548.1.51.1	The Serdes stats.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.51.1 FalconPhySerdes

serdesStats	*table(numeric string) = FalconPhySerdesLaneModel* see 2.548.1.51.1.1	A mapping of SerDes lane to SerDes statistics.

2.548.1.51.1.1 FalconPhySerdesLaneModel

[dfeTaps]	*table(numeric string) = integer*	Serdes lane Decision Feedback Equalizer (DFE) taps.
eyeLeft	*integer*	Horizontal left eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI.
eyeLower	*integer*	Vertical lower eye margin @ 1e-5 as seen by internal diagnostic slicer in mV.
eyeRight	*integer*	Horizontal right eye margin @ 1e-5 as seen by internal diagnostic slicer in mUI.
eyeUpper	*integer*	Vertical upper eye margin @ 1e-5 as seen by internal diagnostic slicer in mV.
lowFrequncyPeakingFilter	*integer*	Low frequency peaking filter control.
mainPeakingFilter	*integer*	Peaking filter main settings.
[rxPpm]	*integer*	Frequency offset of local reference clock with respect to the frequency of received data in ppm.
[txPpm]	*integer*	Frequency offset of local reference clock with respect to the transmit data in ppm.
[txTaps]	*table(numeric string) = integer*	Serdes lane TX pre-emphasis taps.
[vga]	*integer*	Variable gain amplifier value.

2.548.1.52 InternalGen2PhyIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.53 InternalGen3PhyIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.

operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.54 IntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.

serdes	*CondorPhySerdesModel* see 2.548.1.30.2	SerDes information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.55 PeregrinePhyIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*PeregrinePhySerdesModel* see 2.548.1.30.1	The serdes stats.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.56 SfePhyGen3IntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.

[marvellExtPhy] **	*Marvell88E1514Status* see 2.548.1.56.1	Marvell88E1514 external phy status. **Since: 4.33.2
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.56.1 Marvell88E1514Status

autonegComplete	*MarvellAutonegComplete* see 2.548.1.34.1.2	Auto-negotiation completed.
linkStatus	*MarvellLinkStatus* see 2.548.1.56.1.1	Link status reported by Marvell PHY.
remoteFault	*MarvellRemoteFault* see 2.548.1.34.1.3	Remote fault reported by Marvell PHY.

2.548.1.56.1.1 MarvellLinkStatus

changes	*integer*	The number of times the link status changed.
lastChange	*floating point number*	The last time the link status changed.
value	*enum: down | up*	The status of the link.

2.548.1.57 SfePhyNacIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.

[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*table(numeric string) = IntelNacPhySerdes* see 2.548.1.57.1	A mapping of SerDes lane to SerDes diagnostic information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.57.1 IntelNacPhySerdes

[agc]	*list of integer*	SerDes lane receivier Automatic Gain Coefficients.
[ctleAcGain]	*integer*	SerDes lane Continuous Time Linear Equalizer high frequency gain.
[ctleDcGain]	*integer*	SerDes lane Continuous Time Linear Equalizer low frequency gain.
[dfeEvenTaps]	*list of integer*	Receiver Decision Feedback Equalizer even Coefficients.
[dfeOddTaps]	*list of integer*	Receiver Decision Feedback Equalizer odd Coefficients.
[eyeHeight]	*integer*	Eye height margin in mV.
[rxPpm]	*integer*	Frequency offset of received data with respect to the frequency of local reference clock in parts per million of Hz.
[tdfeEvenTaps]	*list of integer*	Receiver Tail Decision Feedback Equalizer even Coefficients.
[tdfeOddTaps]	*list of integer*	Receiver Tail Decision Feedback Equalizer odd Coefficients.
[tdfeTaps]	*list of integer*	Receiver Tail Decision Feedback Equalizer floating tap positions.
[txTaps]	*IntelNacPhyTxTaps* see 2.548.1.57.1.1	SerDes lane TX pre-emphasis taps.

2.548.1.57.1.1 IntelNacPhyTxTaps

main	*integer*	The main cursor tap.
post1	*integer*	The post cursor tap.
pre1	*integer*	The pre cursor tap.

2.548.1.58 SwitchAsic1p6tPhyIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.59 SwitchAsic400gPhyIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.

[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.60 SwitchAsic800gPhyIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.

[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.61 TalonPhyIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*TalonPhySerdes* see 2.548.1.31.2	The serdes stats.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.62 InternalPhyIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.

[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.63 MakoFpgaPhyIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[interruptCount]	*integer*	PHY interrupt counter.
[laneCount]	*enum: 4 | 2 | 10 | 8 | 1*	PHY lane count to support operational speed.
[modulation]	*enum: PAM-4 | NRZ*	PHY modulation configured on the interface.
operSpeed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
phyState	*PhyState* see 2.548.1.24.2	PHY state information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.

[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdes	*MakoSerdesStatus* see 2.548.1.63.1	The Serdes stats.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.63.1 MakoSerdesStatus

[dfeEnabled]	*table(numeric string) = boolean*	RX Equalizer DFE enabled.
[txTaps]	*table(numeric string) = MakoTxTaps* see 2.548.1.63.1.1	Serdes lane TX pre-emphasis taps.

2.548.1.63.1.1 MakoTxTaps

[laneTxTaps]	*table(numeric string) = integer*	Serdes lane TX pre-emphasis taps.

2.548.1.64 LineStatus

badSsdDetected	*boolean*	Bad SSD error detected.
[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
copperDetect	*boolean*	Copper has been detected.
copperLinkStatus	*boolean*	Copper link is up.
copperSpeed	*enum: 10G | 100M | unknown | 1G*	Copper speeed.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
linkStatus	*boolean*	Device has established a link.
lockErrorDetected	*boolean*	Lock error detected.
mdiCrossOverState	*boolean*	MDI is running in crossover mode.
miiCtrl	*integer*	IEEE MII control register.
[miiLinkStatus]	*MiiLinkStatus* see 2.548.1.34.1.4	MII link status.
[miiRemoteFault]	*MiiRemoteFault* see 2.548.1.34.1.5	MII remote fault.
miiStatus	*integer*	IEEE MII status register.
mlt3ErrorDetected	*boolean*	MLT3 code error detected.
onegBaseTAuxStatus	*integer*	1000BASE-T/100BASE-TX auxiliary statusregister.
onegBaseTPhyExtendedStatus	*integer*	1000BASE-T/100BASE-TX PHY extended status register.
onegBaseTStatus	*integer*	1000BASE-T status register.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.

[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
receiveErrorDetected	*boolean*	Receive error detected.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.
tengBaseTAnStatus	*integer*	10GBASE-T autonegotiation status register.
transmitErrorDetected	*boolean*	Transmit error code received.

2.548.1.65 MillenioLinePhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.66 MillenioSystemPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.67 PhyDs280ChipStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.68 PhyDs280IntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdesStats	*table(numeric string) = Ds280PhySerdes* see 2.548.1.68.1	A mapping of SerDes lane to SerDes diagnostic information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.68.1 Ds280PhySerdes

[dfeTaps]	*list of floating point number*	SerDes lane Decision Feedback Equalizer (DFE) taps.
[horizontalEye]	*floating point number*	Eye margin in UI.
[txTaps]	*Ds280PhyTxTaps* see 2.548.1.68.1.1	SerDes lane TX pre-emphasis taps.
[verticalEye]	*floating point number*	Eye margin in mV.

2.548.1.68.1.1 Ds280PhyTxTaps

main	*integer*	The main cursor tap.

post	*integer*	The post cursor tap.
pre	*integer*	The pre cursor tap.

2.548.1.69 PhyDs280LineIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdesStats	*table(numeric string) = Ds280PhySerdes* see 2.548.1.68.1	A mapping of SerDes lane to SerDes diagnostic information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.70 PhyDs280SystemIntfStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
serdesStats	*table(numeric string) = Ds280PhySerdes* see 2.548.1.68.1	A mapping of SerDes lane to SerDes diagnostic information.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.71 RawPhyStatus

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.

[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.
text	*string*	The text from CLI output.

2.548.1.72 ShortfinLinePhyModel

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
mdiStatus **	*MdiCrossoverModel* see 2.548.1.17.1	MDI/MDI-X status. **Since: 4.30.0
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
speedDownshiftedStatus	*SpeedDownshiftedModel* see 2.548.1.72.1	Speed downshifted status.
[stale]	*boolean*	Status of this phy might be stale.

2.548.1.72.1 SpeedDownshiftedModel

changes	*integer*	Number of speed downshift changes.
lastChange	*floating point number*	Last time speed downshift changed.
state	*boolean*	Speed downshifted for mGig PHYs due to unstable link.

2.548.1.73 ShortfinPhyModel

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
chipStatus	*PhyChipStatus* see 2.548.1.2.22	Shortfin chip status.
description	*PhyDescription* see 2.548.1.2.25	Phy description.

[fec]	*Fec* see 2.548.1.2.1	FEC information.
mdioCommand	*integer*	MDIO Command Handler command selection.
mdioData1	*integer*	MDIO Command Handler parameter 1 for command.
mdioData2	*integer*	MDIO Command Handler parameter 2 for command.
mdioData3	*integer*	MDIO Command Handler parameter 3 for command.
mdioData4	*integer*	MDIO Command Handler parameter 4 for command.
mdioData5	*integer*	MDIO Command Handler parameter 5 for command.
mdioStatus	*integer*	MDIO Command Handler command status.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
speed	*enum: 1.6Tbps | unknown | 400Gbps | 40Gbps | 21Gbps | 2.5Gbps | 11Gbps | 42Gbps | 10Mbps | 1Gbps | 5Gbps | 106Gbps | 200Gbps | 100Gbps | 10Gbps | 800Gbps | 25Gbps | 27Gbps | 100Mbps | 50Gbps | 53Gbps*	Operational speed of the interface.
[stale]	*boolean*	Status of this phy might be stale.
[unsupportedSpeed] **	*boolean*	Connection on Unsupported Speed. **Since: 4.35.2

2.548.1.74 ShortfinSystemPhyModel

[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.

[stale]	*boolean*	Status of this phy might be stale.
[usxgmiiCtrl1]	*integer*	USXGMIIM_USXGMII_CTRL1 - USXGMII Control 1.
[usxgmiiErrStatus]	*integer*	USXGMIIM_ERROR_STATUS - ERROR Status.
[usxgmiiRxAutoneg]	*integer*	USXGMIIM_AN_RX_MESSAGE - Autoneg RX Message.
[usxgmiiStatus0]	*integer*	USXGMIIM_USXGMII_STATUS0 - USXGMII Status0.
[usxgmiiStatus1]	*integer*	USXGMIIM_USXGMII_STATUS1 - USXGMII Status1.
[usxgmiiTxConfig]	*integer*	USXGMIIM_TX_CONFIG_REG - TX Config Register.

2.548.1.75 SystemStatus

[blockLock]	*boolean*	XFI PCS block lock.
[chip]	*PhyChipStatus* see 2.548.1.2.22	Phy chip information.
description	*PhyDescription* see 2.548.1.2.25	Phy description.
[fec]	*Fec* see 2.548.1.2.1	FEC information.
macLinkStatus	*boolean*	MAC link is up.
[pcs]	*Pcs* see 2.548.1.2.8	PCS information.
[pma]	*Pma* see 2.548.1.2.26	PMA information.
[preFecBer]	*PreFecBitError* see 2.548.1.2.31.12	Pre FEC bit error rate of the link.
[rs]	*Rs* see 2.548.1.2.41	Reconciliation sublayer information.
[stale]	*boolean*	Status of this phy might be stale.
[xfiPcsStatus]	*integer*	XFI PCS status register.

2.548.1.76 Transceiver

mediaType	*TransceiverMediaType* see 2.548.1.76.1	Transceiver media type.
[vendorSn]	*string*	Vendor serial number of transceiver.

2.548.1.76.1 TransceiverMediaType

changes	*integer*	Number of changes in transceiver presence.
lastChange	*floating point number*	Last time transceiver presence changed.
value	*string*	Transceiver media type.

2.549 show interfaces (phy diag error-correction histogram) | (phy diag error-correction histogram (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

revision 2

interfaces	*table(Interface name) = IntfFecHistogramPhy* see 2.549.1	Map of interface to FEC histogram.

2.549.1 IntfFecHistogramPhy

phys	*list of FecHistogram* see 2.549.1.1	Fec histogram for all phys in order of topology.

2.549.1.1 FecHistogram

Could also be an instance of:
B52LineFecHistogram 2.549.1.2
B52SystemFecHistogram 2.549.1.3
BabbageLineFecHistogram 2.549.1.4
BabbageSystemFecHistogram 2.549.1.5
MillenioLineFecHistogram 2.549.1.13
MillenioSystemFecHistogram 2.549.1.14
PeregrinePhyFecHistogram 2.549.1.15
FecHistogram 2.549.1.9
Bcm87728LineFecHistogram 2.549.1.6
Bcm87728SystemFecHistogram 2.549.1.7
FecHistogram 2.549.1.8
FecHistogram 2.549.1.12
FecHistogram 2.549.1.10
FecHistogram 2.549.1.11

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.
[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.549.1.2 B52LineFecHistogram

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.

[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.549.1.3 B52SystemFecHistogram

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.
[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.549.1.4 BabbageLineFecHistogram

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.
[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.549.1.5 BabbageSystemFecHistogram

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.
[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.549.1.6 Bcm87728LineFecHistogram

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.
[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.549.1.7 Bcm87728SystemFecHistogram

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.
[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.549.1.8 FecHistogram

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.
[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.549.1.9 FecHistogram

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.
[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.549.1.10 FecHistogram

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.
[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.549.1.11 FecHistogram

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.

[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.549.1.12 FecHistogram

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.
[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.549.1.13 MillenioLineFecHistogram

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.
[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.549.1.14 MillenioSystemFecHistogram

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.
[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.549.1.15 PeregrinePhyFecHistogram

[correctedCodewords]	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
[description]	*PhyDescription* see 2.548.1.2.25	Phy description.
[sampled]	*boolean*	Corrected codewords counts are sampled.
[uncorrectedCodewords]	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.550 show interfaces (phy diag test pattern) | (phy diag test pattern (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

interfaces	*table(Interface name) = IntfTestPatternStatus* see 2.550.1	Mapping between an interface and test pattern config.

2.550.1 IntfTestPatternStatus

capabilities	*string*	Supported test-patterns.
[rx]	*TestPatternMode* see 2.550.1.1	Receive test pattern mode.
[tx]	*TestPatternMode* see 2.550.1.1	Transmit test pattern mode.

2.550.1.1 TestPatternMode

[configured]	*enum: prbs7 | patternNone | prbs49 | prbs9 | prbs58 | prbs23 | prbs13 | prbs63 | prbs15 | prbs11 | prbs31*	Configured test pattern mode.
[operational]	*enum: prbs7 | patternNone | prbs49 | prbs9 | prbs58 | prbs23 | prbs13 | prbs63 | prbs15 | prbs11 | prbs31*	Operational test pattern mode.

2.551 show interfaces (phy diag test pattern counters) | (phy diag test pattern counters (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

interfaces	*table(Interface name) = IntfTestPatternCounters* see 2.551.1	Mapping of interface to test pattern counter data.

2.551.1 IntfTestPatternCounters

lanes	*table(numeric string) = LaneTestPatternCounters* see 2.551.1.1	Mapping of lanes that are a part of the interface to test pattern counter data.

2.551.1.1 LaneTestPatternCounters

Could also be an instance of:
LaneTestPatternDetail 2.551.1.2

bitErrors	*integer*	Total bit errors.
burstCount	*integer*	Number of bursts of bit errors.
largestBurst	*integer*	Largest burst of bit errors.
lastErrorTime	*floating point number*	Last time bit errors were observed.
linkState	*enum: notLocked | notApplicable | locked*	Lock status of received diagnostic test pattern.

2.551.1.2 LaneTestPatternDetail

berSinceLastLock	*floating point number*	Bit error rate since last lock.
bitErrorRate	*floating point number*	Bit error rate since last clear.
bitErrors	*integer*	Total bit errors.
bitErrorsSinceLastLock	*integer*	Total bit errors since last lock.
bitRate	*floating point number*	Bit rate of the lane in Gbps.
burstCount	*integer*	Number of bursts of bit errors.
largestBurst	*integer*	Largest burst of bit errors.
lastErrorTime	*floating point number*	Last time bit errors were observed.
lastLinkStateChange	*floating point number*	Time of last link state change.
linkState	*enum: notLocked | notApplicable | locked*	Lock status of received diagnostic test pattern.
linkStateChanges	*integer*	Number of link state changes since last clear.
lockLostLatchState **	*enum: waitingForLock | notLost | lost | unknown*	Status of the lock latch since RX became operational. Reset when a new RX pattern becomes operational. **Since: 4.23.2
totalBits	*floating point number*	Total bits received since last clear in Gb.
totalBitsSinceLastLock	*floating point number*	Total bits received since last lock in Gb.

2.552 show interfaces (phy diag test pattern counters detail) | (phy diag test pattern counters detail (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

`interfaces`	*table(Interface name) = IntfTestPatternDetail* see 2.552.1	Mapping of interface to detailed test pattern data.

2.552.1 IntfTestPatternDetail

`lanes`	*table(numeric string) = LaneTestPatternDetail* see 2.551.1.2	Mapping of lanes to detailed test pattern status.
`lastClear`	*floating point number*	The last time the test pattern counterswere cleared.
`[operationalTestPattern]`	*enum: prbs7 | patternNone | prbs49 | prbs9 | prbs58 | prbs23 | prbs13 | prbs63 | prbs15 | prbs11 | prbs31*	Operational test pattern.

2.553 show interfaces (phy diag test pattern histogram) | (phy diag test pattern histogram (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

`interfaces`	*table(Interface name) = PrbsHistogramLane* see 2.553.1	Map of interface to test pattern histogram.

2.553.1 PrbsHistogramLane

`lanes`	*table(numeric string) = PrbsHistogram* see 2.553.1.1	Map of phy lane to test pattern histogram.

2.553.1.1 PrbsHistogram

`[correctedCodewords]`	*table(string) = FecHistoBin* see 2.548.1.2.2.7	The number of codewords indexed by the number or range of symbol errors in the codeword.
`[uncorrectedCodewords]`	*FecHistoBin* see 2.548.1.2.2.7	The number of codewords with uncorrected errors.

2.554 show interfaces (phy modulation) | (phy modulation (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switch-card MODSLOT_SWITCHCARD)))) [...]

Could also be an instance of:
InterfacesPhyModulation 2.554.1.1
InterfacesPhyLineRate 2.554

interfaceLineRate	*table(Interface name) = InterfacePhyLineRate* see 2.554.1	Mapping between an interface and phy line rate information.

2.554.1 InterfacePhyLineRate

availableLineRates	*InterfaceAvailableLine-Rates* see 2.554.1.1	Line rate choices available for configuration on this interface.
lineRateConfigured	*enum: 100 | 300 | none | 200 | 400*	Configured line rate. 'none' implies that no configuration has been applied on this interface.
lineRateStatus	*enum: 100 | 300 | none | 200 | 400*	Line rate in operation. 'none' implies that this interface is inactive.
modulationStatus	*enum: qam16 | dpQpsk | none | qam8*	Modulation in operation. 'none' implies that this interface is inactive.

2.554.1.1 InterfaceAvailableLineRates

[lr100g]	*boolean*	100g line rate.
[lr200g]	*boolean*	200g line rate.
[lr300g]	*boolean*	300g line rate.
[lr400g]	*boolean*	400g line rate.
interfaceModulation	*table(Interface name) = InterfacePhyModulation* see 2.554.2	Mapping between an interface and phy modulation information.

2.554.2 InterfacePhyModulation

availableModulations	*InterfaceAvailable-Modulations* see 2.554.2.1	Modulation choices available for configuration on this interface.
modulationConfigured	*enum: qam16 | dpQpsk | none | qam8*	Configured modulation. 'none' implies that no configuration has been applied on this interface.
modulationStatus	*enum: qam16 | dpQpsk | none | qam8*	Modulation in operation. 'none' implies that this interface is inactive.

2.554.2.1 InterfaceAvailableModulations

[dpQpsk]	*boolean*	dual-polarization quadrature phase-shift keying.
[qam16]	*boolean*	16 state quadrature amplitude modulation.

[qam8]	*boolean*	8 state quadrature amplitude modulation.

2.555 show interfaces (phy precoding) | (phy precoding (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

interfaces	*table(Interface name) = InterfacePrecoding* see 2.555.1	Mapping between an interface and phy precoding information.

2.555.1 InterfacePrecoding

lanes	*table(numeric string) = PrecodingLaneDetail* see 2.555.1.1	Detailed precoding information on per-lane basis.
rxConfig	*enum: on | default | off*	Configured precoding on receiver.
txConfig	*enum: on | default | off*	Configured precoding on transmitter.

2.555.1.1 PrecodingLaneDetail

requestStatus	*PrecodingRequestStatus* see 2.555.1.1.1	Precoding request status on per-lane basis.
txRxStatus	*PrecodingTxRxStatus* see 2.555.1.1.2	Precoding status of Tx and Rx on per-lane basis.

2.555.1.1.1 PrecodingRequestStatus

requestedByPeer	*boolean*	Link partner requests precoding.
requestedOfPeer	*boolean*	Local device requests precoding.

2.555.1.1.2 PrecodingTxRxStatus

rxEnabled	*boolean*	Precoding is enabled on receiver.
txEnabled	*boolean*	Precoding is enabled on transmitter.

2.556 show interfaces (phy skew) | (phy skew (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

interfaces	*table(Interface name) = InterfacesPhySkew* see 2.556.1	Active interface skew values.

2.556.1 InterfacesPhySkew

receiver	*SkewValues* see 2.556.1.1	Receiver skew values.
transmitter	*SkewValues* see 2.556.1.1	Transmitter skew values.

2.556.1.1 SkewValues

[calibrationFailureReason]	*enum: linkDown* | *linkFlap* | *uncorrectableCodeBlocks-Increment* | *concurrentOperation* | *modulation*	Reason for failed calibration.
[calibrationStatus]	*enum: failed* | *ok*	Status of skew calibration.
skewH	*floating point number*	Horizontal Polarization Skew (picoseconds).
skewV	*floating point number*	Vertical Polarization Skew (picoseconds).
source	*enum: computing* | *persistent* | *default*	Source of the active skew values.

2.557 show interfaces (phy skew persistent) | (phy skew persistent (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switch-card MODSLOT_SWITCHCARD)))) [...]

interfaces	*table(Interface name) = InterfacesPhySkewPstore* see 2.557.1	Active interface skew values.

2.557.1 InterfacesPhySkewPstore

[receiver]	*PstoreSkewValues* see 2.557.1.1	Receiver skew values.
[transmitter]	*PstoreSkewValues* see 2.557.1.1	Transmitter skew values.
version	*integer*	Skew persistent store version.
xcvrSn	*string*	Transceiver serial number.

2.557.1.1 PstoreSkewValues

skewH	*floating point number*	Horizontal Polarization Skew (picoseconds).
skewV	*floating point number*	Vertical Polarization Skew (picoseconds).
state	*enum: inactive* | *active*	Indicates if the values read from non-volatile memory are actively used or not.

2.558 show interfaces (priority-flow-control) | (priority-flow-control (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

revision 3

interfaceCounters	*table(Interface name)* = *PfcFrameCountersModel* see 2.558.1	A mapping of interface name to priority flow control counters.
interfaceStatuses	*table(Interface name)* = *PfcIntfStatusModel* see 2.558.2	A mapping of interface name to priority flow control status.
status	*PfcStatusModel* see 2.558.3	Status of priority flow control at a global level.
[watchdogStatus]	*PfcWatchdogStatusModel* see 2.558.4	Status of priority flow control watchdog at a global level.

2.558.1 PfcFrameCountersModel

[rxFrames]	*integer*	Number of priority flow control frames received.
[txFrames]	*integer*	Number of priority flow control frames transmitted.

2.558.2 PfcIntfStatusModel

active	*boolean*	Indicates whether priority flow control is operationally active.
enabled	*boolean*	Indicates whether priority flow control is enabled.
[note]	*string*	Informational note on the status of priority flow control.
priorities	*list of integer*	Priorities for which priority flow control is enabled.
[watchdogAction]	*enum: notify-only | errdisable | drop*	Action taken by the priority flow control watchdog.
watchdogActive **	*boolean*	Indicates whether priority flow control watchdog is operationally active. **Since: 4.27.2
watchdogEnabled	*boolean*	Indicates whether priority flow control watchdog is enabled.
[watchdogTimer]	*PfcWatchdogTimerModel* see 2.558.2.1	Timer attributes of the priority flow control watchdog.

2.558.2.1 PfcWatchdogTimerModel

forcedRecovery	*boolean*	Indicates whether forced recovery has been configured for the priority flow control watchdog.
[operPollInterval]	*floating point number*	Polling interval (in seconds) actually operational for the priority flow control watchdog.
pollInterval	*floating point number*	Polling interval (in seconds) configured for the priority flow control watchdog.
recoveryTime	*floating point number*	Wait time (in seconds) after which the priority flow control watchdog marks a transmit queue as recovered.
timeout	*floating point number*	Time (in seconds) for the priority flow control watchdog to expire.

2.558.3 PfcStatusModel

enabled	*boolean*	Indicates whether priority flow control is enabled at a global level.
[priorities]	*list of integer*	Priority values for which priority flow control is supported by the hardware.
rxPfcPrioritiesHonored **	*list of integer*	Priorities for which PFC pause framesare honored. **Since: 4.22.0
supported	*boolean*	Indicates whether priority flow control is supported by the hardware.

2.558.4 PfcWatchdogStatusModel

[action]	*enum: notify-only* | *errdisable* | *drop*	Action taken by the priority flow control watchdog.
[forcedNd] **	*boolean*	Indicates whether port action non-disruptive-only behaviour is on or off. **Since: 4.21.3
[hwMonitoredPri] **	*list of integer*	Priority values configured as Hardware monitored priorities. **Since: 4.23.2
[nDAction] **	*enum: forward* | *invalid*	Action taken on non-disruptive queues by the priority flow control watchdog. **Since: 4.22.0
[nDPriorities]	*PfcWatchdogNDPriorities-Model* see 2.558.4.1	Non-disruptive priorities supported by the priority flow control watchdog.
[overrideAction] **	*boolean*	Indicates whether override action has been enabled to unconditionally drop packets. **Since: 4.21.3
supported	*boolean*	Indicates whether priority flow control watchdog is supported at a global level.
[timer]	*PfcWatchdogTimerModel* see 2.558.2.1	Timer attributes of the priority flow control watchdog.

2.558.4.1 PfcWatchdogNDPrioritiesModel

`[priorities]`	*list of integer*	Priority values configured as non-disruptive for the priority flow control watchdog.
`supported`	*boolean*	Indicates whether non-disruptive priorities are supported by the priority flow control watchdog.

2.559 show interfaces (priority-flow-control buffer counters) | (priority-flow-control buffer counters (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

Could also be an instance of:
PfcIntfRangeBufferBytesCountersModel 2.559.4
PfcIntfRangeBufferOnChipCountersModel 2.559.4
PfcIntfRangePacketDescriptorCountersModel 2.559.4

`interfaces`	*table(Interface name) = PfcIntfBufferCounters-Model* see 2.559.1	A mapping of interface name to priority flow control buffers counters.
`[lastCleared]`	*floating point number*	UTC timestamp when clear command was last issued.
`[lastUpdated]`	*floating point number*	UTC timestamp when counters were last polled.

2.559.1 PfcIntfBufferCountersModel

Could also be an instance of:
PfcIntfBufferBytesCountersModel 2.559.2
PfcIntfBufferOnChipCountersModel 2.559.3
PfcIntfPacketDescriptorCountersModel 2.559.4

`priorities`	*table(numeric string) = PfcBufferCountersModel* see 2.559.1.1	A mapping of priority to priority flow control buffers counters.

2.559.1.1 PfcBufferCountersModel

Could also be an instance of:
PfcBufferBytesCountersModel 2.559.1.2
PfcBufferOnChipCountersModel 2.559.1.3
PfcPacketDescriptorCountersModel 2.559.1.4

`[droppedBytes]`	*integer*	Number of dropped bytes.
`[droppedPackets]`	*integer*	Number of dropped packets.

2.559.1.2 PfcBufferBytesCountersModel

`[droppedBytes]`	*integer*	Number of dropped bytes.
`[droppedPackets]`	*integer*	Number of dropped packets.
`wordsMaxTimestamp`	*floating point number*	UTC timestamp when max watermark was set.
`wordsMaxWatermarkBytes`	*integer*	Max watermark in bytes since clear.
`wordsPolledWatermarkBytes`	*integer*	Max watermark in bytes since poll.

2.559.1.3 PfcBufferOnChipCountersModel

[droppedBytes]	*integer*	Number of dropped bytes.
[droppedPackets]	*integer*	Number of dropped packets.
ocbMaxTimestamp	*floating point number*	UTC timestamp when max watermark was set.
ocbMaxWatermark	*integer*	Max watermark in OCB buffers since clear.
ocbPolledWatermark	*integer*	Max watermark in OCB buffers since poll.

2.559.1.4 PfcPacketDescriptorCountersModel

[droppedBytes]	*integer*	Number of dropped bytes.
[droppedPackets]	*integer*	Number of dropped packets.
pdMaxTimestamp	*floating point number*	UTC timestamp when max watermark was set.
pdMaxWatermark	*integer*	Max watermark in SRAM packet descriptors since clear.
pdPolledWatermark	*integer*	Max watermark in SRAM packet descriptors since poll.

2.559.2 PfcIntfBufferBytesCountersModel

priorities	*table(numeric string) = PfcBufferCountersModel* see 2.559.1.1	A mapping of priority to priority flow control buffers counters.

2.559.3 PfcIntfBufferOnChipCountersModel

priorities	*table(numeric string) = PfcBufferCountersModel* see 2.559.1.1	A mapping of priority to priority flow control buffers counters.

2.559.4 PfcIntfPacketDescriptorCountersModel

priorities	*table(numeric string) = PfcBufferCountersModel* see 2.559.1.1	A mapping of priority to priority flow control buffers counters.
interfaces	*table(Interface name) = PfcIntfBufferCountersModel* see 2.559.1	A mapping of interface name to priority flow control buffers counters.
[lastCleared]	*floating point number*	UTC timestamp when clear command was last issued.
[lastUpdated]	*floating point number*	UTC timestamp when counters were last polled.
interfaces	*table(Interface name) = PfcIntfBufferCountersModel* see 2.559.1	A mapping of interface name to priority flow control buffers counters.
[lastCleared]	*floating point number*	UTC timestamp when clear command was last issued.

[lastUpdated]	*floating point number*	UTC timestamp when counters were last polled.
interfaces	*table(Interface name) = PfcIntfBufferCounters-Model* see 2.559.1	A mapping of interface name to priority flow control buffers counters.
[lastCleared]	*floating point number*	UTC timestamp when clear command was last issued.
[lastUpdated]	*floating point number*	UTC timestamp when counters were last polled.

2.560 show interfaces (priority-flow-control buffer on-chip counters) | (priority-flow-control buffer on-chip counters (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

see 2.559.4

2.561 show interfaces (priority-flow-control counters) | (priority-flow-control counters (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

revision 3

interfaceCounters	*table(Interface name) = PfcFrameCountersModel* see 2.558.1	A mapping of interface name to priority flow control counters.

2.562 show interfaces (priority-flow-control counters detail) | (priority-flow-control counters detail (module (MODSLOT | (Supervisor MOD-SLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

revision 3

interfaces	*table(Interface name) = PfcIntfDetailedCounters-Model* see 2.562.1	A mapping of interface name to priority flow control detailed counters.

2.562.1 PfcIntfDetailedCountersModel

priorities	*table(numeric string) = PfcFrameCountersModel* see 2.558.1	A mapping of priority value to priority flow control counters.

2.563 show interfaces (priority-flow-control counters watchdog) | (priority-flow-control counters watchdog (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

revision 2

interfaces	*table(Interface name) = PfcWatchdogIntfCounters-Model* see 2.563.1	A mapping of interface name to priority flow control watchdog counters.

2.563.1 PfcWatchdogIntfCountersModel

txQueues	*table(numeric string) = PfcWatchdogTxQueue-CountersModel* see 2.563.1.1	A mapping of transmit queue id to priority flow control watchdog counters.

2.563.1.1 PfcWatchdogTxQueueCountersModel

lastRecoveryTimestamp **	*floating point number*	Seconds since start-up to last recorded recovery event for transmit queue. **Since: 4.28.1
lastRecoveryTimestampUtc **	*floating point number*	UTC timestamp of last recorded recovery event for transmit queue. **Since: 4.31.1
lastStuckTimestamp **	*floating point number*	Seconds since start-up to last recorded stuck event for transmit queue. **Since: 4.28.1
lastStuckTimestampUtc **	*floating point number*	UTC timestamp of last recorded stuck event for transmit queue. **Since: 4.31.1
queueType	*enum: multicast | unicast*	Type of the transmit queue.
recoveryCount	*integer*	Number of times the transmit queue recovered.
stuckCount	*integer*	Number of times the transmit queue was stuck.

2.564 show interfaces (priority-flow-control counters watchdog drop) | (priority-flow-control counters watchdog drop (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

revision 3

interfaces	*table(Interface name) = PfcWatchdogIntfEgressDropCountersModel* see 2.564.1	A mapping of interface name to priority flow control watchdog drop counters.

2.564.1 PfcWatchdogIntfEgressDropCountersModel

egressCounters	*table(numeric string) = PfcWatchdogEgressDropCountersModel* see 2.564.1.1	A mapping of transmit queue id to priority flow control watchdog drop counters.
ingressCounters	*table(numeric string) = PfcWatchdogIngressDropCountersModel* see 2.564.1.2	A mapping of traffic class to priority flow control watchdog ingress drop counters.

2.564.1.1 PfcWatchdogEgressDropCountersModel

[outAggregateByteDrops]	*integer*	Bytes dropped at the transmit queue.
[outAggregateDrops]	*integer*	Packets dropped at the transmit queue.
[outCurrentByteDrops]	*integer*	Bytes dropped in current stuck-recovery cycle.
[outCurrentDrops]	*integer*	Packets dropped in current stuck-recovery cycle.
[queueType]	*enum: multicast | unicast*	Type of the transmit queue.

2.564.1.2 PfcWatchdogIngressDropCountersModel

[aggregateByteDrops]	*integer*	Bytes dropped on the ingress side.
[aggregateDrops]	*integer*	Packets dropped on the ingress side.
[currentByteDrops]	*integer*	Bytes dropped in current stuck-recovery cycle.
[currentDrops]	*integer*	Number of packets dropped in current stuck-recovery cycle on the ingress side.

2.565 show interfaces (priority-flow-control packet descriptor counters) | (priority-flow-control packet descriptor counters (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

see 2.559.4

2.566 show interfaces (priority-flow-control status) | (priority-flow-control status (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

revision 2

`interfaceStatuses`	*table(Interface name)* = *PfcIntfStatusModel* see 2.558.2	A mapping of interface name to priority flow control status.
`status`	*PfcStatusModel* see 2.558.3	Status of priority flow control at a global level.
`[watchdogStatus]`	*PfcWatchdogStatusModel* see 2.558.4	Status of priority flow control watchdog at a global level.

2.567 show interfaces (status detail) | (status detail (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

`interfaces`	*table(Interface name)* = *InterfaceStatusDetailEntry* see 2.567.1	Map interfaces to status details.

2.567.1 InterfaceStatusDetailEntry

`[description]`	*string*	Interface description.
`details`	*list of StatusDetail* see 2.567.1.1	List of interface status details.
`status`	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.

2.567.1.1 StatusDetail

[detail]	*string*	Detail for the interface status.
[reason]	*string*	Reason for the interface status.

2.568 show interfaces (status errdisabled) | (status errdisabled (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

interfaceStatuses	*table(Interface name) = InterfaceCauseModel* see 2.568.1	Map interfaces to errdisabled status.

2.568.1 InterfaceCauseModel

[causes]	*list of string*	errdisabled causes for an interface.
[description]	*string*	Interface description.
[status]	*string*	Interface enabled state reason.

2.569 show interfaces (tap | tool) | (tap | tool (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

tapProperties	*table(Interface name) = TapProperty* see 2.569.1	Dictionary of tap port properties keyed by interface name.
toolProperties	*table(Interface name) = ToolProperty* see 2.569.2	Dictionary of tool port properties keyed by interface name.

2.569.1 TapProperty

allowedVlans	*string*	The set of allowed vlans on a tap port in the range 1-4094.
configuredMode	*enum: access | dot1qTunnel | tool | tap | tap-tool | routed | trunk*	The configured switchport mode of an interface.
[details]	*Details* see 2.569.1.1	Detailed tap properties.
innerPortIdentity **	*integer*	The inner port identity of a tap port. **Since: 4.20.5
linkStatus	*enum: non-tap | tool | unknown | tap | no-resource | uninitialized | admin | errdisabled | signal | notconnect | autoIsolated | maint-down | non-tool | disabled | inactive | initializing | notapplicable | adminIsolated | noSignal*	The link status of an interface.
nativeVlan	*integer*	The native vlan associated with a tap port.
portIdentity	*integer*	The port identity of a tap port.
truncationSize	*integer*	The size to which packet is to be truncated, in bytes.
[tunnel] **	*Tunnel* see 2.569.1.2	Tunnel tap actions. **Since: 4.25.2

2.569.1.1 Details

aclsAppliedPerType	*table(string) = AclsAppliedPerType* see 2.569.1.1.1	The list of ACLs applied on a port keyed by ACL type.
defaultGroup	*string*	The default group associated with a tap port.
destMac **	*MAC address*	Destination MAC address. **Since: 4.28.0
[groups]	*list of string*	List of default groups for the tap port.
mplsPop **	*boolean*	Indicates whether MPLS pop is enabled on a tap port. **Since: 4.20.5

srcMac **	*MAC address*	Source MAC address. **Since: 4.28.0
[toolPorts]	*list of Interface name*	List of tool ports for the tap port.
vxlanStrip **	*boolean*	Indicates whether VXLAN strip is enabled on a tap port. **Since: 4.20.5

2.569.1.1.1 AclsAppliedPerType

aclsApplied	*list of string*	List of ACL names applied on a port.

2.569.1.2 Tunnel

brTagStrip	*boolean*	Indicates whether 802.1BR Tag strip is enabled on a tap port.
mplsPop	*boolean*	Indicates whether MPLS pop is enabled on a tap port.
vnTagStrip	*boolean*	Indicates whether VN Tag strip is enabled on a tap port.
vxlanStrip	*boolean*	Indicates whether VXLAN strip is enabled on a tap port.

2.569.2 ToolProperty

allowedVlans	*string*	The set of allowed vlans on a tool port in the range 1-4094.
configuredMode	*enum: access* | *dot1qTunnel* | *tool* | *tap* | *tap-tool* | *routed* | *trunk*	The configured switchport mode of an interface.
[details]	*Details* see 2.569.2.1	Detailed tool properties.
identificationTag	*enum: Off* | *dot1q* | *qinq*	The identity tag requirement for packets recieved on a tool port.
linkStatus	*enum: non-tap* | *tool* | *unknown* | *tap* | *no-resource* | *uninitialized* | *admin* | *errdisabled* | *signal* | *notconnect* | *autoIsolated* | *maint-down* | *non-tool* | *disabled* | *inactive* | *initializing* | *notapplicable* | *adminIsolated* | *noSignal*	The link status of an interface.
timestampMode	*enum: NA* | *header* | *before-fcs* | *replace-fcs* | *None*	The timestamping mode on a packet recieved on a tool port.
[tunnel] **	*Tunnel* see 2.569.2.2	Tunnel tool actions. **Since: 4.25.2

2.569.2.1 Details

[aclsAppliedPerType]	*table(string) = AclsAppliedPerType* see 2.569.1.1.1	The dictionary of ACLs applied on a portkeyed by ACL type.
[groups]	*list of string*	List of groups of the tool port.
[removedVlans]	*string*	The set of 802.1Q tags to remove on a tool port.
truncationSize	*integer*	The size to which packet is to be truncated, in bytes.

2.569.2.2 Tunnel

brTagStrip	*boolean*	Indicates whether 802.1BR Tag strip is enabled on a tool port.
mplsPop	*boolean*	Indicates whether MPLS pop is enabled on a tool port.
vnTagStrip	*boolean*	Indicates whether VN Tag strip is enabled on a tool port.

2.570 show interfaces Fabric priority-flow-control

enabled	*boolean*	Indicates whether priority flow control is enabled.
intfName	*string*	Fabric interface name.
priorities	*list of integer*	Priorities for which priority flow control is enabled.
status	*PfcStatusModel* see 2.558.3	Status of priority flow control at a global level.
[watchdogStatus]	*PfcWatchdogStatusModel* see 2.558.4	Status of priority flow control watchdog at a global level.

2.571 show interfaces [...]

interfaces	*table(Interface name)* = *InterfaceStatus* see 2.571.1	Interface Status.

2.571.1 InterfaceStatus

Could also be an instance of:
InterfaceConfigSanity 2.571.7
EthInterfaceStatus 2.571.3
EthPhyInterfaceStatus 2.571.4
SubInterfaceStatus 2.571.8
VlanInterfaceStatus 2.571.11
LagEthInterfaceStatus 2.571.6
InternalRecircInterfaceStatus 2.571.5
TunnelIntfConfigSanity 2.571.9
TunnelIntfStatus 2.571.10
VxlanInterfaceStatus 2.571.12
ApplicationInterfaceStatus 2.571.2

bandwidth	*integer*	Bandwidth (bit).
[burnedInAddress]	*MAC address*	Burned-in Address.
description	*string*	Configured interface description.
forwardingModel	*enum: recirculation* | *quietDataLink* | *unauthorized* | *routed* | *bridged* | *linkQualification* | *layer1Patch* | *dataLink* | *layer1PatchAndLldp*	LinkQualification – the interface forwards packets for link qualification purposes. Protocols do not run on this interface, Layer1Patch – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. Protocols do not run on this interface, Layer1PatchAndLldp – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. LLDP is the only protocol supported on this interface, Recirculation – the interface recirculates packets. Protocols do not run on this port, QuietDataLink – the interface forwards packets but does not participate in bridging or routing and protocols do not run on this interface, Unauthorized – the interface does not participate in bridging or routing and only EAPOL runs on this interface, DataLink – the interface forwards packets given to it but is not participating in bridging or routing operations, Routed – the interface can route packets, Bridged – the interface can bridge packets but not route them.

hardware	*enum: fabric* | *cpu* | *metamux* | *switch* | *metawatch* | *hati* | *ethernet* | *loopback* | *multiaccess* | *fabricInternal* | *test* | *vxlan* | *application* | *trafficGen* | *backplaneChannel* | *fpga* | *portChannel* | *dps* | *tunnel* | *subinterface* | *internalRecirc* | *vlan*	Hardware Description.
interfaceAddress	*list of InterfaceAddressIp4Base* see 2.571.1.1	IPv4 addresses for this interface.
[interfaceAddressIp6]	*InterfaceAddressIp6Base* see 2.571.1.4	IPv6 addresses for this interface.
interfaceStatus	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
l2Mru **	*integer*	L2 MRU (bytes). **Since: 4.25.0
l3MtuConfigured **	*boolean*	Per-interface MTU is set under interface configuration mode. **Since: 4.23.0
[lastStatusChangeTimestamp]	*floating point number*	Timestamp of last status change.
lineProtocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
[maintenanceEnterTime]	*floating point number*	Time at which interface went under maintenance.
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.
[physicalAddress]	*MAC address*	Physical Layer Address.

2.571.1.1 InterfaceAddressIp4Base

Could also be an instance of:
InterfaceAddress 2.571.1.2
InterfaceAddressBrief 2.571.1.3

[lossOfConnectivityReason] **	*cfm*	IPv4 layer 3 interface connectivity status. **Since: 4.31.2

2.571.1.2 InterfaceAddress

broadcastAddress	*string*	IP used for broadcast (typically '255.255.255.255').
[dhcp] **	*boolean*	Whether the address of this interface is determined via DHCP. **Since: 4.18.0
[lossOfConnectivityReason] **	*cfm*	IPv4 layer 3 interface connectivity status. **Since: 4.31.2
primaryIp	*IpAddress* see 2.571.1.2.1	Primary IP address.
secondaryIps	*table(string) = IpAddress* see 2.571.1.2.1	Secondary IP addresses.
[secondaryIpsOrderedList]	*list of IpAddress* see 2.571.1.2.1	Secondary IP addresses ordered list.
[unnumberedIntf] **	*interface name*	Donor interface. **Since: 4.22.1
virtualIp	*IpAddress* see 2.571.1.2.1	Virtual IP address.
virtualSecondaryIps **	*table(string) = IpAddress* see 2.571.1.2.1	Virtual Secondary IP addresses. **Since: 4.18.0
virtualSecondaryIpsOrdered-List **	*list of IpAddress* see 2.571.1.2.1	Virtual Secondary IP addresses ordered list. **Since: 4.18.0

2.571.1.2.1 IpAddress

address	*IPv4 address*	IPv4 address of this interface.
maskLen	*integer*	IP address mask length (e.g 24 for a /24).
[tag] **	*integer*	Route tag number. **Since: 4.35.2

2.571.1.3 InterfaceAddressBrief

ipAddr	*IpAddress* see 2.571.1.2.1	Interface IP address.
[lossOfConnectivityReason] **	*cfm*	IPv4 layer 3 interface connectivity status. **Since: 4.31.2
[unnumberedIntf]	*interface name*	Donor interface.

2.571.1.4 InterfaceAddressIp6Base

Could also be an instance of:
InterfaceAddressIp6 2.571.1.5

[lossOfConnectivityReason] **	*cfm*	IPv6 layer 3 interface connectivity status. **Since: 4.31.2

2.571.1.5 InterfaceAddressIp6

[addrSource] **	*enum: slaac | manual*	How the address is configured on the interface. **Since: 4.20.0
globalAddressesAreVirtual **	*boolean*	Whether configured addresses are physical or virtual. **Since: 4.24.2
globalUnicastIp6s	*list of IpAddress* see 2.571.1.5.1	Global-unicast IPv6 addresses.
[linkLocalIp6]	*IpAddress* see 2.571.1.5.1	Link-local IPv6 address.
[lossOfConnectivityReason] **	*cfm*	IPv6 layer 3 interface connectivity status. **Since: 4.31.2

2.571.1.5.1 IpAddress

active	*boolean*	Whether or not this IPv6 address is currently active.
address	*IPv6 address*	An IPv6 address (e.g. 'fc00::1234').
dadfailed	*boolean*	Whether or not this IPv6 address is a duplicate.
leastpref **	*boolean*	This address is least-preferred. **Since: 4.28.2
subnet	*string*	The subnet of this address (e.g. 'fc00::/64').
[tag] **	*integer*	Route tag number. **Since: 4.35.2

2.571.2 ApplicationInterfaceStatus

bandwidth	*integer*	Bandwidth (bit).
[burnedInAddress]	*MAC address*	Burned-in Address.
description	*string*	Configured interface description.

forwardingModel	*enum: recirculation* | *quietDataLink* | *unauthorized* | *routed* | *bridged* | *linkQualification* | *layer1Patch* | *dataLink* | *layer1PatchAndLldp*	LinkQualification – the interface forwards packets for link qualification purposes. Protocols do not run on this interface, Layer1Patch – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. Protocols do not run on this interface, Layer1PatchAndLldp – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. LLDP is the only protocol supported on this interface, Recirculation – the interface recirculates packets. Protocols do not run on this port, QuietDataLink – the interface forwards packets but does not participate in bridging or routing and protocols do not run on this interface, Unauthorized – the interface does not participate in bridging or routing and only EAPOL runs on this interface, DataLink – the interface forwards packets given to it but is not participating in bridging or routing operations, Routed – the interface can route packets, Bridged – the interface can bridge packets but not route them.
functionInterfaces	*table(Interface name)* = *FunctionInterfaceSummary* see 2.571.2.1	Functional interfaces running on thisApplication FPGA connector interface.
hardware	*enum: fabric* | *cpu* | *metamux* | *switch* | *metawatch* | *hati* | *ethernet* | *loopback* | *multiaccess* | *fabricInternal* | *test* | *vxlan* | *application* | *trafficGen* | *backplaneChannel* | *fpga* | *portChannel* | *dps* | *tunnel* | *subinterface* | *internalRecirc* | *vlan*	Hardware Description.
interfaceAddress	*list of InterfaceAddressIp4Base* see 2.571.1.1	IPv4 addresses for this interface.
[interfaceAddressIp6]	*InterfaceAddressIp6Base* see 2.571.1.4	IPv6 addresses for this interface.
interfaceStatus	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
l2Mru	*integer*	L2 MRU (bytes).
l3MtuConfigured	*boolean*	Per-interface MTU is set under interface configuration mode.

[lastStatusChangeTimestamp]	*floating point number*	Timestamp of last status change.
lineProtocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
[maintenanceEnterTime]	*floating point number*	Time at which interface went under maintenance.
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.
owner	*string*	Owner application.
[physicalAddress]	*MAC address*	Physical Layer Address.

2.571.2.1 FunctionInterfaceSummary

hasRx **	*boolean*	Whether the function intf uses rx. **Since: 4.29.0
hasTx **	*boolean*	Whether the function intf uses tx. **Since: 4.29.0
interfaceStatus	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
[isSecondaryRx] **	*boolean*	Whether the function intf rx is secondary. **Since: 4.29.0
lineProtocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
name	*interface name*	Name of the interface.

2.571.3 EthInterfaceStatus

bandwidth	*integer*	Bandwidth (bit).
[burnedInAddress]	*MAC address*	Burned-in Address.
description	*string*	Configured interface description.

forwardingModel	*enum: recirculation* | *quietDataLink* | *unauthorized* | *routed* | *bridged* | *linkQualification* | *layer1Patch* | *dataLink* | *layer1PatchAndLldp*	LinkQualification – the interface forwards packets for link qualification purposes. Protocols do not run on this interface, Layer1Patch – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. Protocols do not run on this interface, Layer1PatchAndLldp – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. LLDP is the only protocol supported on this interface, Recirculation – the interface recirculates packets. Protocols do not run on this port, QuietDataLink – the interface forwards packets but does not participate in bridging or routing and protocols do not run on this interface, Unauthorized – the interface does not participate in bridging or routing and only EAPOL runs on this interface, DataLink – the interface forwards packets given to it but is not participating in bridging or routing operations, Routed – the interface can route packets, Bridged – the interface can bridge packets but not route them.
hardware	*enum: fabric* | *cpu* | *metamux* | *switch* | *metawatch* | *hati* | *ethernet* | *loopback* | *multiaccess* | *fabricInternal* | *test* | *vxlan* | *application* | *trafficGen* | *backplaneChannel* | *fpga* | *portChannel* | *dps* | *tunnel* | *subinterface* | *internalRecirc* | *vlan*	Hardware Description.
interfaceAddress	*list of InterfaceAddressIp4Base* see 2.571.1.1	IPv4 addresses for this interface.
[interfaceAddressIp6]	*InterfaceAddressIp6Base* see 2.571.1.4	IPv6 addresses for this interface.
[interfaceConnectivity-Status] **	*string*	Interface connectivity status. **Since: 4.34.0
[interfaceCounters]	*EthInterfaceCounters* see 2.571.3.1	Interface Counters and related information.
[interfaceMembership]	*string*	Shows whether the interface is part of a monitor destination or a Port-channel.
[interfaceStatistics]	*EthInterfaceStatistics* see 2.571.3.2	Interface statistics, such as rates.

interfaceStatus	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
l2Mru **	*integer*	L2 MRU (bytes). **Since: 4.25.0
l3MtuConfigured **	*boolean*	Per-interface MTU is set under interface configuration mode. **Since: 4.23.0
[lastStatusChangeTimestamp]	*floating point number*	Timestamp of last status change.
lineProtocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
[maintenanceEnterTime]	*floating point number*	Time at which interface went under maintenance.
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.
[physicalAddress]	*MAC address*	Physical Layer Address.

2.571.3.1 EthInterfaceCounters

[counterRefreshTime]	*floating point number*	UTC of last counter refresh.
[inBroadcastPkts]	*integer*	Input broadcast packets.
[inDiscards]	*integer*	Input packets with errors.
[inMulticastPkts]	*integer*	Input multicast packets.
[inOctets]	*integer*	Input octets.
[inTotalPkts] **	*integer*	Input packets. **Since: 4.20.0
[inUcastPkts]	*integer*	Input unicast packets.
[inputErrorsDetail]	*PhysicalInputErrors* see 2.571.3.1.1	Details on the types of input errors with physical layer counters.
[lastClear]	*floating point number*	Last clear of interface counters.
[lastUpdateTimestamp] **	*floating point number*	Time of last update. **Since: 4.21.3
linkStatusChanges	*integer*	Number of link status changes since last clear.
[outBroadcastPkts]	*integer*	Output broadcast packets.
[outDiscards]	*integer*	Output packets with errors.
[outMulticastPkts]	*integer*	Output multicast packets.
[outOctets]	*integer*	Output octets.
[outTotalPkts] **	*integer*	Output packets. **Since: 4.28.2
[outUcastPkts]	*integer*	Output unicast packets.
[outputErrorsDetail]	*PhysicalOutputErrors* see 2.571.3.1.2	Details on the types of output errors with physical layer counters.
totalInErrors	*integer*	Total number of input errors.

totalOutErrors	*integer*	Total number of output errors.

2.571.3.1.1 PhysicalInputErrors

alignmentErrors	*integer*	Alignment errors.
fcsErrors	*integer*	FCS errors.
giantFrames	*integer*	Number of giant frames received.
runtFrames	*integer*	Number of runt frames received.
rxPause	*integer*	Flow control pause frames received.
symbolErrors	*integer*	Symbol errors.

2.571.3.1.2 PhysicalOutputErrors

collisions	*integer*	Sum of single and multiple collisions.
deferredTransmissions	*integer*	Deferred transmissions.
lateCollisions	*integer*	Late collision frames.
txPause	*integer*	Flow control pause frames sent.

2.571.3.2 EthInterfaceStatistics

inBitsRate	*floating point number*	input bits rate.
inPktsRate	*floating point number*	input packets rate.
outBitsRate	*floating point number*	output bits rate.
outPktsRate	*floating point number*	output packets rate.
updateInterval	*floating point number*	Stats update interval in seconds.

2.571.4 EthPhyInterfaceStatus

autoNegotiate	*enum: negotiating* | *success* | *unknown* | *failed* | *off*	Current auto-negotiation state.
bandwidth	*integer*	Bandwidth (bit).
[burnedInAddress]	*MAC address*	Burned-in Address.
description	*string*	Configured interface description.
duplex	*enum: duplexFull* | *duplexHalf* | *duplexUnknown*	Duplex status of the interface.

forwardingModel	*enum: recirculation* | *quietDataLink* | *unauthorized* | *routed* | *bridged* | *linkQualification* | *layer1Patch* | *dataLink* | *layer1PatchAndLldp*	LinkQualification – the interface forwards packets for link qualification purposes. Protocols do not run on this interface, Layer1Patch – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. Protocols do not run on this interface, Layer1PatchAndLldp – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. LLDP is the only protocol supported on this interface, Recirculation – the interface recirculates packets. Protocols do not run on this port, QuietDataLink – the interface forwards packets but does not participate in bridging or routing and protocols do not run on this interface, Unauthorized – the interface does not participate in bridging or routing and only EAPOL runs on this interface, DataLink – the interface forwards packets given to it but is not participating in bridging or routing operations, Routed – the interface can route packets, Bridged – the interface can bridge packets but not route them.
hardware	*enum: fabric* | *cpu* | *metamux* | *switch* | *metawatch* | *hati* | *ethernet* | *loopback* | *multiaccess* | *fabricInternal* | *test* | *vxlan* | *application* | *trafficGen* | *backplaneChannel* | *fpga* | *portChannel* | *dps* | *tunnel* | *subinterface* | *internalRecirc* | *vlan*	Hardware Description.
interfaceAddress	*list of InterfaceAddressIp4Base* see 2.571.1.1	IPv4 addresses for this interface.
[interfaceAddressIp6]	*InterfaceAddressIp6Base* see 2.571.1.4	IPv6 addresses for this interface.
[interfaceConnectivity-Status] **	*string*	Interface connectivity status. **Since: 4.34.0
[interfaceCounters]	*EthInterfaceCounters* see 2.571.3.1	Interface Counters and related information.
[interfaceMembership]	*string*	Shows whether the interface is part of a monitor destination or a Port-channel.
[interfaceStatistics]	*EthInterfaceStatistics* see 2.571.3.2	Interface statistics, such as rates.

interfaceStatus	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
l2Mru **	*integer*	L2 MRU (bytes). **Since: 4.25.0
l3MtuConfigured **	*boolean*	Per-interface MTU is set under interface configuration mode. **Since: 4.23.0
[lanes] **	*integer*	Number of lanes on the interface. **Since: 4.21.0
[lastStatusChangeTimestamp]	*floating point number*	Timestamp of last status change.
lineProtocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
[loopbackMode]	*enum: loopbackMac* | *loopbackPhyRemote* | *loopbackNone* | *loopbackPhy*	Loopback mode of the interface.
[maintenanceEnterTime]	*floating point number*	Time at which interface went under maintenance.
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.
[physicalAddress]	*MAC address*	Physical Layer Address.

2.571.5 InternalRecircInterfaceStatus

bandwidth	*integer*	Bandwidth (bit).
[burnedInAddress]	*MAC address*	Burned-in Address.
description	*string*	Configured interface description.

forwardingModel	*enum: recirculation* | *quietDataLink* | *unauthorized* | *routed* | *bridged* | *linkQualification* | *layer1Patch* | *dataLink* | *layer1PatchAndLldp*	LinkQualification – the interface forwards packets for link qualification purposes. Protocols do not run on this interface, Layer1Patch – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. Protocols do not run on this interface, Layer1PatchAndLldp – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. LLDP is the only protocol supported on this interface, Recirculation – the interface recirculates packets. Protocols do not run on this port, QuietDataLink – the interface forwards packets but does not participate in bridging or routing and protocols do not run on this interface, Unauthorized – the interface does not participate in bridging or routing and only EAPOL runs on this interface, DataLink – the interface forwards packets given to it but is not participating in bridging or routing operations, Routed – the interface can route packets, Bridged – the interface can bridge packets but not route them.
hardware	*enum: fabric* | *cpu* | *metamux* | *switch* | *metawatch* | *hati* | *ethernet* | *loopback* | *multiaccess* | *fabricInternal* | *test* | *vxlan* | *application* | *trafficGen* | *backplaneChannel* | *fpga* | *portChannel* | *dps* | *tunnel* | *subinterface* | *internalRecirc* | *vlan*	Hardware Description.
interfaceAddress	*list of InterfaceAddressIp4Base* see 2.571.1.1	IPv4 addresses for this interface.
[interfaceAddressIp6]	*InterfaceAddressIp6Base* see 2.571.1.4	IPv6 addresses for this interface.
[interfaceConnectivity-Status] **	*string*	Interface connectivity status. **Since: 4.34.0
[interfaceCounters]	*EthInterfaceCounters* see 2.571.3.1	Interface Counters and related information.
[interfaceMembership]	*string*	Shows whether the interface is part of a monitor destination or a Port-channel.
[interfaceStatistics]	*EthInterfaceStatistics* see 2.571.3.2	Interface statistics, such as rates.

interfaceStatus	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
l2Mru	*integer*	L2 MRU (bytes).
l3MtuConfigured	*boolean*	Per-interface MTU is set under interface configuration mode.
[lastStatusChangeTimestamp]	*floating point number*	Timestamp of last status change.
lineProtocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
[maintenanceEnterTime]	*floating point number*	Time at which interface went under maintenance.
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.
[physicalAddress]	*MAC address*	Physical Layer Address.

2.571.6 LagEthInterfaceStatus

bandwidth	*integer*	Bandwidth (bit).
[burnedInAddress]	*MAC address*	Burned-in Address.
description	*string*	Configured interface description.
fallbackEnabled	*boolean*	LAG fallback configured.
[fallbackEnabledType]	*enum: fallbackStatic* | *fallbackNone* | *fallbackIndividual*	The type of LAG fallback configured.
[fallbackMode]	*enum: monitoring* | *enabledLocally* | *configured* | *unconfigured* | *passive* | *enabled* | *na* | *initialized*	The status of LAG fallback.
[fallbackTimeout]	*floating point number*	The timeout for fallback to occur.

forwardingModel	*enum: recirculation* | *quietDataLink* | *unauthorized* | *routed* | *bridged* | *linkQualification* | *layer1Patch* | *dataLink* | *layer1PatchAndLldp*	LinkQualification – the interface forwards packets for link qualification purposes. Protocols do not run on this interface, Layer1Patch – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. Protocols do not run on this interface, Layer1PatchAndLldp – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. LLDP is the only protocol supported on this interface, Recirculation – the interface recirculates packets. Protocols do not run on this port, QuietDataLink – the interface forwards packets but does not participate in bridging or routing and protocols do not run on this interface, Unauthorized – the interface does not participate in bridging or routing and only EAPOL runs on this interface, DataLink – the interface forwards packets given to it but is not participating in bridging or routing operations, Routed – the interface can route packets, Bridged – the interface can bridge packets but not route them.
hardware	*enum: fabric* | *cpu* | *metamux* | *switch* | *metawatch* | *hati* | *ethernet* | *loopback* | *multiaccess* | *fabricInternal* | *test* | *vxlan* | *application* | *trafficGen* | *backplaneChannel* | *fpga* | *portChannel* | *dps* | *tunnel* | *subinterface* | *internalRecirc* | *vlan*	Hardware Description.
interfaceAddress	*list of InterfaceAddressIp4Base* see 2.571.1.1	IPv4 addresses for this interface.
[interfaceAddressIp6]	*InterfaceAddressIp6Base* see 2.571.1.4	IPv6 addresses for this interface.
[interfaceConnectivity-Status] **	*string*	Interface connectivity status. **Since: 4.34.0
[interfaceCounters]	*EthInterfaceCounters* see 2.571.3.1	Interface Counters and related information.
[interfaceMembership]	*string*	Shows whether the interface is part of a monitor destination or a Port-channel.
[interfaceStatistics]	*EthInterfaceStatistics* see 2.571.3.2	Interface statistics, such as rates.

interfaceStatus	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
l2Mru **	*integer*	L2 MRU (bytes). **Since: 4.25.0
l3MtuConfigured **	*boolean*	Per-interface MTU is set under interface configuration mode. **Since: 4.23.0
[lastStatusChangeTimestamp]	*floating point number*	Timestamp of last status change.
lineProtocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
[maintenanceEnterTime]	*floating point number*	Time at which interface went under maintenance.
memberInterfaces	*table(string) = LagMemberInformation* see 2.571.6.1	The interfaces that are in this LAG. None if no information is available on the interface.
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.
[physicalAddress]	*MAC address*	Physical Layer Address.

2.571.6.1 LagMemberInformation

bandwidth	*integer*	Bandwidth (bit).
duplex	*enum: duplexFull* | *duplexHalf* | *duplexUnknown*	Duplex status of the interface.

2.571.7 InterfaceConfigSanity

bandwidth	*integer*	Bandwidth (bit).
[burnedInAddress]	*MAC address*	Burned-in Address.
description	*string*	Configured interface description.

forwardingModel	*enum: recirculation* | *quietDataLink* | *unauthorized* | *routed* | *bridged* | *linkQualification* | *layer1Patch* | *dataLink* | *layer1PatchAndLldp*	LinkQualification – the interface forwards packets for link qualification purposes. Protocols do not run on this interface, Layer1Patch – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. Protocols do not run on this interface, Layer1PatchAndLldp – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. LLDP is the only protocol supported on this interface, Recirculation – the interface recirculates packets. Protocols do not run on this port, QuietDataLink – the interface forwards packets but does not participate in bridging or routing and protocols do not run on this interface, Unauthorized – the interface does not participate in bridging or routing and only EAPOL runs on this interface, DataLink – the interface forwards packets given to it but is not participating in bridging or routing operations, Routed – the interface can route packets, Bridged – the interface can bridge packets but not route them.
hardware	*enum: fabric* | *cpu* | *metamux* | *switch* | *metawatch* | *hati* | *ethernet* | *loopback* | *multiaccess* | *fabricInternal* | *test* | *vxlan* | *application* | *trafficGen* | *backplaneChannel* | *fpga* | *portChannel* | *dps* | *tunnel* | *subinterface* | *internalRecirc* | *vlan*	Hardware Description.
interfaceAddress	*list of InterfaceAddressIp4Base* see 2.571.1.1	IPv4 addresses for this interface.
[interfaceAddressIp6]	*InterfaceAddressIp6Base* see 2.571.1.4	IPv6 addresses for this interface.
interfaceStatus	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
l2Mru **	*integer*	L2 MRU (bytes). **Since: 4.25.0
l3MtuConfigured	*boolean*	Per-interface MTU is set under interface configuration mode.
[lastStatusChangeTimestamp]	*floating point number*	Timestamp of last status change.

lineProtocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
[maintenanceEnterTime]	*floating point number*	Time at which interface went under maintenance.
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.
[physicalAddress]	*MAC address*	Physical Layer Address.

2.571.8 SubInterfaceStatus

bandwidth	*integer*	Bandwidth (bit).
[burnedInAddress]	*MAC address*	Burned-in Address.
description	*string*	Configured interface description.
forwardingModel	*enum: recirculation* | *quietDataLink* | *unauthorized* | *routed* | *bridged* | *linkQualification* | *layer1Patch* | *dataLink* | *layer1PatchAndLldp*	LinkQualification – the interface forwards packets for link qualification purposes. Protocols do not run on this interface, Layer1Patch – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. Protocols do not run on this interface, Layer1PatchAndLldp – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. LLDP is the only protocol supported on this interface, Recirculation – the interface recirculates packets. Protocols do not run on this port, QuietDataLink – the interface forwards packets but does not participate in bridging or routing and protocols do not run on this interface, Unauthorized – the interface does not participate in bridging or routing and only EAPOL runs on this interface, DataLink – the interface forwards packets given to it but is not participating in bridging or routing operations, Routed – the interface can route packets, Bridged – the interface can bridge packets but not route them.
hardware	*enum: fabric* | *cpu* | *metamux* | *switch* | *metawatch* | *hati* | *ethernet* | *loopback* | *multiaccess* | *fabricInternal* | *test* | *vxlan* | *application* | *trafficGen* | *backplaneChannel* | *fpga* | *portChannel* | *dps* | *tunnel* | *subinterface* | *internalRecirc* | *vlan*	Hardware Description.
interfaceAddress	*list of InterfaceAddressIp4Base* see 2.571.1.1	IPv4 addresses for this interface.

[interfaceAddressIp6]	*InterfaceAddressIp6Base* see 2.571.1.4	IPv6 addresses for this interface.
[interfaceCounters]	*InterfaceCounters* see 2.571.8.1	Interface Counters and related information.
interfaceStatus	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
l2Mru	*integer*	L2 MRU (bytes).
l3MtuConfigured	*boolean*	Per-interface MTU is set under interface configuration mode.
[lastStatusChangeTimestamp]	*floating point number*	Timestamp of last status change.
lineProtocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
[maintenanceEnterTime]	*floating point number*	Time at which interface went under maintenance.
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.
[physicalAddress]	*MAC address*	Physical Layer Address.

2.571.8.1 InterfaceCounters

Could also be an instance of:
EthInterfaceCounters 2.571.3.1

[inBroadcastPkts]	*integer*	Input broadcast packets.
[inDiscards]	*integer*	Input packets with errors.
[inMulticastPkts]	*integer*	Input multicast packets.
[inOctets]	*integer*	Input octets.
[inTotalPkts] **	*integer*	Input packets. **Since: 4.20.0
[inUcastPkts]	*integer*	Input unicast packets.
[lastClear] **	*floating point number*	Last clear of interface counters. **Since: 4.34.0
[lastUpdateTimestamp] **	*floating point number*	Time of last update. **Since: 4.21.3
[outBroadcastPkts]	*integer*	Output broadcast packets.
[outDiscards]	*integer*	Output packets with errors.
[outMulticastPkts]	*integer*	Output multicast packets.
[outOctets]	*integer*	Output octets.
[outTotalPkts] **	*integer*	Output packets. **Since: 4.28.2
[outUcastPkts]	*integer*	Output unicast packets.

2.571.9 TunnelIntfConfigSanity

bandwidth	*integer*	Bandwidth (bit).
[burnedInAddress]	*MAC address*	Burned-in Address.
description	*string*	Configured interface description.
dfBitSet **	*boolean*	Tunnel dont fragment set. **Since: 4.33.2
dfBitValue **	*boolean*	Tunnel dont fragment value. **Since: 4.33.2
forwardingModel	*enum: recirculation* | *quietDataLink* | *unauthorized* | *routed* | *bridged* | *linkQualification* | *layer1Patch* | *dataLink* | *layer1PatchAndLldp*	LinkQualification – the interface forwards packets for link qualification purposes. Protocols do not run on this interface, Layer1Patch – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. Protocols do not run on this interface, Layer1PatchAndLldp – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. LLDP is the only protocol supported on this interface, Recirculation – the interface recirculates packets. Protocols do not run on this port, QuietDataLink – the interface forwards packets but does not participate in bridging or routing and protocols do not run on this interface, Unauthorized – the interface does not participate in bridging or routing and only EAPOL runs on this interface, DataLink – the interface forwards packets given to it but is not participating in bridging or routing operations, Routed – the interface can route packets, Bridged – the interface can bridge packets but not route them.
hardware	*enum: fabric* | *cpu* | *metamux* | *switch* | *metawatch* | *hati* | *ethernet* | *loopback* | *multiaccess* | *fabricInternal* | *test* | *vxlan* | *application* | *trafficGen* | *backplaneChannel* | *fpga* | *portChannel* | *dps* | *tunnel* | *subinterface* | *internalRecirc* | *vlan*	Hardware Description.
interfaceAddress	*list of InterfaceAddressIp4Base* see 2.571.1.1	IPv4 addresses for this interface.
[interfaceAddressIp6]	*InterfaceAddressIp6Base* see 2.571.1.4	IPv6 addresses for this interface.

interfaceStatus	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
l2Mru **	*integer*	L2 MRU (bytes). **Since: 4.25.0
l3MtuConfigured	*boolean*	Per-interface MTU is set under interface configuration mode.
[lastStatusChangeTimestamp]	*floating point number*	Timestamp of last status change.
lineProtocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
[maintenanceEnterTime]	*floating point number*	Time at which interface went under maintenance.
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.
[physicalAddress]	*MAC address*	Physical Layer Address.
tunDecapDipOnlyMatch **	*boolean*	Terminate tunnel from any source. **Since: 4.30.0
tunDiagnosticsInfo	*list of string*	Diagnostic messages.
tunDstAddr	*IP address*	Address for destination.
[tunDstHost] **	*string*	Tunnel destination hostname. **Since: 4.29.1
[tunDuplicateTunnels] **	*list of string*	Tunnel duplicates. **Since: 4.33.1
tunHwFwd	*boolean*	Hardware forwarding.
tunIKey	*integer*	Output key.
tunMode	*enum: tunnelIntfModeIpsec* | *tunnelIntfModeUnspecified* | *tunnelIntfModeIpip* | *tunnelIntfModeGre*	Tunnel mode.
tunMtu	*integer*	Tunnel transport MTU.
tunOKey	*integer*	Input key.
tunPathMtuDiscovery	*boolean*	Tunnel path MTU discovery.
tunSrcAddr	*IP address*	Address for source.
tunTos	*integer*	Tunnel TOS.
tunTtl	*integer*	Tunnel TTL.
tunUnderlayVrf	*string*	Tunnel underlay VRF.

2.571.10 TunnelIntfStatus

bandwidth	*integer*	Bandwidth (bit).
[burnedInAddress]	*MAC address*	Burned-in Address.
description	*string*	Configured interface description.

`dfBitSet` **	*boolean*	Tunnel dont fragment set. **Since: 4.33.2
`dfBitValue` **	*boolean*	Tunnel dont fragment value. **Since: 4.33.2
`forwardingModel`	*enum: recirculation* | *quietDataLink* | *unauthorized* | *routed* | *bridged* | *linkQualification* | *layer1Patch* | *dataLink* | *layer1PatchAndLldp*	LinkQualification – the interface forwards packets for link qualification purposes. Protocols do not run on this interface, Layer1Patch – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. Protocols do not run on this interface, Layer1PatchAndLldp – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. LLDP is the only protocol supported on this interface, Recirculation – the interface recirculates packets. Protocols do not run on this port, QuietDataLink – the interface forwards packets but does not participate in bridging or routing and protocols do not run on this interface, Unauthorized – the interface does not participate in bridging or routing and only EAPOL runs on this interface, DataLink – the interface forwards packets given to it but is not participating in bridging or routing operations, Routed – the interface can route packets, Bridged – the interface can bridge packets but not route them.
`hardware`	*enum: fabric* | *cpu* | *metamux* | *switch* | *metawatch* | *hati* | *ethernet* | *loopback* | *multiaccess* | *fabricInternal* | *test* | *vxlan* | *application* | *trafficGen* | *backplaneChannel* | *fpga* | *portChannel* | *dps* | *tunnel* | *subinterface* | *internalRecirc* | *vlan*	Hardware Description.
`interfaceAddress`	*list of InterfaceAddressIp4Base* see 2.571.1.1	IPv4 addresses for this interface.
`[interfaceAddressIp6]`	*InterfaceAddressIp6Base* see 2.571.1.4	IPv6 addresses for this interface.
`interfaceStatus`	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
`l2Mru` **	*integer*	L2 MRU (bytes). **Since: 4.25.0

l3MtuConfigured **	*boolean*	Per-interface MTU is set under interface configuration mode. **Since: 4.23.0
[lastStatusChangeTimestamp]	*floating point number*	Timestamp of last status change.
lineProtocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
[maintenanceEnterTime]	*floating point number*	Time at which interface went under maintenance.
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.
[physicalAddress]	*MAC address*	Physical Layer Address.
tunDecapDipOnlyMatch **	*boolean*	Terminate tunnel from any source. **Since: 4.30.0
tunDiagnosticsInfo **	*list of string*	Diagnostic messages. **Since: 4.21.3
tunDstAddr	*IP address*	Address for destination.
[tunDstHost] **	*string*	Tunnel destination hostname. **Since: 4.29.1
[tunDuplicateTunnels] **	*list of string*	Tunnel duplicates. **Since: 4.33.1
tunHwFwd **	*boolean*	Hardware forwarding. **Since: 4.21.0
tunIKey **	*integer*	Output key. **Since: 4.20.0
tunMode	*enum: tunnelIntfModeIpsec* | *tunnelIntfModeUnspecified* | *tunnelIntfModeIpip* | *tunnelIntfModeGre*	Tunnel mode.
tunMtu	*integer*	Tunnel transport MTU.
tunOKey **	*integer*	Input key. **Since: 4.20.0
tunPathMtuDiscovery	*boolean*	Tunnel path MTU discovery.
tunSrcAddr	*IP address*	Address for source.
tunTos	*integer*	Tunnel TOS.
tunTtl	*integer*	Tunnel TTL.
tunUnderlayVrf **	*string*	Tunnel underlay VRF. **Since: 4.22.1

2.571.11 VlanInterfaceStatus

bandwidth	*integer*	Bandwidth (bit).
[burnedInAddress]	*MAC address*	Burned-in Address.
description	*string*	Configured interface description.

forwardingModel	*enum: recirculation* | *quietDataLink* | *unauthorized* | *routed* | *bridged* | *linkQualification* | *layer1Patch* | *dataLink* | *layer1PatchAndLldp*	LinkQualification – the interface forwards packets for link qualification purposes. Protocols do not run on this interface, Layer1Patch – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. Protocols do not run on this interface, Layer1PatchAndLldp – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. LLDP is the only protocol supported on this interface, Recirculation – the interface recirculates packets. Protocols do not run on this port, QuietDataLink – the interface forwards packets but does not participate in bridging or routing and protocols do not run on this interface, Unauthorized – the interface does not participate in bridging or routing and only EAPOL runs on this interface, DataLink – the interface forwards packets given to it but is not participating in bridging or routing operations, Routed – the interface can route packets, Bridged – the interface can bridge packets but not route them.
hardware	*enum: fabric* | *cpu* | *metamux* | *switch* | *metawatch* | *hati* | *ethernet* | *loopback* | *multiaccess* | *fabricInternal* | *test* | *vxlan* | *application* | *trafficGen* | *backplaneChannel* | *fpga* | *portChannel* | *dps* | *tunnel* | *subinterface* | *internalRecirc* | *vlan*	Hardware Description.
interfaceAddress	*list of InterfaceAddressIp4Base* see 2.571.1.1	IPv4 addresses for this interface.
[interfaceAddressIp6]	*InterfaceAddressIp6Base* see 2.571.1.4	IPv6 addresses for this interface.
[interfaceCounters]	*VlanInterfaceCounters* see 2.571.11.1	Interface Counters and related information.
[interfaceStatistics]	*VlanInterfaceStatistics* see 2.571.11.2	Interface statistics, such as rates.
interfaceStatus	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
l2Mru **	*integer*	L2 MRU (bytes). **Since: 4.25.0

l3MtuConfigured **	*boolean*	Per-interface MTU is set under interface configuration mode. **Since: 4.23.0
[lastStatusChangeTimestamp]	*floating point number*	Timestamp of last status change.
lineProtocolStatus	*enum: lowerLayerDown | unknown | down | up | testing | notPresent | notApplicable | dormant*	Line protocol status.
[maintenanceEnterTime]	*floating point number*	Time at which interface went under maintenance.
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.
[physicalAddress]	*MAC address*	Physical Layer Address.

2.571.11.1 VlanInterfaceCounters

[counterRefreshTime]	*floating point number*	UTC of last counter refresh.
[inMulticastOctets]	*integer*	Input multicast octets.
[inMulticastPkts] **	*integer*	Input multicast packets. **Since: 4.20.5
[inOctets]	*integer*	Input octets.
[inPkts] **	*integer*	Input packets. **Since: 4.20.5
[inUcastOctets]	*integer*	Input unicast octets.
[inUcastPkts]	*integer*	Input unicast packets.
[lastClear]	*floating point number*	Last clear of interface counters.
[linkStatusChanges]	*integer*	Number of link status changes since last clear.
[outMulticastOctets]	*integer*	Output multicast octets.
[outMulticastPkts] **	*integer*	Output multicast packets. **Since: 4.20.5
[outOctets]	*integer*	Output octets.
[outPkts] **	*integer*	Output packets. **Since: 4.20.5
[outUcastOctets]	*integer*	Output unicast octets.
[outUcastPkts]	*integer*	Output unicast packets.

2.571.11.2 VlanInterfaceStatistics

inBitsRate	*floating point number*	input bits rate.
outBitsRate	*floating point number*	output bits rate.
updateInterval	*floating point number*	Stats update interval in seconds.

2.571.12 VxlanInterfaceStatus

arpLocalAddress **	*boolean*	Enable rewrite of virtual IP with local IP in VXLAN ARP requests. **Since: 4.20.0
arpReplyRelayMode **	*boolean*	ARP Reply Relay Mode. **Since: 4.18.0

bandwidth	*integer*	Bandwidth (bit).
[bfdPrefixList] **	*string*	Prefix list for filtering BFD sessions. **Since: 4.26.0
[burnedInAddress]	*MAC address*	Burned-in Address.
controllerClientMode	*boolean*	Controller Client Mode.
controllerControlPlane **	*boolean*	Controller Control Plane. **Since: 4.18.1
dataPathLearningMode	*boolean*	Datapath Learning Mode.
decapFilterIntf **	*list of Interface name*	VXLAN decapsulation filter excluded interfaces. **Since: 4.25.0
decapFilterMode **	*enum: filterEnabledIntf* | *filterRelaxedIntf* | *filterEnabled* | *filterDisabled* | *filterRelaxedAll*	VXLAN decapsulation filter mode. **Since: 4.25.0
decapRouteAll **	*boolean*	Routing all VXLAN decasulated packets is enabled. **Since: 4.29.0
[decapVniToVrfMap] **	*table(numeric string) = string*	Decapsulation VNI to VRF mapping. **Since: 4.25.0
description	*string*	Configured interface description.
[detectMult] **	*integer*	Number of consecutive BFD packets missed before failure. **Since: 4.25.2
[floodLearnedAll] **	*boolean*	Flood VTEPs learned via datapath learning. **Since: 4.25.1
forwardingModel	*enum: recirculation* | *quietDataLink* | *unauthorized* | *routed* | *bridged* | *linkQualification* | *layer1Patch* | *dataLink* | *layer1PatchAndLldp*	LinkQualification – the interface forwards packets for link qualification purposes. Protocols do not run on this interface, Layer1Patch – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. Protocols do not run on this interface, Layer1PatchAndLldp – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. LLDP is the only protocol supported on this interface, Recirculation – the interface recirculates packets. Protocols do not run on this port, QuietDataLink – the interface forwards packets but does not participate in bridging or routing and protocols do not run on this interface, Unauthorized – the interface does not participate in bridging or routing and only EAPOL runs on this interface, DataLink – the interface forwards packets given to it but is not participating in bridging or routing operations, Routed – the interface can route packets, Bridged – the interface can bridge packets but not route them.

hardware	*enum: fabric* | *cpu* | *metamux* | *switch* | *metawatch* | *hati* | *ethernet* | *loopback* | *multiaccess* | *fabricInternal* | *test* | *vxlan* | *application* | *trafficGen* | *backplaneChannel* | *fpga* | *portChannel* | *dps* | *tunnel* | *subinterface* | *internalRecirc* | *vlan*	Hardware Description.
interfaceAddress	*list of InterfaceAddressIp4Base* see 2.571.1.1	IPv4 addresses for this interface.
[interfaceAddressIp6]	*InterfaceAddressIp6Base* see 2.571.1.4	IPv6 addresses for this interface.
interfaceStatus	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
l2Mru **	*integer*	L2 MRU (bytes). **Since: 4.25.0
l3MtuConfigured **	*boolean*	Per-interface MTU is set under interface configuration mode. **Since: 4.23.0
[lastStatusChangeTimestamp]	*floating point number*	Timestamp of last status change.
lineProtocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
[maintenanceEnterTime]	*floating point number*	Time at which interface went under maintenance.
[mcastGrpDecap]	*string*	IP multicast group list for decap.
mcastRouting **	*boolean*	Multicast routing is enabled. **Since: 4.22.1
mlagSharedRouterMacAddr **	*MAC address*	MAC address of the VXLAN Shared Router Mac. **Since: 4.21.3
[mlagSrcIpAddr] **	*IPv4 address*	IP address of the MLAG source interface. **Since: 4.21.3
[mlagSrcIpAddrV6] **	*IPv6 address*	IPv6 address of the MLAG source interface. **Since: 4.24.0
[mlagSrcIpIntf] **	*interface name*	Source interface for MLAG VTEP IP. **Since: 4.21.3
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.
[physicalAddress]	*MAC address*	Physical Layer Address.
portDot1qVniMapping **	*boolean*	VNI mapping to port, dot1q tag pairs. **Since: 4.20.5

[remoteVxlanDomain] **	*boolean*	VXLAN domain is remote. **Since: 4.27.0
[replicationMode]	*string*	Replication/Flood Mode.
[rxInterval] **	*integer*	Rate in microseconds at which BFD control packets are received. **Since: 4.25.2
secUdpPort **	*integer*	VXLANsec UDP port. **Since: 4.29.0
[srcIpAddr]	*string*	IP address of the source interface.
[srcIpAddrV6] **	*IPv6 address*	IPv6 address of the source interface. **Since: 4.24.0
[srcIpIntf]	*string*	Source interface for vxlan.
staticFloodlists **	*boolean*	Static Floodlists Configured. **Since: 4.21.3
[tcpMssV4] **	*integer*	VXLAN TCP MSS value for IPV4 packet. **Since: 4.28.0
[tcpMssV6] **	*integer*	VXLAN TCP MSS value for IPV6 packet. **Since: 4.28.0
[txInterval] **	*integer*	Rate in microseconds at which BFD control packets are sent. **Since: 4.25.2
udpPort **	*integer*	VXLAN UDP port. **Since: 4.29.0
use32BitVni **	*boolean*	VNI length in the VXLAN header. **Since: 4.22.0
[vArpVtepAddr]	*string*	IP address of virtual vtep.
[vArpVtepAddrV6] **	*IPv6 address*	IPv6 address of the virtual VTEPsource interface. **Since: 4.24.1
[vArpVtepSrcIpIntf] **	*interface name*	Source interface for virtual VTEP IP. **Since: 4.24.1
vccArpProxy **	*boolean*	ARP proxying when in Vxlan Controller Client Mode. **Since: 4.28.2
vccImportVlan **	*string*	Import-enabled VLANs. **Since: 4.23.0
vccNdProxy **	*boolean*	Neighbor Discovery proxying when in Vxlan Controller Client Mode. **Since: 4.29.1
[vlanToLearnRestrict]	*table(numeric string) = VxlanVtepPrefixes* see 2.571.12.3	Per Vlan Learn list.
vlanToVniMap	*table(numeric string) = VniSourcePair* see 2.571.12.1	Vlan to VNI source pair mapping.
vlanToVtepList	*table(numeric string) = VxlanRemoteVtepAddrs* see 2.571.12.2	Per Vlan Headend Vtep list.
vniInDottedNotation	*boolean*	True if vni is displayed in dotted notation.
[vrfToVniMap] **	*table(string) = integer*	VRF to VNI mapping. **Since: 4.18.1

`[vtepAddrMask]` **	*string*	IP address mask assigned to VTEP. **Since: 4.21.0
`vtepSetForSourcePruning` **	*list of IPv4 address*	Source pruning VTEP list. **Since: 4.22.1
`vtepSourcePruningAll` **	*boolean*	Source pruning for all VTEPs. **Since: 4.22.1
`[vtepToSecProfileTotal]` **	*integer*	Total active secure VTEPs. **Since: 4.25.2
`vtepToVtepBridging` **	*boolean*	VTEP to VTEP bridging is enabled. **Since: 4.22.1
`vxlanArpProxy` **	*boolean*	ARP proxying for requests received over VXLAN. **Since: 4.30.0
`vxlanEncapsulation` **	*enum: ipv4AndIpv6 | ipv4 | ipv6*	VXLAN encapsulation type. **Since: 4.24.0
`vxlanMacDrop` **	*boolean*	Drop frames L2 forwarded to VXLAN tunnels. **Since: 4.34.2
`vxlanNdProxy` **	*boolean*	ND proxying for requests received over VXLAN. **Since: 4.30.0

2.571.12.1 VniSourcePair

`source`	*string*	Mapping source.
`vni`	*integer*	Vni.

2.571.12.2 VxlanRemoteVtepAddrs

`remoteVtepAddr`	*list of IPv4 address*	List of IPv4 vteps.
`remoteVtepAddr6` **	*list of IPv6 address*	List of IPv6 vteps. **Since: 4.23.2

2.571.12.3 VxlanVtepPrefixes

`learnFrom`	*enum: learnFromDefault | learnFromList | learnFromFloodList | learnFromAny*	Origin of VTEP learn restriction.
`prefixList`	*list of IP address prefix*	List of vtep (prefixes).

2.572 show interfaces all hardware default

interfaces	*table(Interface name) = InterfaceCapabilitiesData* see 2.572.1	A mapping of interfaces to their capabilities information.

2.572.1 InterfaceCapabilitiesData

[autoNegotiationClause28]	*list of EthSpeedLanesDuplex* see 2.545.1.1.1	List of speed/lane count/duplex triplets at which this interface can perform clause 28 auto negotiation. A missing entry indicates auto negotiation capabilities are unknown.
[autoNegotiationClause37]	*list of EthSpeedLanesDuplex* see 2.545.1.1.1	List of speed/lane count/duplex triplets at which this interface can perform clause 37 auto negotiation. A missing entry indicates auto negotiation capabilities are unknown.
[autoNegotiationClause73]	*AutonegClause73-Capabilities* see 2.545.1.1	List of speed/lane count/duplex triplets at which this interface can perform clause 73 auto negotiation. A missing entry indicates auto negotiation capabilities are unknown.
[coherentModes]	*list of CoherentMode* see 2.545.1.2	List of modulation and coherent error-correction capabilities for this interface.
[coherentTributaries] **	*list of CoherentTributary* see 2.545.1.3	List of tributaries which may be mapped at each line rate. **Since: 4.26.2
[hasAutoneg]	*boolean*	This interface supports speed auto negotiated.
modes	*list of EthIntfMode* see 2.545.1.4	List of link-mode capabilities for this interface.
rxFlowControl	*FlowControlCapabilities* see 2.545.1.5	The rx flow control capabilities of this interface.
[speedGroup]	*SpeedGroup* see 2.545.1.6	Speed Group Id and range of member interfaces.
switchModelName	*string*	Model name of the switch.
transceiverType	*string*	Type of the inserted transceiver.
txFlowControl	*FlowControlCapabilities* see 2.545.1.5	The tx flow control capabilities of this interface.

2.573 show interfaces attached nic counters [...]

interfaces	*table(Interface name) = InterfaceCountersBase* see 2.573.1	Interface Counters.

2.573.1 InterfaceCountersBase

Could also be an instance of:
InterfaceCounters 2.571.8.1
VirtualInterfaceCountersBase 2.573.3
EthInterfaceCounters 2.571.3.1
VlanInterfaceCounters 2.571.11.1
VxlanInterfaceCounters 2.573.4
InterfaceFastCounters 2.573.2

2.573.2 InterfaceFastCounters

[inBroadcastPkts]	*integer*	Input broadcast packets.
[inMulticastPkts]	*integer*	Input multicast packets.
[inOctets]	*integer*	Input octets.
[inUcastPkts]	*integer*	Input unicast packets.
lastUpdateTimestamp	*floating point number*	Time of last update.
[outBroadcastPkts]	*integer*	Output broadcast packets.
[outMulticastPkts]	*integer*	Output multicast packets.
[outOctets]	*integer*	Output octets.
[outUcastPkts]	*integer*	Output unicast packets.

2.573.3 VirtualInterfaceCountersBase

2.573.4 VxlanInterfaceCounters

vnis	*table(string) = VxlanInterfaceVniCounters* see 2.573.4.1	Mapping between VNI and its counters.

2.573.4.1 VxlanInterfaceVniCounters

inOctets	*integer*	Input octets.
inPackets	*integer*	Input packets.
[lastUpdateTimestamp]	*floating point number*	Time of last update.
outOctets	*integer*	Output octets.
outPackets	*integer*	Output packets.

2.574 show interfaces attached nic counters discards [...]

inDiscardsTotal	*integer*	Total input packets discarded.
interfaces	*table(Interface name) = InterfaceCounterDiscards* see 2.574.1	Interface Discard Counters.

[outDiscardsTotal]	*integer*	Total output packets discarded.

2.574.1 InterfaceCounterDiscards

inDiscards	*integer*	Input packets discarded.
[outDiscards]	*integer*	Output packets discarded.

2.575 show interfaces attached nic counters errors [...]

see 2.540

2.576 show interfaces cable detail [...]

interfaces	*table(Interface name) = BaseTCableTestStatus* see 2.576.1	Mapping of base-t interfaces to cable test status.

2.576.1 BaseTCableTestStatus

cableStatus	*CableStatus* see 2.576.1.2	Overall cable health status.
lengthUncertainty	*integer*	Actual length is within this value of the reported length in meters.
pairAStatus	*CablePairStatus* see 2.576.1.1	Status of cable pair A.
pairBStatus	*CablePairStatus* see 2.576.1.1	Status of cable pair B.
pairCStatus	*CablePairStatus* see 2.576.1.1	Status of cable pair C.
pairDStatus	*CablePairStatus* see 2.576.1.1	Status of cable pair D.
testStatus	*TestingStatus* see 2.576.1.3	Status of cable test run.

2.576.1.1 CablePairStatus

lastLengthChange	*floating point number*	Last time cable pair length changed.
lastStateChange	*floating point number*	Last time cable pair state changed.
lengthChanges	*integer*	Number of cable pair length changes.
pairLength	*integer*	Estimated length of the cable pair in meters.
pairState	*enum: intraPairShort | busy | inconclusive | ok | interPairShort | open*	State of cable pair.
stateChanges	*integer*	Number of cable pair state changes.

2.576.1.2 CableStatus

cableState	*enum: inconclusive | notconnect | faulty | ok*	Overall cable state information.
lastStateChange	*floating point number*	Last time cable state changed.
stateChanges	*integer*	Number of cable state changes.

2.576.1.3 TestingStatus

lastStateChange	*floating point number*	Last time test state changed.
numTestRuns	*integer*	Number of cable test runs.
stateChanges	*integer*	Number of test state changes.
testState	*enum: untested | running | failed | completed*	Current testing state.

2.577 show interfaces config-sanity [...]

see 2.571

2.578 show interfaces counters discards [...]

see 2.574

2.579 show interfaces counters drop-precedence [...]

`interfaces`	*table(Interface name) = IntfDropPrecedence-Counters* see 2.579.1	Mapping between interface and all corresponding drop-precedence counters.

2.579.1 IntfDropPrecedenceCounters

`dpCounters`	*table(numeric string) = DpCounters* see 2.579.1.1	Mapping between DP ID and its counter data.

2.579.1.1 DpCounters

`[inOctets]`	*integer*	Ingress octets (bytes).
`[inPkts]`	*integer*	Ingress packets.
`[outOctets]`	*integer*	Egress octets (bytes).
`[outPkts]`	*integer*	Egress packets.

2.580 show interfaces counters egress acl drop [...]

`interfaces`	*table(Interface name) = EgressAclDropCounters* see 2.580.1	Mapping between egress interface and egress ACL drop counter data. These packets are dropped by the egress packet processor to avoid loops (source port) or double delivery of packets (MLAG).

2.580.1 EgressAclDropCounters

`[mlagPackets]`	*integer*	MLAG drop packets.
`[sourcePruningPackets]`	*integer*	Source port pruning packets.

2.581 show interfaces counters egress mtu [...]

destinations	*table(string) = EgressMtuCounters* see 2.581.1	Mapping between destinations and egress MTU counter data. These packets are bigger than the configured Maximum Transmission Unit of the VLAN or routed port. They get recycled back to the CPU to get fragmented and send an "ICMP Fragmentation Needed" message back to the source.

2.581.1 EgressMtuCounters

[droppedPackets]	*integer*	Packets dropped.
[enqueuedPackets]	*integer*	Packets enqueued.
[totalPackets]	*integer*	Total packets.

2.582 show interfaces counters ip [...]

revision 2

interfaces	*table(Interface name) = InterfaceIpv4Ipv6Counters* see 2.582.1	Mapping of an interface to its counters.

2.582.1 InterfaceIpv4Ipv6Counters

[ipv4InOctets]	*integer*	Number of input IPv4 octets.
[ipv4InPkts]	*integer*	Number of input IPv4 packets.
[ipv4OutOctets]	*integer*	Number of output IPv4 octets.
[ipv4OutPkts]	*integer*	Number of output IPv4 packets.
[ipv6InOctets]	*integer*	Number of input IPv6 octets.
[ipv6InPkts]	*integer*	Number of input IPv6 packets.
[ipv6OutOctets]	*integer*	Number of ouput IPv6 octets.
[ipv6OutPkts]	*integer*	Number of ouput IPv6 packets.

2.583 show interfaces counters ip rates [...]

interfaces	*table(Interface name) = InterfaceIpv4Ipv6CounterRates* see 2.583.1	Mapping between an interface and its rate counters.

2.583.1 InterfaceIpv4Ipv6CounterRates

interval	*floating point number*	Interval in seconds.
[ipv4InBitsRate] **	*integer*	Number of input IPv4 bits per second. **Since: 4.30.2
[ipv4InOctetsRate]	*integer*	Number of input IPv4 octets per second.
[ipv4InPktsRate]	*integer*	Number of input IPv4 packets per second.

[ipv4OutBitsRate] **	*integer*	Number of output IPv4 bits per second. **Since: 4.30.2
[ipv4OutOctetsRate]	*integer*	Number of output IPv4 octets per second.
[ipv4OutPktsRate]	*integer*	Number of output IPv4 packets per second.
[ipv6InBitsRate] **	*integer*	Number of input IPv6 bits per second. **Since: 4.30.2
[ipv6InOctetsRate]	*integer*	Number of input IPv6 octets per second.
[ipv6InPktsRate]	*integer*	Number of input IPv6 packets per second.
[ipv6OutBitsRate] **	*integer*	Number of output IPv6 bits per second. **Since: 4.30.2
[ipv6OutOctetsRate]	*integer*	Number of output IPv6 octets per second.
[ipv6OutPktsRate]	*integer*	Number of output IPv6 packets per second.
[lastUpdateTimestamp]	*floating point number*	Time of last update.

2.584 show interfaces counters queue [...]

egressQueueCounters	*EgressQueueCounters* see 2.584.1	Queue counters on the egress chip.
[ingressQueueCounters] **	*IngressQueueCounters* see 2.584.2	Queue counters on the ingress chip. **Since: 4.23.2
[ingressVoqCounters] **	*IngressVoqCounters* see 2.310.1	VOQ counters on the ingress source. **Since: 4.20.5

2.584.1 EgressQueueCounters

interfaces	*table(Interface name) = EgressQueueDestinationTypeCounters* see 2.584.1.1	Mapping between interface and destination type counter data.

2.584.1.1 EgressQueueDestinationTypeCounters

[bandwidth] **	*integer*	Interface speed in kbps. **Since: 4.22.0
[loadInterval] **	*floating point number*	Interval in seconds over which moving average is calculated. **Since: 4.22.0
mcastQueues	*EgressQueueTrafficClassCounters* see 2.584.1.1.1	Multicast traffic class counters.
ucastQueues	*EgressQueueTrafficClassCounters* see 2.584.1.1.1	Unicast traffic class counters.

2.584.1.1.1 EgressQueueTrafficClassCounters

trafficClasses	*table(string) = EgressQueueDropPrecedenceCounters* see 2.584.1.1.1.1	Mapping between traffic class and per drop precedence counter data. In some cases, some classes might be aggregated (ex: "TC1,4"), or totally aggregated (ex: "all").

2.584.1.1.1.1 EgressQueueDropPrecedenceCounters

dropPrecedences	*table(string) = Counters* see 2.310.1.1.1	Mapping between drop precedence and corresponding egress enqueue and drop counter data.
[schedMode] **	*enum: strictPriority | weightedRoundRobin*	Scheduling mode. **Since: 4.22.0
[shapeRate] **	*ShapeRateModel* see 2.584.1.1.1.2	Operational shape rate. **Since: 4.22.0
[wrrBw] **	*integer*	Operational weighted-round-robin bandwidth in percent. **Since: 4.22.0

2.584.1.1.1.2 ShapeRateModel

[percent] **	*integer*	Shape rate as percentage of reference (default link bandwidth). **Since: 4.22.1
[percentOf] **	*enum: unknown | parentInterfaceShapeRate | lineRate | schedulingGroupShapeRate | subinterfaceShapeRate*	Reference for shape rate percent. **Since: 4.25.2
rate	*integer*	Shape rate.
[shared] **	*boolean*	Shared LAG shaping configured. **Since: 4.21.0
unit	*enum: unspecified | pps | kbps*	Shape rate unit.

2.584.2 IngressQueueCounters

interfaces	*table(Interface name) = Counters* see 2.310.1.1.1	Mapping between interface and counter data across all traffic classes.

2.585 show interfaces counters queue drop-precedence [...]

interfaces	*table(Interface name) = IntfDropPrecedenceCounters* see 2.585.1	Mapping between interface and all corresponding drop-precedence counters.

2.585.1 IntfDropPrecedenceCounters

drops	*table(numeric string) = Counters* see 2.310.1.1.1	Mapping between interface and counter data.

2.586 show interfaces counters queue drops [...]

interfaces	*table(Interface name) = QueueTrafficClassDropsCounters* see 2.586.1	Mapping between egress interface and traffic class drops counter data.

2.586.1 QueueTrafficClassDropsCounters

trafficClasses	*table(string) = IngressEgressQueueDropsCounters* see 2.586.1.1	Mapping between traffic class, and ingress VOQ and egress queue drops counter data.

2.586.1.1 IngressEgressQueueDropsCounters

egressQueueCounters	*EgressQueueDrop-PrecedenceDropsCounters* see 2.586.1.1.1	Queue drops counters on the egress chip.
[ingressVoqCounters]	*IngressVoqSourceDrops-Counters* see 2.586.1.1.2	VOQ drops counters on the ingress source.

2.586.1.1.1 EgressQueueDropPrecedenceDropsCounters

[countersSum]	*Counters* see 2.310.1.1.1	Counters summed over drop precedence and destination type.
[dropPrecedences]	*table(string) = EgressQueueDestination-TypeDropsCounters* see 2.586.1.1.1.1	Mapping between drop precedence and corresponding egress destination type drops counter data.

2.586.1.1.1.1 EgressQueueDestinationTypeDropsCounters

[intfSpeed] **	*integer*	Interface speed. **Since: 4.22.0
[loadInterval] **	*integer*	Load Interval. **Since: 4.22.0
mcastQueues	*Counters* see 2.310.1.1.1	Multicast drops counters.
ucastQueues	*Counters* see 2.310.1.1.1	Unicast drops counters.

2.586.1.1.2 IngressVoqSourceDropsCounters

countersSum	*Counters* see 2.310.1.1.1	Counters summed over all sources.
sources	*table(string) = Counters* see 2.310.1.1.1	Mapping between traffic source and drops counter data.

2.587 show interfaces counters queue drops unicast [...]

egressQueueDropCounters	*EgressQueueDropCounters* see 2.587.1	Queue Drop counters on the egress.

2.587.1 EgressQueueDropCounters

interfaces	*table(Interface name) = EgressUcastQueueDrop-Counters* see 2.587.1.1	Mapping between interface and destination type counter data.

2.587.1.1 EgressUcastQueueDropCounters

ucastQueues	*EgressUcastQueueTraffic-ClassCounters* see 2.587.1.1.1	Unicast traffic class counters.

2.587.1.1.1 EgressUcastQueueTrafficClassCounters

trafficClasses	*table(string) = UcastDropCounters* see 2.587.1.1.1.1	Mapping between traffic class and unicast drop counter data.

2.587.1.1.1.1 UcastDropCounters

[droppedBytes]	*integer*	Unicast octets (bytes) dropped.
[droppedPackets]	*integer*	Unicast packets dropped.

2.588 show interfaces counters queue ingress [...]

see 2.310

2.589 show interfaces counters queue rates [...]

egressQueueCounters	*EgressQueueCounters* see 2.584.1	Queue counters on the egress chip.

2.590 show interfaces counters rates [...]

interfaces	*table(Interface name)* = *InterfaceCountersRateBase* see 2.590.1	Mapping between an interface rate counters and model.

2.590.1 InterfaceCountersRateBase

Could also be an instance of:
InterfaceCountersRate 2.590.4
VlanInterfaceCountersRate 2.590.5
VxlanInterfaceCountersRate 2.590.6
InterfaceIpv4Ipv6CounterRates 2.583.1
FabricIntfCountersRateModel 2.590.2
FabricPairCountersRateModel 2.590.3
FabricPeerIntfCountersRateModel 2.590.3.1

2.590.2 FabricIntfCountersRateModel

inBpsRate	*floating point number*	Input bps rate.
inPktsRate	*floating point number*	Input packets rate in percentage of port capacity.
inPpsRate	*floating point number*	Input pps rate.
outBpsRate	*floating point number*	Output bps rate.
outPktsRate	*floating point number*	Output packets rate in percentage of port capacity.
outPpsRate	*floating point number*	Output Kpps rate.

2.590.3 FabricPairCountersRateModel

inBpsRate	*floating point number*	Input bps rate.
inPktsRate	*floating point number*	Input packets rate in percentage of port capacity.
inPpsRate	*floating point number*	Input pps rate.
interval	*integer*	Interval in seconds.
outBpsRate	*floating point number*	Output bps rate.
outPktsRate	*floating point number*	Output packets rate in percentage of port capacity.
outPpsRate	*floating point number*	Output Kpps rate.
[peer]	*FabricPeerIntfCounters-RateModel* see 2.590.3.1	Peer interface rates.

2.590.3.1 FabricPeerIntfCountersRateModel

inBpsRate	*floating point number*	Input bps rate.
inPktsRate	*floating point number*	Input packets rate in percentage of port capacity.
inPpsRate	*floating point number*	Input pps rate.
outBpsRate	*floating point number*	Output bps rate.

outPktsRate	*floating point number*	Output packets rate in percentage of port capacity.
outPpsRate	*floating point number*	Output Kpps rate.

2.590.4 InterfaceCountersRate

description	*string*	Port description.
inBpsRate	*floating point number*	Input bps rate.
[inPktsRate]	*floating point number*	Input packets rate percentage.
inPpsRate	*floating point number*	Input pps rate.
interval	*integer*	Interval in seconds.
[lastUpdateTimestamp] **	*floating point number*	Time of last update. **Since: 4.21.3
outBpsRate	*floating point number*	Output bps rate.
[outPktsRate]	*floating point number*	Output packets rate percentage.
outPpsRate	*floating point number*	Output Kpps rate.

2.590.5 VlanInterfaceCountersRate

description	*string*	Port description.
inBpsRate	*floating point number*	Input bps rate.
interval	*integer*	Interval in seconds.
outBpsRate	*floating point number*	Output bps rate.

2.590.6 VxlanInterfaceCountersRate

vnis	*table(string) = VxlanInterfaceVniCountersRate* see 2.590.6.1	Mapping between VNI and its counters rate.

2.590.6.1 VxlanInterfaceVniCountersRate

description	*string*	Port description.
inBpsRate	*floating point number*	Input bps rate.
[inPktsRate]	*floating point number*	Input packets rate percentage.
inPpsRate	*floating point number*	Input pps rate.
interval	*integer*	Interval in seconds.
[lastUpdateTimestamp]	*floating point number*	Time of last update.
outBpsRate	*floating point number*	Output bps rate.
[outPktsRate]	*floating point number*	Output packets rate percentage.
outPpsRate	*floating point number*	Output pps rate.

2.591 show interfaces counters rates watermark [...]

interfaces	*table(Interface name) = InterfaceRateWatermark* see 2.591.1	Interface rate watermarks within the configured window.
windowEnd	*floating point number*	End of the watermark measurement window.

windowStart	*floating point number*	Start of the watermark measurement window.

2.591.1 InterfaceRateWatermark

[inBitRateWatermark]	*floating point number*	Input bps rate.
[inBitRateWatermarkPct]	*floating point number*	Input packets rate percentage.
intfName	*interface name*	Name of the interface that the watermark rate applies.
[outBitRateWatermark]	*floating point number*	Output ps rate.
[outBitRateWatermarkPct]	*floating point number*	Output packets rate percentagepercentage of total capacity.

2.592 show interfaces counters traffic-class [...]

interfaces	*table(Interface name) = InterfaceTrafficClasses-Counters* see 2.592.1	A mapping between an interface and its traffic class counters.

2.592.1 InterfaceTrafficClassesCounters

trafficClasses	*table(numeric string) = InterfaceTrafficClass-Counters* see 2.592.1.1	A mapping between a traffic class (in range 0 to 7) and its counters.

2.592.1.1 InterfaceTrafficClassCounters

[inBcastPkts]	*integer*	Input broadcast packets.
[inDroppedMcastOctets] **	*integer*	Dropped multicast octets. **Since: 4.30.0
[inDroppedMcastPkts] **	*integer*	Dropped multicast packets. **Since: 4.30.0
[inDroppedUcastOctets] **	*integer*	Dropped unicast octets. **Since: 4.30.0
[inDroppedUcastPkts] **	*integer*	Dropped unicast packets. **Since: 4.30.0
[inMcastOctets] **	*integer*	Input multicast octets. **Since: 4.30.0
[inMcastPkts]	*integer*	Input multicast packets.
inOctets	*integer*	Input octets.
inPkts	*integer*	Input packets.
[inUcastOctets] **	*integer*	Input unicast octets. **Since: 4.30.0
[inUcastPkts]	*integer*	Input unicast packets.

2.593 show interfaces counters vni [...]

Could also be an instance of:
VxlanInterfacesVniCounters 2.593

`interfaces`	*table(Interface name) = VirtualInterfaceCounters-Base* see 2.573.3	Interface Counters.

2.594 show interfaces counters vni rates [...]

see 2.590

2.595 show interfaces counters | (counters (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

see 2.573

2.596 show interfaces debounce | (debounce (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

`interfaces`	*table(Interface name) = InterfaceDebounceTime* see 2.596.1	Mapping between an interface and debounce times.

2.596.1 InterfaceDebounceTime

`linkDownTime`	*integer*	Interface linkdown debounce time in milliseconds, 0 means disabled.
`linkUpTime`	*integer*	Interface linkup debounce time in milliseconds, 0 means disabled.

2.597 show interfaces description [...]

`interfaceDescriptions`	*table(Interface name) = InterfaceDescription* see 2.597.1	Mapping between an interface and its description.

2.597.1 InterfaceDescription

description	*string*	Configured interface description.
interfaceStatus	*enum: adminDown* | *notApplicable* | *down* | *up* | *autoIsolated* | *adminIsolated* | *uninitDown*	Connection status of the interface.
lineProtocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.

2.598 show interfaces encapsulation dot1q vlan [...]

intfEncapsulations	*table(string) = InterfaceEncapsulations* see 2.598.1	The currently configured encapsulation vlan, keyed by interface name.

2.598.1 InterfaceEncapsulations

egressActive	*boolean*	Whether the encapsulation is active on egress.
ingressActive	*boolean*	Whether the encapsulation is active on ingress.
vlanId	*string*	The dot1q encapsulation VLAN Id.

2.599 show interfaces encapsulation vlan [...]

intfEncapsulations	*table(string) = FlexibleEncapsulations* see 2.599.1	Interface VLAN encapsulation status.

2.599.1 FlexibleEncapsulations

entries	*list of FlexEncapEntry* see 2.599.1.1	VLAN encapsulation entries.

2.599.1.1 FlexEncapEntry

client	*FlexEncapSpec* see 2.599.1.1.1	Client side encapsulation.
clientId **	*string*	Client identifier for encapsulation entries. **Since: 4.30.0
[network]	*FlexEncapSpec* see 2.599.1.1.1	Network side encapsulation.
status	*enum: inactive* | *conflict* | *overlap* | *asymmetric* | *active*	VLAN encapsulation status.

2.599.1.1.1 FlexEncapSpec

specType	*enum: untagged | tagged | clientInner | client | unmatched*	Type of encapsulation.
[tagged]	*FlexEncapTaggedSpec* see 2.599.1.1.1.1	Tagged encapsulation.

2.599.1.1.1.1 FlexEncapTaggedSpec

[inner]	*FlexEncapValue* see 2.599.1.1.1.2	Inner VLAN tags.
outer	*FlexEncapValue* see 2.599.1.1.1.2	Outer VLAN tags.

2.599.1.1.1.2 FlexEncapValue

[tags] **	*list of FlexEncapTaggedValue* see 2.599.1.1.1.3	VLAN tags. **Since: 4.24.2
[tpid] **	*integer*	TPID value. **Since: 4.33.1
valueType	*enum: userDefinedTpid | client | dot1ad | dot1q*	Type of encapsulation.

2.599.1.1.1.3 FlexEncapTaggedValue

[endTag] **	*integer*	Ending VLAN tag. **Since: 4.29.1
[tag]	*integer*	Starting VLAN tag.

2.600 show interfaces hardware | (hardware (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

see 2.572

2.601 show interfaces interactions | (interactions (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

interfaces	*table(Interface name) = InterfacesInteractionsDataBySpeed* see 2.601.1	A mapping of interface names to interactions with other interfaces at a desired speed configuration.

2.601.1 InterfacesInteractionsDataBySpeed

[inactiveReason] **	*string*	Reason why the interface is inactive due to having no available configurations. **Since: 4.30.2
[interfaceHardwareResourcePool] **	*InterfaceHardwareResourcePool* see 2.601.1.1	Interface hardware resource pool that this interface belongs to. **Since: 4.23.1
speeds	*table(string) = InterfacesInteractionsData* see 2.601.1.2	A mapping of desired speed configurations to interactions with other interfaces. Speed configurations are represented in the notation <speed> or <speed> -<lane> . <speed> describes the interface speed and, <lane> if specified describes the number of electrical lanes used on the host-side of the transceiver.

2.601.1.1 InterfaceHardwareResourcePool

capacity	*integer*	Maximum number of interface hardware resources available in the pool.
memberInterfaces	*list of Interface name*	Interfaces belonging to this resource pool.
poolId	*integer*	Name of the resource pool.

2.601.1.2 InterfacesInteractionsData

[autonegRequirement] **	*AutonegFecRequirement* see 2.601.1.2.1	Error-correct encoding restriction when auto-negotation is configured. **Since: 4.26.2
[compatibleParentInterfaceConfigurations] **	*CompatibleParentInterfaceConfigurations* see 2.601.1.2.2	List of interfaces that can affect desired configuration and which of their configurations are compatible with desired configuration. **Since: 4.23.1
[hardwarePortGroupRequirement] **	*HardwarePortGroupRequirement* see 2.601.1.2.3	Hardware port-group configuration required to achieve stated speed configuration. **Since: 4.27.0
[inactiveInterfaces]	*InactiveInterfacesInteraction* see 2.601.1.2.4	List of interfaces that become inactive to facilitate desired speed configuration.

[primaryInterface-ConfigurationRequirement]	*PrimaryInterface-ConfigurationRequirement* see 2.601.1.2.5	Speed configuration required on primary interface to facilitate desired speed configuration.
[speedGroupRequirement] **	*SpeedGroupRequirement* see 2.601.1.2.6	Speed-group configuration required to achieve stated speed configuration. **Since: 4.22.1
[speedLimitedInterfaces]	*SpeedLimitedInterfaces-Interaction* see 2.601.1.2.7	List of interfaces that become speed-limited and what speeds they are limited to to facilitate desired speed configuration.

2.601.1.2.1 AutonegFecRequirement

primaryIntf	*interface name*	Name of the primary interface.

2.601.1.2.2 CompatibleParentInterfaceConfigurations

interfaces	*table(Interface name) = SpeedConfigurationList* see 2.601.1.2.2.1	Mapping of interface name to a slash-separated list of its speed configurations that do not conflict with the desired configuration on the desired interface.

2.601.1.2.2.1 SpeedConfigurationList

configurations	*list of SpeedConfiguration* see 2.601.1.2.2.2	List of speed configurations.

2.601.1.2.2.2 SpeedConfiguration

[lanes]	*integer*	Number of electrical lanes used on the host-side of the interface.
speed	*enum: 100M | 2.5G | 1G | 400G | 1.6T | 10G | 100G | 800G | 50G | 5G | 200G | 25G | 40G | 10M*	Configuration speed.

2.601.1.2.3 HardwarePortGroupRequirement

portGroup	*string*	Port-group the referred interface is in.
portMode	*string*	Port-group mode needed for the referred interface speed to take effect.

2.601.1.2.4 InactiveInterfacesInteraction

interfaces	*list of Interface name*	Interfaces that become inactive.

2.601.1.2.5 PrimaryInterfaceConfigurationRequirement

interface	*interface name*	Name of primary interface.

requiredConfiguration	*enum: 400G-4 | 800G-8 | 200G-8 | 400G-2 | 10M | 1G | 1.6T-8 | 200G-1 | 200G-2 | 2.5G | 100G-4 | 100G-1 | 10G | 50G-1 | 200G-4 | 100M | 400G-8 | 50G-2 | 100G-2 | 800G-4 | 5G | 25G | 40G*	Speed configuration required on primary interface. Speed configuration is given in the notation <speed> or <speed> -<lane> . <speed> describes the interface speed, and <lane> if specified describes the number of electrical lanes used on the host-side of the transceiver.

2.601.1.2.6 SpeedGroupRequirement

serdes	*string*	Speed-group SerDes configuration needed for the referred interface speed to take effect.
speedGroup	*string*	Speed-group the referred interface is in.

2.601.1.2.7 SpeedLimitedInterfacesInteraction

interfaces	*table(Interface name) = string*	Mapping of interface name to what speed configurations it becomes limited to. Speed configurations are represented in the notation <speed> or <speed> -<lane> . <speed> describes the interface speed, and <lane> if specified describes the number of electrical lanes used on the host-side of the transceiver.

2.602 show interfaces mac [...]

interfaces	*table(Interface name) = InterfaceMacData* see 2.602.1	A mapping of interfaces to their MAC information.

2.602.1 InterfaceMacData

[additionalStatus]	*table(string) = string*	A mapping of platform specific fields to their values.
adminEnabled	*boolean*	Administratively enabled.
intfState	*enum: inactive | linkUnknown | linkDown | linkUp*	Interface State.
intfStateChangeCount	*integer*	Total number of interface state changes.
intfStateLastChangeTime	*floating point number*	Time of last interface state change.
macRxLastLocalFaultChange-Time	*floating point number*	Time of last local MAC Rx fault.
macRxLastRemoteFaultChange-Time	*floating point number*	Time of last remote MAC Rx fault.
macRxLocalFault	*boolean*	A current local Rx fault has been detected.
macRxLocalFaultChangeCount	*integer*	Total number of local MAC Rx faults.
macRxRemoteFault	*boolean*	A current remote Rx fault has been detected.
macRxRemoteFaultChangeCount	*integer*	Total number of remote MAC Rx faults.

[phyState]	*enum: unknown | autonegotiating | linkUp | detectingXcvr | linkDown | init | errDisabled*	Phy State.
[phyStateChangeCount]	*integer*	Total number of PHY state changes.
[phyStateLastChangeTime]	*floating point number*	Time of last PHY state change.

2.603 show interfaces mac security capabilities [...]

interfaces	*table(Interface name) = Macsec.Cli.MacsecCapableInterface* see 2.603.1	A mapping between MACsec capable interfaces and their capabilities.

2.603.1 Macsec.Cli.MacsecCapableInterface

ciphers	*list of string*	List of ciphers supported.
perIntfPtpBypass	*boolean*	Per Interface PTP bypass is supported.
ptpBypasses	*list of string*	List of PTP bypass packets.
subInterfaces	*boolean*	Subinterfaces are supported.

2.604 show interfaces queue length [...]

cpuPorts	*table(Interface name) = QueueTypeQueueInfo* see 2.604.1	Maps CPU port name to queue information.
fabricPorts	*table(Interface name) = QueueTypeQueueInfo* see 2.604.1	Maps fabric port name to queue information.
frontPanelPorts	*table(Interface name) = QueueTypeQueueInfo* see 2.604.1	Maps front panel port name to queue information.
lagSubIntfs **	*table(Interface name) = QueueTypeQueueInfo* see 2.604.1	Maps LAG sub interface name to queue information. **Since: 4.22.0
recyclePorts	*table(Interface name) = QueueTypeQueueInfo* see 2.604.1	Maps recycle port name to queue information.

2.604.1 QueueTypeQueueInfo

Could also be an instance of:
SandQueueTypeQueueInfo 2.604.2

2.604.2 SandQueueTypeQueueInfo

voqs	*table(string) = SourceQueueInfo* see 2.604.2.1	Maps traffic class to queue information for virtual output queue type.

2.604.2.1 SourceQueueInfo

sources	*table(string) = QueueInfo* see 2.604.2.1.1	Maps traffic source name to queue information.

2.604.2.1.1 QueueInfo

queueLength	*integer*	Current queue length in bytes.

2.605 show interfaces single INTF

see 2.571

2.606 show interfaces status | (status (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

interfaceStatuses	*table(string) = InterfaceStatusEntry* see 2.606.1	Collection of interfaces statuses, keyed by interface name.

2.606.1 InterfaceStatusEntry

[autoNegotiateActive]	*boolean*	Is autonegotiate active.
autoNegotigateActive	*boolean*	Is autonegotiate active. Misspelled autoNegotiateActive (legacy).
bandwidth	*integer*	Bandwidth (bit).
description	*string*	Configured interface description.
duplex	*enum: duplexFull | duplexHalf | duplexUnknown*	Duplex status of the interface.
[encapsulation] **	*Encapsulation* see 2.606.1.1	Encapsulation information. **Since: 4.21.0
[interfaceDamped] **	*boolean*	Indicates that the interface is damped as a result of link flaps. **Since: 4.31.2
interfaceType	*string*	Interface Type.
[lineProtocolStatus]	*enum: lowerLayerDown | unknown | down | up | testing | notPresent | notApplicable | dormant*	Line protocol status.
linkStatus	*enum: inactive | connected | initializing | unknown | notapplicable | errdisabled | maint-down | adminIsolated | noSignal | uninitialized | no-resource | signal | admin | notconnect | disabled | autoIsolated*	Connection status of the interface.
[trafficAboveThreshold]	*boolean*	Indicates that the traffic on the Interface is above traffic threshold.
[underMaintenance]	*boolean*	Indicates an Interface is under maintenance or not.
vlanInformation	*VlanInformation* see 2.606.1.2	Model to describe the VLAN setting.

2.606.1.1 Encapsulation

[dot1qVlanTags]	*list of integer*	Encapsulation dot1q vlan tags.
encapsulationType	*dot1q*	Encapsulation type.

2.606.1.2 VlanInformation

interfaceForwardingModel	*enum: recirculation* | *quietDataLink* | *unauthorized* | *routed* | *bridged* | *linkQualification* | *layer1Patch* | *dataLink* | *layer1PatchAndLldp*	LinkQualification – the interface forwards packets for link qualification purposes. Protocols do not run on this interface, Layer1Patch – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. Protocols do not run on this interface, Layer1PatchAndLldp – the interface runs in Layer 1 mode to patch receive and/or transmit paths of various ports in the system. LLDP is the only protocol supported on this interface, Recirculation – the interface recirculates packets. Protocols do not run on this port, QuietDataLink – the interface forwards packets but does not participate in bridging or routing and protocols do not run on this interface, Unauthorized – the interface does not participate in bridging or routing and only EAPOL runs on this interface, DataLink – the interface forwards packets given to it but is not participating in bridging or routing operations, Routed – the interface can route packets, Bridged – the interface can bridge packets but not route them.
[interfaceMode]	*enum: inactive* | *fabric* | *tool* | *tap* | *routed* | *encap* | *bridged* | *tapTool* | *trunk*	If not in DataLink mode, what mode.
[vlanExplanation]	*string*	Shows whether the interface is part of a monitor destination or a Port-channel.
[vlanId]	*integer*	Vlan ID if interface is bridged, None otherwise.

2.607 show interfaces switchport configuration source [...]

interfaces	*table(Interface name)* = *ConfigSource* see 2.607.1	Switchport config source indexed by interface name.

2.607.1 ConfigSource

config	*list of string*	List of config commands published by this source.
source	*string*	Name of the config source.

2.608 show interfaces switchport vlan mapping [...]

intfVlanMappings	*table(string) = InterfaceVlanMappings* see 2.608.1	Collection of VLAN mappings, keyed by interface.

2.608.1 InterfaceVlanMappings

[egressDoubleTagged-Mappings]	*table(numeric string) = InnerTagMappings* see 2.608.1.1	Double tagged VLAN mappings configured for egress packets on an interface.
egressVlanMappingRequired **	*boolean*	Whether VLAN mapping is required for egress packets. **Since: 4.29.1
egressVlanMappings	*table(numeric string) = MappedVlan* see 2.608.1.1.1	VLAN mappings configured for egress packets on an interface.
[ingressDoubleTagged-Mappings]	*table(numeric string) = InnerTagMappings* see 2.608.1.1	Double tagged VLAN mappings configured for ingress packets on an interface.
ingressVlanMappingRequired **	*boolean*	Whether VLAN mapping is required for ingress packets. **Since: 4.20.5
ingressVlanMappings	*table(numeric string) = MappedVlan* see 2.608.1.1.1	VLAN mappings configured for ingress packets on an interface.

2.608.1.1 InnerTagMappings

mappings	*table(numeric string) = MappedVlan* see 2.608.1.1.1	Inner tag VLAN mappings.

2.608.1.1.1 MappedVlan

active	*boolean*	Whether this mapping is currently active.
[allInnerVid] **	*boolean*	Match on all inner VlanId for dot1q tunnel packet. **Since: 4.27.1
configured	*boolean*	Whether this mapping is currently configured.
[deQinQXlate] **	*boolean*	Untunnel and translate double tagged packets. **Since: 4.27.1
[dot1qTunnel]	*boolean*	Whether the tag is dot1q tunneled.
[innerVlanId]	*integer*	Inner VLAN ID that packets are mapped to.
vlanId	*integer*	VLAN ID that packets are mapped to (the outer VLAN in a double mapping).

2.609 show interfaces switchport | (switchport (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

switchports	*table(Interface name) = SwitchPort* see 2.609.1	A collection of switchports indexed by interface name.

2.609.1 SwitchPort

enabled	*boolean*	Whether switchport is enabled.
[switchportInfo]	*SwitchPortInfo* see 2.609.1.1	Switchport information.

2.609.1.1 SwitchPortInfo

accessVlanId	*integer*	Access VLAN ID.
accessVlanName	*string*	Access VLAN name.
dot1qVlanTagDisallowed **	*boolean*	Drop tagged frames is active on the port. **Since: 4.21.3
dot1qVlanTagRequired **	*boolean*	Allow only vlan tagged frames. **Since: 4.20.5
dot1qVlanTagRequiredStatus **	*boolean*	Allow only vlan tagged frames is active on the port. **Since: 4.20.5
dynamicAllowedVlans	*table(string) = string*	A mapping between a process name and dynamic VLANs out of the allowed trunk VLANs on the switchport. Represented in canonical form.
dynamicBlockedVlans **	*table(string) = string*	A mapping between a process name and VLANs blocked by this process on the switchport. Represented in canonical form. **Since: 4.26.0
dynamicTrunkGroups	*list of string*	List of dynamic trunk group names.
isolated **	*boolean*	Port isolation is enabled. **Since: 4.34.1
macLearning	*boolean*	Whether MAC address learning is enabled.
mbvaEnabled **	*boolean*	MAC-based VLAN assignment is enabled. **Since: 4.27.1
mode	*enum: access | dot1qTunnel | tool | tap | tapTool | trunk*	Administrative or operational mode of the switchport.
phoneTrunk **	*boolean*	Phone Trunk mode is enabled. **Since: 4.22.1
phoneTrunkUntagged **	*boolean*	Phone trunk untagged is enabled. **Since: 4.22.1
phoneVlan **	*integer*	Phone VLAN ID. **Since: 4.22.1
[priorityTaggedTxStatus] **	*boolean*	Whether egress priority tagging is enabled. **Since: 4.34.0

[privateVlanMapping]	*string*	Administrative private VLANs mapped to the switchport. Represented in canonical form.
sourceportFilterMode **	*enum: enabled | disabled | multicastDisabled*	Whether source interface filtering is disabled or not. **Since: 4.18.1
[staticAllowedVlans]	*string*	Static VLANs out of the allowed trunk VLANs on the switchport. Represented in canonical form.
staticTrunkGroups	*list of string*	List of static trunk group names.
taggedEgressOnlyVlans **	*string*	Trunk VLANs on the switchport that allow traffic to only egress. VLAN tagging is enabled. **Since: 4.35.2
[tpid]	*string*	Dot1q ethertype/Tag protocol ID in hex.
[tpidStatus]	*boolean*	Whether tpid is active or not.
trunkAllowedVlans	*string*	Allowed trunk VLANs on the switchport. Represented in canonical form. For eg: (2-40,70,100-200), ALL(1-4094), NONE etc.
trunkingNativeVlanId	*integer*	Trunking native mode VLAN ID.
[trunkingNativeVlanName]	*string*	Trunking native mode VLAN name.
untaggedEgressOnlyVlans **	*string*	Trunk VLANs on the switchport that allow traffic to only egress. VLAN tagging is disabled. **Since: 4.35.2
vlanForwardingMode **	*enum: allConfiguredVlans | allowedVlansOnly*	Whether the VLAN forwarding mode is set to allowed VLANs on the port or all configured VLANs. **Since: 4.21.3

2.610 show interfaces transceiver [...]

interfaces	*table(Interface name) = InterfaceTransceiverBase* see 2.610.1	Mapping between Interface name and the transceiver info.

2.610.1 InterfaceTransceiverBase

Could also be an instance of:
InterfaceTransceiver 2.610.2

2.610.2 InterfaceTransceiver

channel **	*string*	Transceiver optical channel number. **Since: 4.32.2
[details]	*InterfaceTransceiverDetails* see 2.610.2.1	Warning and alarm thresholds.
mediaType	*string*	Media type.
[narrowBand] **	*boolean*	Narrowband Transceiver. **Since: 4.15.4
[rxPower]	*floating point number*	RX power in dBm.
slot **	*string*	Transceiver slot number. **Since: 4.32.2
[temperature]	*floating point number*	Temperature in Celsius.
[totalRxPower] **	*floating point number*	Total RX power in dBm. **Since: 4.15.4
[txBias]	*floating point number*	Current in mA.
[txPower]	*floating point number*	TX power in dBm.
updateTime	*floating point number*	Last update time in UTC.
vendorSn	*string*	Transceiver serial number.
[voltage]	*floating point number*	Voltage in Volts.

2.610.2.1 InterfaceTransceiverDetails

[rxPower]	*InterfaceTransceiverDetail-Thresholds* see 2.610.2.1.1	RX power alarm and warning thresholds in dBm.
[temperature]	*InterfaceTransceiverDetail-Thresholds* see 2.610.2.1.1	Temperature alarm and warning thresholds in Celsius.
[totalRxPower] **	*InterfaceTransceiverDetail-Thresholds* see 2.610.2.1.1	Total RX power alarm and warning thresholds in dBm. **Since: 4.15.4
[txBias]	*InterfaceTransceiverDetail-Thresholds* see 2.610.2.1.1	Bias current alarm and warning thresholds in mA.
[txPower]	*InterfaceTransceiverDetail-Thresholds* see 2.610.2.1.1	TX power alarm and warning thresholds in dBm.
[voltage]	*InterfaceTransceiverDetail-Thresholds* see 2.610.2.1.1	Voltage alarm and warning thresholds in Volts.

2.610.2.1.1 InterfaceTransceiverDetailThresholds

[highAlarm]	*floating point number*	High alarm threshold for parameter.
highAlarmOverridden **	*boolean*	High alarm hardware threshold is overridden by software config. **Since: 4.32.1
[highWarn]	*floating point number*	High warning threshold for parameter.
highWarnOverridden **	*boolean*	High warning hardware threshold is overridden by software config. **Since: 4.32.1
[lowAlarm]	*floating point number*	Low alarm threshold for parameter.
lowAlarmOverridden **	*boolean*	Low alarm hardware threshold is overridden by software config. **Since: 4.32.1
[lowWarn]	*floating point number*	Low warning threshold for parameter.
lowWarnOverridden **	*boolean*	Low warning hardware threshold is overridden by software config. **Since: 4.32.1

2.611 show interfaces transceiver channels [...]

interfaces	*table(Interface name) = InterfaceTransceiverChannels* see 2.611.1	Mapping between interface name and the transceiver channel info.

2.611.1 InterfaceTransceiverChannels

channels	*list of InterfacesTransceiverChannelRow* see 2.611.1.1	Rows in output, specifiy a channel and its corresponding channel number for each spacing.
gridSpacings	*list of floating point number*	Channel spacings (in GHz). Each channel spacing demands a column filled with channel numbers for each frequency.

2.611.1.1 InterfacesTransceiverChannelRow

frequency	*floating point number*	Tuning channel frequency (GHz).
gridSpacingToChannelNumber	*table(string) = integer*	Mapping of the channel number for each grid spacing frequency requested.
wavelength	*floating point number*	Tuning channel wavelength (nm).

2.612 show interfaces transceiver diag test pattern [...]

lineInterfaces	*table(Interface name) = InterfacesTransceiverTestPatternConfiguration* see 2.612.1	Mapping from interface name to line/media side transceiver Test Pattern config information.
systemInterfaces	*table(Interface name) = InterfacesTransceiverTestPatternConfiguration* see 2.612.1	Mapping from interface name to system/host side transceiver Test Pattern config information.

2.612.1 InterfacesTransceiverTestPatternConfiguration

receiver	*InterfacesTransceiverTestPatternSideConfigs* see 2.612.1.1	Configuration for receiver / checker.
transmitter	*InterfacesTransceiverTestPatternSideConfigs* see 2.612.1.1	Configuration for transmitter / generator.

2.612.1.1 InterfacesTransceiverTestPatternSideConfigs

[configuredOptions]	*InterfacesTransceiverTestPatternSideConfig* see 2.612.1.1.1	Test Pattern options selected by the user.
[operationalOptions]	*InterfacesTransceiverTestPatternSideConfig* see 2.612.1.1.1	Test Pattern options currently operational in the module.

2.612.1.1.1 InterfacesTransceiverTestPatternSideConfig

fec	*boolean*	Forward error correction enabled in this config.
pattern	*enum: prbs7 | prbs9 | prbs23 | prbs9q | ssprq | prbs13 | prbs23q | prbs31q | prbs15 | prbs13q | prbs15q | prbs31 | prbs7q*	The pattern present in this config.

2.613 show interfaces transceiver diag test pattern capabilities [...]

interfaces	*table(Interface name) = InterfacesTransceiverTestPatternCapabilities* see 2.613.1	Mapping between interface name and the transceiver info.

2.613.1 InterfacesTransceiverTestPatternCapabilities

[lineReceiver]	*InterfacesTransceiverTestPatternSideCapabilities* see 2.613.1.1	Capabilities for line receiver / media checker.
[lineTransmitter]	*InterfacesTransceiverTestPatternSideCapabilities* see 2.613.1.1	Capabilities for line transmitter / media generator.
[systemReceiver]	*InterfacesTransceiverTestPatternSideCapabilities* see 2.613.1.1	Capabilities for system receiver / host checker.
[systemTransmitter]	*InterfacesTransceiverTestPatternSideCapabilities* see 2.613.1.1	Capabilities for system transmitter / host generator.

2.613.1.1 InterfacesTransceiverTestPatternSideCapabilities

fecSupported	*boolean*	Does this module support forward error correction during test pattern testing.
[supportedPatterns]	*list of string*	The possible patterns that the module's diagnostics can generate and do error counting for.

2.614 show interfaces transceiver diag test pattern counters [...]

lineInterfaces	*table(Interface name) = InterfacesTransceiverTestPatternCounters* see 2.614.1	List of line/media side transceiver test pattern result counters indexed by lane number.
systemInterfaces	*table(Interface name) = InterfacesTransceiverTestPatternCounters* see 2.614.1	List of system/host side transceiver test pattern result counters indexed by lane number.

2.614.1 InterfacesTransceiverTestPatternCounters

[lanes]	*list of InterfacesTransceiverTestPatternLaneCounters* see 2.614.1.1	Mapping from lane number to test pattern result lane counters.
[lastClear]	*floating point number*	The time when the pattern was last cleared.
[operationalPattern]	*enum: prbs7 | prbs9 | prbs23 | prbs9q | ssprq | prbs13 | prbs23q | prbs31q | prbs15 | prbs13q | prbs15q | prbs31 | prbs7q*	The active test pattern.

2.614.1.1 InterfacesTransceiverTestPatternLaneCounters

bitErrors	*integer*	The number of bit errors since test pattern was enabled.
burstCount	*integer*	The number of polling periods where counters changed since test pattern was enabled.

[detailed]	*InterfacesTransceiverTestPatternLaneCountersDetail* see 2.614.1.1.1	Detailed test pattern lane counters.
largestBurst	*integer*	The largest amount of bit errors in a polling period since test pattern was enabled.
[lastErrorTime]	*floating point number*	The last time an error was reported since test pattern was enabled.
linkState	*enum: notLocked | notApplicable | locked*	The lock state of the lane link under test.

2.614.1.1.1 InterfacesTransceiverTestPatternLaneCountersDetail

ber	*floating point number*	The bit error rate of the link.
[lastLinkStateChange]	*floating point number*	The time when the link state last changed.
linkStateChanges	*integer*	The number of link state transitions since test pattern was enabled.
totalBits	*integer*	The total number of bits sent through the link.

2.615 show interfaces transceiver dom [...]

interfaces	*table(Interface name) = InterfaceTransceiverDomBase* see 2.615.1	Mapping between interface name and the transceiver information.

2.615.1 InterfaceTransceiverDomBase

Could also be an instance of:
InterfaceTransceiverDom 2.615.2

[displayName] **	*string*	Interfaces corresponding to the channel of the transceiver. **Since: 4.22.0

2.615.2 InterfaceTransceiverDom

[displayName] **	*string*	Interfaces corresponding to the channel of the transceiver. **Since: 4.22.0
mediaType	*string*	Media type.
parameters	*table(string) = InterfaceTransceiverDomParameter* see 2.615.2.1	A mapping of parameter name to per channel value and thresholds.
updateTime	*floating point number*	Last update time in UTC.
vendorSn	*string*	Transceiver serial number.

2.615.2.1 InterfaceTransceiverDomParameter

channels	*table(string) = floating point number or NULL*	Per channel parameter value. '-' for the channel indicates a channel independent parameter.
[threshold]	*InterfaceTransceiverDetail-Thresholds* see 2.610.2.1.1	Threshold for monitored parameter.
unit	*string*	Parameter unit.

2.616 show interfaces transceiver eeprom [...]

interfaces	*table(Interface name) = InterfacesTransceiverEepromIntf* see 2.616.1	Mapping between interface name and the EEPROM.

2.616.1 InterfacesTransceiverEepromIntf

fields	*table(string) = InterfacesTransceiverEepromField* see 2.616.1.1	Mapping between a field name and its data.

2.616.1.1 InterfacesTransceiverEepromField

[note]	*string*	A note about this field's interpretation.
pages	*table(numeric string) = InterfacesTransceiverEepromBytes* see 2.616.1.1.1	Mapping between a page and the bytes on the page the field is defined over.
[subfields]	*table(string) = InterfacesTransceiverEepromFieldBase* see 2.616.1.1.2	Mapping between a subfield name and its data.
[value]	*InterfacesTransceiverEepromValue* see 2.616.1.1.3	The value of this field.

2.616.1.1.1 InterfacesTransceiverEepromBytes

byteOffsets	*list of integer*	The byte offsets for the field.

2.616.1.1.2 InterfacesTransceiverEepromFieldBase

Could also be an instance of:
InterfacesTransceiverEepromField 2.616.1.1

2.616.1.1.3 InterfacesTransceiverEepromValue

Could also be an instance of:
InterfacesTransceiverEepromBoolValue 2.616.1.1.4
InterfacesTransceiverEepromFloatValue 2.616.1.1.5
InterfacesTransceiverEepromIntValue 2.616.1.1.6
InterfacesTransceiverEepromStrValue 2.616.1.1.7

raw	*integer*	The raw value stored in EEPROM.

2.616.1.1.4 InterfacesTransceiverEepromBoolValue

decoded	*boolean*	The decoded value from the EEPROM.

raw	*integer*	The raw value stored in EEPROM.

2.616.1.1.5 InterfacesTransceiverEepromFloatValue

decoded	*floating point number*	The decoded value from the EEPROM.
[prefix]	*enum:* - | +/- | +	Prefix such as "+/-" for the decoded value.
raw	*integer*	The raw value stored in EEPROM.
[units]	*enum: dB | MBd | s | W | ms | MHz | C | km | Mbps | m | nm*	The units for the decoded value.

2.616.1.1.6 InterfacesTransceiverEepromIntValue

decoded	*integer*	The decoded value from the EEPROM.
[prefix]	*enum:* - | +/- | +	Prefix such as "+/-" for the decoded value.
raw	*integer*	The raw value stored in EEPROM.
[units]	*enum: dB | MBd | s | W | ms | MHz | C | km | Mbps | m | nm*	The units for the decoded value.

2.616.1.1.7 InterfacesTransceiverEepromStrValue

decoded	*string*	The decoded value from the EEPROM.
[possibleValues]	*list of string*	The possible values that decoded can take on.
raw	*integer*	The raw value stored in EEPROM.

2.617 show interfaces transceiver hardware [...]

revision 2

interfaces	*table(Interface name) = InterfacesTransceiverHardware* see 2.617.1	Mapping between interface name and the transceiver info.

2.617.1 InterfacesTransceiverHardware

[cableType]	*enum: CA-S | CA-L | CA-N*	Type of copper cable.
[detectedMediaType]	*string*	The media type set in device's IDPROM.
[maxPowerSupportedCharacteristic]	*floating point number*	Maximum slot power in watts.
[mediaType]	*string*	The effective media type, normally thedetectedMediaType, but can be overridden by cli config.
[modulePresent] **	*boolean*	Transceiver is present. **Since: 4.31.0
[power]	*InterfacesTransceiverHardwarePower* see 2.617.1.1	Power information.
[powerCharacteristic]	*floating point number*	Maximum module power in watts.
[tuning]	*InterfacesTransceiverHardwareTuning* see 2.617.1.2	Tuning information.
[txDisabled]	*boolean*	Optical transmitter disabled.
[wavelength]	*floating point number*	Wavelength of fiber (nm).

2.617.1.1 InterfacesTransceiverHardwarePower

[configuredRxPower]	*floating point number*	RX power in dBm.
[configuredTxPower]	*floating point number*	TX power in dBm.
[operationalRxAttenuation]	*floating point number*	RX attenuation in dB.
[operationalTxPower]	*floating point number*	TX power in dBm.

2.617.1.2 InterfacesTransceiverHardwareTuning

[computedFrequency]	*floating point number*	Computed frequency in GHz.
[computedRxWavelength]	*floating point number*	Computed RX wavelength in nm.
[computedWavelength]	*floating point number*	Computed wavelength in nm.
[configuredChannel]	*integer*	Configured channel.
[configuredFrequency]	*floating point number*	Configured TX frequency in GHz.
[configuredGrid]	*floating point number*	Configured grid in GHz.
[configuredRxFineFrequency]	*floating point number*	Configured RX fine frequency in GHz.
[configuredRxFrequency]	*floating point number*	Configured RX frequency in GHz.
[gridSpacingCapabilities]	*string*	Grid spacing capabilities in GHz.
[operationalChannel]	*integer*	Operational channel.
[operationalFrequency]	*floating point number*	Operational TX frequency in GHz.
[operationalGrid]	*floating point number*	Operational grid in GHz.

[operationalRxFrequency]	*floating point number*	Operational RX frequency in GHz.
[operationalRxWavelength]	*floating point number*	Operational RX wavelength in nm.
[operationalWavelength]	*floating point number*	Operational TX wavelength in nm.

2.618 show interfaces transceiver performance-monitoring [...]

interfaces	*table(Interface name) = InterfaceTransceiver-PerformanceMonitoring* see 2.618.1	Mapping between interface name and the performance monitoring information.
[performanceMonitoring-PeriodSeconds]	*integer*	Performance monitoring period in seconds.

2.618.1 InterfaceTransceiverPerformanceMonitoring

[displayName] **	*string*	Interfaces corresponding to the channel of the transceiver. **Since: 4.30.0
[performanceMonitoring-Intervals]	*table(numeric string) = InterfaceTransceiver-PerformanceMonitoring-Interval* see 2.618.1.1	A mapping of performance monitoring interval number to per interval information. Interval numbers are integers starting from 0. Interval 0 is the interval in progress,Interval 1 is the most recently completed interval and so on.

2.618.1.1 InterfaceTransceiverPerformanceMonitoringInterval

[intervalStartTime]	*floating point number*	Time when this interval started in UTC.
[parameters]	*table(string) = Interface-TransceiverDomParameter* see 2.615.2.1	A mapping of performance monitoring parameter names to per channel value and thresholds in this interval.
[updateTime]	*floating point number*	Last update time in UTC.

2.619 show interfaces transceiver properties [...]

interfaces	*table(Interface name) = TransceiverProperties* see 2.619.1	Mapping between interface name and the transceiver properties.

2.619.1 TransceiverProperties

[adminSpeed]	*TransceiverSpeedLanes-Duplex* see 2.619.1.2	Administrative speed/lane count/duplex.
[mediaType]	*string*	Transceiver type.
[operSpeed]	*TransceiverSpeedLanes-Duplex* see 2.619.1.2	Operational speed/lane count/duplex.

[xcvrCapabilities]	*list of TransceiverCapabilities* see 2.619.1.1	Transceiver capabilities.

2.619.1.1 TransceiverCapabilities

[fecCapabilities] **	*errorCorrectionCapabilities* see 2.619.1.1.1	Transceiver default host error correction capabilities. **Since: 4.26.0
[speedCapabilities]	*EthSpeedLanesDuplex* see 2.545.1.1.1	Transceiver speed capabilities.

2.619.1.1.1 errorCorrectionCapabilities

[hostErrorCorrection]	*enum: fireCode* | *disabled* | *reedSolomon* | *unsupported*	Transceiver default host error correction.

2.619.1.2 TransceiverSpeedLanesDuplex

[autonegSuffix]	*enum: forced* | *autoNegotiated*	Speed forced or auto-negotiated.
[duplex]	*enum: full* | *half* | *autoDuplex* | *unconfigured* | *auto*	Duplex communication capabilities with this speed.
[laneCount]	*integer*	Number of lanes on the interface.
[speed]	*enum: 2p5Gbps* | *400Gbps* | *40Gbps* | *1p6Tbps* | *Hg21Gbps* | *autoSpeed* | *10Mbps* | *1Gbps* | *5Gbps* | *200Gbps* | *Hg11Gbps* | *Hg106Gbps* | *Hg27Gbps* | *100Gbps* | *10Gbps* | *20Gbps* | *Hg42Gbps* | *800Gbps* | *25Gbps* | *Hg53Gbps* | *Unknown* | *100Mbps* | *50Gbps* | *auto*	Interface speed.

2.620 show interfaces transceiver tuning [...]

[interfaces]	*table(Interface name) = InterfaceTransceiverTuning* see 2.620.1	Mapping between interface name and tuning info.

2.620.1 InterfaceTransceiverTuning

lane **	*string*	Transceiver host electrical lane number. **Since: 4.32.2
rxOutputAmplitude	*InterfaceTransceiverTuningParameter* see 2.620.1.1	RX Output Amplitude.
rxOutputPostEmphasis	*InterfaceTransceiverTuningParameter* see 2.620.1.1	RX Output Post-emphasis.

rxOutputPreEmphasis	*InterfaceTransceiver-TuningParameter* see 2.620.1.1	RX Output Pre-emphasis.
slot **	*string*	Transceiver slot number. **Since: 4.32.2
txInputEqualization	*InterfaceTransceiver-TuningParameter* see 2.620.1.1	TX Input Equalization.

2.620.1.1 InterfaceTransceiverTuningParameter

[detail]	*InterfaceTransceiver-TuningDetail* see 2.620.1.1.1	Detail output of module default and configured values.
[operational]	*string*	The tuning value currently programmed into the module.
supported	*boolean*	This tuning parameter is supported.

2.620.1.1.1 InterfaceTransceiverTuningDetail

[configured]	*string*	The user configured tuning value.
[moduleDefault]	*string*	The default tuning value of the module.

2.621 show interfaces trunk | (trunk (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD))))) [...]

trunks	*table(Interface name) = InterfaceTrunk* see 2.621.1	Mapping from an interface name to its' trunk information.

2.621.1 InterfaceTrunk

[activeVlans]	*TrunkVlans* see 2.621.1.1	Vlans allowed and active in management domain.
[activeVlansEgressOnly] **	*VlanIds* see 2.621.1.2	Vlans allowed and active in management domain, Only egress traffic allowed. **Since: 4.35.2
[allowedVlans]	*TrunkVlans* see 2.621.1.1	Vlans allowed on the trunk. No value means no information is available and array with one element of 0 means no vlans are allowed.
[forwardingVlans]	*TrunkVlans* see 2.621.1.1	Vlans in spannning tree forwarding state.
[linkStatus]	*enum: down | trunking | nonTrunking*	Trunk link status for the interface.
[nativeVlan]	*integer*	Native vlan of the trunk.
[phoneTrunk] **	*boolean*	Mode is 'trunk phone'. **Since: 4.23.1

[portMode]	*enum: access | dot1qTunnel | tool | tap | routed | tapTool | trunk*	Port mode of the trunk.

2.621.1.1 TrunkVlans

[allVlans]	*boolean*	When set it means all vlans 1-4094 in which case the vlanIds will be empty.
vlanIds	*list of integer*	A list of the VLAN Ids.

2.621.1.2 VlanIds

Could also be an instance of:
TrunkVlans 2.621.1.1

vlanIds	*list of integer*	A list of the VLAN Ids.

2.622 show interfaces unidirectional | (unidirectional (module (MODSLOT | (Supervisor MODSLOT_SUPERVISOR) | (Linecard MODSLOT_LINECARD) | (Fabric MODSLOT_FABRIC) | (Switchcard MODSLOT_SWITCHCARD)))) [...]

interfaces	*table(Interface name) = InterfaceUnidirectional* see 2.622.1	Mapping between an interface and its unidirectional link information.

2.622.1 InterfaceUnidirectional

status	*enum: inactive | connected | initializing | unknown | notapplicable | errdisabled | maint-down | adminIsolated | noSignal | uninitialized | no-resource | signal | admin | notconnect | disabled | autoIsolated*	Connection status of the interface.
uniLinkMode	*enum: send-only | n/a | send-receive | receive-only | disabled*	Current unidirectional link mode.

2.623 show interfaces vlans [...]

[interfaces]	*table(string) = InterfaceVlansModel* see 2.623.1	Map interfaces to VLANs.
[sourceDetail]	*string*	Description of the source of the VLAN configs.

2.623.1 InterfaceVlansModel

[taggedEgressOnlyVlans] **	*list of integer*	VLANs on the switchport that allow traffic to only egress. VLAN tagging is enabled. **Since: 4.35.2
[taggedVlans]	*list of integer*	Tagged VLANs for an interface.
[untaggedEgressOnlyVlans] **	*list of integer*	VLANs on the switchport that allow traffic to only egress. VLAN tagging is disabled. **Since: 4.35.2
[untaggedVlan]	*integer*	Untagged VLAN for an interface.

2.624 show internet-exit policy [...]

policyStatus	*list of SfeIePolicyStatusModel* see 2.624.1	SFE Internet exit policy status.

2.624.1 SfeIePolicyStatusModel

avtId	*integer*	AVT identifier.
avtName	*string*	AVT name.
exitGroups	*list of SfeIeExitGroupInPolicyModel* see 2.624.1.1	Exit groups configured for this policy.
policyName	*string*	Name of the policy.
vniId	*integer*	VNI identifier.
vrfName	*string*	VRF name.

2.624.1.1 SfeIeExitGroupInPolicyModel

exitGroup	*SfeIeExitGroupStatusModel* see 2.624.1.1.1	Exit group model.
isWinning	*boolean*	This is the winning exit group.

2.624.1.1.1 SfeIeExitGroupStatusModel

exitOption	*list of SfeIeExitOptionStatusModel* see 2.624.1.1.1.1	Collection of exit options under this exit group.
groupName	*string*	Name of the exit group.

2.624.1.1.1.1 SfeIeExitOptionStatusModel

[intf]	*string*	Result interface of the connection.
isActive	*boolean*	Exit option is active.
optionKey	*SfeIeExitKeyModel* see 2.624.1.1.1.2	Composite key of the exit option.
[vrf]	*string*	VRF of the result interface.

2.624.1.1.1.2 SfeIeExitKeyModel

name	*string*	Name of the exit.
type	*string*	Type of the exit.

2.625 show inventory

revision 4

[auxiliaryXcvrSlots]	*table(string) = XcvrSlot* see 2.625.8	Dictionary of Auxiliary Transceiver slots indexed by name.
cardSlots	*table(string) = CardSlot* see 2.625.1	Dictionary of Card slots, only present for modular systems.
cpuPortCount	*integer*	Total count of CPU ports.
dataLinkPortCount	*integer*	Total count of data link ports.
fabricPortCount	*integer*	Total count of Fabric front ports.
[fabricXcvrSlots]	*table(string) = XcvrSlot* see 2.625.8	Dictionary of Fabric Transceiver slots indexed by name.
fanTraySlots	*table(string) = FanTraySlot* see 2.625.3	Dictionary of fan tray slots.
fpgas	*table(string) = Fpga* see 2.625.4	Dictionary of fpgas indexed by fpga name.
frontPanelFabricPortCount	*integer*	Total count of Front Panel Fabric front ports.
internalPortCount	*integer*	Total count of Internal ports.
managementPortCount	*integer*	Total count of Management ports.
mgmtXcvrSlots	*table(string) = XcvrSlot* see 2.625.8	Dictionary of Transceiver slots indexed by name.
portCount	*integer*	Total count of ports.
powerSupplySlots	*table(string) = PowerSupplySlot* see 2.625.5	Dictionary of power supply slots.
[precisionClock]	*Clock* see 2.625.2	System Precision clock.
storageSerials	*table(string) = StorageDevice* see 2.625.6	Dictionary of Storage Devices indexed by Serial Number.
[subcompSerNums]	*table(string) = string*	Dictionary of subcomponent serial numbers.
switchManagementPortCount	*integer*	Total count of Switch management ports.
switchedBootstrapPortCount	*integer*	Total count of Switched/Bootstrap ports.
switchedFortyGOnlyPortCount	*integer*	Total count of Switched 40G Only ports.
switchedPortCount	*integer*	Total count of Switched ports.
systemInformation	*SystemInformation* see 2.625.7	System Information.
[unconnectedPortCount]	*integer*	Total count of unconnected ports.
xcvrSlots	*table(string) = XcvrSlot* see 2.625.8	Dictionary of Transceiver slots indexed by name.

2.625.1 CardSlot

hardwareRev	*string*	Hardware version of the card slot.
hwEpoch	*string*	Hardware Epoch.
mfgDate	*string*	Manufacture Date of the card slot (YYYY-MM-DD).
modelName	*string*	Model name of the card slot.
serialNum	*string*	Serial Number of the card slot.

2.625.2 Clock

2.625.3 FanTraySlot

name	*string*	Model name of the fan tray slot.
numFans	*integer*	Number of fans in the fan tray slot.
secondaryFans	*table(numeric string) = string*	Secondary fans, keyed by their slot number.
secondarySerialNum	*string*	Serial number for the fan tray slot on secondary card.
serialNum	*string*	Serial number for the fan tray slot.

2.625.4 Fpga

fpgaRev	*string*	Revision of the FPGA if present.

2.625.5 PowerSupplySlot

name	*string*	Model name of the power supply slot.
serialNum	*string*	Serial number for the power supply slot.

2.625.6 StorageDevice

firmwareRev	*string*	Firmware Revision of the Storage Device.
model	*string*	Model Name of the Storage Device.
mount	*string*	Mount Point of the Storage Device.
serialNum	*string*	Serial Number of the Storage Device.
storageSize	*integer*	Size in GB of the Storage Device.
storageType	*enum: unknown | SSD | NVME | eUSB | eMMC | SD*	Storage Type of the Storage Device.
[supervisor]	*integer*	The supervisor that this device is associated with.

2.625.7 SystemInformation

description	*string*	Model Description.
hardwareRev	*string*	Hardware Revision.
hwEpoch	*string*	Hardware Epoch.
mfgDate	*string*	Manufacture Date (YYYY-MM-DD).
name	*string*	Model name.
serialNum	*string*	Serial Number.

2.625.8 XcvrSlot

hardwareRev	*string*	Transceiver hardware revision number.
mfgName	*string*	Transceiver Manufacturer name.
modelName	*string*	Transceiver model name.

serialNum	*string*	Transceiver serial number.

2.626 show ip

[multicastRouting]	*IpMulticastRouting* see 2.626.1	IPv4 and IPv6 multicast routing information.
v4RoutingEnabled	*boolean*	IPv4 Routing is enabled.
[v4uRpfState]	*enum: enabled | errorDisabled | disabled*	State of IPv4 uRPF.
[v6EcmpInfo]	*V6EcmpModel* see 2.626.2	IPv6 ECMP Routing Information.
[v6IntfForwarding]	*boolean*	IPv6 interface forwarding is enabled.
v6RoutingEnabled	*boolean*	IPv6 Routing is enabled.
[v6uRpfState]	*enum: enabled | errorDisabled | disabled*	State of IPv6 uRPF.
[vrrpIntfs]	*integer*	Number of interfaces with VRRP configured.

2.626.1 IpMulticastRouting

[ip6MulticastEnabled]	*boolean*	IPv6 multicast routing is enabled.
[ipMulticastEnabled]	*boolean*	IPv4 multicast routing is enabled.

2.626.2 V6EcmpModel

[nextHopIndex]	*integer*	IPv6 ECMP route nexthop index.
[numPrefixBits]	*integer*	IPv6 ECMP route num prefix bits for nexthop index.
v6EcmpRouteSupport	*boolean*	IPv6 ECMP route is supported.

2.627 show ip access-lists [...]

see 2.76.1

2.628 show ip address virtual source-nat sourceNatAddr

vrfs	*table(string) = IPv4 address*	A mapping of VRF names to their source NAT IP address.

2.629 show ip arp inspection interface [...]

interfaceConfigs	*table(Interface name) = ArpInspectionInterfaceConfig* see 2.629.1	Interfaces with non-default configurations.

2.629.1 ArpInspectionInterfaceConfig

errdisableBurstInterval	*integer*	Consecutive interval in seconds over which the interface is monitored for disabling.
errdisableRateLimit	*integer*	Maximum number of Arp packets per second before the interface is disabled.
interfaceTrusted	*boolean*	Interface trusted with Arp traffic.
loggingBurstInterval	*integer*	Consecutive interval in seconds over which the interface is monitored for logging.
loggingRateLimit	*integer*	Maximum number of Arp packets per second before a log message is emitted.

2.630 show ip arp inspection statistics vlan | interface [...]

intfStatistics	*table(Interface name) = ArpInspectionStatistics* see 2.630.1	Arp inspection statistics for interfaces.
vlanStatistics	*table(numeric string) = VlanArpInspectionStatistics* see 2.630.3	Arp inspection statistics for vlans.

2.630.1 ArpInspectionStatistics

Could also be an instance of:
IntfArpInspectionStatistics 2.630.2
VlanArpInspectionStatistics 2.630.3

[lastDroppedPacket]	*ArpPacketBrief* see 2.630.1.1	The last Arp packet dropped.
requestsDropped	*integer*	Number of Arp requests dropped.
requestsForwarded	*integer*	Number of Arp requests forwarded.
responsesDropped	*integer*	Number of Arp responses dropped.
responsesForwarded	*integer*	Number of Arp responses forwarded.

2.630.1.1 ArpPacketBrief

arpOpcode	*enum: response | request | invalid*	Arp operation type.
destinationMac	*MAC address*	Destination Mac address.
[dropReason]	*enum: rateLimitExceeded | invalidBinding*	Drop reason of the Arp packet.
receivedInterfaceId	*interface name*	Interface Arp packet was received on.
receivedVlanId	*integer*	Vlan Arp packet was received on.
senderIp	*IPv4 address*	IPv4 address of the sender.
senderMac	*MAC address*	Mac address of the sender.
sourceMac	*MAC address*	Source Mac address.
timestamp	*floating point number*	Time packet was received.

2.630.2 IntfArpInspectionStatistics

intfId	*interface name*	Interface name.
[lastDroppedPacket]	*ArpPacketBrief* see 2.630.1.1	The last Arp packet dropped.
requestsDropped	*integer*	Number of Arp requests dropped.
requestsForwarded	*integer*	Number of Arp requests forwarded.
responsesDropped	*integer*	Number of Arp responses dropped.
responsesForwarded	*integer*	Number of Arp responses forwarded.

2.630.3 VlanArpInspectionStatistics

[lastDroppedPacket]	*ArpPacketBrief* see 2.630.1.1	The last Arp packet dropped.
name	*string*	Vlan name.

requestsDropped	*integer*	Number of Arp requests dropped.
requestsForwarded	*integer*	Number of Arp requests forwarded.
responsesDropped	*integer*	Number of Arp responses dropped.
responsesForwarded	*integer*	Number of Arp responses forwarded.
vlanId	*integer*	Vlan id.

2.631 show ip arp inspection vlan [...]

vlanStatus	*table(numeric string) = VlanArpInspectionStatus* see 2.631.1	VLANs with Arp inspection enabled on the switch.

2.631.1 VlanArpInspectionStatus

configuration	*boolean*	Arp Inspection enabled on this VLAN.
operationState	*boolean*	Arp Inspection operational state on this VLAN.

2.632 show ip as-path access-list NAME detail

activeIpAsPathLists	*table(string) = IpAsPathList* see 2.632.1	Active AS path lists under the current regex mode.
inactiveIpAsPathLists	*table(string) = IpAsPathList* see 2.632.1	Inactive AS path lists under the current regex mode.
regexMode	*enum: asn | string*	Regex mode.

2.632.1 IpAsPathList

ipAsPathEntries	*list of IpAsPathEntry* see 2.632.1.1	AS path entries.
[ipAsPathListSource] **	*string*	Source URL of the as-path access list. **Since: 4.20.0

2.632.1.1 IpAsPathEntry

filterType	*enum: deny | permit*	Filter type.
origin	*enum: bgpEGP | bgpAny | bgpIGP | bgpIncomplete*	Origin of path information.
userRegex	*string*	Regex describing AS path being filtered.
[valid] **	*boolean*	Entry validity given current regex mode for this as-path entry list. **Since: 4.20.5

2.633 show ip as-path access-list NAME summary

[accessListSource]	*string*	Access list source.
[entryCount]	*integer*	Access list entry count.
[sourceTimeStamp]	*floating point number*	Access list source timestamp.

2.634 show ip as-path access-list [...]

see 2.632

2.635 show ip bgp ((community regex COMMREGEX as-path regex ASPREGEX) | (regex ASPREGEX community regex COMMREGEX)) [...]

revision 3

see 2.20

2.636 show ip bgp (IP | PREFIX) [...]

revision 3

see 2.20

2.637 show ip bgp [...]

revision 3

see 2.20

2.638 show ip bgp access-list AS_PATH_LIST_NAME [...]

revision 3

see 2.20

2.639 show ip bgp community regex REGEX [...]

revision 3

see 2.20

2.640 show ip bgp field-set FSNAME [...]

revision 3

see 2.20

2.641 show ip bgp large-community { LARGE_COMM_VALUE } detail exact [...]

revision 3

see 2.20

2.642 show ip bgp neighbors [...]

revision 2

vrfs	*table(string) = BgpPeerList* see 2.642.1	Per Vrf BGP Peer Information.

2.642.1 BgpPeerList

peerList	*list of BgpPeer* see 2.642.1.1	Bgp Peer List.

2.642.1.1 BgpPeer

[advertisedCommunities] **	*CommunityTypesAdv* see 2.642.1.1.3	Types of communities advertised. **Since: 4.29.0
[advertisedLinkUserWeight] **	*integer*	Link user weight advertised. **Since: 4.34.2
[advertisedRestartTime]	*integer*	Advertised restart time.
[afiSafiInfo] **	*table(string) = PerAfiSafiInfo* see 2.642.1.1.14	A dictionary of address families. **Since: 4.27.2
[aigpSessionIpv4LabeledUni]	*boolean*	AIGP session for IPv4 Labelled Unicast.
[aigpSessionIpv4Uni]	*boolean*	AIGP session for IPv4 Unicast.
[aigpSessionIpv6LabeledUni]	*boolean*	AIGP session for IPv6 Labelled Unicast.
[aigpSessionIpv6Uni]	*boolean*	AIGP session for IPv6 Unicast.
[ancestorPeerGroups] **	*list of string*	Ancestor peer group list. **Since: 4.29.1
[as4]	*integer*	AS.
asn	*string*	Autonomous system number.
[autoLocalAddress]	*string*	Auto local address.
[bfdDampingMaxTime]	*integer*	BFD flap damping max time.
[bfdDampingTime]	*integer*	BFD current flap damping time.
[bfdDampingTimeLeft]	*floating point number*	BFD flap damping time left.
[bfdMinRx] **	*integer*	BFD receive rate in milliseconds. **Since: 4.28.2
[bfdMinTx] **	*integer*	BFD transmit rate in milliseconds. **Since: 4.28.2
[bfdMult] **	*integer*	BFD multiplier value. **Since: 4.28.2
[bfdSessionState]	*enum: unknown | down | up | init | adminDown*	BFD session state when BFD is enabled.
[bfdState]	*integer*	BFD state.
[bgpPeerCaps]	*integer*	BGP capabilities sent by us.
[bgpPeerFlags]	*list of integer*	BGP peer flag list.
[bgpPeerHiscaps]	*integer*	BGP capabilities received from peer.
[bgpPeerOptions]	*integer*	BGP peer options.
[bgpPeerOptions2]	*integer*	BGP peer options 2.
[bgpPeerOptions3]	*integer*	BGP peer options 3.
bgpSoftReconfigInbound	*enum: All | None | Default*	Which inbound routes that are not accepted to retain for soft reconfig.

[clientReflectionMode]	*enum: meshed | clientToClientDisabled*	Route reflector mode.
[clusterId] **	*IPv4 address*	Cluster ID in use by this peer. **Since: 4.29.0
[confHoldTime]	*integer*	Configured hold time.
[confRemotePort]	*integer*	Configured remote port.
[configHoldTime]	*integer*	Configured hold time (multi-agent mode).
[configIdleHoldTime]	*integer*	Configured idle hold time.
[configKeepaliveTime]	*integer*	Configured keepalive time (multi-agent mode).
[configMinHoldTime] **	*integer*	Configured minimum hold time in seconds. **Since: 4.29.0
[configRestartTime]	*integer*	Configured restart time (multi-agent mode).
[configuredKeepaliveTime]	*integer*	Configured keepalive time.
[connectFailed]	*integer*	Failed connection attempts.
[connectInterval]	*integer*	Connection interval.
[connectTimeLeft]	*integer*	Connection time left.
[connectTimerActive]	*boolean*	Connect timer is active.
[description]	*string*	Description.
[dpsBestEcmpPaths]	*integer*	Dynamic Path Selection best ECMP paths received.
[dpsBestPaths]	*integer*	Dynamic Path Selection best paths received.
[dpsPrefixesReceived]	*integer*	Dynamic Path Selection prefixes received.
[dpsPrefixesSent]	*integer*	Dynamic Path Selection prefixes sent.
[dropStats]	*PeerDropStats* see 2.642.1.1.13	Prefix drop statistics.
[enRRefreshstalePath-Removal] **	*boolean*	Enhanced route refresh stale path removal enabled. **Since: 4.30.0
[endOfRibTimeLeft]	*integer*	End of rib time left.
[endOfRibs] **	*EndOfRibs* see 2.642.1.1.4	EOR Information for all negotiated AfiSafi(s). **Since: 4.28.2
[eorTimerActive]	*boolean*	End-of-Rib timer is active.
[establishFailHint]	*string*	Establish failure hint.
[establishedTime]	*integer*	Established time.
[establishedTransitions]	*integer*	Established transitions.
[evpnBestEcmpPaths]	*integer*	Evpn best ECMP paths received.
[evpnBestPaths]	*integer*	Evpn best paths received.
[evpnReceived]	*integer*	Ethernet VPN prefixes received.
[evpnSent]	*integer*	Ethernet VPN prefixes sent.
[fallbackLinkUserWeight-Used] **	*boolean*	Link user fallback weight used. **Since: 4.34.2
[fwdFailoverTriggerSession-Ipv4Uni] **	*boolean*	Forwarding Failover Trigger Session for IPv4 Unicast. **Since: 4.28.2

[fwdFailoverTriggerSession-Ipv6Uni] **	*boolean*	Forwarding Failover Trigger Session for IPv6 Unicast. **Since: 4.28.2
[grRestartTimeLeft]	*integer*	Restart time left (multi-agent mode).
[grStalePolicies] **	*GrHelperStalePolicies* see 2.642.1.1.6	Graceful Restart stale policy information per Afi/Safi. **Since: 4.30.0
[gracefulRestartTimer-Active]	*boolean*	Graceful Restart timer is active.
[holdTime]	*integer*	Hold time.
[holdTimeLeft]	*integer*	Hold time left.
[idleHoldTimeLeft]	*integer*	Idle hold time left.
[idleReason]	*string*	Idle reason if session state is idle.
[idleRestartTimerActive]	*boolean*	Idle restart timer active.
[ifName]	*string*	Interface name.
[inMessageStats]	*MessageStatInfo* see 2.642.1.1.9	Input message statistics.
[inboundUpdateProcessing-Delay] **	*integer*	Inbound update processing delay in seconds. **Since: 4.32.1
[inboundUpdateProcessing-DelayLeft] **	*integer*	Inbound update processing delay time left in seconds. **Since: 4.32.1
[inboundUpdateProcessing-DelayState] **	*string*	Inbound update processing delay state. **Since: 4.32.1
[inboundUpdateProcessing-DelayStateDetail] **	*string*	Inbound update processing delay state detail. **Since: 4.33.2
[invalidNextHopDirectEbgp]	*boolean*	Nexthop invalid for single hop EBGP.
[keepaliveTime]	*integer*	Keepalive time.
[keepaliveTimeLeft]	*integer*	Keepalive time left.
[lastErrorCode]	*string*	Last send error code.
[lastErrorData]	*string*	Last send error data.
[lastErrorRcvdCode]	*string*	Last receive error code.
[lastErrorRcvdData]	*string*	Last receive error data.
[lastErrorRcvdSubcode]	*string*	Last receive error subcode.
[lastErrorRcvdTimeInfo]	*ErrorTimeInfo* see 2.642.1.1.5	Last receive error time information.
[lastErrorSubcode]	*string*	Last send error subcode.
[lastErrorTimeInfo]	*ErrorTimeInfo* see 2.642.1.1.5	Last send error time information.
[lastEvent]	*string*	Last BGP event.
[lastRcvd]	*integer*	Last received.
[lastSent]	*integer*	Last sent.
[lastSocketInErrorMsg]	*string*	Last socket in error message.
[lastSocketInErrorTimeInfo]	*ErrorTimeInfo* see 2.642.1.1.5	Last socket in error time information.
[lastSocketOutErrorMsg]	*string*	Last socket out error message.
[lastSocketOutErrorTime-Info]	*ErrorTimeInfo* see 2.642.1.1.5	Last socket out error time information.
[lastState]	*string*	Last BGP state.

[linkStateBestEcmpPaths]	*integer*	Link State best ECMP paths.
[linkStateBestPaths]	*integer*	Link State best paths received.
[linkStatePeerNodeSegment] **	*LinkStatePeerSegment* see 2.642.1.1.7	BGP link-state peer node segment. **Since: 4.32.2
[linkStateReceived]	*integer*	Link State NLRIs received.
[linkStateSent]	*integer*	Link State NLRIs sent.
linkType	*string*	Link type.
[lldpNeighbors] **	*list of LldpNeighbor* see 2.642.1.1.8	LLDP Neighbors list. **Since: 4.27.2
[llgrTimers] **	*table(string) = integer*	Long lived graceful restart stale path timers per received Afi/Safi. **Since: 4.29.0
[localAddressPort]	*integer*	Local address port.
[localAddressV4]	*IP address*	Local IPv4 address.
[localAddressV6]	*IP address*	Local IPv6 address.
localAsn	*string*	Local autonomous system number.
[localNexthopInterfaces-MissingV4Addr] **	*list of string*	Local next hop interfaces missing IPv4 address. **Since: 4.34.1
[localNexthopInterfaces-MissingV6Addr] **	*list of string*	Local next hop interfaces missing IPv6 address. **Since: 4.34.1
[localPort]	*integer*	Local port.
localRouterId	*IPv4 address*	Local router ID.
[maintenance]	*boolean*	Peering under maintenance.
[maintenanceRcf] **	*string*	Maintenance mode RCF. **Since: 4.34.0
[maintenanceRcfIn] **	*string*	Maintenance mode inbound RCF. **Since: 4.34.0
[maintenanceRcfOut] **	*string*	Maintenance mode outbound RCF. **Since: 4.34.0
[maintenanceRm]	*string*	Maintenance mode route map.
[maintenanceRmIn]	*string*	Maintenance mode inbound route map.
[maintenanceRmOut]	*string*	Maintenance mode outbound route map.
[maxTotalAcceptedRoutes] **	*integer*	Maximum number of accepted routes (0 means unlimited). **Since: 4.28.1
[maxTotalRoutes] **	*integer*	Maximum number of received routes (0 means unlimited). **Since: 4.28.1
maxTtlHops	*integer*	Maximum hops allowed for BGP neighbor.
[md5AuthEnabled]	*boolean*	MD5 authentication is enabled.
[minHoldTime] **	*integer*	Minimum hold time in seconds. **Since: 4.29.0
[miscFlags]	*integer*	BGP miscellaneous flags.
[missingPolicy]	*MissingPolicyTypes* see 2.642.1.1.11	Import/Export missing policies per AFI/SAFI.
[missingPolicyDefaultDeny]	*MissingPolicyDefaultDeny* see 2.642.1.1.10	Missing policy/default deny status.
negotiatedVersion	*integer*	Negotiated BGP version.

[neighborCapabilities]	*NeighborCapabilities* see 2.642.1.1.12	BGP neighbor capabilities.
[nexthopLuOriginateIpv4Uni]	*boolean*	Next hop labeled unicast origination for IPv4 Unicast.
[nexthopLuOriginateIpv6Uni]	*boolean*	Next hop labeled unicast origination for IPv6 Unicast.
[nexthopLuOriginateLfib-BackupIpForwardIpv4Uni]	*boolean*	Next hop labeled unicast origination LFIB backup IP forwarding for IPv4 Unicast.
[nexthopLuOriginateLfib-BackupIpForwardIpv6Uni]	*boolean*	Next hop labeled unicast origination LFIB backup IP forwarding for IPv6 Unicast.
[noComms]	*boolean*	Send no communities.
[noComs]	*boolean*	Send no communities(multi-agent mode).
[orrPosition]	*table(string) = BgpOrrPosition* see 2.239.1	BGP optimal route reflection position per address-family.
[outMessageStats]	*MessageStatInfo* see 2.642.1.1.9	Output message statistics.
[outboundEnRRefreshEnabled] **	*boolean*	Outbound enhanced route refresh enabled. **Since: 4.30.0
[passiveConnEnabled]	*boolean*	Passive TCP connection mode is enabled.
peerAddress	*string*	Peer address.
[peerFilter]	*string*	Peer filter name.
[peerGroup]	*string*	Peer group name.
[peerGroupName]	*string*	Peer group name (multi-agent mode).
[peerInUpdateErrors]	*BgpPeerInUpdateErrors* see 2.642.1.1.1	Peer inbound update errors.
[peerTcpInfo]	*BgpPeerTcpInfo* see 2.642.1.1.2	Peer TCP information.
[prefixListInfo]	*RouteFilterInfo* see 2.642.1.1.16	Neighbor prefix list information.
[prefixesReceived]	*integer*	IPv4 unicast prefixes received.
[prefixesSent]	*integer*	IPv4 unicast prefixes sent.
[prependOwnDisabled]	*boolean*	Do not prepend own AS number.
[rcfInbound]	*string*	Rcf inbound.
[rcfInfo]	*RouteFilterInfo* see 2.642.1.1.16	Neighbor RCF information (supersedes route map).
[rcfOutbound]	*string*	Rcf outbound.
[receivedMessages]	*integer*	Received messages.
[receivedUpdates]	*integer*	Received updates.
[rejectAsSetConfedSetV4Uni] **	*boolean*	Treat-as-withdraw IPv4 Unicast AS path with AS_SET or AS_CONFED_SET. **Since: 4.32.2
[rejectAsSetConfedSetV6Uni] **	*boolean*	Treat-as-withdraw IPv6 Unicast AS path with AS_SET or AS_CONFED_SET. **Since: 4.32.2
[remoteAddrPort]	*integer*	Remote address port.
[remoteAddressV4]	*IP address*	Remote IPv4 address.
[remoteAddressV6]	*IP address*	Remote IPv6 address.
[remotePort]	*integer*	Remote port.

[removeOrReplacePrivateAs-Egress]	*enum: removePrivateAsEgressAll* | *removePrivateAsEgress* | *removePrivateAsEgress-Replace*	From outbound updates to this neighbor: removePrivateAsEgress - Remove private AS numbers when there are only private AS numbers in inbound/outbound AS path lists. removePrivateAsEgressAll - Always remove private AS numbers in outbound AS path lists. removePrivateAsEgressReplace - Replace private AS numbers with the local AS number in outbound AS path lists.
[removeOrReplacePrivateAs-Ingress]	*enum: removePrivateAsIngressReplace* | *removePrivateAsIngress*	From inbound updates to this neighbor: removePrivateAsIngress - Always remove private AS numbers in inbound AS path lists. removePrivateAsIngressReplace - Replace private AS numbers with the local AS number in inbound AS path lists.
[restart]	*integer*	Received restart time.
[restartTimeLeft]	*integer*	Restart time left.
[rfdPolicyInfo] **	*RfdPolicyInfo* see 2.642.1.1.15	Neighbor route flap damping information for AFI/SAFI. **Since: 4.31.0
[routeMapInbound]	*string*	Route map inbound (overridden if RCF is configured).
[routeMapInboundDefined] **	*boolean*	Inbound route-map is defined. **Since: 4.32.2
[routeMapInfo]	*RouteMapFilterInfo* see 2.642.1.1.17	Neighbor route map information.
[routeMapOutbound]	*string*	Route map outbound (overridden if RCF is configured).
[routeMapOutboundDefined] **	*boolean*	Outbound route-map is defined. **Since: 4.32.2
[routeReflectorClient]	*boolean*	Neighbor is a route reflector client.
routerId	*IPv4 address*	BGP router identity.
[rpkiIpv4OvInvalidPaths] **	*integer*	Paths with invalid origin validation for IPv4 Unicast. **Since: 4.31.0
[rpkiIpv4OvUnknownPaths] **	*integer*	Paths with unknown origin validation for IPv4 Unicast. **Since: 4.31.0
[rpkiIpv4OvValidPaths] **	*integer*	Paths with valid origin validation for IPv4 Unicast. **Since: 4.31.0
[rpkiIpv6OvInvalidPaths] **	*integer*	Paths with invalid origin validation for IPv6 Unicast. **Since: 4.31.0
[rpkiIpv6OvUnknownPaths] **	*integer*	Paths with unknown origin validation for IPv6 Unicast. **Since: 4.31.0
[rpkiIpv6OvValidPaths] **	*integer*	Paths with valid origin validation for IPv6 Unicast. **Since: 4.31.0
[rpkiOriginValidation-Method]	*enum: community* | *disabled* | *local* | *preferCommunity*	Method used for validating prefix origin AS.

[rpkiOriginValidationRoute-Map]	*string*	Route map to filter which prefixes should be validated.
[rpkiOriginValidationSend-ExtComm]	*boolean*	Attach an extended community carrying the prefix origin validity.
[rpkiOriginValidationWait-ForRoaSync] **	*boolean*	Origin validation waits for ROA syncing from cache servers. **Since: 4.33.2
[rtMembershipBestEcmpPaths]	*integer*	RT Membership best ECMP paths.
[rtMembershipBestPaths]	*integer*	RT Membership best paths.
[rtMembershipPrefixes-Received]	*integer*	RT Membership prefixes received.
[rtMembershipPrefixesSent]	*integer*	RT Membership prefixes sent.
[sendFailureHoldTime] **	*integer*	Send failure hold time in seconds. **Since: 4.31.1
[sentMessages]	*integer*	Sent messages.
[sentUpdates]	*integer*	Sent updates.
[stalePathRemovalTimer]	*table(string) = integer*	Inbound enhanced route refresh stale path removal timer per negotiated Afi/Safi.
[state]	*string*	BGP state.
[tcpAoInfo] **	*TcpAoInfo* see 2.642.1.1.18	TCP-AO information. **Since: 4.28.1
[thirdPartyNexthopLu-OriginateIpv4Uni]	*boolean*	Next hop labeled unicast origination for received IPv4 Unicast nexthops.
[thirdPartyNexthopLu-OriginateIpv6Uni]	*boolean*	Next hop labeled unicast origination for received IPv6 Unicast nexthops.
[totalAcceptedRoutesWarn-Limit] **	*integer*	Number of accepted routes after which a warning is issued (0 means never warn). **Since: 4.28.1
[totalRoutesWarnLimit] **	*integer*	Number of received routes after which a warning is issued (0 means never warn). **Since: 4.28.1
ttl	*integer*	TTL value for peer connections.
[ttlConfig]	*enum: gtsm | ebgpMultiHop*	TTL max hops configuration mode.
updateGroupIndex	*integer*	Update group index.
[updateSource]	*IP address*	Local TCP address.
[updownTime]	*integer*	Up down time.
[usesGlobalClusterId] **	*boolean*	This peer is using the global cluster ID. **Since: 4.29.0
[v4BestEcmpPaths]	*integer*	IPv4 best ECMP paths received.
[v4BestPaths]	*integer*	IPv4 best paths received.
[v4FlowspecBestEcmpPaths]	*integer*	IPv4 Flow Specification best ECMP paths received.
[v4FlowspecBestPaths]	*integer*	IPv4 Flow Specification best paths received.
[v4FlowspecReceived]	*integer*	IPv4 Flow Specification rules received.
[v4FlowspecSent]	*integer*	IPv4 Flow Specification rules sent.
[v4FlowspecVpnBestEcmp-Paths] **	*integer*	VPN-IPv4 Flow Specification best ECMP paths received. **Since: 4.31.0
[v4FlowspecVpnBestPaths] **	*integer*	VPN-IPv4 Flow Specification best paths received. **Since: 4.31.0

[v4FlowspecVpnReceived] **	*integer*	VPN-IPv4 Flow Specification rules received. **Since: 4.31.0
[v4FlowspecVpnSent] **	*integer*	VPN-IPv4 Flow Specification rules sent. **Since: 4.31.0
[v4LuBestEcmpPaths]	*integer*	IPv4 LU best ECMP paths received.
[v4LuBestPaths]	*integer*	IPv4 LU best paths received.
[v4LuPrefixesReceived]	*integer*	IPv4 LU prefixes received.
[v4LuPrefixesSent]	*integer*	IPv4 LU prefixes sent.
[v4MappedV6NextHop-TranslationIPv6LabeledUni] **	*boolean*	Next hop resolution translates IPv4 mapped IPv6 nexthop addresses to IPv4 addresses for IPv6 with MPLS Labels. **Since: 4.27.2
[v4MplsVpnBestEcmpPaths]	*integer*	IPv4 MPLS VPN best ECMP paths received.
[v4MplsVpnBestPaths]	*integer*	IPv4 MPLS VPN best paths received.
[v4MplsVpnPrefixesReceived]	*integer*	IPv4 MPLS VPN prefixes received.
[v4MplsVpnPrefixesSent]	*integer*	IPv4 MPLS VPN prefixes sent.
[v4MulticastBestEcmpPaths]	*integer*	IPv4 Multicast best ECMP paths received.
[v4MulticastBestPaths]	*integer*	IPv4 Multicast best paths received.
[v4MulticastReceived]	*integer*	IPv4 Multicast prefixes received.
[v4MulticastSent]	*integer*	IPv4 Multicast prefixes sent.
[v4RfdMaxPathsSuppressed-Last24Hours] **	*integer*	Peak IPv4 unicast paths suppressed due to route flap damping in the last 24 hours. **Since: 4.30.2
[v4RfdPathSuppressions-Last24Hours] **	*integer*	IPv4 unicast path suppression events due to route flap damping in the last 24 hours. **Since: 4.30.2
[v4RfdPathsSuppressed] **	*integer*	IPv4 unicast paths currently suppressed due to route flap damping. **Since: 4.30.2
[v4RfdSuppressionsSince-Tracking] **	*integer*	Lifetime IPv4 unicast path suppression events due to route flap damping. **Since: 4.30.2
[v4SrTeBestEcmpPaths]	*integer*	IPv4 segment routing traffic engineering best ECMP paths received.
[v4SrTeBestPaths]	*integer*	IPv4 segment routing traffic engineering best paths received.
[v4SrTePrefixesReceived]	*integer*	IPv4 segment routing traffic engineering policies received.
[v4SrTePrefixesSent]	*integer*	IPv4 segment routing traffic engineering policies sent.
[v4gateway]	*IP address*	IPv4 gateway address.
[v6BestEcmpPaths]	*integer*	IPv6 best ECMP paths received.
[v6BestPaths]	*integer*	IPv6 best paths received.
[v6FlowspecBestEcmpPaths]	*integer*	IPv6 Flow Specification best ECMP paths received.
[v6FlowspecBestPaths]	*integer*	IPv6 Flow Specification best paths received.
[v6FlowspecReceived]	*integer*	IPv6 Flow Specification rules received.
[v6FlowspecSent]	*integer*	IPv6 Flow Specification rules sent.

[v6FlowspecVpnBestEcmp-Paths] **	*integer*	VPN-IPv6 Flow Specification best ECMP paths received. **Since: 4.31.0
[v6FlowspecVpnBestPaths] **	*integer*	VPN-IPv6 Flow Specification best paths received. **Since: 4.31.0
[v6FlowspecVpnReceived] **	*integer*	VPN-IPv6 Flow Specification rules received. **Since: 4.31.0
[v6FlowspecVpnSent] **	*integer*	VPN-IPv6 Flow Specification rules sent. **Since: 4.31.0
[v6LuBestEcmpPaths]	*integer*	IPv6 LU best ECMP paths received.
[v6LuBestPaths]	*integer*	IPv6 LU best paths received.
[v6LuPrefixesReceived]	*integer*	IPv6 LU prefixes received.
[v6LuPrefixesSent]	*integer*	IPv6 LU prefixes sent.
[v6MplsVpnBestEcmpPaths]	*integer*	IPv6 MPLS VPN best ECMP paths received.
[v6MplsVpnBestPaths]	*integer*	IPv6 MPLS VPN best paths received.
[v6MplsVpnPrefixesReceived]	*integer*	IPv6 MPLS VPN prefixes received.
[v6MplsVpnPrefixesSent]	*integer*	IPv6 MPLS VPN prefixes sent.
[v6MulticastBestEcmpPaths]	*integer*	IPv6 Multicast best ECMP paths received.
[v6MulticastBestPaths]	*integer*	IPv6 Multicast best paths received.
[v6MulticastReceived]	*integer*	IPv6 Multicast prefixes received.
[v6MulticastSent]	*integer*	IPv6 Multicast prefixes sent.
[v6PrefixesReceived]	*integer*	IPv6 Unicast prefixes received.
[v6PrefixesSent]	*integer*	IPv6 Unicast prefixes sent.
[v6RfdMaxPathsSuppressed-Last24Hours] **	*integer*	Peak IPv6 unicast paths suppressed due to route flap damping in the last 24 hours. **Since: 4.30.2
[v6RfdPathSuppressions-Last24Hours] **	*integer*	IPv6 unicast path suppression events due to route flap damping in the last 24 hours. **Since: 4.30.2
[v6RfdPathsSuppressed] **	*integer*	IPv6 unicast paths currently suppressed due to route flap damping. **Since: 4.30.2
[v6RfdSuppressionsSince-Tracking] **	*integer*	Lifetime IPv6 unicast path suppression events due to route flap damping. **Since: 4.30.2
[v6SixPeBestEcmpPaths]	*integer*	IPv6 provider edge (6PE) best ECMP paths received.
[v6SixPeBestPaths]	*integer*	IPv6 provider edge (6PE) best paths received.
[v6SixPePrefixesReceived]	*integer*	IPv6 provider edge (6PE) prefixes received.
[v6SixPePrefixesSent]	*integer*	IPv6 provider edge (6PE) prefixes sent.
[v6SrTeBestEcmpPaths]	*integer*	IPv6 segment routing traffic engineering best ECMP paths received.
[v6SrTeBestPaths]	*integer*	IPv6 segment routing traffic engineering best paths received.
[v6SrTePrefixesReceived]	*integer*	IPv6 segment routing traffic engineering policies received.

[v6SrTePrefixesSent]	*integer*	IPv6 segment routing traffic engineering policies sent.
[v6gateway]	*IP address*	IPv6 gateway address.
version	*integer*	BGP version.
[vplsBestEcmpPaths] **	*integer*	VPLS best ECMP paths received. **Since: 4.28.1
[vplsBestPaths] **	*integer*	VPLS best paths received. **Since: 4.28.1
[vplsReceived] **	*integer*	VPLS prefixes received. **Since: 4.28.1
[vplsSent] **	*integer*	VPLS prefixes sent. **Since: 4.28.1
vrf	*string*	Vrf.

2.642.1.1.1 BgpPeerInUpdateErrors

[disableAfiSafiAttr]	*string*	last attribute resulting in AFI/SAFI disable.
[disabledAfiSafi]	*string*	disabled AFI/SAFI.
[ignoreAttr]	*string*	last attribute resulting in ignore.
[inUpdErrDisableAfiSafi]	*integer*	in updates disabling AFI/SAFI.
[inUpdErrIgnore]	*integer*	in updates ignored attributes.
[inUpdErrWithdraw]	*integer*	in updates treated as withdraw.
[lastUpdErrTime]	*integer*	last time of Update inbound error.
[withdrawAttr]	*string*	last attribute resulting in withdraw.

2.642.1.1.2 BgpPeerTcpInfo

congestionWindow	*integer*	TCP send congestion window.
[connectionOptions]	*TcpConnOptions* see 2.642.1.1.2.1	TCP socket optional settings.
delayedAckTimeout	*integer*	TCP socket delayed ACK timeout (microseconds).
inputMaxQueueLength	*integer*	TCP input queue max length.
inputQueueLength	*integer*	TCP input queue length.
maxSegmentSize	*integer*	TCP outgoing maximum segment size.
options	*integer*	TCP socket options.
outputMaxQueueLength	*integer*	TCP output queue max length.
outputQueueLength	*integer*	TCP output queue length.
rcvRtt	*integer*	TCP receive round-trip time (microseconds).
rcvWindow	*integer*	TCP advertised receive window.
rcvWindowScale	*integer*	TCP socket receive window scale.
retransTimeout	*integer*	TCP socket retransmission timeout (microseconds).
sendWindowScale	*integer*	TCP socket send window scale.
slowStartThreshold	*integer*	TCP send slow start size threshold.
sndRtt	*integer*	TCP round-trip time (microseconds).
sndRttVariance	*integer*	TCP round-trip time variance (microseconds).

state	*enum: CLOSED* | *TIME-WAIT* | *CLOSE-WAIT* | *FIN-WAIT-1* | *SYN-RECEIVED* | *ESTABLISHED* | *LISTEN* | *SYN-SENT* | *NOTUSED* | *CLOSING* | *FIN-WAIT-2* | *LAST-ACK*	TCP socket state.
totalRetrans	*integer*	Total number of TCP retransmissions.

2.642.1.1.2.1 TcpConnOptions

ecnEnabled	*boolean*	Explicit Congestion Notification (ECN) is enabled.
selectiveAcknowledgements-Enabled	*boolean*	Selective Acknowledgments are enabled.
timestampsEnabled	*boolean*	Timestamps are enabled.
windowScaleEnabled	*boolean*	Window Scale is enabled.

2.642.1.1.3 CommunityTypesAdv

extended	*boolean*	Extended community advertised.
large	*boolean*	Large community advertised.
standard	*boolean*	Standard community advertised.

2.642.1.1.4 EndOfRibs

[incoming]	*EndOfRib* see 2.642.1.1.4.1	Incoming EOR Information.

2.642.1.1.4.1 EndOfRib

[dps]	*EndOfRibInfo* see 2.642.1.1.4.2	Dynamic Path Selection EOR Information.
[ipv4FlowSpec]	*EndOfRibInfo* see 2.642.1.1.4.2	IPv4 flow specification EOR Information.
[ipv4FlowSpecVpn] **	*EndOfRibInfo* see 2.642.1.1.4.2	VPN-IPv4 flow specification EOR Information. **Since: 4.30.0
[ipv4MplsLabels]	*EndOfRibInfo* see 2.642.1.1.4.2	IPv4 labeled-unicast EOR Information.
[ipv4MplsVpn]	*EndOfRibInfo* see 2.642.1.1.4.2	VPN-IPv4 EOR Information.
[ipv4Multicast]	*EndOfRibInfo* see 2.642.1.1.4.2	IPv4 multicast EOR Information.
[ipv4Mvpn]	*EndOfRibInfo* see 2.642.1.1.4.2	IPv4 MVPN EOR Information.
[ipv4SrTe]	*EndOfRibInfo* see 2.642.1.1.4.2	IPv4 SR-TE EOR Information.

[ipv4Unicast]	*EndOfRibInfo* see 2.642.1.1.4.2	IPv4 unicast EOR Information.
[ipv6FlowSpec]	*EndOfRibInfo* see 2.642.1.1.4.2	IPv6 flow specification EOR Information.
[ipv6FlowSpecVpn] **	*EndOfRibInfo* see 2.642.1.1.4.2	VPN-IPv6 flow specification EOR Information. **Since: 4.30.0
[ipv6MplsLabels]	*EndOfRibInfo* see 2.642.1.1.4.2	IPv6 labeled-unicast EOR Information.
[ipv6MplsVpn]	*EndOfRibInfo* see 2.642.1.1.4.2	VPN-IPv6 EOR Information.
[ipv6Multicast]	*EndOfRibInfo* see 2.642.1.1.4.2	IPv6 multicast EOR Information.
[ipv6SrTe]	*EndOfRibInfo* see 2.642.1.1.4.2	IPv6 SR-TE EOR Information.
[ipv6Unicast]	*EndOfRibInfo* see 2.642.1.1.4.2	IPv6 unicast EOR Information.
[l2VpnEvpn]	*EndOfRibInfo* see 2.642.1.1.4.2	L2VPN EVPN EOR Information.
[l2VpnVpls]	*EndOfRibInfo* see 2.642.1.1.4.2	L2VPN VPLS EOR Information.
[linkState]	*EndOfRibInfo* see 2.642.1.1.4.2	BGP Link State EOR Information.
[rtMembership]	*EndOfRibInfo* see 2.642.1.1.4.2	RT Membership EOR Information.

2.642.1.1.4.2 EndOfRibInfo

[eorReceivedTime]	*floating point number*	UTC time at which EOR was received.
[pathsReceivedBeforeEor] **	*integer*	Number of paths received before EOR. **Since: 4.31.2
[stalePathsDeleted]	*integer*	Number of stale paths deleted after graceful restart.
status	*enum: pending | timeout | received*	Status of the EOR.

2.642.1.1.5 ErrorTimeInfo

[firstTime]	*integer*	Time at which last error occurred for the first time.
[repeats]	*integer*	Number of times last error repeated.
[time]	*integer*	Time at which last error occurred.

2.642.1.1.6 GrHelperStalePolicies

[dps] **	*GrHelperStalePolicy* see 2.642.1.1.6.1	DPS stale policy information. **Since: 4.32.2
[ipv4MplsLabels]	*GrHelperStalePolicy* see 2.642.1.1.6.1	IPv4 Labeled Unicast stale policy information.
[ipv4SrTe] **	*GrHelperStalePolicy* see 2.642.1.1.6.1	IPv4 SrTe stale policy information. **Since: 4.32.2

[ipv4Unicast]	*GrHelperStalePolicy* see 2.642.1.1.6.1	IPv4 Unicast stale policy information.
[ipv6MplsLabels]	*GrHelperStalePolicy* see 2.642.1.1.6.1	IPv6 Labeled Unicast stale policy information.
[ipv6Unicast]	*GrHelperStalePolicy* see 2.642.1.1.6.1	IPv6 Unicast stale policy information.
[l2VpnEvpn] **	*GrHelperStalePolicy* see 2.642.1.1.6.1	EVPN stale policy information. **Since: 4.32.2
[linkState] **	*GrHelperStalePolicy* see 2.642.1.1.6.1	Link State stale policy information. **Since: 4.33.0

2.642.1.1.6.1 GrHelperStalePolicy

[grOptional]	*boolean*	Graceful Restart negotiation is optional.
[staleRmName]	*string*	AFI/SAFI stale policy route map.

2.642.1.1.7 LinkStatePeerSegment

sid	*integer*	The SID value.

2.642.1.1.8 LldpNeighbor

[description]	*string*	LLDP Neighbor system description.
device	*string*	LLDP Neighbor system name.

2.642.1.1.9 MessageStatInfo

[beginOfRtRefreshes]	*integer*	Beginning of Route Refreshes.
[endOfRtRefreshes]	*integer*	End of Route Refreshes.
[keepalives]	*integer*	Keepalives.
[notifications]	*integer*	Notifications.
[opens]	*integer*	Opens.
[queueDepth]	*integer*	Queue Depth.
[rtRefreshes]	*integer*	Route Refreshes.
[updates]	*integer*	Updates.

2.642.1.1.10 MissingPolicyDefaultDeny

[exportActive]	*boolean*	Missing policy/default deny export action is active.
[importActive]	*boolean*	Missing policy/default deny import action is active.

2.642.1.1.11 MissingPolicyTypes

[exportPolicy]	*MissingPolicy* see 2.642.1.1.11.1	AFI/SAFI import missing policy actions.

[importPolicy]	*MissingPolicy* see 2.642.1.1.11.1	AFI/SAFI export missing policy actions.

2.642.1.1.11.1 MissingPolicy

[dps]	*MissingPolicyState* see 2.642.1.1.11.2	Dynamic Path Selection missing policy action.
[ipv4FlowSpec]	*MissingPolicyState* see 2.642.1.1.11.2	IPv4 flow specification missing policy action.
[ipv4FlowSpecVpn] **	*MissingPolicyState* see 2.642.1.1.11.2	VPN-IPv4 flow specification missing policy action. **Since: 4.30.0
[ipv4MplsLabels]	*MissingPolicyState* see 2.642.1.1.11.2	IPv4 labeled-unicast missing policy action.
[ipv4MplsVpn]	*MissingPolicyState* see 2.642.1.1.11.2	VPN-IPv4 missing policy action.
[ipv4Multicast]	*MissingPolicyState* see 2.642.1.1.11.2	IPv4 multicast missing policy action.
[ipv4Mvpn] **	*MissingPolicyState* see 2.642.1.1.11.2	IPv4 MVPN missing policy action. **Since: 4.28.2
[ipv4SrTe]	*MissingPolicyState* see 2.642.1.1.11.2	IPv4 SR-TE missing policy action.
[ipv4Unicast]	*MissingPolicyState* see 2.642.1.1.11.2	IPv4 unicast missing policy action.
[ipv6FlowSpec]	*MissingPolicyState* see 2.642.1.1.11.2	IPv6 flow specification missing policy action.
[ipv6FlowSpecVpn] **	*MissingPolicyState* see 2.642.1.1.11.2	VPN-IPv6 flow specification missing policy action. **Since: 4.30.0
[ipv6MplsLabels]	*MissingPolicyState* see 2.642.1.1.11.2	IPv6 labeled-unicast missing policy action.
[ipv6MplsVpn]	*MissingPolicyState* see 2.642.1.1.11.2	VPN-IPv6 missing policy action.
[ipv6Multicast]	*MissingPolicyState* see 2.642.1.1.11.2	IPv6 multicast missing policy action.
[ipv6SrTe]	*MissingPolicyState* see 2.642.1.1.11.2	IPv6 SR-TE missing policy action.
[ipv6Unicast]	*MissingPolicyState* see 2.642.1.1.11.2	IPv6 unicast missing policy action.
[l2VpnEvpn]	*MissingPolicyState* see 2.642.1.1.11.2	L2VPN EVPN missing policy action.
[l2VpnVpls] **	*MissingPolicyState* see 2.642.1.1.11.2	L2VPN VPLS missing policy action. **Since: 4.28.2
[linkState]	*MissingPolicyState* see 2.642.1.1.11.2	BGP Link State missing policy action.
[rtMembership]	*MissingPolicyState* see 2.642.1.1.11.2	RT Membership missing policy action.

2.642.1.1.11.2 MissingPolicyState

action	*enum: deny | permit*	Missing policy action.

status	*enum: routeMap-MisconfiguredByOtherAf | inboundRouteMap-Misconfigured | misconfiguredSubRouteMap | noRouteMapConfigured | permit | namedRouteMapMissing | outboundRouteMap-Misconfigured | unspecified | misconfiguredPrefixList*	Missing policy status.

2.642.1.1.12 NeighborCapabilities

[addPathsCaps]	*AddPathsCapabilities* see 2.642.1.1.12.1	Additional paths capabilities.
[dynamicCap]	*Capability* see 2.642.1.1.12.5	Dynamic capabilities.
[enhancedRouteRefreshCap]	*Capability* see 2.642.1.1.12.5	Enhanced Route Refresh capability.
[extendedNextHopCaps]	*ExtendedNexthop-Capabilities* see 2.642.1.1.12.6	Extended Next-Hop capabilities.
[fourOctetAsnCap]	*Capability* see 2.642.1.1.12.5	Four Octet ASN capability.
[grCaps]	*GrCapabilities* see 2.642.1.1.12.7	Graceful Restart capabilities.
[longlivedGrCaps]	*LlgrCapabilities* see 2.642.1.1.12.10	Long Lived Graceful Restart capabilities.
[multipleLabelsCap]	*MultipleLabelsCapabilities* see 2.642.1.1.12.13	Multiple labels capability.
[multiprotocolCaps]	*MultiprotocolCapabilities* see 2.642.1.1.12.15	Multiprotocol capabilities.
[negotiationDisabled]	*boolean*	Neighbor capability negotiation is disabled.
[routeRefreshCap]	*Capability* see 2.642.1.1.12.5	Route Refresh capability.
[sendEorMessages]	*Capability* see 2.642.1.1.12.5	Send End-of-RIB messages.
[unsupportedCapReceived]	*boolean*	Neighbor does not support all required capabilities.

2.642.1.1.12.1 AddPathsCapabilities

[dps]	*AddPathsCapability* see 2.642.1.1.12.2	Dynamic Path Selection additional paths capability.
[ipv4FlowSpec]	*AddPathsCapability* see 2.642.1.1.12.2	IPv4 flow specification additional paths capability.
[ipv4FlowSpecVpn] **	*AddPathsCapability* see 2.642.1.1.12.2	VPN-IPv4 flow specification additional paths capability. **Since: 4.30.0
[ipv4MplsLabels]	*AddPathsCapability* see 2.642.1.1.12.2	IPv4 labeled-unicast additional paths capability.

[ipv4MplsVpn]	*AddPathsCapability* see 2.642.1.1.12.2	VPN-IPv4 additional paths capability.
[ipv4Multicast]	*AddPathsCapability* see 2.642.1.1.12.2	IPv4 multicast additional paths capability.
[ipv4Mvpn] **	*AddPathsCapability* see 2.642.1.1.12.2	IPv4 MVPN additional paths capability. **Since: 4.28.2
[ipv4SrTe]	*AddPathsCapability* see 2.642.1.1.12.2	IPv4 SR-TE additional paths capability.
[ipv4Unicast]	*AddPathsCapability* see 2.642.1.1.12.2	IPv4 unicast additional paths capability.
[ipv6FlowSpec]	*AddPathsCapability* see 2.642.1.1.12.2	IPv6 flow specification additional paths capability.
[ipv6FlowSpecVpn] **	*AddPathsCapability* see 2.642.1.1.12.2	VPN-IPv6 flow specification additional paths capability. **Since: 4.30.0
[ipv6MplsLabels]	*AddPathsCapability* see 2.642.1.1.12.2	IPv6 labeled-unicast additional paths capability.
[ipv6MplsVpn]	*AddPathsCapability* see 2.642.1.1.12.2	VPN-IPv6 additional paths capability.
[ipv6Multicast]	*AddPathsCapability* see 2.642.1.1.12.2	IPv6 multicast additional paths capability.
[ipv6SrTe]	*AddPathsCapability* see 2.642.1.1.12.2	IPv6 SR-TE additional paths capability.
[ipv6Unicast]	*AddPathsCapability* see 2.642.1.1.12.2	IPv6 unicast additional paths capability.
[l2VpnEvpn]	*AddPathsCapability* see 2.642.1.1.12.2	L2VPN EVPN additional paths capability.
[l2VpnVpls] **	*AddPathsCapability* see 2.642.1.1.12.2	L2VPN VPLS additional paths capability. **Since: 4.28.1
[linkState]	*AddPathsCapability* see 2.642.1.1.12.2	BGP Link State additional paths capability.
[rtMembership]	*AddPathsCapability* see 2.642.1.1.12.2	RT Membership additional paths capability.

2.642.1.1.12.2 AddPathsCapability

[receivingAddPaths]	*ReceivingAddPaths* see 2.642.1.1.12.3	Negotiation state of receiving additional paths from peer.
[sendingAddPaths]	*SendingAddPaths* see 2.642.1.1.12.4	Negotiation state of sending additional paths to peer.

2.642.1.1.12.3 ReceivingAddPaths

enabled	*boolean*	Receipt of additional paths from peer is enabled.
receiveCapabilityAdvertised	*boolean*	Advertised capability to receive additional paths from peer.
sendCapabilityReceived	*boolean*	Received capability to send additional paths from peer.

2.642.1.1.12.4 SendingAddPaths

enabled	*boolean*	Sending of additional paths to peer is enabled.
receiveCapabilityReceived	*boolean*	Received capability to receive additional paths from peer.
sendCapabilityAdvertised	*boolean*	Advertised capability to send additional paths to peer.

2.642.1.1.12.5 Capability

advertised	*boolean*	Capability advertised to peer.
enabled	*boolean*	Capability is enabled.
received	*boolean*	Capability received from peer.

2.642.1.1.12.6 ExtendedNexthopCapabilities

[ipv4LocalNlriOverIpv6]	*boolean*	Local IPv4 NLRIs advertised over an IPv6 backbone.
[ipv4UnicastOverIpv6]	*Capability* see 2.642.1.1.12.5	IPv4 Unicast over an IPv6 backbone capability.
[v4MplsVpnOverIpv6] **	*Capability* see 2.642.1.1.12.5	IPv4 MPLS VPN over an IPv6 backbone capability. **Since: 4.30.0

2.642.1.1.12.7 GrCapabilities

[advertised]	*GrCapability* see 2.642.1.1.12.8	Graceful Restart capability advertised to peer.
[ipv4VpnCap]	*Capability* see 2.642.1.1.12.5	Graceful Restart IPv4 VPN capability.
[received]	*GrCapability* see 2.642.1.1.12.8	Graceful Restart capability received from peer.

2.642.1.1.12.8 GrCapability

bgpRestarted	*boolean*	BGP restarted.
[forwardingStatesPreserved]	*ForwardingStates* see 2.642.1.1.12.9	Graceful restart capabilities forwarding states are preserved.
gracefulNotification-Supported	*boolean*	Graceful notification is supported.
restartTime	*floating point number*	Restart Time.

2.642.1.1.12.9 ForwardingStates

[dps]	*boolean*	Dynamic Path Selection forwarding state is preserved.
[ipv4FlowSpec] **	*boolean*	IPv4 flow specification forwarding state is preserved. **Since: 4.28.2

[ipv4FlowSpecVpn] **	*boolean*	VPN-IPv4 flow specification forwarding state is preserved. **Since: 4.30.0
[ipv4MplsLabels]	*boolean*	IPv4 labeled-unicast forwarding state is preserved.
[ipv4MplsVpn]	*boolean*	VPN-IPv4 forwarding state is preserved.
[ipv4Multicast]	*boolean*	IPv4 multicast forwarding state is preserved.
[ipv4Mvpn] **	*boolean*	IPv4 MVPN forwarding state is preserved. **Since: 4.28.2
[ipv4SrTe]	*boolean*	IPv4 SR-TE forwarding state is preserved.
[ipv4Unicast]	*boolean*	IPv4 unicast forwarding state is preserved.
[ipv6FlowSpec] **	*boolean*	IPv6 flow specification forwarding state is preserved. **Since: 4.28.2
[ipv6FlowSpecVpn] **	*boolean*	VPN-IPv6 flow specification forwarding state is preserved. **Since: 4.30.0
[ipv6MplsLabels]	*boolean*	IPv6 labeled-unicast forwarding state is preserved.
[ipv6MplsVpn]	*boolean*	VPN-IPv6 forwarding state is preserved.
[ipv6Multicast]	*boolean*	IPv6 multicast forwarding state is preserved.
[ipv6SrTe]	*boolean*	IPv6 SR-TE forwarding state is preserved.
[ipv6Unicast]	*boolean*	IPv6 unicast forwarding state is preserved.
[l2VpnEvpn]	*boolean*	L2VPN EVPN forwarding state is preserved.
[l2VpnVpls] **	*boolean*	L2VPN VPLS forwarding state is preserved. **Since: 4.28.1
[linkState]	*boolean*	BGP Link State forwarding state is preserved.
[rtMembership]	*boolean*	RT Membership forwarding state is preserved.

2.642.1.1.12.10 LlgrCapabilities

[advertised]	*LlgrCapability* see 2.642.1.1.12.11	Long Lived Graceful Restart advertised capabilities.
[received]	*LlgrCapability* see 2.642.1.1.12.11	Long Lived Graceful Restart received capabilities.

2.642.1.1.12.11 LlgrCapability

[dps]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	Dynamic Path Selection capability.
[helperOnly]	*boolean*	Helper only.
[ipv4FlowSpec]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	IPv4 flow specification capability.
[ipv4FlowSpecVpn] **	*LlgrCapabilityInfo* see 2.642.1.1.12.12	VPN-IPv4 flow specification capability. **Since: 4.30.0

[ipv4MplsLabels]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	IPv4 labeled-unicast capability.
[ipv4MplsVpn]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	VPN-IPv4 capability.
[ipv4Multicast]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	IPv4 multicast capability.
[ipv4Mvpn] **	*LlgrCapabilityInfo* see 2.642.1.1.12.12	IPv4 MVPN capability. **Since: 4.28.2
[ipv4SrTe]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	IPv4 SR-TE capability.
[ipv4Unicast]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	IPv4 unicast capability.
[ipv6FlowSpec]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	IPv6 flow specification capability.
[ipv6FlowSpecVpn] **	*LlgrCapabilityInfo* see 2.642.1.1.12.12	VPN-IPv6 flow specification capability. **Since: 4.30.0
[ipv6MplsLabels]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	IPv6 labeled-unicast capability.
[ipv6MplsVpn]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	VPN-IPv6 capability.
[ipv6Multicast]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	IPv6 multicast capability.
[ipv6SrTe]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	IPv6 SR-TE capability.
[ipv6Unicast]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	IPv6 unicast capability.
[l2VpnEvpn]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	L2VPN EVPN capability.
[l2VpnVpls] **	*LlgrCapabilityInfo* see 2.642.1.1.12.12	L2VPN VPLS capability. **Since: 4.28.1
[linkState]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	BGP Link State capability.
[rtMembership]	*LlgrCapabilityInfo* see 2.642.1.1.12.12	RT Membership capability.

2.642.1.1.12.12 LlgrCapabilityInfo

[forwardingStatePreserved]	*boolean*	Forwarding State is preserved.
staleTime	*integer*	Stale time (Seconds).

2.642.1.1.12.13 MultipleLabelsCapabilities

[ipv4MplsLabels]	*MultipleLabelsCapability* see 2.642.1.1.12.14	IPv4 MPLS Label.
[ipv6MplsLabels]	*MultipleLabelsCapability* see 2.642.1.1.12.14	IPv6 MPLS Label.

2.642.1.1.12.14 MultipleLabelsCapability

[advertised]	*integer*	Advertised count.

[received]	*integer*	Received count.

2.642.1.1.12.15 MultiprotocolCapabilities

[dps]	*Capability* see 2.642.1.1.12.5	Dynamic Path Selection capability.
[ipv4FlowSpec]	*Capability* see 2.642.1.1.12.5	IPv4 flow specification capability.
[ipv4FlowSpecVpn] **	*Capability* see 2.642.1.1.12.5	VPN-IPv4 flow specification capability. **Since: 4.30.0
[ipv4MplsLabels]	*Capability* see 2.642.1.1.12.5	IPv4 labeled-unicast capability.
[ipv4MplsVpn]	*Capability* see 2.642.1.1.12.5	VPN-IPv4 capability.
[ipv4Multicast]	*Capability* see 2.642.1.1.12.5	IPv4 multicast capability.
[ipv4Mvpn] **	*Capability* see 2.642.1.1.12.5	IPv4 MVPN capability. **Since: 4.28.2
[ipv4SrTe]	*Capability* see 2.642.1.1.12.5	IPv4 SR-TE capability.
[ipv4Unicast]	*Capability* see 2.642.1.1.12.5	IPv4 unicast capability.
[ipv6FlowSpec]	*Capability* see 2.642.1.1.12.5	IPv6 flow specification capability.
[ipv6FlowSpecVpn] **	*Capability* see 2.642.1.1.12.5	VPN-IPv6 flow specification capability. **Since: 4.30.0
[ipv6MplsLabels]	*Capability* see 2.642.1.1.12.5	IPv6 labeled-unicast capability.
[ipv6MplsVpn]	*Capability* see 2.642.1.1.12.5	VPN-IPv6 capability.
[ipv6Multicast]	*Capability* see 2.642.1.1.12.5	IPv6 multicast capability.
[ipv6SrTe]	*Capability* see 2.642.1.1.12.5	IPv6 SR-TE capability.
[ipv6Unicast]	*Capability* see 2.642.1.1.12.5	IPv6 unicast capability.
[l2VpnEvpn]	*Capability* see 2.642.1.1.12.5	L2VPN EVPN capability.
[l2VpnVpls] **	*Capability* see 2.642.1.1.12.5	L2VPN VPLS capability. **Since: 4.28.1
[linkState]	*Capability* see 2.642.1.1.12.5	BGP Link State capability.
[rtMembership]	*Capability* see 2.642.1.1.12.5	RT Membership capability.

2.642.1.1.13 PeerDropStats

[inDropAsSetConfedSetV4Uni] **	*integer*	In IPv4 Unicast packets dropped due to AS_SET or AS_CONFED_SET in AS path attribute. **Since: 4.32.2

[inDropAsSetConfedSetV6Uni] **	*integer*	In IPv6 Unicast packets dropped due to AS_SET or AS_CONFED_SET in AS path attribute. **Since: 4.32.2
[inDropAsloop]	*integer*	In packets dropped due to Asloop.
[inDropClusterIdLoop] **	*integer*	In packets dropped due to Cluster ID loop. **Since: 4.29.2
[inDropEnforceFirstAs]	*integer*	In packets dropped due to Enforce First As.
[inDropMalformedMpbgp]	*integer*	In packets dropped due to Malformed Mp-Bgp.
[inDropNhAfV6]	*integer*	In packets dropped due to next hop AF V6.
[inDropNhInvalid]	*integer*	In packets dropped due to next hop invalid.
[inDropNhLocal]	*integer*	In packets dropped due to next hop local.
[inDropOrigId]	*integer*	In packets dropped due to Orig Id.
[outDropV4LocalAddr]	*integer*	Out packets dropped due to V4 Local Address.
[outDropV6LocalAddr]	*integer*	Out packets dropped due to V6 Local Address.
[prefixBgpLsDropped-ReceptionUnsupported]	*integer*	Link-state NLRIs dropped due to unsupported route type.
[prefixDroppedMartianV4]	*integer*	IPv4 NLRIs dropped due to Martian prefix.
[prefixDroppedMartianV6]	*integer*	IPv6 NLRIs dropped due to Martian prefix.
[prefixDroppedMaxRoute-LimitViolatedV4] **	*integer*	IPv4 NLRIs dropped due to maximum route limit violation. **Since: 4.31.0
[prefixDroppedMaxRoute-LimitViolatedV6] **	*integer*	IPv6 NLRIs dropped due to maximum route limit violation. **Since: 4.31.0
[prefixEvpnDroppedImport-MatchFailure]	*integer*	L2VPN EVPN NLRIs dropped due to route import match failure.
[prefixEvpnDroppedMaxRoute-LimitViolated] **	*integer*	L2VPN EVPN NLRIs dropped due to maximum route limit violation. **Since: 4.31.0
[prefixEvpnDropped-UnsupportedRouteType]	*integer*	L2VPN EVPN NLRIs dropped due to unsupported route type.
[prefixLuDroppedMartianV4]	*integer*	IPv4 LU NLRIs dropped due to Martian prefix.
[prefixLuDroppedMartianV6]	*integer*	IPv6 LU NLRIs dropped due to Martian prefix.
[prefixLuDroppedMaxRoute-LimitViolatedV4] **	*integer*	IPv4 LU NLRIs dropped due to maximum route limit violation. **Since: 4.31.0
[prefixLuDroppedMaxRoute-LimitViolatedV6] **	*integer*	IPv6 LU NLRIs dropped due to maximum route limit violation. **Since: 4.31.0
[prefixLuDroppedV4]	*integer*	Packets dropped due to V4 Prefix LU.
[prefixLuDroppedV6]	*integer*	Packets dropped due to V6 Prefix LU.
[prefixRtMembershipDropped-LocalAsReject]	*integer*	RT Membership NLRIs dropped due to local origin ASN received from external peer.

[prefixRtMembershipDropped-MaxRouteLimitViolated] **	*integer*	RT Membership NLRIs dropped due to maximum route limit violation. **Since: 4.31.0
[prefixVpnIpv4Dropped-ImportMatchFailure]	*integer*	VPN-IPv4 NLRIs dropped due to route import match failure.
[prefixVpnIpv4DroppedMax-RouteLimitViolated] **	*integer*	VPN-IPv4 NLRIs dropped due to maximum route limit violation. **Since: 4.31.0
[prefixVpnIpv6Dropped-ImportMatchFailure]	*integer*	VPN-IPv6 NLRIs dropped due to route import match failure.
[prefixVpnIpv6DroppedMax-RouteLimitViolated] **	*integer*	VPN-IPv6 NLRIs dropped due to maximum route limit violation. **Since: 4.31.0

2.642.1.1.14 PerAfiSafiInfo

[apSendLimit] **	*integer*	Additional-path send limit. **Since: 4.28.1
[apSendMode] **	*string*	Additional-path send mode. **Since: 4.28.1
[apSendPrefixList] **	*string*	Additional-path send prefix-list. **Since: 4.28.1
[localNexthop]	*string*	Local next hop address for next hop self.
[maxTotalAcceptedRoutes] **	*integer*	Maximum number of accepted routes (0 means unlimited). **Since: 4.28.1
[maxTotalAdvertisedRoutes] **	*integer*	Maximum number of advertised routes (0 means unlimited). **Since: 4.28.1
[maxTotalRoutes] **	*integer*	Maximum number of received routes (0 means unlimited). **Since: 4.28.1
[nlriInputLengths] **	*table(string) = RtMembershipNlriInput-Handling* see 2.642.1.1.14.1	A dictionary of NLRI input handling groups for RT Membership AFI/SAFI. **Since: 4.31.2
[nlriOutputLengths] **	*table(string) = RtMembershipNlriOutput-Handling* see 2.642.1.1.14.3	A dictionary of NLRI output handling groups for RT Membership AFI/SAFI. **Since: 4.31.2
[peerTagIn] **	*string*	Inbound peer-tag. **Since: 4.34.0
[peerTagOut] **	*string*	Outbound peer-tag. **Since: 4.34.0
[peerTagOutAction] **	*string*	Outbound peer-tag action. **Since: 4.34.2
[totalAcceptedRoutesWarn-Limit] **	*integer*	Number of accepted routes after which a warning is issued (0 means never warn). **Since: 4.28.1
[totalAdvertisedRoutesWarn-Limit] **	*integer*	Number of advertised routes after which a warning is issued (0 means never warn). **Since: 4.28.1

[totalRoutesWarnLimit] **	*integer*	Number of received routes after which a warning is issued (0 means never warn). **Since: 4.28.1

2.642.1.1.14.1 RtMembershipNlriInputHandling

action	*enum: translate | accept*	Action taken on NLRI.
key	*RtMembershipNlri-HandlingGroup* see 2.642.1.1.14.2	Conditions for NLRI to be included in this handling group.
[to]	*integer*	New length of NLRI after translation.

2.642.1.1.14.2 RtMembershipNlriHandlingGroup

max	*integer*	Maximum NLRI length.
min	*integer*	Minimum NLRI length.

2.642.1.1.14.3 RtMembershipNlriOutputHandling

action	*enum: advertise | translate | drop*	Action taken on NLRI.
key	*RtMembershipNlri-HandlingGroup* see 2.642.1.1.14.2	Conditions for NLRI to be included in this handling group.
[to]	*integer*	New length of NLRI after translation.

2.642.1.1.15 RfdPolicyInfo

[ipv4Unicast]	*string*	Rfd policy for IPv4 unicast.
[ipv6Unicast]	*string*	Rfd policy for IPv6 unicast.

2.642.1.1.16 RouteFilterInfo

filterType	*enum: RouteMap | RCF | PrefixList*	Type of route filter.
[inboundIpv4SrTe]	*string*	Inbound IPv4 SR-TE.
[inboundIpv4SrTeDefined] **	*boolean*	Inbound IPv4 SR-TE RCF is defined. **Since: 4.32.2
[inboundIpv4Uni]	*string*	Inbound IPv4 Unicast.
[inboundIpv4UniDefined] **	*boolean*	Inbound IPv4 Unicast RCF is defined. **Since: 4.32.2
[inboundIpv6SrTe]	*string*	Inbound IPv6 SR-TE.
[inboundIpv6SrTeDefined] **	*boolean*	Inbound IPv6 SR-TE RCF is defined. **Since: 4.32.2
[inboundIpv6Uni]	*string*	Inbound IPv6 Unicast.
[inboundIpv6UniDefined] **	*boolean*	Inbound IPv6 Unicast RCF is defined. **Since: 4.32.2
[outboundIpv4SrTe] **	*string*	Outbound IPv4 SR-TE. **Since: 4.33.0

[outboundIpv4SrTeDefined] **	*boolean*	Outbound IPv4 SR-TE RCF is defined. **Since: 4.33.0
[outboundIpv4Uni]	*string*	Outbound IPv4 Unicast.
[outboundIpv4UniDefined] **	*boolean*	Outbound IPv4 Unicast RCF is defined. **Since: 4.32.2
[outboundIpv6SrTe] **	*string*	Outbound IPv6 SR-TE. **Since: 4.33.0
[outboundIpv6SrTeDefined] **	*boolean*	Outbound IPv6 SR-TE RCF is defined. **Since: 4.33.0
[outboundIpv6Uni]	*string*	Outbound IPv6 Unicast.
[outboundIpv6UniDefined] **	*boolean*	Outbound IPv6 Unicast RCF is defined. **Since: 4.32.2

2.642.1.1.17 RouteMapFilterInfo

filterType	*RouteMap*	Type of route filter.
[inboundIpv4SrTe]	*string*	Inbound IPv4 SR-TE.
[inboundIpv4SrTeDefined] **	*boolean*	Inbound IPv4 SR-TE route-map is defined. **Since: 4.32.2
[inboundIpv4Uni]	*string*	Inbound IPv4 Unicast (overridden if RCF is configured).
[inboundIpv4UniDefined] **	*boolean*	Inbound IPv4 Unicast route-map is defined. **Since: 4.32.2
[inboundIpv6SrTe]	*string*	Inbound IPv6 SR-TE.
[inboundIpv6SrTeDefined] **	*boolean*	Inbound IPv6 SR-TE route-map is defined. **Since: 4.33.0
[inboundIpv6Uni]	*string*	Inbound IPv6 Unicast (overridden if RCF is configured).
[inboundIpv6UniDefined] **	*boolean*	Inbound IPv6 Unicast route-map is defined. **Since: 4.32.2
[outboundIpv4SrTe] **	*string*	Outbound IPv4 SR-TE. **Since: 4.33.0
[outboundIpv4SrTeDefined] **	*boolean*	Outbound IPv4 SR-TE route-map is defined. **Since: 4.33.0
[outboundIpv4Uni]	*string*	Outbound IPv4 Unicast (overridden if RCF is configured).
[outboundIpv4UniDefined] **	*boolean*	Outbound IPv4 Unicast route-map is defined. **Since: 4.32.2
[outboundIpv6SrTe] **	*string*	Outbound IPv6 SR-TE. **Since: 4.33.0
[outboundIpv6SrTeDefined] **	*boolean*	Outbound IPv6 SR-TE route-map is defined. **Since: 4.33.0
[outboundIpv6Uni]	*string*	Outbound IPv6 Unicast (overridden if RCF is configured).
[outboundIpv6UniDefined] **	*boolean*	Outbound IPv6 Unicast route-map is defined. **Since: 4.32.2

2.642.1.1.18 TcpAoInfo

[activeKeyIds]	*list of integer*	All active key IDs.
[activeKeys] **	*table(string) = TcpAoMktStat* see 2.642.1.1.18.1	All active key details. **Since: 4.35.0
[currentKeyId]	*integer*	Key ID of the current TCP-AO key.
macAlgorithm	*enum: hmacSha196 | hmacSha256 | aes128Cmac96 | none*	MAC computation algorithm.
[receiveNextKeyId]	*integer*	Key ID of the receive next TCP-AO key.
sharedSecretProfile	*string*	TCP-AO shared secret profile.
sharedSecretProfileState **	*enum: noValidSecrets | valid | notExist*	State of the Shared Secret Profile. **Since: 4.28.2

2.642.1.1.18.1 TcpAoMktStat

[addedTimestamp]	*floating point number*	Time stamp when MKT is added on the socket.
[lastRemovalFailTimestamp]	*floating point number*	Time stamp of the last failed removal.
[lastSecretUpdateFail-Timestamp]	*floating point number*	Time stamp of the last failed secret update.
[lastSecretUpdateTimestamp]	*floating point number*	Time stamp of the last successful secret update.
[rnextActiveTimestamp]	*floating point number*	Time stamp when MKT becomes rnext on the socket.

2.643 show ip bgp neighbors update errors [...]

revision 2

vrfs	*table(string) = BgpNeighborUpdateError* see 2.643.1	Per VRF BGP Neighbor Update-Error list.

2.643.1 BgpNeighborUpdateError

peers	*table(string) = BgpUpdateErrorPeerEntry* see 2.643.1.1	Dictionary of BGP Update Error entries indexed by the peer address.
vrf	*string*	VRF Name.

2.643.1.1 BgpUpdateErrorPeerEntry

[disableAfiSafiAttr]	*string*	Disable AFI/SAFI Attribute.
[disableAfiSafiBuffer]	*string*	Disable AFI SAFI Update Buffer.
[ignoreAttr]	*string*	Ignore Attribute.
[ignoreBuffer]	*string*	Ignore Attribute Update Buffer.
[withdrawAttr]	*string*	Withdraw Attribute.
[withdrawBuffer]	*string*	Withdraw Update Buffer.

2.644 show ip bgp regex REGEX [...]

revision 3

see 2.20

2.645 show ip bgp summary [...]

revision 3

see 2.51

2.646 show ip community-list [...]

ipCommunityLists	*table(string) = IpCommunityList* see 2.646.1	Table of community lists by name.

2.646.1 IpCommunityList

entries	*list of IpCommunityListEntry* see 2.646.1.1	Community list entries sorted by increasing sequence number.

2.646.1.1 IpCommunityListEntry

[communityRegex]	*string*	Communities as a regular expression.
[communityValues]	*list of string*	Community list values.
filterType	*enum: deny | permit*	Filter type.
listType	*enum: expanded | standard*	Community list type.

2.647 show ip decap-group [...]

revision 4

decapGroups	*table(string) = DecapGroupModelBase* see 2.647.1	A mapping from name to ip decap-group entry.
globalUdpDestPortToPayload-Type	*table(numeric string) = string*	A global mapping from UDP destination port to payload type.

2.647.1 DecapGroupModelBase

Could also be an instance of:
DecapGroupGreModel 2.647.2
DecapGroupIpIpModel 2.647.3
DecapGroupQosTcModel 2.647.4
DecapGroupUdpModel 2.647.5

[forwardingVrf]	*string*	Forwarding VRF.
persistent	*boolean*	Decap group is present in system configuration.
tunnelType	*enum: gre | udp | unknown | ipip*	Decap tunnel type.

2.647.2 DecapGroupGreModel

decapIntf	*list of DecapIntfModel* see 2.647.2.2	decap intf key list.
decapIp	*list of IP address prefix*	decap ip list.
[decapIpCounters]	*table(IPv4 or IPv6 address prefix) = DecapGroupCounterEntry* see 2.647.2.1	Map decap IP address to decap group counter.
[forwardingVrf]	*string*	Forwarding VRF.
persistent	*boolean*	Decap group is present in system configuration.
tunnelType	*enum: gre | udp | unknown | ipip*	Decap tunnel type.

2.647.2.1 DecapGroupCounterEntry

octets	*integer*	Number of received octets on Decap-Group.
packets	*integer*	Number of received packets on Decap-Group.

2.647.2.2 DecapIntfModel

addressFamily	*enum: ipv4 | ipv6 | ipunknown*	Decap address family.
addressType	*enum: all | primary*	Decap address type.
[counter]	*DecapGroupCounterEntry* see 2.647.2.1	Counter for the decap interface.
intfId	*interface name*	Decap destination interface.

oldConfig	*boolean*	Old way of writing this config.

2.647.3 DecapGroupIpIpModel

decapIntf	*list of DecapIntfModel* see 2.647.2.2	decap intf key list.
decapIp	*list of IP address prefix*	decap ip list.
[decapIpCounters]	*table(IPv4 or IPv6 address prefix) = DecapGroupCounterEntry* see 2.647.2.1	Map decap IP address to decap group counter.
[forwardingVrf]	*string*	Forwarding VRF.
persistent	*boolean*	Decap group is present in system configuration.
tunnelType	*enum: gre | udp | unknown | ipip*	Decap tunnel type.

2.647.4 DecapGroupQosTcModel

[forwardingVrf]	*string*	Forwarding VRF.
persistent	*boolean*	Decap group is present in system configuration.
qosTcFromMplsTc	*boolean*	QoS Traffic Class derived from MPLS Traffic Class.
tunnelType	*enum: gre | udp | unknown | ipip*	Decap tunnel type.

2.647.5 DecapGroupUdpModel

decapIntf	*list of DecapIntfModel* see 2.647.2.2	decap intf key list.
decapIp	*list of IP address prefix*	decap ip list.
[decapIpCounters] **	*table(IPv4 or IPv6 address prefix) = DecapGroupCounterEntry* see 2.647.2.1	Map decap IP address to decap group counter. **Since: 4.32.1
destinationPort	*integer*	The target port for decapsulation. This field will display the default of 0, even if a global rule is configured. Refer to the globalUdpDestPortToPayloadType section for the globally configured port.
[forwardingVrf]	*string*	Forwarding VRF.
payloadType	*enum: ipv4 | unknownPayload | mpls | ipvx | ipv6*	Payload type after decpasulation (e.g. ipv4, ipv6). This field will display the default unknownPayload even if a global rule is configured. Refer to the globalUdpDestPortToPayloadType section for the active global payload mapping.
persistent	*boolean*	Decap group is present in system configuration.
tunnelType	*enum: gre | udp | unknown | ipip*	Decap tunnel type.

2.648 show ip decap-group gre keys [...]

decapGroups	*table(string) = DecapGroupWithOnlyGreKeyToVrfMapModel* see 2.648.1	A mapping from name to GRE decap-group entry.

2.648.1 DecapGroupWithOnlyGreKeyToVrfMapModel

greKeyToForwardingVrfMapping	*table(numeric string) = string*	Map GRE key to forwarding VRF.

2.649 show ip decap-group qos [...]

groups	*table(string) = DecapGroupQosTcModel* see 2.647.4	IP decap groups, keyed by their name.

2.650 show ip dhcp relay

revision 2

see 2.64

2.651 show ip dhcp snooping

[bridgeMac]	*MAC address*	Remote MAC address.
bridgingEnabled **	*boolean*	DHCP Snooping with bridging enabled. **Since: 4.25.2
[circuitIdEnabled]	*boolean*	Circuit ID is enabled.
[circuitIdFormat]	*enum: %p:%v | %h:%p*	Format for circuit-id.
[circuitIdType]	*integer*	Circuit-id default sub-option type.
[circuitIds]	*table(Interface name) = CircuitIdModel* see 2.651.1	Circuit IDs.
enabled	*boolean*	DHCP Snooping is enabled.
enabledVlans	*list of integer*	VLANs on which snooping is configured.
operational	*boolean*	DHCP Snooping is operational.
operationalVlans	*list of integer*	VLANs on which snooping is operational.
option82Enabled	*boolean*	Insertion of Option-82 is enabled.

2.651.1 CircuitIdModel

[circuitType]	*integer*	Circuit ID type.
name	*interface name*	Interface name.
valid	*boolean*	Circuit ID is valid.

`value`	*string*	Circuit ID value.

2.652 show ip dhcp snooping counters [...]

detail_ **	*boolean*	Counter values in detail. **Since: 4.25.2
enabled	*boolean*	DHCP Snooping is enabled.
vlanCounters	*table(numeric string) = VlanCounters* see 2.652.1	Per-VLAN counter information.

2.652.1 VlanCounters

interfaces **	*table(Interface name) = IntfCounters* see 2.652.1.1	Vlan specific L2 interface counters. **Since: 4.25.2
repliesDropped	*integer*	Replies dropped.
repliesForwarded	*integer*	Replies forwarded.
repliesReceived	*integer*	Replies received.
requestsDropped	*integer*	Requests dropped.
requestsForwarded	*integer*	Requests forwarded.
requestsReceived	*integer*	Requests received.
resetTime	*floating point number*	Last time counters were reset.
vlan	*integer*	VLAN ID.

2.652.1.1 IntfCounters

repliesDropped	*integer*	Replies dropped.
repliesForwarded	*integer*	Replies forwarded.
repliesReceived	*integer*	Replies received.
requestsDropped	*integer*	Requests dropped.
requestsForwarded	*integer*	Requests forwarded.
requestsReceived	*integer*	Requests received.

2.653 show ip dhcp snooping counters debug

[dhcpOpErrCounters]	*SnoopingRelayCounters* see 2.653.1	Dropped - Invalid Dhcp Optype.
[disabledErrCounters]	*SnoopingRelayCounters* see 2.653.1	Dropped - Snooping disabled.
enabled	*boolean*	DHCP Snooping is enabled.
[forwardedCounters]	*SnoopingRelayCounters* see 2.653.1	Forwarded.
[infoOptErrCounters]	*SnoopingRelayCounters* see 2.653.1	Dropped - Invalid Info Option.
[parseErrCounters]	*SnoopingRelayCounters* see 2.653.1	Dropped - Parse error.
[receivedCounters]	*SnoopingRelayCounters* see 2.653.1	Recieved.
[remoteIdErrCounters]	*SnoopingRelayCounters* see 2.653.1	Dropped - Invalid Remote-ID Option.
[resetTime]	*floating point number*	Last time counters were reset.

[vlanIdErrCounters]	*SnoopingRelayCounters* see 2.653.1	Dropped - Invalid VlanId.

2.653.1 SnoopingRelayCounters

relayToSnooping	*integer*	Relay to snooping counter.
snoopingToRelay	*integer*	Snooping to relay counter.

2.654 show ip dhcp snooping hardware

enabled	*boolean*	DHCP Snooping is enabled.
vlans	*list of integer*	VLANs on which snooping is enabled.
vlansPerSlice	*table(string) = VlanList* see 2.654.1	VLANs enabled per slice.

2.654.1 VlanList

vlans	*list of integer*	VLANs in slice.

2.655 show ip extcommunity-list [...]

ipExtCommunityLists	*table(string) = IpExtCommunityList* see 2.655.1	Table of extended community lists by name.

2.655.1 IpExtCommunityList

entries	*list of IpCommunityListEntry* see 2.646.1.1	Extended community list entries sorted by increasing sequence number.

2.656 show ip hardware ale adj [...]

[adj]	*table(numeric string) = AleL3AdjInfo* see 2.656.1	Dictionary to map fecId to L3Adj.
[cmdErr]	*string*	Error Message.
[transientAdjsPresent] **	*boolean*	Output contains some transient adjs. **Since: 4.18.1

2.656.1 AleL3AdjInfo

[adjRefCount] **	*integer*	Inter Adjacency references. **Since: 4.22.0
[adjStats]	*AleStats* see 2.656.1.2	SubModel storing Adjacency Timestamps.
[backupL3AdjVia] **	*list of AleL3AdjVia* see 2.56.1.1	List storing the backup L3 V4 Adjacency Vias. **Since: 4.23.2
[backupL3AdjVia6] **	*list of AleL3AdjVia* see 2.56.1.1	List storing the backup L3 V6 Adjacency Vias. **Since: 4.23.2
[extRefCount] **	*integer*	External FEC references. **Since: 4.22.0
[fecRefs] **	*list of AlePrevLevelFecs* see 2.656.1.1	List of previous level fec refs. **Since: 4.24.2
[implicitRefCount] **	*integer*	Implicit references. **Since: 4.33.2
[l2AdjIndex]	*integer*	Layer 2 Adjacency Index.
[l3AdjVia]	*list of AleL3AdjVia* see 2.56.1.1	List storing the L3 V4 Adjacency Vias.
[l3AdjVia6]	*list of AleL3AdjVia* see 2.56.1.1	List storing the L3 V6 Adjacency Vias.
[orderedNexthops] **	*boolean*	The ordering of next-hops is honored. **Since: 4.24.1
[pbrRefCount] **	*integer*	PBR references. **Since: 4.22.0
[prefixCount]	*integer*	Number of Prefixes.
[proxyRefCount] **	*integer*	proxy FEC references. **Since: 4.24.2

[routeType]	*enum: dropRoute | fecInfoUnavailable | bcastReceiveRoute | routeCacheConnectedRoute | nexthopGroupRoute | evpnRoute | forwardRoute | tunnelFibRoute | routeCacheForwardRoute | policyRoute | pwRoute | mplsFloodSetRoute | directedBcastRoute | srv6Route | usedByTunnelRoute | vplsL2UcastRoute | mplsMcastRoute | greMcastRoute | slowReceiveRoute | routeTypeUnknown | receiveRoute | mplsRoute | vplsMcastRoute | invalidRoute | nexthopRoute | attachedRoute*	Specifies Route Type.
[sourceFec] **	*integer*	Source FEC being used by this proxy. **Since: 4.24.2
[totalRefCount] **	*integer*	Total references. **Since: 4.22.0
[transientAdj] **	*boolean*	ECMP Adj programmed as non ECMP in hardware. **Since: 4.18.1
[ucmpRequested] **	*boolean*	Auto UCMP requested. **Since: 4.31.0
[v4PrefixesByVrf] **	*table(string) = AleV4Prefixes* see 2.656.1.3	Dict to list V4 Prefix references by VRF. **Since: 4.22.0
[v6PrefixesByVrf] **	*table(string) = AleV6Prefixes* see 2.656.1.4	Dict to list V6 Prefix references by VRF. **Since: 4.22.0

2.656.1.1 AlePrevLevelFecs

fecId	*integer*	Previous level FEC ID.
tableId	*integer*	FEC table ID.

2.656.1.2 AleStats

insertTime	*floating point number*	Insert timestamp.
lastUpdateTime	*floating point number*	Update timestamp.
numUpdates	*integer*	Number of updates.

2.656.1.3 AleV4Prefixes

[v4Prefixes]	*list of AlePrefix* see 2.656.1.3.1	A mapping between VRF ID and V4 Prefixes.

2.656.1.3.1 AlePrefix

prefix	*string*	Prefix.

2.656.1.4 AleV6Prefixes

[v6Prefixes]	*list of AlePrefix* see 2.656.1.3.1	A mapping between VRF ID and V6 Prefixes.

2.657 show ip hardware ale adj acknowledgement [...]

[cmdErr]	*string*	Error Message.
fecEntries	*table(numeric string) = AcknowledgementFecEntry* see 2.657.1	Mapping fecId to its version ID info.
vrfName	*string*	VRF name.

2.657.1 AcknowledgementFecEntry

[acknowledged]	*AcknowledgementFecVersionId* see 2.657.1.1	FEC version Id that was acknowledged.
[requested]	*AcknowledgementFecVersionId* see 2.657.1.1	FEC version Id to be acknowledged.

2.657.1.1 AcknowledgementFecVersionId

failed **	*boolean*	FEC install failed. **Since: 4.28.0
requestedDelete	*boolean*	FEC is due to be deleted.
versionId	*integer*	FEC version Id to be acknowledged.

2.658 show ip hardware ale adj export [...]

[cmdErr]	*string*	Error message.
[fecs]	*table(numeric string) = AleOpenConfigExportedFec* see 2.658.1	A mapping of FEC IDs to exported FEC information.

2.658.1 AleOpenConfigExportedFec

nextHops	*table(numeric string) = AleOpenConfigExported-NextHop* see 2.658.1.1	A mapping of next-hops IDs to exported next-hop information.
programmedId	*integer*	Exported programmed ID.

2.658.1.1 AleOpenConfigExportedNextHop

interface	*interface name*	Interface.
ipAddress	*IP address*	IP address.
[labels]	*list of integer*	MPLS labels.
macAddress	*MAC address*	MAC address.
popTopLabel	*boolean*	Pop the top label from the MPLS label stack.
weight	*integer*	Next hop weight.

2.659 show ip hardware ale adj platform-api [...]

[adjId]	*table(numeric string) = AleShmemAdjInfo* see 2.659.1	Dictionary to map adjacency ID to adjacency info.
[cmdErr]	*string*	Error Message.

2.659.1 AleShmemAdjInfo

[config]	*AleShmemAdjConfig* see 2.659.1.1	Adjacency Config.
[status]	*AleShmemAdjStatus* see 2.659.1.2	Adjacency Status.

2.659.1.1 AleShmemAdjConfig

[adjTableType]	*AdjTableType* see 2.659.1.1.2	Adjacency table type.
[backupVias]	*list of AleL2AdjVia* see 2.659.1.1.3	List storing the backup adjacency vias.
[depths]	*Depths* see 2.659.1.1.4	Adjacency Depths.
[flags]	*AdjConfigFlags* see 2.659.1.1.1	Adjacency config flags.
[primaryVias]	*list of AleL2AdjVia* see 2.659.1.1.3	List storing the adjacency vias.
[priority] **	*enum: high | normal*	Adjacency config priority. **Since: 4.36.0
[sequence]	*integer*	Adjacency config sequence number.

2.659.1.1.1 AdjConfigFlags

adjOptimized	*boolean*	Adjacency optimized.
forceOptimizeHwResource	*boolean*	Force optimize hardware resource.
maxPredictedHierarchyHeight	*integer*	Max predicted hierarchy height.
potentialEcmp	*boolean*	Potential ECMP.
requiresRealAck	*boolean*	Requires real ack.
useHwFastFailover	*boolean*	Use hardware fast failover.

2.659.1.1.2 AdjTableType

tableTypeExactMatch	*boolean*	Table Type is Exact Match.
tableTypeLabelledFec	*boolean*	Table Type is Labelled Fec.
tableTypeLongestPrefix	*boolean*	Table Type is Longest Prefix.
tableTypeMax	*boolean*	Table Type is Max.
tableTypeMpls	*boolean*	Table Type is MMPLS.
tableTypeMplsMulticast	*boolean*	Table Type is MPLS Multicast.
tableTypeMvpn	*boolean*	Table Type is MVPN.
tableTypePbr	*boolean*	Table Type is PBR.

tableTypeUnknown	*boolean*	Table Type is Unknown.
usedByV4DefaultRoute	*boolean*	Table Type is Used By V4 Default Route.
usedByV4Route	*boolean*	Table Type is Used By V4 Route.
usedByV6DefaultRoute	*boolean*	Table Type is Used By V6 Default Route.
usedByV6Route	*boolean*	Table Type is Used By V6 Route.

2.659.1.1.3 AleL2AdjVia

adjType	*enum: nextHopArpCapacityDrop* | *nextHopArpResolved* | *nextHopPopLabelAndRoute* | *nextHopCpuBcast* | *nextHopVoqFabricTunnel* | *nextHopFallback* | *nextHopCpuSlow* | *nextHopCpu* | *nextHopTunnel* | *nextHopVlanPort* | *nextHopArpRequired* | *nextHopFlow* | *nextHopCpuRouteCache* | *nextHopDrop* | *nextHopArpDrop* | *nextHopMcastTunnel* | *nextHopHierarchical*	L2 Adjacency Type.
[counterId] **	*integer*	Next-Hop Counter Id. **Since: 4.23.0
[decapInfo] **	*DecapInfo* see 2.56.1.1.2	Decap information. **Since: 4.27.0
[fallbackInfo] **	*FallbackInfo* see 2.56.1.1.3	Fallback information. **Since: 4.27.2
forwardingAction **	*enum: forwarding* | *setForwardingVrf* | *encap* | *decapEncap* | *decap* | *decapSetForwardingVrf*	Forwarding action. **Since: 4.31.2
[greEncapInfo] **	*GreEncapInfo* see 2.659.1.1.3.2	GRE Encap information. **Since: 4.24.2
[gueEncapInfo] **	*GueEncapInfo* see 2.659.1.1.3.3	UDP Encap information. **Since: 4.31.1
[ipInIpEncapInfo] **	*IpInIpEncapInfo* see 2.659.1.1.3.4	IP-in-IP Encap information. **Since: 4.28.2
[ipTunnelInfo] **	*IpTunnelInfo* see 2.659.1.1.3.1	Tunnel resolution information. **Since: 4.30.2
l2IntfId	*interface name*	L2 Interface Id.
l3IntfId	*interface name*	L3 Interface Id.
macAddr	*MAC address*	Next-Hop Mac Address.
[mplsEncapInfo] **	*MplsEncapInfo* see 2.659.1.1.3.5	MPLS Encap information. **Since: 4.24.2
[nextLevelL2AdjIndex] **	*integer*	L2 Adjacency ID of the next FEC in a hierarchical FEC. **Since: 4.21.0

[srv6EncapInfo] **	*Srv6EncapInfo* see 2.659.1.1.3.6	SRv6 Encap information. **Since: 4.35.2
[vxlanEncapInfo] **	*VxlanEncapInfo* see 2.659.1.1.3.7	VXLAN Encap information. **Since: 4.26.2
weight	*integer*	Metric representing the hop cost.

2.659.1.1.3.1 IpTunnelInfo

destination	*IP address*	Destination IP address.
[interface]	*interface name*	Tunnel interface.
source	*IP address*	Source IP address.
[underlayL2Adj]	*integer*	L2 Adjacency ID of the underlay FEC.

2.659.1.1.3.2 GreEncapInfo

destination	*IP address prefix*	Location in the IP network where the tunnel terminates.
source	*IP address prefix*	Location in the IP network where the tunnel starts.
[tos]	*integer*	Type of service.
[ttl]	*integer*	Time to live.

2.659.1.1.3.3 GueEncapInfo

destination	*IP address prefix*	Address in the IP network where the tunnel terminates.
source	*IP address prefix*	Address in the IP network where the tunnel starts.
[tos]	*integer*	Type of service.
[ttl]	*integer*	Time to live.

2.659.1.1.3.4 IpInIpEncapInfo

destination	*IP address prefix*	Destination IP address.
source	*IP address prefix*	Source IP address.

2.659.1.1.3.5 MplsEncapInfo

[entropyLabelIndicator-Indices] **	*list of integer*	Entropy label indicator indices in the label stack of the tunnel. **Since: 4.28.1
[entropyLabelIndices] **	*list of integer*	Entropy label indices in the label stack of the tunnel. **Since: 4.28.1
labelStack	*list of integer*	MPLS Label Stack.
operation	*enum: forward | pop | swap | push*	Label Operation.

2.659.1.1.3.6 Srv6EncapInfo

[reducedEncap]	*boolean*	Encap is optimized to exclude first SID from SRH.
segmentList	*list of IP address*	SRv6 segment list.
source	*IP address*	Source IP address.
[tos]	*integer*	Type of service.
[ttl]	*integer*	Time to live.

2.659.1.1.3.7 VxlanEncapInfo

[evpnTunnelId] **	*integer*	EVPN Tunnel ID. **Since: 4.33.2
[l3Intf] **	*interface name*	L3 Interface. **Since: 4.33.2
[macAddr] **	*MAC address*	VXLAN MAC Address. **Since: 4.33.2
srcVti	*interface name*	Source VTI.
[vlanId] **	*integer*	VLAN ID. **Since: 4.33.2
vtepIp	*IP address*	VTEP IP address.

2.659.1.1.4 Depths

depth0	*boolean*	Depth is 0.
depth1ToN	*boolean*	Depth is 1+.

2.659.1.2 AleShmemAdjStatus

[adjHwId]	*integer*	Adjacency hardware ID.
[failReason]	*enum: adjUpdateFailResourceFull | adjUpdateFailNotAle-Syslogged | adjUpdateRepairable-Failure | adjUpdateFailIncompatible | adjUpdateFailNot-Applicable*	Adjacency failure reason.
[flags]	*AdjStatusFlags* see 2.659.1.2.1	Adjacency status flags.

[incompatibleReason]	*enum: adjUpdateIncompatNotApplicable | adjUpdateIncompatSwapToMultipleMplsLabels | adjUpdateIncompatTunnelMplsLabelActionInvalid | adjUpdateIncompatMplsLabelStackSizeUnsupported | adjUpdateIncompatNexthopCombinationUnsupported*	Adjacency incompatible reason.
[parentWalkCount]	*integer*	Parent walk count.
[sequence]	*integer*	Adjacency status sequence number.
[updateStatus]	*enum: adjUpdateSuccess | adjUpdateFail | adjUpdateNotReady | adjUpdateEcmpGroupsFull*	Adjacency update status.

2.659.1.2.1 AdjStatusFlags

ecmp	*boolean*	Equal cost multi path.
hardwareResourceUtilStatusOptimal	*boolean*	Hardware Resource Status is All Optimal.
platformSyncInplace	*boolean*	Platform sync in place.
usingHwResource	*boolean*	Using hardware resource.

2.660 show ip hardware ale adj proxy [...]

[cmdErr]	*string*	Error Message.
[fecAliases]	*list of FecProxyInfo* see 2.660.1	List of FEC proxies.

2.660.1 FecProxyInfo

[cmdErr]	*string*	Error Message.
proxyFecList	*list of integer*	List of proxy FECs for source.
sourceFec	*integer*	Source Fec Id for this proxy set.

2.661 show ip hardware ale counters egress bindings l2-adj [...]

[cmdErr]	*string*	Error Message.
[l2AdjCounterBindings]	*table(numeric string) = AleL2AdjCounterBindingsInfo* see 2.661.1	Dictionary to map Layer 2 adjacency index to its counter related bindings.

2.661.1 AleL2AdjCounterBindingsInfo

pdcks	*list of AlePdckValues* see 2.661.1.1	List of platform-dependent counter keys bound to the L2 Adjacency.

2.661.1.1 AlePdckValues

value1	*integer*	PDCK value 1.
value2	*integer*	PDCK value 2.

2.662 show ip hardware ale counters egress bindings platform-key [...]

[cmdErr]	*string*	Error Message.
[pdcksCounterBindings]	*table(string) = AlePdckCounterBindingsInfo* see 2.662.1	Dictionary to map Ale Platform-dependent counter key (PDCK) to PDCK counter related bindings.

2.662.1 AlePdckCounterBindingsInfo

pick	*integer*	Platform-independent counter key bound to the PDCK.
pickIndex	*integer*	PICK Index.
[pickType]	*enum: counterKeyTypeMax | invalidCounterKeyType | prefixCounterBackup | tunnelCounter | nhgCounterShared | nhgCounterUnshared | prefixCounterPrimary*	Specifies counter key Type.

2.663 show ip hardware ale event counters (summary | (counter COUNTERNAME)) [...]

counters	*table(string) = Ale.Model.AleDebugCountersEntryList* see 2.663.1	A map of all ALE debug counters with counter window info for each counter.

2.663.1 Ale.Model.AleDebugCountersEntryList

name	*string*	counter name.
windows	*list of Ale.Model.AleDebugCounterWindow* see 2.663.1.1	Debug Counter windows info for each counter.

2.663.1.1 Ale.Model.AleDebugCounterWindow

endTime	*floating point number*	End time of counter window.
startTime	*floating point number*	Start time of counter window.
windowCount	*integer*	count for this window.

2.664 show ip hardware ale event statistics [...]

[cmdErr]	*string*	Error message.
[events]	*list of AleEventStatInfo* see 2.664.1	List of event stats.

2.664.1 AleEventStatInfo

dampL3AdjacenciesReviewed	*integer*	Total dampened L3 adjacencies reviewed.
[dampenedL3AdjacencyReview-End]	*floating point number*	Timestamp when high priority dampened L3 adjacency queue was drained of all entries.
dropFecsProgrammed	*integer*	Total drop FEC installed.
dropUnknownL2AdjWithdrawn	*floating point number*	Timestamp when all drop/unknown L2 adjacencies entries added, during event timeframe, were withdrawn.
eventSource	*string*	Event interface/tunnel ID.
eventType	*enum: fibRouteUpdate | fibFecUpdate | linkDown | fibTunnelUpdate | tunnelDown | hwInducedPrefixWalk | bfdDown*	Specifies event type.
[fecMaxPrefixes]	*table(numeric string) = AleFecMaxPrefixKeyInfo* see 2.664.1.1	Top 10 adjacencies scheduling the highest number of prefixes for review.
l2AdjacenciesReviewed	*integer*	Total L2 adjacencies reviewed.
[l2AdjacencyEventCounters]	*list of AleL2AdjEventStat-CounterInfo* see 2.664.1.2	L2 adjacency counters classified based on route type.
l2AdjacencyReviewEnd	*floating point number*	Timestamp when L2 adjacency monitor review queue was drained.
l3AdjacenciesReviewed	*integer*	Total L3 adjacencies reviewed.
[l3AdjacencyReviewEnd]	*floating point number*	Timestamp when high priority L3 adjacency queue was drained of all entries.
[overlappingEvents]	*list of AleOverlappingEventInfo* see 2.664.1.3	Overlapping event, with count for each, that caused churn in the system.
prefixWalkCount	*integer*	Total prefix walks triggered.
routesReviewed	*integer*	Total routes reviewed.
startTimestamp	*floating point number*	Event start timestamp.

2.664.1.1 AleFecMaxPrefixKeyInfo

parentAdjCount	*integer*	Total hierarchical parents for the L3 adjacency.
parentPrefixCount	*integer*	Total prefixes scheduled by the adjacency per review cycle.

2.664.1.2 AleL2AdjEventStatCounterInfo

created	*integer*	Total L2 adjacencies created.
deleted	*integer*	Total L2 adjacencies deleted.
modified	*integer*	Total L2 adjacencies modified.
routeType	*enum: dropRoute* | *fecInfoUnavailable* | *bcastReceiveRoute* | *routeCacheConnectedRoute* | *nexthopGroupRoute* | *evpnRoute* | *forwardRoute* | *tunnelFibRoute* | *routeCacheForwardRoute* | *policyRoute* | *pwRoute* | *mplsFloodSetRoute* | *directedBcastRoute* | *srv6Route* | *usedByTunnelRoute* | *vplsL2UcastRoute* | *mplsMcastRoute* | *greMcastRoute* | *slowReceiveRoute* | *routeTypeUnknown* | *receiveRoute* | *mplsRoute* | *vplsMcastRoute* | *invalidRoute* | *nexthopRoute* | *attachedRoute*	Route type.

2.664.1.3 AleOverlappingEventInfo

eventCount	*integer*	Number of times the event occurred.
eventType	*enum: fibRouteUpdate* | *fibFecUpdate* | *linkDown* | *fibTunnelUpdate* | *tunnelDown* | *hwInducedPrefixWalk* | *bfdDown*	Specifies event type.

2.665 show ip hardware ale l2-adj [...]

[cmdErr]	*string*	Error Message.
[l2Adj]	*table(numeric string) = AleL2AdjInfo* see 2.665.1	Dictionary to map l2AdjIndex to l2Adj Info.

2.665.1 AleL2AdjInfo

[adjCount]	*integer*	Number of L3 Adjacencies.
[backupL2AdjVia] **	*list of AleL2AdjVia* see 2.659.1.1.3	List storing the backup L2 Adjacency Vias. **Since: 4.23.2
l2AdjHardwareState **	*string*	L2 Adjacency Hardware State. **Since: 4.31.0

l2AdjRequestState **	*string*	L2 Adjacency Request State. **Since: 4.31.0
l2AdjState **	*enum: ecmpGroupsFull | pendingDelete | installFailedPreserved | pendingSync | installFailed | garbageCollected | installNotRequired | uninitialized | installNotReady | installed*	L2 Adjacency State. **Since: 4.21.0
[l2AdjStats] **	*AleStats* see 2.656.1.2	L2 Adjacency timestamps. **Since: 4.21.3
[l2AdjVia]	*list of AleL2AdjVia* see 2.659.1.1.3	List storing the L2 Adjacency Vias.
[platformFecIndex] **	*integer*	Platform FEC table index used by the L2 Adjacency. **Since: 4.21.0

2.666 show ip hardware ale mac-address router gateway

macs	*table(string) = VlanListType* see 2.666.1	Mapping MAC address to its VLANs.

2.666.1 VlanListType

vlans	*list of integer*	VLAN IDs.

2.667 show ip hardware ale routes [...]

[cmdErr]	*string*	Error Message.
[fibRoute]	*table(IPv4 or IPv6 address prefix) = AleRouteInfo* see 2.667.1	Mapping prefix to its FibRoute Info.
[numUnprog]	*integer*	Count of unprogrammed routes.
[vrfName]	*string*	VRF name.

2.667.1 AleRouteInfo

[cmdErr]	*string*	Error Message.
[l2AdjInfo]	*table(numeric string) = AleL2AdjInfo* see 2.665.1	Dict to handle L2 Adjacency Info.
[l3AdjInfo]	*table(numeric string) = AleL3AdjInfo* see 2.656.1	Dict to handle L3 Adjacency Info.
[parent]	*string*	Parent prefix.

[routeOptimized]	*enum: optimizedAndCompressed | optimized | unoptimized | optimizedAndExpanded*	Details of Route Optimization.
[routeProgrammed]	*boolean*	Flag to indicate Route is programmed or not.
[routeStats]	*AleStats* see 2.656.1.2	Stats of a route.

2.668 show ip hardware ale routes diff [...]

entriesMap	*table(string) = AleRouteDiffDisplayDataEntryList* see 2.668.1	A map of VRF names to route diff result entries.

2.668.1 AleRouteDiffDisplayDataEntryList

entries	*list of AleRouteDiffDisplayDataEntry* see 2.668.1.1	Route diff result entries for a single VRF.

2.668.1.1 AleRouteDiffDisplayDataEntry

fecId	*integer*	FEC ID of the route.
l2AdjIndex	*integer*	L2 Adj index of the route.
prefix	*IP address prefix*	Prefix of the route.
programmed	*boolean*	Hardware program status of the route.
type	*string*	Type of the route.

2.669 show ip hardware ale routes platform-api [...]

[cmdErr]	*string*	Error Message.
[vrfs]	*table(numeric string) = AleShmemRoutes* see 2.669.1	A mapping of vrfId to routes in that vrf.

2.669.1 AleShmemRoutes

[prefix]	*table(IPv4 or IPv6 address prefix) = AleShmemRoute* see 2.669.1.1	A mapping of prefixes to routes.
[vrfName]	*string*	Vrf name.

2.669.1.1 AleShmemRoute

[config]	*AleShmemRouteConfig* see 2.669.1.1.1	Shmem route config.
[status]	*AleShmemRouteStatus* see 2.669.1.1.2	Shmem route status.

2.669.1.1.1 AleShmemRouteConfig

[fwdingInfo]	*table(numeric string) = RouteFwdingInfo* see 2.669.1.1.1.1	A mapping of RouteIndex to RouteFwdingInfo.
[sequence]	*integer*	PD route config sequence.
[tableType]	*enum: tableTypeMplsMulticast* | *usedByV6DefaultRoute* | *tableTypePbr* | *tableTypeUnknown* | *tableTypeLongestPrefix* | *tableTypeMpls* | *tableTypeMvpn* | *usedByV6Route* | *tableTypeMax* | *tableTypeLabelledFec* | *usedByV4DefaultRoute* | *tableTypeExactMatch* | *usedByV4Route*	Table type.

2.669.1.1.1.1 RouteFwdingInfo

[adjId]	*integer*	Adjacency ID.
[routeType]	*enum: dropRoute* | *fecInfoUnavailable* | *bcastReceiveRoute* | *routeCacheConnectedRoute* | *nexthopGroupRoute* | *evpnRoute* | *forwardRoute* | *tunnelFibRoute* | *routeCacheForwardRoute* | *policyRoute* | *pwRoute* | *mplsFloodSetRoute* | *directedBcastRoute* | *srv6Route* | *usedByTunnelRoute* | *vplsL2UcastRoute* | *mplsMcastRoute* | *greMcastRoute* | *slowReceiveRoute* | *routeTypeUnknown* | *receiveRoute* | *mplsRoute* | *vplsMcastRoute* | *invalidRoute* | *nexthopRoute* | *attachedRoute*	Route type.

2.669.1.1.2 AleShmemRouteStatus

[sequence]	*integer*	PD route status sequence.
[state]	*enum: routeProgrammingFailed* | *routeProgrammingSuccess*	Route programming state.

2.670 show ip hardware ale routes vrf all [...]

[cmdErr]	*string*	Error Message.
[numUnprog]	*integer*	Count of unprogrammed routes in all VRFs.
[vrfs]	*table(string) = AleRoute* see 2.667	Dictionary mapping VRF names to ale routes in that VRF.

2.671 show ip hardware ale vrf

vrfStatus	*table(string) = VrfStatus* see 2.671.1	List of all Vrf names and IDs.

2.671.1 VrfStatus

isVrfValid **	*boolean*	Indicates if the VRF is valid. **Since: 4.34.0
tableId **	*integer*	ID used in Ale for the FIB table. **Since: 4.21.3
vrfId	*integer*	ID used on hardware for the VRF.
vrfName	*string*	Name of a VRF.

2.672 show ip hardware fib ecmp resilience [...]

[policyBasedResRouteInfos] **	*AleResEcmpRouteInfos* see 2.672.1	Policy marked resilient routes information. **Since: 4.29.1
resPrefixesToRouteInfos	*table(IPv4 or IPv6 address prefix) = AleResEcmpRouteInfos* see 2.672.1	Map from resilient ECMP prefixes to their covered routes.
vrfName	*string*	VRF name.

2.672.1 AleResEcmpRouteInfos

[capacity]	*integer*	The resilient capacity.
[orderedVias] **	*boolean*	The resilient prefix is configured as ordered. **Since: 4.28.1
[redundancy]	*integer*	The resilient redundancy.
routes	*list of AleResEcmpRouteInfo* see 2.672.1.1	List of resilient routes information.

2.672.1.1 AleResEcmpRouteInfo

fecId	*integer*	The non-resilient FEC ID.
orderedVias **	*boolean*	The vias in the route's ECMP FEC are programmed in a deterministic order. **Since: 4.28.1
prefix	*IP address prefix*	The route's prefix.

reason	*string*	Resason why route is not programmed as resilient.
resFecId	*integer*	The resilient FEC ID.
resilient	*boolean*	The route is programmed as resilient.

2.673 show ip hardware fib ecmp resilience summary [...]

numOrdered **	*integer*	Number of ordered resilient routes. **Since: 4.28.1
numPrefixes	*integer*	Number of programmed resilient ECMP prefixes.
numProgrammed	*integer*	Number of routes programmed as resilient.
numUnprogrammed	*integer*	Number of routes not programmed as resilient.
vrfName	*string*	VRF Name.

2.674 show ip hardware fib load-balance distribution

revision 2

dlbAccessGroupIpv4	*string*	Access group configured for IPv4 selective DLB.
dlbAccessGroupIpv6	*string*	Access group configured for IPv6 selective DLB.
dlbFlowSetSize	*integer*	DLB flow set size.
dlbInactivityDuration	*integer*	DLB inactivity duration in microseconds.
dlbPortAssignmentMode	*integer*	DLB operational mode.
dlbPortLoadingWeight	*integer*	DLB average traffic weight.
dlbSamplingPeriod	*integer*	DLB sampling period in microseconds.
globalDlbEcmpEnabled	*boolean*	Whether or not dynamic load balancing is enabled globally.
globalRlbEcmpEnabled **	*boolean*	Whether or not randomized load balancing is enabled globally. **Since: 4.35.2
globalRprEnable **	*boolean*	Whether or not reactive path rebalancing is enabled globally. **Since: 4.34.0
globalRprSupport **	*boolean*	Whether or not reactive path rebalancing is supported by the platform. **Since: 4.34.1
lbnBasedDlbHashing	*boolean*	Obsolete since release 4.33.1F.
lbnBasedStaticEcmpHashing	*boolean*	Obsolete since release 4.33.1F.
randomSelectionControlSeed	*integer*	DLB Hash Seed.
rebalanceDelta **	*integer*	Reactive path rebalance delta. **Since: 4.35.0
rebalanceProbability-Threshold **	*integer*	Reactive path rebalance probability threshold. **Since: 4.35.0

2.675 show ip hardware fib load-balance distribution dynamic group RANGE flows

dlbId	*integer*	Value of dlbId from query, -1 if no dlbId provided.
enabled	*boolean*	DLB enabled.
exception	*boolean*	Flag that is set to true when an exception is caused.
exceptionMsg	*string*	Display exception message.
flowList	*list of FlowsetTableEntry* see 2.675.1	List containing active Flows.
flowsetTableStateChange **	*boolean*	Flag to check if there was modification in flowset table while retrieving active flows. **Since: 4.34.2

2.675.1 FlowsetTableEntry

dlbId	*integer*	DLB id associated with a DLB Flow.
portMemberAssignment	*string*	Port member through which the DLB flow is egressing.

2.676 show ip hardware fib load-balance distribution dynamic group flows

see 2.675

2.677 show ip hardware fib load-balance distribution dynamic interfaces

enabled	*boolean*	DLB enabled.
exception	*boolean*	Flag that is set to true when an exception is caused.
exceptionMsg	*string*	Display exception message.
intfList	*list of DlbInterface* see 2.677.1	List containing active DLB interfaces.

2.677.1 DlbInterface

dlbId	*string*	Range of DLB ids.
portName	*string*	Port name.
portState	*boolean*	Interface is present in port state table.

2.678 show ip hardware fib routes [...]

[cmdErr]	*string*	Error flag.
[route]	*table(IPv4 or IPv6 address prefix) = FibFec* see 2.56	Mapping prefix to its FibRoute Info.
[vrfName]	*string*	VRF Name.

2.679 show ip igmp access-list [...]

see 2.62

2.680 show ip igmp groups GROUPADDR [...]

groupList	*list of IgmpGroup* see 2.680.1	List of IGMP groups joined on different interfaces.

2.680.1 IgmpGroup

[expires]	*floating point number*	The timestamp in UTC after which this group expires if there is no new activity.
filterMode	*enum: filterModeExclude | filterModeInclude*	Group Mode for IGMP.
groupAddress	*IPv4 address*	Group Address of interest.
[groupDetail]	*IgmpGroupDetail* see 2.680.1.1	Optional details about this IgmpGroup.
[interfaceAddress] **	*IPv4 address*	Interface Address. **Since: 4.22.0
interfaceName	*interface name*	Interface on which this group is joined.
lastReporter	*IPv4 address*	The IP Address of the latest host who joined this group.
uptime	*floating point number*	The timestamp in UTC at which this group last became active.

2.680.1.1 IgmpGroupDetail

interfaceAddress	*IPv4 address*	Interface IP Address.
sources	*table(IPv4 address) = IgmpGroupSource* see 2.680.1.1.1	Map of Source Addresses for this group.

2.680.1.1.1 IgmpGroupSource

[expires]	*floating point number*	The timestamp in UTC after which this source expires if there is no new activity.
uptime	*floating point number*	The timestamp in UTC at which this source last became active.

2.681 show ip igmp groups [...]

see 2.680

2.682 show ip igmp groups count [...]

count	*integer*	Number of Igmp Groups.
[interfaceName]	*interface name*	Interface on which to count groups.

2.683 show ip igmp groups interface INTF [...]

see 2.680

2.684 show ip igmp groups interface INTF count [...]

see 2.682

2.685 show ip igmp host-proxy (debug | interface) [...]

IgmpHostProxyInterfaces	*table(Interface name) = IgmpHostProxyInterface* see 2.685.1	Map of IGMP host-proxy interfaces.

2.685.1 IgmpHostProxyInterface

aclRulesPriorityOrder **	*enum: denyPrecedence | sequenceNumber*	ACL rules priority order. **Since: 4.32.1
[details]	*IgmpHostProxyInterface-Details* see 2.685.1.3	Detailed interface information.
[deviceName]	*string*	Device name.
groupSource	*table(IPv4 address) = GroupDetail* see 2.685.1.1	Mapping between group address and sources in include/exclude mode.
igmpHostProxyAclInfo	*table(string) = IgmpHostProxyAclInfo* see 2.685.1.2	Mapping between ACL name and information about ACL rules.
igmpHostProxyVersion	*integer*	IGMP host-proxy version on this interface.
mrouteMatchCriteria **	*enum: all | iif*	host-proxy IGMP join criteria. **Since: 4.31.0
unsolicitedReportIntvl	*floating point number*	Unsolicited-report interval on this interface in seconds.

2.685.1.1 GroupDetail

excludeSourceList	*list of IPv4 address*	List of exclude sources.
includeSourceList	*list of IPv4 address*	List of include sources.

2.685.1.2 IgmpHostProxyAclInfo

aclInfo	*table(numeric string) = AclInfo* see 2.685.1.2.1	Mapping between sequence number and information about the rule.

2.685.1.2.1 AclInfo

[action]	*string*	Action on the ACL rule(permit/deny).
[errorMsg]	*string*	Message describing the error in the rule, if any.
[group]	*string*	IpAddress of the group in the rule.
[source]	*string*	IpAddress of the source in the rule.

2.685.1.3 IgmpHostProxyInterfaceDetails

v1QueryReceived	*integer*	IGMP V1 Queries recieved.
v1ReportsSent	*integer*	IGMP V1 reports sent.
v2GeneralQueryReceived	*integer*	IGMP V2 General Queries received.
v2GroupQueryReceived	*integer*	IGMP V2 Group Queries received.

v2ReportsSent	*integer*	IGMP V2 reports sent.
v3GeneralQueryReceived	*integer*	IGMP V3 General Queries received.
v3GroupQueryReceived	*integer*	IGMP V3 Group Queries received.
v3GroupSourceQueryReceived	*integer*	IGMP V3 Group-Source specific received.
v3ReportsSent	*integer*	IGMP V3 reports sent.

2.686 show ip igmp host-proxy config-sanity

intfMisconfigs	*table(Interface name) = IHPPotentialMisconfigs* see 2.686.1	Mapping between interface and the IHP potential misconfigs on it.

2.686.1 IHPPotentialMisconfigs

[denyIpMrouteAcls]	*list of string*	Access-lists with "deny ip any any" rule.
[overlappingGroups]	*list of IpAddrAndMask* see 2.302.1.2.2.9	Groups with overlapping permit and deny configurations.
[sourceFilteredGroups]	*list of IpAddrAndMask* see 2.302.1.2.2.9	Groups with include or exclude sources.
[version]	*enum: 1 | 2*	IGMP Host-Proxy configured as IGMP version (1 or 2).

2.687 show ip igmp interface [...]

IgmpInterfaces	*table(Interface name) = IgmpInterface* see 2.687.1	Map of IGMP enabled interfaces.

2.687.1 IgmpInterface

[generalQueryExpiryTime]	*floating point number*	IGMP general query timer expiry in seconds.
igmpEnabled	*boolean*	Denotes whether IGMP is enabled on this interface.
igmpQuerier	*IPv4 address*	Ip Address of the IGMP Querier on this interface.
igmpQueryInterval	*integer*	IGMP Query interval in seconds.
interfaceAddress	*IPv4 address*	Ip Address of this interface.
lastMemberQueryResponse-Count	*integer*	IGMP last member query response count.
lastMemberQueryResponse-Interval	*floating point number*	IGMP last member query response interval in seconds.
maxQueryResponse	*floating point number*	IGMP max query response interval in seconds.
multicastGroups	*list of IPv4 address*	The list of multicast groups joined on this interface.
multicastRoutingEnabled	*boolean*	Denotes whether multicast routing is enabled.
multicastTTL	*integer*	Multicast TTL Threshold.
[otherQuerierExpiryTime]	*floating point number*	Other querier present timer expiry in seconds.
robustness	*integer*	IGMP Robustness on this interface.
routerAlert	*enum: routerAlertMandatory | routerAlertOptional-Connected | routerAlertOptional*	IGMP Router Alert requirement on this interface.
routerVersion	*enum: 3 | - | 1 | 2*	IGMP router version on this interface.
startupQueryCount	*integer*	IGMP startup query count.
startupQueryInterval	*floating point number*	IGMP startup query interval in seconds.

2.688 show ip igmp membership [...]

members	*table(Interface name) = IgmpMemGrpList* see 2.688.1	Map interface to a list of IGMP membership status.

2.688.1 IgmpMemGrpList

groupList	*list of IgmpMemGrp* see 2.688.1.1	List of IGMP membership groups.

2.688.1.1 IgmpMemGrp

excludeSrcs	*list of IP address*	List of Exclude Source Addresses for this group.
groupAddress	*IP address*	Group Address of interest.
includeSrcs	*list of IP address*	List of Include Source Addresses for this group.
interfaceName	*interface name*	Interface on which this group is joined.

2.689 show ip igmp profile [...]

profiles	*table(string) = ProfileInfo* see 2.689.1	Map IGMP Profile to its filter and list of addresses.

2.689.1 ProfileInfo

action	*enum: deny | permit*	Filter type of profile permit/deny.
ranges	*list of Ranges* see 2.689.1.1	Multicast groups covered by the profile.

2.689.1.1 Ranges

max	*IP address*	Maximum address range.
min	*IP address*	Minimum address range.

2.690 show ip igmp snooping [...]

[igmpSnoopingState]	*enum: enabled* | *disabled*	Global state of IGMP Snooping.
[immediateLeave]	*enum: enabled* | *disabled* | *default*	Fast-leave processing global.
[mlagConnectionState] **	*enum: connected* | *initializing* | *unknown* | *disconnected* | *n/a* | *failed*	IGMP Snooping agent MLAG connection state. **Since: 4.30.1
[mlagMountState] **	*enum: failed* | *unknown* | *n/a* | *mounted*	IGMP Snooping agent MLAG mount state. **Since: 4.30.1
[reportFlooding]	*enum: enabled* | *disabled* | *default*	Forwarding of membership report messages.
reportFloodingSwitchPorts	*list of Interface name*	Interfaces for which report-flooding enabled.
robustness	*integer*	Number of queries sent to age out a port's membership in group.
vlans	*table(numeric string) = IgmpSnoopingVlanInfo* see 2.690.1	Map vlan Id to vlan information.

2.690.1 IgmpSnoopingVlanInfo

[evpnProxyActive] **	*boolean*	IGMP proxying enabled via EVPN. **Since: 4.29.2
floodingTraffic	*boolean*	Flooding traffic to VLAN.
groupsOverrun	*boolean*	Indicate if there is an attempt to create group more than maxGroups.
igmpSnoopingState	*enum: enabled* | *disabled*	State of IGMP Snooping.
immediateLeave	*enum: enabled* | *disabled* | *default*	Fast-leave processing on the vlan.
maxGroups	*integer*	Maximum number of multicast groups that can join the vlan.
multicastRouterLearningMode	*pim-dvmrp*	Multicast Router Learning mode.
proxyActive	*boolean*	IGMP snooping proxy active.
pruningActive	*boolean*	True if IGMP snooping pruning active.
reportFlooding	*enum: enabled* | *disabled* | *default*	Forwarding of membership report messages.

2.691 show ip igmp snooping counters [...]

interfaces	*table(Interface name)* = *IgmpSnooping.Cli.IgmpSnoopingCountersInterface* see 2.691.1	Map Interface name with its counter details.
vteps **	*table(string)* = *IgmpSnooping.Cli.IgmpSnoopingCountersInterface* see 2.691.1	Map Vtep with its counter details. **Since: 4.33.2

2.691.1 IgmpSnooping.Cli.IgmpSnoopingCountersInterface

badChecksumIgmpPackets-Received	*integer*	Number of packets received for which IGMP checksum check failed.
badChecksumIpPackets-Received	*integer*	Number of packets received for which IP checksum check failed.
badChecksumPimPackets-Received	*integer*	Number of packets received for which PIM checksum check failed.
[dvmrpPacketsReceived]	*integer*	Number of DVMRP packets received.
[igmpLeaveSent]	*integer*	Number of IGMP v2 leaves sent.
[igmpQueriesSent]	*integer*	Number of IGMP queries sent.
[igmpReportSent]	*integer*	Number of IGMP reports sent.
[igmpV1QueryReceived]	*integer*	Number of IGMP v1 queries received.
[igmpV1ReportReceived]	*integer*	Number of IGMP v1 reports received.
[igmpV2LeaveReceived]	*integer*	Number of IGMP v2 leaves received.
[igmpV2QueryReceived]	*integer*	Number of IGMP v2 queries received.
[igmpV2ReportReceived]	*integer*	Number of IGMP v2 reports received.
[igmpV3QueryReceived]	*integer*	Number of IGMP v3 queries received.
[igmpV3ReportReceived]	*integer*	Number of IGMP v3 reports received.
[mrdPacketsReceived]	*integer*	Number of MRD packets received.
nonIpPacketsReceived	*integer*	Number of non IP packets received.
[otherIgmpPacketsReceived]	*integer*	Number of other IGMP packets.
[otherPacketsSent]	*integer*	Number of other packets sent.
[pimPacketsReceived]	*integer*	Number of PIM packets received.
shortPacketsReceived	*integer*	Number of packets received with not enough IP payload.
unknownIpPacketsReceived	*integer*	Number of packets received with unknown IP Protocol.

2.692 show ip igmp snooping groups [...]

member	*table(numeric string)* = *VlanMembershipInfo* see 2.692.1	Map vlanId to per VLAN group membership information.

2.692.1 VlanMembershipInfo

[groupMembership]	*table(IPv4 or IPv6 address) = GroupMembershipInfo* see 2.692.1.1	Map IGMP group to source membership information.
[routerIntf]	*table(Interface name) = MemberInfo* see 2.692.1.1.1	List of router interfaces.
[routerVtep]	*table(string) = MemberInfo* see 2.692.1.1.1	List of router VTEPs.

2.692.1.1 GroupMembershipInfo

[interface]	*table(Interface name) = MemberInfo* see 2.692.1.1.1	Member ports information.
[vtep]	*table(string) = MemberInfo* see 2.692.1.1.1	Member VTEPs information.

2.692.1.1.1 MemberInfo

[mcastTunnelInfo]	*McastTunnelInfo* see 2.692.1.1.1.1	Multicast Tunnel Information.
[reporterInfo]	*table(IPv4 or IPv6 address) = ReporterInfo* see 2.692.1.1.1.2	Host information.

2.692.1.1.1.1 McastTunnelInfo

[tunnelType]	*pimTunnel*	Type of multicast tunnel.

2.692.1.1.1.2 ReporterInfo

[creationTime]	*floating point number*	The timestamp in UTC when first heard from host.
[expiryTime]	*floating point number*	The timestamp in UTC when membership will expire.
[lastHeard]	*floating point number*	The timestamp in UTC when last heard from host.

2.693 show ip igmp snooping groups count [...]

numberOfGroups	*integer*	Number of groups in membership.

2.694 show ip igmp snooping groups detail [...]

member	*table(numeric string) = VlanMembershipDetailInfo* see 2.694.1	Map vlanId to per VLAN group membership information.

2.694.1 VlanMembershipDetailInfo

[groupMembership]	*table(IPv4 or IPv6 address) = GroupMembershipDetailInfo* see 2.694.1.1	Map IGMP group to source membership information.
[routerIntf]	*table(Interface name) = MemberInfo* see 2.692.1.1.1	List of router interfaces.
[routerVtep]	*table(string) = MemberInfo* see 2.692.1.1.1	List of router VTEPs.

2.694.1.1 GroupMembershipDetailInfo

sourceMembership	*table(IPv4 or IPv6 address) = SourceMembershipInfo* see 2.694.1.1.1	Map Source address to interested interfaces/VTEPs.

2.694.1.1.1 SourceMembershipInfo

[detail]	*SourceMembershipDetailInfo* see 2.694.1.1.1.1	Additional information about the source.
[excludeIntf]	*table(Interface name) = MemberInfo* see 2.692.1.1.1	Filter mode exclude member ports information.
[excludeVtep]	*table(string) = MemberInfo* see 2.692.1.1.1	Filter mode exclude member VTEPs information.
[includeIntf]	*table(Interface name) = MemberInfo* see 2.692.1.1.1	Filter mode include member ports information.
[includeVtep]	*table(string) = MemberInfo* see 2.692.1.1.1	Filter mode exclude member VTEPs information.

2.694.1.1.1.1 SourceMembershipDetailInfo

creationTime	*floating point number*	Duration since switch boot when source was created.
creationTimeUTC **	*floating point number*	Timestamp in UTC when source was created. **Since: 4.35.2

2.695 show ip igmp snooping groups proxy [...]

detail	*boolean*	Include detailed attributes.
vlanInfo	*table(numeric string) = IgmpSnoopingProxyPorts* see 2.695.1	Dict of VlanId to per interface proxy related information.

2.695.1 IgmpSnoopingProxyPorts

portInfo	*table(Interface name) = IgmpSnoopingProxyGroups* see 2.695.1.1	Dict of Interface to Groups that are reported.

2.695.1.1 IgmpSnoopingProxyGroups

groups	*table(IPv4 or IPv6 address) = IgmpSnoopingProxyGroupInfo* see 2.695.1.1.1	Map Multicast addresses to an optional sourceList.

2.695.1.1.1 IgmpSnoopingProxyGroupInfo

[sourceList]	*IgmpSnoopingProxySourceList* see 2.695.1.1.1.1	Optional Source List.

2.695.1.1.1.1 IgmpSnoopingProxySourceList

filterMode	*enum: Include | Exclude*	Source filter mode.
sources	*list of IP address*	List of sources associated with the multicast group.

2.696 show ip igmp snooping mrouter [...]

vlans	*table(numeric string) = IgmpSnoopingMrouterVlan* see 2.696.1	Maps a VLAN ID to VLAN information.

2.696.1 IgmpSnoopingMrouterVlan

interfaces	*list of IgmpSnoopingMrouterDetail* see 2.696.1.1	Mrouter interface info.

2.696.1.1 IgmpSnoopingMrouterDetail

[address]	*IP address*	Source address of the interface.
[expireTime]	*floating point number*	UTC time at which this router will expire.
[firstHeardTime]	*floating point number*	UTC time at which this router is first heard.
interfaceName	*interface name*	Multicast router interface.
[lastHeardTime]	*floating point number*	UTC time at which this router is last heard.
routerType	*enum: dynamic | mrd | unknown | pim | dvmrp | static | querier*	Type of multicast router.

2.697 show ip igmp snooping report-flooding [...]

[reportFloodingEnabled]	*boolean*	True if ReportFlooding enabled.
reportFloodingSwitchPorts	*list of Interface name*	Interfaces for which report-flooding enabled.
[vlans]	*table(numeric string) = IgmpSnoopingVlanReportFlooding* see 2.697.1	Maps vlanId to vlan information.

2.697.1 IgmpSnoopingVlanReportFlooding

[reportFloodingEnabled]	*boolean*	True if report flooding enabled in vlan.
reportFloodingOperationalState	*enum: enabled | disabled | default*	State of report flooding in vlan.
sanityCheckFailedPorts	*list of Interface name*	Sanity check for all Switchports.
switchPorts	*table(Interface name) = string*	A mapping of ports forwarding IGMP membership report to port status.

2.698 show ip igmp static-groups [...]

intfAddrs	*table(Interface name) = IgmpStaticGroupsInterface* see 2.698.1	Map interface name to list of source-group addrs pairs.

2.698.1 IgmpStaticGroupsInterface

[aclInfo]	*table(string) = IgmpAclInfo* see 2.698.1.1	map from ACL names to ACL info objects.
groupAddrsList	*list of InterfaceAddrs* see 2.698.1.2	list of source-group addr pairs for this interface.

2.698.1.1 IgmpAclInfo

aclDetails	*list of AclInfo* see 2.698.1.1.1	list of objects containing detailed information about ACLs.
[errorMessage]	*string*	error message for improperly configured ACL.

2.698.1.1.1 AclInfo

[sequence]	*integer*	The sequence number for an ACL on an interface.
sourceGroupInfo	*string*	source and group addresses for this ACL or an error message.

2.698.1.2 InterfaceAddrs

groupAddr	*IPv4 address*	group address for group interface.
sourceAddr	*IPv4 address*	source address for group interface.

2.699 show ip igmp static-groups group [...]

`sourceGroups`	*table(IPv4 address) = IgmpInterfacesList* see 2.699.1	Map from sourceGroup addr to interface names.

2.699.1 IgmpInterfacesList

`interfaces`	*list of Interface name*	List of interface names.

2.700 show ip igmp statistics [...]

IgmpStatistics	*table(Interface name) = IgmpStatisticsInterface* see 2.700.1	Map of statistics for IGMP interfaces.

2.700.1 IgmpStatisticsInterface

errorPacketReceived	*integer*	error packets received.
otherPacketReceived	*integer*	other packets received.
totalGeneralQueriesSent	*integer*	IGMP total general queries sent.
v1QueriesReceived	*integer*	IGMP v1 queries received.
v1QueriesSent	*integer*	IGMP v1 queries sent.
v1ReportReceived	*integer*	IGMP v1 reports received.
v2LeaveReceived	*integer*	IGMP v2 leaves received.
v2QueriesReceived	*integer*	IGMP v2 queries received.
v2QueriesSent	*integer*	IGMP v2 queries sent.
v2ReportReceived	*integer*	IGMP v2 reports received.
v3GSQueriesSent	*integer*	IGMP v3 group-specific queries sent.
v3GSSQueriesSent	*integer*	IGMP v3 group-source-specific queries sent.
v3QueriesReceived	*integer*	IGMP v3 queries received.
v3QueriesSent	*integer*	IGMP v3 queries sent.
v3ReportReceived	*integer*	IGMP v3 reports received.

2.701 show ip interface [...]

revision 2

interfaces	*table(Interface name)* = *IpStatus* see 2.701.1	Maps an interface name to its IP status.

2.701.1 IpStatus

addresslessForwarding	*enum: isInvalid* | *isTrue* | *isFalse*	V4 Forwarding mode on the V6 interface.
arpAgingTimeout **	*integer*	Configured ARP aging timeout. **Since: 4.33.0
[description]	*string*	Description of this interface.
directedBroadcastEnabled	*boolean*	Whether or not Directed Broadcast is enabled for this intf.
enabled	*boolean*	Whether or not this interface is enabled.
gratuitousArp **	*boolean*	Whether or not gratuitous ARP is accepted. **Since: 4.20.5
interfaceAddress	*InterfaceAddress* see 2.571.1.2	Network Layer Addresses for this interface.
[interfaceAddressBrief] **	*InterfaceAddressBrief* see 2.571.1.3	Network layer address for this interface. **Since: 4.24.2
interfaceStatus	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
[ipv4Routable0] **	*boolean*	Whether or not IPv4 routable 0.0.0.0/8is enabled. **Since: 4.29.2
[ipv4Routable240] **	*boolean*	Whether or not IPv4 routable 240.0.0.0/4is enabled. **Since: 4.24.2
[isVrrpBackup] **	*boolean*	Whether if the VRRP instance is in VRRP backup mode. **Since: 4.30.2
lineProtocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
localProxyArp	*boolean*	Whether or not local proxy-ARP is enabled.
[lossOfConnectivityReason] **	*cfm*	Layer 3 interface connectivity status. **Since: 4.31.2
[maxMssEgress] **	*integer*	TCP MSS ceiling in bytes enforced on packets forwarded to the network. **Since: 4.21.3

[maxMssIngress] **	*integer*	TCP MSS ceiling in bytes enforced on packets arriving from the network. **Since: 4.21.3
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.
proxyArp	*boolean*	Whether or not proxy-ARP is enabled.
proxyArpAllowDefault **	*boolean*	Whether or not proxy-ARP always consider the default route if it is present in the routing table. **Since: 4.30.2
[proxyArpVirtualMacAddress] **	*MAC address*	The virtual MAC address used in proxy-ARP or local proxy-ARP. **Since: 4.30.2
[routedAddr] **	*MAC address*	The routed MAC address used in proxy-ARP or local proxy-ARP. **Since: 4.30.2
[urpf]	*enum: strictDefault | disable | strict | loose | looseNonDefault*	Unicast Reverse Path Forwarding mode on the interface.
v4IntfForwarding **	*boolean*	V4 Forwarding is enabled on the interface. **Since: 4.31.2
[vrId] **	*integer*	The VRRP group of the virtual router seleted in proxy ARP. **Since: 4.30.2
[vrf]	*string*	Name of the VRF.

2.702 show ip interface brief [...]

interfaces	*table(Interface name) = IpStatusBrief* see 2.702.1	Maps an interface name to an abbreviated IP status.

2.702.1 IpStatusBrief

interfaceAddress	*InterfaceAddressBrief* see 2.571.1.3	Network layer address for this interace.
[interfaceAddressBrief] **	*InterfaceAddressBrief* see 2.571.1.3	Network layer address for this interface. **Since: 4.24.2
interfaceStatus	*enum: inactive | connected | initializing | unknown | notapplicable | errdisabled | maint-down | adminIsolated | noSignal | uninitialized | no-resource | signal | admin | notconnect | disabled | autoIsolated*	Connection status of the interface.
[ipv4Routable0] **	*boolean*	Whether or not IPv4 routable 0.0.0.0/8is enabled. **Since: 4.29.2
[ipv4Routable240] **	*boolean*	Whether or not IPv4 routable 240.0.0.0/4is enabled. **Since: 4.24.2

lineProtocolStatus	*enum: lowerLayerDown | unknown | down | up | testing | notPresent | notApplicable | dormant*	Line protocol status.
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.
[nonRoutableClassEIntf] **	*boolean*	True if class E address configured and class E address routing is disabled. **Since: 4.24.2

2.703 show ip large-community-list [...]

ipLargeCommunityLists	*table(string) = IpLargeCommunityList* see 2.703.1	Table of large community lists by name.

2.703.1 IpLargeCommunityList

entries	*list of IpCommunityListEntry* see 2.646.1.1	Large community list entries sorted by increasing sequence number.

2.704 show ip load-sharing trident fields

revision 2

ecmpHashFieldsCommon **	*EcmpHashFieldsCommon* see 2.704.1	ECMP hashing on MISC fields. **Since: 4.23.2
ecmpHashFieldsGtp **	*EcmpHashFieldsGtp* see 2.704.2	ECMP hashing on GTP fields. **Since: 4.23.1
ecmpHashFieldsIp	*EcmpHashFieldsIp* see 2.704.3	ECMP hashing on IP fields.
ecmpHashFieldsIpv6	*EcmpHashFieldsIpv6* see 2.704.4	Ecmp hashing on IPV6 fields.
hashSeed	*integer*	hash seed.

2.704.1 EcmpHashFieldsCommon

sysMacAddrHashed	*boolean*	ECMP hashing on the system MAC address.

2.704.2 EcmpHashFieldsGtp

gtpVersion	*string*	Hash on either GTP version 1 or 2.
teid	*boolean*	Ecmp hashing on GTP fields.

2.704.3 EcmpHashFieldsIp

Could also be an instance of:
EcmpHashFieldsIpv6 2.704.4

dstIpHashed	*boolean*	ECMP hashing on destination IP address.
dstIpPortHashed	*boolean*	ECMP hashing on destination IP port.
ingressIntfHashed	*boolean*	ECMP hashing on ingress interface.
srcIpHashed	*boolean*	ECMP hashing on source IP address.
srcIpPortHashed	*boolean*	ECMP hashing on source IP port.

2.704.4 EcmpHashFieldsIpv6

dstIpHashed	*boolean*	ECMP hashing on destination IP address.
dstIpPortHashed	*boolean*	ECMP hashing on destination IP port.
flowLabelHashed	*boolean*	ECMP hashing on flow label.
ingressIntfHashed	*boolean*	ECMP hashing on ingress interface.
srcIpHashed	*boolean*	ECMP hashing on source IP address.
srcIpPortHashed	*boolean*	ECMP hashing on source IP port.

2.705 show ip mroute GROUP_OR_SOURCE1 interface [...]

revision 2

bidirectional	*MrouteInterfaceDetails* see 2.705.1	IP Mroute Interfaces for Bidirectional PIM.

sparseMode	*MrouteSmInterfaces* see 2.24	IP Mroute Interfaces for Sparse-mode PIM.

2.705.1 MrouteInterfaceDetails

interfaces	*table(Interface name)* = *MrouteInterface* see 2.705.1.1	Map of interfaces for multicast route.

2.705.1.1 MrouteInterface

[address]	*IP address*	Interface IP address.
downstreamJoinState	*enum: joined* | *noInfo* | *prunePending*	Downstream join state.
forward	*boolean*	Member of outgoing interface set.
iAmDf	*boolean*	This Pim router is the designated router on this interface.
[lastJoinReceived]	*floating point number*	UTC time at which the last downstream join was received.
localReceiverInclude	*boolean*	Local receiver include (*,G,I).

2.706 show ip mroute [...]

revision 2

bidirectional	*Groups* see 2.706.1	IP Mroute for Bidirectional PIM.
sparseMode	*GroupSms* see 2.25	IP Mroute for Sparse-mode PIM.

2.706.1 Groups

groups	*table(IPv4 or IPv6 address) = Mroute* see 2.706.1.1	Map of bidirectional mode PIM multicast groups.

2.706.1.1 Mroute

[active]	*boolean*	Group active.
creationTime	*floating point number*	UTC time at which the route was created.
[details]	*MrouteInterfaceDetails* see 2.705.1	Detailed information for this multicast route.
joinDesired	*boolean*	Join Desired (*, G).
oifList	*list of Interface name*	Outgoing interface list.
[rp]	*IP address*	RP(G): The Rendezvous Point for this group.
[rpf]	*Rpf* see 2.706.1.1.1	Reverse path forwarding information.
[rpfFrr] **	*Rpf* see 2.706.1.1.1	Reverse path forwarding information for MoFRR. **Since: 4.20.0
[rpfFrrInterface] **	*interface name*	Reverse path forwarding interface for MoFRR. **Since: 4.20.0
[rpfInterface]	*interface name*	Reverse path forwarding interface, packets for this mroute must arrive on this interface to be accepted/forwarded. If this value is set to 'Register', the RPF interface is the register tunnel.
upstreamJoinState	*enum: upJoined | upNotJoined*	Upstream joined state.

2.706.1.1.1 Rpf

rpfMetric	*integer*	RPF route metric.
[rpfNeighbor]	*IP address*	RPF neighbor.
rpfPreference	*integer*	RPF route preference.
rpfPrefix	*IP address prefix*	RPF route prefix.
rpfRib	*enum: M | U | none*	RPF routing table.

2.707 show ip mroute bidirectional GROUP_ADDR interface [...]

see 2.706.1

2.708 show ip mroute bidirectional [...]

see 2.706.1

2.709 show ip mroute bidirectional count [...]

groups	*integer*	Number of groups.

2.710 show ip mroute count [...]

revision 2

bidirectional	*MrouteBidirCount* see 2.709	count for bidirectional PIM.
sparseMode	*MrouteCount* see 2.26	count for Sparse-mode PIM.

2.711 show ip mroute sparse-mode (sources | groups) [...]

isSource	*boolean*	If true, we print S-> no of G.
sourceGroup	*table(numeric string) = SourceGroupCollection* see 2.711.1	S-> no of G or G-> no of S mapping.

2.711.1 SourceGroupCollection

sourceOrGroupAddrs	*table(IPv4 or IPv6 address) = string*	List of IP address.

2.712 show ip mroute vrf all [...]

vrfs	*table(string) = IpMroutesAll* see 2.706	Multicast routes for all VRFs.

2.713 show ip msdp peer [...]

revision 2

peerList	*list of PeerInfo* see 2.713.1	list of peers.

2.713.1 PeerInfo

acceptedSas	*list of SaMsg* see 2.713.1.1	List of Accepted SAs.
[connSourceAddress]	*IPv4 address*	The connection source IP address, If Available.
[connSourceInterface]	*interface name*	Connection source interface used, If available.
[description]	*string*	Description of MSDP peer.
peerIpAddress	*IPv4 address*	Ip address of the MSDP peer.
resetCount	*integer*	MSDP peer connection reset count.
saCount	*integer*	Number of SA messages from this MSDP peer in the SA cache.
saFilterIn	*string*	Access list filtering of SA input.
saFilterOut	*string*	Access list filtering of SA output.
[sessionStartTime]	*floating point number*	UTC time at which the peer last switched state to established.
state	*enum: inactive | established | listen | connecting | disabled*	Current status of the peer.

2.713.1.1 SaMsg

[remoteAddress]	*IPv4 address*	Heard from this peer.
rpAddress	*IPv4 address*	Addess of the Rendezvous Point.
sourceGroupPair	*SGPair* see 2.713.1.1.1	(S,G) Pair.

2.713.1.1.1 SGPair

groupAddress	*IPv4 address*	Group Address.
sourceAddress	*IPv4 address*	Source Address.

2.714 show ip msdp peer authentication [...]

peers	*table(string) = Routing.Msdp.Model.PeerAuthentication.TcpAoInfo* see 2.714.1	Maps peer addresses to their TcpAoInfo.
tcpAoSupported **	*boolean*	True if tcp-ao is supported by the kernel. **Since: 4.36.0

2.714.1 Routing.Msdp.Model.PeerAuthentication.TcpAoInfo

activeKeyIds	*list of integer*	All active key IDs.
activeKeys	*table(string) = Routing.Msdp.Model.PeerAuthentication.TcpAoMktStat* see 2.714.1.1	All active key details.
[currentKeyId]	*integer*	Key ID of the current TCP-AO key.
macAlgorithm	*string*	MAC computation algorithm.
[receiveNextKeyId]	*integer*	Key ID of the receive next TCP-AO key.
sharedSecretProfile	*string*	TCP-AO shared secret profile.
sharedSecretProfileState	*string*	State of the Shared Secret Profile.

2.714.1.1 Routing.Msdp.Model.PeerAuthentication.TcpAoMktStat

[addedTimestamp]	*floating point number*	Time stamp when MKT is added on the socket.
[lastRemovalFailTimestamp]	*floating point number*	Time stamp of the last failed removal.
[lastSecretUpdateFailTimestamp]	*floating point number*	Time stamp of the last failed secret update.
[lastSecretUpdateTimestamp]	*floating point number*	Time stamp of the last successful secret update.
[rnextActiveTimestamp]	*floating point number*	Time stamp when MKT becomes rnext on the socket.

2.715 show ip msdp pim sa-cache [...]

saCache	*list of SaMsg* see 2.713.1.1	MSDP soure active messages for local Pim RP.

2.716 show ip msdp sa-cache [...]

acceptedSaMsg	*list of SaMsg* see 2.713.1.1	List of accepted SA Messages.
[rejectedSaMsg]	*list of SaMsg* see 2.713.1.1	List of rejected SA Messages.

2.717 show ip msdp summary [...]

revision 2

peerList	*list of PeerSummary* see 2.717.1	list of peers.

2.717.1 PeerSummary

Could also be an instance of:
PeerInfo 2.713.1

[description]	*string*	Description of MSDP peer.

peerIpAddress	*IPv4 address*	Ip address of the MSDP peer.
resetCount	*integer*	MSDP peer connection reset count.
saCount	*integer*	Number of SA messages from this MSDP peer in the SA cache.
[sessionStartTime]	*floating point number*	UTC time at which the peer last switched state to established.
state	*enum: inactive | established | listen | connecting | disabled*	Current status of the peer.

2.718 show ip multicast boundary [...]

mcastBoundaryInterfaces	*table(Interface name) = McastBoundaryInterface* see 2.718.1	Map of interface to multicast boundary status.

2.718.1 McastBoundaryInterface

boundary	*table(IPv4 or IPv6 address prefix) = boolean*	Map of denied prefix to its data plane filtering status.

2.719 show ip name-server [...]

nameServerConfigs **	*list of NameServerConfig* see 2.528.2	List of configured name servers. **Since: 4.26.0
v4NameServers	*list of string*	List of IPV4 name servers.
v6NameServers	*list of string*	List of IPV6 name servers.

2.720 show ip nat ((access-list \| acl)) [...]

aclList	*list of NatAcl* see 2.720.1	List of the ACLs to display.

2.720.1 NatAcl

aclInfo **	*table(string) = NatAclInfo* see 2.720.1.2	NAT configuration for the ACL. **Since: 4.24.1
aclName	*string*	The name of the specified ACL.
aclRules	*list of AclRule* see 2.720.1.1	Rules that belongs to this ACL, ordered by the sequence number of the rule.
interfaces	*list of Interface name*	List of interfaces using this ACL for NAT.
profiles **	*list of string*	List of profiles using this ACL for NAT. **Since: 4.23.2

2.720.1.1 AclRule

description	*string*	Textual description of the ACL rule if valid, or explanation of why the rule doesn't apply if it isn't.
seqNo	*integer*	Sequence number of the rule.

valid	*boolean*	True if NAT can use this rule to filter translations.

2.720.1.2 NatAclInfo

addrOnly	*boolean*	Access list used in address only NAT.
fullCone	*boolean*	Access list used in full cone NAT.
poolId	*integer*	NAT pool ID associated with the access list.

2.721 show ip nat counters [...]

revision 2

vrfs	*table(string) = NatCounters* see 2.721.1	NAT counters of each VRF.

2.721.1 NatCounters

deleteConnectionErrors	*integer*	Conntrack delete connection errors.
deleteConnectionEvents	*integer*	Number of Conntrack delete connection events.
[eagainDumpCnt]	*integer*	Number of Netlink no data errors during kernel sync.
[eagainRecvCnt]	*integer*	Number of Netlink no data errors during kernel update.
[enobufDumpCnt]	*integer*	Number of Netlink no space errors during kernel sync.
[enobufMsgCnt]	*integer*	Number of Netlink no space errors during kernel update.
iptablesWriteErrors	*integer*	Kernel iptables write errors.
kernelSyncInProgress	*integer*	Conntrack table sync already in progress count.
kernelSyncRequestErrors	*integer*	Conntrack table sync request errors.
kernelSyncRequests	*integer*	Conntrack table sync requests.
[maxMsgCntInRecvBuf]	*integer*	Max number of messages processed in one buffer.
netlinkBadMessageLength-Errors	*integer*	Number of Netlink bad message length errors.
netlinkDumpDoneErrors	*integer*	Number of Netlink unexpected dump done messages.
netlinkDumpIgnoreTcp-Connections	*integer*	Number of Netlink TCP connections ignored in dump.
[netlinkMsgErrors]	*integer*	Number of Netlink msg errors.
netlinkNoBufferErrors	*integer*	Number of Netlink no space errors.
netlinkNoSpaceErrors	*integer*	Number of Netlink no space in message errors.
netlinkReceiveErrors	*integer*	Number of Netlink receive errors.
netlinkSeqNumMismatches	*integer*	Number of Netlink sequence number mismatches.
netlinkSeqNumRange-Mismatches	*integer*	Number of Netlink sequence number out of range errors.
netlinkSyncCreateTxErrors **	*integer*	Number of Netlink Sync creation event errors. **Since: 4.25.0
netlinkSyncDeleteTxErrors **	*integer*	Number of Netlink Sync deletion event errors. **Since: 4.25.0
netlinkSyncEagainErrors **	*integer*	Number of Netlink Sync EAGAIN errors. **Since: 4.25.0

netlinkSyncFCConflictErrors **	*integer*	Number of Netlink Sync full cone conflict event errors. **Since: 4.30.1
netlinkSyncMsgErrors **	*integer*	Number of Netlink Sync messages with errors. **Since: 4.25.0
netlinkSyncNoBufferErrors **	*integer*	Number of Netlink Sync ENOBUFS errors. **Since: 4.25.0
netlinkSyncReceiveErrors **	*integer*	Number of Netlink Sync receive errors. **Since: 4.25.0
netlinkSyncUpdateTxErrors **	*integer*	Number of Netlink Sync update event errors. **Since: 4.25.0
netlinkTruncatedMessages	*integer*	Number of Netlink truncated messages.
newConnectionEvents	*integer*	Number of Conntrack new connection events.
[nlAdd300s] **	*integer*	300s NAT entries learning rate. **Since: 4.27.1
[nlAdd30s] **	*integer*	30s NAT entries learning rate. **Since: 4.27.1
[nlAdd5s] **	*integer*	5s NAT entries learning rate. **Since: 4.27.1
[nlAdd60s] **	*integer*	60s NAT entries learning rate. **Since: 4.27.1
[nlDel300s] **	*integer*	300s NAT entries deletion rate. **Since: 4.27.1
[nlDel30s] **	*integer*	30s NAT entries deletion rate. **Since: 4.27.1
[nlDel5s] **	*integer*	5s NAT entries deletion rate. **Since: 4.27.1
[nlDel60s] **	*integer*	60s NAT entries deletion rate. **Since: 4.27.1
updateConnectionErrors	*integer*	Conntrack update connection errors.
updateConnectionEvents	*integer*	Number of Conntrack update connection events.

2.722 show ip nat dynamic counters [...]

profiles	*table(string) = NatDynamicCounters-ProfileModel* see 2.722.1	NAT profiles, keyed by profile name.

2.722.1 NatDynamicCountersProfileModel

other	*NatDynamicCountersProto-Model* see 2.722.1.1	Non-TCP, non-UDP NAT counters.
tcp	*NatDynamicCountersProto-Model* see 2.722.1.1	TCP NAT counters.

udp	*NatDynamicCountersProtoModel* see 2.722.1.1	UDP NAT counters.

2.722.1.1 NatDynamicCountersProtoModel

destination	*integer*	Number of destination NAT packets.
hairpin	*integer*	Number of hairpin NAT packets.
source	*integer*	Number of source NAT packets.

2.723 show ip nat flow action [...]

policies	*table(string) = NatFlowActionPolicy* see 2.723.1	NAT flow policies, keyed by name.

2.723.1 NatFlowActionPolicy

matches	*table(string) = NatFlowMatchActions* see 2.723.1.1	Matches for this policy, keyed by match name.
[profiles]	*list of string*	List of profiles using this NAT flow policy.

2.723.1.1 NatFlowMatchActions

actions	*table(string) = NatFlowAction* see 2.723.1.1.1	Actions for this match, keyed by action name.

2.723.1.1.1 NatFlowAction

[flowType]	*string*	NAT flow type.
intfs	*table(Interface name) = NatFlowIntf* see 2.723.1.1.1.2	Flow outputs, keyed by interface.
natDst	*IpAddrAndPort* see 2.723.1.1.1.1	The destination IP address and port for the NAT translation.
natSrc	*IpAddrAndPort* see 2.723.1.1.1.1	The source IP address and port for the NAT translation.

2.723.1.1.1.1 IpAddrAndPort

ip	*IPv4 address*	Ip address.
port	*integer*	Port.

2.723.1.1.1.2 NatFlowIntf

mac	*MAC address*	The destination MAC address for the output.

vlanId	*integer*	The VLAN ID for the output.

2.724 show ip nat flow match [...]

hardware	*boolean*	NAT flow hardware state.
policies	*table(string) = NatFlowMatchPolicy* see 2.724.1	NAT flow policies, keyed by name.

2.724.1 NatFlowMatchPolicy

matches	*table(string) = NatFlowMatch* see 2.724.1.1	Matches for this policy, keyed by match name.

2.724.1.1 NatFlowMatch

flow	*NatFlowAddress* see 2.724.1.1.1	NAT flow match fields.
[mcGroup]	*integer*	Hardware multicast replication group.
[ucGroup]	*integer*	Hardware unicast replication group.

2.724.1.1.1 NatFlowAddress

dstAddr	*IpAddrAndMask* see 2.302.1.2.2.9	The destination IP address to match on.
dstPortEnd	*integer*	The end of the destination port range of the match.
dstPortStart	*integer*	The start of the destination port range of the match.
priority	*integer*	The priority of the match.
protocol	*integer*	The protocol of the match.
srcAddr	*IpAddrAndMask* see 2.302.1.2.2.9	The source IP address to match on.
srcPortEnd	*integer*	The end of the source port range of the match.
srcPortStart	*integer*	The start of the source port range of the match.

2.725 show ip nat flow profile [...]

hardware	*boolean*	NAT flow hardware state.
profiles	*table(string) = NatFlowProfilePolicy* see 2.725.1	NAT flow profiles, keyed by name.

2.725.1 NatFlowProfilePolicy

policies	*table(string) = NatFlowPolicyInfo* see 2.725.1.1	NAT flow policy details, keyed by policy name.

2.725.1.1 NatFlowPolicyInfo

[match]	*table(string) = NatFlowMatchInfo* see 2.725.1.1.1	NAT flow match details, keyed by match name.

2.725.1.1.1 NatFlowMatchInfo

groupMc	*integer*	Multicast replication group used for multicast traffic.
groupUc	*integer*	Multicast replication group used for unicast traffic.

2.726 show ip nat logging

enabled	*boolean*	NAT event logging is enabled.

2.727 show ip nat pool [...]

[natPools]	*table(string) = NatPool* see 2.727.1	Map of NAT pools keyed by their name.
[poolName]	*string*	Name of the NAT pool to show.
[showSplit] **	*boolean*	Show local NAT sync port range split. **Since: 4.29.2

2.727.1 NatPool

natRanges	*list of NatRange* see 2.727.1.1	List of NAT pool ranges.
poolId **	*integer*	NAT pool ID. **Since: 4.24.1
portOnly **	*boolean*	NAT Port only pool. **Since: 4.31.0
prefixLen	*integer*	Length of the prefix.

2.727.1.1 NatRange

endIp	*IPv4 address*	NAT end IP address.
endPort	*integer*	NAT end port number.
[localEndPort] **	*integer*	NAT sync port split end. **Since: 4.29.2
[localStartPort] **	*integer*	NAT sync port split start. **Since: 4.29.2
startIp	*IPv4 address*	NAT start IP address.

startPort	*integer*	NAT start port number.

2.728 show ip nat profile [...]

profiles	*list of NatProfile* see 2.728.1	List of profiles.

2.728.1 NatProfile

[intfList]	*table(Interface name) = integer*	List of interfaces configured with the NAT profile.
profileId	*integer*	The numeric ID assigned to each NAT profile.
profileName	*string*	The name of the specified NAT profile.
vrfName **	*string*	The VRF associated with each NAT profile. **Since: 4.23.1

2.729 show ip nat service-list [...]

serviceLists	*list of NatServiceList* see 2.729.1	List of service-list.

2.729.1 NatServiceList

serviceCmdList	*list of NatServiceList-CommandModel* see 2.729.1.1	List of service commands.
serviceListName	*string*	The name of the specified service-list.

2.729.1.1 NatServiceListCommandModel

protocol	*string*	protocol for ALG.

2.730 show ip nat synchronization

connAttempts	*integer*	Number of attempts at synchronizing with peer.
connEstablishedTime	*floating point number*	Peer Connection Establishment time.
connPort	*integer*	Port used for the connection.
connSrcIp	*IPv4 address*	Connection source Ip.
connState	*enum: connected* | *disconnected* | *init* | *failed* | *connecting* | *disconnecting*	State of the connection with peer.
fwdToPeer	*table(string) = NatSyncFwdToPeer* see 2.730.2	NAT profiles' fowardTopeer status.
kernelDevName	*string*	Kernel device name.
localIntf	*interface name*	Local interface.
natVerCompatible	*boolean*	Peer's version is Compatible.
natVersion	*Version* see 2.730.1	Nat version.
peerIpAddr	*IPv4 address*	Peer's IP address.
portRangeMode	*enum: portRangeUpper* | *portRangeFull* | *portRangeLower*	Port range mode used in the system.
shutdown	*boolean*	Shutdown StateFalse: peer connection is administratively down, True: peer connection is administratively up.
statusMountState	*enum: mountUnmounted* | *mountFailed* | *mountMounted* | *mountMounting*	Mount state of peer's status.
versionMountState	*enum: mountUnmounted* | *mountFailed* | *mountMounted* | *mountMounting*	Mount state of peer's version.

2.730.1 Version

maxVersion	*integer*	Maximum version number.
minVersion	*integer*	Minimum version number.

2.730.2 NatSyncFwdToPeer

peerIntf	*interface name*	Local interface connected to peer.
peerIpAddr	*IPv4 address*	Peer's IP address.
peerResolved	*boolean*	Peer's reachability status.

2.731 show ip nat synchronization advertised-translations [...]

revision 3

detailedView	*boolean*	includes additional details if True.
translations	*list of Translation* see 2.731.1	List of NAT translations active on this interface.

2.731.1 Translation

[destinationAddress]	*IpAddr* see 2.731.1.1	The destination IP address and port/mask of the packet.
[details]	*Details* see 2.731.1.2	Details, if requested.
globalAddress	*IpAddr* see 2.731.1.1	The translated source IP address and port/mask of the packet.
[interface]	*string*	Interface or NAT profile name.
natType	*enum: D-TW | STAT | AO | DYN | FC*	Static NAT or Dynamic NAT.
[newDestinationAddress] **	*IpAddr* see 2.731.1.1	The translated destination IP address and port/mask of the packet. **Since: 4.36.0
[sourceAddress]	*IpAddr* see 2.731.1.1	The original source IP address and port/mask of the packet.
target	*enum: SRC | DST*	Source NAT or destination NAT.

2.731.1.1 IpAddr

Could also be an instance of:
IpAddrAndMask 2.302.1.2.2.9
IpAddrAndPort 2.723.1.1.1.1

ip	*IPv4 address*	Ip address.

2.731.1.2 Details

lastActivityTime	*floating point number*	Last time data packets matching this translation were seen.
packetCount	*integer*	Number of packets translated from the original IP address.
packetReplyCount	*integer*	Number of packets translated to the original IP address.
[protocol]	*enum: UDP | TCP | IGMP | ICMP*	IP Protocol, if specified.
[protocolNumber]	*integer*	IP Protocol Number, if specified.
[sourceVrfName]	*string*	Source VRF name.

[tcpState]	*enum: CLOSE | MAX | LAST_ACK | TIME_WAIT | NONE | SYN_SENT | ESTABLISHED | LISTEN | UNACK | RETRANS | TIMEOUT_MAX | FIN_WAIT | IGNORE | CLOSE_WAIT | SYN_RECV*	State of the TCP connection.
vrfName	*string*	VRF name.

2.732 show ip nat synchronization discovered-translations [...]

revision 3

see 2.731

2.733 show ip nat synchronization peer

revision 2

connAttempts	*integer*	Number of attempts at synchronizing with peer.
connEstablishedTime	*floating point number*	Peer Connection Establishment time.
connPort	*integer*	Port used for the connection.
connSrcIp	*IPv4 address*	Connection source Ip.
connState	*enum: connected | disconnected | init | failed | connecting | disconnecting*	State of the connection with peer.
kernelDevName	*string*	Kernel device name.
localIntf	*interface name*	Local interface.
natVerCompatible	*boolean*	Peer's version is Compatible.
natVersion	*Version* see 2.730.1	Nat version.
peerIpAddr	*IPv4 address*	Peer's IP address.
portRangeMode **	*enum: portRangeUpper | portRangeFull | portRangeLower*	Port range mode used in the system. **Since: 4.28.2
shutdown	*boolean*	Shutdown StateFalse: peer connection is administratively downTrue: peer connection is administratively up.
statusMountState	*enum: mountUnmounted | mountFailed | mountMounted | mountMounting*	Mount state of peer's status.
versionMountState	*enum: mountUnmounted | mountFailed | mountMounted | mountMounting*	Mount state of peer's version.

2.734 show ip nat translation (address-only | full-cone) flows [...]

intfTranslationFlows	*table(string) = IntfTranslationFlows* see 2.734.1	List of active NAT translation flows per interface.

2.734.1 IntfTranslationFlows

translationFlows	*list of TranslationFlows* see 2.734.1.1	Flows using an address-only or full-cone NAT Translation.
vrfName	*string*	VRF name.

2.734.1.1 TranslationFlows

flows	*list of TranslationFlow* see 2.734.1.1.1	List of active NAT translations.
globalAddr	*IpAddrAndPort* see 2.723.1.1.1.1	NAT address.

2.734.1.1.1 TranslationFlow

destination	*IpAddrAndPort* see 2.723.1.1.1.1	Packet flow destination IP address and L4 port.
established	*boolean*	Network connection established.
protocol	*enum: UDP | TCP | ICMP | IGMP |*	IP Protocol.
source	*IpAddrAndPort* see 2.723.1.1.1.1	Packet flow source IP address and L4 port.
[sourceVrfName] **	*string*	Source VRF name. **Since: 4.28.0
target	*enum: SRC | DST*	Source NAT or destination NAT.

2.735 show ip nat translation DYNAMIC_TYPE [...]

revision 3

detailedView	*boolean*	includes additional details if True.
hasComments **	*boolean*	True if any translations shown have comments. **Since: 4.28.1
translations	*list of Translation* see 2.735.1	List of NAT translations active on this interface.

2.735.1 Translation

[comment] **	*string*	comment on translation rule. **Since: 4.28.1
[details]	*Details* see 2.735.1.1	Details, if requested.
[direction] **	*enum: EGR | ING*	Ingress or Egress interface. **Since: 4.25.1
[dstAddress]	*IpAddr* see 2.731.1.1	The destination IP address and port/mask of the packet.
[interface]	*string*	Interface or NAT profile name.
natType	*enum: D-TW | AO | E-ST | DYN | TW | FC | ST*	Static NAT or Dynamic NAT.
[newDstAddress]	*IpAddr* see 2.731.1.1	The translated destination IP address and port/mask of the packet.
[newSrcAddress]	*IpAddr* see 2.731.1.1	The translated source IP address and port/mask of the packet.
[protocol]	*integer*	IP Protocol Number, if specified.
[srcAddress]	*IpAddr* see 2.731.1.1	The original source IP address and port/mask of the packet.
[target]	*enum: SRC | DST*	Source NAT or destination NAT.

2.735.1.1 Details

[established] **	*boolean*	Network connection established. **Since: 4.26.2
origin **	*string*	Discovered locally or advertised from sync peer. **Since: 4.30.2
packetCount	*integer*	Number of packets translated from the original IP address.
packetReplyCount	*integer*	Number of packets translated to the original IP address.
[sourceVrfName] **	*string*	Source VRF name. **Since: 4.28.0
vrfName	*string*	VRF name.

2.736 show ip nat translation STATIC_TYPE [...]

revision 3

see 2.735

2.737 show ip nat translation [...]

revision 3

see 2.735

2.738 show ip nat translation address-only mapping [...]

revision 2

addrOnlyTranslations	*table(string) = SrcIpTranslations* see 2.738.1	List of active Nat translations per interface.

2.738.1 SrcIpTranslations

srcIpTranslations	*table(IPv4 address) = TranslationList* see 2.738.1.1	Translations for a source Ip.

2.738.1.1 TranslationList

translations	*list of Translation* see 2.738.1.1.1	List of active NAT translations.

2.738.1.1.1 Translation

[destinationAddress]	*IpAddrAndPort* see 2.723.1.1.1.1	The destination IP address and port/mask of the packet.
globalAddress	*IpAddrAndPort* see 2.723.1.1.1.1	The translated IP address and port/mask of the packet.
natType	*enum: DYN | STAT*	Static NAT or Dynamic NAT.
protocol	*enum: UDP | TCP | ICMP | IGMP |*	IP Protocol.
[sourceAddress]	*IpAddrAndPort* see 2.723.1.1.1.1	The original source IP address and port/mask of the packet.
target	*enum: SRC | DST*	Source NAT or destination NAT.
vrfName **	*string*	VRF name. **Since: 4.23.2

2.739 show ip nat translation connection limit drop [...]

pools **	*list of PoolDropCounter* see 2.739.3	Connection drop counters per pool. **Since: 4.32.0
rules **	*table(string) = DropRuleCounter* see 2.739.1	Connection drop counters, keyed by rule. **Since: 4.32.0
vrfs	*table(string) = DropTable* see 2.739.2	Connection drop counters, keyed by VRF name.

2.739.1 DropRuleCounter

counter	*integer*	Counter.

2.739.2 DropTable

counters	*list of DropCounter* see 2.739.2.1	Counters.
vrfName	*string*	VRF name.

2.739.2.1 DropCounter

counter	*integer*	Counter.
dstIp	*IpAddr* see 2.731.1.1	Destination IP.
srcIp	*IpAddr* see 2.731.1.1	Source IP.

2.739.3 PoolDropCounter

counter	*integer*	Counter.
poolName	*string*	Pool name.
vrfName	*string*	VRF name.

2.740 show ip nat translation dynamic summary

interfaces	*table(string) = DynamicTranslationSummary* see 2.740.1	Map of Dynamic NAT translation summary per interface.

2.740.1 DynamicTranslationSummary

numDynHwConnections	*integer*	Number of Dynamic NAT connections in Hardware.
numDynSwConnections	*integer*	Number of Dynamic NAT connections in Software.
numFcHwConnections	*integer*	Number of Fullcone Dynamic NAT connections in Hardware.
numFcSwConnections	*integer*	Number of Fullcone Dynamic NAT connections in Software.

numSymHwConnections	*integer*	Number of Symmetric Dynamic NAT connections in Hardware.
numSymSwConnections	*integer*	Number of Symmetric Dynamic NAT connections in Software.

2.741 show ip nat translation max-entries

[allHostsConnLimit]	*integer*	Hosts' connection limit.
[allHostsLowMarkPerc]	*integer*	Below this percentage, connection drops are disabled.
[allPoolsLowMarkPerc] **	*integer*	Below this percentage, connection drops are disabled. **Since: 4.29.1
connectionLimit	*integer*	Global connection limit.
connectionLimitLowMark	*integer*	Below this count, connection drops are disabled.
connectionLimitLowMarkPerc	*integer*	Below this percentage, connection drops are disabled.
fullConeConnLimit **	*integer*	Full-cone connection limit. **Since: 4.29.2
fullConeConnLimitLowMark **	*integer*	Below this count, full-cone connection drops are disabled. **Since: 4.29.2
fullConeConnLimitLowMark-Perc **	*integer*	Below this percentage, full-cone connection drops are disabled. **Since: 4.29.2
[hostConnLimits]	*list of NatHostConnectionLimit* see 2.741.1	List of host's connection limit.
numberOfFullConeConnections **	*integer*	Active full-cone connections in Nat agent. **Since: 4.29.2
numberOfSymmetric-Connections **	*integer*	Active symmetric connections in Nat agent. **Since: 4.29.2
[poolConnLimits] **	*list of NatPoolConnectionLimit* see 2.741.2	List of pool's connection limit. **Since: 4.29.1
symmetricConnLimit **	*integer*	Symmetric connection limit. **Since: 4.29.2
symmetricConnLimitLowMark **	*integer*	Below this count, symmetric connection drops are disabled. **Since: 4.29.2
symmetricConnLimitLowMark-Perc **	*integer*	Below this percentage, symmetric connection drops are disabled. **Since: 4.29.2
totalNumberOfConnections	*integer*	Active connections in Nat agent.
totalNumberOfLocal-Connections **	*integer*	Local connections in Nat Sync agent. **Since: 4.28.2

2.741.1 NatHostConnectionLimit

connectionLimit	*integer*	Connection limit per host.
hostIp	*IPv4 address*	Host IP address.
lowMarkPerc	*integer*	Below this percentage, connection drops are disabled.
[numberOfConnections]	*integer*	Number of connections per host.

[numberOfLocalConnections] **	*integer*	Number of connections per host in Nat Sync agent. **Since: 4.28.2

2.741.2 NatPoolConnectionLimit

connectionLimit	*integer*	Connection limit per pool.
lowMarkPerc	*integer*	Below this percentage, connection drops are disabled.
[numberOfConnections]	*integer*	Number of connections per pool.
[numberOfLocalConnections]	*integer*	Number of connections per pool in Nat Sync agent.
poolName	*string*	Pool name.

2.742 show ip nat translation max-entries IPADDR

see 2.741.1

2.743 show ip nat translation max-entries pool POOL

see 2.741.1

2.744 show ip nat translation rates

rates	*table(string) = NatTranslationRates* see 2.744.1	NAT translation learning rates.

2.744.1 NatTranslationRates

rate	*list of NatTranslationRate* see 2.744.1.1	NAT translations measured in a specific interval.

2.744.1.1 NatTranslationRate

numAdd	*integer*	Number of NAT entries added.
numDel	*integer*	Number of NAT entries deleted.
timeLen	*integer*	Length of rates measure.

2.745 show ip nat translation summary [...]

revision 3

translations	*table(string) = TranslationSummary* see 2.745.1	Map of NAT translation summary per interface.

2.745.1 TranslationSummary

numDynHwConnections	*integer*	Number of Dynamic NAT connections in Hardware.
numDynSwConnections	*integer*	Number of Dynamic NAT connections in Software.
numDynTwiceHwConnections	*integer*	Number of Dynamic twice NAT connections in Hardware.
numDynTwiceKernel-Connections	*integer*	Number of Dynamic twice NAT connections in Kernel.
numDynTwiceSwConnections	*integer*	Number of Dynamic twice NAT connections in Software.
numKernelConnections	*integer*	Number of Dynamic NAT connections in Kernel.
numStaticHwConnections	*integer*	Number of Static NAT connections in Hardware.
numStaticSwConnections	*integer*	Number of Static NAT connections in Software.
numTwiceHwConnections	*integer*	Number of Twice NAT connections in Hardware.
numTwiceSwConnections	*integer*	Number of Twice NAT connections in Software.

2.746 show ip nat translation twice [...]

revision 2

detailedView	*boolean*	includes additional details if True.
hasComments **	*boolean*	True if any translations shown have comments. **Since: 4.28.1
pendingView **	*boolean*	Excludes unnecessary columns if True. **Since: 4.24.0
translations	*list of Translation* see 2.746.1	List of Twice NAT translations active on this interface.

2.746.1 Translation

[comment] **	*string*	Comment on translation rule. **Since: 4.28.1
[details]	*Details* see 2.746.1.1	Details, if requested.
dstIpAndPortNew	*IpAddrAndPort* see 2.723.1.1.1.1	The translated destination IP address and port of the packet.
dstIpAndPortOld	*IpAddrAndPort* see 2.723.1.1.1.1	The original destination IP address and port of the packet.
srcIpAndPortNew	*IpAddrAndPort* see 2.723.1.1.1.1	The translated source IP address and port of the packet.
srcIpAndPortOld	*IpAddrAndPort* see 2.723.1.1.1.1	The original source IP address and port of the packet.

2.746.1.1 Details

group	*integer*	Twice NAT Group.
[interface]	*string*	Interface/Profile.
origin **	*string*	Discovered locally or advertised from sync peer. **Since: 4.30.2
packetCount	*integer*	Number of packets translated from the original IP address.
packetReplyCount	*integer*	Number of packets translated to the original IP address.
[protocol]	*enum: UDP | TCP | IGMP | ICMP*	IP Protocol, if specified.
[protocolNumber]	*integer*	IP Protocol Number, if specified.
vrfName **	*string*	VRF name. **Since: 4.23.2

2.747 show ip nat translation vrf [...]

detailedView	*boolean*	includes additional details if True.
pendingView **	*boolean*	Excludes unnecessary columns if True. **Since: 4.24.0

translations	*list of Translation* see 2.747.1	List of Vrf NAT translations active on this interface.

2.747.1 Translation

[destinationAddress]	*IPv4 address*	The destination IP address and port/mask of the packet.
[details]	*Details* see 2.747.1.1	Details, if requested.
globalAddress	*IPv4 address*	The translated IP address and port/mask of the packet.
insideVrf	*string*	Inside vrf name.
[sourceAddress]	*IPv4 address*	The original source IP address and port/mask of the packet.
target	*enum: SRC | DST*	Source NAT or destination NAT.

2.747.1.1 Details

[outsideVrf]	*string*	Outside vrf name.
packetCount	*integer*	Number of packets translated from the original IP address.
packetReplyCount	*integer*	Number of packets translated to the original IP address.

2.748 show ip ospf [...]

vrfs	*table(string) = InstListOspfShowInstModel* see 2.748.1	OSPF instance information for all VRFs.

2.748.1 InstListOspfShowInstModel

instList	*table(numeric string) = OspfShowInstModel* see 2.748.1.1	OSPF Instance list keyed by instance id.

2.748.1.1 OspfShowInstModel

abr	*boolean*	This OSPF instance is an Area Border Router.
[adjacencyExchangeStart-Threshold]	*integer*	Adjacency exchange-start threshold.
[areaList]	*table(IPv4 address) = OspfShowInstAreaModel* see 2.748.1.1.2	List of areas in this OSPF instance.
asbr	*boolean*	This OSPF instance is an AS Border Router.
[ecmpMaximumNexthops]	*integer*	Maximum number of ECMP nexthops.
[externalLsaInformation]	*OspfShowInstExternalLsa-InfoModel* see 2.748.1.1.3	External LSA information.
floodPacing	*integer*	Flood packet pacing timer in msecs.
[gracefulRestartInfo] **	*OspfShowInstGraceful-RestartInfoModel* see 2.748.1.1.4	Graceful restart information. **Since: 4.15.3
instanceId	*integer*	OSPF instance ID.
[lsaInformation]	*OspfShowInstLsaInfoModel* see 2.748.1.1.5	LSA information.
lsaRetransmissionThreshold **	*integer*	LSA retransmission threshold. **Since: 4.18.0
maxLsaInformation	*OspfShowInstMaxLsaInfo-Model* see 2.748.1.1.6	Max LSA information.
[maxMetricExt]	*integer*	Max metric for external LSA.
[maxMetricIncStub]	*integer*	Max metric including stubs.
[maxMetricSum]	*integer*	Max metric for summary LSA.
[maxMetricTypeInformation]	*OspfShowInstMaxMetric-TypeInfoModel* see 2.748.1.1.7	Max metric type information.
[maxMetricUnsetInformation]	*OspfShowInstMaxMetric-UnsetInfoModel* see 2.748.1.1.8	Max metric unset information.
numAreas	*integer*	Number of areas.
numBackboneNeighbors **	*integer*	Number of backbone neighbors. **Since: 4.18.1
numNormalAreas	*integer*	Number of normal areas.
numNssaAreas	*integer*	Number of nssa areas.

numStubAreas	*integer*	Number of stub areas.
[opaqueLsaInformation]	*OspfShowInstOpaqueLsaInfoModel* see 2.748.1.1.9	Opaque LSA information.
[primaryDomainId] **	*string*	Primary domain identifier. **Since: 4.29.1
[referenceBandwidth] **	*integer*	Auto-cost reference bandwidth in Mbps. **Since: 4.15.3
[routerId]	*IPv4 address*	OSPF Router id.
[secondaryDomainIds] **	*list of OspfSecondaryDomainId* see 2.748.1.1.1	List of secondary domain identifiers. **Since: 4.29.1
shutDown **	*boolean*	Indicates if the OSPFv2 instance is currently shut down. **Since: 4.18.1
[spfInformation]	*OspfShowInstSpfInfoModel* see 2.748.1.1.10	SPF information.
[teRouterId] **	*IPv4 address*	OSPF traffic engineering router ID. **Since: 4.22.0
[tunnelRoutesEnabled] **	*boolean*	OSPF routes over GRE tunnel enabled. **Since: 4.23.1
[vrf]	*string*	VRF name.

2.748.1.1.1 OspfSecondaryDomainId

domainId	*string*	Secondary domain identifier.

2.748.1.1.2 OspfShowInstAreaModel

[areaFilterPrefixList] **	*string*	Area Filter prefix-list. **Since: 4.23.0
[areaFiltersConfigured] **	*boolean*	Area Summary Filters configured. **Since: 4.23.0
areaId	*IPv4 address*	OSPF area ID.
[authType]	*enum: MD5 | Simple | SHA512 | SHA1 | SHA256 | SHA384*	Area authentication type.
dcClearCount **	*integer*	DC clear LSA count. **Since: 4.26.2
indLsaCount **	*integer*	Indication LSA count. **Since: 4.26.2
lsaInformation	*OspfShowInstAreaLsaInfoModel* see 2.748.1.1.2.1	Area LSA information.
normalArea	*boolean*	This area is a normal area.
[nssaInformation]	*OspfShowInstAreaNssaModel* see 2.748.1.1.2.2	Area NSSA information.
numIntf	*integer*	Number of interfaces in the area.

opaqueAreaLsaInformation **	*OspfShowInstAreaScope-OpaqueLsaInfoModel* see 2.748.1.1.2.5	Opaque area scope LSA information. **Since: 4.22.0
opaqueLsaInformation	*OspfShowInstAreaOpaque-LsaInfoModel* see 2.748.1.1.2.3	Area link opaque scope LSA information.
rangeList	*table(IPv4 address) = Ospf-ShowInstAreaRangeModel* see 2.748.1.1.2.4	Dictionary of address ranges in this OSPF area keyed by the area range address.
spfCount	*integer*	Area SPF count.
stubArea	*boolean*	This area is a stub area.
teEnabled **	*boolean*	Traffic engineering enabled in the area. **Since: 4.22.0

2.748.1.1.2.1 OspfShowInstAreaLsaInfoModel

asExternalCksum	*integer*	Area AS external LSA checksum sum.
treeSize	*integer*	Area LSA tree size (number of LSA).

2.748.1.1.2.2 OspfShowInstAreaNssaModel

nssaTransAlways	*boolean*	Nssa translate always flag for area.
[nssaTransInt]	*integer*	Nssa translate interval.
[nssaTransState]	*enum: extendedTranslator | translator | stopTranslator | notTranslator*	Nssa translate state flag for area.

2.748.1.1.2.3 OspfShowInstAreaOpaqueLsaInfoModel

opaqueCksum	*integer*	Area opaque link LSA checksum sum.
opaqueTreeSize	*integer*	Area opaque link tree size (number of opaque link LSA).

2.748.1.1.2.4 OspfShowInstAreaRangeModel

address	*IPv4 address*	Area range address.
cost	*integer*	Area range cost.
[doNotAdvertise] **	*boolean*	Do not advertise the area range. The cost value is invalid if this flag is set to true. **Since: 4.17.0
maskLen	*integer*	Area range mask length.

2.748.1.1.2.5 OspfShowInstAreaScopeOpaqueLsaInfoModel

opaqueCksumSum	*integer*	Area opaque scope LSA checksum sum.
opaqueTreeSize	*integer*	Area opaque scope LSA tree size (number of opaque LSA).

2.748.1.1.3 OspfShowInstExternalLsaInfoModel

asExternalCksum	*integer*	AS external LSA checksum.
treeSize	*integer*	OSPF instance external LSA tree size (number of external LSAs.

2.748.1.1.4 OspfShowInstGracefulRestartInfoModel

gracePeriod	*floating point number*	Maximum time for graceful-restart to complete (secs).
gracefulRestart	*boolean*	Graceful restart mode enabled.
helperLooseLsaCheck	*boolean*	Graceful restart helper allows topology changes.
helperMode	*boolean*	Graceful restart helper mode.
[lastExitReason]	*enum: lastExitHelperAborted* | *lastExitNeighborState-Changed* | *lastExitGracePeriodExpired* | *lastExitSuccess* | *lastExitNone* | *lastExitDisabled*	Reason for last graceful restart exit.
lastExitTime	*floating point number*	Time last graceful restart exited.
[lastRestartReason] **	*enum: SSO* | *Unknown* | *RIB restart* | *ASU2*	Specific reason for last graceful restart. **Since: 4.18.0
plannedOnly	*boolean*	Restrict graceful-restarts to planned events.
restartDuration **	*integer*	Graceful restart duration in microseconds. **Since: 4.18.0
restartExpirationTime	*floating point number*	Time current graceful restart expires.
[state]	*enum: pending* | *graceful* | *none* | *exiting* | *signaled*	Graceful restart speaker state.

2.748.1.1.5 OspfShowInstLsaInfoModel

lsaArrivalInterval	*integer*	LSA arrival interval.
lsaHoldInterval	*integer*	LSA hold interval.
lsaMaxWaitInterval	*integer*	LSA max wait interval.
lsaStartInterval	*integer*	LSA start interval.
numLsa	*integer*	Number of LSAs.

2.748.1.1.6 OspfShowInstMaxLsaInfoModel

maxLsa	*integer*	Maximum number of LSAs allowed.
maxLsaAllowedIgnoreCount	*integer*	Max LSA allowed ignore count.
maxLsaCurrentIgnoreCount	*integer*	Max LSA current ignore count.
maxLsaIgnoreTime	*integer*	Max LSA ignore time (mins).
[maxLsaIgnoreTimeEnd]	*floating point number*	Max LSA ignore time end.
maxLsaIgnoring	*boolean*	Ignoring max LSA condition.
maxLsaResetTime	*integer*	Max LSA reset time (mins).

maxLsaThreshold	*integer*	Max LSA threshold for warning message.
maxLsaWarningOnly	*boolean*	Max LSA warning-only option.

2.748.1.1.7 OspfShowInstMaxMetricTypeInfoModel

maxMetricActive **	*boolean*	Max metric advertisements being currently active or not. **Since: 4.20.0
[maxMetricOnStartUpTime]	*integer*	Time interval on startup when maximum metric is advertised (secs).
[maxMetricTimerLeft]	*integer*	Max metric timer left (secs).
maxMetricType	*integer*	Max metric type.
[maxMetricWaitBgp]	*integer*	Max metric while Bgp is converging.

2.748.1.1.8 OspfShowInstMaxMetricUnsetInfoModel

[maxMetricUnsetOrig-Duration]	*integer*	Max metric originate duration (secs).
[maxMetricUnsetReason]	*enum: maxMetricUnset-BgpTimerExpired* | *maxMetricUnsetUserConfig* | *maxMetricUnsetTimer-Expired* | *maxMetricUnsetBgp-Converged* | *maxMetricUnsetBgpNot-Configured*	Max metric unset reason.
maxMetricUnsetTstamp	*integer*	Max metric unset timestamp.

2.748.1.1.9 OspfShowInstOpaqueLsaInfoModel

opaque	*boolean*	Opaque LSAs supported.
opaqueCksum	*integer*	Opaque AS LSA checksum.
opaqueTreeSize	*integer*	OSPF instance opaque AS LSA tree size (number of opaque AS LSAs.

2.748.1.1.10 OspfShowInstSpfInfoModel

lastSpf	*integer*	Last SPF run (secs).
nextSpf	*integer*	Next SPF run (msecs).
spfCurrHoldInterval	*integer*	SPF current hold interval.
spfHoldInterval	*integer*	SPF hold interval.
spfInterval	*integer*	SPF interval.
spfMaxWaitInterval	*integer*	SPF max wait interval.
spfStartInterval	*integer*	SPF start interval.

2.749 show ip ospf access-list [...]

see 2.62

2.750 show ip ospf border-routers [...]

vrfs	*table(string) = InstListOspfBorderRoutersInstance* see 2.750.1	OSPF border routers information for all VRFs.

2.750.1 InstListOspfBorderRoutersInstance

instList	*table(numeric string) = OspfBorderRoutersInstance* see 2.750.1.1	OSPF Instance list keyed by instance id.

2.750.1.1 OspfBorderRoutersInstance

ospfBorderRouterEntries	*table(IPv4 address) = OspfBorderRoutersEntry* see 2.750.1.1.1	Dictionary of OSPF border router entries indexed by area-id.
routerId	*IPv4 address*	OSPF router identifier.
shutDown **	*boolean*	Indicates if the OSPF instance is currently shut down. **Since: 4.22.1
vrf	*string*	VRF name.

2.750.1.1.1 OspfBorderRoutersEntry

borderRouters	*table(IPv4 address) = OspfBorderRoutersType* see 2.750.1.1.1.1	Dictionary of OSPF border routers type indexed by router-id.

2.750.1.1.1.1 OspfBorderRoutersType

abr	*boolean*	Router is an area border router.
asbr	*boolean*	Router is an autonomous system boundary router.
metric **	*integer*	Cost to reach this router. **Since: 4.27.2

2.751 show ip ospf counters [...]

vrfs	*table(string) = InstListOspfCountersInstance* see 2.751.1	OSPF Counters.

2.751.1 InstListOspfCountersInstance

instList	*table(numeric string) = OspfCountersInstance* see 2.751.1.1	OSPF Instance list keyed by instance id.

2.751.1.1 OspfCountersInstance

[lastResetTime]	*floating point number*	UTC timestamp of last counters reset.
lsaTypeCounters	*table(string) = OspfCountersLsaEntry* see 2.751.1.1.1	Dictionary of LSA type counters keyed by counter name.
opaqueLsaReceived	*integer*	Number of opaque LSAs received.
selfOriginatedLsaReceived	*integer*	Number of self-originated LSAs received.
selfOriginatedLsaReceived-Deleted	*integer*	Number of self-originated LSAs received and deleted.
selfOriginatedLsaReceived-Updated	*integer*	Number of self-originated LSAs received and updated.
spfCount	*integer*	Number of SPF runs.

2.751.1.1.1 OspfCountersLsaEntry

numAsex	*integer*	Number of AS-external LSAs.
numNetwork	*integer*	Number of network LSAs.
numNssa	*integer*	Number of type-7 NSSA LSAs.
numOpaqueArea	*integer*	Number of opaque area LSAs.
numOpaqueAs	*integer*	Number of opaque AS LSAs.
numOpaqueLink	*integer*	Number of opaque link LSAs.
numRouter	*integer*	Number of router LSAs.
numSummary	*integer*	Number of summary LSAs.
numSummaryAsbr	*integer*	Number of summary ASBR LSAs.

2.752 show ip ospf counters interface [...]

vrfs	*table(string) = InstListOspfCountersInterface* see 2.752.1	OSPF Interface Counters.

2.752.1 InstListOspfCountersInterface

instList	*table(numeric string) = OspfCountersInterface* see 2.752.1.1	OSPF Instance list keyed by instance id.

2.752.1.1 OspfCountersInterface

interfaces	*table(string) = OspfCountersInterfaceEntry* see 2.752.1.1.1	Dictionary of OSPF interfaces indexed by the interface name.

2.752.1.1.1 OspfCountersInterfaceEntry

delayedLsAcksSent	*integer*	Number of delayed LS acknowledgements sent.
[lastResetTime]	*floating point number*	UTC timestamp of the last time counters were reset.
lsAcksReceived	*integer*	Number of LS acknowledgements received.
lsUpdatesInFloodQueue	*integer*	Number of LS updates currently in the flood queue.
lsaType **	*OspfCountersLsaTypeEntry* see 2.752.1.1.1.1	LSA types. **Since: 4.27.0
multicastLsUpdatesSent	*integer*	Number of multicast LS updates sent.

2.752.1.1.1.1 OspfCountersLsaTypeEntry

asExternal	*OspfLsaCounters* see 2.752.1.1.1.2	Number of AS-external LSAs.
network	*OspfLsaCounters* see 2.752.1.1.1.2	Number of network LSAs.
nssa	*OspfLsaCounters* see 2.752.1.1.1.2	Number of type-7 NSSA LSAs.
opaqueArea	*OspfLsaCounters* see 2.752.1.1.1.2	Number of opaque area LSAs.
opaqueAs	*OspfLsaCounters* see 2.752.1.1.1.2	Number of opaque AS LSAs.
opaqueLink	*OspfLsaCounters* see 2.752.1.1.1.2	Number of opaque link LSAs.
router	*OspfLsaCounters* see 2.752.1.1.1.2	Number of router LSAs.
summary	*OspfLsaCounters* see 2.752.1.1.1.2	Number of summary LSAs.
summaryAsbr	*OspfLsaCounters* see 2.752.1.1.1.2	Number of summary ASBR LSAs.

2.752.1.1.1.2 OspfLsaCounters

`received`	*integer*	Number of LSAs received.
`sent`	*integer*	Number of LSAs sent.

2.753 show ip ospf counters interface rates [...]

vrfs	*table(string) = InstListOspfCountersInterfaceRates* see 2.753.1	OSPF Interface Counters Rates.

2.753.1 InstListOspfCountersInterfaceRates

instList	*table(numeric string) = OspfCountersInterfaceRates* see 2.753.1.1	OSPF Instance list keyed by instance id.

2.753.1.1 OspfCountersInterfaceRates

interfaces	*table(string) = OspfCountersInterfaceRatesEntry* see 2.753.1.1.1	Dictionary of OSPF interfaces indexed by the interface name.

2.753.1.1.1 OspfCountersInterfaceRatesEntry

[lastResetTime]	*floating point number*	UTC timestamp of the last time counters were reset.
lsaTypeRates	*OspfCountersLsaRateTypeEntry* see 2.753.1.1.1.1	LSA type rates.

2.753.1.1.1.1 OspfCountersLsaRateTypeEntry

asExternal	*OspfLsaCountersRate* see 2.753.1.1.1.2	Number of AS-external LSAs.
network	*OspfLsaCountersRate* see 2.753.1.1.1.2	Number of network LSAs.
nssa	*OspfLsaCountersRate* see 2.753.1.1.1.2	Number of type-7 NSSA LSAs.
opaqueArea	*OspfLsaCountersRate* see 2.753.1.1.1.2	Number of opaque area LSAs.
opaqueAs	*OspfLsaCountersRate* see 2.753.1.1.1.2	Number of opaque AS LSAs.
opaqueLink	*OspfLsaCountersRate* see 2.753.1.1.1.2	Number of opaque link LSAs.
router	*OspfLsaCountersRate* see 2.753.1.1.1.2	Number of router LSAs.
summary	*OspfLsaCountersRate* see 2.753.1.1.1.2	Number of summary LSAs.
summaryAsbr	*OspfLsaCountersRate* see 2.753.1.1.1.2	Number of summary ASBR LSAs.

2.753.1.1.1.2 OspfLsaCountersRate

received	*floating point number*	Number of LSAs received per second.

`sent`	*floating point number*	Number of LSAs sent per second.

2.754 show ip ospf counters neighbor [...]

vrfs	*table(string) = InstListOspfCountersNeighbor* see 2.754.1	OSPF Neighbor Counters.

2.754.1 InstListOspfCountersNeighbor

instList	*table(numeric string) = OspfCountersNeighbor* see 2.754.1.1	OSPF Instance list keyed by instance id.

2.754.1.1 OspfCountersNeighbor

neighbors	*list of OspfCountersNeighborEntry* see 2.754.1.1.1	List of neighbor-level counter entries.

2.754.1.1.1 OspfCountersNeighborEntry

databaseDescriptionReceived	*integer*	Number of database description packets received.
databaseDescriptionSent	*integer*	Number of database description packets sent.
interfaceAddress	*IPv4 address*	OSPF neighbor interface address.
interfaceName	*string*	OSPF neighbor interface name.
[lastResetTime]	*floating point number*	UTC timestamp of the last time counters were reset.
lsAcknowledgementSent	*integer*	Number of LS acknowledgements sent.
lsRequestReceived	*integer*	Number of LS requests receieved.
lsRequestSent	*integer*	Number of LS requests sent.
multicastLsAcknowledgementReceived	*integer*	Number of multicast LS acknowledgements received.
multicastLsUpdateReceived	*integer*	Number of multicast LS updates received.
neighborAddress	*IPv4 address*	OSPF neighbor address.
neighborRouterId	*IPv4 address*	OSPF neighbor router identifier.
unicastLsAcknowledgementReceived	*integer*	Number of unicast LS acknowledgements received.
unicastLsUpdateReceived	*integer*	Number of unicast LS updates received.

2.755 show ip ospf database [...]

vrfs	*table(string) = InstListOspfDatabaseInstance* see 2.755.1	OSPF database information.

2.755.1 InstListOspfDatabaseInstance

instList	*table(numeric string) = OspfDatabaseInstance* see 2.755.1.1	OSPF Instance list keyed by instance id.

2.755.1.1 OspfDatabaseInstance

areas	*table(IPv4 address) = OspfAreaModel* see 2.755.1.1.1	A mapping between an area and its LSA list.
externalLsdb	*list of OspfAsExternalLsa* see 2.755.1.1.2	List of LSAs with AS scope LSAs.
type11Lsdb	*list of OspfOpaqueExternalLsa* see 2.755.1.1.3	List of Opaque LSAs with AS scope.

2.755.1.1.1 OspfAreaModel

areaDatabase	*list of OspfAreaScopeLsa* see 2.755.1.1.1.1	Area scoped LSAs.
[interfaces]	*table(string) = OspfInterfaceScopeModel* see 2.755.1.1.1.37	A mapping between an Interface and its LSA list.

2.755.1.1.1.1 OspfAreaScopeLsa

areaLsas	*list of OspfLsa* see 2.755.1.1.1.2	List of LSAs for the area.

2.755.1.1.1.2 OspfLsa

advertisingRouter	*IPv4 address*	LSA advertising router.
age	*integer*	LSA age in seconds.
checksum	*integer*	LSA checksum.
doNotAge	*boolean*	LSA will not be aged.
[exceptionFlag]	*enum: announcingMaximumCost | announcingMaximumMetric*	Indicates maximum cost being advertised for self originated LSAs.
length	*integer*	LSA length.
linkStateId	*IPv4 address*	LSA link state id.

lsaType	*enum: opaqueType11Lsa | routerLsa | asExternalLsa | summaryLsa | opaqueType9Lsa | nssaLsa | opaqueType10Lsa | networkLsa | summaryAsbrLsa*	LSA type.
options	*OspfDatabaseOptions* see 2.755.1.1.1.3	OSPF LSA options.
[ospfExtendedLinkLsa] **	*OspfExtendedLinkLsa* see 2.755.1.1.1.4	Extended Link LSA. **Since: 4.31.1
[ospfExtendedPrefixLsa] **	*OspfExtendedPrefixLsa* see 2.755.1.1.1.10	Extended Prefix LSA. **Since: 4.31.1
[ospfExternalLsa]	*OspfExternalLsa* see 2.755.1.1.1.19	AS or NSSA external LSA.
[ospfGraceLsa] **	*OspfGraceLsa* see 2.755.1.1.1.20	Grace LSA. **Since: 4.35.2
[ospfNetworkLsa]	*OspfNetworkLsa* see 2.755.1.1.1.22	Network LSA.
[ospfRiLsa] **	*OspfRouterInformationLsa* see 2.755.1.1.1.23	Router Information LSA. **Since: 4.31.1
[ospfRouterLsa]	*OspfRouterLsa* see 2.755.1.1.1.28	Router LSA.
[ospfSummaryLsa]	*OspfSummaryLsa* see 2.755.1.1.1.31	Summary LSA or ASBR summary LSA.
[ospfTeInfo]	*OspfTrafficEngineeringInfo* see 2.755.1.1.1.32	Traffic Engineering TLV data.
sequenceNumber	*integer*	LSA sequence number.

2.755.1.1.1.3 OspfDatabaseOptions

demandCircuitsSupport	*boolean*	Originating router supports OSPF over Demand Circuits.
doNotUseInRouteCalc	*boolean*	A type 3,5 or 7 LSA is sent from a PE router to a CE router.
externalRoutingCapability	*boolean*	Originating router capable of accepting AS External LSAs.
linkLocalSignaling	*boolean*	OSPF packet contains Link-Local Signaling data block.
multicastCapability	*boolean*	Originating router supports multicast extensions to OSPF.
multitopologyCapability	*boolean*	Originating router supports Multitopology OSPF.
nssaCapability	*boolean*	Originating router supports Type-7 NSSA-External-LSAs.
opaqueLsaSupport	*boolean*	Originating router supports Type 9,10 and 11 Opaque LSAs.

2.755.1.1.1.4 OspfExtendedLinkLsa

[extendedLinkTlvs]	*list of SegmentRoutingExtLinkTlvInfo* see 2.755.1.1.1.6	Segment Routing Extended Link TLV list.
malformedTlv	*boolean*	The TLV is not parsable.
[unsupportedTlvs]	*list of ExtLinkUnsupportedTlv* see 2.755.1.1.1.5	Unsupported TLV list.

2.755.1.1.1.5 ExtLinkUnsupportedTlv

tlvLength	*integer*	TLV length.
tlvType	*integer*	TLV type.

2.755.1.1.1.6 SegmentRoutingExtLinkTlvInfo

[adjSidSubTlvs]	*list of SegmentRoutingAdjSidSubTlvInfo* see 2.755.1.1.1.8	Segment Routing Adj Sid sub-TLV list.
linkData	*IPv4 address*	Router link data.
linkId	*IPv4 address*	Router link ID.
linkType	*enum: transitNetwork | pointToPoint | unknown*	Link Type.
reserved	*integer*	Reserved.
[unsupportedSubTlvs]	*list of ExtLinkUnsupportedSubTlv* see 2.755.1.1.1.7	Unsupported sub-TLV list.

2.755.1.1.1.7 ExtLinkUnsupportedSubTlv

tlvLength	*integer*	TLV length.
tlvType	*integer*	TLV type.

2.755.1.1.1.8 SegmentRoutingAdjSidSubTlvInfo

flags	*SegmentRoutingAdjSidSubTlvFlags* see 2.755.1.1.1.9	Adj-SID sub-TLV flags.
mtId	*integer*	Multi-Topology ID.
reserved	*integer*	Reserved.
sid	*integer*	SID.

2.755.1.1.1.9 SegmentRoutingAdjSidSubTlvFlags

backup	*boolean*	Backup flag.
group	*boolean*	Group flag.
local	*boolean*	Local/Global flag.
persistent	*boolean*	Persistent flag.
value	*boolean*	Value/Index flag.

2.755.1.1.1.10 OspfExtendedPrefixLsa

[extendedPrefixRangeTlvs]	*list of SegmentRoutingExtPfxRangeTlvInfo* see 2.755.1.1.1.12	Segment Routing Extended Prefix Range TLV list.
[extendedPrefixTlvs]	*list of SegmentRoutingExtPfxTlvInfo* see 2.755.1.1.1.17	Segment Routing Extended Prefix TLV list.
malformedTlv	*boolean*	The TLV is not parsable.
[unsupportedTlvs]	*list of ExtPfxUnsupportedTlv* see 2.755.1.1.1.11	Unsupported TLV list.

2.755.1.1.1.11 ExtPfxUnsupportedTlv

tlvLength	*integer*	TLV length.
tlvType	*integer*	TLV type.

2.755.1.1.1.12 SegmentRoutingExtPfxRangeTlvInfo

addressFamily	*IPv4 unicast*	Address Family.
flags	*SegmentRoutingExtPfxRangeTlvFlags* see 2.755.1.1.1.14	Extended prefix range TLV flags.
[pfxSidSubTlv]	*list of SegmentRoutingPfxSidSubTlvInfo* see 2.755.1.1.1.15	Segment Routing Prefix Sid Sub-TLV list.
prefix	*IPv4 address*	Prefix.
prefixLength	*integer*	Prefix length.
rangeSize	*integer*	Range Size.
reserved	*integer*	Reserved.
[unsupportedSubTlvs]	*list of ExtPfxUnsupportedSubTlv* see 2.755.1.1.1.13	Unsupported sub tlv list.

2.755.1.1.1.13 ExtPfxUnsupportedSubTlv

tlvLength	*integer*	TLV length.
tlvType	*integer*	TLV type.

2.755.1.1.1.14 SegmentRoutingExtPfxRangeTlvFlags

interArea	*boolean*	Inter Area flag.

2.755.1.1.1.15 SegmentRoutingPfxSidSubTlvInfo

algorithm	*enum: Strict Shortest Path First | Shortest Path First*	Algorithm.

flags	*SegmentRoutingPfxSidSubTlvFlags* see 2.755.1.1.1.16	Prefix-SID Sub-TLV flags.
multiTopologyId	*integer*	MT-ID.
sid	*integer*	SID.

2.755.1.1.1.16 SegmentRoutingPfxSidSubTlvFlags

explicitNull	*boolean*	Explicit Null flag.
local	*boolean*	Local/Global flag.
mappingServer	*boolean*	Mapping Server flag.
noPhp	*boolean*	No-PHP flag.
value	*boolean*	Value/Index flag.

2.755.1.1.1.17 SegmentRoutingExtPfxTlvInfo

addressFamily	*IPv4 unicast*	Address Family.
flags	*SegmentRoutingExtPfxTlvFlags* see 2.755.1.1.1.18	Extended prefix TLV flags.
[pfxSidSubTlv]	*list of SegmentRoutingPfxSidSubTlvInfo* see 2.755.1.1.1.15	Segment Routing Prefix Sid Sub-TLV list.
prefix	*IPv4 address*	Prefix.
prefixLength	*integer*	Prefix length.
routeType	*enum: Inter-Area | AS External | Intra-Area | NSSA External | Unspecified*	Route type.
[unsupportedSubTlvs]	*list of ExtPfxUnsupportedSubTlv* see 2.755.1.1.1.13	Unsupported sub tlv list.

2.755.1.1.1.18 SegmentRoutingExtPfxTlvFlags

attach	*boolean*	Attach flag.
node	*boolean*	Node flag.

2.755.1.1.1.19 OspfExternalLsa

externalRouteTag	*integer*	External route tag.
forwardingAddress	*IPv4 address*	Forwarding address.
metric	*integer*	Route cost.
metricType	*enum: type2 | type1*	External metric type (E bit) type1 : External metric Type 1 type2 : External metric Type 2.
networkMask	*IPv4 address*	IP address mask for the advertised destination.

2.755.1.1.1.20 OspfGraceLsa

gracePeriod	*integer*	Graceful restart period in seconds.
graceReason	*integer*	Reason for graceful restart.
[interfaceAddress]	*IPv4 address*	IPv4 address of the interface that issending the Grace-LSA.
malformedTlv	*boolean*	The TLV is not parsable.
[unsupportedTlvs]	*list of GraceUnsupportedTlv* see 2.755.1.1.1.21	Unsupported TLV list.

2.755.1.1.1.21 GraceUnsupportedTlv

tlvLength	*integer*	TLV length.
tlvType	*integer*	TLV type.

2.755.1.1.1.22 OspfNetworkLsa

attachedRouters	*list of IPv4 address*	List of routers attached to the network.
networkMask	*IPv4 address*	IP address mask for the network.

2.755.1.1.1.23 OspfRouterInformationLsa

malformedTlv	*boolean*	The TLV is not parsable.
[sidRanges]	*list of SIDRange* see 2.755.1.1.1.25	SID/Label ranges.
[spfInfo]	*SegmentRoutingSpfInfo* see 2.755.1.1.1.27	Segment Routing SPF data.
[unsupportedTlvs]	*list of RIUnsupportedTlv* see 2.755.1.1.1.24	Unsupported TLV information.

2.755.1.1.1.24 RIUnsupportedTlv

tlvLength	*integer*	TLV length.
tlvType	*integer*	TLV type.

2.755.1.1.1.25 SIDRange

srGbBase	*integer*	SR Global Block base.
srGbSize	*integer*	SR Global Block size.
[unsupportedSubTlvs]	*list of RIUnsupportedSubTlv* see 2.755.1.1.1.26	Unsupported sub-TLVs.

2.755.1.1.1.26 RIUnsupportedSubTlv

tlvLength	*integer*	TLV length.
tlvType	*integer*	TLV type.

2.755.1.1.1.27 SegmentRoutingSpfInfo

[spfAlgorithmSupported]	*boolean*	SPF algorithm is supported.
[sspfAlgorithmSupported]	*boolean*	SSPF algorithm is supported.

2.755.1.1.1.28 OspfRouterLsa

numRtrLinks	*integer*	Number of router links.
routerLsaLinks	*list of OspfRouterLsaLinkEntry* see 2.755.1.1.1.29	Links for this router.
rtrLsaOptions	*OspfRouterLsaOptions* see 2.755.1.1.1.30	Router lsa options.

2.755.1.1.1.29 OspfRouterLsaLinkEntry

linkData	*IPv4 address*	Router link data.
linkId	*IPv4 address*	Router link ID.
linkType	*enum: virtualLink | unknown | pointToPoint | stubNetwork | transitNetwork*	Description of the router link.
metric	*integer*	Cost of the router link.
numTos	*integer*	Number of TOS metrics for the link.

2.755.1.1.1.30 OspfRouterLsaOptions

areaBorderRouter	*boolean*	This is an area border router.
asBoundaryRouter	*boolean*	This is an autonomous system boundary router.
nssaTranslation	*boolean*	Translate nssa lsas to as external lsas.
virtualLinkEndpoint	*boolean*	This is an endpoint for virtual links in the area.

2.755.1.1.1.31 OspfSummaryLsa

metric	*integer*	Route cost.
networkMask	*IPv4 address*	IP address mask for the destination.

2.755.1.1.1.32 OspfTrafficEngineeringInfo

[linkTlvInfo]	*LinkAddressTlv* see 2.755.1.1.1.33	Link TLV.
malformedTlv	*boolean*	The TLV is not parsable.
[rtrTlvInfo]	*RtrAddressTlv* see 2.755.1.1.1.35	Router Address TLV.
[tlvLength]	*integer*	Top Level TLV length.
[tlvName]	*enum: unsupported | routerAddress | link*	Top Level TLV Name.

[tlvType]	*integer*	Top Level TLV type.
[unsupportedSubTlvInfo]	*list of UnsupportedSubTlv* see 2.755.1.1.1.36	Unsupported sub-TLV information.

2.755.1.1.1.33 LinkAddressTlv

[adminGroup]	*integer*	Administrative group assigned to the link.
linkId	*IPv4 address*	Ip Address of the other end of the link.
linkType	*enum: pointToPoint | multiAccess | unknown*	Description of the link.
[localIpAddresses]	*list of IPv4 address*	IP addresses of the link.
[maxLinkBw]	*integer*	Maximum bandwidth (bps) that can be used on the link.
[maxReservableBw]	*integer*	Maximum bandwidth (bps) that can be reserved on the Link.
[maxReservablePriorityBw]	*TeReservablePriority-Bandwidth* see 2.755.1.1.1.34	Maximum bandwidth reservable for a priority.
[remoteIpAddresses]	*list of IPv4 address*	IP addresses of the neighbors of the link.
[srlgs]	*list of integer*	Shared risk link group identifiers.
[teMetric]	*integer*	The cost of the link.

2.755.1.1.1.34 TeReservablePriorityBandwidth

priority0	*integer*	Reservable bandwidth (bps) for priority level 0.
priority1	*integer*	Reservable bandwidth (bps) for priority level 1.
priority2	*integer*	Reservable bandwidth (bps) for priority level 2.
priority3	*integer*	Reservable bandwidth (bps) for priority level 3.
priority4	*integer*	Reservable bandwidth (bps) for priority level 4.
priority5	*integer*	Reservable bandwidth (bps) for priority level 5.
priority6	*integer*	Reservable bandwidth (bps) for priority level 6.
priority7	*integer*	Reservable bandwidth (bps) for priority level 7.

2.755.1.1.1.35 RtrAddressTlv

teRouterId	*IPv4 address*	Traffic Engineering IPv4 Router-Id.

2.755.1.1.1.36 UnsupportedSubTlv

tlvLength	*integer*	TLV length.
tlvType	*integer*	TLV type.

2.755.1.1.1.37 OspfInterfaceScopeModel

linkLsas	*list of OspfType9LsaList* see 2.755.1.1.1.38	List of LSAs for the area.

2.755.1.1.1.38 OspfType9LsaList

ospfType9Lsas	*list of OspfLsa* see 2.755.1.1.1.2	List of LSAs for the interface.

2.755.1.1.2 OspfAsExternalLsa

externalLsas	*list of OspfLsa* see 2.755.1.1.1.2	List of AS external LSAs.

2.755.1.1.3 OspfOpaqueExternalLsa

type11Lsas	*list of OspfLsa* see 2.755.1.1.1.2	Type 11 Opaque LSAs.

2.756 show ip ospf database database-summary [...]

vrfs	*table(string) = InstListOspf-DatabaseSummary* see 2.756.1	OSPF database summary information.

2.756.1 InstListOspfDatabaseSummary

instList	*table(numeric string) = OspfDatabaseSummary* see 2.756.1.1	OSPF Instance list keyed by instance id.

2.756.1.1 OspfDatabaseSummary

numAsex	*integer*	Number of AS-external LSAs.
numNetwork	*integer*	Number of network LSAs.
numNssa	*integer*	Number of type-7 NSSA LSAs.
numOpaqueArea	*integer*	Number of opaque area LSAs.
numOpaqueAs	*integer*	Number of opaque AS LSAs.
numOpaqueLink	*integer*	Number of opaque link LSAs.
numRouter	*integer*	Number of router LSAs.
numSummary	*integer*	Number of summary LSAs.
numSummaryAsbr	*integer*	Number of summary ASBR LSAs.

2.757 show ip ospf interface [...]

vrfs	*table(string) = InstListOspfInterface* see 2.757.1	OSPF instance information for all VRFs.

2.757.1 InstListOspfInterface

instList	*table(numeric string) = OspfInterface* see 2.757.1.1	OSPF Instance list keyed by instance id.

2.757.1.1 OspfInterface

interfaces	*table(string) = OspfInterfaceEntry* see 2.757.1.1.1	Dictionary of OSPF Interfaces indexed by the interface name.

2.757.1.1.1 OspfInterfaceEntry

[activeMetricRule] **	*string*	Active Metric Profile Rule. **Since: 4.29.2
area	*IPv4 address*	Area assigned to the interface.
[authKeyId] **	*integer*	Authentication Key ID. **Since: 4.22.0
[authentication]	*enum: sha256 | sha384 | md5 | simple | sha1 | sha512*	Authentication algorithm.
[backupDesignatedRouter]	*IPv4 address*	Backup designated router ID.
bfdState	*enum: enabled | disabled | default*	BFD configuration state.
cost	*integer*	Interface metric.
deadInterval	*integer*	Dead interval in seconds.
[designatedRouter]	*IPv4 address*	Designated router ID.
helloInterval	*integer*	Hello interval in seconds.
interfaceAddress	*IPv4 address*	Interface IP address.
interfaceMask	*integer*	Interface IP mask length.
[interfaceSpeed] **	*integer*	Interface Speed in mbps. **Since: 4.29.2
interfaceType	*enum: broadcast | virtual | p2mp | p2p | nbma*	Network interface type.
[metricProfile] **	*string*	Metric Profile Name. **Since: 4.29.2
[mplsLdpIgpSync]	*boolean*	MPLS LDP-IGP Synchronization, ensures that LDP is fully established before IGP path is used for switching. Uses global setting as default.
neighborCount	*integer*	Neighbour count.
options	*OspfOptions* see 2.757.1.1.1.1	Interface optional capabilities.
passive	*boolean*	Passive state.
[priority]	*integer*	Interface priority.

`[remoteAddress]` **	*IPv4 address*	Interface remote IP address. **Since: 4.30.1
`retransmitInterval`	*integer*	Retransmit interval in seconds.
`state`	*enum: drOther | waiting | down | loopback | backupDr | dr | p2p*	Interface state.
`teEnabled` **	*boolean*	Traffic engineering state. **Since: 4.22.0
`tilfaProtection` **	*enum: node | disabled | link*	TI-LFA protection mode. **Since: 4.33.1
`transmitDelay`	*integer*	Transmit delay in seconds.

2.757.1.1.1.1 OspfOptions

Could also be an instance of:
OspfDatabaseOptions 2.755.1.1.1.3

`demandCircuitsSupport`	*boolean*	Originating router supports OSPF over Demand Circuits.
`doNotUseInRouteCalc`	*boolean*	A type 3,5 or 7 LSA is sent from a PE router to a CE router.
`externalRoutingCapability`	*boolean*	Originating router capable of accepting AS External LSAs.
`linkLocalSignaling`	*boolean*	OSPF packet contains Link-Local Signaling data block.
`multicastCapability`	*boolean*	Originating router supports multicast extensions to OSPF.
`multitopologyCapability`	*boolean*	Originating router supports Multitopology OSPF.
`nssaCapability`	*boolean*	Originating router supports Type-7 NSSA-External-LSAs.
`opaqueLsaSupport`	*boolean*	Originating router supports Type 9,10 and 11 Opaque LSAs.

2.758 show ip ospf local-convergence-delay [...]

vrfs	*table(string) = InstListOspfConvergence-DelayInstanceModel* see 2.758.1	OSPF Microloop.

2.758.1 InstListOspfConvergenceDelayInstanceModel

instList	*table(numeric string) = OspfConvergenceDelay-InstanceModel* see 2.758.1.1	OSPF Instance list keyed by instance id.

2.758.1.1 OspfConvergenceDelayInstanceModel

cfgDelay	*integer*	Configured delay duration in ms.
[currentDelayDetails]	*OspfConvergenceDelay-CurrentModel* see 2.758.1.1.1	Local convergence delay details.
failedRuns	*integer*	Number of times uloop cancelled early.
instanceId	*integer*	OSPF instance ID.
[previousCompletedDelay-Details]	*OspfConvergenceDelay-LastModel* see 2.758.1.1.2	Last local convergence delay details.
routerId	*IPv4 address*	Router ID.
totalRuns	*integer*	Number of attempts.
vrf	*string*	VRF name.

2.758.1.1.1 OspfConvergenceDelayCurrentModel

cause	*enum: linkDown | bfdDown*	Reason for Microloop prevention attempt.
[delayRoutes]	*list of OspfConvergence-DelayRouteModel* see 2.758.1.1.1.1	List of routes delayed.
delayStartTime	*integer*	Time when microloop prevention started.
delayStopTime	*integer*	Time when microloop prevention delay ended.
intfName	*interface name*	Protected interface.
linkFailTime	*integer*	Time when topology failure was detected.
protection	*enum: node | disabled | link*	TI-LFA protection mode.
result	*enum: success | abortLinkUp | abortLinkDown | partialSuccess | abortCleanup | running | abortInvalidBackup*	Result of Microloop prevention attempt.
routesDelayed	*integer*	Number of routes delayed.
state	*enum: delayRoutes | delaySpfScheduled | delayNotRunning | delayInactive*	State of Microloop prevention attempt.

2.758.1.1.1.1 OspfConvergenceDelayRouteModel

destAddr	*IP address prefix*	IPv4 destination address of delayed route.
[routeExportTime]	*integer*	Time when route was updated.

2.758.1.1.2 OspfConvergenceDelayLastModel

cause	*enum: linkDown | bfdDown*	Reason for Microloop prevention attempt.
[delayRoutes]	*list of OspfConvergence-DelayRouteModel* see 2.758.1.1.1.1	List of routes delayed.
delayStartTime	*integer*	Time when microloop prevention started.
delayStopTime	*integer*	Time when microloop prevention delay ended.
intfName	*interface name*	Protected interface.
linkFailTime	*integer*	Time when topology failure was detected.
protection	*enum: node | disabled | link*	TI-LFA protection mode.
result	*enum: success | abortLinkUp | abortLinkDown | partialSuccess | abortCleanup | running | abortInvalidBackup*	Result of Microloop prevention attempt.
routesDelayed	*integer*	Number of routes delayed.
state	*enum: delayRoutes | delaySpfScheduled | delayNotRunning | delayInactive*	State of Microloop prevention attempt.

2.759 show ip ospf lsa-log [...]

vrfs	*table(string) = InstListOspfLsaLogModel* see 2.759.1	OSPF lsa log information.

2.759.1 InstListOspfLsaLogModel

instList	*table(numeric string) = OspfLsaLogModel* see 2.759.1.1	OSPF Instance list keyed by instance id.

2.759.1.1 OspfLsaLogModel

lsaLogEntries	*list of OspfLsaLogEntry* see 2.759.1.1.1	List of OSPF LSA log entries.
routerId	*IPv4 address*	Router ID.
vrf	*string*	VRF name.

2.759.1.1.1 OspfLsaLogEntry

advertisingRouter	*IPv4 address*	LSA advertising router.
linkStateId	*IPv4 address*	LSA link state identifier.
logTime	*floating point number*	LSA log generation time.
lsaEventType	*enum: backoffStarted* | *backedOff* | *backoffRestarted* | *discarded* | *outDelay* | *maxWaitChanged*	LSA event types: backoffStarted - lsa backoff started backedOff - lsa backed off backoffRestarted - lsa backoff restarted outDelay - lsa delayed discarded - lsa discarded maxWaitChanged - lsa max wait value changed.
lsaHoldInterval	*integer*	LSA Hold interval in milliseconds.
lsaType	*integer*	LSA type.
routerNetworkMask	*integer*	LSA advertising router mask.
sequenceNumber	*integer*	LSA sequence number.

2.760 show ip ospf mpls ldp sync [...]

vrfs	*table(string) = InstListOspfMplsLdpSyncModel* see 2.760.1	OSPF mpls ldp sync information for all VRFS.

2.760.1 InstListOspfMplsLdpSyncModel

instList	*table(numeric string) = OspfMplsLdpSyncModel* see 2.760.1.1	OSPF Instance list keyed by instance id.

2.760.1.1 OspfMplsLdpSyncModel

interfaces	*table(string) = OspfMplsLdpSyncEntry* see 2.760.1.1.1	OSPF MPLS LDP Sync status.

2.760.1.1.1 OspfMplsLdpSyncEntry

[holddownTime]	*integer*	IGP holddown time.
[igpDelay]	*integer*	IGP link notify delay.
instanceId	*integer*	OSPF Instance ID.
interface	*string*	OSPF interface.
ldpEnabled	*boolean*	Ldp enabled.
syncAchieved	*enum: Not applicable* | *Yes* | *No*	Sync achieved.
syncRequired	*boolean*	Sync required.

2.761 show ip ospf neighbor [...]

vrfs	*table(string) = InstListOspfNeighborsInstance* see 2.761.1	OSPF neighbor instance information for all VRFs.

2.761.1 InstListOspfNeighborsInstance

instList	*table(numeric string) = OspfNeighborsInstance* see 2.761.1.1	OSPF Instance list keyed by instance id.

2.761.1.1 OspfNeighborsInstance

ospfNeighborEntries	*list of OspfNeighborsEntry* see 2.761.1.1.1	List of OSPF neighbor entries.

2.761.1.1.1 OspfNeighborsEntry

adjacencyState	*enum: gracefulRestart | full | loading | down | 2Ways | init | attempt | exchange | exchStart*	OSPF neighbor adjacency state. down - No hello received from neighbor attempt - Router attempting to establish connection init - Hello received but two-way communication not established 2Ways - Bi-directional communication established between two routers exchStart - Exchange of link state information between routers and their DR and BDR started exchange - Routers exchanging database descriptor packets loading - Exchange of link state information occuring full - Routers are fully adjacent with each other gracefulRestart - Neighbor is gracefully restarting.
[details]	*OspfNeighborDetails* see 2.761.1.1.1.1	OSPF neighbor details.
drState	*enum: DROTHER | BDR | DR*	OSPF neighbor DR state. DR - Neighbor is the designated router BDR - Neighbor is the backup designated router DROTHER - Neighbor is neither DR or the BDR.
inactivity	*floating point number*	Timestamp of OSPF neighbor inactivity/dead timer.
interfaceAddress	*IPv4 address*	OSPF neighbor interface address.
interfaceName	*string*	OSPF neighbor interface name.
options	*OspfOptions* see 2.757.1.1.1.1	OSPF neighbor options.
priority	*integer*	OSPF neighbor priority.
routerId	*string*	OSPF neighbor router identifier.
[routerName]	*string*	OSPF neighbor router domain name.

2.761.1.1.1.1 OspfNeighborDetails

areaId	*IPv4 address*	OSPF neighbor area identifier.

backupDesignatedRouter	*IPv4 address*	OSPF neighbor backup designated router id.
bfdRequestSent	*boolean*	OSPF neighbor BFD request is sent.
bfdState	*enum: down | up | adminDown | init*	OSPF neighbor BFD state. adminDown - Session taken down for administrative purposes init - Waiting for session establishment up - Session established successfully down - Session is down or has just been created.
designatedRouter	*IPv4 address*	OSPF neighbor designated router identifier.
[grExitReason] **	*enum: grExitHelperDisabled | grExitNetworkChanged | grExitGracePeriodExpired | grExitAdjNotFull | grExitGracefulRestartInProgress | grExitNone | grExitGraceLsaFlushed*	OSPF neighbor graceful restart exit reason. **Since: 4.15.3
grHelperTimer **	*floating point number*	Timestamp of OSPF neighbor graceful period expiration. **Since: 4.15.3
grLastRestartTime **	*floating point number*	Timestamp of the OSPF neighbor last graceful restart time. **Since: 4.15.3
grNumAttempts **	*integer*	OSPF neighbor graceful restart attempts. **Since: 4.15.3
inactivityDefers	*integer*	OSPF neighbor inactivity deferred counter.
numberOfStateChanges	*integer*	OSPF neighbor number of state changes.
retransmissionCount	*integer*	OSPF neighbor retransmission count.
[srNeighborInfo] **	*OspfSegmentRoutingNeighborInfo* see 2.761.1.1.1.2	OSPF SR neighbor details. **Since: 4.23.1
stateTime	*floating point number*	OSPF neighbor current state time.

2.761.1.1.1.2 OspfSegmentRoutingNeighborInfo

srGbBase	*integer*	SR Global Block base.
srGbRange	*integer*	SR Global Block range.

2.762 show ip ospf neighbor adjacency-changes [...]

vrfs	*table(string) = InstListOspfNeighborAdjChanges* see 2.762.1	OSPF adjacency changes info for all VRFs.

2.762.1 InstListOspfNeighborAdjChanges

instList	*table(numeric string) = OspfNeighborAdjChanges* see 2.762.1.1	OSPF Instance list keyed by instance id.

2.762.1.1 OspfNeighborAdjChanges

adjacencyChanges	*list of OspfNeighborAdjChangesEntry* see 2.762.1.1.1	List of OSPF adjacency changes.
routerId **	*IPv4 address*	OSPF router identifier. **Since: 4.22.0
shutDown **	*boolean*	Indicates if the OSPF instance is currently shut down. **Since: 4.22.1

2.762.1.1.1 OspfNeighborAdjChangesEntry

adjChangeTimeStamp	*floating point number*	Time when interface adjacency changes in UTC.
adjEstablished	*boolean*	OSPF neighbor interface is established.
[dropReason]	*string*	Reason for the dropped interface adjacency.
interfaceName	*string*	OSPF interface where adjacency is established.
neighborAddress	*IPv4 address*	OSPF neighbor address.
neighborRouterId	*IPv4 address*	OSPF neighbor router identifier.
[routerName]	*string*	OSPF neighbor router domain name.

2.763 show ip ospf neighbor summary [...]

vrfs	*table(string) = InstListOspfNeighborSummaryInstance* see 2.763.1	OSPF neighbor summary for all VRFs.

2.763.1 InstListOspfNeighborSummaryInstance

instList	*table(numeric string) = OspfNeighborSummaryInstance* see 2.763.1.1	OSPF Instance list keyed by instance id.

2.763.1.1 OspfNeighborSummaryInstance

neighborSummary	*OspfNeighborSummary* see 2.763.1.1.1	OSPF neighbor summary information.

2.763.1.1.1 OspfNeighborSummary

num2Ways	*integer*	Number of neighbors in 2 Ways state.

numAttempt	*integer*	Number of neighbors in Attempt state.
numDown	*integer*	Number of neighbors in Down state.
numExchStart	*integer*	Number of neighbors in Exchange Start state.
numExchange	*integer*	Number of neighbors in Exchange state.
numFull	*integer*	Number of neighbors in Full state.
numGracefulRestart	*integer*	Number of neighbors in Graceful Restart state.
numInit	*integer*	Number of neighbors in Init state.
numLoading	*integer*	Number of neighbors in Loading state.

2.764 show ip ospf request queue [...]

vrfs	*table(string) = InstListOspfLsaRequestList* see 2.764.1	OSPF request list information for all VRFs.

2.764.1 InstListOspfLsaRequestList

instList	*table(numeric string) = OspfLsaRequestList* see 2.764.1.1	OSPF Instance list keyed by instance id.

2.764.1.1 OspfLsaRequestList

neighbors	*table(IPv4 address) = OspfLsaRequestInstance* see 2.764.1.1.1	Dictionary of request list keyed by the neighbor's router ID.

2.764.1.1.1 OspfLsaRequestInstance

interfaceAddress	*IPv4 address*	OSPF neighbor interface address.
interfaceName	*string*	OSPF neighbor interface name.
requestQueueLength	*integer*	LSA request queue length.
requests	*list of OspfLsaEntry* see 2.764.1.1.1.1	LSA request list.

2.764.1.1.1.1 OspfLsaEntry

advertisingRouter	*IPv4 address*	LSA advertising router.
age	*integer*	LSA age in seconds.
checksum	*integer*	LSA checksum.
linkStateId	*IPv4 address*	LSA link state identifier.
lsaType	*enum: opaqueType11Lsa | routerLsa | asExternalLsa | summaryLsa | opaqueType9Lsa | nssaLsa | opaqueType10Lsa | networkLsa | summaryAsbrLsa*	LSA type.

sequenceNumber	*integer*	LSA sequence number.

2.765 show ip ospf retransmission queue [...]

vrfs	*table(string) = InstListOspfLsaRetransmissionList* see 2.765.1	OSPF LSA retransmission information for all VRFs.

2.765.1 InstListOspfLsaRetransmissionList

instList	*table(numeric string) = OspfLsaRetransmissionList* see 2.765.1.1	OSPF Instance list keyed by instance id.

2.765.1.1 OspfLsaRetransmissionList

neighbors	*table(IPv4 address) = OspfLsaRetransmissionInstance* see 2.765.1.1.1	Dictionary of retransmission list keyed by the neighbor's router ID.

2.765.1.1.1 OspfLsaRetransmissionInstance

interfaceAddress	*IPv4 address*	OSPF neighbor interface address.
interfaceName	*string*	OSPF neighbor interface name.
[nextRetransmissionTime]	*floating point number*	Next retransmission time in UTC.
retransmissions	*list of OspfLsaEntry* see 2.764.1.1.1.1	LSA retransmission list.
retransmitQueueLength	*integer*	LSA retransmission queue length.

2.766 show ip ospf segment-routing

vrfs	*table(string) = InstListOspfShowSrModel* see 2.766.1	OSPF SR information for all VRFs.

2.766.1 InstListOspfShowSrModel

instList	*table(numeric string) = OspfShowSrModel* see 2.766.1.1	OSPF Instance list keyed by instance id.

2.766.1.1 OspfShowSrModel

dataPlane	*enum: IPV6 | MPLS | None | BOTH*	Data-plane.
instanceId	*integer*	OSPF instance ID.
mappingServer	*boolean*	This is a Segment Routing Mapping Server (SRMS).
reachabilityAlgorithm	*enum: SPF | SSPF*	OSPF Reachability Algorithm.

[routerId]	*IPv4 address*	Router ID.
selfOriginatedSegment-Statistics	*SelfOriginatedSegment-StatisticsModel* see 2.766.1.1.1	Self-originated segment statistics.
srPeerCount	*integer*	Number of OSPF SR capable peers.
srgbBase	*integer*	Base of SRGB.
srgbSize	*integer*	Size of SRGB.

2.766.1.1.1 SelfOriginatedSegmentStatisticsModel

adjSidCount	*integer*	Number of IS-IS SR adjacency segments.
nodeSidCount	*integer*	Number of SR node segments.
prefixSidCount	*integer*	Number of SR prefix segments.
proxyNodeSidCount	*integer*	Number of SR proxy node segments.

2.767 show ip ospf segment-routing adjacency-segments

vrfs	*table(string) = InstListOspfShowSrAdjacencySegmentSummaryModel* see 2.767.1	OSPF SR adjacency segments for all VRFs.

2.767.1 InstListOspfShowSrAdjacencySegmentSummaryModel

instList	*table(numeric string) = OspfShowSrAdjacencySegmentSummaryModel* see 2.767.1.1	OSPF Instance list keyed by instance id.

2.767.1.1 OspfShowSrAdjacencySegmentSummaryModel

adjSidAllocationMode	*enum: all | none | srOnly*	Adj-SID allocation mode.
[adjSidPoolBase]	*integer*	Base of Adj-SID pool.
[adjSidPoolSize]	*integer*	Size of Adj-SID pool.
adjacencySegments	*list of OspfAdjacencySegmentModel* see 2.767.1.1.1	Adjacency Segments.
dataPlane	*enum: IPV6 | MPLS | None | BOTH*	Data-plane.
instanceId	*integer*	OSPF instance ID.
[routerId]	*IPv4 address*	Router ID.

2.767.1.1.1 OspfAdjacencySegmentModel

flags	*OspfAdjacencySegmentFlagsModel* see 2.767.1.1.1.1	Flags.
ipAddress	*IP address*	IP Address of the adjacency.
lan	*boolean*	This is a LAN-SID.
localIntf	*interface name*	Local interface.
protection	*enum: node | unprotected | link*	Protection mode of the local adj-SID.
sid	*integer*	Adjacency Segment assigned to this adjacency.
sidOrigin	*enum: dynamic | configured*	Indicates if adj-SID is configured manually or assigned dynamically.

2.767.1.1.1.1 OspfAdjacencySegmentFlagsModel

b	*boolean*	Adj-SID is eligible for protection.
g	*boolean*	Adj-SID refers to a group of adjacencies.
l	*boolean*	Adj-SID has local significance.
p	*boolean*	Adj-SID is persistent across router restart and/or interface flap.
v	*boolean*	Adj-SID carries a value.

2.768 show ip ospf segment-routing bindings [...]

Could also be an instance of:
MplsLdpBindingsModel 2.768.1.2.1

bindings	*table(string) = MplsLabelBinding* see 2.768.1	Label bindings.

2.768.1 MplsLabelBinding

[local]	*MplsLocalLabels* see 2.768.1.1	Locally defined label bindings.
[remote]	*list of MplsPeerIdAndLabel* see 2.768.1.2	Remote label bindings.

2.768.1.1 MplsLocalLabels

[bindingUpdateTimestamp]	*floating point number*	UTC timestamp of when the labels were assigned.
[elc] **	*boolean*	Entropy label capability. **Since: 4.25.1
[filtered] **	*boolean*	FEC is filtered. **Since: 4.17.1
labels	*list of integer*	Local labels.
[sources] **	*BindingSources* see 2.768.1.1.1	Sources of the binding. **Since: 4.27.0

2.768.1.1.1 BindingSources

[bgpLs] **	*boolean*	BGP Link State. **Since: 4.32.1
[bgpLu]	*boolean*	BGP labeled-unicast.
[isisSr]	*boolean*	IS-IS SR.
[ldp]	*boolean*	LDP.
[loopbackInterface]	*boolean*	Loopback interface.

2.768.1.2 MplsPeerIdAndLabel

[bindingUpdateTimestamp]	*floating point number*	UTC timestamp of when the labels were assigned.
[elc] **	*boolean*	Entropy label capability. **Since: 4.25.1
[filtered] **	*boolean*	FEC is filtered. **Since: 4.17.1
labels	*list of integer*	Peer labels.
peer	*MplsPeerRouterId* see 2.768.1.2.1	Peer ID.

2.768.1.2.1 MplsPeerRouterId

[hostname] **	*string*	Hostname. **Since: 4.21.3
protocol	*enum: ldp | unknown | ospf | rsvp | mplste | bgplu | isis*	Protocol in which router has this ID.
routerId	*string*	Router ID.
[advertisementsSent]	*table(string) = MplsLdpBindingAdvertisements* see 2.768.2	Advertisements sent for FEC keyed by FEC.
bindings	*table(string) = MplsLabelBinding* see 2.768.1	Label bindings.

2.768.2 MplsLdpBindingAdvertisements

advertisedTo	*list of MplsPeerRouterId* see 2.768.1.2.1	Peers this FEC binding has been sent to.

2.769 show ip ospf segment-routing global-blocks

vrfs	*table(string) = InstListOspfShowSrGlobalBlocksSummaryModel* see 2.769.1	OSPF SR global blocks for all VRFs.

2.769.1 InstListOspfShowSrGlobalBlocksSummaryModel

instList	*table(numeric string) = OspfShowSrGlobalBlocksSummaryModel* see 2.769.1.1	OSPF Instance list keyed by instance id.

2.769.1.1 OspfShowSrGlobalBlocksSummaryModel

dataPlane	*enum: IPV6 | MPLS | None | BOTH*	Data-plane.
globalBlocks	*list of OspfGlobalBlockModel* see 2.769.1.1.1	Global blocks.
instanceId	*integer*	OSPF instance ID.
[routerId]	*IPv4 address*	Router ID.
srPeerCount	*integer*	Number of OSPF SR peers capable segments.

2.769.1.1.1 OspfGlobalBlockModel

base	*integer*	SRGB base.
routerId	*string*	Router ID.
size	*integer*	SRGB size.

2.770 show ip ospf segment-routing prefix-segments [...]

vrfs	*table(string) = InstListOspfShowSrPrefix-SegmentSummaryModel* see 2.770.1	OSPF SR prefix segments for all VRFs.

2.770.1 InstListOspfShowSrPrefixSegmentSummaryModel

instList	*table(numeric string) = OspfShowSrPrefixSegment-SummaryModel* see 2.770.1.1	OSPF Instance list keyed by instance id.

2.770.1.1 OspfShowSrPrefixSegmentSummaryModel

dataPlane	*enum: IPV6 | MPLS | None | BOTH*	Data-plane.
instanceId	*integer*	OSPF instance ID.
nodeSidCount	*integer*	Number of SR node segments.
prefixSegments	*list of OspfPrefixSegmentModel* see 2.770.1.1.1	Prefix segments.
prefixSidCount	*integer*	Number of SR prefix segments.
proxyNodeSidCount	*integer*	Number of SR proxy node segments.
[routerId]	*IPv4 address*	Router ID.

2.770.1.1.1 OspfPrefixSegmentModel

[algorithm]	*string*	Algorithm of the prefix segment.
flags	*OspfPrefixSegmentFlags-Model* see 2.770.1.1.1.1	Flags.
[label] **	*integer*	Absolute Segment ID. **Since: 4.32.0
prefix	*IP address prefix*	Prefix address with netmask.
protection **	*enum: node | unprotected | link*	Protection mode of the prefix segment. **Since: 4.33.1
routerIds	*list of string*	Router IDs.
segmentId	*integer*	Segment ID.
segmentType	*enum: Node | Proxy-Node | Prefix*	Type.
selfOriginatedPrefix	*boolean*	Prefix is self originated.
srReachability	*enum: srPartiallyReachable | srReachable | srUnreachable*	Reachability information for Prefix Segments.

2.770.1.1.1.1 OspfPrefixSegmentFlagsModel

e	*boolean*	Set if any upstream neighbor of the Prefix-SID originator MUST replace the Prefix-SID with a Prefix-SID having an Explicit-NULL value before forwarding the packet.
l	*boolean*	Set if the value/index carried by the Prefix-SID has local significance.
m	*boolean*	Set if the Prefix-SID was advertised by a Segment Routing Mapping Server.
np	*boolean*	Set if the penultimate hop MUST NOT pop the Prefix-SID before delivering the packet to the node that advertised the Prefix-SID.
v	*boolean*	Set if the Adj-SID carries a value.

2.771 show ip ospf segment-routing tunnel [...]

entries	*table(numeric string) = OspfSrTunnelTableEntry* see 2.771.1	Tunnel table entries keyed by tunnel index.

2.771.1 OspfSrTunnelTableEntry

endpoint	*IP address prefix*	Endpoint of the tunnel.
vias	*list of Via* see 2.193.1.1	List of nexthops.

2.772 show ip ospf sham-link [...]

see 2.757

2.773 show ip ospf sham-link route [...]

revision 4

[vrfs]	*table(string) = RibRoutesByProtocol* see 2.773.1	For each VRF, map of routes learned through routing protocols that are considered for installation into the forwarding table.

2.773.1 RibRoutesByProtocol

[ribRoutesByProtocol]	*table(string) = RibRoutes* see 2.773.1.1	Map of routes learned through routing protocols that are considered for installation into the forwarding table.

2.773.1.1 RibRoutes

ribRoutes	*table(IPv4 or IPv6 address prefix) = RibRoute* see 2.773.1.1.1	List of routes learned through routing protocolsfor a given prefix.

2.773.1.1.1 RibRoute

bestRoute	*boolean*	Set to true if this route was selected for installation into the forwarding table, false otherwise.
communityList **	*list of string*	BGP communities. **Since: 4.31.0
lastUpdateEpochTime	*integer*	Timestamp in UTC time of the last time the route has been updated.
loopedRoute	*boolean*	Set to true if this route is part of a recursive route resolution loop, false otherwise.
metric	*integer*	The routing protocols internal metric (cost) for this route.
metricType	*enum: AIGP | MED | metric*	The type of metric.
pendingAttributes **	*boolean*	Set to true if the tag or communityList is pending. **Since: 4.31.0
preference	*integer*	The administrative distance of the route.
[recmpEligible]	*boolean*	Set to true if this route is marked eligible for RECMP.
[recursiveNextHops]	*list of RecursiveNextHop* see 2.773.1.1.1.1	List of next-hop routers through which this route is reachable.
[resolvedNextHops]	*list of ResolvedNextHop* see 2.773.1.1.1.4	List of immediate next-hop routers through which this route is reachable.
[routePriority] **	*enum: medium | high | low*	Route processing priority. **Since: 4.32.1
[srcVrfId]	*integer*	ID of VRF from which this route was leaked.
[srcVrfName]	*string*	Name of VRF from which this route was leaked.
[tag] **	*integer*	The tag. **Since: 4.31.0

2.773.1.1.1.1 RecursiveNextHop

[colors]	*list of ColorAndCoBits* see 2.773.1.1.1.2	The list of SR-TE color values and the CO bits for the recursive nexthop.
[flags]	*ViaFlagDetails* see 2.773.1.1.1.8	Via Flags.
[linkBandwidth]	*floating point number*	The link bandwith associated with this next-hop in bytes per second.
[loopedNextHop]	*boolean*	Set to true if this next-hop is part of a recursive route resolution loop, false otherwise.
[metric]	*integer*	The routing protocols internal metric (cost) for the route used to reach this next-hop.
[metricType]	*enum: AIGP | MED | metric*	The type of metric.
[nextHop]	*IP address*	Next hop router address.
[preference]	*integer*	The administrative distance of the route used to reach this next-hop.
[resolutionRibs]	*ResolutionRibProfile* see 2.773.1.1.1.3	Resolution RIBs.
[resolvedNextHops]	*list of ResolvedNextHop* see 2.773.1.1.1.4	The list of immediate next-hop routers through which this recursive next-hop is reachable.
transportType	*enum: evpn | ipv4 | mpls | ipv6*	The type of transport used to reach the destination.
[unresolvedNextHop]	*boolean*	Set to true if this next-hop is unresolved, false otherwise.
[viaSetType]	*enum: invalid | ipv4 | evpn | tunnel | mpls | nexthop-group | ipv6*	Type of vias in the via set.
[viaType]	*enum: backup | active*	Type of via, either active or backup.
[weight] **	*floating point number*	The weight associated with this next-hop. **Since: 4.31.0

2.773.1.1.1.2 ColorAndCoBits

coBits	*enum: AM | EM | NM*	The type of SR-TE policy matching to be done for this color.
value	*integer*	Color value associated with the nexthop.

2.773.1.1.1.3 ResolutionRibProfile

[error]	*string*	Invalid resolution profile reason.
resolutionMethods	*list of ResolutionRib* see 2.158.1.3.2.15	List of resolution methods.

2.773.1.1.1.4 ResolvedNextHop

[evpnNextHop]	*EvpnNextHop* see 2.773.1.1.1.5	Vtep used to reach a destination overevpn transport.
[ipNextHop]	*ResolvedIpNextHop* see 2.773.1.1.1.6	Immediate next-hop router used to reach a destination over ipv4/ipv6 transport.

[notInFec] **	*boolean*	Not in FEC. **Since: 4.24.0
[ospfShamLinkNextHop] **	*ShamLinkNextHop* see 2.773.1.1.1.7	Sham-link interface used as next hop to reach the destination. **Since: 4.30.2
transportType	*enum: evpn | ipv4 | ipv6*	The type of transport used to reach the destination.
[vrfName] **	*string*	Name of VRF in which this next-hop was learned. **Since: 4.23.1

2.773.1.1.1.5 EvpnNextHop

[localInterface] **	*interface name*	Name of the source interface. **Since: 4.26.0
routerMac	*MAC address*	Router mac address of the vtep.
vni	*integer*	Vni associated with this next-hop.
vtep	*IP address*	Vtep address.

2.773.1.1.1.6 ResolvedIpNextHop

[arpResolved]	*boolean*	Designates if nextHop is resolved in ARP/ND.
[decapActionType] **	*enum: none | ipip*	Decapsulation type. **Since: 4.27.0
[fallbackVrf] **	*string*	Fallback VRF name. **Since: 4.27.2
interface	*interface name*	Interface over which the next-hop router is reachable.
[label] **	*integer*	Mpls label. **Since: 4.21.3
[nextHop]	*IP address*	Next hop router address.
[nexthopGroupName] **	*string*	Nexthop Group name over which via resolves. **Since: 4.20.5
[tunnelInterface] **	*TunnelInfo* see 2.193.1.4.1	Tunnel end point details. **Since: 4.21.3
[tunnelVias] **	*list of TunnelViaInfo* see 2.193.1.4.1.2	LSP's for the tunnel. **Since: 4.21.3
[viaType] **	*enum: backup | active*	Type of via, either active or backup. **Since: 4.31.0
[weight] **	*floating point number*	UCMP weight of the via. **Since: 4.31.0

2.773.1.1.1.7 ShamLinkNextHop

interface	*string*	Interface over which the next-hop router is reachable.
[nextHop]	*IP address*	Next hop router address.

2.773.1.1.1.8 ViaFlagDetails

[arpResolved]	*boolean*	ARP/ND resolution information is available for this via.
[bfdMonitoredVia]	*boolean*	The via is monitored by BFD.
[bgpPeerNexthop] **	*boolean*	The via is for BGP peer reachability. **Since: 4.33.0
[martianVia]	*boolean*	This via is for a martian route.
[mustResolveViaConnected]	*boolean*	Via must recursively resolve only over connected routes.
[requireMplsResolution]	*boolean*	Via may recursively resolve over mpls tunnel or RIB/connected routes.
[routeCacheConnectedVia]	*boolean*	This via is for a route cache connected route.
[suppressResolution]	*boolean*	Resolution status information is not published to protocols.

2.774 show ip ospf spf-log [...]

vrfs	*table(string) = InstListOspfSpfLog* see 2.774.1	OSPF SPF log information.

2.774.1 InstListOspfSpfLog

instList	*table(numeric string) = OspfSpfLog* see 2.774.1.1	OSPF Instance list keyed by instance id.

2.774.1.1 OspfSpfLog

[routerId]	*IPv4 address*	OSPF router identifier.
spflogEntries	*list of OspfSpfLogEntry* see 2.774.1.1.1	OSPF SPF Log entries.

2.774.1.1.1 OspfSpfLogEntry

spfDuration	*floating point number*	SPF run duration in milliseconds.
spfStartTime	*floating point number*	SPF Start time in UTC.

2.775 show ip ospf summary [...]

vrfs	*table(string) = InstListOspfShowSummaryModel* see 2.775.1	OSPF instance information for all VRFs.

2.775.1 InstListOspfShowSummaryModel

instList	*table(numeric string) = OspfShowSummaryModel* see 2.775.1.1	OSPF Instance list keyed by instance id.

2.775.1.1 OspfShowSummaryModel

inst	*_OspfShowInstModelAcc* see 2.775.1.1.2	OSPF instance information.
lsasByArea	*table(string) = OspfDatabaseSummary* see 2.756.1.1	Database info by area.
neighbors	*_OspfNeighborsInstanceAcc* see 2.775.1.1.1	Neighbor information.

2.775.1.1.1 _OspfNeighborsInstanceAcc

ospfNeighborEntries	*list of OspfNeighborsEntry* see 2.761.1.1.1	List of OSPF neighbor entries.

2.775.1.1.2 _OspfShowInstModelAcc

abr	*boolean*	This OSPF instance is an Area Border Router.
[areaList]	*table(IPv4 address) = OspfShowInstAreaModel* see 2.748.1.1.2	List of areas in this OSPF instance.
asbr	*boolean*	This OSPF instance is an AS Border Router.
[externalLsaInformation] **	*OspfShowInstExternalLsaInfoModel* see 2.748.1.1.3	External LSA information. **Since: 4.34.2
instanceId	*integer*	OSPF instance ID.
[lsaInformation]	*OspfShowInstLsaInfoModel* see 2.748.1.1.5	LSA information.
maxLsaInformation	*OspfShowInstMaxLsaInfoModel* see 2.748.1.1.6	Max LSA information.
[primaryDomainId] **	*string*	Primary domain identifier. **Since: 4.30.2
[routerId]	*IPv4 address*	OSPF Router id.
[secondaryDomainIds] **	*list of OspfSecondaryDomainId* see 2.748.1.1.1	List of secondary domain identifiers. **Since: 4.30.2

`shutDown` **	*boolean*	Indicates if the OSPF instance is currently shut down. **Since: 4.20.5
`[spfInformation]`	*OspfShowInstSpfInfoModel* see 2.748.1.1.10	SPF information.
`[vrf]`	*string*	VRF name.

2.776 show ip ospf ti-lfa path [...]

vrfs	*table(string)* = *TilfaPathOspfVrfModel* see 2.776.1	A mapping between a vrf and its TI-LFA paths.

2.776.1 TilfaPathOspfVrfModel

[v4Info]	*TilfaPathOspfAfModel* see 2.776.1.1	TI-LFA path information for IPv4 address family.
[v6Info]	*TilfaPathOspfAfModel* see 2.776.1.1	TI-LFA path information for IPv6 address family.

2.776.1.1 TilfaPathOspfAfModel

topologies	*table(string)* = *TilfaPathOspfTopoIdModel* see 2.776.1.1.1	A mapping of topology ID to all TI-LFA paths.

2.776.1.1.1 TilfaPathOspfTopoIdModel

destinations	*table(string)* = *TilfaPathOspfDestModel* see 2.776.1.1.1.1	A mapping of destination Router ID to TI-LFA path for that destination.

2.776.1.1.1.1 TilfaPathOspfDestModel

[hostname]	*string*	Hostname.
pathIds	*table(numeric string)* = *TilfaPathOspfEntryModel* see 2.776.1.1.1.2	mapping of ID representing a constraint to the corresponding TI-LFA path.

2.776.1.1.1.2 TilfaPathOspfEntryModel

constraint	*TilfaPathConstraintModel* see 2.776.1.1.1.4	Path constraint.
[details]	*TilfaPathDetails* see 2.776.1.1.1.8	Detailed path information.
[excludeNodeReachableVia-EcmpInterfaces] **	*list of Interface name*	List of Ecmp interfaces. **Since: 4.34.1
routerIds	*list of RouterIdHostnameModel* see 2.776.1.1.1.3	Ordered list of Router IDs or hostname specifying the path to the destination.
status	*enum: pathNotFound | pathNotComputed | cspfPending | explicitPathFailedValidation | pathFound*	Status of path computation.

2.776.1.1.1.3 RouterIdHostnameModel

[hostname]	*string*	Hostname.

routerId	*string*	OSPF Router ID.

2.776.1.1.1.4 TilfaPathConstraintModel

algoId **	*integer*	Algorithm Id. **Since: 4.30.1
[algoName] **	*string*	Algorithm name. **Since: 4.30.1
[excludeCommonSrlgOfEcmp-Intf] **	*EcmpIntfSrlg* see 2.776.1.1.1.5	Common SRLG of ECMP interfaces that are to be excluded. **Since: 4.34.1
[excludeEcmpInterfaces] **	*list of Interface name*	List of ECMP interfaces. **Since: 4.34.1
[excludeIntf]	*interface name*	Interface excluded from this path.
[excludeNode]	*string*	Node excluded from this path.
[excludeSrlgMode] **	*enum: loose | strict*	Type of SRLG exclusion. **Since: 4.24.2
[excludeSrlgOfIntf] **	*IntfSrlg* see 2.776.1.1.1.7	SRLG exclude of interface. **Since: 4.24.2
[flexAlgo] **	*FlexAlgoPathConstraint-Model* see 2.776.1.1.1.6	FlexAlgo constraint. **Since: 4.30.1

2.776.1.1.1.5 EcmpIntfSrlg

[srlgIds]	*list of integer*	List of common SRLG IDs of ECMP interfaces.

2.776.1.1.1.6 FlexAlgoPathConstraintModel

[excludeAdminGroup]	*integer*	Admin Group excluded.
[excludeAdminGroups-Extended] **	*list of integer*	Extended Admin Groups excluded. **Since: 4.31.1
[excludeSrlg]	*list of integer*	List of SRLG IDs excluded.
[excludeSrlgMode]	*enum: loose | strict*	Type of SRLG exclusion.
[includeAllAdminGroup]	*integer*	Admin Group included.
[includeAllAdminGroups-Extended] **	*list of integer*	Extended Admin Groups included. **Since: 4.31.1
[includeAnyAdminGroup]	*integer*	Any Admin Group included.
[includeAnyAdminGroups-Extended] **	*list of integer*	Any Extended Admin Groups included. **Since: 4.31.1
metricType	*enum: minDelay | igp | te*	Metric type.

2.776.1.1.1.7 IntfSrlg

interface	*interface name*	Interface name.
[srlgIds]	*list of integer*	List of SRLG IDs of the interface.

2.776.1.1.1.8 TilfaPathDetails

[changeCount]	*integer*	Number of times path updated.
[lastUpdatedTime]	*floating point number*	UTC timestamp of the last path update.
refreshReqSeq	*integer*	Request sequence number.
[refreshRespSeq]	*integer*	Response sequence number.

2.777 show ip pim access-list [...]

see 2.62

2.778 show ip pim anycast-rp [...]

anycastRpAddrs	*list of IP address*	a List of Anycase RP addresses.
peerAddrs	*list of IP address*	a List of Anycase peers addresses.

2.779 show ip pim bidirectional df [...]

rpaDfInfo	*table(Interface name) = Rpas* see 2.779.1	Mapping from interface to DF information.

2.779.1 Rpas

dfInfo	*table(IPv4 or IPv6 address) = DfInfo* see 2.779.1.1	Mapping from RP address to DF information.

2.779.1.1 DfInfo

[df]	*boolean*	If true, the router is the DF for the specified interface.
[dfAddr]	*IP address*	DF IP address.
dfState	*enum: backoff | win | lose | offer*	Current DF election state.
[intf] **	*interface name*	Blah Interface. **Since: 4.22.0
[routeMetric]	*integer*	DF route metric.
[routePreference]	*integer*	DF route preference.

2.780 show ip pim bidirectional rp [...]

see 2.27

2.781 show ip pim bidirectional rp-hash GROUP_ADDR [...]

see 2.28

2.782 show ip pim bidirectional upstream joins [...]

see 2.29

2.783 show ip pim bsr [...]

electedBsrs	*table(IPv4 or IPv6 address prefix) = ElectedBsr* see 2.783.1	Map of Bootstrap Routers per Administrative scoped Zone.

2.783.1 ElectedBsr

eBsrAddress	*IP address*	Elected BSR Address.
eBsrCreationTime	*floating point number*	UTC time at which the BSR was elected.
eBsrExpires	*floating point number*	Time after which this BSR might expire.
eBsrExpiryTime	*floating point number*	UTC time at which the BSR will expire.
eBsrHashMaskLen	*integer*	BSR Hash Mask Length.
eBsrPriority	*integer*	BSR priority.
eBsrUpTime	*floating point number*	Time for which this BSR has been elected.
eBsrZone	*IP address prefix*	Administrative Scope Zone.
[local]	*boolean*	Indicates of this router is the BSR.
[scope]	*string*	Hints if the BSR is global or admin scoped.

2.784 show ip pim bsr counters [...]

[errorCounters]	*PimBsrErrorCounters* see 2.784.1	Error counters.
[rx]	*integer*	Total packets received.
[rxBsm]	*integer*	Total BSM's received.
[rxBsmError]	*integer*	Total BSMs received and dropped due to errors.
[rxBsmSuccess]	*integer*	Total BSMs successfully processed.
[rxCrpAdv]	*integer*	Total CRP Advertisement messages received.
[rxCrpAdvError]	*integer*	Total Crp Advertisements received and dropped due toerrors or configuration.
[rxCrpAdvSuccess]	*integer*	Total CRP Advertisements successfully processed.
[rxError]	*integer*	Total packets received and dropped due to errors.
[rxSuccess]	*integer*	Total packets received and processed successfully.
[tx]	*integer*	Total packets transmitted.
[txError]	*integer*	Total packets transmitted and dropped due to errors.
[txSuccess]	*integer*	Total packets transmitted successfully.

2.784.1 PimBsrErrorCounters

rxFilter	*integer*	Total packets received and dropped due to filters.
rxInvalid	*integer*	Total invalid BSMs received.
rxNbrRpfCheck	*integer*	Total BSMs dropped due to RPF check failure.
rxNoForwardBsm	*integer*	Total BSMs dropped due to no forward flag.
rxScopeMismatch	*integer*	Total BSMs dropped due to scope mismatch.
rxUnicastBsm	*integer*	Total BSMs dropped due to unicast destination.

2.785 show ip pim bsr debug

af	*enum: ipv4 | ipv6 | ipunknown*	Address Family supported in this instance.
bootstrapRouter	*BootstrapRouter* see 2.783	Elected Bootstrap Router.
bsBorder	*table(IPv4 or IPv6 address prefix) = PimBsrBorder* see 2.785.1	Pim BSR Border Map.
bsTimeout	*integer*	Boorstrap Holdtime.
cbsr	*table(IPv4 or IPv6 address prefix) = PimBsrCandidate* see 2.785.2	Candidate BSR Map.
counters	*PimBsrCounters* see 2.784	Pim BSR packet counters.
crp	*table(IPv4 or IPv6 address) = PimBsrRpCandidate* see 2.785.3	Candidate RP Map.
crpPermit	*list of IP address prefix*	Candidate RP permit list.
crpStatus	*table(IPv4 or IPv6 address prefix) = PimBsrRpCandidateStatus* see 2.785.4	C-RP sets for G-RP mapping.
szTimeout	*integer*	Scope Zone timeout interval.
zoneAcl	*table(string) = ZoneAcl* see 2.785.5	IntfId to Acl map.
zoneGroup	*table(IPv4 or IPv6 address prefix) = ZoneGroup* see 2.785.6	IntfId to Zone map.

2.785.1 PimBsrBorder

intfs	*list of Interface name*	Interface list.
prefix	*IP address prefix*	Group Prefix.

2.785.2 PimBsrCandidate

address	*IP address*	Candidate BSR IP.
bsPeriod	*integer*	Bootstrap message interval.
elected	*boolean*	Indicates if the candidate BSR is elected BSR.
hashMaskLen	*integer*	Candidate BSR hash mask length.
intfId	*interface name*	Candidate BSR interface identifier.
priority	*integer*	Candidate BSR priority.
state	*enum: pBsr | cBsr | noInfoBsr | eBsr*	Current state of candidate BSR as per RFC.
zone	*IP address prefix*	Zone.

2.785.3 PimBsrRpCandidate

address	*IP address*	Candidate RP IP addres.
interval	*integer*	Candidate RP advertisement interval.
intfId	*interface name*	Candidate RP interface identifier.
prefixOptions	*table(IPv4 or IPv6 address prefix) = integer*	Group prefixes and associated priorities.
prefixSet	*list of IP address prefix*	Group prefixes served by the candidate RP.

2.785.4 PimBsrRpCandidateStatus

crpSet	*table(IPv4 or IPv6 address prefix) = PimRpCandidateSet* see 2.27.1	C-RP set map.
rpSetType	*enum: noneRp | staticRp | bsrRp*	Type of RP Set.
zone	*IP address prefix*	Zone.

2.785.5 ZoneAcl

intfId	*interface name*	Interface Identifier.
zone	*string*	Administrative Scoped Zone.

2.785.6 ZoneGroup

intfId	*interface name*	Interface Identifier.
zone	*IP address prefix*	Administrative Scoped Zone.

2.786 show ip pim bsr rp [...]

see 2.27

2.787 show ip pim bsr rp-hash GROUP [...]

see 2.28

2.788 show ip pim config-sanity anycast-rp [...]

downIntfs	*list of Interface name*	Anycast RP interfaces which are down.
notAnycastRPs	*list of IP address*	This RP address is not configured as anycast RP.
notCfgRPs	*list of IP address*	Anycast RPs not configured on the router.
notIntfCfgRPs	*list of IP address*	Anycast RP not configured on any interface.
notLoopback	*list of Interface name*	Anycast RP interfaces which are not loopback.

notRPs	*list of IP address*	Anycast RPs not configured as RP addresses.
routeCheck	*list of RouteCheck* see 2.788.1	route check hints.

2.788.1 RouteCheck

hintsFound	*integer*	number of hints found.
noRoute	*boolean*	No route to the prefix.
nodeType	*string*	Node type.
nonPimHop	*list of IPv4 address*	Route via non-Pim hops.
nonPimIntf	*list of Interface name*	Route via non-Pim interface.
prefix	*IPv4 address*	Route check for this prefix.

2.789 show ip pim config-sanity bidirectional [...]

[mroute]	*MrtConfigCheck* see 2.789.1	mroute config check for PIM Bidirectional mode.
[pimBidirEnabled]	*boolean*	PIM Bidirectional enabled.
[pimBidirSupported]	*boolean*	PIM Bidirectional supported platform.
[staticRpSet]	*StaticRpSet* see 2.789.2	staticRp config check for PIM Bidirectional mode.

2.789.1 MrtConfigCheck

hintsFound	*integer*	number of hints found.
noRpGroups	*list of IP address*	Group without RP.
rcModel	*list of RouteCheck* see 2.788.1	Route config check.
uroutes	*integer*	number of unresolved routes.

2.789.2 StaticRpSet

hintsFound	*integer*	number of hints found.
noDefaultRp	*boolean*	No default RP configured.
noRp	*boolean*	No RP configured.
notDefinedAcl **	*list of NotDefinedAcl* see 2.789.2.1	Not defined ACL. **Since: 4.33.1
[notDefinedAclConfig] **	*NotDefinedAclConfig* see 2.789.2.2	Not defined ACL config. **Since: 4.33.1
overlapSet	*list of OverlapGroup* see 2.789.2.3	List of overlaping group ranges.
rcModel	*list of RouteCheck* see 2.788.1	Route config check.
rpSet	*list of StaticRp* see 2.789.2.4	List of group RP mappings.

2.789.2.1 NotDefinedAcl

acl	*string*	Acl name.

2.789.2.2 NotDefinedAclConfig

2.789.2.3 OverlapGroup

group	*IP address prefix*	Group address prefix.
overlaps	*list of IP address prefix*	List of overlaping group ranges.

2.789.2.4 StaticRp

mGroup	*string*	group address.
mRpList	*list of string*	List of RPs configured.

2.790 show ip pim config-sanity igmp [...]

boundaryIntfs	*list of Interface name*	Interfaces with multicast boundaries.
disabledIntfs	*list of Interface name*	Disabled interfaces.
hintsFound	*integer*	number of hints found.
igmpSnoopingQuerierVlans **	*list of Interface name*	VLANs with IGMP Snooping L2 querier and IGMP configured. **Since: 4.32.1
invalidBoundaryGroups	*list of InvalidBoundaryGroup* see 2.790.1	Invalid groups configured for boundary.
noRpGroupc	*list of IP address*	Connected group without RP.
noRpGroups	*list of IP address*	Static group without RP.
nonDrIntfs	*list of Interface name*	Non DR interfaces.
nonDrSgIntfs	*list of Interface name*	Interfaces which are not DR.
notDefinedBAcl	*list of NotDefinedBAcl* see 2.790.2	Not defined Acl.
notStandardBAcl	*list of NotStandardBAcl* see 2.790.3	Not standard Acl.
rcModel	*list of RouteCheck* see 2.788.1	Route config check.

2.790.1 InvalidBoundaryGroup

group	*IpAddrAndMask* see 2.302.1.2.2.9	Invalid group prefix.
reason	*string*	Reason for the group being invalid.

2.790.2 NotDefinedBAcl

acl	*string*	Acl name.
intf	*interface name*	Interface Name.

2.790.3 NotStandardBAcl

acl	*string*	Acl name.
intf	*interface name*	Interface Name.

2.791 show ip pim config-sanity interface [...]

disabled	*boolean*	PIM is disabled.
hintsFound	*integer*	number of hints found.
intfsDown	*list of Interface name*	Interfaces which are down.
intfsNoIp	*list of Interface name*	Interfaces without IP address.
intfsNotRouted	*list of Interface name*	Interfaces where routing not enabled.
intfsSparseModeBorderRouter **	*list of Interface name*	Interfaces with PIM sparse-mode and multicast border router enabled. **Since: 4.17.0

2.792 show ip pim config-sanity neighbor [...]

delta	*integer*	time difference.
hintsFound	*integer*	number of hints found.
invalidHello	*list of InvalidHello* see 2.792.1	List of invalid HELLOs.
nfIntf	*list of Interface name*	Neighbor filter enabled interfaces.

2.792.1 InvalidHello

delta	*integer*	Time difference in second between invalid HELLOS.
intfs	*list of Interface name*	interfaces with secondary IP address.

2.793 show ip pim config-sanity sparse-mode [...]

[mroute]	*MrtConfigCheck* see 2.789.1	mroute config check for PIM sparse-mode.
[staticRpSet]	*StaticRpSet* see 2.789.2	staticRp config check for PIM sparse-mode.

2.794 show ip pim interface [...]

interfaces	*table(Interface name) = PimInterface* see 2.794.1	Pim interfaces.

2.794.1 PimInterface

address	*IP address*	Interface address.
[details]	*PimInterfaceDetails* see 2.794.1.1	Pim message detailed counters.
helloPeriod	*integer*	My time interval between sending Hellos in seconds.
intf	*interface name*	Interface name.
[kernelIntf]	*PimKernelInterface* see 2.794.1.2	Interface information from the kernel.
mode	*PimMode* see 2.794.1.3	Pim mode.
neighborCount	*integer*	Number of neighbors on this interface.
[usedDrAddress]	*IP address*	Current DR.
[usedDrPriority]	*integer*	Effective DR priority.

2.794.1.1 PimInterfaceDetails

assertOverrideInterval	*integer*	Assert override interval in seconds.
assertTimeout	*integer*	Assert timeout in seconds.
drPriority	*integer*	My DR priority.
generationId	*integer*	My generation id.
helloDelay	*integer*	My triggered hello delay in seconds.
helloHoldTime	*integer*	My hello hold time in seconds.
joinPruneHoldTime	*integer*	Join/prune hold time in seconds.
joinPrunePeriod	*integer*	Join/prune interval in seconds.
overrideInterval	*integer*	My override interval in milliseconds.
propagationDelay	*integer*	My propagation delay in milliseconds.
[secondaryAddress] **	*list of IP address*	Secondary addresses. **Since: 4.28.1
trackingSupport	*boolean*	Tracking support and disabling join suppression.
usedOverrideInterval	*integer*	Effective propagation delay in milliseconds.
usedPropagationDelay	*integer*	Effective propagation delay in milliseconds.
usedTrackingSupport	*boolean*	Effective tracking support.

2.794.1.2 PimKernelInterface

bytesIn	*integer*	Bytes received.
bytesOut	*integer*	Bytes sent.
name	*string*	Kernel interface name.
pktsDropped	*integer*	Number of packets dropped by kernel.

pktsIn	*integer*	Packets received.
pktsOut	*integer*	Packets received.
pktsQueued	*integer*	Number of packets queued by kernel.
[virtualInterface]	*integer*	Virtual interface number.

2.794.1.3 PimMode

borderRouter	*boolean*	Multicast border router is enabled.
mode	*enum: Sparse/Bidir* **|** *Bidir* **|** *None* **|** *Sparse*	Pim operational mode.

2.795 show ip pim neighbor [...]

revision 2

vrfs	*table(string) = VrfPimNeighbors* see 2.795.1	A mapping between VRF name and PimNeighbors.

2.795.1 VrfPimNeighbors

interfaces	*table(string) = IntfPimNeighbors* see 2.795.1.1	Pim neighbors by interfaces.

2.795.1.1 IntfPimNeighbors

neighbors	*table(IPv4 or IPv6 address) = PimNeighbor* see 2.795.1.1.1	Pim neighbors.

2.795.1.1.1 PimNeighbor

address	*IP address*	Neighbor address.
bfdState	*enum: down | up | init | adminDown | disabled*	BFD session state with neighbor.
creationTime	*floating point number*	UTC time when neighbor was created.
[detail] **	*boolean*	Display detailed neighbor information. **Since: 4.28.1
holdTime	*integer*	Holdtime for neighbor in seconds.
intf	*interface name*	Interface through which neighbor was discovered.
lastRefreshTime	*floating point number*	UTC time when neighbor last sent Hello message.
maintenanceReceived **	*boolean*	Neighbor is undergoing maintenance. **Since: 4.31.0
maintenanceSent **	*boolean*	Communicated to neighbor that we are undergoing maintenance. **Since: 4.31.0
mode	*PimMode* see 2.794.1.3	Interface mode.
[multipathColor] **	*integer*	Multipath Color. **Since: 4.28.1
[routerId] **	*IPv4 address*	Router ID. **Since: 4.28.1
[secondaryAddress] **	*list of IP address*	Pim neighbor secondary addresses. **Since: 4.28.1
transport	*enum: tcp | sctp | datagram*	The transport mechanism used for sending/receiving or join/prune messages.

2.796 show ip pim neighbor bfd [...]

revision 2

vrfs	*table(string) = VrfPimBfdNeighbors* see 2.796.1	A mapping between VRF name and PimBfdNeighbors.

2.796.1 VrfPimBfdNeighbors

interfaces	*table(string) = IntfPimNeighbors* see 2.795.1.1	Pim neighbors by interfaces.

2.797 show ip pim protocol counters [...]

counters	*table(string) = PimMessageCounter* see 2.797.1	Map from message type to its counters.
[details]	*PimMessageCounters-Details* see 2.797.2	Detailed interface information.

2.797.1 PimMessageCounter

rxFiltered	*integer*	Filtered received packets.
rxInvalid	*integer*	Invalid/errored received packets.
rxPackets	*integer*	Received packets.
txFiltered	*integer*	Filtered sent packets.
txInvalid	*integer*	Invalid/errored sent packets.
txPackets	*integer*	Sent packets.

2.797.2 PimMessageCountersDetails

subtypeCounters	*table(string) = PimMessageSubtypeCounters* see 2.797.2.1	Map from message type to its subtype counters.

2.797.2.1 PimMessageSubtypeCounters

subtypeCounter	*table(string) = PimMessageCounter* see 2.797.1	Subtype message counters.

2.798 show ip pim register-source [...]

intf	*interface name*	Interface name.
setting	*enum: no config | iif | default | interface*	Register source setting configured.

2.799 show ip pim rp [...]

revision 2

[bidirectional]	*PimRpCandidates* see 2.27	RP Candidate Set for Bidirectional PIM.
[sparseMode]	*PimRpCandidates* see 2.27	RP Candidate Set for Sparse-mode PIM.

2.800 show ip pim rp-candidate [...]

crps	*table(IPv4 or IPv6 address) = PimRpCandidate* see 2.800.1	Map of Candidate RP local to this router.

2.800.1 PimRpCandidate

holdTime	*integer*	C-RP Holdtime.
prefixOptions	*table(IPv4 or IPv6 address prefix) = PimCrpPrefixOptions* see 2.800.1.2	List of priority associated with prefixes.
prefixSet	*table(IPv4 or IPv6 address prefix) = PimCrpPrefix* see 2.800.1.1	List of group prefixes supported by C-RP.
rpAddress	*IP address*	IP address of RP.

2.800.1.1 PimCrpPrefix

prefix	*IP address prefix*	Group Prefix.

2.800.1.2 PimCrpPrefixOptions

prefix	*IP address prefix*	Group Prefix.
priority	*integer*	Group RP Priority.

2.801 show ip pim rp-hash GROUP_ADDR [...]

[bidirectional]	*PimRpHash* see 2.28	RP Hash for Bidirectional PIM.
[sparseMode]	*PimRpHash* see 2.28	RP Hash for Sparse-mode PIM.

2.802 show ip pim upstream joins [...]

see 2.29

2.803 show ip prefix-list NAME detail

ipPrefixLists	*table(string) = IpPrefixList* see 2.803.1	Map prefix list name to prefix list.

2.803.1 IpPrefixList

[duplicateHandling] **	*string*	Enable handling of duplicate entries in URL prefix list. **Since: 4.18.0
ipPrefixEntries	*list of IpPrefixEntry* see 2.803.1.1	Prefix list entries sorted by increasing sequence number.
[ipPrefixListSource] **	*string*	Source URL of the prefix list. **Since: 4.18.0
[ipRemarkEntries] **	*list of IpRemarkEntry* see 2.803.1.2	Remark list entries sorted by increasing sequence number. **Since: 4.33.1
[vrfName] **	*string*	Enable handling of custom VRF in URL prefix list. **Since: 4.30.1

2.803.1.1 IpPrefixEntry

[eq]	*integer*	Exact prefix length.
filterType	*enum: deny | permit*	Filter type.
[ge]	*integer*	Minimum prefix length.
[le]	*integer*	Maximum prefix length.
prefix	*IP address prefix*	Subnet upon which command filters routes.
seqno	*integer*	Sequence number of prefix list entry.

2.803.1.2 IpRemarkEntry

remark	*string*	Comment, up to 100 characters.
seqno	*integer*	Sequence number of remark list entry.

2.804 show ip prefix-list NAME summary

[entryCount]	*integer*	Prefix list entry count.
[pfxListSource]	*string*	Prefix list source.
[sourceTimeStamp]	*floating point number*	Prefix list source timestamp.

2.805 show ip prefix-list [...]

see 2.803

2.806 show ip rip access-list [...]

see 2.62

2.807 show ip route (PREFIX | ADDR) longer-prefixes [...]

revision 4

Could also be an instance of:
VrfLdpIpRoutes 2.807.1.1.3

vrfs	*table(string) = IpRoutes* see 2.807.1	Route info of each Vrf.

2.807.1 IpRoutes

allRoutesProgrammedHardware	*boolean*	True if every route is programmed in hardware.
allRoutesProgrammedKernel	*boolean*	True if every route is programmed in kernel.
defaultRouteState	*enum: notReachable | reachable | notSet*	The state of the default route.
routes	*table(string) = IpRoute* see 2.807.1.1	List of routes keyed by prefix.
routingDisabled	*boolean*	True if routing is disabled.

2.807.1.1 IpRoute

[cbfVias]	*list of CbfVia* see 2.807.1.1.1	List of Class based forwarding vias.
directlyConnected	*boolean*	True if this route is directly connected though an interface, internal, or is a drop route.
hardwareProgrammed	*boolean*	True if this route is programmed in hardware.
kernelProgrammed	*boolean*	True if this route is programmed in the kernel.
[loopingRoute] **	*boolean*	True if this route is part of a recursive route resolution loop. **Since: 4.33.1
[metric]	*integer*	Used by routing protocol to determine whether one route should be chosen over another. Lower metrics have precedence.
[preference]	*integer*	Administrative distance; lower values have precedence.
routeAction	*enum: forward | drop*	What kind of route it is.
routeLeaked	*boolean*	True if this route is leaked from different VRF.
[routePriority] **	*enum: medium | high | low*	Route processing priority. **Since: 4.31.2
[routeSubtype] **	*enum: External2 | NssaExternal2 | InterArea | IntraArea | NssaExternal1 | External1*	OSPFv3 route type. **Since: 4.33.1

routeType	*enum: RIP | dropRoute | OSPF | static | CBFLeaked | iBGP | ospfSummary | ISISLevel2 | ospfInterArea | vcs | ospfNssaExternalType2 | ospfExternalType2 | nexthopGroupStaticRoute | bgpAggregate | ospfNssaExternalType1 | connected | kernel | eBGP | ospfExternalType1 | routeCacheConnected | BGP | gribi | dynamicPolicy | martian | OSPFv3 | dhcp | ISISLevel1*	The IPv4 route type.
[srTePolicy]	*list of RouteSrTePolicy* see 2.807.1.1.1.2	SR-TE policy.
[srcVrf]	*string*	Name of the VRF route is leaked from.
vias	*list of IpRouteVia* see 2.807.1.1.2	List of vias.

2.807.1.1.1 CbfVia

[coloredEndpoints]	*list of CbfColoredTep* see 2.807.1.1.1.1	CBF colored endpoints information.
[dscpValues]	*list of integer*	List of DSCP values.
[labelStack]	*list of integer*	MPLS label stack (top-of-stack label first).
[mplsLabel]	*integer*	MPLS label (service label); may also be included in the labelStack.
[srTePolicy]	*RouteSrTePolicy* see 2.807.1.1.1.2	SR-TE policy.
[tcValues] **	*list of integer*	List of traffic class values. **Since: 4.29.0
[tunnelSource]	*enum: BGP LU Forwarding | maxTunnelType | IP-in-IP | MLDP P2MP | invalidTunnel | VXLAN VTEP Encap | IS-IS SRv6 | Nexthop | Static MPLS | SR-TE Policy | SR-TE | OSPF SR | IS-IS SRv6 TI-LFA | IS-IS FlexAlgo | Static MPLS Multicast | Nexthop Group | TI-LFA | LDP | RSVP LER SUB | SRv6 SR-TE SL | RSVP P2MP | RSVP LER | EosSdk sBFD | UDP | SRv6 Transport | EVPN VXLAN | VXLAN | RSVP FRR | IS-IS Remote TI-LFA | BGP LU | RSVP | IS-IS SR | Static Interface*	Tunnel Type.

[vrfSelectionInfo] **	*VrfSelectionInfo* see 2.807.1.1.1.3	VRF Selection Info. **Since: 4.30.2

2.807.1.1.1.1 CbfColoredTep

[algorithm] **	*string*	Algorithm name. **Since: 4.35.2
color	*integer*	Color assigned to Tunnel.
endpoint	*IP address prefix*	Tunnel endpoint.

2.807.1.1.1.2 RouteSrTePolicy

color	*integer*	SR-TE policy color.
endpoint	*IP address*	SR-TE policy destination.

2.807.1.1.1.3 VrfSelectionInfo

policyName	*string*	VRF Selection Policy Name.
vrfName	*string*	VRF name to which the route is leaked.

2.807.1.1.2 IpRouteVia

Could also be an instance of:
IpRibRouteVia 2.807.1.1.3

[decapActionType] **	*enum: none | ipip*	Decapsulation type. **Since: 4.27.0
[egressVrf] **	*string*	Name of the nexthop's VRF if the route is an inter-vrf route. **Since: 4.23.0
[fallbackVrf] **	*string*	Fallback VRF. **Since: 4.27.2
[interface]	*interface name*	Name of the interface.
[interfaceDescription]	*string*	Interface description.
[labelStack] **	*list of integer*	MPLS label stack (top-of-stack label first). **Since: 4.20.0
[localAddress] **	*IP address*	Local address of the BFD session when this route via is BFD tracked. **Since: 4.30.1
[localInterface] **	*interface name*	Name of the source interface. **Since: 4.26.0
[mplsLabel]	*integer*	MPLS label (service label); may also be included in the labelStack.
[nexthopAddr]	*IP address*	Nexthop address of the via.
[nexthopGroup] **	*IpRouteNexthopGroup* see 2.807.1.1.2.1	Nexthop group. **Since: 4.21.3
[resolvedVias] **	*list of IpRouteVia* see 2.807.1.1.2	List of resolution vias. **Since: 4.26.2
[routerMac]	*MAC address*	VXLAN remote VTEP mac address.

[srTePolicy] **	*list of RouteSrTePolicy* see 2.807.1.1.1.2	SR-TE policy. **Since: 4.35.2
[srv6Sid] **	*IPv6 address*	SRv6 SID (service SID). **Since: 4.29.0
[tunViaBackupVias] **	*list of TunnelViaInfo* see 2.193.1.4.1.2	List of nested tunnel backup vias. **Since: 4.25.2
[tunnelDescriptor] **	*TunnelInfo* see 2.193.1.4.1	Tunnel information. **Since: 4.20.5
[ucmpGenerationMode] **	*linkBandwidth*	UCMP mode. **Since: 4.31.0
[viaType]	*enum: backup | active*	Type of Via. PIC has backup Vias.
[viaWeight] **	*string*	UCMP load-balance weight. **Since: 4.20.5
[vias] **	*list of TunnelViaInfo* see 2.193.1.4.1.2	List of nested tunnel vias. **Since: 4.20.5
[vni]	*integer*	VXLAN Virtual Network Identifier.
[vtepAddr]	*IP address*	VXLAN remote VTEP IP address.

2.807.1.1.2.1 IpRouteNexthopGroup

groupId	*integer*	Nexthop group Id.
groupName	*string*	Nexthop group name.

2.807.1.1.3 IpRibRouteVia

[decapActionType] **	*enum: none | ipip*	Decapsulation type. **Since: 4.27.0
[egressVrf] **	*string*	Name of the nexthop's VRF if the route is an inter-vrf route. **Since: 4.23.0
[fallbackVrf] **	*string*	Fallback VRF. **Since: 4.27.2
[interface]	*interface name*	Name of the interface.
[interfaceDescription]	*string*	Interface description.
[labelStack] **	*list of integer*	MPLS label stack (top-of-stack label first). **Since: 4.20.0
[localAddress] **	*IP address*	Local address of the BFD session when this route via is BFD tracked. **Since: 4.30.1
[localInterface] **	*interface name*	Name of the source interface. **Since: 4.26.0
[mplsLabel]	*integer*	MPLS label (service label); may also be included in the labelStack.
[nexthopAddr]	*IP address*	Nexthop address of the via.
[nexthopGroup] **	*IpRouteNexthopGroup* see 2.807.1.1.2.1	Nexthop group. **Since: 4.21.3
[nexthopName]	*string*	Nexthop name.
[resolvedVias] **	*list of IpRouteVia* see 2.807.1.1.2	List of resolution vias. **Since: 4.25.2
[routerMac] **	*MAC address*	VXLAN remote VTEP mac address. **Since: 4.18.0

[srTePolicy] **	*list of RouteSrTePolicy* see 2.807.1.1.1.2	SR-TE policy. **Since: 4.35.2
[srv6Sid] **	*IPv6 address*	SRv6 SID (service SID). **Since: 4.29.0
[tunViaBackupVias] **	*list of TunnelViaInfo* see 2.193.1.4.1.2	List of nested tunnel backup vias. **Since: 4.25.2
[tunnelDescriptor] **	*TunnelInfo* see 2.193.1.4.1	Tunnel information. **Since: 4.20.5
[ucmpGenerationMode] **	*linkBandwidth*	UCMP mode. **Since: 4.31.0
[viaType]	*enum: backup | active*	Type of Via. PIC has backup Vias.
[viaWeight] **	*string*	UCMP load-balance weight. **Since: 4.20.5
[vias] **	*list of TunnelViaInfo* see 2.193.1.4.1.2	List of nested tunnel vias. **Since: 4.20.5
[vni] **	*integer*	VXLAN Virtual Network Identifier. **Since: 4.18.0
[vtepAddr] **	*IP address*	VXLAN remote VTEP IP address. **Since: 4.18.0
vrfs	*table(string) = IpRoutes* see 2.807.1	Route info of each Vrf.

2.808 show ip route [...]

revision 4

see 2.807

2.809 show ip route fec [...]

vrfs	*table(string) = FecRoutesModel* see 2.809.1	Mapping of VRF name to its FECs.

2.809.1 FecRoutesModel

fecRoutes	*table(string) = FecRouteModel* see 2.809.1.1	A mapping of FEC ID to its routes.

2.809.1.1 FecRouteModel

ipv4PrefixCount	*integer*	Number of IPv4 prefixes using this FEC.
ipv6PrefixCount	*integer*	Number of IPv6 prefixes using this FEC.
nextHops	*list of FecNextHopModel* see 2.809.1.1.1	Next hops for this FEC.
[orderedFec]	*boolean*	This is an ordered FEC.
[ucmpEligibleFec] **	*boolean*	This is an UCMP eligible FEC. **Since: 4.30.2

2.809.1.1.1 FecNextHopModel

[decapActionType] **	*enum: none | ipip*	Decapsulation type. **Since: 4.27.0
[directlyConnected]	*boolean*	This is a direct connection.
[fallbackVrf] **	*string*	Fallback VRF name. **Since: 4.27.2
[groupID]	*integer*	The ID of the next hop group.
[groupName]	*string*	The name of the next hop group.
[hop]	*IP address*	The hop prefix.
[internalConnection]	*boolean*	The connection is internal.
[intfID]	*interface name*	The Interface ID.
[isDynamicTunnel]	*boolean*	This route is a dynamic tunnel connection.
[tunnelID]	*integer*	The ID of the tunnel connection.

[tunnelTypeStr]	*enum: ipInIpTunnel* | *maxTunnelType* | *isisSrv6IgpTilfaTunnel* | *nexthopTunnel* | *staticInterfaceTunnel* | *nexthopGroupTunnel* | *mldpP2mpTunnel* | *bgpLuForwardingTunnel* | *srv6SrTeSegmentListTunnel* | *invalidTunnel* | *staticV4Tunnel* | *rsvpP2mpTunnel* | *ospfSrTunnel* | *rsvpLerSubTunnel* | *vxlanVtepEncapTunnel* | *tiLfaTunnel* | *evpnVxlanTunnel* | *rsvpLerTunnel* | *eosSdkSbfdSessionTunnel* | *ldpTunnel* | *srV4Tunnel* | *staticV6Tunnel* | *vxlanTunnel* | *bgpLuTunnel* | *rsvpTunnel* | *srv6TransportTunnel* | *isisFlexAlgoTunnel* | *gueTunnel* | *staticTunnel* | *srTePolicyTunnel* | *rsvpFrrTunnel* | *srTeSegmentListTunnel* | *staticMcastTunnel* | *isisRemoteTiLfaTunnel* | *isisSrv6IgpTunnel* | *srV6Tunnel* | *srTunnel*	The type of tunnel connection.
[viaNull]	*boolean*	There are no next hops.

2.810 show ip route fec protocol summary

protocols	*table(string) = FecTypeBreakdown* see 2.810.1	Breakdown of FECs per FEC source.
receiveFecCount	*integer*	Count of receive FECs.

2.810.1 FecTypeBreakdown

drop	*integer*	Number of FECs of type drop.
ecmp	*integer*	Number of FECs with multiple next hops.
nonEcmp	*integer*	Number of FECs with single next hop.
stale	*integer*	Number of stale FECs.

2.811 show ip route fec summary [...]

fecBreakdowns	*table(numeric string) = FecBreakdown* see 2.811.1	Breakdown of FECs, Prefixes and Hierarchical References per FEC Size.

2.811.1 FecBreakdown

fecSize	*integer*	FEC Size.
numFecs	*integer*	Total number of FECs.
numHierarchicalRefs **	*integer*	Total number of hierarchical references. **Since: 4.20.5
numPrefixes	*integer*	Total number of prefixes.

2.812 show ip route host [...]

revision 2

vrfs	*table(string) = IpRoutesHost* see 2.812.1	A mapping of VRF to its host routes.

2.812.1 IpRoutesHost

allRoutesProgrammedHardware	*boolean*	Every route is programmed in hardware.
routes	*table(string) = IpRouteHost* see 2.812.1.1	IP host routes keyed by prefix.
[routingDisabled]	*boolean*	Routing is disabled.

2.812.1.1 IpRouteHost

hardwareProgrammed	*boolean*	True if this route is programmed in hardware.
routeType	*enum: broadcast | attached | receive | directedBcast | FIB*	The ip route host type.
vias	*list of IpRouteHostVia* see 2.812.1.1.1	List of host vias.

2.812.1.1.1 IpRouteHostVia

[interface]	*interface name*	Name of the interface.
[nexthopAddr]	*IP address*	Nexthop address of the via.
[routerMac]	*MAC address*	VXLAN remote VTEP mac address.
toCpu	*boolean*	True if route goes to cpu.
[vni]	*integer*	VXLAN Virtual Network Identifier.
[vtepAddr]	*IP address*	VXLAN remote VTEP IP address.

2.813 show ip route kernel unprogrammed [...]

vrfs	*table(string) = UnprogrammedRoutes* see 2.813.1	A dictionary of unprogrammed routes keyed by VRF.

2.813.1 UnprogrammedRoutes

prefixes	*table(IPv4 or IPv6 address prefix) = UnprogrammedRoute* see 2.813.1.1	A dictionary of unprogrammed route details keyed by prefix.

2.813.1.1 UnprogrammedRoute

errorCode	*integer*	Standard error code.
[interface]	*interface name*	Unprogrammed route interface.

2.814 show ip route multicast [...]

revision 3

routes	*table(IPv4 or IPv6 address prefix) = MulticastRibRoute* see 2.814.1	Multicast static routes.

2.814.1 MulticastRibRoute

[routeCreationTime]	*string*	Route creation time.
routeMetric	*integer*	Route metric.
routePreference	*integer*	Route preference.
routeProtocol	*string*	Routing protocol through which this route was learnt.
vias	*table(IPv4 or IPv6 address) = string*	set of next-hop addresses that this route is reachable via.

2.815 show ip route next-hop nexthop-group [...]

revision 4

see 2.807

2.816 show ip route next-hop vxlan [...]

revision 4

see 2.807

2.817 show ip route priority summary [...]

vrfs	*table(string) = IpRoutePrioritySummaryForVrf* see 2.817.1	Route priority summary of each VRF.

2.817.1 IpRoutePrioritySummaryForVrf

[attached]	*PriorityCount* see 2.817.1.1	Attached routes priority breakdown.
[bgpAggregate]	*PriorityCount* see 2.817.1.1	BGP aggregate routes priority breakdown.
[bgpExternal]	*PriorityCount* see 2.817.1.1	BGP external routes priority breakdown.
[bgpInternal]	*PriorityCount* see 2.817.1.1	BGP internal routes priority breakdown.
[bgpOther]	*PriorityCount* see 2.817.1.1	BGP other routes priority breakdown.
[connected]	*PriorityCount* see 2.817.1.1	Connected routes priority breakdown.
[dhcp]	*PriorityCount* see 2.817.1.1	DHCP routes priority breakdown.
[dynamicPolicy]	*PriorityCount* see 2.817.1.1	Dynamic policy routes priority breakdown.
[gribi]	*PriorityCount* see 2.817.1.1	gRIBI routes priority breakdown.
[isisLevel1]	*PriorityCount* see 2.817.1.1	IS-IS level 1 routes priority breakdown.
[isisLevel2]	*PriorityCount* see 2.817.1.1	IS-IS level 2 routes priority breakdown.
[kernel]	*PriorityCount* see 2.817.1.1	Kernel routes priority breakdown.
[martian]	*PriorityCount* see 2.817.1.1	Martian routes priority breakdown.
[nextHopGroup]	*PriorityCount* see 2.817.1.1	Nexthop group routes priority breakdown.
[ospf]	*PriorityCount* see 2.817.1.1	OSPF routes priority breakdown.
[ospfExternalType1]	*PriorityCount* see 2.817.1.1	OSPF external type 1 routes priority breakdown.
[ospfExternalType2]	*PriorityCount* see 2.817.1.1	OSPF external type 2 routes priority breakdown.
[ospfInterArea]	*PriorityCount* see 2.817.1.1	OSPF inter area routes priority breakdown.
[ospfNssaExternalType1]	*PriorityCount* see 2.817.1.1	OSPF NSSA external type 1 routes priority breakdown.
[ospfNssaExternalType2]	*PriorityCount* see 2.817.1.1	OSPF NSSA external type 2 routes priority breakdown.
[ospfSummary]	*PriorityCount* see 2.817.1.1	OSPF summary routes priority breakdown.
[ospfV3]	*PriorityCount* see 2.817.1.1	OSPFv3 routes priority breakdown.

[ospfV3ExternalType1]	*PriorityCount* see 2.817.1.1	OSPFv3 external type 1 routes priority breakdown.
[ospfV3ExternalType2]	*PriorityCount* see 2.817.1.1	OSPFv3 external type 2 routes priority breakdown.
[ospfV3InterArea]	*PriorityCount* see 2.817.1.1	OSPFv3 inter area routes priority breakdown.
[ospfV3NssaExternalType1]	*PriorityCount* see 2.817.1.1	OSPFv3 NSSA external type 1 routes priority breakdown.
[ospfV3NssaExternalType2]	*PriorityCount* see 2.817.1.1	OSPFv3 NSSA external type 2 routes priority breakdown.
[rip]	*PriorityCount* see 2.817.1.1	RIP routes priority breakdown.
[routeCache]	*PriorityCount* see 2.817.1.1	Route Cache routes priority breakdown.
[staticNonPersistent]	*PriorityCount* see 2.817.1.1	Static non-persistent routes priority breakdown.
[staticPersistent]	*PriorityCount* see 2.817.1.1	Static persistent routes priority breakdown.
[vcs]	*PriorityCount* see 2.817.1.1	VXLAN control service routes priority breakdown.

2.817.1.1 PriorityCount

high	*integer*	Number of high priority routes.
low	*integer*	Number of low priority routes.
medium	*integer*	Number of medium priority routes.

2.818 show ip route rpf unicast [...]

[interfaces]	*table(Interface name) = UrpfInterface* see 2.818.1	Mapping of interface to the additional interface state details.
[prefix]	*IP address prefix*	Destination Prefix.
[viaDefaultRoute]	*boolean*	uRPF is carried out via the default route.

2.818.1 UrpfInterface

allowDefault	*boolean*	Packets are permitted to come in on the default interface.
[lookupVrf] **	*string*	Name of uRPF lookup VRF. **Since: 4.28.2
uRpfMode	*enum: disable | loose | strictDefault | strict*	URPF mode state.

2.819 show ip route static not-installed bfd [...]

vrfs	*table(string) = NotInstalledBfd* see 2.819.1	Route info of each Vrf.

2.819.1 NotInstalledBfd

routes	*table(string) = AllRoutes* see 2.819.1.1	Bfd disabled static routes.

2.819.1.1 AllRoutes

viaGroups	*list of ViaList* see 2.819.1.1.1	List of all paths.

2.819.1.1.1 ViaList

[metric]	*integer*	Used by routing protocol to determine whether one route should be chosen over another. Lower metrics have precedence.
[preference]	*integer*	Administrative distance; lower values have precedence.
vias	*list of IpRouteSimpleVia* see 2.819.1.1.1.1	List of vias.

2.819.1.1.1.1 IpRouteSimpleVia

Could also be an instance of:
IpRibRouteVia 2.807.1.1.3
IpRouteVia 2.807.1.1.2

[egressVrf] **	*string*	Name of the nexthop's VRF if the route is an inter-vrf route. **Since: 4.23.0
[interface]	*interface name*	Name of the interface.
[localAddress] **	*IP address*	Local address of the BFD session when this route via is BFD tracked. **Since: 4.30.1
[nexthopAddr]	*IP address*	Nexthop address of the via.

2.820 show ip route summary [...]

revision 3

protoModelStatus **	*ServiceRoutingProtoModelStatus* see 2.820.2	Active and configured protocol models. **Since: 4.23.0
vrfs	*table(string) = IpRouteSummaryForVrf* see 2.820.1	Route summary of each VRF.

2.820.1 IpRouteSummaryForVrf

aggregate	*integer*	Number of aggregate routes.
attached	*integer*	Number of attached routes.
bgpCounts	*bgpTotals* see 2.820.1.1	BGP route count breakdown.
connected	*integer*	Number of connected routes.
dynamicPolicy **	*integer*	Number of dynamic policy routes. **Since: 4.21.0
[fibRouteCount] **	*integer*	Fib Route Count. **Since: 4.34.1
[fibRouteLimit] **	*integer*	Fib Route Limit. **Since: 4.34.1
[fibRouteLimitSuppressedCount] **	*integer*	FIB Suppressed Route Count. **Since: 4.34.1
gribi **	*integer*	Number of gRIBI routes. **Since: 4.26.2
internal	*integer*	Number of internal routes.
isisCounts	*isisTotals* see 2.820.1.2	IS-IS route count breakdown.
maskLen	*table(numeric string) = integer*	Counts for each mask length.
ospfCounts	*ospfTotals* see 2.820.1.3	OSPF route count breakdown.
ospfv3Counts	*ospfv3Totals* see 2.820.1.4	OSPFv3 route count breakdown.
rip	*integer*	Number of rip routes.
static	*integer*	Number of static routes.
staticNexthopGroup	*integer*	Number of static nexthop-group routes.
staticNonPersistent	*integer*	Number of static routes configured using the SDK with persistent=False.
staticPersistent	*integer*	Number of static routes configured to persist.
totalRoutes	*integer*	Total number of routes.
[vcs]	*integer*	Number of VXLAN Control Service routes.
[vrfCount]	*integer*	Total number of vrf instances.

2.820.1.1 bgpTotals

bgpExternal	*integer*	Number of bgp External routes.
bgpInternal	*integer*	Number of bgp Internal routes.
bgpLocal **	*integer*	Number of bgp Other routes. **Since: 4.22.1
bgpTotal	*integer*	Total number of bgp routes.

2.820.1.2 isisTotals

isisLevel1	*integer*	Number of isis Level-1 routes.
isisLevel2	*integer*	Number of isis Level-2 routes.
isisTotal	*integer*	Total number of isis routes.

2.820.1.3 ospfTotals

nssaExternal1	*integer*	Number of Ospf NSSA External-1 routes.
nssaExternal2	*integer*	Number of Ospf NSSA External-2 routes.
ospfExternal1	*integer*	Number of Ospf External-1 routes.
ospfExternal2	*integer*	Number of Ospf External-2 routes.
ospfInterArea	*integer*	Number of Ospf Inter-area routes.
ospfIntraArea	*integer*	Number of Ospf Intra-area routes.
ospfTotal	*integer*	Total number of Ospf routes.

2.820.1.4 ospfv3Totals

ospfv3External1	*integer*	Number of Ospfv3 External-1 routes.
ospfv3External2	*integer*	Number of Ospfv3 External-2 routes.
ospfv3InterArea	*integer*	Number of Ospfv3 Inter-area routes.
ospfv3IntraArea	*integer*	Number of Ospfv3 Intra-area routes.
ospfv3NssaExternal1	*integer*	Number of Ospfv3 NSSA External-1 routes.
ospfv3NssaExternal2	*integer*	Number of Ospfv3 NSSA External-2 routes.
ospfv3Total	*integer*	Total number of Ospfv3 routes.

2.820.2 ServiceRoutingProtoModelStatus

configuredProtoModel	*enum: ribd | multi-agent*	Configured service routing protocols model.
operatingProtoModel	*enum: ribd | multi-agent*	Active service routing protocols model.

2.821 show ip route vrf all summary brief [...]

see 2.820.1

2.822 show ip security applied-profile [...]

ipsecAppliedProfiles	*table(string) = IpsecAppliedProfile* see 2.822.1	A mapping between Ipsec profile name and profile applied to aninterface.

2.822.1 IpsecAppliedProfile

appliedIntf	*list of Interface name*	Tunnel interface List for this profile.
appliedPath **	*list of string*	Path list for this profile. **Since: 4.22.1
ipsecConnectionDetails	*table(string) = IpsecConnectionDetail* see 2.822.1.1	A mapping between Ipsec profile info and corresponding connection.

2.822.1.1 IpsecConnectionDetail

[assignedVtepIp] **	*IP address*	Assigned Peer IP address from peer pool. **Since: 4.36.0
connectionName	*string*	Name of the IPsec connection.
dstAddr	*IP address*	Destination IP Address.
pathDict **	*table(string) = string*	Ipsec path dict. **Since: 4.22.1
[peerPool] **	*string*	Peer address pool name. **Since: 4.36.0
[policyBasedVpnTunnel] **	*boolean*	This is a tunnel used for Policy Based VPN. **Since: 4.33.0
[policyConnectionState] **	*table(string) = string*	Dict of IPsec policy connection states. **Since: 4.33.1
[policyTunnelName] **	*string*	Tunnel name for Policy Based VPN connection. **Since: 4.33.0
srcAddr	*IP address*	Source IP Address.
[trafficSelectorDstPrefix] **	*IP address prefix*	Traffic selector destination prefix. **Since: 4.33.0
[trafficSelectorSrcPrefix] **	*IP address prefix*	Traffic selector source prefix. **Since: 4.33.0
tunnelDict **	*table(Interface name) = string*	Tunnel interface dict, with SA info. **Since: 4.20.5
tunnelNs	*string*	Tunnel namespace for this profile.

2.823 show ip security connection [...]

revision 2

connections	*table(string) = IpsecConnection* see 2.823.1	A mapping between tunnel name andIPsec tunnel.

2.823.1 IpsecConnection

[assignedVtepIp] **	*IP address*	Assigned Peer IP address from peer pool. **Since: 4.36.0
connName	*string*	Name of the IPsec connection.
daddr	*IP address*	Destination IP Address.
dynPathDict **	*table(string) = IpsecDynamicPathInfoM* see 2.823.1.1	A mapping of paths to dynamic IPsec info. **Since: 4.29.2
dynamicPath **	*boolean*	Identifies if peer is a dynamic path. **Since: 4.29.2
[inboundSA]	*SecurityAssociation* see 2.823.1.2	SA for an inbound Flow.
initiator **	*boolean*	This peer is an initiator. **Since: 4.29.2
ipsecInputDataBytes	*integer*	Ipsec Input Data in bytes.
ipsecInputDataPkts	*integer*	Ipsec Input Data in packets.
ipsecOutputDataBytes	*integer*	Ipsec Output Data in bytes.
ipsecOutputDataPkts	*integer*	Ipsec Output Data in packets.
[outboundSA]	*SecurityAssociation* see 2.823.1.2	SA for an outbound Flow.
[pathDict] **	*table(string) = string*	Path name for this connection. **Since: 4.22.1
[peerPool] **	*string*	Peer address pool name. **Since: 4.36.0
[policyBasedVpnTunnel] **	*boolean*	This is a tunnel used for Policy Based VPN. **Since: 4.33.0
[policyConnectionState] **	*table(string) = string*	Dict of IPsec policy connection states. **Since: 4.33.1
[policyTunnelName] **	*string*	Tunnel name for Policy Based VPN connection. **Since: 4.33.0
rekeyTime	*integer*	Seconds remaining until next rekey.
remoteIp **	*IP address*	Remote IP. **Since: 4.29.2
saddr	*IP address*	Source IP Address.
[srcIntf] **	*string*	Source interface matching source address. **Since: 4.33.2
[trafficSelectorDstPrefix] **	*IP address prefix*	Traffic selector destination prefix. **Since: 4.33.0
[trafficSelectorSrcPrefix] **	*IP address prefix*	Traffic selector source prefix. **Since: 4.33.0
[tunnelDict]	*table(Interface name) = string*	Tunnel interface List for this connection.

tunnelNs	*string*	Tunnel namespace for this profile.
upTimeStr	*string*	Ipsec connection uptime.
vrfName **	*string*	VRF name. **Since: 4.29.2

2.823.1.1 IpsecDynamicPathInfoM

dhCryptoInfo	*list of IpsecDynamicSpiInfoM* see 2.823.1.1.3	DH crypto entries.
dhStateInfo	*list of IpsecDynamicDhStateM* see 2.823.1.1.1	DH state entries.
lastEstablishedTime	*floating point number*	Time when session was last established.
lastKnownLocalRekeyCount	*integer*	Last rekey count.

pathState	*enum: dhInitiatorOutSaInstalled | dhInitiatorSimultaneous | saResponderNonce-ResponseSent | saInitiatorRekeyComplete | dhResponderOutSaInstalled | dhInitiatorInSaInstalled | dhInitiatorInSaPkts-Received | dhResponderRekeyInitiated | saResponderOutSaInstalled | dhTransientOutSaInstalled | dhResponderInSaInstalled | dhResponderSimultaneous | connected | initial | saInitiatorNonceResponse-Received | saResponderInSaPkts-Received | saResponderRekeyComplete | saInitiatorInSaInstalled | saResponderNonceRequest-Received | saInitiatorOutSaInstalled | established | saResponderInSaInstalled | invalid | saResponderSimultaneous | dhInitiatorPktsRx-Simultaneous | dhInitiatorRekeyInitiated | dhResponderRekey-Complete | dhInitiatorRekeyComplete | saInitiatorSimultaneous | saInitiatorNonceRequest-Sent | active | saInitiatorNonceRequest-Received*	Dynamic path state.
saCryptoInfo	*list of IpsecDynamicSpiInfoM* see 2.823.1.1.3	SA crypto entries.
saInfo	*list of IpsecDynamicSaInfoM* see 2.823.1.1.2	SA info entries.
saSmState	*enum: invalid | dhRekeyInProgress | simultaneous | notRekeying | initiator | responder*	Current SA state.
sessionPktsIn	*integer*	Session input packets.
sessionPktsOut	*integer*	Session output packets.

2.823.1.1.1 IpsecDynamicDhStateM

dhRekeyState	*enum: initiated* | *inSaInstalled* | *invalid* | *peerOutSaInstalled* | *notRekeying* | *inProgress*	Current DH rekey state.
dhSmState	*enum: invalid* | *dhRekeyInProgress* | *simultaneous* | *notRekeying* | *initiator* | *responder*	Current DH state machine state.
localRekey	*integer*	Local rekey count.
peerRekey	*integer*	Peer rekey count.

2.823.1.1.2 IpsecDynamicSaInfoM

addTime	*floating point number*	Time when the SA was programmed.
initiator	*boolean*	This peer is an initiator.
pairSpi	*integer*	Pair SPI.
peerNonceType	*enum: invalid* | *request* | *response* | *init*	Peer nonce type.
pkts	*integer*	Packets seen on this path.
saRekeyState	*enum: invalid* | *peerOutSaInstalled* | *created* | *initial* | *installed*	SA rekey state.
saType	*enum: oldOutSa* | *inOutSa* | *newDhInSa* | *newDhOutSa* | *newSaOutSa* | *unknownSa* | *inSa* | *outSa* | *newSaInSa* | *oldInSa*	SA type.
spi	*integer*	SPI value.

2.823.1.1.3 IpsecDynamicSpiInfoM

inSpi	*integer*	Inbound SPI value.
localRekey	*integer*	Local rekey count.
outSpi	*integer*	Outbound SPI value.
peerRekey	*integer*	Peer rekey count.

2.823.1.2 SecurityAssociation

connId **	*integer*	Connection Id of SA. **Since: 4.32.0
daddr	*IP address*	Dest IP Address.
family	*enum: unknownFamily* | *ipv4* | *ipv6*	v4 or v6 family.
lifetimeCfg	*LifetimeCfg* see 2.823.1.2.1	Lifetime interval config in bytes/time:.
lifetimeCurrent	*LifetimeCur* see 2.823.1.2.2	Lifetime interval current status in bytes/time:.

mode	*enum: beet | unknownMode | transport | inboundTrigger | tunnel | routeOptimization*	mode of SA (tunnel, transport, beet, pass etc).
packetsOutOfReplayWindow	*integer*	Number of packets outside Replay Window.
proto	*enum: ah | esp | unknownProto*	IP Transform Protocol (AH/ESP).
replayErrors	*integer*	Number of Replay Errors.
replayWindow	*integer*	Sequence number window for replay protection.
reqid	*integer*	Request Id for a given SA pair.
saddr	*IP address*	Source IP Address.
seq	*integer*	Sequence Number to help with replay protection.
spi	*integer*	Security Policy Index for ESP/AH.
statsIntegrityFailed	*integer*	Number of Integrity check failures for incoming packets.

2.823.1.2.1 LifetimeCfg

xfrmPolicyByteLimitExpiry	*integer*	Expiry of byte transfer limit.
xfrmPolicyByteLimitWarning	*integer*	Warning about impending expiry of byte transfer limit.
xfrmPolicyPacketLimitExpiry	*integer*	Expiry of packet transfer limit.
xfrmPolicyPacketLimit-Warning	*integer*	Warning about impending expiry of packet transfer limit.
xfrmPolicyTimeLimitExpiry	*integer*	Expiry of time limit (in secs).
xfrmPolicyTimeLimitWarning	*integer*	Warning about impending expiry of time limit (in secs).
xfrmPolicyUseTimeExpiry	*integer*	Expiry of use time.
xfrmPolicyUseTimeWarning	*integer*	Warning about impending expiry of use time.

2.823.1.2.2 LifetimeCur

bytesProcessed	*integer*	Number of bytes processed in tx & rx.
packetsProcessed	*integer*	Number of pkts processed in tx & rx.
policyAddTime	*integer*	Timestamp when the policy was added.
policyLastAccessTime	*integer*	Timestamp when policy was last accessed.

2.824 show ip security connection policy [...]

revision 2

see 2.823

2.825 show ip security daemon [...]

`strongSwanEnabled`	*boolean*	strongSwan enabled.
`strongSwanRunning`	*boolean*	strongSwan running.

2.826 show ip security daemon log [...]

`[daemonLog]`	*list of string*	Log in charon.log.

2.827 show ip security encryption status

`ikeIpsecKeyAlignment`	*boolean*	Enforcing IKE encryption key length to be greater or equal to IPsec encryption key.

2.828 show ip security fips status

revision 2

`ikeFipsEnabled`	*boolean*	Control plane FIPS enabled.
`platformFipsEnabled`	*boolean*	Data path FIPS enabled.

2.829 show ip security key controller local

`[keyController]`	*IpsecLocalKey* see 2.829.1	Configured IPsec Key Controller.

2.829.1 IpsecLocalKey

`dhGroup`	*enum: modp768* | *modp1024* | *ecp256* | *modp2048s256* | *modp6144* | *modp4096* | *ecp384* | *modp1536* | *ecp521* | *modp2048* | *unknownDhGroup* | *modp3072*	Diffie-Hellman (DH) group number.
`encryptAlgo`	*enum: aes256gcm128* | *nullesp* | *aes128gcm64* | *aes256* | *aes128gcm128* | *aes128* | *unknownEncr* | *des3* | *aes192*	Encryption Algorithm.
`firstDhKeyAddTime` **	*integer*	Seconds the initial DH key was created. **Since: 4.25.2
`firstKeyAddTime`	*floating point number*	Seconds the initial DH key was created.
`hashAlgo`	*enum: unknownIntegrity* | *sha256* | *sha384* | *md5* | *nonehash* | *sha1* | *nullhash* | *sha512*	Integrity Algorithm.

lastKeyUptime	*integer*	Seconds since the last key was created.
rekeyTime	*integer*	Seconds remaining until next rekey.

2.830 show ip security key controller peer [...]

peers	*table(IPv4 or IPv6 address) = IpsecPeer* see 2.830.1	A mapping between peer address and IPsec peer info of the key controller.

2.830.1 IpsecPeer

dhGroup	*integer*	Diffie-Hellman (DH) group number.
encryptAlgo	*enum: aes256gcm128 | nullesp | aes128gcm64 | aes256 | aes128gcm128 | aes128 | unknownEncr | des3 | aes192*	Encryption Algorithm.
hashAlgo	*enum: unknownIntegrity | sha256 | sha384 | md5 | nonehash | sha1 | nullhash | sha512*	INTEGRITY Algorithm.
initiator	*boolean*	The peer is the initiator.
lastKeyUptime	*integer*	Seconds since the last key material received.
peerIp	*IP address*	Peer IP Address.
peerStatus	*enum: dhLenMismatch | cryptoKeyGenerationErr | unknownPeerState | encryptAlgoMismatch | licenseDisabled | nonceLenMismatch | dhGroupMismatch | hashAlgoMismatch | peerUp*	Status of the IPsec key controller peer.
uptime	*floating point number*	Seconds since the peer came up.

2.831 show ip security policy [...]

ipsecPolicies	*table(string) = IpsecPolicy* see 2.831.1	A mapping between IPSEC policy name and an IPSEC policy.

2.831.1 IpsecPolicy

cryptoSuites **	*list of string*	Crypto suites used in IKE. **Since: 4.31.1
dhGroup	*enum: modp768 | modp1024 | ecp256 | modp2048s256 | modp6144 | modp4096 | ecp384 | modp1536 | ecp521 | modp2048 | modp3072*	Identifier for Diffie-Hellman (DH) group.
encryption	*enum: aes256gcm128 | nullesp | aes128gcm64 | aes256 | aes128gcm128 | aes128 | unknownEncr | des3 | aes192*	Encryption Algorithm used in IKE.
ikeLifetime	*integer*	Lifetime for the keying channel.
ikeLifetimeUnit **	*enum: hours | minutes*	Time unit for configuring lifetime for the keying channel. **Since: 4.33.0
integrity	*enum: unknownIntegrity | sha256 | sha384 | md5 | nonehash | sha1 | nullhash | sha512*	Hash algorithm to verify integrity mechanism.
ipsecAuth	*enum: pre_share | unknownAuth | pki*	Peer Authentication method.
rekey	*boolean*	Rekey Enabled.
version	*string*	Version of IKE Policy.

2.832 show ip security profile [...]

ipsecProfiles	*table(string) = IpsecProfile* see 2.832.1	A mapping between a IPSEC profile name and an IPSEC profile.

2.832.1 IpsecProfile

[pkiProfile] **	*string*	PKI Profile Information. **Since: 4.32.2
[pkiProfileStatus] **	*enum: valid | invalid | notPresent*	PKI Profile Status. **Since: 4.32.2
policyName	*string*	Unique identifier of IKE Policy.
[securityAssociation]	*string*	Transformset associated with profile.

2.833 show ip security security-association [...]

ipsecSecurityAssociations	*table(string) = IpsecSecurityAssociation* see 2.833.1	A mapping between a security association and it's information.

2.833.1 IpsecSecurityAssociation

byteLimit **	*integer*	Byte count limit for the SA. **Since: 4.22.0
cryptoSuites **	*list of string*	Crypto suites used in SA. **Since: 4.31.1
espAes	*enum: aes256gcm128 | nullesp | aes128gcm64 | aes256 | aes128gcm128 | aes128 | unknownEncr | des3 | aes192*	ESP Advanced Encryption Standard Algorithm.
espSha	*enum: unknownIntegrity | sha256 | sha384 | md5 | nonehash | sha1 | nullhash | sha512*	ESP Secure Hash Algorithm.
packetLimit **	*integer*	Packet count limit for the SA. **Since: 4.22.0
pfsGroup	*enum: modp768 | modp1024 | ecp256 | modp2048s256 | modp6144 | modp4096 | ecp384 | modp1536 | ecp521 | modp2048 | modp3072*	PFS Group to force a new DH key exchange.
replayWindowSize **	*integer*	Anti-Replay Window size to detect replay attack. **Since: 4.20.5
saLifetime	*integer*	Lifetime for the SA.
saLifetimeUnit **	*enum: hours | minutes*	Time unit for configuring lifetime for the SA. **Since: 4.33.0

2.834 show ip source binding static [...]

bindingEntries	*list of IpMacBindingEntry* see 2.834.1	List of valid IP-MAC bindings.

2.834.1 IpMacBindingEntry

entryType	*enum: static | dynamic*	Binding type.
interface	*interface name*	Interface name.
ipAddr	*IPv4 address*	IPv4 address.
leaseTime	*integer*	Lease time in seconds.
macAddr	*MAC address*	MAC address.
vlanId	*integer*	Vlan this binding applies to.

2.835 show ip user route [...]

revision 2

vrfs	*table(string) = IpRibRoutes* see 2.835.1	A mapping from VRF to the RIB routes it contains.

2.835.1 IpRibRoutes

routes	*table(string) = IpRibRoutePreference* see 2.835.1.1	A mapping from prefix to a collection of RIB routes.

2.835.1.1 IpRibRoutePreference

preference	*table(numeric string) = IpRibRouteByNexthop* see 2.835.1.1.1	A mapping from preference to a RIB route.

2.835.1.1.1 IpRibRouteByNexthop

nexthop	*list of IpRibRoute* see 2.835.1.1.1.1	A List of all nexthops.

2.835.1.1.1.1 IpRibRoute

[commandTag]	*string*	Associated command-tag name.
[dropNextHopName]	*string*	Nexthop name for drop route.
[nexthopGroupName]	*string*	Nexthop group name.
[nexthopGroupWeight]	*integer*	UCMP weight for the nexthop group.
[preference]	*integer*	Administrative distance; lower values have precedence.
routeType	*enum: forward | nexthopGroup | drop*	RIB route type.
source	*string*	Source user agent which created the route.
[tag]	*integer*	Route tag number.
vias	*list of IpRibRouteVia* see 2.807.1.1.3	List of vias.

2.836 show ip verify source

interfaceStates	*table(Interface name) = IpsgInterfaceOperational-State* see 2.836.1	A mapping from interfaces to IP source guardoperational states on these interfaces.

2.836.1 IpsgInterfaceOperationalState

operationalState	*enum: IP source guard enabled | IP source guard disabled | Error: hardware resource unavailable*	Operational state of IP source guard on an-interface.

2.837 show ip verify source detail

detailStates	*table(Interface name) = IpsgBindingDetailStateList* see 2.837.1	IP source binding entries and their state.

2.837.1 IpsgBindingDetailStateList

intfDetailList	*list of IpsgBindingDetailState* see 2.837.1.1	IP source binding entries and the states.

2.837.1.1 IpsgBindingDetailState

ipAddr	*IPv4 address*	IPv4 address.
macAddr	*MAC address*	MAC address.
state	*enum: Active | IP source guard disabled | Port-Channel down | Hardware resource unavailable*	Operational state of an IP source binding entry.
vlanId	*integer*	VLAN ID of an IP source binding entry.

2.838 show ip verify source vlan

vlanStates	*table(numeric string) = IpsgVlanOperationalState* see 2.838.1	A mapping from VLANs to IP source guard operationalstates on these VLANs.

2.838.1 IpsgVlanOperationalState

operationalState	*enum: IP source guard disabled | Error: hardware resource unavailable | Error: vlan classification failed*	Operational state of IP source guard on a VLAN.

2.839 show ip virtual-router [...]

revision 2

advertiseInterval	*integer*	Mac address advertisement interval.
virtualMacs	*list of VirtualRouterMacModel* see 2.839.4	Virtual MAC addresses configured.
virtualRouters	*list of VarpRouterBase* see 2.839.1	Virtual Routers configured.

2.839.1 VarpRouterBase

Could also be an instance of:
VarpRouterV4 2.839.2
VarpRouterV6 2.839.3

interface	*interface name*	Name of Interface.
interfaceStatus	*enum: adminDown* | *notApplicable* | *down* | *up* | *autoIsolated* | *adminIsolated* | *uninitDown*	Connection status of the interface.
protocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
[state]	*enum: stopped* | *active*	stopped – the virtual router is inactive, active – the virtual router is active.
vrfName	*string*	Name of VRF.

2.839.2 VarpRouterV4

interface	*interface name*	Name of Interface.
interfaceStatus	*enum: adminDown* | *notApplicable* | *down* | *up* | *autoIsolated* | *adminIsolated* | *uninitDown*	Connection status of the interface.
ipAddress	*IpAddrAndMask* see 2.302.1.2.2.9	Interface address.
protocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
[state]	*enum: stopped* | *active*	stopped – the virtual router is inactive, active – the virtual router is active.
virtualIps	*list of IpAddrAndMask* see 2.302.1.2.2.9	Virtual IPv4 addresses.
vrfName	*string*	Name of VRF.

2.839.3 VarpRouterV6

interface	*interface name*	Name of Interface.
interfaceStatus	*enum: adminDown* | *notApplicable* | *down* | *up* | *autoIsolated* | *adminIsolated* | *uninitDown*	Connection status of the interface.
ipv6Addresses	*list of Ip6AddrAndMask* see 2.302.1.2.2.8	Ipv6 interface addresses.
protocolStatus	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.
[state]	*enum: stopped* | *active*	stopped – the virtual router is inactive, active – the virtual router is active.
virtualIpv6	*list of IPv6 address*	Virtual Ipv6 addresses.
vrfName	*string*	Name of VRF.

2.839.4 VirtualRouterMacModel

Could also be an instance of:
VarpRouterMac 2.839.6
MlagPeerRouterMac 2.839.5

macAddress	*MAC address*	Virtual router MAC address.
macType	*enum: varp* | *mlag*	varp – VARP MAC address, mlag – Mlag peer router MAC address.

2.839.5 MlagPeerRouterMac

configured	*boolean*	True if the routing using Mlag peer MAC address is configured.
macAddress	*MAC address*	Virtual router MAC address.
macType	*enum: varp* | *mlag*	varp – VARP MAC address, mlag – Mlag peer router MAC address.

2.839.6 VarpRouterMac

macAddress	*MAC address*	Virtual router MAC address.
macType	*enum: varp* | *mlag*	varp – VARP MAC address, mlag – Mlag peer router MAC address.
[mask] **	*MAC address*	Virtual router MAC address mask. **Since: 4.21.0
subnetRoutes **	*boolean*	Virtual subnet routes enabled. **Since: 4.24.2

2.840 show ipv6 access-lists [...]

see 2.76.2

2.841 show ipv6 address virtual source-nat sourceNatAddr

`vrfs`	*table(string) = IPv6 address*	A mapping of VRF names to their source NAT IPv6 address.

2.842 show ipv6 bgp (IP | PREFIX) [...]

revision 3

see 2.20

2.843 show ipv6 bgp [...]

revision 3

see 2.20

2.844 show ipv6 bgp access-list AS_PATH_LIST_NAME [...]

revision 3

see 2.20

2.845 show ipv6 bgp field-set FSNAME [...]

revision 3

see 2.20

2.846 show ipv6 bgp large-community { LARGE_COMM_VALUE } detail exact [...]

revision 3

see 2.20

2.847 show ipv6 bgp peers [...]

revision 2

see 2.642

2.848 show ipv6 bgp peers update errors [...]

revision 2

see 2.643

2.849 show ipv6 bgp regex REGEX [...]

revision 3

see 2.20

2.850 show ipv6 bgp summary [...]

revision 3

see 2.51

2.851 show ipv6 dhcp relay installed routes [...]

`vrfs`	*table(string) = Dhcp6InstalledRoutesPerVrf* see 2.851.1	DHCP Relay prefixes keyed by VRF.

2.851.1 Dhcp6InstalledRoutesPerVrf

`routes`	*table(IPv4 or IPv6 address prefix) = Dhcp6InstalledRoute* see 2.851.1.1	DHCP Relay installed routes keyed by IPv6 prefix.

2.851.1.1 Dhcp6InstalledRoute

`clientIpAddress`	*IPv6 address*	DHCP client's IP address.
`expiryTime`	*floating point number*	Expiry time of prefix in UTC.
`interface`	*interface name*	DHCP client's interface.
`[source]` **	*string*	Source of prefix binding. **Since: 4.35.0

2.852 show ipv6 dhcp relay routes sync

`listening`	*boolean*	Local S4Sync server listening state.
`localAddr`	*IP address*	IP address used for local server.
`localPort`	*integer*	Port number used for local server.
`[noListenReason]`	*string*	Reason that local sync server is not listening.

remoteDevice	*table(IPv4 or IPv6 address) = Ip.Helper.DhcpRelay.Cli.RemoteNeighborSyncStatus* see 2.852.1	Remote sync device IP address, port number and sync status.
updateSent	*integer*	Number of prefix sync request sent.
vrf	*string*	VRF name.

2.852.1 Ip.Helper.DhcpRelay.Cli.RemoteNeighborSyncStatus

lastSyncComplete	*floating point number*	Last synchronization completion time.
remoteAddr	*IP address*	Remote neighbor IP address.
remotePort	*integer*	Remote neighbor port.
syncStatus	*string*	S4 sync status.
updateReceived	*integer*	Number of updates received from this neighbor.

2.853 show ipv6 dhcp snooping

enabled	*boolean*	DHCPv6 Snooping is enabled.
enabledVlans	*list of integer*	VLANs on which snooping is configured.
operational	*boolean*	DHCPv6 Snooping is operational.
operationalVlans	*list of integer*	VLANs on which snooping is operational.
remoteIdOption	*boolean*	Insertion of Option-37 is enabled.

2.854 show ipv6 dhcp snooping counters [...]

detail_ **	*boolean*	Counter values in detail. **Since: 4.25.2
enabled	*boolean*	DHCPv6 Snooping is enabled.
vlanCounters	*table(numeric string) = VlanCounters* see 2.652.1	Per-VLAN counter information.

2.855 show ipv6 dhcp snooping counters debug

[dhcpOpErrCounters]	*SnoopingRelayCounters* see 2.653.1	Dropped - Invalid Dhcp Optype.
[disabledErrCounters]	*SnoopingRelayCounters* see 2.653.1	Dropped - Snooping disabled.
enabled	*boolean*	DHCPv6 Snooping is enabled.
[forwardedCounters]	*SnoopingRelayCounters* see 2.653.1	Forwarded.
[infoOptErrCounters]	*SnoopingRelayCounters* see 2.653.1	Dropped - Invalid Info Option.
[parseErrCounters]	*SnoopingRelayCounters* see 2.653.1	Dropped - Parse error.
[receivedCounters]	*SnoopingRelayCounters* see 2.653.1	Recieved.

[remoteIdErrCounters]	*SnoopingRelayCounters* see 2.653.1	Dropped - Invalid Remote-ID Option.
[resetTime]	*floating point number*	Last time counters were reset.
[vlanIdErrCounters]	*SnoopingRelayCounters* see 2.653.1	Dropped - Invalid VlanId.

2.856 show ipv6 dhcp snooping hardware

enabled	*boolean*	DHCPv6 Snooping is enabled.
vlans	*list of integer*	VLANs on which snooping is enabled.
vlansPerSlice	*table(string) = VlanList* see 2.654.1	VLANs enabled per slice.

2.857 show ipv6 hardware ale routes [...]

see 2.667

2.858 show ipv6 hardware ale routes platform-api [...]

see 2.669

2.859 show ipv6 hardware ale routes vrf all [...]

see 2.670

2.860 show ipv6 hardware fib ecmp resilience [...]

see 2.672

2.861 show ipv6 hardware fib ecmp resilience summary [...]

see 2.673

2.862 show ipv6 hardware fib routes [...]

see 2.678

2.863 show ipv6 interface [...]

interfaces	*table(Interface name) = Ip6Status* see 2.863.1	Maps an interface name to its IPv6 status.

2.863.1 Ip6Status

acceptUnsolicitedNa **	*boolean*	Accept unsolicited neighbor advertisements to update neighbor cache as per RFC9131. **Since: 4.28.2
[addrSource] **	*enum: slaac | manual*	How the address is configured on the interface. **Since: 4.20.0
addresses	*list of IpAddress* see 2.571.1.5.1	Addresses configured on this interface.
autoConfigStatus	*enum: dhcp | stateless | stateful*	IPv6 address assignment option.
dadAttempts	*integer*	Number of DAD attempts.
[dadStatus]	*enum: unsupported | unavailable | strict | enabled | disabled*	Current status of Duplicate Address Detection.
[enhancedDad] **	*boolean*	RFC7527 enhanced duplicate address detection. **Since: 4.18.1
globalAddressesAreVirtual **	*boolean*	Whether configured addresses are physical or virtual. **Since: 4.24.2
[interfaceAddressBrief] **	*InterfaceAddressBrief* see 2.571.1.3	Network layer address for this interface. **Since: 4.24.2
interfaceStatus	*enum: inactive | connected | initializing | unknown | notapplicable | errdisabled | maint-down | adminIsolated | noSignal | uninitialized | no-resource | signal | admin | notconnect | disabled | autoIsolated*	Connection status of the interface.
[ipv4Routable0] **	*boolean*	Whether or not IPv4 routable 0.0.0.0/8is enabled. **Since: 4.29.2
[ipv4Routable240] **	*boolean*	Whether or not IPv4 routable 240.0.0.0/4is enabled. **Since: 4.24.2
lineProtocolStatus	*enum: lowerLayerDown | unknown | down | up | testing | notPresent | notApplicable | dormant*	Line protocol status.
[linkLocal]	*IpAddress* see 2.571.1.5.1	Link-local IPv6 address of this interface.
[lossOfConnectivityReason] **	*cfm*	Layer 3 interface connectivity status. **Since: 4.31.2

[maxMssEgress] **	*integer*	TCP MSS ceiling in bytes enforced on packets forwarded to the network. **Since: 4.21.3
[maxMssIngress] **	*integer*	TCP MSS ceiling in bytes enforced on packets arriving from the network. **Since: 4.21.3
mtu **	*integer*	MTU (bytes). **Since: 4.23.1
mtuConfigError **	*boolean*	Whether the MTU is less than 1280. **Since: 4.32.1
multicastGroupAddresses	*list of string*	Addresses of multicast groups joined.
name	*interface name*	Name of the interface.
[ndCacheExpiryTime] **	*integer*	Neighbor discovery cache expiry time (in seconds). **Since: 4.33.0
ndReachableTime	*integer*	Neighbor discovery reachable time (in milliseconds).
ndRetransmitInterval	*integer*	Neighbor discovery retransmit interval (in milliseconds).
[neighborDiscoverDetails]	*NeighborDiscoverDetails* see 2.863.1.1	Neighbor discovery Rds.
state	*enum: enabled* | *disabled* | *stalled*	Whether or not the interface is enabled, or stalled in case of a DAD failure on the link-local IP.
[urpf]	*enum: strictDefault* | *disable* | *strict* | *loose* | *looseNonDefault*	Unicast Reverse Path Forwarding mode on the interface.
[urpfV4V6Mismatch]	*boolean*	Whether V4 and V6 urpf conflict on the same interface.
[vrf]	*string*	Name of the VRF.

2.863.1.1 NeighborDiscoverDetails

ndAdvertisedReachableTime	*integer*	Neighbor discovery reachable time being advertised (in milliseconds).
ndRouterAdvInterval	*integer*	Interval in milliseconds between neighbor discovery route advertisements.
ndRouterAdvRetransmit-Interval	*integer*	Neighbor discovery retransmit interval for Router Advertisement (in millisecond).
ndRouterAdvSuppressed	*boolean*	Whether or not Neighbor Discovery Router Advertisement messages are enabled.
routerAdvHopLimit	*integer*	Current hop limit to use in Router Advertisements.
routerAdvLifetime	*integer*	Router lifetime in Router Advertisement messages.
routerPreference	*enum: High* | *Medium* | *Low*	Router preference to be used in Router Advertisements.

2.864 show ipv6 interface brief [...]

interfaces	*table(Interface name) = Ip6StatusBrief* see 2.864.1	Maps an interface name to its abbreviated IPv6 status.

2.864.1 Ip6StatusBrief

[addrSource]	*enum: slaac | manual*	How the address is configured on the interface.
addresses	*list of IpAddress* see 2.571.1.5.1	Addresses configured on this interface.
[interfaceAddressBrief] **	*InterfaceAddressBrief* see 2.571.1.3	Network layer address for this interface. **Since: 4.24.2
interfaceStatus	*enum: inactive | connected | initializing | unknown | notapplicable | errdisabled | maint-down | adminIsolated | noSignal | uninitialized | no-resource | signal | admin | notconnect | disabled | autoIsolated*	Connection status of the interface.
[ipv4Routable0] **	*boolean*	Whether or not IPv4 routable 0.0.0.0/8is enabled. **Since: 4.29.2
[ipv4Routable240] **	*boolean*	Whether or not IPv4 routable 240.0.0.0/4is enabled. **Since: 4.24.2
lineProtocolStatus	*enum: lowerLayerDown | unknown | down | up | testing | notPresent | notApplicable | dormant*	Line protocol status.
[linkLocal]	*IpAddress* see 2.571.1.5.1	Link-local IPv6 address of this interface.
mtu	*integer*	MTU (bytes).
name	*interface name*	Name of the interface.

2.865 show ipv6 nd proxy [...]

ndProxyInterfaces	*table(Interface name) = Arp.Cli.NdProxyPrefixInterface* see 2.865.1	A mapping of Interfaces to ND Proxy prefixes.

2.865.1 Arp.Cli.NdProxyPrefixInterface

ip6Configured	*boolean*	Interface has an IPv6 address configured.
ndProxyConnected	*boolean*	ND Proxy connected prefix is enabled.
[ndProxyConnectedInclude-Vxlan]	*boolean*	ND Proxy connected prefix including VXLAN is enabled.
ndProxyDad **	*boolean*	ND DAD Proxy is enabled. **Since: 4.31.2

ndProxyPrefixes	*list of Arp.Cli.IpAddress* see 2.865.1.1	Prefixes with ND Proxy enabled.

2.865.1.1 Arp.Cli.IpAddress

active	*boolean*	Whether the address is active.
address	*string*	IP address.
dadfailed	*boolean*	Whether DAD failed for this address.
leastpref **	*boolean*	Whether the address is deprecated (least preferred). **Since: 4.28.2
subnet	*string*	Subnet mask.

2.866 show ipv6 nd ra internal state [...]

revision 2

interfaces	*table(string) = Interface* see 2.866.1	A mapping of interface ID to interface information.
vrfs	*table(string) = VrfGlobalCounters* see 2.866.2	A mapping of VRF name to global counter information.

2.866.1 Interface

dnsServersLifetime	*integer*	DNS servers lifetime (seconds).
dnsSuffixesLifetime	*integer*	DNS suffixes lifetime (seconds).
hopLimit	*integer*	Router advertisements hop limit value.
initialized	*boolean*	Interface SM is initialized.
intfIndex	*integer*	Interface index.
lastRaTime	*floating point number*	Last router advertisement sent time (epoch).
lastRsRspSentTime	*floating point number*	Last router solicitation response time (epoch).
managedConfigFlag	*boolean*	Managed address configuration flag is set.
mtu	*integer*	Interface status MTU.
nextTimeout	*floating point number*	Next timeout (seconds).
nsRetransmitInterval	*integer*	Time between neighbor solicitation retransmissions.
numDnsServers	*integer*	Number of DNS servers.
numDnsSuffixes	*integer*	Number of DNS domain name suffixes.
numIpv6Addr	*integer*	Number of IPv6 interfaces.
numPktDroppedUnexpectedType	*integer*	Number of packets dropped due to unexpected type.
numPrefixToAdvertise	*integer*	Number of prefixes to advertise.
numPrefixToSuppress	*integer*	Number of prefixes to suppress.
numRaRcvd	*integer*	Number of route advertisements received.
numRaRcvdConsistent	*integer*	Number of consistent route advertisements received.
numRaRcvdInconsistent	*integer*	Number of inconsistent route advertisements received.
numRaSent	*integer*	Number of route advertisements sent.
numRsDroppedInvalidHopLimit	*integer*	Number of router solicitation requests droppped as the hoplimit is less than 255.
numRsRcvd	*integer*	Number of router solicitation requests received.
numRsRspSent	*integer*	Number of router solicitation responses sent.
numRsSuppressed	*integer*	Number of router solicitation requests received with the response suppressed.
otherConfigFlag	*boolean*	Other stateful configuration flag is set.
raIntervalMaxMsec	*integer*	Router advertisements maximum interval (milliseconds).
raIntervalMinMsec	*integer*	Route advertisements minimum interval (milliseconds).

raLifetime	*integer*	Router lifetime value in router advertisements.
raMtuSuppress	*boolean*	Suppress IPv6 RA MTU option is set.
raNotSentIntfNotReady	*boolean*	No router advertisements sent on this interface.
raSuppress	*boolean*	Router advertisements are suppressed.
reachableTime	*integer*	The amount of time that a remote IPv6 node is considered reachable.
routerPreference	*integer*	Router preference type.
rsRspSuppress	*boolean*	Router solicitation responses are suppressed.
vrf	*string*	VRF name.

2.866.2 VrfGlobalCounters

ipv6UnicastRouting	*boolean*	IPv6 unicast routing is enabled.
[neighborRouterLifetime-Ignored]	*boolean*	RA neighbor router-lifetime ignored.
numCmsgDataErrors	*integer*	Number of Cmessage data errors.
numPktDroppedIntfStateNot-Found	*integer*	Number of packets dropped due to interface state not found.
numPktDroppedUnexpectedType	*integer*	Number of packets dropped due to unexpected type.
numRecvMsgErrors	*integer*	Number of received message errors.
numRsDroppedInvalidHopLimit	*integer*	Number of routes dropped due to invalid hop limit.

2.867 show ipv6 nd ra neighbors [...]

vrfs	*table(string) = InterfaceNeighbors* see 2.867.1	A mapping of VRF name to its neighbors.

2.867.1 InterfaceNeighbors

interfaces	*table(string) = RouterNeighbors* see 2.867.1.1	A mapping of interface to its neighbors.

2.867.1.1 RouterNeighbors

routerNeighbors	*list of RouterNeighbor* see 2.867.1.1.1	IPv6 link local address of neighbors discovered byRouter Advertisement.

2.867.1.1.1 RouterNeighbor

address	*IPv6 address*	IPv6 link local address of neighbor.
lastRa	*floating point number*	UTC time at which the last RA was received fromthe neighbor.

2.868 show ipv6 neighbor [...]

revision 2

dynamicEntries	*integer*	Number of dynamically learnt addresses in ARP table.
ipV6Neighbors	*list of IpV6Neighbor* see 2.868.1	IPv6 neighbors discovered by neighbor discovery.
notLearnedEntries	*integer*	Number of addresses in ARP table not due to learning.
staticEntries	*integer*	Number of statically configured addresses in ARP table.
totalEntries	*integer*	Total number of addresses in ARP table.

2.868.1 IpV6Neighbor

address	*string*	IPv6 address or hostname.
[age]	*integer*	How many minutes ago the neighbor entry was learned.
[extra]	*string*	Extra metadata about this neighbor's discovery.
hwAddress	*string*	Hardware (layer 2) address learnt for the corresponding network (layer 3) address.
interface	*string*	Interface name the neighbor was learned on.

2.869 show ipv6 ospf [...]

vrfs	*table(string) = InstList-Ospf3ShowInstModel* see 2.869.1	OSPFv3 instance information for all VRFs.

2.869.1 InstListOspf3ShowInstModel

instList	*table(numeric string) = Ospf3ShowInstModel* see 2.869.1.1	OSPF Instance list keyed by instance id.

2.869.1.1 Ospf3ShowInstModel

abrInstance	*boolean*	This OSPFv3 instance is an Area Border Router.
[adjacencyExchangeStart-Threshold]	*integer*	Adjacency exchange-start threshold.
[areaList]	*table(IPv4 address) = Ospf3ShowInstAreaModel* see 2.869.1.1.2	List of areas in this OSPFv3 instance.
asbrInstance	*boolean*	This OSPFv3 instance is an AS Border Router.
[ecmpMaximumNexthops]	*integer*	Maximum number of ECMP nexthops.
fipsStatus **	*boolean*	Indicates if FIPS mode is successfully enabled. **Since: 4.20.5
floodPacing **	*integer*	Flood packet pacing timer in msecs. **Since: 4.20.0
[gracefulRestartInfo] **	*OspfShowInstGraceful-RestartInfoModel* see 2.748.1.1.4	Graceful restart information. **Since: 4.18.0
[instanceId] **	*integer*	OSPFv3 instance ID. **Since: 4.17.0
[lsaInformation]	*Ospf3ShowInstLsaThrottle-TimersInfoModel* see 2.869.1.1.4	LSA information.
lsaLimitInformation **	*Ospf3ShowInstLsaLimit-InfoModel* see 2.869.1.1.3	LSA limit information. **Since: 4.26.2
[maxMetricTypeInformation]	*Ospf3ShowInstMaxMetric-TypeInfoModel* see 2.869.1.1.5	Max metric type information.
[maxMetricUnsetInformation]	*Ospf3ShowInstMaxMetric-UnsetInfoModel* see 2.869.1.1.6	Max metric unset information.
numAreas	*integer*	Number of areas.
numBackboneNeighbors **	*integer*	Number of backbone neighbors. **Since: 4.20.5
numNeighbors	*integer*	Number of neighbors.
numNormalAreas	*integer*	Number of normal areas.
numNssaAreas	*integer*	Number of nssa areas.
numStubAreas	*integer*	Number of stub areas.

[primaryDomainId] **	*string*	Primary domain identifier. **Since: 4.32.0
processId	*integer*	OSPFv3 process ID.
[referenceBandwidth] **	*integer*	Auto-cost reference bandwidth in Mbps. **Since: 4.15.3
[routerId]	*IPv4 address*	OSPFv3 Router id.
[secondaryDomainIds] **	*list of Ospf3SecondaryDomainId* see 2.869.1.1.1	List of secondary domain identifiers. **Since: 4.32.0
shutDown	*boolean*	Indicates if OSPFv3 instance is currently shut down.
[spfInformation]	*Ospf3ShowInstSpfThrottle-TimersInfoModel* see 2.869.1.1.7	SPF information.
[vrf]	*string*	VRF name.

2.869.1.1.1 Ospf3SecondaryDomainId

domainId	*string*	Secondary domain identifier.

2.869.1.1.2 Ospf3ShowInstAreaModel

[areaAuthTypeInformation]	*Ospf3AreaAuthInfoModel* see 2.869.1.1.2.1	Area authentication information.
[areaFilterPrefixList] **	*string*	Area Filter prefix-list. **Since: 4.26.2
areaFiltersConfigured **	*boolean*	Area summary filters configured. **Since: 4.26.0
areaId	*IPv4 address*	OSPFv3 area ID.
areaType	*enum: normalArea | stubArea | nssaArea*	Type of area(normal/stub/nssa).
nssaTransState	*boolean*	Nssa translate always flag for area.
numIntf	*integer*	Number of interfaces in the area.
rangeList	*table(IPv6 address) = Ospf3ShowInstAreaRange-Model* see 2.869.1.1.2.2	List of address ranges in this OSPFv3 area.
spfCount **	*integer*	Area SPF count. **Since: 4.20.5

2.869.1.1.2.1 Ospf3AreaAuthInfoModel

areaAuthConfig	*boolean*	area authenticationis enabled or not.
[authProtocol]	*enum: IPPROTO_AH | IPPROTO_ESP*	OSPFv3 area authentication protocol.
[hmacAlgorithm]	*enum: HMAC-MD5 | HMAC-SHA1*	HMAC algorithm being used.
[secParamIndex]	*integer*	IPsec Security paramater index.

2.869.1.1.2.2 Ospf3ShowInstAreaRangeModel

address	*IPv6 address*	Area range address.
cost	*integer*	Area range cost.
[doNotAdvertise] **	*boolean*	Do not advertise the area range. The cost value is invalid if this flag is set to true. **Since: 4.17.0
maskLen	*integer*	Area range mask length.

2.869.1.1.3 Ospf3ShowInstLsaLimitInfoModel

allowedIncidentCount	*integer*	LSA limit allowed incident count.
clearTimeout	*integer*	LSA limit clear timeout (mins).
currentIncidentCount	*integer*	LSA limit current incident count.
disabled	*boolean*	disabled due to LSA limit.
disabledTime	*integer*	LSA limit disabled time (mins).
[disabledTimeEnd]	*floating point number*	LSA limit disabled time end.
exceedAction	*string*	LSA limit exceed-action option.
lsaLimit	*integer*	Maximum number of LSAs allowed.
warningLimit	*integer*	LSA limit threshold for warning message.

2.869.1.1.4 Ospf3ShowInstLsaThrottleTimersInfoModel

lsaArrivalInterval	*integer*	LSA arrival interval in msecs.
lsaHoldInterval	*integer*	LSA hold interval in msecs.
lsaMaxWaitInterval	*integer*	LSA max wait interval in msecs.
lsaStartInterval	*integer*	LSA start interval in msecs.
numLsa **	*integer*	Number of LSAs. **Since: 4.20.0

2.869.1.1.5 Ospf3ShowInstMaxMetricTypeInfoModel

[maxMetricCfgDuration]	*integer*	Max metric config durationin secs.
maxMetricCondition	*boolean*	Originating router LSA with max metric, is configured or not.
[maxMetricExpiryTimestamp]	*integer*	UTC time stamp of expiry of max metricadvertisement.
[maxMetricExternal]	*integer*	Max metric for external LSA.
maxMetricState	*boolean*	Max metric advertisements being currently active or not.
[maxMetricStub]	*boolean*	Max metric including stubs.
[maxMetricSummary]	*integer*	Max metric for summary LSA.
maxMetricWaitBgp	*boolean*	Max metric while Bgp is converging.

2.869.1.1.6 Ospf3ShowInstMaxMetricUnsetInfoModel

[maxMetricUnsetOrigDuration]	*integer*	Max metric originate duration (secs).

[maxMetricUnsetReason]	*enum: UserConfig* | *TimerExpired* | *BgpTimerExpired* | *BgpConverged*	Max metric unset reason.
[maxMetricUnsetTimestamp]	*integer*	Max metric unset timestamp.

2.869.1.1.7 Ospf3ShowInstSpfThrottleTimersInfoModel

lastSpf	*integer*	Last SPF run (secs).
nextSpf	*integer*	Next SPF run (msecs).
spfCurrHoldInterval	*integer*	SPF current hold interval in msecs.
spfHoldInterval	*integer*	SPF hold interval in msecs.
spfMaxWaitInterval	*integer*	SPF max wait interval in msecs.
spfStartInterval	*integer*	SPF start interval in msec.

2.870 show ipv6 ospf access-list [...]

see 2.62

2.871 show ipv6 ospf border-routers [...]

vrfs	*table(string) = InstListOspf3Border-RoutersInstance* see 2.871.1	OSPFv3 border routers information for all VRFs.

2.871.1 InstListOspf3BorderRoutersInstance

instList	*table(numeric string) = Ospf3BorderRouters-Instance* see 2.871.1.1	OSPFv3 Instance list keyed by instance id.

2.871.1.1 Ospf3BorderRoutersInstance

ospf3BorderRouterEntries	*table(IPv4 address) = Ospf3BorderRoutersEntry* see 2.871.1.1.1	Dictionary of OSPFv3 border router entries indexed by area-id.
processId	*integer*	OSPFv3 process identifier.
vrf	*string*	VRF name.

2.871.1.1.1 Ospf3BorderRoutersEntry

borderRouters	*table(IPv4 address) = Ospf3BorderRoutersType* see 2.871.1.1.1.1	Dictionary of OSPFv3 border routers type indexed by router-id.

2.871.1.1.1.1 Ospf3BorderRoutersType

abr	*boolean*	Router is an area border router.
asbr	*boolean*	Router is an autonomous system boundary router.

2.872 show ipv6 ospf database [...]

vrfs	*table(string) = InstList-Ospf3DatabaseInstance* see 2.872.1	OSPFv3 database information for all VRFs.

2.872.1 InstListOspf3DatabaseInstance

instList	*table(numeric string) = Ospf3DatabaseInstance* see 2.872.1.1	OSPFv3 Instance list keyed by instance id.

2.872.1.1 Ospf3DatabaseInstance

ospf3AreaEntries	*table(IPv4 address) = Ospf3AreaModel* see 2.872.1.1.1	A mapping between an Area and its LSA list.
ospf3AsLsas	*list of Ospf3Lsa* see 2.872.1.1.1.1	List of LSAs with AS scope.
ospf3InterfaceEntries	*table(string) = Ospf3InterfaceModel* see 2.872.1.1.2	A mapping between an Interface and its LSA list.

2.872.1.1.1 Ospf3AreaModel

ospf3AreaLsaList	*list of Ospf3Lsa* see 2.872.1.1.1.1	List of LSAs for the area.

2.872.1.1.1.1 Ospf3Lsa

advertisingRouter	*IPv4 address*	LSA advertising router.
age	*integer*	LSA age in seconds.
checksum	*integer*	LSA checksum.
[exceptionFlag]	*enum: announcingMaximumCost* | *announcingMaximum-Metric*	Indicates maximum cost being advertised for self originated LSAs.
length	*integer*	LSA length.
linkStateId	*IPv4 address*	LSA link state id.
lsaType	*enum: graceLsa* | *linkLsa* | *intraAreaPrefixLsa* | *routerLsa* | *asExternalLsa* | *nssaLsa* | *interAreaPrefixLsa* | *interAreaRouterLsa* | *networkLsa*	LSA type.
[ospf3ExternalLsa]	*Ospf3ExternalLsa* see 2.872.1.1.1.2	AS external or NSSA LSA.
[ospf3InterAreaPrefixLsa]	*Ospf3InterAreaPrefixLsa* see 2.872.1.1.1.5	Inter area prefix LSA.
[ospf3InterAreaRouterLsa]	*Ospf3InterAreaRouterLsa* see 2.872.1.1.1.6	Intra area router LSA.

[ospf3IntraAreaPrefixLsa]	*Ospf3IntraAreaPrefixLsa* see 2.872.1.1.1.8	Intra area prefix LSA.
[ospf3LinkLsa]	*Ospf3LinkLsa* see 2.872.1.1.1.9	Link LSA.
[ospf3NetworkLsa]	*Ospf3NetworkLsa* see 2.872.1.1.1.10	Network LSA.
[ospf3RouterLsa]	*Ospf3RouterLsa* see 2.872.1.1.1.11	Router LSA.
sequenceNumber	*integer*	LSA sequence number.

2.872.1.1.1.2 Ospf3ExternalLsa

[externalRouteTag]	*integer*	External route tag.
[forwardingAddress]	*IP address*	Forwarding address if available.
metric	*integer*	Route cost.
metricType	*enum: type2 | type1*	External metric type (E bit) type1 : External metric Type 1 type2 : External metric Type 2.
prefix	*Ospf3LsaPrefix* see 2.872.1.1.1.3	Prefix adverstised in the LSA.

2.872.1.1.1.3 Ospf3LsaPrefix

[metric]	*integer*	Prefix cost.
prefix	*IP address*	Prefix advertised.
prefixLength	*integer*	Prefix length.
prefixOptions	*Ospf3LsaPrefixOptions* see 2.872.1.1.1.4	Prefix options.

2.872.1.1.1.4 Ospf3LsaPrefixOptions

doNotUseInRouteCalc **	*boolean*	A type 3,5 or 7 LSA is sent from a PE router to a CE router. **Since: 4.25.0
localAddressCapability	*boolean*	Prefix scope is IPv6 link local.
multicastCapability	*boolean*	Originating router supports multicast extensions to OSPFv3.
noUnicastCapability	*boolean*	Prefix excluded from IPv6 unicast calculations.
propagateNssaPrefix	*boolean*	Prefix propagated by NSSA area border routers.

2.872.1.1.1.5 Ospf3InterAreaPrefixLsa

metric	*integer*	Route cost.
prefix	*Ospf3LsaPrefix* see 2.872.1.1.1.3	Prefix advertised in the LSA.

2.872.1.1.1.6 Ospf3InterAreaRouterLsa

destinationRouterId	*IPv4 address*	Router id of the destination router.
metric	*integer*	Route cost.
options	*Ospf3IntfOptions* see 2.872.1.1.1.7	Optional capabilities supported by the destination router.

2.872.1.1.1.7 Ospf3IntfOptions

activeRouter	*boolean*	Originator is an Active-router.
[addressFamily] **	*boolean*	Router supports address families. **Since: 4.17.0
demandCircuit	*boolean*	Demand Circuit Handling.
ipv6	*boolean*	Include in IPV6 Route Calculations.
multicastForwarding	*boolean*	IP Multicast datagram forwarding.
nonStubArea	*boolean*	Attached to a non-stub area.
nssa	*boolean*	Attached to a Not-so-stubby-area.

2.872.1.1.1.8 Ospf3IntraAreaPrefixLsa

numPrefixes	*integer*	Number of prefixes in intra area prefix LSA.
prefixList	*list of Ospf3LsaPrefix* see 2.872.1.1.1.3	List of prefixes in intra area prefix LSA.
referencedAdvertisingRouter	*IPv4 address*	Referenced advertising router.
referencedLinkStateId	*IPv4 address*	Referenced link state id.
referencedLsaType	*enum: graceLsa* | *linkLsa* | *intraAreaPrefixLsa* | *routerLsa* | *asExternalLsa* | *nssaLsa* | *interAreaPrefixLsa* | *interAreaRouterLsa* | *networkLsa*	Referenced LSA type.

2.872.1.1.1.9 Ospf3LinkLsa

linkLocalAddress	*IP address*	Link local address of the originating router.
numPrefixes	*integer*	Number of prefixes in link LSA.
options	*Ospf3IntfOptions* see 2.872.1.1.1.7	Optional capabalities supported by the originating router.
prefixList	*list of Ospf3LsaPrefix* see 2.872.1.1.1.3	List of prefixes in link LSA.
priority	*integer*	Router priority of the originating router.

2.872.1.1.1.10 Ospf3NetworkLsa

attachedRouters	*list of IPv4 address*	List of routers attached to the link.
options	*Ospf3IntfOptions* see 2.872.1.1.1.7	Optional capabilities supported by the router.

2.872.1.1.1.11 Ospf3RouterLsa

options	*Ospf3RouterLsaOptions* see 2.872.1.1.1.13	Optional capabilities supported by the router.
routerLsaLinks	*list of Ospf3RouterLsaInterfaceEntry* see 2.872.1.1.1.12	List of router links.

2.872.1.1.1.12 Ospf3RouterLsaInterfaceEntry

interfaceId	*IPv4 address*	Local interface id.
interfaceType	*enum: transitNetwork | reserved | pointToPoint | virtualLink*	Router LSA interface type. pointToPoint : Point-to-Point connected interface transitNetwork : Connected to transit network reserved : Reserved virtualLink : Virtual link.
metric	*integer*	Interface cost.
neighborInterfaceId	*IPv4 address*	Interface id of the neighbor router.
neighborRouterId	*IPv4 address*	Router id of the neighbor router.

2.872.1.1.1.13 Ospf3RouterLsaOptions

areaBorderRouter	*boolean*	Area border router.
asBoundaryRouter	*boolean*	Autonomous system boundary router.
nssaTranslation	*boolean*	Translate NSSA LSAs to AS external LSAs.
virtualLinkEndpoint	*boolean*	Endpoint for virtual link(s) in the area.

2.872.1.1.2 Ospf3InterfaceModel

ospf3InterfaceLsaList	*list of Ospf3Lsa* see 2.872.1.1.1.1	List of LSAs for the interface.

2.873 show ipv6 ospf database database-summary [...]

vrfs	*table(string) = InstList-Ospf3DatabaseSummary* see 2.873.1	OSPFv3 database information for all VRFs.

2.873.1 InstListOspf3DatabaseSummary

instList	*table(numeric string) = Ospf3DatabaseSummary* see 2.873.1.1	OSPFv3 Instance list keyed by instance id.

2.873.1.1 Ospf3DatabaseSummary

areaId	*IP address*	Area identifier.
instanceId	*integer*	Instance ID.
numAsex	*integer*	Number of AS-external LSAs.

numGrace	*integer*	Number of Grace LSAs.
numInterPfx	*integer*	Number of Inter Area Prefix LSAs.
numInterRtr	*integer*	Number of Inter Area Router LSAs.
numIntraPfx	*integer*	Number of Intra-Area Prefix LSAs.
numLink	*integer*	Number of Link LSAs.
numNetwork	*integer*	Number of Network LSAs.
numNssa	*integer*	Number of type-7 NSSA LSAs.
numRouter	*integer*	Number of Router LSAs.
vrf	*string*	VRF name.

2.874 show ipv6 ospf interface [...]

vrfs	*table(string)* = *InstListOspf3Interface* see 2.874.1	OSPFv3 instance information for all VRFs.

2.874.1 InstListOspf3Interface

instList	*table(numeric string)* = *Ospf3Interface* see 2.874.1.1	OSPFv3 Instance list keyed by instance id.

2.874.1.1 Ospf3Interface

indices	*table(string)* = *Ospf3InterfaceEntry* see 2.874.1.1.1	Dictionary of OSPFv3 Interfaces indexed by the interface name.

2.874.1.1.1 Ospf3InterfaceEntry

area	*IPv4 address*	Area assigned to the interface.
[authentication]	*Ospf3IntfAuthInfo* see 2.874.1.1.1.1	Interface authentication details.
backupDesignatedRouter	*IPv4 address*	Backup designated router ID.
bfdState	*enum: enabled | disabled | default*	BFD configuration state.
cost	*integer*	Interface metric.
deadInterval	*integer*	Router dead interval in seconds.
designatedRouter	*IPv4 address*	Designated router ID.
helloInterval	*integer*	hello-interval in seconds.
interfaceAddress	*IP address*	Interface ipv6 link-local address.
interfaceType	*enum: broadcast | virtual | p2mp | p2p | nbma*	OSPFv3 interface type. broadcast - Broadcast interface. nbma - Non-Broadcast Multi-Access interface. virtual - Virtual interface. p2p - Point-to-point interface. p2mp - Point-to-multipoint interface.
[interfaceV4Address] **	*IPv4 address*	Interface ipv4 primary address. **Since: 4.18.0
[interfaceV4MaskLen] **	*integer*	Interface ipv4 primary address prefix len. **Since: 4.18.0
neighborCount	*integer*	Neighbor count.
options	*Ospf3IntfOptions* see 2.872.1.1.1.7	Interface optional capabilities.
passive **	*boolean*	Passive state. **Since: 4.18.0
priority	*integer*	Interface priority.
[remoteAddress] **	*IPv6 address*	Interface remote IPv6 address. **Since: 4.31.2
retransmitInterval	*integer*	Retransmit interval in seconds.

state	*enum: drOther | waiting | down | loopback | backupDr | dr | p2p*	OSPFv3 interface state. down - Initial interface state. loopback - Interface is looped back. waiting - Identity determination of designated routers underway. p2p - Interface connects to a point-to-point network or virtual link. dr - Router is the designated router on the attached network. backupDr - Router is the backup designated router on the network. drOther - Interface is neither DR or BDR, and connects to a DR or BDR.
transmitDelay	*integer*	Transmit delay in seconds.
vrf	*string*	VRF name.

2.874.1.1.1.1 Ospf3IntfAuthInfo

algorithm	*enum: HMAC-MD5 | HMAC-SHA1*	Authentication HMAC Algorithm.
protocol	*enum: AH | ESP*	IP Security Protocol. AH - Authentication Header ESP - Encapsulating Security Payload.
spi	*integer*	Security Parameter Index.

2.875 show ipv6 ospf lsa-log [...]

vrfs	*table(string) = InstListOspf3LsaLogInst* see 2.875.1	OSPFv3 lsa-log for the given VRF.

2.875.1 InstListOspf3LsaLogInst

instList	*table(numeric string) = Ospf3LsaLogInst* see 2.875.1.1	OSPFv3 Instance list keyed by instance id.

2.875.1.1 Ospf3LsaLogInst

ospf3LsaLogEntries	*list of Ospf3LsaLogEntry* see 2.875.1.1.1	List of LSA log entries.
[routerId]	*IPv4 address*	OSPFv3 router identifier.

2.875.1.1.1 Ospf3LsaLogEntry

advertisingRouter	*IPv4 address*	LSA advertising router.
linkStateId	*IPv4 address*	LSA link state identifier.
logTime	*floating point number*	LSA log generation time in seconds.
lsaEventType	*enum: backoffStarted | backedOff | backoffRestarted | discarded | outDelay*	LSA event types: backoffStarted - lsa backoff started backedOff - lsa backed off backoffRestarted - lsa backoff restarted outDelay - lsa delayed discarded - lsa discarded.

`lsaHoldInterval`	*integer*	LSA Hold interval in milliseconds.
`lsaType`	*enum: graceLsa* | *linkLsa* | *intraAreaPrefixLsa* | *routerLsa* | *asExternalLsa* | *nssaLsa* | *interAreaPrefixLsa* | *interAreaRouterLsa* | *networkLsa*	LSA type.
`sequenceNumber`	*integer*	LSA sequence number.

2.876 show ipv6 ospf neighbor [...]

vrfs	*table(string) = InstList-Ospf3NeighborsInstance* see 2.876.1	OSPFv3 neighbor instance information for all VRFs.

2.876.1 InstListOspf3NeighborsInstance

instList	*table(numeric string) = Ospf3NeighborsInstance* see 2.876.1.1	OSPFv3 Instance list keyed by instance id.

2.876.1.1 Ospf3NeighborsInstance

ospf3NeighborEntries	*list of Ospf3NeighborsEntry* see 2.876.1.1.1	List of OSPFv3 neighbor entries.

2.876.1.1.1 Ospf3NeighborsEntry

adjacencyState	*enum: full | loading | down | 2Ways | init | restart | attempt | exchange | exchStart*	OSPFv3 neighbor adjacency state. down - No hello received from neighbor attempt - Router attempting to establish connection init - Hello received but two-way communication not established 2-ways - Bi-directional communication established between two routers exch-start - Exchange of link state information between routers and their DR and BDR are started exchange - Routers exchanging database descriptor packets loading - Exchange of link state information occuring full - Routers are fully adjacent with each other restart - Neighbor is restarting.
areaId	*IPv4 address*	OSPFv3 neighbor area identifier.
backupDesignatedRouter	*IPv4 address*	OSPFv3 neighbor ID of backup designated router.
designatedRouter	*IPv4 address*	OSPFv3 neighbor ID of designated router.
[details]	*Ospf3NeighborDetails* see 2.876.1.1.1.1	OSPFv3 neighbor details.
inactivity	*floating point number*	Timestamp of OSPFv3 neighbor inactivity/dead timer.
interfaceName	*string*	OSPFv3 neighbor interface name.
options	*Ospf3NeighborOptions* see 2.876.1.1.1.2	OSPFv3 neighbor options.
priority	*integer*	OSPFv3 neighbor priority.
routerId	*string*	OSPFv3 neighbor router identifier.

2.876.1.1.1.1 Ospf3NeighborDetails

bfdRequestSent	*boolean*	OSPFv3 neighbor BFD request is sent.

bfdState	*enum: down | up | adminDown | init*	OSPFv3 neighbor BFD state. adminDown - Session taken down for administrative purposes init - Waiting for session establishment up - Session established successfully down - Session is down or has just been created.
[grExitReason] **	*enum: grExitHelperDisabled | grExitNetworkChanged | grExitGracePeriodExpired | grExitAdjNotFull | grExitGracefulRestartInProgress | grExitNone | grExitGraceLsaFlushed*	OSPFv3 neighbor graceful restart exit reason. **Since: 4.18.0
[grHelperTimer] **	*floating point number*	Timestamp of OSPFv3 neighbor graceful period expiration. **Since: 4.18.0
[grLastRestartTime] **	*floating point number*	Timestamp of the OSPFv3 neighbor last graceful restart time. **Since: 4.18.0
grNumAttempts **	*integer*	OSPFv3 neighbor graceful restart attempts. **Since: 4.18.0
stateTime **	*floating point number*	OSPFv3 neighbor current state time. **Since: 4.30.1

2.876.1.1.1.2 Ospf3NeighborOptions

activeRouter	*boolean*	Originating router is active or not.
[addressFamily] **	*boolean*	Router supports address families. **Since: 4.17.0
demandCircuitsSupport	*boolean*	Originating router supports OSPFv3 over Demand Circuits.
doNotUseInRouteCalc	*boolean*	A type 3,5 or 7 LSA is sent from a PE router to a CE router.
externalRoutingCapability	*boolean*	Originating router is capable of accepting AS External LSAs.
multicastCapability	*boolean*	Originating router supports multicast extensions to OSPFv3.
nssaCapability	*boolean*	Originating router supports Type-7 NSSA-External-LSAs.

2.877 show ipv6 ospf request-list [...]

vrfs	*table(string) = InstListOspf3LsaRequestList* see 2.877.1	OSPFv3 LSA request list information for all VRFs.

2.877.1 InstListOspf3LsaRequestList

instList	*table(numeric string) = Ospf3LsaRequestList* see 2.877.1.1	OSPF Instance list keyed by instance id.

2.877.1.1 Ospf3LsaRequestList

instanceId	*integer*	OSPFv3 instance identifier.
neighbors	*table(IPv4 address) = Ospf3LsaRequestInstance* see 2.877.1.1.1	Dictionary of request keyed by neighbor router ID.

2.877.1.1.1 Ospf3LsaRequestInstance

interfaceAddress	*IP address*	OSPFv3 neighbor interface address.
interfaceName	*string*	OSPFv3 neighbor interface name.
requestQueueLength	*integer*	LSA request queue length.
requests	*list of Ospf3LsaEntry* see 2.877.1.1.1.1	LSA request list.

2.877.1.1.1.1 Ospf3LsaEntry

advertisingRouter	*IPv4 address*	LSA advertising router.
age	*integer*	LSA age in seconds.
checksum	*integer*	LSA checksum.
linkStateId	*IPv4 address*	LSA link state identifier.
lsaType	*enum: graceLsa | linkLsa | intraAreaPrefixLsa | routerLsa | asExternalLsa | nssaLsa | interAreaPrefixLsa | interAreaRouterLsa | networkLsa*	LSA type.
sequenceNumber	*integer*	LSA sequence number.

2.878 show ipv6 ospf retransmission-list [...]

vrfs	*table(string) = InstListOspf3Lsa-RetransmissionList* see 2.878.1	OSPFv3 LSA retransmission information for all VRFs.

2.878.1 InstListOspf3LsaRetransmissionList

instList	*table(numeric string) = Ospf3LsaRetransmission-List* see 2.878.1.1	OSPF Instance list keyed by instance id.

2.878.1.1 Ospf3LsaRetransmissionList

neighbors	*table(IPv4 address) = Ospf3LsaRetransmission-Instance* see 2.878.1.1.1	Dictionary of retransmission list keyed by neighbor router ID.

2.878.1.1.1 Ospf3LsaRetransmissionInstance

interfaceAddress	*IP address*	OSPFv3 neighbor interface address.
interfaceName	*string*	OSPFv3 neighbor interface name.
nextRetransmissionTime	*floating point number*	Next retransmission time in UTC.
retransmissions	*list of Ospf3LsaEntry* see 2.877.1.1.1.1	LSA retransmission list.

2.879 show ipv6 ospf spf-log [...]

vrfs	*table(string) = InstListOspf3SpfLogInst* see 2.879.1	OSPFv3 spf-log for the given VRF.

2.879.1 InstListOspf3SpfLogInst

instList	*table(numeric string) = Ospf3SpfLogInst* see 2.879.1.1	OSPFv3 Instance list keyed by instance id.

2.879.1.1 Ospf3SpfLogInst

ospf3SpfLogEntries	*list of Ospf3SpfLogEntry* see 2.879.1.1.1	OSPFv3 SPF Log Entries.
[routerId]	*IPv4 address*	OSPFv3 router identifier.

2.879.1.1.1 Ospf3SpfLogEntry

spfDuration	*floating point number*	SPF duration in milliseconds.
spfScheduleReason	*string*	Reason for scheduling SPF.
spfStartTime	*floating point number*	SPF start time in UTC.

2.880 show ipv6 prefix-list NAME detail

see 2.803

2.881 show ipv6 prefix-list NAME summary

see 2.804

2.882 show ipv6 prefix-list [...]

see 2.803

2.883 show ipv6 route (PREFIX | ADDR) longer-prefixes [...]

revision 5

vrfs	*table(string) = Ip6Routes* see 2.883.1	Route info of each VRF.

2.883.1 Ip6Routes

allRoutesProgrammedHardware	*boolean*	True if every route is programmed in hardware.
allRoutesProgrammedKernel	*boolean*	True if every route is programmed in kernel.
defaultRouteState	*enum: notReachable | reachable | notSet*	The state of the default route.
routes	*table(string) = Ip6Route* see 2.883.1.1	List of ipv6 routes keyed by prefix.
routingDisabled	*boolean*	True if routing is disabled.

2.883.1.1 Ip6Route

[cbfVias]	*list of CbfVia* see 2.807.1.1.1	List of Class based forwarding vias.
directlyConnected	*boolean*	True if this route is directly connected though an interface, internal, or is a drop route.
hardwareProgrammed	*boolean*	True if this route is programmed in hardware.
kernelProgrammed	*boolean*	True if this route is programmed in the kernel.
[loopingRoute] **	*boolean*	True if this route is part of a recursive route resolution loop. **Since: 4.33.1
[metric]	*integer*	Used by routing protocol to determine whether one route should be chosen over another. Lower metrics have precedence.
[preference]	*integer*	Administrative distance; lower values have precedence.
routeAction	*enum: forward | drop*	What kind of route it is.
routeLeaked	*boolean*	True if this route is leaked from different VRF.
[routePriority] **	*enum: medium | high | low*	Route processing priority. **Since: 4.31.2
[routeSubtype] **	*enum: External2 | NssaExternal2 | InterArea | IntraArea | NssaExternal1 | External1*	OSPFv3 route type. **Since: 4.33.1

routeType	*enum: dropRoute | static | CBFLeaked | isisL1 | iBGP | ospfSummary | ospf | isisL2 | nexthopGroupStaticRoute | bgpAggregate | rip | connected | kernel | bgp | eBGP | gribi | dynamicPolicy | martian | dhcp | isis*	The ipv6 route type.
[srTePolicy]	*list of RouteSrTePolicy* see 2.807.1.1.1.2	SR-TE policy.
[srcVrf]	*string*	Name of the VRF route is leaked from.
vias	*list of IpRouteVia* see 2.807.1.1.2	List of vias.

2.884 show ipv6 route [...]

revision 5

see 2.883

2.885 show ipv6 route fec [...]

see 2.809

2.886 show ipv6 route fec summary [...]

see 2.811

2.887 show ipv6 route host [...]

revision 2

vrfs	*table(string) = Ip6RoutesHost* see 2.887.1	A mapping of VRF to its IPv6 host routes.

2.887.1 Ip6RoutesHost

allRoutesProgrammedHardware	*boolean*	Every route is programmed in hardware.
routes	*table(string) = Ip6RouteHost* see 2.887.1.1	IPv6 host routes keyed by prefix.
routingDisabled	*boolean*	Routing is disabled.

2.887.1.1 Ip6RouteHost

hardwareProgrammed	*boolean*	True if this route is programmed in hardware.
routeType	*enum: FIB | broadcast | receive | attached*	The ipv6 route host type.
vias	*list of IpRouteHostVia* see 2.887.1.1.1	List of host vias.

2.887.1.1.1 IpRouteHostVia

[interface]	*interface name*	Name of the interface.
[nexthopAddr]	*IP address*	Nexthop address of the via.
toCpu	*boolean*	True if route goes to cpu.

2.888 show ipv6 route kernel unprogrammed [...]

see 2.813

2.889 show ipv6 route multicast [...]

revision 3

routes	*table(IPv4 or IPv6 address prefix) = MulticastRibRoute* see 2.814.1	A mapping from IPv6 prefix to MulticastRibRoute.

2.890 show ipv6 route next-hop nexthop-group [...]

revision 5

see 2.883

2.891 show ipv6 route priority summary [...]

see 2.817

2.892 show ipv6 route rpf unicast [...]

[interfaces]	*table(Interface name) = Ip6UrpfInterface* see 2.892.1	Mapping of interface to the additional interface state details.
[prefix]	*IP address prefix*	Destination Prefix.
[viaDefaultRoute]	*boolean*	uRPF carried out via the default route.

2.892.1 Ip6UrpfInterface

`allowDefault`	*boolean*	Packets are permitted to come in on the default interface.
`[lookupVrf]` **	*string*	Name of uRPF lookup VRF. **Since: 4.28.2
`uRpfMode`	*enum: disable* | *loose* | *strictDefault* | *strict*	URPF mode state.

2.893 show ipv6 route static not-installed bfd [...]

see 2.819

2.894 show ipv6 route summary [...]

revision 3

protoModelStatus **	*ServiceRoutingProtoModelStatus* see 2.820.2	Active and configured protocol models. **Since: 4.23.0
vrfs	*table(string) = Ip6RouteSummaryForVrf* see 2.894.1	Route summary for each VRF.

2.894.1 Ip6RouteSummaryForVrf

aggregate	*integer*	Number of aggregate routes.
attached	*integer*	Number of attached routes.
bgpCounts6	*bgpTotals6* see 2.894.1.1	BGP route count breakdown.
connected	*integer*	Number of connected routes.
[dhcp]	*integer*	Number of dhcp routes.
dynamicPolicy **	*integer*	Number of dynamic policy routes. **Since: 4.21.0
[fibRouteCount] **	*integer*	Fib Route Count. **Since: 4.34.1
[fibRouteLimit] **	*integer*	Fib Route Limit. **Since: 4.34.1
[fibRouteLimitSuppressedCount] **	*integer*	FIB Suppressed Route Count. **Since: 4.34.1
gribi **	*integer*	Number of gRIBI routes. **Since: 4.30.2
internal	*integer*	Number of internal routes.
isisCounts6	*isisTotals6* see 2.894.1.2	IS-IS route count breakdown.
maskLen	*table(numeric string) = integer*	Counts for each mask length.
ospfCounts6	*ospfTotals6* see 2.894.1.3	OSPF route count breakdown.
static	*integer*	Number of static routes.
staticNexthopGroup	*integer*	Number of static nexthop-group routes.
staticNonPersistent	*integer*	Number of static routes configured using the SDK with persistent=False.
staticPersistent	*integer*	Number of static routes configured to persist.
totalRoutes	*integer*	Total number of routes.
[vcs]	*integer*	Number of vxlan-control-service routes.
[vrfCount]	*integer*	Total number of vrf instances.

2.894.1.1 bgpTotals6

bgpExternal	*integer*	Number of bgp External routes.
bgpInternal	*integer*	Number of bgp Internal routes.
bgpLocal **	*integer*	Number of bgp Other routes. **Since: 4.22.1

bgpTotal	*integer*	Total number of bgp routes.

2.894.1.2 isisTotals6

isisLevel1	*integer*	Number of isis Level-1 routes.
isisLevel2	*integer*	Number of isis Level-2 routes.
isisTotal	*integer*	Total number of isis routes.

2.894.1.3 ospfTotals6

nssaExternal1	*integer*	Number of NSSA External-1 routes.
nssaExternal2	*integer*	Number of NSSA External-2 routes.
ospfExternal1	*integer*	Number of ospf External-1 routes.
ospfExternal2	*integer*	Number of ospf External-2 routes.
ospfInterArea	*integer*	Number of ospf Inter-area routes.
ospfIntraArea	*integer*	Number of ospf Intra-area routes.
ospfTotal	*integer*	Total number of ospf routes.

2.895 show ipv6 route vrf all summary brief [...]

see 2.894.1

2.896 show ipv6 user route [...]

revision 2

see 2.835

2.897 show ipv6 virtual-router [...]

revision 2

see 2.839

2.898 show isis (area proxy) | (INSTANCE area proxy) | (area proxy vrf VRFNAME)

vrfs	*table(string) = Instances-IsisShowAreaProxyModel* see 2.898.1	Area proxy for all VRFs.

2.898.1 InstancesIsisShowAreaProxyModel

isisInstances	*table(string) = IsisShowAreaProxyModel* see 2.898.1.1	IS-IS Instance list keyed by instance name.

2.898.1.1 IsisShowAreaProxyModel

entry	*IsisShowAreaProxyEntry-Model* see 2.898.1.1.1	Show area proxy information.

2.898.1.1.1 IsisShowAreaProxyEntryModel

proxyHostname	*string*	Area proxy hostname.
proxySysId	*string*	Area proxy system identifier.
status	*string*	Area proxy status.

2.899 show isis (database (detail | traffic-engineering)) | (INSTANCE database (detail | traffic-engineering)) | (database (detail | traffic-engineering) vrf VRFNAME) [...]

vrfs	*table(string) = Instances-IsisLsdbDetailModel* see 2.899.1	IS-IS instance information for all VRFs.

2.899.1 InstancesIsisLsdbDetailModel

isisInstances	*table(string) = IsisLsdbDetailModel* see 2.899.1.1	IS-IS Instance list keyed by instance name.

2.899.1.1 IsisLsdbDetailModel

level	*table(numeric string) = LevelDetailModel* see 2.899.1.1.1	A mapping of isis level to LSDB.

2.899.1.1.1 LevelDetailModel

lsps	*table(string) = LspDetailModel* see 2.899.1.1.1.1	A mapping of systemId to LSP in LSDB.

2.899.1.1.1.1 LspDetailModel

[addrFamily]	*string*	Address Family.
[appSrlgInfos] **	*list of ApplicationSrlg* see 2.899.1.1.1.2	Application Specific Shared Risk Link Group information. **Since: 4.26.0
areaAddresses	*list of LspAreaAddress* see 2.899.1.1.1.8	List of Area Addresses.
[areaProxySubTlvs] **	*list of AreaProxySubTlv* see 2.899.1.1.1.5	Area proxy information. **Since: 4.24.2
[auth]	*LspAuthModel* see 2.899.1.1.1.9	Auth details for the LSP.
checksum	*integer*	Checksum value.
[dynFloodNodeId] **	*list of LspDynFloodNodeId* see 2.899.1.1.1.10	Dynamic Flooding Area Node IDs. **Since: 4.23.0
[dynFloodPath] **	*list of LspDynFloodPath* see 2.899.1.1.1.11	Dynamic Flooding Paths. **Since: 4.23.0
expiryTime	*floating point number*	UTC time for Future Expiry time of LSP.
[flags]	*LspFlags* see 2.899.1.1.1.12	IS-IS Lsp flags.
[hostname]	*LspHostname* see 2.899.1.1.1.13	IS-IS hostname.
hostnameConflict **	*boolean*	LSP originated by node with conflicting hostname. **Since: 4.32.1

[interfaceAddresses]	*list of InterfaceAddresses* see 2.899.1.1.1.7	List of Interface Addresses.
[intermediateSystemType]	*enum: L1 | L2 | none*	IS-type for LSP.
[ip6SrlgInfos] **	*list of TeIpv6Srlg* see 2.899.1.1.1.58	Traffic Engineering IPv6 Shared Risk Link Group information. **Since: 4.22.0
[lastRcvdTime] **	*floating point number*	Last received time of LSP in UTC. **Since: 4.33.2
length **	*integer*	LSP length. **Since: 4.27.1
[lspGenerationTime]	*floating point number*	Next LSP generation time in UTC.
[modifiedLifetime] **	*integer*	Modified remaining lifetime of an LSP (in seconds). **Since: 4.21.3
[multiTopologies]	*list of LspMtModel* see 2.899.1.1.1.14	Multi Topology details for the LSP.
[neighbors]	*list of LspNeighbors* see 2.899.1.1.1.15	List of LSP neighbors Details.
nodeUnreachable **	*boolean*	Flag for LSPs originated by Unreachable/Stale Nodes. **Since: 4.31.1
[purgeOriginator] **	*string*	Purge originator. **Since: 4.23.1
[purgeUpstreamNgb] **	*string*	Purge originator upstream neighbor. **Since: 4.23.1
[rcvdLifetime] **	*integer*	Received remaining lifetime of an LSP (in seconds). **Since: 4.21.3
[reachabilities]	*list of LspReachabilities* see 2.899.1.1.1.28	Reachabilities Information of LSP.
[refreshTime] **	*floating point number*	Future refresh time of LSP in UTC. **Since: 4.21.3
[routerCapabilities]	*list of RouterCapability* see 2.899.1.1.1.32	Router Capability Information.
sequence	*integer*	Sequence number for this LSP.
[srBindings]	*list of SrBindingModel* see 2.899.1.1.1.51	Segment Routing Binding Information.
[srlgInfos]	*list of TeSrlg* see 2.899.1.1.1.61	Traffic Engineering Shared Risk Link Group information.
[srv6Locators] **	*list of Srv6Locators* see 2.899.1.1.1.53	SRv6 Locators information of LSP. **Since: 4.29.0
[supportedInstTlvs] **	*list of SupportedInstTlv* see 2.899.1.1.1.57	Supported instance TLV information. **Since: 4.26.0
[teRouterID]	*TeRouterId* see 2.899.1.1.1.60	IS-IS TE Router-ID.
[unsupportedTlvs] **	*list of UnsupportedTlv* see 2.899.1.1.1.62	Unsupported IS-IS TLV Information. **Since: 4.22.0

2.899.1.1.1.2 ApplicationSrlg

applications	*ApplicationIdentifiers* see 2.899.1.1.1.3	Application identifiers.

[interfaceAddress]	*IP address*	Interface address.
[localLinkId]	*integer*	Local link identifier.
[neighborAddress]	*IP address*	Neighbor address.
ngbSystemId	*string*	System identifier of the neighbor.
[remoteLinkId]	*integer*	Remote link identifier.
srlgIds	*list of SrlgIds* see 2.899.1.1.1.4	List of Shared Risk Link Group IDs.
[v6InterfaceAddress]	*IPv6 address*	IPv6 interface address.
[v6NeighborAddress]	*IPv6 address*	IPv6 neighbor address.

2.899.1.1.1.3 ApplicationIdentifiers

[standardApps]	*list of string*	Standard applications.
[standardAppsUseLegacy]	*boolean*	Use legacy link attributes.
[userDefinedApps]	*list of string*	User defined applications.

2.899.1.1.1.4 SrlgIds

gid	*integer*	Shared Risk Link Group Identifier.

2.899.1.1.1.5 AreaProxySubTlv

[areaProxySystemId]	*string*	Area proxy system ID.
[flags]	*AreaSegmentFlags* see 2.899.1.1.1.6	Area segment flags.
[index]	*integer*	Area segment index/label.
[maskLength] **	*integer*	Area segment IP Prefix Mask Length. **Since: 4.25.1
[prefix] **	*IP address*	Area segment IP Prefix. **Since: 4.25.1

2.899.1.1.1.6 AreaSegmentFlags

areaSegAf	*boolean*	Area segment address family flag.
areaSegLocal	*boolean*	Area segment local flag.
areaSegValue	*boolean*	Area segment value flag.

2.899.1.1.1.7 InterfaceAddresses

[ipv4Address]	*IPv4 address*	IPv4 address.
[ipv6Address]	*IPv6 address*	IPv6 address.

2.899.1.1.1.8 LspAreaAddress

address	*string*	Area Address for lsp.

2.899.1.1.1.9 LspAuthModel

[authKeyId] **	*integer*	Authentication Key Id. **Since: 4.21.3
authLength	*integer*	Authentication Key Length.
authMode	*enum: MD5 | Text | SHA*	Authentication Mode.

2.899.1.1.1.10 LspDynFloodNodeId

endIndex	*integer*	End index of enclosed systems.
startIndex	*integer*	Start index of enclosed systems.

2.899.1.1.1.11 LspDynFloodPath

path	*string*	Path of node indices.

2.899.1.1.1.12 LspFlags

dbOverload	*boolean*	LSP Database Overload.
defaultAttached	*boolean*	Attached to other areas by the Default Metric.
delayAttached	*boolean*	Attached to other areas by the Delay Metric.
errorAttached	*boolean*	Attached to other areas by the Error Metric.
expenseAttached	*boolean*	Attached to other areas by the Expense Metric.
partitionSupport	*boolean*	Support to Partition Repair.

2.899.1.1.1.13 LspHostname

name	*string*	LSP Hostname.

2.899.1.1.1.14 LspMtModel

mtAttached	*boolean*	MultiTopology Attached Flag.
mtOverloaded	*boolean*	MultiTopology Overload Flag.
topologyId	*integer*	Topology Id.

2.899.1.1.1.15 LspNeighbors

TEInfo	*LinkTeInfo* see 2.899.1.1.1.16	TE Information for the Link.
adjInterfaceAddresses	*list of LspAdjInterfaceAddress* see 2.899.1.1.1.18	List of interface addresses.

adjLanSids	*list of LspAdjLanSid* see 2.899.1.1.1.19	List of LAN Adj SID.
adjNarrowMetricsEnabled	*boolean*	Neighbor narrow metric.
adjSids	*list of LspAdjSid* see 2.899.1.1.1.21	List of Adj SID.
adjTopoId	*integer*	Neighbor topology Id.
[applicationLinkAttributes] **	*list of LspApplicationLink-Attributes* see 2.899.1.1.1.22	List of application specific link attributes. **Since: 4.26.0
[ip6GlobalInterfaceAddress] **	*IPv6 address*	IPv6 global interface address. **Since: 4.22.0
[ip6NeighborAddress] **	*IPv6 address*	Neighbor IPv6 global address. **Since: 4.22.0
metric	*integer*	Link Metric.
neighborAddr	*IPv4 address*	Neighbor Interface address.
srv6EndXLanSids **	*list of LspSrv6EndXLanSid* see 2.899.1.1.1.23	List of SRv6 END.X Lan Sids. **Since: 4.35.2
srv6EndXSids **	*list of LspSrv6EndXSid* see 2.899.1.1.1.26	List of SRv6 END.X Sids. **Since: 4.35.2
systemId	*string*	IS-IS System Id.

2.899.1.1.1.16 LinkTeInfo

[administrativeGroup] **	*integer*	Administrative Group of the Link. **Since: 4.21.3
[administrativeGroups-Extended] **	*list of integer*	Extended Administrative Groups of the Link. **Since: 4.31.2
[averageDelay] **	*integer*	Average unidirectional link delay (us). **Since: 4.32.0
[delayVariation] **	*integer*	Unidirectional link delay variation (us). **Since: 4.32.0
[localLinkId] **	*integer*	Local link ID. **Since: 4.32.1
[maxDelay] **	*integer*	Max unidirectional link delay (us). **Since: 4.26.0
[maxLinkBw]	*integer*	Maximum bandwidth (bps) that can be used on Directed Link.
[maxReservableBw]	*integer*	Maximum bandwidth (bps) that can be reserved on Directed Link.
[maxReservablePriorityBw]	*TeReservablePriority-Bandwidth* see 2.899.1.1.1.17	Maximum bandwidth reservable for a priority.
[metric]	*integer*	TE Link cost (if configured on link).
[minDelay] **	*integer*	Min unidirectional link delay (us). **Since: 4.26.0
[minMaxDelayAnomalous] **	*boolean*	Anomalous min/max link delay. **Since: 4.26.0
[remoteLinkId] **	*integer*	Remote link ID. **Since: 4.32.1
[utilizedBw] **	*integer*	Utilized bandwidth (bps). **Since: 4.36.0

2.899.1.1.1.17 TeReservablePriorityBandwidth

priority0	*integer*	Reservable Bandwidth (bps) for priority level 0.
priority1	*integer*	Reservable Bandwidth (bps) for priority level 1.
priority2	*integer*	Reservable Bandwidth (bps) for priority level 2.
priority3	*integer*	Reservable Bandwidth (bps) for priority level 3.
priority4	*integer*	Reservable Bandwidth (bps) for priority level 4.
priority5	*integer*	Reservable Bandwidth (bps) for priority level 5.
priority6	*integer*	Reservable Bandwidth (bps) for priority level 6.
priority7	*integer*	Reservable Bandwidth (bps) for priority level 7.

2.899.1.1.1.18 LspAdjInterfaceAddress

adjInterfaceAddress	*IPv4 address*	Interface Address.

2.899.1.1.1.19 LspAdjLanSid

adjLanFlags	*AdjFlags* see 2.899.1.1.1.20	Adjacency LAN Flags.
adjLanSid	*integer*	Adjacency LAN SID.
adjLanSystemId	*string*	Adjacency SystemId.
adjLanWeight	*integer*	Adjacency LAN Weight.

2.899.1.1.1.20 AdjFlags

adjAf	*boolean*	Sr Adj AddressFamily Flag.
adjBackup	*boolean*	Sr Adj Backup Flag.
adjLocal	*boolean*	Sr Adj Local Flag.
adjSet	*boolean*	Sr Adj Set Flag.
adjValue	*boolean*	Sr Adj Value Flag.

2.899.1.1.1.21 LspAdjSid

adjFlags	*AdjFlags* see 2.899.1.1.1.20	Adjacency Flags.
adjSid	*integer*	Adjacency SID.
adjWeight	*integer*	Adjacency Weight.

2.899.1.1.1.22 LspApplicationLinkAttributes

applications	*ApplicationIdentifiers* see 2.899.1.1.1.3	Application identifiers.
[linkAttributes]	*LinkTeInfo* see 2.899.1.1.1.16	TE link attributes.

2.899.1.1.1.23 LspSrv6EndXLanSid

endXAlgo	*integer*	EndX SID algorithm.
endXFlags	*EndXFlags* see 2.899.1.1.1.24	EndX SID flags.
endXFlavors	*Srv6SidFlavorFlags* see 2.20.1.1.2.36	EndX SID flavors.
[endXNgbSysId]	*string*	EndX SID LAN neighbor system ID.
endXSid	*IPv6 address*	EndX SID value.
[endXSidStructure]	*Srv6EndXLanSidStructure* see 2.899.1.1.1.25	SID Structure.
endXWeight	*integer*	EndX SID weight.

2.899.1.1.1.24 EndXFlags

endXBackup	*boolean*	Backup flag.
endXPersistent	*boolean*	Persistent flag.
endXSet	*boolean*	Set flag.

2.899.1.1.1.25 Srv6EndXLanSidStructure

argumentLength	*integer*	Argument length in bits.
blockLength	*integer*	Block length in bits.
functionLength	*integer*	Function length in bits.
nodeLength	*integer*	Node length in bits.

2.899.1.1.1.26 LspSrv6EndXSid

endXAlgo	*integer*	EndX SID algorithm.
endXFlags	*EndXFlags* see 2.899.1.1.1.24	EndX SID flags.
endXFlavors	*Srv6SidFlavorFlags* see 2.20.1.1.2.36	EndX SID flavors.
[endXNgbSysId]	*string*	EndX SID LAN neighbor system ID.
endXSid	*IPv6 address*	EndX SID value.
[endXSidStructure]	*Srv6EndXSidStructure* see 2.899.1.1.1.27	SID Structure.
endXWeight	*integer*	EndX SID weight.

2.899.1.1.1.27 Srv6EndXSidStructure

argumentLength	*integer*	Argument length in bits.
blockLength	*integer*	Block length in bits.
functionLength	*integer*	Function length in bits.
nodeLength	*integer*	Node length in bits.

2.899.1.1.1.28 LspReachabilities

maskLength	*integer*	Mask Length.
metric	*integer*	Cost of the Adjacency.
metricType	*enum: External | Internal*	Metric Type.
reachabilityNarrowMetrics	*boolean*	Unsupported Reachability Narrow Metrics.
reachabilityTopoId	*integer*	Reachable Topology Id.
reachabilityUpDown	*boolean*	Reachability Status.
[reachabilityV4Addr]	*IPv4 address*	Reachability IPv4 address.
[reachabilityV6Addr]	*IPv6 address*	Reachability IPv6 address.
[routeTags] **	*list of RouteTag* see 2.899.1.1.1.29	List of Route Tags. **Since: 4.21.3
srPrefixReachabilities	*list of SrPrefixReachability* see 2.899.1.1.1.30	List of SR Prefix Reachability.

2.899.1.1.1.29 RouteTag

tag	*integer*	Administrative Tag for IP Prefix.

2.899.1.1.1.30 SrPrefixReachability

algo	*string*	SR Algo Used.
algoNum **	*integer*	SR Algorithm. **Since: 4.25.0
options	*SrPrefixOptions* see 2.899.1.1.1.31	SR Flags for Prefix options.
sid	*integer*	SR Prefix SID.

2.899.1.1.1.31 SrPrefixOptions

explicitNull	*boolean*	SR Explicit Null Flag.
local	*boolean*	Value/Index carried by the Prefix-SID has local significance.
noPenultimate	*boolean*	SR No Penultimate Hop Flag.
nodeSID	*boolean*	SR Node SID Flag.
readvert	*boolean*	SR readvertisement Flag.
value	*boolean*	Prefix-SID carries a value instead of an index.

2.899.1.1.1.32 RouterCapability

[areaLeader] **	*AreaLeaderModel* see 2.899.1.1.1.33	Area Leader. **Since: 4.23.0
[dynamicFlooding] **	*DynamicFloodingModel* see 2.899.1.1.1.34	Dynamic Flooding. **Since: 4.23.0
flags	*RouterCapabilityFlags* see 2.899.1.1.1.47	Router Capability Flags.
flexAlgoDefs **	*list of FlexAlgoDefModel* see 2.899.1.1.1.35	Flexible Algorithm Definitions. **Since: 4.26.0
[msd] **	*NodeMsdModel* see 2.899.1.1.1.46	Node maximum SID depth. **Since: 4.28.0
routerId	*string*	Router Id.
srAlgos	*list of SrAlgo* see 2.899.1.1.1.48	Algorithm used.
srCapabilities	*list of SrCapabilityModel* see 2.899.1.1.1.41	SR Capabilities.
[srlb] **	*SrlbModel* see 2.899.1.1.1.44	SR Local Block Information. **Since: 4.21.3
[srv6Capabilities] **	*Srv6CapabilityModel* see 2.899.1.1.1.49	SRv6 capabilities. **Since: 4.29.0

2.899.1.1.1.33 AreaLeaderModel

algo	*integer*	Area leader algorithm.
prio	*integer*	Area leader priority.

2.899.1.1.1.34 DynamicFloodingModel

enabled	*boolean*	Dynamic flooding enabled.

2.899.1.1.1.35 FlexAlgoDefModel

algorithm	*integer*	Algorithm identifier.
calcType	*enum: SPF | Undefined | SSPF*	Calculation type.
calcTypeValue	*integer*	Calculation type value.
excludeGroups	*list of FlexAlgoExcludeModel* see 2.899.1.1.1.36	Flexible Algorithm Exclude Admin Group.
excludeGroupsDecimal **	*list of integer*	Flexible Algorithm Exclude Admin Group. **Since: 4.31.2
excludeSrlgGroups	*list of FlexAlgoExcludeSrlgModel* see 2.899.1.1.1.37	Flexible Algorithm Exclude Shared Risk Link Group.
flags	*list of FlexAlgoFlagsModel* see 2.899.1.1.1.38	Flexible Algorithm Flags.
includeAllGroups	*list of FlexAlgoIncludeAllModel* see 2.899.1.1.1.39	Flexible Algorithm Include All Admin Group.

includeAllGroupsDecimal **	*list of integer*	Flexible Algorithm Include All Admin Group. **Since: 4.31.2
includeAnyGroups	*list of FlexAlgoIncludeAnyModel* see 2.899.1.1.1.40	Flexible Algorithm Include Any Admin Group.
includeAnyGroupsDecimal **	*list of integer*	Flexible Algorithm Include Any Admin Group. **Since: 4.31.2
metricType	*enum: TE Metric | IGP Metric | Min Unidirectional Delay Metric | Undefined*	Metric type.
metricTypeValue	*integer*	Metric type value.
prio	*integer*	Priority.

2.899.1.1.1.36 FlexAlgoExcludeModel

group	*string*	Administrative Groups.

2.899.1.1.1.37 FlexAlgoExcludeSrlgModel

group	*integer*	Shared Risk Link Group.

2.899.1.1.1.38 FlexAlgoFlagsModel

flags	*string*	Flags.

2.899.1.1.1.39 FlexAlgoIncludeAllModel

group	*string*	Administrative Groups.

2.899.1.1.1.40 FlexAlgoIncludeAnyModel

group	*string*	Administrative Groups.

2.899.1.1.1.41 SrCapabilityModel

flags	*SrCapabilityFlags* see 2.899.1.1.1.42	SR Capability Flags.
srCapabilitySrgb	*list of SrCapabilitySrgb* see 2.899.1.1.1.43	Segment Routing Global Block Capability Info.

2.899.1.1.1.42 SrCapabilityFlags

mplsV4	*boolean*	Sr Capability mpls V4 Flag.
mplsV6	*boolean*	Sr capability mpls V6 Flag.

srcapV6	*boolean*	Sr Capability V6 Flag.

2.899.1.1.1.43 SrCapabilitySrgb

srgbBase	*integer*	Srgb base.
srgbRange	*integer*	Srgb range.

2.899.1.1.1.44 SrlbModel

srlbRanges	*list of SrlbRange* see 2.899.1.1.1.45	Ranges of labels making up SR Local Block.

2.899.1.1.1.45 SrlbRange

srlbBase	*integer*	Minimum label in range.
srlbRange	*integer*	Length of label range.

2.899.1.1.1.46 NodeMsdModel

[baseMplsImposition]	*integer*	Base MPLS imposition.

2.899.1.1.1.47 RouterCapabilityFlags

rtrCapD	*boolean*	Router Capability D Flag.
rtrCapS	*boolean*	Router Capability S Flag.

2.899.1.1.1.48 SrAlgo

algoNum **	*integer*	SR Algorithm. **Since: 4.25.0
srAlgo	*string*	SR Algo Used.

2.899.1.1.1.49 Srv6CapabilityModel

flags	*Srv6CapabilityFlags* see 2.899.1.1.1.50	SRv6 Capability flags.

2.899.1.1.1.50 Srv6CapabilityFlags

oamSupport	*boolean*	SRv6 OAM capability flag.

2.899.1.1.1.51 SrBindingModel

flags	*SrBindingFlags* see 2.899.1.1.1.52	SR Binding Flags.
label	*integer*	SR Binding Label.

maskLength	*integer*	SR Binding Mask Length.
prefix	*IP address*	SR Binding Ip Prefix.
rangeValue	*integer*	SR Binding Range.
srBindingTopologyId	*integer*	Sr Binding Topology Id.
srPrefixReachabilities	*list of SrPrefixReachability* see 2.899.1.1.1.30	List of SR Reachable Prefixes.
weight	*integer*	SR Binding Weight of the path.

2.899.1.1.1.52 SrBindingFlags

addrFamily	*boolean*	Sr Binding Address Family Flag.
attach	*boolean*	Sr Binding Attach Flags.
flood	*boolean*	Sr Binding flood Flag.
leak	*boolean*	Sr Binding leak Flag.
mirror	*boolean*	Sr Binding Mirror Flag.

2.899.1.1.1.53 Srv6Locators

algorithm	*integer*	Locator algorithm.
[endSids] **	*list of Srv6EndSid* see 2.899.1.1.1.54	End SID information. **Since: 4.30.0
flags	*Srv6LocatorFlags* see 2.899.1.1.1.56	Locator flags.
locatorPrefix	*IP address prefix*	Locator prefix.
locatorTopoId	*integer*	Locator Topology Id.
metric	*integer*	Cost of the Locator reachability.

2.899.1.1.1.54 Srv6EndSid

flavors	*Srv6SidFlavorFlags* see 2.20.1.1.2.36	SID flavors.
[sidStructure]	*Srv6SidStructure* see 2.899.1.1.1.55	SID structure.
sidValue	*IPv6 address*	End SID value.

2.899.1.1.1.55 Srv6SidStructure

argumentLength	*integer*	Argument length in bits.
blockLength	*integer*	Block length in bits.
functionLength	*integer*	Function length in bits.
nodeLength	*integer*	Node length in bits.

2.899.1.1.1.56 Srv6LocatorFlags

down	*boolean*	Up/Down bit.

2.899.1.1.1.57 SupportedInstTlv

instanceId	*integer*	IS-IS Instance Id.
supportedInstances	*list of integer*	List of supported instances.

2.899.1.1.1.58 TeIpv6Srlg

flags	*v6SrlgFlags* see 2.899.1.1.1.59	IPv6 SRLG flags.
ngbSystemId	*string*	System identifier of the neighbor.
srlgIds	*list of SrlgIds* see 2.899.1.1.1.4	List of Shared Risk Link Group IDs.
v6InterfaceAddress	*IPv6 address*	IPv6 interface address.
[v6NeighborAddress]	*IPv6 address*	IPv6 neighbor address.

2.899.1.1.1.59 v6SrlgFlags

neighborAddressIncluded	*boolean*	IPv6 neighbor address is included (NA bit).

2.899.1.1.1.60 TeRouterId

v4RouterId	*IPv4 address*	TE IPv4 Router-Id.
[v6RouterId] **	*IPv6 address*	TE IPv6 Router-Id. **Since: 4.21.3

2.899.1.1.1.61 TeSrlg

flags	*enum: Numbered | Unnumbered*	SRLG flags.
intfAddr	*IP address*	Interface address.
[localLinkId] **	*integer*	Local link identifier. **Since: 4.32.1
ngbAddr	*IP address*	Neighbor address.
ngbSystemId	*string*	System identifier of the neighbor.
[remoteLinkId] **	*integer*	Remote link identifier. **Since: 4.32.1
srlgIds	*list of SrlgIds* see 2.899.1.1.1.4	List of Shared Risk Link Group IDs.

2.899.1.1.1.62 UnsupportedTlv

tlvLength	*integer*	TLV length.
tlvType	*integer*	TLV type.

2.900 show isis (database detail tlv) | (INSTANCE database detail tlv) | (database detail tlv vrf VRFNAME) [...]

vrfs	*table(string) = Instances-IsisLsdbDetailTlvModel* see 2.900.1	IS-IS instance information for all VRFs.

2.900.1 InstancesIsisLsdbDetailTlvModel

isisInstances	*table(string) = IsisLsdbDetailTlvModel* see 2.900.1.1	IS-IS Instance list keyed by instance name.

2.900.1.1 IsisLsdbDetailTlvModel

level	*table(numeric string) = LevelDetailTlvModel* see 2.900.1.1.1	A mapping of isis level to LSDB.

2.900.1.1.1 LevelDetailTlvModel

lsps	*table(string) = LspDetailTlvModel* see 2.900.1.1.1.1	A mapping of systemId to LSP in LSDB.

2.900.1.1.1.1 LspDetailTlvModel

checksum	*integer*	Checksum value.
expiryTime	*floating point number*	UTC time for Future Expiry time of LSP.
[flags]	*LspFlags* see 2.899.1.1.1.12	IS-IS Lsp flags.
hostnameConflict	*boolean*	LSP originated by node with conflicting hostname.
[intermediateSystemType]	*enum: L1 | L2 | none*	IS-type for LSP.
[lastRcvdTime] **	*floating point number*	Last received time of LSP in UTC. **Since: 4.33.2
length	*integer*	LSP length.
[lspGenerationTime]	*floating point number*	Next LSP generation time in UTC.
[modifiedLifetime]	*integer*	Modified remaining lifetime of an LSP (in seconds).
nodeUnreachable	*boolean*	Flag for LSPs originated by Unreachable/Stale Nodes.
[rcvdLifetime]	*integer*	Received remaining lifetime of an LSP (in seconds).
[refreshTime]	*floating point number*	Future refresh time of LSP in UTC.
sequence	*integer*	Sequence number for this LSP.
[tlvList] **	*list of LspTlvListModel* see 2.900.1.1.1.2	A list of all TLVs with their type, length and value. **Since: 4.33.2

2.900.1.1.1.2 LspTlvListModel

tlvLength	*integer*	The length of TLV.
tlvType	*integer*	The type of TLV.
tlvValue	*TlvBaseModel* see 2.900.1.1.1.3	The value of TLV.

2.900.1.1.1.3 TlvBaseModel

Could also be an instance of:
AdministrativeTagSubTlv 2.900.1.1.1.4
AreaLeaderSubTlv 2.900.1.1.1.5
AreaProxyAreaSegmentSubTlv 2.900.1.1.1.6
AreaProxyModel 2.900.1.1.1.8
AreaProxySubTlvList 2.900.1.1.1.9
AreaProxySystemIdSubTlv 2.900.1.1.1.11
DynamicFloodNodeIdTlv 2.900.1.1.1.12
DynamicFloodPathTlv 2.900.1.1.1.13
DynamicFloodingSubTlv 2.900.1.1.1.14
FlexAlgoDefSubTlv 2.900.1.1.1.15
FlexAlgoExcludeGrpSubSubTlv 2.900.1.1.1.18
FlexAlgoExcludeSrlgSubSubTlv 2.900.1.1.1.19
FlexAlgoFlagsSubSubTlv 2.900.1.1.1.20
FlexAlgoIncludeAllGrpSubSubTlv 2.900.1.1.1.21
FlexAlgoIncludeAnyGrpSubSubTlv 2.900.1.1.1.22
InterfaceAddressesTlv 2.900.1.1.1.23
LspAdjIP6GlobalIntfAddrSubTlv 2.900.1.1.1.24
LspAdjIP6NgbAddrSubTlv 2.900.1.1.1.25
LspAdjInterfaceAddressSubTlv 2.900.1.1.1.26
LspAdjLanSidSubTlv 2.900.1.1.1.27
LspAdjNeighborAddrSubTlv 2.900.1.1.1.28
LspAdjSidSubTlv 2.900.1.1.1.29
LspAreaAddressTlv 2.900.1.1.1.30
LspAuthTlvModel 2.900.1.1.1.31
LspHostnameTlv 2.900.1.1.1.32
LspMtModelTlv 2.900.1.1.1.33
LspNeighborsTlv 2.900.1.1.1.34
LspProtocolsSupportedTlv 2.900.1.1.1.37
LspPurgeOriginatorTlv 2.900.1.1.1.38
LspReachabilitiesTlv 2.900.1.1.1.40
LspSrv6EndxSidSubTlv 2.900.1.1.1.43
LspSrv6LanEndxSidSubTlv 2.900.1.1.1.46
LspUnsupportedTlv 2.900.1.1.1.47
NodeMsdSubTlv 2.900.1.1.1.48
PrefixSegmentIdSubTlv 2.900.1.1.1.49
RouterCapabilityTlv 2.900.1.1.1.50
SrAlgoSubTlv 2.900.1.1.1.53
SrBindingTlv 2.900.1.1.1.54
SrCapabilitySrgbSubSubTlv 2.900.1.1.1.57
SrCapabilitySubTlv 2.900.1.1.1.58
SrlbRangeSubSubTlv 2.900.1.1.1.61
SrlbSubTlv 2.900.1.1.1.62
Srv6CapabilitySubTlv 2.900.1.1.1.65
Srv6EndSidSubTlv 2.900.1.1.1.66

Srv6LocatorsTlv 2.900.1.1.1.68
Srv6SidStructureSubSubTlv 2.900.1.1.1.71
SupportedInstanceIdentifierTlv 2.900.1.1.1.72

2.900.1.1.1.4 AdministrativeTagSubTlv

administrativeTags	*list of RouteTag* see 2.899.1.1.1.29	32-bit administrative tag sub-TLV list.

2.900.1.1.1.5 AreaLeaderSubTlv

areaLeader	*AreaLeaderModel* see 2.899.1.1.1.33	IS-IS area leader sub-TLV.

2.900.1.1.1.6 AreaProxyAreaSegmentSubTlv

areaSid	*AreaProxyAreaSegment-Model* see 2.900.1.1.1.7	Area segment identifier sub-TLV.

2.900.1.1.1.7 AreaProxyAreaSegmentModel

Could also be an instance of:
AreaProxySubTlv 2.899.1.1.1.5

[flags]	*AreaSegmentFlags* see 2.899.1.1.1.6	Area segment flags.
[index]	*integer*	Area segment index/label.
[maskLength]	*integer*	Area segment IP Prefix Mask Length.
[prefix]	*IP address*	Area segment IP Prefix.

2.900.1.1.1.8 AreaProxyModel

areaProxySubTlvs	*AreaProxySubTlvList* see 2.900.1.1.1.9	Area proxy TLV. It contains a list of all sub-TLVs with area proxy information.

2.900.1.1.1.9 AreaProxySubTlvList

tlvList	*list of AreaProxySubTlvListModel* see 2.900.1.1.1.10	List of all area proxy sub-TLVs.

2.900.1.1.1.10 AreaProxySubTlvListModel

tlvLength	*integer*	The length of TLV.
tlvType	*integer*	The type of TLV.
tlvValue	*TlvBaseModel* see 2.900.1.1.1.3	The value of TLV.

2.900.1.1.1.11 AreaProxySystemIdSubTlv

areaProxySystemId	*string*	Area proxy system ID sub-TLV.

2.900.1.1.1.12 DynamicFloodNodeIdTlv

dynamicFloodNodeId	*LspDynFloodNodeId* see 2.899.1.1.1.10	Dynamic flood node ID TLV.

2.900.1.1.1.13 DynamicFloodPathTlv

dynamicFloodPath	*LspDynFloodPath* see 2.899.1.1.1.11	Dynamic flood path TLV.

2.900.1.1.1.14 DynamicFloodingSubTlv

dynamicFlooding	*DynamicFloodingModel* see 2.899.1.1.1.34	IS-IS dynamic flooding sub-TLV.

2.900.1.1.1.15 FlexAlgoDefSubTlv

flexibleAlgorithmDefinition	*FlexAlgoDefSubTlvTlvList* see 2.900.1.1.1.16	Flexible algorithm definition sub-TLV.

2.900.1.1.1.16 FlexAlgoDefSubTlvTlvList

algorithm	*integer*	Algorithm identifier.
calcType	*enum: SPF | Undefined | SSPF*	Calculation type.
calcTypeValue	*integer*	Calculation type value.
metricType	*enum: TE Metric | IGP Metric | Min Unidirectional Delay Metric | Undefined*	Metric type.
metricTypeValue	*integer*	Metric type value.
prio	*integer*	Priority.
tlvList	*list of FlexAlgoDefSubTlvTlvListModel* see 2.900.1.1.1.17	List of all sub-sub-TLV of flexible algorithm definition sub-TLV.

2.900.1.1.1.17 FlexAlgoDefSubTlvTlvListModel

tlvLength	*integer*	The length of TLV.
tlvType	*integer*	The type of TLV.
tlvValue	*TlvBaseModel* see 2.900.1.1.1.3	The value of TLV.

2.900.1.1.1.18 FlexAlgoExcludeGrpSubSubTlv

excludeGroups	*list of FlexAlgoExcludeModel* see 2.899.1.1.1.36	Flexible Algorithm Exclude Admin Group sub-sub-TLV.
excludeGroupsDecimal	*list of integer*	Flexible Algorithm Exclude Admin Group.

2.900.1.1.1.19 FlexAlgoExcludeSrlgSubSubTlv

flexAlgoExcludeSrlg	*list of FlexAlgoExcludeSrlgModel* see 2.899.1.1.1.37	Flexible algorithm exlclude SRLG sub-sub-TLV.

2.900.1.1.1.20 FlexAlgoFlagsSubSubTlv

flexAlgoFlags	*FlexAlgoFlagsModel* see 2.899.1.1.1.38	Flexible Algorithm flags sub-sub-TLV.

2.900.1.1.1.21 FlexAlgoIncludeAllGrpSubSubTlv

includeAllGroups	*list of FlexAlgoIncludeAllModel* see 2.899.1.1.1.39	Flexible Algorithm Include all Admin Group sub-sub-TLV.
includeAllGroupsDecimal	*list of integer*	Flexible Algorithm Include all Admin Group.

2.900.1.1.1.22 FlexAlgoIncludeAnyGrpSubSubTlv

includeAnyGroups	*list of FlexAlgoIncludeAnyModel* see 2.899.1.1.1.40	Flexible Algorithm Include any Admin Group sub-sub-TLV.
includeAnyGroupsDecimal	*list of integer*	Flexible Algorithm Include any Admin Group.

2.900.1.1.1.23 InterfaceAddressesTlv

interfaceAddresses	*list of InterfaceAddresses* see 2.899.1.1.1.7	List of Interface Addresses.

2.900.1.1.1.24 LspAdjIP6GlobalIntfAddrSubTlv

ipv6InterfaceAddress	*IPv6 address*	Global ipv6 interface address sub-TLV.

2.900.1.1.1.25 LspAdjIP6NgbAddrSubTlv

ipv6NeighborAddress	*IPv6 address*	IPv6 neighbor address sub-TLV.

2.900.1.1.1.26 LspAdjInterfaceAddressSubTlv

ipv4InterfaceAddress	*LspAdjInterfaceAddress* see 2.899.1.1.1.18	IPv4 interface address sub-TLV.

2.900.1.1.1.27 LspAdjLanSidSubTlv

lanAdjacencySid	*LspAdjLanSid* see 2.899.1.1.1.19	LAN Adjacenecy Segment Identifier sub-TLV.

2.900.1.1.1.28 LspAdjNeighborAddrSubTlv

ipv4NeighborAddress	*IPv4 address*	IPv4 neighbor address sub-TLV.

2.900.1.1.1.29 LspAdjSidSubTlv

adjacencySid	*LspAdjSid* see 2.899.1.1.1.21	Adjacency Segment Identifier sub-TLV.

2.900.1.1.1.30 LspAreaAddressTlv

areaAddresses	*list of LspAreaAddress* see 2.899.1.1.1.8	List of area addresses.

2.900.1.1.1.31 LspAuthTlvModel

auth	*LspAuthModel* see 2.899.1.1.1.9	Authentication details for the LSP.

2.900.1.1.1.32 LspHostnameTlv

hostname	*LspHostname* see 2.899.1.1.1.13	IS-IS hostname.

2.900.1.1.1.33 LspMtModelTlv

multiTopologies	*list of LspMtModel* see 2.899.1.1.1.14	Multi Topology details for the LSP.

2.900.1.1.1.34 LspNeighborsTlv

neighbors	*list of LspNeighborsTlvList* see 2.900.1.1.1.35	List of LSP neighbors Details.

2.900.1.1.1.35 LspNeighborsTlvList

adjNarrowMetricsEnabled	*boolean*	Neighbor narrow metric.
adjTopoId	*integer*	Neighbor topology Id.
metric	*integer*	Link Metric.
systemId	*string*	IS-IS System Id.
tlvList	*list of LspNeighborsTlvListModel* see 2.900.1.1.1.36	A list of all neighbor sub-TLVs with their type, length and value.

2.900.1.1.1.36 LspNeighborsTlvListModel

tlvLength	*integer*	The length of TLV.
tlvType	*integer*	The type of TLV.
tlvValue	*TlvBaseModel* see 2.900.1.1.1.3	The value of TLV.

2.900.1.1.1.37 LspProtocolsSupportedTlv

protocolsSupported	*string*	Protocols supported TLV.

2.900.1.1.1.38 LspPurgeOriginatorTlv

purgeOriginator-Identification	*LspPurgeOriginator* see 2.900.1.1.1.39	Purge originator identificationTLV.

2.900.1.1.1.39 LspPurgeOriginator

purgeOriginator	*string*	Purge originator.
[purgeUpstreamNgb]	*string*	Purge originator upstream neighbor.

2.900.1.1.1.40 LspReachabilitiesTlv

reachabilities	*list of LspReachabilitiesTlvList* see 2.900.1.1.1.41	Reachabilities Information of LSP.

2.900.1.1.1.41 LspReachabilitiesTlvList

maskLength	*integer*	Mask Length.
metric	*integer*	Cost of the Adjacency.
metricType	*enum: External | Internal*	Metric Type.
reachabilityNarrowMetrics	*boolean*	Unsupported Reachability Narrow Metrics.
reachabilityTopoId	*integer*	Reachable Topology Id.
reachabilityUpDown	*boolean*	Reachability Status.
[reachabilityV4Addr]	*IPv4 address*	Reachability IPv4 address.
[reachabilityV6Addr]	*IPv6 address*	Reachability IPv6 address.
tlvList	*list of LspReachabilitiesTlv-ListModel* see 2.900.1.1.1.42	A list of all the sub-tlvs of reachability TLV.

2.900.1.1.1.42 LspReachabilitiesTlvListModel

tlvLength	*integer*	The length of TLV.
tlvType	*integer*	The type of TLV.
tlvValue	*TlvBaseModel* see 2.900.1.1.1.3	The value of TLV.

2.900.1.1.1.43 LspSrv6EndxSidSubTlv

srv6EndXSid	*LspSrv6EndXSidSubTlvList* see 2.900.1.1.1.44	SRv6 End.X SID sub-TLV.

2.900.1.1.1.44 LspSrv6EndXSidSubTlvList

endXAlgo	*integer*	EndX SID algorithm.
endXFlags	*EndXFlags* see 2.899.1.1.1.24	EndX SID flags.
endXFlavors	*Srv6SidFlavorFlags* see 2.20.1.1.2.36	EndX SID flavors.
[endXNgbSysId]	*string*	EndX SID LAN neighbor system ID.
endXSid	*IPv6 address*	EndX SID value.
endXWeight	*integer*	EndX SID weight.
tlvList	*list of Srv6EndSidSubTlvListModel* see 2.900.1.1.1.45	A list of all endx sub-sub-TLVs with their type, length and value.

2.900.1.1.1.45 Srv6EndSidSubTlvListModel

tlvLength	*integer*	The length of TLV.
tlvType	*integer*	The type of TLV.
tlvValue	*TlvBaseModel* see 2.900.1.1.1.3	The value of TLV.

2.900.1.1.1.46 LspSrv6LanEndxSidSubTlv

srv6LanEndXSid	*LspSrv6EndXSidSubTlvList* see 2.900.1.1.1.44	SRv6 LAN End.X SID sub-TLV.

2.900.1.1.1.47 LspUnsupportedTlv

unsupportedTlv	*string*	Value of the unsupported TLV in hex.

2.900.1.1.1.48 NodeMsdSubTlv

nodeMsd	*NodeMsdModel* see 2.899.1.1.1.46	Node MSD sub-TLV.

2.900.1.1.1.49 PrefixSegmentIdSubTlv

prefixSegmentIdentifier	*SrPrefixReachability* see 2.899.1.1.1.30	Prefix segment identifier sub-TLV.

2.900.1.1.1.50 RouterCapabilityTlv

routerCapability	*RouterCapabilityTlvList* see 2.900.1.1.1.51	Router capability TLV Information.

2.900.1.1.1.51 RouterCapabilityTlvList

flags	*RouterCapabilityFlags* see 2.899.1.1.1.47	Router Capability Flags.
routerId	*string*	Router Id.
tlvList	*list of RouterCapabilityTlvListModel* see 2.900.1.1.1.52	List of all sub-TLVs of router capability.

2.900.1.1.1.52 RouterCapabilityTlvListModel

tlvLength	*integer*	The length of TLV.
tlvType	*integer*	The type of TLV.
tlvValue	*TlvBaseModel* see 2.900.1.1.1.3	The value of TLV.

2.900.1.1.1.53 SrAlgoSubTlv

segmentRoutingAlgorithm	*list of SrAlgo* see 2.899.1.1.1.48	Segment routing algorithm sub-TLV.

2.900.1.1.1.54 SrBindingTlv

srBinding	*SrBindingTlvList* see 2.900.1.1.1.55	Segment routing binding TLV.

2.900.1.1.1.55 SrBindingTlvList

flags	*SrBindingFlags* see 2.899.1.1.1.52	SR Binding Flags.
label	*integer*	SR Binding Label.
maskLength	*integer*	SR Binding Mask Length.
prefix	*IP address*	SR Binding Ip Prefix.
rangeValue	*integer*	SR Binding Range.
srBindingTopologyId	*integer*	Sr Binding Topology Id.
tlvList	*list of SrBindingTlvListModel* see 2.900.1.1.1.56	List of all SR binding sub-TLVs.
weight	*integer*	SR Binding Weight of the path.

2.900.1.1.1.56 SrBindingTlvListModel

tlvLength	*integer*	The length of TLV.
tlvType	*integer*	The type of TLV.
tlvValue	*TlvBaseModel* see 2.900.1.1.1.3	The value of TLV.

2.900.1.1.1.57 SrCapabilitySrgbSubSubTlv

srCapabilitySrgb	*SrCapabilitySrgb* see 2.899.1.1.1.43	Segment Routing Global Block Capability sub-sub-TLV.

2.900.1.1.1.58 SrCapabilitySubTlv

srCapability	*SrCapabilitySubTlvTlvList* see 2.900.1.1.1.59	Segment routing capability sub-TLV.

2.900.1.1.1.59 SrCapabilitySubTlvTlvList

flags	*SrCapabilityFlags* see 2.899.1.1.1.42	SR Capability Flags.
tlvList	*list of SrCapabilitySubTlv-TlvListModel* see 2.900.1.1.1.60	List of all sub-sub-TLV of segment routing capability sub-TLV.

2.900.1.1.1.60 SrCapabilitySubTlvTlvListModel

tlvLength	*integer*	The length of TLV.
tlvType	*integer*	The type of TLV.
tlvValue	*TlvBaseModel* see 2.900.1.1.1.3	The value of TLV.

2.900.1.1.1.61 SrlbRangeSubSubTlv

srlbRanges	*SrlbRange* see 2.899.1.1.1.45	Segment Routing label/SID sub-sub-TLV.

2.900.1.1.1.62 SrlbSubTlv

segmentRoutingLocalBlock	*SrlbSubTlvTlvList* see 2.900.1.1.1.63	Segment routing local block sub-TLV.

2.900.1.1.1.63 SrlbSubTlvTlvList

tlvList	*list of SrlbSubTlvTlvListModel* see 2.900.1.1.1.64	List of all sub-sub-TLV of segment routing local block sub-TLV.

2.900.1.1.1.64 SrlbSubTlvTlvListModel

tlvLength	*integer*	The length of TLV.
tlvType	*integer*	The type of TLV.
tlvValue	*TlvBaseModel* see 2.900.1.1.1.3	The value of TLV.

2.900.1.1.1.65 Srv6CapabilitySubTlv

srv6Capability	*Srv6CapabilityModel* see 2.899.1.1.1.49	Srv6 Capability sub-TLV.

2.900.1.1.1.66 Srv6EndSidSubTlv

srv6EndSid	*Srv6EndSidSubTlvList* see 2.900.1.1.1.67	SRv6 end sid sub-TLV information.

2.900.1.1.1.67 Srv6EndSidSubTlvList

flavors	*Srv6SidFlavorFlags* see 2.20.1.1.2.36	SID flavors.
sidValue	*IPv6 address*	End SID value.
tlvList	*list of Srv6EndSidSubTlvListModel* see 2.900.1.1.1.45	A list of all the sub-TLVs of SRv6 end sid sub-TLV.

2.900.1.1.1.68 Srv6LocatorsTlv

srv6Locators	*list of Srv6LocatorsTlvList* see 2.900.1.1.1.69	SRv6 Locators information of LSP.

2.900.1.1.1.69 Srv6LocatorsTlvList

algorithm	*integer*	Locator algorithm.
flags	*Srv6LocatorFlags* see 2.899.1.1.1.56	Locator flags.
locatorPrefix	*IP address prefix*	Locator prefix.
locatorTopoId	*integer*	Locator Topology Id.
metric	*integer*	Cost of the Locator reachability.
tlvList	*list of Srv6LocatorTlvListModel* see 2.900.1.1.1.70	A list of all the sub-TLVs of SRv6Locator TLV.

2.900.1.1.1.70 Srv6LocatorTlvListModel

tlvLength	*integer*	The length of TLV.
tlvType	*integer*	The type of TLV.
tlvValue	*TlvBaseModel* see 2.900.1.1.1.3	The value of TLV.

2.900.1.1.1.71 Srv6SidStructureSubSubTlv

srv6SidStructure	*Srv6SidStructure* see 2.899.1.1.1.55	Sub-sub-TLV of SRv6Locator TLV.

2.900.1.1.1.72 SupportedInstanceIdentifierTlv

supportedInstanceIdentifier	*SupportedInstTlv* see 2.899.1.1.1.57	Supported instance identifier TLV.

2.901 show isis (dynamic flooding interfaces) | (INSTANCE dynamic flooding interfaces) | (dynamic flooding interfaces vrf VRFNAME) [...]

vrfs	*table(string) = InstancesIsisDynFloodInterfacesModel* see 2.901.1	Dynamic flooding interfaces for all VRFs.

2.901.1 InstancesIsisDynFloodInterfacesModel

isisInstances	*table(string) = IsisDynFloodInterfacesModel* see 2.901.1.1	IS-IS Instance list keyed by instance name.

2.901.1.1 IsisDynFloodInterfacesModel

levels	*table(numeric string) = IsisDynFloodInterfacesLevelModel* see 2.901.1.1.1	A dict of lists of IS-IS flooding interfaces keyed by level.

2.901.1.1.1 IsisDynFloodInterfacesLevelModel

interfaces	*list of IsisDynFloodInterfacesEntryModel* see 2.901.1.1.1.1	A list of IS-IS flooding paths.

2.901.1.1.1.1 IsisDynFloodInterfacesEntryModel

intf	*interface name*	Interface name.
tempIntf	*boolean*	Temporary interface addition to the flooding topology.

2.902 show isis (dynamic flooding nodes) | (INSTANCE dynamic flooding nodes) | (dynamic flooding nodes vrf VRFNAME) [...]

vrfs	*table(string) = InstancesIsisDynFloodNodeModel* see 2.902.1	Dynamic flooding nodes for all VRFs.

2.902.1 InstancesIsisDynFloodNodeModel

isisInstances	*table(string) = IsisDynFloodNodeModel* see 2.902.1.1	IS-IS Instance list keyed by instance name.

2.902.1.1 IsisDynFloodNodeModel

levels	*table(numeric string) = IsisDynFloodNodeLevelModel* see 2.902.1.1.1	A dict of IS-IS nodes keyed by level.

2.902.1.1.1 IsisDynFloodNodeLevelModel

nodes	*table(numeric string) = IsisDynFloodNodeEntryModel* see 2.902.1.1.1.1	A dict of IS-IS nodes keyed by index.

2.902.1.1.1.1 IsisDynFloodNodeEntryModel

nodeId	*string*	Node ID.

2.903 show isis (dynamic flooding paths) | (INSTANCE dynamic flooding paths) | (dynamic flooding paths vrf VRFNAME) [...]

vrfs	*table(string) = InstancesIsisDynFloodPathsModel* see 2.903.1	Dynamic flooding paths for all VRFs.

2.903.1 InstancesIsisDynFloodPathsModel

isisInstances	*table(string) = IsisDynFloodPathsModel* see 2.903.1.1	IS-IS Instance list keyed by instance name.

2.903.1.1 IsisDynFloodPathsModel

levels	*table(numeric string) = IsisDynFloodPathsLevelModel* see 2.903.1.1.1	A dict of lists of IS-IS paths keyed by level.

2.903.1.1.1 IsisDynFloodPathsLevelModel

paths	*list of IsisDynFloodPathsEntryModel* see 2.903.1.1.1.1	A list of IS-IS paths.

2.903.1.1.1.1 IsisDynFloodPathsEntryModel

path	*string*	Path.

2.904 show isis (dynamic flooding topology) | (INSTANCE dynamic flooding topology) | (dynamic flooding topology vrf VRFNAME) [...]

vrfs	*table(string) = InstancesIsisDynFloodTopologyModel* see 2.904.1	Dynamic flooding topology for all VRFs.

2.904.1 InstancesIsisDynFloodTopologyModel

isisInstances	*table(string) = IsisDynFloodTopologyModel* see 2.904.1.1	IS-IS Instance list keyed by instance name.

2.904.1.1 IsisDynFloodTopologyModel

levels	*table(numeric string) = IsisDynFloodTopologyLevelModel* see 2.904.1.1.1	A dict of lists of IS-IS flooding topology keyed by level.

2.904.1.1.1 IsisDynFloodTopologyLevelModel

topology	*list of IsisDynFloodTopologyPathModel* see 2.904.1.1.1.1	A list of IS-IS flooding paths.

2.904.1.1.1.1 IsisDynFloodTopologyPathModel

index	*integer*	Path index.
path	*list of IsisDynFloodTopologyEntryModel* see 2.904.1.1.1.2	A path in the flooding topology.

2.904.1.1.1.2 IsisDynFloodTopologyEntryModel

name	*string*	A node in a path in the flooding topology.

2.905 show isis (flex-algo) | (INSTANCE flex-algo) | (flex-algo vrf VRF-NAME) [...]

vrfs	*table(string) = InstancesIsisShowFlexAlgoModel* see 2.905.1	Flex-algo for all VRFs.

2.905.1 InstancesIsisShowFlexAlgoModel

isisInstances	*table(string) = IsisShowFlexAlgoModel* see 2.905.1.1	IS-IS Instance list keyed by instance name.

2.905.1.1 IsisShowFlexAlgoModel

details	*list of IsisShowFlexAlgoDetailEntryModel* see 2.905.1.1.1	Flex-algo algorithm details.
routers	*list of IsisShowFlexAlgoRouterModel* see 2.905.1.1.2	Flex-algo participating router.
summaries	*list of IsisShowFlexAlgoSummaryEntryModel* see 2.905.1.1.3	Flex-algo algorithm summaries.

2.905.1.1.1 IsisShowFlexAlgoDetailEntryModel

advertised	*boolean*	Definition advertised.
algorithm	*string*	Algorithm identifier.
alternates	*list of IsisShowFlexAlgoAlternate* see 2.905.1.1.1.1	Other definition advertisers.
color	*integer*	Color for resulting paths.
exclude	*string*	List of administrative groups a link must exclude.
excludeDecimal **	*list of integer*	List of administrative groups a link must exclude. **Since: 4.31.2
excludeSrlg	*string*	List of shared risk link groups that must be excluded.
includeAll	*string*	List of administrative groups a link must include.
includeAllDecimal **	*list of integer*	List of administrative groups a link must include. **Since: 4.31.2
includeAny	*string*	List of administrative groups a link may include.
includeAnyDecimal **	*list of integer*	List of administrative groups a link may include. **Since: 4.31.2
level	*string*	IS-IS Level.

metric	*enum: minDelay | igpMetric | te*	Metric type.
priority	*integer*	Priority of the definition.
system	*string*	System name.

2.905.1.1.1.1 IsisShowFlexAlgoAlternate

name	*string*	System name.

2.905.1.1.2 IsisShowFlexAlgoRouterModel

algorithm	*string*	Algorithm identifier.
level	*enum: L1 | L1L2 | L2*	IS-IS Level.
routers	*list of IsisShowFlexAlgoRouterEntry* see 2.905.1.1.2.1	Flex-algo algorithm router entry.

2.905.1.1.2.1 IsisShowFlexAlgoRouterEntry

advertising	*boolean*	Router advertising an algorithm definition for this algorithm.
[priority]	*integer*	Priority of the advertised algorithm.
router	*string*	Router name or system id.

2.905.1.1.3 IsisShowFlexAlgoSummaryEntryModel

advertised	*boolean*	Definition advertised.
algorithm	*string*	Algorithm identifier.
level	*string*	IS-IS Level.
metric	*enum: minDelay | igpMetric | te*	Metric type.
system	*string*	System name.

2.906 show isis (graceful-restart) | (INSTANCE graceful-restart) | (graceful-restart vrf VRFNAME)

vrfs	*table(string) = Instances-IsisGracefulRestartModel* see 2.906.1	Graceful Restart information for all VRFs.

2.906.1 InstancesIsisGracefulRestartModel

isisInstances	*table(string) = IsisGracefulRestartModel* see 2.906.1.1	IS-IS Instance list keyed by instance name.

2.906.1.1 IsisGracefulRestartModel

grNeighbors	*table(string) = IsisGracefulRestartNgb-EntryModel* see 2.906.1.1.1	A Dict of GracefulRestart Neighbors entries keyed by systemID.
[grState] **	*enum: expired | cancelled*	Graceful Restart State. **Since: 4.27.1
gracefulRestart	*enum: enabled | disabled*	Graceful Restart.
gracefulRestartHelper	*enum: enabled | disabled*	Graceful Restart Helper.
state	*enum: Start in progress | | Last Start exited after T2 (level-1) expiry | Last Restart exited after T2 (level-2) expiry | Last Start was completed successfully | Last Restart exited after T2 (level-1) expiry | Last Restart exited after T3 expiry | Graceful Restart disabled during startup | Restart in progress | Last Start exited after T2 (level-2) expiry | Last Restart was completed successfully*	Graceful Restart State.
systemId	*string*	SystemId.
t1Timer	*integer*	T1 timer - Time after which an unacknowledged start or restart attempt will be repeated (in seconds).
t2ConfigLevel1	*integer*	T2 timer - Maximum time to wait for LSP database synchronization for level-1 (in seconds).
t2ConfigLevel2	*integer*	T2 timer - Maximum time to wait for LSP database synchronization for level-2 (in seconds).
[t2L1Stopped] **	*floating point number*	T2 timer - time when Level-1 stopped. **Since: 4.27.1
[t2L2Stopped] **	*floating point number*	T2 timer - time when Level-2 stopped. **Since: 4.27.1

[t2Level1]	*integer*	Remaining T2 for level-1 (in seconds).
[t2Level2]	*integer*	Remaining T2 for level-2 (in seconds).
[t3Stopped] **	*floating point number*	T3 timer - time when stopped. **Since: 4.27.1
[t3Timer]	*integer*	T3 timer - Time after which the router will declare that it has failed to achieve database synchronization during restart (in seconds).

2.906.1.1.1 IsisGracefulRestartNgbEntryModel

adjacencies	*list of IsisGrNgbListModel* see 2.906.1.1.1.1	List of adjacency data for a neighbor.
[hostname]	*string*	Hostname of Neighbor.

2.906.1.1.1.1 IsisGrNgbListModel

gracefulRestartCapable	*boolean*	Graceful-Restart Capable.
interface	*interface name*	IS-IS interface name.
level	*enum: L1 | L1L2 | L2*	IS-IS level.
status	*enum: na | running | reStarting | starting*	Graceful-Restart State.

2.907 show isis (local-convergence-delay) | (INSTANCE local-convergence-delay) | (local-convergence-delay vrf VRFNAME) [...]

vrfs	*table(string) = InstancesIsisUloopModel* see 2.907.1	Micro-loop information for all VRFs.

2.907.1 InstancesIsisUloopModel

isisInstances	*table(string) = IsisUloopModel* see 2.907.1.1	IS-IS Instance list keyed by instance name.

2.907.1.1 IsisUloopModel

cfgDelayV4	*integer*	IPv4 local convergence delay.
cfgDelayV6	*integer*	IPv6 local convergence delay.
delayAbortsL1	*integer*	Number of failures at level-1.
delayAbortsL2	*integer*	Number of failures at level-2.
delayAttemptsL1	*integer*	Number of attempts at level-1.
delayAttemptsL2	*integer*	Number of attempts at level-2.
systemId	*string*	System ID.
uloopSms	*list of IsisUloopSmModel* see 2.907.1.1.1	List of Micro-loop SMs.

2.907.1.1.1 IsisUloopSmModel

adjacencyDownTimestamp **	*integer*	Link or BFD failure timestamp. **Since: 4.25.1
cause	*enum: linkDown | bfdDown*	Reason for Micro-loop prevention attempt.
delayTimeRemainingV4	*integer*	Delay time remaining for IPv4 routes.
delayTimeRemainingV6	*integer*	Delay time remaining for IPv6 routes.
delayTimerStartedV4	*integer*	Time delay timer started for IPv4 routes.
delayTimerStartedV6	*integer*	Time delay timer started for IPv6 routes.
delayTimerStoppedV4	*integer*	Time delay timer stopped for IPv4 routes.
delayTimerStoppedV6	*integer*	Time delay timer stopped for IPv6 routes.
delayV4	*integer*	IPv4 local convergence delay in msecs.
delayV6	*integer*	IPv6 local convergence delay in msecs.
[delayedRoutesV4]	*list of IsisUloopDelayedV4-RouteModel* see 2.907.1.1.1.1	List of IPv4 routes delayed.
[delayedRoutesV6]	*list of IsisUloopDelayedV6-RouteModel* see 2.907.1.1.1.2	List of IPv6 routes delayed.
intfIndex	*integer*	Interface index.
intfName	*interface name*	Protected interface.
lastAttempt	*boolean*	Last attempt.
level	*integer*	Level.
protectionV4	*enum: node | disabled | link*	TI-LFA protection mode for IPv4.
protectionV6	*enum: node | disabled | link*	TI-LFA protection mode for IPv6.

result	*enum: delaySucceeded | delayAbortedLinkDown | delayAbortedSpfNot-Scheduled | delayAbortedDelayRoutes-NewSpf | delayAbortedLinkUp | delayAbortedStateStarted | delayAbortedSpfScheduled | delayAbortedDelayRoutes | delayAbortedInvalidBackup | delayAbortedCleanup | delayPartiallySucceeded*	Result of Micro-loop prevention attempt.
routesDelayedV4	*integer*	Number of IPv4 routes delayed.
routesDelayedV6	*integer*	Number of IPv6 routes delayed.
state	*enum: delayStarted | delayRoutesNewSpf | delayNotRunnng | delayRoutes | delaySpfScheduled*	State of Micro-loop prevention attempt.

2.907.1.1.1.1 IsisUloopDelayedV4RouteModel

[algorithm] **	*string*	Algorithm identifier. **Since: 4.30.2
maskLength	*integer*	Mask Length.
[routeExportTime] **	*integer*	Time when route was updated. **Since: 4.34.0
v4DestAddr	*IPv4 address*	IPv4 destination address of delayed route.

2.907.1.1.1.2 IsisUloopDelayedV6RouteModel

[algorithm] **	*string*	Algorithm identifier. **Since: 4.30.2
maskLength	*integer*	Mask Length.
[routeExportTime] **	*integer*	Time when route was updated. **Since: 4.34.0
v6DestAddr	*IPv6 address*	IPv6 destination address of delayed route.

2.908 show isis (lsp log) | (INSTANCE lsp log) | (lsp log vrf VRFNAME)

vrfs	*table(string) = Instances-IsisLspLogTableModel* see 2.908.1	IS-IS instance information for all VRFs.

2.908.1 InstancesIsisLspLogTableModel

isisInstances	*table(string) = IsisLspLogTableModel* see 2.908.1.1	IS-IS Instance list keyed by instance name.

2.908.1.1 IsisLspLogTableModel

lspLogs	*list of IsisLspLogEntryModel* see 2.908.1.1.1	List of lsplog Entries.

2.908.1.1.1 IsisLspLogEntryModel

event	*enum: backoff restarted, hold value | backoff started, hold value | backoff continue, remaining wait time | out-delay applied, delayed by*	Event associated with Log.
holdInterval	*integer*	Hold interval for the LSP in ms.
logId	*integer*	Log entry identifier.
logTime	*integer*	Log time stamp.
lspId	*string*	IS-IS LSPID.
[lspIdHostname] **	*string*	Hostname of the LSP owner. **Since: 4.31.0
lspLevel	*integer*	Level of the LSP.

2.909 show isis (lsp purges) | (INSTANCE lsp purges) | (lsp purges vrf VRFNAME) [...]

revision 2

vrfs	*table(string) = Instances-IsisLspPurgesModel* see 2.909.1	IS-IS instance information for all VRFs.

2.909.1 InstancesIsisLspPurgesModel

isisInstances	*table(string) = IsisLspPurgesModel* see 2.909.1.1	IS-IS Instance list keyed by instance name.

2.909.1.1 IsisLspPurgesModel

levels	*table(numeric string) = IsisLevelLspPurgesModel* see 2.909.1.1.1	Dictionary of purges keyed by level.

2.909.1.1.1 IsisLevelLspPurgesModel

purgeLogs	*list of IsisLspPurgesEntryModel* see 2.909.1.1.1.1	List of IS-IS purge entries.

2.909.1.1.1.1 IsisLspPurgesEntryModel

logTime	*floating point number*	Log time stamp.
lspId	*string*	IS-IS LSPID of purge.
[lspIdHostname]	*string*	Hostname of the source node of LSP which was purged.
[originatorHostname]	*string*	Purge Originator or receiver Dynamic Hostname.
[originatorSystemId]	*string*	Purge Originator or receiver SystemID.
[reason]	*enum: systemIdChanged* | *differentChecksum* | *noContents* | *obsoleteProxyLsp* | *disResigned* | *userClearedLsp* | *receivedOldIncarnation* | *lspLifetimeExpired*	Reason for purge generation.
[upstreamNgbHostname]	*string*	Neighbour Hostname who send purge.
[upstreamNgbSystemId]	*string*	Neighbour SystemID who send purge.

2.910 show isis (network topology) | (INSTANCE network topology) | (network topology vrf VRFNAME) [...]

vrfs	*table(string) = Instances-IsisTopologyModel* see 2.910.1	Topology information for all VRFs.

2.910.1 InstancesIsisTopologyModel

isisInstances	*table(string) = IsisTopologyModel* see 2.910.1.1	IS-IS Instance list keyed by instance name.

2.910.1.1 IsisTopologyModel

levels	*table(numeric string) = IsisTopologyEntryModel* see 2.910.1.1.1	A dict of isis Topology keyed by isis level.

2.910.1.1.1 IsisTopologyEntryModel

topologies	*table(string) = IsisTopologyNextHopModel* see 2.910.1.1.1.1	Dict of address-families keyed by topology-id.

2.910.1.1.1.1 IsisTopologyNextHopModel

nexthops	*table(string) = IsisTopologyNextHops-EntryModel* see 2.910.1.1.1.2	Dict of next-hops keyed by system-id.

2.910.1.1.1.2 IsisTopologyNextHopsEntryModel

[destinationHostname]	*string*	Hostname.
vias	*list of IsisTopologyEntryListModel* see 2.910.1.1.1.3	Isis nexthops list.

2.910.1.1.1.3 IsisTopologyEntryListModel

iaMetric **	*integer*	IS-IS inter-area metric value. **Since: 4.24.0
[igpShortcutTunnel] **	*TunnelInfo* see 2.193.1.4.1	IGP Shortcut tunnel. **Since: 4.25.1
interface	*interface name*	IS-IS interface name.
metric	*integer*	IS-IS metric value.
[nexthopHostname]	*string*	Hostname.
nexthopSystemId	*string*	Next Hop.
snpa	*string*	Subnetwork Point of Attachment of Neighbor.

2.911 show isis (segment-routing) | (INSTANCE segment-routing) | (segment-routing vrf VRFNAME)

revision 2

vrfs	*table(string) = InstancesSrSummaryModel* see 2.911.1	IS-IS instance information for all VRFs.

2.911.1 InstancesSrSummaryModel

isisInstances	*table(string) = SrSummaryModel* see 2.911.1.1	IS-IS Instance list keyed by instance name.

2.911.1.1 SrSummaryModel

adjSidAllocationMode	*enum: None | All | SrOnly*	Adj-SID allocation mode.
[adjSidPoolBase]	*integer*	Base of Adj-SID pool.
[adjSidPoolSize]	*integer*	Size of Adj-SID pool.
dataPlane	*enum: IPV6 | MPLS | None | BOTH*	Data-plane.
[hostname]	*string*	Hostname.
inspectProxyAttachedFlag	*boolean*	Inspect attached-flag for proxy-node segments.
mappingServer	*boolean*	Set if this is a Segment Routing Mapping Server (SRMS).
reachabilityAlgorithm	*enum: SPF | SSPF*	IS-IS Reachability Algorithm.
[routerId]	*IPv4 address*	Router ID.
selfOriginatedSegment-Statistics	*SelfOriginatedSegment-StatisticsModel* see 2.766.1.1.1	Self-originated segment statistics.
srPeerCount	*integer*	Number of IS-IS SR capable peers.
srgbs	*list of SrGlobalBlockModel* see 2.911.1.1.1	SRGBs.
systemId	*string*	System ID.

2.911.1.1.1 SrGlobalBlockModel

Could also be an instance of:
OspfGlobalBlockModel 2.769.1.1.1
GlobalBlockModel 2.911.1.1.2

base	*integer*	SRGB base.
size	*integer*	SRGB size.

2.911.1.1.2 GlobalBlockModel

base	*integer*	SRGB base.
hasConflictingSrCapTlv **	*boolean*	Has conflicting SR Capability TLV. **Since: 4.34.2

[hostname]	*string*	Hostname.
isLocal	*boolean*	Is local srgb.
size	*integer*	SRGB size.
systemId	*string*	System ID.

2.912 show isis (segment-routing adjacency-segments) | (INSTANCE segment-routing adjacency-segments) | (segment-routing adjacency-segments vrf VRFNAME)

vrfs	*table(string) = InstancesAdjacency-SegmentSummaryModel* see 2.912.1	IS-IS instance information for all VRFs.

2.912.1 InstancesAdjacencySegmentSummaryModel

isisInstances	*table(string) = Adjacency-SegmentSummaryModel* see 2.912.1.1	IS-IS Instance list keyed by instance name.

2.912.1.1 AdjacencySegmentSummaryModel

adjSidAllocationMode	*enum: None | All | SrOnly*	Adj-SID allocation mode.
[adjSidPoolBase]	*integer*	Base of Adj-SID pool.
[adjSidPoolSize]	*integer*	Size of Adj-SID pool.
adjacencySegments	*list of AdjacencySegmentModel* see 2.912.1.1.1	List of locally originated Adjacency Segments.
dataPlane	*enum: IPV6 | MPLS | None | BOTH*	Data-plane.
[hostname] **	*string*	Hostname. **Since: 4.20.0
misconfiguredAdjacency-Segments **	*list of Misconfigured-AdjacencySegmentModel* see 2.912.1.1.2	List of misconfigured Adjacency Segments. **Since: 4.20.0
receivedGlobalAdjacency-Segments **	*list of ReceivedGlobal-AdjacencySegmentModel* see 2.912.1.1.3	List of received global Adjacency Segments. **Since: 4.21.0
[routerId]	*IPv4 address*	Router ID.
systemId	*string*	System ID.

2.912.1.1.1 AdjacencySegmentModel

flags **	*AdjacencySegmentFlags-Model* see 2.912.1.1.1.1	Flags. **Since: 4.20.5
ipAddress	*IP address*	IP Address of the adjacency.
lan	*boolean*	This is a LAN-SID.
level **	*integer*	Level. **Since: 4.20.5
localIntf	*interface name*	Local interface.
protection **	*enum: node | unprotected | link*	Protection mode of the local adj-SID. **Since: 4.22.1
sid	*integer*	Adjacency Segment assigned to this adjacency.

sidOrigin **	*enum: dynamic | configured*	Indicates if adj-SID is configured manually or assigned dynamically. **Since: 4.20.0
[srlgProtection] **	*enum: loose | strict*	TI-LFA SRLG protection mode of the segment. **Since: 4.24.1

2.912.1.1.1.1 AdjacencySegmentFlagsModel

b	*boolean*	Adj-SID is eligible for protection.
f	*boolean*	Adj-SID refers to an adjacency with outgoing IPv6 encapsulation.
l	*boolean*	Adj-SID has local significance.
s	*boolean*	Adj-SID refers to a set of adjacencies.
v	*boolean*	Adj-SID carries a value.

2.912.1.1.2 MisconfiguredAdjacencySegmentModel

af	*enum: ipv4 | ipv6*	Address Family.
localIntf	*interface name*	Local interface.
reason	*enum: out-of-range | interface-type-mismatch*	Reason why this configured adjacency segments is invalid.
sid	*integer*	Adjacency Segment assigned to this adjacency.

2.912.1.1.3 ReceivedGlobalAdjacencySegmentModel

flags	*AdjacencySegmentFlagsModel* see 2.912.1.1.1.1	Flags.
[hostname]	*string*	Hostname of the segment originator.
[ngbHostname]	*string*	IS-IS neighbor hostname of the segment originator.
ngbSystemId	*string*	IS-IS neighbor of the segment originator.
protection **	*enum: node | unprotected | link*	Protection mode of the global adj-SID. **Since: 4.22.1
sid	*integer*	Segment Id assigned to this adjacency segment.
srReachability **	*enum: srPartiallyReachable | srReachable | srUnreachable*	Reachability information for Adjacency Segments. **Since: 4.25.2
[srlgProtection] **	*enum: loose | strict*	TI-LFA SRLG protection mode of the segment. **Since: 4.24.1
systemId	*string*	System ID of the segment originator.

2.913 show isis (segment-routing global-blocks) | (INSTANCE segment-routing global-blocks) | (segment-routing global-blocks vrf VRF-NAME)

revision 2

vrfs	*table(string) = InstancesGlobalBlockSummaryModel* see 2.913.1	IS-IS instance information for all VRFs.

2.913.1 InstancesGlobalBlockSummaryModel

isisInstances	*table(string) = GlobalBlockSummaryModel* see 2.913.1.1	IS-IS Instance list keyed by instance name.

2.913.1.1 GlobalBlockSummaryModel

dataPlane	*enum: IPV6 | MPLS | None | BOTH*	Data-plane.
globalBlocks	*list of GlobalBlockModel* see 2.911.1.1.2	Global blocks.
[hostname]	*string*	Hostname.
[routerId]	*IPv4 address*	Router ID.
srPeerCount	*integer*	Number of IS-IS SR peers capable segments.
srgbs	*list of SrGlobalBlockModel* see 2.911.1.1.1	SRGBs.
systemId	*string*	System ID.

2.914 show isis (segment-routing prefix-segments) | (INSTANCE segment-routing prefix-segments) | (segment-routing prefix-segments vrf VRF-NAME) [...]

revision 2

vrfs	*table(string) = InstancesPrefixSegment-SummaryModel* see 2.914.1	IS-IS instance information for all VRFs.

2.914.1 InstancesPrefixSegmentSummaryModel

isisInstances	*table(string) = Prefix-SegmentSummaryModel* see 2.914.1.1	IS-IS Instance list keyed by instance name.

2.914.1.1 PrefixSegmentSummaryModel

dataPlane	*enum: IPV6 | MPLS | None | BOTH*	Data-plane.
[hostname]	*string*	Hostname.
[misconfiguredPrefix-Segments] **	*list of MisconfiguredPrefix-SegmentModel* see 2.914.1.1.1	Misconfigured prefix segments. **Since: 4.31.2
nodeSidCount	*integer*	Number of SR node segments.
prefixSegments	*list of PrefixSegmentModel* see 2.914.1.1.2	Prefix segments.
prefixSidCount	*integer*	Number of SR prefix segments.
proxyNodeSidCount	*integer*	Number of SR proxy node segments.
[routerId]	*IPv4 address*	Router ID.
systemId	*string*	System ID.

2.914.1.1.1 MisconfiguredPrefixSegmentModel

prefix	*IP address prefix*	Prefix address with netmask.
prefixRange **	*integer*	Range of addresses associated with Prefix-SIDs. **Since: 4.32.1
reason	*enum: outOfValidSrgbRange | conflictingWithAnother-LabelOrIndex*	Invalid reason.
segmentType	*enum: node | prefix | proxyNode*	Segment type.
sidValueType	*enum: label | index*	Segment id value type.
value	*integer*	Segment id value.

2.914.1.1.2 PrefixSegmentModel

[algorithm] **	*string*	Algorithm of the prefix segment. **Since: 4.26.2
flags	*PrefixSegmentFlagsModel* see 2.914.1.1.2.1	Flags.
[hostname]	*string*	Hostname.
[label] **	*integer*	Absolute Segment ID. **Since: 4.32.0
level	*integer*	Level.
prefix	*IP address prefix*	Prefix address with netmask.
protection	*enum: node* | *unprotected* | *link*	Protection mode of the prefix segment.
[proxyNodeFlags] **	*ProxyNodeSegmentFlagsModel* see 2.914.1.1.2.2	proxyNodeFlags. **Since: 4.30.2
segmentId	*integer*	Segment ID.
segmentType	*enum: Node* | *Proxy-Node* | *Prefix*	Type.
selfOriginatedPrefix	*boolean*	Prefix is self originated.
srReachability	*enum: srPartiallyReachable* | *srReachable* | *srUnreachable*	Reachability information for Prefix Segments.
[srlgProtection]	*enum: loose* | *strict*	TI-LFA SRLG protection mode of the segment.
[systemId]	*string*	System identifier.
[systemIds]	*list of string*	System IDs sharing anycast segment.

2.914.1.1.2.1 PrefixSegmentFlagsModel

e	*boolean*	Set if any upstream neighbor of the Prefix-SID originator MUST replace the Prefix-SID with a Prefix-SID having an Explicit-NULL value before forwarding the packet.
l	*boolean*	Set if the value/index carried by the Prefix-SID has local significance.
n	*boolean*	Set if the Prefix-SID refers to the router identified by the prefix.
p	*boolean*	Set if the penultimate hop MUST NOT pop the Prefix-SID before delivering the packet to the node that advertised the Prefix-SID.
r	*boolean*	Set if prefix to which this Prefix-SID is attached has been propagated by the router either from another level or from redistribution.
v	*boolean*	Set if the Adj-SID carries a value.

2.914.1.1.2.2 ProxyNodeSegmentFlagsModel

a	*boolean*	Set if the proxy-node segment is directly connected to the node advertising the prefix.

2.915 show isis (spf log) | (INSTANCE spf log) | (spf log vrf VRFNAME) [...]

vrfs	*table(string) = Instances-IsisSpfLogTableModel* see 2.915.1	IS-IS instance information for all VRFs.

2.915.1 InstancesIsisSpfLogTableModel

isisInstances	*table(string) = IsisSpfLogTableModel* see 2.915.1.1	IS-IS Instance list keyed by instance name.

2.915.1.1 IsisSpfLogTableModel

levels	*table(numeric string) = IsisLevelSpfLogModel* see 2.915.1.1.1	Dictionary of SPF logs keyed by level.

2.915.1.1.1 IsisLevelSpfLogModel

spfLogs	*list of IsisSpfLogEntry* see 2.915.1.1.1.1	ISIS SPF log entries.

2.915.1.1.1.1 IsisSpfLogEntry

[ipv4Nodes]	*integer*	Number of IPv4 routers that make up the topology.
[ipv6Nodes]	*integer*	Number of IPv6 routers that make up the topology.
[partial]	*boolean*	Partial SPF optimization.
reason	*string*	The first trigger that scheduled the SPF.
[scheduled]	*boolean*	Scheduled SPF run.
startTime	*floating point number*	SPF start time in UTC.
[timeTaken]	*floating point number*	SPF run duration(ms).
triggers	*integer*	Number of SPF triggers consumed in this SPF run.

2.916 show isis (srv6 locators detail) | (INSTANCE srv6 locators detail) | (srv6 locators detail vrf VRFNAME)

vrfs	*table(string) = Instances-IsisInstanceSrv6Locators* see 2.916.1	SRv6 Locators in IS-IS for all VRFs.

2.916.1 InstancesIsisInstanceSrv6Locators

isisInstances	*table(string) = IsisInstanceSrv6Locators* see 2.916.1.1	IS-IS Instance list keyed by instance name.

2.916.1.1 IsisInstanceSrv6Locators

topologies	*table(numeric string) = IsisSrv6TopologyLocators* see 2.916.1.1.1	SRv6 Locators in the IS-IS instance keyed by Topology Id.

2.916.1.1.1 IsisSrv6TopologyLocators

levels	*table(numeric string) = IsisSrv6LevelLocators* see 2.916.1.1.1.1	SRv6 Locators in the IS-IS topology keyed by level.

2.916.1.1.1.1 IsisSrv6LevelLocators

locatorPrefixes	*table(IPv4 or IPv6 address prefix) = IsisSrv6Locator* see 2.916.1.1.1.2	SRv6 Locators in the IS-IS level keyed by prefix.

2.916.1.1.1.2 IsisSrv6Locator

locatorInstances	*list of IsisSrv6LocatorInstance* see 2.916.1.1.1.3	SRv6 Locator info advertised by routers.

2.916.1.1.1.3 IsisSrv6LocatorInstance

algorithm	*integer*	Locator algorithm.
flags	*Srv6LocatorFlags* see 2.899.1.1.1.56	Locator flags.
[hostName]	*string*	Hostname.
metric	*integer*	Cost of the Locator reachability.
systemId	*string*	System ID.

2.917 show isis (summary-address) | (INSTANCE summary-address) | (summary-address vrf VRFNAME) [...]

vrfs	*table(string) = InstancesIsisLeakedRouteSumAddrInstanceModel* see 2.917.1	ISIS route summary-address for all VRFs.

2.917.1 InstancesIsisLeakedRouteSumAddrInstanceModel

isisInstances	*table(string) = IsisLeakedRouteSumAddrInstanceModel* see 2.917.1.1	IS-IS Instance list keyed by instance name.

2.917.1.1 IsisLeakedRouteSumAddrInstanceModel

level1ToLevel2Summary-Addresses	*table(IPv4 or IPv6 address prefix) = IsisSumAddrEntryModel* see 2.917.1.1.1	A dictionary of summary-addresses for L1 to L2 leaked routes.

2.917.1.1.1 IsisSumAddrEntryModel

advertised	*string*	Summary address advertised.
[contributors]	*list of IP address prefix*	List of contributors.
metric	*integer*	Metric value.
totalContributors	*integer*	Total number of contributors.

2.918 show isis counters | (INSTANCE counters) | (counters vrf VRF-NAME) [...]

vrfs	*table(string) = Instances-IsisInstanceCounters* see 2.918.1	ISIS instance information for all VRFs.

2.918.1 InstancesIsisInstanceCounters

isisInstances	*table(string) = IsisInstanceCounters* see 2.918.1.1	IS-IS Instance list keyed by instance name.

2.918.1.1 IsisInstanceCounters

interfaceCounters	*table(Interface name) = IsisInterfaceCounters* see 2.918.1.1.1	Dictionary of Isis Interface counterskeyed by interface name.
[systemCounters] **	*IsisSystemCounters* see 2.918.1.1.2	Data pertaining to IS-IS System counters. **Since: 4.28.0

2.918.1.1.1 IsisInterfaceCounters

[dropCounters]	*IsisInterfaceDropCounters* see 2.918.1.1.1.1	Data pertaining to IS-IS drop counters.
[lastResetTime] **	*integer*	UTC timestamp when the counters are reset last. **Since: 4.21.3
[packetCounters]	*IsisInterfacePacketCounters* see 2.918.1.1.1.13	Data pertaining to the packet counters.
[rateCounters] **	*IsisInterfacePacketRate-Counter* see 2.918.1.1.1.16	Data pertaining to IS-IS packet rate counters. **Since: 4.35.2

2.918.1.1.1.1 IsisInterfaceDropCounters

csnpL1	*integer*	Number of Level-1 IS-IS Complete Sequence Number Packets dropped.
csnpL2	*integer*	Number of Level-2 IS-IS Complete Sequence Number Packets dropped.
[details]	*IsisInterfaceDropCounters-Details* see 2.918.1.1.1.2	Reasons ofdrop for each PDU with their respective counts.
iihLanL1	*integer*	Number of Level-1 IS-IS Lan Hello Packets Dropped.
iihLanL2	*integer*	Number of Level-2 IS-IS Lan Hello Packets Dropped.
iihP2p	*integer*	Number of IS-IS P2P Hello Packets Dropped.
lspL1	*integer*	Number of Level-1 IS-IS Link State PDUs dropped.
lspL2	*integer*	Number of Level-2 IS-IS Link State PDUs dropped.

malformedPdus	*integer*	Number of IS-IS PDUs received malformed. The received PDU had either a wrong header length, wrong version, or the System Id length in the PDU is not supported by the system received.
psnpL1	*integer*	Number of Level-1 IS-IS Partial Sequence Number Packets dropped.
psnpL2	*integer*	Number of Level-2 IS-IS Partial Sequence Number Packets dropped.

2.918.1.1.1.2 IsisInterfaceDropCountersDetails

[csnpL1DropReasons]	*IsisInterfaceDropReasons-L1Csnps* see 2.918.1.1.1.3	Reasons which led to Level-1 IS-IS Complete Sequence number packets getting dropped and their respective counts.
[csnpL2DropReasons]	*IsisInterfaceDropReasons-L2Csnps* see 2.918.1.1.1.7	Reasons which led to Level-2 IS-IS Complete Sequence number packets getting dropped and their respective counts.
[iihLanL1DropReasons]	*IsisInterfaceDropReasons-L1LanHellos* see 2.918.1.1.1.4	Reasons which led to Level-1 IS-IS LAN Hellosgetting dropped and their respective counts.
[iihLanL2DropReasons]	*IsisInterfaceDropReasons-L2LanHellos* see 2.918.1.1.1.8	Reasons which led to Level-2 IS-IS LAN Hellosgetting dropped and their respective counts.
[iihP2pDropReasons]	*IsisInterfaceDropReasons-P2pHellos* see 2.918.1.1.1.12	Reasons which led IS-IS P2P Hellosgetting dropped and their respective counts.
[lspL1DropReasons]	*IsisInterfaceDropReasons-L1Lsps* see 2.918.1.1.1.5	Reasons which led to IS-IS Level-1 Link State PDUs getting dropped and their respective counts.
[lspL2DropReasons]	*IsisInterfaceDropReasons-L2Lsps* see 2.918.1.1.1.9	Reasons which led to IS-IS Level-2 Link State PDUs getting dropped and their respective counts.
[malformedPdusDropReasons]	*IsisInterfaceDropReasons-MalformedPdus* see 2.918.1.1.1.11	Reasons which led to malformed PDUsgetting dropped and their respective counts.
[psnpL1DropReasons]	*IsisInterfaceDropReasons-L1Psnps* see 2.918.1.1.1.6	Reasons which led to IS-IS Level-1 Partial Sequence number packets getting dropped and their respective counts.
[psnpL2DropReasons]	*IsisInterfaceDropReasons-L2Psnps* see 2.918.1.1.1.10	Reasons which led to IS-IS Level-2 Partial Sequence number packets getting dropped and their respective counts.

2.918.1.1.1.3 IsisInterfaceDropReasonsL1Csnps

[authFailure]	*integer*	The PDU could not be authenticated.
[badLength]	*integer*	Length indicated in the packet header is different from the actual length of the packet.
[badOptionLength]	*integer*	Length of one or more of the optional TLVs in the PDU is different from that indicated in the Length section of that TLV.

[circuitLevelMismatch]	*integer*	The circuit level indicated in the PDU does not match with the level on which the IS-IS interface receiving this PDU is configured on.
[iidTlvMismatch] **	*integer*	Invalid IID-TLV received in the PDU. **Since: 4.30.0
[invalidLspEntryOption]	*integer*	CSNPs and PSNPs are dropped with this reason. one or more of the LSP entry sub-TLVs in the PDU has an invalid length.
[malformedTlv]	*integer*	one of the optional TLVs in the PDU could not be validated.
[nonAdjSource]	*integer*	LSPs, CSNPs or PSNPs are dropped with this reason. The system receiving this PDU does not have an adjacency with the system sending this PDU.

2.918.1.1.1.4 IsisInterfaceDropReasonsL1LanHellos

[authFailure]	*integer*	The PDU could not be authenticated.
[badAreaOption]	*integer*	Hellos are dropped with this reason. The Area address sub-option in the Areas option is malformed. The areas indicated in the PDU can hence not be used.
[badLength]	*integer*	Length indicated in the packet header is different from the actual length of the packet.
[badOptionLength]	*integer*	Length of one or more of the optional TLVs in the PDU is different from that indicated in the Length section of that TLV.
[circuitLevelMismatch]	*integer*	The circuit level indicated in the PDU does not match with the level on which the IS-IS interface receiving this PDU is configured on.
[circuitTypeMismatches]	*integer*	The Circuit type indicated in the PDU does not match with that of the interface on which it was received For instance, a p2p Hello received on a IS-IS Broadcast interface is dropped with this reason.
[dupSysIdDetected] **	*integer*	We already have an adjacency with the same system Id. **Since: 4.21.3
[iidTlvMismatch] **	*integer*	Invalid IID-TLV received in the PDU. **Since: 4.30.0
[incompatibleAdjAttrs]	*integer*	Hellos are dropped with this reason. we drop with this reason when there are no usable addresses configured on the interface receiving this Hello OR the protocols supported by our syatem have changed and have become inconsistent with those supported by the system sending this Hello.
[lengthGreaterThanMTU]	*integer*	Length of the PDU is greater than the MTU configured on the interface on which it is received.

[malformedTlv]	*integer*	one of the optional TLVs in the PDU could not be validated.
[maxAreaAddressMismatch]	*integer*	Hellos are dropped with this reason. The max number of areas indicated in the Hello mismatch with the maximum number of areas supported by the system receiving this hello.
[missingAreas]	*integer*	Hellos are dropped with this reason. The IS-IS interface receiving this Hello is on Level-1 but there is no area TLV in the Hello. We hence drop the Hello.
[neighbourSysIdChanged]	*integer*	LAN Hellos are Dropped with this reason. The system Id of the neighbour sending this Hellohas changed. We hence drop the Hello and delete the adjacency.
[ngbSysIdMismatchInRestart-TLVWithRA]	*integer*	Hellos are dropped with this reason. The neighbour system Id indicated in restart TLV with RA does not match our own System Id.
[noMatchingAreas]	*integer*	Hellos are dropped with this reason. The IS-IS interface on which the Hello was received is in level-1 but none of the areas indicated in the Hello match with the areas supported by the system.
[noRemTimeInRestartTlvWith-RA]	*integer*	Hellos are dropped with this reason. Remaining time is not indicated in restart TLV with RA.
[noSourceMac]	*integer*	LAN Hellos are dropped with this reason. The Hello is received without any source MAC address.
[noSupportedProtocols]	*integer*	Hellos are dropped with this reason. The Hello received does not have NLPID TLV indicating that no protocols are supported by the system sending the Hello.
[ownSystemIdPdu]	*integer*	The System Id on the PDU is similar to that of the system on which it is received indicating the system received the PDU it has sent (or) some other system is using the same system ID. The PDU is dropped.
[protocolAddressesMismatch]	*integer*	Hellos are dropped with this reason.The Interface addresses received in the Hello are inconsistent with the NLPIDs received indicating that there is an inconsistency between the protocols supported and interface addresses configured on the system sending this Hello.
[supportedProtocols-Mismatch]	*integer*	Hellos are dropped with this reason.The NLPIDs received in the PDU do not match the protocols supported by the system receiving this PDU.

[topoSuppProtocolsMismatch]	*integer*	Hellos are dropped with this reaosn. This happens when the MTIDs and NLPIDs in the PDU mismatch, indicating that there is an inconsistency between the topologies and protocols supported by the system sending this Hello.
[unknownCircuitType]	*integer*	The circuit type indicated in the PDU is unknown. This Happens when a IS-IS Hello has a circuit type other than 1,2 or 3 indicating Level-1,Level-2,Level-1-2 respectively.

2.918.1.1.1.5 IsisInterfaceDropReasonsL1Lsps

[authFailure]	*integer*	The PDU could not be authenticated.
[badChecksum]	*integer*	The checksum indicated in the LSP is wrong indicating that the Lsp is corrupted.
[badLength]	*integer*	Length indicated in the packet header is different from the actual length of the packet.
[badLspLength]	*integer*	Length of the LSP is greater than the length of LSP buffer of the receiving system.
[circuitLevelMismatch]	*integer*	The circuit level indicated in the PDU does not match with the level on which the IS-IS interface receiving this PDU is configured on.
[differentChecksumLsp]	*integer*	LSP received has samilar sequence number as that in the LSP database of the system receiving the LSP, but their checksums are different. The LSP is dropped. If the LSP is self generated then it is regenerated with a newer sequence number. If it is not self generated then it is force expired.
[iidTlvMismatch] **	*integer*	Invalid IID-TLV received in the PDU. **Since: 4.30.0
[invalidPurge]	*integer*	LSPs are dropped with this reason. The Purge LSP must contain only the Header (or) the Header and Auth option. If it contains anything more or less, it is dropped.
[malformedTlv]	*integer*	one of the optional TLVs in the PDU could not be validated.
[nonAdjSource]	*integer*	LSPs, CSNPs or PSNPs are dropped with this reason. The system receiving this PDU does not have an adjacency with the system sending this PDU.
[olderLsp]	*integer*	LSP with older sequence number than that of the corresponding LSP in the database of the system is received. The LSP is dropped and the latest LSP is flooded into the circuit on which the LSP was received.

olderPurgeLsp	*integer*	Purge LSP with a sequence number older than that in the LSP database of the system is received. The LSP is dropped and the latest LSP is flooded.
[ownExpiredLsp]	*integer*	LSP is received with the system Id in the LSPID matching the system Id of the system receiving it, but the LSP is no longer present in the LSP database of the system.This LSP might be from the previous incarnation of the system. The LSP is dropped and is force expired.
[ownLspPurge]	*integer*	Self-originated LSP of the system is received with a zero-life but the remaining life of the LSP as indicated in the LSP database is non-zero. The system drops this LSP and regenerates the LSP with a newer sequence number.
[ownNewerSequenceLsp]	*integer*	Self generated LSP with a newer sequence number has been received. It is dropped and a new LSP is regenerated and flooded.
[parsingFailure]	*integer*	LSPs are dropped with this reasons. The options in the LSP could not be parsed properly, indicating that the received LSP is corrupted.

2.918.1.1.1.6 IsisInterfaceDropReasonsL1Psnps

[authFailure]	*integer*	The PDU could not be authenticated.
[badLength]	*integer*	Length indicated in the packet header is different from the actual length of the packet.
[badOptionLength]	*integer*	Length of one or more of the optional TLVs in the PDU is different from that indicated in the Length section of that TLV.
[circuitLevelMismatch]	*integer*	The circuit level indicated in the PDU does not match with the level on which the IS-IS interface receiving this PDU is configured on.
[iidTlvMismatch] **	*integer*	Invalid IID-TLV received in the PDU. **Since: 4.30.0
[invalidLspEntryOption]	*integer*	CSNPs and PSNPs are dropped with this reason. one or more of the LSP entry sub-TLVs in the PDU has an invalid length.
[malformedTlv]	*integer*	one of the optional TLVs in the PDU could not be validated.
[nonAdjSource] **	*integer*	LSPs, CSNPs or PSNPs are dropped with this reason. The system receiving this PDU does not have an adjacency with the system sending this PDU. **Since: 4.23.0
[psnpOnNonDisSystem]	*integer*	PSNP is received on a circuit of the system of type broadcast but system is not a DIS on that circuit.

2.918.1.1.1.7 IsisInterfaceDropReasonsL2Csnps

[authFailure]	*integer*	The PDU could not be authenticated.
[badLength]	*integer*	Length indicated in the packet header is different from the actual length of the packet.
[badOptionLength]	*integer*	Length of one or more of the optional TLVs in the PDU is different from that indicated in the Length section of that TLV.
[circuitLevelMismatch]	*integer*	The circuit level indicated in the PDU does not match with the level on which the IS-IS interface receiving this PDU is configured on.
[iidTlvMismatch] **	*integer*	Invalid IID-TLV received in the PDU. **Since: 4.30.0
[invalidLspEntryOption]	*integer*	CSNPs and PSNPs are dropped with this reason. one or more of the LSP entry sub-TLVs in the PDU has an invalid length.
[malformedTlv]	*integer*	one of the optional TLVs in the PDU could not be validated.
[nonAdjSource]	*integer*	LSPs, CSNPs or PSNPs are dropped with this reason. The system receiving this PDU does not have an adjacency with the system sending this PDU.

2.918.1.1.1.8 IsisInterfaceDropReasonsL2LanHellos

[authFailure]	*integer*	The PDU could not be authenticated.
[badAreaOption]	*integer*	Hellos are dropped with this reason. The Area address sub-option in the Areas option is malformed. The areas indicated in the PDU can hence not be used.
[badLength]	*integer*	Length indicated in the packet header is different from the actual length of the packet.
[badOptionLength]	*integer*	Length of one or more of the optional TLVs in the PDU is different from that indicated in the Length section of that TLV.
[circuitLevelMismatch]	*integer*	The circuit level indicated in the PDU does not match with the level on which the IS-IS interface receiving this PDU is configured on.
[circuitTypeMismatches]	*integer*	The Circuit type indicated in the PDU does not match with that of the interface on which it was received For instance, a p2p Hello received on a IS-IS Broadcast interface is dropped with this reason.
[dupSysIdDetected] **	*integer*	We already have an adjacency with the same system Id. **Since: 4.21.3
[iidTlvMismatch] **	*integer*	Invalid IID-TLV received in the PDU. **Since: 4.30.0

[incompatibleAdjAttrs]	*integer*	Hellos are dropped with this reason. we drop with this reason when there are no usable addresses configured on the interface receiving this Hello OR the protocols supported by our syatem have changed and have become inconsistent with those supported by the system sending this Hello.
[lengthGreaterThanMTU]	*integer*	Length of the PDU is greater than the MTU configured on the interface on which it is received.
[malformedTlv]	*integer*	one of the optional TLVs in the PDU could not be validated.
[maxAreaAddressMismatch]	*integer*	Hellos are dropped with this reason. The max number of areas indicated in the Hello mismatch with the maximum number of areas supported by the system receiving this hello.
[missingAreas]	*integer*	Hellos are dropped with this reason. The IS-IS interface receiving this Hello is on Level-1 but there is no area TLV in the Hello. We hence drop the Hello.
[neighbourSysIdChanged]	*integer*	LAN Hellos are Dropped with this reason. The system Id of the neighbour sending this Hellohas changed. We hence drop the Hello and delete the adjacency.
[ngbSysIdMismatchInRestart-TLVWithRA]	*integer*	Hellos are dropped with this reason. The neighbour system Id indicated in restart TLV with RA does not match our own System Id.
[noMatchingAreas]	*integer*	Hellos are dropped with this reason. The IS-IS interface on which the Hello was received is in level-1 but none of the areas indicated in the Hello match with the areas supported by the system.
[noRemTimeInRestartTlvWith-RA]	*integer*	Hellos are dropped with this reason. Remaining time is not indicated in restart TLV with RA.
[noSourceMac]	*integer*	LAN Hellos are dropped with this reason. The Hello is received without any source MAC address.
[noSupportedProtocols]	*integer*	Hellos are dropped with this reason. The Hello received does not have NLPID TLV indicating that no protocols are supported by the system sending the Hello.
[ownSystemIdPdu]	*integer*	The System Id on the PDU is similar to that of the system on which it is received indicating the system received the PDU it has sent (or) some other system is using the same system ID. The PDU is dropped.

[protocolAddressesMismatch]	*integer*	Hellos are dropped with this reason.The Interface addresses received in the Hello are inconsistent with the NLPIDs received indicating that there is an inconsistency between the protocols supported and interface addresses configured on the system sending this Hello.
[supportedProtocols-Mismatch]	*integer*	Hellos are dropped with this reason.The NLPIDs received in the PDU do not match the protocols supported by the system receiving this PDU.
[topoSuppProtocolsMismatch]	*integer*	Hellos are dropped with this reaosn. This happens when the MTIDs and NLPIDs in the PDU mismatch, indicating that there is an inconsistency between the topologies and protocols supported by the system sending this Hello.
[unknownCircuitType]	*integer*	The circuit type indicated in the PDU is unknown. This Happens when a IS-IS Hello has a circuit type other than 1,2 or 3 indicating Level-1,Level-2,Level-1-2 respectively.

2.918.1.1.1.9 IsisInterfaceDropReasonsL2Lsps

[authFailure]	*integer*	The PDU could not be authenticated.
[badChecksum]	*integer*	The checksum indicated in the LSP is wrong indicating that the Lsp is corrupted.
[badLength]	*integer*	Length indicated in the packet header is different from the actual length of the packet.
[badLspLength]	*integer*	Length of the LSP is greater than the length of LSP buffer of the receiving system.
[circuitLevelMismatch]	*integer*	The circuit level indicated in the PDU does not match with the level on which the IS-IS interface receiving this PDU is configured on.
[differentChecksumLsp]	*integer*	LSP received has samilar sequence number as that in the LSP database of the system receiving the LSP, but their checksums are different. The LSP is dropped. If the LSP is self generated then it is regenerated with a newer sequence number. If it is not self generated then it is force expired.
[iidTlvMismatch] **	*integer*	Invalid IID-TLV received in the PDU. **Since: 4.30.0
[invalidPurge]	*integer*	LSPs are dropped with this reason. The Purge LSP must contain only the Header (or) the Header and Auth option. If it contains anything more or less, it is dropped.
[malformedTlv]	*integer*	one of the optional TLVs in the PDU could not be validated.

[nonAdjSource]	*integer*	LSPs, CSNPs or PSNPs are dropped with this reason. The system receiving this PDU does not have an adjacency with the system sending this PDU.
[olderLsp]	*integer*	LSP with older sequence number than that of the corresponding LSP in the database of the system is received. The LSP is dropped and the latest LSP is flooded into the circuit on which the LSP was received.
olderPurgeLsp	*integer*	Purge LSP with a sequence number older than that in the LSP database of the system is received. The LSP is dropped and the latest LSP is flooded.
[ownExpiredLsp]	*integer*	LSP is received with the system Id in the LSPID matching the system Id of the system receiving it, but the LSP is no longer present in the LSP database of the system.This LSP might be from the previous incarnation of the system. The LSP is dropped and is force expired.
[ownLspPurge]	*integer*	Self-originated LSP of the system is received with a zero-life but the remaining life of the LSP as indicated in the LSP database is non-zero. The system drops this LSP and regenerates the LSP with a newer sequence number.
[ownNewerSequenceLsp]	*integer*	Self generated LSP with a newer sequence number has been received. It is dropped and a new LSP is regenerated and flooded.
[parsingFailure]	*integer*	LSPs are dropped with this reasons. The options in the LSP could not be parsed properly, indicating that the received LSP is corrupted.

2.918.1.1.1.10 IsisInterfaceDropReasonsL2Psnps

[authFailure]	*integer*	The PDU could not be authenticated.
[badLength]	*integer*	Length indicated in the packet header is different from the actual length of the packet.
[badOptionLength]	*integer*	Length of one or more of the optional TLVs in the PDU is different from that indicated in the Length section of that TLV.
[circuitLevelMismatch]	*integer*	The circuit level indicated in the PDU does not match with the level on which the IS-IS interface receiving this PDU is configured on.
[iidTlvMismatch] **	*integer*	Invalid IID-TLV received in the PDU. **Since: 4.30.0
[invalidLspEntryOption]	*integer*	CSNPs and PSNPs are dropped with this reason. one or more of the LSP entry sub-TLVs in the PDU has an invalid length.

[malformedTlv]	*integer*	one of the optional TLVs in the PDU could not be validated.
[nonAdjSource] **	*integer*	LSPs, CSNPs or PSNPs are dropped with this reason. The system receiving this PDU does not have an adjacency with the system sending this PDU. **Since: 4.23.0
[psnpOnNonDisSystem]	*integer*	PSNP is received on a circuit of the system of type broadcast but system is not a DIS on that circuit.

2.918.1.1.1.11 IsisInterfaceDropReasonsMalformedPdus

[idFieldLengthMismatches]	*integer*	System Id Length in the PDU is different from the System Id length supported by the sytem on which the PDU was received.
[shortHeaders]	*integer*	Header length of the IS-IS PDU received is short.
[wrongVersion]	*integer*	Version of the PDU header is incompatible with the version we support.

2.918.1.1.1.12 IsisInterfaceDropReasonsP2pHellos

[authFailure]	*integer*	The PDU could not be authenticated.
[badAdjStateOption]	*integer*	P2P Hellos are dropped with this reason. The option length or the Adjacency state indicated in the option is incompatible with the state of adjacency in which the system receiving this hello currently in.
[badAdjStateTransition] **	*integer*	Hellos are dropped when the state of adjacency in the system receiving the hello is incompatible with Adjacency State Transition. **Since: 4.35.0
[badAreaOption]	*integer*	Hellos are dropped with this reason. The Area address sub-option in the Areas option is malformed. The areas indicated in the PDU can hence not be used.
[badLength]	*integer*	Length indicated in the packet header is different from the actual length of the packet.
[badOptionLength]	*integer*	Length of one or more of the optional TLVs in the PDU is different from that indicated in the Length section of that TLV.
[circuitLevelMismatch] **	*integer*	The circuit level indicated in the PDU does not match with the level on which the IS-IS interface receiving this PDU is configured on. **Since: 4.22.1

[circuitTypeMismatches]	*integer*	The Circuit type indicated in the PDU does not match with that of the interface on which it was received For instance, a p2p Hello received on a IS-IS Broadcast interface is dropped with this reason.
[iidTlvMismatch] **	*integer*	Invalid IID-TLV received in the PDU. **Since: 4.30.0
[incompatibleAdjAttrs]	*integer*	Hellos are dropped with this reason. we drop with this reason when there are no usable addresses configured on the interface receiving this Hello OR the protocols supported by our syatem have changed and have become inconsistent with those supported by the system sending this Hello.
[lengthGreaterThanMTU]	*integer*	Length of the PDU is greater than the MTU configured on the interface on which it is received.
[malformedTlv]	*integer*	one of the optional TLVs in the PDU could not be validated.
[maxAreaAddressMismatch]	*integer*	Hellos are dropped with this reason. The max number of areas indicated in the Hello mismatch with the maximum number of areas supported by the system receiving this hello.
[noCommonTopology]	*integer*	Hellos are dropped with this reason. This happens when the system receiving the Hello is in Multi-Topology mode but no MTIDs in the Hello and system are common.
[noMatchingAreas]	*integer*	Hellos are dropped with this reason. The IS-IS interface on which the Hello was received is in level-1 but none of the areas indicated in the Hello match with the areas supported by the system.
[noRemTimeInRestartTlvWithRA]	*integer*	Hellos are dropped with this reason. Remaining time is not indicated in restart TLV with RA.
[noSupportedProtocols]	*integer*	Hellos are dropped with this reason. The Hello received does not have NLPID TLV indicating that no protocols are supported by the system sending the Hello.
[nonMatchingThreeWayHandshake]	*integer*	P2P Hellos are dropped with this reason. The neighbour system Id and the Neighbour extended circuit Id indicated in the adjacency state option do not match the system Id and the circuit Id of the system receiving the Hello.
[ownSystemIdPdu]	*integer*	The System Id on the PDU is similar to that of the system on which it is received indicating the system received the PDU it has sent (or) some other system is using the same system ID. The PDU is dropped.

[protocolAddressesMismatch]	*integer*	Hellos are dropped with this reason.The Interface addresses received in the Hello are inconsistent with the NLPIDs received indicating that there is an inconsistency between the protocols supported and interface addresses configured on the system sending this Hello.
[supportedProtocols-Mismatch]	*integer*	Hellos are dropped with this reason.The NLPIDs received in the PDU do not match the protocols supported by the system receiving this PDU.
[topoSuppProtocolsMismatch]	*integer*	Hellos are dropped with this reaosn. This happens when the MTIDs and NLPIDs in the PDU mismatch, indicating that there is an inconsistency between the topologies and protocols supported by the system sending this Hello.
[unknownCircuitType]	*integer*	The circuit type indicated in the PDU is unknown. This Happens when a IS-IS Hello has a circuit type other than 1,2 or 3 indicating Level-1,Level-2,Level-1-2 respectively.

2.918.1.1.1.13 IsisInterfacePacketCounters

processed **	*IsisInterfacePacket-CountersData* see 2.918.1.1.1.14	Processed packet counters. **Since: 4.27.2
received	*IsisInterfacePacket-CountersData* see 2.918.1.1.1.14	Received packet counters.
retransmitted **	*IsisInterfacePacket-CountersRetransmittedData* see 2.918.1.1.1.15	Retransmitted packet counters. **Since: 4.27.2
transmitted	*IsisInterfacePacket-CountersData* see 2.918.1.1.1.14	Transmitted packet counters.

2.918.1.1.1.14 IsisInterfacePacketCountersData

csnpL1	*integer*	Number of L1 CSN Packets.
csnpL2	*integer*	Number of L2 CSN Packets.
iihL1	*integer*	Number of L1 LAN IS-IS Hello Packets.
iihL2	*integer*	Nunber of L2 LAN IS-IS Hello Packets.
iihP2p	*integer*	Number of p2p Hello Packets.
lspL1	*integer*	Number of L1 LSPs.
lspL2	*integer*	Number of L2 LSPs.
psnpL1	*integer*	Number of L1 PSN Packets.
psnpL2	*integer*	Number of L2 PSN Packets.

2.918.1.1.1.15 IsisInterfacePacketCountersRetransmittedData

lspL1	*integer*	Number of L1 LSPs.
lspL2	*integer*	Number of L2 LSPs.

2.918.1.1.1.16 IsisInterfacePacketRateCounter

lspRateCounter	*IsisInterfaceLspFlooding-RateData* see 2.918.1.1.1.17	LSP flooding rate.

2.918.1.1.1.17 IsisInterfaceLspFloodingRateData

lspFloodingRate	*floating point number*	Average LSP flooding rate.
maxLspFloodingRate	*floating point number*	Maximum LSP flooding rate.

2.918.1.1.2 IsisSystemCounters

systemCountersL1	*IsisSystemCountersData* see 2.918.1.1.2.1	System Counters for Level-1.
systemCountersL2	*IsisSystemCountersData* see 2.918.1.1.2.1	System Counters for Level-2.

2.918.1.1.2.1 IsisSystemCountersData

authKeyFails	*integer*	Number of authentication key failures.
authTypeFails	*integer*	Number of authentication type mismatches.
corruptedLsps	*integer*	Number of corrupted in-memory LSPs detected.
databaseOverloads	*integer*	Number of times the database has become overloaded.
exceededMaxSeqNums	*integer*	Number of times the system has attempted to exceed the maximum sequence number.
idLenMismatches	*integer*	Number of times a PDU is received with a different value for ID field length from that of the receiving system.
lspErrors	*integer*	Number of received LSPs with errors.
maxAreaAddressMismatches	*integer*	Number of times a PDU is received with a different value for MaximumAreaAddresses from that of the receiving system.
othersLspPurgesSent **	*integer*	Number of others' LSP purges sent. **Since: 4.32.2
ownLspPurges	*integer*	Number of times a zero-aged copy of the system's own LSP is received from some other node.
ownLspPurgesSent **	*integer*	Number of own LSP purges sent. **Since: 4.32.2
seqNumSkips	*integer*	Number of times a seq number skip has occurred.
spfRuns	*integer*	Number of times SPF was run for this level.

2.919 show isis database | (INSTANCE database) | (database vrf VRF-NAME) [...]

vrfs	*table(string) = Instances-IsisLsdbSummaryModel* see 2.919.1	IS-IS instance information for all VRFs.

2.919.1 InstancesIsisLsdbSummaryModel

isisInstances	*table(string) = IsisLsdbSummaryModel* see 2.919.1.1	IS-IS Instance list keyed by instance name.

2.919.1.1 IsisLsdbSummaryModel

level	*table(numeric string) = LevelSummaryModel* see 2.919.1.1.1	A mapping of isis level to LSDB.

2.919.1.1.1 LevelSummaryModel

lsps	*table(string) = LspBaseModel* see 2.919.1.1.1.1	A mapping of systemId to LSP in LSDB.

2.919.1.1.1.1 LspBaseModel

Could also be an instance of:
LspDetailModel 2.899.1.1.1.1
LspDetailTlvModel 2.900.1.1.1.1

checksum	*integer*	Checksum value.
expiryTime	*floating point number*	UTC time for Future Expiry time of LSP.
[flags]	*LspFlags* see 2.899.1.1.1.12	IS-IS Lsp flags.
hostnameConflict **	*boolean*	LSP originated by node with conflicting hostname. **Since: 4.32.1
[intermediateSystemType]	*enum: L1 | L2 | none*	IS-type for LSP.
length **	*integer*	LSP length. **Since: 4.27.1
nodeUnreachable **	*boolean*	Flag for LSPs originated by Unreachable/Stale Nodes. **Since: 4.31.1
sequence	*integer*	Sequence number for this LSP.

2.920 show isis flex-algo path [...]

vrfs	*table(string) = FlexAlgoPathVrfModel* see 2.920.1	A mapping between VRF and information of all flex algo paths in that VRF.

2.920.1 FlexAlgoPathVrfModel

[v4Info]	*FlexAlgoPathAfModel* see 2.920.1.1	Flex algo path information for IPv4 address family.
[v6Info]	*FlexAlgoPathAfModel* see 2.920.1.1	Flex algo path information for IPv6 address family.

2.920.1.1 FlexAlgoPathAfModel

topologies	*table(numeric string) = FlexAlgoPathTopoIdModel* see 2.920.1.1.1	A mapping of topology ID to all flex algo paths.

2.920.1.1.1 FlexAlgoPathTopoIdModel

destinations	*table(string) = FlexAlgoPathDestModel* see 2.920.1.1.1.1	A mapping of path destination to all flex algo paths for that destination.

2.920.1.1.1.1 FlexAlgoPathDestModel

[hostname]	*string*	Hostname.
paths	*table(numeric string) = FlexAlgoPathEntryModel* see 2.920.1.1.1.2	A mapping of an algorithm to the corresponding flex algo path.

2.920.1.1.1.2 FlexAlgoPathEntryModel

[algoName]	*string*	Algorithm name.
[details]	*FlexAlgoPathEntryDetailModel* see 2.920.1.1.1.3	Detailed path information.
vias	*list of FlexAlgoViaModel* see 2.920.1.1.1.5	List of flex algo vias.

2.920.1.1.1.3 FlexAlgoPathEntryDetailModel

changeCount	*integer*	Number of times path updated.
constraint	*FlexAlgoPathConstraintModel* see 2.920.1.1.1.4	Path constraint.
lastUpdatedTime	*floating point number*	UTC timestamp of the last path update.
[metric]	*integer*	Path metric.
pathId	*integer*	Path ID number.
refreshReqSeq	*integer*	Request sequence number.

refreshRespSeq	*integer*	Response sequence number.

2.920.1.1.1.4 FlexAlgoPathConstraintModel

[excludeAdminGroup]	*integer*	Admin Group excluded.
[excludeAdminGroups-Extended] **	*list of integer*	Extended Admin Groups excluded. **Since: 4.31.1
[excludeSrlg]	*list of integer*	List of SRLG IDs excluded.
[includeAllAdminGroup]	*integer*	Admin Group included.
[includeAllAdminGroups-Extended] **	*list of integer*	Extended Admin Groups included. **Since: 4.31.1
[includeAnyAdminGroup]	*integer*	Any Admin Group included.
[includeAnyAdminGroups-Extended] **	*list of integer*	Any Extended Admin Groups included. **Since: 4.31.1
metricType	*enum: minDelay | igp | te*	Metric type.

2.920.1.1.1.5 FlexAlgoViaModel

intf	*interface name*	L3 interface of next hop.
nexthop	*IP address*	Next hop IP address.

2.921 show isis hostname | (INSTANCE hostname) | (hostname vrf VRF-NAME)

vrfs	*table(string) = InstancesIsisHostname-InstanceModel* see 2.921.1	Hostname information for all VRFs.

2.921.1 InstancesIsisHostnameInstanceModel

isisInstances	*table(string) = Isis-HostnameInstanceModel* see 2.921.1.1	IS-IS Instance list keyed by instance name.

2.921.1.1 IsisHostnameInstanceModel

systemIds	*table(string) = IsisHostnameEntryModel* see 2.921.1.1.1	Dictionary of IS-IS hostnames keyed by SystemID.

2.921.1.1.1 IsisHostnameEntryModel

hostname	*string*	Hostname.
hostnameConflict **	*boolean*	LSP originated by node with conflicting hostname. **Since: 4.32.1
level	*enum: L1 | L1L2 | L2*	IS type.

`nodeUnreachable` **	*boolean*	Node is unreachable. **Since: 4.31.2

2.922 show isis interface | (INSTANCE interface) | (interface vrf VRF-NAME) | (interface intf) [...]

vrfs	*table(string) = InstancesIsisInterfaceModel* see 2.922.1	IS-IS interface information for all VRFs.

2.922.1 InstancesIsisInterfaceModel

isisInstances	*table(string) = IsisInterfaceModel* see 2.922.1.1	IS-IS Instance list keyed by instance name.

2.922.1.1 IsisInterfaceModel

interfaces	*table(Interface name) = IsisInterface* see 2.922.1.1.1	Dictionary of IS-IS interfaces keyed by interface name.

2.922.1.1.1 IsisInterface

[areaProxyBoundary] **	*boolean*	Interface enabled for area proxy boundary. **Since: 4.23.2
[bfdIpv4DampingEnabled] **	*boolean*	Whether IPv4 BFD damping is enabled on the interface. **Since: 4.35.2
[bfdIpv4DampingParameters] **	*BfdDampingParameters* see 2.922.1.1.1.1	IPv4 BFD damping parameters. **Since: 4.35.2
[bfdIpv4Enabled]	*boolean*	Whether IPv4 BFD is enabled on the interface.
[bfdIpv4WaitForUpEnabled] **	*boolean*	Whether IPv4 BFD wait-for-up is enabled on the interface. **Since: 4.34.1
[bfdIpv6DampingEnabled] **	*boolean*	Whether IPv6 BFD damping is enabled on the interface. **Since: 4.35.2
[bfdIpv6DampingParameters] **	*BfdDampingParameters* see 2.922.1.1.1.1	IPv6 BFD damping parameters. **Since: 4.35.2
[bfdIpv6Enabled]	*boolean*	Whether IPv6 BFD is enabled on the interface.
[bfdIpv6WaitForUpEnabled] **	*boolean*	Whether IPv6 BFD wait-for-up is enabled on the interface. **Since: 4.34.1
[disabledReason]	*DisabledReason* see 2.922.1.1.1.2	Reason for interface being disabled.
enabled	*boolean*	Interface enabled or not.
[fastFloodingProfile] **	*string*	Fast flooding profile. **Since: 4.34.2

[helloPadding] **	*enum: enabled | enabledUntilAdj | disabled*	ISIS hello padding behavior enabled - Hello packets always padded enabledUntilAdj - Hello packets padded until adjacency is up disabled - Hello packets never padded. **Since: 4.33.1
[helloPaddingEnabled]	*boolean*	Whether hello padding is enabled on the interface.
[index]	*integer*	Interface index.
[interfaceAddressFamily] **	*enum: ipv4 | none | ipv6 | both*	Address Family configured on this interface none : Address Family not configured on interface ipv4 : IPv4 configured on interface ipv6 : IPv6 configured on interface both : IPv4 and IPv6 configured on interface. **Since: 4.26.0
[interfaceSpeed]	*integer*	Interface speed in mbps.
[interfaceType]	*enum: broadcast | point-to-point | loopback*	Interface type.
[intfLevels]	*table(string) = IsisInterfaceLevelModel* see 2.922.1.1.1.4	Dictionary of levels of the interface keyed by level name.
[ipv4MetricProfile]	*string*	IPv4 metric profile.
[ipv4RouteTag] **	*integer*	IPv4 route tag. **Since: 4.21.3
[ipv6MetricProfile]	*string*	IPv6 metric profile.
[ipv6RouteTag] **	*integer*	IPv6 route tag. **Since: 4.21.3
[localFastFlooding-Parameters] **	*IsisFastFloodingParams-Model* see 2.922.1.1.1.3	IS-IS fast flooding parameters. **Since: 4.34.2
[mtu]	*integer*	MTU.
[snpa]	*string*	Subnetwork point of attachment.
[srIndexV4]	*integer*	Node segment index for IPv4.
[srIndexV6]	*integer*	Node segment index for IPv6.
[srNodeSegments] **	*list of IsisNodeSegmentModel* see 2.922.1.1.1.9	Node segments for flex-algo. **Since: 4.26.0
[topology]	*enum: ipv4, ipv6 | ipv4 | ipv6*	Type of topologies enabled.

2.922.1.1.1.1 BfdDampingParameters

[holdInterval]	*integer*	Hold interval for BFD damping (in seconds).
[initialInterval]	*integer*	Initial BFD damping interval (in seconds).
[maxInterval]	*integer*	Max interval for BFD damping (in seconds).

2.922.1.1.1.2 DisabledReason

circuitType	*string*	Configured circuit type on interface.

message	*string*	Reason for interface being disabled.
routerCircType	*string*	Circuit type of router instance.

2.922.1.1.1.3 IsisFastFloodingParamsModel

lppCount	*integer*	Number of LSPs acknowledged in PSNP.
lspBurstSize	*integer*	The LSP burst size.
lspRecvWin	*integer*	Receiver window size.
lspTxIntv	*integer*	The LSP transmission interval.
psnpTxIntv	*integer*	PSNP Tx interval.

2.922.1.1.1.4 IsisInterfaceLevelModel

[authRxDisabled] **	*boolean*	Received hello authentication check is disabled. **Since: 4.22.1
[authenticationMode]	*enum: MD5 | Text | SHA*	Authentication mode.
[authenticationModeKeyId] **	*integer*	Authentication mode key ID. **Since: 4.21.3
[broadcastCircuitInfo]	*BroadcastCircuitInfoModel* see 2.922.1.1.1.5	Broadcast circuit information.
[grStatus]	*GracefulRestartStatus* see 2.922.1.1.1.6	Status of graceful restart.
ipv4Metric	*integer*	IPv4 metric.
[ipv6Metric]	*integer*	IPv6 metric.
isisAdjacencies	*list of IsisLevelAdjModel* see 2.922.1.1.1.7	List of ISIS adjacency entries.
[linkId]	*string*	Link ID for P2P interface.
[numAdjacencies]	*integer*	Number of adjacencies (except for loopback interfaces).
passive **	*boolean*	Passive state. **Since: 4.21.3
[sharedSecretProfile] **	*string*	Shared secret profile. **Since: 4.30.0
v4IpProtection **	*enum: disabled | link*	IP LFA protection mode for IPv4. **Since: 4.36.0
v4Protection **	*enum: node | disabled | link*	TI-LFA protection mode for IPv4. **Since: 4.22.1
[v4SrlgProtection] **	*enum: loose | strict*	TI-LFA SRLG protection mode for IPv4. **Since: 4.24.1
v6IpProtection **	*enum: disabled | link*	IP LFA protection mode for IPv6. **Since: 4.36.0
v6Protection **	*enum: node | disabled | link*	TI-LFA protection mode for IPv6. **Since: 4.22.1
[v6SrlgProtection] **	*enum: loose | strict*	TI-LFA SRLG protection mode for IPv6. **Since: 4.24.1

2.922.1.1.1.5 BroadcastCircuitInfoModel

dis	*string*	System ID of DIS for broadcast circuit.

[disHostname]	*string*	Hostname of DIS for broadcast circuit.
disPriority	*integer*	DIS Priority for broadcast circuit.
lanId	*string*	LAN ID for broadcast circuit.
[lanIdWithHostname]	*string*	Lan ID with Hostname for broadcast circuit.
priority	*integer*	Priority for broadcast circuit.

2.922.1.1.1.6 GracefulRestartStatus

csnpRcvd	*boolean*	CSNP received.
raRcvd	*boolean*	Restart Acknowledgement received.
rrSent	*boolean*	Restart Request Sent.
saSent	*boolean*	Suppress Adjacency Sent.

2.922.1.1.1.7 IsisLevelAdjModel

addrFamily	*enum: unknown* | *ipv6* | *ipv4, ipv6* | *none* | *ipv4* | *both*	Address Family advertised by neighbor none : Address Family not advertised by neighbor ipv4 : IPv4 advertised by neighbor ipv6 : IPv6 advertised by neighbor both : IPv4 and IPv6 advertised by neighbor.
adjAddrFamilyMatch **	*boolean*	Address families should match for adjacency formation. **Since: 4.26.0
adjType	*enum: es* | *unknown* | *l1l2* | *l2* | *l1*	Adjacency type.
[fastFloodingParameters-Used] **	*IsisFastFloodingParams-Model* see 2.922.1.1.1.3	Fast flooding parameters used. **Since: 4.35.0
holdTime	*integer*	Hold time in seconds.
[hostname]	*string*	Hostname.
intfAreas	*list of IsisIntfAreaModel* see 2.922.1.1.1.8	List of interface areas.
[ipv4IntfAddr]	*IPv4 address*	IPv4 interface address.
[ipv6IntfAddr]	*IPv6 address*	IPv6 interface address.
level	*enum: level1* | *level1-2* | *unknown* | *level2*	Level.
[peerFastflooding-Parameters] **	*IsisFastFloodingParams-Model* see 2.922.1.1.1.3	IS-IS fast flooding parameters. **Since: 4.34.2
[priority]	*integer*	Priority.
[snpa]	*string*	Subnetwork point of attachment of neighbor.
state	*enum: failed* | *down* | *up* | *init*	Adjacency state.
[staticNeighborSource] **	*bgpSession*	Static neighbor source. **Since: 4.34.0
[supportedTopologies]	*enum: unknown* | *ipv6* | *ipv4, ipv6* | *none* | *ipv4* | *both*	Supported topologies.

systemId	*string*	System ID of neighbor.

2.922.1.1.1.8 IsisIntfAreaModel

areaId	*string*	Area ID.

2.922.1.1.1.9 IsisNodeSegmentModel

[flexAlgo]	*string*	Flexible algorithm name.
index	*integer*	Node segment index.
ipv6	*boolean*	Whether node segment index is for IPv6.

2.923 show isis mpls ldp sync [...]

vrfs	*table(string) = Instances-IsisMplsLdpSyncModel* see 2.923.1	MPLS LDP sync information for all vrfs.

2.923.1 InstancesIsisMplsLdpSyncModel

isisInstances	*table(string) = IsisMplsLdpSyncModel* see 2.923.1.1	IS-IS Instance list keyed by instance name.

2.923.1.1 IsisMplsLdpSyncModel

interfaces	*table(Interface name) = IsisMplsLdpSyncInterface-Model* see 2.923.1.1.1	MPLS LDP sync information keyed by interface name.

2.923.1.1.1 IsisMplsLdpSyncInterfaceModel

[holddownTime]	*integer*	Holddown time in seconds. Hold until established if zero.
[igpNotifyDelay]	*integer*	IGP notify delay in seconds. Immediate if zero.
ldpEnabled	*boolean*	LDP Enabled.
[syncAchieved]	*boolean*	LDP sync achieved.
syncRequired	*boolean*	LDP sync required.

2.924 show isis neighbors | (INSTANCE neighbors) | (neighbors vrf VRF-NAME) [...]

revision 2

vrfs	*table(string) = Instances-IsisInstanceNeighbors* see 2.924.1	ISIS instance information for all VRFs.

2.924.1 InstancesIsisInstanceNeighbors

isisInstances	*table(string) = IsisInstanceNeighbors* see 2.924.1.1	IS-IS Instance list keyed by instance name.

2.924.1.1 IsisInstanceNeighbors

neighbors	*table(string) = IsisSystemIdNeighbors* see 2.924.1.1.1	Dictionary of ISIS neighbors keyed by SystemID.

2.924.1.1.1 IsisSystemIdNeighbors

adjacencies	*list of IsisNeighborEntry* see 2.924.1.1.1.1	List of neighbors for SystemID.

2.924.1.1.1.1 IsisNeighborEntry

circuitId	*string*	Circuit Identifier.
[details]	*IsisNeighborDetails* see 2.924.1.1.1.2	ISIS neighbor details.
[holdTimerExpiry] **	*integer*	UTC timestamp of hold timer expiry. **Since: 4.34.1
[hostname]	*string*	Hostname.
interfaceName	*interface name*	ISIS Interface Name.
lastHelloTime	*integer*	UTC timestamp when the last hello was received.
level	*enum: level-1 | level-1-2 | level-2*	Level information of the neighbor.
[routerIdV4]	*IPv4 address*	ISIS neighbor router ID in IP format.
[snpa]	*string*	Sub Network Point Of Attachment Address.
state	*enum: down | up | init*	ISIS Adjacency state.

2.924.1.1.1.2 IsisNeighborDetails

[adjWaitingForBfdIpv4Up] **	*boolean*	Whether adjacency state is stuck in INIT waiting for BFD IPv4 up. **Since: 4.34.1
[adjWaitingForBfdIpv6Up] **	*boolean*	Whether adjacency state is stuck in INIT waiting for BFD IPv6 up. **Since: 4.34.1

advertisedHoldTime	*integer*	Negotiated hold time (in seconds) between neighbors.
areaIds	*list of string*	ISIS Neighbor area(s).
[bfdIpv4DampingExpiry] **	*integer*	BFD IPv4 damping timer expiry in UTC. **Since: 4.35.2
[bfdIpv4State]	*enum: down | up | init | NA | adminDown*	ISIS neighbor BFD state. adminDown - Session taken down for administrative purposes init - Waiting for session establishment up - Session established successfully down - Session is down or has just been created.
[bfdIpv6DampingExpiry] **	*integer*	BFD IPv6 damping timer expiry in UTC. **Since: 4.35.2
[bfdIpv6State]	*enum: down | up | init | NA | adminDown*	ISIS neighbor BFD state. adminDown - Session taken down for administrative purposes init - Waiting for session establishment up - Session established successfully down - Session is down or has just been created.
[grState]	*string*	Shows the state of GR.
grSupported	*string*	Shows whether GR is Supported or Not.
interfaceAddressFamily	*enum: ipv4 | none | ipv6 | both*	Address Family configured on this interface none : Address Family not configured on interface ipv4 : IPv4 configured on interface ipv6 : IPv6 configured on interface both : IPv4 and IPv6 configured on interface.
[intfBfdIpv4WaitForUpEnabled] **	*boolean*	Whether IPv4 BFD wait-for-up is enabled on this interface. **Since: 4.34.1
[intfBfdIpv6WaitForUpEnabled] **	*boolean*	Whether IPv6 BFD wait-for-up is enabled on this interface. **Since: 4.34.1
[ip4Address]	*IPv4 address*	ISIS Neighbor IPv4 address.
[ip6Address]	*IPv6 address*	ISIS Neighbor IPv6 address.
[ip6GlobalAddress]	*IPv6 address*	ISIS Neighbor Global IPv6 address.
neighborAddressFamily	*enum: ipv4 | none | ipv6 | both*	Address Family advertised by neighbor none : Address Family not advertised by neighbor ipv4 : IPv4 advertised by neighbor ipv6 : IPv6 advertised by neighbor both : IPv4 and IPv6 advertised by neighbor.
[ngbBfdIpv4WaitForUpEnabled] **	*boolean*	Whether IPv4 BFD wait-for-up is advertised by neighbor. **Since: 4.34.1
[ngbBfdIpv6WaitForUpEnabled] **	*boolean*	Whether IPv6 BFD wait-for-up is advertised by neighbor. **Since: 4.34.1
[outdelayEvent] **	*enum: Completed | Running*	LSP Out-delay event status. **Since: 4.35.2
[outdelayTime] **	*floating point number*	LSP Out-delay expiry in UTC. **Since: 4.35.2
[priority]	*integer*	ISIS neighbor priority.

srEnabled	*boolean*	Shows whether SR enabled on dut.
[srInfoDetail]	*SrInfoDetail* see 2.924.1.1.1.3	Information about segment routing.
stateChanged	*integer*	UTC Time at which the state changed.
[staticNeighborSource]	*bgpSession*	Static neighbor source.
[topologyIpv4WaitingForBfd-Up] **	*boolean*	Whether topology IPv4 is waiting for BFD IPv4 up. **Since: 4.34.1
[topologyIpv6WaitingForBfd-Up] **	*boolean*	Whether topology IPv6 is waiting for BFD IPv6 up. **Since: 4.34.1

2.924.1.1.1.3 SrInfoDetail

[srLabelV4]	*integer*	Adjacency Label for V4.
[srLabelV6]	*integer*	Adjacency Label for V6.
srRouterId	*IPv4 address*	SR Router Id.
srgbs	*list of SrGlobalBlockModel* see 2.911.1.1.1	SRGBs.

2.925 show isis segment-routing tunnel [...]

revision 2

entries	*table(numeric string) = IsisSrTunnelTableEntry* see 2.925.1	Tunnel table entries keyed by tunnel index.

2.925.1 IsisSrTunnelTableEntry

endpoint	*IP address prefix*	Endpoint of the tunnel.
vias	*list of Via* see 2.193.1.1	List of nexthops.

2.926 show isis summary | (INSTANCE summary) | (summary vrf VRF-NAME)

revision 2

vrfs	*table(string) = InstancesIsisInstanceSummaryModel* see 2.926.1	ISIS instance information for all VRFs.

2.926.1 InstancesIsisInstanceSummaryModel

isisInstances	*table(string) = IsisInstanceSummaryModel* see 2.926.1.1	IS-IS Instance list keyed by instance name.

2.926.1.1 IsisInstanceSummaryModel

addressFamily	*enum: ipv4 | none | ipv6 | both*	Address Family none : Address Family disabled ipv4 : Routes ipv4 only ipv6 : Routes ipv6 only both : Routes both ipv4 and ipv6.
areaIds	*list of string*	List of area-ids in this instance.
[areaLeaderL1]	*string*	Area leader for Level 1.
[areaLeaderL2]	*string*	Area leader for Level 2.
attached	*boolean*	IPv4 Attached or not.
[authModeKeyIdL1]	*integer*	Authentication mode key id in Level1.
[authModeKeyIdL2]	*integer*	Authentication mode key id in Level2.
[authModeL1]	*enum: md5 | sha | none | text*	Authentication mode Level1 none : No Authentication md5 : Authentication mode is MD5 text : Authentication mode is TEXT.
[authModeL2]	*enum: md5 | sha | none | text*	Authentication mode Level2 none : No Authentication md5 : Authentication mode is MD5 text : Authentication mode is TEXT.
[authRxDisabledL1]	*boolean*	Received LSP authentication check is disabled for level-1.
[authRxDisabledL2]	*boolean*	Received LSP authentication check is disabled for level-2.
[coloredTunnelsInLdp-TunnelingSpf]	*boolean*	Shortcut SPF enabled for LDP over RSVP-TE tunneling.
csnpGenInterval	*integer*	CSNP generation interval.
dynamicFloodingL1	*boolean*	Dynamic Flooding is enabled for Level 1.
dynamicFloodingL2	*boolean*	Dynamic Flooding is enabled for Level 2.
enabled	*boolean*	Instance Enabled or not.
gracefulRestart	*boolean*	GR Enabled or not.
gracefulRestartHelper	*boolean*	GR helper Enabled or not.
[hostName]	*string*	Hostname.
instanceId	*integer*	Instance ID.

isType	*enum: level1 | level1-2 | unknown | level2*	Type of IS(Intermediate System) unknown : unknown IS Type level1 : IS type is level-1 level2 : IS type is level-2 level1-2 : IS type is level-1-2.
[lsdbSizeL1]	*integer*	LSDB size (number of link state database records)for level1.
[lsdbSizeL2]	*integer*	LSDB size (number of link state database records)for level2.
lspGenInfo	*IsisInstanceSummaryLspGenInterval* see 2.926.1.1.1	Lsp Gen Information.
lspSizeMaxL1	*integer*	LSP size maximum for Level 1.
lspSizeMaxL2	*integer*	LSP size maximum for Level 2.
[msdBaseMplsImposition]	*integer*	MSD type base MPLS imposition (number of MPLS label which can be imposed).
multiTopologyAttached	*boolean*	IPv6 Attached or not.
multiTopologyEnabled	*boolean*	multiTopology Enabled or not.
numActiveInterfaces	*integer*	Number of active interfaces.
[numDisInterfacesL1]	*integer*	Number of DIS interfaces for leve1.
[numDisInterfacesL2]	*integer*	Number of DIS interfaces for level2.
overloadBitSetL1	*boolean*	Overload bit set for Level 1 LSP.
overloadBitSetL2	*boolean*	Overload bit set for Level 2 LSP.
[overloadBitUpdateTimestampL1]	*floating point number*	UTC timestamp when overload bit status for Level 1 LSP was updated.
[overloadBitUpdateTimestampL2]	*floating point number*	UTC timestamp when overload bit status for Level 2 LSP was updated.
preferenceInfo	*IsisInstanceSummaryPreferenceModel* see 2.926.1.1.2	Preference Information.
redistRoutesCountL1	*integer*	Redistributed routes count for Level 1.
redistRoutesCountL2	*integer*	Redistributed routes count for Level 2.
redistRoutesMaxLimitL1	*integer*	Maximum redistributed routes allowed for Level 1.
redistRoutesMaxLimitL2	*integer*	Maximum redistributed routes allowed for Level 2.
[routerIdV4]	*IPv4 address*	ISIS router ID in IP format.
[sharedSecretProfileL1]	*string*	Shared secret profile for Level-1.
[sharedSecretProfileL2]	*string*	Shared secret profile for Level-2.
[shortcutSpfForIgp]	*boolean*	IPv4 Shortcut SPF enabled for IGP.
[shortcutSpfForLdpTunneling]	*boolean*	Shortcut SPF enabled for LDP tunneling.
spfInfo	*IsisInstanceSummarySpfModel* see 2.926.1.1.3	Spf Information.
systemId	*string*	System Id.
[v4ColoredShortcutSpfForIgp] **	*boolean*	Colored shortcut spf over RSVP-TE tunneling for v4 address enabled. **Since: 4.33.1
[v6ColoredShortcutSpfForIgp] **	*boolean*	Colored shortcut spf over RSVP-TE tunneling for v6 address enabled. **Since: 4.33.1
v6ShortcutSpfForIgp	*boolean*	IPv6 Shortcut SPF enabled for IGP.

2.926.1.1.1 IsisInstanceSummaryLspGenInterval

lspGenHoldInterval	*integer*	Lsp Generation Interval:Hold Interval(s).
lspGenInitialWaitInterval	*integer*	Lsp Generation Interval:Initial wait(ms).
lspGenMaxWaitInterval	*integer*	Lsp Generation Interval:Max wait(s).

2.926.1.1.2 IsisInstanceSummaryPreferenceModel

[internalV4PreferenceL1]	*integer*	internal preference of level1.
[internalV4PreferenceL2]	*integer*	internal preference of level2.
[internalV6PreferenceL1]	*integer*	internal preference of level1.
[internalV6PreferenceL2]	*integer*	internal preference of level2.

2.926.1.1.3 IsisInstanceSummarySpfModel

[spfCurrentHoldIntervalL1]	*integer*	Current SPF hold interval(ms) for Level1.
[spfCurrentHoldIntervalL2]	*integer*	Current SPF hold interval(ms) for Level2.
spfHoldInterval	*integer*	Spf Interval:Hold Interval(ms).
spfInitialWaitInterval	*integer*	Spf Interval:Initial wait(ms).
[spfLastRunL1]	*floating point number*	Last Level 1 SPF ran time.
[spfLastRunL2]	*floating point number*	Last Level 2 SPF ran time.
spfMaxWaitInterval	*integer*	Spf Interval:Max wait(ms).

2.927 show isis ti-lfa path [...]

vrfs	*table(string) = TilfaPathVrfModel* see 2.927.1	A mapping between a vrf and its TI-LFA paths.

2.927.1 TilfaPathVrfModel

[v4Info]	*TilfaPathAfModel* see 2.927.1.1	TI-LFA path information for IPv4 address family.
[v6Info]	*TilfaPathAfModel* see 2.927.1.1	TI-LFA path information for IPv6 address family.

2.927.1.1 TilfaPathAfModel

topologies	*table(numeric string) = TilfaPathTopoIdModel* see 2.927.1.1.1	A mapping of topology ID to all TI-LFA paths.

2.927.1.1.1 TilfaPathTopoIdModel

destinations	*table(string) = TilfaPathDestModel* see 2.927.1.1.1.1	A mapping of path systemIds to all TI-LFA paths for that destination.

2.927.1.1.1.1 TilfaPathDestModel

[hostname]	*string*	Hostname.
pathIds	*table(numeric string) = TilfaPathEntryModel* see 2.927.1.1.1.2	A mapping of an ID representing a constraint to the corresponding TI-LFA path.

2.927.1.1.1.2 TilfaPathEntryModel

constraint	*TilfaPathConstraintModel* see 2.776.1.1.1.4	Path constraint.
[details]	*TilfaPathDetails* see 2.776.1.1.1.8	Detailed path information.
[excludeNodeReachableVia-EcmpInterfaces] **	*list of Interface name*	List of Ecmp interfaces. **Since: 4.34.1
status	*enum: pathNotFound | pathNotComputed | cspfPending | explicitPathFailedValidation | pathFound*	Status of path computation.
sysIds	*list of SystemIdHostnameModel* see 2.927.1.1.1.3	Ordered list of system identifiers or hostname specifying the path to the destination.

2.927.1.1.1.3 SystemIdHostnameModel

[hostname]	*string*	Hostname.

sysId	*string*	System identifier.

2.928 show isis ti-lfa tunnel [...]

entries	*table(numeric string) = TilfaTunnelTableEntry* see 2.928.1	Tunnel table entries keyed by tunnel index.

2.928.1 TilfaTunnelTableEntry

backupVias	*list of MplsVia* see 2.193.1.4	List of tunnel backup vias.
tunnelId	*integer*	Tunnel identifier.
tunnelIndex	*integer*	Tunnel index within tunnel type.
tunnelType	*enum: BGP LU Forwarding | maxTunnelType | IP-in-IP | MLDP P2MP | invalidTunnel | VXLAN VTEP Encap | IS-IS SRv6 | Nexthop | Static MPLS | SR-TE Policy | SR-TE | OSPF SR | IS-IS SRv6 TI-LFA | IS-IS FlexAlgo | Static MPLS Multicast | Nexthop Group | TI-LFA | LDP | RSVP LER SUB | SRv6 SR-TE SL | RSVP P2MP | RSVP LER | EosSdk sBFD | UDP | SRv6 Transport | EVPN VXLAN | VXLAN | RSVP FRR | IS-IS Remote TI-LFA | BGP LU | RSVP | IS-IS SR | Static Interface*	Tunnel type.
vias	*list of MplsVia* see 2.193.1.4	List of tunnel vias.

2.929 show kernel interface addr [...]

vrfs	*table(string) = ShowKernelInterfaceAddrVrf* see 2.929.1	A mapping of VRF to its interfaces.

2.929.1 ShowKernelInterfaceAddrVrf

interfaces	*table(string) = ShowKernelInterfaceAddrDetails* see 2.929.1.1	A mapping of interface to its details.

2.929.1.1 ShowKernelInterfaceAddrDetails

[brd]	*string*	Broadcast address.
[extraDetails]	*table(string) = string*	A mapping of extra kernel details to their values.
flags	*string*	Interface flags.
[group]	*string*	Group associated with interface.
inet	*table(string) = ShowKernelInterfaceAddrInet* see 2.929.1.1.1	A mapping of IPv4 internet networking scope to its details.
inet6	*table(string) = ShowKernelInterfaceAddrInet* see 2.929.1.1.1	A mapping of IPv6 internet networking scope to its details.
[link]	*string*	Link address.
[linkNetnsid]	*integer*	Link network namespace id.
mtu	*integer*	Maximum transmission unit.
[qdisc]	*string*	Queuing discipline.
[qlen]	*integer*	Queue length.
[state]	*enum: lowerLayerDown | unknown | down | up | testing | notPresent | dormant*	Interface state.

2.929.1.1.1 ShowKernelInterfaceAddrInet

[addr]	*IP address*	Inet(6) address.
[brd]	*IP address*	Broadcast address.
preferredLft	*string*	Preferred lifetime.
validLft	*string*	Valid lifetime.

2.930 show kernel interface counters [...]

vrfs	*table(string) = ShowKernelInterfaceCountersVrf* see 2.930.1	A mapping of VRFs to interfaces.

2.930.1 ShowKernelInterfaceCountersVrf

interfaces	*table(string) = ShowKernelInterfaceCountersVrfDetails* see 2.930.1.1	A mapping of interfaces to interface details.

2.930.1.1 ShowKernelInterfaceCountersVrfDetails

[broadcast]	*IPv4 address*	Broadcast address.
[deviceInterrupt]	*integer*	Device interrupt number.
[ether]	*MAC address*	Ethernet(MAC) address.
flags	*string*	Flag information.
[inet]	*IPv4 address*	IPv4 internet networking.
[inet6]	*table(string) = ShowKernelInterfaceCountersInet6* see 2.930.1.1.1	A mapping of IPv6 internet networking to its details.
[loop]	*string*	Type of loop.
mtu	*integer*	Maximum transmission unit.
[netmask]	*IPv4 address*	Netmask mask.
rx	*ShowKernelInterfaceCountersRxTxDetails* see 2.930.1.1.2	Packets received details.
tx	*ShowKernelInterfaceCountersRxTxDetails* see 2.930.1.1.2	Packets transmitted details.
txqueuelen	*integer*	Transaction queue length.
[unspec]	*string*	Unspecified address.

2.930.1.1.1 ShowKernelInterfaceCountersInet6

address	*IPv6 address*	IPv6 address.
[prefixlen]	*integer*	Prefix length.
[scopeid]	*integer*	Scope ID.

2.930.1.1.2 ShowKernelInterfaceCountersRxTxDetails

[carrier]	*integer*	Number of carriers.
[collisions]	*integer*	Number of collisions.
dropped	*integer*	Number of frames dropped.
[misaligned]	*integer*	Number of misaligned frames.
numBytes	*integer*	Number of bytes.
numErrors	*integer*	Number of errors.
numPackets	*integer*	Number of packets.

`overruns`	*integer*	Number of overruns.

2.931 show kernel ip acl [...]

vrfs	*table(string) = ShowKernelIpAclVrf* see 2.931.1	A mapping of VRFs to its ACL.

2.931.1 ShowKernelIpAclVrf

chainAcls	*table(string) = ShowKernelIpAclChain* see 2.931.1.1	A mapping of ACLs to their details.

2.931.1.1 ShowKernelIpAclChain

[chainBytes]	*integer*	Number of bytes in ACL.
[chainPackets]	*integer*	Number of packets in ACL.
details	*list of ShowKernelIpAclDetails* see 2.931.1.1.1	A list of the ACLs details.
[policy]	*string*	Policy type.
[references]	*integer*	Number of references.

2.931.1.1.1 ShowKernelIpAclDetails

[aclExtraDetails]	*string*	ACL extra details.
destination	*AclDetailsInvertedIp-Address* see 2.931.1.1.1.1	Destination address.
inbound	*AclDetailsInvertedString* see 2.931.1.1.1.2	Inbound rule.
numBytes	*integer*	Number of bytes.
numPackets	*integer*	Number of packets.
opt	*AclDetailsInvertedString* see 2.931.1.1.1.2	Interface option.
outbound	*AclDetailsInvertedString* see 2.931.1.1.1.2	Outbound rule.
proto	*AclDetailsInvertedString* see 2.931.1.1.1.2	IP protocol.
source	*AclDetailsInvertedIp-Address* see 2.931.1.1.1.1	Source address.
target	*string*	Target value.

2.931.1.1.1.1 AclDetailsInvertedIpAddress

inverted	*boolean*	Attribute is inverted.
value	*IP address*	ACL details value.

2.931.1.1.1.2 AclDetailsInvertedString

inverted	*boolean*	Attribute is inverted.
value	*string*	ACL details value.

2.932 show kernel ip arp [...]

vrfs	*table(string) = ShowKernelIpArpVrf* see 2.932.1	A mapping of VRFs to its ARP tables.

2.932.1 ShowKernelIpArpVrf

arpAddresses	*table(IPv4 or IPv6 address) = ShowKernelIpArpDetails* see 2.932.1.1	A mapping of ARP addresses to their details.

2.932.1.1 ShowKernelIpArpDetails

dev	*string*	ARP device name.
[externallyLearned]	*boolean*	This entry was externally learned.
[lladdr]	*MAC address*	Link layer address.
[proxy]	*boolean*	This neighbor is being proxied.
[router]	*boolean*	This neighbor is a router.
state	*enum: delay | permanent | probe | none | stale | failed | incomplete | reachable | noArp*	State of neighbour entry.

2.933 show kernel ip counters [...]

vrfs	*table(string) = ShowKernelIpCountersVrfDetails* see 2.933.1	A mapping of VRFs to detail sections.

2.933.1 ShowKernelIpCountersVrfDetails

arista	*table(string) = integer*	A mapping of Arista details to Arista values.
[icmp]	*ShowKernelIpCountersIcmp* see 2.933.1.1	VRF ICMP infomation.
[icmp6]	*ShowKernelIpCountersIcmp* see 2.933.1.1	VRF ICMP6 information.
icmpMsg	*table(string) = integer*	A mapping of ICMPMsg details to IMCPMsg values.
[ip]	*table(string) = integer*	A mapping of IP details to IP values.
[ip6]	*table(string) = integer*	A mapping IP6 details to IP6 values.
ipExt	*table(string) = integer*	A mapping of IP extension details to IP extension values.
[sctp]	*table(string) = integer*	A mapping of SCTP details to SCTP values.
tcp	*table(string) = integer*	A mapping of TCP details to TCP values.
tcpExt	*table(string) = integer*	A mapping of TCP extension details to TCP extension values.
[udp]	*table(string) = integer*	A mapping of UDP details to UDP values.
[udp6]	*table(string) = integer*	A mapping of UDP6 details to UDP6 values.
[udpLite]	*table(string) = integer*	A mapping of UDPLite details to UDPLite values.
[udpLite6]	*table(string) = integer*	A mapping of UDPLite6 details to UDPLite6 values.

2.933.1.1 ShowKernelIpCountersIcmp

details	*table(string) = integer*	A mapping of ICMP(6) details to ICMP(6) values.
inputHistogram	*table(string) = integer*	A mapping of ICMP(6) input histogram details to input histogram values.
outputHistogram	*table(string) = integer*	A mapping of ICMP(6) output histogram details to output histogram values.

2.934 show kernel ip interface addr [...]

see 2.929

2.935 show kernel ip route [...]

vrfs	*table(string) = ShowKernelIpRouteVrf* see 2.935.1	A mapping of VRFs to their IP routes.

2.935.1 ShowKernelIpRouteVrf

routes	*table(IPv4 or IPv6 address) = ShowKernelIpRouteDetails* see 2.935.1.1	A mapping of IP routes to route details.

2.935.1.1 ShowKernelIpRouteDetails

[dead]	*boolean*	Route has dead flag.
[dev]	*string*	Device name.
[errorNum]	*integer*	Error number.
[linkdown]	*boolean*	Route has linkdown flag.
[metric]	*integer*	Metric value.
[notify]	*boolean*	Route has notify flag.
[offload]	*boolean*	Route has offload flag.
[onlink]	*boolean*	Route has onlink flag.
[pervasive]	*boolean*	Route has pervasive flag.
[pref]	*enum: medium | high | low*	Preference value.
[proto]	*string*	Protocol type.
[routeType]	*string*	Route type.
[scope]	*string*	Route scope.
[src]	*IP address*	Source address.
[unresolved]	*boolean*	Route has unresolved flag.
[via]	*IP address*	Next hop address.

2.936 show kernel ipsec [...]

[connections]	*table(string) = ShowKernelIpsecConnections* see 2.936.1	IPsec Connections.
[dataPath]	*table(string) = integer*	Details of /proc/net/xfrm_stat.
[listeningIpAddresses]	*list of IP address*	IPsec Listening IP Addresses.
[securityAssociations]	*table(string) = ShowKernelIpsecSecurityAssociations* see 2.936.2	IPsec Security Associations.
[strongSwan]	*ShowKernelIpsecStrongSwan* see 2.936.3	Details about IKE charon daemon.

2.936.1 ShowKernelIpsecConnections

summary	*list of string*	Details about a connection.

2.936.2 ShowKernelIpsecSecurityAssociations

[ikeSa]	*table(string) = ShowKernelIpsecIkeSa* see 2.936.2.1	Details about each security associations ikeSa's and related childSa's.

2.936.2.1 ShowKernelIpsecIkeSa

childSa	*table(string) = ShowKernelIpsecChildSa* see 2.936.2.1.1	ChildSa's relevant to this ikeSa.
summary	*list of string*	Details about an ikeSa.

2.936.2.1.1 ShowKernelIpsecChildSa

summary	*list of string*	Details about a childSa.

2.936.3 ShowKernelIpsecStrongSwan

architecture	*string*	Architecture running on.
linux	*string*	Linux kernel version.
malloc	*table(string) = integer*	Details of memory.
[plugins]	*list of string*	Plugins enabled.
startTime	*floating point number*	Start time in UTC.
uptime	*integer*	Uptime in seconds.
version	*string*	StrongSwan version number.
workerThreads	*ShowKernelIpsecWorkerThreads* see 2.936.3.1	Details of all worker threads.

2.936.3.1 ShowKernelIpsecWorkerThreads

idle	*integer*	Number of idle threads.
queue	*string*	Number of threads in the queue.
scheduled	*integer*	Number of scheduled threads.
total	*integer*	Total number of threads.
working	*string*	Number of working threads.

2.937 show kernel ipv6 acl [...]

see 2.931

2.938 show kernel ipv6 counters [...]

see 2.933

2.939 show kernel ipv6 interface addr [...]

see 2.929

2.940 show kernel ipv6 neighbors [...]

see 2.932

2.941 show kernel ipv6 route [...]

see 2.935

2.942 show kernel ports in-use [...]

vrfs	*table(string) = ShowKernelInUsePorts* see 2.942.1	Show all ports currently used.

2.942.1 ShowKernelInUsePorts

ports	*table(string) = ShowKernelInUsePortsDetails* see 2.942.1.1	Mapping of currently used ports and their details.

2.942.1.1 ShowKernelInUsePortsDetails

[peerAddr]	*IP address*	Remote address.
[peerPort]	*integer*	Remote port.
[processes]	*table(numeric string) = string*	Mapping of process IDs to their process names.
proto	*enum: tcp | udp*	Protocol type.
recvQ	*integer*	Bytes to receive.
sendQ	*integer*	Bytes to send.
state	*enum: finWait1 | synRecv | finWait2 | listen | closeWait | synSent | estab | timeWait | lastAck | closing | unconn*	Connection state.

2.943 show kernel software forwarding hardware offload config-sanity [...]

vrfs	*table(string) = Fwd0EthTypeConfigSanityEntries* see 2.943.1	A mapping of VRF to its forward devices.

2.943.1 Fwd0EthTypeConfigSanityEntries

forwardDevices	*table(string) = Fwd0EthTypeConfigSanityEntry* see 2.943.1.1	A mapping of forward device to its attributes.

2.943.1.1 Fwd0EthTypeConfigSanityEntry

[aclEnabledIntf]	*interface name*	ACL enabled routed interface.
protocols	*list of string*	The protocols that are enabled on this forwarding device.
[urpfEnabledIntf]	*interface name*	uRPF enabled routed interface.
vlanId	*integer*	Forwarding VLAN ID.

2.944 show kernel software forwarding hardware offload summary [...]

vrfs	*table(string) = Fwd0EthTypeEntries* see 2.944.1	A mapping of VRF to its forward devices.

2.944.1 Fwd0EthTypeEntries

forwardDevices	*table(string) = Fwd0EthTypeEntry* see 2.944.1.1	A mapping of forward device to its attributes.

2.944.1.1 Fwd0EthTypeEntry

Could also be an instance of:
Fwd0EthTypeConfigSanityEntry 2.943.1.1

protocols	*list of string*	The protocols that are enabled on this forwarding device.
vlanId	*integer*	Forwarding VLAN ID.

2.945 show kernelFib scheduler [...]

see 2.92

2.946 show l1 counters status [...]

status	*table(Interface name)* = *L1CounterStatus* see 2.946.1	A map of Ethernet interfaces counter statuses.

2.946.1 L1CounterStatus

rxInterface	*interface name*	The Rx counter destination interface of this Ethernet interface.
rxStatus	*L1CounterRxStatus* see 2.946.1.1	Rx Status information.
txInterface	*interface name*	The Tx counter source interface of the Ethernet interface.

2.946.1.1 L1CounterRxStatus

[rejectedReason]	*string*	The reason if the status is set to rejected.
rxStatus	*enum: multiDestinationBidirInterface* | *multiDestinationSwitchInterface* | *configured* | *noSource* | *rejected* | *singleDestination* | *multiDestinationLowestInterface*	Current status of the Rx counter interface.

2.947 show l1 destination [...]

revision 2

interfaces	*table(Interface name)* = *L1Destination* see 2.947.1	A mapping of source interface to a list of destination interfaces and connection type.
physicalInterfaces	*table(Interface name)* = *VirtualIntfs* see 2.947.3	A mapping of physical interface name to virtual interface name.
virtualInterfaces	*table(Interface name)* = *PhysicalIntfs* see 2.947.2	A mapping of virtual interface name to physical interface name.

2.947.1 L1Destination

[connectionType]	*enum: static | dynamic*	L1 Connection Type.
destinationInterfaces	*list of string*	A list of destination interfaces.

2.947.2 PhysicalIntfs

[rxPhysicalInterface]	*interface name*	Rx physical interface.
[txPhysicalInterface]	*interface name*	Tx physical interface.

2.947.3 VirtualIntfs

[rxVirtualInterfaces]	*list of Interface name*	A list of Rx virtual interfaces.
[txVirtualInterface]	*interface name*	Tx virtual Interface.

2.948 show l1 matrix [...]

revision 2

interfaces	*table(string) = L1MatrixEntry* see 2.948.1	A mapping of interface to its source and destinations.
physicalInterfaces **	*table(Interface name) = VirtualIntfs* see 2.947.3	A mapping of physical interface name to virtual interface name. **Since: 4.31.0
virtualInterfaces **	*table(Interface name) = PhysicalIntfs* see 2.947.2	A mapping of virtual interface name to physical interface name. **Since: 4.31.0

2.948.1 L1MatrixEntry

[description]	*string*	Interface description.
destinations	*list of string*	A list of destination interfaces.
[source]	*string*	Interface name.

2.949 show l1 modules profile configuration [...]

[builtin]	*table(string) = Enumeration* see 2.949.1	The builtin L1 module profiles installed on the system.

2.949.1 Enumeration

[applicableModules]	*list of string*	Applicable modules of L1 module profile.
description	*string*	The description of the L1 module profile.

2.950 show l1 modules profile status [...]

modules	*table(string) = Status* see 2.950.1	The L1 module profile configuration status for a particular module.

2.950.1 Status

[configured]	*string*	The configured L1 module profile.
[operational]	*string*	The operational L1 module profile.
status	*enum: applied | notInserted | pending | error*	The status of the L1 module profile configuration.

2.951 show l1 path [...]

revision 2

paths	*table(Interface name) = L1Source* see 2.951.1	A list of paths.
physicalInterfaces	*table(Interface name) = VirtualIntfs* see 2.947.3	A mapping of physical interface name to virtual interface name.
virtualInterfaces	*table(Interface name) = PhysicalIntfs* see 2.947.2	A mapping of virtual interface name to physical interface name.

2.951.1 L1Source

[connectionType]	*enum: static | dynamic*	L1 Connection Type.
[sourceInterface]	*string*	Interface Name.

2.952 show l1 port breakout status [...]

ports	*table(string) = PortBreakoutStatus* see 2.952.1	Map port to port breakout status.

2.952.1 PortBreakoutStatus

breakout	*enum: 4 | 2 | auto | 8 | 1*	Configured port breakout.
distribution	*enum: port | transceiver | auto*	Configured interface distribution rule.
interfaces	*list of Interface name*	Breakout interfaces.

2.953 show l1 port phy polarity [...]

ports	*table(string) = PhyPolaritySetting* see 2.953.1	A mapping of port to its lanes.

2.953.1 PhyPolaritySetting

lanes	*table(numeric string) = DirectionSetting* see 2.953.1.1	A mapping of lanes to direction.

2.953.1.1 DirectionSetting

direction	*table(string) = PolaritySetting* see 2.953.1.1.1	A mapping of direction to polarities.

2.953.1.1.1 PolaritySetting

configured	*enum: standard | default | reversed*	The configured value of polarity.
moduleDefault	*enum: standard | reversed*	The module default polarity.
operational	*enum: standard | reversed*	The operational value of polarity.

2.954 show l1 port status [...]

ports	*table(string) = L1PortStatus* see 2.954.1	Map port to port status.

2.954.1 L1PortStatus

[description]	*string*	Configured port description.
[interfaces]	*list of Interface name*	Interfaces within the port.
[mediaType]	*string*	Type of inserted media.
[portType]	*string*	Physical type of the port.

2.955 show l1 source [...]

revision 2

interfaces	*table(Interface name) = L1Source* see 2.951.1	A mapping of destination interface to source interface and connection type.
physicalInterfaces	*table(Interface name) = VirtualIntfs* see 2.947.3	A mapping of physical interface name to virtual interface name.
virtualInterfaces	*table(Interface name) = PhysicalIntfs* see 2.947.2	A mapping of virtual interface name to physical interface name.

2.956 show l1 source capabilities [...]

interfaces	*table(Interface name) = SourceableIntfs* see 2.956.1	A mapping of interface to sourceable interfaces.

2.956.1 SourceableIntfs

sources	*list of Interface name*	A list of sourceable interfaces.

2.957 show l2-protocol forwarding interfaces [...]

interfaces	*table(Interface name) = L2ProtocolForwarding-Interface* see 2.957.1	L2 protocol forwarding information for interfaces.

2.957.1 L2ProtocolForwardingInterface

profileName	*string*	Active L2 protocol forwarding profile.
[protocolInfo]	*list of L2ProtocolForwardingInfo* see 2.957.1.1	L2 protocol forwarding information.

2.957.1.1 L2ProtocolForwardingInfo

action	*enum: forward | forwardCpu | drop*	Action to be performed on protocol packets.
[address] **	*MAC address*	Protocol MAC address. **Since: 4.33.1
[protocol]	*enum: lldp | macsec | stp | isis | lacp | elmi | mbfd | pause | ptp*	L2 Protocol.
[tagFormat] **	*enum: tagged | all | untagged*	VLAN tag format. **Since: 4.21.3
[trafficType] **	*enum: l2PtTrafficTypeVxlanDecap | l2PtTrafficTypeAll | l2PtTrafficTypeInvalid*	L2PtTrafficType. **Since: 4.35.0

2.958 show l2-protocol forwarding profile [...]

profiles	*table(string) = L2Protocol-ForwardingProfile* see 2.958.1	A mapping of L2 protocol forwarding profile name to profile information.

2.958.1 L2ProtocolForwardingProfile

[protocolInfo]	*list of L2ProtocolForwardingInfo* see 2.957.1.1	L2 protocol forwarding information.

2.959 show l2-protocol forwarding profile summary [...]

profiles	*table(string) = L2Protocol-ForwardingProfileSummary* see 2.959.1	A mapping of L2 protocol forwarding profile name to interfaces on which it is active/configured.

2.959.1 L2ProtocolForwardingProfileSummary

[activeIntfs]	*list of Interface name*	Interfaces on which profile is active.
[configuredIntfs]	*list of Interface name*	Interfaces on which profile is configured.

2.960 show l2Rib (input SOURCE) [...]

hosts	*list of HostEntry* see 2.960.1	Host table entries.
invalidHosts	*list of HostEntry* see 2.960.1	Invalid host table entries.

2.960.1 HostEntry

Could also be an instance of:
HostEntryAndSource 2.960.2

dests	*list of L2RibObject* see 2.960.1.1	collection of destination objects.
entryType	*string*	Host entry type.
macAddress	*MAC address*	MAC Address.
pref	*integer*	Preference for the host entry.
seqNo	*integer*	Sequence number.
vlanId	*integer*	VLAN Id of MAC address.

2.960.1.1 L2RibObject

Could also be an instance of:
Dest 2.960.1.2
Label 2.960.1.3
LoadBalance 2.960.1.4

[index]	*integer*	Object table key.
level	*integer*	Level in the chain of objects.
spacePerLevel	*integer*	Number of spaces to indent per level.

2.960.1.2 Dest

[color] **	*integer*	Color of SR-TE policy tunnel. **Since: 4.24.1
destType	*enum: MPLS | VXLAN | Tunnel | Interface | CPU*	Destination type.
[domain] **	*enum: local | remote*	EVPN Domain. **Since: 4.31.1
[dropMode] **	*enum: srcAndDst | none | dst*	Drop mode. **Since: 4.33.0
[index]	*integer*	Object table key.
[interface]	*interface name*	Local interface.
level	*integer*	Level in the chain of objects.
[mplsLabel]	*integer*	MPLS Label.
spacePerLevel	*integer*	Number of spaces to indent per level.
[tunnelEndPoint] **	*IP address prefix*	IP prefix of the MPLS tunnel endpoint. **Since: 4.20.5
[tunnelId]	*TunnelId* see 2.193.1.2.6.4	Tunnel Identifier.
[vlanRange] **	*list of integer*	VLAN Range. **Since: 4.33.1

[vtepAddr]	*IpGenericAddr* see 2.365.1.1.1.1	IP address of VXLAN tunnel endpoint.
[vtepType] **	*enum: umrVtep* | *remoteDomainVtep* | *controlPlaneVtep* | *dataPlaneVtep*	VTEP type. **Since: 4.33.1

2.960.1.3 Label

[index]	*integer*	Object table key.
label	*integer*	MPLS Label.
level	*integer*	Level in the chain of objects.
spacePerLevel	*integer*	Number of spaces to indent per level.

2.960.1.4 LoadBalance

[index]	*integer*	Object table key.
level	*integer*	Level in the chain of objects.
num	*integer*	Number of load balance objects.
spacePerLevel	*integer*	Number of spaces to indent per level.

2.960.2 HostEntryAndSource

dests	*list of L2RibObject* see 2.960.1.1	collection of destination objects.
entryType	*string*	Host entry type.
macAddress	*MAC address*	MAC Address.
pref	*integer*	Preference for the host entry.
seqNo	*integer*	Sequence number.
source	*string*	host entry source.
vlanId	*integer*	VLAN Id of MAC address.

2.961 show l2Rib (input SOURCE) destination [...]

destSummaries	*list of DestsFromHostTable* see 2.961.1	Destination floodset summary collection.

2.961.1 DestsFromHostTable

[destType]	*enum: MPLS* | *VXLAN* | *Tunnel* | *Interface* | *CPU*	Filter by destination type.
dests	*list of Dest* see 2.960.1.2	Destination summary.
[source]	*string*	L2Rib Destination Flood Set table source.
tableName	*string*	L2Rib Destination Flood Set table name.

2.962 show l2Rib (input SOURCE) destination floodset [...]

destFloodSetSummaries	*list of DestFloodSetSummary* see 2.962.1	Destination floodset summary collection.

2.962.1 DestFloodSetSummary

[destType]	*enum: MPLS | VXLAN | Tunnel | Interface | CPU*	Filter by destination type.
dests	*list of Dest* see 2.960.1.2	Destination summary.
[source]	*string*	L2Rib Destination Flood Set table source.
tableName	*string*	L2Rib Destination Flood Set table name.

2.963 show l2Rib (input SOURCE) floodset [...]

floodSetSummaries	*list of FloodSetSummary* see 2.963.1	Vlan flood set summary collection.

2.963.1 FloodSetSummary

floodSets	*list of FloodSet* see 2.963.1.1	Vlan flood set summary.
[source]	*string*	L2Rib Flood Set table source.
tableName	*string*	L2Rib Flood Set table name.

2.963.1.1 FloodSet

dests	*list of Dest* see 2.960.1.2	Flood destination.
floodType	*enum: All | Any*	Flood type.
macAddr	*MAC address*	Flood set MAC address.
vlanId	*integer*	Vlan Id.

2.964 show l2Rib output [...]

see 2.960

2.965 show l2Rib output destination [...]

see 2.961

2.966 show l2Rib output destination floodset [...]

see 2.962

2.967 show l2Rib output floodset [...]

see 2.963

2.968 show l2Rib summary

tables	*list of TableSummary* see 2.968.1	Number of entries in each table.

2.968.1 TableSummary

hosts	*integer*	Number of hosts in table.
name	*string*	Table name.

2.969 show lacp aggregates [...]

[markerMessages]	*LacpMarkerMessages* see 2.969.1	LACP annotation markers and messages.
otherAggregates	*table(string) = PortChannelAggregate* see 2.969.2	Aggregates not bound to any port-channel.
portChannels	*table(Interface name) = PortChannelAggregate* see 2.969.2	Map port-channel to aggregate IDs and list of bundled ports.

2.969.1 LacpMarkerMessages

markerMessages	*list of LacpMarkerMessage* see 2.969.1.1	LACP annotation markers and messages.

2.969.1.1 LacpMarkerMessage

marker	*string*	LACP annotation marker.
msg	*string*	LACP annotation marker message.

2.969.2 PortChannelAggregate

[aggregateId]	*string*	Aggregate ID.
bundledPorts	*list of Interface name*	Ports in aggregate.
incompatiblePortsDetail	*table(string) = IncompatiblePorts* see 2.969.2.1	Ports aggregable, but in incompatible aggregate indexed by their aggregate ID.
[markers]	*LacpAnnotationMarkerSet* see 2.969.2.2	annotation brief marker.
negotiationPorts	*list of Interface name*	Ports still in negotiation.
otherPorts	*list of Interface name*	Ports that are selected and/or standby but not part of an aggregate.
standbyPorts	*list of Interface name*	Standby Ports.

2.969.2.1 IncompatiblePorts

[ports]	*list of Interface name*	Ports configured to be in port-channel, aggregable, but not in agg.

2.969.2.2 LacpAnnotationMarkerSet

markers	*list of string*	Set of LACP annotation markers.

2.970 show lacp counters [...]

[markerMessages]	*LacpMarkerMessages* see 2.969.1	LACP annotation markers and messages.
orphanPorts	*table(Interface name) = InterfaceLacpCounters* see 2.970.1	LACP counters for orphaned ports.
portChannels	*table(Interface name) = PortChannelLacpCounters* see 2.970.2	Map port-channel LACP traffic statistics.

2.970.1 InterfaceLacpCounters

actorPortStatus	*enum: unknown | bundled | noAgg | idle | standby | negotiation | unselected | mismatchAgg*	LACP port status.
[details]	*InterfaceLacpCounters-Details* see 2.970.1.1	Additional LACP counter information.
illegalRxCount	*integer*	Illegal Rx packet count.
lacpdusRxCount	*integer*	LACP PDUs Rx count.
lacpdusTxCount	*integer*	LACP PDUs Tx count.
markerResponseRxCount	*integer*	Marker response Rx count.
markerResponseTxCount	*integer*	Marker response Tx count.
markersRxCount	*integer*	Markers Rx count.
markersTxCount	*integer*	Markers Tx count.

2.970.1.1 InterfaceLacpCountersDetails

actorChangeCount	*integer*	Actor port change count.
actorChurnCount	*integer*	Actor port churn count.
actorSyncTransitionCount	*integer*	Actor port sync transition count.
lastRxTime	*floating point number*	UTC timestamp of when the actor last received LACP packet.
partnerChangeCount	*integer*	Partner port change count.
partnerChurnCount	*integer*	Partner port churn count.
partnerSyncTransitionCount	*integer*	Partner port sync transition count.

2.970.2 PortChannelLacpCounters

interfaces	*table(Interface name) = InterfaceLacpCounters* see 2.970.1	Map ports to traffic values.
[markers]	*LacpAnnotationMarkerSet* see 2.969.2.2	annotation brief marker.

2.971 show lacp interface [...]

[interface]	*interface name*	LACP information for this interface only.
[markerMessages]	*LacpMarkerMessages* see 2.969.1	LACP annotation markers and messages.
orphanPorts	*table(Interface name) = InterfaceLacp* see 2.971.1	LACP information for orphaned ports.
portChannels	*table(Interface name) = PortChannelLacp* see 2.971.2	Map port-channels to their LACP information.

2.971.1 InterfaceLacp

actorOperKey	*string*	LACP actor operational key.
actorPortId	*integer*	Actor port number.
actorPortPriority	*integer*	Actor port priority.
actorPortState	*LacpPortState* see 2.971.1.2	LACP actor port state.
actorPortStatus	*enum: unknown* | *bundled* | *noAgg* | *idle* | *standby* | *negotiation* | *unselected* | *mismatchAgg*	LACP port status.
[details]	*InterfaceLacpDetails* see 2.971.1.1	Additional LACP port information.
partnerOperKey	*string*	LACP partner operational key.
partnerPortId	*integer*	Partner port number.
partnerPortPriority	*integer*	Partner port priority.
partnerPortState	*LacpPortState* see 2.971.1.2	LACP partner port state.
partnerSysId	*string*	System Identifier.

2.971.1.1 InterfaceLacpDetails

actorAdminKey	*string*	Actor adminstrative key.
actorChurnState	*enum: churnDetected* | *churnMonitor* | *noChurn*	LACP port churn state.
actorLastRxTime	*floating point number*	UTC timestamp of when the actor last received LACP packet.
actorMuxReason	*string*	LACP actor mux reason.
actorMuxSmState	*enum: muxSmDisablingInProgress* | *muxSmCollecting* | *muxSmAttached* | *muxSmDistributing* | *muxSmCollectingDistributing* | *muxSmWaiting* | *muxSmDetached*	LACP MUX state machine state.

actorRxSmState	*enum: rxSmPortDisabled | rxSmLacpDisabled | rxSmInitialize | rxSmDefaulted | rxSmCurrent | rxSmExpired*	LACP Receive state machine state.
[actorTimeoutMultiplier] **	*integer*	LACP actor timeout multiplier. **Since: 4.25.1
aggSelectionState	*enum: selectedStateUnselected | selectedStateStandby | selectedStateSelected*	Interface aggregator selection state.
partnerChurnState	*enum: churnDetected | churnMonitor | noChurn*	LACP port churn state.
partnerCollectorMaxDelay	*integer*	Partner Collector max delay in tens of microseconds.

2.971.1.2 LacpPortState

activity	*boolean*	LACP active or passive.
aggregation	*boolean*	Link aggregateable or individual.
collecting	*boolean*	Collection of incoming frames enabled.
defaulted	*boolean*	Using defaulted operational partner information.
distributing	*boolean*	Distribution of outgoing frames enabled.
expired	*boolean*	Receive machine in expired state.
synchronization	*boolean*	Link in sync with the correct LAG.
timeout	*boolean*	LACP long (False) or short (True) timeout.

2.971.2 PortChannelLacp

interfaces	*table(Interface name) = InterfaceLacp* see 2.971.1	Map ports to port LACP information.
[markers]	*LacpAnnotationMarkerSet* see 2.969.2.2	annotation brief marker.

2.972 show lacp interface counters [...]

see 2.970

2.973 show lacp interface internal [...]

[markerMessages]	*LacpMarkerMessages* see 2.969.1	LACP annotation markers and messages.
[miscLacpSysIds]	*list of LacpSysIdBase* see 2.973.2	Misc System Id.
orphanPorts	*table(Interface name) = InterfaceLacpInternal* see 2.973.1	LACP internal information for orphaned ports.
portChannels	*table(Interface name) = PortChannelLacpInternal* see 2.973.4	Map channel to local LACP state.
[systemId]	*string*	LACP System-identifier.

2.973.1 InterfaceLacpInternal

actorOperKey	*string*	LACP actor operational key used to form aggregate.
actorPortId	*integer*	LACP actor port ID.
actorPortPriority	*integer*	LACP actor port priority.
actorPortState	*LacpPortState* see 2.971.1.2	LACP actor port state.
actorPortStatus	*enum: unknown | bundled | noAgg | idle | standby | negotiation | unselected | mismatchAgg*	LACP port status.
[details]	*InterfaceLacpInternal-Details* see 2.973.1.1	Detailed LACP port information.
partnerSystemId	*string*	LACP partner system identifier.

2.973.1.1 InterfaceLacpInternalDetails

actorAdminKey	*string*	LACP admin key.
actorChurnState	*enum: churnDetected | churnMonitor | noChurn*	LACP port churn state.
actorMuxReason	*string*	LACP actor mux reason.
actorMuxSmState	*enum: muxSmDisablingInProgress | muxSmCollecting | muxSmAttached | muxSmDistributing | mux-SmCollectingDistributing | muxSmWaiting | muxSmDetached*	LACP MUX state machine state.
actorRxSmState	*enum: rxSmPortDisabled | rxSmLacpDisabled | rxSmInitialize | rxSmDefaulted | rxSmCurrent | rxSmExpired*	LACP Receive state machine state.
[actorTimeoutMultiplier] **	*integer*	LACP actor timeout multiplier. **Since: 4.25.1

aggSelectionState	*enum: selectedStateUnselected | selectedStateStandby | selectedStateSelected*	Interface aggregator selection state.
[allowToWarmup]	*boolean*	Is interface allowed to warm up?
lastRxTime	*floating point number*	UTC timestamp of when the actor last received LACP packet.

2.973.2 LacpSysIdBase

Could also be an instance of:
MlagLacpSysId 2.973.3

2.973.3 MlagLacpSysId

priority	*integer*	System priority.
systemId	*string*	System Identifier.

2.973.4 PortChannelLacpInternal

interfaces	*table(Interface name) = InterfaceLacpInternal* see 2.973.1	Map ports to LACP protocol information.
[markers]	*LacpAnnotationMarkerSet* see 2.969.2.2	annotation brief marker.

2.974 show lacp interface peer [...]

[markerMessages]	*LacpMarkerMessages* see 2.969.1	LACP annotation markers and messages.
orphanPorts	*table(Interface name) = InterfaceLacpNeighbors* see 2.974.1	LACP neighbor information for orphaned ports.
portChannels	*table(Interface name) = PortChannelLacpNeighbors* see 2.974.2	Map the port-channels to their remote neighbor LACP protocol state.

2.974.1 InterfaceLacpNeighbors

actorPortStatus	*enum: unknown* | *bundled* | *noAgg* | *idle* | *standby* | *negotiation* | *unselected* | *mismatchAgg*	LACP port status.
[details]	*InterfaceLacpNeighbors-Details* see 2.974.1.1	Detailed LACP port neighbor information.
partnerOperKey	*string*	LACP partner operational key.
partnerPortId	*integer*	LACP partner port ID.
partnerPortPriority	*integer*	LACP partner port priority.
partnerPortState	*LacpPortState* see 2.971.1.2	LACP partner port state.
partnerSystemId	*string*	LACP partner system identifier.

2.974.1.1 InterfaceLacpNeighborsDetails

aggSelectionState	*enum: selectedStateUnselected* | *selectedStateStandby* | *selectedStateSelected*	Interface aggregator selection state.
collectorMaxDelay	*integer*	Collector max delay in tens of microseconds.
partnerChurnState	*enum: churnDetected* | *churnMonitor* | *noChurn*	LACP port churn state.

2.974.2 PortChannelLacpNeighbors

interfaces	*table(Interface name) = InterfaceLacpNeighbors* see 2.974.1	Map ports to LACP neighbor information.
[markers]	*LacpAnnotationMarkerSet* see 2.969.2.2	annotation brief marker.

2.975 show lacp internal [...]

see 2.973

2.976 show lacp internal events [...]

lacpInternalEventRecords	*list of LacpInternalEventRecord* see 2.976.1	LACP state transition events.

2.976.1 LacpInternalEventRecord

currentWhileTimerExpired	*boolean*	currentWhile timer has expired.
intfId	*interface name*	Port channel member interface name.
lacpEnabled	*boolean*	LACP is enabled.
lacpduRx	*boolean*	LACPDU is received.
partnerSync	*boolean*	Partner is synced.
portChannel	*interface name*	Port channel name.
portEnabled	*boolean*	Port is enabled.
portMoved	*boolean*	Port has moved.
reason	*string*	Reason for the port channel member state transition.
selected	*enum: selectedStateUnselected* | *selectedStateStandby* | *selectedStateSelected*	Selected state.
smName	*string*	rx or mux state machine.
state	*enum: rxSmPortDisabled* | *muxSmDisablingInProgress* | *muxSmCollecting* | *rxSmLacpDisabled* | *rxSmInitialize* | *muxSmAttached* | *muxSmDistributing* | *muxSmCollectingDistributing* | *rxSmDefaulted* | *rxSmCurrent* | *muxSmWaiting* | *rxSmExpired* | *muxSmDetached*	Port Channel member state.
timestamp	*floating point number*	UTC timestamp of the state transition.

2.977 show lacp peer [...]

see 2.974

2.978 show lacp sys-id [...]

[details]	*Details* see 2.978.1	LACP System-Id details.
miscLacpSysIds	*list of LacpSysIdBase* see 2.973.2	Misc System-Id.
systemId	*string*	System identifier.

2.978.1 Details

address	*string*	Switch MAC address.
priority	*integer*	System priority.

2.979 show led [...]

systemLeds	*table(string) = LedSetting* see 2.979.1	A mapping of system LED to its settings.

2.979.1 LedSetting

blue	*boolean*	Blue LED is on.
green	*boolean*	Green LED is on.
maxBright	*integer*	Maximum brightness (%).
minBright	*integer*	Minimum brightness (%).
period	*floating point number*	Flash period (seconds).
red	*boolean*	Red LED is on.
status	*enum: inactive | unknown | bad | good | beacon | warning | off*	LED status.
yellow	*boolean*	Yellow LED is on.

2.980 show led palette [...]

ledCapability	*table(string) = LedCapability* see 2.980.1	All LED capabilities; key is name of the LED.

2.980.1 LedCapability

lightSetting	*table(string) = LightSetting* see 2.980.1.1	All LedCapability LightSettings; key is name of the color.
name	*string*	The name of the LED (e.g. Ethernet1/1, Fan1/1, etc.).

2.980.1.1 LightSetting

color	*string*	The color of the LightSetting.
ledFlashRate	*floating point number*	Duration per flash (in seconds) of the LED.An LED flash-rate of 0.0 means no flash.

2.981 show led state [...]

leds	*table(string) = LedStateDict* see 2.981.1	All LEDs with their states, key is the name of the LED.

2.981.1 LedStateDict

name	*string*	The name of the LED.
state	*table(string) = LedState* see 2.981.1.1	All LED states; key is the name of the state.

2.981.1.1 LedState

available	*boolean*	Indicate whether the state is available for the hardware.
name	*string*	The name of the LED state (e.g. linkUpActivity400G, etc.).

2.982 show led theme

theme	*table(string) = LightSettingTheme* see 2.982.1	All themes created, the key is names of the themes.

2.982.1 LightSettingTheme

name	*string*	The name of the theme.
setting	*table(string) = LightSetting* see 2.980.1.1	All theme settings; the key is led state.

2.983 show led theme interface [...]

ledsTheme	*table(string) = string*	Mapping of which LEDs have which themes.
theme	*table(string) = LightSettingTheme* see 2.982.1	All themes created, the key is names of the themes.

2.984 show license [...]

customerName	*string*	Customer name.
deviceSerial	*string*	System Serial number.
domainName	*string*	Domain name.
features	*table(string) = FeatureModel* see 2.984.1	A mapping between feature name and its license information.
[platform] **	*string*	Platform model. **Since: 4.21.0
systemMac	*string*	System MAC address.

2.984.1 FeatureModel

[featureDescription]	*string*	Description of the feature.
licenses	*list of LicenseInstance* see 2.984.1.1	List of licenses for the feature.

2.984.1.1 LicenseInstance

count	*integer*	Number of licenses of this type.
endTime	*floating point number*	POSIX Timestamp of when license will expire.
[parameter]	*string*	Parameter associated with the license.
source **	*string*	Source. **Since: 4.24.0
startTime	*floating point number*	POSIX Timestamp of when license will become valid.

2.985 show license features

active	*list of string*	List of active licenses.
missing	*list of string*	List of missing licenses.

2.986 show license files [...]

licenseText	*table(string) = string*	A mapping between license file name and its contents.

2.987 show line system dom [...]

see 2.615

2.988 show line system eeprom [...]

interfaces	*table(string) = Interfaces-TransceiverEepromIntf* see 2.616.1	Mapping between port name and the EEPROM.

2.989 show line system idprom [...]

interfaces	*table(string) = Interfaces-TransceiverIdpromPages* see 2.532.1	Mapping between port name and the eeprom.

2.990 show line system status [...]

ports	*table(string) = InterfacesTransceiverStatusValues* see 2.990.1	Mapping between port name and transceiver status.

2.990.1 InterfacesTransceiverStatusValues

[adapters]	*InterfacesTransceiverStatuValuesSwizzlerList* see 2.990.1.1	Form factor adapter types in use.
[badEepromChecksums]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Number of bad Eeprom checksums.
[bandwidth] **	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Signal bandwidth of linear pluggable optics. **Since: 4.33.2
[cfp2Dco]	*InterfacesTransceiverStatusExtCfp2Dco* see 2.990.1.3	CFP2-DCO specific attributes.
[channels]	*table(numeric string) = InterfacesTransceiverStatusChannelSpecific* see 2.990.1.2	Channel specific attributes indexed by channel number.
[dataPathFirmwareFault]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Data path firmware fault.
[dataPathState]	*table(numeric string) = InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Data path state indexed by host lane number.
[domControlFail]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Number of DOM control/status failures.
[eepromReadTimeouts]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Number of Eeprom read timeouts.
[hostLanes]	*table(numeric string) = InterfacesTransceiverStatusHostLaneSpecific* see 2.990.1.4	Host lane specific attributes indexed by lane number.
[interfaces]	*table(string) = InterfacesTransceiverStatusInterfaceSpecific* see 2.990.1.5	Interface specific attributes indexed by interface name.
[interrupts]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Number of transceiver interrupts.
[managementMode] **	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Transceiver management mode. **Since: 4.34.0
[mdioFailures]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Number of transceiver management data input/output failures.

mediaType	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Transceiver media type.
[moduleFirmwareFault]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	Module firmware fault.
[moduleState]	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Module state.
[presence]	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Indication of transceiver presence.
[resets]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	Number of transceiver resets.
serialNumber	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	Transceiver serial number.
[smbusFailures]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	Number of transceiver system managements bus failures.
[spuriousDet]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	Number of spurious detections of the transceiver.
[tempHiAlarm]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	High temperature alarm.
[tempHiWarn]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	High temperature warn.
[tempLoAlarm]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	Low temperature alarm.
[tempLoWarn]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	Low temperature warn.
[voltageHiAlarm]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	High voltage alarm.
[voltageHiWarn]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	High voltage alarm.
[voltageLoAlarm]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	Low voltage alarm.
[voltageLoWarn]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	Low voltage alarm.

2.990.1.1 InterfacesTransceiverStatuValuesSwizzlerList

[changes]	*integer*	Changes since system boot.
[lastChange]	*floating point number*	Last update time in UTC.

state	*list of string*	List of adapters in use.

2.990.1.2 InterfacesTransceiverStatusChannelSpecific

[coherentAlarms]	*InterfacesTransceiverStatusCoherentChannelSpecific* see 2.990.1.2.1	Coherent media channel specific alarms.
[frequencyTuningAlarms]	*InterfacesTransceiverStatusFrequencyTuningChannelSpecific* see 2.990.1.2.2	Frequency tuning media channel specific CMIS alarms.
[rxCdrLol]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Receive clock and data recovery loss of lock.
[rxLos]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Receive loss of signal.
[rxPowerHiAlarm]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Receive high power alarm.
[rxPowerHiWarn]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Receive high power warning.
[rxPowerLoAlarm]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Receive low power alarm.
[rxPowerLoWarn]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Receive low power warning.
[txBiasHiAlarm]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Transmit high bias alarm.
[txBiasHiWarn]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Transmit high bias warning.
[txBiasLoAlarm]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Transmit low bias alarm.
[txBiasLoWarn]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Transmit low bias warning.
[txFault]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Transmit fault.
[txOutputSignalStats]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Transmit output signal status.
[txPowerHiAlarm]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Transmit high power alarm.

[txPowerHiWarn]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	Transmit high power warning.
[txPowerLoAlarm]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	Transmit low power alarm.
[txPowerLoWarn]	*InterfacesTransceiver-StatusValueFormat* see 2.990.1.2.3	Transmit low power warning.

2.990.1.2.1 InterfacesTransceiverStatusCoherentChannelSpecific

[fecDetectedDegrade]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Receive FEC detect degrade (indicates that BER exceeded the detected degrade threshold).
[fecDetectedDegradeEnabled]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Receive FEC detected degrade monitoring enabled.
[fecExcessiveDegrade]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Receive FEC excessive degrade (indicates that BER exceeded the excessive degrade threshold).
[fecExcessiveDegrade-Enabled]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Receive FEC excessive degrade monitoring enabled.
[rxChrDispCompensationLoss-OfLock]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Receive chromatic dispersion compensation loss of lock.
[rxDemodulationLossOfLock]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Receive demodulator loss of lock.
[rxDeskewLossOfLock]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Receive deskew loss of lock.
[rxFifoErr]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Receive FIFO error.
[rxLossOfAlignment]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Receive loss of alignment.
[rxOutOfAlignment]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Receive out of alignment.
[txCmuLossOfLock]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Transmit clock monitor unit clock loss of lock.
[txDeskewLossOfLock]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Transmit deskew clock loss of lock.
[txFifoErr]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Transmit FIFO error.

[txLossOfAlignment]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Transmit loss of alignment.
[txOutOfAlignment]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Transmit out of alignment.
[txRefClkLossOfLock]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Transmit reference clock loss of lock.

2.990.1.2.1.1 InterfacesTransceiverStatusValueFormatBool

[changes]	*integer*	Changes since system boot.
[lastChange]	*floating point number*	Last update time in UTC.
state	*boolean*	Current value.

2.990.1.2.2 InterfacesTransceiverStatusFrequencyTuningChannelSpecific

[invalidChannel]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Frequency tuning invalid channel (configured channel is outside the range for the selected grid spacing).
[tuningComplete]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Frequency tuning completed.
[tuningInProgress]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Frequency tuning in progress.
[tuningNotAccepted]	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	Frequency tuning busy.

2.990.1.2.3 InterfacesTransceiverStatusValueFormat

Could also be an instance of:
InterfacesTransceiverStatuValuesSwizzlerList 2.990.1.1
InterfacesTransceiverStatusIntfValueFormatEgressAlarmStatus 2.990.1.2.4
InterfacesTransceiverStatusIntfValueFormatIngressAlarmStatus 2.990.1.2.5
InterfacesTransceiverStatusValueFormatBool 2.990.1.2.1.1
InterfacesTransceiverStatusValueFormatFloat 2.990.1.2.6
InterfacesTransceiverStatusValueFormatHex 2.990.1.2.7
InterfacesTransceiverStatusValueFormatInt 2.990.1.2.8
InterfacesTransceiverStatusValueFormatLaneAlignment 2.990.1.2.9
InterfacesTransceiverStatusValueFormatModuleFaultStatus 2.990.1.2.10
InterfacesTransceiverStatusValueFormatModuleGeneralStatus 2.990.1.2.11
InterfacesTransceiverStatusValueFormatModuleStateDec 2.990.1.2.12
InterfacesTransceiverStatusValueFormatNetworkLaneFaultStatus 2.990.1.2.13
InterfacesTransceiverStatusValueFormatNetworkLaneRxOTNStatus 2.990.1.2.14
InterfacesTransceiverStatusValueFormatNetworkLaneVendorFAWS 2.990.1.2.15
InterfacesTransceiverStatusValueFormatRxTurnUpStateDec 2.990.1.2.16
InterfacesTransceiverStatusValueFormatScientificFloat 2.990.1.2.17
InterfacesTransceiverStatusValueFormatStr 2.990.1.2.4.1
InterfacesTransceiverStatusValueFormatTrib 2.990.1.2.18

InterfacesTransceiverStatusValueFormatTxModulatorBiasVOA 2.990.1.2.19
InterfacesTransceiverStatusValueFormatTxTurnUpStateDec 2.990.1.2.20
InterfacesTransceiverStatusValueFormatVendorSpecificFaultStatus 2.990.1.2.21

[changes]	*integer*	Changes since system boot.
[lastChange]	*floating point number*	Last update time in UTC.

2.990.1.2.4 InterfacesTransceiverStatusIntfValueFormatEgressAlarmStatus

alignmentMarkerLock	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	PCS alignment marker lock.
bipErrorsDetected	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	PCS BIP errors detected.
blockLock	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	PCS block lock.
[changes]	*integer*	Changes since system boot.
erroredBlocksDetected	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	PCS errored blocks detected.
highBer	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	PCS high BER.
[lastChange]	*floating point number*	Last update time in UTC.
loa	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	PCS loss of alignment.
[los]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	PCS loss of signal.
rxLocalFault	*InterfacesTransceiverStatusValueFormatBool* see 2.990.1.2.1.1	RX local fault.
rxRemoteFault	*InterfacesTransceiverStatusValueFormatBool* see 2.990.1.2.1.1	RX remote fault.

2.990.1.2.4.1 InterfacesTransceiverStatusValueFormatStr

[changes]	*integer*	Changes since system boot.
[lastChange]	*floating point number*	Last update time in UTC.
state	*string*	Current value.

2.990.1.2.5 InterfacesTransceiverStatusIntfValueFormatIngressAlarmStatus

alignmentMarkerLock	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	PCS alignment marker lock.

bipErrorsDetected	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	PCS BIP errors detected.
blockLock	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	PCS block lock.
[changes]	*integer*	Changes since system boot.
erroredBlocksDetected	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	PCS errored blocks detected.
[lastChange]	*floating point number*	Last update time in UTC.
loa	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	PCS loss of alignment.
[los]	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	PCS loss of signal.
rxLocalFault	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	RX local fault.
rxRemoteFault	*InterfacesTransceiver-StatusValueFormatBool* see 2.990.1.2.1.1	RX remote fault.

2.990.1.2.6 InterfacesTransceiverStatusValueFormatFloat

[changes]	*integer*	Changes since system boot.
[lastChange]	*floating point number*	Last update time in UTC.
state	*floating point number*	Current value.

2.990.1.2.7 InterfacesTransceiverStatusValueFormatHex

[changes]	*integer*	Changes since system boot.
[lastChange]	*floating point number*	Last update time in UTC.
state	*integer*	Current value.

2.990.1.2.8 InterfacesTransceiverStatusValueFormatInt

[changes]	*integer*	Changes since system boot.
[lastChange]	*floating point number*	Last update time in UTC.
state	*integer*	Current value.

2.990.1.2.9 InterfacesTransceiverStatusValueFormatLaneAlignment

[changes]	*integer*	Changes since system boot.
[lastChange]	*floating point number*	Last update time in UTC.
modemLockFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	RX alignment modem lock fault.

modemSyncDetectFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX alignment modem sync detect fault.
netLaneTxAlignment	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Network lane TX alignment.

2.990.1.2.10 InterfacesTransceiverStatusValueFormatModuleFaultStatus

[changes]	*integer*	Changes since system boot.
checkSum	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Module fault status checksum.
[lastChange]	*floating point number*	Last update time in UTC.
modOverTempFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Module fault status module over temperature fault.
modSpecFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Module fault status module specific hw fault.
pldFlashInitFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Module fault status pld flash init fault.
powerSupplyFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Module fault status power supply fault.

2.990.1.2.11 InterfacesTransceiverStatusValueFormatModuleGeneralStatus

[changes]	*integer*	Changes since system boot.
hiPowerOn	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Module general status high power on.
hwInterlock	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Module general status hw interlock.
[lastChange]	*floating point number*	Last update time in UTC.
outOfAlgn	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Module general status out of alignment.
[pmIntervalDone]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Module general status PM interval done.
rxLOS	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Module general status RX loss of signal.
rxNetworkLOL	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Module general status RX network loss of lock.
txHostLOL	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Module general status TX host loss of lock.

txLOF	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Module general status TX loss of signal functionality.

2.990.1.2.12 InterfacesTransceiverStatusValueFormatModuleStateDec

[changes]	*integer*	Changes since system boot.
fault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Module state fault.
hiPwrDown	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Module state high power down.
hiPwrUp	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Module state high power up.
init	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Module state initialization.
[lastChange]	*floating point number*	Last update time in UTC.
lowPwr	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Module state low power.
ready	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Module state ready.
txOff	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Module state TX off.
txTurnOff	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Module state TX turn off.
txTurnOn	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Module state TX turn on.

2.990.1.2.13 InterfacesTransceiverStatusValueFormatNetworkLaneFaultStatus

[changes]	*integer*	Changes since system boot.
[lastChange]	*floating point number*	Last update time in UTC.
rxFIFOFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	RX FIFO fault.
rxLOL	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	RX LOL.
rxLOS	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	RX LOS.
rxTECFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	RX TEC fault.

tecFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	TEC fault.
txLOL	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	TX LOL.
txLOSF	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	TX LOSF.
wavelengthUnlockFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Wavelength unlock fault.

2.990.1.2.14 InterfacesTransceiverStatusValueFormatNetworkLaneRxOTNStatus

[changes]	*integer*	Changes since system boot.
fastPMRxSignalDegradeAlarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Fast PM RX signal degrade alarm.
fastPMRxSignalFailAlarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Fast PM RX signal fail alarm.
fastPMTxSignalDegradeAlarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Fast PM TX signal degrade alarm.
fastPMTxSignalFailAlarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Fast PM TX signal fail alarm.
ingressFDDAlarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Ingress FDD alarm.
ingressFEDAlarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Ingress FED alarm.
[lastChange]	*floating point number*	Last update time in UTC.
lossOfFrame	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Loss of frame.
lossOfMultiframe	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Loss of multiframe.
oduAISMaintSignal	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	ODU AIS maintenance signal.
oduLCKMaintSignal	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	ODU LCK maintenance signal.
outOfFrame	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Out of frame.
outOfMultiframe	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Out of multiframe.

sectionMonitoringBackDefect	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Section monitoring back defect.

2.990.1.2.15 InterfacesTransceiverStatusValueFormatNetworkLaneVendorFAWS

adcOutputLow	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	ADC output low.
[changes]	*integer*	Changes since system boot.
[lastChange]	*floating point number*	Last update time in UTC.
modBiasConvergeFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Modulator bias converge fault.
oaPumpBiasHighAlarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	OA pump bias high alarm.
oaPumpBiasHighWarn	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	OA pump bias high warn.
oaPumpBiasLowAlarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	OA pump bias low alarm.
oaPumpBiasLowWarn	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	OA pump bias low warn.
rxPhaseCtrlLoopHighAlarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	RX phase control loop high alarm.
rxPhaseCtrlLoopHighWarn	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	RX phase control loop high warn.
rxPhaseCtrlLoopLowAlarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	RX phase control loop low alarm.
rxPhaseCtrlLoopLowWarn	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	RX phase control loop low warn.
rxTunedChannelPwrHighAlarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	RX tuned channel power high alarm.
rxTunedChannelPwrHighWarn	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	RX tuned channel power high warn.
rxTunedChannelPwrLowAlarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	RX tuned channel power low alarm.
rxTunedChannelPwrLowWarn	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	RX tuned channel power low warn.
txModBiasVOAHighAlarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	TX mod bias VOA control loop high alarm.

txModBiasVOAHighWarn	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX mod bias VOA control loop high warn.

2.990.1.2.16 InterfacesTransceiverStatusValueFormatRxTurnUpStateDec

adcOutput	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX turn up state ADC output.
[changes]	*integer*	Changes since system boot.
dispersionLock	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX turn up state dispersion lock.
[lastChange]	*floating point number*	Last update time in UTC.
rxDemodLock	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX turn up state demodulator lock.
rxInit	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX turn up state path initialization.
rxLoLaserReady	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX turn up state RX LO laser ready.
rxWaitForInput	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX turn up state wait for signal input.

2.990.1.2.17 InterfacesTransceiverStatusValueFormatScientificFloat

[changes]	*integer*	Changes since system boot.
[lastChange]	*floating point number*	Last update time in UTC.
state	*floating point number*	Current value.

2.990.1.2.18 InterfacesTransceiverStatusValueFormatTrib

[changes]	*integer*	Changes since system boot.
[lastChange]	*floating point number*	Last update time in UTC.
state	*integer*	Current value.

2.990.1.2.19 InterfacesTransceiverStatusValueFormatTxModulatorBiasVOA

[changes]	*integer*	Changes since system boot.
[lastChange]	*floating point number*	Last update time in UTC.
loop1Alarm	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 1 alarm.
loop1Warn	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 1 warn.

loop2Alarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 2 alarm.
loop2Warn	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 2 warn.
loop3Alarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 3 alarm.
loop3Warn	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 3 warn.
loop4Alarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 4 alarm.
loop4Warn	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 4 warn.
loop5Alarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 5 alarm.
loop5Warn	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 5 warn.
loop6Alarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 6 alarm.
loop6Warn	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 6 warn.
loop7Alarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 7 alarm.
loop7Warn	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 7 warn.
loop8Alarm	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 8 alarm.
loop8Warn	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Net mod bias VOA loop 8 warn.

2.990.1.2.20 InterfacesTransceiverStatusValueFormatTxTurnUpStateDec

[changes]	*integer*	Changes since system boot.
[lastChange]	*floating point number*	Last update time in UTC.
txDataPathLock	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	TX turn up state data path lock.
txInit	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	TX turn up state path initialization.

txLasReadyOff	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX turn up state TX laser ready off.
txLaserReady	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX turn up state TX laser ready.
txModulatorConverge	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX turn up state TX modulator converge.
txOutPwrAdj	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX turn up state TX output power adjustment.

2.990.1.2.21 InterfacesTransceiverStatusValueFormatVendorSpecificFaultStatus

adcCalibrationFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	ADC calibration fault.
apexRWFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	APEX RW fault.
bootEepromCRCFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Boot EEPROM CRC fault.
[changes]	*integer*	Changes since system boot.
cpldDevRWFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	CPLD device RW fault.
cryptoDevRWFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Crypto device RW fault.
ctrlProcImgABBootFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Controller proc image AB boot fault.
ctrlProcIntCommFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Controller proc internal comm fault.
dacCalibrationFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	DAC calibration fault.
dacRefClockRWFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	DAC reference clock RW fault.
devInitFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Device initialization fault.
fwHwMismatchFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	FW HW mismatch fault.
[lastChange]	*floating point number*	Last update time in UTC.
modemProcIntCommFault	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Modem proc internal comm fault.

opticsProcIntCommFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Optics proc internal comm fault.
picDriverRWFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	PIC driver RW fault.
picEepromCRCFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	PIC EEPROM CRC fault.
picEepromRWFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	PIC EEPROM RW fault.
picXTiaRWFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	PIC X TIA RW fault.
picYTiaRWFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	PIC Y TIA RW fault.
powerSupplyRWFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Power supply RW fault.
rxITLAFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	RX ITLA fault.
txITLAFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	TX ITLA fault.
viMonitorDevRWFault	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	VI monitor device RW fault.

2.990.1.3 InterfacesTransceiverStatusExtCfp2Dco

[adcFaultCode]	*InterfacesTransceiver-StatusValueFormatHex* see 2.990.1.2.7	ADC fault code.
controllerState	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Controller state.
controllerSubState	*InterfacesTransceiver-StatusValueFormatStr* see 2.990.1.2.4.1	Controller substate.
[dacFaultCode]	*InterfacesTransceiver-StatusValueFormatHex* see 2.990.1.2.7	DAC fault code.
[laneAlignment]	*InterfacesTransceiver-StatusValueFormatLane-Alignment* see 2.990.1.2.9	TX/RX alignment.
laserFaultCode	*InterfacesTransceiver-StatusValueFormatHex* see 2.990.1.2.7	Laser fault code.

[modulatorBiasFaultCode]	*InterfacesTransceiverStatusValueFormatHex* see 2.990.1.2.7	Modulator bias fault code.
[modulatorConvergenceIter]	*InterfacesTransceiverStatusValueFormatInt* see 2.990.1.2.8	Modulator convergence iteration count.
[modulatorConvergenceStep]	*InterfacesTransceiverStatusValueFormatInt* see 2.990.1.2.8	Modulator convergence step.
[moduleFaultStatus]	*InterfacesTransceiverStatusValueFormatModuleFaultStatus* see 2.990.1.2.10	Module fault status for cfp2Dco Dp04 module.
[moduleFaults]	*InterfacesTransceiverStatusValueFormatHex* see 2.990.1.2.7	Module fault status.
[moduleGeneral]	*InterfacesTransceiverStatusValueFormatHex* see 2.990.1.2.7	Module general status.
[moduleGeneralStatus]	*InterfacesTransceiverStatusValueFormatModuleGeneralStatus* see 2.990.1.2.11	Module general status for cfp2Dco Dp04 module.
[moduleState]	*InterfacesTransceiverStatusValueFormatHex* see 2.990.1.2.7	Module state.
[moduleStateDec]	*InterfacesTransceiverStatusValueFormatModuleStateDec* see 2.990.1.2.12	Module state deciphered for cfp2Dco Dp04 module.
[netLaneFaultStatus]	*InterfacesTransceiverStatusValueFormatNetworkLaneFaultStatus* see 2.990.1.2.13	Network lane fault/status.
[netLaneVendorSpecificFAWS]	*InterfacesTransceiverStatusValueFormatNetworkLaneVendorFAWS* see 2.990.1.2.15	Network lane vendor specific fault/status.
[networkLaneRxOTNStatus]	*InterfacesTransceiverStatusValueFormatNetworkLaneRxOTNStatus* see 2.990.1.2.14	Network lane RX OTN status.
[networkTxModulatorBiasVoaAWS]	*InterfacesTransceiverStatusValueFormatTxModulatorBiasVOA* see 2.990.1.2.19	Network TX modulator bias VOA AWS.
[networkVendorFaults]	*InterfacesTransceiverStatusValueFormatHex* see 2.990.1.2.7	Network vendor-specific faults/status.
[rxLaserFaultCode]	*InterfacesTransceiverStatusValueFormatHex* see 2.990.1.2.7	RX laser fault code.

[rxLaserPowerHighAlarm]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX laser power high alarm.
[rxLaserPowerHighWarn]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX laser power high warn.
[rxLaserPowerLowAlarm]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX laser power low alarm.
[rxLaserPowerLowWarn]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX laser power low warn.
[rxLaserTempHighAlarm]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX laser temperature high alarm.
[rxLaserTempHighWarn]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX laser temperature high warn.
[rxLaserTempLowAlarm]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX laser temperature low alarm.
[rxLaserTempLowWarn]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX laser temperature low warn.
[rxPowerHighAlarm]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX total power high alarm.
[rxPowerHighWarn]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX total power high warn.
[rxPowerLowAlarm]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX total power low alarm.
[rxPowerLowWarn]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	RX total power low warn.
[rxTurnUpState]	*InterfacesTransceiverStatusValueFormatHex* see 2.990.1.2.7	RX turn-up state.
[rxTurnUpStateDec]	*InterfacesTransceiverStatusValueFormatRxTurnUpStateDec* see 2.990.1.2.16	RX turn up state deciphered for cfp2Dco Dp04 module.
[sopFastTracking]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	State of Polarization (SOP) fast tracking.
[txLaserPowerHighAlarm]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX laser power high alarm.
[txLaserPowerHighWarn]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX laser power high warn.

[txLaserPowerLowAlarm]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX laser power low alarm.
[txLaserPowerLowWarn]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX laser power low warn.
[txLaserTempHighAlarm]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX laser temperature high alarm.
[txLaserTempHighWarn]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX laser temperature high warn.
[txLaserTempLowAlarm]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX laser temperature low alarm.
[txLaserTempLowWarn]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX laser temperature low warn.
[txModBiasHighAlarm]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX modulator bias high alarm.
[txModBiasHighWarn]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX modulator bias high warn.
[txModBiasLowAlarm]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX modulator bias low alarm.
[txModBiasLowWarn]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	TX modulator bias low warn.
[txTurnUpState]	*InterfacesTransceiverStatusValueFormatHex* see 2.990.1.2.7	TX turn-up state.
[txTurnUpStateDec]	*InterfacesTransceiverStatusValueFormatTxTurnUpStateDec* see 2.990.1.2.20	TX turn up state deciphered for cfp2Dco Dp04 module.
[vendorFaults]	*InterfacesTransceiverStatusValueFormatHex* see 2.990.1.2.7	Vendor specific faults/status.
[vendorSpecificFaultStatus]	*InterfacesTransceiverStatusValueFormatVendorSpecificFaultStatus* see 2.990.1.2.21	Vendor specific fault status.

2.990.1.4 InterfacesTransceiverStatusHostLaneSpecific

[errFramesCurHost]	*InterfacesTransceiverStatusValueFormatScientificFloat* see 2.990.1.2.17	Current value of host-side post-FEC errored frames ratio.
[preFecBERCurrHost]	*InterfacesTransceiverStatusValueFormatScientificFloat* see 2.990.1.2.17	Current value of host-side pre-FEC bit error rate.
[rxOutputSignalStats]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Receive output signal status.
[txAdaptiveInputEqFault]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Transmit adaptive input equalization fault.
[txCdrLol]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Transmit clock and data recovery loss of lock.
[txLos]	*InterfacesTransceiverStatusValueFormat* see 2.990.1.2.3	Transmit loss of signal.

2.990.1.5 InterfacesTransceiverStatusInterfaceSpecific

[cfp2Dco]	*InterfacesTransceiverStatusExtCfp2DcoIntf* see 2.990.1.5.1	CFP2-DCO specific attributes.
[channels]	*table(numeric string) = InterfacesTransceiverStatusChannelSpecific* see 2.990.1.2	Channel specific attributes indexed by channel number.
[hostLanes]	*table(numeric string) = InterfacesTransceiverStatusHostLaneSpecific* see 2.990.1.4	Host lane specific attributes indexed by lane number.
[interface]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Interface name.
[operSpeed]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Operational speed of the interface.

2.990.1.5.1 InterfacesTransceiverStatusExtCfp2DcoIntf

[egressAlarmStatus]	*InterfacesTransceiverStatusIntfValueFormatEgressAlarmStatus* see 2.990.1.2.4	Client egress alarms/status.
[fec]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Client forward error correction type.

[fecUncorrectedBlocks]	*InterfacesTransceiverStatusValueFormatInt* see 2.990.1.2.8	Client FEC uncorrected blocks.
[ingressAlarmStatus]	*InterfacesTransceiverStatusIntfValueFormatIngressAlarmStatus* see 2.990.1.2.5	Client ingress alarms/status.
[laneCount]	*InterfacesTransceiverStatusValueFormatInt* see 2.990.1.2.8	Client speed PMD lane count.
[pcsAlarmStatus]	*InterfacesTransceiverStatusValueFormatHex* see 2.990.1.2.7	Client physical coding sublayer alarm status.
[preFecBer]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Client pre-FEC bit error rate.
[rsFecCodewordSize]	*InterfacesTransceiverStatusValueFormatInt* see 2.990.1.2.8	Client Reed-Solomon FEC codeword size.
[speed]	*InterfacesTransceiverStatusValueFormatStr* see 2.990.1.2.4.1	Client operational speed.
[tributary]	*InterfacesTransceiverStatusValueFormatTrib* see 2.990.1.2.18	Optical tributary.

2.991 show lldp [...]

enabledTlvTypes	*list of TlvType* see 2.991.2	Enabled optional TLVs.
lldpInterfaces	*table(Interface name) = LldpInterface* see 2.991.1	Lldp enabled Interfaces.
[managementAddressTransmitted]	*string*	Management Address used in the TLV.
managementAddressVrf	*string*	LLDP Management Address VRF.
messageTxHoldTime	*integer*	The holdtime in seconds inserted in the transmitted LLDP frames.
messageTxInterval	*integer*	The interval in seconds at which LLDP frames are transmitted.
reinitDelay	*integer*	The delay in seconds before LLDP reinitialization is attempted.

2.991.1 LldpInterface

rxEnabled	*boolean*	Indicates whether LLDP frames can be received on this interface.
txEnabled	*boolean*	Indicates whether LLDP frames can be sent from this interface.

2.991.2 TlvType

tlvType	*enum: linkAggregation8021 | medLocationIdentification | medCapabilities | systemName | linkAggregation8023 | maxFrameSize | powerViaMdi | portVlan | serialNumber | medNetworkPolicy | systemCapabilities | portVlanName | portDescription | managementAddress | systemDescription*	portDescription – Port Description TLV, systemName – System Name TLV, systemDescription – System Description TLV, systemCapabilities – System Capabilities TLV, managementAddress – Management Address TLV, portVlan – IEEE802.1 Port VLAN ID TLV, portVlanName – IEEE802.1 Port VLAN Name TLV, linkAggregation8021 – IEEE802.1 Link Aggregation TLV, linkAggregation8023 – IEEE802.3 Link Aggregation TLV, maxFrameSize – IEEE802.3 Maximum Frame Size TLV, powerViaMdi – IEEE802.3 Power Via MDI TLV, medCapabilities – LLDP-MED Capabilities TLV, medNetworkPolicy – LLDP-MED Network Policy TLV, medLocationIdentification – LLDP-MED Location Identification TLV, serialNumber – LLDP-MED Serial Number TLV,.

2.992 show lldp counters [...]

interfaces	*table(string) = LldpInterfaceTraffic* see 2.992.1	Lldp Interface Counters.

2.992.1 LldpInterfaceTraffic

rxDiscards	*integer*	The number of LLDP frames received and then discarded.
rxErrors	*integer*	The number of LLDP frames received with one or more detectable errors.
rxFrames	*integer*	The number of LLDP frames received.
tlvsDiscarded	*integer*	The number of LLDP TLVs discarded.
tlvsUnknown	*integer*	The number of LLDP TLVs received on this port that are not recognized.
txFrames	*integer*	The number of LLDP frames transmitted.
txFramesLengthExceeded	*integer*	The number of LLDP frames transmitted on this port that could not hold all the desired information.

2.993 show lldp local-info [...]

chassisId	*string*	Chassis identifier string.
chassisIdType	*enum: unknown* | *local* | *macAddress* | *chassisComponent* | *reserved* | *networkAddress* | *interfaceAlias* | *portComponent* | *interfaceName*	Type of the chassis.
localInterfaceInfo	*table(Interface name) = LocalInterfaceInfo* see 2.993.1	A mapping between local interface and local Interface information such as interface id, description, sent TLVs etc.
managementAddresses	*list of ManagementAddr* see 2.993.2	A list of management addresses ordered by priority.
[systemCapabilities]	*SystemCapabilities* see 2.993.3	Supported system capabilities and information about whether they are enabled.
[systemDescription]	*string*	System description.
[systemName]	*string*	System name.

2.993.1 LocalInterfaceInfo

[autoclassCompleted] **	*boolean*	PSE has concluded the Autoclass measurement. **Since: 4.23.0
[autoclassRequest] **	*boolean*	PD has requested an Autoclass measurement by the PSE. **Since: 4.23.0
[controlAbility] **	*boolean*	Indicates whether the pair selection can be controlled on neighbor interface. **Since: 4.21.3
[dualSignaturePowerClass-ExtModeA] **	*enum: powerClass1* | *powerClass3* | *singleSignaturePd* | *powerClass2* | *powerClass4* | *powerClass5* | *twoPairOnlyPse*	Power class on Mode A. **Since: 4.23.0
[dualSignaturePowerClass-ExtModeB] **	*enum: powerClass1* | *powerClass3* | *singleSignaturePd* | *powerClass2* | *powerClass4* | *powerClass5* | *twoPairOnlyPse*	Power class on Mode B. **Since: 4.23.0
[interfaceDescription]	*string*	Description of local/neighbor interface.
interfaceId	*string*	Name of local/neighbor interface(may contain escaped quotation marks).
interfaceIdType	*enum: unknown* | *local* | *macAddress* | *reserved* | *networkAddress* | *interfaceAlias* | *agentCircuitId* | *portComponent* | *interfaceName*	Type of local/neighbor interface.

interfaceId_v2 **	*string*	Name of local/neighbor interface. **Since: 4.24.2
[linkAggregation8021-InterfaceId] **	*integer*	Link Aggregation 802.1 interface identifier. **Since: 4.29.2
[linkAggregation8021Status] **	*enum: capableAndEnabled* | *notCapable* | *capableAndDisabled*	Link Aggregation 802.1 Status. **Since: 4.29.2
[linkAggregation8023-InterfaceId] **	*integer*	Link Aggregation 802.3 interface identifier. **Since: 4.29.2
[linkAggregation8023Status] **	*enum: capableAndEnabled* | *notCapable* | *capableAndDisabled*	Link Aggregation 802.3 Status. **Since: 4.29.2
[maxFrameSize]	*integer*	Indicates the maximum supported frame size in octets on the given interface.
[medInfo] **	*LldpMedInfo* see 2.993.1.1	LLDP-MED Info. **Since: 4.21.3
[pd4Pid] **	*boolean*	The PD supports powering of both Modes simultaneously. **Since: 4.23.0
[pdLoad] **	*boolean*	PD is dual-signature and power demand on Mode A and Mode B are electrically isolated. **Since: 4.23.0
[pdPoweredStatus] **	*enum: poweredSingleSignature* | *fourPairPoweringDual-Signature* | *twoPairPoweringDual-Signature*	Existing powered configuration of the PD. **Since: 4.23.0
[pdRequestedPowerValue] **	*floating point number*	Power requested by device in watts. **Since: 4.21.3
[pdRequestedPowerValueMode-A] **	*floating point number*	Maximum input power (in watts) the PD is requesting for the A Mode. **Since: 4.23.0
[pdRequestedPowerValueMode-B] **	*floating point number*	Maximum input power (in watts) the PD is requesting for the B Mode. **Since: 4.23.0
[portClass] **	*enum: pClassPSE* | *unknown* | *pClassPD*	Port class of neighbor interface. **Since: 4.21.3
[portVlanId]	*integer*	Port VLAN ID.
[powerClass] **	*integer*	Power classification of neighbor interface. **Since: 4.21.3
[powerClassExt] **	*enum: powerClassExt4* | *powerClassExt2* | *dualSignaturePd* | *powerClassExt6* | *powerClassExt5* | *powerClassExt7* | *powerClassExt3* | *powerClassExt1* | *powerClassExt8*	Power class ext. **Since: 4.23.0

[powerDownRequest] **	*boolean*	PD has requested a power down. **Since: 4.23.0
[powerDownTime] **	*integer*	Time in seconds the PD requests to be unpowered. Zero means to remain unpowered indefinitely. **Since: 4.23.0
[powerOverEthernetEnabled] **	*boolean*	Indicates whether MDI power is enabled on neighbor interface. **Since: 4.21.3
[powerOverEthernet-Supported] **	*boolean*	Indicates whether MDI power is supported on neighbor interface. **Since: 4.21.3
[powerPairs] **	*enum: spare* | *signal* | *unknown*	PSE power pairs on use on neighbor interface. **Since: 4.21.3
[powerPriority] **	*enum: critical* | *high* | *low* | *unknown*	Power priority on neighbor interface. **Since: 4.21.3
[powerSource] **	*enum: backup* | *pse* | *unknown* | *pseAndLocal* | *primary* | *reserved*	Power Source. **Since: 4.21.3
[powerType] **	*enum: type2PseDevice* | *type2PdDevice* | *type1PseDevice* | *type1PdDevice*	Power Type - type 1/2 and Power Sourcing Entity/Powered Device. **Since: 4.21.3
[powerTypeExt] **	*enum: type4Pse* | *type3SingleSignaturePd* | *type3Pse* | *type4DualSignaturePd* | *type3DualSignaturePd* | *type4SingleSignaturePd*	Power Type ext. **Since: 4.23.0
[pseAllocatedPowerValue] **	*floating point number*	Power granted to device in watts. **Since: 4.21.3
[pseAllocatedPowerValue-AlternativeA] **	*floating point number*	Maximum output power (in watts) the PSE is providing for the A Mode. **Since: 4.23.0
[pseAllocatedPowerValue-AlternativeB] **	*floating point number*	Maximum output power (in watts) the PSE is providing for the B Mode. **Since: 4.23.0
[pseAutoclassSupport] **	*boolean*	PSE supports Autoclass. **Since: 4.23.0
[pseMaximumAvailablePower] **	*floating point number*	Highest power (in watts) the PSE can grant. **Since: 4.23.0
[psePowerPairsExt] **	*enum: alternativeB* | *alternativeA* | *bothAlternatives*	Alternative used by PSE. **Since: 4.23.0
[psePoweringStatus] **	*enum: fourPairPowering-DualSignature* | *fourPairPoweringSingle-Signature* | *twoPairPowering* | *poweringStatusReserved0*	Existing powering configuration of the PSE. **Since: 4.23.0

unknownOrgDefinedTlvs	*list of UnknownOrgDefTlv* see 2.993.1.2	A list of unknown organizationally specific TLVs.
vlanNames **	*table(numeric string) = string*	A mapping between vlan id and vlan name. **Since: 4.26.0
vlanNamesChanged **	*boolean*	List of VLAN Name TLVs might not be up to date. **Since: 4.26.2
vlanNamesIncomplete **	*boolean*	List of VLAN Name TLVs is not complete. **Since: 4.26.2
[ztpBootVlan] **	*integer*	ZTP Boot VLAN. **Since: 4.26.0

2.993.1.1 LldpMedInfo

[assetIDTlvInfo] **	*string*	Asset ID Tlv. **Since: 4.22.0
[capabilities]	*MedCapabilitiesInfo* see 2.993.1.1.1	MED Capabilities.
[firmwareRevisionTlvInfo] **	*string*	Firmware Revision Tlv. **Since: 4.22.0
[hardwareRevisionTlvInfo] **	*string*	Hardware Revision Tlv. **Since: 4.22.0
[locationId] **	*MedLocationIdentification-Info* see 2.993.1.1.2	Location Identification information. **Since: 4.22.0
[manufacturerNameTlvInfo] **	*string*	Manufacturer Name Tlv. **Since: 4.22.0
[modelNameTlvInfo] **	*string*	Model Name Tlv. **Since: 4.22.0
networkPolicies	*list of MedNetworkPolicyInfo* see 2.993.1.1.3	Collection of Network Policies.
[serialNumberTlvInfo] **	*string*	Serial Number Tlv. **Since: 4.22.0
[softwareRevisionTlvInfo] **	*string*	Software Revision Tlv. **Since: 4.22.0

2.993.1.1.1 MedCapabilitiesInfo

capabilities	*boolean*	System supports 'Capabilities' TLV.
deviceType	*enum: notDefined | endpointClass3 | networkConnectivity | endpointClass1 | reserved | endpointClass2*	MED device type.
extendedPd	*boolean*	System supports 'Extended Power via MDI - PD' TLV.
extendedPse	*boolean*	System supports 'Extended Power via MDI - PSE' TLV.
inventory	*boolean*	System supports 'Inventory' TLV.
location	*boolean*	System supports 'Location Identification' TLV.

networkPolicy	*boolean*	System supports 'Network Policy' TLV.

2.993.1.1.2 MedLocationIdentificationInfo

[civicAddress]	*CivicAddress* see 2.993.1.1.2.1	Civic Address LCI as per draft-ietf-geopriv-dhcp-civil-09.
[coordinateBased]	*CoordinateBasedLocationInfo* see 2.993.1.1.2.3	Coordinate-based LCI info as per RFC 3825.
[ecsElin]	*string*	Emergency Location Identification Number to support traditional PSAP-based Emergency Communications Systems.

2.993.1.1.2.1 CivicAddress

civicAddressElements	*list of CivicAddressElement* see 2.993.1.1.2.2	List of Civic Address Elements.
countryCode	*string*	Two-letter ISO 3166 country code.
what	*integer*	Which location the address refers to as per RFC 4776.

2.993.1.1.2.2 CivicAddressElement

caType	*integer*	Civic Address (CA) Type as per draft-ietf-geopriv-dhcp-civil-09.
caValue	*string*	Civic Address (CA) Value as per draft-ietf-geopriv-dhcp-civil-09.

2.993.1.1.2.3 CoordinateBasedLocationInfo

aT	*integer*	Altitude type (at) as per RFC 3825.
altRes	*integer*	Altitude resolution as per RFC 3825.
altitude	*integer*	Altitude as per RFC 3825: fixed point value with 8 bits fractional part.
datum	*integer*	Datum as per RFC 3825.
laRes	*integer*	Latitude resolution as per RFC 3825.
latitude	*integer*	Latitude as per RFC 3825: fixed point value with 25 bits fractional part.
loRes	*integer*	Longitude resolution as per RFC 3825.
longitude	*integer*	Longitude as per RFC 3825: fixed point value with 25 bits fractional part.

2.993.1.1.3 MedNetworkPolicyInfo

applicationType	*integer*	Application Type for given policy.
dscpValue	*integer*	DSCP value to be used by Endpoint Device for given application to specify priority for IP datagram.
[layer2Priority]	*integer*	Layer 2 priority to be used for the specified application type.

tagged	*boolean*	The specified application type is using a 'tagged' VLAN.
unknownPolicy	*boolean*	Endpoint Device wants to explicitly advertise that this policy is required by the device, but is currently unknown.
[vlanId]	*integer*	VLAN identifier for the port as defined in IEEE 802.1Q-2003.

2.993.1.2 UnknownOrgDefTlv

[malformedTlvError]	*string*	Error string if the TLV is malformed.
[ouiStr]	*string*	Hexdump of Organizationally Unique Identifier of the information received from the neighbor.
[subType]	*integer*	Unknown Organizationally-Defined TLV type.
tlvLines	*list of string*	Represents the received Unknown Organizationally-Defined TLV in either decoded string format or hexdump depending on whether decoding was successful.

2.993.2 ManagementAddr

address	*string*	LLDP management address which could either be an IPv4/v6 address or a MAC address, may be used to reach higher layer entities.
addressType	*enum: ipv4 | unknown | ipv6 | ethernet*	Type of LLDP management address.
interfaceNum	*integer*	Interface number associated with the management address, in the encoding specified by interfaceNumType attribute.
interfaceNumType	*enum: badType | ifIndex | unknown | systemPortNumber*	Interface numbering method used by the interfaceNum attribute.
[interfaceNumTypeValue]	*integer*	Interface number subtype value which is unrecognized.
oidString	*string*	OID value used to identify the type of hardware component or protocol entity associated with the management address.

2.993.3 SystemCapabilities

[bridge]	*boolean*	Indicates whether the system is enabled to be a bridge.
[docsisCableDevice]	*boolean*	Indicates whether the system is enabled to be a DOCSIS Cable Device.
[other]	*boolean*	Indicates whether the system has any capabilities other than repeater, bridge, wlanAccessPoint, router, telephone, docsisCableDevice, stationOnly.

[repeater]	*boolean*	Indicates whether the system is enabled to be a repeater.
[router]	*boolean*	Indicates whether the system is enabled to be a router.
[stationOnly]	*boolean*	Indicates whether the system is enabled to be a station and nothing else.
[telephone]	*boolean*	Indicates whether the system is enabled to be a telephone.
[wlanAccessPoint]	*boolean*	Indicates whether the system is enabled to be a WLAN Access Point.

2.994 show lldp neighbors [...]

lldpNeighbors	*list of LldpNeighbor* see 2.994.1	Lldp Neighbors.
lldpSwagNeighbors **	*list of LldpSwagNeighbor* see 2.994.2	SWAG Neighbors. **Since: 4.35.0
tablesAgeOuts	*integer*	The number of times the information advertised by a MSAP has been deleted from tables contained in the LLDP remote systems MIB because the information timeliness interval has expired.
tablesDeletes	*integer*	The number of times the information advertised by a MSAP has been deleted from tables contained in the LLDP remote systems MIB.
tablesDrops	*integer*	The number of times the information advertised by a MSAP could not be entered into tables contained in the LLDP remote systems MIB.
tablesInserts	*integer*	The number of times the information advertised by a MSAP has been inserted into tables contained in the LLDP remote systems MIB.
[tablesLastChangeTime]	*floating point number*	The last time tables contained in the LLDP remote systems MIB are updated.

2.994.1 LldpNeighbor

neighborDevice	*string*	Name of the neighbor device.
neighborPort	*string*	Name of the neighbor port.
port	*interface name*	Name of the interface.
ttl	*integer*	The Time To Live value (in seconds) advertised by the remote system.

2.994.2 LldpSwagNeighbor

member	*integer*	SWAG member Id.
neighborDevice	*string*	Name of the neighbor device.
neighborPort	*string*	Name of the neighbor port.
[originatorMember]	*integer*	Neighbor's SWAG member Id.
[originatorRole]	*enum: candidate* | *supervisorServer* | *worker* | *supervisorSwitch*	Neighbor's SWAG role.
port	*interface name*	Name of the interface.

2.995 show lldp neighbors detail [...]

lldpNeighbors	*table(Interface name) = LldpNeighborsList* see 2.995.1	A mapping between local interface and neighbors discovered on that interface.
lldpSwagMemberDetail **	*table(numeric string) = LldpSwagMemberDetail* see 2.995.2	SWAG member Detail. **Since: 4.35.2

2.995.1 LldpNeighborsList

lldpNeighborInfo	*list of LldpNeighborInfo* see 2.995.1.1	List of LLDP neighbors' information.

2.995.1.1 LldpNeighborInfo

chassisId	*string*	Chassis identifier string.
chassisIdType	*enum: unknown | local | macAddress | chassisComponent | reserved | networkAddress | interfaceAlias | portComponent | interfaceName*	Type of the chassis.
lastChangeTime	*floating point number*	The UTC time at which the neighbor entry was last updated.
lastContactTime	*floating point number*	The UTC time at which the neighbor last communicated with the system.
managementAddresses	*list of ManagementAddr* see 2.993.2	List of management addresses ordered by priority.
neighborDiscoveryTime	*floating point number*	The UTC time at which the neighbor was created.
neighborInterfaceInfo	*NeighborInterfaceInfo* see 2.995.1.1.1	Information of neighbor interface like interface id, description along with all the TLVs received on it.
[systemCapabilities]	*SystemCapabilities* see 2.993.3	Supported system capabilities and information about whether they are enabled.
[systemDescription]	*string*	System description.
[systemName]	*string*	System name.
ttl	*integer*	The Time To Live value (in seconds) advertised by the neighbor.

2.995.1.1.1 NeighborInterfaceInfo

autoNegAdvertised-Capabilities	*list of string*	List of auto-negotiation capabilities advertised on neighbor interface.
[autoNegCapability]	*enum: capableAndEnabled | notCapable | capableAndDisabled*	Auto-negotiation capability of neighbor interface.
[autoclassCompleted] **	*boolean*	PSE has concluded the Autoclass measurement. **Since: 4.23.0

[autoclassRequest] **	*boolean*	PD has requested an Autoclass measurement by the PSE. **Since: 4.23.0
[controlAbility]	*boolean*	Indicates whether the pair selection can be controlled on neighbor interface.
[dualSignaturePowerClass-ExtModeA] **	*enum: powerClass1 | powerClass3 | singleSignaturePd | powerClass2 | powerClass4 | powerClass5 | twoPairOnlyPse*	Power class on Mode A. **Since: 4.23.0
[dualSignaturePowerClass-ExtModeB] **	*enum: powerClass1 | powerClass3 | singleSignaturePd | powerClass2 | powerClass4 | powerClass5 | twoPairOnlyPse*	Power class on Mode B. **Since: 4.23.0
[interfaceDescription]	*string*	Description of local/neighbor interface.
interfaceId	*string*	Name of local/neighbor interface(may contain escaped quotation marks).
interfaceIdType	*enum: unknown | local | macAddress | reserved | networkAddress | interfaceAlias | agentCircuitId | portComponent | interfaceName*	Type of local/neighbor interface.
interfaceId_v2 **	*string*	Name of local/neighbor interface. **Since: 4.24.2
[linkAggregation8021-InterfaceId] **	*integer*	Link Aggregation 802.1 interface identifier. **Since: 4.29.2
[linkAggregation8021Status] **	*enum: capableAndEnabled | notCapable | capableAndDisabled*	Link Aggregation 802.1 Status. **Since: 4.29.2
[linkAggregation8023-InterfaceId] **	*integer*	Link Aggregation 802.3 interface identifier. **Since: 4.29.2
[linkAggregation8023Status] **	*enum: capableAndEnabled | notCapable | capableAndDisabled*	Link Aggregation 802.3 Status. **Since: 4.29.2
[managementVid]	*integer*	Management vlan id.
[maxFrameSize]	*integer*	Indicates the maximum supported frame size in octets on the given interface.
[medInfo] **	*LldpMedInfo* see 2.993.1.1	LLDP-MED Info. **Since: 4.21.3
[operMauType]	*string*	Operational Medium Attachment Unit type of the neighbor interface.
[pd4Pid] **	*boolean*	The PD supports powering of both Modes simultaneously. **Since: 4.23.0

[pdLoad] **	*boolean*	PD is dual-signature and power demand on Mode A and Mode B are electrically isolated. **Since: 4.23.0
[pdPoweredStatus] **	*enum: poweredSingleSignature | fourPairPoweringDualSignature | twoPairPoweringDualSignature*	Existing powered configuration of the PD. **Since: 4.23.0
[pdRequestedPowerValue] **	*floating point number*	Power requested by device in watts. **Since: 4.21.3
[pdRequestedPowerValueModeA] **	*floating point number*	Maximum input power (in watts) the PD is requesting for the A Mode. **Since: 4.23.0
[pdRequestedPowerValueModeB] **	*floating point number*	Maximum input power (in watts) the PD is requesting for the B Mode. **Since: 4.23.0
portAndProtocolVlanEnabled	*table(numeric string) = boolean*	A mapping between Port And Protocol VLAN ID and whether it is enabled.
portAndProtocolVlanSupported	*table(numeric string) = boolean*	A mapping between Port And Protocol VLAN ID and whether it is supported.
[portClass]	*enum: pClassPSE | unknown | pClassPD*	Port class of neighbor interface.
[portVlanId]	*integer*	Port VLAN ID.
[powerClass]	*integer*	Power classification of neighbor interface.
[powerClassExt] **	*enum: powerClassExt4 | powerClassExt2 | dualSignaturePd | powerClassExt6 | powerClassExt5 | powerClassExt7 | powerClassExt3 | powerClassExt1 | powerClassExt8*	Power class ext. **Since: 4.23.0
[powerDownRequest] **	*boolean*	PD has requested a power down. **Since: 4.23.0
[powerDownTime] **	*integer*	Time in seconds the PD requests to be unpowered. Zero means to remain unpowered indefinitely. **Since: 4.23.0
[powerOverEthernetEnabled]	*boolean*	Indicates whether MDI power is enabled on neighbor interface.
[powerOverEthernetSupported]	*boolean*	Indicates whether MDI power is supported on neighbor interface.
[powerPairs]	*enum: spare | signal | unknown*	PSE power pairs on use on neighbor interface.
[powerPriority] **	*enum: critical | high | low | unknown*	Power priority on neighbor interface. **Since: 4.21.3
[powerSource] **	*enum: backup | pse | unknown | pseAndLocal | primary | reserved*	Power Source. **Since: 4.21.3

[powerType] **	*enum: type2PseDevice* | *type2PdDevice* | *type1PseDevice* | *type1PdDevice*	Power Type - type 1/2 and Power Sourcing Entity/Powered Device. **Since: 4.21.3
[powerTypeExt] **	*enum: type4Pse* | *type3SingleSignaturePd* | *type3Pse* | *type4DualSignaturePd* | *type3DualSignaturePd* | *type4SingleSignaturePd*	Power Type ext. **Since: 4.23.0
protocolIdentityInfo	*list of string*	Protocols enabled on neighbor interface.
[pseAllocatedPowerValue] **	*floating point number*	Power granted to device in watts. **Since: 4.21.3
[pseAllocatedPowerValue-AlternativeA] **	*floating point number*	Maximum output power (in watts) the PSE is providing for the A Mode. **Since: 4.23.0
[pseAllocatedPowerValue-AlternativeB] **	*floating point number*	Maximum output power (in watts) the PSE is providing for the B Mode. **Since: 4.23.0
[pseAutoclassSupport] **	*boolean*	PSE supports Autoclass. **Since: 4.23.0
[pseMaximumAvailablePower] **	*floating point number*	Highest power (in watts) the PSE can grant. **Since: 4.23.0
[psePowerPairsExt] **	*enum: alternativeB* | *alternativeA* | *bothAlternatives*	Alternative used by PSE. **Since: 4.23.0
[psePoweringStatus] **	*enum: fourPairPowering-DualSignature* | *fourPairPoweringSingle-Signature* | *twoPairPowering* | *poweringStatusReserved0*	Existing powering configuration of the PSE. **Since: 4.23.0
[swagInfo] **	*SwagInfo* see 2.995.1.1.1.1	SWAG information. **Since: 4.35.0
unknownOrgDefinedTlvs	*list of UnknownOrgDefTlv* see 2.993.1.2	A list of unknown organizationally specific TLVs.
unknownTlvs	*list of UnknownTlv* see 2.995.1.1.1.2	List of Unknown Tlvs which are outside the standard TLVs defined by LLDP protocol.
[vidUsageDigest]	*integer*	VID usage Digest associated with the neighbor.
vlanNames	*table(numeric string) = string*	A mapping between vlan id and vlan name.
[ztpBootVlan] **	*integer*	ZTP Boot VLAN. **Since: 4.26.0

2.995.1.1.1.1 SwagInfo

[expectedPeerMember]	*integer*	Expected neighbor SWAG member.
member	*integer*	SWAG member Id.
[receivedPeerMember]	*integer*	Received neighbor SWAG member.

role	*enum: candidate* | *supervisorServer* | *worker* | *supervisorSwitch*	SWAG role.
[sysdbConnected]	*boolean*	Indicates if member is connected to Sysdb.

2.995.1.1.1.2 UnknownTlv

[tlvLines]	*list of string*	Hexdump of the information aboutreceived Unknown TLV.
[tlvType]	*integer*	Unknown TLV type which is not defined in LLDP protocol.

2.995.2 LldpSwagMemberDetail

lldpSwagNeighbors	*table(Interface name) = LldpSwagNeighborsList* see 2.995.2.1	A mapping between interface and neighbors discovered on that interface.

2.995.2.1 LldpSwagNeighborsList

lldpSwagNeighborInfo	*list of LldpSwagNeighborInfo* see 2.995.2.1.1	List of LLDP neighbors' information.

2.995.2.1.1 LldpSwagNeighborInfo

chassisId	*string*	Chassis identifier string.
chassisIdType	*enum: unknown* | *local* | *macAddress* | *chassisComponent* | *reserved* | *networkAddress* | *interfaceAlias* | *portComponent* | *interfaceName*	Type of the chassis.
interfaceId	*string*	Name of local/neighbor interface.
interfaceIdType	*enum: unknown* | *local* | *macAddress* | *reserved* | *networkAddress* | *interfaceAlias* | *agentCircuitId* | *portComponent* | *interfaceName*	Type of local/neighbor interface.
[swagInfo]	*SwagInfo* see 2.995.1.1.1.1	SWAG information.
ttlInMilliseconds	*integer*	The Time To Live value advertised by the neighbor in milliseconds.

2.996 show load-balance destination ip ingress-interface INTF dst-mac-address DST_MAC { ((src-ip-address SRC_IP) | (dst-ip-address DST_IP) | (ip-ttl IP_TTL) | (ip-protocol IP_PROTO)) | ((src-l4-port SRC_L4_PORT) | (dst-l4-port DST_L4_PORT)) } | { ((src-ipv6-address SRC_IPV6) | (dst-ipv6-address DST_IPV6) | (hop-limit HOP_LIMIT) | (next-header NEXT_HDR) | (flow-label FLOW_LABEL)) | ((src-l4-port SRC_L4_PORT) | (dst-l4-port DST_L4_PORT)) } [...]

`dlbEcmpEnable`	*boolean*	Dynamic load balancing for ECMP is enabled.
`[egressIntf]`	*interface name*	Egress interface taken to reach destination.

2.997 show load-balance destination ip ingress-interface INTF src-ipv4-address SRC_IPV4ADDR dst-ipv4-address DST_IPV4ADDR ip-protocol PROTO [...]

see 2.996

2.998 show load-balance destination ip ingress-interface INTF src-ipv6-address SRC_IPV6ADDR dst-ipv6-address DST_IPV6ADDR ip-protocol PROTO [...]

see 2.996

2.999 show load-balance destination mac ingress-interface INTF src-mac-address SRC_MAC dst-mac-address DST_MAC (ether-type ETH_TYPE) | { ((src-ip-address SRC_IP) | (dst-ip-address DST_IP) | (ip-ttl IP_TTL) | (ip-protocol IP_PROTO)) | ((src-l4-port SRC_L4_PORT) | (dst-l4-port DST_L4_PORT)) } | { ((src-ipv6-address SRC_IPV6) | (dst-ipv6-address DST_IPV6) | (hop-limit HOP_LIMIT) | (next-header NEXT_HDR) | (flow-label FLOW_LABEL)) | ((src-l4-port SRC_L4_PORT) | (dst-l4-port DST_L4_PORT)) } [...]

see 2.996

2.1000 show load-balance destination port-channel PORT_CHANNEL (bridged ((vlan-id VLAN) (src-mac-address SRC_MAC) (dst-mac-address DST_MAC))) | (routed ((vlan-id VLAN) (src-mac-address SRC_MAC) (dst-mac-address DST_MAC)) ((src-ip-address SRC_IP) (dst-ip-address DST_IP) (ip-protocol IP_PROTO))) [...]

outputIntf	*interface name*	Destination interface of the Port-Channel.

2.1001 show load-balance destination port-channel PORT_CHANNEL { ((ingress-interface ING_INTF) | (vlan-id VLAN) | non-unicast) | ((src-mac-address SRC_MAC) | (dst-mac-address DST_MAC) | (eth-type ETH_TYPE)) } | { ((ingress-interface ING_INTF) | (vlan-id VLAN) | non-unicast) | ((src-ip-address SRC_IP) | (dst-ip-address DST_IP) | (ip-ttl IP_TTL) | (ip-protocol IP_PROTO)) | ((src-l4-port SRC_L4_PORT) | (dst-l4-port DST_L4_PORT)) } | { ((ingress-interface ING_INTF) | (vlan-id VLAN) | non-unicast) | ((src-ipv6-address SRC_IPV6) | (dst-ipv6-address DST_IPV6) | (hop-limit HOP_LIMIT) | (next-header NEXT_HDR) | (flow-label FLOW_LABEL)) | ((src-l4-port SRC_L4_PORT) | (dst-l4-port DST_L4_PORT)) }

outputIntf	*interface name*	Destination interface of the Port-Channel.

2.1002 show load-balance ecmp sand fields [...]

revision 3

modules	*list of Module* see 2.1002.1	Collection of linecard's ECMP hashing settings.

2.1002.1 Module

ecmpHashIngressIntf	*boolean*	ECMP hashing on ingress interface.
ecmpHashKeyShift	*integer*	ECMP hash key shift.
ecmpHashPolynomial	*integer*	ECMP hash polynomial.
ecmpHashSeed	*integer*	ECMP hash seed.
extendedHashingSeed	*integer*	Extended hashing seed.
featureErrorCodes	*table(string) = string*	Mapping of load-balance features to error codes.
gre	*LoadBalanceFieldsGre* see 2.1002.1.1	GRE hash fields settings.
gtp	*LoadBalanceFieldsGtp* see 2.1002.1.2	GTP hash fields settings.
ipv4	*LoadBalanceFieldsIpv4* see 2.1002.1.3	IPv4 hash fields settings.
ipv6	*LoadBalanceFieldsIpv6* see 2.1002.1.4	IPv6 hash fields settings.
l4	*LoadBalanceFieldsL4* see 2.1002.1.5	L4 hash fields settings.
mac	*LoadBalanceFieldsMac* see 2.1002.1.6	MAC hash fields settings.
mpls	*LoadBalanceFieldsMpls* see 2.1002.1.7	MPLS hash fields settings.
name	*string*	Name of the load balance profile or module.
pktTypeGueHashMode	*enum: inner-and-outer-ip | outer-ip | inner-ip*	GUE packet hash settings.
pktTypeIpOGueTransitOuterUdp	*boolean*	IP over GUE transit outer UDP hash enabled.
pktTypeMplsOGre	*enum: inner-and-outer-ip | outer-ip | inner-ipv4-or-mac | inner-ip*	MPLS over GRE packet hash settings.
pktTypeTunneledIpv4OuterParserDepth **	*integer*	IPv4 Outer Parser Depth settings. **Since: 4.31.2
pktTypeTunneledIpv6OuterParserDepth **	*integer*	IPv6 Outer Parser Depth settings. **Since: 4.31.2
replacementHashingSeed	*integer*	Replacement hashing seed.
spnSeed **	*integer*	SPN seed. **Since: 4.32.2
symmetricHash	*boolean*	Full symmetric hash setting. When showing a linecard's load-balance policy, this becomes an estimate made by comparing the linecard's configuration with the expected full symmetric hashing settings.
udp	*LoadBalanceFieldsUdp* see 2.1002.1.8	UDP hash fields settings.

2.1002.1.1 LoadBalanceFieldsGre

key	*boolean*	Hashing on Key.

2.1002.1.2 LoadBalanceFieldsGtp

teid	*boolean*	Hashing on TEID.

2.1002.1.3 LoadBalanceFieldsIpv4

inner	*LoadBalanceFieldsIpv4-Header* see 2.1002.1.3.1	Hashing on inner IPv4 header.
outer	*LoadBalanceFieldsIpv4-Header* see 2.1002.1.3.1	Hashing on outer IPv4 header.

2.1002.1.3.1 LoadBalanceFieldsIpv4Header

dst	*boolean*	Hashing on destination IPv4 address.
protocol	*boolean*	Hashing on Protocol.
src	*boolean*	Hashing on source IPv4 address.
[symmetric]	*boolean*	Symmetrize source and destination fields.
ttl	*boolean*	Hashing on Time-To-Live.

2.1002.1.4 LoadBalanceFieldsIpv6

inner	*LoadBalanceFieldsIpv6-Header* see 2.1002.1.4.1	Hashing on inner IPv6 header.
outer	*LoadBalanceFieldsIpv6-Header* see 2.1002.1.4.1	Hashing on outer IPv6 header.

2.1002.1.4.1 LoadBalanceFieldsIpv6Header

dst	*boolean*	Hashing on destination IPv6 address.
flowLabel	*boolean*	Hashing on Flow Label.
hopLimit	*boolean*	Hashing on Hop-Limit.
nextHeader	*boolean*	Hashing on Next Header.
src	*boolean*	Hashing on source IPv6 address.
[symmetric]	*boolean*	Symmetrize source and destination fields.

2.1002.1.5 LoadBalanceFieldsL4

inner	*LoadBalanceFieldsL4-Header* see 2.1002.1.5.1	Hashing on inner L4 header.
outer	*LoadBalanceFieldsL4-Header* see 2.1002.1.5.1	Hashing on outer L4 header.

2.1002.1.5.1 LoadBalanceFieldsL4Header

portDst	*boolean*	Hashing on destination port.
portSrc	*boolean*	Hashing on source port.
[symmetric]	*boolean*	Symmetrize source and destination fields.

2.1002.1.6 LoadBalanceFieldsMac

inner	*LoadBalanceFieldsMac-Header* see 2.1002.1.6.1	Hashing on inner MAC header.
outer	*LoadBalanceFieldsMac-Header* see 2.1002.1.6.1	Hashing on outer MAC header.

2.1002.1.6.1 LoadBalanceFieldsMacHeader

dst	*boolean*	Hashing on destination MAC address.
ethType	*boolean*	Hashing on ethertype.
src	*boolean*	Hashing on source MAC address.
[symmetric]	*boolean*	Symmetrize source and destination fields.
vlan	*boolean*	Hashing on vlan.

2.1002.1.7 LoadBalanceFieldsMpls

entropyLabelEnabled	*boolean*	Hashing on Entropy label.
label	*boolean*	Hashing on MPLS label.

2.1002.1.8 LoadBalanceFieldsUdp

dstPortPayload	*table(numeric string) = LoadBalanceUdpPayload* see 2.1002.1.8.1	Payload hashing per destination port.

2.1002.1.8.1 LoadBalanceUdpPayload

conditional **	*list of ConditionalLoad-BalanceUdp* see 2.1002.1.8.1.1	Conditional matches. **Since: 4.33.1
payloadBytes	*list of integer*	Payload bytes to hash.

2.1002.1.8.1.1 ConditionalLoadBalanceUdp

criteria	*list of ConditionalLoadBalanceUdpMatchCriteria* see 2.1002.1.8.1.2	Conditional matching criteria.
payloadBytes	*list of integer*	Payload bytes to hash.

2.1002.1.8.1.2 ConditionalLoadBalanceUdpMatchCriteria

end	*integer*	End of the bits to match.
pattern	*integer*	Payload pattern.
start	*integer*	Start of the bits to match.

2.1003 show load-balance port-channel sand fields [...]

revision 4

modules	*list of Module* see 2.1003.1	Collection of load-balance hashing profiles or linecard LAG hashing settings.

2.1003.1 Module

Could also be an instance of:
AradProfile 2.1003.2

egressReplicationLagLb	*boolean*	Load Balancing using egress replication.
extendedHashingSeed	*integer*	Extended hashing seed.
featureErrorCodes	*table(string) = string*	Mapping of load-balance features to error codes.
gre	*LoadBalanceFieldsGre* see 2.1002.1.1	GRE hash fields settings.
gtp	*LoadBalanceFieldsGtp* see 2.1002.1.2	GTP hash fields settings.
ipPktIpTcpUdp	*boolean*	L4 and IP header hash on LAG for IP packets.
ipPktMac	*boolean*	MAC header hash on LAG for IP packets.
ipv4	*LoadBalanceFieldsIpv4* see 2.1002.1.3	IPv4 hash fields settings.
ipv6	*LoadBalanceFieldsIpv6* see 2.1002.1.4	IPv6 hash fields settings.
l4	*LoadBalanceFieldsL4* see 2.1002.1.5	L4 hash fields settings.
lagHashIngressIntf	*boolean*	LAG hashing on ingress interface.
lagHashKeyShift	*integer*	LAG hash key shift.
lagHashMode	*enum: clock-based | flow-based | round-robin*	packet distribution policy for LAGs.
lagHashPolynomial	*integer*	LAG hash polynomial.
lagHashSeed	*integer*	LAG hash seed.
lagPreferLocalMembers	*boolean*	Local LAG members programmed on each chip.
loadSharingPreferLocal-Supported	*boolean*	System supports prefer local setting.
mac	*LoadBalanceFieldsMac* see 2.1002.1.6	MAC hash fields settings.
mpls	*LoadBalanceFieldsMpls* see 2.1002.1.7	MPLS hash fields settings.
name	*string*	Name of the load balance profile or module.
pktTypeGueHashMode	*enum: inner-and-outer-ip | outer-ip | inner-ip*	GUE packet hash settings.
pktTypeIpOGueTransitOuter-Udp	*boolean*	IP over GUE transit outer UDP hash enabled.
pktTypeMplsOGre	*enum: inner-and-outer-ip | outer-ip | inner-ipv4-or-mac | inner-ip*	MPLS over GRE packet hash settings.

pktTypeTunneledIpv4Outer-ParserDepth **	*integer*	IPv4 Outer Parser Depth settings. **Since: 4.31.2
pktTypeTunneledIpv6Outer-ParserDepth **	*integer*	IPv6 Outer Parser Depth settings. **Since: 4.31.2
replacementHashingSeed	*integer*	Replacement hashing seed.
selectionMethods	*SelectionMethods* see 2.1003.1.1	Methods to select member from LAG hash key.
spnSeed **	*integer*	SPN seed. **Since: 4.32.2
symmetricHash	*boolean*	Full symmetric hash setting. When showing a linecard's load-balance policy, this becomes an estimate made by comparing the linecard's configuration with the expected full symmetric hashing settings.
udp	*LoadBalanceFieldsUdp* see 2.1002.1.8	UDP hash fields settings.
unadjustSwitchportFirst-Header	*boolean*	Do not adjust the starting header for calculating LAG hashing key on switchport.

2.1003.1.1 SelectionMethods

multiplication	*boolean*	Multiply hash key by member number then shift.
smoothDivision	*boolean*	Use 8 LSB of hash key to look up table.

2.1003.2 AradProfile

ecmpHashIngressIntf	*boolean*	ECMP hashing on ingress interface.
ecmpHashKeyShift	*integer*	ECMP hash key shift.
ecmpHashPolynomial	*integer*	ECMP hash polynomial.
ecmpHashSeed	*integer*	ECMP hash seed.
egressReplicationLagLb	*boolean*	Load Balancing using egress replication.
extendedHashingSeed	*integer*	Extended hashing seed.
featureErrorCodes	*table(string) = string*	Mapping of load-balance features to error codes.
gre	*LoadBalanceFieldsGre* see 2.1002.1.1	GRE hash fields settings.
gtp	*LoadBalanceFieldsGtp* see 2.1002.1.2	GTP hash fields settings.
ipPktIpTcpUdp	*boolean*	L4 and IP header hash on LAG for IP packets.
ipPktMac	*boolean*	MAC header hash on LAG for IP packets.
ipv4	*LoadBalanceFieldsIpv4* see 2.1002.1.3	IPv4 hash fields settings.
ipv6	*LoadBalanceFieldsIpv6* see 2.1002.1.4	IPv6 hash fields settings.
l4	*LoadBalanceFieldsL4* see 2.1002.1.5	L4 hash fields settings.
lagHashIngressIntf	*boolean*	LAG hashing on ingress interface.
lagHashKeyShift	*integer*	LAG hash key shift.
lagHashMode	*enum: clock-based | flow-based | round-robin*	packet distribution policy for LAGs.

lagHashPolynomial	*integer*	LAG hash polynomial.
lagHashSeed	*integer*	LAG hash seed.
lagPreferLocalMembers	*boolean*	Local LAG members programmed on each chip.
loadSharingPreferLocal-Supported	*boolean*	System supports prefer local setting.
mac	*LoadBalanceFieldsMac* see 2.1002.1.6	MAC hash fields settings.
mpls	*LoadBalanceFieldsMpls* see 2.1002.1.7	MPLS hash fields settings.
name	*string*	Name of the load balance profile or module.
pktTypeGueHashMode	*enum: inner-and-outer-ip | outer-ip | inner-ip*	GUE packet hash settings.
pktTypeIpOGueTransitOuter-Udp	*boolean*	IP over GUE transit outer UDP hash enabled.
pktTypeMplsOGre	*enum: inner-and-outer-ip | outer-ip | inner-ipv4-or-mac | inner-ip*	MPLS over GRE packet hash settings.
pktTypeTunneledIpv4Outer-ParserDepth **	*integer*	IPv4 Outer Parser Depth settings. **Since: 4.31.2
pktTypeTunneledIpv6Outer-ParserDepth **	*integer*	IPv6 Outer Parser Depth settings. **Since: 4.31.2
replacementHashingSeed	*integer*	Replacement hashing seed.
selectionMethods	*SelectionMethods* see 2.1003.1.1	Methods to select member from LAG hash key.
sliceIds	*list of string*	Linecards that are associated with this profile.
spnSeed **	*integer*	SPN seed. **Since: 4.32.2
symmetricHash	*boolean*	Full symmetric hash setting. When showing a linecard's load-balance policy, this becomes an estimate made by comparing the linecard's configuration with the expected full symmetric hashing settings.
udp	*LoadBalanceFieldsUdp* see 2.1002.1.8	UDP hash fields settings.
unadjustSwitchportFirst-Header	*boolean*	Do not adjust the starting header for calculating LAG hashing key on switchport.

2.1004 show load-balance profile [...]

revision 4

see 2.1003

2.1005 show logging counters

hosts	*table(string) = LogCounterStat* see 2.1005.1	Logging counter statistics.

2.1005.1 LogCounterStat

bytesSent	*integer*	Bytes sent to network.
failed	*integer*	Number of messages failed during processing.
lastRefreshed	*floating point number*	Counter statistics refreshed time in UTC.
processed	*integer*	Number of messages processed by forwarding action.
protocol	*enum: tcp | udp | tls*	logging protocol.
resumed	*integer*	Number of times forwarding action resumed itself.
suspended	*integer*	Number of times forwarding action suspended itself.
suspendedDuration	*integer*	Number of seconds forwarding action was disabled.

2.1006 show logging group server [...]

groups	*table(string) = LogGroupStatus* see 2.1006.1	A mapping of groups to their logging hosts' status.

2.1006.1 LogGroupStatus

groupName	*string*	Group name for hosts.
hostStatus	*list of LogHostStatus* see 2.1006.1.1	A list of host servers configured for this host and their rsyslog status.

2.1006.1.1 LogHostStatus

endpoint	*string*	ip or hostname for server.
lastResponse	*floating point number*	Timestamp when the server was last reachable.
port	*integer*	Port for endpoint server.
serverType	*string*	Host is primary or standby.
state	*string*	The state a probe can be in, either active if we are sending syslog messages to this host, or probing if not.
vrf	*string*	Vrf name for this host.

2.1007 show loop-protection [...]

[detail]	*LoopProtectShowDetail* see 2.1007.1	Loop protection detailed.
disableTime	*integer*	How long interface will be disabled, if a loop is detected, in seconds.
enabled	*boolean*	Loop Protection enabled.
rateLimit	*integer*	Throttling level of loop protection messages per second.
totalVlansEnabled	*integer*	Total number of vlans loop protection is enabled on.
transmitInterval	*integer*	Packet transmission interval per second.

2.1007.1 LoopProtectShowDetail

destinationAddress	*MAC address*	Destination address for loop protection packets.
ethernetType	*0x88b7*	Ethernet type used by protocol.
receiveAction	*Interface Disable*	Trigger when a loop protection packet is received.
vlans	*table(numeric string) = LoopProtectShowDetailVlan* see 2.1007.1.1	A dict with the mapping vlan to loop protect vlan information.

2.1007.1.1 LoopProtectShowDetailVlan

disabledIntfs	*list of Interface name*	Interfaces disabled by loop protection.
[latestDisabledTime]	*floating point number*	Last time an interface was disabled on this vlan by loop protection.
[loopDetected]	*boolean*	Loop detected on Vlan.
totalIntfs	*integer*	Total number of interfaces in vlan protected by loop protection.

2.1008 show loop-protection counters

enabled	*boolean*	Loop protection enabled.
intfCounters	*table(string) = LoopProtectCounter* see 2.1008.1	List of counters per interface.
vlanCounters	*table(numeric string) = LoopProtectCounter* see 2.1008.1	List of counters per vlan.

2.1008.1 LoopProtectCounter

rx	*integer*	Packets received.
rxOther	*integer*	Packets received in error.
tx	*integer*	Packets transmitted.

2.1009 show loop-protection vlan VLANSET

enabled	*boolean*	Loop protection enabled.
vlanIntfs	*table(numeric string) = LoopProtectVlanIntfList* see 2.1009.1	Loop protect vlan information.

2.1009.1 LoopProtectVlanIntfList

intfs	*list of LoopProtectIntfInfo* see 2.1009.1.1	Loop protect information for interfaces in this vlan.

2.1009.1.1 LoopProtectIntfInfo

[disabledAt]	*floating point number*	When the interface was disabled.
[disabledUntil]	*floating point number*	When loop protection is scheduled to bring this interface up.
[intf]	*interface name*	Loop protection information about this interface.
[lpDisabled]	*boolean*	Loop detected on Vlan.
lpEnabled	*boolean*	Whether this interface is protected on loop protection.
[lpExcludedReason] **	*enum: stp | cli*	Reason if LP is not enabled. **Since: 4.35.0
[state]	*enum: unknownEnabledState | shutdown | enabled*	Current state of the interface.

2.1010 show mac access-lists [...]

see 2.76.3

2.1011 show mac pause-frame

pauseFramePassThrough	*boolean*	Pause frame visibility.

2.1012 show mac security counters [...]

interfaces	*table(Interface name) = MacSecCountersInterface* see 2.1012.1	A mapping between an interface and MAC security counters.

2.1012.1 MacSecCountersInterface

[countersDetail]	*MacSecIntfCountersDetail* see 2.1012.1.1	MAC security interface counter detailed information.
inOctetsDecrypted	*integer*	Number of received octets decrypted.
inPktsDecrypted	*integer*	Number of received packets decrypted.
outOctetsEncrypted	*integer*	Number of transmitted octets encrypted.
outPktsEncrypted	*integer*	Number of transmitted packets encrypted.

2.1012.1.1 MacSecIntfCountersDetail

[inBroadcastPkts] **	*integer*	Number of received broadcast packets on the controlled port. **Since: 4.28.2
[inMulticastPkts] **	*integer*	Number of received multicast packets on the controlled port. **Since: 4.28.2
[inOctets] **	*integer*	Number of received octets on the controlled port. **Since: 4.28.2
[inOctetsProtected] **	*integer*	Number of received octets that were ICV protected but unencrypted. **Since: 4.29.1
inPktsBadTag	*integer*	Number of received packets with bad security tag.
inPktsCtrl	*integer*	Number of received control packets.
inPktsDelayed **	*integer*	Number of received packets with PN lower than LPN when replay protection is disabled. **Since: 4.34.0
[inPktsDrop] **	*integer*	Number of received packets dropped for any reason. **Since: 4.28.2
inPktsLate **	*integer*	Number of received packets that failed sequence number check. **Since: 4.18.1
inPktsNoSCI	*integer*	Number of received packets dropped with unknown SCI.
inPktsNoTag	*integer*	Number of received packets without security tag when validateFrames is Strict.
inPktsNotUsingSA	*integer*	Number of received packets for an SA not in use.
inPktsNotValid	*integer*	Number of received invalid packets.
inPktsOK	*integer*	Number of received packets with no error.
inPktsTagged	*integer*	Number of received packets with security tag.

inPktsUnchecked	*integer*	Number of received packets not checked.
[inPktsUnknownSCI] **	*integer*	Number of received packets for an unknown SCI. **Since: 4.28.2
[inPktsUntagged] **	*integer*	Number of received packets without security tag when validateFrames is not Strict. **Since: 4.28.2
[inPktsUnusedSA] **	*integer*	Number of received packets for a SA not in use. **Since: 4.28.2
[inSecureChannelTcamHit] **	*integer*	Number of received packets that hit in the secure channel TCAM. **Since: 4.29.1
[inSecureChannelTcamMiss] **	*integer*	Number of received packets that missed the secure channel TCAM. **Since: 4.28.2
[inSubportTcamHit] **	*integer*	Number of received packets that hit in the subport TCAM. **Since: 4.29.1
[inSubportTcamMiss] **	*integer*	Number of received packets that missed the subport TCAM. **Since: 4.28.2
[inUcastPkts] **	*integer*	Number of received unicast packets on the controlled port. **Since: 4.28.2
[outBroadcastPkts] **	*integer*	Number of transmitted broadcast packets on the controlled port. **Since: 4.28.2
[outInvalidSA] **	*integer*	Number of transmitted packets which used an invalid SA. **Since: 4.29.1
[outMulticastPkts] **	*integer*	Number of transmitted multicast packets on the controlled port. **Since: 4.28.2
[outOctets] **	*integer*	Number of transmitted octets on the controlled port. **Since: 4.28.2
[outOctetsProtected] **	*integer*	Number of transmitted octets that were ICV protected but unencrypted. **Since: 4.29.1
outPktCtrl	*integer*	Number of transmitted control packets.
[outPktsProtected] **	*integer*	Number of transmitted packets that were ICV protected but unencrypted. **Since: 4.29.1
outPktsTooLong	*integer*	Number of transmitted packets larger than MTU.
outPktsUntagged	*integer*	Number of transmitted packets without security tag.
[outUcastPkts] **	*integer*	Number of transmitted unicast packets on the controlled port. **Since: 4.28.2

2.1013 show mac security interface [...]

interfaces	*table(Interface name)* = *MacsecInterface* see 2.1013.1	A mapping between interfaces and MAC security interface information.

2.1013.1 MacsecInterface

address	*MAC address*	MAC address of the local port.
controlledPort	*boolean*	MAC security is operational.
[details]	*MacsecInterfaceDetailData* see 2.1013.1.1	MAC security Interface detail information.
keyMsgId	*string*	Message identifier of the distributed key currently used.
keyNum	*integer*	Key number of the distributed key currently used.
portId	*integer*	Port number of the local port.

2.1013.1.1 MacsecInterfaceDetailData

bypassProtocol **	*list of string*	List of protocols without MAC security protection. **Since: 4.22.1
cachedSak **	*boolean*	Cached SAK is used. **Since: 4.25.1
ethFlowControl **	*enum: Bypassed | None | Encrypted*	Flow control frame handling. **Since: 4.26.2
fipsPostStatus **	*enum: passed | failed | inProgress | none*	FIPS Power-on self-test. **Since: 4.21.3
keyDerivationPadding **	*enum: prepend | append*	Padding for short length CAK/CKN. **Since: 4.31.1
keyServerPriority	*integer*	Configured key server priority for the interface.
latestKeyMsgId	*string*	A 96 bit message identifier for the latest key.
latestKeyMsgNum	*integer*	Message number of the latest key.
latestKeyReceiving	*boolean*	The latest key is currently used for decrypting data packets.
latestKeyTransmitting	*boolean*	The latest key is currently used for encrypting data packets.
localSsci	*string*	Value of local SSCI.
mkaLifeTime **	*integer*	Time in seconds after which peers are removed from live or potential peers list, upon no response. **Since: 4.26.0
oldKeyMsgId	*string*	A 96 bit message identifier for the old key.
oldKeyMsgNum	*integer*	Message number of the old key.
oldKeyReceiving	*boolean*	The old key is currently used for decrypting data packets.
oldKeyTransmitting	*boolean*	The old key is currently used for encrypting data packets.

`profileName` **	*string*	MAC security profile name. **Since: 4.24.1
`ptpBypass` **	*list of MacsecPtpBypassSupport* see 2.1013.1.1.1	List of supported PTP bypasses. **Since: 4.29.2
`replayProtection` **	*boolean*	Configured replay protection status for the interface. **Since: 4.34.0
`replayProtectionWindow` **	*integer*	Configured replay protection window size for the interface. **Since: 4.34.0
`sakRetireDelay` **	*integer*	Time in seconds after which the old SAK is retired. **Since: 4.29.0
`sakTransmitDelay` **	*integer*	Time in seconds after which the latest key transmit is enabled on key server. **Since: 4.29.0
`sessionReKeyPeriod`	*floating point number*	Period in seconds after which the session keys are refreshed.
`[suspensionEvent]` **	*enum: ssu | sso | suspended*	Event due to which MKA is suspended. **Since: 4.30.0
`traffic` **	*enum: None | Protected | Unprotected*	Type of traffic. **Since: 4.21.3
`unauthBypassProtocol` **	*list of string*	List of protocols allowed in unauthorized state. **Since: 4.29.2

2.1013.1.1.1 MacsecPtpBypassSupport

`support`	*enum: controlPlane | multicast | full | notSupported | unicast | dataPlane*	Supported PTP bypasses.

2.1014 show mac security mka counters [...]

interfaces	*table(Interface name)* = *MacsecMessageCounters-Interface* see 2.1014.1	A mapping between interfaces and MAC security MKA counters.

2.1014.1 MacsecMessageCountersInterface

[details]	*MacsecMessageCounter-Detail* see 2.1014.1.1	MAC security counter detailed information.
rxPacketsFailure	*integer*	Total of invalid/errored received packets.
rxPacketsSuccess	*integer*	Total of successfully received packets.
txPacketsFailure	*integer*	Total of invalid/errored transmitted packets.
txPacketsSuccess	*integer*	Total of successfully transmitted packets.

2.1014.1.1 MacsecMessageCounterDetail

rxBasicParamSetError	*integer*	Basic parameter set errored received packets.
rxDistCakSetError **	*integer*	Dist CAK Set errored received packets. **Since: 4.20.5
rxDistSakSetError	*integer*	Dist SAK Set errored received packets.
rxEapolDmacError **	*integer*	EAPOL Destination MAC errored packets. **Since: 4.35.2
rxEapolError	*integer*	EAPOL errored packets.
rxIcvIndicatorError **	*integer*	ICV Indicator errored received packets. **Since: 4.18.1
rxIcvValidationError	*integer*	ICV validation error in received packets.
rxInvalid	*integer*	Invalid interface or null packets.
rxLivePeerListError	*integer*	Live peerlist set errored received packets.
rxPotentialPeerListError	*integer*	Potential peerlist set errored received packets.
rxReplayError **	*integer*	Replay errored received packets. **Since: 4.34.1
rxSakUseSetError	*integer*	SAK Use Set errored received packets.
rxUnrecognizedCkn	*integer*	Unrecognized ckn in received packets.
rxUnrecognizedSetError	*integer*	Unrecognized parameter set errored received packets.
rxXpnSetError **	*integer*	XPN Set errored received packets. **Since: 4.30.0
txInvalid	*integer*	Invalid interface in tx packets.

2.1015 show mac security participants [...]

interfaces	*table(Interface name) = MacsecParticipants-Interface* see 2.1015.1	A mapping between interfaces and MAC security interface participants.

2.1015.1 MacsecParticipantsInterface

participants	*table(string) = MacsecParticipant* see 2.1015.1.1	A mapping between CKN and MAC security participants.

2.1015.1.1 MacsecParticipant

defaultActor	*boolean*	The participant is spawned from a configured fallback key.
[details]	*MacsecParticipantDetail* see 2.1015.1.1.1	MAC security participant detail information.
electedSelf	*boolean*	The participant has elected itself as the key server.
msgId	*string*	Member identifier generated for the participant.
principalActor	*boolean*	The participant is also a principal actor.
success	*boolean*	The participant has successfully elected a key server and has at least one live peer.

2.1015.1.1.1 MacsecParticipantDetail

keyNum	*integer*	Key number of the distributed session association key.
keyServerAddr	*MAC address*	Mac address of the key server.
keyServerMsgId	*string*	Message identifier of the key server.
keyServerPortId	*integer*	Port Id of the key server.
livePeerList	*list of string*	List of all live peers for this participant.
llpnExhaustion	*integer*	Number of times LLPN exhaustion event detected when this participant is the principal actor.
potentialPeerList	*list of string*	List of all potential peers for this participant.
sakTransmit	*boolean*	The participant is using the distributed SAK for transmit.

2.1016 show mac security profile [...]

sources	*table(string) = MacsecProfiles* see 2.1016.1	Mapping between source and profiles.

2.1016.1 MacsecProfiles

profiles	*table(string) = MacsecProfile* see 2.1016.1.1	Mapping between profile name and profile details.

2.1016.1.1 MacsecProfile

bypassProtocol **	*list of string*	List of protocols without MAC security protection. **Since: 4.28.1
cakSha256Hash	*string*	Sha256 hash of primary connectivity association key.
cipher	*enum: aes256-gcm-xpn | aes128-gcm-xpn | aes128-gcm | aes256-gcm*	Cipher suite for a profile.
ckn	*string*	Primary connectivity association key name.
fallbackCakSha256Hash	*string*	Sha256 hash of fallback connectivity association key.
fallbackCkn	*string*	Fallback connectivity association key name.
[fallbackKeySource] **	*enum: preSharedKey | sharedSecretProfile | dot1x*	Pre-shared CAK/CKN, 802.1x derived CAK/CKN or CAK/CKN from a shared-secret profile. **Since: 4.27.0
fallbackSecProfName **	*string*	Fallback shared secret profile name. **Since: 4.27.2
includeSci **	*boolean*	Include secure channel identifier in data packets. **Since: 4.28.1
interfaces	*list of Interface name*	List of interfaces this profile is configured on.
keyDerivationPadding **	*enum: prepend | append*	Padding for short length CAK/CKN. **Since: 4.31.1
keyRetirePolicy	*enum: immediate | delayed*	Key retirement policy.
keyServerPriority **	*integer*	Configured key server priority for the interface. **Since: 4.28.1
mkaLifeTime **	*integer*	Time in seconds after which peers are removed from live or potential peers list, upon no response. **Since: 4.26.0
[primaryKeySource] **	*enum: preSharedKey | sharedSecretProfile | dot1x*	Pre-shared CAK/CKN, 802.1x derived CAK/CKN or CAK/CKN from a shared-secret profile. **Since: 4.27.0

priority	*integer*	MACsec config priority.
replayProtection **	*boolean*	Configured replay protection status for the profile. **Since: 4.34.0
replayProtectionWindow **	*integer*	Configured replay protection window size for the profile. **Since: 4.34.0
sakAnMax **	*integer*	Maximum value of AN of any SAK generated when the interface configured with this profile is keyserver. **Since: 4.28.2
sakRetireDelay **	*integer*	Time in seconds after which the old SAK is retired. **Since: 4.29.0
sakTransmitDelay **	*integer*	Time in seconds after which the latest key transmit is enabled on key server. **Since: 4.29.0
secProfName **	*string*	Primary shared secret profile name. **Since: 4.27.2
sessionReKeyPeriod **	*integer*	Period in seconds after which the session keys are refreshed. **Since: 4.28.1
source	*string*	Cli or EosSdk agent name.
unauthBypassProtocol **	*list of string*	List of protocols allowed in unauthorized state. **Since: 4.29.2
unprotectedTrafficPolicy **	*enum: drop | allow* *active-sak | allow*	Unprotected traffic policy. **Since: 4.25.1

2.1017 show mac security ptp bypass

interfaces	*table(Interface name) = MacsecPtpBypassInterface* see 2.1017.1	A mapping between interfaces and PTP bypass information.

2.1017.1 MacsecPtpBypassInterface

bypassSupport	*list of MacsecPtpBypassSupport* see 2.1013.1.1.1	List of supported PTP bypasses.

2.1018 show mac security sak [...]

interfaces	*table(Interface name) = MacsecSak* see 2.1018.1	A mapping between interfaces and MAC security interface SAKs.

2.1018.1 MacsecSak

forcedNewTxSakInstallation	*integer*	Number of times new tx sak installed without the acknowledgement from non key server.
forcedOldRxSakDeletion	*integer*	Number of times old sak deleted without the acknowledgement from non key server.
[nextSakGenUtcTime] **	*floating point number*	Next SAK generation time in UTC. **Since: 4.35.2
rxSakInstallDurations	*table(string) = integer*	A mapping between rxSak install time and count.
rxSakMaxInstallTime	*floating point number*	Max time taken to install Rx SAK in seconds.
sakFrom	*enum: None | previous-CA | static-SA | current-CA*	SAK generated source.
sakGenLivePeer	*integer*	SAK generated due to live peer.
sakGenPN	*integer*	SAK generated due to packet number exhaustion.
sakGenRekey	*integer*	SAK generated due to rekey.
sakGenerated	*integer*	Number of SAK generated.
sakKeyServer	*string*	Identifier of Key Server whose sak is programmed.
sakNumber	*integer*	Key number of the distributed key currently in use.
txSakInstallDurations	*table(string) = integer*	A mapping between txSak install time and count.
txSakMaxInstallTime	*floating point number*	Max time taken to install Tx SAK in seconds.

2.1019 show mac security status

activeProfiles	*integer*	Number of profiles configured in at least one interface.
adminStateEnabled **	*boolean*	Administrative state is enabled. **Since: 4.31.0
delayProtection **	*boolean*	Data delay protection is enabled. **Since: 4.20.5
eapolDestMac **	*MAC address*	MACsec EAPoL destination MAC address. **Since: 4.25.0
[eapolEtherType]	*integer*	MACsec EAPoL Ethernet type.
fipsMode	*boolean*	FIPS Mode is enabled.
[hwLicenseEnabled] **	*boolean*	Hardware license is enabled. **Since: 4.25.2
licenseEnabled **	*boolean*	License is enabled. **Since: 4.21.3
securedInterfaces	*integer*	Number of interfaces running encrypted traffic.

2.1020 show mac source-check invalid

sourceCheckInvalid	*boolean*	Source check invalid Mac.

2.1021 show mac source-check system-mac

sourceCheckCPUMac	*boolean*	Source check CPU Mac.

2.1022 show mac timestamp keyframe profile [...]

profiles	*table(string) = Profile* see 2.1022.1	Keyframe profiles configuration, keyed by name.

2.1022.1 Profile

[egressInterfaces]	*list of Interface name*	Egress interfaces with this profile applied.
[profileConfig]	*ProfileConfig* see 2.1022.1.1	Detailed configuration of the profile.

2.1022.1.1 ProfileConfig

clockSkew	*boolean*	Clock skew is appended to the keyframe.
destinationIp	*IPv4 address*	Destination IPv4 address.
destinationMac	*MAC address*	Destination MAC address.
deviceId	*integer*	Device identifier.
hasDefaultSourceIp	*boolean*	The source IPv4 address is the default one.
interval	*integer*	Number of milliseconds between each keyframe.
sourceIp	*IPv4 address*	Source IPv4 address.
txDropCount	*boolean*	TxDropCount is appended to the keyframe.
vlanId	*integer*	Identifier for a Virtual LAN.

2.1023 show mac traffic-policy field-set [...]

sources	*table(string) = MacTrafficPolicyMacFieldSetSource* see 2.1023.1	Mapping of source name to MAC field set configuration.

2.1023.1 MacTrafficPolicyMacFieldSetSource

macFieldSets	*table(string) = MacTrafficPolicyMacFieldSet* see 2.1023.1.1	Mapping of field set name to MAC address information.

2.1023.1.1 MacTrafficPolicyMacFieldSet

macAddrs	*list of MAC address*	List of all MAC addresses.

2.1024 show mac traffic-policy summary

sources	*table(string) = MacTrafficPolicySourceSummary* see 2.1024.1	A mapping of source path to its configuration.

2.1024.1 MacTrafficPolicySourceSummary

enabled	*boolean*	Enable status of MAC traffic policy.
hostMoveDisabled **	*boolean*	Enable status of Host Move Disable. **Since: 4.35.2
rules	*table(string) = RuleSummary* see 2.1024.1.1	A mapping of rule to its configuration.

2.1024.1.1 RuleSummary

actions	*RuleAction* see 2.1024.1.1.1	Actions of the rule.
matches	*RuleMatch* see 2.1024.1.1.2	Match criteria for the rule.

2.1024.1.1.1 RuleAction

[accessList]	*AccessListAction* see 2.1024.1.1.1.1	Access list information.

2.1024.1.1.1.1 AccessListAction

name	*string*	Access list name.

2.1024.1.1.2 RuleMatch

[macFieldSet]	*MacFieldSet* see 2.1024.1.1.2.1	MAC field set information.

2.1024.1.1.2.1 MacFieldSet

name	*string*	Name of MAC field set.

2.1025 show maintenance

interfaces	*table(Interface name) = MaintenanceStatus* see 2.1025.1.1	Map Interfaces to their Maintenance status.
units	*table(string) = MaintenanceStatus* see 2.1025.1.1	Map Unit name to status.

`vrfs`	*table(string) = MaintenanceProtocolInfo* see 2.1025.1	Map Vrf name to its members and their Maintenance status.

2.1025.1 MaintenanceProtocolInfo

`bgpPeers`	*table(string) = MaintenanceStatus* see 2.1025.1.1	Map Bgp Peers to their Maintenance status.

2.1025.1.1 MaintenanceStatus

`adminState` **	*enum: underMaintenance* | *active*	Admin state of unit under Maintenance. **Since: 4.18.0
`[aggInBpsRate]` **	*integer*	Aggregate input bps rate of the Unit. **Since: 4.18.1
`[aggOutBpsRate]` **	*integer*	Aggregate output bps rate of the Unit. **Since: 4.18.1
`[intfsViolatingTraffic-Threshold]`	*boolean*	Interfaces part of this unit are violating traffic threshold after reaching maintenance.
`[onBootMaintenance]`	*boolean*	Maintenance operation due to on-boot config.
`state`	*enum: init* | *maintenanceModeExit* | *failedEnter* | *failedExit* | *underMaintenance* | *maintenanceModeEnter* | *active*	Operational state of unit under Maintenance.
`stateChangeTime`	*floating point number*	UTC time at which the operational state of Maintenance unit changed.

2.1026 show maintenance bgp (IP_PEER | IP6_PEER | IP6_LL_PEER) [...]

revision 5

vrfs	*table(string) = BgpPeerMaintenanceInfo* see 2.1026.1	Per VRF BGP peer maintenance information.

2.1026.1 BgpPeerMaintenanceInfo

groups	*list of string*	List of Groups that the peer is part of.
peer	*string*	Neighbor address.
routeMapInfo	*RouteMaps* see 2.1026.1.2	Route map information.
routeMapInfoIn **	*RouteMaps* see 2.1026.1.2	Inbound route map information. **Since: 4.24.0
routeMapInfoOut **	*RouteMaps* see 2.1026.1.2	Outbound route map information. **Since: 4.24.0
[selectedProfile]	*string*	Selected profile from BGP groups.
status	*BgpMaintenanceStatusPerPeer* see 2.1026.1.1	BGP Maintenance status of this peer.

2.1026.1.1 BgpMaintenanceStatusPerPeer

asn	*integer*	Autonomous System Number.
peers	*table(string) = BgpPeerMaintenanceStatus* see 2.1026.1.1.1	Dictionary of BGP peer entries indexed by the peer address.
routerId	*IPv4 address*	BGP Router Identity.
vrf	*string*	VRF Name.

2.1026.1.1.1 BgpPeerMaintenanceStatus

[appliedRcf] **	*string*	Maintenance inout RCF applied for the peer. **Since: 4.34.0
[appliedRcfIn] **	*string*	Maintenance inbound RCF applied for the peer. **Since: 4.34.0
[appliedRcfOut] **	*string*	Maintenance outbound RCF applied for the peer. **Since: 4.34.0
[appliedRouteMap]	*string*	Maintenance inout route map applied for the peer.
[appliedRouteMapIn] **	*string*	Maintenance inbound route map applied for the peer. **Since: 4.24.0
[appliedRouteMapOut] **	*string*	Maintenance outbound route map applied for the peer. **Since: 4.24.0

underMaintenance	*boolean*	Peering under maintenance.

2.1026.1.2 RouteMaps

Could also be an instance of:
ConfigSanityRouteMaps 2.1026.1.3

routeMaps	*table(string) = RouteMap* see 2.1026.1.2.1	Route maps by name.

2.1026.1.2.1 RouteMap

entries	*table(numeric string) = RouteMapEntry* see 2.1026.1.2.1.1	Route map entries by sequence number.

2.1026.1.2.1.1 RouteMapEntry

[continueClause]	*boolean*	Continue to next clause.
[continueSeqno]	*integer*	Sequence number of next clause.
description	*list of string*	Route map entry description.
filterType	*enum: deny | permit*	Filter type.
matchRules	*MatchRules* see 2.158.1.3.2.1	Match rules.
setRules	*SetRules* see 2.158.1.3.2.8	Set rules.
[statementName] **	*string*	Statement name for the YANG model. **Since: 4.33.0
[subRouteMap]	*SubRouteMap* see 2.1026.1.2.1.2	Sub route map.

2.1026.1.2.1.2 SubRouteMap

[debugInfo]	*SubRMDebugInfo* see 2.1026.1.2.1.3	Debugging information for sub-route-maps.
[invert]	*boolean*	Invert sub route map result.
name	*string*	Sub route map name.

2.1026.1.2.1.3 SubRMDebugInfo

[name]	*AttributeDebug* see 2.158.1.3.2.6	Debugging information for sub-route-maps.

2.1026.1.3 ConfigSanityRouteMaps

routeMaps	*table(string) = RouteMap* see 2.1026.1.2.1	Route maps by name.

2.1027 show maintenance bgp ip all [...]

revision 2

vrfs	*table(string) = BgpMaintenanceStatus* see 2.1027.1	Per VRF BGP peer maintenance status information.

2.1027.1 BgpMaintenanceStatus

asn	*integer*	Autonomous System Number.
peers	*table(string) = BgpPeerMaintenanceStatus* see 2.1026.1.1.1	Dictionary of BGP peer entries indexed by the peer address.
routerId	*IPv4 address*	BGP Router Identity.
vrf	*string*	VRF Name.

2.1028 show maintenance bgp ipv6 all [...]

revision 2

see 2.1027

2.1029 show maintenance bgp receiver route-map

revision 5

see 2.1026.1.2

2.1030 show maintenance debug [...]

maintenanceEventInfo	*table(string) = MaintenanceEventInfo* see 2.1030.1	Map Unit name to historical information.

2.1030.1 MaintenanceEventInfo

maintEnterEvents	*list of MaintenanceEventInfoEntry* see 2.1030.1.1	Historical information for maintenance enter of unit.
maintExitEvents	*list of MaintenanceEventInfoEntry* see 2.1030.1.1	Historical information for maintenance exit of unit.

2.1030.1.1 MaintenanceEventInfoEntry

eventInfo	*string*	Information about a Maintenance related event.
timeStamp	*floating point number*	Time at which the event occured.

2.1031 show maintenance debug bgp

see 2.1030

2.1032 show maintenance debug bgp (GROUP | IP_PEER | IP6_PEER | IP6_LL_PEER) [...]

see 2.1030

2.1033 show maintenance groups

bgpGroups	*table(string) = BgpGroup* see 2.1033.1	Map group name to BGP Group information.
intfGroups	*table(string) = InterfaceGroup* see 2.1033.2	Map group name to Interface group information.

2.1033.1 BgpGroup

[bgpProfile]	*string*	Bgp profile associated with group.
neighbors	*table(string) = BgpNeighbors* see 2.1033.1.1	Map Peer Type to list of Peers, where peer type, the key, could be either peerGroup, peerIpv4 or peerIpv6.
origin	*enum: userConfigured | builtin*	origin of this group.
units	*list of string*	List of Maintenance units of which this group is a member of.
vrfName	*string*	Name of the Vrf.

2.1033.1.1 BgpNeighbors

peers	*list of string*	List of peers, which could be either peer groups, IPv4 or IPv6 peers.

2.1033.2 InterfaceGroup

bgpProfile	*string*	BGP Maintenance Profile for this group.
interfaces	*list of string*	List of Interfaces in the group.
intfProfile	*string*	Interface Maintenance Profile for this group.
origin	*enum: userConfigured | builtin*	origin of this group.
units	*list of string*	List of Maintenance Units of which this group is a member of.

2.1034 show maintenance groups bgp [...]

bgpGroups	*table(string) = BgpGroup* see 2.1033.1	Map group name to BGP Group information.

2.1035 show maintenance groups interface [...]

intfGroups	*table(string) = InterfaceGroup* see 2.1033.2	Map group name to Interface Group information.

2.1036 show maintenance interface [...]

interfaces	*table(Interface name) = MaintenanceInterfaceBrief* see 2.1036.1	Maintenance mode information for interfaces.

2.1036.1 MaintenanceInterfaceBrief

adminState **	*enum: underMaintenance | active*	Maintenance admin state of this interface. **Since: 4.18.0
[lastInBpsRate]	*floating point number*	Input bps rate.
[lastOutBpsRate]	*floating point number*	Output bps rate.
[maintDownTime]	*floating point number*	Time at which the interface was shutdown for maintenance.
state	*enum: init | maintenanceModeExit | failedEnter | failedExit | underMaintenance | maintenanceModeEnter | active*	Maintenance operational state of this interface.
[trafficAboveThreshold]	*boolean*	Indicates if the traffic on the interface is above threshold.

2.1037 show maintenance interface detail [...]

revision 2

interfaces	*table(Interface name)* = *MaintenanceInterfaceStatus* see 2.1037.1	Maintenance mode information for interfaces.

2.1037.1 MaintenanceInterfaceStatus

adminState	*enum: underMaintenance* | *active*	Maintenance admin state of this interface.
[bgpProfile]	*string*	Name of the BGP Maintenance Profile applied during Maintenance.
[bgpStatus]	*MaintenanceInterfaceBgpStatus* see 2.1037.1.1	BGP status for the interface.
groups	*list of string*	Groups that the interface is part of.
history	*list of string*	Historical information for dynamic interface unit.
[intfProfile]	*string*	Name of the Interface Maintenance Profile applied during Maintenance.
[rateMonStatus]	*MaintenanceInterfaceRateMonStatus* see 2.1037.1.2	Rate Monitoring status for the interface.
[state]	*enum: init* | *maintenanceModeExit* | *failedEnter* | *failedExit* | *underMaintenance* | *maintenanceModeEnter* | *active*	Maintenance operational state of this interface.

2.1037.1.1 MaintenanceInterfaceBgpStatus

maintState	*enum: init* | *maintenanceModeExit* | *failedEnter* | *failedExit* | *underMaintenance* | *maintenanceModeEnter* | *active*	Maintenance State of the Interface.
peers	*table(string)* = *MaintenanceInterfaceBgpPeerStatus* see 2.1037.1.1.1	Maintenance state of the peers on this interface.
vrf	*string*	VRF Name.

2.1037.1.1.1 MaintenanceInterfaceBgpPeerStatus

[appliedRcf] **	*string*	Maintenance RCF applied for the peer. **Since: 4.34.0
[appliedRcfIn] **	*string*	Maintenance inbound RCF applied for the peer. **Since: 4.34.0

[appliedRcfOut] **	*string*	Maintenance outbound RCF applied for the peer. **Since: 4.34.0
[appliedRouteMap]	*string*	Maintenance routemap applied for the peer.
[appliedRouteMapIn] **	*string*	Maintenance inbound routemap applied for the peer. **Since: 4.24.0
[appliedRouteMapOut] **	*string*	Maintenance outbound routemap applied for the peer. **Since: 4.24.0

2.1037.1.2 MaintenanceInterfaceRateMonStatus

lastInBpsRate	*floating point number*	Input bps rate.
lastOutBpsRate	*floating point number*	Output bps rate.
lastSampleTime	*floating point number*	The time at which the last sample was taken.
[maintDownTime]	*floating point number*	Time at which the interface was shutdown for maintenance.
numSamplesAboveThreshold-PostMaint	*integer*	Number of samples above threshold, after maintenance.
numSamplesAboveThreshold-PreMaint	*integer*	Number of samples above threshold, before maintenance.
numSamplesBelowThreshold-PostMaint	*integer*	Number of samples below threshold, after maintenance.
numSamplesBelowThreshold-PreMaint	*integer*	Number of samples below threshold, before maintenance.
profile	*string*	Name of the Interface profile being used to monitor the interface.
startTime	*floating point number*	The time at which rate monitoring was started for this interface.
state	*enum: monitorPassive | monitorStop | monitorThreshold | monitorInit*	State of traffic rate monitoring for the interface.
stateTime	*floating point number*	The time at which the state was entered.
totalSamples	*integer*	Total number of samples collected so far.

2.1038 show maintenance profiles

bgpProfiles	*table(string) = BgpProfile* see 2.1038.1	Map profile name to BGP Profile information.
intfProfiles	*table(string) = InterfaceProfile* see 2.1038.2	Map profile name to Interface Profile information.
unitProfiles	*table(string) = UnitProfile* see 2.1038.3	Map profile name to Unit Profile information.

2.1038.1 BgpProfile

rcfIn **	*string*	Inbound initiator RCF for BGP profile. **Since: 4.34.0
rcfInOut **	*string*	Initiator RCF for BGP profile. **Since: 4.34.0
rcfOut **	*string*	Outbound initiator RCF for BGP profile. **Since: 4.34.0
routeMapIn **	*string*	Inbound initiator route map for BGP profile. **Since: 4.24.0
routeMapInOut	*string*	Initiator route map for BGP profile.
routeMapOut **	*string*	Outbound initiator route map for BGP profile. **Since: 4.24.0

2.1038.2 InterfaceProfile

rateMonLoadInterval	*integer*	Duration, in seconds, for which the traffic needs to remain below the threshold before the interface can be declared to be under maintenance.
rateMonThreshold	*floating point number*	Traffic threshold, in Kbps.
shutdown	*boolean*	Whether to shutdown interface when the traffic goes below threshold.
shutdownMaxDelay	*floating point number*	Maximum time to wait, in seconds, before shutting down the interface, if shutdown is configured.

2.1038.3 UnitProfile

onBootDuration	*integer*	Duration, in seconds, for which the unit will be under maintenance on boot.
onBootEnabled	*boolean*	Whether onboot is enabled or not.

2.1039 show maintenance profiles bgp [...]

bgpProfiles	*table(string) = BgpProfile* see 2.1038.1	Map BGP Profile name to BGP Profile information.

2.1040 show maintenance profiles bgp default

revision 5

profileName	*string*	Profile name.
[rcf] **	*string*	Default RCF function. **Since: 4.34.0
[rcfIn] **	*string*	Default inbound RCF function. **Since: 4.34.0
[rcfOut] **	*string*	Default outbound RCF function. **Since: 4.34.0

[routeMap]	*string*	Default route map name.
[routeMapIn] **	*string*	Default inbound route map name. **Since: 4.24.0
routeMapInfo	*RouteMaps* see 2.1026.1.2	Route map information.
routeMapInfoIn **	*RouteMaps* see 2.1026.1.2	Inbound route map information. **Since: 4.24.0
routeMapInfoOut **	*RouteMaps* see 2.1026.1.2	Outbound route map information. **Since: 4.24.0
[routeMapOut] **	*string*	Default outbound route map name. **Since: 4.24.0

2.1041 show maintenance profiles interface [...]

intfProfiles	*table(string) = InterfaceProfile* see 2.1038.2	Map Interface Profile name to Interface Profile information.

2.1042 show maintenance profiles interface default

[profileAttributes]	*InterfaceProfile* see 2.1038.2	Attributes of the default Interface profile.
profileName	*string*	Default Interface Profile Name.

2.1043 show maintenance profiles unit [...]

unitProfiles	*table(string) = UnitProfile* see 2.1038.3	Map Unit Profile name to Unit Profile.

2.1044 show maintenance profiles unit default

[profileAttributes]	*UnitProfile* see 2.1038.3	Attributes of the default Unit profile.
profileName	*string*	Default Unit Profile Name.

2.1045 show maintenance stages [...]

maintenanceEnterStages	*list of MaintenanceStage* see 2.1045.1	List of Maintenance enter stages.
maintenanceExitStages	*list of MaintenanceStage* see 2.1045.1	List of Maintenance exit stages.

2.1045.1 MaintenanceStage

stageDescription	*string*	Maintenance stage description.
stageName	*string*	Maintenance stage name.

2.1046 show maintenance summary

intfDirectlyInMaintenance	*table(string) = integer*	Map Maintenance States to number of Interfaces directly put in Maintenance.
numUnitsConfigured	*integer*	Number of Units configured.
peerDirectlyInMaintenance	*table(string) = integer*	Map Maintenance States to number of Peers directly put in Maintenance.
[rateMonSummary]	*MaintenanceRateMonSummary* see 2.1046.1	Interface Rate Monitoring summary.
unitStatistics	*table(string) = integer*	Map different Maintenance States to number of Units.

2.1046.1 MaintenanceRateMonSummary

numIntfsEnterMaint	*integer*	Number of interfaces entering maintenance.
numIntfsMaintDown	*integer*	Number of interfaces shutdown for maintenance.
numIntfsThresholdViolation	*integer*	Number of interfaces which violated the traffic threshold after going under maintenance.
numIntfsUnderMaint	*integer*	Number of interfaces under maintenance.

2.1047 show maintenance units [...]

maintenanceUnits	*table(string) = MaintenanceUnit* see 2.1047.1	Map Unit name to Unit.

2.1047.1 MaintenanceUnit

adminState **	*enum: underMaintenance | active*	Admin state of the Maintenance Unit. **Since: 4.18.0
bgpGroups	*list of string*	List of Bgp Groups.
history	*list of MaintenanceEventInfoEntry* see 2.1030.1.1	Historical information for unit.
interfaceGroups	*list of string*	List of Interface Groups.
[intfsViolatingTraffic-Threshold]	*list of Interface name*	List of interfaces which are violating traffic threshold.
[onBootExitTime]	*floating point number*	Exit time of on-boot maintenance.
[onBootMaintenance]	*boolean*	Maintenance operation due to on-boot config.
[origin]	*enum: userConfigured | builtin*	origin of this unit.
state	*enum: init | maintenanceModeExit | failedEnter | failedExit | underMaintenance | maintenanceModeEnter | active*	Operational state of the Maintenance Unit.

[timeOfStateChange]	*floating point number*	Time since last state change.
[totalIntfTraffic-Violations]	*integer*	Number of interfaces which have violated traffic threshold since maintenance.
unitProfile	*string*	Name of the Unit Maintenance Profile applied during Maintenance.

2.1048 show management api eos-sdk-rpc

enabled	*boolean*	Aggregate transports enabled.
transports	*table(string) = EosSdkRpcTransportStatus* see 2.1048.1	Transports indexed by name.

2.1048.1 EosSdkRpcTransportStatus

allServicesEnabled	*boolean*	All EosSdkRpc services are enabled.
[configErrors]	*ConfigurationErrors* see 2.1048.1.1	Configuration error which occurred before starting the gRPC server.
enabled	*boolean*	Transport is enabled.
[enabledServices]	*EnabledServices* see 2.1048.1.2	Explicitly enabled EosSdkRpc services.
[endpoints]	*ListeningEndpoints* see 2.1048.1.3	The endpoints this transport is listening on.
metadataUserAuth	*enum: secureChannelOnly | disabled*	Certificate username authentication.
[pid]	*integer*	The PID of the process, if the agent is running.
running	*boolean*	Transport is running.
serverSecurity	*enum: tls | mtls | insecure | unknown*	Type of security channel in place.
[sslProfile]	*string*	SSL profile name.

2.1048.1.1 ConfigurationErrors

[invalidSslProfileState]	*boolean*	Invalid SSL profile configured for this transport.
[localIntfAddressInUse]	*boolean*	Local interface IP address and port are already in use by another process.
[loopbackAddressInUse]	*boolean*	Local interface IP address and port is already in use by another process.
[loopbackVrfSkipped]	*boolean*	Listener for localhost loopback is not enabled, due to conflicting VRF configuration.
[noSslCertOrKeyFile]	*boolean*	Could not locate the certificate or key for the configured SSL profile.
[noSslProfileFound]	*boolean*	No SSL profile found for the configured SSL profile name.
[noTrustedCertsFound]	*boolean*	No trusted certificate found for the configured SSL profile.
[noValidAddresses]	*boolean*	No valid addresses are configured to listen on.
[unavailableActiveIp]	*boolean*	Local interface is not configured with an available IP address.
[unixSocketInUse]	*boolean*	UNIX Domain Socket is already in use by another process.

2.1048.1.2 EnabledServices

[aclService]	*boolean*	AclService is enabled.
[agentService]	*boolean*	AgentService is enabled.
[bgpLinkWeightService] **	*boolean*	BgpLinkWeightService is enabled. **Since: 4.34.2
[bgpPathService]	*boolean*	BgpPathService is enabled.
[bgpService]	*boolean*	BgpService is enabled.
[classMapService] **	*boolean*	ClassMapService is enabled. **Since: 4.32.1
[eapiService]	*boolean*	EapiService is enabled.
[ethLagIntfService]	*boolean*	EthLagIntfService is enabled.
[ethPhyIntfCountersService]	*boolean*	EthPhyIntfCountersService is enabeld.
[ethPhyIntfService]	*boolean*	EthPhyIntfService is enabled.
[fastService]	*boolean*	FastService is enabled.
[fibOverrideService] **	*boolean*	FibOverrideService is enabled. **Since: 4.34.2
[intfCounterService]	*boolean*	IntfCounterService is enabled.
[intfService]	*boolean*	IntfService is enabled.
[ipIntfService]	*boolean*	IpIntfService is enabled.
[ipRouteService]	*boolean*	IpRouteService is enabled.
[isisInterfaceService] **	*boolean*	IsisInterfaceService is enabled. **Since: 4.35.0
[macsecService]	*boolean*	MacsecService is enabled.
[mplsRouteService]	*boolean*	MplsRouteService is enabled.
[mplsVrfLabelService]	*boolean*	MplsvrfLabelService is enabled.
[nexthopGroupService]	*boolean*	NexthopGroupService is enabled.
[policyMapCountersService]	*boolean*	PolicyMapServiceCounterService is enabled.
[policyMapService]	*boolean*	PolicyMapService is enabled.

2.1048.1.3 ListeningEndpoints

[localInterface]	*LocalInterfaceEndpoint* see 2.1048.1.3.2	Listening local interface endpoint details.
[localhostLoopback]	*IpEndpoint* see 2.1048.1.3.1	Listening local host loopback endpoint details.
[localhostUnixSocket]	*LocalhostUnixSocketEndpoint* see 2.1048.1.3.3	Local host loopback endpoint details.
vrfName	*string*	The VRF this transport is listening in.

2.1048.1.3.1 IpEndpoint

Could also be an instance of:
LocalInterfaceEndpoint 2.1048.1.3.2

ipAddress	*IP address*	IP address for gRPC to listen on.
isListening	*boolean*	This endpoint is listening for incoming connections.
port	*integer*	The port this transport is listening on.

2.1048.1.3.2 LocalInterfaceEndpoint

intfId	*interface name*	Listening interface ID.
ipAddress	*IP address*	IP address for gRPC to listen on.
isListening	*boolean*	This endpoint is listening for incoming connections.
port	*integer*	The port this transport is listening on.

2.1048.1.3.3 LocalhostUnixSocketEndpoint

isListening	*boolean*	This endpoint is listening for incoming connections.
socketPath	*string*	Unix domain socket path to listen on.

2.1049 show management api gnmi

revision 3

enabled	*boolean*	Aggregate transports enabled.
grpctunnelClients	*table(string) = GrpctunnelClientStatus* see 2.1049.2	gRPC-tunnel clients indexed by name.
octa	*boolean*	Octa enabled.
setNamespace **	*boolean*	Set namespace enabled. **Since: 4.34.2
setPersistence	*boolean*	Set is persistent.
transports	*table(string) = GnmiEndpointStatus* see 2.1049.1	Transports indexed by name.

2.1049.1 GnmiEndpointStatus

accounting	*boolean*	RPC requests accounting.
authnUsernamePriority	*list of string*	Authentication username extraction priority.
authorization	*boolean*	per-RPC authorization.
connectionLimit **	*integer*	gRPC connection limit. **Since: 4.35.2
enabled	*boolean*	Endpoint is enabled.
error	*string*	error which occurred while starting the endpoint.
listenAddrs	*list of IpGenericAddr* see 2.365.1.1.1.1	Addresses for gRPC to listen on.
port	*integer*	The port this protocol's server is listening on.
qosDscp	*integer*	The QoS DSCP value.
skipEapiAaa **	*boolean*	Skip AAA for EAPI commands. **Since: 4.34.2
sslProfile	*string*	SSL profile name.
useNotifSendTime	*boolean*	Subscription notification timestamp.
vrfName	*string*	The VRF this protocol's server is listening in.

2.1049.2 GrpctunnelClientStatus

destinationHost	*string*	Destination address the client is dialing to.
destinationPort	*integer*	Destination port the client is dialing to.
enabled	*boolean*	gRPC-tunnel dial-out client is enabled.
error	*string*	Error which occurred while starting the gRPC-tunnel dial-out client.
gnmiSslProfile	*string*	SSL profile used by the gNMI server.
localAddressAndPort	*IpGenericAddrAndPort* see 2.365.1.1.1.2	Local address/port the client is dialing from.
localInterface	*interface name*	Local interface the client is dialing from.
status	*string*	Status of the gRPC-tunnel dial-out client.

targetId	*string*	Target ID used by the gRPC-tunnel connection.
tunnelSslProfile	*string*	SSL profile used by the tunnel.
vrf	*string*	VRF of the gRPC-tunnel dial-out client.

2.1050 show management api gnmi access-list [...]

revision 2

transports	*table(string) = AllAclList* see 2.62	Transport ACLs indexed by transport name.

2.1051 show management api gnpsi

enabled	*boolean*	Aggregate transports enabled.
transports	*table(string) = GnpsiTransportStatus* see 2.1051.1	Transports indexed by name.

2.1051.1 GnpsiTransportStatus

accounting	*boolean*	Accounting enabled for this transport.
authnUsernamePriority	*list of string*	Authentication username extraction priority.
configErrors	*ConfigurationErrors* see 2.1051.1.1	Configuration error which occurred before starting the gRPC server.
enabled	*boolean*	Transport is enabled.
port	*integer*	Port number of all listener IP addresses.
running	*boolean*	Transport is running.
securityType	*enum: tls | mtls | insecure | unknown*	Type of security channel in place.
source	*enum: sflow | unknown*	The source sampling agent for this collector.
sslProfile	*string*	SSL profile name.
statistics	*TransportStatistics* see 2.1051.1.3	Per source statistics for this transport.
vrfs	*table(string) = ListenVrfs* see 2.1051.1.2	All configured listeners indexed by VRF.

2.1051.1.1 ConfigurationErrors

[invalidPort]	*boolean*	Invalid port configured.
[invalidSslProfile]	*boolean*	Invalid SSL profile configured for this transport.
[listenerAlreadyInUse]	*boolean*	Listening addresses are already in use.
[noCollectorSource]	*boolean*	No source configured for this collector.
[noSslProfileFound]	*boolean*	No SSL profile found for the configured SSL profile name.

2.1051.1.2 ListenVrfs

ipAddrs	*list of IP address*	The addresses that this transport is actively listening on.
skippedAddrs	*list of IP address*	The addresses that this transport failed to listen on.

2.1051.1.3 TransportStatistics

[sflow]	*Statistics* see 2.1051.1.3.1	Sflow related collector statistics.

2.1051.1.3.1 Statistics

activeClientSubscriptions	*integer*	Number of active client subscriptions.

droppedDatagrams	*integer*	Number of detected dropped datagrams.
receivedDatagrams	*integer*	Number of datagrams received.

2.1052 show management api gnsi

acctzEnabled **	*boolean*	Acctz service is enabled. **Since: 4.32.2
acctzHistoryLimit **	*integer*	Acctz records history limit. **Since: 4.32.2
attestzEnabled **	*boolean*	Attestz service is enabled. **Since: 4.34.2
authzEnabled	*boolean*	Authz service is enabled.
authzPolicy	*boolean*	Authz policy exists/is configured.
certzEnabled	*boolean*	Certz service is enabled.
credentialzEnabled	*boolean*	Credentialz service is enabled.
enrollzEnabled **	*boolean*	Enrollz service is enabled. **Since: 4.34.2
pathzEnabled **	*boolean*	Pathz service is enabled. **Since: 4.32.2
transports	*table(string) = GnsiEndpointStatus* see 2.1052.1	Transports indexed by name.

2.1052.1 GnsiEndpointStatus

enabled	*boolean*	Endpoint is enabled.
error	*string*	error which occurred while starting the endpoint.
port	*integer*	The port this protocol's server is listening on.
vrfName	*string*	The VRF this protocol's server is listening in.

2.1053 show management api gribi

revision 2

accountingRequests **	*boolean*	gRIBI RPC accounting requests is enabled. **Since: 4.33.0
authnUsernamePriority	*list of string*	Authentication username extraction priority.
authzEnabled **	*boolean*	policy based gRPC authorization is enabled. **Since: 4.33.1
dscp	*integer*	The DSCP value set for outgoing packets.
enabled	*boolean*	The endpoint is enabled.
[error]	*string*	Error which occurred while starting the endpoint.
lastServiceStartTimeStamp	*floating point number*	Timestamp of last grpc service start.
mTls **	*boolean*	gRIBI server is running mTLS. **Since: 4.32.2
port	*integer*	The port this protocol's server is listening on.
[rpcStatus]	*GribiRpcStatus* see 2.1053.1	gRIBI RPC server and client status.
[serviceAcl]	*string*	The access control group to filter which gRIBI clients can connect via IPv4.
[serviceAclV6]	*string*	The access control group to filter which gRIBI clients can connect via IPv6.
[sslProfile]	*string*	SSL profile name.
started	*boolean*	gRIBI server is started.
vrfName	*string*	The VRF this protocol's server is listening in.

2.1053.1 GribiRpcStatus

highestElectionId	*GribiElectionId* see 2.1053.1.1	Highest election ID received so far.
highestElectionIdTimeStamp	*floating point number*	Timestamp when highest election ID is received.
modifyRpcClients	*table(IPv4 or IPv6 address) = GribiModifyRpcClientIpStatus* see 2.1053.1.2	Map of Modify RPC client status, keyed by client IP.
primaryClientId	*integer*	Current Modify RPC primary client internal ID.
[primaryClientIp]	*IP address*	Current Modify RPC primary client IP address.
[primaryClientPort]	*integer*	Current Modify RPC primary client port.
totalClients	*integer*	Total number of Modify RPC client connections.

2.1053.1.1 GribiElectionId

high	*integer*	High 64 bits of the 128-bit election ID.
low	*integer*	Low 64 bits of the 128-bit election ID.

2.1053.1.2 GribiModifyRpcClientIpStatus

ports	*table(numeric string) = GribiModifyRpcClientIpPortStatus* see 2.1053.1.2.1	Map of Modify RPC status, keyed by port.

2.1053.1.2.1 GribiModifyRpcClientIpPortStatus

streams	*table(numeric string) = GribiModifyRpcStreamStatus* see 2.1053.1.2.1.1	Map of Modify RPC stream status, keyed by stream ID.

2.1053.1.2.1.1 GribiModifyRpcStreamStatus

[aftOpAckTypeApplied]	*enum: ribAndFibAck | ribAck | invalid*	AFT operation acknowledgement type applied.
[aftOpAckTypeRequested]	*enum: ribAndFibAck | ribAck | invalid*	AFT operation acknowledgement type requested.
[aftPersistence]	*enum: preserve | delAft | invalid*	AFT persistence.
[clientRedundancy]	*enum: invalid | singlePrimary | allPrimary*	Client redundancy.
connectionTimeStamp	*floating point number*	Timestamp when the stream connected.
[electionId]	*GribiElectionId* see 2.1053.1.1	Election ID received.
[electionIdTimeStamp]	*floating point number*	Timestamp when election ID is received.
lastAftOpTimeStamp	*floating point number*	Timestamp of last AFT operation received.
sessionParamsTimeStamp	*floating point number*	Timestamp when session parameters are received.

2.1054 show management api gribi access-list [...]

transports	*table(string) = AllAclList* see 2.62	Transport ACLs indexed by transport name.

2.1055 show management api http-commands

[bufferSize] **	*integer*	The send and receive buffer size for TCP session. **Since: 4.33.2
bytesIn	*integer*	The number of bytes received from HTTP requests.
bytesOut	*integer*	The number of bytes sent in HTTP responses.
commandCount	*integer*	The number of CLI commands requested to run.
[corsOrigins]	*list of string*	Allowed CORS Origins. Present when CORS is supported.
[dscpValue]	*integer*	The QoS DSCP value set in outgoing IP packets.
enabled	*boolean*	Whether the server is globally enabled.
executionTime	*floating point number*	The time in seconds spent executing CLI commands.
[fipsEnabled]	*boolean*	Whether FIPS mode is enabled for HTTPS algorithms.
hitCount	*integer*	The number of incoming HTTP requests the server has seen.
httpServer	*HttpProtocolStatus* see 2.1055.1	The status of the HTTP server.
httpsServer	*HttpProtocolStatus* see 2.1055.1	The status of the HTTPS server.
iframeAncestors	*list of string*	Allowed Iframe ancestors.
[lastHitTime]	*floating point number*	The UTC timestamp of the last request.
[localHttpServer]	*HttpProtocolStatus* see 2.1055.1	The status of the localhost HTTP server.
logLevel **	*enum: notice | crit | warn | none | alert | info | debug | emerg | error*	Logging level for the HTTP server. **Since: 4.20.0
requestCount	*integer*	The number of valid JSON-RPC requests received.
sessionTimeout **	*integer*	The user session's expiry timeout in minutes. **Since: 4.33.0
[sslProfile]	*SslProfile* see 2.1055.2	The configuration and status of the SSL profile.
tlsProtocol	*list of string*	Allowed TLS protocol versions.
[unixSocketServer]	*UnixProtocolStatus* see 2.1055.3	The status of the Unix Domain Socket server.
urls	*list of string*	URLs the server is listening on.
users	*table(string) = UserStatistics* see 2.1055.4	Mapping from username to statistics about that user.
vrf	*string*	The VRF the API is configured to serve in.
vrfs **	*list of string*	All VRFs enabled in CAPI. **Since: 4.20.0

2.1055.1 HttpProtocolStatus

`configured`	*boolean*	Whether this protocol is configured to be enabled.
`port`	*integer*	The port this protocol's server is listening on.
`running`	*boolean*	Whether this protocol is currently serving and accepting requests.

2.1055.2 SslProfile

`configured`	*boolean*	Whether this profile is configured in SSL Manager.
`name`	*string*	SSL profile name.
`[state]`	*enum: valid | updating | invalid*	State of the SSL profile.

2.1055.3 UnixProtocolStatus

`configured`	*boolean*	Whether this protocol is configured to be enabled.
`running`	*boolean*	Whether this protocol is currently serving and accepting requests.

2.1055.4 UserStatistics

`bytesIn`	*integer*	The number of bytes received from the user's requests.
`bytesOut`	*integer*	The number of bytes sent in responses to the user.
`lastHitTime`	*floating point number*	The UTC timestamp of the user's last request.
`requestCount`	*integer*	Number of requests received from the user.

2.1056 show management api http-commands ((ip access-list) | (ipv6 access-list)) [...]

see 2.62

2.1057 show management api http-commands https certificate

revision 2

`certificate`	*string*	Certificate used by SSL/TLS.

2.1058 show management api http-commands https cipher

`enabledCipherSuites`	*list of CipherSuite* see 2.1058.1	Enabled CipherSuites.

2.1058.1 CipherSuite

cipherSuite	*enum: TLS_PSK_WITH_AES_256_CCM* | *TLS_DHE_PSK_WITH_ARIA_256_GCM_SHA384* | *TLS_PSK_WITH_AES_128_GCM_SHA256* | *TLS_DHE_PSK_WITH_AES_128_CBC_SHA* | *TLS_ECDHE_RSA_WITH_CAMELLIA_256_CBC_SHA384* | *TLS_DHE_RSA_WITH_AES_128_CBC_SHA* | *TLS_DH_anon_WITH_AES_128_CBC_SHA256* | *TLS_DHE_RSA_WITH_CAMELLIA_128_CBC_SHA* | *TLS_ECDHE_ECDSA_WITH_ARIA_256_GCM_SHA384* | *TLS_PSK_WITH_AES_256_CCM_8* | *TLS_PSK_WITH_AES_128_CBC_SHA256* | *TLS_SRP_SHA_WITH_AES_128_CBC_SHA* | *TLS_SRP_SHA_WITH_AES_256_CBC_SHA* | *TLS_RSA_WITH_RC4_128_MD5* | *TLS_ECDHE_PSK_WITH_AES_128_CBC_SHA* | *TLS_PSK_WITH_CAMELLIA_128_CBC_SHA256* | *TLS_DHE_DSS_WITH_CAMELLIA_128_CBC_SHA256* | *TLS_DHE_PSK_WITH_AES_256_GCM_SHA384* | *TLS_RSA_PSK_WITH_AES_128_GCM_SHA256* | *TLS_ECDHE_PSK_WITH_CHACHA20_POLY1305_SHA256* | *TLS_DHE_DSS_WITH_ARIA_128_GCM_SHA256* | *TLS_DH_anon_WITH_AES_256_CBC_SHA256* | *TLS_ECDHE_PSK_WITH_CAMELLIA_128_CBC_SHA256* | *TLS_DHE_RSA_WITH_AES_128_CCM_8* | *TLS_DHE_PSK_WITH_AES_256_CBC_SHA* | *TLS_DHE_DSS_WITH_AES_256_GCM_SHA384* | *TLS_PSK_WITH_CHACHA20_POLY1305_SHA256* |	CipherSuite Name.

2.1059 show management api http-commands https diffie-hellman

`diffieHellmanParameters`	*string*	Parameters used by SSL/TLS for diffie-hellman key exchange.

2.1060 show management api models

revision 2

aclOptions **	*AclOptions* see 2.1060.1	Set of ACL options. **Since: 4.33.2
aftIPv4Unicast	*boolean*	IPv4 Unicast is enabled for AFT.
aftIPv6Unicast	*boolean*	IPv6 Unicast is enabled for AFT.
aftMpls **	*boolean*	MPLS is enabled for AFT. **Since: 4.28.1
aftRouteSummary **	*boolean*	OpenConfig route summary is enabled for AFT. **Since: 4.30.1
cpuCountersEapiInterval-Minutes **	*integer*	Interval used to summarise CPU counters queue in minutes. **Since: 4.32.0
defaultLeafVisible **	*boolean*	Visibility of default leafs. **Since: 4.32.2
disabledAirStreamPaths **	*list of string*	List of disabled AirStream paths. **Since: 4.35.2
disabledSmashPaths	*list of string*	List of disabled Smash paths.
disabledSysdbPaths	*table(string) = SysdbExcludesStatus* see 2.1060.5	A mapping of a disabled Sysdb path to its status.
enabledSmashPaths	*list of string*	List of enabled Smash paths.
exclusiveModuleGroups **	*list of string*	List of exclusive YANG module groups. **Since: 4.31.2
ipfixOptions **	*IpfixOptions* see 2.1060.2	Set of IPFIX options. **Since: 4.26.2
isisOptions **	*IsisOptions* see 2.1060.3	Set of IS-IS options. **Since: 4.28.2
sflowOptions **	*SflowOptions* see 2.1060.4	Set of sFlow options. **Since: 4.26.2
yangPaths **	*table(string) = boolean*	A mapping of a YANG path to whether it is explicitly enabled. **Since: 4.27.2

2.1060.1 AclOptions

[trafficPolicy]	*boolean*	Set if Traffic Policy is the provider.

2.1060.2 IpfixOptions

[address]	*string*	Listening address for the collector.
[domain]	*string*	Domain value used by the collector.
enableCollector	*boolean*	The collector is enabled.
[flowLifetime]	*integer*	Lifetime (in seconds) of entries in internal flow table.
[flowTableSize]	*integer*	Maximum number of entries in internal flow table.
[port]	*integer*	Listening port for the collector.

2.1060.3 IsisOptions

linkStateDatabase	*boolean*	Set if Link State Database is enabled.

2.1060.4 SflowOptions

[address]	*string*	Listening address for the collector.
[domain]	*string*	Domain value used by the collector.
enableCollector	*boolean*	The collector is enabled.
[flowLifetime]	*integer*	Lifetime (in seconds) of entries in internal sample table.
[flowTableSize]	*integer*	Maximum number of entries in internal sample table.
[port]	*integer*	Listening port for the collector.

2.1060.5 SysdbExcludesStatus

status	*enum: unknown* | *ok* | *error*	Status of the excluded Sysdb path.

2.1061 show management api netconf

enabled	*boolean*	Endpoint is enabled.
error	*string*	error which occurred while starting the endpoint.
port	*integer*	The port this protocol's server is listening on.
vrfName	*string*	The VRF this protocol's server is listening in.

2.1062 show management api restconf

enabled	*boolean*	Endpoint is enabled.
error	*string*	error which occurred while starting the endpoint.
port	*integer*	The port this protocol's server is listening on.
qosDscp **	*integer*	The QoS DSCP value. **Since: 4.21.0
sslProfile	*string*	SSL profile name.
vrfName	*string*	The VRF this protocol's server is listening in.

2.1063 show management api restconf access-list [...]

see 2.62

2.1064 show management archive

revision 2

destName	*string*	Nickname of the archival destination.
destPath	*string*	Absolute path of the archival destination.
devForceDisabled	*boolean*	Using the device is not allowed. This is only relevant of the ssd drive.
devMounted	*boolean*	The installed device is mounted.
devName	*string*	Name of the device containing the archival destination.
devPhysical	*boolean*	The device is physical.
devPresent	*boolean*	The device is present on the switch.
exists	*boolean*	The archive symlink and directory tree exist and have the right permissions.
fileArchivalEnabled **	*boolean*	EOS file archival is enabled. **Since: 4.25.1
fsMntPt	*string*	Mountpoint of the filesystem.
fsQuotaMount	*boolean*	The filesystem is mounted with quotas.
fsSize	*integer*	Size of the filesystem in Kibibytes.
fsUsedKiB	*integer*	Filesystem used space in Kibibytes.
fsUsedPct	*integer*	Filesystem used space as a percentage.
quotaKiB	*integer*	Quota limit in Kibibytes.
quotaOn	*boolean*	Quota are enabled for the filesystem.
quotaPct	*integer*	Quota limit as a percentage.
shutdown	*boolean*	True if file archival is disabled.
usedKiB	*integer*	Archive space usage in Kibibytes.
usedPct	*integer*	Archive space usage as a percentage.

2.1065 show management cvx

revision 3

clusterStatus	*MgmtCvxClusterStatus* see 2.1065.1	Management CVX Cluster status.
[secondaryClusterStatus]	*MgmtCvxClusterStatus* see 2.1065.1	Management Secondary CVX Cluster status.

2.1065.1 MgmtCvxClusterStatus

controllerStatuses	*table(string) = ControllerStatus* see 2.1065.1.1	Controller connection status.
cvxClusterName	*string*	Name of the CVX cluster.
enabled	*boolean*	CVX client state.
heartbeatInterval	*floating point number*	Heartbeat interval in seconds.
heartbeatTimeout	*floating point number*	Heartbeat timeout in seconds.
sourceIntf	*string*	source-interface name.
[sourceIntfAddr]	*IPv4 address*	source-interface address.
[sslProfileStatus]	*SslProfileStatus* see 2.1065.1.2	SSL profile status.
[vrfName]	*string*	VRF used to connect to CVX.

2.1065.1.1 ControllerStatus

[connectionTime]	*floating point number*	Connection establishment UTC timestamp.
controllerUUID	*string*	Controller UUID.
[duplicatedConnection]	*boolean*	Multiple host entries for the same server.
heartbeatStatus	*HeartbeatStatus* see 2.340.1.1	Heartbeat status of the controller.
hostname **	*string*	Controller hostname. **Since: 4.27.0
[ibConnectionSecured]	*boolean*	Whether in-band connection is SSL secured.
[lastLeaderChangeTs]	*floating point number*	Last leader switchover UTC timestamp.
[leader]	*boolean*	Leader of the CVX cluster.
negotiatedVersion	*integer*	Negotiated version.
[oobConnectionSecured]	*boolean*	Whether out-of-band connection is SSL secured.
oobConnectionStatus	*enum: negotiating* | *established* | *shutdown* | *connecting* | *disconnecting*	Out-of-band connection status.
versionCompatibility	*enum: unnegotiated* | *incompatible* | *inNegotiation* | *compatible*	Compatibility of switch with controller.

2.1065.1.2 SslProfileStatus

[disableReason]	*enum: profileNotExist* | *noError* | *certNotConfigured* | *profileInvalid* | *trustedCertNotConfigured* | *dhparamsNotReady*	Reason for disabled SSL profile.
enabled	*boolean*	Whether SSL profile is enabled.
sslProfileName	*string*	SSL profile name.

2.1066 show management cvx debug pingpong

see 2.344

2.1067 show management cvx mounts

mountStates	*list of MountState* see 2.347.1.1.1.1	State of CVX published mounts.

2.1068 show management cvx service

services	*list of MgmtCvxService* see 2.1068.1	Status of all services on the switch.

2.1068.1 MgmtCvxService

name	*string*	Service name.
status	*ServiceStatus* see 2.349.1.1	Service status.

2.1069 show management cvx service NAME

see 2.1068.1

2.1070 show management data sources

sensors	*table(string) = SensorClient.SensorStatusModel* see 2.1070.1	A mapping of sensor name to sensor status.

2.1070.1 SensorClient.SensorStatusModel

dataSources	*table(string) = SensorClient.DataSourceStatusModel* see 2.1070.1.1	A mapping of data source name to data source status.
sensorName	*string*	Sensor name.

2.1070.1.1 SensorClient.DataSourceStatusModel

[active]	*boolean*	Is the active data source.
dataSourceName	*string*	Data source name.
hostnames	*list of string*	A list of data source endpoints.
lastStateChangeTime	*integer*	Update timestamp from epoch time.
serviceType	*string*	Service provided by this data source.
status	*string*	Operational status.
statusDetail	*string*	Operational status detail.
type	*string*	Data source type.

2.1071 show management data sources sensors

connections	*table(string) = SensorClient.ConnectionStatusModel* see 2.1071.1	A mapping of remote resources endpoints to connection status.

2.1071.1 SensorClient.ConnectionStatusModel

address	*IP address*	IP address of a remote resource.
connectionReason	*string*	Connection status detail.
connectionStatus	*string*	Connection status to remote resource provider.
port	*integer*	Port of a remote resource provider.
remoteUri	*string*	Remote resource endpoint.
sensorName	*string*	Sensor device hosting the remote resource.
sslProfile	*string*	SSL profile being used to secure this connection.

2.1072 show management dmf controller zerotouch

controllers	*list of IP address*	List of controllers used for ZTN.
enabled	*boolean*	ZTN enabled.
[errorMessage]	*string*	Reason for ZTN handshake failure.
manifestTimestamp	*floating point number*	Time of manifest download in UTC.

state	*enum: invalidManifest* | *configDownloadFailed* | *swiDownloadFailed* | *swiInstallComplete* | *rebooting* | *configSaveComplete* | *configDownloaded* | *invalidConfig* | *none* | *configSaveError* | *init* | *configDownloadInProgress* | *manifestReady* | *swiDownloaded* | *complete* | *swiDownloadInProgress* | *invalidSwi* | *manifestDownloadFailed*	State of ZTN on the switch.

2.1073 show management dmf controller zerotouch detail

configDigest	*string*	SHA-256 digest of the downloaded startup-config.
configUrl	*string*	URL used by ZTN to download startup-config.
enabled	*boolean*	ZTN enabled.
imageDigest	*string*	SHA-256 digest of the downloaded image.
imageUrl	*string*	URL used by ZTN to download EOS image.
logMessages	*list of LogMsg* see 2.1073.1	Most recent ZTN log messages.
platform	*string*	Platform name sent to the controller for establishing connection.
systemMac	*MAC address*	MAC address of the system sent to the controller for establishing connection.

2.1073.1 LogMsg

message	*string*	Log message.
timestamp	*floating point number*	Timestamp of the log.

2.1074 show management dmf dynamic configuration

see 2.324.1.1

2.1075 show management dmf version

sha256	*string*	EOS software image SHA-256 hash.

2.1076 show management http-server

[bufferSize] **	*integer*	The send and receive buffer size for TCP session. **Since: 4.33.2
[dscpValue]	*integer*	The QoS DSCP value set in outgoing IP packets.
[fipsEnabled]	*boolean*	Whether FIPS mode is enabled for HTTPS algorithms.
iframeAncestors	*list of string*	Allowed Iframe ancestors.
logLevel	*enum: notice | crit | warn | none | alert | info | debug | emerg | error*	Logging level for the HTTP server.
[sslProfile]	*SslProfile* see 2.1055.2	The configuration and status of the SSL profile.
tlsProtocol	*list of string*	Allowed TLS protocol versions.
vrfs	*table(string) = HttpServiceVrf* see 2.1076.1	A mapping between the VRF name and http server status.

2.1076.1 HttpServiceVrf

httpServer	*HttpProtocolStatus* see 2.1055.1	The status of the HTTP server in vrf.
httpsServer	*HttpProtocolStatus* see 2.1055.1	The status of the HTTPS server in vrf.
[localHttpServer]	*HttpProtocolStatus* see 2.1055.1	The status of localhost HTTP server in vrf.
services	*list of string*	The list of enabled http services in VRF.
[unixSocketServer]	*UnixProtocolStatus* see 2.1055.3	The status of the Unix Domain Socket server.

2.1077 show management http-server ((ip access-list) | (ipv6 access-list)) [...]

see 2.62

2.1078 show management http-server counters

vrfs	*table(string) = VrfStats* see 2.1078.1	A mapping between VRF name and running nginx statistics.

2.1078.1 VrfStats

acceptConnections	*integer*	The total number of accepted client connections.
activeConnections	*integer*	The current number of active client connections.
handledConnections	*integer*	The total number of handled connections.

maxConnections	*integer*	The maximum number of simultaneous connections.
readingConnections	*integer*	The current number of connections where nginx is reading the request header.
refusedConnections	*integer*	The total number of refused connections.
requests	*integer*	The total number of client requests.
waitingConnections	*integer*	The current number of connections waiting for a request.
writingConnections	*integer*	The current number of connections where nginx is writing the response back to the client.

2.1079 show management ldap

[groups]	*table(string) = ServerGroupModel* see 2.1079.3	Mapping of group name to group information.
lastCounterClearTime	*floating point number*	UTC time when the counters were last cleared.
ldapServers	*table(string) = LdapStatsModel* see 2.1079.1	Mapping of server IP address or hostname to server statistics.
ldapStatus	*table(string) = LdapStatusModel* see 2.1079.2	Mapping of server IP address or hostname to server status.

2.1079.1 LdapStatsModel

bindFails	*integer*	Number of failed binds to the LDAP server.
bindRequests	*integer*	Number of bind requests to the LDAP server.
bindSuccesses	*integer*	Number of successful binds to the LDAP server.
bindTimeouts	*integer*	Number of binds timedout to the LDAP server.
searchFails **	*integer*	Number of failed searches to the LDAP server. **Since: 4.32.2
searchRequests **	*integer*	Number of search requests to the LDAP server. **Since: 4.32.2
searchSuccesses **	*integer*	Number of successful searches to the LDAP server. **Since: 4.32.2
searchTimeouts **	*integer*	Number of searches timedout to the LDAP server. **Since: 4.32.2

2.1079.2 LdapStatusModel

fipsStatus	*boolean*	Status of LDAP FIPS mode.

2.1079.3 ServerGroupModel

members	*list of ServerInfoModel* see 2.1079.3.1	List of LDAP servers in the server group.
serverGroup	*string*	Configured server group.

2.1079.3.1 ServerInfoModel

hostname	*string*	IP address or hostname of LDAP server.
port	*integer*	LDAP authorization port number.

2.1080 show management package [...]

revision 2

see 2.404

2.1081 show management package repository [...]

repositories	*table(string) = RepositoryEntry* see 2.1081.1	List of extension repositories.

2.1081.1 RepositoryEntry

description	*string*	Repository description.
name	*string*	Repository name.
rType	*enum: pypi | swix | yum | unknown*	Repository type (yum or pypi).
url	*string*	Repository URL.

2.1082 show management security

[blockedNetworkProtocols] **	*list of string*	Blocked unencrypted network protocols. **Since: 4.25.0
[cpuModel]	*string*	CPU Model name and manufacturer.
cryptoModule **	*string*	Cryptographic Module name and version (deprecated by cryptoModules). **Since: 4.26.2
cryptoModules **	*list of string*	Cryptographic Modules details list. **Since: 4.34.0
entropyServerEnabled **	*boolean*	True if entropy server is serving entropy in the entropy queue. **Since: 4.22.1
hardwareEntropyEnabled	*boolean*	True if the source of entropy is hardware.
[hardwareEntropyQueueSize] **	*integer*	Number of bytes of hardware generated entropy in the queue. **Since: 4.22.0
havegedEntropyEnabled **	*boolean*	True if the source of entropy is haveged. **Since: 4.23.1
jitterEntropyEnabled **	*boolean*	True if the source of entropy is jitter. **Since: 4.26.2
[securityChipVersion]	*string*	Security chip version. Not present on older platforms.
[switchChip]	*string*	Model of the switch chip.

2.1083 show management security auto-certificate profile [...]

certificates	*table(string) = AutoCertMgmt.Cli.CertProfile* see 2.1083.1	Mapping from certificate profile name to certificate profiles used for Automatic Certificate Management.

2.1083.1 AutoCertMgmt.Cli.CertProfile

currentState	*string*	Certificate's current state.
[details]	*AutoCertMgmt.Cli.CertDetails* see 2.1083.1.1	Certificate's details.
[lastError]	*AutoCertMgmt.Cli.LastError* see 2.1083.1.2	Details on last error encountered.
[nextRequestTimestamp]	*floating point number*	Timestamp of next request attempt.
privateKeyName	*string*	Name of the private key.

2.1083.1.1 AutoCertMgmt.Cli.CertDetails

enrollFailures	*integer*	Number of initial enroll failures.
enrollSuccesses	*integer*	Number of initial enroll successes.
renewalFailures	*integer*	Number of renewal failures.
renewalSuccesses	*integer*	Number of renewal successes.

2.1083.1.2 AutoCertMgmt.Cli.LastError

errorMessage	*string*	Human-readable message describing the last error.
[errorTimestamp]	*floating point number*	Timestamp of when the last error occured.

2.1084 show management security auto-certificate protocol est [...]

profiles	*table(string) = AutoCertMgmt.Cli.EstProfile* see 2.1084.1	Mapping from EST profile name to EST profiles used for Automatic Certificate Management.

2.1084.1 AutoCertMgmt.Cli.EstProfile

currentState	*string*	EST profile's current state.
[lastError]	*AutoCertMgmt.Cli.LastError* see 2.1083.1.2	Details on last error encountered.
managedProfiles	*list of AutoCertMgmt.Cli.ManagedCertProfile* see 2.1084.1.1	List of certificates profiles using this policy.

2.1084.1.1 AutoCertMgmt.Cli.ManagedCertProfile

certProfile	*string*	Name of Certificate profile.
certProfileState	*string*	Certificate profile current state.

2.1085 show management security certificate [...]

certificates	*table(string) = Certificate* see 2.1085.1	Mapping from certificate name to certificate used in SSL/TLS.

2.1085.1 Certificate

[extension]	*table(string) = Extension* see 2.1085.1.2	Mapping from X.509 version 3 extension name to extension value.
issuer	*DistinguishedName* see 2.1085.1.1	Entity who has signed and issued the certificate.
notAfter	*integer*	Timestamp on which the certificate validity period ends.
notBefore	*integer*	Timestamp on which the certificate validity period begins.
publicKey	*PublicKey* see 2.1085.1.3	Public key information.
serialNumber	*integer*	Serial number.
subject	*DistinguishedName* see 2.1085.1.1	Entity associated with the certificate.
version	*integer*	X.509 version.

2.1085.1.1 DistinguishedName

commonName	*string*	Common name.
[country]	*string*	Name of the country.
[email]	*string*	Email address.
[locality]	*string*	Name of the locality.
[organization]	*string*	Name of the organization.
[organizationUnit]	*string*	Name of the organizational unit.
[serialNumber] **	*string*	Serial number. **Since: 4.34.2
[stateOrProvince]	*string*	Name of the state or province.

2.1085.1.2 Extension

critical	*boolean*	Whether the extension is critical.
value	*string*	Value of the X.509 version 3 extension.

2.1085.1.3 PublicKey

[ellipticCurve] **	*string*	Elliptic curve used to generate the ECDSA key. This field is not present for other key types. **Since: 4.28.1
encryptionAlgorithm	*enum: ECDSA | RSA*	Encryption algorithm of the key.
modulus	*integer*	Modulus of the key (a value of 0 means no modulus).
[publicExponent]	*integer*	Public exponent of the RSA key. This field is not present for DSA key.

`size`	*integer*	Size of the key in bits.

2.1086 show management security session shared-secret profile NAME [...]

[currentRxExpiration]	*integer*	The date and time when the current receive secret expires.
[currentRxId]	*integer*	The id of the current secret being used for reception if it can be represented as an integer [deprecated].
[currentTxExpiration]	*integer*	The date and time when the current transmit secret expires.
[currentTxId]	*integer*	The id of the current secret being used for transmition if it can be represented as an integer [deprecated].
[profileName]	*string*	The name associated with the shared secret profile.
[rxId] **	*string*	The id of the current secret being used for reception. **Since: 4.27.0
rxRotation	*list of string*	The order in which receive secrets will be used.
secrets	*list of SecretModel* see 2.1086.1	The secrets currently configured in the profile.
[txId] **	*string*	The id of the current secret being used for transmition. **Since: 4.27.0
txRotation	*list of string*	The order in which transmit secrets will be used.

2.1086.1 SecretModel

id **	*string*	The id of the secret. **Since: 4.27.0
rxLifetimeEnd	*integer*	The time (UTC) when the secret is no longer valid for receiving data.
rxLifetimeStart	*integer*	The time (UTC) when the secret is valid for receiving data.
secret	*string*	The encrypted secret used for authentication.
secretID	*integer*	The id of the secret when it can be represented as an integer [deprecated].
[timezone] **	*string*	The timezone of the secret lifetime. **Since: 4.29.1
txLifetimeEnd	*integer*	The time (UTC) when the secret is no longer valid for transmitting data.
txLifetimeStart	*integer*	The time (UTC) when the secret is valid for transmitting data.

2.1087 show management security session shared-secret profile [...]

profiles	*table(string) = SharedSecretProfile* see 2.1086	Shared secret profiles indexed by name.

2.1088 show management security ssl crl [...]

crls	*table(string) = Crl* see 2.1088.1	Mapping from CRL name to CRL used in SSL/TLS.

2.1088.1 Crl

crlNumber	*integer*	CRL number.
issuer	*DistinguishedName* see 2.1085.1.1	Entity who has signed and issued the certificate.
lastUpdate	*integer*	Timestamp on which the CRL validity period begins.
nextUpdate	*integer*	Timestamp on which the CRL validity period ends.
revokedList **	*list of RevokedCertificate* see 2.1088.1.1	Serial number and Timestamp of the revoked certificate. **Since: 4.20.0

2.1088.1.1 RevokedCertificate

revocationDate	*floating point number*	revocation Date.
serialNumber	*string*	Serial number of the CRL.

2.1089 show management security ssl diffie-hellman [...]

[dhparamsLastResetFailed]	*boolean*	Whether last attempt to reset Diffie-Hellman parameters failed.
[dhparamsLastSuccessful-Reset]	*integer*	Last successful Diffie-Hellman parameters reset timestamp.
dhparamsResetInProgress	*boolean*	Whether Diffie-Hellman parameters is being reset.
[diffieHellmanParameters]	*DiffieHellmanParameters* see 2.1089.1	Diffie-Hellman parameters.

2.1089.1 DiffieHellmanParameters

generator	*integer*	Generator used in Diffie-Hellman key exchange.
prime	*integer*	Prime number used in Diffie-Hellman key exchange.
size	*integer*	Size of the prime number in bits.

2.1090 show management security ssl key [...]

publicKeys	*table(string) = PublicKey* see 2.1085.1.3	Mapping from key name to public key used in SSL/TLS.

2.1091 show management security ssl profile [...]

profileStatus	*table(string) = ProfileStatus* see 2.1091.1	Mapping from SSL profile name to status.

2.1091.1 ProfileStatus

[certName] **	*string*	Certificate name. **Since: 4.30.0
[chainedCertificates] **	*list of string*	Chained certificates. **Since: 4.30.0
[cipherList] **	*string*	Cipher list of TLSv1.2 and below. **Since: 4.32.0
[cipherSuiteV1_3] **	*string*	Cipher suite names of TLSv1.3. **Since: 4.32.0
[crls] **	*list of string*	Certificate revocation lists. **Since: 4.30.0
[dtlsVersion] **	*list of string*	DTLS versions. **Since: 4.35.2
[fipsMode] **	*boolean*	Whether FIPS restriction is enabled. **Since: 4.32.0
[isAutoCert] **	*boolean*	Whether certificate is automatically managed. **Since: 4.33.2
[isAutoKey] **	*boolean*	Whether key is automatically managed. **Since: 4.33.2
[keyEstablishmentGroups] **	*string*	Key establishment group of TLSv1.3. **Since: 4.34.2
[keyName] **	*string*	Key name. **Since: 4.30.0
[ocspProfileName] **	*string*	OCSP profile name. **Since: 4.33.0
[profileError]	*list of ProfileError* see 2.1091.1.1	List of SSL profile errors in 'invalid' state.
profileState	*enum: valid* | *updating* | *invalid*	SSL profile state.
[signatureAlgorithm] **	*list of string*	Signature algorithm list. **Since: 4.35.0
[tlsVersion] **	*list of string*	TLS versions. **Since: 4.32.0
[trustedCertificates] **	*list of string*	Trusted certificates. **Since: 4.30.0

2.1091.1.1 ProfileError

errorAttr	*enum: certificate* | *profile* | *trustedCertificate* | *key* | *chainedCertificate* | *ocsp* | *crl* | *keyEstablishmentGroups*	SSL profile attribute to which the error applies.
errorAttrValue	*string*	SSL profile attribute value.
[errorDates] **	*InvalidCertificateDates* see 2.1091.1.1.1	Invalid certificate dates. **Since: 4.33.1

errorType	*enum: kexGroupWithLowTlsVersion | certCloseToExpiry | noCABasicConstraintChain | noExtendedKeyUsage | certExpired | certNotYetValid | notFqdn | noCABasicConstraintTrust | noProfileData | notExist | missingCrlForTrustChain | vrfDoesNotExist | notMatchingCertKey | fileMultiplePEMs | crlNotSignedByCa | certTrustChainNotValid | noCrlSign | noError | hostnameMismatch | certChainNotValid*	Error type.
[errorTypeExtra] **	*string*	Error type extra information. **Since: 4.31.2

2.1091.1.1.1 InvalidCertificateDates

[notAfter]	*floating point number*	Certificate expiry date.
[notBefore]	*floating point number*	Certificate validity start date.

2.1092 show management security ssl profile cipher [...]

profileCiphers	*table(string) = ProfileCipher* see 2.1092.1	Mapping from SSL profile name to configured cipher suite names.

2.1092.1 ProfileCipher

cipherList	*list of string*	Cipher suite names of TLSv1.2 and below.
cipherSuiteV1_3	*list of string*	Cipher suite names of TLSv1.3.

2.1093 show management security ssl profile key-establishment-group [...]

profileKexGroups	*table(string) = ProfileKexGroup* see 2.1093.1	Mapping from SSL profile name to configured key establishment group names.

2.1093.1 ProfileKexGroup

kexGroupList	*list of string*	Key estalishment group names.

2.1094 show management security ssl profile signature algorithms [...]

profileSignatureAlgorithms	*table(string) = ProfileSignatureAlgorithm* see 2.1094.1	Mapping from SSL profile name to signature algorithms configuration string.

2.1094.1 ProfileSignatureAlgorithm

signatureAlgorithms	*list of string*	Signature algorithms names.

2.1095 show management security tpm measured-boot version

versions	*list of MeasuredBootVersion* see 2.1095.1	Measured boot versions.

2.1095.1 MeasuredBootVersion

name	*string*	Name of the measured boot component.
version	*string*	Version of the measured boot component.

2.1096 show management security tpm pcr PCR_RANGE [...]

[aikCert]	*string*	Attestation key certificate.
[attestationKeyCert] **	*string*	Attestation key certificate. **Since: 4.35.2
[attestationKeyName] **	*string*	Attestation key name. **Since: 4.35.2
bankToRegisters **	*table(string) = PcrValueList* see 2.1096.1	A mapping of TPM Platform Configuration Register bank to its index and value (a hexadecimal string). **Since: 4.35.2
[quoteData]	*string*	Quote data in base64 format.
[quoteInfo]	*string*	Quote info in base64 format.
registers	*table(numeric string) = string*	A mapping of TPM Platform Configuration Register index to its value (a hexadecimal string) with default PCR bank.
tpmVersion	*enum: 1.2 | 2.0*	TPM version.

2.1096.1 PcrValueList

pcrValues	*list of PcrValue* see 2.1096.1.1	PCR register and its value.

2.1096.1.1 PcrValue

register	*integer*	TPM PCR index.
value	*string*	Value of this PCR.

2.1097 show management security tpm pcr event revision

abootEventRevision	*table(string) = integer*	A mapping between Aboot TPM Platform Configuration Register extension event name and its revision number.
biosEventRevision	*table(string) = integer*	A mapping between BIOS TPM Platform Configuration Register extension event name and its revision number.
eosEventRevision	*table(string) = integer*	A mapping between EOS TPM Platform Configuration Register extension event name and its revision number.

2.1098 show management security tpm pcr log [...]

logs	*list of PcrLog* see 2.1098.1	TPM Platform Configuration Register extension logs.

2.1098.1 PcrLog

context	*list of string*	Additional data/context about this PCR log.
event **	*enum: abootSwi* | *abootAconf* | *abootConsoleLogged* | *abootBootConfig* | *abootPassword* | *evSCrtmContents* | *eosKernelParams* | *eosExtensionUninstall* | *eosExtensionInstall* | *abootImage* | *eosZerotouchConfig* | *evPostCode* | *biosAbootImage* | *evEfiVariableDriverConfig* | *evEfiPlatformFirmwareBlob* | *eosExtensionInstallFailure* | *eosRcEos* | *ubootImage* | *abootSbCert* | *eosExtensionUninstallFailure* | *evPlatformConfigFlags* | *unknownEvent* | *abootSbConfig* | *eosStartupConfig*	Event type of this PCR log. **Since: 4.28.1
eventRevision **	*integer*	Event revision number of this PCR log. **Since: 4.32.2
extend	*string*	Hexdecimal extended to PCR.
hashAlg **	*string*	Hash algorithm used for this event. **Since: 4.34.0
register	*integer*	TPM PCR index.
timestamp	*floating point number*	Timestamp when PCR extended.

2.1099 show management ssh ((ip access-list) | (ipv6 access-list)) [...]

see 2.62

2.1100 show management ssh authorized-principals [...]

`users`	*table(string) = SshUserConfig* see 2.1100.1	List of SSH Users.

2.1100.1 SshUserConfig

`sshAuthKeys`	*table(string) = SshAuthKey* see 2.1100.1.1	SSH user key configuration, maps an SSH-key name to SshAuthKey type.
`sshAuthPrincipals` **	*table(string) = SshAuthPrincipal* see 2.1100.1.2	SSH user principal configuration, maps an SSH-principal name to SshAuthPrincipal type. **Since: 4.32.2

2.1100.1.1 SshAuthKey

`keyContents`	*string*	SSH key contents.
`sshOptions`	*table(string) = SshOption* see 2.1100.1.1.1	SSH key options, maps an SSH-option name to a list of SSH-option values.

2.1100.1.1.1 SshOption

`sshValues`	*list of string*	SSH key option values.

2.1100.1.2 SshAuthPrincipal

`sshOptions`	*table(string) = SshOption* see 2.1100.1.1.1	SSH principal options, maps an SSH-option name to a list of SSH-option values.

2.1101 show management ssh key ((KEYALGO | hidden_alias) | FILENAME) public

`hostKey`	*string*	The public host key of the switch.
`[metadata]`	*table(string) = string*	Algorithm-specific metadata for ssh host key.

2.1102 show management ssh key server cert [...]

`certificates`	*table(string) = string*	A Mapping between configured host certificate filenames and the raw certificate.

2.1103 show management ssh trusted-ca key public [...]

keys	*list of string*	List of trusted CA public keys.

2.1104 show management ssh user-keys authorized-keys [...]

see 2.1100

2.1105 show management ssh user-keys revoke-list [...]

keys	*list of string*	List of revoked public keys.

2.1106 show management telnet ((ip access-list) | (ipv6 access-list)) [...]

see 2.62

2.1107 show management telnet [...]

[globalDefault]	*boolean*	VRF service state is dependent on default telnet state.
maxTelnetSessions	*integer*	Maximum telnet sessions.
maxTelnetSessionsPerHost **	*integer*	Maximum telnet sessions from one host. **Since: 4.24.0
serverState	*enum: enabled | disabled*	State of the telnet session either enabled or disabled.
vrfName	*string*	Configured VRF for telnet session.

2.1108 show match-list prefix-ipv4 [...]

matchLists	*table(string) = MatchList* see 2.1108.1	A mapping of match list name to prefixes.

2.1108.1 MatchList

prefixes	*list of IP address prefix*	List of configured segment prefixes.

2.1109 show match-list prefix-ipv6 [...]

see 2.1108

2.1110 show mdns counters

ignoredKA	*integer*	Ignored Known Answer records.
ignoredNsec	*integer*	Ignored NSEC records.
ignoredProbing	*integer*	Ignored probing queries.
ignoredQuestions	*integer*	Ignored One-shot queries.
rxDsoParseErrors	*integer*	Discarded DSO packets.
rxPamErrors	*integer*	Discarded MDNS packets received on the wrong interface.
rxParseErrors	*integer*	Discarded MDNS packets.
rxTcpPkts	*integer*	Received DSO packets.
rxUdpPkts	*integer*	Received MDNS packets.
suppressedResponseRecords	*integer*	Suppressed MDNS responses.
txDsoGenErrors	*integer*	DSO packet generation errors.
txGenErrors	*integer*	MDNS packet generation errors.
txPamErrors	*integer*	Packet transmission errors.
txTcpPkts	*integer*	Sent DSO packets.
txUdpPkts	*integer*	Sent MDNS packets.

2.1111 show mdns links

interfaces	*table(Interface name) = MdnsLinkList* see 2.1111.1	mDNS enabled interfaces indexed by interface name.

2.1111.1 MdnsLinkList

intfInfos	*list of MdnsLinkEntry* see 2.1111.1.1	Interfaces information.

2.1111.1.1 MdnsLinkEntry

defaultTag **	*string*	Configured default location tag. **Since: 4.26.2
family	*enum: ipv4 | ipv6 | ipunknown*	Address family.
linkId	*string*	Configured link name.
status	*enum: inactive | active*	Interface status.

2.1112 show mdns service name NAME [...]

[conflicts] **	*boolean*	Existence of conflicting records in the network. **Since: 4.32.1
name	*string*	Service name.
services	*list of MdnsServiceInfo* see 2.1112.1	Service information.

2.1112.1 MdnsServiceInfo

[hosts]	*table(string) = MdnsServiceHostInfo* see 2.1112.1.1	A mapping of Host name to its meta information.
[interface]	*interface name*	Interface the service record is learned from.
[link]	*string*	Name of the link the service record is learned from.
[srvTxts]	*list of Record* see 2.1112.1.1.1.1	Service TXT records.

2.1112.1.1 MdnsServiceHostInfo

[conflicts] **	*boolean*	Existence of conflicting records in the network. **Since: 4.32.1
[port]	*integer*	SRV record port.
[priority]	*integer*	SRV record priority.
[txts]	*list of Record* see 2.1112.1.1.1.1	TXT records.
[unknownTypes]	*table(numeric string) = MdnsUnknownList* see 2.1112.1.1.1	A mapping of unknown types to records.
[v4Addrs]	*list of string*	Information of the A record.
[v6Addrs]	*list of string*	Information of the AAAA record.
[weight]	*integer*	SRV record weight.

2.1112.1.1.1 MdnsUnknownList

unknowns	*list of Record* see 2.1112.1.1.1.1	Unknown records.

2.1112.1.1.1.1 Record

recordBytes	*list of integer*	Raw bytes of records.

2.1113 show mdns service record name NAME

records	*table(string) = MdnsRecordEntryList* see 2.1113.1	A mapping of MDNS lower cased record name to record entries.

2.1113.1 MdnsRecordEntryList

recordEntryList	*list of MdnsRecordEntry* see 2.1113.1.1	MDNS records.

2.1113.1.1 MdnsRecordEntry

recordClass	*integer*	MDNS record class.
recordInfos	*table(string) = MdnsRecordInfoList* see 2.1113.1.1.1	A mapping of mDNS original record name to its information.
recordName	*string*	MDNS record name lower cased.
recordType	*enum: cname | rp | px | aaaa | srv | dname | ns | a | afsdb | kx | any | ptr | mx | nsec | opt | rt | soa | txt*	MDNS record type.

2.1113.1.1.1 MdnsRecordInfoList

recordInfoList	*list of MdnsRecordInfo* see 2.1113.1.1.1.1	MDNS records.

2.1113.1.1.1.1 MdnsRecordInfo

[conflicts]	*boolean*	Existence of conflicting records in the network.
[interface]	*interface name*	Interface the service record is learned from.
[link]	*string*	Link name the service record is learned from.
locations	*list of string*	Location tags of the service record.

2.1114 show mdns service rule NAME [...]

queryLinks **	*list of Interface name*	Configured query links. **Since: 4.26.2
responseIntfs **	*list of Interface name*	Configured response interfaces. **Since: 4.26.2
responseLinks **	*list of string*	Configured response links. **Since: 4.26.2
services	*table(string) = MdnsServiceList* see 2.1114.1	A mapping of service name to its information.
srvTypes **	*list of string*	Discovering service types. **Since: 4.26.2

2.1114.1 MdnsServiceList

srvInfos	*list of MdnsServiceEntry* see 2.1114.1.1	MDNS services.

2.1114.1.1 MdnsServiceEntry

[conflicts] **	*boolean*	Existence of conflicting records in the network. **Since: 4.32.1
[interface]	*interface name*	Interface the service record is learned from.
[link]	*string*	Link name the service record is learned from.
locations	*list of string*	Location tags of the service record.

2.1115 show mdns service type [...]

serviceTypes	*table(Interface name) = MdnsServiceTypeList* see 2.1115.1	Observed service types indexed by interface name.

2.1115.1 MdnsServiceTypeList

intfInfos	*list of MdnsServiceTypeEntry* see 2.1115.1.1	Interfaces information.

2.1115.1.1 MdnsServiceTypeEntry

family	*enum: ipv4 | ipv6 | ipunknown*	Address family.
serviceType	*string*	Service type.
timestamp	*floating point number*	Timestamp of when the service type was last observed.

2.1116 show mdns status

dsoEnabled	*boolean*	DSO server is enabled.
dsoRunning	*boolean*	DSO server is running.
floodSuppression **	*boolean*	Flooding suppression is enabled. **Since: 4.32.1
mdnsEnabled	*boolean*	mDNS agent is enabled.
mdnsRunning	*boolean*	mDNS agent is running.
tcpClient	*list of MdnsServerGatewayStatus* see 2.1116.1	Connections to DSO servers.
tcpServerClient	*list of IpGenericAddrAndPort* see 2.365.1.1.1.2	Connection from DSO clients.

2.1116.1 MdnsServerGatewayStatus

client	*IpGenericAddrAndPort* see 2.365.1.1.1.2	Remote gateway.
connectionStatus	*string*	Connection Status.

2.1117 show metamux counters

interfaces	*table(Interface name) = FpgaMetaMuxBase-InterfaceCounters* see 2.1117.1	Interface statistics.

2.1117.1 FpgaMetaMuxBaseInterfaceCounters

Could also be an instance of:
FpgaMetaMuxInInterfaceCounters 2.1117.2
FpgaMetaMuxOutInterfaceCounters 2.1117.3

2.1117.2 FpgaMetaMuxInInterfaceCounters

bufferedPkts	*integer*	Number of received packets sent to the input buffer.
dropped	*integer*	Number of received packets dropped because input buffer is full.
errorPcs	*integer*	Number of received error, including PCS.
frameTooLongs	*integer*	Number of received packets that are bigger than MTU.
totalPkts	*integer*	Number of received packets.

2.1117.3 FpgaMetaMuxOutInterfaceCounters

totalPkts	*integer*	Number of transmitted packets.

2.1118 show metamux counters queue

see 2.473

2.1119 show metamux interfaces [...]

interfaces	*table(Interface name) = FpgaMetaMuxInterfaces-BaseStatus* see 2.1119.1	A mapping from an interface name to their status information.

2.1119.1 FpgaMetaMuxInterfacesBaseStatus

Could also be an instance of:
FpgaMetaMuxInInterfacesStatus 2.1119.2
FpgaMetaMuxOutInterfacesStatus 2.1119.3

2.1119.2 FpgaMetaMuxInInterfacesStatus

`enabled`	*boolean*	Interface is enabled by agent.
`rxLock`	*boolean*	Ethernet signal is detected at the input of the interface.
`[sourceInterface]`	*interface name*	Source interface name.

2.1119.3 FpgaMetaMuxOutInterfacesStatus

`buffering`	*boolean*	Buffering enabled.
`schedulerType`	*enum: orderOfArrival | roundRobin | profileDefault*	Scheduler type.

2.1120 show metamux mux status [...]

`instances`	*table(string) = MetaMux.Cli.MetaMuxMuxInstanceStatus* see 2.1120.1	MetaMux instance status, keyed by name.

2.1120.1 MetaMux.Cli.MetaMuxMuxInstanceStatus

`muxes`	*table(numeric string) = MetaMux.Cli.MetaMuxMuxStatus* see 2.1120.1.1	A Mapping between Mux global ID and Mux status.

2.1120.1.1 MetaMux.Cli.MetaMuxMuxStatus

`[buffering]`	*boolean*	Buffering enabled.
`[schedulerType]`	*enum: orderOfArrival | roundRobin | profileDefault*	Scheduler type.

2.1121 show metamux status [...]

`instances`	*table(string) = FpgaMetaMuxStatus or NULL* see 2.1121.1	MetaMux instance status, keyed by name.

2.1121.1 FpgaMetaMuxStatus

`enabled`	*boolean*	Instance is enabled and running.
`[fpgaName]`	*string*	FPGA name of where MetaMux is running.

oscillatorAdjustment	*integer*	Oscillator adjustment in parts-per-million.
oscillatorStabilized	*boolean*	Oscillator control loop is stable.
[profile]	*string*	Applied profile.

2.1122 show metamux storm-control [...]

see 2.475

2.1123 show metawatch counters [...]

see 2.467

2.1124 show metawatch counters deduplication [...]

see 2.468

2.1125 show metawatch device-id [...]

see 2.466

2.1126 show metawatch ptp

revision 2

see 2.469

2.1127 show metawatch status [...]

see 2.470

2.1128 show mlag [...]

revision 2

[configSanity]	*enum: inconsistent* | *consistent*	Peer configuration consistency check.
[detail]	*Detail* see 2.1128.1	More details of MLAG status.
[domainId]	*string*	MLAG domain ID.
[dualPrimaryDetectionState]	*enum: detected* | *running* | *configured* | *disabled*	Dual-primary detection state.
[dualPrimaryMlagRecovery-Delay]	*integer*	How long (in seconds) to delay the recovery of MLAG interfaces after dual primary is resolved.
[dualPrimaryNonMlag-RecoveryDelay]	*integer*	How long (in seconds) to delay the recovery of non-MLAG interfaces after dual primary is resolved.
dualPrimaryPortsErrdisabled	*boolean*	True if ports are errdisabled because dual-primary is detected or recovery delay is active.
[dualPrimaryPorts-ErrdisabledTime]	*floating point number*	Time when the ports were errdisabled due to dual-primary recovery delay.
[heartbeatPeerAddress]	*IP address*	IP address of the other MLAG peer used for UDP heartbeats (if different from peerAddress).
[heartbeatPeerVrf]	*string*	VRF for the heartbeat peer address.
[localInterface]	*interface name*	Layer 3 interface used for communication with MLAG peer.
[localIntfStatus]	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Operational state of the MLAG local interface.
mlagPorts	*table(string) = integer*	Number of MLAGs having each state. Key values are: Disabled, Configured, Inactive, Active-partial, Active-full.
[negStatus]	*enum: connected* | *inNegotiation* | *hardwareNotReady* | *connecting* | *invalidPeer* | *versionIncompatible* | *domainMismatch*	Negotiation status.
[peerAddress]	*IP address*	IP address of the other MLAG peer.
[peerLink]	*interface name*	Layer 2 interface used for communication with MLAG peer.
[peerLinkStatus]	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Operational state of the MLAG peer link.
portsErrdisabled	*boolean*	True if ports are disabled because reload delay is active.
[portsErrdisabledTime]	*floating point number*	Time when the ports were errdisabled.

reloadDelay	*integer*	How long (in seconds) the non-peer-link ports are errdisabled after a reboot. -1 means inifinite.
reloadDelayNonMlag	*integer*	How long (in seconds) the non-peer-link, non-MLAG ports are errdisabled after a reboot.
state	*enum: inactive* | *disabling* | *disabled* | *active*	MLAG state.
[systemId]	*MAC address*	MLAG System ID.

2.1128.1 Detail

[dualPrimaryAction]	*enum: none* | *errdisableAllInterfaces*	Action to take when dual primary is detected.
[dualPrimaryDetectionDelay]	*integer*	How long (in seconds) to delay the detection of dual-primary after failover.
effectiveHeartbeatInterval	*integer*	Effective time (in milliseconds) between the sending of each MLAG heartbeat.
enabled	*boolean*	True if the MLAG feature is enabled.
failover	*boolean*	True if this MLAG peer is in Failover mode.
failoverCauseList	*list of string*	List of causes for Failover.
failoverInitiated	*boolean*	True if failover is initiated by this MLAG peer due to forceful failover. Examples : Maintenance Mode, Fast Boot Reload.
[fastMacRedirectionEnabled]	*boolean*	True if fast MAC redirection is enabled for faster L2/L3 convergence.
heartbeatInterval	*integer*	Configured time (in milliseconds) between the sending of each MLAG heartbeat.
heartbeatTimeout	*integer*	Time (in milliseconds) of no received MLAG heartbeats before a timeout is declared.
heartbeatTimeoutsSinceReboot	*integer*	Number of MLAG heartbeat timeouts that occurred since the last reload.
lacpStandby	*boolean*	True if LACP standby is used to disable the non-peer-link, MLAG ports during the reload delay window.
[lastFailoverChangeTime]	*floating point number*	Time of the last failover transition.
[lastHeartbeatTimeout]	*floating point number*	Time of the last MLAG heartbeat timeout.
[lastStateChangeTime]	*floating point number*	Time of the last MLAG state transition.
[mlagHwReady]	*boolean*	True if the switch hardware is ready to be configured as an MLAG peer.
[mlagIntfEgressAclInterlockInactiveReason] **	*enum: noPeerConfiguration* | *noLocalConfiguration* | *noInactiveReason* | *mlagFailover* | *mlagNotActive*	Reason why MLAG interface interlock with egress filter is Inactive. **Since: 4.29.0
[mlagIntfEgressAclInterlockState] **	*enum: inactive* | *unsupported* | *active* | *unconfigured*	State of the MLAG interface interlock with egress filter. **Since: 4.29.0

mlagState	*enum: inactive | secondary | primary | disabling | disabled*	Specific MLAG state.
mountChanges	*integer*	Number of MLAG peer mount state transitions.
[peerLinkForwarding-Restricted] **	*boolean*	True if peer-link forwarding is restricted to only the VLAN used to forward MLAG PDUs. **Since: 4.34.0
peerMacAddress	*MAC address*	The other MLAG peer's bridge MAC address.
[peerMacRoutingSupported]	*boolean*	True if the switch hardware can route using peer's bridge MAC address.
peerMlagState	*enum: secondary | primary | unknown*	Peer MLAG state.
[peerMonotonicClockOffset]	*floating point number*	System monotonic time difference (in seconds) between the MLAG peers.
peerPortsErrdisabled	*boolean*	True if the other MLAG peer's ports are disabled because reload delay is active.
peerPrimaryPriority	*integer*	The other MLAG peer's primaryPriority value.
primaryPriority	*integer*	Used to determine which MLAG peer becomes primary when negotiating from scratch.
secondaryFromFailover	*boolean*	True if this MLAG peer's state is secondary because the other peer assumed the primary state due to failover.
stateChanges	*integer*	Number of MLAG state transitions.
udpHeartbeatAlive	*boolean*	True if we received UDP heartbeats from peer within the last timeout period.
udpHeartbeatsReceived	*integer*	Number of MLAG UDP heartbeat received.
udpHeartbeatsSent	*integer*	Number of MLAG UDP heartbeat sent.

2.1129 show mlag config-sanity [...]

[detail]	*boolean*	Will list matching peer-local value pairs too.
globalConfiguration	*table(string) = GlobalFeatureParam* see 2.1129.1	Global configuration keyed on feature.
interfaceConfiguration	*table(string) = IntfFeatureParam* see 2.1129.2	Interface configuration keyed on feature.
mlagActive	*boolean*	Command is enabled if MLAG state is active.
mlagConnected **	*boolean*	Command is enabled if MLAG peer is connected. **Since: 4.26.0

2.1129.1 GlobalFeatureParam

`globalParameters`	*table(string) = ParamValue* see 2.1129.1.1	Local and peer values for parameter.

2.1129.1.1 ParamValue

`[localValue]`	*string*	Local value.
`[peerValue]`	*string*	Peer value.

2.1129.2 IntfFeatureParam

`interfaceParameters`	*table(string) = InterfaceValue* see 2.1129.2.1	Local and peer values for interface parameter.

2.1129.2.1 InterfaceValue

`interface`	*table(string) = ParamValue* see 2.1129.1.1	Local and peer values for interface.

2.1130 show mlag interfaces [...]

interfaces	*table(string) = MlagInterface* see 2.1130.1	MLAG interfaces, keyed by MLAG ID.
[mlagIntfEgressAcl-InterlockEnabled] **	*boolean*	Is the MLAG interface egress ACL interlock enabled or not. **Since: 4.29.2

2.1130.1 MlagInterface

[detail]	*Detail* see 2.1130.1.1	More details of MLAG interface.
[ignoreReason] **	*enum: not-a-switchport | n/a*	Ignore reason for MLAG. **Since: 4.32.0
[lastTimeoutTime] **	*floating point number*	Time of the last timeout during egress filter interlock. **Since: 4.29.0
[localAclProtocolState] **	*enum: pending | installed | timeout | n/a*	State of local egress ACL protocol. **Since: 4.29.0
[localInterface]	*interface name*	Local interface corresponding to the MLAG.
[localInterfaceDescription]	*string*	Description of the local interface corresponding to the MLAG.
[localInterfaceStatus]	*enum: lowerLayerDown | unknown | down | up | testing | notPresent | notApplicable | dormant*	Operational state of the local MLAG interface.
[members]	*list of Interface name*	MLAG interface members (from both peers).
[peerAclProtocolState] **	*enum: pending | installed | n/a*	State of peer egress ACL protocol. **Since: 4.29.0
[peerInterface]	*interface name*	Peer interface corresponding to the MLAG.
[peerInterfaceStatus]	*enum: lowerLayerDown | unknown | down | up | testing | notPresent | notApplicable | dormant*	Operational state of the peer MLAG interface.
[status]	*enum: inactive | n/a | disabled-ignored | configured | active-full | active-partial-local-up | disabled | active-partial | active-partial-remote-up*	Status of MLAG.
timeoutCount **	*integer*	Number of timeouts that have occurred during egress filter interlock. **Since: 4.29.0

2.1130.1.1 Detail

[changeCount]	*integer*	Number of status transitions.
[lastChangeTime]	*floating point number*	Time of the last status transition.
[localInterfaceEnabled]	*enum: dis | ena*	Enabled state of the local MLAG interface.

[peerInterfaceEnabled]	*enum: dis | ena*	Enabled state of the peer MLAG interface.

2.1131 show mlag interfaces ignored [...]

see 2.1130

2.1132 show mlag interfaces interlock filter egress [...]

see 2.1130

2.1133 show mlag interfaces members [...]

see 2.1130

2.1134 show mlag issu compatibility URL

revision 2

currentVersion	*string*	The EOS version of the current image.
[detailedErrMessage]	*string*	detailed error message for invalid image.
isValid	*boolean*	True if the new image is valid.
newImagePath	*string*	The path to the new image.
[newVersion]	*string*	The EOS version of the new image.

2.1135 show mlag issu warnings

issuWarnings	*list of string*	Warning messages after a reload of an MLAG peer is requested.

2.1136 show mlag subinterfaces [...]

[badInterfaces]	*list of integer*	A list of invalid MLAG IDs.
mlags	*table(numeric string) = MlagToSubIntf* see 2.1136.1	MLAG to sub-interface map.

2.1136.1 MlagToSubIntf

subInterfaces	*table(Interface name) = MlagSubIntf* see 2.1136.1.1	A mapping of subinterface to its status.

2.1136.1.1 MlagSubIntf

[desc]	*string*	Description.
localStatus	*enum: lowerLayerDown | unknown | down | up | testing | notPresent | notApplicable | dormant*	Operational state of the local MLAG sub-interface.

2.1137 show mld membership [...]

interfaces	*table(Interface name) = MldMembershipInterface* see 2.1137.1	Map of interfaces for which there are listeners attached.

2.1137.1 MldMembershipInterface

groups	*table(IPv6 address) = MldGroup* see 2.1137.1.1	Map of groups for which there are local listeners.

2.1137.1.1 MldGroup

[compatibilityVersion]	*enum: version1 | version2*	The compatibility version is set to version1 or version2. It is set to version2 by default, but set to version1 whenever an MLDv1 report is received for the group.
[creationTime]	*floating point number*	UTC time at which this group was created.
[expiryTime]	*floating point number*	UTC time at which this group will expire.
[filterMode] **	*enum: include | exclude*	The filter mode may be include or exclude. This mode is based on modes of sources. In case there are no sources, the mode is exclude and it means to exclude no sources. **Since: 4.21.0
[lastReporter]	*IPv6 address*	The last host to send an MLD report for this group.
[sources]	*table(IPv6 address) = MldSource* see 2.1137.1.1.1	Map of include or exclude sources for this group.

2.1137.1.1.1 MldSource

[creationTime]	*floating point number*	UTC time at which this source was created.
[expiryTime]	*floating point number*	UTC time at which this source will expire.
filterMode	*enum: include | exclude*	The filter mode may be include or exclude. In include mode, packet reception is enabled for this source. In exclude mode, it is not.

2.1138 show mld querier [...]

interfaces	*table(Interface name) = MldQuerierInterface* see 2.1138.1	Map of querier information for MLD interfaces.

2.1138.1 MldQuerierInterface

[generalQueryExpiryTime]	*floating point number*	UTC time at which general query will be sent.
lastListenerQueryCount	*integer*	Configured last listener query count.
lastListenerQueryInterval	*floating point number*	Configured last listener query response interval in seconds.
[otherQuerierExpiryTime]	*floating point number*	UTC time at which the other querier will expire.
querier	*IPv6 address*	Ip Address of the querier on this interface.
queryInterval	*floating point number*	Active query interval in seconds.
queryResponseInterval	*floating point number*	Active maximum query response interval in seconds.
robustness	*integer*	Active robustness on this interface.
startupQueryCount	*integer*	Configured startup query count.
startupQueryInterval	*floating point number*	Effective startup query interval in seconds.
version	*enum: 1 | 2*	The MLD version configured on this interface.

2.1139 show mld snooping [...]

[mlagConnectionState] **	*enum: connected | initializing | unknown | n/a | disconnected | failed | connecting | disconnecting*	MLD Snooping agent MLAG connection state. **Since: 4.30.1
[mlagMountState] **	*enum: unknown | n/a | unmounted | failed | mounting | mounted*	MLD Snooping agent MLAG mount state. **Since: 4.30.1
[mldSnoopingState]	*enum: enabled | disabled*	Global state of MLD Snooping.
[robustness]	*integer*	Number of queries sent to age out a port's membership in group.
[vlans]	*table(numeric string) = MldSnoopingVlanInfo* see 2.1139.1	A mapping of VLAN's ID to its information.

2.1139.1 MldSnoopingVlanInfo

[evpnProxyActive] **	*boolean*	MLD proxying enabled via EVPN. **Since: 4.29.2
floodingTraffic	*boolean*	Flooding traffic to VLAN.
groupsOverrun	*boolean*	There has been an attempt to create more than the maximum number of groups.
maxGroups	*integer*	Maximum number of multicast groups that can join the VLAN.
mldSnoopingState	*enum: enabled | disabled*	State of MLD Snooping.

pruningActive	*boolean*	MLD snooping pruning is active.

2.1140 show mld snooping counters [...]

interfaces	*table(Interface name) = MldSnoopingCounters-Interface* see 2.1140.1	Map Interface name with its counter details.

2.1140.1 MldSnoopingCountersInterface

badChecksumIcmpV6Packets-Received	*integer*	Number of packages received for which ICMP v6 checksum check failed.
badChecksumIpPackets-Received	*integer*	Number of packets received for which IP checksum check failed.
badChecksumPimPackets-Received	*integer*	Number of packets received for which PIM checksum check failed.
badMldQueryReceived	*integer*	Number of invalid MLD querys received.
badMldV2ReportReceived	*integer*	Number of invalid MLD v2 reports received.
[mldQuerySend]	*integer*	Number of MLD querys sent.
[mldReportSend]	*integer*	Number of MLD reports sent.
[mldV1QueryReceived]	*integer*	Number of MLD v1 queries received.
[mldV2QueryReceived]	*integer*	Number of MLD v2 queries received.
[mldV2ReportReceived]	*integer*	Number of MLD v2 reports received.
nonIpPacketsReceived	*integer*	Number of non IP packets received.
[otherIcmpPacketsReceived]	*integer*	Number of other ICMP v6 packets received.
[otherPacketsSent]	*integer*	Number of other packets sent.
[pimPacketsReceived]	*integer*	Number of PIM packets received.
shortPacketsReceived	*integer*	Number of packets received with not enough IP payload.
unknownIpPacketsReceived	*integer*	Number of packets received with unknown IP Protocol.

2.1141 show mld snooping groups [...]

see 2.692

2.1142 show mld snooping groups count [...]

see 2.693

2.1143 show mld snooping groups detail [...]

see 2.694

2.1144 show mld snooping mrouter [...]

see 2.696

2.1145 show mld snooping querier [...]

vlans	*table(numeric string) = MldSnoopingVlanQuerier* see 2.1145.1	Mapping vlan Id to the vlan querier info.

2.1145.1 MldSnoopingVlanQuerier

[adminState] **	*enum: enabled | disabled*	State of MLD querier in the Vlan. **Since: 4.29.0
[listenerTimeout] **	*floating point number*	Time before the querier decides there are no morelisteners for a multicast address in the VLAN. **Since: 4.29.0
mldVersion	*enum: v1 | unknown | v2*	Version of MLD snooping querier in the vlan.
[operationalState] **	*enum: querierStateQuerier | querierStateNonQuerier | querierStateInitial*	Operational state of querier in the Vlan. **Since: 4.29.0
querierAddress	*IPv6 address*	Address of MLD querier in the VLAN.
querierInterface	*interface name*	Interface where the querier is located.
[queryInterval] **	*floating point number*	Period between MLD Membership Query messages. **Since: 4.29.0
queryResponseInterval	*floating point number*	Effective maximum period a recipient can wait before responding with a membership report in seconds.

2.1146 show mld snooping querier counters [...]

rxCounters	*MldSnoopingPacketCounters* see 2.1146.1	RX Counters.
txCounters	*MldSnoopingPacketCounters* see 2.1146.1	TX counters.

2.1146.1 MldSnoopingPacketCounters

errorPackets	*integer*	Number of error packets.
otherPackets	*integer*	Number of other packets.
v1Dones	*integer*	Number of v1 dones.
v1GSQueries	*integer*	Number of v1 group specific queries.
v1GeneralQueries	*integer*	Number of v1 general queries.
v1Reports	*integer*	Number of v1 reports.
v2GSQueries	*integer*	Number of v2 group specific queries.

v2GSSQueries	*integer*	Number of v2 group source specific queries.
v2GeneralQueries	*integer*	Number of v2 general queries.
v2Reports	*integer*	Number of v2 reports.

2.1147 show mld snooping querier detail [...]

vlans	*table(numeric string) = MldSnoopingVlanQuerier* see 2.1145.1	Mapping vlan Id to the vlan querier info.

2.1148 show mld snooping querier membership [...]

[vlanMemberships]	*table(numeric string) = VlanMembership* see 2.1148.1	Mapping vlan id to the membership info.

2.1148.1 VlanMembership

groupMemberships	*table(IPv6 address) = GroupMembership* see 2.1148.1.1	Mapping group address to the group info.

2.1148.1.1 GroupMembership

filterMode	*enum: filterModeInclude | filterModeExclude*	Filter mode of multicast group.
mldVersion	*enum: v1 | unknown | v2*	Version of MLD snooping querier.
[sourceMemberships]	*table(IPv6 address) = SourceMembership* see 2.1148.1.1.1	Mapping source address to the source info.

2.1148.1.1.1 SourceMembership

Could also be an instance of:
GroupMembership 2.1148.1.1

mldVersion	*enum: v1 | unknown | v2*	Version of MLD snooping querier.

2.1149 show mld static-group access-list ACL_NAME [...]

[errorMessage]	*string*	Error message for improperly configured access-list.
interfaces	*list of Interface name*	List of the interface names in the VRF using this access-list for static groups.
ruleDetails	*table(numeric string) = RuleInfo* see 2.1149.1	Map of sequence number to rule data for this access-list.
totalSGs	*integer*	Total number of valid (S,G) pairs within the access-list across all rules.

totalStarGs	*integer*	Total number of (*,G) pairs within the access-list across all rules.

2.1149.1 RuleInfo

[errorMessage]	*string*	Error message for improperly defined rule.
group	*IP address and netmask*	IP Address of the group and mask in this rule.
groupsInRule	*integer*	Number of groups in the specified rule.
source	*IPv6 address*	IP Address of the source in this rule.

2.1150 show mld statistics [...]

interfaces	*table(Interface name)* = *MldStatisticsInterface* see 2.1150.1	Map of statistics for MLD interfaces.

2.1150.1 MldStatisticsInterface

[errorPacketsReceived]	*integer*	Error packets received.
[otherPacketsReceived]	*integer*	Other packets received.
[v1Statistics]	*MldV1StatisticsInterface* see 2.1150.1.1	MLD version 1 statistics.
[v2Statistics]	*MldV2StatisticsInterface* see 2.1150.1.2	MLD version 2 statistics.

2.1150.1.1 MldV1StatisticsInterface

donesReceived	*integer*	MLD v1 multicast listener dones received.
generalQueriesReceived	*integer*	MLD v1 general queries received.
generalQueriesSent	*integer*	MLD v1 general queries sent.
gsQueriesReceived	*integer*	MLD v1 multicast address specific queries received.
gsQueriesSent	*integer*	MLD v1 multicast address specific queries sent.
reportsReceived	*integer*	MLD v1 multicast listener reports received.

2.1150.1.2 MldV2StatisticsInterface

generalQueriesReceived	*integer*	MLD v2 general queries received.
generalQueriesSent	*integer*	MLD v2 general queries sent.
gsQueriesReceived	*integer*	MLD v2 multicast address specific queries received.
gsQueriesSent	*integer*	MLD v2 multicast address specific queries sent.
gssQueriesReceived	*integer*	MLD multicast address and source specific queries received.
gssQueriesSent	*integer*	MLD v2 multicast address and source specific queries sent.
reportsReceived	*integer*	MLD v2 multicast listener reports received.

2.1151 show mld summary [...]

interfaces	*table(Interface name)* = *MldSummaryInterface* see 2.1151.1	Map of summary information for MLD interfaces.

2.1151.1 MldSummaryInterface

[ipAddress]	*IPv6 address*	Link Local Ip Address of this interface used in sending queries.
numGroups	*integer*	Number of MLD groups joined on this interface.
querierState	*enum: querier* | *non-querier* | *init*	The querier state may be init, querier, or non-querier.

2.1152 show module [...]

modules	*table(string) = Module* see 2.1152.1	Mapping between Module's name and its data.
redundancyMode **	*enum: initializing* | *unknown* | *standby* | *disabled* | *active* | *switchover*	informs current redundancy mode. **Since: 4.20.0
redundancyProtocol **	*enum: unknownProtocol* | *sso* | *simplex* | *rpr*	informs current redundancy protocol. **Since: 4.20.0

2.1152.1 Module

hardwareRev	*string*	Hardware Revision.
maxMacAddress	*MAC address*	Allocated Module's MAC address range. Inclusive upper bound.
minMacAddress	*MAC address*	Allocated Module's MAC address range. Inclusive lower bound.
modelName	*string*	Module's model string.
numMacAddresses **	*integer*	Number of MAC addresses in range. **Since: 4.22.0
portCount	*integer*	Number of ports.
[powerOffReason] **	*enum: cardModelIncompatible* | *incompatibleFan* | *overheat* | *unknown* | *slotUnsupported* | *SSU* | *powerOffNotSupported* | *tempSensorGroupFailure* | *ejectorOpen* | *userConfig* | *insufficientPower* | *insufficientFans*	Reason for being powered off. **Since: 4.28.0
serialNumber	*string*	Serial number.
softwareRev	*string*	Software Revision.

`status`	*enum: unknown* | *poweredOff* | *poweringOn* | *disabledUntilSystem-Upgrade* | *standby* | *failed* | *upgradingFpga* | *ok* | *disabled* | *active*	Module's status. For all Modules: ok-Module operating properly. failed-Module in a failed state. unknown-Unable to determine Module's state. poweringOn-Module is powering on. disabledUntilSystemUpgrade-Module is disabled until system software upgrade. poweredOff-Module is powered off. For supervisor Modules: active-Supervisor is currently active. standby-Supervisor is in standby mode. disabled-Supervisor is disabled.
`typeDescription`	*string*	Verbose description of the Module's type.
`[uptime]` **	*floating point number*	UTC timestamp of module power-on completion. **Since: 4.18.0

2.1153 show module power [...]

modules	*table(string) = Module* see 2.1153.1	A mapping of module name to its power consumption.

2.1153.1 Module

inResetPower	*floating point number*	module power consumption when in reset.
moduleModel	*string*	Model of module.
moduleName	*string*	Module slot.
numPresentXcvrs **	*integer*	Number of present transcievers. **Since: 4.27.2
outResetPower	*floating point number*	module power consumption when out of reset.
powerConsumption	*floating point number*	Current power consumption of the module.
powerSources **	*table(string) = PowerSource* see 2.1153.1.1	A mapping of power source name to its telemetry. **Since: 4.26.2
presentXcvrs **	*table(string) = string*	A mapping of transciever name to type of inserted module. **Since: 4.27.2
risers **	*table(string) = Riser* see 2.1153.1.3	A mapping of riser name to its status and affected interfaces. **Since: 4.30.1
secondaryPowerSources **	*table(string) = SecondaryPowerSource* see 2.1153.1.2	A mapping of secondary power source name to its telemetry. **Since: 4.27.2
transceiverPowerSources **	*table(string) = PowerSource* see 2.1153.1.1	A mapping of transceiver power source name to its telemetry. **Since: 4.27.1

2.1153.1.1 PowerSource

Could also be an instance of:
SecondaryPowerSource 2.1153.1.2

current	*floating point number*	Current reading from the power source (amps).
power	*floating point number*	Power reading from the power source (watts).
voltage	*floating point number*	Voltage reading from the power source (volts).

2.1153.1.2 SecondaryPowerSource

current	*floating point number*	Current reading from the power source (amps).
firstMediaType	*string*	Type of transciever in the first port.
power	*floating point number*	Power reading from the power source (watts).
secondMediaType	*string*	Type of transciever in the second port.
voltage	*floating point number*	Voltage reading from the power source (volts).

2.1153.1.3 Riser

interfaces	*string*	Interfaces on this riser.
powerGood	*boolean*	Power status of the riser (true or false).

2.1154 show module power budget

currPowerDraw	*floating point number*	Total power consumption of all cards in watts.
featureEnabled	*boolean*	Current status of the feature (Enabled/Disabled).
modelNames	*table(string) = string*	Model name of the cards.
modularPowerBudget	*floating point number*	System power budget in watts.
powerBudgetCards	*table(string) = floating point number*	Typical power draw of current cards.
powerBudgetMargin	*floating point number*	Power budget safety margin.
poweredOffCards	*table(string) = floating point number*	Typical power draw of powered off cards.
psuCapacity	*floating point number*	Single PSU capacity in watts.
totalPsuOutput	*floating point number*	Total power supply capacity in watts.

2.1155 show monitor connectivity [...]

revision 3

vrfs	*table(string) = ConnMonitorVrf* see 2.1155.1	A mapping between VRF and the hosts which are probed in it.

2.1155.1 ConnMonitorVrf

[clients]	*table(string) = ConnMonitorClient* see 2.1155.1.1	Connectivity monitor clients keyed by name.
description	*string*	A brief description of the VRF.
hosts	*table(string) = ConnMonitorHost* see 2.1155.1.1.1	A mapping between a host name and its probe statistics.

2.1155.1.1 ConnMonitorClient

hosts	*table(string) = ConnMonitorHost* see 2.1155.1.1.1	A mapping between a host name and its probe statistics.

2.1155.1.1.1 ConnMonitorHost

[configError]	*string*	Error string to indicate if there is a config error related to this host.
description	*string*	A brief description of the host.
hostname	*string*	Hostname destination for ICMP probes.
httpLatencyThreshold **	*floating point number*	Latency threshold for HTTP ping. **Since: 4.35.2
icmpDscp **	*integer*	DSCP marking for ICMP echo packets. **Since: 4.32.1
icmpEnabled **	*boolean*	ICMP probes are enabled. **Since: 4.32.2
icmpLatencyThreshold **	*floating point number*	Latency threshold for ICMP ping. **Since: 4.35.2
interfaces	*table(string) = Stats* see 2.1155.1.1.1.1	A mapping between source interface and the statistics generated using it.
ipAddr	*IP address*	IP address of the host.
pingCount **	*integer*	Number of ICMP pings. **Since: 4.33.0
pingSize	*integer*	Size of ping packet in bytes.
tcpLatencyThreshold **	*floating point number*	Latency threshold for TCP ping. **Since: 4.35.2
url	*string*	URL of the host.
useDport **	*boolean*	TCP port is enabled. **Since: 4.33.0

2.1155.1.1.1.1 Stats

hostUnreachable	*boolean*	Has the sequential failed probe count crossed the threshold.
httpDestinations	*table(string) = HttpStat* see 2.1155.1.1.1.2	A mapping between url and the HTTP statistics generated using it.
icmpDestinations	*table(IPv4 or IPv6 address) = IcmpStat* see 2.1155.1.1.1.3	A mapping between ip address and the ICMP statistics generated using it.
lastResponseAt	*floating point number*	Timestamp when the last response was received.
sequentialFailedProbeCount	*integer*	Number of sequential probes that did not receive any response.
tcpDestinations **	*table(string) = TcpStat* see 2.1155.1.1.1.4	A mapping between ip address and the TCP statistics generated using it. **Since: 4.33.0

2.1155.1.1.1.2 HttpStat

[httpProbeError]	*string*	HTTP probes error message.
[httpResponseTime]	*floating point number*	HTTP response time in milliseconds to reach the host.

2.1155.1.1.1.3 IcmpStat

[icmpProbeError]	*string*	ICMP probes error message.
[jitter]	*floating point number*	Packet delay variance observed while probing the host.
[latency]	*floating point number*	Network latency in milliseconds to reach the host usingthe ICMP protocol.
packetLoss	*integer*	Percentage packet loss when reaching the host.

2.1155.1.1.1.4 TcpStat

[latency]	*floating point number*	Network latency in milliseconds to reach the host using the TCP protocol.
[tcpProbeError]	*string*	TCP probes error message.

2.1156 show monitor dataplane integrity profiles

profiles	*table(string) = IpicProfileModel* see 2.1156.1	Summary of each Dataplane Integrity profile keyed by profile name.

2.1156.1 IpicProfileModel

bitPatternType	*enum: incrementing | custom | repeating | random | unspecified*	Bit pattern type.
[patternRepeating]	*integer*	Bit pattern repeating.

pktSize	*integer*	Packet size in bytes.

2.1157 show monitor dataplane integrity test

corruptPackets	*integer*	Number of corrupt packets.
coverage	*string*	Description of dataplane test coverage.
dataplanes	*list of string*	Description of tested dataplanes.
domain	*string*	Test domain.
duration	*integer*	Duration of current test.
endTime **	*floating point number*	End time. **Since: 4.32.1
errorSummary	*string*	Error summary.
firstError	*floating point number*	First time an error occurred.
lastError	*floating point number*	Last time an error occurred.
lostPackets	*integer*	Number of packets not returned from loop.
numPossibleDataplanes	*integer*	Number of dataplanes tasked in current operation.
profileName	*string*	Name of the test profile.
startTime	*floating point number*	Start time.
status	*enum: partiallyRunning* | *running* | *allocatingResources* | *partiallyDraining* | *failedToStart* | *notStarted* | *resourcesPartiallyAllocated* | *releasingResources* | *drainingComplete* | *failedToConfigureAcl* | *aclConfigured* | *failedToAllocateResources* | *complete* | *resourcesAllocated* | *aclPartiallyConfigured* | *countersCleared* | *failedToDrain* | *draining*	Run state.
testMode	*enum: foreground* | *background* | *none*	Type of test running.
validCount	*integer*	Valid packets.
warningSummary	*string*	Warning summary.

2.1158 show monitor device-health

categories	*table(string) = HealthCategoryModel* see 2.1158.1	A mapping between category and category information.
healthMonitoringEnabled	*boolean*	Device health monitoring enabled.

2.1158.1 HealthCategoryModel

metrics	*table(string) = HealthMetricModel* see 2.1158.1.1	A mapping between metric and metric information.

2.1158.1.1 HealthMetricModel

handlers	*list of string*	A mapping between handler and handler information.

2.1159 show monitor ethernet reflectors [...]

reflectorInterfaces	*table(string) = ReflectorInterfaceModel* see 2.1159.1	Mapping between reflector interface identifiers and their config and status.

2.1159.1 ReflectorInterfaceModel

direction	*enum: not configured | in | out*	Direction of the reflector interface.
macAction	*enum: not configured | swap*	MAC action of the reflector interface.
status	*enum: inactive | active*	Status of the reflector interface.
statusReason	*string*	Reason for the status of the reflector interface.

2.1160 show monitor fail-to-wire status [...]

[agents]	*table(string) = FailToWireAgentMonitoredModel* see 2.1160.1	Mapping of agent's name to its monitored status.
monitorStatus **	*enum: enabled | disabled*	Fail-To-Wire monitored status. **Since: 4.32.1
[relayStatus]	*enum: close | open*	Fail-To-Wire Relay Switch Status.

2.1160.1 FailToWireAgentMonitoredModel

[error]	*string*	Agent's Error.

2.1161 show monitor latency measurement end-to-end status

endToEndHistogram	*LatencyFeatureStatus* see 2.1161.1	End-to-end histogram feature status.
endToEndMaximum	*LatencyFeatureStatus* see 2.1161.1	End-to-end maximum feature status.
[measurementLastBecameInaccurateUtc]	*floating point number*	Timestamp when measurements last became inaccurate.

2.1161.1 LatencyFeatureStatus

configured	*boolean*	Whether this feature is currently configured.
mayContainInaccurateData	*boolean*	Whether this feature might have collected inaccurate measurements.

operational	*boolean*	Whether this feature is currently operational.
timeSyncRequested	*boolean*	Whether this feature has requested timesync.
[valueCollectionBeganUtc]	*floating point number*	When data collection started for this feature.

2.1162 show monitor link qualification generators [...]

enabled **	*boolean*	Link Qualification feature is enabled. **Since: 4.28.2
interfaces	*table(Interface name) = LinkQualification-GeneratorIntfModel* see 2.1162.1	Summary of each generator interface config and the test result, keyed by generator interface.

2.1162.1 LinkQualificationGeneratorIntfModel

duration	*integer*	Duration of the test in seconds.
endTime	*floating point number*	Time (in seconds) when test ended, Unix time.
[errorCode] **	*integer*	Error code to report different failures. **Since: 4.28.2
pktDropped **	*integer*	Number of packets lost. **Since: 4.27.2
pktRcvd	*integer*	Number of packets received.
pktSent	*integer*	Number of packets sent.
pktSize	*integer*	Packet size in bytes.
rate	*integer*	Traffic rate value for the test.
rateUnit **	*enum: rateUnitMbps | rateUnitGbps | rateUnitKbps | rateUnitInvalid | rateUnitbps*	Traffic rate unit for the test. **Since: 4.27.2
rxErrors **	*integer*	Number of receive errors. **Since: 4.27.2
rxOctetCount **	*integer*	Number of octets received. **Since: 4.28.2
startTime	*floating point number*	Time (in seconds) when test was started, Unix time.
state	*enum: completeWithFailure | interfaceFailed | cancelled | none | failed | complete | running*	Link qualification test state.
txErrors **	*integer*	Number of transmit errors. **Since: 4.27.2
txOctetCount **	*integer*	Number of octets sent. **Since: 4.28.2

2.1163 show monitor link qualification generators profiles [...]

enabled **	*boolean*	Link Qualification feature is enabled. **Since: 4.28.2
profiles	*table(string) = LinkQualificationProfileModel* see 2.1163.1	Summary of each link qualification profile config, keyed by profile name.

2.1163.1 LinkQualificationProfileModel

duration	*integer*	Duration of the link qualification test in seconds.
pktSize	*integer*	Packet size in bytes.
rate	*integer*	Traffic rate value for the link qualification test.
rateUnit **	*enum: rateUnitMbps | rateUnitGbps | rateUnitKbps | rateUnitInvalid | rateUnitbps*	Traffic rate unit for the link qualification test. **Since: 4.27.2

2.1164 show monitor rfc2544 generators profiles [...]

enabled	*boolean*	RFC2544 generator is enabled.
profileNames	*table(string) = Rfc2544ProfileModel* see 2.1164.1	A mapping of profile names to test profiles.
running	*boolean*	RFC2544 generator is running.

2.1164.1 Rfc2544ProfileModel

benchmarkTests	*list of BenchmarkTestModel* see 2.1164.1.1	List of RFC2544 benchmark tests.
destinationMac	*MAC address*	Destination MAC address in test packets.
direction	*enum: flowDirectionUnknown | flowIn | flowOut*	Direction of packets injected by generator.
duration	*floating point number*	Test duration in seconds.
[packetRate]	*PacketRateAndUnitModel* see 2.1164.1.2	Packet rate with unit.
packetSizes	*list of integer*	List of packet sizes.
sourceMac	*MAC address*	Source MAC address in test packets.

2.1164.1.1 BenchmarkTestModel

test	*enum: benchmarkThroughput | benchmarkFrameLossRate*	RFC2544 benchmark test.

2.1164.1.2 PacketRateAndUnitModel

rate	*floating point number*	Packet rate.
unit	*enum: rateUnitGbps | rateUnitbps | rateUnitKbps | rateUnitMbps*	Packet rate unit.

2.1165 show monitor rfc2544 generators test-report [...]

enabled	*boolean*	RFC2544 generator is enabled and running.
interfaces	*table(Interface name) = IntfTestReportModel* see 2.1165.1	A mapping of interfaces to its test reports.

2.1165.1 IntfTestReportModel

testReports	*list of TestReportModel* see 2.1165.1.1	Historic test reports.

2.1165.1.1 TestReportModel

[destinationMac]	*MAC address*	Destination MAC address in test packets.
[direction]	*enum: flowDirectionUnknown | flowIn | flowOut*	Direction of packets injected by generator.
execId	*ExecIdModel* see 2.1165.1.1.1	Unique ID for this test report.
[frameLossRateTest] **	*FrameLossRateTestReportModel* see 2.1165.1.1.2	Frame loss rate test report. **Since: 4.29.0
[profileName]	*string*	RFC2544 inititator profile name.
[sourceMac]	*MAC address*	Source MAC address in test packets.
[throughputTest]	*ThroughputTestReportModel* see 2.1165.1.1.3	Throughput test report.

2.1165.1.1.1 ExecIdModel

count	*integer*	Count.
pid	*integer*	PID.
timestamp	*integer*	UTC timestamp.

2.1165.1.1.2 FrameLossRateTestReportModel

[endTime]	*floating point number*	Timestamp when test was ended.
[rateAndUnit]	*PacketRateAndUnitModel* see 2.1164.1.2	Maximum packet rate.
results	*table(numeric string) = FrameLossRateTestResultModel* see 2.1165.1.1.2.1	A mapping of test packet sizes to frame loss rate test results.
[startTime]	*floating point number*	Timestamp when test was started.
state	*enum: flowStateRestart | flowStateFailure | flowStateRunning | flowStateAborted | flowStateNone | flowStateSuccess*	Overall state of test.

[stateReason]	*enum: sourceMacAddrNotFound* | *throughputFailureWith-ProfileDuration* | *packetRateExceeded* | *execRequestStop* | *hardwareProgramming-Failed* | *eoamAgentRestart* | *noReason* | *execRequestDeleted* | *frameLossRateFailureWith-ProfileDuration* | *clientEncapNotFound* | *frameLossRateSearch-SpaceExhausted* | *throughputNotFound* | *intfDown*	Reason for test state.

2.1165.1.1.2.1 FrameLossRateTestResultModel

[endTime]	*floating point number*	Timestamp when test was ended.
[startTime]	*floating point number*	Timestamp when test was started.
state	*enum: flowStateRestart* | *flowStateFailure* | *flowStateRunning* | *flowStateAborted* | *flowStateNone* | *flowStateSuccess*	Individual state of test.
[stateReason]	*enum: sourceMacAddrNotFound* | *throughputFailureWith-ProfileDuration* | *packetRateExceeded* | *execRequestStop* | *hardwareProgramming-Failed* | *eoamAgentRestart* | *noReason* | *execRequestDeleted* | *frameLossRateFailureWith-ProfileDuration* | *clientEncapNotFound* | *frameLossRateSearch-SpaceExhausted* | *throughputNotFound* | *intfDown*	Reason for test state.
trials	*table(numeric string) = FrameLossRateTestTrial-Model* see 2.1165.1.1.2.2	A mapping of test trials to results.

2.1165.1.1.2.2 FrameLossRateTestTrialModel

[duration]	*floating point number*	Trial duration in seconds.

[packetRate]	*PacketRateAndUnitModel* see 2.1164.1.2	Trial packet rate.
[packetsReceived]	*integer*	Number of packets received by the generator.
[packetsSent]	*integer*	Number of packets sent by the generator.
state	*enum: flowStateRestart* | *flowStateFailure* | *flowStateRunning* | *flowStateAborted* | *flowStateNone* | *flowStateSuccess*	State of test trial.
[stateReason]	*enum: sourceMacAddrNotFound* | *throughputFailureWithProfileDuration* | *packetRateExceeded* | *execRequestStop* | *hardwareProgrammingFailed* | *eoamAgentRestart* | *noReason* | *execRequestDeleted* | *frameLossRateFailureWithProfileDuration* | *clientEncapNotFound* | *frameLossRateSearchSpaceExhausted* | *throughputNotFound* | *intfDown*	Reason for test state.

2.1165.1.1.3 ThroughputTestReportModel

[endTime]	*floating point number*	Timestamp when test was ended.
results	*table(numeric string) = ThroughputTestResultModel* see 2.1165.1.1.3.1	A mapping of test packet sizes to throughput test results.
[startTime]	*floating point number*	Timestamp when test was started.
state	*enum: flowStateRestart* | *flowStateFailure* | *flowStateRunning* | *flowStateAborted* | *flowStateNone* | *flowStateSuccess*	Overall state of test.

[stateReason]	*enum: sourceMacAddrNotFound* | *throughputFailureWith-ProfileDuration* | *packetRateExceeded* | *execRequestStop* | *hardwareProgramming-Failed* | *eoamAgentRestart* | *noReason* | *execRequestDeleted* | *frameLossRateFailureWith-ProfileDuration* | *clientEncapNotFound* | *frameLossRateSearch-SpaceExhausted* | *throughputNotFound* | *intfDown*	Reason for test state.

2.1165.1.1.3.1 ThroughputTestResultModel

[detail]	*ThroughputTestResult-DetailModel* see 2.1165.1.1.3.2	Detailed throughput test trial results.
[packetsSent]	*integer*	Number of packets sent by the generator for this test.
[rateAndUnit]	*PacketRateAndUnitModel* see 2.1164.1.2	Final throughput rate.
state	*enum: flowStateRestart* | *flowStateFailure* | *flowStateRunning* | *flowStateAborted* | *flowStateNone* | *flowStateSuccess*	Individual state of test.
[stateReason]	*enum: sourceMacAddrNotFound* | *throughputFailureWith-ProfileDuration* | *packetRateExceeded* | *execRequestStop* | *hardwareProgramming-Failed* | *eoamAgentRestart* | *noReason* | *execRequestDeleted* | *frameLossRateFailureWith-ProfileDuration* | *clientEncapNotFound* | *frameLossRateSearch-SpaceExhausted* | *throughputNotFound* | *intfDown*	Reason for test state.

2.1165.1.1.3.2 ThroughputTestResultDetailModel

[endTime]	*floating point number*	Timestamp when test was ended.

[startTime]	*floating point number*	Timestamp when test was started.
trials	*table(numeric string) = ThroughputTestTrialModel* see 2.1165.1.1.3.3	A mapping of test trials to results.

2.1165.1.1.3.3 ThroughputTestTrialModel

[duration]	*floating point number*	Trial duration in seconds.
[packetRate]	*PacketRateAndUnitModel* see 2.1164.1.2	Trial packet rate.
[packetsReceived]	*integer*	Number of packets received by the generator.
[packetsSent]	*integer*	Number of packets sent by the generator.
state	*enum: flowStateRestart | flowStateFailure | flowStateRunning | flowStateAborted | flowStateNone | flowStateSuccess*	State of test trial.

2.1166 show monitor security awake [...]

nucleuses	*table(string) = MsaNucleus* see 2.1166.1	A mapping of nucleus name to its status.
[status]	*MsaStatus* see 2.1166.2	Monitor security awake status.

2.1166.1 MsaNucleus

destinationAddr	*IP address*	IP address of the nucleus.
destinationPort	*integer*	Port number of the nucleus.
inactiveReasons	*list of MsaNucleusInactiveReason* see 2.1166.1.1	Reasons why the nucleus is not active.
lastEstablished	*floating point number*	Last time that connection was established successfully.
localAddr	*IP address*	Local IP address from which to connect.
localIntf	*interface name*	Local interface from which to connect.
sslProfile	*string*	SSL profile name.
status	*enum: inactive | connected*	Status of the nucleus connection.
vrf	*string*	VRF name.

2.1166.1.1 MsaNucleusInactiveReason

[errorReason]	*string*	TCP or SSL error reason.
inactiveReason	*enum: cipherSuiteV1_3NotConfigured | topicNotConfigured | sslProfileNameNotConfigured | trustedCertsNotConfigured | dnsResolutionInProgress | localAddrNotConfigured | hostNotConfigured | sslProfileNotConfigured | certNotConfigured | connectionInProgress | duplicateDestination | tlsVersionsNotConfigured | cipherSuiteNotConfigured | sslProfileNotValid | connectionLost | connectionFailed | vrfNotConfigured | portNotConfigured*	Nucleus inactive reason.

2.1166.2 MsaStatus

active	*boolean*	Indicates whether the monitor is active or not.
activeIntfs	*list of Interface name*	Interfaces on which monitor is active.
flowTableInactiveTimeout	*floating point number*	Timeout of flows in seconds.
flowTableSize	*integer*	Maximum flow table size.

`inactiveReasons`	*list of MsaInactiveReason* see 2.1166.2.1	Reasons why monitor is not active.
`lowMemoryMode` **	*boolean*	Indicates whether the monitor is running in low memory mode. **Since: 4.30.0
`monitorPointId`	*integer*	Configured monitor point identifier.
`topicName`	*string*	Configured name of topic.

2.1166.2.1 MsaInactiveReason

`inactiveReason`	*enum: hwExporterNotActive* | *hwFlowTrackingNotRunning* | *monitorSessionNotActive* | *nucleusNotConnected* | *monitorSecurityAwakeDisabled* | *eosExtensionNotInstalled* | *monitorSecurityAwakeInitializing*	Nucleus inactive reason.

2.1167 show monitor security awake counters [...]

[activityRecordQueueFull] **	*integer*	Activity record queue full. **Since: 4.29.0
[flowCounters]	*FlowCounters* see 2.1167.1	Cumulative flow counters.
[flowTableFull] **	*integer*	Flow table full. **Since: 4.31.1
ipfixCounters	*list of IpfixCounters* see 2.1167.2	A list of per-exporter IPFIX counters.
nucleusCounters	*table(string) = NucleusCounters* see 2.1167.3	A list of per-nucleus counters.
[packetBundleQueueFull] **	*integer*	Packet bundle queue full. **Since: 4.29.0

2.1167.1 FlowCounters

activeFlows	*integer*	Number of active flows.
expiredFlows	*integer*	Cumulative expired flow count.
flows	*integer*	Cumulative created flow count.
flowsRates **	*table(numeric string) = floating point number*	A mapping of time interval to flows created per second. **Since: 4.30.0
ipv4AppCounters	*table(string) = AppCounters* see 2.1167.1.1	A mapping of IPv4 application name to flow counters.
ipv6AppCounters	*table(string) = AppCounters* see 2.1167.1.1	A mapping of IPv6 application name to flow counters.
lastCountersClearedTime	*floating point number*	Last time that the flows counters were-cleared.
packets	*integer*	Cumulative count of packets received.
packetsRates **	*table(numeric string) = floating point number*	A mapping of time interval to packets received per second. **Since: 4.30.0

2.1167.1.1 AppCounters

activeFlows	*integer*	Number of active flows.
expiredFlows	*integer*	Cumulative expired flow count.
flows	*integer*	Cumulative created flow count.

2.1167.2 IpfixCounters

dataRecordsRates **	*table(numeric string) = floating point number*	A mapping of time interval to data records received per second. **Since: 4.30.0
exporter	*IpGenericAddrAndPort* see 2.365.1.1.1.2	Exporter IP address and port number.
flowRecordQueueFull	*integer*	Flow record queue full.
invalidIpfixMsgs	*integer*	Invalid IPFIX messages received.

lastCountersClearedTime	*floating point number*	Last time that the IPFIX counters were cleared.
messagesRates **	*table(numeric string) = floating point number*	A mapping of time interval to messages received per second. **Since: 4.30.0
observationDomainId	*integer*	Observation domain ID.
rxDataRecords	*integer*	Data records received.
rxMessages	*integer*	Messages received.
rxOptionsDataRecords	*integer*	Options data records received.
rxOptionsTemplateRecords	*integer*	Options template records received.
rxTemplateRecords	*integer*	Template records received.
templateIdErrors	*integer*	Unknown template ID errors.

2.1167.3 NucleusCounters

activityRecordsRates **	*table(numeric string) = floating point number*	A mapping of time interval to activity records transmitted per second. **Since: 4.30.0
connectionErrorCount	*integer*	Number of failed connections.
connectionSuccessCount	*integer*	Number of successful connections.
lastActivityTransmission-Timestamp	*floating point number*	Time when the last activity record was sent.
lastConnectionError-Timestamp	*floating point number*	Time of the last failed connection.
lastConnectionSuccess-Timestamp	*floating point number*	Time of the last successful connection.
lastCountersClearedTime	*floating point number*	Last time that the nucleus counters were cleared.
lastProgressTransmission-Timestamp	*floating point number*	Time when the last progress record was sent.
numActivityRecordsInQueue	*integer*	Number of activity records currently in the queue.
numActivityRecords-Transmitted	*integer*	Number of activity records sent.
numProgressRecordsInQueue	*integer*	Number of progress records currently in the queue.
numProgressRecords-Transmitted	*integer*	Number of progress records sent.
progressRecordsRates **	*table(numeric string) = floating point number*	A mapping of time interval to progress records transmitted per second. **Since: 4.30.0
throughputs **	*table(numeric string) = floating point number*	A mapping of time interval to outgoing activity and progress records throughput in Mbps. **Since: 4.30.2

2.1168 show monitor security awake dpi memory

[allocated]	*MsaDpiMemoryDetails* see 2.1168.1	Allocated memory details.
[inUse]	*MsaDpiMemoryDetails* see 2.1168.1	In use memory details.

2.1168.1 MsaDpiMemoryDetails

current	*integer*	Current memory use in bytes.
maximum	*integer*	Maximum memory use observed in bytes.
maximumTime	*floating point number*	Time when the maximum memory use was observed.
minimum	*integer*	Minimum memory use observed in bytes.
minimumTime	*floating point number*	Time when the minimum memory use was observed.

2.1169 show monitor security awake dpi memory allocations [...]

contexts	*table(string) = MsaDpiCtxMemoryAllocations* see 2.1169.1	Mapping from context to allocations.

2.1169.1 MsaDpiCtxMemoryAllocations

structures	*table(string) = MsaDpiStructMemoryAllocations* see 2.1169.1.1	Mapping from structure to allocations.

2.1169.1.1 MsaDpiStructMemoryAllocations

maxAlloc	*integer*	Maximum number of allocations observed.
maxBytes	*integer*	Maximum byte allocation observed.
maxTime	*floating point number*	Time when the maximum number of allocations was observed.
minAlloc	*integer*	Minimum number of allocations observed.
minBytes	*integer*	Minimum byte allocation observed.
minTime	*floating point number*	Time when the minimum number of allocations was observed.
numAlloc	*integer*	Current number of allocations.
numBytes	*integer*	Current allocation in bytes.

2.1170 show monitor security awake dpi memory pools

memoryPools	*table(string) = MsaDpiMemoryPoolDetails* see 2.1170.1	Mapping from pool ID to pool details.

2.1170.1 MsaDpiMemoryPoolDetails

allocCount	*integer*	Number of blocks allocated.
allocSize	*integer*	Number of bytes allocated.
blockSize	*integer*	Block size of this memory pool in bytes.
maximumCount	*integer*	Maximum number of blocks in use observed.
maximumSize	*integer*	Maximum number of bytes in use observed.
maximumTime	*floating point number*	Time when the maximum use was observed.
minimumCount	*integer*	Minimum number of blocks in use observed.
minimumSize	*integer*	Minimum number of bytes in use observed.
minimumTime	*floating point number*	Time when the minimum use was observed.
usedCount	*integer*	Number of blocks in use.
usedSize	*integer*	Number of bytes in use.

2.1171 show monitor security awake flow-table [...]

Could also be an instance of:
FlowTableDetail 2.1171.1.1.1

activeFlows	*integer*	Number of active flows.
groups	*table(string) = FlowGroup* see 2.1171.1	A mapping between group name and group.

2.1171.1 FlowGroup

flows	*list of Flow* see 2.1171.1.1	A list of active flows.

2.1171.1.1 Flow

[flowDetail]	*FlowDetail* see 2.1171.1.1.1	Flow detailed information.
higherIpAddress	*IpGenericAddrAndPort* see 2.365.1.1.1.2	Higher IP address.
ipProtocol	*enum: ipProtoTcp* | *ipProtoOspf* | *ipProtoUdp* | *ipProtoIpv6Frag* | *ipProtoExperiment1* | *ipProtoIgmp* | *ipProtoIpv6NoNxt* | *ipProtoIpip6* | *ipProtoSctp* | *ipProtoIpv6HopByHop* | *ipProtoIsis* | *ipProtoGre* | *ipProtoIpip* | *ipProtoVrrp* | *ipProtoAh* | *ipProtoUnknown* | *ipProtoRsvp* | *ipProtoIpv6Opts* | *ipProtoL2tp* | *ipProtoEsp* | *ipProtoExperiment2* | *ipProtoIcmpv6* | *ipProtoIcmp* | *ipProtoPim* | *ipProtoIpv6Route*	IP protocol.
ipProtocolNumber	*integer*	IP protocol number.
lowerIpAddress	*IpGenericAddrAndPort* see 2.365.1.1.1.2	Lower IP address.
numBytesH2L	*integer*	Number of bytes from higher IP to lower IP.
numBytesL2H	*integer*	Number of bytes from lower IP to higher IP.
numPacketsH2L	*integer*	Number of packets from higher IP to lower IP.
numPacketsL2H	*integer*	Number of packets from lower IP to higher IP.
startTime	*floating point number*	Flow start time.

2.1171.1.1.1 FlowDetail

lastUpdateTime	*floating point number*	Last flow update time.
activeFlows	*integer*	Number of active flows.
groups	*table(string) = FlowGroup* see 2.1171.1	A mapping between group name and group.

2.1172 show monitor server PROTOCOL [...]

[probeMethod]	*enum: accessRequestPacket | statusServerPacket*	Server probe method.
probedServers	*list of ServerProbeStats* see 2.1172.1	List of all probed servers.
protocol	*string*	Protocol of the probed server.

2.1172.1 ServerProbeStats

lastClearTime	*floating point number*	UTC time when the counters were last cleared.
probesSent	*integer*	Number of probe packets sent to the server.
responseAccepted	*integer*	Number of valid responses accepted.
responseDropped	*integer*	Number of responses dropped.
serverInfo	*ServerInfo* see 2.1172.1.1	Probed server information.

2.1172.1.1 ServerInfo

[acctPort]	*integer*	Accounting port number.
alive	*boolean*	Server is alive.
failCount	*integer*	Failed probes since last successful response.
host	*string*	IP address or hostname of the probed server.
lastProbeTime	*floating point number*	UTC time when the server was last probed.
lastResponseTime	*floating point number*	UTC time when receiving the last successful response.
lastStatusChangeTime	*floating point number*	UTC time when the server status was last changed.
port	*integer*	Server port number.
[vrf]	*string*	The VRF over which this server is reachable.

2.1173 show monitor server-failure

enabled	*boolean*	Server-failure feature is enabled or not.
networkServers	*table(string) = integer*	Number of servers in each monitored networkIndexed by network.
[proxyLifetime]	*integer*	Current lifetime.
proxyLifetimeDefault	*integer*	Default proxy lifetime.
proxyService	*boolean*	Is proxy service enabled or not.

2.1174 show monitor server-failure history

fsfEnabled	*boolean*	Is Server-failure feature is enabled or not.
servers	*list of Server* see 2.1174.1	List of servers monitored by Server-failure.

2.1174.1 Server

discoveryTime	*floating point number*	Time at which the server was discovered.
ethAddress	*MAC address*	Server Ethernet Address.
intf	*interface name*	Interface the server is on.
ipAddress	*IPv4 address*	Server IP Address.
isValid	*boolean*	Is the server info valid.
lastFailureTime	*floating point number*	Time at which the server last failed.
lastInactiveTime	*floating point number*	Time at which the server was last made inactive.
lastProxyTime	*floating point number*	Time at which the server was last proxied.
numFailed	*integer*	Number of times the server failed.
numInactive	*integer*	Number of times the server was made inactive.
numProxied	*integer*	Number of times the server was proxied.
state	*string*	Server state.
subnet	*string*	Subnet to which the server belongs.

2.1175 show monitor server-failure servers IP_ADDR

see 2.1174.1

2.1176 show monitor server-failure servers [...]

fsfEnabled	*boolean*	Is Server-failure feature is enabled or not.
servers	*list of Server* see 2.1174.1	List of servers monitored by Server-failure.
summaryStatement	*string*	Summary statement for type of servers in the list.

2.1177 show monitor session [...]

revision 3

`invalidHeaderRemoval-Sessions` **	*list of string*	List of sessions that have egress sFlow running on tx mirror sources and have invalid header removal sizes. **Since: 4.35.0
`multiDestDisableAllHeader-Removal` **	*boolean*	Whether header removal should be disabled for all mirror sessions due to incompatibility with multi-destination mirroring. **Since: 4.35.0
`multiDestSessions` **	*list of string*	List of sessions that have multiple active destinations configured. **Since: 4.23.1
`[name]`	*string*	The name of the specified session in the CLI command, if it was set.
`sessions`	*table(string) = MirrorSession* see 2.1177.1	Map from session name to the session details.

2.1177.1 MirrorSession

`[aclType]`	*enum: ipv6 | mac | ip*	ACL type.
`[aclsWithMirrorAction]` **	*AclsWithMirrorAction* see 2.1177.1.3	Access lists with mirror action rules. **Since: 4.24.1
`congestionMonitor` **	*boolean*	Mirroring on congestion. **Since: 4.31.1
`[cpuQueue]` **	*string*	Copp queue set for CPU port. **Since: 4.33.1
`[egressAclMirrored-Truncation]` **	*integer*	Set to 128 if metadata is enabled for the TX mirroring to GRE. **Since: 4.24.1
`greMetadata`	*list of string*	Metadata elements in the GRE header.
`[grePayloadType]`	*enum: payloadTypeInnerPacket | payloadTypeFullPacket | payloadTypeNone*	Payload type of mirrored packets in the session.
`[greTimestampingEnabled]`	*boolean*	Whether timestamping is enabled for GRE mirror sessions.
`greTimestampingSupported`	*boolean*	Whether the hardware platform supports GRE timestamping. Can be used by CLI to determine whether or not to report timestamping enabled state.
`[greTunnels]`	*table(Interface name) = TunnelIntfs* see 2.1177.1.5	Next hop interfaces selected for GRE tunnel destination.
`headerRemovalSize` **	*integer*	Header removal size in the session. **Since: 4.22.1
`hwProgrammingStatus-Supported`	*boolean*	Whether platform code supports outputting hardware programming status. Can be used by CLI to indicate whether monitor sessions are programmed in hardware.

[mirrorDeviceName]	*string*	The mirror-device name to use for receiving packets mirrored to cpu.
[mirrorRateLimit]	*integer*	Mirroring rate limit in bps.
[mirrorRateLimitChip]	*enum: per-egress-chip | per-ingress-chip*	Rate limit on multi-chip.
programmedInHw	*boolean*	Whether session is programmed in HW.
[rxSampleRate]	*integer*	Mirroring sampling rate.
sessionAcl	*string*	ACL applied to the session.
[sessionAclDetails] **	*AclDetails* see 2.1177.1.2	Session access-list details. **Since: 4.22.1
[sourceAcls]	*table(string) = Acl* see 2.1177.1.1	The ACL applied to the source interface.
[sourceAclsDetails] **	*table(string) = AclDetails* see 2.1177.1.2	Mapping from source ACL name to its details. **Since: 4.27.0
sourceBothInterfaces	*list of string*	Interfaces mirroring both their ingress and egress traffic.
sourceInactiveInterfaces	*list of Interface* see 2.1177.1.4	Inactive interfaces configured to mirror traffic in this session.
[sourceInactiveVlans] **	*list of Vlan* see 2.1177.1.6	Inactive VLANs configured to mirror traffic in this session. **Since: 4.26.2
sourceInterfaces **	*list of string*	All Interfaces configured as mirroring sources in this session. **Since: 4.22.0
sourceRxInterfaces	*list of string*	Interfaces mirroring their ingress traffic.
[sourceRxVlans] **	*list of integer*	VLANs mirroring their ingress traffic. **Since: 4.26.2
sourceTxInterfaces	*list of string*	Interfaces mirroring their egress traffic.
sourceUnknownInterfaces	*list of string*	Interfaces in an unknown state.
[sourceVlans] **	*list of integer*	All VLANs configured as mirroring sources in this session. **Since: 4.26.2
[targetInterfaces]	*list of Interface* see 2.1177.1.4	Interfaces to which traffic is forwarded.
[tcamProfileFeature] **	*enum: mirror-feature1 | mirror-feature2 | mirror-feature4 | mirror-feature3*	TCAM profile feature for mirroring ACL. **Since: 4.31.0
truncate	*boolean*	Packet truncation enabled in the session.
truncateStatus	*string*	Status and reason for truncation in the session.
[truncationSize]	*integer*	Packet truncation size in the session.
[txMirrorAclSupported] **	*boolean*	Whether tx Mirroring ACLs are supported for mirror sessions. **Since: 4.28.0
[vxlanTunnels] **	*table(Interface name) = TunnelIntfs* see 2.1177.1.5	Next hop interfaces selected for VXLAN tunnel destination. **Since: 4.30.2

2.1177.1.1 Acl

aclDetails	*boolean*	Display the unsupported TCAM qualifiers.
aclName	*string*	ACL name.
[aclPriority]	*integer*	ACL priority.
[aclType]	*enum: ipv6 | mac | ip*	ACL type.
[aclUnsupportedQualifiers]	*list of string*	Unsupported qualifiers.
[activeTxMirrorSource] **	*boolean*	Indicates if the egress mirroring source interface is active. **Since: 4.35.0

2.1177.1.2 AclDetails

[ipAclList]	*IpAclList* see 2.62.1	IPv4 access-lists.
[ipv6AclList]	*Ipv6AclList* see 2.62.2	IPv6 access-lists.
[macAclList]	*MacAclList* see 2.302.1.2.1.1	MAC access-lists.

2.1177.1.3 AclsWithMirrorAction

[ipAcls]	*list of Ipv4AclWithMirrorAction* see 2.1177.1.3.1	IPv4 access lists with mirror action.
[ipv6Acls]	*list of Ipv6AclWithMirrorAction* see 2.1177.1.3.2	IPv6 access lists with mirror action.
[macAcls]	*list of MacAclWithMirrorAction* see 2.1177.1.3.3	MAC access lists with mirror action.

2.1177.1.3.1 Ipv4AclWithMirrorAction

acl	*IpAclList* see 2.62.1	IPv4 access lists.
direction **	*enum: in | out*	Direction of access-list with mirror action. **Since: 4.26.2
name	*string*	ACL name.

2.1177.1.3.2 Ipv6AclWithMirrorAction

acl	*Ipv6AclList* see 2.62.2	IPv6 access lists.
direction **	*enum: in | out*	Direction of access-list with mirror action. **Since: 4.26.2
name	*string*	ACL name.

2.1177.1.3.3 MacAclWithMirrorAction

acl	*MacAclList* see 2.302.1.2.1.1	MAC access lists.

direction **	*enum: in | out*	Direction of access-list with mirror action. **Since: 4.26.2
name	*string*	ACL name.

2.1177.1.4 Interface

[dscp]	*integer*	DSCP of Mirroring Tunnel.
[dstIpGenAddr] **	*IP address*	Mirroring Tunnel destination address. **Since: 4.23.0
[forwardingDrop]	*boolean*	mirror drop packets.
[greHdrProto]	*integer*	protocol in GRE header.
[key] **	*integer*	Key in GRE tunnel. **Since: 4.26.2
name	*interface name*	Interface name.
operState	*enum: inactive | active | unknown*	The interface's current operating status.
operStateReason	*string*	Reason for the current operating status. Only set if the operState is inactive.
[srcIpGenAddr] **	*IP address*	Mirroring Tunnel source address. **Since: 4.23.0
[ttl]	*integer*	TTL of Mirroring Tunnel.
[tunnelType] **	*enum: gre | vxlan | invalid*	Type of mirroring tunnel. **Since: 4.30.2
[vlan] **	*integer*	VLAN of VXLAN tunnel. **Since: 4.30.2
[vni] **	*integer*	VNI of VXLAN tunnel. **Since: 4.30.2
[vrf]	*string*	VRF of Mirroring Tunnel.
[vti] **	*interface name*	VXLAN tunnel interface. **Since: 4.30.2

2.1177.1.5 TunnelIntfs

tunnelIntfs	*table(Interface name) = MemberIntfs* see 2.1177.1.5.1	tunnel next hop interface.

2.1177.1.5.1 MemberIntfs

memberIntfs	*list of Interface name*	Port-Channel member interfaces.

2.1177.1.6 Vlan

operState	*enum: inactive | unknown*	The interface's current operating status.
[operStateReason]	*string*	Reason the state is inactive. Only set if the operState is inactive.
vlan	*integer*	VLAN ID.

2.1178 show monitor system

currLowMemModeStatus	*boolean*	The system is currently under Memory Exhaustion.
featureEnabled	*boolean*	Memory Exhaustion feature is enabled.
[lastLowMemModeEntered]	*floating point number*	Time of last entrance in Memory Exhaustion.
[lastLowMemModeExited]	*floating point number*	Time of last exit from Memory Exhaustion.
lowMemModeCount	*integer*	Number of times the system has entered Memory Exhaustion.

2.1179 show monitor telemetry inband

deviceId	*string*	Device ID of the switch.
enabled	*boolean*	Inband telemetry is enabled on the switch.
inProgressReason	*string*	Reason for operational status in progress.
intDetectionMethod	*string*	Default Inband telemetry detection method.
intVersion **	*string*	InbandTelemetry version. **Since: 4.29.2
operStatus	*string*	Operational status of Inband telemetry.
[policies]	*table(string) = SamplePolicyModel* see 2.1179.2	Maps sample policy name to its configuration.
probeMarker	*integer*	Configured probe marker for Inband telemetry.
probeProtocol	*integer*	IP header protocol/next-header field for INT packets.
profiles	*InbandTelemetryProfiles* see 2.1179.1	Core, Edge and Vxlan profiles.
udpDstPorts **	*list of integer*	Configured udp destination ports for INT packets. **Since: 4.29.2

2.1179.1 InbandTelemetryProfiles

[coreProfiles]	*table(string) = Profile* see 2.1179.1.1	Maps core profiles to their corresponding configuration.
[edgeProfiles]	*table(string) = Profile* see 2.1179.1.1	Maps edge profiles to their corresponding configuration.
intVersion **	*string*	InbandTelemetry version. **Since: 4.29.2
transitOnly **	*boolean*	InbandTelemetry transit only mode. **Since: 4.32.2
[vxlanProfiles] **	*table(string) = Profile* see 2.1179.1.1	Maps vxlan profiles to their corresponding configuration. **Since: 4.27.0

2.1179.1.1 Profile

egressCollection	*string*	The collector name.
[egressDrop]	*string*	Whether egress drop is enabled or disabled.
profileErrorReason	*string*	None or the reason for error.
profileStatus	*string*	Whether the port is active or inactive or in error condition.
profileType	*string*	The type of profile.
[sampleRate]	*integer*	Sample rate of the profile.

2.1179.2 SamplePolicyModel

rules	*list of Rule* see 2.1179.2.1	Detailed information of match rules.

2.1179.2.1 Rule

[actions]	*Actions* see 2.1179.2.1.1	Actions for the rule.
matchOption	*string*	Match on packet type.
[matches]	*Matches* see 2.1179.2.1.2	Matches for the rule.
ruleString	*string*	Match rule name.

2.1179.2.1.1 Actions

[count] **	*integer*	(Deprecated - refer to the "inputCounter" attribute) Number of packets hitting the rule applied on input. **Since: 4.23.0
[countNamed] **	*table(string) = CountData* see 2.1179.2.1.1.1	(Deprecated - refer to the "inputNamedCounters" attribute) A mapping of counter name to its input count data. **Since: 4.24.2
[drop]	*boolean*	Drop action.
[dropNotification] **	*DropNotification* see 2.1179.2.1.1.2	Drop notification action. **Since: 4.32.1
[flow] **	*SessionOffloadActions* see 2.1179.2.1.1.18	Match on the specified rule flow to offload. **Since: 4.33.2
[flowTracking] **	*boolean*	Flow tracking action. **Since: 4.35.2
[goto] **	*GotoAction* see 2.1179.2.1.1.3	Match on the specified rule next. **Since: 4.26.2
[inputCounter] **	*integer*	Number of packets hitting the rule applied on input. **Since: 4.26.0
[inputNamedCounters] **	*table(string) = CountData* see 2.1179.2.1.1.1	A mapping of counter name to its input count data. **Since: 4.26.0
[log] **	*boolean*	Log action. **Since: 4.24.1
[mirrorSession] **	*string*	Set mirror action. **Since: 4.28.2
[outputCounter] **	*integer*	Number of packets hitting the rule applied on output. **Since: 4.26.0
[outputNamedCounters] **	*table(string) = CountData* see 2.1179.2.1.1.1	A mapping of counter name to its output count data. **Since: 4.26.0
[police]	*PoliceRate* see 2.1179.2.1.1.7	Police action.
[policeCount] **	*PoliceCount* see 2.1179.2.1.1.4	Descriptive count for police. **Since: 4.31.2

`[policer]` **	*Policer* see 2.1179.2.1.1.8	Policer action. **Since: 4.34.2
`[redirectInfo]` **	*TapAggRedirect* see 2.1179.2.1.1.17	Redirect traffic action. **Since: 4.31.2
`[redirectNexthop]` **	*RedirectNexthop* see 2.1179.2.1.1.10	Action of redirect traffic to next-hop(s). **Since: 4.27.1
`[redirectNexthopGroups]` **	*list of string*	Action of redirect traffic to next-hop group(s). **Since: 4.26.2
`[redirectNexthopInterface]` **	*interface name*	Action of redirect traffic to a next-hop interface. **Since: 4.32.0
`[redirectVxlan]` **	*RedirectVxlan* see 2.1179.2.1.1.12	Action of redirect traffic to VXLAN next-hop. **Since: 4.34.1
`[replicatePacket]` **	*ReplicatePacket* see 2.1179.2.1.1.13	Replicate packet actions. **Since: 4.31.2
`[sample]` **	*boolean*	Sample action. **Since: 4.26.0
`[sampleAll]` **	*boolean*	Sample all action. **Since: 4.26.0
`[setDecapVrf]` **	*SetDecapVrfModel* see 2.1179.2.1.1.19	Set Decap VRF. **Since: 4.31.1
`[setDscp]` **	*integer*	Set header DSCP value. **Since: 4.23.1
`[setHeaderRemove]` **	*SetHeaderRemoveModel* see 2.1179.2.1.1.20	Set header remove. **Since: 4.29.1
`[setIdentityTag]` **	*SetIdentityTagModel* see 2.1179.2.1.1.15	Set Dot1Q identity tag. **Since: 4.27.0
`[setMacAddress]` **	*SetMacAddressModel* see 2.1179.2.1.1.16	Set MAC address. **Since: 4.28.2
`[setTc]` **	*integer*	Set forwarding traffic class. **Since: 4.23.1
`[setTimestampHeader]` **	*boolean*	Set MAC timestamp header. **Since: 4.28.1
`[setTtl]` **	*integer*	Set header TTL value. **Since: 4.30.0
`[setVrf]` **	*string*	Set forwarding VRF. **Since: 4.27.0
`[setVrfSecondary]` **	*SetVrfSecondaryModel* see 2.1179.2.1.1.21	Set secondary forwarding VRF. **Since: 4.28.2
`[sflow]` **	*boolean*	Sflow action. **Since: 4.29.1
`[stripHeaderBytes]` **	*string*	Remove 802.1Q outer tag. **Since: 4.27.0
`[tapAggRedirect]` **	*TapAggRedirect* see 2.1179.2.1.1.17	Redirect traffic action in Tap Aggregation mode. **Since: 4.26.2
`[verifyFlowReturnFailure]` **	*VerifyFlowReturnFailure* see 2.1179.2.1.1.22	Verify flow return failure. **Since: 4.33.1

2.1179.2.1.1.1 CountData

[byteCount]	*integer*	Number of bytes matched.
[packetCount]	*integer*	Number of packets matched.
[undefined]	*boolean*	Named counter has not been defined.

2.1179.2.1.1.2 DropNotification

[eligible] **	*string*	Condition under which to drop and notify. **Since: 4.34.2
[icmpCode]	*integer*	ICMP code.
[icmpType]	*integer*	ICMP type.
messageType	*enum: icmp6NoRoute | trim | icmpHostUnreachable | icmpNetUnreachable | tcpReset | icmpNetProhibited | tcp6Reset | icmp6AddrUnreachable | icmpPortUnreachable | icmp6AdminProhibited | icmp6PortUnreachable | icmpHostProhibited | icmpAdminProhibited | icmpProtoUnreachable*	Message type.

2.1179.2.1.1.3 GotoAction

[matchName]	*string*	Specified match rule name to go to next.
[nextMatch]	*boolean*	Match on the next match rule.

2.1179.2.1.1.4 PoliceCount

[above] **	*TotalInfo* see 2.1179.2.1.1.6	Number of packets above police rate. **Since: 4.31.2
[aboveRate] **	*CounterRateAndUnit* see 2.1179.2.1.1.5	Counter rate above the police rate limit. **Since: 4.32.0
[below] **	*TotalInfo* see 2.1179.2.1.1.6	Number of packets below police rate. **Since: 4.31.2
[belowRate] **	*CounterRateAndUnit* see 2.1179.2.1.1.5	Counter rate below the police rate limit. **Since: 4.32.0

2.1179.2.1.1.5 CounterRateAndUnit

[rate]	*floating point number*	Counter rate above/below the police rate limit.
[unit]	*enum: tbps | mbps | gbps | bps | kbps*	Unit of counter rate above/below the police rate limit.

2.1179.2.1.1.6 TotalInfo

[byteTotal]	*integer*	Total byte count.
[packetTotal]	*integer*	Total packet count.

2.1179.2.1.1.7 PoliceRate

[burstSize] **	*integer*	Lower burst size. **Since: 4.27.2
[burstUnit] **	*string*	Unit of police burst size. **Since: 4.27.2
rate	*integer*	Lower police rate.
unit	*string*	Unit of police rate.

2.1179.2.1.1.8 Policer

[groupPolicer]	*GroupPolicer* see 2.1179.2.1.1.9	Group policer.

2.1179.2.1.1.9 GroupPolicer

[policerName]	*string*	Group policer name.

2.1179.2.1.1.10 RedirectNexthop

[allowResolutionByDefault] **	*boolean*	Allow next hop resolution via default route. **Since: 4.35.0
nexthops	*list of IP address*	List of configured next hops.
[recursive]	*boolean*	Enable recursive next hop resolution.
[resolvedNexthops] **	*table(string) = NexthopInfo* see 2.1179.2.1.1.11	A mapping of ingress VRF name to its active next hops. **Since: 4.27.2
[unresolvedAction] **	*string*	Action if nexthop is not resolved. **Since: 4.35.2
[vrfName]	*string*	Resolve next hop in a VRF.

2.1179.2.1.1.11 NexthopInfo

nexthops	*list of IP address*	List of next hops.

2.1179.2.1.1.12 RedirectVxlan

[macAddr]	*MAC address*	Configured MAC address for VXLAN next-hop.
remoteVtep	*IP address*	Configured remote VTEP address for VXLAN next-hop.

[resolvedVteps] **	*table(string) = boolean*	A mapping of ingress VRF name to its VTEP resolution state. **Since: 4.35.0
[vni]	*integer*	Configured VNI for VXLAN next-hop.
[vti]	*interface name*	Configured interface for VXLAN next-hop.

2.1179.2.1.1.13 ReplicatePacket

namedActionSets	*table(string) = ReplicatePacketActions* see 2.1179.2.1.1.14	Action sets, keyed by action set name.

2.1179.2.1.1.14 ReplicatePacketActions

[setIdentityTag]	*SetIdentityTagModel* see 2.1179.2.1.1.15	Set Dot1Q identity tag.
[setMacAddress]	*SetMacAddressModel* see 2.1179.2.1.1.16	Set MAC address.
[stripHeaderBytes]	*string*	Remove 802.1Q outer tag.
[tapAggRedirect]	*TapAggRedirect* see 2.1179.2.1.1.17	Redirect traffic action in Tap Aggregation mode.

2.1179.2.1.1.15 SetIdentityTagModel

idTag	*integer*	Id-tag value.
innerIdTag	*integer*	Inner id-tag value.

2.1179.2.1.1.16 SetMacAddressModel

destMacAddr	*MAC address*	MAC address for the destination.
srcMacAddr	*MAC address*	MAC address for the source.

2.1179.2.1.1.17 TapAggRedirect

groups	*list of string*	List of aggregation groups.
interfaces	*list of string*	List of tool interfaces.

2.1179.2.1.1.18 SessionOffloadActions

offload	*boolean*	Match on the rule and offload the flow.

2.1179.2.1.1.19 SetDecapVrfModel

decapVrf	*string*	Decapsulation VRF name.
fallbackVrf	*string*	Fallback VRF name.
forwardVrf	*string*	Forwarding VRF name.

2.1179.2.1.1.20 SetHeaderRemoveModel

preserveEth	*boolean*	Preserve the original Ethernet header, including VLAN tags if any.
size	*integer*	The number of bytes (after the Ethernet header, including any VLAN tags) to remove.

2.1179.2.1.1.21 SetVrfSecondaryModel

[useVrfSecondaryResult]	*boolean*	Use secondary VRF route result.
[vrfName]	*string*	Secondary forwarding VRF name.

2.1179.2.1.1.22 VerifyFlowReturnFailure

[action]	*drop*	Failure action.

2.1179.2.1.2 Matches

[addressFamily] **	*enum: ipv4 | mac | ipv6*	Address family of encapsulated packet. **Since: 4.26.2
[appProfiles] **	*list of ApplicationProfile* see 2.1179.2.1.2.1	Application profile names. **Since: 4.32.1
[cosData] **	*list of CosMatch* see 2.1179.2.1.2.2	COS match criteria. **Since: 4.31.0
[description] **	*string*	Match description. **Since: 4.33.1
[destExtPrefixSet] **	*list of PrefixFieldSet* see 2.1179.2.1.2.14	Destination prefix field-sets. **Since: 4.26.0
[destLpmPrefixSet] **	*list of PrefixFieldSet* see 2.1179.2.1.2.14	Destination prefix field-sets (longest prefix match). **Since: 4.26.2
[destLpmPrefixes] **	*list of IP address prefix*	Destination prefix (longest prefix match). **Since: 4.26.2
[destPrefixSets] **	*list of string*	(Deprecated - refer to "destExtPrefixSet") Destination prefix field-sets. **Since: 4.23.0
[destPrefixes]	*list of IP address prefix*	Destination prefix.
[destSelf] **	*DestSelf* see 2.1179.2.1.2.4	Destination prefix self. **Since: 4.31.0
[dot1qVlanTags] **	*list of Dot1QMatch* see 2.1179.2.1.2.5	802.1Q VLAN tags. **Since: 4.26.2
[dscps]	*list of NumericalRange* see 2.1179.2.1.2.3	DSCP.
[dstMacAddrSet] **	*list of MacAddrFieldSet* see 2.1179.2.1.2.11	Destination MAC field-set. **Since: 4.29.1
[dstMacs] **	*list of MAC address*	Destination MAC addresses. **Since: 4.29.1
[dzGreMatch] **	*MatchesBase* see 2.1179.2.1.2.12	DzGRE packet match criteria. **Since: 4.32.0

[dzGrePolicyIds] **	*list of NumericalRange* see 2.1179.2.1.2.3	DzGRE Policy Id. **Since: 4.32.0
[dzGrePortIds] **	*list of NumericalRange* see 2.1179.2.1.2.3	DzGRE Port Id. **Since: 4.32.0
[dzGreSwitchIds] **	*list of NumericalRange* see 2.1179.2.1.2.3	DzGRE Switch Id. **Since: 4.32.0
[ecns] **	*list of NumericalRange* see 2.1179.2.1.2.3	ECN. **Since: 4.27.1
[encapsulation] **	*Encapsulation* see 2.1179.2.1.2.23	Encapsulation match criteria. **Since: 4.26.2
[ethTypes] **	*list of NumericalRange* see 2.1179.2.1.2.3	(Deprecated - refer to "ethTypesExt") Ethernet type. **Since: 4.29.2
[ethTypesExt] **	*list of HexNumericalRange* see 2.1179.2.1.2.8	Ethernet type. **Since: 4.30.0
[forwardingTypes] **	*list of string*	Forwarding type match criteria. **Since: 4.35.2
[fragment] **	*Fragment* see 2.1179.2.1.2.7	Fragment. **Since: 4.23.1
[innerMatch] **	*MatchesBase* see 2.1179.2.1.2.12	Inner packet match criteria. **Since: 4.26.2
[ipLengths] **	*list of NumericalRange* see 2.1179.2.1.2.3	IP length. **Since: 4.23.2
[locations] **	*list of LocationMatch* see 2.1179.2.1.2.9	Location. **Since: 4.30.2
[matchIpOptions] **	*boolean*	Match on any IP options. **Since: 4.23.2
[matchL4Protocol]	*string*	Protocol BGP.
[matchTracked] **	*boolean*	Match on any tracked packet. **Since: 4.27.1
[neighborProtocol]	*string*	Neighbor protocol.
[neighborProtocolBgp-Dynamic] **	*string*	Match on configured dynamic BGP peer listen ranges. **Since: 4.34.1
[nexthopGroups] **	*list of string*	Next-hop groups. **Since: 4.29.2
[packetTypes] **	*PacketTypes* see 2.1179.2.1.2.13	PacketType match criteria. **Since: 4.32.1
[protocols]	*list of Protocol* see 2.1179.2.1.2.15	Protocol.
[serviceSet] **	*list of ServiceFieldSet* see 2.1179.2.1.2.21	Service field-sets. **Since: 4.32.1
[srcExtPrefixSet] **	*list of PrefixFieldSet* see 2.1179.2.1.2.14	Source prefix field-sets. **Since: 4.26.0
[srcLpmPrefixSet] **	*list of PrefixFieldSet* see 2.1179.2.1.2.14	Source prefix field-sets (longest prefix match). **Since: 4.26.2
[srcLpmPrefixes] **	*list of IP address prefix*	Source prefix (longest prefix match). **Since: 4.26.2
[srcMacAddrSet] **	*list of MacAddrFieldSet* see 2.1179.2.1.2.11	Source MAC field-set. **Since: 4.29.1

[srcMacs] **	*list of MAC address*	Source MAC addresses. **Since: 4.29.1
[srcPrefixSets] **	*list of string*	Deprecated - refer to "srcExtPrefixSet") Source prefix field-sets. **Since: 4.23.0
[srcPrefixes]	*list of IP address prefix*	Source prefix.
[teidFieldSets] **	*list of TeidFieldSet* see 2.1179.2.1.2.22	TEID field-sets. **Since: 4.28.0
[teids] **	*list of NumericalRange* see 2.1179.2.1.2.3	Tunnel endpoint identifier. **Since: 4.28.0
[trimmed] **	*boolean*	Match on any trimmed packet. **Since: 4.35.0
[ttls]	*list of NumericalRange* see 2.1179.2.1.2.3	TTL.
[vlans] **	*list of NumericalRange* see 2.1179.2.1.2.3	VLAN IDs. **Since: 4.31.2

2.1179.2.1.2.1 ApplicationProfile

[apps]	*integer*	Number of apps in the profile.
name	*string*	Name of application profile.
[undefined]	*boolean*	Application profile has not been defined.

2.1179.2.1.2.2 CosMatch

[coss]	*list of NumericalRange* see 2.1179.2.1.2.3	Class of Service values.

2.1179.2.1.2.3 NumericalRange

high	*integer*	Maximum value.
low	*integer*	Minimum value.

2.1179.2.1.2.4 DestSelf

[selfIpUnicast]	*boolean*	Unicast packets to CPU for self IP.

2.1179.2.1.2.5 Dot1QMatch

[dot1qVlanFieldSets]	*list of VlanFieldSet* see 2.1179.2.1.2.6	Outer VLAN field sets.
[dot1qVlans]	*list of NumericalRange* see 2.1179.2.1.2.3	Outer VLAN tags.
[innerVlans] **	*list of NumericalRange* see 2.1179.2.1.2.3	Inner VLAN tags. **Since: 4.28.2

2.1179.2.1.2.6 VlanFieldSet

[name]	*string*	Name of VLAN field-set.

[numVlans]	*integer*	Number of VLANs in field-set.
[undefined]	*boolean*	VLAN field-set has not been defined.

2.1179.2.1.2.7 Fragment

[fragmentOffsets]	*list of NumericalRange* see 2.1179.2.1.2.3	Fragment offset.
[matchAllFragments]	*boolean*	Match all fragments.

2.1179.2.1.2.8 HexNumericalRange

high	*string*	Maximum value.
low	*string*	Minimum value.

2.1179.2.1.2.9 LocationMatch

[alias]	*string*	Location alias name.
[matches]	*list of ValueMask* see 2.1179.2.1.2.10	Location alias matches.

2.1179.2.1.2.10 ValueMask

[mask]	*string*	Mask for the match.
[value]	*string*	Value to match.

2.1179.2.1.2.11 MacAddrFieldSet

name	*string*	Name of MAC field-set.
[numMacAddresses]	*integer*	Number of MAC addresses in field-set.
[undefined]	*boolean*	MAC field-set has not been defined.

2.1179.2.1.2.12 MatchesBase

Could also be an instance of:
Matches 2.1179.2.1.2

[addressFamily]	*enum: ipv4 | mac | ipv6*	Address family of encapsulated packet.
[appProfiles] **	*list of ApplicationProfile* see 2.1179.2.1.2.1	Application profile names. **Since: 4.32.1
[cosData] **	*list of CosMatch* see 2.1179.2.1.2.2	COS match criteria. **Since: 4.31.0
[destExtPrefixSet]	*list of PrefixFieldSet* see 2.1179.2.1.2.14	Destination prefix field-sets.
[destLpmPrefixSet]	*list of PrefixFieldSet* see 2.1179.2.1.2.14	Destination prefix field-sets (longest prefix match).
[destLpmPrefixes]	*list of IP address prefix*	Destination prefix (longest prefix match).
[destPrefixSets]	*list of string*	(Deprecated - refer to "destExtPrefixSet") Destination prefix field-sets.

[destPrefixes]	*list of IP address prefix*	Destination prefix.
[destSelf] **	*DestSelf* see 2.1179.2.1.2.4	Destination prefix self. **Since: 4.31.0
[dot1qVlanTags]	*list of Dot1QMatch* see 2.1179.2.1.2.5	802.1Q VLAN tags.
[dscps]	*list of NumericalRange* see 2.1179.2.1.2.3	DSCP.
[dstMacAddrSet] **	*list of MacAddrFieldSet* see 2.1179.2.1.2.11	Destination MAC field-set. **Since: 4.29.1
[dstMacs] **	*list of MAC address*	Destination MAC addresses. **Since: 4.29.1
[dzGrePolicyIds] **	*list of NumericalRange* see 2.1179.2.1.2.3	DzGRE Policy Id. **Since: 4.32.0
[dzGrePortIds] **	*list of NumericalRange* see 2.1179.2.1.2.3	DzGRE Port Id. **Since: 4.32.0
[dzGreSwitchIds] **	*list of NumericalRange* see 2.1179.2.1.2.3	DzGRE Switch Id. **Since: 4.32.0
[ecns] **	*list of NumericalRange* see 2.1179.2.1.2.3	ECN. **Since: 4.27.1
[encapsulation]	*Encapsulation* see 2.1179.2.1.2.23	Encapsulation match criteria.
[ethTypes] **	*list of NumericalRange* see 2.1179.2.1.2.3	(Deprecated - refer to "ethTypesExt") Ethernet type. **Since: 4.29.2
[ethTypesExt] **	*list of HexNumericalRange* see 2.1179.2.1.2.8	Ethernet type. **Since: 4.30.0
[forwardingTypes] **	*list of string*	Forwarding type match criteria. **Since: 4.35.2
[fragment]	*Fragment* see 2.1179.2.1.2.7	Fragment.
[ipLengths]	*list of NumericalRange* see 2.1179.2.1.2.3	IP length.
[locations] **	*list of LocationMatch* see 2.1179.2.1.2.9	Location. **Since: 4.30.2
[matchIpOptions]	*boolean*	Match on any IP options.
[matchL4Protocol]	*string*	Protocol BGP.
[matchTracked] **	*boolean*	Match on any tracked packet. **Since: 4.27.1
[neighborProtocol]	*string*	Neighbor protocol.
[neighborProtocolBgp-Dynamic] **	*string*	Match on configured dynamic BGP peer listen ranges. **Since: 4.34.1
[nexthopGroups] **	*list of string*	Next-hop groups. **Since: 4.29.2
[packetTypes] **	*PacketTypes* see 2.1179.2.1.2.13	PacketType match criteria. **Since: 4.32.1
[protocols]	*list of Protocol* see 2.1179.2.1.2.15	Protocol.
[serviceSet] **	*list of ServiceFieldSet* see 2.1179.2.1.2.21	Service field-sets. **Since: 4.32.1
[srcExtPrefixSet]	*list of PrefixFieldSet* see 2.1179.2.1.2.14	Source prefix field-sets.

[srcLpmPrefixSet]	*list of PrefixFieldSet* see 2.1179.2.1.2.14	Source prefix field-sets (longest prefix match).
[srcLpmPrefixes]	*list of IP address prefix*	Source prefix (longest prefix match).
[srcMacAddrSet] **	*list of MacAddrFieldSet* see 2.1179.2.1.2.11	Source MAC field-set. **Since: 4.29.1
[srcMacs] **	*list of MAC address*	Source MAC addresses. **Since: 4.29.1
[srcPrefixSets]	*list of string*	Deprecated - refer to "srcExtPrefixSet") Source prefix field-sets.
[srcPrefixes]	*list of IP address prefix*	Source prefix.
[teidFieldSets] **	*list of TeidFieldSet* see 2.1179.2.1.2.22	TEID field-sets. **Since: 4.28.0
[teids] **	*list of NumericalRange* see 2.1179.2.1.2.3	Tunnel endpoint identifier. **Since: 4.28.0
[trimmed] **	*boolean*	Match on any trimmed packet. **Since: 4.35.0
[ttls]	*list of NumericalRange* see 2.1179.2.1.2.3	TTL.
[vlans] **	*list of NumericalRange* see 2.1179.2.1.2.3	VLAN IDs. **Since: 4.31.2

2.1179.2.1.2.13 PacketTypes

[multicast] **	*multicastOnly*	Mutlicast PacketType values. **Since: 4.33.2
[vxlanDecap]	*enum: vxlanDecapOnly | vxlanDecapExclude*	Vxlan Decap packet type values.

2.1179.2.1.2.14 PrefixFieldSet

name	*string*	Name of prefix field-set.
[numExceptPrefixes]	*integer*	Number of except prefixes in field-set.
[numPrefixes]	*integer*	Number of accept prefixes in field-set.
[undefined]	*boolean*	Prefix field-set has not been defined.

2.1179.2.1.2.15 Protocol

[icmps] **	*list of IcmpType* see 2.1179.2.1.2.16	ICMP info. **Since: 4.24.2
[ports] **	*list of Port* see 2.1179.2.1.2.17	List of L4 ports that can be ORed together. **Since: 4.25.1
[protocolRange]	*NumericalRange* see 2.1179.2.1.2.3	Protocol.
[tcpFlagGroups] **	*list of TcpFlags* see 2.1179.2.1.2.19	List of TCP flags that can be ORed together. **Since: 4.25.2

2.1179.2.1.2.16 IcmpType

[icmpCodes]	*list of NumericalRange* see 2.1179.2.1.2.3	ICMP code.

[icmpTypes]	*NumericalRange* see 2.1179.2.1.2.3	ICMP type.

2.1179.2.1.2.17 Port

[destExtL4PortFieldSet] **	*list of L4PortFieldSet* see 2.1179.2.1.2.18	Destination l4-port field-set info. **Since: 4.26.0
[destL4PortFieldSets]	*list of string*	(Deprecated - refer to "destExtL4PortFieldSet") Destination l4-port field-sets.
[destPorts]	*list of NumericalRange* see 2.1179.2.1.2.3	Destination port.
[srcExtL4PortFieldSet] **	*list of L4PortFieldSet* see 2.1179.2.1.2.18	Source l4-port field-set info. **Since: 4.26.0
[srcL4PortFieldSets]	*list of string*	(Deprecated - refer to "srcExtL4PortFieldSet") Source l4-port field-sets".
[srcPorts]	*list of NumericalRange* see 2.1179.2.1.2.3	Source port.

2.1179.2.1.2.18 L4PortFieldSet

[name]	*string*	Field-set name.
[numPorts]	*integer*	Number of ports in field-set.
[undefined]	*boolean*	L4 port field-set has not been defined.

2.1179.2.1.2.19 TcpFlags

[tcpFlags]	*list of TcpFlag* see 2.1179.2.1.2.20	List of ANDed TCP flags.

2.1179.2.1.2.20 TcpFlag

name	*string*	TCP flag name.
value	*boolean*	TCP flag bit value.

2.1179.2.1.2.21 ServiceFieldSet

[name]	*string*	Name of service field-set.
[numProtocols]	*integer*	Number of protocols in field-set.
[undefined]	*boolean*	Service field-set has not been defined.

2.1179.2.1.2.22 TeidFieldSet

[fieldSetType]	*integer*	Type of field-set.
[name]	*string*	Name of TEID field-set.
[numTeids]	*integer*	Number of TEIDs in field-set.
[undefined]	*boolean*	TEID field-set has not been defined.

2.1179.2.1.2.23 Encapsulation

[encapsulationType]	*enum: dzgre | vxlan | gtpv1*	Encapsulation type.

2.1180 show monitor telemetry inband profile [...]

see 2.1179.1

2.1181 show monitor telemetry inband profile summary [...]

[coreIntfList]	*table(string) = IntfList* see 2.1181.1	Core profiles.
[edgeIntfList]	*table(string) = IntfList* see 2.1181.1	Edge profiles.
[vxlanIntfList] **	*table(string) = IntfList* see 2.1181.1	Vxlan profiles. **Since: 4.27.0

2.1181.1 IntfList

[Intfs]	*list of Interface name*	Interface list.

2.1182 show monitor telemetry influx

destinationInfluxdb	*table(string) = InfluxTelemetry.Cli.DestinationInfluxdb* see 2.1182.1	A mapping between an InfluxDB destination name and an InfluxDB destination context.
globalTags	*table(string) = string*	A mapping between a global tag key and a global tag value.
sourceGroups **	*table(string) = string*	A mapping between a source group name and its state. **Since: 4.25.2
sourceSocket	*table(string) = InfluxTelemetry.Cli.SourceSocket* see 2.1182.2	A mapping between a socket name and a socket context.
telegrafRunning	*boolean*	Telegraf running status.

2.1182.1 InfluxTelemetry.Cli.DestinationInfluxdb

databaseName	*string*	Database name of the InfluxDB destination.
retentionPolicyName	*string*	Retention policy name of the InfluxDB destination.
url	*string*	URL of the InfluxDB destination.
vrfName **	*string*	VRF telegraf will use to transmit data. **Since: 4.25.2

2.1182.2 InfluxTelemetry.Cli.SourceSocket

`connectionLimit`	*integer*	Maximum number of connections allowed.
`url`	*string*	URL of the socket.

2.1183 show monitor telemetry path characteristics [...]

peers	*table(string) = ItsPeer* see 2.1183.1	A mapping of peer IP address to peer path groups.

2.1183.1 ItsPeer

groups	*table(string) = ItsGroup* see 2.1183.1.1	A mapping of path group name to its paths.
peerName	*string*	Peer name.

2.1183.1.1 ItsGroup

paths	*table(string) = ItsPath* see 2.1183.1.1.1	A mapping of path name to path state.

2.1183.1.1.1 ItsPath

dstIp	*IP address*	Destination IP address of the path.
sessions	*table(numeric string) = ItsSession* see 2.1183.1.1.1.1	A mapping of traffic class to telemetry session.
srcIp	*IP address*	Source IP address of the path.

2.1183.1.1.1.1 ItsSession

[characteristics]	*SessionCharacts* see 2.1183.1.1.1.2	Characteristics of the telemetry session.
[counters]	*SessionCounters* see 2.1183.1.1.1.3	Counters for the telemetry session.

2.1183.1.1.1.2 SessionCharacts

active	*boolean*	The telemetry session state is active.
availBandwidth **	*integer*	Available capacity for the path. **Since: 4.32.1
jitter	*floating point number*	Jitter in milliseconds of the telemetry session.
latency	*floating point number*	One way delay in milliseconds of the telemetry session.
load **	*floating point number*	Current load for the path. **Since: 4.32.1
lossRate	*floating point number*	Loss rate in percentage of the telemetry session.
[mtu] **	*integer*	Path MTU. **Since: 4.28.0
seconds	*integer*	Number of seconds the telemetrysession has been in this state.
throughput	*floating point number*	Throughput in Mbps of the telemetry session.

totalBandwidth **	*integer*	Total capacity for the path. **Since: 4.32.1

2.1183.1.1.1.3 SessionCounters

inBytes	*integer*	Number of bytes received from the telemetry session.
inPkts	*integer*	Number of packets received from the telemetry session.
inPktsDrop	*integer*	Number of packets dropped after being received from the telemetry session.
outBytes	*integer*	Number of bytes sent out of the telemetry session.
outPkts	*integer*	Number of packets sent out of the telemetry session.
outPktsDrop	*integer*	Number of packets dropped before being sent out of the telemetry session.

2.1184 show monitor telemetry path counters [...]

see 2.1183

2.1185 show monitor telemetry postcard counters

grePktSent	*integer*	GRE packets sent to collector.
multiDstSampleRcvd	*integer*	Muti destination packets sampled by GreenT.
sampleDiscarded	*integer*	Total samples discarded.
sampleRcvd	*integer*	Total packets sampled by GreenT.
sampleSent	*integer*	Total samples sent to collector.

2.1186 show monitor telemetry postcard policy

[collection]	*Collection* see 2.1186.1	Collection attributes.
enabled	*boolean*	Postcard telemetry is enabled.
sampleRate	*integer*	Sampling rate of 1 in 16k, 32k or 64k packets.
[sampleTcpUdpChecksum] **	*SampleTcpUdpChecksum* see 2.1186.2	TCP/UDP checksum and mask. **Since: 4.27.1
vxlanEnabled **	*boolean*	VXLAN marker mode is enabled. **Since: 4.27.1
[vxlanMarkerBit] **	*integer*	VXLAN marker bit. **Since: 4.27.1

2.1186.1 Collection

dstIp	*IP address*	Destination IP address.
srcIp	*IP address*	Source IP address.
version **	*integer*	GRE postcard version. **Since: 4.29.1

2.1186.2 SampleTcpUdpChecksum

mask	*integer*	Mask of TCP/UDP checksum or IP ID.
value	*integer*	TCP/UDP checksum or IP ID value.

2.1187 show monitor telemetry postcard policy profile [...]

profiles	*table(string) = ProfileModel* see 2.1187.1	Maps core profiles to their corresponding configuration.

2.1187.1 ProfileModel

appliedInterfaces	*list of Interface name*	Applied interface list for IPv4 rules.
appliedInterfaces6 **	*list of Interface name*	Applied interface list for IPv6 rules. **Since: 4.27.0
failures **	*table(string) = IntfList* see 2.1187.1.1	Failed interfaces for IPv4 rules, indexed by the failure message. **Since: 4.26.2
failures6 **	*table(string) = IntfList* see 2.1187.1.1	Failed interfaces for IPv6 rules, indexed by the failure message. **Since: 4.27.0
interfaces	*list of Interface name*	Interface list.
[samplePolicy]	*string*	Sample Policy.

2.1187.1.1 IntfList

[interfaces]	*list of Interface name*	Interface list.

2.1188 show monitor telemetry postcard sample policy [...]

policies	*table(string) = SamplePolicyModel* see 2.1188.1	Maps sample policy name to its configuration.

2.1188.1 SamplePolicyModel

rules	*list of Rule* see 2.1179.2.1	Detailed information of match rules.
tcpFlags **	*table(string) = string*	Maps tcp flags to their corresponding match rules. **Since: 4.31.2

2.1189 show monitor twamp-light ((ip IP) | (interface INTF)) raw [...]

results	*table(string) = TwampLightDelaysModel* see 2.1189.1	TWAMP light results.

2.1189.1 TwampLightDelaysModel

delays	*list of TwampLightProbeModel* see 2.1189.1.1	TWAMP light delays in microseconds.
interface	*interface name*	Name of the interface.

2.1189.1.1 TwampLightProbeModel

delay	*floating point number*	Delay in microseconds.
rxTime	*floating point number*	Rx time in seconds.
seqnum	*integer*	Sequence number.

2.1190 show monitor twamp-light [...]

addresses	*table(IPv4 or IPv6 address) = Result* see 2.1190.1	TWAMP light results, keyed by address.

2.1190.1 Result

intfId	*interface name*	Name of the interface.
oneWayMinDelay	*integer*	One way min delay in microseconds.
twoWayMinDelay	*integer*	Two way min delay in microseconds.

2.1191 show monitor twamp-light counters [...]

interfaces	*table(Interface name) = TwampLightCountersPerInterface* see 2.1191.1	Twamp Light counters, keyed by Interface.

2.1191.1 TwampLightCountersPerInterface

dropIncorrectTimestamps	*integer*	Incorrect timestamps packet drop counters.
dropInternalError	*integer*	Internal error packet drop counters.
dropInvalid	*integer*	Invalid packet drop counters.
dropTooSmall	*integer*	Too small packet drop counters.
dropTotal	*integer*	Twamp Light drop counters.
dropUnknownIP	*integer*	Unknown IP packet drop counters.
dropWrongDstPort	*integer*	Wrong dst port packet drop counters.
dropWrongEthType	*integer*	Wrong EtherType packet drop counters.

reflectors	*table(IPv4 or IPv6 address) = TwampLightReflector-CountersPerIp* see 2.1191.1.2	Twamp Light reflector counters, keyed by IP Address.
senders	*table(IPv4 or IPv6 address) = TwampLighSender-CountersPerIp* see 2.1191.1.1	Twamp Light sender counters, keyed by IP Address.

2.1191.1.1 TwampLighSenderCountersPerIp

rx	*integer*	Packets transferred from sender.
tx	*integer*	Packets received on sender.

2.1191.1.2 TwampLightReflectorCountersPerIp

rx	*integer*	Packets received on reflector.
tx	*integer*	Packets transferred from reflector.

2.1192 show monitor twamp-light detail [...]

addressesDetailed	*table(IPv4 or IPv6 address) = ResultDetailed* see 2.1192.1	TWAMP light detailed results, keyed by address.

2.1192.1 ResultDetailed

intfDescription	*string*	Interface description.
intfId	*interface name*	Name of the interface.
oneWayAvgDelay	*integer*	One way avg delay in microseconds.
oneWayDelayVariation	*integer*	One way min variation in microseconds.
oneWayMaxDelay	*integer*	One way max delay in microseconds.
oneWayMinDelay	*integer*	One way min delay in microseconds.
pktRx	*integer*	Packets received.
pktTx	*integer*	Packets sent.
samplingRate	*floating point number*	Effective sampling rate.
senderProfile	*string*	Sender profile name.
status **	*string*	Status description. **Since: 4.34.1
twoWayAvgDelay	*integer*	Two way avg delay in microseconds.
twoWayDelayVariation	*integer*	Two way min variation in microseconds.
twoWayMaxDelay	*integer*	Two way max delay in microseconds.
twoWayMinDelay	*integer*	Two way min delay in microseconds.

2.1193 show mpls bgp labeled-unicast bindings [...]

see 2.768

2.1194 show mpls bgp link-state bindings [...]

see 2.768

2.1195 show mpls config route [...]

revision 3

[multiLabelRoutes] **	*table(string) = MplsRoute* see 2.1195.1	Dictionary of multi-label MPLS routes configured, keyed by their top labels, comma-separated, ordered top-most to bottom-most. **Since: 4.22.0
routes	*table(numeric string) = MplsRoute* see 2.1195.1	Dictionary of MPLS routes configured, keyed by their top label.

2.1195.1 MplsRoute

adjacencies	*table(numeric string) = MplsAdjacency* see 2.1195.1.1	Dictionary of adjacencies keyed by metric.
topLabel	*integer*	Incoming MPLS label, set to 1048576 (N/A) if topLabels attribute is present.
[topLabels] **	*string*	Incoming MPLS labels for multi-label routes, comma-separated, ordered top-most to bottom-most. **Since: 4.22.0
[viaSetType] **	*enum: multicast | unicast*	Via set type. **Since: 4.31.1

2.1195.1.1 MplsAdjacency

[algorithm] **	*string*	The algorithm for the path computation. **Since: 4.26.2
[backupIpLookupVias] **	*list of IpLookupVia* see 2.1195.1.1.6	List of backup IP lookup vias. **Since: 4.26.2
[backupMplsVias] **	*list of MplsVia* see 2.1195.1.1.7	List of backup MPLS vias. **Since: 4.22.1
[cbfVias] **	*list of MplsVia* see 2.1195.1.1.7	List of CBF vias. **Since: 4.31.1
[evpnEthernetSegmentFilterVias]	*list of EvpnEthernetSegmentFilterVia* see 2.1195.1.1.1	List of EVPN Ethernet Segment Filter vias.
[evpnEtreeLeafLabelVias] **	*list of EvpnEtreeLeafLabelVia* see 2.1195.1.1.2	List of EVPN E-Tree Leaf Label vias. **Since: 4.34.2
[evpnVlanAwareFloodVias]	*list of EvpnVlanAwareFloodVia* see 2.1195.1.1.3	List of EVPN VLAN Aware Flood vias.
[evpnVlanAwareVias]	*list of EvpnVlanAwareVia* see 2.1195.1.1.4	List of EVPN VLAN Aware vias.
[evpnVlanFloodVias]	*list of EvpnVlanFloodVia* see 2.1195.1.1.5	List of EVPN VLAN Flood vias.
[fecForRoute]	*string*	The FEC for the route.
[fecId] **	*integer*	FEC ID. **Since: 4.24.0

[gribi] **	*RouteGribi* see 2.1195.1.1.10	gRIBI LFIB route info. **Since: 4.23.0
[ipLookupVias]	*list of IpLookupVia* see 2.1195.1.1.6	List of IP lookup vias.
[lspName] **	*string*	Lsp Name of the route. **Since: 4.32.1
[mplsVias]	*list of MplsVia* see 2.1195.1.1.7	List of MPLS vias.
[multicastIpLookupVias] **	*list of MulticastIpLookupVia* see 2.1195.1.1.8	List of Multicast IP lookup vias. **Since: 4.26.2
[pseudowireVias] **	*list of PwVia* see 2.1195.1.1.9	List of PW vias. **Since: 4.22.1
[source]	*enum: ldp | bgpLuToIsisSr | ospfSrV4Adj | mldp | isisSrProxySegmentFallbackPop | bgpLuToLdp | isisSrV6Adj | ldpToBgpLu | ospfSrProxySegmentFallbackPop | bgpL3Vpn | isisSrV4Prefix | isisSrToLdp | staticMpls | bgpLu | ldpToOspfSr | ospfSrToLdp | ldpToIsisSr | isisSrV6Area | bgpL2Evpn | staticMcast | rsvp | isisSrV4Area | isisSrV6Prefix | pseudowire | srp2mp | debug | ospfSrV4Prefix | srtepolicy | gribi | bgpLs | isisSrToBgpLu | isisSrV4Adj*	LFIB source.
[srTePolicy] **	*RouteSrTePolicy* see 2.807.1.1.1.2	SR-TE policy. **Since: 4.20.5
viaType	*enum: viaTypeEvpnVlanFlood | viaTypeMplsStaticPseudowire | viaTypeIpLookup | viaTypeEvpnEthernetSegment | viaTypeMax | viaTypeMplsBgpPseudowire | viaTypeVlan | viaTypeEvpnVlanAware | viaTypeMplsUnknown | viaTypeMplsIp | viaTypeExternalFec | viaTypeIpLookupBackup | viaTypeMulticastIpLookup | viaTypeNexthopGroup | viaTypeMplsVpwsPseudowire | viaTypeEvpnEtreeLeafLabel | viaTypeEvpnVlanAwareFlood | viaTypeMplsLdpPseudowire*	Obsolete because an adjacency can contain mixed via types.

[vlanVias]	*list of VlanVia* see 2.1195.1.1.11	List of VLAN vias.

2.1195.1.1.1 EvpnEthernetSegmentFilterVia

intf	*interface name*	Interface mapping to ESI label.

2.1195.1.1.2 EvpnEtreeLeafLabelVia

2.1195.1.1.3 EvpnVlanAwareFloodVia

controlWordEnabled	*boolean*	Control word is enabled.
dot1qTagToVlan	*Dot1qTagToVlan* see 2.1195.1.1.3.1	Dot1Q to VLAN map.

2.1195.1.1.3.1 Dot1qTagToVlan

dot1qTagToVlanId	*table(numeric string) = integer*	Mapping of Dot1Q tags to VLAN IDs.
dot1qTagToVlanKey	*Dot1qTagToVlanKey* see 2.1195.1.1.3.2	Dot1Q to VLAN map key.

2.1195.1.1.3.2 Dot1qTagToVlanKey

index	*integer*	Index of the Dot1Q to VLAN key.

source	*enum:* *lfibSourceBgpLuToLdp* | *lfibSourceBgpLu* | *lfibSourceUnknown* | *lfibSourceForwarding-ConvergenceTimeTest* | *lfibSourceOspfSrV4Prefix* | *lfibSourceIsisSrToLdp* | *lfibSourceStaticL3Vpn* | *lfibSourceRsvp* | *lfibSourceLdp* | *lfibSourceStaticDecapMvpn* | *lfibSourceBgpL2Evpn* | *lfibSourceRsvpAlt* | *lfibSourceIsisSrProxySeg-FallbackPop* | *lfibSourceVssCbf* | *lfibSourceBgpLs* | *lfibSourceOspfSrProxySeg-FallbackPop* | *lfibSourceOspfSrV4Adj* | *lfibSourceLdpToOspfSr* | *lfibSourceSrTePolicy* | *lfibSourceIsisSrV6Adj* | *lfibSourceOspfSrToLdp* | *lfibSourceBgpL3Vpn* | *lfibSourceLdpToBgpLu* | *lfibSourceLdpToIsisSr* | *lfibSourceGribi* | *lfibSourcePseudowire* | *lfibSourceSrP2mp* | *lfibSourceMldp* | *lfibSourceMax* | *lfibSourceIsisSrV4Prefix* | *lfibSourceIsisSrToBgpLu* | *lfibSourceStaticMcast* | *lfibSourceDebug* | *lfibSourceIsisSrV6Prefix* | *lfibSourceBgpLuToIsisSr* | *lfibSourceStaticMpls* | *lfibSourceIsisSrV4Adj*	Lfib source.

2.1195.1.1.4 EvpnVlanAwareVia

controlWordEnabled	*boolean*	Control word is enabled.
dot1qTagToVlan	*Dot1qTagToVlan* see 2.1195.1.1.3.1	Dot1Q to VLAN map.

2.1195.1.1.5 EvpnVlanFloodVia

controlWordEnabled	*boolean*	Control word is enabled.
vlanId	*integer*	VLAN ID.

2.1195.1.1.6 IpLookupVia

addressFamily	*enum: autoDecide | ipv4 | ipv6*	Address family. 'autoDecide' indicates that the lookup decision will be handled dynamically by the platform based on the header following the label.
vrfName	*string*	Name of VRF.

2.1195.1.1.7 MplsVia

[backupVias] **	*list of TunnelViaInfo* see 2.193.1.4.1.2	List of backup tunnel vias. **Since: 4.22.0
[bgpPeer] **	*IP address*	Bgp peer IP address. **Since: 4.28.2
[color] **	*integer*	Color of RSVP-LER tunnel. **Since: 4.31.1
[dscpMode] **	*enum: undefinedTtlMode | pipe | uniform | platformDefault*	DSCP mode. **Since: 4.25.1
[index] **	*integer*	Via index unique to a via and label action. **Since: 4.33.1
intf	*interface name*	Egress L3 interface of next hop.
labelAction	*enum: forward | unknown | push | pop | swap*	Label action.
[multicastIndex] **	*integer*	Via index for associating primary and backup multicast vias. **Since: 4.31.2
nexthop	*IP address*	Next hop IP address.
[nexthopGroup] **	*string*	Nexthop Group for Via. **Since: 4.26.0
outLabel	*integer*	Legacy attribute, use outLabels.
[outLabels] **	*list of integer*	Out labels for the packet. **Since: 4.33.1
payloadType	*enum: ipv4 | autoDecide | undefinedPayload | mpls | ipv6*	Type of payload being carried.
[skipEgressAcl]	*boolean*	Bypass egress ACL for the inner IP packets after MPLS pop.
[skipPayloadSet] **	*boolean*	Skip payload setup, let hardware auto detect. **Since: 4.35.2
[srTePolicyId] **	*SrTePolicyId* see 2.193.1.2.6.2	SR-TE policy id. **Since: 4.26.0
[status] **	*enum: down | up*	Resolution status of entry. **Since: 4.22.1
ttlMode	*enum: undefinedTtlMode | pipe | uniform | platformDefault*	TTL mode.
[tunnelDescriptor] **	*TunnelInfo* see 2.193.1.4.1	Tunnel information. **Since: 4.21.0
[ucmpGenerationMode] **	*linkBandwidth*	UCMP mode. **Since: 4.31.2

[vias] **	*list of TunnelViaInfo* see 2.193.1.4.1.2	List of nested tunnel vias. **Since: 4.21.0
[vrf] **	*string*	VRF used for next hop resolution. **Since: 4.34.0
[weight] **	*integer*	Weight for the via. **Since: 4.26.0

2.1195.1.1.8 MulticastIpLookupVia

addressFamily	*enum: autoDecide | ipv4 | ipv6*	Address family. 'autoDecide' indicates that the lookup decision will be handled dynamically by the platform based on the header following the label.
ingressIntf	*string*	Name of the ingress interface.

2.1195.1.1.9 PwVia

connector	*string*	(deprecated; use connectors).
connectors **	*table(string) = FlexibleEncapsulations* see 2.599.1	Local connectors for PW. **Since: 4.26.0
controlWordEnabled	*boolean*	Control word is enabled.
flowLabelEnabled **	*boolean*	Flow label is enabled. **Since: 4.23.2
patch	*string*	Patch associated with PW.
pwType	*enum: pwTypeWildcard | pwType5 | pwTypeNone | pwType4*	Pseudowire type.
viaType **	*enum: viaTypeEvpnVlanFlood | viaTypeMplsStatic-Pseudowire | viaTypeIpLookup | viaType-EvpnEthernetSegment | viaTypeMax | viaTypeMpls-BgpPseudowire | viaTypeVlan | viaTypeEvpnVlanAware | viaTypeMplsUnknown | viaTypeMplsIp | viaTypeExternalFec | viaTypeIpLookupBackup | viaTypeMulticastIpLookup | viaTypeNexthopGroup | via-TypeMplsVpwsPseudowire | viaTypeEvpnEtreeLeafLabel | viaTypeEvpnVlanAware-Flood | viaTypeMplsLdpPseudowire*	Via type indicating pseudowire signaling. **Since: 4.32.0
[vplsInstance] **	*string*	VPLS instance name. **Since: 4.27.0

2.1195.1.1.10 RouteGribi

nhgId	*integer*	gRIBI Nexthop Group ID.

2.1195.1.1.11 VlanVia

controlWordEnabled	*boolean*	Control word is enabled.
vlanId	*integer*	VLAN ID.

2.1196 show mpls hardware ale adj [...]

routes	*table(string) = MplsFecRequestTableEntry* see 2.1196.1	MPLS FEC ID keyed by labels.

2.1196.1 MplsFecRequestTableEntry

installedFecId	*integer*	Installed FEC ID for MPLS route.
programStatus	*string*	Programming status of the requested FEC ID.
requestedAlternateFecIds **	*list of integer*	Requested FEC IDs with alternate configurations for MPLS routes. **Since: 4.28.1
requestedFecId	*integer*	Requested FEC ID for MPLS route.

2.1197 show mpls hardware ale routes acknowledgement [...]

routes	*table(string) = MplsRouteAckTableEntry* see 2.1197.1	MPLS route acknowledgements by labels.

2.1197.1 MplsRouteAckTableEntry

[acknowledgedId]	*integer*	Acknowledged MPLS route version ID.
[fecProgrammingStatus]	*enum: allProgrammed | partiallyProgrammed | drop*	Programming status of the installed FEC ID.
[installedFecId]	*integer*	Installed FEC ID for MPLS route.
[installedFecVersion]	*integer*	Installed FEC version ID.
[requestedId]	*integer*	MPLS route version ID to be acknowledged.

2.1198 show mpls interface [...]

Could also be an instance of:
MplsInterfaceIngressCounters 2.1198.1

intfs	*table(Interface name) = MplsInterfaceInfo* see 2.1198.1	A mapping between an Interface and MPLS interface info.

2.1198.1 MplsInterfaceInfo

ldpConfigured	*boolean*	Configuration of LDP on interface.
mplsConfigured	*boolean*	Configuration of MPLS on interface.
rsvpConfigured	*boolean*	Configuration of RSVP on interface.
status	*enum: down | up | adminIsolated | uninitDown | adminDown | notApplicable | autoIsolated*	Operational status of the interface.
interfaces	*table(Interface name)* = *MplsInterfaceIngress-Counters* see 2.1198.2	MPLS interface ingress counters.
intfs	*table(Interface name)* = *MplsInterfaceInfo* see 2.1198.1	A mapping between an Interface and MPLS interface info.

2.1198.2 MplsInterfaceIngressCounters

mplsInOctets	*integer*	Number of input MPLS octets.
mplsInPkts	*integer*	Number of input MPLS packets.

2.1199 show mpls interface counters [...]

see 2.1198.1

2.1200 show mpls label ranges

conflictingRanges **	*list of MplsLabelRange* see 2.1200.1	Set of operationally inactive label ranges due to conflict with some other range. **Since: 4.25.1
ranges	*list of MplsLabelRange* see 2.1200.1	Set of operationally active label ranges.

2.1200.1 MplsLabelRange

blockSize	*integer*	The number of labels in the range.
blockStart	*integer*	The first MPLS label in the range.
[protocol]	*string*	The protocol which uses the range, or absent if the range is unused.
rangeType	*enum: static | dynamic | unassigned*	How the range was added.

2.1201 show mpls ldp [...]

vrfs **	*table(string) = MplsLdpStatus* see 2.1201.1	MPLS LDP information for all vrfs keyed by vrf name. **Since: 4.17.1

2.1201.1 MplsLdpStatus

[adjCount]	*integer*	Number of adjacencies.
enabled	*boolean*	LDP enabled/disabled.
[entropyLabel] **	*boolean*	Entropy label signaling. **Since: 4.25.0
[fecCount]	*integer*	Number of unfiltered FECs.
[fecFilterDenyAll] **	*boolean*	All unicast FECs denied by filter. **Since: 4.34.2
[fecFilterPrefixListName]	*string*	FEC filter prefix list.
[fecFilteredCount] **	*integer*	Number of filtered FECs. **Since: 4.18.0
[grMode] **	*enum: grModeSpeaker | grModeHelper | grModeDisabled*	Graceful restart mode. **Since: 4.22.1
[grPseudowireMode] **	*enum: grModeSpeaker | grModeHelper | grModeDisabled*	Graceful restart mode for Pseudowire. **Since: 4.34.0
[labelLocalTerminationMode] **	*enum: implicitNull | explicitNull*	Label local termination mode. **Since: 4.23.0
[linkCount]	*integer*	Number of links.
[localGrState] **	*enum: grStateActive | grStateUnknown | grStateInactive*	Graceful restart speaker operational state. **Since: 4.22.1
[localLdpId]	*MplsLdpId* see 2.1201.1.2	Local LDP ID.
[localLdpIdIntf]	*interface name*	Interface used for local LDP ID.
[mldpBudFecCount] **	*integer*	Number of bud MLDP FECs. **Since: 4.26.2
[mldpFecCount] **	*integer*	Number of MLDP FECs. **Since: 4.26.2
[mldpLeafFecCount] **	*integer*	Number of leaf MLDP FECs. **Since: 4.26.2
[mldpRootFecCount] **	*integer*	Number of root MLDP FECs. **Since: 4.26.2
[mldpTransitFecCount] **	*integer*	Number of transit MLDP FECs. **Since: 4.26.2
[mldpUnknownFecCount] **	*integer*	Number of unknown role MLDP FECs. **Since: 4.26.2
operational	*boolean*	LDP operational state.
[parameters]	*MplsLdpDetail* see 2.1201.1.1	Protocol parameters.
[peerCount]	*integer*	Number of peers.
[reason]	*string*	Reason for LDP not to be operational.
[sessionCount]	*integer*	Number of sessions.
[transportIp]	*IP address*	Transport IP.

[transportIpIntf]	*interface name*	Interface used for Transport IP.

2.1201.1.1 MplsLdpDetail

advertisedIntfIps	*list of IpGenericAddr* see 2.365.1.1.1.1	Interface addresses advertised to peers.
defaultLdpIntfEnabled **	*boolean*	Default LDP interface state is enabled. **Since: 4.22.0
grMaxNeighborLivenessTime **	*integer*	Graceful restart maximum neighbor liveness timeout in seconds. **Since: 4.22.1
grMaxRecoveryTime **	*integer*	Graceful restart max recovery timeout in seconds. **Since: 4.22.1
grReconnectTime **	*integer*	Graceful restart reconnect timeout in seconds. **Since: 4.22.1
grStateHoldTime **	*integer*	Graceful restart state holding timeout in seconds. **Since: 4.22.1
helloHoldTime	*integer*	Discovery hello hold time in seconds, 65535 is infinite as per RFC 5036.
helloInterval	*integer*	Discovery hello interval in seconds.
initialBackoff	*floating point number*	LDP initial backoff in seconds.
keepAlive	*integer*	Session keepalive time in seconds.
maximumBackoff	*floating point number*	LDP maximum backoff in seconds.
protocolVersion	*integer*	Protcol version.
targetedHelloHoldTime	*integer*	Discovery targeted-hello hold time in seconds, 65535 is infinite as per RFC 5036.
targetedHelloInterval	*integer*	Discovery targeted-hello interval in seconds.

2.1201.1.2 MplsLdpId

Could also be an instance of:
MplsLdpAdjacency 2.1201.1.3

ldpLabelSpace	*integer*	Local label space.
ldpRouterId	*IPv4 address*	LDP Router ID.

2.1201.1.3 MplsLdpAdjacency

[configurationSource]	*list of string*	Configuration source of targeted adjacencies.
[helloDetail]	*MplsLdpAdjacencyDetail* see 2.1201.1.3.1	Detailed hello packet information.
ldpLabelSpace	*integer*	Local label space.
ldpRouterId	*IPv4 address*	LDP Router ID.
[passwordInfo] **	*PasswordInformation* see 2.1201.1.3.2	LDP MD5 password information. **Since: 4.27.2

2.1201.1.3.1 MplsLdpAdjacencyDetail

adjExpireTime **	*floating point number*	UTC time at which discovery entry will expire. **Since: 4.18.1
adjSrcIp	*IP address*	Source IP of adjacency's hello packets.
adjTransportIp	*IP address*	Transport IP of adjacency's hello packets.
holdTime	*integer*	Operational hold time in seconds.
localHoldTime	*integer*	Local proposed hold time in seconds.
peerHoldTime	*integer*	Peer proposed hold time in seconds.

2.1201.1.3.2 PasswordInformation

passwordIndex **	*integer*	MD5 Password index. **Since: 4.27.2
passwordSet	*boolean*	MD5 Password enabled.

2.1202 show mpls ldp access-list [...]

see 2.62

2.1203 show mpls ldp bindings [...]

see 2.768.1.2.1

2.1204 show mpls ldp bindings mldp [...]

see 2.768.1.2.1

2.1205 show mpls ldp discovery [...]

vrfs	*table(string) = MplsLdpDiscovery* see 2.1205.1	Discovery information in all vrfs keyed by vrf name.

2.1205.1 MplsLdpDiscovery

discoveryInterfaces	*table(Interface name) = MplsLdpDiscoverySource* see 2.1205.1.1	Link adjacencies discovered on each interface.
discoveryTargets	*table(string) = MplsLdpDiscoverySource* see 2.1205.1.1	Targeted adjacencies discovered from each target.
localLdpId	*MplsLdpId* see 2.1201.1.2	Local LDP ID.

[passwordInfo]	*PasswordInformation* see 2.1201.1.3.2	LDP MD5 password information.

2.1205.1.1 MplsLdpDiscoverySource

adjacencies	*list of MplsLdpAdjacency* see 2.1201.1.3	List of adjacencies.
[helloInterval]	*integer*	Hello interval in seconds.
[srcIp]	*IP address*	Hello source IP address.

2.1206 show mpls ldp neighbor [...]

vrfs	*table(string) = MplsLdpNeighborList* see 2.1206.1	Neighbor sessions in requested vrfs keyed by vrf name.

2.1206.1 MplsLdpNeighborList

neighbors	*list of MplsLdpNeighbor* see 2.1206.1.1	Neighbor sessions in a specific vrf.

2.1206.1.1 MplsLdpNeighbor

boundAddresses	*list of IpGenericAddr* see 2.365.1.1.1.1	Addresses bound to peer.
boundAddressesDup **	*list of IpGenericAddr* see 2.365.1.1.1.1	Addresses bound to peer (duplicate). **Since: 4.24.2
capabilities **	*list of string*	Capabilities advertised by the peer. **Since: 4.20.5
discoveryInterfaces **	*list of Interface name*	LDP Discovery interface sources. **Since: 4.17.1
discoveryTargets **	*list of string*	LDP Discovery target sources. **Since: 4.17.1
endOfLib **	*enum: notSupported | supported | received | sentAndReceived | sent*	End-of-LIB operational state. **Since: 4.24.1
endOfLibTypesReceived **	*list of string*	FEC element types received for End-of-LIB. **Since: 4.34.1
endOfLibTypesSent **	*list of string*	FEC element types sent for End-of-LIB. **Since: 4.34.1
grState **	*enum: grStateActive | grStateUnknown | notSupported | grStateInactive*	Graceful restart operational state. **Since: 4.22.1
localIdent	*MplsLdpId* see 2.1201.1.2	Local LDP ID.
localKeepAliveHoldTime **	*integer*	Local proposed keepalive time in seconds. **Since: 4.21.3
localKeepAliveInterval **	*integer*	Local proposed keepalive transmit interval in seconds. **Since: 4.21.3
msgRx	*integer*	Messages received.
msgTx	*integer*	Messages sent.
peerGrReconnectTime **	*integer*	Peer graceful restart reconnect timeout in seconds. **Since: 4.22.1
peerGrRecoveryTime **	*integer*	Peer graceful restart recovery timeout in seconds. **Since: 4.22.1
peerIdent	*MplsLdpId* see 2.1201.1.2	Peer LDP ID.

`peerKeepAliveHoldTime` **	*integer*	Peer proposed keepalive time in seconds. **Since: 4.21.3
`peerKeepAliveInterval` **	*integer*	Peer proposed keepalive transmit interval in seconds. **Since: 4.21.3
`[rxMsgCounters]` **	*LdpMessageCount* see 2.1206.1.1.1	Number of received messages, categorized by type. **Since: 4.18.1
`[rxNotifCounters]` **	*LdpNotificationCount* see 2.1206.1.1.2	Number of received notifications, categorized by their status code. **Since: 4.18.1
`sessionExpireTime` **	*floating point number*	Session expiry in UTC, if no further session messages received. **Since: 4.18.1
`sessionKeepAliveHoldTime` **	*integer*	Negotiated session keepalive time in seconds. **Since: 4.21.3
`sessionKeepAliveInterval` **	*integer*	Negotiated session keepalive transmit interval in seconds. **Since: 4.21.3
`[sessionStateLog]` **	*list of LdpSessionStateLogEntryModel* see 2.1206.1.1.3	The last few session states and their information. **Since: 4.18.0
`sessionUpTimestamp`	*floating point number*	UTC timestamp of when the session went up.
`state`	*enum: stateOperational* | *stateNonExist* | *stateOpenRecv* | *stateExpired* | *stateOpenSent* | *stateInitialized* | *stateUnknown*	Ldp session state.

[stateCode] **	*enum: malformedTlv* | *illegalCBit* | *unknownMessageTypeIgnore* | *noRoute* | *sessionInitFailed* | *wrongCBit* | *loopDetected* | *authKeyChange* | *unknownTlv* | *rejectParamLabelRange* | *neighborCleared* | *rejectParamAdvMode* | *shutdown* | *noLabelResources* | *pwStatus* | *unknownFec* | *badTlvLength* | *tcpConnectionClosed* | *peerAddrChange* | *unsupportedAddressFamily* | *labelRequestAborted* | *badVersion* | *noAdjacency* | *sessionRejectBadKeepAliveTime* | *rejectNoHello* | *targetAdjRemoved* | *linkAdjRemoved* | *keepAliveExpired* | *unknownMessageType* | *localTransportAddrChange* | *success* | *internalError* | *missingMessageParams* | *rejectMaxPduLength* | *idChange* | *sessionRoleChanged* | *badMessageLength* | *labelResourcesAvailable* | *eolConfigChange* | *badLdpId* | *endOfLib* | *badPduLength* | *establishingTcpConnection* | *grConfigChange* | *holdTimerExpired* | *mLdpChange*	In states non-exist or expired, the code used for the last state transition. **Since: 4.18.0
[stateCodeDescription] **	*string*	In states non-exist or expired, the reason describing the last state transition. **Since: 4.18.0
stream	*enum: onDemand* | *unknownAdvDspl* | *unSolicited*	Ldp advertisement discipline.
[tcpLocalIp]	*IpGenericAddrAndPort* see 2.365.1.1.1.2	Local IP address.
[tcpPeerIp]	*IpGenericAddrAndPort* see 2.365.1.1.1.2	Peer IP address.
[txMsgCounters] **	*LdpMessageCount* see 2.1206.1.1.1	Number of transmitted messages, categorized by type. **Since: 4.18.1

[txNotifCounters] **	*LdpNotificationCount* see 2.1206.1.1.2	Number of received notifications, categorized by their status code. **Since: 4.18.1

2.1206.1.1.1 LdpMessageCount

ldpAddress	*integer*	Number of LDP Address messages.
ldpAddressWithdraw	*integer*	Number of LDP AddressWithdraw messages.
ldpInit	*integer*	Number of LDP Init messages.
ldpKeepAlive	*integer*	Number of LDP KeepAlive messages.
ldpLabelAbortReq	*integer*	Number of LDP LabelAbortReq messages.
ldpLabelMapping	*integer*	Number of LDP LabelMapping messages.
ldpLabelRelease	*integer*	Number of LDP LabelRelease messages.
ldpLabelRequest	*integer*	Number of LDP LabelRequest messages.
ldpLabelWithdraw	*integer*	Number of LDP LabelWithdraw messages.
ldpNotification	*integer*	Number of LDP Notification messages.

2.1206.1.1.2 LdpNotificationCount

authKeyChange **	*integer*	Number of notification messages with status code 'Authentication Key Change'. **Since: 4.27.1
badLdpId	*integer*	Number of notification messages with status code 'Bad LDP Identifier'.
badMessageLength	*integer*	Number of notification messages with status code 'Bad Message Length'.
badPduLength	*integer*	Number of notification messages with status code 'Bad PDU Length'.
badTlvLength	*integer*	Number of notification messages with status code 'Bad TLV Length'.
badVersion	*integer*	Number of notification messages with status code 'Bad Protocol Version'.
endOfLib **	*integer*	Number of notification messages with status code 'End-of-LIB'. **Since: 4.24.0
eolConfigChange **	*integer*	Number of notification messages with status code 'End-of-LIB Config Change'. **Since: 4.24.1
establishingTcpConnection **	*integer*	Number of notification messages with status code 'Establishing Tcp Connection'. **Since: 4.21.3
grConfigChange **	*integer*	Number of notification messages with status code 'Gr Destructive Config Change'. **Since: 4.22.1
holdTimerExpired	*integer*	Number of notification messages with status code 'Hold Timer Expired'.
idChange **	*integer*	Number of notification messages with status code 'ID Change'. **Since: 4.21.3

`illegalCBit` **	*integer*	Number of notification messages with status code 'Illegal C Bit'. **Since: 4.21.3
`internalError`	*integer*	Number of notification messages with status code 'Internal Error'.
`ipChange` **	*integer*	Number of notification messages with status code 'IP Connectivity Change'. **Since: 4.21.3
`ipConnectivityChange` **	*integer*	Number of notification messages with status code 'IP Connectivity Change'. **Since: 4.23.0
`keepAliveExpired`	*integer*	Number of notification messages with status code 'KeepAlive Timer Expired'.
`labelRequestAborted`	*integer*	Number of notification messages with status code 'Label Request Aborted'.
`labelResourcesAvailable`	*integer*	Number of notification messages with status code 'Label Resources / Available'.
`linkAdjRemoved` **	*integer*	Number of notification messages with status code 'Link Adjacency Removed'. **Since: 4.26.2
`localTransportAddrChange` **	*integer*	Number of notification messages with status code 'Local Transport Address Change'. **Since: 4.26.2
`loopDetected`	*integer*	Number of notification messages with status code 'Loop Detected'.
`mLdpChange` **	*integer*	Number of notification messages with status code 'mLdp Change'. **Since: 4.22.0
`malformedTlv`	*integer*	Number of notification messages with status code 'Malformed TLV Value'.
`missingMessageParams`	*integer*	Number of notification messages with status code 'Missing Message Parameters'.
`neighborCleared` **	*integer*	Number of notification messages with status code 'Neighbor Cleared'. **Since: 4.26.2
`noAdjacency` **	*integer*	Number of notification messages with status code 'No Adjacency'. **Since: 4.26.2
`noLabelResources`	*integer*	Number of notification messages with status code 'No Label Resources'.
`noRoute`	*integer*	Number of notification messages with status code 'No Route'.
`peerAddrChange` **	*integer*	Number of notification messages with status code 'Peer Address Change'. **Since: 4.26.2
`pwStatus` **	*integer*	Number of notification messages with status code 'PW Status'. **Since: 4.21.3
`rejectMaxPduLength`	*integer*	Number of notification messages with status code 'Session Rejected / Parameters Max PDU Length'.

rejectNoHello	*integer*	Number of notification messages with status code 'Session Rejected / No Hello'.
rejectParamAdvMode	*integer*	Number of notification messages with status code 'Session Rejected / Parameters Advertisement Mode'.
rejectParamLabelRange	*integer*	Number of notification messages with status code 'Session Rejected / Parameters Label Range'.
sessionInitFailed **	*integer*	Number of notification messages with status code 'Session Init Failed'. **Since: 4.21.3
sessionRejectBadKeepAlive-Time	*integer*	Number of notification messages with status code 'Session Rejcted / Bad KeepAlive Time'.
sessionRoleChanged **	*integer*	Number of notification messages with status code 'Session Role Changed'. **Since: 4.21.3
shutdown	*integer*	Number of notification messages with status code 'Shutdown'.
success	*integer*	Number of notification messages with status code 'Success'.
targetAdjRemoved **	*integer*	Number of notification messages with status code 'Target Adjacency Removed'. **Since: 4.26.2
tcpConnectionClosed **	*integer*	Number of notification messages with status code 'Tcp Connection Closed'. **Since: 4.21.3
unknownFec	*integer*	Number of notification messages with status code 'Unknown FEC'.
unknownMessageType	*integer*	Number of notification messages with status code 'Unknown Message Type'.
unknownMessageTypeIgnore **	*integer*	Number of notification messages with status code 'Ignored Unknown Message Type'. **Since: 4.21.3
unknownTlv	*integer*	Number of notification messages with status code 'Unknown TLV'.
unsupportedAddressFamily	*integer*	Number of notification messages with status code 'Unsupported Address Family'.
wrongCBit **	*integer*	Number of notification messages with status code 'Wrong C Bit'. **Since: 4.21.3

2.1206.1.1.3 LdpSessionStateLogEntryModel

code	*enum: malformedTlv* | *illegalCBit* | *unknown-MessageTypeIgnore* | *noRoute* | *sessionInitFailed* | *wrongCBit* | *loopDetected* | *authKeyChange* | *unknownTlv* | *rejectParamLabelRange* | *neighborCleared* | *rejectParamAdvMode* | *shutdown* | *noLabelResources* | *pwStatus* | *unknownFec* | *badTlvLength* | *tcpConnectionClosed* | *peerAddrChange* | *unsupportedAddressFamily* | *labelRequestAborted* | *badVersion* | *noAdjacency* | *sessionRejectBadKeep-AliveTime* | *rejectNoHello* | *targetAdjRemoved* | *linkAdjRemoved* | *keepAliveExpired* | *unknownMessageType* | *localTransportAddrChange* | *success* | *internalError* | *missingMessageParams* | *rejectMaxPduLength* | *idChange* | *sessionRoleChanged* | *badMessageLength* | *labelResourcesAvailable* | *eolConfigChange* | *badLdpId* | *endOfLib* | *badPduLength* | *establishingTcpConnection* | *grConfigChange* | *holdTimerExpired* | *mLdpChange*	In states non-exist or expired, the code used for the last state transition.
reason	*string*	In states non-exist or expired, the reason describing the last state transition.
sessionState	*enum: stateOperational* | *stateNonExist* | *stateOpenRecv* | *stateExpired* | *stateOpenSent* | *stateInitialized* | *stateUnknown*	Ldp session state.
timeStamp	*floating point number*	Time of state change in seconds.

2.1207 show mpls ldp tunnel [...]

revision 3

`entries`	*table(numeric string) = LdpTunnelTableEntry* see 2.1207.1	LDP tunnel table entries keyed by tunnel index.

2.1207.1 LdpTunnelTableEntry

`[backupVia]` **	*list of Via* see 2.193.1.1	Backup Nexthops. **Since: 4.36.0
`endpoint`	*IP address prefix*	Endpoint of the tunnel.
`vias`	*list of Via* see 2.193.1.1	List of nexthops.

2.1208 show mpls ldp tunnel mldp [...]

`entries`	*table(numeric string) = MldpTunnelTableEntry* see 2.1208.1	MLDP tunnel table entries keyed by tunnel index.

2.1208.1 MldpTunnelTableEntry

`mcastTreeId`	*string*	Multicast tree identifier.
`vias`	*list of Via* see 2.193.1.1	List of nexthops.

2.1209 show mpls lfib counters [...]

`counters`	*table(numeric string) = MplsLfibCounterLabelEntry* see 2.1209.1	A dictionary of ingress MPLS LFIB counters keyed by their top label.
`[multiLabelCounters]` **	*table(string) = MplsLfibCounterLabelEntry* see 2.1209.1	A dictionary of ingress multi-label MPLS LFIB counters keyed by their top labels (ordered top-most to bottom-most). **Since: 4.22.0

2.1209.1 MplsLfibCounterLabelEntry

[failedCounterAlloc] **	*boolean*	Counter resources for the label could not be allocated. **Since: 4.30.0
[source] **	*enum: ldp | bgpLuToIsisSr | ospfSrV4Adj | mldp | isisSrProxySegmentFallbackPop | bgpLuToLdp | isisSrV6Adj | ldpToBgpLu | ospfSrProxySegmentFallbackPop | bgpL3Vpn | isisSrV4Prefix | isisSrToLdp | staticMpls | bgpLu | ldpToOspfSr | ospfSrToLdp | ldpToIsisSr | isisSrV6Area | bgpL2Evpn | staticMcast | rsvp | isisSrV4Area | isisSrV6Prefix | pseudowire | srp2mp | debug | ospfSrV4Prefix | srtepolicy | gribi | bgpLs | isisSrToBgpLu | isisSrV4Adj*	LFIB source. **Since: 4.28.1
[sourceDetails] **	*string*	Details from the source for the label. **Since: 4.28.1
totalBytes	*integer*	Total number of received bytes on label.
totalPackets	*integer*	Total number of received packets on label.
unprogrammed	*boolean*	Route is unprogrammed in hardware.

2.1210 show mpls lfib counters no-resource

see 2.1209

2.1211 show mpls lfib counters summary

agreggateNoResourceBytes	*integer*	Total aggregated bytes for all MPLS LFIB label stacks which are unable to be individually counted due to lack of availble counter resources.
agreggateNoResourcePkts	*integer*	Total aggregated packets for all MPLS LFIB label stacks which are unable to be individually counted due to lack of availble counter resources.
[countableMplsLabels]	*integer*	Total unique MPLS label stacks being individually counted.
[noResourceMplsLabels]	*integer*	Total unique MPLS label stacks unable to be individuallycounted due to lack of availble counter resources.
totalMplsLabels	*integer*	Total unique MPLS label stacks in the LFIB.

2.1212 show mpls lfib input bgp labeled-unicast

revision 3

see 2.1195

2.1213 show mpls lfib route [...]

revision 3

see 2.1195

2.1214 show mpls lfib stitching preferences [...]

`destinationProtocol`	*table(string) = MplsDestinationProtocol-StitchingPreferences* see 2.1214.1	LFIB stitching preferences keyed by destination protocol.

2.1214.1 MplsDestinationProtocolStitchingPreferences

`sourceProtocol`	*table(string) = integer*	Destination protocol stitching preferences keyed by source protocol.

2.1215 show mpls parsing speculative

`entries`	*table(string) = boolean*	Status of MPLS speculative parsing, indexed by packet type.

2.1216 show mpls ping access-list [...]

see 2.62

2.1217 show mpls route [...]

revision 2

[allowDefaultRoute]	*boolean*	True if MPLS next-hop is allowed to resolve over default route.
mplsSupported	*boolean*	True if MPLS routing is supported.
[multiLabelRoutes] **	*table(string) = MplsHwRoute* see 2.1217.1	Dictionary of programmed multi-label routes, keyed by their incoming MPLS labels, comma-separated, ordered top-most to bottom-most. **Since: 4.22.0
routes	*table(numeric string) = MplsHwRoute* see 2.1217.1	Dictionary of programmed routes, keyed by their incoming MPLS label.

2.1217.1 MplsHwRoute

adjacencies	*table(numeric string) = MplsHwAdjacency* see 2.1217.1.1	Dictionary of adjacencies keyed by metric.
[adjacencySetUnprogrammed]	*boolean*	Adjacency set is programmed in hardware.
bestMetric	*integer*	Metric for the best available path.
label	*integer*	Incoming MPLS label, set to 1048576 (N/A) if labels attribute is present.
[labels] **	*string*	Incoming MPLS labels for multi-label routes, comma-separated, ordered top-most to bottom-most. **Since: 4.22.0
unprogrammed	*boolean*	Route is unprogrammed in hardware.
[viaSetType] **	*enum: multicast | unicast*	Via set type. **Since: 4.22.1

2.1217.1.1 MplsHwAdjacency

[backupIpLookupVias] **	*list of IpLookupVia* see 2.1195.1.1.6	List of backup IP lookup vias. **Since: 4.27.0
[backupMplsVias] **	*list of MplsHwVia* see 2.1217.1.1.1	List of backup MPLS vias. **Since: 4.22.1
[evpnEthernetSegmentFilterVias]	*list of EvpnEthernetSegmentFilterVia* see 2.1195.1.1.1	List of EVPN Ethernet Segment Filter vias.
[evpnEtreeLeafLabelVias] **	*list of EvpnEtreeLeafLabelVia* see 2.1195.1.1.2	List of EVPN E-Tree Leaf Label vias. **Since: 4.34.2
[evpnVlanAwareFloodVias]	*list of EvpnVlanAwareFloodVia* see 2.1195.1.1.3	List of EVPN VLAN Aware Flood vias.
[evpnVlanAwareVias]	*list of EvpnVlanAwareVia* see 2.1195.1.1.4	List of EVPN VLAN Aware vias.
[evpnVlanFloodVias]	*list of EvpnVlanFloodVia* see 2.1195.1.1.5	List of EVPN VLAN Flood vias.

[ipLookupVias]	*list of IpLookupVia* see 2.1195.1.1.6	List of IP lookup vias.
[mplsVias]	*list of MplsHwVia* see 2.1217.1.1.1	List of MPLS vias.
[multicastIpLookupVias] **	*list of MulticastIpLookupVia* see 2.1195.1.1.8	List of Multicast IP lookup vias. **Since: 4.26.2
viaType	*enum: viaTypeEvpnVlanFlood | viaTypeMplsStatic-Pseudowire | viaTypeIpLookup | viaType-EvpnEthernetSegment | viaTypeMax | viaTypeMpls-BgpPseudowire | viaTypeVlan | viaTypeEvpnVlanAware | viaTypeMplsUnknown | viaTypeMplsIp | viaTypeExternalFec | viaTypeIpLookupBackup | viaTypeMulticastIpLookup | viaTypeNexthopGroup | via-TypeMplsVpwsPseudowire | viaTypeEvpnEtreeLeafLabel | viaTypeEvpnVlanAware-Flood | viaTypeMplsLdpPseudowire*	Obsolete because an adjacency can contain mixed via types.
[vlanVias]	*list of VlanVia* see 2.1195.1.1.11	List of VLAN vias.

2.1217.1.1.1 MplsHwVia

[backupVias] **	*list of TunnelViaInfo* see 2.193.1.4.1.2	List of backup tunnel vias. **Since: 4.22.0
[dscpMode] **	*enum: undefinedTtlMode | pipe | uniform | platformDefault*	DSCP mode. **Since: 4.25.1
l2Intf	*interface name*	Egress L2 interface.
l3Intf	*interface name*	Egress L3 interface.
labelAction	*enum: forward | unknown | push | pop | swap*	Label action.
macAddr	*MAC address*	Destination MAC address.
[nexthopGroup] **	*string*	Nexthop Group for Via. **Since: 4.26.0
outLabel	*integer*	Legacy attribute, use outLabels.
[outLabel1] **	*integer*	Legacy attribute, use outLabels. **Since: 4.31.0
[outLabels] **	*list of integer*	Out labels for the packet. **Since: 4.33.2
payloadType	*enum: ethernet | ipv4 | undefinedPayload | autoDecide | mpls | ipv6*	Type of payload being carried.

recursiveNextHop	*IP address*	Recursive nexthop IP address.
resolvedNextHop	*IP address*	Resolved nexthop IP address.
[skipEgressAcl]	*boolean*	True if egress ACL is bypassed for the inner IP packets after MPLS pop.
ttlMode	*enum: undefinedTtlMode | pipe | uniform | platformDefault*	TTL mode.
[tunnelDescriptor] **	*TunnelInfo* see 2.193.1.4.1	Tunnel information. **Since: 4.21.0
[vias] **	*list of TunnelViaInfo* see 2.193.1.4.1.2	List of nested tunnel vias. **Since: 4.21.0
vlanId	*integer*	VLAN ID.
[weight] **	*integer*	Weight of the Via. **Since: 4.26.0

2.1218 show mpls route summary

numBackupAdjs	*integer*	Number of backup adjacencies (via groups).
numHwAdjs	*integer*	Number of adjacencies (via groups) used in hardware.
numLabels	*integer*	Number of labels.
numUnprogrammedLabels	*integer*	Number of unprogrammed labels.

2.1219 show mpls rsvp

adminState	*enum: enabled | disabled*	Is RSVP enabled by config.
authentication	*enum: disabled | MD5*	Cryptographic authentication.
bypassOptimizationInterval **	*integer*	Time interval in seconds between FRR bypass tunnel re-optimization attempts. **Since: 4.31.0
bypassTunnelCount	*integer*	Number of bypass tunnels.
egressCount	*integer*	Number of egress sessions.
fastReroute	*boolean*	Is fast re-route enabled.
fastRerouteMode	*enum: linkProtection | nodeProtection | none*	Fast re-route mode.
[grHelper] **	*GrHelper* see 2.1219.1	Graceful restart helper configuration. **Since: 4.29.0
[grSpeaker] **	*GrSpeaker* see 2.1219.2	Graceful restart speaker configuration. **Since: 4.29.0
helloEnabled	*boolean*	Are hello messages enabled.
[helloInterval]	*floating point number*	Time interval in seconds between RSVP hello messages. Set when helloEnabled is True.
[helloMultiplier]	*floating point number*	Number of missed hellos after which the neighbor is expired. Set when helloEnabled is True.
hierarchicalFecsEnabled	*boolean*	Are hierarchical FECs enabled.
[hitlessRestart] **	*HitlessRestart* see 2.1219.3	Hitless restart configuration. **Since: 4.30.1
ingressCount	*integer*	Number of ingress sessions.
interfaceCount	*integer*	Number of interfaces.
[labelLocalTerminationMode] **	*enum: implicitNull | explicitNull*	Label local termination mode. **Since: 4.24.1
lspCount	*LspCount* see 2.1219.4	LSP related counts.
mtuSignalingEnabled **	*boolean*	Is MTU signaling enabled. **Since: 4.23.2
neighborCount	*integer*	Number of neighbors.
operationalState	*enum: down | up*	Operational state of RSVP.
p2mpEnabled **	*boolean*	Is P2MP enabled. **Since: 4.32.2
[p2mpLspCount] **	*P2mpLspCount* see 2.1219.5	P2MP LSP related counts. **Since: 4.32.2
[p2mpSessionCount] **	*integer*	Number of P2MP sessions. **Since: 4.32.2
[p2mpSubLspCount] **	*P2mpSubLspCount* see 2.1219.6	P2MP sub-LSP related counts. **Since: 4.32.2
preemptionPeriod **	*floating point number*	Preemption timer value in seconds. **Since: 4.23.2
refreshInterval	*floating point number*	Time interval in seconds between RSVP neighbor state refresh messages.
refreshReduction	*boolean*	Is bundling of RSVP neighbor messages enabled.
[reversionMode]	*enum: local | global*	Operational FRR reversion mode.

[reversionModeConfig] **	*enum: local | global*	Configured FRR reversion mode. **Since: 4.22.1
sessionCount	*integer*	Number of sessions.
srlgMode **	*enum: srlgStrict | srlgNone | srlgLoose*	SRLG mode. **Since: 4.24.1
transitCount	*integer*	Number of transit sessions.

2.1219.1 GrHelper

[maximumAcceptedRecovery]	*floating point number*	Maximum accepted recovery value from neighbors in seconds.
[maximumAcceptedRestart]	*floating point number*	Maximum accepted restart value from neighbors in seconds.

2.1219.2 GrSpeaker

recovery	*floating point number*	Graceful Restart recovery value in seconds.
restart	*floating point number*	Graceful Restart restart value in seconds.

2.1219.3 HitlessRestart

recovery	*floating point number*	Hitless Restart recovery value in seconds.

2.1219.4 LspCount

egress	*integer*	Number of egress LSPs.
ingress	*integer*	Number of ingress LSPs.
operational	*integer*	Number of operational LSPs.
total	*integer*	Number of LSPs.
transit	*integer*	Number of transit LSPs.
usingBypassTunnels	*integer*	Number of LSP using bypass tunnels.

2.1219.5 P2mpLspCount

bud	*integer*	Number of bud P2MP LSPs.
egress	*integer*	Number of egress P2MP LSPs.
ingress	*integer*	Number of ingress P2MP LSPs.
operational	*integer*	Number of operational P2MP LSPs.
total	*integer*	Number of P2MP LSPs.
transit	*integer*	Number of transit P2MP LSPs.
usingBypassTunnels	*integer*	Number of LSP using bypass tunnels.

2.1219.6 P2mpSubLspCount

egress	*integer*	Number of egress sub-LSPs.
ingress	*integer*	Number of ingress sub-LSPs.
operational	*integer*	Number of operational sub-LSPs.

total	*integer*	Number of sub-LSPs.
transit	*integer*	Number of transit sub-LSPs.
usingBypassTunnels	*integer*	Number of LSP using bypass tunnels.

2.1220 show mpls rsvp ((ip access-list) | (ipv6 access-list)) [...]

see 2.62

2.1221 show mpls rsvp bandwidth [...]

interfaces	*table(Interface name) = RsvpBandwidthIntfModel* see 2.1221.1	Interface's Bandwidth information.

2.1221.1 RsvpBandwidthIntfModel

reservedBandwidth	*table(numeric string) = floating point number*	A map of priority to bandwidth reserved in bits per second.
totalBandwidth	*floating point number*	Total bandwidth available to RSVP in bits per second.

2.1222 show mpls rsvp bandwidth summary [...]

interfaces	*table(Interface name) = RsvpBandwidthIntf-SummaryModel* see 2.1222.1	A mapping of interface to bandwidth summary.

2.1222.1 RsvpBandwidthIntfSummaryModel

reservedBandwidth	*floating point number*	Bandwidth reserved in bits per second.
totalBandwidth	*floating point number*	Total bandwidth available to RSVP in bits per second.

2.1223 show mpls rsvp counters [...]

errorCounts **	*table(string) = RsvpErrorCounter* see 2.1223.1	Error counters. **Since: 4.27.2
interfaces	*table(Interface name) = RsvpInterfaceCounter* see 2.1223.2	Interface message counters.

2.1223.1 RsvpErrorCounter

rx	*integer*	Received error counts.
tx	*integer*	Sent error counts.

2.1223.2 RsvpInterfaceCounter

rx	*RsvpMessageCounter* see 2.1223.2.1	Received message counts.
tx	*RsvpMessageCounter* see 2.1223.2.1	Sent message counts.

2.1223.2.1 RsvpMessageCounter

counts	*table(string) = integer*	Message counts keyed by RsvpMessageType(Path, PathTear, PathErr, Resv, ResvTearSrefresh, Other, Errors).

2.1224 show mpls rsvp neighbor [...]

neighbors	*table(IPv4 or IPv6 address) = RsvpNeighbor* see 2.1224.1	Neighbor information.

2.1224.1 RsvpNeighbor

[authentication]	*enum: disabled | MD5*	Cryptographic authentication.
backupDownstreams **	*list of NeighborLspInfo* see 2.1224.1.2	Backup downstream session LSP information. **Since: 4.31.2
backupUpstreams **	*list of NeighborLspInfo* see 2.1224.1.2	Backup upstream session LSP information. **Since: 4.31.2
[bypassInfoNode] **	*table(IPv4 or IPv6 address) = NeighborBypassInfo* see 2.1224.1.1	A dictionary of bypass tunnel state for node protection keyed by tunnel destination IP address. **Since: 4.22.0
[bypassLabel]	*integer*	Bypass tunnel label.
[bypassNextHop]	*IP address*	Bypass tunnel next hop.
bypassTunnel	*enum: inUse | available | notAvailable | notRequested*	Bypass tunnel state.
[bypassTunnelName]	*string*	Bypass tunnel name.
downstreams	*list of NeighborLspInfo* see 2.1224.1.2	Downstream session LSP information.
[lastHelloReceived]	*floating point number*	UTC time when the last RSVP hello message was received.
[lastHelloSent]	*floating point number*	UTC time when the last RSVP hello message was sent.
[neighborCreationTime]	*floating point number*	UTC time when neighbor was created.
operGrState **	*enum: inactive | unsupported | recovery | unknown | restart*	Graceful restart state. **Since: 4.28.2
p2mpBackupDownstreams **	*list of NeighborP2mpLspInfo* see 2.1224.1.3	Backup downstream P2MP session LSP information. **Since: 4.32.2
p2mpBackupUpstreams **	*list of NeighborP2mpLspInfo* see 2.1224.1.3	Backup upstream P2MP session LSP information. **Since: 4.32.2
p2mpDownstreams **	*list of NeighborP2mpLspInfo* see 2.1224.1.3	Downstream P2MP session LSP information. **Since: 4.32.2
p2mpUpstreams **	*list of NeighborP2mpLspInfo* see 2.1224.1.3	Upstream P2MP session LSP information. **Since: 4.32.2
[recoveryTime] **	*floating point number*	Graceful restart recovery time advertised by the neighbor in seconds. **Since: 4.28.2
[restartTime] **	*floating point number*	Graceful restart restart time advertised by the neighbor in seconds. **Since: 4.28.2
upstreams	*list of NeighborLspInfo* see 2.1224.1.2	Upstream session LSP information.

2.1224.1.1 NeighborBypassInfo

[bypassLabel]	*integer*	Bypass tunnel label.
[bypassNextHop]	*IP address*	Bypass tunnel next hop.
bypassTunnel	*enum: inUse | available | notAvailable | notRequested*	Bypass tunnel state.
[bypassTunnelName]	*string*	Bypass tunnel name.

2.1224.1.2 NeighborLspInfo

lspId	*integer*	LSP ID.
sessionId	*integer*	Session ID.
[sessionName] **	*string*	Session name. **Since: 4.25.1

2.1224.1.3 NeighborP2mpLspInfo

extendedTunnelId	*IP address*	Extended tunnel ID.
lspId	*integer*	LSP ID.
[sessionName]	*string*	Session name.

2.1225 show mpls rsvp neighbor summary

neighborSummary	*table(IPv4 or IPv6 address) = RsvpNeighborStatistics* see 2.1225.1	Neighbor summary.

2.1225.1 RsvpNeighborStatistics

backupDownstreamLspCount **	*integer*	Number of backup downstream LSPs. **Since: 4.31.2
backupDownstreamSession-Count **	*integer*	Number of backup downstream sessions. **Since: 4.31.2
backupUpstreamLspCount **	*integer*	Number of backup upstream LSPs. **Since: 4.31.2
backupUpstreamSessionCount **	*integer*	Number of backup upstream sessions. **Since: 4.31.2
downstreamLspCount	*integer*	Number of downstream LSPs.
downstreamSessionCount	*integer*	Number of downstream sessions.
upstreamLspCount	*integer*	Number of upstream LSPs.
upstreamSessionCount	*integer*	Number of upstream sessions.

2.1226 show mpls rsvp session [...]

revision 2

p2mpSessions **	*table(string) = RsvpP2mpSession* see 2.1226.1	Table of P2MP session information keyed by session ID string. **Since: 4.32.2
sessions	*table(numeric string) = RsvpSession* see 2.1226.2	Table of P2P session information keyed by session number.

2.1226.1 RsvpP2mpSession

extendedTunnelId	*IP address*	Extended tunnel ID.
[history] **	*list of RsvpHistoryEntry* see 2.1226.1.1	Session history entries. **Since: 4.33.2
lsps	*table(numeric string) = RsvpP2mpLsp* see 2.1226.1.2	Table of LSP information keyed by LSP ID.
p2mpId	*integer*	P2MP ID.
[pmsiIntfId]	*interface name*	Egress PMSI interface.
sessionCreationTime	*floating point number*	UTC time when session was created.
[sessionName]	*string*	Session name.
state	*enum: down | up*	Session operational state.
tunnelId	*integer*	Tunnel ID.

2.1226.1.1 RsvpHistoryEntry

event	*string*	History event.
timestamp	*floating point number*	Timestamp of the event.

2.1226.1.2 RsvpP2mpLsp

lspCreationTime	*floating point number*	UTC time when LSP was created.
lspRole	*enum: unknown | bud | transit | ingress | egress*	Role for LSP.
state	*enum: down | up*	LSP operational state.
subGroups	*table(numeric string) = RsvpP2mpSubGroup* see 2.1226.1.2.1	Table of sub-group information keyed by group ID.

2.1226.1.2.1 RsvpP2mpSubGroup

downstreamNeighbors	*table(IPv4 or IPv6 address) = RsvpP2mpDsNeighbor* see 2.1226.1.2.1.1	Table of downstream neighbor information keyed by neighbor IP address.
mtuSignalingEnabled	*boolean*	MTU signaling is enabled for this sub-group.
[sessionName]	*string*	Sub-group session name.
subLsps	*table(IPv4 or IPv6 address) = RsvpP2mpSubLsp* see 2.1226.1.2.1.2	Table of sub-LSP information keyed by destination IP address.

upstreamNeighbors	*table(IPv4 or IPv6 address) = RsvpP2mpUsNeighbor* see 2.1226.1.2.1.5	Table of upstream neighbor information keyed by neighbor IP address.

2.1226.1.2.1.1 RsvpP2mpDsNeighbor

[backupLocalInterface]	*interface name*	Backup local interface.
[backupNeighborAddress]	*IP address*	Backup neighbor address.
[bandwidth]	*floating point number*	Requested bandwidth in bps.
[bandwidthState]	*enum: pending | preempted | unknown | failedPreemption | reserved | failedAdmission*	Current status of bandwidth reservation.
[bypassLabel]	*integer*	Bypass tunnel label.
[bypassLastHopLabel]	*integer*	Merge point label.
[bypassNextHop]	*IP address*	Bypass tunnel next hop.
bypassTunnel	*enum: inUse | available | notAvailable | notRequested*	Bypass tunnel state.
[bypassTunnelName]	*string*	Bypass tunnel name.
[downstreamLabel]	*integer*	Downstream MPLS label.
frrOperationalMode	*enum: linkProtection | nodeProtection | none*	Fast re-route mode operational.
frrRequestedMode	*enum: linkProtection | nodeProtection | none*	Fast re-route mode requested.
[holdPriority]	*integer*	Hold priority.
[localInterface]	*interface name*	Local interface.
[outMtu] **	*integer*	MTU sent in the outgoing path message. **Since: 4.33.0
[setupPriority]	*integer*	Setup priority.
[softPreemptionRequested]	*boolean*	Soft preemption has been requested.

2.1226.1.2.1.2 RsvpP2mpSubLsp

[downstreamNeighbor]	*IP address*	Downstream neighbor address.
dsRro	*list of RsvpRroHop* see 2.1226.1.2.1.4	Record route hops from downstream.
ero	*list of RsvpEroHop* see 2.1226.1.2.1.3	Explicit route hops.
[lastDsRefreshReceived]	*floating point number*	UTC time when the last downstream neighbor refresh was received.
[lastDsRefreshSent]	*floating point number*	UTC time when the last downstream neighbor refresh was sent.
[lastUsRefreshReceived]	*floating point number*	UTC time when the last upstream neighbor refresh was received.
[lastUsRefreshSent]	*floating point number*	UTC time when the last upstream neighbor refresh was sent.
pathState	*enum: down | up | sentOnly | receivedOnly*	Path state.
resvState	*enum: down | up | sentOnly | receivedOnly*	Reservation state.

role	*enum: ingress | transit | unknown | egress*	Role for sub-LSP.
state	*enum: down | up | pathOnly*	Sub-LSP operational state.
[upstreamNeighbor]	*IP address*	Upstream neighbor address.
usRro	*list of RsvpRroHop* see 2.1226.1.2.1.4	Record route hops from upstream.

2.1226.1.2.1.3 RsvpEroHop

[asNumber]	*integer*	ERO hop AS number.
loose	*boolean*	ERO hop is a loose hop.
[prefix]	*IP address prefix*	ERO hop prefix.

2.1226.1.2.1.4 RsvpRroHop

address	*IP address*	RRO hop address.
frrInUse	*boolean*	RRO hop actively uses fast re-route local protection.
frrMode	*enum: linkProtection | nodeProtection | none*	RRO hop's fast re-route mode.
[label]	*integer*	RRO hop label.
nodeId	*boolean*	RRO hop is a node ID.

2.1226.1.2.1.5 RsvpP2mpUsNeighbor

[backupLocalInterface]	*interface name*	Backup local interface.
[backupNeighborAddress]	*IP address*	Backup neighbor address.
[inMtu] **	*integer*	MTU received in the incoming path message. **Since: 4.33.0
[localInterface]	*interface name*	Local interface.
[localLabel]	*integer*	Local MPLS label.
[unprogrammed] **	*boolean*	LSP is unprogrammed in hardware. **Since: 4.34.2

2.1226.2 RsvpSession

destination	*IP address*	Destination address.
[extendedTunnelId]	*IP address*	Extended tunnel ID.
lsps	*table(numeric string) = Lsp* see 2.1226.2.1	Table of LSP information keyed by LSP ID.
[sessionCreationTime]	*floating point number*	UTC time when session was created.
[sessionHistory]	*RsvpHistory* see 2.1226.2.1.2	Session history events.
sessionRole	*enum: ingress | unknown | egress | transit*	Role for Session.
[state]	*enum: down | up*	Session operational state.
[tunnelId]	*integer*	Tunnel ID.

2.1226.2.1 Lsp

[backupDownstreamNeighbor-Address]	*IP address*	Downstream backup neighbor address.
[backupUpstreamNeighbor-Address]	*IP address*	Upstream backup neighbor address.
[bandwidth]	*floating point number*	Requested bandwidth in bps.
[bandwidthInterface] **	*interface name*	Bandwidth reservation interface. **Since: 4.29.1
[bandwidthState]	*enum: pending | preempted | unknown | failedPreemption | reserved | failedAdmission*	Current status of bandwidth reservation.
[bypassLabel]	*integer*	Bypass tunnel label.
[bypassLastHopLabel]	*integer*	Merge point label.
[bypassNextHop]	*IP address*	Bypass tunnel next hop.
bypassTunnel	*enum: available | notRequested | inUse | notAvailable | egress*	Bypass tunnel state.
[bypassTunnelName]	*string*	Bypass tunnel name.
[downstreamLabel]	*integer*	Downstream MPLS label.
[downstreamNeighbor]	*LspNeighborInfo* see 2.1226.2.1.1	Downstream neighbor information.
[dsRro] **	*list of RsvpRroHop* see 2.1226.1.2.1.4	Record route hops from downstream. **Since: 4.26.0
[ero] **	*list of RsvpEroHop* see 2.1226.1.2.1.3	Explicit route hops. **Since: 4.26.0
[frrOperationalMode]	*enum: linkProtection | nodeProtection | none*	Fast re-route mode operational.
[frrRequestedMode]	*enum: linkProtection | nodeProtection | none*	Fast re-route mode requested.
[holdPriority]	*integer*	Hold priority.
[inMtu]	*integer*	MTU received in the incoming path message.
[localLabel]	*integer*	Local MPLS label.
[lspCreationTime]	*floating point number*	UTC time when LSP was created.
[lspHistory]	*RsvpHistory* see 2.1226.2.1.2	SP history events.
[lspId]	*integer*	LSP ID.
[lspType]	*enum: secondary | primary | bypass*	LSP purpose.
[mtuSignalingEnabled]	*boolean*	MTU signaling is enabled for this LSP.
[outMtu]	*integer*	MTU sent in the outgoing path message.
pathState	*enum: down | up | sentOnly | receivedOnly*	Path state.
resvState	*enum: down | up | sentOnly | receivedOnly*	Reservation state.
[sessionName]	*string*	Head end session name.
[setupPriority]	*integer*	Setup priority.
[softPreemptionRequested]	*boolean*	Soft preemption has been requested.
[sourceAddress]	*IP address*	Source address.
state	*enum: down | up | pathOnly*	Operational state.

[unprogrammed] **	*boolean*	LSP is unprogrammed in hardware. **Since: 4.28.0
[upstreamNeighbor]	*LspNeighborInfo* see 2.1226.2.1.1	Upstream neighbor information.
[usRro] **	*list of RsvpRroHop* see 2.1226.1.2.1.4	Record route hops from upstream. **Since: 4.26.0

2.1226.2.1.1 LspNeighborInfo

address	*IP address*	Neighbor address.
[lastRefreshReceived]	*floating point number*	UTC time when the last neighbor refresh was received.
[lastRefreshSent]	*floating point number*	UTC time when the last neighbor refresh was sent.
[localInterface]	*interface name*	Local interface.

2.1226.2.1.2 RsvpHistory

history	*list of RsvpHistoryEntry* see 2.1226.1.1	Recent history events.

2.1227 show mpls segment-routing bindings [...]

see 2.768

2.1228 show mpls tunnel counters [...]

entries	*list of MplsTunnelCountersEntry* see 2.1228.1	MPLS tunnel hardware counters.

2.1228.1 MplsTunnelCountersEntry

[counterInUse] **	*boolean*	Counter is in use for the tunnel entry. **Since: 4.30.1
[endpoint]	*IP address prefix*	Endpoint of the tunnel.
tunnelIndex	*integer*	Index of the tunnel entry in the source tunnel table.
[tunnelName] **	*string*	Name for the tunnel entry. **Since: 4.26.2

tunnelType	*enum: BGP LU Forwarding | maxTunnelType | IP-in-IP | MLDP P2MP | IS-IS SR IPv6 | invalidTunnel | IS-IS SR IPv4 | VXLAN VTEP Encap | IS-IS SRv6 | Nexthop | Static MPLS | SR-TE Policy | SR-TE | OSPF SR | IS-IS SRv6 TI-LFA | IS-IS FlexAlgo | Static IPv6 | Static MPLS Multicast | Nexthop Group | TI-LFA | LDP | RSVP LER SUB | SRv6 SR-TE SL | RSVP P2MP | RSVP LER | EosSdk sBFD | UDP | SRv6 Transport | EVPN VXLAN | VXLAN | RSVP FRR | IS-IS Remote TI-LFA | BGP LU | RSVP | IS-IS SR | Static | Static Interface*	Tunnel type.
[txBytes]	*integer*	Total number of transmitted bytes.
[txPackets]	*integer*	Total number of transmitted packets.
vias	*list of IpVia* see 2.193.1.3	List of nexthops.

2.1229 show mpls tunnel fib

revision 3

entries	*list of MplsTunnelFibEntry* see 2.1229.1	List of mpls tunnel FIB entries.

2.1229.1 MplsTunnelFibEntry

[endpoint]	*IP address prefix*	Endpoint of the tunnel.
tunnelIndex	*integer*	Index of the tunnel entry in the source tunnel table.

tunnelType	*enum: BGP LU Forwarding | maxTunnelType | IP-in-IP | MLDP P2MP | IS-IS SR IPv6 | invalidTunnel | IS-IS SR IPv4 | VXLAN VTEP Encap | IS-IS SRv6 | Nexthop | Static MPLS | SR-TE Policy | SR-TE | OSPF SR | IS-IS SRv6 TI-LFA | IS-IS FlexAlgo | Static IPv6 | Static MPLS Multicast | Nexthop Group | TI-LFA | LDP | RSVP LER SUB | SRv6 SR-TE SL | RSVP P2MP | RSVP LER | EosSdk sBFD | UDP | SRv6 Transport | EVPN VXLAN | VXLAN | RSVP FRR | IS-IS Remote TI-LFA | BGP LU | RSVP | IS-IS SR | Static | Static Interface*	Tunnel type.
[tunnelViaStatus] **	*enum: usingPrimaryVias | usingBackupVias | notProgrammed | unknown | unresolved*	Tunnel programming status. **Since: 4.21.3
vias	*list of MplsVia* see 2.193.1.4	List of nexthops.

2.1230 show mpls tunnel static [...]

revision 3

entries	*table(numeric string) = StaticTunnelTableEntry* see 2.1230.1	Static tunnel table entries keyed by tunnel index.

2.1230.1 StaticTunnelTableEntry

endpoint	*IP address prefix*	Endpoint of the tunnel.
name	*string*	Static tunnel name.
vias	*list of MplsVia* see 2.193.1.4	List of nexthops.

2.1231 show mpls tunnel termination qos maps [...]

vrfsToDscpToTcNamedMaps	*table(string) = string*	VRF to DSCP to TC named maps, indexed by VRF name.

2.1232 show msdp mesh-group [...]

members	*table(string) = Group* see 2.1232.1	Dictionary of Mesh group names to list of member IPs.

2.1232.1 Group

ipList	*list of IPv4 address*	Mesh group members ip.

2.1233 show msdp rpf-peer RP [...]

queryCompleted	*boolean*	If the RPF query completed.
queryStarted	*boolean*	RPF query started.
rpAddress	*IPv4 address*	RP address.
[rpfPeer]	*IPv4 address*	RPF peer address, if query succeeds.

2.1234 show msrp [...]

interfaces	*table(Interface name) = Intf* see 2.1234.1	Msrp information for a port.
maxFanInPorts	*integer*	Maxiumum number of ingress ports supporting streaming down, beyond which no more Talker streams are allowed.
maxFrameSize	*integer*	Maximum allowed frame size.
msrpEnabled	*boolean*	Indicates whether Msrp is enabled.
srClasses	*table(string) = SrClassGlobal* see 2.1234.2	Globally configured parameters for SR Classes.

2.1234.1 Intf

operState	*enum: Active | LinkDown | Disabled | Blocked*	Operational Msrp state on this interface: Disabled – Msrp is disabled, LinkDown – Physical link is down, Blocked – STP port state is blocked, Active – Msrp is running successfully.
srClasses	*table(string) = SrClass* see 2.1234.1.1	Msrp information for a given SR Class.
srPvid	*integer*	Default VLAN ID for streams on this interface.

2.1234.1.1 SrClass

bandwidth	*integer*	Maximum bandwidth allowed for the SR Class.
bandwidthUnit	*enum: Mbps | pps | kbps | bps*	The unit of bandwidth for SR Classes.
listenerAskFailed	*integer*	Number of ListenerAskingFailed of a given SR Class received on the interface.
listenerReady	*integer*	Number of ListenerReady and ListenerReadyFailed of a given SR Class received on the interface.
state	*enum: NotSupported | Core | WaitingForPeer | Boundary*	The state of an SR Class.
talkerAdvertise	*integer*	Number of TalkerAdvertise of a given SR Class received on the interface.
talkerFailed	*integer*	Number of TalkerFailed of a given SR Class received on the interface.

2.1234.2 SrClassGlobal

bandwidth	*integer*	Maximum bandwidth allowed for SR Class.
priority	*integer*	Priority associated with the SR Class.
supported	*boolean*	Indicates whether SR Class is supported.

2.1235 show msrp counters [...]

interfaces	*table(Interface name) = Intf* see 2.1235.1	Msrp information for a port.

2.1235.1 Intf

operState	*enum: Active | LinkDown | Disabled | Blocked*	Operational Msrp state on this interface: Disabled – Msrp is disabled, LinkDown – Physical link is down, Blocked – STP port state is blocked, Active – Msrp is running successfully.
rxCounters	*table(string) = integer*	MSRP Rxcounters values for respective interfaces.
txCounters	*table(string) = integer*	MSRP TxCounters value for respective interfaces.

2.1236 show msrp interfaces (streams | listeners | talkers) [...]

interfaces	*table(Interface name) = Intf* see 2.1236.1	Msrp streams information for a given interface.

2.1236.1 Intf

streamListenerData	*table(string) = Listener* see 2.1236.1.1	Msrp listener information for a given stream.
streamTalkerData	*table(string) = Talker* see 2.1236.1.2	Msrp talker information for a given stream.

2.1236.1.1 Listener

listenerAge	*string*	Age since the last state of Listener changed.
listenerDirection	*enum: None | Rx | Tx*	Rx – Listener message was received, Tx – Listener message was transmitted, None – No Listener present.
listenerState	*enum: NoListener | ListenerReady | ListenerAskingFailed | ListenerReadyFailed*	Listener state on the given stream.

2.1236.1.2 Talker

talkerAge	*string*	Age since the last state of Talker changed.
talkerDirection	*enum: None | Rx | Tx*	Rx – Talker message was received, Tx – Talker message was transmitted, None – No Talker present.

talkerFailureCode	*enum: noFailure* | *priorityIsNotAnSrClass* | *maxFrameSizeTooLarge* | *insufficientBandwidth* | *maxFanInPortsLimit-Reached* | *vlanBlockedOnEgress* | *egressPortNotAvbCapable* | *vlanTaggingDisabledOn-Egress* | *outOfMmrpResources* | *latencyHasChanged* | *useDifferentDestination-Address* | *srClassPriorityMismatch* | *outOfMsrpResources* | *cannotStoreDestination-Address* | *firstValueChangedFor-StreamId* | *streamPreemptedByHigher-Rank* | *streamDestinationAddress-InUse* | *insufficientResources* | *insufficientTrafficClass-Bandwidth* | *streamIdInUse*	Error code behind the Talker Failed message.
talkerState	*enum: TalkerFailed* | *NoTalker* | *TalkerAdvertise*	Talker state on the given stream.

2.1237 show msrp mrp [...]

interfaces	*table(Interface name) = IntfDatabase* see 2.1237.1	MRP attribute information indexed by interface.

2.1237.1 IntfDatabase

attributeTypes	*table(numeric string) = AttrTypeDatabase* see 2.1237.1.1	MRP type attribute information.

2.1237.1.1 AttrTypeDatabase

attributes	*table(string) = Attribute* see 2.1237.1.1.1	MRP attribute information indexed by keys.

2.1237.1.1.1 Attribute

applicantState	*enum: mrpLeavingObserver | mrpAnxiousNew | mrpQuietObserver | mrpQuietPassive | mrpLeavingActive | mrpQuietActive | mrpVeryAnxiousPassive | mrpAnxiousObserver | mrpAnxiousActive | mrpVeryAnxiousObserver | mrpAnxiousPassive | mrpVeryAnxiousNew*	MRP applicant state.
registrarState	*enum: mrpMt | mrpIn | mrpLv*	MRP registrar state.
[value]	*string*	String representation of the MRP attribute value.

2.1238 show msrp streams [...]

streams	*table(string) = Stream* see 2.1238.1	Msrp stream information collected from the Talker attributes.

2.1238.1 Stream

bandwidth	*integer*	Bandwidth allocated to the stream.
bandwidthUnit	*enum: Mbps | pps | kbps | bps*	The unit of bandwidth for SR Classes.

[bridgeFailureCode]	*enum: noFailure* | *priorityIsNotAnSrClass* | *maxFrameSizeTooLarge* | *insufficientBandwidth* | *maxFanInPortsLimit-Reached* | *vlanBlockedOnEgress* | *egressPortNotAvbCapable* | *vlanTaggingDisabledOn-Egress* | *outOfMmrpResources* | *latencyHasChanged* | *useDifferentDestination-Address* | *srClassPriorityMismatch* | *outOfMsrpResources* | *cannotStoreDestination-Address* | *firstValueChangedFor-StreamId* | *streamPreemptedByHigher-Rank* | *streamDestinationAddress-InUse* | *insufficientResources* | *insufficientTrafficClass-Bandwidth* | *streamIdInUse*	Failure code associated with bridge that changed Talker Advertise to Talker Failed.
destinationMacAddr	*MAC address*	Stream destination MAC address.
[failedBridgeId]	*integer*	Bridge ID of Bridge that changed Talker Advertise to Talker Failed.
[ingressIntf]	*interface name*	Interface on which talker has registered the stream.
[latency]	*integer*	Accumulated latency in nanoseconds for the stream.
[maxFrameSize]	*integer*	Maximum frame size sent by talker.
[maxIntervalFrames]	*integer*	Maximum number of frames sent per class measurement.
[srClass]	*enum: SrClassB* | *SrClassA*	SR Class of the stream.
[talkerState]	*enum: TalkerFailed* | *NoTalker* | *TalkerAdvertise*	State of the talker on the ingress interface.
[vlanId]	*integer*	Vlan Id for the stream.

2.1239 show msrp streams count

activeAvbStreams	*integer*	Number of established AVB Streams. An established AVB stream is one which has a registered talker and has bandwidth allocated to it.

2.1240 show msrp streams propagation [...]

streams	*table(string) = Stream* see 2.1240.1	Shows the propagation of talker and listener attributes for a given stream through the switch.

2.1240.1 Stream

bandwidth	*integer*	Bandwidth allocated to the stream.
bandwidthUnit	*enum: Mbps | pps | kbps | bps*	The unit of bandwidth for SR Classes.
destinationMacAddr	*MAC address*	Stream destination MAC address.
[listenerEgressIntf]	*interface name*	Egress interface on which the listener message was transmitted.
listenerIngressInterfaces	*table(Interface name) = ListenerIngressPort* see 2.1240.1.1	Ingress interfaces on which the listener attributes for a given stream are received.
listenerStateEgressIntf	*enum: NoListener | ListenerReady | ListenerAskingFailed | ListenerReadyFailed*	State of the listener in the message transmitted on the egress interface.
[srClass]	*enum: SrClassB | SrClassA*	SR Class of the stream.
talkerEgressInterfaces	*table(Interface name) = TalkerEgressPort* see 2.1240.1.2	Egress interfaces on which the talker state of a given stream is propagated.
[talkerIngressIntf]	*interface name*	Interface on which the talker message was received.
talkerStateIngressIntf	*enum: TalkerFailed | NoTalker | TalkerAdvertise*	State of the talker in the message received on the ingress interface.
talkerStatePropagated	*enum: TalkerFailed | NoTalker | TalkerAdvertise*	State of the talker propagated on the given egress interface.
[vlanId]	*integer*	Vlan Id for the stream.

2.1240.1.1 ListenerIngressPort

listenerStateIngress	*enum: NoListener | ListenerReady | ListenerAskingFailed | ListenerReadyFailed*	State of the listener in the message received on the given ingress interface.
[listenerStatePropagated]	*enum: NoListener | ListenerReady | ListenerAskingFailed | ListenerReadyFailed*	State of the listener propagated to the egress interface.

2.1240.1.2 TalkerEgressPort

talkerStateEgress	*enum: TalkerFailed | NoTalker | TalkerAdvertise*	State of the talker propagated on the given egress interface.

2.1241 show multicast (ipv4 | ipv6) evpn decap joined [...]

revision 2

[detail_]	*boolean*	Display information in detail.
interfaces	*table(string) = MrouteVxlanDecapInterface* see 2.1241.1	A mapping of interface to joined groups.

2.1241.1 MrouteVxlanDecapInterface

groups	*table(IPv4 or IPv6 address) = MrouteVxlanDecapGroup* see 2.1241.1.1	A mapping of group to it's sources.

2.1241.1.1 MrouteVxlanDecapGroup

sources	*table(IPv4 or IPv6 address) = DecapExtraInfo* see 2.1241.1.1.1	Mapping of source to more information of decap group.

2.1241.1.1.1 DecapExtraInfo

role	*enum: bud | decap*	Decap role status.

2.1242 show multicast (ipv4 | ipv6) source route export [...]

revision 3

see 2.50

2.1243 show multicast AF evpn decap received

[underlayReplication] **	*UnderlayReplicationModel* see 2.1243.2	Underlay replication. **Since: 4.28.1
vlans	*table(numeric string) = MulticastTunnelVlan* see 2.1243.1	A mapping of VLAN ID to multicast tunnel encapsuslation information.

2.1243.1 MulticastTunnelVlan

groups	*table(IPv4 or IPv6 address) = MulticastTunnelGroup* see 2.1243.1.1	A mapping of a multicast group in a VLAN to traffic sources.

2.1243.1.1 MulticastTunnelGroup

sources	*table(IPv4 or IPv6 address) = MulticastTunnelSource* see 2.1243.1.1.1	A mapping of source to encapsulating multicast sources and groups.

2.1243.1.1.1 MulticastTunnelSource

groups	*list of MulticastEncapSourceGroup* see 2.1243.1.1.1.1	A list of encapsulating groups for this (S,G).

2.1243.1.1.1.1 MulticastEncapSourceGroup

[domain] **	*enum: local | remote*	EVPN domain associated with the tunnel. **Since: 4.34.2
group	*IP address*	Destination group address used in tunnel encapsulation.
source	*IP address*	Source address used in tunnel encapsulation.
[tunnelType]	*enum: pimSsm | pimSm | pimBidir*	Tunnel type.

2.1243.2 UnderlayReplicationModel

headendReplication	*boolean*	Underlay HER enabled.
multicast	*boolean*	Underlay multicast enabled.
[multicastRemoteDomain] **	*boolean*	Underlay multicast to EVPN remote domain enabled. **Since: 4.34.2

2.1244 show multicast AF evpn decap received flood

vlans	*table(numeric string) = MulticastFloodVlan* see 2.1244.1	A mapping of VLAN ID to multicast tunnel encapsuslation information for broadcast, unknown unicast and link-local multicast traffic.

2.1244.1 MulticastFloodVlan

floodGroups	*list of MulticastEncapSourceGroup* see 2.1243.1.1.1.1	A list of encapsulating (S,G) for a VLAN.

2.1245 show multicast AF evpn encap

see 2.1243

2.1246 show multicast AF evpn encap flood

see 2.1244

2.1247 show multicast fib ipv4 PIM_MODE [...]

groups	*table(IPv4 or IPv6 address prefix) = MfibGroup* see 2.1247.1	Map of multicast groups.
hwPollingInterval	*integer*	Hardware polling interval.
hwResourceFull	*boolean*	No space remaining in hardware.

2.1247.1 MfibGroup

routes	*table(IPv4 or IPv6 address prefix) = MfibRoute* see 2.1247.1.1	Multicast routes for this group.

2.1247.1.1 MfibRoute

[bitsRateCounter] **	*RateCounter* see 2.1247.1.1.3	Hardware multicast traffic counter rate, in bits/s, if supported. **Since: 4.26.0
[bytesCounter]	*Counter* see 2.1247.1.1.1	Hardware multicast traffic counter, in bytes, if supported.
[fastdropInterfaces]	*list of Interface name*	List of fastdrop interfaces.
[hwRoute]	*MfibHwRoute* see 2.1247.1.1.2	Hardware route information.
[incomingInterface]	*interface name*	Incoming interface for the route.
[incomingInterfaceFrr]	*interface name*	Incoming interface for fast failover route.
[notifyInterface]	*interface name*	Notify interface for the route.
[outgoingInterfaces]	*list of Interface name*	List of outgoing interfaces for the route.
[packetsCounter]	*Counter* see 2.1247.1.1.1	Hardware multicast traffic counter, in packets, if supported.
[pktsRateCounter] **	*RateCounter* see 2.1247.1.1.3	Hardware multicast traffic counter rate, in pkts/s, if supported. **Since: 4.26.0
[rpaIndex]	*integer*	Rendezvous point address index for the route.
[staticFastdropInterface]	*interface name*	Interface with static fastdrop installed.
[toCpu]	*boolean*	Route has local listeners.

2.1247.1.1.1 Counter

[active]	*boolean*	Counter active in hardware.
[value]	*integer*	Stored count retrieved from hardware when counter is active.

2.1247.1.1.2 MfibHwRoute

creationTime	*floating point number*	UTC time when the hardware route was created.
programmed	*boolean*	Route programmed in hardware.

[routeActivity]	*floating point number*	Last polled UTC time when the route was seen as active in hardware.

2.1247.1.1.3 RateCounter

[active]	*boolean*	Counter active in hardware.
[value]	*floating point number*	Stored counter rate.

2.1248 show multicast fib ipv4 [...]

see 2.1247

2.1249 show multicast fib ipv4 df [...]

bidirEnabled	*boolean*	Pim Bidir enabled.
dfProfiles	*table(Interface name) = integer*	Mapping from interface to DF bitmap.

2.1250 show multicast fib ipv4 rpa [...]

bidirEnabled	*boolean*	Pim Bidir enabled.
groups	*table(IPv4 or IPv6 address prefix) = integer*	Mapping from prefix to RPA index.

2.1251 show multicast fib ipv6 PIM_MODE [...]

see 2.1247

2.1252 show multicast fib ipv6 [...]

see 2.1247

2.1253 show multicast ipv4 boundary [...]

see 2.718

2.1254 show multicast ipv4 evpn config-sanity [...]

[evpnVlanVniSet]	*EvpnVlanVniCheck* see 2.1254.1	VLANs missing VXLAN VNI configuration.
[vrfSet]	*VrfCheck* see 2.1254.2	VRFs missing VXLAN VNI configuration.

2.1254.1 EvpnVlanVniCheck

[vlans]	*table(numeric string) = integer or NULL*	Mapping of VLAN to VNI.

2.1254.2 VrfCheck

[vrfs]	*table(string) = integer or NULL*	Mapping of VRF to VNI.

2.1255 show multicast ipv4 evpn encap mapping (vrf VRF) OVERLAY_GRP

vlans	*table(numeric string) = IP address*	A mapping of VLAN ID to multicast tunnel encapsuslation group.

2.1256 show multicast ipv4 evpn mpls vrf

vrfs	*table(string) = MvpnVrfPmsis* see 2.1256.1	Mapping of VRF to PMSIs.

2.1256.1 MvpnVrfPmsis

pmsis	*list of string*	List of PMSIs for MVPN VRF.

2.1257 show multicast ipv6 boundary [...]

see 2.718

2.1258 show multicast oifset hardware [...]

oifSets	*table(string) = McastCommon.CliModel.-OifsetInfo* see 2.1258.1	Map from Oifset id's to OifSets.

2.1258.1 McastCommon.CliModel.OifsetInfo

acceptingVlanId	*integer*	Acceping VLAN ID of the interface Vlan Set.
bidir	*boolean*	Bidir flag is set.
fastdrop	*boolean*	Fastdrop for interface Vlan Set is set.
featureFlag	*string*	Feature flags of the interface Vlan Set.
ignoreType	*boolean*	Ignore route key type is set.
interfaces	*table(string) = McastCommon.CliModel.-PortVlanModel* see 2.1258.1.1	Map from Vlan Interfaces to their properties.
keyType	*enum: vlanFloodset | mroute | mcastGroup | ethGroup | evpnMultihomeFloodset | multicastV6Floodset | multicastFloodset | unknownRouteKeyType | vxlanCoreSideFloodset*	Type of interface.
oifsetId	*string*	OifSetID of the interface Vlan Set.
toCpuPurpose	*enum: toCpuVxlan | toCpuMcast | null*	toCpu for mcast or vxlan.

2.1258.1.1 McastCommon.CliModel.PortVlanModel

isMacSecViaLoopBack	*boolean*	Is MACSec via loopback.
isMlagPort	*boolean*	Is MLAG Interface.
isNonDfPort	*boolean*	Is Non DF Interface.
isTagOnEgress	*boolean*	Is Tag on Egress.
logicalPortId	*integer*	Logical interface ID for the interface.
outLif	*integer*	Output Logical Interface for the interface.
overlayVlanId	*integer*	Overlay VLAN ID for the interface.
sharedPort	*boolean*	Is Shared interface.

2.1259 show multicast tunnel counters (rsvp | static)

entries	*list of McastMplsTunnel-CounterEntry* see 2.1259.1	Multicast tunnel counters.

2.1259.1 McastMplsTunnelCounterEntry

tunnelId	*integer*	Index of the tunnel entry in the source tunnel table.
tunnelIdentifier	*string*	Tunnel ID string.
[txBytes]	*integer*	Total number of transmitted bytes.
[txPackets]	*integer*	Total number of transmitted packets.

2.1260 show mvpn ipv4 decapsulation [...]

vrfs	*table(string) = PmsiTunnelDecapModel* see 2.1260.1	PMSI tunnel decapsulation information indexed by VRF name.

2.1260.1 PmsiTunnelDecapModel

[mldpP2mp]	*PmsiMldpTunnelDecap* see 2.1260.1.1	MLDP P2MP tunnel decapsulation information.
[rsvpTeP2mpLsp]	*PmsiRsvpTunnelDecap* see 2.1260.1.2	RSVP-TE P2MP tunnel decapsulation information.
[vrfId]	*integer*	VRF ID.

2.1260.1.1 PmsiMldpTunnelDecap

rootAddrs	*table(IPv4 or IPv6 address) = PmsiMldpOpaqueValueModel* see 2.1260.1.1.1	Dictionary of OpaqueValue models indexed by root addr.

2.1260.1.1.1 PmsiMldpOpaqueValueModel

opaqueValues	*PmsiMldpOpaqueValue* see 2.1260.1.1.1.1	MLDP P2MP tunnel opaque value information.

2.1260.1.1.1.1 PmsiMldpOpaqueValue

[genericLspIds]	*table(numeric string) = Interface name*	Dictionary of pmsiIntfIds indexed by LSP ID.
[invalidOpaqueValues]	*table(string) = Interface name*	Dictionary of pmsiIntfIds indexed by invalid opaque values.
[transitV4Src]	*table(IPv4 or IPv6 address) = PmsiMldpOpaqueValueGroup* see 2.1260.1.1.1.2	Dictionary of OpaqueValueGroup models indexed by source address.

2.1260.1.1.1.2 PmsiMldpOpaqueValueGroup

groups	*table(IPv4 or IPv6 address) = PmsiMldpOpaqueValueRd* see 2.1260.1.1.1.3	Dictionary of OpaqueValueRd models indexed by group addr.

2.1260.1.1.1.3 PmsiMldpOpaqueValueRd

rds	*table(string) = Interface name*	Dictionary of pmsiIntfIds indexed by route distinguisher.

2.1260.1.2 PmsiRsvpTunnelDecap

p2mpIds	*table(numeric string) = PmsiRsvpTunnelDecapTunnelId* see 2.1260.1.2.1	Dictionary of RSVP tunnel ID models indexed by P2MP ID.

2.1260.1.2.1 PmsiRsvpTunnelDecapTunnelId

tunnelIds	*table(numeric string) = PmsiRsvpTunnelDecapExtTunnelId* see 2.1260.1.2.1.1	Dictionary of ext tunnel ID models indexed by tunnel ID.

2.1260.1.2.1.1 PmsiRsvpTunnelDecapExtTunnelId

extTunnelIds	*table(IPv4 or IPv6 address) = Interface name*	Dictionary of pmsiIntfIds indexed by ext tunnel ID.

2.1261 show mvpn ipv4 encapsulation [...]

vrfs	*table(string) = EncapVrfModel* see 2.1261.1	Dictionary of encapsulation status entries indexed by VRF name.

2.1261.1 EncapVrfModel

tunnelTypes	*table(string) = EncapGroupModel* see 2.1261.1.1	Dictionary of multicast groups indexed by mulitcast tunnel type.
[vrfId]	*integer*	VRF ID.

2.1261.1.1 EncapGroupModel

groups	*table(IPv4 or IPv6 address) = EncapSourceModel* see 2.1261.1.1.1	Dictionary of multicast sources indexed by mulitcast group address.

2.1261.1.1.1 EncapSourceModel

sources	*table(IPv4 or IPv6 address) = EncapTunnelModel* see 2.1261.1.1.1.1	PMSI tunnels indexed by multicast source address.

2.1261.1.1.1.1 EncapTunnelModel

[pmsiTunnel]	*PmsiTunnelId* see 2.20.1.1.2.39	PMSI tunnel identifier information.
[vlans]	*table(numeric string) = PmsiTunnelId* see 2.20.1.1.2.39	Dictionary of PMSI tunnel identifiers indexed by VLAN ID.

2.1262 show mvpn ipv4 vrf

see 2.1256

2.1263 show mvrp [...]

interfaces	*table(Interface name) = Intf* see 2.1263.1	Mvrp information for a port.
mvrpEnabled	*boolean*	Indicates whether Mvrp is enabled.

2.1263.1 Intf

declaredVlans	*list of integer*	Mvrp vlans declared on a given port.
operState	*enum: Active | LinkDown | Disabled | Blocked*	Operational Mvrp state on this interface: Disabled – Mvrp is disabled, LinkDown – Physical link is down, Blocked – STP port state is blocked, Active – Mvrp is running successfully.
registeredVlans	*list of integer*	Mvrp vlans registered on a given port.
requester **	*enum: CLI | Dot1x*	Requester of MVRP configuration on this interface: Dot1x – Dot1x agent, CLI – Config agent. **Since: 4.33.0

2.1264 show mvrp mrp [...]

interfaces	*table(Interface name) = IntfDatabase* see 2.1264.1	MRP attribute information indexed by interface.

2.1264.1 IntfDatabase

attributeTypes	*table(numeric string) = AttrTypeDatabase* see 2.1264.1.1	MRP type attribute information.

2.1264.1.1 AttrTypeDatabase

attributes	*table(numeric string) = Attribute* see 2.1264.1.1.1	MRP attribute information indexed by keys.

2.1264.1.1.1 Attribute

applicantState	*enum: mrpLeavingObserver | mrpAnxiousNew | mrpQuietObserver | mrpQuietPassive | mrpLeavingActive | mrpQuietActive | mrpVeryAnxiousPassive | mrpAnxiousObserver | mrpAnxiousActive | mrpVeryAnxiousObserver | mrpAnxiousPassive | mrpVeryAnxiousNew*	MRP applicant state.
registrarState	*enum: mrpMt | mrpIn | mrpLv*	MRP registrar state.
[value]	*string*	String representation of the MRP attribute value.

2.1265 show mvrp vlans [...]

vlans	*table(numeric string) = Vlan* see 2.1265.1	Mvrp information for a vlan.

2.1265.1 Vlan

declaredIntfs	*list of string*	Ports on which a given Mvrp Vlan is declared.
registeredIntfs	*list of string*	Ports on which a given Mvrp Vlan is registered.

2.1266 show nat map-t domain [...]

domains	*table(string) = Domain* see 2.1266.1	MAP domains, keyed by name.

2.1266.1 Domain

brPrefix	*IP address prefix*	Border Relay IPv6 prefix.
eaLength	*integer*	Length of the Embedded Address bits.
exceptionOffloadIp	*IPv4 address*	Exception offload nexthop IP address.
exceptionOffloadState	*enum: unresolvedDrop | unconfiguredDrop | resolved*	State of the exception offload next hop.
[exceptionOffloadToCpu] **	*boolean*	Exception offload using local CPU. **Since: 4.30.0
mapId	*integer*	MAP domain ID.
mtu	*integer*	MTU for traffic headed to the MAP domain.

psidOffset	*integer*	Port Set IDentifier offset within the L4 port.
rules	*table(IPv4 or IPv6 address prefix) = Rule* see 2.1266.1.1	A mapping of IPv6 prefix to MAP rule.
state	*enum: programmedInHw | unknown | hwProgrammingFailed | complete | incomplete*	State of the domain.
vrf	*string*	VRF name.

2.1266.1.1 Rule

description	*string*	Description of the MAP rule.
ipv4Prefix	*IP address prefix*	IPv4 rule prefix.
ipv6Prefix	*IP address prefix*	IPv6 rule prefix.

2.1267 show nat map-t domain counters [...]

domains	*table(string) = DomainCountersSummary* see 2.1267.1	A mapping of MAP domain name to MAP domain counters.

2.1267.1 DomainCountersSummary

drop	*PktsAndBytes* see 2.1267.1.1	A cumulative count of dropped traffic in a MAP domain.
fourToSix	*PktsAndBytes* see 2.1267.1.1	A cumulative count of all 4To6 translated traffic in a MAP domain.
offload	*PktsAndBytes* see 2.1267.1.1	A cumulative count of all offloaded traffic in a MAP domain.
sixToFour	*PktsAndBytes* see 2.1267.1.1	A cumulative count of all 6To4 translated traffic in a MAP domain.

2.1267.1.1 PktsAndBytes

byteCount	*integer*	Byte count.
packetCount	*integer*	Packet count.

2.1268 show nat map-t domain counters drop [...]

domains	*table(string) = DomainDropCounters* see 2.1268.1	A mapping of MAP domain name to MAP domain drop counters.

2.1268.1 DomainDropCounters

mapDrop **	*PktsAndBytes* see 2.1267.1.1	A packet/bytes count of all traffic that was dropped during MAP translation from expected drop causes (ICMP drop, unsupported L4, etc). **Since: 4.32.0
platformError **	*PktsAndBytes* see 2.1267.1.1	A packet/bytes count of all traffic that was dropped during MAP translation due to malformed packets or unexpected internal errors. **Since: 4.32.0
spoofCheckFailed	*PktsAndBytes* see 2.1267.1.1	A packet/bytes count of all traffic that failed the spoof checks.

2.1269 show nat map-t domain counters exception [...]

domains	*table(string) = DomainExceptionCounters* see 2.1269.1	A mapping of MAP domain name to MAP domain exception counters.

2.1269.1 DomainExceptionCounters

fourToSixFragments-Reassembled	*PktsAndBytes* see 2.1267.1.1	A count of 4To6 reassembled fragments.
fourToSixFragmentsReceived	*PktsAndBytes* see 2.1267.1.1	A count of 4To6 received fragments.
fourToSixFragments-Transmitted	*PktsAndBytes* see 2.1267.1.1	A count of 4To6 transmitted fragments.
fourToSixIcmpFragmentation-NeededSent **	*PktsAndBytes* see 2.1267.1.1	A count of 4To6 ICMP fragmentation needed sent packets. **Since: 4.35.2
fourToSixIcmpTranslated **	*PktsAndBytes* see 2.1267.1.1	A count of 4To6 ICMP translated packets. **Since: 4.32.1
fourToSixPacketsFragmented	*PktsAndBytes* see 2.1267.1.1	A count of 4To6 fragmented packets.
fourToSixUdpCsum-Recalculated **	*PktsAndBytes* see 2.1267.1.1	A count of 4To6 packets whose UDP checksum was recalculated. **Since: 4.32.0
sixToFourFragments-Reassembled	*PktsAndBytes* see 2.1267.1.1	A count of 6To4 reassembled fragments.
sixToFourFragmentsReceived	*PktsAndBytes* see 2.1267.1.1	A count of 6To4 received fragments.
sixToFourIcmpTranslated **	*PktsAndBytes* see 2.1267.1.1	A count of 6To4 ICMP translated packets. **Since: 4.32.1

2.1270 show nat map-t domain counters offload [...]

domains	*table(string) = DomainOffloadCounters* see 2.1270.1	A mapping of MAP domain name to MAP domain offload counters.

2.1270.1 DomainOffloadCounters

ipv4Fragment	*PktsAndBytes* see 2.1267.1.1	A count of all IPv4 traffic that was offloaded for reassembly.
ipv4MtuExceeded	*PktsAndBytes* see 2.1267.1.1	A count of all traffic that was offloaded for fragmentation.
ipv4NonTcpUdp	*PktsAndBytes* see 2.1267.1.1	A count of all non-TCP/UDP IPv4 traffic that was offloaded.
ipv4Options	*PktsAndBytes* see 2.1267.1.1	A count of all IPv4 options traffic that was offloaded.
ipv4UdpChecksum0	*PktsAndBytes* see 2.1267.1.1	A count of all traffic that was offloaded for checksum recalc.
ipv6Fragment	*PktsAndBytes* see 2.1267.1.1	A count of all IPv6 traffic that was offloaded for reassembly.
ipv6NonTcpUdp	*PktsAndBytes* see 2.1267.1.1	A count of all non-TCP/UDP IPv6 traffic that was offloaded.

2.1271 show nat map-t domain counters rule [...]

domains	*table(string) = DomainRuleCounters* see 2.1271.1	A mapping of MAP domain name to rule counters for that domain.

2.1271.1 DomainRuleCounters

rules	*table(IPv4 or IPv6 address prefix) = RuleCounters* see 2.1271.1.1	Mapping of IPv6 prefix to MAP rule.

2.1271.1.1 RuleCounters

fourToSix	*PktsAndBytes* see 2.1267.1.1	A packet/byte count of all 4To6 traffic for this rule.
ipv4Prefix	*IP address prefix*	IPv4 rule prefix.
ipv6Prefix	*IP address prefix*	IPv6 rule prefix.
sixToFour	*PktsAndBytes* see 2.1267.1.1	A packet/byte count of all 6To4 traffic for this rule.

2.1272 show nat map-t summary

domains	*table(string) = DomainSummary* see 2.1272.1	A mapping of domain name to its summary.

2.1272.1 DomainSummary

mapId	*integer*	MAP domain ID.
ruleCount	*integer*	Count of rules in this domain.
state	*enum: programmedInHw | unknown | complete | incomplete | hwProgrammingFailed*	State of the domain.

2.1273 show neighbor classification [...]

neighbors	*table(MAC address) = NbrClassificationModel* see 2.1273.1	A dictionary of neighbors classifications keyed by ethernet address.

2.1273.1 NbrClassificationModel

classification	*list of string*	Classifications.
description	*string*	Description that helps identify neighbor.
interface	*interface name*	Interface that neighbor is connected to.
source **	*string*	Source of phone neighbor. **Since: 4.29.2

2.1274 show neighbor classification summary [...]

none	*NbrClassificationSummaryModel* see 2.1274.1	Summary for devices classified as none.
phone	*NbrClassificationSummaryModel* see 2.1274.1	Summary for devices classified as phone.

2.1274.1 NbrClassificationSummaryModel

aaa	*integer*	Deprecated - Number of AAA neighbors.
cli	*integer*	Number of CLI (manual) neighbors.
lldp	*integer*	Number of LLDP neighbors.

2.1275 show network physical-topology hosts [...]

hosts	*table(string) = Host* see 2.1275.1	Set of hosts in topology.

2.1275.1 Host

[details]	*boolean*	Details including logical ports and port channels.
hostname	*string*	Hostname of the device. This is typically configured.
logicalPorts	*table(string) = LogicalPort* see 2.1275.1.1	Logical ports on this host.
name	*string*	Unique name/id which identifies this device.
port	*table(string) = Port* see 2.1275.1.2	Ports on this host.
portChannels	*table(string) = PortGroup* see 2.1275.1.3	Port channels on this host.

2.1275.1.1 LogicalPort

[memberPorts]	*list of string*	Names of the member ports in this port channel.
name	*string*	Name of the logical port, port channel or physical port.

2.1275.1.2 Port

hostid **	*string*	Unique name/id which identifies host owning this port. **Since: 4.20.0
hostname	*string*	Host owning this port.
name	*string*	Name of the port, for e.g., Ethernet1, Management1..
[portChannel]	*string*	Port channel which this port is a member of.

2.1275.1.3 PortGroup

memberPorts	*list of string*	Names of the member ports in this port channel.
name	*string*	Name of the portGroup, for e.g., portChannel1.

2.1276 show network physical-topology neighbors [...]

neighbors	*table(string) = DirectedEdge* see 2.1276.1	Collection of neighbors in topology.

2.1276.1 DirectedEdge

fromPort	*Port* see 2.1275.1.2	Starting port of the directed edge.
toPort	*list of Port* see 2.1275.1.2	Ending port of the directed edge.

2.1277 show nexthop-group [...]

nexthopGroups	*table(string) = NexthopGroup* see 2.1277.1	Mapping between nexthop group name and status.

2.1277.1 NexthopGroup

[autoSize] **	*boolean*	Nexthop group auto resizing. **Since: 4.15.3
[backupSize] **	*integer*	Nexthop group backup entry size. **Since: 4.32.0
[backupVia] **	*table(numeric string) = Via* see 2.1277.1.1	Mapping between backup entry index, and via. **Since: 4.32.0
destinationIps	*table(numeric string) = string*	Destination Ip address list.
[dscpToDscpMap] **	*string*	Name of the Dscp to Dscp map. **Since: 4.36.0
[entryCounterType] **	*enum: unshared | disabled | shared*	Entry counter type. **Since: 4.20.5
[greKeyType]	*enum: noGreKey | customKey | ingressIntf*	GRE key type.
[hierarchicalFecsEnabled] **	*boolean*	True if hierarchical fecs are enabled for this nexthop group. **Since: 4.21.0
nexthopGroupId	*integer*	Nexthop group Id.
nexthopGroupName	*string*	Nexthop group name.
nexthopGroupType	*enum: mplsOverUdpPseudowire | invalid | mplsOverUdp | ipv6OverUdp | gre | ip | mplsOverGre | mpls | dzgre | vxlan | ipv4OverUdp | ipInIp*	Nexthop group type.
[numProgrammedBackup-Tunnels] **	*integer*	Number of backup tunnels programmed in hardware. **Since: 4.32.0
[numProgrammedTunnels] **	*integer*	Number of tunnels programmed in hardware. **Since: 4.15.3
[perEntryBackups] **	*boolean*	True if per entry backups are enabled for this nexthop group. **Since: 4.33.2
[persistentCounters] **	*boolean*	Entry counters persist through configuration updates. **Since: 4.29.1
[programmed]	*boolean*	Whether the group has been programmed in hardware.
size	*integer*	Nexthop group entry size.
[sourceIntf] **	*interface name*	Source interface. **Since: 4.17.0
sourceIp	*IP address*	Source Ip address.

[tos] **	*integer*	Type of service value. **Since: 4.25.2
ttl	*integer*	Time to live value.
[udpDestPort] **	*integer*	UDP destination port. **Since: 4.31.1
via	*table(numeric string) = Via* see 2.1277.1.1	Mapping between entry index, and via.

2.1277.1.1 Via

[bytes]	*integer*	Number of bytes matched.
[counterInUse] **	*boolean*	True if counter is in use. **Since: 4.30.1
destinationAddr	*IP address*	Destination Ip address.
entryIndex	*integer*	Nexthop group entry index.
isTunnelVia	*boolean*	True if destination is a tunnel.
l2Via	*L2Via* see 2.1277.1.1.1	L2 via.
l3Intf	*interface name*	Egress L3 interface.
[mplsLabelOperation] **	*enum: pop | swap | unknown | push*	Label Stack Operation. **Since: 4.22.0
[mplsLabelStack]	*list of integer*	MPLS label stack to push on to the packet. Left most label is the top of the stack.
[nextLevelFecIndex] **	*integer*	Next level FIB FEC if the via is hierarchical. **Since: 4.21.0
[nextLevelNexthopGroupName]	*string*	Next level nexthop group name.
nexthopAddr	*IP address*	Nexthop address.
[nexthopGroupType]	*enum: mplsOverUdpPseudowire | invalid | mplsOverUdp | ipv6OverUdp | gre | ip | mplsOverGre | mpls | dzgre | vxlan | ipv4OverUdp | ipInIp*	Nexthop group type.
[packets]	*integer*	Number of packets matched.
[platformNextLevelFecIndex] **	*integer*	Platform-specific version of the next level FIB FEC. **Since: 4.21.0
route	*IP address prefix*	Route used to resolve destination.
[sbfdSessionTunnelId] **	*integer*	SBFD session tunnel ID for liveness detection. **Since: 4.31.1
[sharedTunnel]	*boolean*	True for shared tunnel.
[sourceIp] **	*IP address*	Tunnel Source IP. **Since: 4.29.0
[unresolvedNexthopAction] **	*enum: notProgrammed | notActive | drop*	Nexthop programming action if not resolved. **Since: 4.15.3
[unresolvedNexthopReason]	*string*	A description of why this next hop is unresolved.

2.1277.1.1.1 L2Via

l2Intf	*interface name*	Egress L2 interface.
macAddr	*MAC address*	Destination MAC address.
vlanId	*integer*	Vlan Id.

2.1278 show nexthop-group id [...]

nexthopGroups	*table(numeric string) = NexthopGroup* see 2.1277.1	Mapping between nexthop group ID and status.

2.1279 show nexthop-group id mapping

nexthopGroups	*table(numeric string) = string*	Mapping between nexthop group ID and name.

2.1280 show nexthop-group summary

numDropNexthopGroups **	*integer*	Number of drop programmed nexthop groups. **Since: 4.35.2
numNexthopGroups	*integer*	Number of nexthop groups configured.
numNexthopGroupsPerSize	*table(string) = integer*	Number of nexthop groups configured indexed by number of entries.
numNexthopGroupsPerType	*table(string) = integer*	Number of nexthop groups configured indexed by nexthop group type.
numUnprogrammedNexthop-Groups	*integer*	Number of unprogrammed nexthop groups.

2.1281 show nexthop-group tunnel [...]

indexes	*table(numeric string) = NexthopGroupTunnelTable-Entry* see 2.1281.1	Nexthop Group tunnel entries keyed by tunnel index.

2.1281.1 NexthopGroupTunnelTableEntry

endpoint	*IP address prefix*	Endpoint of the tunnel.
igpMetric	*integer*	IGP Metric for tunnel entry.
igpPref	*integer*	IGP Preference for tunnel entry.
nexthopGroupName	*string*	Nexthop group name.

2.1282 show ntp ((ip access-list) | (ipv6 access-list)) [...]

see 2.62

2.1283 show ntp associations

peers	*table(string) = NtpPeer* see 2.1283.1	A mapping between peer host name and peer host information.

2.1283.1 NtpPeer

condition	*enum: backup | outlier | falsetick | pps.peer | reject | candidate | excess | sys.peer*	Select field of the peer status word.
delay	*floating point number*	Roundtrip delay (milliseconds).
jitter	*floating point number*	jitter (milliseconds).
lastReceived	*floating point number*	Timestamp of last received packet.
offset	*floating point number*	offset of server relative to this host (milliseconds).
peerIpAddr	*IP address*	IP of the peer.
peerType	*enum: broadcast | local | unicast*	Type of peer.
pollInterval	*integer*	Poll interval (seconds).
reachabilityHistory	*list of boolean*	A list of poll history success.
refid	*string*	Reference ID.
stratumLevel	*integer*	Accuracy of the clock source (1 is best).

2.1284 show ntp status

[maxEstimatedError]	*integer*	Maximum estimated error of the clock (in milliseconds).
[ntsClient] **	*NtpComponentInfo* see 2.1284.1	Client NTS state. **Since: 4.34.2
[ntsKeClient] **	*NtsKeClientInfo* see 2.1284.2	NTS-KE client state. **Since: 4.34.2
[ntsKeServer] **	*NtsKeServerInfo* see 2.1284.3	NTS-KE server state. **Since: 4.34.2
[ntsServer] **	*NtpComponentInfo* see 2.1284.1	Server NTS state. **Since: 4.34.2
[pollingInterval]	*integer*	Polling interval of the peer (in seconds).
[server]	*IP address*	Time source (NTP server or reference clock) to which the system clock is currently synchronised.
status	*enum: starting | synchronised | local | unsynchronised | non-existing | disabled*	Status of NTP synchronisation service.
[stratum]	*integer*	Indicates the level of the server in the NTP hierarchy - see RFC 5905, 7.3.
[warning] **	*list of string*	NTP configuration warnings. **Since: 4.34.2

2.1284.1 NtpComponentInfo

recvsError	*integer*	Number of invalid NTS-secured packets received.
recvsGood	*integer*	Number of valid NTS-secured packets received.
sends	*integer*	Number of NTS-secured packets sent.

2.1284.2 NtsKeClientInfo

probesBad	*integer*	Number of unsuccessful key establishments.
probesGood	*integer*	Number of successful key establishments.

2.1284.3 NtsKeServerInfo

servesBad	*integer*	Number of unsuccessful key establishments served.
servesGood	*integer*	Number of successful key establishments served.

2.1285 show openflow

bindMode	*BindModeEntries* see 2.1285.1	Bind mode.
connectSuccessCount	*integer*	Connect success count.
[connectedCtrl]	*list of ConnectedController* see 2.1285.2	List of connected controllers.
controllers	*list of IpAddrAndPort* see 2.723.1.1.1.1	List of openflow controllers.
[controllersInfo]	*list of ControllerConfig* see 2.1285.3	List of openflow controllers.
datapathID	*integer*	Datapath ID.
description	*string*	Datapath description.
enabled	*boolean*	OpenFlow enabled.
[expiredTtlOutput-Controller]	*boolean*	Send expired ttl packets to controller.
flowTableProfile	*enum: full-match* | *vxlan-match* | *auto* | *l2-match*	Table profile.
flowTableState	*boolean*	Flow table enabled or not.
forwardingPipeline	*enum: flow* | *flow-and-normal*	Forwarding pipeline.
ipRoutingState	*boolean*	Enabled if rvlans.
keepalivePeriod	*integer*	Keepalive in seconds.
[minimumVersion]	*1.3*	Minimum OpenFlow protocol version required.
[passiveControllerConfig]	*list of ControllerConfig* see 2.1285.3	List of configured passive controllers.
[passiveControllerStatus]	*list of ConnectedController* see 2.1285.2	List of listening passive controllers.
[rvlans]	*RvlanEntries* see 2.1285.4	rvlan entries.
shellCommandAllowed	*boolean*	Shell commands allowed.
totalPacketCount	*integer*	Matched packets.

2.1285.1 BindModeEntries

[bindInterfaces]	*list of Interface name*	Bind interfaces.
bindMode	*enum: None* | *bindModeVlan* | *bindModeInterface* | *bindModeMonitor*	Bind mode.
[bindVlan]	*string*	Bind vlans.
[nativeVlan]	*string*	Native vlan.

2.1285.2 ConnectedController

auxConnected	*boolean*	Auxiliary channel connected.
controllerAddr	*IpAddrAndPort* see 2.723.1.1.1.1	Connected controller.
[controllerRole]	*enum: slave* | *equal* | *master*	Controller role.

[negotiatedVersion]	*string*	Version negotiated with the connected controller.

2.1285.3 ControllerConfig

auxEnabled	*boolean*	Auxiliary channel connected.
connectionMode	*enum: active | passive*	Switch's network connection mode with controller.
controllerAddr	*IpAddrAndPort* see 2.723.1.1.1.1	Connected controller.

2.1285.4 RvlanEntries

rIntf	*interface name*	Recirculation interface.
rvlanEntry	*list of Entries* see 2.1285.4.1	rvlan entries.

2.1285.4.1 Entries

rvlan	*integer*	rvlan entry.
vlan	*integer*	Vlan entry.

2.1286 show openflow flows [...]

flows	*list of Flow* see 2.365.1.1	Flows.

2.1287 show openflow groups [...]

groups	*list of Group* see 2.1287.1	Groups.

2.1287.1 Group

[buckets]	*list of Bucket* see 2.1287.1.1	List of buckets in the group.
flows	*list of string*	Flows referring to the group.
groupId	*integer*	Group Identifier.
status	*string*	Status of the group.

2.1287.1.1 Bucket

bucketId	*integer*	Bucket Id.
[macDst]	*MacAddr* see 2.365.1.1.1.3	Set destination Mac address.
[macSrc]	*MacAddr* see 2.365.1.1.1.3	Set source Mac address.
[outInterfaces]	*list of Interface name*	Output interfaces.
[ttlDec]	*boolean*	Decrement TTL.

[vlan]	*integer*	Set Vlan ID.

2.1288 show openflow ports

portInterface	*list of Entry* see 2.1288.1	List of openflow Ports to switch interface.

2.1288.1 Entry

intf	*interface name*	Switch interface.
mirror	*boolean*	mirror destination.
port	*integer*	OpenFlow port.

2.1289 show openflow profiles

tables	*list of OpenFlowTableProfile* see 2.1289.1	Table profiles.

2.1289.1 OpenFlowTableProfile

action	*OpenFlowTableProfile-Action* see 2.1289.1.1	Actions.
match	*OpenFlowTableProfile-Match* see 2.1289.1.2	Match conditions.
numFlowEntries	*integer*	Table size entries.
profile	*string*	Table profile.
wildcardMatch	*OpenFlowTableProfile-Match* see 2.1289.1.2	Wildcard match conditions.

2.1289.1.1 OpenFlowTableProfileAction

egrMirrorInterfaces	*boolean*	Copy egress to mirror destination interfaces.
icmpCode **	*boolean*	Set ICMP code. **Since: 4.23.1
icmpType **	*boolean*	Set ICMP type. **Since: 4.23.1
ingrMirrorInterfaces	*boolean*	Copy ingress to mirror destination interfaces.
ipDst	*boolean*	Set destination IP address.
ipPortDst	*boolean*	Set TCP/UDP destination port.
ipPortSrc	*boolean*	Set TCP/UDP source port.
ipSrc	*boolean*	Set source IP address.
ipTos	*boolean*	Set Ipv4 Tos.
loopback	*boolean*	Output to ingress interface.
macDst	*boolean*	Set destination Mac address.
macSrc	*boolean*	Set source Mac address.
outInterfaces	*boolean*	Output interfaces.
outputAll	*boolean*	Flood to all interfaces except ingress.
outputController	*boolean*	Send to controller.
outputDrop	*boolean*	Drop packet.
outputFlood	*boolean*	Flood to all non-blocked interfaces except ingress.
outputLocal	*boolean*	Send to switch CPU.
outputNormal	*boolean*	Process normally.
outputQ	*boolean*	Output queue.
[setGroup]	*boolean*	Forward to group.
[ttlDec]	*boolean*	Decrement TTL.
vlan	*boolean*	Set Vlan ID.
vlanPCP	*boolean*	Set Vlan PCP.

2.1289.1.2 OpenFlowTableProfileMatch

ethType	*boolean*	Ethernet type.
icmpCode **	*boolean*	ICMP code. **Since: 4.23.1
icmpType **	*boolean*	ICMP type. **Since: 4.23.1
inInterface	*boolean*	Ingress interface.
ipDst	*boolean*	IPv4 destination address.
ipPortDst	*boolean*	TCP/UDP destination port.
ipPortSrc	*boolean*	TCP/UDP source port.
ipProto	*boolean*	IPv4 protocol.
ipSrc	*boolean*	IPv4 source address.
ipTos	*boolean*	IPv4 TOS.
macDst	*boolean*	Ethernet destination address.
macSrc	*boolean*	Ethernet source address.
vlan	*boolean*	Vlan ID.
vlanPCP	*boolean*	VLAN priority.

2.1290 show openflow queues

controllerQ	*list of OpenFlowQStats* see 2.1290.1	Controller Queues.
portQ	*list of PortQ* see 2.1290.2	Ports.

2.1290.1 OpenFlowQStats

ID	*integer*	Q id.
byteCount	*integer*	Byte count.
errCount	*integer*	Error count.
packetCount	*integer*	Packet count.

2.1290.2 PortQ

interface	*interface name*	Interface.
port	*integer*	Port ID.
stats	*list of OpenFlowQStats* see 2.1290.1	Port Queues.

2.1291 show openflow statistics

activityStats	*list of Stats* see 2.1291.1	Activity stats for 5 second intervals.

2.1291.1 Stats

endTime	*integer*	End time of this interval.
flowEntryCount	*integer*	Number of flows at the end of this interval.

flowModifications	*integer*	Number of messages modified by flows.
packetsDropped	*integer*	Packets dropped instead of being sent to controller.
packetsOut	*integer*	Number of packets.
packetsToController	*integer*	Packets sent to controller.

2.1292 show openstack (ip | ipv6) access-list [...]

see 2.62

2.1293 show openstack agent uuid

uuid	*string*	OpenStack agent UUID.

2.1294 show openstack config all-regions

regions	*table(string) = RegionConfig* see 2.1294.1	Collection of regions.

2.1294.1 RegionConfig

regionName	*string*	Region Name.
tenants	*table(string) = TenantConfig* see 2.1294.1.1	Collection of tenants within the region.

2.1294.1.1 TenantConfig

[tenantBaremetalInstances] **	*table(string) = BaremetalInstanceConfig* see 2.1294.1.1.1	Collection of baremetal instances for a tenant. **Since: 4.18.1
tenantId	*string*	Tenant Id.
tenantNetworks	*table(string) = NetworkConfig* see 2.1294.1.1.2	Collection of tenant networks for a tenant.
[tenantRouterInstances] **	*table(string) = RouterInstanceConfig* see 2.1294.1.1.3	Collection of Routers for a tenant. **Since: 4.18.1
tenantVmInstances	*table(string) = VmInstanceConfig* see 2.1294.1.1.4	Collection of VMs for a tenant.

2.1294.1.1.1 BaremetalInstanceConfig

baremetalHostId	*string*	Ironic node id on which Baremetal Instance executes.
baremetalInstanceId	*string*	Baremetal Instance Id.
baremetalPorts	*table(string) = PortConfig* see 2.1294.1.1.1.1	Collection of ports for a baremetal instance.

2.1294.1.1.1.1 PortConfig

[hosts] **	*list of string*	Hosts on which the port exists (used to provision vms and routers). **Since: 4.18.1
networkId	*string*	Tenant Network Id.
portId	*string*	Port Id.
[portVlanType] **	*enum: access | native | allowed*	Port Vlan Type. **Since: 4.18.1
segments **	*list of SegmentConfig* see 2.1294.1.1.1.2	Collection of segments in the network. **Since: 4.21.0
[switches] **	*table(string) = SwitchportList* see 2.1294.1.1.1.3	Collection of physical switchports for this logical port keyed by switch id (used to provision baremetal nodes). **Since: 4.18.1

2.1294.1.1.1.2 SegmentConfig

networkId	*string*	Network id associated with the segment.
segmentId	*string*	Segment id.
segmentationType	*enum: vlan | vxlan*	Segmentation Type.
segmentationTypeId	*integer*	VLAN/VxLAN ID.

2.1294.1.1.1.3 SwitchportList

switchports	*list of string*	Connected physical interfaces.

2.1294.1.1.2 NetworkConfig

[dynamicSegment] **	*list of SegmentConfig* see 2.1294.1.1.1.2	Collection of dynamic segments in the network. **Since: 4.18.1
networkId	*string*	Tenant Network Id.
networkName	*string*	Tenant network name.
segmentationType	*enum: vlan | vxlan*	Segmentation type of the first static segment.
segmentationTypeId	*integer*	VLAN/VxLAN ID of the first static segment.
shared	*boolean*	Indicates whether the network is a shared network or not.
staticSegment **	*list of SegmentConfig* see 2.1294.1.1.1.2	Collection of static segments in the network. **Since: 4.18.1

2.1294.1.1.3 RouterInstanceConfig

routerHostId	*string*	Host on which Router Instance executes.
routerInstanceId	*string*	Router Instance Id.
routerPorts	*table(string) = PortConfig* see 2.1294.1.1.1.1	Collection of ports for a Router.

2.1294.1.1.4 VmInstanceConfig

vmHostId	*string*	Host on which VM Instance executes.
vmInstanceId	*string*	VM Instance Id.
vmPorts	*table(string) = PortConfig* see 2.1294.1.1.1.1	Collection of ports for a VM.

2.1295 show openstack config networks vni mapping

vlanToVniMap	*table(string) = VlanToVniMap* see 2.1295.1	VLAN to VNI mapping keyed by OpenStack region names.

2.1295.1 VlanToVniMap

mapping	*table(string) = string*	Mapping from vlan range to vni range.

2.1296 show openstack config region REGION_NAME

tenants	*table(string) = TenantConfig* see 2.1294.1.1	Collection of tenants within the specified region.

2.1297 show openstack config region REGION_NAME timestamp

regionName	*string*	Region name.
regionTimestamp	*string*	OpenStack agent UUID.

2.1298 show openstack features

features	*table(string) = integer*	OpenStack Features.

2.1299 show openstack grace-period

gracePeriod	*floating point number*	Grace period in seconds for which the OpenStack agent waits for OpenStack region data.

2.1300 show openstack instances [...]

Could also be an instance of:
Vms 2.1300.1.2.4

[detail]	*boolean*	Display detailed information.
[hosts]	*table(string) = Host* see 2.1275.1	Collection of hosts in topology.
[neighbors]	*table(string) = DirectedEdge* see 2.1276.1	Collection of neighbors in topology.
regions	*table(string) = Region* see 2.1300.1	Collection of regions.

2.1300.1 Region

[lastSyncTime] **	*floating point number*	Last successful sync. **Since: 4.31.1
regionName	*string*	Region Name.
[serviceEndPoints]	*table(string) = ServiceEndPoint* see 2.1300.1.1	Collection of serviceendpoints within the region.
[syncInterval]	*floating point number*	ML2 Sync Interval.
[syncStatus]	*enum: syncComplete | syncInProgress | unknown | syncTimedout*	Sync Status.
tenants	*table(string) = Tenant* see 2.1300.1.2	Collection of tenants within the region.

2.1300.1.1 ServiceEndPoint

authUrl	*string*	Service Auth URL.
name	*string*	Service Name.
[tenantname]	*string*	Keystone admin tenant name.
[username]	*string*	Keystone admin user name.

2.1300.1.2 Tenant

[tenantBaremetalInstances] **	*table(string) = BaremetalInstance* see 2.1300.1.2.1	Collection of baremetal instances for a tenant. **Since: 4.18.1
tenantId	*string*	Tenant Id.
[tenantName]	*string*	Tenant Name.
tenantNetworks	*table(string) = Network* see 2.1300.1.2.2	Collection of tenant networks for a tenant.
tenantRouterInstances **	*table(string) = RouterInstance* see 2.1300.1.2.3	Collection of routers for a tenant. **Since: 4.18.1
tenantVmInstances	*table(string) = VmInstance* see 2.1300.1.2.4	Collection of VMs for a tenant.

2.1300.1.2.1 BaremetalInstance

baremetalHostId	*string*	Ironic node id on which Baremetal Instance executes.
baremetalInstanceId	*string*	Baremetal Instance Id.
[baremetalInstanceName]	*string*	Baremetal Instance Name.
baremetalPorts	*table(string) = Port* see 2.1300.1.2.1.1	Collection of ports for a Baremetal instance.

2.1300.1.2.1.1 Port

[hosts] **	*list of string*	Hosts on which the port exists (used to provision vms and routers). **Since: 4.18.1
networkId	*string*	Tenant Network Id.
portId	*string*	Port Id.
[portName]	*string*	Port Name.
[portVlanType] **	*enum: access | native | allowed*	Port Vlan Type. **Since: 4.18.1
segments **	*list of SegmentConfig* see 2.1294.1.1.1.2	List of segments the port is bound to. **Since: 4.21.3
[switches] **	*table(string) = SwitchportList* see 2.1294.1.1.1.3	Collection of physical switchports for this logical port keyed by switch id (used to provision baremetal nodes). **Since: 4.18.1

2.1300.1.2.2 Network

[dhcpInstances]	*table(string) = DhcpInstance* see 2.1300.1.2.2.2	Collection of DHCP instances.
mappedVni	*integer*	VNI to which the VLAN maps to.
[networkBaremetalInstancesIdName] **	*table(string) = BaremetalInstanceIdName* see 2.1300.1.2.2.1	Collection of baremetal instances for a tenant. **Since: 4.18.1
networkId	*string*	Tenant Network Id.
[networkName]	*string*	Tenant Network Name.
[networkVmInstancesIdName]	*table(string) = VmInstanceIdName* see 2.1300.1.2.2.3	Collection of VMs for a tenant.
segmentationType	*enum: vlan | vxlan*	Segmentation Type.
segmentationTypeId	*integer*	VLAN/VxLAN ID.
shared	*boolean*	Indicates whether the network is a shared network or not.

2.1300.1.2.2.1 BaremetalInstanceIdName

baremetalHostId	*string*	Ironic node id on which Baremetal Instance executes.
baremetalInstanceId	*string*	Baremetal Instance Id.
[baremetalInstanceName]	*string*	Baremetal Instance Name.

[switches]	*table(string) = SwitchportList* see 2.1294.1.1.1.3	Collection of physical switchports for this baremetal on a single network keyed by switch id.

2.1300.1.2.2.2 DhcpInstance

dhcpHostId	*string*	Host on which DHCP Instance executes.
dhcpInstanceId	*string*	DHCP Instance Id.
dhcpPorts	*table(string) = Port* see 2.1300.1.2.1.1	Collection of ports for a DHCP instance.

2.1300.1.2.2.3 VmInstanceIdName

[switches] **	*table(string) = SwitchportList* see 2.1294.1.1.1.3	Collection of physical switchports for this vm on a single network keyed by switch id. **Since: 4.18.1
vmHostId	*string*	Host on which VM Instance executes.
vmInstanceId	*string*	VM Instance Id.
[vmInstanceName]	*string*	VM Instance Name.

2.1300.1.2.3 RouterInstance

routerHostId	*string*	Host on which the router in placed on.
routerInstanceId	*string*	Router Instance Id.
routerInstanceName	*string*	Router Instance Name.
routerPorts	*table(string) = Port* see 2.1300.1.2.1.1	Collection of ports for a router instance.

2.1300.1.2.4 VmInstance

vmHostId	*string*	Host on which VM Instance executes.
vmInstanceId	*string*	VM Instance Id.
[vmInstanceName]	*string*	VM Instance Name.
vmPorts	*table(string) = Port* see 2.1300.1.2.1.1	Collection of ports for a VM.
[detail]	*boolean*	Display detailed information.
[hosts]	*table(string) = Host* see 2.1275.1	Collection of hosts in topology.
[neighbors]	*table(string) = DirectedEdge* see 2.1276.1	Collection of neighbors in topology.
regions	*table(string) = Region* see 2.1300.1	Collection of regions.

2.1301 show openstack networks [...]

[detail]	*boolean*	Display detailed information.
[hosts]	*table(string) = Host* see 2.1275.1	Collection of hosts in topology.

[neighbors]	*table(string) = DirectedEdge* see 2.1276.1	Collection of neighbors in topology.
regions	*table(string) = Region* see 2.1300.1	Collection of regions.

2.1302 show openstack physical-network [...]

[detail]	*boolean*	Display detailed information.
[hosts]	*table(string) = Host* see 2.1275.1	Collection of hosts in topology.
[neighbors]	*table(string) = DirectedEdge* see 2.1276.1	Collection of neighbors in topology.
regions	*table(string) = Region* see 2.1300.1	Collection of regions.
switches	*table(string) = Switch* see 2.1302.1	Collection of switches.

2.1302.1 Switch

hostname	*string*	Hostname configured by user.
interfaces	*table(string) = Interface* see 2.1302.1.1	Collection of interfaces on this switch.
switchId	*string*	Unique identifier (typically MAC-addr) for the switch.

2.1302.1.1 Interface

allowedVlans	*string*	Allowed list of trunk vlans on the interface.
name	*string*	Interface name (Ethernet1, Management1 etc).
[nativeVlan] **	*integer*	Native vlan on the interface. **Since: 4.18.1

2.1303 show openstack regions [...]

regions	*table(string) = Region* see 2.1300.1	Collection of regions.

2.1304 show openstack resource-pool vlan region REGION_NAME uuid

uuid	*string*	OpenStack VLAN assignment UUID.

2.1305 show openstack resource-pools [...]

physicalNetwork	*table(string) = PhysicalNetworkVlanPool* see 2.1305.1	Physical networks keyed by OpenStack region names.

2.1305.1 PhysicalNetworkVlanPool

vlanPool	*table(string) = VlanPool* see 2.1305.1.1	VLAN pools keyed by physical network names.

2.1305.1.1 VlanPool

allocatedVlans	*string*	VLANs that are being used by the OpenStack region.
assignedVlans	*string*	VLANs assigned to the OpenStack region.
availableVlans	*string*	VLANs that are unused in the OpenStack region'sVLAN assignment.

2.1306 show openstack segments { (host HOSTNAME) | (network NETWORK_NAME_OR_ID) | (port PORT_NAME_OR_ID) | (instance INSTANCE_NAME_OR_ID) | (region REGION_NAME) | (switch SWITCH) | (tenant TENANT_NAME_OR_ID) }

regions	*table(string) = RegionInstanceBinding* see 2.1306.1	Collection of instance in region.

2.1306.1 RegionInstanceBinding

instances	*table(string) = InstancePortBinding* see 2.1306.1.1	Collection of ports keyed by instance Id.

2.1306.1.1 InstancePortBinding

instanceId	*string*	Instance Id.
instanceName	*string*	Instance Name.
ports	*table(string) = PortBinding* see 2.1306.1.1.1	Collection of ports in instance keyed by portId.
tenantId	*string*	Tenant Id.
tenantName	*string*	Tenant name.

2.1306.1.1.1 PortBinding

[hosts]	*table(string) = NetworkSegment* see 2.1306.1.1.1.1	Hosts on which the port exists keyed by host name.
portId	*string*	Port Id.

[switches]	*table(string) = NetworkSegment* see 2.1306.1.1.1.1	Physical switches on which the port is connected to keyed by switch name and interface.

2.1306.1.1.1.1 NetworkSegment

networkId	*string*	Tenant Network Id.
networkName	*string*	Tenant network name.
segments	*list of SegmentConfig* see 2.1294.1.1.1.2	List of segments on the network.

2.1307 show openstack sync-timeout

regionSyncTimeout	*floating point number*	Timeout value in seconds for region syncronization.

2.1308 show openstack tenants [...]

regions	*table(string) = Region* see 2.1300.1	Collection of regions.

2.1309 show openstack vlans

switches	*table(string) = Switch* see 2.1302.1	Collection of switches and their vlan information.

2.1310 show openstack vms [...]

see 2.1300.1.2.4

2.1311 show ospfv3 [...]

vrfs	*table(string) = AddressFamilyOspf3MultiAfShowInstModel* see 2.1311.1	OSPFv3 per AF instance information for all VRFs.

2.1311.1 AddressFamilyOspf3MultiAfShowInstModel

addressFamily	*table(string) = Ospf3MultiAfShowInstModel* see 2.1311.1.1	OSPFv3 instance information indexed by address family.

2.1311.1.1 Ospf3MultiAfShowInstModel

abrInstance	*boolean*	This OSPFv3 instance is an Area Border Router.
[adjacencyExchangeStart-Threshold]	*integer*	Adjacency exchange-start threshold.
[areaList]	*table(IPv4 address) = Ospf3MultiAfShowInstArea-Model* see 2.1311.1.1.1	List of areas in this OSPFv3 instance.
asbrInstance	*boolean*	This OSPFv3 instance is an AS Border Router.
[ecmpMaximumNexthops]	*integer*	Maximum number of ECMP nexthops.
fipsStatus **	*boolean*	Indicates if FIPS mode is successfully enabled. **Since: 4.20.5
floodPacing **	*integer*	Flood packet pacing timer in msecs. **Since: 4.20.0
[gracefulRestartInfo] **	*OspfShowInstGraceful-RestartInfoModel* see 2.748.1.1.4	Graceful restart information. **Since: 4.18.0
[instanceId]	*integer*	OSPFv3 instance ID.
[lsaInformation]	*Ospf3ShowInstLsaThrottle-TimersInfoModel* see 2.869.1.1.4	LSA information.
lsaLimitInformation **	*Ospf3ShowInstLsaLimit-InfoModel* see 2.869.1.1.3	LSA limit information. **Since: 4.26.2
[maxMetricTypeInformation]	*Ospf3ShowInstMaxMetric-TypeInfoModel* see 2.869.1.1.5	Max metric type information.
[maxMetricUnsetInformation]	*Ospf3ShowInstMaxMetric-UnsetInfoModel* see 2.869.1.1.6	Max metric unset information.
numAreas	*integer*	Number of areas.
numBackboneNeighbors **	*integer*	Number of backbone neighbors. **Since: 4.20.5
numNeighbors	*integer*	Number of neighbors.
numNormalAreas	*integer*	Number of normal areas.
numNssaAreas	*integer*	Number of nssa areas.

numStubAreas	*integer*	Number of stub areas.
[primaryDomainId] **	*string*	Primary domain identifier. **Since: 4.32.0
[referenceBandwidth]	*integer*	Auto-cost reference bandwidth in Mbps.
[routerId]	*IPv4 address*	OSPFv3 Router id.
[secondaryDomainIds] **	*list of Ospf3SecondaryDomainId* see 2.869.1.1.1	List of secondary domain identifiers. **Since: 4.32.0
shutDown	*boolean*	Indicates if OSPFv3 instance is currently shut down.
[spfInformation]	*Ospf3ShowInstSpfThrottle-TimersInfoModel* see 2.869.1.1.7	SPF information.
[vrf]	*string*	VRF name.

2.1311.1.1.1 Ospf3MultiAfShowInstAreaModel

[areaAuthTypeInformation]	*Ospf3AreaAuthInfoModel* see 2.869.1.1.2.1	Area authentication information.
[areaFilterPrefixList] **	*string*	Area Filter prefix-list. **Since: 4.26.2
areaFiltersConfigured **	*boolean*	Area summary filters configured. **Since: 4.26.0
areaId	*IPv4 address*	OSPFv3 area ID.
areaType	*enum: normalArea | stubArea | nssaArea*	Type of area(normal/stub/nssa).
nssaTransState	*boolean*	Nssa translate always flag for area.
numIntf	*integer*	Number of interfaces in the area.
rangeList	*table(IPv4 or IPv6 address) = Ospf3MultiAfShowInst-AreaRangeModel* see 2.1311.1.1.1.1	List of address ranges in this OSPFv3 area.
spfCount **	*integer*	Area SPF count. **Since: 4.20.5

2.1311.1.1.1.1 Ospf3MultiAfShowInstAreaRangeModel

address	*IP address*	Area range address.
cost	*integer*	Area range cost.
[doNotAdvertise]	*boolean*	Do not advertise the area range. The cost value is invalid if this flag is set to true.
maskLen	*integer*	Area range mask length.

2.1312 show ospfv3 access-list [...]

see 2.62

2.1313 show ospfv3 border-routers [...]

vrfs	*table(string) = AddressFamilyOspf3MultiAfBorderRoutersInstance* see 2.1313.1	OSPFv3 per AF border routers information for all VRFs.

2.1313.1 AddressFamilyOspf3MultiAfBorderRoutersInstance

addressFamily	*table(string) = Ospf3MultiAfBorderRoutersInstance* see 2.1313.1.1	OSPFv3 instance information indexed by address family.

2.1313.1.1 Ospf3MultiAfBorderRoutersInstance

instanceId	*integer*	OSPFv3 instance identifier.
ospf3BorderRouterEntries	*table(IPv4 address) = Ospf3BorderRoutersEntry* see 2.871.1.1.1	Dictionary of OSPFv3 border router entries indexed by area-id.
vrf	*string*	VRF name.

2.1314 show ospfv3 counters [...]

vrfs	*table(string) = AddressFamilyOspf3-CountersInstance* see 2.1314.1	OSPFv3 Counters.

2.1314.1 AddressFamilyOspf3CountersInstance

addressFamily	*table(string) = Ospf3CountersInstance* see 2.1314.1.1	OSPFv3 instance information indexed by address family.

2.1314.1.1 Ospf3CountersInstance

[lastResetTime]	*floating point number*	UTC timestamp of last counters reset.
lsaTypeCounters	*table(string) = Ospf3CountersLsaEntry* see 2.1314.1.1.1	Dictionary of LSA type counters keyed by counter name.
selfOriginatedLsaReceived	*integer*	Number of self-originated LSAs received.
selfOriginatedLsaReceived-Deleted	*integer*	Number of self-originated LSAs received and deleted.
selfOriginatedLsaReceived-Updated	*integer*	Number of self-originated LSAs received and updated.
spfCount	*integer*	Number of SPF runs.

2.1314.1.1.1 Ospf3CountersLsaEntry

numAsex	*integer*	AS-External LSAs.
numGrc	*integer*	Grace LSAs.
numIap	*integer*	Inter-Area Prefix LSAs.
numIar	*integer*	Inter-Area Router LSAs.
numLink	*integer*	Link LSAs.
numNap	*integer*	Intra-Area Prefix LSAs.
numNetwork	*integer*	Network LSAs.
numNssa	*integer*	NSSA LSAs.
numRouter	*integer*	Router LSAs.

2.1315 show ospfv3 counters interface [...]

vrfs	*table(string) = AddressFamilyOspf3-CountersInterface* see 2.1315.1	OSPFv3 Interface Counters.

2.1315.1 AddressFamilyOspf3CountersInterface

addressFamily	*table(string) = Ospf3CountersInterface* see 2.1315.1.1	OSPFv3 instance information indexed by address family.

2.1315.1.1 Ospf3CountersInterface

interfaces	*table(string) = Ospf3CountersInterfaceEntry* see 2.1315.1.1.1	Dictionary of OSPFv3 interfaces indexed by the interface name.

2.1315.1.1.1 Ospf3CountersInterfaceEntry

delayedLsAcksSent	*integer*	Number of delayed LS acknowledgements sent.
[lastResetTime]	*floating point number*	UTC timestamp of the last time counters were reset.
lsAcksReceived	*integer*	Number of LS acknowledgements received.
lsUpdatesInFloodQueue	*integer*	Number of LS updates currently in the flood queue.
multicastLsUpdatesSent	*integer*	Number of multicast LS updates sent.

2.1316 show ospfv3 counters neighbor [...]

vrfs	*table(string) = AddressFamilyOspf3MultiAfCountersNeighor* see 2.1316.1	OSPFv3 Neighbor Counters.

2.1316.1 AddressFamilyOspf3MultiAfCountersNeighor

addressFamily	*table(string) = Ospf3MultiAfCountersNeighor* see 2.1316.1.1	OSPFv3 instance information indexed by address family.

2.1316.1.1 Ospf3MultiAfCountersNeighor

instanceId	*integer*	Instance ID.
neighborCounterEntries	*list of Ospf3CountersNeighborEntry* see 2.1316.1.1.1	List of neighbor-level counter entries.
vrf	*string*	VRF name.

2.1316.1.1.1 Ospf3CountersNeighborEntry

databaseDescriptionReceived	*integer*	Number of database description packets received.
databaseDescriptionSent	*integer*	Number of database description packets sent.
floodScopeMismatch	*integer*	Number of dropped LSAs due to an AS-external type LSA being received in a stub area.
interfaceName	*string*	Name of interface connected to neighbor.
invalidChecksum	*integer*	Number of dropped LSAs due to invalid checksum.
[lastResetTime]	*floating point number*	UTC timestamp of the last time counters were reset.
lsAcknowledgementSent	*integer*	Number of LS acknowledgement packets sent.
lsRequestReceived	*integer*	Number of LS request packets received.
lsRequestSentDueTo-Retransmission	*integer*	Number of LS request packets sent due to retransmission.
lsRequestsInRequestTree	*integer*	Number of LS requests in request tree.
lsUpdateSentDueToLsRequest	*integer*	Number of LS update packets sent due to receiving LS requests.
lsUpdateSentDueToOldLsa-Received	*integer*	Number of LS update packets sent due to receiving old LSAs.
lsUpdateSentDueTo-Retransmission	*integer*	Number of LS update packets sent due to retransmission.
lsUpdatesInRetransmission-List	*integer*	Number of LS updates in retransmission list.
multicastLsAcknowledgement-Received	*integer*	Number of multicast LS acknowledgement packets received.

multicastLsUpdateReceived	*integer*	Number of multicast LS update packets received.
neighborLinkLocalAddress	*IP address*	OSPFv3 neighbor link local address.
neighborRouterId	*IPv4 address*	OSPFv3 neighbor router identifier.
neighborStateChanges	*integer*	Number of neighbor state changes.
newCopyTooQuick	*integer*	Number of dropped LSAs due to LSA arriving before its scheduled next receive time.
newLsRequestSent	*integer*	Number of new LS request packets sent.
prefixLenBig	*integer*	Number of dropped LSAs due to the prefix length of the received LSA being greater than AF mask.
prefixLenInvalid	*integer*	Number of dropped LSAs due to the LSA received whose length of the prefix header was less than (packet's prefix length + length of empty prefix packet).
prefixLenSmall	*integer*	Number of dropped LSAs due to the prefix length of received LSA being less than minimum prefix length.
prefixScopeMismatch	*integer*	Number of dropped LSAs due to the prefix address scope of received LSA not sitelocal or global (only for IPv6 address family).
rtrIdZero	*integer*	Number of dropped LSAs due to the advertising router id of recieved LSA being zero.
type7InNonNssa	*integer*	Number of dropped LSAs due to an NSSA type LSA being received in a non-NSSA area.
unicastLsAcknowledgement-Received	*integer*	Number of unicast LS acknowledgment packets received.
unicastLsUpdateReceived	*integer*	Number of unicast LS update packets received.
unknownLsType	*integer*	Number of dropped LSAs due to an unknown LSA with U-bit set being received in a stub area.
unknownLsaReceived	*integer*	Number of unknown LSAs received.

2.1317 show ospfv3 database [...]

vrfs	*table(string) = AddressFamilyOspf3MultiAfDatabaseInstance* see 2.1317.1	OSPFv3 per AF database information for all VRFs.

2.1317.1 AddressFamilyOspf3MultiAfDatabaseInstance

addressFamily	*table(string) = Ospf3MultiAfDatabaseInstance* see 2.1317.1.1	OSPFv3 instance information indexed by address family.

2.1317.1.1 Ospf3MultiAfDatabaseInstance

instanceId	*integer*	OSPFv3 instance ID.
ospf3AreaEntries	*table(IPv4 address) = Ospf3AreaModel* see 2.872.1.1.1	A mapping between an Area and its LSA list.
ospf3AsLsas	*list of Ospf3Lsa* see 2.872.1.1.1.1	List of LSAs with AS scope.
ospf3InterfaceEntries	*table(string) = Ospf3InterfaceModel* see 2.872.1.1.2	A mapping between an Interface and its LSA list.
shutdown **	*boolean*	OSPFv3 instance is currently shut down. **Since: 4.23.0

2.1318 show ospfv3 database database-summary [...]

vrfs	*table(string) = AddressFamilyOspf3MultiAfDatabaseSummary* see 2.1318.1	OSPFv3 per AF database summary information for all VRFs.

2.1318.1 AddressFamilyOspf3MultiAfDatabaseSummary

addressFamily	*table(string) = Ospf3MultiAfDatabaseSummary* see 2.1318.1.1	OSPFv3 instance information indexed by address family.

2.1318.1.1 Ospf3MultiAfDatabaseSummary

areaId	*IP address*	Area identifier.
instanceId	*integer*	Instance ID.
numAsex	*integer*	Number of AS-external LSAs.
numGrace	*integer*	Number of Grace LSAs.
numInterPfx	*integer*	Number of Inter Area Prefix LSAs.
numInterRtr	*integer*	Number of Inter Area Router LSAs.
numIntraPfx	*integer*	Number of Intra-Area Prefix LSAs.
numLink	*integer*	Number of Link LSAs.
numNetwork	*integer*	Number of Network LSAs.
numNssa	*integer*	Number of type-7 NSSA LSAs.
numRouter	*integer*	Number of Router LSAs.
vrf	*string*	VRF name.

2.1319 show ospfv3 interface [...]

vrfs	*table(string) = AddressFamilyOspf3MultiAfInterface* see 2.1319.1	OSPFv3 per AF interface information for all VRFs.

2.1319.1 AddressFamilyOspf3MultiAfInterface

addressFamily	*table(string) = Ospf3MultiAfInterface* see 2.1319.1.1	OSPFv3 instance information indexed by address family.

2.1319.1.1 Ospf3MultiAfInterface

interfaces	*table(string) = Ospf3InterfaceEntry* see 2.874.1.1.1	Dictionary of OSPFv3 interfaces indexed by the interface name.

2.1320 show ospfv3 ipv6 sham-link [...]

see 2.1319

2.1321 show ospfv3 ipv6 sham-link route [...]

revision 4

see 2.773

2.1322 show ospfv3 lsa-log [...]

vrfs	*table(string) = AddressFamilyOspf3MultiAfLsaLogInst* see 2.1322.1	OSPFv3 per AF Lsa Log for all VRFs.

2.1322.1 AddressFamilyOspf3MultiAfLsaLogInst

addressFamily	*table(string) = Ospf3MultiAfLsaLogInst* see 2.1322.1.1	OSPFv3 instance information indexed by address family.

2.1322.1.1 Ospf3MultiAfLsaLogInst

instanceId	*integer*	Private attribute for instance identifier.
ospf3LsaLogEntries	*list of Ospf3LsaLogEntry* see 2.875.1.1.1	List of LSA log entries.
[routerId]	*IPv4 address*	OSPFv3 router identifier.
shutdown **	*boolean*	OSPFv3 instance is currently shut down. **Since: 4.23.0

2.1323 show ospfv3 neighbor [...]

vrfs	*table(string) = AddressFamilyOspf3MultiAfNeighborsInstance* see 2.1323.1	OSPFv3 per AF neighbor information for all VRFs.

2.1323.1 AddressFamilyOspf3MultiAfNeighborsInstance

addressFamily	*table(string) = Ospf3MultiAfNeighborsInstance* see 2.1323.1.1	OSPFv3 instance information indexed by address family.

2.1323.1.1 Ospf3MultiAfNeighborsInstance

instanceId	*integer*	OSPFv3 instance ID.
ospf3NeighborEntries	*list of Ospf3NeighborsEntry* see 2.876.1.1.1	List of OSPFv3 neighbor entries.

2.1324 show ospfv3 request-list [...]

vrfs	*table(string) = AddressFamilyOspf3MultiAfLsaRequestList* see 2.1324.1	OSPFv3 AF LSA request list information for all VRFs.

2.1324.1 AddressFamilyOspf3MultiAfLsaRequestList

addressFamily	*table(string) = Ospf3MultiAfLsaRequestList* see 2.1324.1.1	OSPFv3 instance information indexed by address family.

2.1324.1.1 Ospf3MultiAfLsaRequestList

instanceId	*integer*	OSPFv3 instance identifier.
neighbors	*table(IPv4 address) = Ospf3LsaRequestInstance* see 2.877.1.1.1	Dictionary of request keyed by neighbor router ID.

2.1325 show ospfv3 retransmission-list [...]

vrfs	*table(string) = AddressFamilyOspf3MultiAfLsaRetransmissionList* see 2.1325.1	OSPFv3 per AF LSA retransmission information for all VRFs.

2.1325.1 AddressFamilyOspf3MultiAfLsaRetransmissionList

addressFamily	*table(string) = Ospf3MultiAfLsaRetransmissionList* see 2.1325.1.1	OSPFv3 instance information indexed by address family.

2.1325.1.1 Ospf3MultiAfLsaRetransmissionList

instanceId	*integer*	OSPFv3 instance identifier.
neighbors	*table(IPv4 address) = Ospf3LsaRetransmissionInstance* see 2.878.1.1.1	Dictionary of retransmission list keyed by neighbor router ID.

2.1326 show ospfv3 spf-log [...]

vrfs	*table(string) = AddressFamilyOspf3MultiAfSpfLogInst* see 2.1326.1	OSPFv3 per AF SPF Log for all VRFs.

2.1326.1 AddressFamilyOspf3MultiAfSpfLogInst

addressFamily	*table(string) = Ospf3MultiAfSpfLogInst* see 2.1326.1.1	OSPFv3 instance information indexed by address family.

2.1326.1.1 Ospf3MultiAfSpfLogInst

instanceId	*integer*	Private attribute for instance identifier.
ospf3SpfLogEntries	*list of Ospf3SpfLogEntry* see 2.879.1.1.1	OSPFv3 SPF Log Entries.
[routerId]	*IPv4 address*	OSPFv3 router identifier.
shutdown **	*boolean*	OSPFv3 instance is currently shut down. **Since: 4.23.0

2.1327 show p4-runtime

revision 2

authzEnabled	*boolean*	P4Runtime Authz is enabled.
[devices]	*table(string) = P4RtDeviceStatusEntry* see 2.1327.1	P4Runtime device status entries keyed by device name.
enabled	*boolean*	P4Runtime server is enabled.
lastServiceStartTimeStamp	*floating point number*	Timestamp of last gRPC service start.
numClients	*integer*	Number of P4Runtime client connections.
[transport]	*P4RtTransport* see 2.1327.2	P4Runtime server transport status.

2.1327.1 P4RtDeviceStatusEntry

deviceId	*integer*	P4Runtime device ID.
deviceName	*string*	Device name.
[primaryElectionId]	*P4RuntimeElectionId* see 2.1327.1.1	Primary election ID.

2.1327.1.1 P4RuntimeElectionId

high	*integer*	High 64 bits of the 128-bit election ID.
low	*integer*	Low 64 bits of the 128-bit election ID.

2.1327.2 P4RtTransport

accountingRequests **	*boolean*	P4Runtime RPC accounting requests is enabled. **Since: 4.33.1
authnUsernamePriority	*list of string*	Authentication username extraction priority.
port	*integer*	The port this server is listening on.
[sslProfile]	*string*	SSL Profile.
vrfName	*string*	The VRF this server is listening in.

2.1328 show p4-runtime device

[devices]	*table(string) = P4RtDeviceStatusEntryDetail* see 2.1328.1	P4Runtime device status entries keyed by name.

2.1328.1 P4RtDeviceStatusEntryDetail

deviceId	*integer*	P4Runtime device ID.
deviceName	*string*	Device name.
packetMetadata	*list of P4RtControllerPktMetadataEntry* see 2.1328.1.1	Packet metatadatas received.

primaryElectionId	*P4RuntimeElectionId* see 2.1327.1.1	Primary election ID.
writeRpcReceived	*boolean*	Write RPC request received.

2.1328.1.1 P4RtControllerPktMetadataEntry

bitWidth	*integer*	Bit width of the metadata.
messageType	*string*	Type of Message containing the metadata.
metadataId	*integer*	Metadata ID.
name	*string*	Name of the metadata.

2.1329 show p4-runtime device counters packet-io

devicesCounter	*table(string) = P4RtDeviceCounterEntry* see 2.1329.1	A mapping of P4Runtime devices to its packet IO counters.

2.1329.1 P4RtDeviceCounterEntry

packetIn	*integer*	Number of PacketIn responses sent.
packetOut	*integer*	Number of PacketOut requests received.

2.1330 show patch panel [...]

revision 2

patches	*table(string) = Patch* see 2.1330.1	Maps patch names to their respective configuration and operational state.

2.1330.1 Patch

connectors	*table(string) = Connector* see 2.1330.1.1	Maps connector names to their respective configuration.
[lastStatusChange] **	*floating point number*	Time of last time patch state changed. **Since: 4.27.2
status	*enum: partiallyUp | down | up | unprogrammed | standby | adminDown | cliConflict*	Patch status. Admin down - Patch disabled Down - Patch connectors not ready Cli conflict - Patch configuration is invalid Standby - Patch configured but on standby Unprogrammed - Patch configured but not programmed in hardware Up - Patch configured and installed Partially up - Patch configured but only partially installed.

2.1330.1.1 Connector

[alternatives] **	*table(string) = LdpPseudowireConnectorInfo* see 2.1330.1.1.3	a mapping of pwName to ldpPseudowireInfo. **Since: 4.28.0
[bgpPseudowireConnectorInfo]	*BgpPseudowireConnector* see 2.1330.1.1.1	BGP pseudowire connector information.
connType	*enum: ldp | tagged | mplsStatic | bgp | port*	Connector type. tagged - Local interface delimited by an 802.1Q tag value port - Local interface not delimited by 802.1Q tag values ldp - LDP pseudowire bgp - BGP pseudowire.
[ldpPseudowireConnectorInfo]	*LdpPseudowireConnector* see 2.1330.1.1.2	LDP pseudowire connector information.
[mplsStaticPseudowireConnectorInfo] **	*MplsStaticPseudowireConnector* see 2.1330.1.1.4	MPLS static pseudowire connector information. **Since: 4.30.1
[portConnectorInfo]	*PortConnector* see 2.1330.1.1.5	Port connector information.

status	*enum: unknown* | *disabledByPw* | *decapConnInfoMissing* | *decapHwProgramming-Failed* | *cliConflict* | *encapHwFec-Unprogrammed* | *noTunnelRib* | *hasTaggedIntf* | *down* | *mtuMismatch* | *noTunnel* | *noPeerLabel* | *noLocalEnd* | *encapHwProgramming-Failed* | *partiallyUp* | *unsupportedTunnelMode* | *up* | *noLocalMapping* | *adminDown* | *noAdPerESRoute* | *cliIncomplete* | *pwNotForwardingRemote* | *waitingForVlanId* | *neighborEvpn* | *encapConnInfoMissing* | *encapInvalidConnConfig* | *decapInvalidConnConfig* | *intfMode* | *noRemoteEnd* | *connectorUnprogrammed* | *unprogrammed* | *standby* | *disabledByPwLacpStandby* | *pwTypeMismatch* | *controlWordMismatch* | *cannotAllocateVlanId*	Connector status.
[taggedConnectorInfo]	*TaggedConnector* see 2.1330.1.1.6	Tagged connector information.

2.1330.1.1.1 BgpPseudowireConnector

[color] **	*integer*	Pseudowire color. **Since: 4.30.2
[flowLabelUsed]	*enum: disabled* | *both* | *receive* | *transmit*	Flow label used.
[localConfig]	*BgpPseudowireLocalConfig* see 2.1330.1.1.1.1	Local BGP pseudowire config.
[neighborConfigs]	*table(IPv4 or IPv6 address) = BgpPseudowireNeighbor-Config* see 2.1330.1.1.1.2	BGP neighbors' pseudowire configs.
[pwName]	*string*	BGP VPWS pseudowire name.
[qosMapName]	*string*	QoS map name.
[qosMapType]	*enum: cosToTc* | *dscpToTc*	QoS map type.
[vpwsName]	*string*	BGP VPWS instance name.
[vpwsType]	*enum: port* | *vlan* | *fxc*	EVPN VPWS type. port - port-based vlan - VLAN-based fxc - flexible cross connect.

2.1330.1.1.1.1 BgpPseudowireLocalConfig

[controlWord]	*boolean*	Control word used.
[label]	*integer*	Pseudowire Label.
[mtu]	*integer*	Maximum transmission unit.

2.1330.1.1.1.2 BgpPseudowireNeighborConfig

[color] **	*integer*	Pseudowire color. **Since: 4.30.2
[controlWord]	*boolean*	Control word used.
[label]	*integer*	Pseudowire label.
[mtu]	*integer*	Maximum transmission unit.
[status] **	*enum: standby* | *up* | *unknown* | *mtuMismatch*	Neighbor status. **Since: 4.27.0
[tunnelIndex]	*integer*	Tunnel ending at this tunnel endpoint.
[tunnelType]	*enum: BGP LU Forwarding* | *maxTunnelType* | *IP-in-IP* | *MLDP P2MP* | *IS-IS SR IPv6* | *invalidTunnel* | *IS-IS SR IPv4* | *VXLAN VTEP Encap* | *IS-IS SRv6* | *Nexthop* | *Static MPLS* | *SR-TE Policy* | *SR-TE* | *OSPF SR* | *IS-IS SRv6 TI-LFA* | *IS-IS FlexAlgo* | *Static IPv6* | *Static MPLS Multicast* | *Nexthop Group* | *TI-LFA* | *LDP* | *RSVP LER SUB* | *SRv6 SR-TE SL* | *RSVP P2MP* | *RSVP LER* | *EosSdk sBFD* | *UDP* | *SRv6 Transport* | *EVPN VXLAN* | *VXLAN* | *RSVP FRR* | *IS-IS Remote TI-LFA* | *BGP LU* | *RSVP* | *IS-IS SR* | *Static* | *Static Interface*	Tunnel type.

2.1330.1.1.2 LdpPseudowireConnector

[color]	*integer*	Pseudowire color.
controlWord	*boolean*	Control word used.
[flowLabelUsed]	*enum: disabled* | *both* | *receive* | *transmit*	Flow label used.
[localConfig]	*LdpPseudowirePeerConfig* see 2.1330.1.1.2.3	Local LDP pseudowire config.
[name]	*string*	LDP pseudowire name.
[neighbor]	*IP address*	LDP neighbor.
[neighborConfig]	*LdpPseudowirePeerConfig* see 2.1330.1.1.2.3	LDP neighbor's pseudowire config.
[neighborFaultFlags]	*LdpPseudowireErrorFlags* see 2.1330.1.1.2.2	Neighbor pseudowire error flags.

neighborForwarding	*boolean*	Pseudowire forwarding traffic.
[pseudowireId]	*integer*	Pseudowire ID.
pseudowireType	*enum: pwTypeWildcard | pwType5 | pwTypeNone | pwType4*	Pseudowire type.
[qosMapName]	*string*	QoS map name.
[qosMapType]	*enum: cosToTc | dscpToTc*	QoS map type.
[tunnels]	*list of TunnelInfo* see 2.1330.1.1.2.1	List of resolving tunnels for this peer.

2.1330.1.1.2.1 TunnelInfo

[color]	*integer*	Tunnel color.
tunnelIndex	*integer*	Tunnel index.
tunnelType	*enum: BGP LU Forwarding | maxTunnelType | IP-in-IP | MLDP P2MP | IS-IS SR IPv6 | invalidTunnel | IS-IS SR IPv4 | VXLAN VTEP Encap | IS-IS SRv6 | Nexthop | Static MPLS | SR-TE Policy | SR-TE | OSPF SR | IS-IS SRv6 TI-LFA | IS-IS FlexAlgo | Static IPv6 | Static MPLS Multicast | Nexthop Group | TI-LFA | LDP | RSVP LER SUB | SRv6 SR-TE SL | RSVP P2MP | RSVP LER | EosSdk sBFD | UDP | SRv6 Transport | EVPN VXLAN | VXLAN | RSVP FRR | IS-IS Remote TI-LFA | BGP LU | RSVP | IS-IS SR | Static | Static Interface*	Tunnel type.

2.1330.1.1.2.2 LdpPseudowireErrorFlags

[etInFault]	*boolean*	Ethernet receive fault.
[etOutFault]	*boolean*	Ethernet transmit fault.
[notForwarding]	*boolean*	Pseudowire not forwarding (other reason).
[tunInFault]	*boolean*	Tunnel receive fault.
[tunOutFault]	*boolean*	Tunnel transmit fault.

2.1330.1.1.2.3 LdpPseudowirePeerConfig

[controlWord] **	*boolean*	Control Word Used. **Since: 4.31.2
[dot1qTagRequested]	*integer*	802.1Q VLAN requested.
[flowLabelCapability]	*enum: disabled | both | receive | transmit*	Flow label config.

[groupId]	*integer*	Group ID.
[intfDescription]	*string*	Interface description.
[label]	*integer*	Pseudowire Label.
[mtu]	*integer*	Maximum transmission unit.
[vccvCcTypes]	*integer*	Supported VCCV CC types.
[vccvCvTypes]	*integer*	Supported VCCV CV types.

2.1330.1.1.3 LdpPseudowireConnectorInfo

[active]	*boolean*	Current active pseudowire.
[alternate]	*boolean*	Indicate pseudowire is alternate or primary.
[color]	*integer*	Pseudowire color.
[neighbor]	*IP address*	LDP neighbor.
[pseudowireId]	*integer*	Pseudowire ID.
status	*enum: unknown* | *disabledByPw* | *decapConnInfoMissing* | *decapHwProgramming-Failed* | *cliConflict* | *encapHwFec-Unprogrammed* | *noTunnelRib* | *hasTaggedIntf* | *down* | *mtuMismatch* | *noTunnel* | *noPeerLabel* | *noLocalEnd* | *encapHwProgramming-Failed* | *partiallyUp* | *unsupportedTunnelMode* | *up* | *noLocalMapping* | *adminDown* | *noAdPerESRoute* | *cliIncomplete* | *pwNotForwardingRemote* | *waitingForVlanId* | *neighborEvpn* | *encapConnInfoMissing* | *encapInvalidConnConfig* | *decapInvalidConnConfig* | *intfMode* | *noRemoteEnd* | *connectorUnprogrammed* | *unprogrammed* | *standby* | *disabledByPwLacpStandby* | *pwTypeMismatch* | *controlWordMismatch* | *cannotAllocateVlanId*	ldp pseudowire connector status.

2.1330.1.1.4 MplsStaticPseudowireConnector

[controlWord] **	*boolean*	Indicate whether to use control word. **Since: 4.31.0
[localLabel]	*integer*	Local MPLS label used.
[name]	*string*	MPLS static pseudowire name.

[neighborLabel]	*integer*	Neighbor MPLS label used.
[nexthopGroupName] **	*string*	MPLS static nexthopGroup transport. **Since: 4.33.2
[transportIntf]	*interface name*	MPLS static transport interface.
[tunnelIntfMode] **	*enum: ipSecEncap* | *srv6TunnelEncap* | *gueEncap* | *ipSecGreEncap* | *mplsEncap* | *combinedEncap* | *dsfEncap* | *vxlanEncap* | *greEncap* | *invalidEncap* | *ipInIpEncap*	Transport interface tunnel mode. **Since: 4.30.2

2.1330.1.1.5 PortConnector

[errorDisableTrigger] **	*enum: suppressedBy-AlternateConnector* | *remoteFailure* | *remoteNotForwarding* | *suppressedByNoError-Disable* | *standbyState* | *none*	Configuration which will error disable the interface. **Since: 4.28.2
[errorDisableTriggers] **	*list of string*	List of error disable triggers configured for this interface. **Since: 4.33.2
interface	*interface name*	Local interface.

2.1330.1.1.6 TaggedConnector

dot1qTag	*integer*	802.1Q Tag.
interface	*interface name*	Local interface.

2.1331 show patch panel forwarding

revision 3

labelForwardingInfoTable	*LabelForwardingInfoTable* see 2.1331.1	Label forwarding information table.
portForwardingInfoTable	*PortForwardingInfoTable* see 2.1331.2	Port forwarding information table.
taggedForwardingInfoTable	*TaggedForwardingInfoTable* see 2.1331.3	Tagged forwarding information table.

2.1331.1 LabelForwardingInfoTable

labelForwardingInfos	*table(numeric string) = LabelForwardingInfo* see 2.1331.1.1	a mapping of decap labels to Label forwarding information entries.

2.1331.1.1 LabelForwardingInfo

[flowLabel]	*string*	Flow label used.
label	*integer*	Pseudowire decap label.
outConnInfo	*ForwardingConnectorInfo* see 2.1331.1.1.1	(deprecated; use outConnectors).
outConnectors	*list of ForwardingConnectorInfo* see 2.1331.1.1.1	Out connectors.
patch	*string*	Patch name.
pseudowireType	*enum: pwTypeWildcard | pwType5 | pwTypeNone | pwType4*	Pseudowire type.
source	*enum: MPLS static | EVPN | LDP*	Pseudowire source.

status	*enum: unknown* | *disabledByPw* | *decapConnInfoMissing* | *decapHwProgramming-Failed* | *cliConflict* | *encapHwFec-Unprogrammed* | *noTunnelRib* | *hasTaggedIntf* | *down* | *mtuMismatch* | *noTunnel* | *noPeerLabel* | *noLocalEnd* | *encapHwProgramming-Failed* | *partiallyUp* | *unsupportedTunnelMode* | *up* | *noLocalMapping* | *adminDown* | *noAdPerESRoute* | *cliIncomplete* | *pwNotForwardingRemote* | *waitingForVlanId* | *neighborEvpn* | *encapConnInfoMissing* | *encapInvalidConnConfig* | *decapInvalidConnConfig* | *intfMode* | *noRemoteEnd* | *connectorUnprogrammed* | *unprogrammed* | *standby* | *disabledByPwLacpStandby* | *pwTypeMismatch* | *controlWordMismatch* | *cannotAllocateVlanId*	Connector status.

2.1331.1.1.1 ForwardingConnectorInfo

[labelConnFwdingInfo]	*LabelConnectorFwdingInfo* see 2.1331.1.1.1.1	Label connector forwarding information.
[portConnFwdingInfo]	*PortConnectorFwdingInfo* see 2.1331.1.1.1.3	Port connector forwarding information.
[taggedConnFwdingInfo]	*TaggedConnectorFwding-Info* see 2.1331.1.1.1.4	Tagged connector forwarding information.

2.1331.1.1.1.1 LabelConnectorFwdingInfo

peers	*table(IPv4 or IPv6 address) = LabelConnectorFwding-PeerInfo* see 2.1331.1.1.1.2	List of peers for this connector.

2.1331.1.1.1.2 LabelConnectorFwdingPeerInfo

[encapControlWord]	*boolean*	Control word used to encapsulate packets toward this peer.

[nexthopGroupName] **	*string*	Name of the nexthopGroup. **Since: 4.33.2
peerLabel	*integer*	Label received from the peer.
tunnels	*list of TunnelInfo* see 2.1330.1.1.2.1	List of resolving tunnels for this peer.

2.1331.1.1.1.3 PortConnectorFwdingInfo

[decapControlWord]	*boolean*	Control word used to decapsulate packets toward this AC.
interface	*interface name*	Local interface.

2.1331.1.1.1.4 TaggedConnectorFwdingInfo

[decapControlWord]	*boolean*	Control word used to decapsulate packets toward this AC.
dot1qVlan	*integer*	802.1Q VLAN.
interface	*interface name*	Local interface.

2.1331.2 PortForwardingInfoTable

portForwardingInfos	*table(string) = PortForwardingInfo* see 2.1331.2.1	A mapping of port connectors to connector forwarding information entries.

2.1331.2.1 PortForwardingInfo

[flowLabel]	*string*	Flow label used.
inConnInfo	*ForwardingConnectorInfo* see 2.1331.1.1.1	In connector.
outConnInfo	*ForwardingConnectorInfo* see 2.1331.1.1.1	Out connector.
patch	*string*	Patch name.
[pseudowireType]	*enum: pwTypeWildcard | pwType5 | pwTypeNone | pwType4*	Pseudowire type.
[source]	*enum: MPLS static | EVPN | LDP*	Pseudowire source.

status	*enum: unknown* | *disabledByPw* | *decapConnInfoMissing* | *decapHwProgramming-Failed* | *cliConflict* | *encapHwFec-Unprogrammed* | *noTunnelRib* | *hasTaggedIntf* | *down* | *mtuMismatch* | *noTunnel* | *noPeerLabel* | *noLocalEnd* | *encapHwProgramming-Failed* | *partiallyUp* | *unsupportedTunnelMode* | *up* | *noLocalMapping* | *adminDown* | *noAdPerESRoute* | *cliIncomplete* | *pwNotForwardingRemote* | *waitingForVlanId* | *neighborEvpn* | *encapConnInfoMissing* | *encapInvalidConnConfig* | *decapInvalidConnConfig* | *intfMode* | *noRemoteEnd* | *connectorUnprogrammed* | *unprogrammed* | *standby* | *disabledByPwLacpStandby* | *pwTypeMismatch* | *controlWordMismatch* | *cannotAllocateVlanId*	Connector status.

2.1331.3 TaggedForwardingInfoTable

taggedForwardingInfos	*table(string) = TaggedForwardingInfo* see 2.1331.3.1	A mapping of tagged connectors to connector forwarding information entries.

2.1331.3.1 TaggedForwardingInfo

[dot1qVlan]	*integer*	802.1Q VLAN.
[flowLabel]	*string*	Flow label used.
inConnInfo	*ForwardingConnectorInfo* see 2.1331.1.1.1	In connector.
outConnInfo	*ForwardingConnectorInfo* see 2.1331.1.1.1	Out connector.
patch	*string*	Patch name.
[pseudowireType]	*enum: pwTypeWildcard* | *pwType5* | *pwTypeNone* | *pwType4*	Pseudowire type.
[source]	*enum: MPLS static* | *EVPN* | *LDP*	Pseudowire source.

status	*enum: unknown* | *disabledByPw* | *decapConnInfoMissing* | *decapHwProgramming-Failed* | *cliConflict* | *encapHwFec-Unprogrammed* | *noTunnelRib* | *hasTaggedIntf* | *down* | *mtuMismatch* | *noTunnel* | *noPeerLabel* | *noLocalEnd* | *encapHwProgramming-Failed* | *partiallyUp* | *unsupportedTunnelMode* | *up* | *noLocalMapping* | *adminDown* | *noAdPerESRoute* | *cliIncomplete* | *pwNotForwardingRemote* | *waitingForVlanId* | *neighborEvpn* | *encapConnInfoMissing* | *encapInvalidConnConfig* | *decapInvalidConnConfig* | *intfMode* | *noRemoteEnd* | *connectorUnprogrammed* | *unprogrammed* | *standby* | *disabledByPwLacpStandby* | *pwTypeMismatch* | *controlWordMismatch* | *cannotAllocateVlanId*	Connector status.

2.1332 show patch panel summary

bgpVpwsCount	*table(string) = integer*	BGP EVPN VPWS patch count by status.
ldpCount	*table(string) = integer*	LDP patch count by status.
localCount	*table(string) = integer*	Local patch count by status.
mplsStaticCount **	*table(string) = integer*	MPLS static patch count by status. **Since: 4.30.1
patchCount	*integer*	Patch count.

2.1333 show path-selection application counters [...]

lbProfiles	*table(numeric string) = Dps.Cli.DpsLbCounters-Profiles* see 2.1333.1	A mapping of load-balance profile index to its counters.

2.1333.1 Dps.Cli.DpsLbCountersProfiles

appProfile	*string*	Name of the application profile.
flows	*integer*	Number of flows for the application.

outBytes	*integer*	Number of out bytes for the application.
outPkts	*integer*	Number of out packets for the application.
pathGroups	*table(string) = Dps.Cli.-DpsLbCountersPathGroups* see 2.1333.1.1	A mapping of group name to its counters.
peerIp	*IP address*	Peer IP address of the ITS session.
peerName **	*string*	Name of the peer. **Since: 4.23.2
throughput	*floating point number*	Throughput in Mbps for the application.
vrf	*string*	Name of the VRF.

2.1333.1.1 Dps.Cli.DpsLbCountersPathGroups

paths	*table(numeric string) = Dps.Cli.DpsLbCounters-PathData* see 2.1333.1.1.1	A mapping of path index to its counters.

2.1333.1.1.1 Dps.Cli.DpsLbCountersPathData

flows	*integer*	Number of flows going through the path.
outBytes	*integer*	Number of bytes going via the path.
outPkts	*integer*	Number of packets going via the path.
throughput	*floating point number*	Throughput in Mbps of the path.

2.1334 show path-selection load-balance counters [...]

see 2.1333

2.1335 show path-selection mtu [...]

dpsPeers **	*table(IPv4 or IPv6 address) = DpsPeer* see 2.1335.1	A mapping of peer IP to peer path groups. **Since: 4.23.2

2.1335.1 DpsPeer

[avtRegionId] **	*integer*	Adaptive virtual topology region ID. **Since: 4.29.2
[avtSiteId] **	*integer*	Adaptive virtual topology site ID. **Since: 4.29.2
[avtZoneId] **	*integer*	Adaptive virtual topology zone ID. **Since: 4.29.2
dpsGroups	*table(string) = DpsGroup* see 2.1335.1.1	A mapping of group name to its paths.
peerName	*string*	Peer name.

2.1335.1.1 DpsGroup

dpsPaths	*table(string) = DpsPath* see 2.1335.1.1.1	A mapping of path name to its state.

2.1335.1.1.1 DpsPath

destination	*string*	Destination IP address of the path group.
[destinationPort] **	*integer*	Destination UDP port of the DPS path. **Since: 4.27.1
[destinationWanId] **	*integer*	Destination WAN ID of the DPS path. **Since: 4.27.1
[destinationWanIdPathGroup] **	*string*	Path group of the destination WAN ID of the DPS path. **Since: 4.32.1
dpsSessions **	*table(numeric string) = DpsSession* see 2.1335.1.1.1.1	A mapping of traffic class to DPS session. **Since: 4.23.2
[label] **	*integer*	Label value of the DPS path. **Since: 4.29.1
[localIntf] **	*interface name*	Local interface name of this path. **Since: 4.29.2
[mtu] **	*integer*	Path MTU. **Since: 4.27.2
[mtuConfigType] **	*enum: static | disabled | auto*	Type of MTU config. **Since: 4.27.2
[mtuDiscDueSecs] **	*integer*	MTU discovery due in secs. **Since: 4.27.2
[mtuDiscIntervalSecs] **	*integer*	MTU discovery interval in secs. **Since: 4.28.0
[mtuDiscTimeTakenMsecs] **	*floating point number*	MTU discovery time taken in msecs. **Since: 4.27.2

[mtuErrStateReason] **	*enum: path down event | response message timeout | none | mtu outside defined range*	MTU error state reason. **Since: 4.28.0
[mtuNumProbesRcvd] **	*integer*	Number of Probes received. **Since: 4.27.2
[mtuNumProbesSent] **	*integer*	Number of Probes sent. **Since: 4.27.2
[mtuNumReportReqRcvd] **	*integer*	Number of Report Requests received. **Since: 4.27.2
[mtuNumReportReqSent] **	*integer*	Number of Report Requests sent. **Since: 4.27.2
[mtuNumReportRespRcvd] **	*integer*	Number of Report Responses received. **Since: 4.27.2
[mtuNumReportRespSent] **	*integer*	Number of Report Responses sent. **Since: 4.27.2
[mtuNumReqProcErr] **	*integer*	Number of Request processing error. **Since: 4.27.2
[mtuNumRespProcErr] **	*integer*	Number of Reponse processing error. **Since: 4.27.2
[mtuState] **	*enum: done | probing | init | notApplicable | error*	MTU discovery state. **Since: 4.27.2
pathType **	*enum: static | dynamic*	Type of the path. **Since: 4.26.2
source	*string*	Source IP address of the path group.
[sourcePort] **	*integer*	Source UDP port of the DPS path. **Since: 4.27.1
[sourceWanId] **	*integer*	Source WAN ID of the DPS path. **Since: 4.27.1
[sourceWanIdPathGroup] **	*string*	Path group of the source WAN ID of the DPS path. **Since: 4.32.1
state	*enum: ipsecPending | routeStateInvalid | routeResolved | ipsecEstablished | ipsecProgrammed | routePending | arpPending*	Routing state of this path.

2.1335.1.1.1.1 DpsSession

active	*boolean*	The telemetry session state is active.
seconds	*integer*	Number of seconds the telemetry session has been in this state.

2.1336 show path-selection paths [...]

see 2.1335

2.1337 show path-selection paths export

[vtep]	*IP address*	VTEP IP address.
wans	*table(numeric string) = Dps.Cli.DpsExport* see 2.1337.1	A mapping of WAN ID to exported endpoint.

2.1337.1 Dps.Cli.DpsExport

intf	*interface name*	Local interface (deprecated; use pathGroups).
ipAddress	*IP address*	Exported IP address in the path group where the interface is configured (deprecated; use pathGroups).
ipSource	*enum: stun | intfpublic | interface*	Source of the IP address (deprecated; use pathGroups).
pathGroup	*string*	Path group name where the interface is configured (deprecated; use pathGroups).
pathGroups **	*table(string) = Dps.Cli.DpsPathGroupExport* see 2.1337.1.1	A mapping of path group name to its exported endpoints. **Since: 4.33.0
port	*integer*	Exported port number in the path group where the interface is configured (deprecated; use pathGroups).

2.1337.1.1 Dps.Cli.DpsPathGroupExport

intf	*interface name*	Local interface.
ipAddress	*IP address*	Exported IP address.
ipSource	*enum: stun | intfpublic | interface*	Source of the IP address.
port	*integer*	Exported port number.

2.1338 show pci

pciIds	*table(string) = PciErrorSum* see 2.1338.1	Summary of error counters for each PCI device.
switchs	*table(string) = integer*	Summary of smBus errors on PCIe switch.

2.1338.1 PciErrorSum

correctableErrors	*integer*	Correctable error counter.
fatalErrors	*integer*	Uncorrectable fatal error counter.
linkSpeed	*floating point number*	Current link speed of the PCI device in GT/s.
linkWidth	*integer*	Current link width of the PCI device.
name	*string*	PCI device name.
nonFatalErrors	*integer*	Uncorrectable non-fatal error counter.

2.1339 show pci detail

devices	*table(string) = PciDetailError* see 2.1339.1	Summary of pci device errors.

2.1339.1 PciDetailError

name	*string*	Name of pci device.
pciErrors	*table(string) = integer*	Error counts.
severity	*integer*	Uncorrectable errors severity.

2.1340 show pci errors rates

devices	*table(string) = PciErrorsStats* see 2.1340.1	Devices with recorded errors (a mapping of pciId to their stats).

2.1340.1 PciErrorsStats

errorStats	*table(string) = PciErrorStats* see 2.1340.1.1	Error stats (a mapping of error types to their stats).
name	*string*	PCI device name.

2.1340.1.1 PciErrorStats

masked	*boolean*	Denotes whether this error type is currently being masked.
units	*PciErrorStatsUnits* see 2.1340.1.1.1	List containing details of all units (from second to week).

2.1340.1.1.1 PciErrorStatsUnits

day	*PciErrorStatsUnit* see 2.1340.1.1.1.1	Unit containing details about number of errors per day.
hour	*PciErrorStatsUnit* see 2.1340.1.1.1.1	Unit containing details about number of errors per hour.
minute	*PciErrorStatsUnit* see 2.1340.1.1.1.1	Unit containing details about number of errors per minute.
second	*PciErrorStatsUnit* see 2.1340.1.1.1.1	Unit containing details about number of errors per second.
week	*PciErrorStatsUnit* see 2.1340.1.1.1.1	Unit containing details about number of errors per week.

2.1340.1.1.1.1 PciErrorStatsUnit

averagingPeriod	*integer*	Last number of seconds over which the estimation was made.
rate	*floating point number*	Error hits per time unit (errors/second = rate/unitSeconds).

unitSeconds	*integer*	Unit's name translated into number of seconds.

2.1341 show pci errors rates detail

devices	*table(string) = PciErrorsStatsDetail* see 2.1341.1	Devices with recorded errors (a mapping of pciId to their stats).

2.1341.1 PciErrorsStatsDetail

errorStats	*table(string) = PciErrorStatsDetail* see 2.1341.1.1	Error stats (a mapping of error types to their stats).
name	*string*	PCI device name.

2.1341.1.1 PciErrorStatsDetail

masked	*boolean*	Denotes whether this error type is currently being masked.
maskedEver	*boolean*	Denotes whether this error type has ever been masked.
maximumRatePerSecond	*floating point number*	Maximum error hits per second recorded since boot / clear pci.
maximumRateTimestamp	*floating point number*	UNIX timestamp when the maximumRatePerSecond occurred.
summary	*string*	Name of the unit that was dynamically selected as human-readable.
units	*PciErrorStatsUnits* see 2.1340.1.1.1	List containing details of all units (from second to week).

2.1342 show pci tree

[devices]	*table(string) = PciTreeNode* see 2.1342	PCI children of this device.

2.1343 show peer-filter [...]

peerFilters	*table(string) = PeerFilter* see 2.1343.1	Peer filters by name.

2.1343.1 PeerFilter

description	*list of string*	Peer filter description.
entries	*table(numeric string) = PeerFilterEntry* see 2.1343.1.1	Peer filter entries by sequence number.

2.1343.1.1 PeerFilterEntry

filterType	*enum: reject | accept*	Filter type.
matchRules	*PeerFilterMatchRules* see 2.1343.1.1.1	Match rules.

2.1343.1.1.1 PeerFilterMatchRules

[asRange]	*AsnRange* see 2.1343.1.1.1.1	BGP ASN range.

2.1343.1.1.1.1 AsnRange

[end]	*integer*	ASN range end.
start	*integer*	ASN range start.

2.1344 show phy transmitter equalization profile [...]

ports	*table(string) = PhyTxEqPort* see 2.1344.1	A mapping of transceiver ports to their lane tuning data.

2.1344.1 PhyTxEqPort

lanes	*table(numeric string) = PhyTxEqPortLane* see 2.1344.1.1	A mapping of transceiver lane numbers to their tuning profile configs.

2.1344.1.1 PhyTxEqPortLane

configured	*list of string*	Profiles that are currently configured.
operational	*string*	Profile that is currently operational.

2.1345 show pim (ipv4 | ipv6) anycast-rp [...]

see 2.778

2.1346 show pim (ipv4 | ipv6) bsr [...]

see 2.783

2.1347 show pim (ipv4 | ipv6) bsr counters [...]

see 2.784

2.1348 show pim (ipv4 | ipv6) bsr debug

see 2.785

2.1349 show pim (ipv4 | ipv6) bsr rp [...]

see 2.27

2.1350 show pim (ipv4 | ipv6) bsr rp-hash GROUP [...]

see 2.28

2.1351 show pim (ipv4 | ipv6) config-sanity anycast-rp [...]

downIntfs	*list of Interface name*	Anycast RP interfaces which are down.
notAnycastRPs	*list of IP address*	This RP address is not configured as anycast RP.
notCfgRPs	*list of IP address*	Anycast RPs not configured on the router.
notIntfCfgRPs	*list of IP address*	Anycast RP not configured on any interface.
notLoopback	*list of Interface name*	Anycast RP interfaces which are not loopback.
notRPs	*list of IP address*	Anycast RPs not configured as RP addresses.
routeCheck	*list of GenRouteCheck* see 2.1351.1	route check hints.

2.1351.1 GenRouteCheck

hintsFound	*integer*	number of hints found.
noRoute	*boolean*	No route to the prefix.
nodeType	*string*	Node type.
nonPimHop	*list of IP address*	Route via non-Pim hops.
nonPimIntf	*list of Interface name*	Route via non-Pim interface.
prefix	*IP address*	Route check for this prefix.

2.1352 show pim (ipv4 | ipv6) interface [...]

see 2.794

2.1353 show pim (ipv4 | ipv6) neighbor [...]

revision 2

see 2.795

2.1354 show pim (ipv4 | ipv6) neighbor bfd [...]

revision 2

see 2.796

2.1355 show pim (ipv4 | ipv6) register-source [...]

see 2.798

2.1356 show pim (ipv4 | ipv6) rp [...]

revision 2

see 2.799

2.1357 show pim (ipv4 | ipv6) rp-candidate [...]

see 2.800

2.1358 show pim evpn gateway dr [...]

`vlans`	*table(numeric string) = EvpnGatewayDr* see 2.1358.1	Mapping of VLAN to external gateway DR information.

2.1358.1 EvpnGatewayDr

`addr`	*IP address*	Address of Designated Router.
`[algorithm]` **	*enum: modulus | hrw | preference*	Algorithm used to elect DR. **Since: 4.27.1
`[remoteAddr]` **	*IP address*	Address of Designated Router for remote domain. **Since: 4.35.2
`[remoteAlgorithm]` **	*enum: modulus | hrw | preference*	Algorithm used to elect remote Domain DR. **Since: 4.35.2
`[remoteRole]` **	*enum: nonDr | dr*	Router role on this VLAN for remote Domain. **Since: 4.35.2
`role`	*enum: nonDr | dr*	Router role on this VLAN.

2.1359 show pim ipv4 sparse-mode non-dr drop-rules [...]

interfaces	*table(Interface name) = NonDrDropRuleInterface* see 2.1359.1	Map of interfaces for non DR install oifs feature.

2.1359.1 NonDrDropRuleInterface

[inactiveReason]	*enum: Drop rule programming timed out | Drop rule unprogramming failed on interface | Drop rule creation failed | Multicast routes forwarding | Drop rule unprogramming timed out | Interface is DR | Conflicting drop rule programmed on interface | Waiting for platform to program drop rule | Drop rule programming failed on interface*	Reason why state is inactive or error.
numRoutesForwarding	*integer*	Number of multicast routes forwarding on this interface.
numRoutesReadyToForward **	*integer*	Number of multicast routes ready to forward on this interface. **Since: 4.24.0
state	*enum: inactive | unprogramming | unprogrammed | programming | init | active | error*	Non-DR drop rule state for interface.

2.1360 show pim ipv6 sparse-mode join [...]

see 2.29

2.1361 show pim ipv6 sparse-mode route IP1 IP2 interface [...]

see 2.24

2.1362 show pim ipv6 sparse-mode route [...]

see 2.25

2.1363 show pim ipv6 sparse-mode route count [...]

see 2.26

2.1364 show pim ipv6 sparse-mode rp [...]

see 2.27

2.1365 show pim ipv6 sparse-mode rp hash GROUP [...]

see 2.28

2.1366 show pim protocol counters [...]

see 2.797

2.1367 show pim sparse-mode evpn cli membership [...]

`vlans`	*table(numeric string) = VlanMembership* see 2.1367.1	Map VLAN ID to per-VLAN group membership information.

2.1367.1 VlanMembership

`[groups]`	*table(IPv4 or IPv6 address) = GroupMembership* see 2.1367.1.1	Map group to source membership information.
`[vrfName]`	*string*	VRF name.

2.1367.1.1 GroupMembership

`[sources]`	*table(IPv4 or IPv6 address) = SourceMembership* see 2.1367.1.1.1	Map Source to membership information.

2.1367.1.1.1 SourceMembership

`[mode]`	*enum: include | none | exclude*	Membership mode.

2.1368 show pim sparse-mode evpn gateway [...]

`vrfs`	*table(string) = EvpnGatewayVrf* see 2.1368.1	Mapping of VRFs to their VLAN IDs.

2.1368.1 EvpnGatewayVrf

`vlan`	*integer*	Internal VLAN ID for this VRF.

2.1369 show pim sparse-mode evpn pim membership [...]

see 2.1367

2.1370 show pim sparse-mode pim evpn membership [...]

Could also be an instance of:
MembershipJoinStatusMlagPimsm 2.1370

vlans	*table(numeric string) = VlanMembership* see 2.1367.1	Map VLAN ID to per-VLAN group membership information.
vlans	*table(numeric string) = VlanMembership* see 2.1367.1	Map VLAN ID to per-VLAN group membership information.

2.1371 show platform (fap | arad) eci hardware-sync [...]

eciTimeSyncInfo	*table(string) = AradEciTimeSyncInfo* see 2.1371.1	Mapping of each Arad to its corresponding ECI TimeSync Information.

2.1371.1 AradEciTimeSyncInfo

latestCmicTod	*integer*	Latest CMIC ToD (in ns).
latestEciTod	*integer*	Latest ECI ToD (in ns).
numUpdates	*integer*	Number of ECI ToD updates received.
phase	*list of integer*	Last 4 phase differences of the ECI ToD (in ns).
state	*string*	State of Arad's ECI ToD.

2.1372 show platform (fap | arad) zuma [...]

zumaMappings	*table(string) = ZumaMapping* see 2.1372.1	A mapping between Arad names and their corresponding Zuma name and Microblaze index.

2.1372.1 ZumaMapping

microblazeIndex	*integer*	The microblaze index for this Arad.
zumaName	*string*	The name of the Zuma FPGA for this Arad.

2.1373 show platform (fap | arad) zuma detail [...]

zumasDetails	*table(string) = ZumaDetails* see 2.1373.1	A mapping between Zuma names and detailed information about those Zumas.

2.1373.1 ZumaDetails

aradsMicroblazeIndexes	*table(string) = integer*	A mapping between Arad names and their corresponding Microblaze index on this Zuma.
multiBitEccErrors	*integer*	The number of multi-bit ECC errors in this Zuma.
pciAddress	*string*	The PCI address of this Zuma.
singleBitEccErrors	*integer*	The number of single-bit ECC errors in this Zuma.

2.1374 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) [...]

switches	*table(string) = FapInfo* see 2.1374.1	Maps FAP names to their corresponding chip information.

2.1374.1 FapInfo

[device]	*enum: jerichoPlus | jericho2cPlus | qumran4d | qumran2a | jericho2 | qumran3d | jericho3Plus | jericho2m | jericho3 | jericho2c | jericho3ai | jericho | n/A | qumran3a | jericho3aiPlus | aradPlus | arad | qumranAx | jericho4*	Chip device name.
[fapId]	*integer*	FAP ID.
[fapType]	*enum: jericho | n/A | jericho2 | arad | jericho3 | jericho4*	Chip family name.
[revision]	*enum: 81a0 | q4d200 | q3nB0 | a0 | q2cPlusA2 | q4d100 | a1 | 84a0 | b1 | 82a0 | b0 | q3uB0 | 82a1 | 84a1 | 81a1 | q2c2tA1 | q3uA0 | q3nA0 | q2cPlusA0 | n/A | c0 | q2cPlusA1 | a2*	Chip revision name.

2.1375 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) cint [...]

stages	*table(string) = CintFap* see 2.1375.1	A mapping between a stage and its faps.

2.1375.1 CintFap

faps	*table(string) = string*	A mapping between a fap and its cint.

2.1376 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) copp mapping [...]

revision 2

classes	*table(string) = AradGenericCoppClassStats* see 2.1376.1	Generic COPP port information.
policerClasses	*table(string) = AradPolicerCoppClassStats* see 2.1376.2	Special COPP port information.

2.1376.1 AradGenericCoppClassStats

firstVoq	*integer*	First VOQ number.
[flowPolicer] **	*FlowPolicer* see 2.1376.1.1	CoPP flow policer status. **Since: 4.36.0
minimumBandwidth	*integer*	COPP class minimum bandwidth in kbps.
shape	*integer*	COPP class shape in kbps.
sysPhyPort	*integer*	System Physical Port ID.
totalVoqs	*integer*	Total number of VOQs.

2.1376.1.1 FlowPolicer

[flowPolicerBurst]	*integer*	CoPP flow policer burst in kbytes.
[flowPolicerRate]	*integer*	CoPP flow policer rate in kbps.
operational	*boolean*	CoPP flow policer is operational.

2.1376.2 AradPolicerCoppClassStats

firstVoq	*integer*	First VOQ ID.
policerBurst	*integer*	COPP class policer burst in kbytes.
policerRate	*integer*	COPP class policer rate in kbps.
sysPhyPort	*integer*	System physical port ID.
totalVoqs	*integer*	Total number of VOQs.

2.1377 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) eedb outac [...]

faps	*table(string) = EedbOutAcPoolMap* see 2.1377.1	A mapping of FAP name to its output attachment circuit (OutAc) pools.

2.1377.1 EedbOutAcPoolMap

pools	*table(string) = EedbOutAcIndexMap* see 2.1377.1.1	A mapping of pool name to its OutAc entries.

2.1377.1.1 EedbOutAcIndexMap

[outAcIndices]	*table(numeric string) = EedbOutAcEntry* see 2.1377.1.1.1	A mapping of OutAc index to its OutAc details.

2.1377.1.1.1 EedbOutAcEntry

[bank]	*integer*	Bank used for the OutAc.
[bankOffset]	*string*	Bank and offset of OutAc.
[dropAction]	*boolean*	Drop packets when true.
[oamLif]	*boolean*	OAM LIF set.
[offset]	*integer*	Offset in the bank for the OutAc.
[outAcHexStr]	*string*	Output attachment circuit index.
[outAcIndex]	*integer*	Output attachment circuit index.
[outlifProfileId]	*integer*	OutLIF profile ID.
[pcpDeiProfileId]	*integer*	PCP-DEI profile ID.
[statObjectCmd]	*integer*	Statistics object command.
[statObjectId]	*integer*	Statistics object ID.
[sviUsers]	*integer*	SVI users.
[sviVlan]	*integer*	SVI VLAN ID.
[vid1]	*integer*	Outer VLAN tag.
[vid2]	*integer*	Inner VLAN tag.
[vlanEditProfileId]	*integer*	VLAN edit profile ID.

2.1378 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) evpn mpls decap [...]

revision 2

[l2]	*L2EvpnMplsDecapMapping* see 2.1378.1	L2 decaps.
[l3]	*L3EvpnMplsDecapMapping* see 2.1378.2	L3 decaps.

2.1378.1 L2EvpnMplsDecapMapping

labels	*table(numeric string) = L2LabelBosEvpnMplsDecapMapping* see 2.1378.1.1	A mapping of MPLS label to BOS flag states.

2.1378.1.1 L2LabelBosEvpnMplsDecapMapping

[bos0]	*L2EvpnMplsDecapEntries* see 2.1378.1.1.1	L2 hardware programming details when label BOS == 0.
[bos1]	*L2EvpnMplsDecapEntries* see 2.1378.1.1.1	L2 hardware programming details when label BOS == 1.

2.1378.1.1.1 L2EvpnMplsDecapEntries

decapEntries	*list of L2EvpnMplsDecapEntry* see 2.1378.1.1.1.1	Hardware programming detail of decap entries.

2.1378.1.1.1.1 L2EvpnMplsDecapEntry

[destination]	*integer*	Encoded destination.
inLifProfile **	*integer*	Incoming logical interface profile. **Since: 4.32.0
[innerTag]	*integer*	Inner VLAN tag.
labelType	*enum: imet | evpn*	Label type.
lifBank	*integer*	Logical interface bank index.
lifIndex	*integer*	Logical interface index.
vlan	*integer*	VLAN.

2.1378.2 L3EvpnMplsDecapMapping

labels	*table(numeric string) = L3LabelBosEvpnMplsDecapMapping* see 2.1378.2.1	A mapping of MPLS label to BOS flag states.

2.1378.2.1 L3LabelBosEvpnMplsDecapMapping

[bos0]	*L3EvpnMplsDecapEntry* see 2.1378.2.1.1	L3 hardware programming details when label BOS == 0.
[bos1]	*L3EvpnMplsDecapEntry* see 2.1378.2.1.1	L3 hardware programming details when label BOS == 1.

2.1378.2.1.1 L3EvpnMplsDecapEntry

lifBank	*integer*	Logical interface bank index.
lifIndex	*integer*	Logical interface index.
payloadType	*enum: mpls | ip*	Payload type.
rifIndex	*integer*	Routing interface index.
vrfName	*string*	VRF name.

2.1379 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) evpn mpls encap [...]

revision 2

faps	*table(string) = VlanEvpnMplsEncapMap* see 2.1379.1	A mapping of FAP name to its VLAN IDs.

2.1379.1 VlanEvpnMplsEncapMap

vlans	*table(numeric string) = IntfEvpnMplsEncapMap* see 2.1379.1.1	A mapping of VLAN ID to its interfaces.

2.1379.1.1 IntfEvpnMplsEncapMap

interfaces	*table(Interface name) = EvpnMplsEncapEntries* see 2.1379.1.1.1	A mapping of interface name to its hardware programming details.

2.1379.1.1.1 EvpnMplsEncapEntries

intfEntries	*list of EvpnMplsEncapEntry* see 2.1379.1.1.1.1	Hardware programming detail of encap entry.

2.1379.1.1.1.1 EvpnMplsEncapEntry

[esiLabel]	*integer*	ESI label.
[lifBank]	*integer*	Logical interface bank index.
[lifIndex]	*integer*	Logical interface index.
[numConfiguredMembers]	*integer*	Count of configured members of the port-channel on the FAP.
[numProgrammedMembers]	*integer*	Count of programmed members of the port-channel on the FAP.

[tunnelId]	*integer*	Hardware tunnel ID.
[vlanDomain]	*integer*	VLAN domain.
[vlanTag]	*integer*	VLAN tag.

2.1380 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) fabric load distribution [...]

revision 2

faps	*table(string) = WfdConfigNumSerdes* see 2.1380.1	Load balancing config for the specified FAPs.

2.1380.1 WfdConfigNumSerdes

feIdNumSerdes	*table(numeric string) = FeIdNumSerdes* see 2.1380.1.1	Show the number of links to each FE ID from this FAP.
[wfdProfile]	*integer*	Load balancing profile for this FAP.

2.1380.1.1 FeIdNumSerdes

feName	*string*	FE name.
numSerdes	*integer*	Number of links to this FE.
[wfdProfile]	*integer*	Load balancing profile for this FAP.

2.1381 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) fabric load distribution destination (fap | arad | jericho | jericho2 | jericho3 | jericho4) [...]

faps	*table(string) = FapWfdSerdesWeights* see 2.1381.1	Load balancing weights for these source FAPs to destination FAPs.

2.1381.1 FapWfdSerdesWeights

faps	*table(string) = WfdConfigSerdesWeights* see 2.1381.1.1	SerDes weights for destination FAPs given a source FAP.

2.1381.1.1 WfdConfigSerdesWeights

serdesWeights	*table(numeric string) = integer*	Weight from 1-127 for any given SerDes ID.
[wfdProfile]	*integer*	Load balancing profile for this FAP.

2.1382 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) flow tracking sampled flow-table hw [...]

faps	*table(string) = FlowTableFapLevelInfo* see 2.1382.1	Flows per FAP.

2.1382.1 FlowTableFapLevelInfo

flows	*list of FlowTableEntry* see 2.1382.1.1	List of flows.

2.1382.1.1 FlowTableEntry

counterIndex	*integer*	Counter index.
dstAddr	*IP address*	Destination IP address.
dstPort	*integer*	Destination port.
fragmented	*boolean*	Whether to match on fragmented packets.
ipProtocol	*integer*	IP protocol.
portLabel	*integer*	Port label.
srcAddr	*IP address*	Source IP address.
srcPort	*integer*	Source port.
vlanId	*integer*	Flow VLAN ID.
vrf	*integer*	VRF.

2.1383 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) ip route prefix compression tcam [...]

banks	*table(numeric string) = PrefixCompressionTcam-Entries* see 2.1383.1	A mapping of TCAM bank to its indices.

2.1383.1 PrefixCompressionTcamEntries

indices	*table(numeric string) = PrefixCompressionTcam-Entry* see 2.1383.1.1	A mapping of TCAM index to its entries.

2.1383.1.1 PrefixCompressionTcamEntry

destIpBit	*integer*	Destination IP bit indicator.
eeiMsb4b	*integer*	MSB 4 bits of EEI.
fec0	*integer*	FEC0 hardware index.
fec1	*integer*	FEC1 hardware index.
lem2Lookup	*integer*	LEM2 lookup success.
overridingFecId	*integer*	Overriding FEC hardware index.

2.1384 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) label sharing inlif shadow [...]

revision 2

entries	*list of LabelSharingInLif-EntriesForFap* see 2.1384.1	Label sharing InLIF entries for each FAP.

2.1384.1 LabelSharingInLifEntriesForFap

entriesForFap	*list of LabelSharingInLifEntry* see 2.1384.1.1	Label sharing InLIF entries on this FAP.
[entriesForFapCore] **	*list of PmfDataInLifEntry* see 2.1384.1.2	PMF data InLif entries on this FAP and core. **Since: 4.23.2
fapId	*integer*	FAP ID.
[fapName] **	*string*	FAP name. **Since: 4.23.2
[localCoreId] **	*integer*	Local core ID. **Since: 4.23.2
[systemTcamId] **	*integer*	System TCAM ID. **Since: 4.23.2

2.1384.1.1 LabelSharingInLifEntry

[innerTag]	*integer*	Inner VLAN tag.
[lifEntry]	*LifAcMp* see 2.1384.1.1.3	LIF entry.
[outerTag]	*integer*	Outer VLAN tag.
request	*LabelSharingRequest* see 2.1384.1.1.2	Label sharing request.
[semPayload]	*InAcSemPayload* see 2.1384.1.1.1	SEM payload.
[vlanDomain]	*integer*	VLAN domain.

2.1384.1.1.1 InAcSemPayload

lifIndex	*integer*	Raw SEM payload value converted to SW LIF index.
startingLifBank	*integer*	Starting LIF bank index.
value	*integer*	Raw U32 sem payload value.

2.1384.1.1.2 LabelSharingRequest

fapId	*integer*	The FAP ID of the FAP this entry was found on.
intfName	*interface name*	Interface name.
l3FloodPortVlanId	*integer*	Layer 3 flood port VLAN ID.

2.1384.1.1.3 LifAcMp

inLifAdditionalData	*InLifAdditionalData* see 2.1384.1.1.3.1	InLifAdditionalData value.
vsi	*integer*	VSI value.

2.1384.1.1.3.1 InLifAdditionalData

ipv4	*integer*	IPv4 InLifAdditionalData field.
ipv6	*integer*	IPv6 InLifAdditionalData field.
l2PF **	*integer*	l2PF InLifAdditionalData field. **Since: 4.26.0
macl	*integer*	MACL InLifAdditionalData field.
pbr	*integer*	PBR InLifAdditionalData field.
policerIdxMeterA **	*integer*	policerIndexMeterA InLifAdditionalData field. **Since: 4.26.0
policerIdxMeterB **	*integer*	policerIndexMeterB InLifAdditionalData field. **Since: 4.26.0
qos	*integer*	QoS InLifAdditionalData field.
sFlow **	*integer*	sflowSubintf InLifAdditionalData field. **Since: 4.29.0
value	*integer*	Raw InLifAdditionalData U64 value.

2.1384.1.2 PmfDataInLifEntry

[innerTag]	*integer*	Inner VLAN tag.
intfName	*interface name*	Interface name.
[lagName]	*interface name*	Parent LAG interface name.
[lifEntry]	*LifAcMpGenericData* see 2.1384.1.2.1	LIF entry.
[lifIndex]	*integer*	Raw SEM payload value converted to SW LIF index.
[outerTag]	*integer*	Outer VLAN tag.
[vlanDomain]	*integer*	VLAN domain.
[vlanIntfName] **	*interface name*	VLAN interface name. **Since: 4.24.1

2.1384.1.2.1 LifAcMpGenericData

eei	*integer*	Egress Encapsulation Information.
lifGenericData0	*integer*	LIF generic data word 0.
lifGenericData1	*integer*	LIF generic data word 1.
policyId	*PolicyId* see 2.1384.1.2.1.1	Policy ID for every feature type.

2.1384.1.2.1.1 PolicyId

[lifAclBlockIntf] **	*integer*	BlockIntf label. **Since: 4.26.2
[lifAegisLabel]	*integer*	AEGIS label.
[lifAegisLabelInterface-Ignore] **	*integer*	AEGIS ignore interface label. **Since: 4.33.2
[lifAegisLabelVlan-Interface] **	*integer*	AEGIS VLAN Interface label. **Since: 4.30.2
[lifAegisUnsharedPolicer] **	*integer*	Base label for unshared Aegis policers. **Since: 4.29.1
[lifArpFeature] **	*integer*	ARP feature label. **Since: 4.26.2
[lifBumFilter] **	*integer*	EVPN MPLS BUM filter label. **Since: 4.27.2
[lifCpuLabel] **	*integer*	CPU policy label. **Since: 4.24.1
[lifDhcpSnooping] **	*integer*	DHCP snooping label. **Since: 4.29.1
[lifDot1xMode] **	*integer*	Dot1x mode. **Since: 4.32.1
[lifEsiLabel]	*integer*	ESI label.
[lifEsiLabelTunnelId] **	*integer*	ESI label and HwTunnel Id. **Since: 4.30.1
[lifFlowspecLabel] **	*integer*	Flowspec label. **Since: 4.24.1
[lifGroupPolicing] **	*integer*	Policer label for grouped interface policing. **Since: 4.29.1
[lifInterfacePolicing] **	*integer*	Dedicated policer label for interface policing. **Since: 4.29.1
[lifIpsecLabel] **	*integer*	IPsec label. **Since: 4.29.1
[lifJ2GroupPolicing] **	*integer*	Policer label for grouped interface policing. **Since: 4.30.0
[lifJ2InterfacePolicing] **	*integer*	Dedicated policer label for interface policing. **Since: 4.28.2
[lifL2ProtocolFwdLabel]	*integer*	L2 protocol forwarding label.
[lifL2SubIntf] **	*integer*	L2 Subinterface label. **Since: 4.27.2
[lifMaclLabel]	*integer*	MACL label.
[lifMplsEvpnLabel1]	*integer*	MPLS EVPN label 1.
[lifMplsEvpnLabel2]	*integer*	MPLS EVPN label 2.
[lifNdProxy] **	*integer*	ND proxy label for VLAN interfaces. **Since: 4.32.0
[lifPaclV4Label] **	*integer*	IPv4 PACL label. **Since: 4.24.0
[lifPaclV6Label] **	*integer*	IPv6 PACL label. **Since: 4.24.0
[lifPbrLabel]	*integer*	PBR label.

[lifPvlan] **	*integer*	PVLAN secondary VLAN. **Since: 4.29.2
[lifPwxOam] **	*integer*	Label for L3 subinterfaces patched to pseudowire. **Since: 4.29.1
[lifQosLabel]	*integer*	QoS label.
[lifRaclV4Label] **	*integer*	IPv4 RACL label. **Since: 4.28.0
[lifRaclV6Label]	*integer*	IPv6 RACL label.
[lifSampledFlowTracking-Label] **	*integer*	Sampled flow tracking label. **Since: 4.25.0
[lifSegmentSecurity] **	*integer*	Segment Security label. **Since: 4.29.1
[lifSflowFilteredSampling] **	*integer*	Sflow label for filtered sampling. **Since: 4.31.0
[lifSflowSubintf] **	*integer*	Sflow label for subinterfaces. **Since: 4.29.1
[lifStormControlSubintf] **	*integer*	StormControl label for subinterfaces. **Since: 4.30.2
[lifTunnelAclV4] **	*integer*	IPv4 ACL label for GRE/IPsec tunnel interfaces. **Since: 4.29.1
[lifTunnelAclV6] **	*integer*	IPv6 ACL label for GRE/IPsec tunnel interfaces. **Since: 4.33.0
[lifTunnelPbrV4] **	*integer*	IPV4 PBR label for GRE/IPsec tunnel interfaces. **Since: 4.29.1
[lifUnsharedPolicer] **	*integer*	Base policer label for unshared QoS policy-maps. **Since: 4.28.2
[lifUrpfLookupVrfLabel] **	*integer*	uRPF lookup VRF label. **Since: 4.28.2
[lifVlanEdit] **	*integer*	Label for extended vlan editing. **Since: 4.29.1
[lifVlanEtreeRole] **	*integer*	VLAN etree role label. **Since: 4.27.2
[lifVrfSelectionLabel] **	*integer*	VRF Selection Policy label. **Since: 4.28.1

2.1385 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) label sharing isem (shadow | hardware | diff) [...]

isemForFap	*list of LabelSharingIsemForFap* see 2.1385.1	Label sharing ISEM for each FAP.

2.1385.1 LabelSharingIsemForFap

entriesWithRequests	*list of LabelSharingIsemEntryWithRequest* see 2.1385.1.2	Label sharing requests and ISEM entries inserted.
entriesWithRequests-Mismatches	*list of LabelSharingIsemEntryWithRequestMismatch* see 2.1385.1.3	Label sharing requests and ISEM entries inserted that mismatch.
entryOnly	*list of LabelSharingIsemEntryOnly* see 2.1385.1.1	Label sharing ISEM entry with no matching request.
fapId	*integer*	FAP ID.
isHalo	*boolean*	True if this FAP is Halo enabled.
requestOnly	*list of LabelSharingRequestOnly* see 2.1385.1.4	List of label sharing requests that are in progress.

2.1385.1.1 LabelSharingIsemEntryOnly

policyId	*LabelSharingPolicyId* see 2.1385.1.1.1	Policy ID parsed from ISEM.
vlanDomain	*integer*	VLAN domain.
vlanId	*integer*	VLAN ID.

2.1385.1.1.1 LabelSharingPolicyId

haloAclLabel	*integer*	Halo ACL label bits.
ipv4Policy	*integer*	IPv4 policy ID bits.
ipv6EgressPolicy	*integer*	IPv6 egress policy bits.
ipv6Policy	*integer*	IPv6 policy ID bit.
ipv6PolicyValid	*integer*	IPv6 policy valid bit.
pbrPolicy	*integer*	PBR policy ID bits.
qosPolicy	*integer*	QoS policy ID bits.
value	*integer*	Raw policy ID value.

2.1385.1.2 LabelSharingIsemEntryWithRequest

policyId	*LabelSharingPolicyId* see 2.1385.1.1.1	Policy ID parsed from ISEM.
request	*LabelSharingRequest* see 2.1384.1.1.2	Label sharing request.
vlanDomain	*integer*	VLAN domain.
vlanId	*integer*	VLAN ID.

2.1385.1.3 LabelSharingIsemEntryWithRequestMismatch

expected	*LabelSharingPolicyId* see 2.1385.1.1.1	The requested policy ID.
policyId	*LabelSharingPolicyId* see 2.1385.1.1.1	Policy ID parsed from ISEM.
request	*LabelSharingRequest* see 2.1384.1.1.2	Label sharing request.
vlanDomain	*integer*	VLAN domain.
vlanId	*integer*	VLAN ID.

2.1385.1.4 LabelSharingRequestOnly

expected	*LabelSharingPolicyId* see 2.1385.1.1.1	Policy ID requested to be inserted.
request	*LabelSharingRequest* see 2.1384.1.1.2	Label sharing request.
[vlanDomain]	*integer*	VLAN domain.
[vlanId]	*integer*	VLAN ID.

2.1386 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) label sharing ppmc l2 shadow [...]

ppmcEntries	*table(numeric string) = PpmcLabelSharingEntries* see 2.1386.1	A mapping of PPMC index to PPMC label sharing entry.

2.1386.1 PpmcLabelSharingEntries

globalOutlif1	*integer*	Global Outlif1.
globalOutlif2	*integer*	Global Outlif2.
[ppmcMacLabel]	*integer*	Egress Mac label.
[ppmcV4Label]	*integer*	Egress IPv4 label.
[ppmcV6Label]	*integer*	Egress IPv6 label.

2.1387 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) label sharing ppmc l3 shadow [...]

see 2.1386

2.1388 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) lag [...]

revision 3

aradLags	*table(string) = AradLags* see 2.1388.1	Mapping of Arad chip name to LAG information.

2.1388.1 AradLags

lags	*table(string) = AradLag* see 2.1388.1.1	Mapping of port channel name to LAG ID and associated port lists.
mode	*enum: 64x256 | 2048x8 | 1024x16 | 512x32 | 128x128 | 256x64*	Programmed LAG mode.

2.1388.1.1 AradLag

application	*string*	Application that uses the LAG.
collectingMemberOrder	*list of Interface name*	Order of interface.
collectingMembers	*table(Interface name) = integer*	Mapping of interface name to sysPortId.
distributingMemberOrder	*list of Interface name*	Order of interface.
distributingMemberWeights	*table(Interface name) = integer*	Mapping of interface name to speed weight.
distributingMembers	*table(Interface name) = integer*	Mapping of interface name to sysPortId.
id	*string*	Hardware LAG ID.
partition	*string*	Hardware LAG ID Partition.
unmappedCollectingMembers	*list of integer*	SysPortId of members who don't have an interface name.
unmappedDistributingMembers	*list of integer*	SysPortId of members who don't have an interface name.

2.1389 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) mac-address-table [...]

faps	*table(string) = FapMacAddressTable* see 2.1389.1	Map of FAP names to its MAC address table entries.
[pollerFap]	*PollerFapInfo* see 2.1389.2	Poller FAP details.

2.1389.1 FapMacAddressTable

macEntries	*list of MacEntry* see 2.1389.1.1	MAC address table entries.

2.1389.1.1 MacEntry

[ageCycles]	*integer*	Number of age cycles before the entry expires if it is not refreshed.
destType	*enum: multicast | fec | singlePort | drop | lag*	Destination type.
destValue	*integer*	Destination value.
[dropSrcAddr]	*boolean*	Drop mode is configured for source and destination.
dynamic	*boolean*	Entry is dynamically learned.
interface	*interface name*	Interface name.

macAddr	*string*	MAC address.
[swProgrammed]	*boolean*	Entry is programmed by software.
vlanId	*integer*	VLAN ID.

2.1389.2 PollerFapInfo

fapName	*string*	Name of the poller FAP.
pollingInterval	*floating point number*	Poller FAP polling interval in seconds.

2.1390 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) mac-address-table diff [...]

faps	*table(string) = FapMacAddressTableDiff* see 2.1390.1	Map of FAP names to the differences between MAC address table entries in hardware and software.
[pollerFap]	*PollerFapInfo* see 2.1389.2	Poller FAP details.

2.1390.1 FapMacAddressTableDiff

macEntries	*list of DiffMacEntry* see 2.1390.1.1	Delta MAC entries in hardware and software.

2.1390.1.1 DiffMacEntry

[hardware]	*HwMacEntryDetails* see 2.1390.1.1.1	Entry payload details in hardware.
macAddr	*string*	MAC address.
[software]	*SwMacEntryDetails* see 2.1390.1.1.2	Entry payload details in software.
vlanId	*integer*	VLAN ID.

2.1390.1.1.1 HwMacEntryDetails

[ageCycles]	*integer*	Number of age cycles before the entry expires if not refreshed.
dynamic	*boolean*	Hardware entry is dynamically learned.
interface	*interface name*	Hardware entry interface name.

2.1390.1.1.2 SwMacEntryDetails

dynamic	*boolean*	Software entry is dynamically learned.
interface	*interface name*	Software entry interface name.

2.1391 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) mapping [...]

revision 5

aradMappings	*list of PortMappings* see 2.1391.1	List of Port Mappings for each switch.

2.1391.1 PortMappings

baseSystemCoreId	*integer*	System Core Id of the first core of this fap.
cores	*integer*	Number of cores for this fap.
fapId	*integer*	Fap Id.
fapName	*string*	Fap Name.
portMappings	*table(numeric string) = PortMapping* see 2.1391.1.1	Maps Port Mappings to the system physical port IDs.

2.1391.1.1 PortMapping

baseQueuePair	*integer*	First egress transmit queue pair used by the system port.
coreId	*integer*	Core Id.
fapId	*integer*	Fap Id.
fapPortId	*integer*	Fap Port Id.
interface	*interface name*	An Interface name that maps to the system port.
nifPortId	*integer*	Nif Port Id.
outTmPortId	*integer*	Out TM Port Id.
qsgmiiId	*integer*	QSGMII ID used by the system port.
queuePairs	*integer*	Number of queue pairs used by the port in the egress.
serdesIds	*list of integer*	List of Serdes used by the system port.
voqId	*integer*	Voq Id.
xlgeId	*integer*	40G xlge which maps to the system port.

2.1392 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) mroute [...]

[cmdErr]	*string*	Error Message.
[ipv4]	*FapToIpv4MroutesMapping* see 2.1392.1	Model for IPv4 Multicast Mroutes within respective FAP.
[ipv6]	*FapToIpv6MroutesMapping* see 2.1392.2	Model for IPv6 Multicast Mroutes within respective FAP.

2.1392.1 FapToIpv4MroutesMapping

[cmdErr]	*string*	Error Message.
[faps]	*table(string) = Ipv4MroutesList* see 2.1392.1.1	Mapping FAP name to its IPv4 multicast routes entries.

2.1392.1.1 Ipv4MroutesList

multicastRoutes	*list of Ipv4MrouteModel* see 2.1392.1.1.1	List of detailed IPv4 multicast routes entries.

2.1392.1.1.1 Ipv4MrouteModel

[cmdErr]	*string*	Error Message.
[group]	*IP address prefix*	Group ID.
[iifVlan]	*integer*	Incoming interface VLAN.
[iifVrf]	*integer*	Incoming interface VRF.
[inLem]	*boolean*	Mroute installed in LEM table.
[instance]	*integer*	TCAM Bank instance of multicast route entry.
[location]	*integer*	Index of mroute entry in TCAM.
[multicastId]	*integer*	Multicast ID.
[oifCpu]	*boolean*	OIF have Ingress Receive Editor, in packet goes to CPU too.
[oifVlans]	*table(numeric string) = OutgoingInfo* see 2.1392.1.1.1.1	Mapping OIF VLAN to its Interfaces.
[source]	*IP address prefix*	Source IP Prefix.

2.1392.1.1.1.1 OutgoingInfo

interfaces	*list of Interface name*	Outgoing interfaces.
[isPmsi] **	*boolean*	MVPN encap outgoing interface. **Since: 4.27.1
[tunnelEndInterfaces]	*list of Interface name*	Core facing interfaces: multicast packet copies for these Interfaces are done with encapsulation.
[tunnelType] **	*enum: pmsi | gre*	Outgoing tunnel interface. **Since: 4.31.1

2.1392.2 FapToIpv6MroutesMapping

[cmdErr]	*string*	Error Message.
[faps]	*table(string) = Ipv6MroutesList* see 2.1392.2.1	Mapping FAP name to its IPv6 multicast routes entries.

2.1392.2.1 Ipv6MroutesList

multicastRoutes	*list of Ipv6MrouteModel* see 2.1392.2.1.1	List of detailed IPv6 multicast routes entries.

2.1392.2.1.1 Ipv6MrouteModel

[cmdErr]	*string*	Error Message.
[flpGroupId]	*integer*	FLP Group ID.
[flpLocation]	*integer*	FLP Location.
[group]	*IP address prefix*	Group ID in TT stage.
[iifVlan]	*integer*	Incoming interface VLAN.
[instance] **	*integer*	TCAM Bank instance of multicast route entry. **Since: 4.27.1
[location] **	*integer*	Index of mroute entry in TCAM. **Since: 4.27.1
[multicastId]	*integer*	Multicast ID.
[oifCpu]	*boolean*	OIF have Ingress Receive Editor, in packet goes to CPU too.
[oifVlans]	*table(numeric string) = OutgoingInfo* see 2.1392.1.1.1.1	Mapping OIF VLAN to its Interfaces.
[source]	*IP address prefix*	Source IP Prefix.
[ttGroupId]	*integer*	TT Group ID.
[ttLocation]	*integer*	TT Location.

2.1393 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) mroute ipv4 [...]

see 2.1392.1

2.1394 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) mroute ipv6 [...]

see 2.1392.2

2.1395 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) mvpn decap [...]

labels	*table(numeric string) = MvpnDecapEntry* see 2.1395.1	A mapping of MPLS label to MVPN decap information.

2.1395.1 MvpnDecapEntry

lifIndex	*integer*	Logical interface index.
pmsiVlan	*integer*	PMSI VLAN interface ID.

2.1396 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) phy PHY_FROM_PORT dump [...]

aradPhysicalInfo	*list of PhysicalInfo* see 2.1396.1	The Arad Physical information.

2.1396.1 PhysicalInfo

aradName	*string*	Arad Name.
ports	*list of string*	Physical information for the ports.

2.1397 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) phy PHY_FROM_PORT register mmd PHY_REG_START [...]

aradPhysicalRegisters	*list of PhysicalRegister* see 2.1397.1	The Arad Physical registers.

2.1397.1 PhysicalRegister

aradName	*string*	Arad Name.
ports	*list of string*	Physical register information for the ports.

2.1398 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) pim bidirectional df [...]

[cmdErr]	*string*	Error Message.
[faps]	*table(string) = DfEntryListModel* see 2.1398.1	Mapping FAP name to its DF check entries.

2.1398.1 DfEntryListModel

[cmdErr]	*string*	Error Message.
dfEntries	*list of DfEntryModel* see 2.1398.1.1	List of DF check entries.

2.1398.1.1 DfEntryModel

[cmdErr]	*string*	Error Message.
[iif]	*string*	Incoming interface VLAN.
[rpaId]	*integer*	RPA ID.

2.1399 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) pim bidirectional rpa [...]

[cmdErr]	*string*	Error message.
rpaEntries	*list of RpaEntryModel* see 2.1399.1	List of RPA entries.

2.1399.1 RpaEntryModel

[cmdErr]	*string*	Error message.
[group]	*IP address prefix*	Group ID.
[rpaId]	*integer*	RPA ID.
[vrf]	*integer*	Incoming VRF.

2.1400 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) pmf [...]

profileInstances	*list of ProfileInstance* see 2.1400.1	List of profile instances.

2.1400.1 ProfileInstance

fapIds	*list of integer*	Programmed FAP IDs.
fapRevMajor	*enum: majorAradPlus* | *majorJericho4* | *majorJericho3aiPlus* | *majorJericho2c* | *majorQumranAx* | *majorArad* | *majorJerichoPlus* | *majorUnknown* | *majorJericho2m* | *majorQumran3a* | *majorQumran4d* | *majorJericho2cPlus* | *majorQumran2a* | *majorJericho3ai* | *majorJericho3Plus* | *majorJericho2* | *majorJericho3* | *majorJericho* | *majorQumran3d*	Major FAP revision.
fapRevMinor	*enum: minorB0* | *minorQ3uB0* | *minorC0* | *minor82A1* | *minorA1* | *minorQ3uA0* | *minorQ2cPlusA0* | *minorQ2cPlusA1* | *minorA0* | *minorA2* | *minor81A0* | *minor82A0* | *minorUnknown* | *minor84A1* | *minorQ2cPlusA2* | *minorQ4d100* | *minorQ2c2tA1* | *minorQ3nA0* | *minorB1* | *minor84A0* | *minor81A1* | *minorQ3nB0* | *minorQ4d200*	Minor FAP revision.
multiAgent	*boolean*	SandFap/SandPmf both programming PMF.
profileName	*string*	TCAM profile name.
stages	*table(string) = Stage* see 2.1400.1.1	Mapping from PMF stage to preselectors and contexts.
version	*integer*	TCAM profile version number.

2.1400.1.1 Stage

contexts	*table(numeric string) = Context* see 2.1400.1.1.1	Mapping from context ID to key and action info.
preselectors	*table(string) = Preselector* see 2.1400.1.1.2	Mapping from preselector ID to match criteria.

2.1400.1.1.1 Context

femIds **	*table(numeric string) = Fem* see 2.1400.1.1.1.1	Mapping from FEM ID to FEM hardware tables info. **Since: 4.32.2
fesIds	*table(numeric string) = Fes* see 2.1400.1.1.1.3	Mapping from FES ID to action info.
keyConstructions	*table(string) = KeyConstruction* see 2.1400.1.1.1.4	Mapping from PmfKey to key construction info.
keyLookups	*table(string) = KeyLookup* see 2.1400.1.1.1.6	Mapping from PmfKey to key lookup info.

2.1400.1.1.1.1 Fem

femKeySource	*list of FemKeySource* see 2.1400.1.1.1.2	List of FEM key input source.
lsbSelectPmfKey	*enum: pmfKeyJ | pmfKeyE | pmfKeyI | pmfKeyG | pmfKeyK | pmfKeyA | pmfKeyD | pmfKeyF | pmfKeyH | pmfKeyB | pmfKeyNone | pmfKeyC | pmfKeyL*	PMF key of replace-LSB.

lsbSelectSrc	*enum: dbIpCpuTrafficPolicy* | *dbDirectExtractionPmf3* | *dbSegmentSecurityIp6* | *swEgressIpBridgeDot1q* | *dbVxlanRouting* | *dbElkResultIp6Racl* | *dbDot1x* | *dbEgressIp6Racl* | *dbFlow* | *dbIpSubIntfPbr* | *dbDirectExtraction-InterfacePolicing* | *dbIp6SubIntfAcl* | *dbIpMirror* | *dbMplsPbr* | *swIpOMpls* | *dbEgressOlp* | *dbVxlanFemDirect-Extraction* | *dbOutLifDirectExtraction* | *dbMcastCounters* | *dbIpv4TtBasic* | *dbIp6PostcardPolicy* | *dbDirectExtractionPmf1-SubintfSflow* | *dbMplsSubIntfPbr* | *dbSystem6* | *dbIp6RaclStage1* | *dbMacTapAgg* | *dbOamIdentification* | *dbQosUnsharedPolicer* | *dbIpDstXformed* | *dbHashingReplacement-Ipv6Low* | *dbElkResultIp6Pacl* | *dbIp6Decap* | *dbMogIp6DirectExtraction* | *dbSegmentSecurityIp4* | *dbPvlan* | *dbDirect-ExtractionPmf1Srv6Usid* | *dbDirectExtractionSetEcn* | *dbDirectExtractionPmf1-SetBridgedToRouted* | *dbIp6VrfSelection* | *dbDirectExtractionPmf1-CopyTtlV6* | *dbElkResultIpRacl* | *dbIp6Pbr* | *dbEgressIp6Pacl* | *dbTrafficPolicyIp4Copy-TtlSw* | *swEgressQinQ* | *dbDirectExtractionPmf1-Srv6UsidWFunc* | *dbIpPbr* | *dbSecondaryVrfDestDirect-Extraction* | *dbEgressRfc2544* | *dbIpPostcardPolicy* | *dbMacSystem* | *dbIpsec* | *dbVxlanMcastTunTerm* | *swVsiOverwriteAlways* | *dbMplsGreIp6* | *dbFlexRoute* | *dbIpMcastRouting* | *dbDirectExtractionSetDscp* | *dbVxlanMultihomingMcast*	TCAM result to use for replace-LSB option.

pgmId	*integer*	FEM PGM-ID, index into the IPPC_FEM_BIT_SELECT table.
selectMsbVal	*integer*	Bit select value to copy MSB of the key.

2.1400.1.1.1.2 FemKeySource

db	*enum: dbIpCpuTrafficPolicy* | *dbDirectExtractionPmf3* | *dbSegmentSecurityIp6* | *swEgressIpBridgeDot1q* | *dbVxlanRouting* | *dbElkResultIp6Racl* | *dbDot1x* | *dbEgressIp6Racl* | *dbFlow* | *dbIpSubIntfPbr* | *dbDirectExtraction-InterfacePolicing* | *dbIp6SubIntfAcl* | *dbIpMirror* | *dbMplsPbr* | *swIpOMpls* | *dbEgressOlp* | *dbVxlanFemDirect-Extraction* | *dbOutLifDirectExtraction* | *dbMcastCounters* | *dbIpv4TtBasic* | *dbIp6PostcardPolicy* | *dbDirectExtractionPmf1-SubintfSflow* | *dbMplsSubIntfPbr* | *dbSystem6* | *dbIp6RaclStage1* | *dbMacTapAgg* | *dbOamIdentification* | *dbQosUnsharedPolicer* | *dbIpDstXformed* | *dbHashingReplacement-Ipv6Low* | *dbElkResultIp6Pacl* | *dbIp6Decap* | *dbMogIp6DirectExtraction* | *dbSegmentSecurityIp4* | *dbPvlan* | *dbDirect-ExtractionPmf1Srv6Usid* | *dbDirectExtractionSetEcn* | *dbDirectExtractionPmf1-SetBridgedToRouted* | *dbIp6VrfSelection* | *dbDirectExtractionPmf1-CopyTtlV6* | *dbElkResultIpRacl* | *dbIp6Pbr* | *dbEgressIp6Pacl* | *dbTrafficPolicyIp4Copy-TtlSw* | *swEgressQinQ* | *dbDirectExtractionPmf1-Srv6UsidWFunc* | *dbIpPbr* | *dbSecondaryVrfDestDirect-Extraction* | *dbEgressRfc2544* | *dbIpPostcardPolicy* | *dbMacSystem* | *dbIpsec* | *dbVxlanMcastTunTerm* | *swVsiOverwriteAlways* | *dbMplsGreIp6* | *dbFlexRoute* | *dbIpMcastRouting* | *dbDirectExtractionSetDscp* | *dbVxlanMultihomingMcast*	DB source of FEM's key selection.

lsb	*integer*	LSB of FEM key.
msb	*integer*	MSB of FEM key.
pmfString	*enum: pmfKeyJ* | *pmfKeyE* | *pmfKeyI* | *pmfKeyG* | *pmfKeyK* | *pmfKeyA* | *pmfKeyD* | *pmfKeyF* | *pmfKeyH* | *pmfKeyB* | *pmfKeyNone* | *pmfKeyC* | *pmfKeyL*	PMF key of FEM's key source.
sourceType	*enum: tcamResult* | *smallExactMatchKey* | *allZeros* | *largeExactMatchKey* | *directExtractionKey* | *sourceNone* | *directKey*	Source type of FEM's key input.

2.1400.1.1.1.3 Fes

andMask	*integer*	AND-mask applied to FES source.

db	*enum: dbIpCpuTrafficPolicy* | *dbDirectExtractionPmf3* | *dbSegmentSecurityIp6* | *swEgressIpBridgeDot1q* | *dbVxlanRouting* | *dbElkResultIp6Racl* | *dbDot1x* | *dbEgressIp6Racl* | *dbFlow* | *dbIpSubIntfPbr* | *dbDirectExtraction-InterfacePolicing* | *dbIp6SubIntfAcl* | *dbIpMirror* | *dbMplsPbr* | *swIpOMpls* | *dbEgressOlp* | *dbVxlanFemDirect-Extraction* | *dbOutLifDirectExtraction* | *dbMcastCounters* | *dbIpv4TtBasic* | *dbIp6PostcardPolicy* | *dbDirectExtractionPmf1-SubintfSflow* | *dbMplsSubIntfPbr* | *dbSystem6* | *dbIp6RaclStage1* | *dbMacTapAgg* | *dbOamIdentification* | *dbQosUnsharedPolicer* | *dbIpDstXformed* | *dbHashingReplacement-Ipv6Low* | *dbElkResultIp6Pacl* | *dbIp6Decap* | *dbMogIp6DirectExtraction* | *dbSegmentSecurityIp4* | *dbPvlan* | *dbDirect-ExtractionPmf1Srv6Usid* | *dbDirectExtractionSetEcn* | *dbDirectExtractionPmf1-SetBridgedToRouted* | *dbIp6VrfSelection* | *dbDirectExtractionPmf1-CopyTtlV6* | *dbElkResultIpRacl* | *dbIp6Pbr* | *dbEgressIp6Pacl* | *dbTrafficPolicyIp4Copy-TtlSw* | *swEgressQinQ* | *dbDirectExtractionPmf1-Srv6UsidWFunc* | *dbIpPbr* | *dbSecondaryVrfDestDirect-Extraction* | *dbEgressRfc2544* | *dbIpPostcardPolicy* | *dbMacSystem* | *dbIpsec* | *dbVxlanMcastTunTerm* | *swVsiOverwriteAlways* | *dbMplsGreIp6* | *dbFlexRoute* | *dbIpMcastRouting* | *dbDirectExtractionSetDscp* | *dbVxlanMultihomingMcast*	Corresponding Database for source bits.

hwAction	*enum: aceStampValueAct* | *rpfOutLifAct* | *udh31To00Act* | *statisticsObject2Act* | *pemGeneralData1Act* | *nwkHeaderAppendSizeAct* | *pemGeneralData3Act* | *learnInfoPayload1Act* | *wexemLearnKey0Act* | *rpfDestinationAct* | *globOutLif0Act* | *statisticsObjectAtr10Act* | *learnInfoKey2Act* | *cudOutlifOrMcdbPtrAct* | *statisticalAct* | *statisticsObjectAtr3Act* | *extStatistics2Act* | *inLifProfile0Act* | *mirrorProfileAct* | *generalData3Act* | *statisticsObject6Act* | *systemHeaderProfileIndex-Act* | *visibilityAct* | *ieee1588DataAct* | *portRateAddressAct* | *generalData4Act* | *fheiExt63To32Act* | *pmf-ForwardOverrideEnableAct* | *statisticsObject7Act* | *snoopStrengthAct* | *ftmhCniAct* | *ftmhAse47To32Act* | *learnInfoKey0Act* | *btk-OffsetInBytesFromSopAct* | *destinationAct* | *ftmhTcAct* | *slbFoundAct* | *stateAddressAct* | *statisticsObjectAtr1Act* | *userHeadersTypeAct* | *dspaAct* | *statisticsObjectAtr4Act* | *pmfEesEntryTypeAct* | *statisticsObjectAtr2Act* | *srcSystemPortIdAct* | *wexemLearnKey3Act* | *generalData2Act* | *wexemLearnKey1Act* | *faiDoNotDecrementTtlAct* | *aceStatLmReadAct* | *pemGeneralData4Act* | *nwkQosAct* | *slbPayload1Act* | *generalData63To32Act* | *counter1ProfileAct* | *userHeader2ExtAct* | *pushOutLifAct* | *fwdContextAct* | *learnOrTransplantAct* | *oamIdAct* | *admtProfileAct* | *lagLbKeyActMetadata2* | *pmfCounter0PtrAct* |	Hardware action.

`instruction`	*integer*	FES 2nd instruction ID.
`orMask`	*integer*	OR-mask applied to FES source.
`orSelect`	*integer*	Source for OR-mask.
`polarity`	*integer*	If validBit is true, polarity of LSB.
`shift`	*integer*	Right bit-shift applied to FES source.

source	*enum: pmf3_key_a_63_0* | *pmf2_key_j_159_96* | *pmf2_direct_0_87_24* | *pmf3_tcam_1_31_0_tcam_0_63_32* | *pmf2_tcam_6_31_0_tcam_5_63_32* | *pmf3_key_b_31_0_key_a_159_128* | *pmf2_nexem_27_0_4_b0_tcam_7_63_32* | *pmf2_key_l_31_0_key_k_159_128* | *pmf3_direct_87_24* | *pmf2_key_k_127_64* | *pmf2_tcam_3_63_0* | *egress_lexem_4_b0_59_0* | *pmf2_lexem_27_0_4_b0_tcam_7_63_32* | *pmf2_direct_1_23_0_8_b0_direct_0_119_88* | *pmf3_sexem_27_0_4_b0_tcam_1_63_32* | *pmf3_key_a_31_0_nexem_59_28* | *pmf2_nexem_59_0_4_b0* | *pmf2_key_k_31_0_wexem_59_28* | *pmf2_key_i_63_0* | *pmf2_key_j_63_0* | *egress_key_d_63_0* | *pmf2_tcam_2_31_0_tcam_1_63_32* | *pmf2_tcam_0_31_0_32_b0* | *pmf2_key_j_127_64* | *pmf2_wexem_27_0_4_b0_nexem_59_28* | *pmf2_tcam_4_63_0* | *pmf2_tcam_6_63_0* | *pmf2_direct_0_23_0_8_b0_key_j_159_128* | *pmf3_tcam_1_63_0* | *pmf2_key_l_63_0* | *pmf2_tcam_7_31_0_tcam_6_63_32* | *pmf3_nexem_27_0_4_b0_tcam_1_63_32* | *pmf2_direct_1_87_24* | *pmf2_key_k_63_0* | *pmf2_lexem_59_0_4_b0* | *pmf3_key_a_31_0_sexem_59_28* | *pmf3_tcam_0_63_0* | *pmf2_sexem_27_0_4_b0_lexem_59_28* | *pmf3_tcam_0_31_0_32_b0* | *egress_tcam_1_payload_31_0_tcam_0_payload_63_32* | *pmf2_direct_0_119_56* | *pmf3_key_a_95_32* | *pmf2_tcam_0_63_0* | *pmf3_key_b_127_64* | *pmf2_key_i_31_0_sexem_59_28* | *pmf3_sexem_59_0_4_b0* | *pmf2_tcam_7_63_0* | *egress_key_d_31_0_tcam_1_payload_63_32* | *pmf3_direct_31_0_key_b_159_128*	Source bits for FES.

tcamAction	*enum: egrStatProfile0* | *statId* | *compressed_drop_strength_10* | *statId1GroupPolicer* | *egrCounterPtr1* | *femPolicerData* | *fwd_hdr_encapsulation* | *femInTtlCopy* | *femInTtlV6Copy* | *femTrafficPolicySetBridged-ToRoutedSviV6* | *femDropDirectFlow* | *statProfile0StormControl* | *femVtepDecapCounter* | *noSysHeader* | *udh2AlwaysOn* | *outlif0* | *compressed_egr_trap* | *stat-ProfileVniPolicerCounter* | *statProfile1* | *femPolicer* | *vxlanVt4ProfileToInLif-Profile1Fem* | *statProfile2* | *set_ecn1* | *statProfile5* | *femDropIpTapAgg* | *outlif0_16b* | *compressed_aegis_notification_and_log* | *egrCounterPtrAndStat-Profile1* | *compressed_aegis_log* | *femMplsCounter* | *femVxlanOrientHub* | *femFlowTrackingRocev2* | *femTrafficPolicySetBridged-ToRoutedV6* | *ace_type* | *statProfile6* | *overridingRedirectTrap* | *parsingStartTypeTxInject* | *egress_learn_enable* | *femTrafficPolicySetBridged-ToRoutedV4* | *set_ttl_3b* | *femDropPacl* | *femTrafficPolicySetBridged-ToRoutedSviV4* | *udh1AlwaysOn* | *user_header_1* | *learn_fid* | *default_egrDiscard* | *oamData* | *snp* | *userHeader1Type* | *learn_data_16_to_39* | *end-OfPacketEditing_always_on* | *orientation_is_hub* | *inLif0* | *dp_always_on* | *inTtl_always_on* | *tc_always_on* | *outlif0_17b* | *ts_always_on* | *ace_pointer* | *inLif0_always_on* | *irppCrossStageVar2* | *pphType_always_on* | *dest* | *aegis_lexem_cross_field_label_cascade* | *pemGeneralData3* | *latencyFlow* | *aegisNotificationMessage-*	Action SW label.

validBit	*boolean*	Whether LSB of FES source enables action.

2.1400.1.1.1.4 KeyConstruction

db	*enum: dbIpCpuTrafficPolicy* | *dbDirectExtractionPmf3* | *dbSegmentSecurityIp6* | *swEgressIpBridgeDot1q* | *dbVxlanRouting* | *dbElkResultIp6Racl* | *dbDot1x* | *dbEgressIp6Racl* | *dbFlow* | *dbIpSubIntfPbr* | *dbDirectExtraction-InterfacePolicing* | *dbIp6SubIntfAcl* | *dbIpMirror* | *dbMplsPbr* | *swIpOMpls* | *dbEgressOlp* | *dbVxlanFemDirect-Extraction* | *dbOutLifDirectExtraction* | *dbMcastCounters* | *dbIpv4TtBasic* | *dbIp6PostcardPolicy* | *dbDirectExtractionPmf1-SubintfSflow* | *dbMplsSubIntfPbr* | *dbSystem6* | *dbIp6RaclStage1* | *dbMacTapAgg* | *dbOamIdentification* | *dbQosUnsharedPolicer* | *dbIpDstXformed* | *dbHashingReplacement-Ipv6Low* | *dbElkResultIp6Pacl* | *dbIp6Decap* | *dbMogIp6DirectExtraction* | *dbSegmentSecurityIp4* | *dbPvlan* | *dbDirect-ExtractionPmf1Srv6Usid* | *dbDirectExtractionSetEcn* | *dbDirectExtractionPmf1-SetBridgedToRouted* | *dbIp6VrfSelection* | *dbDirectExtractionPmf1-CopyTtlV6* | *dbElkResultIpRacl* | *dbIp6Pbr* | *dbEgressIp6Pacl* | *dbTrafficPolicyIp4Copy-TtlSw* | *swEgressQinQ* | *dbDirectExtractionPmf1-Srv6UsidWFunc* | *dbIpPbr* | *dbSecondaryVrfDestDirect-Extraction* | *dbEgressRfc2544* | *dbIpPostcardPolicy* | *dbMacSystem* | *dbIpsec* | *dbVxlanMcastTunTerm* | *swVsiOverwriteAlways* | *dbMplsGreIp6* | *dbFlexRoute* | *dbIpMcastRouting* | *dbDirectExtractionSetDscp* | *dbVxlanMultihomingMcast*	PMF database.

`ffcIds`	*table(numeric string) = Ffc* see 2.1400.1.1.1.5	Mapping from FFC ID to FFC attributes.

2.1400.1.1.1.5 Ffc

`hwQualifier`	*enum: userHeader4Ext* | *pphInLifProfile0* | *keyIInitial* | *cmpKey0Decoded* | *ecmpLbKey0* | *greTunnelValid* | *statisticsAtr10* | *userHeader1Ext* | *itppDelta* | *stateTableData* | *incomingTagStructure* | *extStatisticsAtr1* | *packetHeaderSizeRange* | *snoopActionProfileIndex* | *learnExtData* | *ecmpLbKey2Metadata2* | *lfsr2* | *dstSysPort* | *tracePacket* | *userHeader1Type* | *ftmhVisibility* | *acInLifWideData* | *rpfDst* | *generalDataPmfContainer* | *btkOffsetSop* | *userHeader2Ext* | *bierStrOffset* | *elkLkpHit0* | *keyJInitial* | *elephantTrapInfo* | *cfgCoreId* | *fwdContext* | *l4opsEncoder2* | *mactEntryGrouping* | *nasid* | *aegisSportLabel* | *fcoeVftExist* | *outTmPort* | *cudOutlifOrMcdbPtr* | *extStatisticsAtr0* | *mirrorCode* | *fcoeIsEncap* | *iveBytesToAdd* | *encoder2* | *statisticsId10* | *protocol* | *ppPortPmfProfile* | *itmhPphType* | *ftmhSrcSysPort* | *stateDataWrite* | *fwdActionDp* | *weakTmProfile* | *generalData2* | *ftmhAqmProfile* | *fwdStrength* | *statisticsAtr9* | *systemHeadersSize* | *ipsecDecrypted* | *statisticsAtr11* | *ipv4FirstFragOrNonFrag* | *stateTableAddress* | *learnInfo* | *inPortKeyGenVar* | *latencyFlowId* | *rpfOpaqueField* | *fwdActionDestination* | *statisticsId0* | *ferStage1InDst* | *fwdPayload* | *nextMicroSidIsNull* | *encoder0* | *tmProfile* | *outLifProfileLfsr1InRange* |	Hardware qualifier.

index	*integer*	Header/layer index for base offset.
lsb	*integer*	Key offset LSB.
msb	*integer*	Key offset MSB.
offset	*integer*	Bit offset from base header/layer.
size	*integer*	Number of bits extracted by FFC.
source	*enum: cascade* | *headerOrMetadata* | *absoluteHeader* | *absoluteLayerRecord* | *forwardingHeader* | *metaData* | *layerRecord*	FFC source.

tcamQualifier	*enum:* *in_lif_data_aegis_base_policer_idx* | *hdr_4_ipv4_mc_opt_frag* | *in_lif_data_basePolicer_idx* | *srv6_next_sid_1* | *hdr_3_ethertype* | *l4ops_3b* | *in_lif_aegis_ignore_interface* | *ip_version_and_tc* | *null_qualifier_8b* | *hdr_5_ipv4_tcp_ctl_ack_psh_rst_syn* | *ipv4_mc* | *sys6_cascade* | *itmh_destination_ext_present* | *in_lif_data_0* | *hdr_2_ipv4_next_prtcl* | *full_fwd_domain_padded* | *in_lif_data_racl_ipv4* | *srv6_next_usid_2* | *flp_dport_xformed* | *hdr_4_ipv4_sip_high* | *augment_nibble_0* | *ipv6_mcast_prefix* | *global_out_lif_1* | *flp_sport_passthrough* | *gre_flags* | *orig_src_port* | *udf_32b_5* | *mpls_next_label* | *fwd_act_dest_encoding* | *fwd_hdr_ipv6_sip_high_32* | *sys_cascade* | *hdr_4_ipv4_dest_port* | *null_qualifier_pool0_6* | *ipv4_tcp_ctl* | *itmh_pph_base_present* | *vt_ip6_egress_racl* | *mpls_payload_type* | *injected_pph_forward_domain* | *vxlan_vt4_in_lif_profile* | *hdr_4_ipv6_hop_limit* | *tcp_first_option_kind* | *fwd_hdr_ipv4_mc* | *in_lif_data_vrf_selection* | *hdr_3_ipv6_dip_low_32* | *hdr_1_arp_opcode* | *lem_2nd_lookup_found* | *ipv6_tcp_ctl_bits_8_15* | *ipv4_dip_low* | *dip_idx_type* | *hdr_3_ipv6_dip_high_32* | *fwd_hdr_ipv6_sip_low_0* | *user_header_1_24b* | *hdr_4_da_0* | *flp_inner_dip_xformed* | *hdr_2_ipv4_ttl* | *orig_egress_port* | *hdr_3_ipv4_options* | *inner_ipv4_has_options* | *hdr_3_ipv6_tc* | *ptp_ase_use_ingress_time_compensation* | *fwd_hdr_ipv6_tc* | *postcard_marker_vxlan* | *tt1_result_13* |	Qualifier SW label.

2.1400.1.1.1.6 KeyLookup

appDb	*integer*	AppDbId for PMF key.

db	*enum: dbIpCpuTrafficPolicy* | *dbDirectExtractionPmf3* | *dbSegmentSecurityIp6* | *swEgressIpBridgeDot1q* | *dbVxlanRouting* | *dbElkResultIp6Racl* | *dbDot1x* | *dbEgressIp6Racl* | *dbFlow* | *dbIpSubIntfPbr* | *dbDirectExtraction-InterfacePolicing* | *dbIp6SubIntfAcl* | *dbIpMirror* | *dbMplsPbr* | *swIpOMpls* | *dbEgressOlp* | *dbVxlanFemDirect-Extraction* | *dbOutLifDirectExtraction* | *dbMcastCounters* | *dbIpv4TtBasic* | *dbIp6PostcardPolicy* | *dbDirectExtractionPmf1-SubintfSflow* | *dbMplsSubIntfPbr* | *dbSystem6* | *dbIp6RaclStage1* | *dbMacTapAgg* | *dbOamIdentification* | *dbQosUnsharedPolicer* | *dbIpDstXformed* | *dbHashingReplacement-Ipv6Low* | *dbElkResultIp6Pacl* | *dbIp6Decap* | *dbMogIp6DirectExtraction* | *dbSegmentSecurityIp4* | *dbPvlan* | *dbDirect-ExtractionPmf1Srv6Usid* | *dbDirectExtractionSetEcn* | *dbDirectExtractionPmf1-SetBridgedToRouted* | *dbIp6VrfSelection* | *dbDirectExtractionPmf1-CopyTtlV6* | *dbElkResultIpRacl* | *dbIp6Pbr* | *dbEgressIp6Pacl* | *dbTrafficPolicyIp4Copy-TtlSw* | *swEgressQinQ* | *dbDirectExtractionPmf1-Srv6UsidWFunc* | *dbIpPbr* | *dbSecondaryVrfDestDirect-Extraction* | *dbEgressRfc2544* | *dbIpPostcardPolicy* | *dbMacSystem* | *dbIpsec* | *dbVxlanMcastTunTerm* | *swVsiOverwriteAlways* | *dbMplsGreIp6* | *dbFlexRoute* | *dbIpMcastRouting* | *dbDirectExtractionSetDscp* | *dbVxlanMultihomingMcast*	PMF database.

lookupType	*enum: smallExactMatch | tcam | directExtraction | direct | doubleWideTcam | largeExactMatch | software*	PMF key lookup type.

2.1400.1.1.2 Preselector

context	*integer*	Context ID.
databases	*list of PmfDatabase* see 2.1400.1.1.2.1	List of PMF databases.
line	*integer*	Selection CAM line.
preselectorFields	*table(string) = PreselectorField* see 2.1400.1.1.2.2	Mapping from preselector field name to value and mask.

2.1400.1.1.2.1 PmfDatabase

db	*enum: dbIpCpuTrafficPolicy* | *dbDirectExtractionPmf3* | *dbSegmentSecurityIp6* | *swEgressIpBridgeDot1q* | *dbVxlanRouting* | *dbElkResultIp6Racl* | *dbDot1x* | *dbEgressIp6Racl* | *dbFlow* | *dbIpSubIntfPbr* | *dbDirectExtraction-InterfacePolicing* | *dbIp6SubIntfAcl* | *dbIpMirror* | *dbMplsPbr* | *swIpOMpls* | *dbEgressOlp* | *dbVxlanFemDirect-Extraction* | *dbOutLifDirectExtraction* | *dbMcastCounters* | *dbIpv4TtBasic* | *dbIp6PostcardPolicy* | *dbDirectExtractionPmf1-SubintfSflow* | *dbMplsSubIntfPbr* | *dbSystem6* | *dbIp6RaclStage1* | *dbMacTapAgg* | *dbOamIdentification* | *dbQosUnsharedPolicer* | *dbIpDstXformed* | *dbHashingReplacement-Ipv6Low* | *dbElkResultIp6Pacl* | *dbIp6Decap* | *dbMogIp6DirectExtraction* | *dbSegmentSecurityIp4* | *dbPvlan* | *dbDirect-ExtractionPmf1Srv6Usid* | *dbDirectExtractionSetEcn* | *dbDirectExtractionPmf1-SetBridgedToRouted* | *dbIp6VrfSelection* | *dbDirectExtractionPmf1-CopyTtlV6* | *dbElkResultIpRacl* | *dbIp6Pbr* | *dbEgressIp6Pacl* | *dbTrafficPolicyIp4Copy-TtlSw* | *swEgressQinQ* | *dbDirectExtractionPmf1-Srv6UsidWFunc* | *dbIpPbr* | *dbSecondaryVrfDestDirect-Extraction* | *dbEgressRfc2544* | *dbIpPostcardPolicy* | *dbMacSystem* | *dbIpsec* | *dbVxlanMcastTunTerm* | *swVsiOverwriteAlways* | *dbMplsGreIp6* | *dbFlexRoute* | *dbIpMcastRouting* | *dbDirectExtractionSetDscp* | *dbVxlanMultihomingMcast*	PMF database.

2.1400.1.1.2.2 PreselectorField

mask	*integer*	Field mask.
value	*integer*	Field value.

2.1401 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) pmf dbinfo [...]

faps	*table(string) = TcamDbInfoTable* see 2.1401.1	TCAM feature DbInfo information, keyed by FAP name.

2.1401.1 TcamDbInfoTable

dbActions	*table(string) = TcamDbInfoActionTable* see 2.1401.1.1	Database actions, keyed by DB name.
dbInfoDatabases	*table(string) = TcamDbInfoData* see 2.1401.1.2	DbInfo databases, keyed by DB name.
dbKeys	*table(string) = TcamDbInfoKeyTable* see 2.1401.1.3	Database keys, keyed by DB name.
dbQualifiers	*table(string) = TcamDbInfoQualifierTable* see 2.1401.1.4	Database qualifiers, keyed by DB name.

2.1401.1.1 TcamDbInfoActionTable

ruleActions	*table(string) = TcamDbInfoActionData* see 2.1401.1.1.1	Rule actions, keyed by rule name.

2.1401.1.1.1 TcamDbInfoActionData

actionLsb	*integer*	Action Lsb.
actionMsb	*integer*	Action Msb.
isFem	*boolean*	This is Fem.
sdkAction	*boolean*	This is an Sdk Action.

2.1401.1.2 TcamDbInfoData

andBits	*integer*	And Bits.
keySize	*integer*	Key Size in bits.
orBits	*integer*	Or Bits.
ownerBits	*enum: Vtt | Erpp | Pmf | Flp*	Owner bits.
[primaryDb]	*string*	Primary DB.
profileIndex	*integer*	Profile Index.
[reservedBanks]	*list of integer*	Reserved Banks.
storage **	*enum: Halo | Internal | Software | External | Exem*	Database storage type. **Since: 4.34.0

2.1401.1.3 TcamDbInfoKeyTable

ruleKeys	*table(numeric string) = TcamDbInfoKeyData* see 2.1401.1.3.1	Rule keys, keyed by rule name.

2.1401.1.3.1 TcamDbInfoKeyData

cycle	*integer*	cycle.
key	*string*	Key.

2.1401.1.4 TcamDbInfoQualifierTable

ruleQualifiers	*table(string) = TcamDbInfoQualifierData* see 2.1401.1.4.1	Rule Qualifiers, keyed by rule name.

2.1401.1.4.1 TcamDbInfoQualifierData

keyLsb	*integer*	Key Lsb.
keyMsb	*integer*	Key Msb.
keyOffset	*integer*	Key Offset.
lostBits	*integer*	Lost Bits.
nCopyBits	*integer*	Number Copy Bits.
qualLsb	*integer*	Qualifer Lsb.
qualMsb	*integer*	Qualifer Msb.
second	*boolean*	This qualifier is on the second key.

2.1402 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) ppmc multicast [...]

[cmdErr]	*string*	Error Message.
[ppmcEntries]	*table(numeric string) = PpmcEntries* see 2.1402.1	A collection of the mappings from ppmc index to (global outlif0, global outlif1) keyed by fapId.

2.1402.1 PpmcEntries

entries	*list of PpmcDoubleOutlifEntry* see 2.1402.1.1	List of ppmc multicast entries per fap.

2.1402.1.1 PpmcDoubleOutlifEntry

globalOutlif0	*integer*	Global Outlif0.
globalOutlif1	*integer*	Global Outlif1.
index	*integer*	Ppmc Index.

2.1403 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) priority-flow-control buffer profile [...]

faps	*table(string) = FapConfig* see 2.1403.1	Mapping of FAP name to its PFC thresholds.
globalConfig	*GlobalConfig* see 2.1403.2	All global CLI config parameters related to PFC.

2.1403.1 FapConfig

rateClasses	*table(string) = Threshold* see 2.1403.1.1	A mapping of rate class to its thresholds.

2.1403.1.1 Threshold

flowControl	*FlowControlThreshold* see 2.1403.1.1.1	Flow control threshold parameters.
reject	*RejectThreshold* see 2.1403.1.1.2	Reject threshold parameters.

2.1403.1.1.1 FlowControlThreshold

alpha	*integer*	FADT alpha.
maxThreshold	*integer*	FADT max flow control threshold in bytes.
minThreshold	*integer*	FADT min flow control threshold in bytes.
offset	*integer*	Resume offset in bytes.

2.1403.1.1.2 RejectThreshold

alpha	*integer*	FADT alpha.
maxThreshold	*integer*	FADT max reject threshold in bytes.
minThreshold	*integer*	FADT min reject threshold in bytes.

2.1403.2 GlobalConfig

bufferUtilizationFactor	*integer*	DRAM utilization factor in percentage used in determining PFC thresholds in bytes from the number of buffers available for each source port and traffic class.
defaultBufferUtilization-Factor	*integer*	Default DRAM utilization factor in percentage.
defaultNumTrafficClasses	*integer*	Default number of traffic classes in use.
defaultXoffTime	*integer*	Default XOFF duration in microseconds.
defaultXonTime	*integer*	Default XON duration in microseconds.
numTrafficClasses	*integer*	Number of traffic classes in use.
xoffTime	*integer*	Configured XOFF duration in microseconds.
xonTime	*integer*	Configured XON duration in microseconds.

2.1404 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) ptp hardware-sync [...]

slaves	*table(string) = SlaveModel* see 2.1404.1	A Mapping between a TimeSync Slave and its time synchronization information.

2.1404.1 SlaveModel

[crcErrors]	*integer*	CRC Error(s).
[fifoRetryLimitExceeded] **	*integer*	FIFO Retry Limit Exceeded Error(s). **Since: 4.18.1
[invalidTimestampErrors] **	*integer*	Invalid Timestamp Error(s). **Since: 4.18.1
[localCounter]	*integer*	Latest Local Counter.
[masterTod]	*integer*	Latest Master Time of Day (ToD).
[phaseDifferences]	*list of integer*	Last 4 phase differences (in ns).
[retriesLeftSelfTest] **	*integer*	Retries Left after self test. **Since: 4.21.3
[slaveFreqErrors] **	*integer*	Slave Frequency Error(s). **Since: 4.18.1
state	*enum: synchronizing | failed | stable | disabled | initialized | switchover*	Operational State.
[timeToStability]	*integer*	Time to stability (in s).
[timeoutErrors] **	*integer*	Timeout Error(s). **Since: 4.18.1
[updates]	*integer*	Sync Update(s).

2.1405 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) qos policy mapping [...]

faps	*table(string) = FapQosPolicyMapping* see 2.1405.1	Qos policy mappings, keyed by fapName.

2.1405.1 FapQosPolicyMapping

pmaps	*table(string) = PolicyMapMapping* see 2.1405.1.1	Policy maps, keyed by policy map name.
unitId	*integer*	Unit Id.

2.1405.1.1 PolicyMapMapping

featureDbs	*table(string) = FeatureDbMapping* see 2.1405.1.1.1	FeatureDbs, keyed by featureDb name.

2.1405.1.1.1 FeatureDbMapping

policyKeyTypeMappings	*table(string) = PolicyKeyTypeMapping* see 2.1405.1.1.1.1	Policy key type mapping, keyed by keyType(ruleShareType,labelShareType).

2.1405.1.1.1.1 PolicyKeyTypeMapping

classMaps	*list of ClassMapMapping* see 2.1405.1.1.1.2	Class Map mappings in the Policy Map.
labelSpaceType	*string*	Label Space Type.
labelValue	*integer*	Label Value.
ruleShareType	*string*	Rule Share Type.
tcamActionSwTable	*string*	Tcam Action software table name.
tcamDb	*string*	Tcam database.
tcamEntrySwTable	*string*	Tcam Entry software table name.

2.1405.1.1.1.2 ClassMapMapping

bankAndOffsetRange	*list of BankAndOffsetRange* see 2.1405.1.1.1.3	Range of entries in software table associated with class map.
[classOffset]	*integer*	Class offset, in case of unshared policers.
cmapName	*string*	Class Map name.
[counterIndex]	*integer*	Counter index, if configured.
[policerIndex]	*integer*	Policer index, if configured.
ruleRange	*list of RuleRange* see 2.1405.1.1.1.5	Range of rules associated with class map.

2.1405.1.1.1.3 BankAndOffsetRange

`end`	*BankAndOffset* see 2.1405.1.1.1.4	End of entries in software table.
`start`	*BankAndOffset* see 2.1405.1.1.1.4	Start of entries in software table.

2.1405.1.1.1.4 BankAndOffset

`bank`	*integer*	Bank number for the software table entry key.
`offset`	*integer*	Offset in the bank for the software table entry key.

2.1405.1.1.1.5 RuleRange

`end`	*integer*	End of rule range.
`start`	*integer*	Start of rule range.

2.1406 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) qos tcam mapping [...]

fapTcamMapping	*table(string) = FapQosAclTcamMappingModel* see 2.1406.1	List of tcam mapping models per fap.

2.1406.1 FapQosAclTcamMappingModel

fapName	*string*	Name of the fap.
pmapMapping	*table(string) = PolicyMapTcamMappingModel* see 2.1406.1.1	Policy-map models on the fap.

2.1406.1.1 PolicyMapTcamMappingModel

policyMapName	*string*	Name of policy-map.
policyTypeMapping	*table(string) = PolicyTypeTcamMappingModel* see 2.1406.1.1.1	Mapping models per policy type.

2.1406.1.1.1 PolicyTypeTcamMappingModel

policyKeyTypeMapping	*table(string) = PolicyKeyTypeTcamMappingModel* see 2.1406.1.1.1.1	Mapping models per policy key type.
policyType	*string*	Type of class-maps listed in the model.

2.1406.1.1.1.1 PolicyKeyTypeTcamMappingModel

appliedTo	*integer*	Applied to.
classMapMapping	*table(string) = ClassMapTcamMappingModel* see 2.1406.1.1.1.2	Class-maps in the policy-map.
classMapOrder	*list of string*	Order of class-maps in policy-map.
dbType	*string*	Db used by the class-maps listed in the model.
keyType	*string*	Key Type.

2.1406.1.1.1.2 ClassMapTcamMappingModel

classMapName	*string*	Class-map name.
[classOffset] **	*string*	Associated class-offset, if configured. **Since: 4.28.2
[counterIndex]	*string*	Associated counterB index, if configured.
[policerIndex]	*string*	Associated policer-meter index, if configured.
ruleRange	*RuleRangeModel* see 2.1406.1.1.1.3	Associated range of rules in aad.

tcamRange	*TcamRangeModel* see 2.1406.1.1.1.4	Associated range of tcam-entries.

2.1406.1.1.1.3 RuleRangeModel

end	*integer*	End of range.
start	*integer*	Start of range.

2.1406.1.1.1.4 TcamRangeModel

discontiguousRange **	*boolean*	TCAM-Range is discontiguous. **Since: 4.23.1
endEntry	*TcamEntryModel* see 2.1406.1.1.1.5	End entry of tcam range.
startEntry	*TcamEntryModel* see 2.1406.1.1.1.5	Start entry of tcam range.

2.1406.1.1.1.5 TcamEntryModel

banks	*list of integer*	Bank in which the tcam entry is located.
offset	*integer*	Offset of the entry in bank.

2.1407 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) qos tcam mapping bank BANK ENTRY [...]

fapTcamEntry	*table(string) = FapQosAclTcamEntryModel* see 2.1407.1	TcamEntry Model per fap.

2.1407.1 FapQosAclTcamEntryModel

[aclGroup]	*string*	Corresponding aclGroup.
[aclNumVal]	*integer*	aclNum.
[aclType]	*string*	aclType.
[aclTypes]	*integer*	Number of aclTypes.
actions	*list of ActionModel* see 2.1407.1.1	dpMeterCommand action.
[classMap]	*string*	Name of class-map associated to the entry.
[dbType]	*string*	dbType.
[fapName]	*string*	Name of the fap.
[matchingRuleId]	*integer*	Corresponding rule-id in the associated aad.
[policyMap]	*string*	Name of policy-map associated to the entry.
qosEntry	*boolean*	Does Qos feature own this entry?
qualifiers	*list of QualifierModel* see 2.1407.1.2	List of qualifiers in the tcam-entry.
[skippedEntry]	*boolean*	Is it a skipped entry?
[startRuleId]	*integer*	First rule id of the associated class-map.

2.1407.1.1 ActionModel

fields **	*table(string) = integer*	Action field values, keyed by action field names. **Since: 4.23.2
name	*string*	Action name.
[valid]	*boolean*	Is action valid?
value	*integer*	Action value.

2.1407.1.2 QualifierModel

mask	*integer*	Qualifier mask.
name	*string*	Qualifier name.
value	*integer*	Qualifier value.

2.1408 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) qos tcam mapping policy-map PMAP [...]

see 2.1406

2.1409 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) sflow accel [...]

collectorVrf	*string*	sFlow accel selected collector VRF.
fapResourceInfo	*table(string) = PlatformSflowAccelResourceInfo* see 2.1409.1	sFlow accel resources keyed by fapName.

2.1409.1 PlatformSflowAccelResourceInfo

mcid	*integer*	sFlow accel multicast Id.
outLif	*integer*	sFlow accel global outLif.
tunnelOutLifs	*list of PlatformSflowAccelTunnelOutlifInfo* see 2.1409.1.1	sFlow accel tunnel outLifs for this collector.

2.1409.1.1 PlatformSflowAccelTunnelOutlifInfo

collectorIP	*IP address*	source address for group interface.
tunnelOutlif	*integer*	sFlow accel global outlif.
udpPort	*integer*	sFlow accel UDP port associated with collector IP.
vlanId	*integer*	Internal VLAN Id mapped to this collector VRF.

2.1410 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) sflow accel counters [...]

countersDict	*table(string) = PlatformSflowAccelCountersInfo* see 2.1410.1	sFlow accel counters keyed by str(fapName.coreId).

2.1410.1 PlatformSflowAccelCountersInfo

intfCounterList	*list of PlatformSflowAccelIntfCounters* see 2.1410.1.1	sFlow accel counters interface list for specific fap and core.

2.1410.1.1 PlatformSflowAccelIntfCounters

counterIdx	*integer*	Counter Index.
counterValue	*integer*	Counter Value.
interfaceName	*interface name*	Interface Name.

2.1411 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) split-horizon group [...]

vlans	*table(numeric string) = VlanSplitHorizonGroup* see 2.1411.1	A mapping of VLAN ID to split horizon and spoke group information.

2.1411.1 VlanSplitHorizonGroup

groups	*table(string) = SplitHorizonGroupDetails* see 2.1411.1.1	Information of Split horizon and spoke group(s) in a VLAN.

2.1411.1.1 SplitHorizonGroupDetails

inlifOrientation	*integer*	Inlif orientation value.
inlifProfile	*integer*	Inlif profile value.
interfaces	*list of string*	Member interfaces of the split horizon or spoke group.
outlifOrientation	*integer*	Outlif orientation value.
outlifProfile	*integer*	Outlif profile value.

2.1412 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) subinterface mapping [...]

subInterfaces	*table(string) = SubInterfaceMap* see 2.1412.1	A mapping of subinterface name to its hardware programming details.

2.1412.1 SubInterfaceMap

parentInterfaces	*table(string) = SubIntfInfo* see 2.1412.1.1	A mapping of parent interface name to its subinterface details.

2.1412.1.1 SubIntfInfo

eveProfile **	*integer*	Egress vlan edit profile index. **Since: 4.29.1
fap	*integer*	FAP ID.
fapPortId	*integer*	FAP port ID.
lifEntryVsi	*integer*	Virtual switch instance.
lifIndex	*integer*	Logical interface index.
outAcIndex	*integer*	Output attachment circuit index.
outAcTag	*string*	Output attachment circuit tag.
vlanDomain	*integer*	VLAN domain.

2.1413 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) subinterface mapping l2 [...]

subInterfaces	*table(Interface name) = SubInterfaceL2Map* see 2.1413.1	A mapping of subinterface name to its hardware programming details.

2.1413.1 SubInterfaceL2Map

parentInterfaces	*table(Interface name) = SubIntfL2Info* see 2.1413.1.1	A mapping of parent interface name to its subinterface details.

2.1413.1.1 SubIntfL2Info

encapVlanTag	*string*	Output attachment circuit tag.
eveProfile **	*integer*	Egress vlan edit profile index. **Since: 4.29.1
fap	*integer*	FAP ID.
fapPortId	*integer*	FAP port ID.
glemIndex	*integer*	GlobalOutlif.
lifEntryVsi	*integer*	Virtual switch instance.
lifIndex	*integer*	Logical interface index.
outAcIndex	*integer*	Output attachment circuit index.
vlanDomain	*integer*	VLAN domain.

2.1414 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) subinterface mapping l3 [...]

subInterfaces	*table(string) = SubInterfaceL3Map* see 2.1414.1	A mapping of subinterface name to its hardware programming details.

2.1414.1 SubInterfaceL3Map

parentInterfaces	*table(string) = SubIntfL3Info* see 2.1414.1.1	A mapping of parent interface name to its subinterface details.

2.1414.1.1 SubIntfL3Info

encapVlanTag	*string*	Output attachment circuit tag.
eveProfile **	*integer*	Egress vlan edit profile index. **Since: 4.29.1
fap	*integer*	FAP ID.
fapPortId	*integer*	FAP port ID.
lifEntryVsi	*integer*	Virtual switch instance.
lifIndex	*integer*	Logical interface index.
outAcIndex	*integer*	Output attachment circuit index.
propagationProfile	*integer*	Propagation profile.

protectionPointer	*string*	Protection pointer.
qosProfile	*integer*	QoS profile.
vlanDomain	*integer*	VLAN domain.

2.1415 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) tcam action-priority [...]

faps	*table(string) = TcamFapActionPriorityInfo* see 2.1415.1	TCAM feature action priority information, keyed by FAP name.

2.1415.1 TcamFapActionPriorityInfo

databases	*table(string) = TcamActionPriorityInfo* see 2.1415.1.1	TCAM action priorities, keyed by db name.

2.1415.1.1 TcamActionPriorityInfo

dbActionPriorityActive	*integer*	Active TCAM database action priority.
dbActionPriorityDefault	*integer*	Default TCAM database action priority.

2.1416 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) tcam port qualifiers [...]

maxSharedSizes	*table(string) = integer*	TCAM shared qualifier size limits per share type.
profiles	*table(string) = TcamFapPortQualifiersInfo* see 2.1416.1	TCAM faps port qualifiers information, keyed by profile name.

2.1416.1 TcamFapPortQualifiersInfo

fapTypes	*table(string) = TcamFapAttrPortQualifiersInfo* see 2.1416.1.1	TCAM fap attributes for port qualifiers, keyed by fapType.

2.1416.1.1 TcamFapAttrPortQualifiersInfo

active_qualifiers	*table(string) = ActiveTcamPortQualifiersInfo* see 2.1416.1.1.1	Active TCAM port qualifiers, keyed by qualifier name.
explicit_qualifiers	*table(string) = ExplicitTcamPortQualifiersInfo* see 2.1416.1.1.2	Explicit TCAM port qualifiers, keyed by qualifier name.
implicit_inactive_qualifiers	*table(string) = InactiveTcamPortQualifiersInfo* see 2.1416.1.1.3	Inactive TCAM port qualifiers, keyed by qualifier name.
linecards	*list of string*	Linecards associated with this profile, fapType.

2.1416.1.1.1 ActiveTcamPortQualifiersInfo

databases	*table(string) = TcamPortQualifiersDbFeatures* see 2.1416.1.1.1.2	TCAM databases associated with the qualifier.
portQualifierActiveSize	*integer*	Active TCAM port qualifier size.
portQualifierOffset	*integer*	TCAM port qualifier bit offset.
tcamPortQualifierAttrs	*TcamPortQualifierAttrs* see 2.1416.1.1.1.1	TCAM attributes associated with the qualifier.

2.1416.1.1.1.1 TcamPortQualifierAttrs

portQualifierDefaultSize	*integer*	Default TCAM port qualifier size.
portQualifierScaleSource	*enum: scaleSourceUnsharedPolicer | scaleSourcePortQualifierSize | scaleSourceFixedSize*	TCAM port qualifier scale source.
portQualifierShareType	*enum: shareInPort | shareInLifData | sharePpmc | shareUdh4*	TCAM port qualifier share type.

2.1416.1.1.1.2 TcamPortQualifiersDbFeatures

features	*list of string*	TCAM features associated with the database.

2.1416.1.1.2 ExplicitTcamPortQualifiersInfo

keyfields	*list of string*	TCAM key-fields associated with the qualifier.
tcamPortQualifierAttrs	*TcamPortQualifierAttrs* see 2.1416.1.1.1.1	TCAM attributes associated with the qualifier.

2.1416.1.1.3 InactiveTcamPortQualifiersInfo

databases	*table(string) = TcamPortQualifiersDbFeatures* see 2.1416.1.1.1.2	TCAM databases associated with the qualifier.
tcamPortQualifierAttrs	*TcamPortQualifierAttrs* see 2.1416.1.1.1.1	TCAM attributes associated with the qualifier.

2.1417 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) tcam summary [...]

faps	*table(string) = TcamFapInfo* see 2.1417.1	Map of FAPs to their TCAM bank information.

2.1417.1 TcamFapInfo

bankInfo	*list of TcamBankInfo* see 2.1417.1.1	List of TCAM bank numbers and their corresponding TCAM databases.

2.1417.1.1 TcamBankInfo

bankNum	*integer*	TCAM bank number.
dbName	*string*	TCAM database used name.
dbNameReserved **	*string*	TCAM database reserved name. **Since: 4.20.5

2.1418 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) tpid [...]

tpids	*list of PlatformTpid* see 2.1418.1	Globally registered TPIDs.

2.1418.1 PlatformTpid

index	*integer*	TPID register index.
value	*integer*	TPID value.

2.1419 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) voq credit rates [...]

faps	*table(string) = FapStatus* see 2.1419.1	Mapping of FAP name to its credit rates.

2.1419.1 FapStatus

baseRate	*integer*	Base credit rate.
levels	*table(numeric string) = LevelStatus* see 2.1419.1.1	Credit rates per level.

2.1419.1.1 LevelStatus

creditRate	*integer*	Credit rate in bits per second.
factor	*floating point number*	Credit rate factor.

2.1420 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) vpls pseudowire decap [...]

revision 2

pseudowires	*table(Interface name) = VplsPseudowireDetails* see 2.1420.1	VPLS decap entry information keyed by pw interface.

2.1420.1 VplsPseudowireDetails

active	*boolean*	Pseudowire is active.
[controlWord]	*boolean*	ControlWord is present.
[flowLabel]	*boolean*	FlowLabel is present.
[globalInLif]	*integer*	GlobalInLif value.
[hwFec]	*integer*	Hardware FEC table index.
[inLifProfile]	*integer*	Jericho2LifProfiles value.
[instanceContext]	*string*	VPLS-pwInstance-neighbour IP-pwId-pwInterface.
label	*integer*	VPLS MPLS label.
[orientation]	*integer*	In/Out Orinetation value.
[pseudowireGroup]	*string*	Pw group name.
termProfile	*integer*	Index to Tunnel termination profile.
vlans	*table(numeric string) = VlanToTag* see 2.1420.1.1	VPLS Pw information keyed by instfDisplayContext.

2.1420.1.1 VlanToTag

lifIndex	*integer*	Index to inLif table.
[normalizedTag]	*integer*	Dot1Q Tag.

2.1421 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) vrf selection inlif [...]

banks	*table(numeric string) = VrfSelectionInLifBank* see 2.1421.1	VRF selection InLIF banks, keyed by index.

2.1421.1 VrfSelectionInLifBank

inLifs	*table(numeric string) = VrfSelectionInLifEntry* see 2.1421.1.1	VRF selection InLIF entries, keyed by index.

2.1421.1.1 VrfSelectionInLifEntry

fallbackVrf	*integer*	Fallback VRF ID.
inLifProfile	*integer*	InLIF profile index.
lemVrf	*integer*	LEM VRF ID.
teVrf	*integer*	TE VRF ID.

2.1422 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) vrf selection tcam shadow [...]

[ipv4TcamEntries]	*list of VrfSelectionV4TcamEntries* see 2.1422.2	A collection of IPv4 tcam entries.
[ipv6ExtendedTcamEntries] **	*list of VrfSelection-ExtendedV6TcamEntries* see 2.1422.1	A collection of IPv6 tcam entries. **Since: 4.30.1
[ipv6TcamEntries]	*list of VrfSelectionV6TcamEntries* see 2.1422.3	A collection of IPv6 tcam entries.

2.1422.1 VrfSelectionExtendedV6TcamEntries

bank	*string*	TCAM Bank.
dscp	*integer*	DSCP.
dscpMask	*integer*	DSCP Mask.
index	*integer*	TCAM Index.
label	*integer*	Policy Label.
labelMask	*integer*	Policy Label Mask.
lemVrf	*integer*	LEM VRF ID.
sourcePrefix	*IP address prefix*	IPv6 Source prefix.
teVrf	*integer*	TE VRF ID.

2.1422.2 VrfSelectionV4TcamEntries

bank	*integer*	TCAM Bank.
dscp	*integer*	DSCP.
dscpMask	*integer*	DSCP Mask.
inLifBank	*integer*	InLif Bank.
inLifIndex	*integer*	InLif Index.
index	*integer*	TCAM Index.
ipProtocol	*integer*	IP Protocol Mask.
ipProtocolMask	*integer*	IP Protocol.
label	*integer*	Policy Label.
labelMask	*integer*	Policy Label Mask.
sourcePrefix **	*IP address prefix*	IP Source prefix. **Since: 4.27.0

2.1422.3 VrfSelectionV6TcamEntries

bank	*integer*	TCAM Bank.
dscp	*integer*	DSCP.
dscpMask	*integer*	DSCP Mask.
inLifBank	*integer*	InLif Bank.
inLifIndex	*integer*	InLif Index.
index	*integer*	TCAM Index.
label	*integer*	Policy Label.

labelMask	*integer*	Policy Label Mask.

2.1423 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) vxlan egress filter multihoming [...]

ethernetSegmentToMultihome-Labels	*table(Interface name) = EthernetSegmentTo-MultihomeInfo* see 2.1423.1	Mapping from ethernet segment interfaces to OutLIF profiles.
peerVtepIpToInLifProfiles	*table(IPv4 or IPv6 address) = integer*	Mapping from peer VTEP IPs to InLIF profiles.

2.1423.1 EthernetSegmentToMultihomeInfo

outLifProfile	*integer*	OutLIF Profile.
peerVtepIps	*list of IP address*	A list of peer VTEP IPs.

2.1424 show platform (fap | arad | jericho | jericho2 | jericho3 | jericho4) vxlan multicast route underlay [...]

underlayMrouteEntries	*list of VxlanUnderlayMrouteBase* see 2.1424.1	A collection of underlay multicast IPv4 routes with EVPN VxLAN.
underlayMrouteV6Entries **	*list of VxlanUnderlayMrouteBase* see 2.1424.1	A collection of underlay multicast IPv6 routes with EVPN VxLAN. **Since: 4.35.0

2.1424.1 VxlanUnderlayMrouteBase

Could also be an instance of:
VxlanUnderlayMrouteV4Entry 2.1424.2
VxlanUnderlayMrouteV6Entry 2.1424.3

2.1424.2 VxlanUnderlayMrouteV4Entry

destination	*IP address*	Destination IP address.
lifIndex	*integer*	Logical interface index.
source	*IP address*	Source IP address.
vlanId	*integer*	VLAN ID.

2.1424.3 VxlanUnderlayMrouteV6Entry

destination	*IP address*	Destination IP address.
lifIndex	*integer*	Logical interface index.

2.1425 show platform (fap | fe | arad | jericho | jericho2 | jericho3 | jericho4 | fe1600 | fe3600 | ramon | ramon3) fabric [...]

fapFeSerdesInfo	*table(string) = FapFeSerdesInfo* see 2.1425.1	Maps Fap/Fe name to all its serdes.

2.1425.1 FapFeSerdesInfo

linkActiveMask	*list of integer*	Link Active Mask.
peerSerdesInfo	*table(numeric string) = SerdesInfo* see 2.1425.1.1	Maps SerdesId to peer's Serdes information.
serdesInfo	*table(numeric string) = SerdesInfo* see 2.1425.1.1	Maps SerdesId to Serdes information.

2.1425.1.1 SerdesInfo

adminStatus	*enum: Down | Up*	Serdes Admin status.
[correctedCells]	*integer*	Corrected cells.
[correctedCellsLastOccurred] **	*floating point number*	Time Corrected cells last occurred in UTC. **Since: 4.17.0
[correctedCellsOverflow]	*boolean*	Corrected cells overflowed.
crcErrorCells	*integer*	Cells received with CRC errors.
[crcErrorCellsChanges] **	*integer*	Times CRC errors has changed. **Since: 4.33.1
crcErrorCellsOverflow	*boolean*	Cells received with CRC errors overflowed.
[crcErrorsLastOccurred]	*floating point number*	Time CRC errors last occurred in UTC.
[fecCells]	*integer*	FEC corrected cells.
[fecCellsLastOccurred]	*floating point number*	Time FEC cells last occurred in UTC.
[fecCellsOverflow]	*boolean*	FEC corrected cells.
[fecErrorBits] **	*integer*	FEC corrected bits. **Since: 4.32.2
[fecErrorBitsOverflow] **	*boolean*	FEC corrected bits overflowed. **Since: 4.32.2
[fecErrorSymbols] **	*integer*	FEC corrected symbols. **Since: 4.32.2
[fecErrorSymbolsOverflow] **	*boolean*	FEC corrected symbols overflowed. **Since: 4.32.2
interruptsInfo	*table(string) = InterruptInfo* see 2.1425.1.1.1	Maps Interrupt name to interrupt info.
[intfId] **	*string*	Fabric Interface Name. **Since: 4.32.1
isolatedCount	*integer*	Operational status changed to Isolated count.
[isolatedLastOccurred]	*floating point number*	Time status change to Isolated occurred in UTC.
leakyBucketTokens	*integer*	Tokens in Leaky Bucket which monitors serdes health.
maxInFifoCells	*integer*	Maximum cells In-Fifo.

[maxInFifoLastOccurred]	*floating point number*	Time maximum In-Fifo last occurred in UTC.
maxOutFifoCells	*integer*	Maximum cells in Out-Fifo.
[maxOutFifoLastOccurred]	*floating point number*	Time maximum Out-Fifo last occurred in UTC.
operationalStatus	*enum: Cleared | Down | Isolated | Up*	Serdes Operational status.
[peerFapFeName]	*string*	Peer's Fap/Fe name.
[peerSerdesId]	*integer*	Peer's Serdes Id.
pollLastOccurred **	*floating point number*	Time serdes counters were last polled in UTC. **Since: 4.32.2
[rxCells]	*integer*	Received cells.
[rxCellsOverflow]	*boolean*	Received cells overflowed.
[rxControlCells]	*integer*	Received control cells.
[rxControlCellsOverflow]	*boolean*	Received control cells overflowed.
[rxDataRate] **	*integer*	Receive data rate in Mbps. **Since: 4.21.3
[txCells]	*integer*	Transmitted cells.
[txCellsOverflow]	*boolean*	Transmitted cells overflowed.
[txDataRate] **	*integer*	Transmit data rate in Mbps. **Since: 4.21.3

2.1425.1.1.1 InterruptInfo

interruptCount	*integer*	Interrupt occurred count.
[lastOccurred]	*floating point number*	Time interrupt last occurred in UTC.

2.1426 show platform (fap | fe | arad | jericho | jericho2 | jericho3 | jericho4 | fe1600 | fe3600 | ramon | ramon3) fabric detail [...]

see 2.1425

2.1427 show platform (fap | fe | arad | jericho | jericho2 | jericho3 | jericho4 | fe1600 | fe3600 | ramon | ramon3) fabric interface mapping [...]

interfaces	*table(Interface name) = FabricIntfToSerdesMapping* see 2.1427.1	Maps interface name to serdes IDs.

2.1427.1 FabricIntfToSerdesMapping

chip	*string*	Chip name.
interface	*string*	Interface name.
logicalSerdesId	*integer*	Logical SDK serdes ID.
serdesId	*integer*	FAP or FE serdes ID.

2.1428 show platform (fap | fe | arad | jericho | jericho2 | jericho3 | jericho4 | fe1600 | fe3600 | ramon | ramon3) fabric rates mbps [...]

see 2.1425

2.1429 show platform (fap | jericho2) mac security [...]

faps	*table(string) = MacSecTableFap* see 2.1429.1	A mapping of FAP name to MACsec properties.

2.1429.1 MacSecTableFap

forwardingEngineEncryption	*boolean*	Forwarding engine encryption is enabled.
[interfaces]	*table(string) = InterfacesEntry* see 2.1429.1.1	A mapping of interface name to MACsec properties.
is2bAssocNumSupported	*boolean*	2b association number is supported.

2.1429.1.1 InterfacesEntry

[bypass]	*list of string*	Bypass MACsec encryption/decryption.
[egress]	*EgressEntry* see 2.1429.1.1.1	The egress indicies.
enabled	*boolean*	MACsec is enabled.
[ingress]	*IngressEntry* see 2.1429.1.1.2	The ingress indicies.
instance	*integer*	The MACsec instance #.
port	*integer*	The MACsec port #.
[svTag]	*integer*	The svTag #.

2.1429.1.1.1 EgressEntry

saIndex	*integer*	The egress saIndex.
scIndex	*integer*	The egress scIndex.

2.1429.1.1.2 IngressEntry

saIndex	*list of integer*	The ingress saIndex.
scIndex	*integer*	The ingress scIndex.
scTcamIndex **	*integer*	The ingress scTcamIndex. **Since: 4.33.0
spIndex	*integer*	The ingress spIndex.

2.1430 show platform (fap | jericho2) mac security counters default [...]

[egress]	*DefaultEntCounterTable-Direction* see 2.1430.1	The egress FAPs.
[ingress]	*DefaultEntCounterTable-Direction* see 2.1430.1	The ingress FAPs.

2.1430.1 DefaultEntCounterTableDirection

faps	*table(string) = DefaultEntCounterTableFap* see 2.1430.1.1	A mapping of FAP name to MACsec instances.

2.1430.1.1 DefaultEntCounterTableFap

instances	*table(numeric string) = DefaultEntCounterTableSecInst* see 2.1430.1.1.1	A mapping of MACsec instance number to hardware tables.

2.1430.1.1.1 DefaultEntCounterTableSecInst

tables	*table(string) = hwTableEntry* see 2.1430.1.1.1.1	A mapping of hardware table names to MACsec counters.

2.1430.1.1.1.1 hwTableEntry

counters	*table(string) = integer*	A mapping of counter name to counter value.

2.1431 show platform (fap | jericho2) policer fairness [...]

faps	*table(string) = MeterToFairnessLevelMapping* see 2.1431.1	Mapping from FAP name to meter engine ID.

2.1431.1 MeterToFairnessLevelMapping

meters	*table(string) = integer*	Mapping from meter engine id to fairness level.

2.1432 show platform (fe | fe1600 | fe3600 | ramon | ramon3) [...]

switches	*table(string) = FeInfo* see 2.1432.1	Maps fabric chip names to their corresponding chip information.

2.1432.1 FeInfo

[feId]	*integer*	Fabric chip ID.
[feRevisionMajor] **	*string*	FE major revision. **Since: 4.30.1
[feRevisionMinor] **	*string*	FE minor revision. **Since: 4.30.1
[feType] **	*string*	Chip type name. **Since: 4.30.1

2.1433 show platform (fe | fe1600 | fe3600 | ramon | ramon3) dcs mapping [...]

fes	*table(string) = DcsBlock* see 2.1433.1	DCS block link info for specified FEs.

2.1433.1 DcsBlock

dcsBlock	*table(numeric string) = Faps* see 2.1433.1.1	Serdes and peer FAP info for specified DCS block.

2.1433.1.1 Faps

faps	*table(string) = FeFapLinks* see 2.1433.1.1.1	Maps each FAP to its connecting links from this DCS block.

2.1433.1.1.1 FeFapLinks

feFapLinks	*list of FeFapLinkPair* see 2.1433.1.1.1.1	list of FE-FAP link pair.

2.1433.1.1.1.1 FeFapLinkPair

fapLink	*integer*	FAP serdes number.
feLink	*integer*	FE serdes number.

2.1434 show platform aegisalgo stage [...]

batches	*list of Batch* see 2.1434.1	A batch of events to update configuration for a list of chips.

2.1434.1 Batch

batchId	*integer*	Batch ID number.
chips	*table(string) = ChipInfo* see 2.1434.1.1	A mapping of chip name to its update stages and status.
[endBatchTime]	*floating point number*	UTC epoch timestamp for batch end time.
[startBatchTime]	*floating point number*	UTC epoch timestamp for batch start time.

2.1434.1.1 ChipInfo

stages	*list of StageInfo* see 2.1434.1.1.2	A list of Aegis stages.
status	*BatchStatus* see 2.1434.1.1.1	Status of updates.

2.1434.1.1.1 BatchStatus

[endHardwareTimeStamp] **	*floating point number*	UTC epoch timestamp for hitful convergence end time. **Since: 4.34.1
[failedResourceTypes] **	*list of FailureResourceType* see 2.1434.1.1.1.1	A list of resource types that led to a hitful update. **Since: 4.34.1
[startHardwareTimeStamp] **	*floating point number*	UTC epoch timestamp for hitful convergence start time. **Since: 4.34.1
updateType	*enum: versionless | hitful | noUpdate | hitless*	Update type for this chip's rules.
[updatedResourceTypes] **	*list of UpdatedResourceType* see 2.1434.1.1.1.2	A list of resource types that are updated in a versionless update. **Since: 4.35.2
version **	*integer*	Traffic policy version installed in the hardware. **Since: 4.34.0

2.1434.1.1.1.1 FailureResourceType

failedResourceType	*enum: l2Rewrite | mirror | policer | tcam | none | lpm | lexem*	Resource type failure that led to a hitful update.

2.1434.1.1.1.2 UpdatedResourceType

updatedResourceType	*enum: lpm | groupPolicer*	Resource types updated in a versionless update.

2.1434.1.1.2 StageInfo

[endTime]	*floating point number*	UTC epoch timestamp for Aegis stage end time.
[errorMessage]	*string*	Error messages for Aegis stage.
name	*string*	Aegis processing stage name.
[startTime]	*floating point number*	UTC epoch timestamp for Aegis stage start time.
status	*enum: completed | notStarted | inProgress*	Stage update status.

2.1435 show platform agent-state verify (AGENT | all)

agentVerifyState	*table(string) = PerAgentVerifyResultDict* see 2.1435.1	Agent verify state indexed by agent Name.

2.1435.1 PerAgentVerifyResultDict

perAgentResult	*table(string) = string*	dict of { sm name : error str }.

2.1436 show platform arad lag mode

configLagMode	*enum: 64x256 | 2048x8 | 1024x16 | 512x32 | 128x128 | 256x64 |*	Configured LAG mode.
configLagModeB **	*enum: 64x256 | 2048x8 | 1024x16 | 512x32 | 128x128 | 256x64 |*	Configured LAG mode B. **Since: 4.33.1
statusLagMode	*enum: 64x256 | 2048x8 | 1024x16 | 512x32 | 128x128 | 256x64 |*	Actual LAG mode.
statusLagModeB **	*enum: 64x256 | 2048x8 | 1024x16 | 512x32 | 128x128 | 256x64 |*	Actual LAG mode B. **Since: 4.33.1

2.1437 show platform bios

revision 2

[availableVersions] **	*list of string*	Available bios version updates(s) for the switch. **Since: 4.36.0
[biosDeprecated] **	*string*	Information about deprecated BIOS. **Since: 4.32.2
[fallbackVersion]	*BiosVersion* see 2.1437.1	BIOS fallback version programmed on the switch.
[programmedVersion]	*BiosVersion* see 2.1437.1	BIOS version programmed on the switch.
[queuedVersions] **	*list of string*	Pending bios version updates(s) for the switch. **Since: 4.31.0
runningVersion	*BiosVersion* see 2.1437.1	BIOS version currently running on the switch.
[standbyVersions]	*BiosVersions* see 2.1437.2	Versions on standby supervisor.
sysName	*string*	Name of the system.

2.1437.1 BiosVersion

changeNumber **	*string*	Change number. **Since: 4.26.2
[core]	*string*	Core string.
line **	*string*	Aboot line (eg. norcal9). **Since: 4.26.2
[pcieLaneConfig] **	*string*	PCIe lane configuration. **Since: 4.26.2
version **	*string*	Version string (eg. 7.2.1). **Since: 4.26.2
versionString **	*string*	Complete Aboot version string. **Since: 4.26.2

2.1437.2 BiosVersions

Could also be an instance of:
DualSupBiosVersions 2.1437

[availableVersions] **	*list of string*	Available bios version updates(s) for the switch. **Since: 4.36.0
[biosDeprecated] **	*string*	Information about deprecated BIOS. **Since: 4.32.2
[fallbackVersion]	*BiosVersion* see 2.1437.1	BIOS fallback version programmed on the switch.
[programmedVersion]	*BiosVersion* see 2.1437.1	BIOS version programmed on the switch.
[queuedVersions] **	*list of string*	Pending bios version updates(s) for the switch. **Since: 4.31.0

runningVersion	*BiosVersion* see 2.1437.1	BIOS version currently running on the switch.
sysName	*string*	Name of the system.

2.1438 show platform bios history [...]

revision 2

history	*list of HistoryEntry* see 2.1438.1.1	List of installation history.
[standbyHistory]	*BiosHistory* see 2.1438.1	History on standby supervisor.
sysName	*string*	Name of the system.

2.1438.1 BiosHistory

Could also be an instance of:
DualSupBiosHistory 2.1438

history	*list of HistoryEntry* see 2.1438.1.1	List of installation history.
sysName	*string*	Name of the system.

2.1438.1.1 HistoryEntry

checksum	*string*	Checksum of AUF used.
epoch	*integer*	Epoch of update.
error	*integer*	Error code.
name	*string*	Name of AUF used.
payloadType	*enum: certificateBundle | aboot | other*	Type of AUF used.

2.1439 show platform cortina INTF diag counters

[cmdErr]	*string*	The error message if any.
[interfaces]	*table(Interface name) = CountersModel* see 2.1439.1	A mapping of the interface to its counters.

2.1439.1 CountersModel

counters	*table(string) = integer*	Map of counter names and their values.

2.1440 show platform etba counters [...]

[ebraCounters]	*table(string) = HandlerCounter* see 2.1440.1	Maps EbraTestBridge routing handler names to respective counters.
ebraIgnored	*integer*	Number of packets that were ignored by all EbraTestBridge routing handlers.
ebraRouted	*integer*	Number of packets that were routed by at least one EbraTestBridge routing handler.
[fwdIntfCounters]	*table(string) = HandlerCounter* see 2.1440.1	Maps FwdIntfDevice routing handler names to respective counters.
fwdIntfIgnored	*integer*	Number of packets that were ignored by all FwdIntfDevice routing handlers.
fwdIntfRouted	*integer*	Number of packets that were routed by a FwdIntfDevice routing handler.

2.1440.1 HandlerCounter

ignored	*integer*	Number of ignored packets.
routed	*integer*	Number of routed packets.

2.1441 show platform fap ecmp hash [...]

faps	*table(string) = HashInfoFap* see 2.1441.1	Mapping of FAP names and cores to hash parameters and associated values.

2.1441.1 HashInfoFap

extendedHashPolys **	*list of integer*	Collection of extended hash polynomials that exist in the FAP. **Since: 4.31.0
hashPolys	*list of integer*	Collection of hash polynomials that exist in the FAP.
hashSeeds	*list of integer*	Collection of hash seeds that exist in the FAP.
keyShifts	*list of integer*	Collection of hash key shifts that exist in the FAP.
layerMsbLsb **	*list of string*	Collection that indicates whether MSB or LSB is used in a layer. **Since: 4.31.0
pmfKey **	*list of string*	Collection of nibbles chosen to form the PMF key. **Since: 4.31.0

2.1442 show platform fap interfaces INTFS profile latency

interfaces	*table(Interface name) = Sand.Cli.Model.Latency-Details* see 2.1442.1	Interface to latency profile mapping.

2.1442.1 Sand.Cli.Model.LatencyDetails

voqs	*list of Sand.Cli.Model.VoqRange* see 2.1442.1.1	Range of ECN latency profile ID.

2.1442.1.1 Sand.Cli.Model.VoqRange

maxLatencyProfileId	*integer*	Maximum Latency Profile ID for maxVoq.
maxVoqId	*integer*	Maximum VOQ ID in the range.
minLatencyProfileId	*integer*	Minimum Latency Profile ID for minVoq.
minVoqId	*integer*	Minimum VOQ ID in the range.

2.1443 show platform fap interfaces INTFS profile rate-class

interfaces	*table(Interface name) = VoqDetailsDict* see 2.1443.1	Interface to Rate Class mapping.

2.1443.1 VoqDetailsDict

voqs	*table(numeric string) = VoqDetails* see 2.1443.1.1	Interface to Rate Class mapping.

2.1443.1.1 VoqDetails

rateClass	*integer*	Rate Class ID.
trafficClass	*integer*	Traffic Class for the given interface.

2.1444 show platform fap ip security counters [...]

vrfs	*table(string) = AleTunnelsec.Counters.-TunnelsecIntfCounterCli-Table* see 2.1444.1	Collection of tunnel counters mapped to their underlay vrfs.

2.1444.1 AleTunnelsec.Counters.TunnelsecIntfCounterCliTable

interfaces	*table(Interface name) = AleTunnelsec.Counters.-TunnelSecIntfCounters* see 2.1444.1.1	Collection of ipsec tunnel counters mapped to the the intfId.
peers	*table(IPv4 or IPv6 address) = AleTunnelsec.Counters.-TunnelSecIntfCounters* see 2.1444.1.1	Collection of secure vxlan tunnel counters mapped to the remote vtep ip.

2.1444.1.1 AleTunnelsec.Counters.TunnelSecIntfCounters

inBroadcastPkts	*integer*	Incoming broadcast packets.
inMulticastPkts	*integer*	Incoming multicast packets.
inOctets	*integer*	Total incoming octets.
inOctetsDecrypted	*integer*	Payload octets decrypted including padding.
inOctetsProtected	*integer*	Incoming octets of plaintext recovered from received packets that were integrity protected but not encrypted.
inPktsBadTag	*integer*	Incoming packets with invalid security header, zero value PN, or invalid ICV.
inPktsCtrl	*integer*	Number of management packets.
inPktsDelayed	*integer*	Incoming packets whose PN was lower than the lowest acceptable PN and replay protection was disabled.
inPktsDrop	*integer*	Counter accounts for any drop that occurred in the MACsec engine.
inPktsInvalid	*integer*	Incoming packets with the condition that the packets are not valid and ValidateFrames is in CHECK mode.
inPktsLate	*integer*	Incoming packets whose PN was lower than the lowest acceptable PN and replay protection was enabled.
inPktsNoSCI	*integer*	Incoming packets discarded with unknown SPI information while ValidateFrames is STRICT.
inPktsNoTag	*integer*	Incoming packets without security header while ValidateFrames is STRICT.
inPktsNotUsingSA	*integer*	Incoming packets that have been discarded either because the packets were encrypted or ValidateFrames is STRICT for an SA that is not currently in use.

inPktsNotValid	*integer*	Incoming packets that are fully decrypted, but have an authentication failure.
inPktsOK	*integer*	Incoming packets successfully decrypted and validated.
inPktsReplayed	*integer*	Counts IPsec packets that are fully decrypted, passed authentication check but are dropped due to being replayed.
inPktsUnchecked	*integer*	Incoming packets received while ValidateFrames is DISABLED.
inPktsUnknownSCI	*integer*	Incoming packets discarded with unknown SPI information while ValidateFrames is not STRICT.
inPktsUntagged	*integer*	Incoming packets without security header while ValidateFrames is not STRICT.
inPktsUnusedSA	*integer*	Number of received unencrypted packets with ValidateFrames not STRICT for an SA that is not currently in use.
inScTcamHit	*integer*	Number of TCAM hits for SC.
inScTcamMiss	*integer*	Number of TCAM misses for SC.
inSpTcamHit	*integer*	Number of TCAM hits for SP.
inSpTcamMiss	*integer*	Number of TCAM misses for SP.
inUcastPkts	*integer*	Incoming unicast packets.
outBroadcastPkts	*integer*	Outgoing broadcast packets.
outInvalidSA	*integer*	Outgoing packets with an invalid SA.
outMulticastPkts	*integer*	Outgoing multicast packets.
outOctets	*integer*	Total outgoing octets.
outOctetsEncrypted	*integer*	Number of plain text octets that are integrity protected and encrypted.
outOctetsProtected	*integer*	Number of plain text octets that are integrity protected but not encrypted.
outPktCtrl	*integer*	Counter accounts for outgoing control packets.
outPktsEncrypted	*integer*	Number of packets forwarded after successful encapsulation.
outPktsProtected	*integer*	Number of integrity protected but not encrypted packets.
outPktsTooLong	*integer*	Outgoing packets dropped due to MTU check.
outPktsUntagged	*integer*	Outgoing packets that are not encapsulated and bypassed.
outUcastPkts	*integer*	Outgoing unicast packets.

2.1445 show platform fap port-channel hash [...]

see 2.1441

2.1446 show platform fap voq delete

voqDeleteEntries	*list of VoqDeleteEntry* see 2.1446.1	List of VOQ delete entries.

2.1446.1 VoqDeleteEntry

chipName	*string*	Ingress chip.
coreId	*integer*	Core ID.
count	*integer*	Count of VOQ deletes.
firstOccurrence	*floating point number*	UTC timestamp of the first delete occurrence for this VOQ.
intfName	*interface name*	Name of the interface.
lastOccurrence	*floating point number*	UTC timestamp of the last recorded VOQ delete.
trafficClass	*integer*	Traffic class.

2.1447 show platform ip igmp snooping groups [...]

vlans	*table(numeric string) = VlanStatus* see 2.1447.1	A mapping of VLAN ID to its Ethernet groups.

2.1447.1 VlanStatus

ethGroups	*table(MAC address) = VlanOrMcastGrpStatus* see 2.1447.1.1	Ethernet groups information, keyed by their address.

2.1447.1.1 VlanOrMcastGrpStatus

interfaces	*table(Interface name) = InterfaceModel* see 2.1447.1.1.1	A mapping of interface to its programmed status.
mcastId	*integer*	Multicast ID.
programmedIn	*enum: software | hardware | both*	Database in which the Ethernet group is programmed. 'software'- ethGroup programmed in software only. 'hardware'- ethGroup programmed in hardware only. 'both'- ethGroup present in both hardware & software.

2.1447.1.1.1 InterfaceModel

programmedIn	*enum: software | hardware | both*	Database in which the interface is programmed: 'software'- interface programmed in software only. 'hardware'- interface programmed in hardware only. 'both'- interface in both hardware & software.

2.1448 show platform module [...]

`modules`	*table(string) = PlatformModuleStatus* see 2.1448.1	Mapping between module name and module status.

2.1448.1 PlatformModuleStatus

`status`	*enum: empty | diags | inserted | unknown*	Status of module.

2.1449 show platform power controller

`powerControllers`	*list of PowerController* see 2.1449.1	List of power controller info.

2.1449.1 PowerController

`modelName`	*string*	power controller model name.
`name`	*string*	power controller name.
`resetCount`	*integer*	power controller reset count.
`version`	*string*	power controller version.

2.1450 show platform power isl [...]

islControllers	*table(string) = IslController* see 2.1450.1	ISL controllers, keyed by their names.

2.1450.1 IslController

agentName	*string*	Name of ISL's agent.
controllerState	*string*	Controller state.
outputVoltageRails	*list of OutputVoltageRail* see 2.1450.1.1	Metrics for each ISL output.
vin	*floating point number*	Input voltage.

2.1450.1.1 OutputVoltageRail

[description]	*string*	Output description.
[iout]	*floating point number*	Measured output current.
online **	*boolean*	Device is online. **Since: 4.29.1
[outputPhaseCurrents] **	*list of OutputPhaseCurrent* see 2.1450.1.1.2	Metrics for each phase current output. **Since: 4.35.2
[phaseToFrequencies] **	*table(numeric string) = BucketFrequencies* see 2.1450.1.1.1	Mapping of phase number to its bucket frequency data. **Since: 4.35.2
[pout]	*floating point number*	Measured output power.
[status] **	*enum: Ok | Failed | Offline*	Rail page status. **Since: 4.33.0
[vout]	*floating point number*	Measured output voltage.
voutConfigured	*floating point number*	Configured output voltage.

2.1450.1.1.1 BucketFrequencies

bucketFrequencies	*table(string) = integer*	Mapping of phase current buckets (in amps) to its number of hits.

2.1450.1.1.2 OutputPhaseCurrent

current	*floating point number*	Latest measured sensor current (amps).
maxCurrent	*floating point number*	Maximum measured sensor current (amps).
meanCurrent	*floating point number*	Average measured sensor current (amps).
minCurrent	*floating point number*	Minimum measured sensor current (amps).
phase	*integer*	Phase number.
[standardDeviation]	*floating point number*	Standard deviation of measured sensor current (amps).

2.1451 show platform power isl current phase [...]

see 2.1450

2.1452 show platform power isl current phase histogram [...]

see 2.1450

2.1453 show platform ptp hardware-sync

configuredState	*enum: on | off*	Configured State.
masters	*table(string) = MasterModel* see 2.1453.1	A Mapping between a TimeSync Master and its time synchronization information.
operationalState	*enum: synchronizing | stable | enabled | disabled | active*	Operational State.
slaves	*table(string) = SlaveModel* see 2.1404.1	A Mapping between a TimeSync Slave and its time synchronization information.
syncInterval	*floating point number*	Synchronization Interval (in milliseconds).

2.1453.1 MasterModel

[firmwareVersion] **	*integer*	Firmware Version. **Since: 4.36.0
[localTod]	*integer*	Latest Local Time of Day (ToD).
[masterTod]	*integer*	Latest Master Time of Day (ToD).
[phaseDifferences]	*list of integer*	Last 4 phase differences (in ns).
pidState **	*enum: runServo | adjustSkew | jumpClock | servoDisabled | watchSkew*	Servo State. **Since: 4.20.5
[skew] **	*floating point number*	Active Master Skew. **Since: 4.20.5
state	*enum: stableStandby | synchronizingStandby | failed | initializedStandby | disabled | active | initialized | switchover*	Operational State.
[timeToStability]	*integer*	Time to stability (in s).
[updates]	*integer*	Sync Update(s).

2.1454 show platform ptp hardware-sync master SCD_NAME

masters	*table(string) = MasterModel* see 2.1453.1	A Mapping between a TimeSync Master and its time synchronization information.

2.1455 show platform ptp hardware-sync slave SWITCH_NAME

see 2.1404

2.1456 show platform sand capabilities

revision 3

aclHwStatusReporting-Supported	*boolean*	ACL hardware status reporting supported.
arpTableSize	*integer*	ARP table size.
asyncSupportRequired	*boolean*	QoS ACL asynchronous support required.
defaultCos	*integer*	Default CoS.
defaultCosSupported	*boolean*	Default CoS supported.
defaultDscp	*integer*	Default DSCP.
defaultDscpSupported	*boolean*	Default DSCP supported.
dot1qTunnelSupported	*boolean*	Dot1q tunnel supported.
dropsLogDirectionSupport	*enum: directionNone* | *directionTxOnly* | *directionTxAndRx*	Congestion drops log direction support.
dynamicExpMappingSupported	*boolean*	Dynamic MPLS EXP bits to/from TC mapping supported.
ecmpSupported	*boolean*	IPv6 ECMP supported.
ecnSupported	*boolean*	ECN supported.
egressArpTableSize	*integer*	Maximum egress ARP table entries.
fecForEachHop	*boolean*	FEC for each hop.
hwStatusReportingSupported	*boolean*	Hardware status reporting supported.
ingressPolicingSupported	*boolean*	Ingress policing supported.
ingressTrTcmPolicing-Supported	*boolean*	Ingress trTcm (two rate three color) policing supported.
ip6AclsSupported	*boolean*	IPv6 ACLs supported.
ipAclsSupported	*boolean*	IPv4 ACLs supported.
ipv6AclPbrSupported	*boolean*	IPv6 ACL PBR supported.
ipv6NexthopPbrSupported	*boolean*	IPv6 nexthop PBR supported.
lagMulticastLoadBalancing	*boolean*	LAG multicast load balancing.
maxEcmp	*integer*	Maximum ECMP.
maxIpsecTunnelInterfaces	*integer*	Maximum IP Security tunnel interfaces.
maxLags	*integer*	Maximum LAGs.
maxMacTableSize	*integer*	Maximum MAC table entries.
maxMembersPerLag	*integer*	Maximum members per LAG.
maxMulticastGroups	*integer*	Maximum multicast groups.
maxNexthopGroupEcmp	*integer*	Maximum nexthop group ECMP.
maxShapeRatePps	*integer*	Maximum shape rate (pps).
maxSvi	*integer*	Maximum SVI.
maximumTopologiesSupported	*integer*	Maximum topologies supported.
minPortShapeRate	*integer*	Minimum port shape rate (kbps).
minTxQueueShapeRate	*integer*	Minimum transmit queue shape rate (kbps).
mplsMatchRulePbrSupported	*boolean*	MPLS match rule PBR supported.
mplsPseudowireSupported	*boolean*	MPLS pseudowire supported.
mplsStaticPseudowire-Supported	*boolean*	MPLS static pseudowire supported.
msrpSupported	*boolean*	MSRP supported.
mvrpSupported	*boolean*	MVRP supported.
neighborTableSize	*integer*	ARP neighbor table size.

nexthopGroupMplsLabelStack-Size	*integer*	Nexthop group MPLS label stack entries.
nexthopGroupPbrSupported	*boolean*	Nexthop group PBR supported.
nexthopGroupSupported	*boolean*	Nexthop group supported.
nexthopGroupTypeSupported	*table(string) = boolean*	A mapping between nexthop group type and if it is supported.
pbrNexthopVrfSupported	*boolean*	PBR Nexthop Vrf supported.
pbrSupported	*boolean*	PBR supported.
policeByteModeMaxBurstBytes	*integer*	Police byte mode maximum burst bytes.
policeByteModeMaxRateKbps	*integer*	Police byte mode maximum rate (kbps).
policeByteModeMinBurstBytes	*integer*	Police byte mode minimum burst bytes.
policeByteModeMinRateKbps	*integer*	Police byte mode minimum rate (kbps).
policyQosActionsSupported	*table(string) = boolean*	A mapping between Policy QoS actions and if it is supported.
policyQosNumCMapSupported	*integer*	Number of QoS policy class maps supported.
policyQosSupported	*boolean*	Policy QoS supported.
routingMplsVpnV4	*boolean*	MPLS VPNv4 supported.
routingMplsVpnV6	*boolean*	MPLS VPNv6 supported.
sandDanzRunnable	*boolean*	Sand DANZ runnable.
sandIpsecRunnable	*boolean*	Sand Ipsec runnable.
sflowDscpRewriteSupported	*boolean*	Sflow DSCP rewrite supported.
sharedPolicerSupported	*boolean*	Shared policer supported.
tcToDscpMapSupported	*boolean*	TC to DSCP map supported.
tunnelInterfaceModes-Supported	*table(string) = boolean*	Supported tunnel interface modes.
txQueueShapeRateUnitPps-Supported	*boolean*	Transmit queue shape rate unit (pps) supported.
urpfSupportedOnAllFaps	*boolean*	URPF supported on all FAPs.
usableLags	*integer*	Usable LAGs.
v6maxEcmp	*integer*	IPv6 Maximum ECMP.
vrfRoutingSupported	*boolean*	VRF routing supported.
vtepGroupSupported	*boolean*	VXLAN L2 ECMP supported.
vxlanBfdSupported	*boolean*	VXLAN bfd supported.
vxlanMcastGroupSupported	*boolean*	VXLAN multicast group supported.
vxlanSupported	*boolean*	VXLAN supported.
wredSupported	*boolean*	WRED supported.

2.1457 show platform sand counters mac-address-table flush

avgDuration	*floating point number*	Average Duration of flushes of all types.
bulkCount	*integer*	Counter for number of bulk flushes.
flushCount	*integer*	Counter for number of regular flushes.
lastDuration	*floating point number*	Duration of most recent flush.
maxDuration	*floating point number*	Maximal Duration of flushes of all types.
minDuration	*floating point number*	Minimal Duration of flushes of all types.

2.1458 show platform sand fabric monitor capacity

fabricCapacityMonitorLog	*boolean*	Fap fabric capacity monitor log enable config.
fabricCapacityMonitor-Threshold	*integer*	Fap fabric capacity monitor threshold.
fapFabricCapacityInfo	*table(string) = FapFabricCapacityInfo* see 2.1458.1	Maps FapName to Fap fabric capacity info.

2.1458.1 FapFabricCapacityInfo

lastFabricCapacityMonitor-Event	*string*	Fabric Capacity monitor event.
lastFabricCapacityMonitor-EventTime	*string*	Last time fabric Capacity %% crossed above/below configiruredthreshold.
lastFullFabricCapacity **	*integer*	Full Fabric capacity. **Since: 4.25.0
lastFullFapCapacity	*integer*	Full Fap capacity.
lastOperationalFabric-Capacity	*integer*	Operational Serdess capacity.
lastOperationalFapCapacity	*integer*	Operational Fap capacity.

2.1459 show platform sand health

revision 2

activeMeshPaths **	*list of string*	Active fabric mesh paths. **Since: 4.34.1
dataGenerationTime	*floating point number*	Time at which data was generated in UTC.
fabricAuditLog **	*list of EventLogModel* see 2.1459.1	Fabric audit events. **Since: 4.30.1
fabricCardsNotInitialized	*table(string) = string*	A mapping of fabric card name to its hardware state.
fabricInterruptOccurrences	*table(string) = FabricInterruptDataModel* see 2.1459.2	A mapping of fabric name to its last interrupt data.
fabricMeshLog **	*list of EventLogModel* see 2.1459.1	Fabric mesh events. **Since: 4.30.1
fabricSerdesIsolated	*table(string) = PeerLinkId* see 2.1459.5	A mapping of chip name to isolated fabric SerDes.
linecardsNotInitialized	*table(string) = string*	A mapping of linecard name to its hardware state.
meshDstDroppedPaths **	*table(string) = PeerFapListModel* see 2.1459.4	A mapping of destination to source FAPs where the destination FAP caused drops during fabric mesh. **Since: 4.34.1
meshSrcDroppedPaths **	*table(string) = PeerFapListModel* see 2.1459.4	A mapping of source to destination FAPs where the source FAP caused drops during fabric mesh. **Since: 4.34.1
numFabricCards	*integer*	Number of fabric cards.
numLinecards	*integer*	Number of linecards.
shutdownSerdes	*table(string) = PeerLinkId* see 2.1459.5	A mapping of chip name to SerDes.
suspiciousRxFaps	*table(string) = FapDataModel* see 2.1459.3	A mapping of FAP name to number of times it's caused RQP discards.
suspiciousTxFaps	*table(string) = FapDataModel* see 2.1459.3	A mapping of FAP name to number of times it's caused RQP discards.
totalSerdesAdminShutdowns	*integer*	Fabric SerDes admin shutdown.

2.1459.1 EventLogModel

eventMessage	*string*	Event log.
eventTime	*floating point number*	Event time.

2.1459.2 FabricInterruptDataModel

count	*integer*	Number of occurrences.
[lastOccurrence]	*floating point number*	Time since fabric interrupt occurrence.

2.1459.3 FapDataModel

count	*integer*	Number of occurrences.

2.1459.4 PeerFapListModel

peerFaps	*list of string*	Peer FAPs involved in paths which dropped packets.

2.1459.5 PeerLinkId

peerLinks	*table(numeric string) = PeerLinkIdSubModel* see 2.1459.5.1	A mapping of link ID to peer Link.

2.1459.5.1 PeerLinkIdSubModel

[count]	*integer*	Number of times serDes link has been isolated.
[lastOccurrence]	*floating point number*	Last Occurrence.
name	*string*	Peer Link.

2.1460 show platform sand lag id reserved

features	*table(string) = SandLagIdReservationByPartition* see 2.1460.1	Map reserved ID(s) to features.

2.1460.1 SandLagIdReservationByPartition

partitions	*table(string) = SandLagIdReservationList* see 2.1460.1.1	Map reserved ID(s) to partitions.

2.1460.1.1 SandLagIdReservationList

ids	*list of integer*	Lag ID list.

2.1461 show platform sand lag interlock [...]

portChannels	*table(Interface name) = SandLagInterlockPortChannel* see 2.1461.1	Map port-channels to their member information.

2.1461.1 SandLagInterlockPortChannel

ports	*table(Interface name) = SandLagInterlockPort* see 2.1461.1.1	Map ports to list of interlock states.

2.1461.1.1 SandLagInterlockPort

mlagEgressAcl	*boolean*	MLAG egress ACL interlock is blocking.
[vlanTranslation]	*boolean*	VLAN translation interlock is blocking.

2.1462 show platform sand lag mode

see 2.1436

2.1463 show platform sand mcast replication ingress maximum

config	*integer*	Configured maximum number of ingress replications.
status	*integer*	Actual maximum number of ingress replications.

2.1464 show platform sand mdb profile [...]

revision 2

fapProfiles	*table(string) = MdbFapProfile* see 2.1464.1	MDB profile for each FAP, keyed by FAP name.
[systemProfile]	*enum: l3-xxl | l3-traffic-policy | default | l3-xl | l3 | balanced-xl | l3-host-xl | balanced | l3-xl-oam | l3-xxxl | l3-adj-xxxl*	MDB system profile.

2.1464.1 MdbFapProfile

fapId	*integer*	FAP ID.
fapType	*string*	FAP type.
profile	*string*	MDB Profile.

2.1465 show platform sand pmf qualifier warnings

[profileWarnings]	*table(string) = FeatureWarningsModel* see 2.1465.1	A mapping from a TCAM profile to its detailed warnings per feature.

2.1465.1 FeatureWarningsModel

featureWarning	*table(string) = DescriptionsModel* see 2.1465.1.1	A mapping between TCAM feature configuration to its detailed warning messages.

2.1465.1.1 DescriptionsModel

headerIndexWarning	*list of HeaderIndexWarning* see 2.1465.1.1.1	Header index warnings.
headerTypeMismatchWarning	*list of HeaderTypeMismatchWarning* see 2.1465.1.1.2	Header type mismatch warnings.
headerTypeMissingQualifierWarning	*list of HeaderTypeMissingQualifierWarning* see 2.1465.1.1.3	Header type warnings with missing next protocol qualifier.

2.1465.1.1.1 HeaderIndexWarning

actualHeaderIndex	*integer*	Actual index of header type.
actualHeaderType	*string*	Matched layer type.
expectedHeaderIndex	*integer*	Expected index for header type.
expectedHeaderType	*string*	Expected layer type.
genInfo	*HeaderWarningGeneralInfo* see 2.1465.1.1.1.1	General warning details.

2.1465.1.1.1.1 HeaderWarningGeneralInfo

databases	*string*	Database(s) for qualifier.
headers	*string*	Headers of preselector.
preselector	*string*	Preselector.
qualifiers	*list of string*	Qualifiers with same warning.

2.1465.1.1.2 HeaderTypeMismatchWarning

actualHeaderType	*string*	Matched layer type.
expectedHeaderType	*string*	Expected layer type.
ffcHeaderIndex	*integer*	Index of matched header.
genInfo	*HeaderWarningGeneralInfo* see 2.1465.1.1.1.1	General warning details.

2.1465.1.1.3 HeaderTypeMissingQualifierWarning

expectedHeaderType	*string*	Expected layer type.

ffcHeaderIndex	*integer*	Index of matched header.
genInfo	*HeaderWarningGeneralInfo* see 2.1465.1.1.1.1	General warning details.
missingQualifier	*string*	Qualifier missing to match on Layer 4.

2.1466 show platform sand qos map cpu traffic-class to cos [...]

mapNameToMapId	*table(string) = integer*	Map Name to Map Id.

2.1467 show platform sand recirculation mapping

recirculationMappingInfo	*table(string) = RecirculationMappingInfo* see 2.1467.1	Mapping of Recirculation Interface to Features and Users.

2.1467.1 RecirculationMappingInfo

[feature]	*string*	Feature that is using this Recirculation Port.
[user]	*string*	Feature-specific use.

2.1468 show platform sand scheduler copp COPP_PORT_NAME (fap | arad | jericho | jericho2 | jericho3 | jericho4) [...]

FlowList	*table(numeric string) = PrintFlowUpModel* see 2.1468.1	Maps FAP Id to their corresponding copp class scheduler flow.

2.1468.1 PrintFlowUpModel

aggrClSchedulers **	*table(string) = ClScheduler* see 2.1468.1.1	Aggregate CL (Class) scheduler per scheduler index. **Since: 4.31.2
clSchedulers	*table(string) = ClScheduler* see 2.1468.1.1	CL (Class) scheduler per scheduler index.
coreId	*integer*	Local core ID for the given interface.
cores	*table(string) = VoqIngressCore* see 2.1468.1.5	VOQ flows per ingress core.
fapId	*integer*	FAP ID for the given interface.
fqSchedulers	*table(string) = FqScheduler* see 2.1468.1.2	FQ (Fair Queue) scheduler per scheduler index.
hrScheduler	*HrScheduler* see 2.1468.1.3	HR (Heirarchial) scheduler.
parentInterface	*InterfaceSubmodel* see 2.1468.1.4	Parent interface.
[subInterface]	*InterfaceSubmodel* see 2.1468.1.4	Subinterface.

2.1468.1.1 ClScheduler

classSchedMode	*enum: (SP,WFQ,WFQ,WFQ) | Unsupported | SP | WFQ | (SP,SP,WFQ,WFQ)*	Class scheduler mode.
configuredRate **	*floating point number*	Applied shaped rate in bps. **Since: 4.32.0
cos	*integer*	CoS value (weight).
creditRate	*integer*	Credit rate in bps.
flowControlCounter	*integer*	Counts the number of clocks that flow control was issued at the port.
flowId	*integer*	Flow ID.
flowState	*enum: on | slow | off*	Flow state.
parentSE	*integer*	Parent scheduler element.
parentSeIsDefault **	*boolean*	A default SE grants no credits. **Since: 4.32.1
schedId **	*integer*	scheduler ID. **Since: 4.30.0
wfqMode	*enum: discrete | perClass | independent*	WFQ mode.

2.1468.1.2 FqScheduler

compositeFlow	*boolean*	Current flow is a composite flow.
configuredRate **	*floating point number*	Applied shaped rate in bps. **Since: 4.32.0
cos	*integer*	CoS value (weight).
creditRate	*integer*	Credit rate in bps.
flowId	*integer*	Flow ID.
flowState	*enum: on | slow | off*	Flow state.
parentSE	*integer*	Parent scheduler element.
parentSeIsDefault **	*boolean*	A default SE grants no credits. **Since: 4.32.1

2.1468.1.3 HrScheduler

cos	*integer*	CoS value (weight).
creditRate	*integer*	Credit rate in bps.
flowId	*integer*	Flow ID.
schedulerIndex	*integer*	HR scheduler index.

2.1468.1.4 InterfaceSubmodel

name	*interface name*	Interface name.
sppid	*integer*	Interface system physical port ID.

2.1468.1.5 VoqIngressCore

flows	*table(string) = VoqFlow* see 2.1468.1.5.1	VOQ flows for this ingress core.

2.1468.1.5.1 VoqFlow

configuredRate **	*floating point number*	Applied shaped rate in bps. **Since: 4.32.0
cos	*integer*	CoS value (weight).
creditRate	*integer*	Credit rate in bps.
parentSE **	*integer*	Parent scheduler element. **Since: 4.32.1
parentSeIsDefault **	*boolean*	A default SE grants no credits. **Since: 4.32.1
voqId	*integer*	VOQ Id corresponding to the intf and core.

2.1469 show platform sand scheduler interface INTF

see 2.1468.1

2.1470 show platform sand srv6 endpoint [...]

2.1471 show platform sand srv6 endpoint detail [...]

2.1472 show platform sand subinterface anchor [...]

interfaces	*table(Interface name) = Interface name*	A mapping of subinterface to its anchor interface.

2.1473 show platform sand subinterface capabilities

maxPortShapeRate	*integer*	Maximum SubInterface port shape rate (kbps).
maxSubIntfsWithVoqs	*integer*	Maximum number of subInterfaces with VOQ supported.
maxSubIntfsWithVoqsPerCore	*table(numeric string) = integer*	A mapping between system core and max subInterfaces with voq supported.
minPortShapeRate	*integer*	Minimum SubInterface port shape rate (kbps).
numVoqsPerSubIntf	*integer*	Number of Voqs per SubInterface.
parentSchedulingMode **	*enum: Round Robin | Strict Priority*	Scheduling mode between shaped subinterfaces and their parent interface. **Since: 4.31.1
schedulingMode	*table(string) = string*	A mapping between traffic class and scheduling mode.
subIntfSchedulingMode **	*enum: Priority Propagation | Default*	Subinterface scheduling mode. **Since: 4.35.2
tcToVoqMapping	*table(string) = string*	A mapping between traffic class and Voq.
voqTailDropThresholdBD	*integer*	Voq tail drop threshold in Buffer descriptors.
voqTailDropThresholdMB	*floating point number*	Voq tail drop threshold in MBs.

2.1474 show platform sand subinterface load-balancing [...]

interfaces	*table(Interface name) = InterfaceLoadBalancingModel* see 2.1474.1	A mapping of lag subinterface to its detail status.

2.1474.1 InterfaceLoadBalancingModel

[members]	*list of InterfaceSubmodel* see 2.1468.1.4	Interface and SPP ID.
remark	*string*	Remark for interface loadbalancing.
shapingStatus	*boolean*	Traffic is shaped.

2.1475 show platform sand tapagg [...]

revision 6

groups	*table(numeric string) = TapAggGroup* see 2.1475.1	Tap-agg groups keyed by groupId.
nexthopGroups	*table(string) = TapAggNexthopGroup* see 2.1475.2	Tap-agg nexthop groups keyed by name.
tapPorts	*table(Interface name) = TapPort* see 2.1475.3	Dictionary of tap port configurations keyed by interface name.
toolPorts	*table(Interface name) = ToolPort* see 2.1475.4	Dictionary of tool ports configurations keyed by interface name.

2.1475.1 TapAggGroup

destinationId	*integer*	Destination ID.
destinationType	*enum: fec | port | drop | mcg | flow | lag*	Destination Type.
[egressTruncation-DestinationId]	*integer*	Destination ID for egress truncation.
[egressTruncationIngress-Rep]	*boolean*	Ingress replication enabled for egress truncation destinations.
[egressTruncationToolPorts]	*list of Interface name*	List of egress truncated tool ports.
[groupName]	*string*	Group name.
ingressRep	*boolean*	Ingress replication enabled.
[notEgressTruncation-DestinationId]	*integer*	Destination ID for egress non-egress truncated ports.
[notEgressTruncation-IngressRep]	*boolean*	Ingress replication enabled for non-egress truncated destinations.
[notEgressTruncationTool-Ports]	*list of Interface name*	List of non-egress truncated tool ports.
[outlif]	*integer*	OutLIF allocated for tool group.
sourceInterfaces	*list of Interface name*	List of source interfaces.
[sourcePolicies]	*list of string*	List of source policies.
toolPorts	*list of Interface name*	List of tool ports.

2.1475.2 TapAggNexthopGroup

destinationId	*integer*	Destination ID.
destinationType	*enum: fec | port | drop | mcg | flow | lag*	Destination Type.
egressInterfaces	*list of NhgEgressInterface* see 2.1475.2.1	List ofnexthop group egress interfaces.
groupName	*string*	Group name.
nexthopGroupNames	*list of string*	List of nexthop group names.
sourceInterfaces	*list of Interface name*	List of source interfaces.

2.1475.2.1 NhgEgressInterface

intf	*interface name*	Interface for traffic destination.
outLif	*integer*	Logical output interface for traffic destination.

2.1475.3 TapPort

defaultGroup	*string*	The default group associated with a tap port.
greStrip	*boolean*	Remove GRE encapsulation header.
gtpStrip	*boolean*	Remove GTPv1 encapsulation header.
innerPortIdentity	*integer*	The inner port identity of a tap port.
[lag]	*interface name*	Port-channel this interface belongs to.
mplsPop	*boolean*	Remove MPLS labels.
portIdentity	*integer*	The port identity of a tap port.
truncationSize	*integer*	The size to which packet is to be truncated, in bytes.
vxlanStrip	*boolean*	Remove VXLAN header.

2.1475.4 ToolPort

brStrip	*boolean*	Remove BR Tag.
dot1qStrip	*list of integer*	The set of 802.1Q tags to remove on a tool port.
identityMode	*enum: dot1q | none | qinq*	Identity tagging mode.
[lag]	*interface name*	Port-channel this interface belongs to.
mplsPop	*boolean*	Remove MPLS labels.
[outLif]	*integer*	Logical output interface for traffic destination.
truncationSize	*integer*	The size to which packet is to be truncated, in bytes.
vnStrip	*boolean*	Remove VN Tag.

2.1476 show platform sand tapagg truncation-profile

revision 2

truncationProfileFapModel	*table(numeric string) = TruncationProfileFapModel* see 2.1476.1	Dictionary of truncation profile fap models keyed by fapId.

2.1476.1 TruncationProfileFapModel

fapName	*string*	Name of the fap.
numFree	*integer*	Number of free profiles.
truncationProfileInfoModel	*table(numeric string) = TruncationProfileInfoModel* see 2.1476.1.1	Dictionary of truncation profile info model keyed by profileId.

2.1476.1.1 TruncationProfileInfoModel

destination	*integer*	Destination ID.
groups	*table(numeric string) = string*	Group names keyed by groupId.
profileId	*integer*	Profile ID.
tapPortList	*list of string*	List of tap ports.
toolPortList	*list of Interface name*	List of tool ports.

2.1477 show platform sand traffic-class to network-qos map

tcToNwkQos	*table(numeric string) = integer*	Mapping between Traffic-class to network-qos.

2.1478 show platform sand voq tail-drop

ingressThresholds	*table(string) = IngressThresholds* see 2.1478.1	Arad ingress thresholds for each speed. Also includes ingress thresholds for speed and traffic class if any configured.

2.1478.1 IngressThresholds

fadtAlpha **	*integer*	Fair adaptive drop threshold scaling factor (alpha) for dynamic packet queue size. **Since: 4.20.0
fadtMinQSize **	*integer*	Minimum packet queue size for fair adaptive drop threshold. **Since: 4.20.0
[guaranteedBuff]	*integer*	Number of guaranteed buffers for Packet Queue.
pqMaxQBuffSize	*integer*	Packet Queue Buffer size thresholds for DP Normal.
pqMaxQBuffSizeCpu	*integer*	Packet Queue Buffer size thresholds for DP Cpu.
pqMaxQSize	*integer*	Packet Queue size thresholds for DP Normal.
pqMaxQSizeCpu	*integer*	Packet Queue size thresholds for DP Cpu.
[trafficClassThresholds]	*table(numeric string) = IngressTcThresholds* see 2.1478.1.1	Arad ingress thresholds for speed and traffic class. Key is traffic class number 0-7.

2.1478.1.1 IngressTcThresholds

fadtAlpha **	*integer*	Fair adaptive drop threshold scaling factor (alpha) for dynamic packet queue size. **Since: 4.20.0
fadtMinQSize **	*integer*	Minimum packet queue size for fair adaptive drop threshold. **Since: 4.20.0
[guaranteedBuff]	*integer*	Number of guaranteed buffers for Packet Queue.
[guaranteedBuffActive]	*table(string) = IngressGuaranteedBuff* see 2.1478.1.1.1	Mapping of linecard to active guaranteed buffer value. Key ALL - all linecards, Key LinecardN - linecard <N> .
pqMaxQBuffSize	*integer*	Packet Queue Buffer size thresholds for DP Normal.
pqMaxQBuffSizeCpu	*integer*	Packet Queue Buffer size thresholds for DP Cpu.
pqMaxQSize	*integer*	Packet Queue size thresholds for DP Normal.
pqMaxQSizeCpu	*integer*	Packet Queue size thresholds for DP Cpu.

2.1478.1.1.1 IngressGuaranteedBuff

runningGuaranteedBuff	*integer*	Active guaranteed buffer value.

status	*enum: inactive | active*	inactive - reload linecard for guaranteed buffer configuration to take effect. active - linecard running with configured guaranteed buffer.

2.1479 show platform sand voq tail-drop fadt

ingressThresholds	*table(string) = IngressThresholds* see 2.1478.1	Arad ingress thresholds for each speed. Also includes ingress thresholds for speed and traffic class if any configured.

2.1480 show platform sand voq tail-drop fadt status

fadtStatus	*table(string) = string*	FADT enabled status for each FAP.

2.1481 show platform sand voq tail-drop subinterface

ingressThresholds	*table(string) = IngressThresholds* see 2.1478.1	Arad ingress thresholds for each speed. Also includes ingress thresholds for speed and traffic class if any configured.

2.1482 show platform sand voq tail-drop subinterface fadt

ingressThresholds	*table(string) = IngressThresholds* see 2.1478.1	Arad ingress thresholds for each speed. Also includes ingress thresholds for speed and traffic class if any configured.

2.1483 show platform scd satellite debug [...]

scds	*table(string) = SatelliteScd* see 2.1483.1	Satellite Scds.

2.1483.1 SatelliteScd

collectionTime	*string*	Collection time.
name	*string*	Satellite Scd Name.
registers	*table(numeric string) = DebugRegister* see 2.1483.1.1	Debug registers.

2.1483.1.1 DebugRegister

name	*string*	Register name.
offset	*integer*	Register offset.
value	*integer*	Register value.

2.1484 show platform schanaccel command batch tracking duration

see 2.93

2.1485 show platform sfe counters [...]

counters	*table(numeric string) = Counter* see 2.1485.1	A list of counters used by Bessd keyed by the counterId.
owners	*table(numeric string) = string*	A list of counter owners keyed by the ownerId.

2.1485.1 Counter

count	*integer*	Number of occurrences.
counterType	*enum: gatehook | module*	Counter type.
[name]	*string*	Name of the counter.
[ownerId]	*integer*	ID used to look up the module owner of the counter in the owners dictionary.
unit	*enum: packets | bytes | memoryBlocks | flows*	Basic unit of the counter.

2.1486 show platform sfe flow tracking counters

exportInfoInRspAdd	*integer*	Number of add export message received.
exportInfoInRspRemove	*integer*	Number of remove export message received.
exportInfoInRspRemoveNoFlow	*integer*	Number of remove export message received for invalid flow.
exportInfoReq	*integer*	Number of export GRPC request message sent.
exportInfoRsp	*integer*	Number of export GRPC response message received.
exportInfoRspInvalidFlow **	*integer*	Number of export received for stale flows. **Since: 4.26.2
exportInfoRspInvalidFt	*integer*	Number of export received for invalid flow traker.
exportInfoRspInvalidIntf	*integer*	Number of export received for invalid flow tracker interface.
exportInfoRspNoModule	*integer*	Number of export received for invalid flow tracker module.
exportQueuePushAttempt **	*integer*	Number of export record enqueue attempted. **Since: 4.24.2
exportQueuePushFail	*integer*	Number of export record enqueue failed.
exportQueueWriteUnavailable **	*integer*	Number of times export queue write unavailable. **Since: 4.24.2
exportRingAddEnqFail	*integer*	Number of BESS export ring add enqueue failure.
exportRingDelEnqFail	*integer*	Number of BESS export ring delete enqueue failure.
exportRingInuse	*integer*	Number of export ring data in use.
exportRingSize	*integer*	Size of BESS export ring.
exportfd	*integer*	Export ring BESS file descriptor.
exportfdReq	*integer*	Number of export ring read indication.
exportfdReqFail	*integer*	Number of export ring read indication failure.
fcudPoolAvailable	*integer*	Number of BESS flow-cache user data available.
fcudPoolFull	*integer*	Number of BESS flow-cache user data pool allocation failure.
fcudPoolGet	*integer*	Number of BESS flow-cache user data pool allocation.
fcudPoolInuse	*integer*	Number of BESS flow-cache user data in use.
fcudPoolPut	*integer*	Number of BESS flow-cache user data pool deallocation.
fcudPoolSize	*integer*	Size of BESS flow-cache user data pool.
flowAdd	*integer*	Number flow added.
flowDel	*integer*	Number flow deleted.
flowKeyUdInReq	*integer*	Number of user data requested.
flowKeyUdInRsp	*integer*	Number of user data response received.

flowKeyUdInRspInvalidFlow **	*integer*	Number of user data response for stale flows. **Since: 4.26.2
flowKeyUdInRspInvalidFt	*integer*	Number of user data response for invalid flow tracker.
flowKeyUdInRspInvalidIntf	*integer*	Number of user data response for invalid flow tracker interface.
flowKeyUdInRspNoFlow	*integer*	Number of user data response for invalid flow.
flowKeyUdInRspNoModule	*integer*	Number of user data response for invalid flow tracker module.
flowKeyUdInRspNoPktSeen	*integer*	Number of user data response with no update.
flowKeyUdInRspNotFound	*integer*	Number of user data response not found.
flowUdReq	*integer*	Number of user data GRPC request sent.
flowUdRsp	*integer*	Number of user data GRPC response received.
getExportInfo	*integer*	Number of BESS get export info requests.
getflowUd	*integer*	Number of BESS get user data requests.
grpcErr	*integer*	Number of errors in GRPC processing.

2.1487 show platform sfe high availability

[capabilityReceived]	*integer*	Peer capability received.
[capabilitySupported]	*integer*	Peer capability supported.
[ctrlPacketsReceived]	*integer*	Control packets received.
[ctrlPacketsSent]	*integer*	Control packets sent.
[dataFwdPacketsReceived]	*integer*	Data packets received.
[dataFwdPacketsSent]	*integer*	Data packets forwarded.
[peerGroupId]	*integer*	Peer group identifier.
[peerStateChanges]	*integer*	Peer state changes.
[peerTunnelState]	*enum: down | up*	Peer tunnel state.
[peerVtep]	*IPv4 address*	Peer vtep IP address.
status	*enum: inactive | active | unconfigured*	High availability status.

2.1488 show platform sfe interface profile PROFILE_NAME detail

interfaces	*table(Interface name) = InterfaceProfileIntfParams* see 2.1488.1	Profile details mapping of interface to their hardware parameters.

2.1488.1 InterfaceProfileIntfParams

numRxQs	*integer*	Number of receive queues.
rxMode	*string*	interface mode.
rxWorkers	*string*	List of receive workers.

2.1489 show platform sfe interface profile [...]

profileData	*table(string) = InterfaceProfileEntry* see 2.1489.1	A mapping of interface profiles to their status.

2.1489.1 InterfaceProfileEntry

explanation	*list of string*	List of reasons behind profile status validity.
status	*string*	profile status and validity.

2.1490 show platform sfe ip route [...]

[cmdErr] **	*string*	Error Message. **Since: 4.31.2
gates	*table(string) = AsyncGate* see 2.1490.1	Output Gates keyed by interface string.
vrfs	*table(string) = AsyncPrefix* see 2.1490.2	Maps vrf to prefix.

2.1490.1 AsyncGate

outputGate	*integer*	Output gate.
vrfName	*string*	VRF associated with this interface.

2.1490.2 AsyncPrefix

routes	*table(string) = AsyncFec* see 2.1490.2.1	Maps prefix to FEC info.

2.1490.2.1 AsyncFec

fecKey	*integer*	FecKey associated with L2Adj.
nhLocalIndexes	*list of AsyncNhLocalIndex* see 2.1490.2.1.1	nexthop local indexes.

2.1490.2.1.1 AsyncNhLocalIndex

nhLocalIndex	*integer*	Next Hop Local Index.

2.1491 show platform sfe ip route diff

cModule	*ModuleTable* see 2.1491.3	control Module FIBV4 Table.
diffFIB	*boolean*	Diff FIBV4 packet Module with control Module.
diffModuleFec	*ModuleTable* see 2.1491.3	FIBV4 (FEC) Table Diff.
fecs	*table(numeric string) = FibFecInfo* see 2.1491.1	Maps a FecKey index to FecInfo.
gates	*table(string) = Gates* see 2.1491.2	Output Gates keyed by interface string.
pModVrfs	*table(string) = PModStatusTable* see 2.1491.4	pModule VRFS.
pModuleFec	*ModuleTable* see 2.1491.3	packet Module FEC Table Diff.
pModuleFib	*ModuleTable* see 2.1491.3	packet Module FIBV4 Table Dump.
routes	*table(string) = Fec* see 2.1491.5	Maps vrf/prefix to its FecKey.

2.1491.1 FibFecInfo

fecInfos	*list of pModNextHop* see 2.1491.1.1	Lists of pModNextHop.
numberOfUniqueNextHops	*integer*	Number of Unique Next Hops.

2.1491.1.1 pModNextHop

gate	*integer*	pModule Gate.
nhLocalIndex	*integer*	Next Hop Local Index.

2.1491.2 Gates

outputGate	*integer*	Output gate.

2.1491.3 ModuleTable

fecIndexes	*table(numeric string) = FibFecInfo* see 2.1491.1	Maps a FecKey index to FibFecInfo.
fibs	*list of Fib* see 2.1491.3.1	Lists of Fib.
nhInfos	*list of NextHop* see 2.1491.3.2	Lists of NextHop.

2.1491.3.1 Fib

fecKey	*integer*	FecKey associated with L2Adj.
nextHops	*string*	Comma separated list of Next Hop(s).
prefix	*string*	Prefix.
vrfName	*string*	VrfName.

2.1491.3.2 NextHop

ethAddr	*MAC address*	Destination MAC address.
intf	*interface name*	Egress interface.
nhLocalIndex	*integer*	Next Hop Local Index.
[pktCmd]	*enum: pktCmdSlowReceive | pktCmdNone | pktCmdDrop | pktCmdArpTrap | pktCmdForward | pktCmdTrapVxlanULFlood | pktCmdForwardAndTrap | pktCmdReceive*	Next Hop Type.

2.1491.4 PModStatusTable

activeStatus	*boolean*	pModule status.

2.1491.5 Fec

fecKey	*integer*	FecKey associated with L2Adj.

2.1492 show platform sfe ip route multicast

routes	*table(string) = McastGates* see 2.1492.1	Maps vrf/prefix to its ogate.

2.1492.1 McastGates

cpuGate	*integer*	ogate used for multicast control packet.
dataGate	*integer*	ogate used for multicast data packet.

2.1493 show platform sfe ipv6 route [...]

see 2.1490

2.1494 show platform sfe l3 next-hops [...]

fecs	*table(numeric string) = AsyncFecInfo* see 2.1494.1	Maps a FecKey index to FecInfo.

2.1494.1 AsyncFecInfo

nhInfos	*list of AsyncNextHop* see 2.1494.1.1	Lists of NextHops in this fec.
numberOfUniqueNextHops	*integer*	Number of Unique Next Hops.

2.1494.1.1 AsyncNextHop

l2Adj	*integer*	L2Adj from fecToL2Adjs.
nhFecIndex	*integer*	Index of this nh in the NextHopKey hashmap.
[nhGate] **	*integer*	Next Hop Gate. **Since: 4.28.0
[nhIndex] **	*integer*	Next Hop Index. **Since: 4.28.0
nhIntf	*interface name*	Egress interface.
nhLocalIndex	*integer*	Next Hop Local Index.
nhMac	*MAC address*	Destination MAC address.
[nhType] **	*enum: single | ecmp*	Next Hop Type. **Since: 4.28.0
[nhVlanId] **	*integer*	Next Hop VLAN ID. **Since: 4.28.0
[packetCmd]	*enum: pktCmdSlowReceive | pktCmdNone | pktCmdDrop | pktCmdArpTrap | pktCmdForward | pktCmdTrapVxlanULFlood | pktCmdForwardAndTrap | pktCmdReceive*	Next Hop Type.

2.1495 show platform sfe l3 next-hops diff

cModule	*ModuleTable* see 2.1491.3	control Module Next Hop Table.
diffModule	*ModuleTable* see 2.1491.3	Next Hop Table Diff.
diffNH	*boolean*	Diff Next Hop packet Module with control Module.
fecToL2Adjs	*table(numeric string) = string*	Maps a FecKey to L2Adj.
fecs	*table(numeric string) = FecInfo* see 2.1495.1	Maps a FecKey index to FecInfo.
l2Adjs	*table(string) = Fec* see 2.1491.5	Maps a L2Adj index to FecKey.

pModIntfs	*table(Interface name) = PModStatusTable* see 2.1491.4	pModule interfaces.
pModule	*ModuleTable* see 2.1491.3	packet Module Next Hop Table.

2.1495.1 FecInfo

fecInfos	*list of NextHop* see 2.1491.3.2	Lists of NextHop.
numberOfUniqueNextHops	*integer*	Number of Unique Next Hops.

2.1496 show platform sfe l3 peer-group

peerGroupIdToVtepIpMap	*table(numeric string) = string*	Map for peer group id to vtepIp.

2.1497 show platform sfe l3 software summary

adjCreates	*integer*	Number of adjacency creates.
adjDeletes	*integer*	Number of adjacency deletes.
adjUpdates	*integer*	Number of adjacency updates.
ipVersion	*enum: IPV6 | IPV4*	Version of IP.
lpmCreates	*integer*	Number of LPM creates.
lpmDeletes	*integer*	Number of LPM deletes.
lpmUpdates	*integer*	Number of LPM updates.
lpmUpdatesFecChanged	*integer*	Number of LPM updates where Fec Changed.
lpmUpdatesFecUpdated	*integer*	Number of LPM updates where Fec Updated.
routeDeletes	*integer*	Number of routes deleted.
routeInserts	*integer*	Number of routes inserted.
routeUpdates	*integer*	Number of routes updated.
routeUpdatesFecChanged	*integer*	Number of route updates where Fec Changed.
routeUpdatesFecUpdated	*integer*	Number of route updates where Fec Updated.
routeUpdatesIgnored	*integer*	Number of route updates ignored.

2.1498 show platform sfe l3 unicast summary

forwardingMode	*enum: storeAndForward | defaultMode | cutThrough*	Forwarding mode.
lpmCreateV4 **	*integer*	Number of IPV4 LPM creates. **Since: 4.21.3
lpmCreateV6 **	*integer*	Number of IPV6 LPM creates. **Since: 4.30.2
lpmDeleteV4 **	*integer*	Number of IPV4 LPM deletes. **Since: 4.21.3
lpmDeleteV6 **	*integer*	Number of IPV6 LPM deletes. **Since: 4.30.2
lpmRoutes	*integer*	Number of IPV4 and IPV6 LPM routes.
lpmRoutesV4	*integer*	Number of IPV4 LPM routes.
lpmRoutesV6 **	*integer*	Number of IPV6 LPM routes. **Since: 4.30.2
lpmUpdateV4 **	*integer*	Number of IPV4 LPM updates. **Since: 4.21.3
lpmUpdateV6 **	*integer*	Number of IPV6 LPM updates. **Since: 4.30.2
mcastEnabledV4	*boolean*	Status of IPV4 multicast routing.
mplsEnabled	*boolean*	Status of MPLS routing.
platformAdjSharing	*boolean*	Status of Platform Adjacency sharing.
routeDeletionDelay	*floating point number*	Route deletion delay.
ucastEnabledV4	*boolean*	Status of IPV4 unicast routing.
ucastEnabledV6	*boolean*	Status of IPV6 unicast routing.

2.1499 show platform sfe licensing

tcLicenseCreated	*boolean*	License TC has been created.
throttledInterfaces	*table(Interface name) = integer*	A mapping of interface to its throttled speed in Mbps.

2.1500 show platform sfe memory counters

revision 2

blocks	*table(numeric string) = BessdCounterBlock* see 2.1500.1	Dictionary of all counter blocks keyed by blockId.
countersInBlock	*integer*	Number of counters in each block.
inUseBlocks	*integer*	Number of blocks currently used by the system.
inUseCounters	*integer*	Number of counters currently used by the system.
memoryUsed	*integer*	Memory (in KB) used by the counters in use in the system.
totalBlocks	*integer*	Number of blocks the system supports.

2.1500.1 BessdCounterBlock

allocatedCounters	*integer*	Count of how many counters are allocated from this block.
blockAddress	*integer*	internal memory location allocated for this block.
countersYetToBeFreed	*integer*	Count of how many counters are still in use from this block.

2.1501 show platform sfe memory counters free

counters	*table(numeric string) = BessdCounterInfo* see 2.1501.1	Dictionary of counter info keyed by the counterId.
countersYetToBeFreed	*integer*	Number of counters freed by the control plane but yet to be freed by the data plane.
memoryUsed	*integer*	Memory (in KB) used by the counters in use.

2.1501.1 BessdCounterInfo

blockAddress	*integer*	Internal memory location allocated for this block.
counterAddress	*integer*	Internal memory location allocated for this counter.
[name]	*string*	Name of the counter.
[owner]	*string*	Name of the module using the counter.

2.1502 show platform sfe memory pool

memoryPools	*list of MempoolStatsModel* see 2.1502.1	List of all memory pools.

2.1502.1 MempoolStatsModel

capacity	*integer*	Overall capacity.
capacityLimit	*integer*	Overall capacity limit.
dpdkNamePrefix **	*string*	String used as a common prefix of all underlying memory pools' names. **Since: 4.32.0
entriesAvailable	*integer*	Entries available.
entriesInUse	*integer*	Entries in use.
entrySize	*integer*	One entry size in bytes.
freeMemoryPoolsMap	*string*	Underlying memory pools bit map - 0: full, 1: free.
growthFailsCapacityLimit	*integer*	Count of the memory pool growth fails due to the overall capacit limit.
growthFailsOverall	*integer*	Count of the memory pool growth fails overall.
initialized	*boolean*	Initialized.

memoryPoolsCount	*integer*	Count of the underlying memory pools.
name	*string*	Name.
poolIndex	*integer*	Pool index.

2.1503 show platform sfe mirroring

sessions	*table(string) = MirrorSession* see 2.1503.1	Map from session name to session details.

2.1503.1 MirrorSession

globalId	*integer*	Global Id.
mirrorGroup	*integer*	Mirror group.
sfeModules	*table(string) = SfeModule* see 2.1503.1.1	Map from module name to module details.
srcIntfs	*table(Interface name) = SourceIntf* see 2.1503.1.2	Map from source interface to direction.
tgtIntfs	*table(Interface name) = TargetIntf* see 2.1503.1.3	Map from target interface to encapsulation type.

2.1503.1.1 SfeModule

sfeCounters	*table(string) = SfeSuccessFailCounter* see 2.1503.1.1.2	Counter for success and failure.
sfeSourceIntfs	*table(Interface name) = SfeSourceIntf* see 2.1503.1.1.1	Map from source interface to output gate.
sfeTargetIntfs	*table(Interface name) = SfeTargetIntf* see 2.1503.1.1.3	Map from target interface to input gate.

2.1503.1.1.1 SfeSourceIntf

direction	*enum: Rx | Tx | Both*	direction of traffic to be mirrored.
gate	*integer*	Output gate number.

2.1503.1.1.2 SfeSuccessFailCounter

fail	*integer*	Failure counter.
success	*integer*	Success counter.

2.1503.1.1.3 SfeTargetIntf

gate	*integer*	Input gate number.

2.1503.1.2 SourceIntf

direction	*enum: Rx | Tx | Both*	direction of traffic to be mirrored.

2.1503.1.3 TargetIntf

encapType	*string*	Encapsulation type.

2.1504 show platform sfe mroute AF [...]

groups	*table(IPv4 or IPv6 address) = MfibMrouteGroup* see 2.1504.1	A mapping of group address to MFIB mroute groups.

2.1504.1 MfibMrouteGroup

mroutes	*table(IPv4 or IPv6 address) = MfibMroute* see 2.1504.1.1	A mapping of source address to MFIB mroutes.

2.1504.1.1 MfibMroute

iifRegister	*boolean*	Route is iif register.
[incomingInterface]	*interface name*	Incoming interface for the route.
[incomingInterfaceFrr]	*interface name*	Incoming interface for fast failover route.
[notifyInterface]	*interface name*	Notify interface for the route.
oifRegister	*boolean*	Route is oif register.
outgoingInterfaceGates	*table(Interface name) = OutgoingInterfaceGate* see 2.1504.1.1.1	A mapping of outgoing interface to gate information.
[staticFastdropInterface]	*interface name*	Interface with static fastdrop installed.
toCpu	*boolean*	Route has local listeners.

2.1504.1.1.1 OutgoingInterfaceGate

outgoingInterface	*interface name*	Outgoing interface for the route.
outgoingInterfaceGate	*integer*	Software networking gate for outgoing interface.

2.1505 show platform sfe multicast interface counter AF [...]

intfCounter	*table(Interface name) = McastIntfCounter* see 2.1505.1	Multicast interface counters.

2.1505.1 McastIntfCounter

bytesIn	*integer*	Bytes received.
bytesOut	*integer*	Bytes sent.
pktsDropped	*integer*	Number of packets dropped by kernel.
pktsIn	*integer*	Packets received.
pktsOut	*integer*	Packets sent.
pktsQueued	*integer*	Number of packets queued by kernel.

`vrfName`	*string*	VRF name.

2.1506 show platform sfe nat counters

dyDstAddAttempt	*integer*	Number of dynamic destination add attempts.
dyDstAddSuccess	*integer*	Number of dynamic destination add successes.
dyDstData	*integer*	Number of dynamic destination records.
dyDstDelAttempt	*integer*	Number of dynamic destination delete attempts.
dyDstDelSuccess	*integer*	Number of dynamic destination delete successes.
dyDstModuleFlows	*integer*	Number of dynamic destination module flows.
dyDstTrap	*integer*	Number of dynamic destination trap records.
dyDstTrapAddAttempt	*integer*	Number of dynamic destination trap add attempts.
dyDstTrapAddSuccess	*integer*	Number of dynamic destination trap add successes.
dyDstTrapDelAttempt	*integer*	Number of dynamic destination trap delete attempts.
dyDstTrapDelSuccess	*integer*	Number of dynamic destination trap delete successes.
dyDstUpdAttempt	*integer*	Number of dynamic destination update attempts.
dyDstUpdSuccess	*integer*	Number of dynamic destination update successes.
dySrcAddAttempt	*integer*	Number of dynamic source add attempts.
dySrcAddSuccess	*integer*	Number of dynamic source add successes.
dySrcData	*integer*	Number of dynamic source records.
dySrcDelAttempt	*integer*	Number of dynamic source delete attempts.
dySrcDelSuccess	*integer*	Number of dynamic source delete successes.
dySrcModuleFlows	*integer*	Number of dynamic source module flows.
dySrcTrap	*integer*	Number of dynamic source trap records.
dySrcTrapAddAttempt	*integer*	Number of dynamic source trap add attempts.
dySrcTrapAddSuccess	*integer*	Number of dynamic source trap add successes.
dySrcTrapDelAttempt	*integer*	Number of dynamic source trap delete attempts.
dySrcTrapDelSuccess	*integer*	Number of dynamic source trap delete successes.
dySrcUpdAttempt	*integer*	Number of dynamic source update attempts.
dySrcUpdSuccess	*integer*	Number of dynamic source update successes.
modFlowProcessingFail	*integer*	Number of failure in dynamic flow processing by module.
modProcessingError	*integer*	Number of errors in processing grpc messages by module.

stDstAclData	*integer*	Number of static destination ACL records.
stDstAddAttempt	*integer*	Number of static destination add attempts.
stDstAddSuccess	*integer*	Number of static destination add successes.
stDstData	*integer*	Number of static destination NAT records.
stDstDelAttempt	*integer*	Number of static destination delete attempts.
stDstDelSuccess	*integer*	Number of static destination delete successes.
stDstModuleFlows	*integer*	Number of static destination module flows.
stDstUpdAttempt	*integer*	Number of static destination update attempts.
stDstUpdSuccess	*integer*	Number of static destination update successes.
stSrcAclData	*integer*	Number of static source ACL records.
stSrcAddAttempt	*integer*	Number of static source add attempts.
stSrcAddSuccess	*integer*	Number of static source add successes.
stSrcData	*integer*	Number of static source records.
stSrcDelAttempt	*integer*	Number of static source delete attempts.
stSrcDelSuccess	*integer*	Number of static source delete successes.
stSrcModuleFlows	*integer*	Number of static source module flows.
stSrcUpdAttempt	*integer*	Number of static source update attempts.
stSrcUpdSuccess	*integer*	Number of static source update successes.
twData **	*integer*	Number of twice records. **Since: 4.27.0
twDstAddAttempt **	*integer*	Number of twice destination add attempts. **Since: 4.27.0
twDstAddSuccess **	*integer*	Number of twice destination add successes. **Since: 4.27.0
twDstDelAttempt **	*integer*	Number of twice destination delete attempts. **Since: 4.27.0
twDstDelSuccess **	*integer*	Number of twice destination delete successes. **Since: 4.27.0
twDstModuleFlows **	*integer*	Number of twice destination module flows. **Since: 4.27.0
twDstUpdAttempt **	*integer*	Number of twice destination update attempts. **Since: 4.27.0
twDstUpdSuccess **	*integer*	Number of twice destination update successes. **Since: 4.27.0
twSrcAddAttempt **	*integer*	Number of twice source add attempts. **Since: 4.27.0
twSrcAddSuccess **	*integer*	Number of twice source add successes. **Since: 4.27.0
twSrcDelAttempt **	*integer*	Number of twice source delete attempts. **Since: 4.27.0
twSrcDelSuccess **	*integer*	Number of twice source delete successes. **Since: 4.27.0

`twSrcModuleFlows` **	*integer*	Number of twice source module flows. **Since: 4.27.0
`twSrcUpdAttempt` **	*integer*	Number of twice source update attempts. **Since: 4.27.0
`twSrcUpdSuccess` **	*integer*	Number of twice source update successes. **Since: 4.27.0
`twTrapData` **	*integer*	Number of twice ACL records. **Since: 4.27.0

2.1507 show platform sfe nat module pool-mgr

[flowCacheEntryNotFound] **	*integer*	FlowCache entry not found. **Since: 4.28.1
[natAddressSelectionHash] **	*boolean*	Address allocation algorithm hash enabled. **Since: 4.29.1
[natDropRule] **	*boolean*	Drop rule enabled. **Since: 4.30.2
[natDropRuleFullCone] **	*boolean*	Drop rule full cone enabled. **Since: 4.30.2
[natDropRuleHostHasEntry] **	*boolean*	Drop rule host has entry. **Since: 4.31.1
[natDropRulePoolHasEntry] **	*boolean*	Drop rule pool has entry. **Since: 4.31.1
[natDropRuleSymmetric] **	*boolean*	Drop rule symmetric enabled. **Since: 4.30.2
[natFlowAddErr] **	*integer*	Erros during inserting into NAT flow table. **Since: 4.30.1
[natFlowCacheEexistsErr] **	*integer*	Errors inserting flowCache entry, entry exists. **Since: 4.29.0
[natFlowCacheFwdErr] **	*integer*	Errors inserting flowCache entry for NAT flow, forward flow. **Since: 4.29.0
[natFlowCacheInsertUserObjExistsErr] **	*integer*	Errors inserting flowCache entry with user object, user object exists for the entry after insertion. **Since: 4.31.0
[natFlowCacheRvsErr] **	*integer*	Errors inserting flowCache entry for NAT flow, reverse flow. **Since: 4.29.0
[natFlowCacheUserObjExistsErr] **	*integer*	Errors inserting flowCache entry, entry with user object exists. **Since: 4.30.2
[natFlowExportAddAllocErr] **	*integer*	Allocation errors during flow export add operation. **Since: 4.29.1
[natFlowExportDelAllocErr] **	*integer*	Allocation errors during flow export delete operation. **Since: 4.29.1
[natFlowExportUpdateAllocErr] **	*integer*	Allocation errors during flow export update operation. **Since: 4.29.1
[natFlowFwdAddErr] **	*integer*	Erros during the insertion of the forward entry into NAT flow table. **Since: 4.30.2
[natFlowRvsAddErr] **	*integer*	Erros during the insertion of the reverse entry into NAT flow table. **Since: 4.30.2
[natIpAddressTranslationAny] **	*boolean*	Address allocation IP translation any enabled. **Since: 4.29.1

[natObjectNotFound] **	*integer*	User object not found in flowCache entry. **Since: 4.28.1
[natRestartInProgress] **	*boolean*	Hitless restart in progress. **Since: 4.30.2
[natSourceIpOnlyHash] **	*boolean*	Address allocation source IP only hash enabled. **Since: 4.29.1
[numDropRuleErrors] **	*integer*	Packets dropped because drop rule is set to true. **Since: 4.30.2
[numDropRuleFlowCache-Errors] **	*integer*	Failure to add flow-cache entry, at-least one kind of drop rule is set to true. **Since: 4.32.2
[numDropRuleFullConeErrors] **	*integer*	Packets dropped because drop rule full cone is set to true. **Since: 4.30.2
[numDropRuleHostErrors] **	*integer*	Packets dropped because drop rule set for host. **Since: 4.31.0
[numDropRuleNewConnection-Errors] **	*integer*	Address allocate failure, at-least one kind of drop rule is set to true. **Since: 4.32.2
[numDropRulePoolErrors] **	*integer*	Packets dropped because drop field is set to true for poolId. **Since: 4.31.0
[numDropRuleSymmetric-Errors] **	*integer*	Packets dropped because drop rule symmetric is set to true. **Since: 4.30.2
[numFlowCacheAllocErrors] **	*integer*	Errors allocating from ArNatFlow-CacheEntry mempool. **Since: 4.30.0
[numFlowCacheDeleteErrors] **	*integer*	Errors deleting from flow cache. **Since: 4.30.0
[numFlowCacheEntries]	*integer*	Entries currently in flowCacheTable.
[numFlowCacheEntriesAlloc] **	*integer*	Entries allocated in flowCacheTable. **Since: 4.30.1
[numFlowCacheEntriesFree] **	*integer*	Entries freed in flowCacheTable. **Since: 4.30.1
[numFlowCacheErrors]	*integer*	Failures inserting flowCache entry.
[numNatFlowEntries]	*integer*	Entries in natFlowTable.
[numRestartInProgress-Errors] **	*integer*	Address allocate failure, restart in progress. **Since: 4.30.2
[numRwInfo]	*integer*	Rewrite information currently allocated.
[numRwInfoAlloc] **	*integer*	Rewrite information allocated. **Since: 4.30.1
[numRwInfoFree] **	*integer*	Rewrite information freed. **Since: 4.30.1
[numTwiceRwInfo]	*integer*	Rewrite information currently allocated for TwiceNat.
[numTwiceRwInfoAlloc] **	*integer*	Rewrite information allocated for Twice-Nat. **Since: 4.30.1

[numTwiceRwInfoFree] **	*integer*	Rewrite information freed for TwiceNat. **Since: 4.30.1
[poolAddrNotAvail] **	*integer*	Address allocate failure, address not available. **Since: 4.29.1
[poolAttempts]	*integer*	Address allocate attempts.
[poolFailure]	*integer*	Address allocate failure.
[poolFlowCacheFwdErr]	*integer*	Errors inserting flowCache entry, forward flow.
[poolFlowCacheRvsErr]	*integer*	Errors inserting flowCache entry, reverse flow.
[poolFlowExportErr] **	*integer*	Errors in exporting flow information. **Since: 4.29.1
[poolLookupHits]	*integer*	Lookup hits, address in-use.
[poolMissing]	*integer*	Address allocate failure, missing poolId.
[poolRwInfoAllocErr] **	*integer*	Errors allocating from ArNatRwInfo mempool. **Since: 4.28.1
[poolSuccess]	*integer*	Address allocate success.
[poolTotal]	*integer*	Address allocate function calls.
[poolTwiceRwInfoAllocErr] **	*integer*	Errors allocating from ArNatTwiceRwInfo mempool. **Since: 4.28.1

2.1508 show platform sfe nat pool [...]

detail	*boolean*	Verbose output.
poolRanges	*list of PoolRange* see 2.1508.1	NAT pool ranges configured in the platform.

2.1508.1 PoolRange

addrEnd	*IPv4 address*	NAT pool range start IP address.
addrLast	*IPv4 address*	Last IP address allocated in the NAT pool range.
addrStart	*IPv4 address*	NAT pool range start IP address.
entryId	*integer*	NAT pool range hardware entry ID.
nextEntryId	*integer*	Next NAT pool range hardware entry ID.
overload **	*boolean*	NAT overload pool. **Since: 4.26.2
poolId	*integer*	NAT pool ID.
portEnd	*integer*	NAT pool range start L4 port.
portLast	*integer*	Last L4 port allocated in the NAT pool range.
portStart	*integer*	NAT pool range start L4 port.

2.1509 show platform sfe network-accelerator counters [...]

interfaces	*table(Interface name) = InterfaceCounters* see 2.1509.1	A mapping of interface to their counters.
internalIntfs **	*table(string) = InterfaceCounters* see 2.1509.1	A mapping of internal interface to their counters. **Since: 4.31.1

2.1509.1 InterfaceCounters

counters	*table(string) = integer*	A mapping of all NAC counter names to their values.
inOctets	*integer*	Input octets.
inPackets	*integer*	Input Packets.
outOctets	*integer*	Output octets.
outPackets	*integer*	Output Packets.

2.1510 show platform sfe network-accelerator flows

rules	*table(numeric string) = NacIesSaFlowParams* see 2.1510.1	A mapping of rule id to their SA flow information.

2.1510.1 NacIesSaFlowParams

destination	*IP address*	Destination IP Address.
interface	*interface name*	Physical interface.
portId	*integer*	Interface port number.
spi	*string*	Security Policy Index for ESP.
tableId	*integer*	SA list table IPv4 or IPv6.
udpPort	*integer*	UDP port.

2.1511 show platform sfe network-accelerator mac address-table

rules	*table(numeric string) = NacIesMacTableParams* see 2.1511.1	A mapping of rule id to their MAC table information.

2.1511.1 NacIesMacTableParams

dmac	*MAC address*	MAC address.
interface	*interface name*	Physical interface.
portId	*integer*	Interface port number.
tableId	*integer*	PreVeb table.
vlan	*integer*	VLAN ID.

2.1512 show platform sfe network-accelerator status

decryptionPortStatus	*enum: enabled* | *disabled* | *unknown*	Decryption port status.
encryptionPortStatus	*enum: enabled* | *disabled* | *unknown*	Encryption port status.
interfaces	*table(Interface name)* = *InterfaceState* see 2.1512.1	A mapping of interface to their NAC state.
internalIntfs **	*table(string)* = *InterfaceState* see 2.1512.1	A mapping of internal interfaces to their NAC state. **Since: 4.31.1
ipsecEnabled	*boolean*	Is IPsec enabled.
nacEtrackId	*string*	NAC E-Track ID.
nacSwitchNattStatus	*enum: enabled* | *disabled* | *unknown*	NAC switch NAT traversal status.
nacSwitchState	*enum: enabled* | *disabled* | *unknown*	NAC switch state.
nacVersion	*string*	NAC firmware version.
nisVersion	*string*	NIS firmware version.
phyVersion	*string*	PHY firmware version.
saMax	*integer*	Maximum SAs programmable in the switch.
saProgrammed	*integer*	Total SAs programmed in the switch.
switchRevision	*enum: C0* | *A0* | *unknown* | *B0*	Switch device revision number.

2.1512.1 InterfaceState

interfaceType	*enum: 10G-SFI* | *unknown* | *n/a* | *10GBASE-KR* | *1000BASE-X*	Interface Type.
mode	*enum: inactive* | *connected* | *initializing* | *unknown* | *notapplicable* | *errdisabled* | *maint-down* | *adminIsolated* | *noSignal* | *uninitialized* | *no-resource* | *signal* | *admin* | *notconnect* | *disabled* | *autoIsolated*	Connection status of the interface.
status	*enum: lowerLayerDown* | *unknown* | *down* | *up* | *testing* | *notPresent* | *notApplicable* | *dormant*	Line protocol status.

2.1513 show platform sfe qos

cpuReceiveLimit	*integer*	Control plane receive limit.
rateUnit	*enum: rateUnitMbps* | *rateUnitKbps* | *rateUnitInvalid* | *rateUnitbps* | *rateUnitPps*	Rate unit of Control plane receive limit.

txModeCpu	*enum: txModeEnqueue | txModeDirect | txModeInvalid | txModeAdaptive*	Tx Mode CPU.
txModeInterface	*enum: txModeEnqueue | txModeDirect | txModeInvalid | txModeAdaptive*	Tx Mode Interface.

2.1514 show platform sfe route-cache ip hitbit (vrf VRF)

hitbitEntries	*list of HitbitEntry* see 2.1514.1	List of hitbit entries.

2.1514.1 HitbitEntry

hitbit	*integer*	Hitbit value.
prefix	*IP address prefix*	IP prefix.

2.1515 show platform sfe route-cache ip hitbit summary

vrfs	*table(string) = integer*	Mapping of VRF to hitbit count.

2.1516 show platform sfe route-cache summary

revision 2

hitbitCount	*integer*	Number of IPv4 prefixes in hitbit table.
ipv4NotificationFailCounter	*integer*	IPv4 prefix notification fail count.
ipv4NotificationSuccess-Counter	*integer*	IPv4 prefix notification success count.
ipv4PrefixesAgedOutCount	*integer*	Number of IPv4 prefixes aged out.
ipv4PrefixesMovedToHwCount	*integer*	Number of IPv4 prefixes moved to HW.
ipv4RoutePrefixHwSpaceLeft	*integer*	Space left in HW for IPv4 prefixes.
kickAttemptCount	*integer*	Kick attempt count in BESS.
[kickFailCount]	*integer*	Kick attempt fail count in BESS.
prefixEnqFailCount	*integer*	Prefix enqueue fail count in BESS.
readKickNotificationCount	*integer*	Read kick notification count.
routeCachePrefixReqCount	*integer*	Route cache prefix request count.

2.1517 show platform sfe status

revision 2

bessBuffers	*integer*	Number of bess buffers.
cloudInstanceType	*string*	Cloud instance type.
cpuGhz	*floating point number*	Clock speed of CPU in Ghz.
cpuModel	*string*	Processor model name.
dpMem	*integer*	Memory for datapath in MB.
dpdkVersion	*string*	DPDK version.
flowCache	*table(string) = FlowCacheInsertionModel* see 2.1517.1	A mapping from IP type to flow cache details.
isolCpuHigh	*integer*	Upper limit of the range of isolated CPUs.
isolCpuLow	*integer*	Lower limit of the range of isolated CPUs.
lastReloadTime	*string*	Last Sfe agent reload time.
maxVrfs	*integer*	Maximum number of VRFs.
nCpCores	*integer*	Number of control plane cores.
nDpCores	*integer*	Number of datapath cores.
nicInfo	*table(Interface name) = NicInfo* see 2.1517.2	Dictionary of NIC information keyed by interface name.
num1GbHugepages	*integer*	Number of 1GB hugepages allocated.
num2MbHugepages	*integer*	Number of 2MB hugepages allocated.
platform	*string*	Cloud platform.
threadsPerCore	*integer*	Number of threads per core.
vrfCount	*integer*	Number of VRFs in use.

2.1517.1 FlowCacheInsertionModel

insertionRates	*table(string) = floating point number*	Flow Cache Insert Averages, keyed by interval in seconds.
maxKeys	*integer*	Max keys supported by the Flow Cache.
numFlows	*integer*	Current Flow Cache entries.

2.1517.2 NicInfo

busInfo	*string*	PCI bus information.
driver	*string*	Driver.
l3SubIntfCapable	*boolean*	Layer-3 sub-interface capable.
macAddr	*MAC address*	MAC address.
nicType	*enum: nac | virtualNic | vSwitch | nicUnknown | vni | xl710 | acceleratedNetworking | cn10k | e810 | x553 | physical | i226 | i350 | vf | passthrough*	NIC Type.
pciAddr	*string*	PCI address.
version	*string*	Version.

2.1518 show platform sfe worker summary [...]

revision 2

[dpiFlowsByTotalPackets] **	*TopDpiFlowsModel* see 2.1518.1	Top IPsec flows by total packets. **Since: 4.35.0
flowCache	*table(string) = FlowCacheInsertionModel* see 2.1517.1	Flow Cache details keyed by ip version.
[ipsecFlowsByPps] **	*TopIpsecFlowsModel* see 2.1518.2	Top DPI flows by PPS. **Since: 4.35.0
workers	*table(numeric string) = WorkerInfoModel* see 2.1518.3	Worker Summary, keyed by worker ID.

2.1518.1 TopDpiFlowsModel

ipv4	*list of DpiFlowModel* see 2.1518.1.1	DPI flows ordered by total packets.

2.1518.1.1 DpiFlowModel

destinationIp	*string*	Destination IP address.
dpiPkts	*integer*	DPI total packets.
[protocol]	*enum: igmp | tcp | udp | icmp*	L4 protocol.
sourceIp	*string*	Source IP address.
vrfName	*string*	VRF name.
workerId	*integer*	Worker ID.

2.1518.2 TopIpsecFlowsModel

ipv4	*list of IpsecFlowModel* see 2.1518.2.1	IPsec flows ordered by PPS.

2.1518.2.1 IpsecFlowModel

destinationIp	*string*	Destination IP address.
ipsecPps	*integer*	IPsec packets per second.
[protocol]	*enum: igmp | tcp | udp | icmp*	L4 protocol.
sourceIp	*string*	Source IP address.
vrfName	*string*	VRF name.
workerId	*integer*	Worker ID.

2.1518.3 WorkerInfoModel

busy	*integer*	Worker busy percentage.
core	*integer*	Worker coreId mapping.
[dpi]	*integer*	DPI flows.
[dpiPkts]	*integer*	DPI packets.

[ipsec]	*integer*	IPsec flows.
[ipsecPps]	*integer*	IPsec packets per second.
pps	*integer*	Worker packets per second.

2.1519 show platform smbus counters

devices	*table(string) = DeviceModel* see 2.1519.1	Mapping from SMBus device address to device counter info.

2.1519.1 DeviceModel

name	*string*	Name of SMBus device.
rxByteCount	*integer*	Number of rx bytes processed.
rxEstByteRate	*floating point number*	Estimated rate of rx bytes per second.
txByteCount	*integer*	Number of tx bytes processed.
txEstByteRate	*floating point number*	Estimated rate of tx bytes per second.

2.1520 show platform smbus counters errors

devices	*table(string) = DeviceErrorModel* see 2.1520.1	Mapping from SMBus device address to device error counter info.

2.1520.1 DeviceErrorModel

ack	*integer*	Number of ack errors for SMBus device.
busConflict	*integer*	Number of bus conflict errors for SMBus device.
name	*string*	Name of SMBus Device.
[rxPecError] **	*integer*	Number of rx PEC errors for SMBus device. **Since: 4.34.0
timeout	*integer*	Number of timeout errors for SMBus device.
[txPecError] **	*integer*	Number of tx PEC errors for SMBus device. **Since: 4.34.0

2.1521 show platform tfa counters flow

[interfaceTypes]	*table(string) = ArfaRateCounterDirections* see 2.1521.1	Collections keyed by counter's name.
[l3Ports] **	*table(string) = ArfaRateCounterDirections* see 2.1521.1	Collections keyed by counter's name. **Since: 4.35.2

[routingHandlers]	*table(string) = ArfaRateCounterDirections* see 2.1521.1	Collections keyed by counter's name.

2.1521.1 ArfaRateCounterDirections

[input]	*ArfaRateCounter* see 2.1521.1.1	Input counters.
[output]	*ArfaRateCounter* see 2.1521.1.1	Output counters.

2.1521.1.1 ArfaRateCounter

bitsRate	*integer*	Number of bits per second.
interval	*integer*	Interval in seconds.
octets	*integer*	Number of octets counted in this bucket.
packets	*integer*	Number of packets counted in this bucket.
packetsRate	*integer*	Number of packets per second.

2.1522 show platform tfa counters kernel interfaces

pams	*table(string) = PamCollectionEntry* see 2.1522.1	PAMs keyed by their name.

2.1522.1 PamCollectionEntry

inDrops	*integer*	The number of drops on the rx queue.
inErrors	*integer*	The number of rx failures.
inOctets	*integer*	The number of bytes received.
inPkts	*integer*	The number of packets received.
[lastOutError]	*string*	The errno returned while attempting to send the packet.
outDrops	*integer*	The number of tx failures because the socket buf was full.
outErrors	*integer*	The number of tx failures for any other reason.
outOctets	*integer*	The number of bytes sent.
outPkts	*integer*	The number of packets sent.

2.1523 show platform tfa interface mode

bootMode	*enum: relaying | default | unknown*	The interface mode at initial boot time. Is 'unknown' if forwarding has not been initialized.
configuredMode	*enum: relaying | default | unknown*	The configured interface mode. Is 'unknown' if the mode has not been configured.
mode	*enum: relaying | default | unknown*	The interface mode. Is 'unknown' if forwarding has not been initialized.

needsRestart **	*boolean*	If the interface mode has changed, the system needs to be restarted. **Since: 4.34.2

2.1524 show platform tfa kernel interfaces path

devices	*table(string) = EosLabKernelInterfaceSortingInfo* see 2.1524.1	Maps kernel device name to interface sorting information.

2.1524.1 EosLabKernelInterfaceSortingInfo

[acpiIndex]	*integer*	ACPI index, if present.
path	*string*	kernel device path.

2.1525 show platform tfa lookups

lookupsTable	*table(string) = GenericLookups* see 2.1525.1	LookupsTable keyed by their name.

2.1525.1 GenericLookups

lookups	*list of GenericLookup* see 2.1525.1.1	Lookups specified by this feature.

2.1525.1.1 GenericLookup

handler	*string*	Handler of lookup.
id	*string*	Id of lookup.
key	*string*	Key(EnumName) of lookup.
lookupCount **	*integer*	Lookup count. **Since: 4.35.0

2.1526 show platform tfa pbr nexthops

nexthopsInUse	*list of ArfaPbrNexthopModel* see 2.1526.1	list of nexthops in use.

2.1526.1 ArfaPbrNexthopModel

nexthop	*IP address*	nexthop in use.
vrf	*string*	vrf in which the nexthop is used.

2.1527 show platform tfa rates mac security

buckets	*table(string) = MacsecSingleFlowRateModel* see 2.1527.1	A mapping from token bucket to tokens and flow rate.

2.1527.1 MacsecSingleFlowRateModel

currentTokens	*floating point number*	Current tokens in Bits.
fillRate	*floating point number*	Token bucket fill rate in Bits per second.
flowRate	*floating point number*	Actual flow rate in Bits per second.
maxTokens	*floating point number*	Maximum number of tokens that could be in the bucket.

2.1528 show platform trident ((counters raw) | (counters raw (interface INTERFACE) | (all (interface INTERFACE)))) [...]

interfaces	*table(Interface name) = PlatformCounterInterfaceRawModel* see 2.1528.1	Mapping between port interface and interface registers and tables.

2.1528.1 PlatformCounterInterfaceRawModel

registers	*table(string) = PlatformCounterUnitRawModel* see 2.1528.1.1.1	Mapping between register name and register information.
tables	*table(string) = PlatformCounterTableRawModel* see 2.1528.1.1	Mapping between table name and table information.

2.1528.1.1 PlatformCounterTableRawModel

elements	*table(string) = PlatformCounterUnitRawModel* see 2.1528.1.1.1	Mapping between table index and table information.

2.1528.1.1.1 PlatformCounterUnitRawModel

[byteCount]	*integer*	Absolute byte count.
[count]	*integer*	Absolute count (register-specific).
[packetCount]	*integer*	Absolute packet count.
[redPacketCount]	*integer*	Absolute count (register-specific).
[wredPacketCount]	*integer*	Absolute packet count.
[wredRedPacketCount]	*integer*	Absolute count (register-specific).
[wredYellowPacketCount]	*integer*	Absolute count (register-specific).
[yellowPacketCount]	*integer*	Absolute count (register-specific).

2.1529 show platform trident acl [...]

activeAcls	*list of StrataAclRequestModel* see 2.1529.1	Active ACLs.
failedAcls	*list of StrataAclRequestModel* see 2.1529.1	ACLs which have failed to install.

2.1529.1 StrataAclRequestModel

aclDirection	*enum: in | out*	Direction of ACL.
aclGroup	*string*	ACL group name.
aclName	*string*	Name of the ACL.
aclType	*enum: ipv6 | mac | ip*	Type of ACL.

featureGroupType	*enum: fgtEfpBreadthTest* | *fgtIfpTrafficConc* | *fgtIfpOpenflowFloodTable* | *fgtPolicyQosIp* | *fgtBreadthTest1* | *fgtIfpGroupMirrorAcl4* | *fgtIfpGroupMirrorIpAcl1* | *fgtL2CtrlArpInspection* | *fgtCompressionL4SrcPort* | *fgtIfpOpenflowRegularTable* | *fgtSecurityIngressIfpPAcl-Ip6Std* | *fgtL3CtrlTtlCheck* | *fgtAegisEgressRoutedIpv4* | *fgtUnicastEapol* | *fgtIfpAegisSegmentSecurity* | *fgtSecurityIngressVAclIp* | *fgtUnsupportedQualTestIfp* | *fgtIfpMacCollision-HandlingDst* | *fgtMirroringAcl3Mac-Ingress* | *fgtEgrPolicyQosIp* | *fgtEfpGroupMirrorPort-RateLimit* | *fgtIfpDirectflowL2Only* | *fgtSecurityIngressIfpPAcl-Ip6Vni* | *fgtIfpGroupMirrorIpAcl2* | *fgtEfpPTPBypass* | *fgtIfpTcpMssClamping* | *fgtVfpBreadthTest1* | *fgtIpv4v6EgressCounter* | *fgtL2CtrlDot1xMba* | *fgtMacsecInlineEgress* | *fgtIfpGroupMirrorIp6Acl4* | *fgtSecurityEgressPAclIp6-Std* | *fgtIntIfaTransitRules* | *fgtIfpGroupMirrorIpAcl4* | *fgtIntRules* | *fgtL2CtrlLlc-FrameValidation* | *fgtIfpOpenflowFull* | *fgtIfpOpenflowUdf* | *fgtIfpGroupMirrorMacAcl2* | *fgtInvalid* | *fgtVfpDirectflowP4RtVrf* | *fgtSviSharedPolicyQosIp* | *fgtDirectedBroadcastRules* | *fgtIfpChannelRedirection* | *fgtIfpOpenflowL2OnlyLow* | *fgtSecurityIngressPAclIp-Vni* | *fgtL3CtrlMlagCtrlTraffic* | *fgtIfpDirectflowP4Rt-PostcardIpv6* | *fgtMirroringAcl2Ip6Ingress* | *fgtMirroringAcl2IpIngress* | *fgtIfpL3ctrlExceptionTHx-Openflow* | *fgtVfpTripleBreadthTest* | *fgtIfpGroupMirrorAcl3* | *fgtSecurityIngressPAclIp6* | *fgtL2CtrlL3Routing* |	Feature group type.

[interfaces]	*table(Interface name) = InterfaceDetails* see 2.1529.1.1	Interfaces on which ACL is applied.
requestConfigType	*enum: deleteConfig | deleteConfigInRevOrder | testDrivenPartial-Exhaustion | invalid | updateInterfaceInRevOrder | updateInterface | revertConfig | updateAction | updateConfig | updateEntry | testDrivenExhaustion | newConfig*	Last request type.
requestStatusType	*enum: requestFailureOut-OfPolicerOrCounter | requestNone | requestFailureUnknown | requestFailureOutOf-SubportGroupId | requestFailureOutOfUDF | requestFailureOutOfSpace | requestFailureCounter-ObjectExhaustion | requestSuccess | request-FailureOutOfRangeChecker | requestFailureTimeout | requestFailureUDFGroup-Expansion | requestNotApplicable | requestPending | requestFailureConfigError | requestFailureIntfProfileId-NotFound*	Last known status of this request.
[ruleIdsDetails]	*list of StrataAclRuleIdModel* see 2.1529.1.2	Rule Details, keyed by sequence number.
rulesIdsCount	*integer*	Number of rule IDs used by ACL.
[sharingId]	*integer*	Resource sharing ID.
standard	*boolean*	Standard ACL.

2.1529.1.1 InterfaceDetails

interfaceType	*enum: tunnel | port | svi | subIntf*	Interface type.
relatedInterface	*interface name*	Related interface name.

2.1529.1.2 StrataAclRuleIdModel

description	*string*	Description of rule.
[ethAddrQualifiers]	*table(string) = Qualifier* see 2.1529.1.2.1	Qualifiers, keyed by qualifier type.
[featureActions]	*list of string*	List of ACL actions.

hits	*integer*	Number of packets hit this rule.
[ip6Qualifiers]	*table(string) = Qualifier* see 2.1529.1.2.1	Qualifiers, keyed by qualifier type.
[portQualifiers]	*table(string) = PortQualifier* see 2.1529.1.2.3	Qualifiers, keyed by qualifier type.
[qualifiers]	*table(string) = Qualifier* see 2.1529.1.2.1	Qualifiers, keyed by qualifier type.
[rangeCheckers]	*table(string) = RangeChecker* see 2.1529.1.2.2	Range Checkers, keyed by range checker type.
ruleEnabled	*boolean*	Rule is enabled in hardware.
ruleId	*integer*	Unique identifier for this rule.
sequenceNo	*integer*	User-set sequence number for this rule.

2.1529.1.2.1 Qualifier

data	*string*	Qualifier data.
mask	*string*	Qualifier mask.

2.1529.1.2.2 RangeChecker

high	*integer*	Highest range.
low	*integer*	Lowest range.

2.1529.1.2.3 PortQualifier

modIdData	*integer*	Module Id Data.
modIdMask	*integer*	Module Id Mask.
portIdData	*integer*	Port Id Data.
portIdMask	*integer*	Port Id Mask.

2.1530 show platform trident agent [...]

agents	*table(string) = TridentAgentModel* see 2.1530.1	Agent information by chip name.

2.1530.1 TridentAgentModel

chipName	*string*	Chip name.
configEnabled	*boolean*	Agent config enabled.
configGenId	*integer*	Agent config GenID.
fapId	*integer*	Fap ID.
logicalFapId	*integer*	Logical Fap ID.
sliceName	*string*	Slice name.
statusEnabled	*boolean*	Agent status enabled.

statusGenId	*integer*	Agent status GenID.

2.1531 show platform trident agent port [...]

chips	*table(string) = ChipPortsModel* see 2.1531.1	Per-chip port information keyed by chip name.

2.1531.1 ChipPortsModel

interfaces	*table(Interface name) = PortInfoModel* see 2.1531.1.1	Port information keyed by interface.

2.1531.1.1 PortInfoModel

logical	*integer*	Logical port number.
mmu	*integer*	MMU port number.
modId	*integer*	Module ID.
physical	*integer*	Physical port number.

2.1532 show platform trident agent role [...]

agentRoles	*table(string) = RoleModel* see 2.1532.1	Agent role information, keyed by chip name.

2.1532.1 RoleModel

operationalMode	*string*	Slice Operational Mode.
role	*string*	Agent role.
sliceName	*string*	Slice name.

2.1533 show platform trident ces connection [...]

switchcards	*table(string) = ConnectionsModel* see 2.1533.1	Per-switchard CES connections.

2.1533.1 ConnectionsModel

interfaces	*table(Interface name) = ConnectionModel* see 2.1533.1.1	CES connections by keyed by interface.

2.1533.1.1 ConnectionModel

channelId	*integer*	Channel ID.
linecard	*interface name*	Linecard Fabric Interface.
logicalPort	*integer*	Switchcard Logical Port number.
modId	*integer*	Switchcard ModId.
subport	*integer*	Switchcard Subport number.
switchcard	*interface name*	Switchcard Fabric Interface.

2.1534 show platform trident ces queue-mapping

linecards	*table(string) = PortQueueMapsModel* see 2.1534.1	Per-linecard CES port queue map info.

2.1534.1 PortQueueMapsModel

interfaces	*table(Interface name) = PerSWCQueueMapModel* see 2.1534.1.1	CES port queue mapping per switchcard.

2.1534.1.1 PerSWCQueueMapModel

controlQueue	*integer*	L2 Control Queue ID.
dataQueue	*integer*	Data Queue ID.
flowControlQueue	*integer*	Flow Control Queue ID.
peerSwitchcard	*table(string) = PortMappingModel* see 2.1534.1.1.1	frontpanel to backpanel mappings.

2.1534.1.1.1 PortMappingModel

linecard	*interface name*	Linecard Fabric Interface.
switchcard	*interface name*	Switchcard Fabric Interface.

2.1535 show platform trident counters [...]

revision 2

cpu **	*table(Interface name) = PlatformCountType-CountersModel* see 2.1535.1	CPU Port Interface Counters. **Since: 4.29.1
cpuMappings **	*table(Interface name) = string*	Chip names for cpu port ids. **Since: 4.29.1
ethernet	*table(Interface name) = PlatformCountType-CountersModel* see 2.1535.1	Front Panel Interface Counters.
fabric	*table(Interface name) = PlatformCountType-CountersModel* see 2.1535.1	Fabric Port Interface Counters.
internalRecirc **	*table(Interface name) = PlatformCountType-CountersModel* see 2.1535.1	Internal Recirc Interface Counters. **Since: 4.33.1

2.1535.1 PlatformCountTypeCountersModel

count	*PlatformInterfaceCounter-Model* see 2.1535.1.1	Various platform counters for this interface.

2.1535.1.1 PlatformInterfaceCounterModel

drop	*PlatformDropCounter-Model* see 2.1535.1.1.1	Drop platform counters for this interface.
[dropreason] **	*PlatformDropReason-CounterModel* see 2.1535.1.1.2	Drop reason counters for this interface. **Since: 4.28.1
error	*PlatformErrorCounter-Model* see 2.1535.1.1.3	Error platform counters for this interface.
ok	*PlatformOkCounterModel* see 2.1535.1.1.4	Non Error/Drop platform counters for this interface.
sampled	*PlatformSampledCounter-Model* see 2.1535.1.1.5	Sampled counters for this interface.

2.1535.1.1.1 PlatformDropCounterModel

[inDiscards]	*integer*	RX Discards.
[ipv4L3Discard]	*integer*	RX - IPV4 L3 Discard.
[ipv6L3Discard]	*integer*	RX - IPV6 L3 Discard.
[nonCongestionDiscard]	*integer*	RX - Non congestion discards.
[outDiscards]	*integer*	TX Discards.

[rxAccessPortTrillDiscard]	*integer*	RX - Access Port Trill Packets Discarded.
[rxBufferPoolDiscard]	*integer*	RX - IBP discard and CPB full.
[rxFpDrop]	*integer*	RX - Packets dropped by FP.
[rxIngressNFDrop]	*integer*	RX - Dropped as ingress not forwarding.
[rxMCDrop]	*integer*	RX - Receive multicast drop.
[rxMmuDrop]	*integer*	RX - Packets dropped by the MMU.
[rxNetworkPortNonTrill-Discard]	*integer*	RX - Network Port Non-Trill Packets Discarded.
[rxPipelineDrop]	*integer*	RX - Packets dropped by the pipeline.
[rxPolicyDiscard]	*integer*	RX - Receive policy discard.
[rxUrpfDrop]	*integer*	RX - Receive uRPF drop.
[txAccessPortTrillDiscard]	*integer*	TX - Access Port Trill Packets Discarded.
[txL2MCDrop]	*integer*	TX - L2 multicast drop.
[txL3UCAgedDrop]	*integer*	TX - IPV4 L3 unicast aged and dropped packets.
[txMmuDrop]	*integer*	TX - Packets dropped by the MMU.
[txMmuDropRed]	*integer*	TX - Red packets dropped by the MMU.
[txMmuDropYellow]	*integer*	TX - Yellow packets dropped by the MMU.
[txNetworkPortNonTrill-Discard]	*integer*	TX - Network Port Non-Trill Packets Discarded.
[txPipelineDrop]	*integer*	TX - Packets dropped by the pipeline.
[txTTLDrop]	*integer*	TX - Dropped because TTL counter.
[wredDropPktCounter]	*integer*	TX - WRED drop.

2.1535.1.1.2 PlatformDropReasonCounterModel

[CMLFlags]	*integer*	RX - drop due to CML flags.
[DSTFP]	*integer*	RX - drop due to destination FP.
[EMFT]	*integer*	RX - drop due to EM FT.
[IFP]	*integer*	RX - drop due to IFP.
[IFPMeter]	*integer*	RX - drop due to IFP Meter.
[IPMCL3IIFOrRPAIDCheck-Failed]	*integer*	RX - drop due to IPMC L3 IIF.
[IVXLT]	*integer*	RX - drop due to IVXLT.
[PVLANDrop]	*integer*	RX - drop due to PVLAN drop.
[VFP]	*integer*	RX - drop due to VFP.
[blockMaskDrop]	*integer*	RX - drop due to block mask drop.
[dstLinkDown]	*integer*	RX - drop due to dst linkdown.
[dstPBMZero]	*integer*	RX - drop due to dst PBM zero.
[egrMembershipCheckFailed]	*integer*	RX - drop due to egress membership.
[egrSpanningTreeCheck-Failed]	*integer*	RX - drop due to egress spanning tree.
[forteIpv4Gateway] **	*integer*	RX - drop due to FORTE IPV4 gateway. **Since: 4.29.0
[incomingPvlanCheckFailed]	*integer*	RX - drop due to incoming PVLAN.
[ingRecircleHdrDrop] **	*integer*	RX - drop due to EP NIH packet. **Since: 4.29.0
[l2DstDiscard]	*integer*	RX - drop due to L2 dst discard.
[l2DstLookupMiss]	*integer*	RX - drop due to L2 dst lookup.
[l2SrcDiscard]	*integer*	RX - drop due to L2 src discard.

[l2SrcStaticMove]	*integer*	RX - drop due to L2 src static.
[l3DstDiscard]	*integer*	RX - drop due to L3 dst discard.
[l3DstLookupMiss]	*integer*	RX - drop due to L3 dst lookup.
[l3HdrError]	*integer*	RX - drop due to L3 header error.
[l3IIFEqL3OIF]	*integer*	RX - drop due to L3 IIF equals L3.
[l3MtuCheckFailed]	*integer*	RX - drop due to L3 MTU check.
[l3TTLError]	*integer*	RX - drop due to L3 TTL error.
[lagFailoverPortDown]	*integer*	RX - drop due to lag failover port.
[macSaMulticast]	*integer*	RX - drop due to MacSa Multicast.
[membershipCheckFailed]	*integer*	RX - drop due to membership check.
[mplsCtrlPktDrop]	*integer*	RX - drop due to mpls ctrl pkt.
[mplsEcnError]	*integer*	RX - drop due to mpls ECN error.
[mplsLabelActionInvalid]	*integer*	RX - drop due to mpls label action.
[mplsProtectionDrop]	*integer*	RX - drop due to mpls protection.
[mplsReservedLabelExposed]	*integer*	RX - drop due to mpls reserved.
[mplsTTLError]	*integer*	RX - drop due to mpls TTL error.
[mplsTermPolicySelectTable-Drop]	*integer*	RX - drop due to mpls term policy.
[noDrop]	*integer*	Dropped with no reason.
[outerTpidCheckFailed]	*integer*	RX - drop due to outer TPID check.
[pktIntegrityCheckFailed]	*integer*	RX - drop due to packet integrity.
[protocolPktDrop]	*integer*	RX - drop due to protocol packet.
[seqNumCheckFailed]	*integer*	RX - drop due to seq num check.
[spanningTreeCheckFailed]	*integer*	RX - drop due to spanning tree.
[splitHorizonCheckFailed]	*integer*	RX - drop due to split horizon.
[srcPortKnockoutDrop]	*integer*	RX - drop due to source port knockout.
[stormControlDrop]	*integer*	RX - drop due to storm control.
[tunnelAdaptDrop]	*integer*	RX - drop due to tunnel adapt drop.
[tunnelObjectValidation-Failed]	*integer*	RX - drop due to tunnel object.
[tunnelShimHdrError]	*integer*	RX - drop due to tunnel shim.
[tunnelTTLCheckFailed]	*integer*	RX - drop due to tunnel TTL check.
[unknownDropReason] **	*integer*	RX - drop for unknown reason. **Since: 4.29.0
[urpfCheckFailed]	*integer*	RX - drop due to Urpf check failed.

2.1535.1.1.3 PlatformErrorCounterModel

[alignmentErrors]	*integer*	Alignment Errors.
[fcsErrors]	*integer*	FCS Errors.
[frameTooLongs]	*integer*	Frame Too Long.
[frameTooShorts]	*integer*	Undersize packets.
[inErrors]	*integer*	RX Errors.
[internalMacReceiveErrors]	*integer*	RX Internal MAC Errors.
[ipv4L3HeaderError]	*integer*	RX - IPV4 header error.
[ipv6L3HeaderError]	*integer*	RX - IPV6 header error.
[outErrors]	*integer*	TX Errors.
[rxL2MTUError]	*integer*	RX - L2 MTU oversize dropped packets.
[rxTunnelError]	*integer*	RX - Tunnel error packets.

[rxVlanDrop]	*integer*	RX - Receive VLAN drop.
[sqeTestErrors]	*integer*	SQE Test Errors.
[symbolErrors]	*integer*	Symbol Errors.
[txFCSError]	*integer*	TX - FCS error.
[txInvalidVlan]	*integer*	TX - Invalid VLAN.
[txL2MTUError]	*integer*	TX - L2 MTU oversize dropped packets.
[txMACError]	*integer*	TX - Transmit MAC error.
[txPCError]	*integer*	TX - Purge or cell error.
[txSplitHorizonDrop]	*integer*	TX - Packets dropped by Split Horizon.
[txUnknownDrop]	*integer*	TX - Packet dropped due to any condition.
[txVxltMiss]	*integer*	TX - Miss in VXLT table counter.

2.1535.1.1.4 PlatformOkCounterModel

[deferredTransmissions]	*integer*	Deferred Transmissions.
[ecnMarkedPackets]	*integer*	TX - ECN marked packets.
[fragments]	*integer*	Fragments.
[in1024To1518OctetFrames]	*integer*	RX counter bin 1024-1518 bytes.
[in128To255OctetFrames]	*integer*	RX counter bin 128-255 bytes.
[in1519To2047OctetFrames]	*integer*	RX counter bin 1519-2047 bytes.
[in2048To4095OctetFrames]	*integer*	RX counter bin 2048-4095 bytes.
[in256To511OctetFrames]	*integer*	RX counter bin 256-511 bytes.
[in4096To9216OctetFrames]	*integer*	RX counter bin 4096-9216 bytes.
[in512To1023OctetFrames]	*integer*	RX counter bin 512-1023 bytes.
[in64OctetFrames]	*integer*	RX counter bin 64 bytes.
[in65To127OctetFrames]	*integer*	RX counter bin 65-127 bytes.
[in9217To16383OctetFrames]	*integer*	RX counter bin 9217-16383 bytes.
[inBroadcastPkts]	*integer*	RX Broadcast packets.
[inMulticastPkts]	*integer*	RX Multicast packets.
[inOctets]	*integer*	RX bytes.
[inPauseFrames]	*integer*	RX Pause Frames.
[inPfc0Frames]	*integer*	Pfc0 Indications.
[inPfc1Frames]	*integer*	Pfc1 Indications.
[inPfc2Frames]	*integer*	Pfc2 Indications.
[inPfc3Frames]	*integer*	Pfc3 Indications.
[inPfc4Frames]	*integer*	Pfc4 Indications.
[inPfc5Frames]	*integer*	Pfc5 Indications.
[inPfc6Frames]	*integer*	Pfc6 Indications.
[inPfc7Frames]	*integer*	Pfc7 Indications.
[inPfcFrames]	*integer*	Pfc Indications.
[inTotalPkts]	*integer*	RX packets.
[inUcastPkts]	*integer*	RX Unicast.
[ipv4L3Mcast]	*integer*	RX - Routed IPV4 multicast.
[ipv4L3Ok]	*integer*	RX - Good IPV4 L3 Unicast.
[ipv6L3Mcast]	*integer*	RX - Routed IPV6 multicast.
[ipv6L3Ok]	*integer*	RX - Good IPV6 L3 Unicast.
[jabbers]	*integer*	Jabbers.
[out1024To1518OctetFrames]	*integer*	TX counter bin 1024-1518 bytes.
[out128To255OctetFrames]	*integer*	TX counter bin 128-255 bytes.

[out1519To2047OctetFrames]	*integer*	TX counter bin 1519-2047 bytes.
[out2048To4095OctetFrames]	*integer*	TX counter bin 2048-4095 bytes.
[out256To511OctetFrames]	*integer*	TX counter bin 256-511 bytes.
[out4096To9216OctetFrames]	*integer*	TX counter bin 4096-9216 bytes.
[out512To1023OctetFrames]	*integer*	TX counter bin 512-1023 bytes.
[out64OctetFrames]	*integer*	TX counter bin 64 bytes.
[out65To127OctetFrames]	*integer*	TX counter bin 65-127 bytes.
[out9217To16383OctetFrames]	*integer*	TX counter bin 9217-16383 bytes.
[outBroadcastPkts]	*integer*	TX Broadcast packets.
[outMulticastPkts]	*integer*	TX Multicast packets.
[outOctets]	*integer*	TX bytes.
[outPauseFrames]	*integer*	TX Pause Frames.
[outPfc0Frames]	*integer*	TX Pfc0 Requests.
[outPfc1Frames]	*integer*	TX Pfc1 Requests.
[outPfc2Frames]	*integer*	TX Pfc2 Requests.
[outPfc3Frames]	*integer*	TX Pfc3 Requests.
[outPfc4Frames]	*integer*	TX Pfc4 Requests.
[outPfc5Frames]	*integer*	TX Pfc5 Requests.
[outPfc6Frames]	*integer*	TX Pfc6 Requests.
[outPfc7Frames]	*integer*	TX Pfc7 Requests.
[outPfcFrames]	*integer*	TX Pfc Requests.
[outUcastPkts]	*integer*	TX Unicast packets.
[rxUC]	*integer*	RX - Good L2, L3 unicast.
[txIpv4L3MCOk]	*integer*	TX - Good IPV4 L3 multicast packets.
[txIpv4L3UCOk]	*integer*	TX - Good IPV4 L3 unicast packets.
[txIpv6L3MCOk]	*integer*	TX - Good IPV6 L3 multicast packets.
[txIpv6L3UCOk]	*integer*	TX - Good IPV6 L3 unicast packets.
[wredEctDropPktCounter]	*integer*	TX - WRED ECT drop.
[wredNonEctDropPktCounter]	*integer*	TX - WRED non-ECT drop.

2.1535.1.1.5 PlatformSampledCounterModel

[adapt_2_miss_drop]	*integer*	TX - Adapt 2 miss drop (sampled).
[classbasedmovedrop]	*integer*	RX - Class based station movement drop (sampled).
[dsfrag]	*integer*	RX - DOS fragment error packets (sampled).
[dsicmp]	*integer*	RX - DOS ICMP error packets (sampled).
[dsl3he]	*integer*	RX - DOS L3 header error packets (sampled).
[dsl4he]	*integer*	RX - DOS L4 header error packets (sampled).
[dstdiscarddrop]	*integer*	RX - L2/L3 lookup DST_DISCARD drop (sampled).
[egressProtectionDataDrop]	*integer*	TX - Protection data drop (sampled).
[fcmPortClass2RxDiscards]	*integer*	RX - FCOE L2 RX discarded frames (sampled).
[fcmPortClass2RxFrames]	*integer*	RX - FCOE L2 RX frames (sampled).
[fcmPortClass2TxFrames]	*integer*	TX - FCOE L2 TX frames (sampled).

[fcmPortClass3RxDiscards]	*integer*	RX - FCOE L3 RX discarded frames (sampled).
[fcmPortClass3RxFrames]	*integer*	RX - FCOE L3 RX frames (sampled).
[fcmPortClass3TxFrames]	*integer*	TX - FCOE L3 TX frames (sampled).
[hGoE]	*integer*	RX - HGoE Rx frames (sampled).
[hghdre]	*integer*	RX - Higig header error packets (sampled).
[higigLoopbackDrop]	*integer*	RX - HiGig loopback drop (sampled).
[higigUnknownOpcodDrop]	*integer*	RX - HiGig unknown opcode drop (sampled).
[imbp]	*integer*	RX - Bridged multicast packets (sampled).
[imirror]	*integer*	RX - HiGig mirror packet (sampled).
[imrp4]	*integer*	RX - Routed IPv4 multicast packets (sampled).
[imrp6]	*integer*	RX - Routed IPv6 multicast packet (sampled).
[ingressProtectionDataDrop]	*integer*	RX - Protection data drop (sampled).
[irhol]	*integer*	RX - HiGig End-to-End HOL rx packets (sampled).
[iribp]	*integer*	RX - HiGig End-to-End IBP rx packets (sampled).
[irpse]	*integer*	RX - HiGig IPIC pause rx (sampled).
[iunkhdr]	*integer*	RX - Unknown HiGig header type packet (sampled).
[laglup]	*integer*	RX - LAG failover loopback packets (sampled).
[laglupd]	*integer*	RX - LAG backup port down (sampled).
[maclmt_drop]	*integer*	RX - Mac limit exceeded and packet dropped (sampled).
[maclmt_nodrop]	*integer*	RX - Mac limit exceeded and packet not dropped (sampled).
[macsaequalmacda]	*integer*	RX - Dos Attack L2 Packets (same MAC source and destination) (sampled).
[mcidxe]	*integer*	RX - Multicast index error packets (sampled).
[modidtoolargedrop]	*integer*	TX - MODID greater than 31 drop counter (sampled).
[mtuerr]	*integer*	RX - Packets trapped to CPU due to egress L3 MTU violation (sampled).
[nonHGoE]	*integer*	RX - Non HGoE Rx frames on an HGoE port (sampled).
[parityd]	*integer*	RX - Parity error packets (sampled).
[pdisc]	*integer*	RX - Policy discard (sampled).
[pfm]	*integer*	RX - PFM multicast drop (sampled).
[pktmodtoolargedrop]	*integer*	TX - Byte additions too large drop counter (sampled).
[rdisc]	*integer*	RX - IBP discard and CBP full (sampled).
[rdrop]	*integer*	RX - Port bitmap zero drop condition (sampled).
[rfildr]	*integer*	RX - Packets dropped by FP (sampled).
[rhgmc]	*integer*	RX - HiGig lookup MC cases (sampled).
[rhguc]	*integer*	RX - HiGig lookup UC cases (sampled).

[rimdr]	*integer*	RX - Multicast (L2 + L3) packets that are dropped (sampled).
[ripc4]	*integer*	RX - Good IPv4 packets (sampled).
[ripc6]	*integer*	RX - Good IPv6 packets (sampled).
[ripd4]	*integer*	RX - IPv4 L3 discard packets (sampled).
[ripd6]	*integer*	RX - IPv6 L3 discard packets (sampled).
[riphe4]	*integer*	RX - IPv4 header error packets (sampled).
[riphe6]	*integer*	RX - IPv6 header error packets (sampled).
[rportd]	*integer*	RX - Packets dropped when ingress port is not in forwarding state (sampled).
[rtun]	*integer*	RX - Number of tunnel packets received (sampled).
[rtune]	*integer*	RX - Tunnel error packets (sampled).
[ruc]	*integer*	RX - Good unicast (L2+L3 packets) (sampled).
[rxBFDUnknownAchError]	*integer*	RX - BFD packets with invalid ACH header (sampled).
[rxBFDUnknownControlFrames]	*integer*	RX - Unrecognized BFD control packets (sampled).
[rxBFDUnknownVersion-Discards]	*integer*	RX - Unknown BFD version or discard dropped (sampled).
[rxBlockMaskDrop]	*integer*	RX - Bitmap of ports blocked (sampled).
[rxBpduDrop]	*integer*	RX - BPDU packets dropped (sampled).
[rxCompositeError]	*integer*	RX - HW related error like lookup table with parity error (sampled).
[rxDSL2HE]	*integer*	RX - Dos Attack L2 Packets (sampled).
[rxDiscStage] **	*integer*	RX - Packets dropped in discard stage (sampled). **Since: 4.32.2
[rxDlbRhResolutionError]	*integer*	RX - DLB or RH resolution error (sampled).
[rxEcmpMemberNotResolved-Drop] **	*integer*	RX - packets dropped due to primary, secondary and tertiary next hop selections are down or programmatically disabled and a valid next hop could not be resolved (sampled). **Since: 4.34.1
[rxEcmpProtectionMember-Active] **	*integer*	RX - packets due to secondary or tertiary next hop is picked during next hop resolution because primary/secondary next hop is either down or programmatically disabled (sampled). **Since: 4.34.1
[rxEcmpProtectionMember-CollisionDrop] **	*integer*	RX - packets dropped due to ECMP member table bank collision is detected while resolving primary and secondary next hops (sampled). **Since: 4.34.1
[rxEcmpResolutionError]	*integer*	RX - Packets dropped due to ECMP resolution error (sampled).
[rxEgressMaskDrop]	*integer*	RX - Packets dropped due to egress mask (sampled).

[rxEgressMaskSrcPortDrop]	*integer*	RX - Packets dropped due to block traffic from egress based on ingress port (sampled).
[rxEgressVlanMemberMismatch]	*integer*	RX - Packets dropped due to mismatched egress port for the VLAN (sampled).
[rxFcoeSrcBindError]	*integer*	RX - FCOE source bind check failure (sampled).
[rxFcoeSrcFpmaError]	*integer*	RX - Source FPMA prefix check failure (sampled).
[rxFcoeVftDrop]	*integer*	RX - FVT header error (sampled).
[rxFcoeZoneError]	*integer*	RX - FCOE_ZONE check failure (sampled).
[rxFcoeZoneLookupMiss]	*integer*	RX - FCOE_ZONE lookup miss (sampled).
[rxFieldChangeL2NoRedirectDrop]	*integer*	RX - Change L2 fields without deploying redirect action drop (sampled).
[rxFieldDelayDrop]	*integer*	RX - Packets dropped due to ingress FP delayed action (sampled).
[rxFieldRedirectMaskDrop]	*integer*	RX - Packets dropped due to FP redirection mask (sampled).
[rxHgFailoverPortDown] **	*integer*	RX - Lag failover packet detected on loopback port, treat as ingress mirror copy, so switched copy dropped (sampled). **Since: 4.32.2
[rxHigig3Drop] **	*integer*	RX - packets dropped due to the drop configuration on HIGIG3 packets (sampled). **Since: 4.34.1
[rxINTVectorMismatch]	*integer*	RX - INT packets dropped due to request vector match failure (sampled).
[rxIcnm] **	*integer*	RX - ICNM counter (sampled). **Since: 4.33.1
[rxIntMtuError] **	*integer*	RX - In-band Network Telemetry (INT) packets experiencing L3 MTU check failure due to metadata insertion (sampled). **Since: 4.34.1
[rxIpHdrBeyondParsingDepth] **	*integer*	RX - IP header beyond parsing depth (sampled). **Since: 4.33.1
[rxIpInIpDrop]	*integer*	RX - IPinIP tunnel process failure (sampled).
[rxIpmcDrop]	*integer*	RX - IPMC process failure (sampled).
[rxIrvoqfc] **	*integer*	RX - Virtual-Output-Queue-based Flow-Control-Message receive packet (sampled). **Since: 4.33.1
[rxL2DstDiscardDrop]	*integer*	RX - L2 DST_DISCARD drop (sampled).
[rxL2HeaderError]	*integer*	RX - L2 header error (sampled).
[rxL2RpfError]	*integer*	RX - Incoming port/lag/svp check failure (sampled).
[rxL2SrcDiscardDrop]	*integer*	RX - L2 SRC_DISCARD drop (sampled).
[rxL2SrcStaticMoveDrop]	*integer*	RX - Port movement of static L2 addr (sampled).

[rxL2TtlError]	*integer*	RX - L2 ZONE TTL check failure (sampled).
[rxL2TunnelSvpAssignFailDrop] **	*integer*	RX - indicate packets dropped due to source virtual port assignment failure. Applicable for VxLAN and SRv6 (sampled). **Since: 4.34.1
[rxL3DisableDrop]	*integer*	RX - V4/V6 L3_ENABLE unset drop (sampled).
[rxL3DstDiscardDrop]	*integer*	RX - L3 DST_DISCARD drop (sampled).
[rxL3DstLookupDrop]	*integer*	RX - IPMC processing drop, or L3_DESTINATION == 0 for L3UC packets (sampled).
[rxL3HeaderError]	*integer*	RX - L3 header error (sampled).
[rxL3SrcDiscardDrop]	*integer*	RX - L3 SRC_DISCARD drop (sampled).
[rxL3TtlError]	*integer*	RX - L3 TTL check failure (sampled).
[rxL3TunnelLookupMiss]	*integer*	RX - L3 Tunnel lookup miss (sampled).
[rxLAGFailLoopback]	*integer*	RX - LAG fail loopback packets in packet discard stage (sampled).
[rxLagBackupPortDown] **	*integer*	RX - LAG failover loopback packets discarded due to backup port down (sampled). **Since: 4.32.2
[rxLagLoopBackHg] **	*integer*	RX - LAG failover loopback packets from either loopback port or higig (sampled). **Since: 4.32.2
[rxLinkDownDrop]	*integer*	RX - packets dropped due to link down or destination port disabled (sampled).
[rxMCError]	*integer*	RX - Packets dropped due to multicast errors (sampled).
[rxMacBlockMaskDrop]	*integer*	RX - Packets dropped due to MAC block mask (sampled).
[rxMacControlDrop]	*integer*	RX - Packets dropped due to MAC control frame (sampled).
[rxMacIpBindError]	*integer*	RX - MAC to IP bind check failure (sampled).
[rxMacSaEqual0Drop]	*integer*	RX - Packets dropped due to MACSA == 0 (sampled).
[rxMimDrop]	*integer*	RX - MiM tunnel process failure (sampled).
[rxMplsActionInvalid]	*integer*	RX - MPLS invalid action (sampled).
[rxMplsControlWordInvalid]	*integer*	RX - MPLS invalid control word (sampled).
[rxMplsEntropyDrop]	*integer*	RX - MPLS Entropy label in unallowed range (sampled).
[rxMplsErr]	*integer*	RX - MPLS packets with error (sampled).
[rxMplsGalNotBosDrop]	*integer*	RX - MPLS Generic Label is not BOS (sampled).
[rxMplsLabelLookupMiss]	*integer*	RX - MPLS label lookup miss (sampled).
[rxMplsLookupMiss]	*integer*	RX - MPLS lookup miss (sampled).
[rxMplsPayloadInvalid]	*integer*	RX - MPLS invalid payload (sampled).
[rxMplsSeqNumberError]	*integer*	RX - MPLS control word sequence number error (sampled).

[rxMyStationDrop]	*integer*	RX - MY_STATION.DISCARD drop (sampled).
[rxNatDrop]	*integer*	RX - NAT process failure (sampled).
[rxNextHopDrop]	*integer*	RX - NEXT_HOP drop (sampled).
[rxNextHopOrL3EifRange-Error]	*integer*	RX - Packets dropped due to next hop or L3 egress interface ID range error (sampled).
[rxNivForwardingDrop] **	*integer*	RX - NIV forwarding error dropped (sampled). **Since: 4.33.1
[rxNonEmbeddedHgPkt-Received] **	*integer*	RX - Non-embedded HiGig packets received on a Embedded HiGig port (not including PAUSE/PFC) (sampled). **Since: 4.33.1
[rxNonFirstPass] **	*integer*	RX - packets marked as non-first pass packets (sampled). **Since: 4.34.1
[rxNonHigig3Drop] **	*integer*	RX - packets dropped due to the drop configuration on non-HIGIG3 packets (sampled). **Since: 4.34.1
[rxNonUnicastLAGMaskDrop]	*integer*	RX - Packets dropped due to multicast and broadcast trunk block mask (sampled).
[rxNonUnicastMaskDrop]	*integer*	RX - Packets dropped due to block masks (sampled).
[rxOffsetNontrillFrameOnNw-PortDrop] **	*integer*	RX - Non-Trill frame on network port dropped (sampled). **Since: 4.33.1
[rxOffsetTrillErrorsDrop] **	*integer*	RX - Trill errors dropped (sampled). **Since: 4.33.1
[rxOffsetTrillFrameOn-AccessPortDrop] **	*integer*	RX - Trill frame on access port dropped (sampled). **Since: 4.33.1
[rxOffsetTrillHopcount-CheckFail] **	*integer*	RX - Trill HopCount check fail dropped (sampled). **Since: 4.33.1
[rxOffsetTrillRbridge-LookupMissDrop] **	*integer*	RX - Trill RBridge lookup miss dropped (sampled). **Since: 4.33.1
[rxOffsetTrillRpfCheckFail-Drop] **	*integer*	RX - Trill RPF check fail dropped (sampled). **Since: 4.33.1
[rxOlpDaPrefixMatchedDrop] **	*integer*	RX - OLP DA Prefix matched drop (sampled). **Since: 4.33.1
[rxOlpErrorDrop] **	*integer*	RX - OLP related error (sampled). **Since: 4.33.1
[rxPartialLinkDownDrop]	*integer*	RX - non-UC packets dropped partially due to link down or dest port disabled (sampled).
[rxPrivateVlanMismatch]	*integer*	RX - PVLAN VID mismatch (sampled).
[rxPrivateVlanVpFilterDrop]	*integer*	RX - Packets dropped based on src/dst VP type (sampled).

[rxProtocolDrop]	*integer*	RX - Protocol packets dropped (sampled).
[rxProtocolErrorIP4]	*integer*	RX - Packets dropped due to IPv4 protocol error (sampled).
[rxProtocolErrorIP6]	*integer*	RX - Packets dropped due to IPv6 protocol error (sampled).
[rxSplitHorizonDrop] **	*integer*	RX - Split horizon check failure (sampled). **Since: 4.32.2
[rxSrcKnockoutDrop]	*integer*	RX - SGPP == DGPP or SVP == DVP, etc (sampled).
[rxSrcRouteDrop]	*integer*	RX - MACSA is multicast(bit 40 == 1) (sampled).
[rxSrv6ProcessErrorDrop] **	*integer*	RX - packets dropped due to SRV6 process error (sampled). **Since: 4.34.1
[rxSrv6UnknownRoutingType-WithNonZeroSlDrop] **	*integer*	RX - packets dropped due to unknown routing type in SRV6 packets with nonzero segments left field (sampled). **Since: 4.34.1
[rxSrv6ValidationErrorDrop] **	*integer*	RX - packets dropped due to SRV6 validation error (sampled). **Since: 4.34.1
[rxStatefulModSecondPass-Drop] **	*integer*	RX - switch copies dropped due to 2nd pass processing of stateful MOD (sampled). **Since: 4.34.1
[rxStgDrop]	*integer*	RX - STP not in forwarding state (sampled).
[rxStgMaskDrop]	*integer*	RX - Packets dropped due to spanning tree group state (sampled).
[rxStormControlDrop]	*integer*	RX - Storm control metering drop (sampled).
[rxTagUntagDiscardDrop]	*integer*	RX - PORT_DIS_UNTAG/PORT_DIS_TAG drop (sampled).
[rxTimeSyncDrop]	*integer*	RX - Network time sync packets dropped (sampled).
[rxTpidMismatch]	*integer*	RX - VLAN TPID mismatch (sampled).
[rxTunnelDecapEcnError]	*integer*	RX - Tunnel decap ECN error (sampled).
[rxTunnelErr]	*integer*	RX - Packets dropped due to tunnel errors (sampled).
[rxTunnelInterfaceError]	*integer*	RX - IPMC tunnel incoming interface is incorrect (sampled).
[rxTunnelObjectValidation-Fail]	*integer*	RX - Tunnel termination failure (sampled).
[rxTunnelShimError]	*integer*	RX - Tunnel shim header error (sampled).
[rxTunnelTtlError]	*integer*	RX - Tunnel TTL check failure (sampled).
[rxUnknownMacSaDrop]	*integer*	RX - Unknown MACSA packets dropped (sampled).
[rxUnknownSubtendingPort] **	*integer*	RX - Drop due to unknown subtending port (sampled). **Since: 4.32.2

[rxVfiAdaptLookupMiss]	*integer*	RX - Packets dropped due a lookup miss drop during ingress VFI adaption (sampled).
[rxVfiP2pDrop]	*integer*	RX - Packets arrived from a VP that is not programmed in PT2PT connection (sampled).
[rxVlanBlockMaskDrop]	*integer*	RX - Packets dropped due to VLAN blocked ports (sampled).
[rxVlanCrossConnectOrNonUnicastDrop]	*integer*	RX - L2 forwarding lookup miss or PBT non unicast packets drop (sampled).
[rxVlanMemberMismatch]	*integer*	RX - Ingress port not in VLAN membership (sampled).
[rxVlanMismatch]	*integer*	RX - VLAN ID invalid (sampled).
[rxVlanTranslate1LookupMiss]	*integer*	RX - VLAN Translate1 lookup miss (sampled).
[rxVlanTranslate2LookupMiss]	*integer*	RX - VLAN Translate2 lookup miss (sampled).
[rxVntagError] **	*integer*	RX - VNTAG error packet dropped (sampled). **Since: 4.33.1
[rxVxlanDecapSrcIpLookupMiss]	*integer*	RX - VXLAN packet dropped due to source IP lookup miss during tunnel decap (sampled).
[rxVxlanTunnelErrorDrop]	*integer*	RX - Drop due to Vxlan tunnel error (sampled).
[rxVxlanVnidLookupMissDrop]	*integer*	RX - Drop due to Vxlan network id lookup miss (sampled).
[taged]	*integer*	TX - Packets dropped due to packet aged (sampled).
[tcfid]	*integer*	TX - Packets dropped when CFI set & packet is untagged or L3 switched for IPMC (sampled).
[tgip4]	*integer*	TX - Good IPv4 L3 UC packets (sampled).
[tgip6]	*integer*	TX - Good IPv6 L3 UC packets (sampled).
[tgipmc4]	*integer*	TX - Good IPv4 IPMC packets (sampled).
[tgipmc6]	*integer*	TX - Good IPv6 IPMC packets (sampled).
[thgi]	*integer*	TX - Unknown HiGig drop (sampled).
[thgmc]	*integer*	TX - HiGig lookedup L3MC packets (sampled).
[thguc]	*integer*	TX - HiGig lookedup L3UC packets (sampled).
[thigig2]	*integer*	TX - Unknown HiGig2 drop (sampled).
[tip_len_fail]	*integer*	TX - IP length check fail drop (sampled).
[tipd4]	*integer*	TX - IPv4 L3 UC Aged and Drop packets (sampled).
[tipd6]	*integer*	TX - IPv6 L3 UC Aged and Drop Packets (sampled).
[tipmcd4]	*integer*	TX - IPv4 IPMC Aged and Drop packets (sampled).
[tipmcd6]	*integer*	TX - IPv6 IPMC Aged and Drop packets (sampled).
[tl2_mtu]	*integer*	TX - L2 MTU fail drop (sampled).

[tl2mcd]	*integer*	TX - L2 MC packet drop counter (sampled).
[tmirr]	*integer*	TX - mirrored packets (sampled).
[tparity_err]	*integer*	TX - Parity Error drop (sampled).
[tpktd]	*integer*	TX - Packets dropped due to any condition (sampled).
[tsipl]	*integer*	TX - SIP Link Local Drop (sampled).
[tslld]	*integer*	TX - ESIP link local (sampled).
[tstgd]	*integer*	TX - Packets dropped due to spanning tree state not in forwarding state (sampled).
[ttnl]	*integer*	TX - Tunnel packets (sampled).
[ttnle]	*integer*	TX - Tunnel error packets (sampled).
[tttld]	*integer*	TX - Packets dropped due to TTL threshold counter (sampled).
[tvlan]	*integer*	TX - VLAN tagged packets (sampled).
[tvland]	*integer*	TX - Pkts dropped due to invalid VLAN counter (sampled).
[tvxltmd]	*integer*	TX - Packets dropped due to miss in VXLT table counter (sampled).
[txAdaptLookupMiss]	*integer*	TX - packets dropped due to egress adapt lookup miss (sampled).
[txCellTooSmall]	*integer*	TX - Multi-cell packets with SOP cell size <64 bytes after decap (sampled).
[txCnmDrop] **	*integer*	TX - Invalid CNM packet (sampled). **Since: 4.32.2
[txDcnPktRoutingPlaneMapDrop] **	*integer*	TX - drop congestion notification packets dropped due to routing plane mapping (sampled). **Since: 4.34.1
[txDropOrig] **	*integer*	TX - Original packets dropped (sampled). **Since: 4.32.2
[txEgressFilterDrop]	*integer*	TX - Packets dropped by EFP (sampled).
[txEgressPortDrop]	*integer*	TX - EGR_LPORT_PROFILE.DROP (sampled).
[txEpRecircDrop] **	*integer*	TX - packets dropped due to EP recirculation drop (sampled). **Since: 4.34.1
[txEpRecircSupress] **	*integer*	TX - packets experiencing EP recirculation suppressing (sampled). **Since: 4.34.1
[txFcmPortPacketDrop] **	*integer*	TX - FCOE packet got dropped (sampled). **Since: 4.33.1
[txFwdDomainNotFoundDrop]	*integer*	TX - Forwarding domain not found (sampled).
[txIfaActionNotApplied] **	*integer*	TX - packets IFA action not applied (sampled). **Since: 4.34.1
[txIfaTermMirrorCopySuppress] **	*integer*	TX - IFA terminated packets experiencing mirror copy suppressing (sampled). **Since: 4.34.1

[txInvalid1588Drop] **	*integer*	TX - Invalid 1588 packet format (sampled). **Since: 4.32.2
[txIpmcL2SrcPortPruneDrop]	*integer*	TX - IPMC L2 self port drop (sampled).
[txL3EgressOrIntfRangeError]	*integer*	TX - packets dropped due to L3 next hop and interface indices do not comply with configured allocation bitmap (sampled).
[txLoopbackToLoopbackDrop]	*integer*	TX - Packets dropped due to loopback packet dest is also loopback port (sampled).
[txMmuPurgeDrop]	*integer*	TX - Packets dropped due to MMU purge (sampled).
[txNonFirstPass] **	*integer*	TX - packets marked as non-first pass packets (sampled). **Since: 4.34.1
[txNonTrillDrop] **	*integer*	TX - Not a trill packet (sampled). **Since: 4.32.2
[txNonUnicastPruneDrop]	*integer*	TX - Non unicast pruning (sampled).
[txNotFwdDomainMemberDrop]	*integer*	TX - Not forwarding domain member (sampled).
[txPacketTooSmall] **	*integer*	TX - Packet is too small (sampled). **Since: 4.32.2
[txSplitHorizonCheckDrop]	*integer*	TX - Split horizon check failure (sampled).
[txStgDisableDrop]	*integer*	TX - Packets dropped due to STG disabled (sampled).
[txSvpEsDrop]	*integer*	TX - pkts dropped due to ethernet segment filtering on source virtual port (sampled).
[txSvpRemoveDrop]	*integer*	TX - Virtual port pruning (sampled).
[txTnivPrun] **	*integer*	NIV prune (sampled). **Since: 4.33.1
[txVisibilityDrop]	*integer*	TX - Visibility packets dropped (sampled).
[txVplagPruneDrop]	*integer*	TX - VPLAG pruning (sampled).
[urpf]	*integer*	RX - Unicast RPF drop case (sampled).
[vfpdr]	*integer*	RX - VLAN FP drop case (sampled).
[vlandr]	*integer*	RX - VLAN drops (sampled).

2.1536 show platform trident counters fast-polling [...]

averageFetchTime	*floating point number*	Average number of milliseconds to collect counters.
[detail] **	*FastPollInfoDetail* see 2.1536.1	Late poll details. **Since: 4.25.1
lastPollTimestamp	*floating point number*	Timestamp of at the end of last poll interval.
latePollCount	*integer*	Number of times poll interval has been missed.
maximumFetchTime	*floating point number*	Maximum number of milliseconds to collect counters.
pollFastInterval	*integer*	Configured fast polling period in milliseconds.
reEnqueueCount	*integer*	Number of times update requests saturated Schan.
retryDequeueCount	*integer*	Number of times waited for request completion.
totalFetchCount	*integer*	Number of times the event has occurred.
totalPollCount	*integer*	Numer of times the polling has completed.

2.1536.1 FastPollInfoDetail

latePollHistory	*list of LatePollEvent* see 2.1536.1.2	Last late poll events.
[statsLastDay]	*FastPollStats* see 2.1536.1.1	Statistics over the last day.
[statsLastHour]	*FastPollStats* see 2.1536.1.1	Statistics over the last hour.

2.1536.1.1 FastPollStats

averageFetchTime	*floating point number*	Average time needed to collect counters (ms).
latePollCount	*integer*	Number of times poll interval has been missed.
maximumFetchTime	*floating point number*	Maximum time needed to collect counters (ms).
statsStartTimestamp	*floating point number*	Start of the monitored period.
totalPollCount	*integer*	Numer of times the polling has completed.

2.1536.1.2 LatePollEvent

delay	*floating point number*	Polling delay (in milliseconds).
timestamp	*floating point number*	Timestamp of the late poll.

2.1537 show platform trident counters fast-polling interface [...]

interfaces	*table(Interface name) = InterfaceFastCounters* see 2.573.2	A mapping of interface to its fast counters.

2.1538 show platform trident counters interface (FABRIC | ETH | UETH | INTERNALRECIRC)

revision 2

see 2.1535

2.1539 show platform trident counters polling [...]

Could also be an instance of:
PollInfo 2.1539
PollInfoDir 2.1539

averageFetchTime	*floating point number*	Average number of seconds to collect counters.
lastPollTimestamp	*floating point number*	Timestamp of at the end of last poll interval.
latePollCount	*integer*	Number of times poll interval has been missed.
maximumFetchTime	*floating point number*	Maximum number of seconds to collect counters.
pollInterval	*floating point number*	Configured polling period in seconds.
reEnqueueCount	*integer*	Number of times update requests saturated Schan.
retryDequeueCount	*integer*	Number of times waited for request completion.
totalFetchCount	*integer*	Number of times the event has occurred.
totalPollCount	*integer*	Numer of times the polling has completed.
switchAggregationGroupMember	*table(string) = PollInfo* see 2.1539	Polling info per switch aggregation member.

2.1540 show platform trident counters sampling

sampledCounterChip	*list of SampledCounterChipModel* see 2.1540.1	Sampling information per chip.

2.1540.1 SampledCounterChipModel

chip	*list of string*	Chips this sampling information applies to.
rxSampledData	*SampledData* see 2.1540.1.1	Rx pipeline sampeld data.
txSampledData	*SampledData* see 2.1540.1.1	Tx pipeline sampeld data.

2.1540.1.1 SampledData

samplingRegisters	*integer*	Number of pipeline sampling registers.
samplingTriggers	*integer*	Number of triggers being sampled.
triggerActiveRatio	*floating point number*	Percentage of the time a given trigger is being counted.

2.1541 show platform trident cpu-queue mapping [...]

queueMaps	*table(numeric string) = CpuQueueMap* see 2.1541.1	Dictionary of non-empty CPU queue maps for each unit in the agent (Key = Unit ID).

2.1541.1 CpuQueueMap

allocatedQueues	*integer*	Number of queues allocated.
coppServiceEnabled	*boolean*	True if CoPP is enabled.
dynamicQueues	*integer*	Number of dynamic queues allocated.
maxQueues	*integer*	Maximum number of queues supported.
policyMap	*string*	Name of the policy map attached to the control plane.
queues	*table(numeric string) = CpuQueue* see 2.1541.1.1	Dictionary of every allocated CPU queue in the unit (Key = Queue ID).
staticQueues	*integer*	Number of static queues allocated.

2.1541.1.1 CpuQueue

classMap	*string*	Name of the class mapped to this CPU queue.
classMapType	*string*	Class map type of the CPU queue.
queueName	*string*	Name of the queue.

2.1542 show platform trident directflow [...]

slices	*table(string) = StrataSliceInfo* see 2.1542.1	A mapping from slice name to flow.

2.1542.1 StrataSliceInfo

flows	*table(string) = DirectFlowFlowName* see 2.1542.1.1	A mapping from flow name to resource allocation info.

2.1542.1.1 DirectFlowFlowName

fabricResources	*table(string) = FabricResourceInfo* see 2.1542.1.1.2	A mapping of fabric name to fabric tcam state.
hgClassId	*integer*	HiGig class ID.
hgClassResourceState	*enum: Acquired | NA | Pending*	HiGig class resource state.
ipmcIndex **	*integer*	L3_IPMC index. **Since: 4.22.0
ipmcIndexResourceState **	*enum: Acquired | NA | Pending*	IPMC resource state. **Since: 4.22.0
l2McIndex	*integer*	L2MC index.
l2McResourceState	*enum: Acquired | NA | Pending*	L2MC resource state.
mirrorResources	*table(string) = FlowMirrorTargetIntf* see 2.1542.1.1.3	A mapping of mirrorKey to mirror resource info.
nextHopIndex	*integer*	Nexthop index.
nextHopResourceState	*enum: Acquired | NA | Pending*	NextHop resource state.
opaqueId **	*integer*	Opaque object ID. **Since: 4.22.0
opaqueIdResourceState **	*enum: Acquired | NA | Pending*	Opaque object resource state. **Since: 4.22.0
[tcamEntries] **	*table(string) = DirectFlowTcamEntry* see 2.1542.1.1.1	TCAM entries associated with the flow. **Since: 4.23.0
tcamResourceState	*enum: Acquired | Pending*	TCAM resource state.

2.1542.1.1.1 DirectFlowTcamEntry

[entryId]	*integer*	Flow TCAM entry ID.

2.1542.1.1.2 FabricResourceInfo

fabricStatus	*enum: Acquired | Pending*	Fabric index program state.

2.1542.1.1.3 FlowMirrorTargetIntf

direction	*enum: Ingress | Egress*	Mirroring direction.
mirrorIndex	*integer*	Mirroring index.
mirrorResourceState	*enum: Acquired | NA | Pending*	L2MC resource state.
targetIntf	*string*	Mirroring target interface.

2.1543 show platform trident ecmp-lag (software | shadow) [...]

ecmpLags	*table(string) = EcmpLagStatus* see 2.1543.1	A mapping from lag Name to EcmpLag Status.

2.1543.1 EcmpLagStatus

lagId	*integer*	Ecmp Lag Id.
members	*table(numeric string) = EcmpLagMember* see 2.1543.1.1	A mapping from Index to EcmpLagMember.

2.1543.1.1 EcmpLagMember

intfId	*interface name*	Interface Name.
modId	*integer*	Module Id.
portId	*integer*	Port Id.

2.1544 show platform trident egress event debug [...]

chips	*table(string) = EgrEventListModel* see 2.1544.1	Map of chip name to list of egress debug events seen.

2.1544.1 EgrEventListModel

[eventCounters] **	*table(string) = integer*	Map of eress debug events seen since last cleared.Value represents the egress debug event count. **Since: 4.27.1
events	*list of string*	List of egress debug events seen since last cleared.Order is chip-dependent. Each appears at most once per chip.

2.1545 show platform trident exact-match [...]

entries	*table(string) = StrataEmCliModelEntry* see 2.1545.1	EM entries indexed by their ID.

2.1545.1 StrataEmCliModelEntry

appName	*string*	Application name.
[classId] **	*integer*	Entry class Id. **Since: 4.31.2
[drop]	*boolean*	Packet has been dropped.
[dstIp]	*IP address*	Destination IP address.
[dstL4Port]	*integer*	Destination L4 Port.
[dstQPair] **	*integer*	CLB destination queue pair. **Since: 4.32.2
[ecmp] **	*boolean*	Nexthop is an ECMP group. **Since: 4.24.2
[extractionCtrlId]	*integer*	Extraction Control Id.
[groupClassId] **	*integer*	Table Id. **Since: 4.24.2
[hiGig] **	*boolean*	Match traffic ingressing on HiGig. **Since: 4.24.2
[hits] **	*integer*	Number of times entry has been hit. **Since: 4.24.2
[ipProtocol]	*integer*	IP Protocol.
[logicalSrcPort] **	*integer*	Incoming Source Port. **Since: 4.25.0
ltId	*integer*	HW Logical Table ID.
[mcastGroupIp] **	*IP address*	VxLAN Underlay Multicast Group IP address. **Since: 4.25.0
[mcastSrcIp] **	*IP address*	VxLAN Underlay Multicast Source IP address. **Since: 4.25.0
[moduleId] **	*integer*	Module ID. **Since: 4.25.0
[nextHopId] **	*integer*	Nexthop value. **Since: 4.24.2
[numAppEntries]	*integer*	Number of Exact Match entries available for this application.
[opaqueId1]	*integer*	Opaque Id 1.
[opaqueId3]	*integer*	Opaque Id 3.
[redirectDvp] **	*integer*	Redirect DVP value. **Since: 4.24.2
[srcIp]	*IP address*	Source IP address.
[srcL4Port]	*integer*	Source L4 Port.
[tableSize]	*integer*	Maximum number of single wide Exact Match entries available.
[vrf] **	*integer*	VRF ID. **Since: 4.26.2

2.1546 show platform trident exact-match keygen-mask

entries	*table(string) = StrataEmKeyGenMaskEntry* see 2.1546.2	ExactMatch KeyGenMask entries indexed by their ID.
keySplitInfo	*list of StrataEmAppInfo* see 2.1546.1	ExactMatch KeyGenMask entry split info keyed by application ID.

2.1546.1 StrataEmAppInfo

[appId]	*string*	ExactMatch Application Id.
[clbDstQPair]	*list of string*	List of Mask Positions for RoCEV2.
[destMac]	*list of string*	List of Mask Positions for Destination MAC Address.
[dstIp]	*list of string*	List of Mask Positions for Destination IP Address.
[dstL4Port]	*list of string*	List of Mask Positions for Destination L4 Port.
[entryIds]	*list of integer*	List of Entry Ids for a particular App Id.
[hiGig]	*list of string*	List of Mask Positions for HiGig Field.
[hiGigProxy]	*list of string*	List of Mask Positions for HiGig Proxy Field.
[hole]	*list of string*	List of reserved Mask Positions for bits set to match RoCEV2 data properly.
[ipFrag]	*list of string*	List of Mask Positions for IP Fragment.
[ipProtocol]	*list of string*	List of Mask Positions for IP Protocol.
[logicalTableId]	*list of string*	List of Mask Positions for Logical Table Id.
[modId]	*list of string*	List of Mask Positions for Module Id.
[sourceMac]	*list of string*	List of Mask Positions for Source MAC Address.
[srcIp]	*list of string*	List of Mask Positions for Source IP Address.
[srcL4Port]	*list of string*	List of Mask Positions for Source L4 Port.
[srcPort]	*list of string*	List of Mask Positions for Source Port.
[udfDstIp]	*list of string*	List of Mask Positions for UDF Destination IP Address.
[udfSrcIp]	*list of string*	List of Mask Positions for UDF Source IP Address.
[vrf]	*list of string*	List of Mask Positions for VRF Id.

2.1546.2 StrataEmKeyGenMaskEntry

mask	*string*	ExactMatch KeyGenMask entry value.

2.1547 show platform trident exact-match summary

entries	*table(string) = StrataEmCliSummaryModelEntry* see 2.1547.1	EM entries indexed by their appName.
[hitbitPolling] **	*StrataEmHitbitIntervalSummary* see 2.1547.2	Summary of hitbit polling. **Since: 4.31.2

2.1547.1 StrataEmCliSummaryModelEntry

[errorCount]	*integer*	Number of Exact Match entries that could not be installed for this application.
[installedEntries]	*integer*	Number of Exact Match entries installed for this application.
[numAppEntries]	*integer*	Number of Exact Match entries available for this application.
[tableSize]	*integer*	Maximum number of single wide Exact Match entries available.

2.1547.2 StrataEmHitbitIntervalSummary

interval	*floating point number*	Hitbit update interval in seconds.
source	*enum: dfwFlowOffloadV4 | defaultInterval | dfwFlowOffloadV6 | cli*	The source from which the hitbit update interval is derived.

2.1548 show platform trident fabric counters fec [...]

chips	*table(string) = PlatformSliceFecCounterModel* see 2.1548.1	Mapping from chip name to FEC counters.

2.1548.1 PlatformSliceFecCounterModel

fapId **	*integer*	Fabric switch FAP ID. **Since: 4.25.0
modId	*integer*	Fabric switch module ID (legacy attribute, use fapId instead).
ports	*table(Interface name) = InterfaceFecCounterModel* see 2.1548.1.1	Mapping from interface to FEC Counters.

2.1548.1.1 InterfaceFecCounterModel

correctable	*integer*	RX - Correctable FEC error.
uncorrectable	*integer*	RX - Uncorrectable FEC error.

2.1549 show platform trident fabric counters queue [...]

fabricChips	*table(string) = StrataFabricQueueCounterDropModel* see 2.1549.1	Mapping from fabric chip to fabric ports.

2.1549.1 StrataFabricQueueCounterDropModel

fapId **	*integer*	Fabric switch FAP ID. **Since: 4.25.0
modId	*integer*	Fabric switch module ID (legacy attribute, use fapId instead).
ports	*table(Interface name) = StrataInterfaceQueueDropCounters* see 2.1549.1.1	Mapping from fabric port to drop counters.

2.1549.1.1 StrataInterfaceQueueDropCounters

egressMcDroppedPackets	*integer*	Multicast egress packets dropped.
egressUcDroppedPackets	*integer*	Unicast egress packets dropped.
ingressDroppedPackets	*integer*	Ingress packets dropped.

2.1550 show platform trident fabric counters queue detail [...]

fabricChips	*table(string) = StrataFabricInterfaceCounterModel* see 2.1550.1	Mapping from fabric chip to fabric ports.

2.1550.1 StrataFabricInterfaceCounterModel

fapId **	*integer*	Fabric switch FAP ID. **Since: 4.25.0
modId	*integer*	Fabric switch module ID (legacy attribute, use fapId instead).
ports	*table(Interface name) = StrataInterfaceEgressQueueDestinationTypeCounter* see 2.1550.1.1	Mapping from fabric port to egress tx-queue counters.

2.1550.1.1 StrataInterfaceEgressQueueDestinationTypeCounter

destinationQueues	*table(string) = Counters* see 2.310.1.1.1	Mapping from destination queue (unicast/multicast) to counter values.

2.1551 show platform trident fabric counters rate

see 2.590

2.1552 show platform trident fabric fib shadow [...]

linecards	*table(string) = StrataFabricFibLinecard-ShadowModel* see 2.1552.1	Fabric fib shadow information for all linecards.

2.1552.1 StrataFabricFibLinecardShadowModel

coprocessor **	*string*	Coprocessor status. **Since: 4.35.2
fapId	*integer*	Fap ID.
modules	*table(numeric string) = StrataFabricFibShadow-EntryModel* see 2.1552.1.1	Fabric fib shadow info for a linecard.

2.1552.1.1 StrataFabricFibShadowEntryModel

destination	*integer*	Egress HiGig trunk ID.
module	*integer*	module ID.
status **	*string*	Table entry status in hardware. **Since: 4.35.2

2.1553 show platform trident fabric fib software [...]

members	*table(string) = Strata-FabricFibMemberModel* see 2.1553.1	Fabric fib information for swag member(s).

2.1553.1 StrataFabricFibMemberModel

linecards	*table(string) = Strata-FabricFibLinecardModel* see 2.1553.1.1	Fabric fib information for a swag member.

2.1553.1.1 StrataFabricFibLinecardModel

destMembers	*table(string) = StrataFabricFibDest-MemberModel* see 2.1553.1.1.1	Fabric fib info for a linecard.
fapId	*integer*	Fap ID.

2.1553.1.1.1 StrataFabricFibDestMemberModel

modules	*table(string) = StrataFabricFibMember-ReachabilityModel* see 2.1553.1.1.1.1	Fabric fib info for a destination member.

2.1553.1.1.1.1 StrataFabricFibMemberReachabilityModel

egressInterface	*interface name*	Egress backplane interface to reach the module.
module	*integer*	Module ID.

2.1554 show platform trident fabric fib-mirror shadow [...]

see 2.1552

2.1555 show platform trident fabric fib-mirror software [...]

see 2.1553

2.1556 show platform trident fifo-dma

fifoDrivers	*table(string) = FifoDriverStateModel* see 2.1556.1	Fifo driver global states.

2.1556.1 FifoDriverStateModel

aristaBdeHandle	*integer*	Handle for Arista BDE.
fifoFlags	*boolean*	L2MOD FIFO driver flags.
fifoReadReadyCnt	*integer*	Count of times the FIFO is ready for reading.
intrCallbackCnt	*integer*	Number of global interrupt callback executions.
listAddCnt	*integer*	Number of times items added to ready-to-read list.
listDelCnt	*integer*	Number of times items deleted from ready-to-read list.
mfcStates	*table(string) = MfcStateModel* see 2.1556.1.1	FIFO DMA state per chip.
unsupportedDevice	*integer*	Number of unsupported or ignored devices.

2.1556.1.1 MfcStateModel

bdeDevHandle	*integer*	Arista BDE device handle.
bufferSize	*integer*	Size of the FIFO buffer in bytes in bytes.
bufferWrapped	*boolean*	The buffer has wrapped around.
bytesAvailable	*integer*	Number of bytes available from the chip.
cmicRegisters	*CmicRegisterModel* see 2.1556.1.1.1	CMIC specific functions and register mapping.
cpuAddr	*integer*	DMA cpu address.
deviceName	*string*	Name of the current chip device.
dmaHandle	*integer*	DMA handle provided to the current device.
dmaStateFlags	*boolean*	FIFO DMA state flags.
driver	*integer*	Either eviction counters or L2MOD FIFO driver.
entriesRead	*integer*	Number of entries read.
errorCount	*integer*	Number of times any failed bits has been set.
fifoChannel	*integer*	FIFO channel.
irqMask	*string*	Bitmask for interrupts controlled by the Arista BDE driver.
lastErrorMask	*boolean*	Mask bit for the last seen error is set.
nextReadOffset	*integer*	Byte offset of the next element to read.
numInterrupts	*integer*	Number of interrupts.
overflow	*boolean*	Host memory overflow.
pciBusAddr	*string*	PCI bus address.
pciPtr	*integer*	PCI device structure memory pointer.
timeout	*boolean*	Host memory timeout.

wrNumberOfEntries	*integer*	Bit indicating the number of entries to latch.

2.1556.1.1.1 CmicRegisterModel

[cfg]	*integer*	FIFO read DMA config register.
[ctrlCfg]	*integer*	Configuration settings for FIFO DMA control.
[entriesRead]	*integer*	Number of entries read by S/W from host memory.
[entriesValid]	*integer*	Number of entries pending for S/W read.
[hostmemConsumer]	*integer*	Consumer position pointer in FIFO DMA host memory.
[hostmemProducer]	*integer*	Producer position pointer in FIFO DMA host memory.
[hostmemPtr]	*integer*	Base address pointer for FIFO DMA host memory.
[hostmemPtrHi]	*integer*	Upper 32 bits of FIFO DMA host memory base address pointer.
[hostmemStart]	*integer*	FIFO read DMA host memory start address.
[hostmemStartHi]	*integer*	Upper 32 bits of the FIFO read DMA host memory start address.
[hostmemThreshold]	*integer*	FIFO read DMA threshold.
[hostmemWrite]	*integer*	Write pointer index for FIFO read DMA host memory.
[hostmemWriteHi]	*integer*	Upper 32 bits of the write pointer index for FIFO read DMA host memory.
[intrCtrl]	*integer*	Control register for FIFO DMA interrupts.
[intrStat]	*integer*	Status register for FIFO DMA interrupts.
[opcode]	*integer*	FIFO read DMA opcode index.
[sbusStart]	*integer*	SBus Address for FIFO POP instruction.
[stat]	*integer*	FIFO read DMA status.
[timer]	*integer*	Timer settings for FIFO DMA operations.

2.1557 show platform trident flexcounters l3intf in summary

l3intfs	*table(string) = L3IntfInFlexCounterInfo* see 2.1557.1	A mapping from l3 intf to L3IntfInFlexCounterInfo.

2.1557.1 L3IntfInFlexCounterInfo

baseCounterIndex	*integer*	Base counter index for flexcounter.
counterIndex	*integer*	Counter index for flexcounter.
offsetMode	*integer*	Offset mode for flexcounter.
poolId	*integer*	Pool id for flexcounter.

2.1558 show platform trident flexcounters l3intf in values

`l3intfs`	*table(string) = FlexCounterValuesColl* see 2.1558.1	A mapping from l3Intf addresss to flexCounterValues.

2.1558.1 FlexCounterValuesColl

`counters`	*table(string) = FlexCounterValues* see 2.1558.1.1	a container list for FlexCounterValues in counterTable.
`snapShotCounters`	*table(string) = FlexCounterValues* see 2.1558.1.1	a container list for FlexCounterValues in snapShotTable.

2.1558.1.1 FlexCounterValues

`nbytes`	*integer*	Number of bytes for flexcounter.
`npackets`	*integer*	Number of packets for flexcounter.

2.1559 show platform trident flexcounters l3intf out summary

see 2.1557

2.1560 show platform trident flexcounters l3intf out values

see 2.1558

2.1561 show platform trident flexcounters multicast summary

`groups`	*table(IPv4 or IPv6 address) = McastSources* see 2.1561.1	A mapping of Group IP addresses to Source IP addresses.

2.1561.1 McastSources

`sources`	*table(IPv4 or IPv6 address) = Vlans* see 2.1561.1.1	A mapping of Source IP addresses to VLAN IDs.

2.1561.1.1 Vlans

`vlans`	*table(numeric string) = Vrfs* see 2.1561.1.1.1	A mapping of VLAN IDs to VRFs.

2.1561.1.1.1 Vrfs

vrfs	*table(numeric string) = CounterIndexes* see 2.1561.1.1.1.1	A mapping of VRFs to their Counter Indices.

2.1561.1.1.1.1 CounterIndexes

counterIndexes	*table(numeric string) = McastSummaryTableInfo* see 2.1561.1.1.1.2	A mapping of Counter Indices to their counter information.

2.1561.1.1.1.2 McastSummaryTableInfo

baseCounterIndex	*integer*	Base Counter Index for flexcounter.
offsetMode	*enum: 3 | 0 | 1 | 2*	Offset Mode for flexcounter.
poolId	*integer*	Pool Id for flexcounter.

2.1562 show platform trident flexcounters multicast values

groups	*table(IPv4 or IPv6 address) = McastSources* see 2.1562.1	A mapping of Group IP addresses to Source IP addresses.

2.1562.1 McastSources

sources	*table(IPv4 or IPv6 address) = Vlans* see 2.1562.1.1	A mapping of Source IP addresses to VLAN IDs.

2.1562.1.1 Vlans

vlans	*table(numeric string) = Vrfs* see 2.1562.1.1.1	A mapping of VLAN IDs to VRFs.

2.1562.1.1.1 Vrfs

vrfs	*table(numeric string) = CounterIndexes* see 2.1562.1.1.1.1	A mapping of VRFs to their Counter Indices.

2.1562.1.1.1.1 CounterIndexes

counterIndexes	*table(numeric string) = McastValueTables* see 2.1562.1.1.1.2	A mapping of Counter Indices to their Snapshot and Counter Tables.

2.1562.1.1.1.2 McastValueTables

counterTable	*McastValueTableInfo* see 2.1562.1.1.1.3	Counter Table for flex counter.

snapshotTable	*McastValueTableInfo* see 2.1562.1.1.1.3	Snapshot Table for flex counter.

2.1562.1.1.1.3 McastValueTableInfo

nbytes	*integer*	Byte counter for mroute.
npackets	*integer*	Packet counter for mroute.

2.1563 show platform trident flexcounters requests

revision 2

egressRequests	*table(string) = FlexRequest* see 2.1563.1	Mapping from egress action name to action config.
ingressRequests	*table(string) = FlexRequest* see 2.1563.1	Mapping from ingress action name to action config.

2.1563.1 FlexRequest

[actionId]	*integer*	Action ID.
countOnDrop	*enum: countAll | countOnlyDropped | ignoreIfDropped*	Counter behavior regarding dropped packets.
[countOnMirror]	*boolean*	The counter updates on switch-generated mirror packets (Only applicable to EPIPE instances).
counterMode	*enum: slim | simple | normal | wide*	Mode for dividing counter entries.
index	*ValueSource* see 2.1563.1.1	The operation used to compute the counter index.
operatorA	*enum: decrement | setBit | average | min | xorOp | setValue | rdecrement | noop | max | increment*	Operation used to update counter A.
operatorB	*enum: decrement | setBit | average | min | xorOp | setValue | rdecrement | noop | max | increment*	Operation used to update counter B.
[rejectOnAllocFail] **	*boolean*	Reject the counter if it fails to allocate immediately. **Since: 4.33.1
requestName	*string*	Name of the request.
sourceAgent	*string*	Name of the agent that created the request.
sourceTableName	*string*	Name of the source table.
status	*enum: pending | unknown | allocated | rejected*	Status of the request.
valueA	*ValueSource* see 2.1563.1.1	The source value for updating counter A.
valueB	*ValueSource* see 2.1563.1.1	The source value for updating counter B.

2.1563.1.1 ValueSource

lowerBits	*ObjectSelector* see 2.1563.1.1.1	Information to compute lower bits of op profile.
upperBits	*ObjectSelector* see 2.1563.1.1.1	Information to compute upper bits of op profile.

2.1563.1.1.1 ObjectSelector

maskSize	*integer*	Size of mask in bits (actual size is this value + 1).
objectName	*string*	Value used to compute the index, A, or B.
shiftLeft	*integer*	Bits to shift value left indicated by srcField.
shiftRight	*integer*	Bits to shift value right indicated by srcField.

2.1564 show platform trident flexcounters requests summary

egressRequests	*table(string) = FlexRequestSummary* see 2.1564.1	Egress FlexCounters2 requests, keyed by name.
ingressRequests	*table(string) = FlexRequestSummary* see 2.1564.1	Ingress FlexCounters2 requests, keyed by name.

2.1564.1 FlexRequestSummary

[actionId]	*integer*	Allocated action ID.
counterMode	*enum: slim | simple | normal | wide*	Mode for dividing counter entries.
[pool]	*integer*	Base pool allocated to counter action.
requestedSize	*integer*	Requested number of entries.
[size]	*integer*	Number of entries to allocated from pool.
sourceAgent	*string*	Name of the agent providing the request.
sourceTableName	*string*	Name of the source table.
status	*enum: pending | unknown | allocated | rejected*	Status of the request.

2.1565 show platform trident flexcounters summary

poolDict	*table(string) = PoolInfoList* see 2.1565.1	Mapping from feature ID to list of pool info.

2.1565.1 PoolInfoList

poolInfoList	*table(numeric string) = PoolInfo* see 2.1565.1.1	Mapping from request ID to pool info.

2.1565.1.1 PoolInfo

poolType	*enum: ingress | egress*	Strata pool type.
[responseData]	*ResponseData* see 2.1565.1.1.1	Model containing corresponding response information.
validRequest	*boolean*	Denotes whether request ID came from a pool request.

2.1565.1.1.1 ResponseData

poolId	*integer*	Pool ID.
size	*integer*	Number of counters.
startIndex	*integer*	Start Index.

2.1566 show platform trident flexcounters vni egress summary

vnis	*table(string) = VniFlexCounterInfo* see 2.1566.1	A mapping from VNIs to VniFlexCounterInfo for egress.

2.1566.1 VniFlexCounterInfo

baseCounterIndex	*integer*	Base counter index for flexcounter.
offsetMode	*integer*	Offset mode for flexcounter.
poolId	*integer*	Pool ID for flexcounter.
vfiIndex	*integer*	VNI index for flexcounter.

2.1567 show platform trident flexcounters vni egress values

vnis	*table(string) = FlexCounterValuesColl* see 2.1558.1	A mapping from Vni addresss to flexCounterValues.

2.1568 show platform trident flexcounters vni ingress summary

vnis	*table(string) = VniFlexCounterInfo* see 2.1566.1	A mapping from VNIs to VniFlexCounterInfo for ingress.

2.1569 show platform trident flexcounters vni ingress values

see 2.1567

2.1570 show platform trident flexcounters vtep decap summary

vteps	*table(string) = VtepDecapFlexCounterInfo* see 2.1570.1	A mapping from remote VTEP IP addresss to VtepDecapFlexCounterInfo.

2.1570.1 VtepDecapFlexCounterInfo

baseCounterIndex	*integer*	Base counter index for flexcounter.
offsetMode	*integer*	Offset mode for flexcounter.
poolId	*integer*	Pool id for flexcounter.

svpIndex	*integer*	Svp Index for flexcounter.

2.1571 show platform trident flexcounters vtep decap values

vteps	*table(IPv4 address) = FlexCounterValuesColl* see 2.1558.1	A mapping from remote VTEP IP addresss to flexCounterValues.

2.1572 show platform trident flexcounters vtep encap summary

vteps	*table(string) = VtepFlexCounterInfo* see 2.1572.1	A mapping from remote VTEP IP addresss to VtepEncapFlexCounterInfo.

2.1572.1 VtepFlexCounterInfo

baseCounterIndex	*integer*	Base counter index for flexcounter.
dvpIndex	*integer*	Hardware Index for flexcounter.
offsetMode	*integer*	Offset mode for flexcounter.
poolId	*integer*	Pool id for flexcounter.

2.1573 show platform trident flexcounters vtep encap values

see 2.1571

2.1574 show platform trident flow tracker counters [...]

faps	*table(numeric string) = StftOneLinecardCounter* see 2.1574.1	A mapping of FAP ID to its flow groups.

2.1574.1 StftOneLinecardCounter

flowGroups	*table(numeric string) = StftOneFlowGroupCounter* see 2.1574.1.1	A mapping of flow group ID to its counters.

2.1574.1.1 StftOneFlowGroupCounter

active	*integer*	Active flow count.
ageOut	*integer*	AgeOut flow count.
exceed	*integer*	Exceed flow count.
groupName	*string*	Hardware flow group name.
learned	*integer*	Learned flow count.
missed	*integer*	Missed flow count.

2.1575 show platform trident flow tracker summary

revision 2

logicalFaps	*table(numeric string) = OneLinecardFlowTracker* see 2.1575.1	A mapping of Logical FAP ID to flow tracker information on it.

2.1575.1 OneLinecardFlowTracker

flowtrackers	*list of FlowTracker* see 2.1575.1.1	Configured flow trackers.

2.1575.1.1 FlowTracker

collector	*integer*	Collector ID of the flow tracker.
flowgroups	*table(string) = integer*	A mapping of flow group name to its ID.
intfs	*list of Interface name*	List of interfaces on which the flow tracker is enabled.
name	*string*	Name of the flow tracker.
state	*enum: flowTrackerNotProgrammed | flowTrackerFtfpDeleteInProg | flowTrackerIdle | flowTrackerIntfClassProgrammed | flowTrackerGroupDirProgrammed | flowTrackerFtfpProgrammed | flowTrackerFtfpDeleteDone | flowTrackerGroupDirSetupInProg | flowTrackerIntfClassSetupInProg | flowTrackerGroupDirDeleteDone | flowTrackerFtfpSetupFailed | flowTrackerDeleteDone | flowTrackerProgrammed | flowTrackerGroupDirDeleteInProg | flowTrackerIntfClassDeleteDone | flowTrackerFailed | flowTrackerAny | flowTrackerFtfpSetupInProg | flowTrackerIntfClassSetupFailed*	State of the flow tracker.

2.1576 show platform trident forwarding-table partition

chipModel	*string*	Chip Model.
[egressVlanRemapTableSize]	*integer*	Egress VLAN remap table size.

[exactMatchSupported]	*boolean*	Exact Match feature supported.
[l2TableSize]	*integer*	L2 table size.
[l3TableSize]	*integer*	L3 table size.
[lpmTableSize]	*integer*	LPM table size.
[totalEmEntries]	*integer*	Exact Match table size.
[totalL2Entries]	*integer*	L2 table size.
[totalL3Entries]	*integer*	L3 host table size.
uftMode	*enum: 2 | flexible | 0 | alpm | 3 | 1*	UFT Mode.
[urpfEnabled]	*boolean*	URPF enabled.
[vlanRemapTableSize]	*integer*	VLAN remap table size.

2.1577 show platform trident forwarding-table partition flexible

revision 2

[alpmEntries] **	*integer*	Shared ALPM entries. **Since: 4.25.2
emBankMappings	*table(numeric string) = integer*	EM physical to logical bank mapping.
emHashOffsets	*table(numeric string) = integer*	Exact Match hash offsets indexed by physical bank id.
[exactMatchEntries]	*integer*	Shared Exact Match entries.
[exactMatchMaxEntries]	*integer*	Maximum Exact Match UFT entries.
[exactMatchNumHwLogicalTables]	*integer*	Maximum Exact Match hardware logical tables.
[exactMatchNumHwLookups]	*integer*	Maximum Exact Match hardware lookups.
[exactMatchSupported]	*boolean*	Exact Match feature supported.
[flexibleUftEnabled]	*boolean*	Flexible UFT mode is enabled.
[initialized]	*boolean*	Flexible UFT mode attributes initialized.
[ipv4McastAlpmEntries] **	*integer*	IPv4 Multicast ALPM entries. **Since: 4.31.1
[ipv4McastAlpmMaxEntries] **	*integer*	Maximum Multicast ALPM entries. **Since: 4.31.1
[ipv4McastAlpmMinEntries] **	*integer*	Minimum Multicast ALPM entries. **Since: 4.32.2
l2BankMappings	*table(numeric string) = integer*	L2 physical to logical bank mapping.
l2HashOffsets	*table(numeric string) = integer*	L2 hash offsets indexed by physical bank id.
[l2SharedEntries]	*integer*	Shared L2 entries.
l3BankMappings	*table(numeric string) = integer*	L3 physical to logical bank mapping.
l3HashOffsets	*table(numeric string) = integer*	L3 hash offsets indexed by physical bank id.
[l3SharedEntries]	*integer*	Shared L3 entries.
[numEmSharedBanks]	*integer*	Shared Exact Match UFT banks.
[numL2SharedBanks]	*integer*	Shared L2 UFT banks.
[numL3SharedBanks]	*integer*	Shared L3 UFT banks.
[onlyAlpmBasedL3Supported] **	*boolean*	Only ALPM-based L3 routing is supported and enabled implicitly in flexible UFT mode. **Since: 4.34.0
[uftAlpmEntriesPerBank] **	*integer*	ALPM Entries per bank. **Since: 4.25.2
[uftCrcStringBytes]	*integer*	Maximum number of bytes in a bucket.
[uftExactMatchEntriesPerBucket]	*integer*	Exact Match entries per bucket.
[uftKeyShift]	*integer*	Number of bits to shift a key before hashing.
[uftL2EntriesPerBucket]	*integer*	L2 entries per bucket.
[uftL2MinEntries]	*integer*	Minimum L2 UFT entries.
[uftL2NumDedicatedBanks]	*integer*	Minimum L2 UFT banks.
[uftL2SharedMaxEntries]	*integer*	Maximum L2 UFT entries.

[uftL3EntriesPerBucket]	*integer*	L3 entries per bucket.
[uftL3MinEntries]	*integer*	Minimum L3 UFT entries.
[uftL3NumDedicatedBanks]	*integer*	Minimum L3 UFT banks.
[uftL3SharedMaxEntries]	*integer*	Maximum L3 UFT entries.
[uftMaxEntriesPerBucket]	*integer*	Maximum entries per bucket.
[uftMaxSharedBanks]	*integer*	Maximum shared UFT banks.
[uftMaxSharedBuckets]	*integer*	Maximum buckets in shared UFT banks.
[uftMaxSharedEmBanks] **	*integer*	Maximum shared Exact Match UFT banks. **Since: 4.27.1
[uftMaxSharedL2Banks] **	*integer*	Maximum shared L2 UFT banks. **Since: 4.27.1
[uftMaxSharedL3Banks] **	*integer*	Maximum shared L3 UFT banks. **Since: 4.27.1
[uftMode]	*integer*	uftMode.
[uftSharedBankSize]	*integer*	Base entries in shared UFT bank.

2.1578 show platform trident forwardingplane featureagents

agents	*list of AgentModel* see 2.1578.1	List of forwarding plane agents.

2.1578.1 AgentModel

name	*string*	Agent name.

2.1579 show platform trident ingress event debug [...]

chips	*table(string) = IngEventListModel* see 2.1579.1	Map of chip name to list of ingress debug events seen.

2.1579.1 IngEventListModel

[eventCounters] **	*table(string) = integer*	Map of ingress debug events seen since last cleared. Value represents the ingress debug event count. **Since: 4.27.1
events	*list of string*	List of ingress debug events seen since last cleared. Order is chip-dependent. Each appears at most once per chip.

2.1580 show platform trident interface map [...]

chips	*table(string) = ChipEntry* see 2.1580.1	Interface mappings indexed by chip.

2.1580.1 ChipEntry

fapId	*integer*	Fap ID.
interfaces	*table(string) = InterfaceEntry* see 2.1580.1.1	Interface map info indexed by interface or port name.
numPortMax	*integer*	Maximum number of ports.
[openFlowInterfaces]	*table(Interface name) = OpenFlowEntry* see 2.1580.1.2	OpenFlow interface info keyed by interface name.

2.1580.1.1 InterfaceEntry

[egressXpe]	*list of integer*	Egress crosspoint elements.
[ingressXpe]	*list of integer*	Ingress crosspoint elements.
logicalPort	*integer*	Logical port number.
[mmuPort]	*integer*	MMU port number.
[modId]	*integer*	Module identifier.
physicalPort	*integer*	Physical port number.
[pipe]	*integer*	Pipe number.
portName	*string*	Port name.
[vpNativeIndex]	*integer*	Virtual port native index.
[vpTaggedIndex]	*integer*	Virtual port tagged index.

2.1580.1.2 OpenFlowEntry

modId	*integer*	Module identifier.
portId	*integer*	OpenFlow port identifier.

2.1581 show platform trident l2 hardware mac-address-table [...]

chips	*table(string) = MacAddressTable* see 2.1581.1	A mapping of chip name to its MAC address table.

2.1581.1 MacAddressTable

macTableEntries	*list of MacTableEntry* see 2.1581.1.1	List of MAC table entries.

2.1581.1.1 MacTableEntry

classId	*integer*	Class ID.
hwTblIndex **	*integer*	Index in the hardware table. **Since: 4.28.1

interfaces **	*list of string*	Interface for this MAC address. **Since: 4.26.0
macAddress	*MAC address*	MAC address.
macAddressType	*enum: dynamic | dropDst | static | dropSrc | drop*	Type of the MAC address.
[mcastGroupId] **	*integer*	Multicast group ID. **Since: 4.26.0
vlan	*integer*	VLAN ID.

2.1582 show platform trident l2 hardware mac-address-table diff [...]

macTableDiffEntries	*list of MacTableDiffEntry* see 2.1582.1	List of MAC table diff entries.

2.1582.1 MacTableDiffEntry

hwEntries	*table(string) = DiffEntry* see 2.1582.1.1	A mapping of chip name to its hardware entries.
hwTblIndex **	*integer*	Index in the hardware table. **Since: 4.28.1
mac	*MAC address*	MAC address.
swEntries	*list of DiffEntry* see 2.1582.1.1	Software entries.
vlan	*integer*	VLAN ID.

2.1582.1.1 DiffEntry

[classId]	*integer*	Class Id.
[dstDiscard]	*boolean*	Destination Discard.
[invalidEntry]	*boolean*	Invalid Entry.
[macAddressType]	*string*	Type of the MAC address.
[mcastId]	*integer*	Multicast ID.
[mod]	*integer*	Mod.
[port]	*integer*	Port.
[trunkId]	*integer*	Trunk Id.

2.1583 show platform trident l2 hardware mac-address-table missing [...]

macTableMissingEntries	*list of MacTableMissingEntry* see 2.1583.1	List of MAC table missing entries.

2.1583.1 MacTableMissingEntry

hwTblIndex **	*integer*	Index in the hardware table. **Since: 4.28.1
inSw	*boolean*	MAC address present in software.
[keyType] **	*string*	Hardware key type. **Since: 4.35.2

mac	*MAC address*	MAC address.
modules	*list of string*	Chip cards.
vlan	*integer*	VLAN ID.

2.1584 show platform trident l2 shadow egr-vlan-xlate [...]

egrVlanXlateTables	*table(string) = EgrVlanXlateHwTable* see 2.1584.1	Egress Vlan Xlate Tables for all Line Cards in a MultiChip System with the Line Card Name as key.

2.1584.1 EgrVlanXlateHwTable

dvpXlateEntries	*table(numeric string) = EgrVlanXlateDvpEntry* see 2.1584.1.1	Destination Virtual Port based Entries with the key being EntryId which is a hardware Index.
l2GreVfiXlateEntries **	*table(numeric string) = EgrVlanXlateL2GreVfiEntry* see 2.1584.1.3	L2Gre Virtual Forwarding Instance based Entries with key being EntryId which is a hardware index. **Since: 4.35.2
rawXlateEntries	*table(numeric string) = EgrVlanXlateRawEntry* see 2.1584.1.4	All Entries in Raw Format with EntryId as key which is a hardware index. This format is to support the raw option in CLI.
vfiXlateEntries	*table(numeric string) = EgrVlanXlateVfiEntry* see 2.1584.1.5	Virtual Forwarding Instance based Entries with key being EntryId which is a hardware index.
vxlanEncapXlateEntries **	*table(numeric string) = EgrVlanXlateVxlanEncapEntry* see 2.1584.1.6	Virtual Forwarding Instance based Entries with key being EntryId which is a hardware index. **Since: 4.26.0
xlateEntries	*table(numeric string) = EgrVlanXlateEntry* see 2.1584.1.2	Port Vlan Xlate Entries with the key being EntryId which is a hardware Index.

2.1584.1.1 EgrVlanXlateDvpEntry

[classId] **	*integer*	The forwarding class ID of the entry. **Since: 4.31.1
dvp	*integer*	Destination Virtual Port.
newOvid	*integer*	New Outer VLAN ID.
ovid	*integer*	Outer VLAN ID.
tagActionProfilePtr	*integer*	Index into Ingress VLAN Tag Action Profile Table.

2.1584.1.2 EgrVlanXlateEntry

[classId] **	*integer*	The forwarding class ID of the entry. **Since: 4.31.1
newOvid	*integer*	New Outer VLAN ID.
ovid	*integer*	Outer VLAN ID.
portGroupId	*integer*	Port Group ID of the egress Port.
tagActionProfilePtr	*integer*	Index into Ingress VLAN Tag Action Profile Table.

2.1584.1.3 EgrVlanXlateL2GreVfiEntry

vfi	*integer*	VFI.
vpnId	*integer*	VPN ID.

2.1584.1.4 EgrVlanXlateRawEntry

entryValue	*string*	Raw dump of the entry.

2.1584.1.5 EgrVlanXlateVfiEntry

[classId] **	*integer*	The forwarding class ID of the entry. **Since: 4.31.1
sdTagActionIfPresent	*integer*	Index into Ingress VlanTagActionProfileTable if the packet contains SD Tag.
vfi	*integer*	VFI.
vnId	*integer*	VN ID.

2.1584.1.6 EgrVlanXlateVxlanEncapEntry

newOvid	*integer*	New Outer Dot1q Tag.
ovid	*integer*	Outer VLAN ID.
portGroupId	*integer*	Port Group ID of the egress Port.
tagActionProfilePtr	*integer*	Index into Ingress VLAN Tag Action Profile Table.

2.1585 show platform trident l2 shadow egr-vlan-xlate-2 [...]

egrVlanXlate2Tables	*table(string) = EgrVlanXlate2HwTable* see 2.1585.1	Egress Vlan Xlate 2 Tables keyed by linecards.

2.1585.1 EgrVlanXlate2HwTable

assignIfaMdHdrEntries **	*table(numeric string) = EgrVlanXlate2AssignIfaMdHdrEntry* see 2.1585.1.1	AssignIfaMdHdr entries keyed by their hardware index. **Since: 4.25.1
changeL2FieldsEntries	*table(numeric string) = EgrVlanXlate2L2FieldsEntry* see 2.1585.1.3	L2 Fields keyed by their hardware index.
ifaMdLookup1Entries **	*table(numeric string) = EgrVlanXlate2IfaMdLookup1Entry* see 2.1585.1.2	IfaMdLookup1 entries keyed by their hardware index. **Since: 4.25.1
rawEntries	*table(numeric string) = EgrVlanXlate2RawEntry* see 2.1585.1.4	All Entries in Raw Format keyed by their heardware index.

2.1585.1.1 EgrVlanXlate2AssignIfaMdHdrEntry

actionVector	*integer*	Action vector.
currentLength	*integer*	Current length.
gns	*integer*	Global Namespace.
hopLimit	*integer*	Hop limit.
ifaFlags	*integer*	IFA flags.
ifaVersion	*integer*	IFA Version.
maxLength	*integer*	Max length.
opaque4	*integer*	Opaque object.
requestVector	*integer*	Request vector.

2.1585.1.2 EgrVlanXlate2IfaMdLookup1Entry

deviceId	*integer*	Device Id.
dgpp	*integer*	DGPP.
egressPortSpeed	*integer*	Egress Port Speed.
lns	*integer*	Local Namespace.
opaqueData	*integer*	Opaque object data.

2.1585.1.3 EgrVlanXlate2L2FieldsEntry

dataType **	*integer*	Data Type Valid Value : 22, 27. **Since: 4.23.0
dmac	*string*	New destination MAC address.
dvp	*integer*	Destination Virtual Port.
opaqueId	*integer*	Opaque object ID.

smac	*string*	New source MAC address.
tapp	*integer*	Index into Egress Vlan Tag Action Profile Table.
vlan	*integer*	New VLAN ID.

2.1585.1.4 EgrVlanXlate2RawEntry

entryValue	*string*	Raw dump of the entry.

2.1586 show platform trident l2 shadow vlan-xlate [...]

vlanXlateTables	*table(string) = VlanXlateHwTable* see 2.1586.1	Vlan Xlate Tables for all Line Cards in a MultiChip System with the Line Card Name as key.

2.1586.1 VlanXlateHwTable

dipEntries	*table(numeric string) = VlanXlateVxlanDipEntry* see 2.1586.1.5	Destionation IP (DIP) Entries with the key being EntryId which is a hardware Index.
l2GreDipEntries **	*table(numeric string) = VlanXlateL2GreDipEntry* see 2.1586.1.1	Destionation IP (DIP) Entries with the key being EntryId which is a hardware Index. **Since: 4.35.2
ovidEntries	*table(numeric string) = VlanXlateOvidEntry* see 2.1586.1.2	Outer VLAN ID based Entries with the key being EntryId which is a hardware Index.
rawEntries	*table(numeric string) = VlanXlateRawEntry* see 2.1586.1.3	All Entries in Raw Format with the key being EntryId which is a hardware index. This format is to support the raw option in CLI.
vniVfiMapEntries **	*table(numeric string) = VlanXlateVniVfiMapEntry* see 2.1586.1.4	VNI-VFI maps with the key being EntryId which is a hardware Index. **Since: 4.23.0

2.1586.1.1 VlanXlateL2GreDipEntry

dip	*IP address*	DIP Prefix.

2.1586.1.2 VlanXlateOvidEntry

disableVlanChecks	*boolean*	Disable Vlan Membership and STP checks, if Set.
moduleId	*integer*	Module Id.
newOvid	*integer*	New Outer VLAN ID.
ovid	*integer*	Outer VLAN ID.
portNum	*integer*	Port Number.
sourceType	*integer*	Source Type : 0 for SVP and 1 for Source Global Logical Ports.
sourceVp	*integer*	Source Virtual Port Value.
tagActionProfilePtr	*integer*	Index into Ingress VLAN Tag Action Profile Table.
vlanActionValid	*boolean*	Vlan Translation Action is Valid, if Set.

2.1586.1.3 VlanXlateRawEntry

entryValue	*string*	Raw dump of the entry.

2.1586.1.4 VlanXlateVniVfiMapEntry

ovid	*integer*	Outer VLAN ID field in the entry.
tagActionProfilePtr	*integer*	Index into Ingress VLAN Tag Action Profile Table.
vfi	*integer*	VFI.
vni	*integer*	VNI.

2.1586.1.5 VlanXlateVxlanDipEntry

dip	*IP address*	DIP Prefix.

2.1587 show platform trident l2 shadow vlan-xlate-2 [...]

vlanXlate2Tables	*table(string) = VlanXlate2HwTable* see 2.1587.1	Vlan Xlate 2 Tables for all Line Cards in a MultiChip System with the Line Card Name as key.

2.1587.1 VlanXlate2HwTable

intMshipChkDisableEntries	*table(numeric string) = VlanXlate2IntMshipChkDisableEntry* see 2.1587.1.1	L2 Fields keyed by their hardware index.
rawEntries	*table(numeric string) = VlanXlate2RawEntry* see 2.1587.1.2	All Entries in Raw Format with the key being EntryId which is a hardware index. This format is to support the raw option in CLI.

2.1587.1.1 VlanXlate2IntMshipChkDisableEntry

dataLower	*integer*	Data lower.
dataUpper	*integer*	Data upper.
key	*integer*	Key.
moduleId	*integer*	Module ID.

2.1587.1.2 VlanXlate2RawEntry

entryValue	*string*	Raw dump of the entry.

2.1588 show platform trident l2 software ingress-vlan-range

intfVlanRanges	*table(Interface name) = VlanRangeEntry* see 2.1588.1	Ingress VLAN ranges list.

2.1588.1 VlanRangeEntry

entryId	*integer*	EntrId of Ingress Vlan Range table.
[lag]	*interface name*	LAG Interface the interface belongs.
logicalPort	*integer*	Switchcard Logical Port number.
modId	*integer*	Switchcard module ID.
overflow	*boolean*	Inticates if the VLAN Ranges have overflown.
[vlanRanges]	*list of VlanRange* see 2.1588.1.1	List of Ingress VLAN Range to match for VLAN mapping.

2.1588.1.1 VlanRange

vlanMax	*integer*	Max VLAN ID of VLAN Range to match.
vlanMin	*integer*	Min VLAN ID of VLAN Range to match.

2.1589 show platform trident l2 software mac-address-table

macTableEntries	*list of L2SwMacAddrTableEntry* see 2.1589.1	List of MAC table entries.
numEntries	*integer*	Number of shadow entries.

2.1589.1 L2SwMacAddrTableEntry

bitmap	*integer*	MAC address bitmap.
[interface]	*interface name*	Interface for this MAC address.
keyType	*enum: vfi | int | bridge*	Mac address key type.
macAddress	*MAC address*	MAC address.

macAddressType	*enum: evpnConfiguredRemoteMac | peerRouterMac | configuredStaticMac | pendingSecureMac | vplsDynamicRemoteMac | learnedDynamicMac | peerDynamicMac | peerEvpnRemoteMac | peerSecureMac | evpnDynamicRemoteMac | evpnIntfStaticMac | receivedRemoteMac | learnedRemoteMac | dropDst | peerLearnedRemoteMac | peerStaticMac | learnedSecureMac | peerAuthenticatedMac | peerConfiguredRemoteMac | drop | evpnIntfDynamicMac | configuredRemoteMac | configuredRouterMac | peerReceivedRemoteMac | dropSrc | authenticatedMac | configuredDynamicMac | configuredSecureMac*	Type of the MAC address.
markedForDeletion	*boolean*	MAC address is marked for deletion.
[mcastId]	*integer*	Multicast group ID.
pending	*boolean*	MAC addres is pending.
source	*integer*	MAC address learning bitmap.
stale	*boolean*	MAC address is stale.
[virtualPort]	*integer*	Virtual port number.
[virtualPortType]	*enum: tagged | native | numeric*	Type of virtual port.
vlan	*integer*	VLAN ID.

2.1590 show platform trident l2 software mac-address-table count

numberOfShadowEntries	*integer*	Number of shadow entries.

2.1591 show platform trident l2 software mac-address-table remote count

numberOfRemoteMacs	*integer*	Number of remote MAC addresses.

2.1592 show platform trident l2 software multicast-group-table count

numberOfGroups	*integer*	Number of groups.

2.1593 show platform trident l2 status [...]

addHosts	*integer*	Number of Add Hosts.
addMcastHosts	*integer*	Number of Mcast Hosts.
agingTimeReconfigs	*integer*	Number of Aging Time Reconfigs.
agingTimerFirings	*integer*	Number of Aging Timer Firings.
busyFailures	*integer*	Number of MAC Program Busy Failures.
clearMacEntries	*integer*	Number of Clear MAC Entries.
fullFailures	*integer*	Number of MAC Program Full Failures.
inProgressOps	*integer*	In-Progress MAC Ops.
l2modInvalidIndexReads	*integer*	Number of L2mod Invalid Index Reads.
l2modReads	*integer*	Number of L2mod Reads.
l2modSpuriousReads	*integer*	Number of L2mod Spurious Reads.
[l2modTotalEvents]	*integer*	Number of L2mod Total Events.
[l2modVxlanEvents]	*integer*	Number of L2mod Total VXLAN Events.
macProgrammerFapIds	*table(numeric string) = L2StatusMacProgrammer-Status* see 2.1593.1	Mapping from FapId to MAC Programmer Counts. Populated only for detail version of command.
[macProgrammerTotals]	*L2StatusMacProgrammer-Status* see 2.1593.1	Total Counts of all FapIds.
macTable	*integer*	Entries in MAC table.
macUpdateList	*integer*	Update Lists.
mcastAgentFapIds	*table(numeric string) = L2StatusMcastStatus* see 2.1593.2	Mapping from FapId to Mcast Agent Counts.
mcastBulkReadCmds	*integer*	Number of Multicast Bulk Read Commands.
mcastClearCmds	*integer*	Number of Multicast Clear Commands.
mcastGroups	*integer*	Number of Multicast Groups.
mcastPendingGroups	*integer*	Number of Multicast Pending Groups.
mcastReadCmds	*integer*	Number of Multicast Read Commands.
mcastWriteCmds	*integer*	Number of Multicast Write Commands.
mcastWriteCmdsForReserved-Groups	*integer*	Number of Multicast Write Commands for Reserved Groups.
otherFailures	*integer*	Number of Other MAC Program Failures.
overflowOps	*integer*	Overflow Address Ops.
parityFailures	*integer*	Number of MAC Program Parity Errors.
pendingOps	*integer*	Pending MAC Ops.
removeHosts	*integer*	Number of Remove Hosts.
syncMacEntries	*integer*	Number of Sync MAC Entries.

2.1593.1 L2StatusMacProgrammerStatus

commandQueue	*integer*	Command Queue.
commandRingConfigQueue	*integer*	Command Ring Config Queue.
commandRingStatusQueue	*integer*	Command Ring Status Queue.
l2modAgeEvents	*integer*	L2mod Aging Events.
l2modDiscardedEvents	*integer*	L2mod Discarded Events.

l2modFlushEvents	*integer*	L2mod Flush Events.
l2modLagEvents	*integer*	L2mod Lag Events.
l2modLearnEvents	*integer*	L2mod Learn Events.
l2modMulticastEvents	*integer*	L2mod Multicast Events.
l2modNonLagEvents	*integer*	L2mod Non-Lag Events.
l2modRelearnEvents	*integer*	L2mod Relearn Events.
l2modSwLagEvents	*integer*	L2mod Software Lag Events.
l2modTotalEvents	*integer*	L2mod Total Events.
l2modUnexpectedEvents	*integer*	L2mod Unexpected Events.

2.1593.2 L2StatusMcastStatus

mcastBulkReadCmds	*integer*	Number of Multicast Bulk Read Commands.
mcastClearCmds	*integer*	Number of Multicast Clear Commands.
mcastReadCmds	*integer*	Number of Multicast Read Commands.
mcastUnsyncedGroups	*integer*	Number of Multicast Unsynced Groups.
mcastWriteCmds	*integer*	Number of Multicast Write Commands.
mcastWriteCmdsForReservedGroups	*integer*	Number of Multicast Write Commands for Reserved Groups.

2.1594 show platform trident l3 cmdring

l3AgentStatus	*L3AgentStatus* see 2.1594.2	L3 agent status.
l3CmdRing	*CmdRing* see 2.1594.1	L3 schan command ring summary.

2.1594.1 CmdRing

cmdRingFull	*boolean*	True if CmdRing buffer is full.
cmdRingFullCount	*integer*	Number of times CmdRing buffer has been full.
dlbEcmpFlowset **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset command statistics. **Since: 4.24.2
dlbEcmpFlowsetMember **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset Member command statistics. **Since: 4.24.2
dlbEcmpFlowsetMemberPipe0 **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset Member Pipe0 command statistics. **Since: 4.24.2
dlbEcmpFlowsetMemberPipe1 **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset Member Pipe1 command statistics. **Since: 4.24.2
dlbEcmpFlowsetMemberPipe2 **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset Member Pipe2 command statistics. **Since: 4.24.2
dlbEcmpFlowsetMemberPipe3 **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset Member Pipe3 command statistics. **Since: 4.24.2
dlbEcmpFlowsetMemberPipe4 **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset Member Pipe4 command statistics. **Since: 4.24.2
dlbEcmpFlowsetMemberPipe5 **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset Member Pipe5 command statistics. **Since: 4.24.2
dlbEcmpFlowsetMemberPipe6 **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset Member Pipe6 command statistics. **Since: 4.24.2
dlbEcmpFlowsetMemberPipe7 **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset Member Pipe7 command statistics. **Since: 4.24.2
dlbEcmpFlowsetPipe0 **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset command statistics. **Since: 4.24.2
dlbEcmpFlowsetPipe1 **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset command statistics. **Since: 4.24.2
dlbEcmpFlowsetPipe2 **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset command statistics. **Since: 4.24.2
dlbEcmpFlowsetPipe3 **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset command statistics. **Since: 4.24.2
dlbEcmpFlowsetPipe4 **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset command statistics. **Since: 4.24.2
dlbEcmpFlowsetPipe5 **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset command statistics. **Since: 4.24.2

`dlbEcmpFlowsetPipe6` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset command statistics. **Since: 4.24.2
`dlbEcmpFlowsetPipe7` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Flowset command statistics. **Since: 4.24.2
`dlbEcmpGlbQuantizeThreshold` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Glb Quantize Threshold command statistics. **Since: 4.23.0
`dlbEcmpGroupControl` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Group Control command statistics. **Since: 4.20.0
`dlbEcmpGroupMembership` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Group Membership command statistics. **Since: 4.20.0
`dlbEcmpGroupNhiMembers0To12` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Group Nhi Members 0 To 12 command statistics. **Since: 4.23.0
`dlbEcmpGroupNhiMembers13-To25` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Group Nhi Members 13 To 25 command statistics. **Since: 4.23.0
`dlbEcmpGroupNhiMembers26-To38` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Group Nhi Members 26 To 38 command statistics. **Since: 4.23.0
`dlbEcmpGroupNhiMembers39-To51` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Group Nhi Members 39 To 51 command statistics. **Since: 4.23.0
`dlbEcmpGroupNhiMembers52-To63` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Group Nhi Members 52 To 63 command statistics. **Since: 4.23.0
`dlbEcmpGroupPortMembers0-To15` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Group Port Members 0 To 15 command statistics. **Since: 4.23.0
`dlbEcmpGroupPortMembers16-To31` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Group Port Members 16 To 31 command statistics. **Since: 4.23.0
`dlbEcmpGroupPortMembers32-To47` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Group Port Members 32 To 47 command statistics. **Since: 4.23.0
`dlbEcmpGroupPortMembers48-To63` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Group Port Members 48 To 63 command statistics. **Since: 4.23.0
`dlbEcmpGroupPortToMember` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Group Port To Member command statistics. **Since: 4.20.0
`dlbEcmpPortQualityMapping` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Port Quality Mapping command statistics. **Since: 4.23.0
`dlbEcmpPortQualityUpdate-MeasureControl` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Port Quality Update Measure Cotrol command statistics. **Since: 4.24.0
`dlbEcmpPortState` **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Port State command statistics. **Since: 4.34.2

dlbEcmpQuantizeControl **	*SchanCmd* see 2.1594.1.1	Dlb Ecmp Quantize Control command statistics. **Since: 4.23.0
ecmp	*SchanCmd* see 2.1594.1.1	Ecmp command statistics.
ecmpDlbControl **	*SchanCmd* see 2.1594.1.1	Ecmp Dlb Control command statistics. **Since: 4.20.0
ecmpGroup	*SchanCmd* see 2.1594.1.1	EcmpGroup command statistics.
egrIpTunnel	*SchanCmd* see 2.1594.1.1	EgrIpTunnel command statistics.
egrIpTunnelIpv6	*SchanCmd* see 2.1594.1.1	EgrIpTunnelIpv6 command statistics.
egrIpmc **	*SchanCmd* see 2.1594.1.1	EgrIpmc command statistics. **Since: 4.34.0
egrMacDaProfile	*SchanCmd* see 2.1594.1.1	EgrMacDaProfile command statistics.
egrMplsVcAndSwapLabel	*SchanCmd* see 2.1594.1.1	EgrMplsVcAndSwapLabel command statistics.
ignoreTotal	*integer*	Total number of ignored schan commands.
ingActiveL3IifProfile	*SchanCmd* see 2.1594.1.1	IngActiveL3IifProfile command statistics.
ingDvpTable	*SchanCmd* see 2.1594.1.1	IngDvpTable command statistics.
interface	*SchanCmd* see 2.1594.1.1	Interface command statistics.
ipMulticastTcam	*SchanCmd* see 2.1594.1.1	IpMulticastTcam command statistics.
ipOptionControlProfileTable **	*SchanCmd* see 2.1594.1.1	Ip Option Control Profile Table command statistics. **Since: 4.30.0
l2GreSipMplsEntry **	*SchanCmd* see 2.1594.1.1	L2GreSipMplsEntry command statistics. **Since: 4.35.2
l2GreVpnIdMplsEntry **	*SchanCmd* see 2.1594.1.1	L2GreVpnIdMplsEntry command statistics. **Since: 4.35.2
l2Mc	*SchanCmd* see 2.1594.1.1	L2Mc command statistics.
l3AlpmIp4Mroute **	*SchanCmd* see 2.1594.1.1	L3AlpmIp4Mroute command statistics. **Since: 4.31.1
l3AlpmIp4Ucast	*SchanCmd* see 2.1594.1.1	L3AlpmIp4Ucast command statistics.
l3AlpmIp6Ucast	*SchanCmd* see 2.1594.1.1	L3AlpmIp6Ucast command statistics.
l3AlpmLevel2Ip4Mroute **	*SchanCmd* see 2.1594.1.1	L3AlpmLevel2Ip4Mroute command statistics. **Since: 4.31.1
l3DefIp4Mcast **	*SchanCmd* see 2.1594.1.1	L3DefIp4Mcast command statistics. **Since: 4.31.0
l3DefIp4Ucast	*SchanCmd* see 2.1594.1.1	L3DefIp4Ucast command statistics.

l3DefIp6Ucast	*SchanCmd* see 2.1594.1.1	L3DefIp6Ucast command statistics.
l3DefipAlpmLevel2Ecc **	*SchanCmd* see 2.1594.1.1	L3DefipAlpmLevel2Ecc command statistics. **Since: 4.21.3
l3DefipAlpmLevel3Ecc **	*SchanCmd* see 2.1594.1.1	L3DefipAlpmLevel3Ecc command statistics. **Since: 4.21.3
l3EcmpGroupHierarchical **	*SchanCmd* see 2.1594.1.1	EcmpGroupHierarchical command statistics. **Since: 4.27.2
l3Entry4Mcast	*SchanCmd* see 2.1594.1.1	L3Entry4Mcast command statistics.
l3Entry4Ucast	*SchanCmd* see 2.1594.1.1	L3Entry4Ucast command statistics.
l3Entry6Mcast **	*SchanCmd* see 2.1594.1.1	L3Entry6Mcast command statistics. **Since: 4.22.0
l3Entry6Ucast	*SchanCmd* see 2.1594.1.1	L3Entry6Ucast command statistics.
l3EntryEcc	*SchanCmd* see 2.1594.1.1	L3EntryEcc command statistics.
l3EntryOnlyEcc **	*SchanCmd* see 2.1594.1.1	L3EntryOnlyEcc command statistics. **Since: 4.20.5
l3IifProfile	*SchanCmd* see 2.1594.1.1	L3IifProfile command statistics.
l3Ipmc	*SchanCmd* see 2.1594.1.1	L3Ipmc command statistics.
l3Ipmc1 **	*SchanCmd* see 2.1594.1.1	L3Ipmc1 command statistics. **Since: 4.35.2
l3IpmcRemap	*SchanCmd* see 2.1594.1.1	L3IpmcRemap command statistics.
l3Tunnel	*SchanCmd* see 2.1594.1.1	L3Tunnel command statistics.
l3TunnelEcc **	*SchanCmd* see 2.1594.1.1	L3TunnelEcc command statistics. **Since: 4.23.1
maxCmdRingSize	*integer*	Maximum size in the history of CmdRing buffer.
mmuReplCopyCount	*SchanCmd* see 2.1594.1.1	MmuReplCopyCount command statistics.
mmuReplHead	*SchanCmd* see 2.1594.1.1	MmuReplHead command statistics.
mmuReplInfo0	*SchanCmd* see 2.1594.1.1	MmuReplInfo0 command statistics.
mmuReplInfo1	*SchanCmd* see 2.1594.1.1	MmuReplInfo1 command statistics.
mmuReplList	*SchanCmd* see 2.1594.1.1	MmuReplList command statistics.
mplsEntry	*SchanCmd* see 2.1594.1.1	MplsEntry command statistics.
mplsEntryEcc **	*SchanCmd* see 2.1594.1.1	MplsEntryEcc command statistics. **Since: 4.20.0

mplsNextHop	*SchanCmd* see 2.1594.1.1	MplsNextHop command statistics.
mtuValues	*SchanCmd* see 2.1594.1.1	MtuValues command statistics.
myStationTcam	*SchanCmd* see 2.1594.1.1	MyStationTcam command statistics.
name	*string*	Name to give to the summary of all schan commands.
nextHop	*SchanCmd* see 2.1594.1.1	NextHop command statistics.
retryTotal	*integer*	Total number of retried schan commands.
sdTagNextHop	*SchanCmd* see 2.1594.1.1	SdTagNextHop command statistics.
subIntfMplsEntry **	*SchanCmd* see 2.1594.1.1	SubIntfMplsEntry command statistics. **Since: 4.32.1
successTotal	*integer*	Total number of successful schan commands.
vxlanDip6MplsEntry **	*SchanCmd* see 2.1594.1.1	VxlanDip6MplsEntry command statistics. **Since: 4.23.2
vxlanEgrDvpAttribute	*SchanCmd* see 2.1594.1.1	VxlanEgrDvpAttribute command statistics.
vxlanSip6MplsEntry **	*SchanCmd* see 2.1594.1.1	VxlanSip6MplsEntry command statistics. **Since: 4.23.2
vxlanSipMplsEntry	*SchanCmd* see 2.1594.1.1	VxlanSipMplsEntry command statistics.
vxlanVniMplsEntry	*SchanCmd* see 2.1594.1.1	VxlanVniMplsEntry command statistics.

2.1594.1.1 SchanCmd

ignoreCnt	*integer*	Schan command ignore count.
retryCnt	*integer*	Schan command retry count.
successCnt	*integer*	Schan command success count.

2.1594.2 L3AgentStatus

bulkDownloads	*table(numeric string) = integer*	Bulk download statistics. Key is module ID, value is number of bulk downloads.
coprocessors	*integer*	Number of coprocessors.
coprocessorsAttached	*integer*	Number of attached coprocessors.
hwParityErrors	*table(string) = integer*	Number of hardware parity errors. Key is hardware table id, value is number of parity errors.
pendingCmds	*integer*	Number of pending schan commands.
totalCmds	*integer*	Total number of schan commands.
ucastAdjsV4	*integer*	Total number of IPv4 unicast adjacencies.
ucastAdjsV6	*integer*	Total number of IPv6 unicast adjacencies.
ucastPendingAdjsV4	*integer*	Number of IPv4 unicast adjacencies pending hardware programming.
ucastPendingAdjsV6	*integer*	Number of IPv6 unicast adjacencies pending hardware programming.

ucastPendingRoutesV4	*integer*	Number of IPv4 unicast routes pending hardware programming.
ucastPendingRoutesV6	*integer*	Number of IPv6 unicast routes pending hardware programming.
ucastRoutesV4	*integer*	Total number of IPv4 unicast routes.
ucastRoutesV6	*integer*	Total number of IPv6 unicast routes.
ucastUnprogrammedAdjsV4	*integer*	Number of IPv4 unicast adjacencies that failed hardware programming.
ucastUnprogrammedAdjsV6	*integer*	Number of IPv6 unicast adjacencies that failed hardware programming.
ucastUnprogrammedRoutesV4	*integer*	Number of IPv4 unicast routes that failed hardware programming.
ucastUnprogrammedRoutesV6	*integer*	Number of IPv6 unicast routes that failed hardware programming.

2.1595 show platform trident l3 shadow (my-station | my-station-2) [...]

l3MyStation	*table(numeric string) = L3MyStationEntry* see 2.1595.1	Collection of MyStation objects keyed by the entry ID.

2.1595.1 L3MyStationEntry

arp	*boolean*	Arp termination.
cpu	*boolean*	Copy to CPU enabled.
dscd	*boolean*	Discard enabled.
ingressPort	*integer*	Ingress port for this entry.
ingressPortMask	*integer*	Mask for this ingress port.
macAddress	*MAC address*	MAC address of this entry.
macMask	*MAC address*	Mask for the MAC address of the entry.
modId	*integer*	The module ID of the entry.
modIdMask	*integer*	The moduleId mask of the entry.
mpls	*boolean*	MPLS termination.
[profileId] **	*integer*	Profile Id. **Since: 4.21.3
trunkBit	*integer*	Trunk bit.
trunkBitMask	*integer*	Trunk bit mask.
[v4Multicast]	*boolean*	IPv4 Multicast routing enabled.
v4Unicast	*boolean*	IPv4 Unicast routing enabled.
[v6Multicast]	*boolean*	IPv6 Multicast routing enabled.
v6Unicast	*boolean*	IPv6 Unicast routing enabled.
vlan	*integer*	The VLAN the entry belongs to.
vlanMask	*integer*	VLAN mask for this entry.

2.1596 show platform trident l3 shadow counter [...]

revision 2

cntrTables	*table(string) = CounterTable* see 2.1596.1	Individual Counter tables, indexed by the table name.

2.1596.1 CounterTable

cmds	*table(string) = CounterTableEntry* see 2.1596.1.1	Counters in each HW Table, where the key is the command type inside the table.

2.1596.1.1 CounterTableEntry

deltaAdds	*integer*	Incremental additions on the table.
deltaDeletes	*integer*	Incremental deletions on the table.
deltaModifications	*integer*	Incremental modifications on the table.
totalAdds	*integer*	Total number of add operations on the table.

totalDeletes	*integer*	Total number of delete operations on the table.
totalModifications	*integer*	Total number of modification operations on the table.

2.1597 show platform trident l3 shadow dlb-ecmp-group-control [...]

dlbEcmpGroupControl	*table(numeric string) = L3ShwDlbEcmpGroupControlEntry* see 2.1597.1	Individual DLB_ECMP_GROUP_CONTROL keyed by entryId.

2.1597.1 L3ShwDlbEcmpGroupControlEntry

baseAddr	*integer*	Group Port To Member Base Address.
flowBase	*integer*	Flow Set Base.
flowSize	*integer*	Flow Set Size.
groupSize	*integer*	Number of members in Primary Group.
inDur	*integer*	Inactivity Duration.
memPtr	*integer*	Group Membership Pointer.
mode	*integer*	Port Assignment Mode.
oc	*integer*	Optimal Candidate.
path	*integer*	Primary Path Threshold.

2.1598 show platform trident l3 shadow dlb-ecmp-group-membership [...]

dlbEcmpGroupMembership	*table(numeric string) = L3ShwDlbEcmpGroupMembershipEntry* see 2.1598.1	Individual DLB_ECMP_GROUP_MEMBERSHIP keyed by DLB ID.

2.1598.1 L3ShwDlbEcmpGroupMembershipEntry

portMap	*string*	Indicates whether a logical port is a member of a DLB group.

2.1599 show platform trident l3 shadow dlb-ecmp-group-port-to-member [...]

dlbEcmpGroupPortToMember	*table(numeric string) = L3ShwDlbEcmpGroupPortToMemberEntry* see 2.1599.1	Individual DLB_ECMP_GROUP_PORT_TO_MEMBER keyed by MaxPort * DLB id + port number.

2.1599.1 L3ShwDlbEcmpGroupPortToMemberEntry

ecmpBitmap	*string*	Indicate if this port is part of DLB.

2.1600 show platform trident l3 shadow ecmp-dlb-control [...]

ecmpDlbControl	*table(numeric string) = L3ShwEcmpDlbControlEntry* see 2.1600.1	Individual ECMP_DLB_CONTROL keyed by ECMP group entryId.

2.1600.1 L3ShwEcmpDlbControlEntry

dlbId	*integer*	DLB Id of the ECMP group.
enable	*boolean*	DLB group is enabled.

2.1601 show platform trident l3 shadow interfaces [...]

l3Intf	*table(numeric string) = L3ShwIntfEntry* see 2.1601.1	Individual L3 Interfaces keyed by interface value.

2.1601.1 L3ShwIntfEntry

group	*integer*	The multicast group the interface is in.
innerVlan	*integer*	The inner vlan.
ipmcIif	*integer*	IP Mutlicast IIF.
sourceMac	*MAC address*	The MAC address of this interface.
ttl	*integer*	The TTL value of the interface.
tunnel	*integer*	The tunnel index.
unit	*integer*	The forwarding chip the interface belongs to.
vlan	*integer*	The vlan for the interface.
vrf	*integer*	The VRF the interface belongs to.

2.1602 show platform trident l3 shadow l3-iif-profile [...]

l3IifProfile	*table(numeric string) = L3ShwIifProfileEntry* see 2.1602.1	Individual L3 iif profile entries indexed by entry ID.

2.1602.1 L3ShwIifProfileEntry

allowGlobalRouting	*boolean*	Allow global routing.
icmpToCpu	*boolean*	ICMP messages to CPU enabled.
trustDscpPtr	*integer*	Pointer to trust DSCP.
uRPFDefRc	*boolean*	URPF Default route check enabled.
uRPFMode	*integer*	The URPF mode of the interface.
unit	*integer*	The forwarding chip the l3-iif-profile belongs to.
unkMC2CpuV4	*boolean*	v4 unknown multicast to CPU.
unkMC2CpuV6	*boolean*	v6 unknown multicast to CPU.
v4Multicast	*boolean*	v4 multicast routing enabled.
v4Unicast	*boolean*	v4 unicast routing enabled.

v6Multicast	*boolean*	v6 multicast routing enabled.
v6Unicast	*boolean*	v6 unicast routing enabled.

2.1603 show platform trident l3 shadow l3-tunnel [...]

revision 2

l3Tunnel	*table(numeric string) = L3ShwL3TunnelEntry* see 2.1603.1	Individual L3 tunnel keyed by entryId.

2.1603.1 L3ShwL3TunnelEntry

Iif	*integer*	L3 IIF index entry points to.
TT	*integer*	Tunnel Type.
dip	*IP address*	Destination IP address.
endId	*integer*	End Index of entry.
grePayload4	*integer*	GRE Payload Ipv4.
grePayload6	*integer*	GRE Payload Ipv6.
payload4	*integer*	Payload Ipv4.
payload6	*integer*	Payload Ipv6.
proto	*integer*	Protocol.
sip **	*IP address*	Source IP address. **Since: 4.22.1
startId	*integer*	Start Index of entry.
subTT	*integer*	SubTunnel Type.
unit	*integer*	The forwarding chip l3_tunnel belongs to.

2.1604 show platform trident l3 shadow mroutes [...]

mRoutes	*table(numeric string) = L3ShwMroutesEntry* see 2.1604.1	Multicast Routing table, indexed by the entry ID.

2.1604.1 L3ShwMroutesEntry

classId	*integer*	Class ID.
fDrop	*string*	Fast Drop.
groupId	*integer*	Group ID.
grpAddr	*IP address*	Multicast groupaddress.
[rpaId]	*integer*	RPA ID.
srcAddr	*IP address*	Multicast source address.
vlan	*integer*	VLAN ID for the entry.
vrf	*integer*	VRF.

2.1605 show platform trident l3 shadow mtu [...]

l3Mtu	*table(numeric string) = L3ShwMtuEntry* see 2.1605.1	Individual L3 MTUs keyed by interface value.

2.1605.1 L3ShwMtuEntry

mtu	*integer*	Maximum transmission unit for this interface.

2.1606 show platform trident l3 shadow next-hops her

l3NextHopsHer	*table(numeric string) = L3ShwNextHopsHerEntry* see 2.1606.1	HER next hops table, indexed by the entryId.

2.1606.1 L3ShwNextHopsHerEntry

drop	*boolean*	Drop enabled.
dvp	*integer*	DVP for the entry.
intf	*integer*	Interface for the entry.
mac	*MAC address*	MAC address of the entry.
macDaIdx	*integer*	MAC DA Index for the entry.
modId	*integer*	Module ID for the entry.
port	*integer*	Port for the entry.
toCpu	*boolean*	Send to CPU enabled.
vlan	*integer*	VLAN ID for the entry.

2.1607 show platform trident l3 shadow next-hops multipath [...]

l3NextHopsEcmp	*table(numeric string) = L3NextHopsEcmp* see 2.1607.1	ECMP next hops table, indexed by the entry ID.

2.1607.1 L3NextHopsEcmp

intfs	*list of integer*	The interfaces associated with the multipath next hop entry ID.

2.1608 show platform trident l3 shadow next-hops multipath ecmp [...]

see 2.1607

2.1609 show platform trident l3 shadow next-hops multipath hfec [...]

l3HierarchicalEcmpGroup	*table(numeric string) = L3NextHopsEcmp-HierarchicalList* see 2.1609.1	Hierarchical ECMP group table, indexed by the entry ID.

2.1609.1 L3NextHopsEcmpHierarchicalList

members	*list of L3NextHopsEcmp-HierarchicalMember* see 2.1609.1.1	The members associated with the multi-path next hop entry ID.

2.1609.1.1 L3NextHopsEcmpHierarchicalMember

overlayNextHop	*integer*	Overlay next hop index.
underlayEcmp	*boolean*	Underlay next hop is ECMP.
underlayNextHop	*integer*	Underlay next hop index.

2.1610 show platform trident l3 shadow next-hops simple [...]

l3NextHopsSimple	*table(numeric string) = L3-ShwNextHopsSimpleEntry* see 2.1610.1	Simple next hops table, indexed by the entryId.

2.1610.1 L3ShwNextHopsSimpleEntry

drop	*boolean*	Drop enabled.
intf	*integer*	Interface for the entry.
mac	*MAC address*	MAC address of the entry.
macDaIdx	*integer*	Mac DA Index for the entry.
modId	*integer*	Module ID for the entry.
mplsLabel	*integer*	MPLS Label for the entry.
port	*integer*	Port for the entry.
toCpu	*boolean*	Send to CPU enabled.
vlan	*integer*	VLAN ID for the entry.

2.1611 show platform trident l3 shadow routes defip [...]

freeV6Entries	*integer*	Free IPv6 entries available.
ipVersion	*enum: v6 | v4*	The IP version of table in this object, either v4 or v6.
l3Routes	*table(string) = L3ShwRoutesDefipEntry* see 2.1611.1	Defip routing table, indexed by the entry ID.
maxEcmpPaths	*integer*	Max number of ECMP paths in v6.
totalDefIpEntries	*integer*	The number of DEFIP entries in Unit 0.

2.1611.1 L3ShwRoutesDefipEntry

bktId	*integer*	Bucket ID.
classId	*integer*	Class ID.
ecmp	*boolean*	ECMP Nexthop.
hit	*string*	Hit counter.
hitIdx	*integer*	Hit Index.
index	*integer*	LPM index.
intf	*integer*	Interface.
macAddress	*MAC address*	Next hop MAC address.
modId	*integer*	Module ID.
netAddr	*IP address prefix*	IP address.
port	*integer*	Port.
priority	*integer*	Priority.
vlan	*string*	Vlan.
vrf	*integer*	VRF.

2.1612 show platform trident l3 shadow routes host [...]

freeTableEntries	*integer*	The number of free table entries, L3 table for IP v4, IPv6 table for IP v6.
ipVersion	*enum: v6 | v4*	The IP version of table in this object, either v4 or v6.
l3Routes	*table(numeric string) = L3ShwRoutesHostEntry* see 2.1612.1	Host Routing table, indexed by the entryId.

2.1612.1 L3ShwRoutesHostEntry

classId	*integer*	Class ID.
ecmp	*boolean*	ECMP Nexthop.
hit	*string*	Hit counter.
intf	*integer*	L3 interface.
ipAddr	*IP address*	IP address.
macAddress	*MAC address*	The MAC address.
modId	*integer*	Module ID.
port	*integer*	Port.

`vrf`	*integer*	VRF.

2.1613 show platform trident l3 shadow routes lpm [...]

freeV6Entries	*integer*	Free IPv6 entries available.
ipVersion	*enum: v6 | v4*	The IP version of table in this object, either v4 or v6.
l3Routes	*table(string) = L3ShwRoutesLpmEntry* see 2.1613.1	LPM routing table, indexed by the entry ID.
maxEcmpPaths	*integer*	Max number of ECMP paths in v6.
totalDefIpEntries	*integer*	The number of DEFIP entries in Unit 0.

2.1613.1 L3ShwRoutesLpmEntry

classId	*integer*	Class ID.
ecmp	*boolean*	ECMP Nexthop.
hit	*string*	Hit counter.
index	*integer*	LPM index.
intf	*integer*	Interface.
macAddress	*MAC address*	Next hop MAC address.
modId	*integer*	Module ID.
netAddr	*IP address prefix*	IP address.
port	*integer*	Port.
priority	*integer*	Priority.
vlan	*string*	Vlan.
vrf	*integer*	VRF.

2.1614 show platform trident l3 shadow routes-v6 defip [...]

see 2.1611

2.1615 show platform trident l3 shadow routes-v6 host [...]

see 2.1612

2.1616 show platform trident l3 shadow routes-v6 lpm [...]

see 2.1613

2.1617 show platform trident l3 shadow tunnel TYPE [...]

l3EgrIpTunnel	*table(numeric string) = L3ShwEgrIpTunnelEntry* see 2.1617.1	Individual L3 egr ip tunnels keyed by entryId.
l3EgrIpTunnelVxlanIpv6 **	*table(numeric string) = L3ShwEgrIpTunnelEntry-VxlanIpv6* see 2.1617.2	Individual L3 egr ip tunnels for vxlan ipv6 underlay keyed by entryId. **Since: 4.32.2

2.1617.1 L3ShwEgrIpTunnelEntry

dscpSel	*integer*	The DSCP select value of the tunnel.
dstIp	*IP address*	The destination IP address of the tunnel.
entryType	*string*	The type of entry.
srcIp	*IP address*	The source IP address of the tunnel.
ttl	*integer*	The TTL of the IP tunnel.
tunnelType	*integer*	The type of tunnel.
unit	*integer*	The forwarding chip the IP tunnel belongs to.

2.1617.2 L3ShwEgrIpTunnelEntryVxlanIpv6

entryType	*string*	The type of entry.
flexVxlanIpv6QosActionSel	*integer*	The DSCP select value of the tunnel.
srcIp	*IP address*	The source IP address of the tunnel.
ttl	*integer*	The TTL of the IP tunnel.
tunnelType	*integer*	The type of tunnel.
unit	*integer*	The forwarding chip the IP tunnel belongs to.

2.1618 show platform trident l3 shadow unified-tcam

unifiedTcamEntries	*table(numeric string) = UnifiedTcamEntry* see 2.1618.1	Collection of UnifiedTcamEntry objects keyed by entry ID.

2.1618.1 UnifiedTcamEntry

bankId	*integer*	Unified TCAM Bank ID.

2.1619 show platform trident l3 shadow unified-tcam map

unifiedTcamMapEntries	*table(numeric string) = UnifiedTcamMapEntry* see 2.1619.1	Collection of UnifiedTcamMapEntry objects keyed by entry ID.

2.1619.1 UnifiedTcamMapEntry

banks	*list of UnifiedTcamBankId* see 2.1619.1.1	Unified TCAM Bank Map.

2.1619.1.1 UnifiedTcamBankId

bankId	*integer*	Unified TCAM Bank Id.

2.1620 show platform trident l3 software alpm-table [...]

revision 2

[l3AlpmRouteLpm]	*L3AlpmRouteLpm* see 2.1620.2	LPM route.
[l3AlpmRoutes]	*L3AlpmRoutes* see 2.1620.3	List of IPv4 routes.
[l3AlpmRoutesV6]	*L3AlpmRoutes* see 2.1620.3	List of IPv4 routes.
[l3AlpmTableBuckets]	*L3AlpmTableBuckets* see 2.1620.4	ALPM Buckets.
[l3AlpmTableState]	*AlpmTableState* see 2.1620.1	ALPM table.
[l3AlpmThreeLevelTable-Stats]	*L3AlpmThreeLevelTable-Stats* see 2.1620.5	3 Level ALPM Statistics.
[l3AlpmTwoLevelTableStats]	*L3AlpmTwoLevelTableStats* see 2.1620.6	2 Level ALPM Statistics.
[l3AlpmUnprogL2Routes]	*L3AlpmRoutes* see 2.1620.3	List of unprogrammed IPv4 L2 pivots.
[l3AlpmUnprogL2RoutesV6]	*L3AlpmRoutes* see 2.1620.3	List of unprogrammed IPv4 L2 pivots.
[l3AlpmUnprogL3Routes]	*L3AlpmRoutes* see 2.1620.3	List of unprogrammed IPv4 L3 routes.
[l3AlpmUnprogL3RoutesV6]	*L3AlpmRoutes* see 2.1620.3	List of unprogrammed IPv4 L3 routes.

2.1620.1 AlpmTableState

alpmTableMode	*integer*	ALPM table mode.
bucketsV4	*integer*	Number of IPv4 buckets in use.
bucketsV6Full	*integer*	Number of /128 IPv6 buckets in use.
bucketsV6Half	*integer*	Number of /64 IPv6 buckets in use.
fibRoutesV4	*integer*	Number of IPv4 entries in UFT table.
fibRoutesV6Full	*integer*	Number of /128 IPv6 entries in the UFT table.
fibRoutesV6Half	*integer*	Number of /64 IPv6 entries in the UFT table.
maxAlpmTableEntries	*integer*	Maximum number of entries in ALPM table.
maxFibRoutesV4	*integer*	Maximum possible number of IPv4 entries in UFT table.
maxFibRoutesV6Full	*integer*	Maximum possible number of /128 IPv6 entries in the UFT table.
maxFibRoutesV6Half	*integer*	Maximum possible number of /64 IPv6 entries in the UFT table.
pivotsV4	*integer*	Number of IPv4 entries in DEFIP table.
pivotsV6Full	*integer*	Number of /128 IPv6 entries in DEFIP table.
pivotsV6Half	*integer*	Number of /64 IPv6 entries in DEFIP table.

2.1620.2 L3AlpmRouteLpm

[fibBank]	*integer*	Fib bank.
[fibBucket]	*integer*	Fib bucket.
[fibEntry]	*integer*	Fib entry.
[fibPos]	*integer*	Fib Position.
[fibRoute]	*IP address prefix*	Fib route.
[fibSubBucket]	*integer*	Fib sub-bucket.
[l1Pivot]	*IP address prefix*	L1 pivot.
[l1PivotBucket]	*integer*	L1 pivot bucket.
[l1PivotCoveringPrefix]	*IP address prefix*	L1 pivot covering prefix.
[l1PivotRouteCount]	*integer*	L1 pivot route count.
[pivot]	*IP address prefix*	Pivot.
[pivotBucket]	*integer*	Pivot bucket.
[pivotCoveringPrefix]	*IP address prefix*	Pivot covering prefix.
[pivotRouteCount]	*integer*	Pivot route count.
prefix	*IP address prefix*	IP Route Address Prefix.
vrf	*integer*	VRF.

2.1620.3 L3AlpmRoutes

l3AlpmRoutes	*table(numeric string) = L3AlpmRouteAttributes* see 2.1620.3.1	ALPM routes indexed by physical position in ALPM.

2.1620.3.1 L3AlpmRouteAttributes

[bank]	*integer*	Bank Id.
[bucket]	*integer*	Bucket Id.
[entry]	*integer*	Entry Id.
route	*IP address prefix*	Route prefix.
[subBucket]	*integer*	SubBucket Id.
vrf	*integer*	VRF Id.

2.1620.4 L3AlpmTableBuckets

buckets	*list of L3AlpmBucket* see 2.1620.4.1	List of buckets in use.
numBuckets	*integer*	Number of buckets.
[numBucketsPerPage]	*integer*	Number of buckets / page.
[numDefragsV4]	*integer*	Number of V4 defrags.
[numDefragsV6]	*integer*	Number of V6 defrags.
[numPages]	*integer*	Number of pages.
[routeTypes]	*table(string) = L3AlpmBucketsRouteType* see 2.1620.4.2	A mapping of pivot route types to their counters.
uRPF	*boolean*	uRPF is enabled.

2.1620.4.1 L3AlpmBucket

entry	*integer*	Id of bucket entry.
freeBitmap	*integer*	Free bit map.
page	*integer*	Pages allocated.
routeType	*enum: v4 | v6Half | v6Full*	Route type.
subBuckets	*list of L3AlpmSubBucket* see 2.1620.4.1.1	List of sub-buckets.

2.1620.4.1.1 L3AlpmSubBucket

allocated	*integer*	Number of entries allocated for pivot route.
pivot	*IP address prefix*	Pivot route identifier.
vrf	*integer*	VRF of pivot route.

2.1620.4.2 L3AlpmBucketsRouteType

bucketsPerPivot	*integer*	Number of buckets / pivot for this route type.
entriesPerPivot	*integer*	Number of entries / pivot for this route type.

2.1620.5 L3AlpmThreeLevelTableStats

batchedRequests	*integer*	Number of Batched Requests.
batches	*integer*	Batches.
batchesCleanseTime	*floating point number*	CLeanse Time for Batches.
cleanses	*integer*	Cleanses.
l1PivotsFree	*integer*	L1 Pivots Free Percentage.
l1PivotsPeak	*integer*	L1 Pivots peak.
l1PivotsTotal	*integer*	Total of L1 Pivots.
l1PivotsUsed	*integer*	L1 Pivots Used.
l2BanksBucketRows	*integer*	This represents the smem_prows.
l2BanksFormat1	*integer*	L2 Banks for Format 1.
l2BanksFormat2	*integer*	L2 Banks for Format 2.
l2BanksFormat3	*integer*	L2 Banks for Format 3.
l2BanksFormat4	*integer*	L2 Banks for Format 4.
l2BanksFormat5	*integer*	L2 Banks for Format 5.
[l2BanksFormat6] **	*integer*	L2 Banks for Format 6. **Since: 4.27.2
[l2BanksFormat7] **	*integer*	L2 Banks for Format 7. **Since: 4.27.2
[l2BanksFormat8] **	*integer*	L2 Banks for Format 8. **Since: 4.27.2
[l2BanksFormat9] **	*integer*	L2 Banks for Format 9. **Since: 4.27.2
l2BanksPeak	*integer*	L2 Banks Peak.
l2BanksPercent	*integer*	L2 Banks Percentage.
l2BanksTotalPoolsPerRows	*integer*	L2 Banks Total Pools Per Rows.
l2BanksUsed	*integer*	L2 Banks Used.

l2BucketsPeakRows	*integer*	L2 Buckets Peak Rows.
l2BucketsRowsPercent	*integer*	L2 Buckets Rows Percentage.
l2BucketsRowsUsed	*integer*	L2 Buckets Rows Used.
l2PivotsFree	*integer*	L2 Pivots Free Percentage.
l2PivotsPeak	*integer*	L2 Pivots Peak.
l2PivotsTotal	*integer*	Total of L2 Pivots.
l2PivotsUsed	*integer*	L2 Pivots Used.
l2V4PivotsUnprogrammed	*integer*	L2 V4 Pivots Unprogrammed.
l2V6PivotsUnprogrammed	*integer*	L2 V6 Pivots Unprogrammed.
l3BanksBucketRows	*integer*	This represents the smem_prows.
l3BanksFormat1	*integer*	L3 Banks for Format 1.
l3BanksFormat2	*integer*	L3 Banks for Format 2.
l3BanksFormat3	*integer*	L3 Banks for Format 3.
l3BanksFormat4	*integer*	L3 Banks for Format 4.
l3BanksFormat5	*integer*	L3 Banks for Format 5.
l3BanksFormat6	*integer*	L3 Banks for Format 6.
l3BanksFormat7	*integer*	L3 Banks for Format 7.
l3BanksFormat8	*integer*	L3 Banks for Format 8.
l3BanksFormat9	*integer*	L3 Banks for Format 9.
l3BanksPeak	*integer*	L3 Banks Peak.
l3BanksPercent	*integer*	L3 Banks Percentage.
l3BanksTotalPoolsPerRows	*integer*	L2 Banks Total Pools Per Rows.
l3BanksUsed	*integer*	L3 Banks Used.
l3BucketsPeakRows	*integer*	L3 Buckets Peak Rows.
l3BucketsRowsPercent	*integer*	L2 Buckets Rows Percentage.
l3BucketsRowsUsed	*integer*	L3 Buckets Rows Used.
numRequests	*integer*	Number of Requests.
peakCleanseTime	*floating point number*	Peak Cleanse Time.
requestHandleTime	*floating point number*	Request Handling Time.
v4ConfigRoutes	*integer*	v4 Configuration Routes.
v4StatusRoutes	*integer*	v4 Status Routes.
v4UnprogrammedRoutes	*integer*	v4 Unprogrammed Routes.
v6ConfigRoutes	*integer*	v6 Configuration Routes.
v6L1Pivots	*integer*	v6 L1 Pivots.
v6L2Pivots	*integer*	v6 L2 Pivots.
v6StatusRoutes	*integer*	v6 Status Routes.
v6UnprogrammedRoutes	*integer*	v6 Unpprogrammed Routes.

2.1620.6 L3AlpmTwoLevelTableStats

v4Route	*L3AlpmStatsRouteType* see 2.1620.6.1	v4Route.
v6FullHalfPivot	*integer*	Move Pivot v6Full to v6Half.
v6FullHalfRoute	*integer*	Move Routes v6Full to v6Half.
v6FullRoute	*L3AlpmStatsRouteType* see 2.1620.6.1	v6FullRoute.
v6HalfFullPivot	*integer*	Move Pivot v6Half to v6Full.
v6HalfFullRoute	*integer*	Move Routes v6Half to v6Full.

v6HalfRoute	*L3AlpmStatsRouteType* see 2.1620.6.1	v6HalfRoute.

2.1620.6.1 L3AlpmStatsRouteType

bucketCreateFailWithSwap	*integer*	Bucket Create Fail with Swap.
bucketCreateFailWithoutSwap	*integer*	Bucket Create Fail Without Swap.
[deleteMerges]	*integer*	Delete Merge.
[deleteMergesFail]	*integer*	Delete Merges Fail.
[deleteMergesToChild]	*integer*	Delete Merges to Child.
[deleteMergesToChildFail]	*integer*	Delete Merges to Child Fail.
[deleteMergesToChildFail-Node]	*integer*	Delete Merge to Child Fail Node.
[deleteMergesToParent]	*integer*	Delete Merges to Parent.
[deleteMergesToParentFail]	*integer*	Delete Merges to Parent Fail.
[deleteMergesToParentFail-Node]	*integer*	Delete Merges to Parent Fail Node.
[deleteMergesToParentFail-Tcam]	*integer*	Delete Merges to Parent Fail Tcam.
[deleteMergesToParentNon-Pivot]	*integer*	Delete Merges to Parent Non Pivot.
[deleteMergesToParentPivot]	*integer*	Delete Merges to Parent Pivot.
[splitMerges]	*integer*	Splits Merges.
[splitMergesFail]	*integer*	Split Merges Fail.
[splitMergesToChild-ExistingPivot]	*integer*	Split Merges Child Existing Pivot.
[splitMergesToChild-ExistingPivotFail]	*integer*	Split Merges to Child Fail.
[splitMergesToChildSplit-Pivot]	*integer*	Split Merges to Child Split Pivot.
[splitMergesToChildSplit-PivotFail]	*integer*	Split Merge Child Split Pivot.
[splitMergesToParent]	*integer*	Split Merges to Parent.
[splitMergesToParentFail]	*integer*	Split Merge to Parent Fail.
[splitMergesToParentFail-Node]	*integer*	Split Merge to Parent Fail Node.
[splitMergesToParentFail-Tcam]	*integer*	Split Merge to Parent Fail Tcam.
[splitMergesToParentNon-Pivot]	*integer*	Split Merges to Parent Non Pivot.
[splitMergesToParentPivot]	*integer*	Split Merges to Parent Pivot.
splits	*integer*	Splits Stats.
splitsByBucket-Redistribution	*integer*	Splits by Bucket Redistribution.
splitsByCount	*integer*	Splits by Count.
splitsByRedistribution	*integer*	Splits by Redistribution.
splitsFail	*integer*	Splits Fail.
splitsFailTcam	*integer*	Splits Fail Tcam.

2.1621 show platform trident l3 software alpm-table routes-v6 [...]

revision 2

see 2.1620

2.1622 show platform trident l3 software ecmp

simpleUcastEcmpRange	*table(string) = simpleUcastEcmpBlocks* see 2.1622.1	A mapping of ECMP Range to ECMP Blocks.

2.1622.1 simpleUcastEcmpBlocks

ecmpBlockDetail	*list of simpleUcastEcmpBlockDetails* see 2.1622.1.1	A mapping of ECMP Blocks to ECMP group ID.
ecmpFreeEntries **	*integer*	Number of free entries. **Since: 4.23.0
ecmpRangeMaxId	*integer*	Maximum ID of ECMP range.
ecmpRangeMinId	*integer*	Minimum ID of ECMP range.

2.1622.1.1 simpleUcastEcmpBlockDetails

ecmpBlockSize	*integer*	ECMP block size.
[ecmpGrpId]	*integer*	ECMP group ID.
ecmpId	*integer*	ECMP ID.
[shadowEcmpId]	*integer*	ECMP shadow ID.

2.1623 show platform trident l3 software host-table [...]

[bankEntriesList]	*list of HostBankBucketInfo* see 2.1623.1	Status and usage of each host bank entry.
[banks]	*table(numeric string) = HostBankInfo* see 2.1623.2	Host banks, keyed by logical bank ID.
[fwdTableMode]	*integer*	Forwarding Mode.
[hostTableEntries]	*integer*	Entries Allocated.
[hostTableSize]	*integer*	Size of the host table.
[hostsV4]	*integer*	Number of IPv4 unicast hosts.
[hostsV6]	*integer*	Number of IPv6 unicast hosts.
[mroutesV4]	*integer*	Number of IPv4 multicast hosts.
[mroutesV6]	*integer*	Number of IPv6 multicast hosts.

2.1623.1 HostBankBucketInfo

buckets	*table(numeric string) = HostBucketInfo* see 2.1623.1.1	Host buckets, keyed by bucket ID.
[logicalBank]	*integer*	Logical Bank ID.
[physicalBank]	*integer*	Physical Bank ID.
[status]	*string*	Message if bank is unused or no buckets in use.

2.1623.1.1 HostBucketInfo

entries	*table(numeric string) = HostBucketEntryInfo* see 2.1623.1.1.1	Host bucket entries, keyed by entry ID.
state	*string*	Bucket State.

2.1623.1.1.1 HostBucketEntryInfo

bucketType	*enum: v6Mc | v4Mc | v6Uc | v4Uc*	bucket type.
[grp]	*string*	Group.
host	*string*	Host.
hwEntry	*string*	Hardware entry position.
[src]	*string*	Source.
[vlan]	*integer*	VLAN ID.
vrf	*integer*	VRF ID.

2.1623.2 HostBankInfo

hostsV4	*integer*	Number of IPv4 hosts.
hostsV6	*integer*	IPv6 hosts.
mroutesV4	*integer*	IPv4 multicast routes.
physicalBank	*integer*	Physical Bank ID.
v4McastEntries	*integer*	Number of IPv4 multicast routes.

v6UcastEntries	*integer*	Number of IPv6 hosts.

2.1624 show platform trident l3 software interfaces tunnel decap [...]

tunnels	*table(numeric string) = L3ShwL3IntfTunnelEntry* see 2.1624.1	Individual L3 tunnel keyed by tunnel ID.

2.1624.1 L3ShwL3IntfTunnelEntry

destinationIp	*IP address*	Destination IP address.
entryId	*integer*	Table entry index.
grePayloadP4	*integer*	GRE Payload IPv4.
grePayloadP6	*integer*	GRE Payload IPv6.
iif	*integer*	L3 IIF entryId.
ipHeader	*string*	Ip header.
protocol	*string*	Protocol.
sourceIp	*IP address*	Source IP address.
tunnelType	*string*	Tunnel Type.

2.1625 show platform trident l3 software interfaces tunnel encap [...]

tunnels	*table(numeric string) = L3ShwEgrIpIntfTunnelEntry* see 2.1625.1	Individual EGR tunnel keyed by tunnel ID.

2.1625.1 L3ShwEgrIpIntfTunnelEntry

destinationIp	*IP address*	Destination IP address.
dmac **	*MAC address*	Destionation Mac address. **Since: 4.26.2
dscp	*integer*	DSCP.
ecn	*integer*	ECN.
entryId	*integer*	Table entry index.
entryType	*string*	entryType.
sourceIp	*IP address*	Source IP address.
timeToLive	*integer*	Time To Live.
tunnelType	*string*	Tunnel Type.

2.1626 show platform trident l3 software l3-iif-profile

iifProfiles	*table(numeric string) = IifTableRow* see 2.1626.1	A mapping of IIF Profiles, keyed by their index.

2.1626.1 IifTableRow

urpfDefaultRouteCheck	*boolean*	Perform unicast RPF check on default routes in the DEFIP table.
urpfMode	*enum: loose | disable | strict*	Controls the type of unicast RPF checks that are enabled.
v4L3Enable	*boolean*	IPv4 unicast routing is enabled for this SVP/SVP-LAG.
v4McL3Enable	*boolean*	IPv4 multicast routing is enabled from this SVP/SVP-LAG.
v4UnknownMcToCpu	*boolean*	Unknown IPv4 Multicast (IPMC miss) is sent to the CPU.
v6L3Enable	*boolean*	IPv6 unicast routing is enabled for this SVP/SVP-LAG.
v6McL3Enable	*boolean*	IPv6 multicast routing is enabled from this SVP/SVP-LAG.
v6UnknownMcToCpu	*boolean*	Unknown IPv6 Multicast (IPMC miss) is sent to the CPU.

2.1627 show platform trident l3 software lpm-table [...]

[l3LpmTable]	*L3LpmTableRoutes* see 2.1627.2	List of LPM table entries.
[l3LpmTableIndexRanges]	*L3LpmTableIndexRanges* see 2.1627.1	List of LPM table index ranges.
[l3LpmTableSummary]	*L3LpmTableSummary* see 2.1627.3	LPM table summary.

2.1627.1 L3LpmTableIndexRanges

routeTypes	*table(string) = L3LpmIndexRange* see 2.1627.1.1	Index ranges, keyed by IP route type.

2.1627.1.1 L3LpmIndexRange

prefixLengths	*table(numeric string) = L3LpmIndexRangeEntry* see 2.1627.1.1.1	Index ranges, keyed by prefix length.

2.1627.1.1.1 L3LpmIndexRangeEntry

[actualEnd]	*integer*	(IPv6 full size only) Actual ending entry for this range.
[actualStart]	*integer*	(IPv6 full size only) Actual starting entry for this range.
end	*integer*	Ending entry for this range.
start	*integer*	Starting entry for this range.

2.1627.2 L3LpmTableRoutes

routeTypes	*table(string) = L3LpmRoute* see 2.1627.2.1	Route data collections, keyed by route type.

2.1627.2.1 L3LpmRoute

entries	*table(numeric string) = L3LpmRouteEntry* see 2.1627.2.1.1	Route data, keyed by entry index into LPM table.

2.1627.2.1.1 L3LpmRouteEntry

routes	*list of L3LpmRouteData* see 2.1627.2.1.1.1	Route data for this entry index. IPv4 may have multiple.

2.1627.2.1.1.1 L3LpmRouteData

[pairedEntry]	*integer*	(IPv6 full only) Paired entry index into LPM table.
[position]	*enum: right | left*	(IPv4 only) Route position (left or right).

route	*IP address prefix*	Route IP prefix.
vrf	*integer*	Route VRF Id.

2.1627.3 L3LpmTableSummary

lpmTableMode	*integer*	LPM table mode.
maxLpmTableEntries	*integer*	Maximum possible number of entries in LPM table.
routeTypes	*table(string) = L3LpmSummaryRouteEntry* see 2.1627.3.1	Summary of route type data, keyed by route type.
tcamEffectiveSize	*integer*	LPM table effective TCAM size.
tcamSize	*integer*	LPM table TCAM size.
urpfEnabled	*integer*	LPM table uRPF enabled.

2.1627.3.1 L3LpmSummaryRouteEntry

numEntries	*integer*	Number of entries in LPM table for this route type.
[numHalfEntries]	*integer*	(IPv4 Only) Number of half full IPv4 entries.
numMoves	*integer*	Number of moved routes in LPM table for this route type.
numRoutes	*integer*	Number of routes in LPM table for this route type.

2.1628 show platform trident l3 software mgroups [...]

groups	*table(numeric string) = MGroupModel* see 2.1628.1	A mapping of group ID to multicast groups.

2.1628.1 MGroupModel

[hiGig]	*boolean*	Multicast group has HiGig ports.
modules	*table(numeric string) = PortListModel* see 2.1628.1.1	A mapping of FAP ID to ports in multicast group.
[programmed]	*boolean*	Programmed in hardware.
[removeSGLP]	*boolean*	Remove Source Global Logical Port from Outgoing Interface List.
[tagged]	*boolean*	Group is tagged.

2.1628.1.1 PortListModel

l2Ports	*list of L2PortModel* see 2.1628.1.1.1	L2 ports per multicast group per module ID.
l3Ports	*list of L3PortModel* see 2.1628.1.1.2	L3 ports per multicast group per module ID.

2.1628.1.1.1 L2PortModel

[interface]	*interface name*	Interface.
[logId]	*integer*	Logical port ID.
[mmuId]	*integer*	MMU port ID.
[phyId]	*integer*	Physical port ID.
[port]	*enum: hiGig | cpu | allPhyPorts*	Port type.

2.1628.1.1.2 L3PortModel

interface	*interface name*	Interface.
[logId]	*integer*	Logical port ID.
[mmuId]	*integer*	MMU port ID.
nextHops	*list of NextHopModel* see 2.1628.1.1.2.1	Next hops for L3 port.
[phyId]	*integer*	Physical port ID.
[replListId]	*integer*	Replication list ID.
[switchcardIntf] **	*interface name*	Switchcard Interface. **Since: 4.24.2

2.1628.1.1.2.1 NextHopModel

[nextHopId]	*integer*	Next hop ID.
nextHopTunnel **	*boolean*	Next hop is a tunnel. **Since: 4.24.0

`vlanId`	*integer*	VLAN ID.
`[vlanTagged]`	*boolean*	Next hop is tagged.

2.1629 show platform trident l3 software next-hops [...]

revision 2

[l3SoftwareNextHopsHwHer] **	*L3SoftwareNextHopsHwHer* see 2.1629.1	Head end replication next hop table info. **Since: 4.22.0
[l3SoftwareNextHopsMcast]	*L3SoftwareNextHopsMcast* see 2.1629.2	Multicast next hop table info.
[l3SoftwareNextHopsSdTag]	*L3SoftwareNextHopsSdTag* see 2.1629.3	SdTag next hop table info.
[l3SoftwareNextHopsUcast]	*L3SoftwareNextHopsUcast* see 2.1629.4	Unicast next hop table info.

2.1629.1 L3SoftwareNextHopsHwHer

hwHerNHTable	*table(numeric string) = HwHerNH* see 2.1629.1.1	Dictionary of her next hop identifier to next hop Table.

2.1629.1.1 HwHerNH

[dvpIndex]	*integer*	Hardware destination index.
[interface]	*string*	HER next hop interface name:: Interface name will be full name with exception of the following special names : HiGigLport, VxlanFlood, Recirc, VxlanPeer, EcmpArp, VlanFlood.
macAddress	*MAC address*	HER next hop MAC address.
[moduleId]	*integer*	HER module id.
[moduleIdFab]	*integer*	HER module id for fabric chip.
[moduleIdFp]	*integer*	HER module id for front panel chip.
[nextHopType]	*enum: cpu | multicast | remoteHost | flood | her | flow | cpuAndDrop | localHost | cpuSlow | drop | port | lag | cpuEcmpArp | cpuAndDropArpRequired | fp*	HER next hop type.
[nexthopUnderlay]	*boolean*	Next hop is in underlay.
[nhAdjIndex]	*integer*	HER adjacency index.
[pktRewriteFab]	*boolean*	Status of packet rewrite for fabric chip.
[pktRewriteFp]	*boolean*	Packets are rewritten for front panel chip.
[portId]	*integer*	HER port id.
[portIdFab]	*integer*	HER port info for fabric chip.
[portIdFp]	*integer*	HER port info for front panel chip.
[refCount]	*integer*	HER reference count of the next-hop.
vlanId	*integer*	HER VLAN id.
[vxlanEnabled]	*boolean*	Vxlan is enabled:.

2.1629.2 L3SoftwareNextHopsMcast

mcastVlanIdTable	*table(numeric string) = McastVlanIdTable* see 2.1629.2.1	A mapping of nexthop ID to nexthop entry.

2.1629.2.1 McastVlanIdTable

[interface] **	*interface name*	Multicast next hop interface name. **Since: 4.22.0
refCount	*integer*	Multicast refcount for the next hop.
[taggingEnabled]	*boolean*	Status of tagging for the multicast next hop.
vlanId	*integer*	Multicast Vlan id.

2.1629.3 L3SoftwareNextHopsSdTag

sdTagNextHops	*table(numeric string) = SdTagNextHopTable* see 2.1629.3.1	Dictionary keyed at sdTag next-hop identifier to next-hop table.

2.1629.3.1 SdTagNextHopTable

dvpIndex	*integer*	Hardware destination index.
interface	*interface name*	interface name for the next hop.
[taggingEnabled]	*boolean*	Status of tagging for the SdTag next hop.
vlanId	*integer*	Vlan id.

2.1629.4 L3SoftwareNextHopsUcast

[l3SoftwareNextHopsHierUcastEcmp] **	*L3SoftwareNextHopsHierUcastEcmp* see 2.1629.4.1	Hierarchical ECMP Unicast next hop. **Since: 4.33.1
l3SoftwareNextHopsUcastEcmp	*L3SoftwareNextHopsUcastEcmp* see 2.1629.4.2	ECMP Unicast next hop.
l3SoftwareNextHopsUcastSimple	*L3SoftwareNextHopsUcastSimple* see 2.1629.4.3	Simple Unicast next hop Table.

2.1629.4.1 L3SoftwareNextHopsHierUcastEcmp

hierEcmpTable	*table(numeric string) = HierEcmpUcastEcmpId* see 2.1629.4.1.1	Unicast ECMP table dictionary keyed with Ecmp Id.

2.1629.4.1.1 HierEcmpUcastEcmpId

arpResolverNeeded	*boolean*	Boolean to indicate if Arp resolver is needed.
blockSize	*integer*	Number of ECMP next-hops.
ecmpType	*string*	Type of the Ecmp.

hierEcmpNextHops	*list of HierEcmpUcastNextHop* see 2.1629.4.1.1.1	Hierarchical ECMP table list.
hierEcmpNextHopsDetail	*list of HierEcmpUcastNext-HopDetail* see 2.1629.4.1.1.2	Hierarchical ECMP detail table list.
[nexthopUnderlay]	*boolean*	Flag indicating if the next hop is in underlay.
nhAdjIndex	*integer*	Adjacency index of the ECMP next hop.
refCount	*integer*	Reference count for the ECMP next hop.
startIndex	*integer*	ECMP start index.

2.1629.4.1.1.1 HierEcmpUcastNextHop

nextHopId	*integer*	Unicast ECMP next hop id.
ulEcmp	*boolean*	Flag indicating if underlay is an ecmp.
ulNextHop	*integer*	Underlay Next Hop Id.
[weight]	*integer*	Repetition count/weight of the fec/adjacency.

2.1629.4.1.1.2 HierEcmpUcastNextHopDetail

bitmapList	*list of integer*	Port bitmap List of ECMP next hop.
nextHopId	*integer*	Unicast ECMP next hop id.

2.1629.4.2 L3SoftwareNextHopsUcastEcmp

ecmpTable	*table(numeric string) = EcmpUcastEcmpId* see 2.1629.4.2.1	Unicast ECMP table dictionary keyed with Ecmp Id.

2.1629.4.2.1 EcmpUcastEcmpId

arpResolverNeeded	*boolean*	Boolean to indicate if Arp resolver is needed.
blockSize	*integer*	Number of ECMP next-hops.
ecmpNextHops	*list of EcmpUcastNextHop* see 2.1629.4.2.1.1	ECMP table list.
ecmpNextHopsDetail	*list of EcmpUcastNextHopDetail* see 2.1629.4.2.1.2	ECMP detail table list.
ecmpType **	*string*	Type of the Ecmp. **Since: 4.33.1
[nexthopUnderlay]	*boolean*	Flag indicating if the next hop is in underlay.
nhAdjIndex	*integer*	Adjacency index of the ECMP next hop.
refCount	*integer*	Reference count for the ECMP next hop.
startIndex	*integer*	ECMP start index.

2.1629.4.2.1.1 EcmpUcastNextHop

[dvp] **	*integer*	DVP index. **Since: 4.20.0
nextHopId	*integer*	Unicast ECMP next hop id.
[weight]	*integer*	Repetition count/weight of the fec/adjacency.

2.1629.4.2.1.2 EcmpUcastNextHopDetail

bitmapList	*list of integer*	Port bitmap List of ECMP next hop.
[dvp] **	*integer*	DVP index. **Since: 4.20.0
nextHopId	*integer*	Unicast ECMP next hop id.

2.1629.4.3 L3SoftwareNextHopsUcastSimple

simpleUcastNHTable	*table(numeric string) = SimpleUcastNH* see 2.1629.4.3.1	Dictionary of non-ECMP next hop identifier to next hop Table.

2.1629.4.3.1 SimpleUcastNH

[dvpIndex] **	*integer*	Hardware destination index. **Since: 4.18.0
[interface]	*string*	Unicast Non-ECMP next hop interface name:: Interface name will be full name with exception of the following special names : HiGigLport, VxlanFlood, Recirc, VxlanPeer, EcmpArp, VlanFlood.
macAddress	*MAC address*	Unicast Non-ECMP next hop mac address.
[moduleId]	*integer*	Unicast Non-ECMP module id.
[moduleIdFab] **	*integer*	Unicast Non-ECMP module id for fabric chip. **Since: 4.22.0
[moduleIdFp] **	*integer*	Unicast Non-ECMP module id for front panel chip. **Since: 4.22.0
[nextHopType]	*enum: cpu | multicast | remoteHost | flood | her | flow | cpuAndDrop | localHost | cpuSlow | drop | port | lag | cpuEcmpArp | cpuAndDropArpRequired | fp*	Unicast Non-ECMP next hop type.
[nexthopUnderlay] **	*boolean*	Flag indicating if the next hop is in underlay. **Since: 4.18.0
[nhAdjIndex]	*integer*	Unicast Non-ECMP adjacency index.
[pktRewriteFab] **	*boolean*	Status of packet rewrite for fabric chip. **Since: 4.22.0

[pktRewriteFp] **	*boolean*	Status of packet rewrite for front panel chip. **Since: 4.22.0
[portId]	*integer*	Unicast Non-ECMP port id.
[portIdFab] **	*integer*	Unicast Non-ECMP port info for fabric chip. **Since: 4.22.0
[portIdFp] **	*integer*	Unicast Non-ECMP port info for front panel chip. **Since: 4.22.0
[refCount]	*integer*	Unicast reference count of the next-hop.
vlanId	*integer*	Unicast Non-ECMP Vlan id.
[vxlanEnabled] **	*boolean*	Vxlan is enabled:. **Since: 4.22.0

2.1630 show platform trident l3 software routes [...]

[cmdErr] **	*string*	Error Message. **Since: 4.20.0
[hostTable]	*StrataL3Vrfs* see 2.1630.1	Host route table info.
[lpmTable]	*StrataL3Vrfs* see 2.1630.1	LPM route table info.

2.1630.1 StrataL3Vrfs

vrfs	*table(numeric string) = RoutesPerVrfEntry* see 2.1630.1.1	A mapping of vrf id to routes.

2.1630.1.1 RoutesPerVrfEntry

routes	*table(string) = StrataL3RouteEntry* see 2.1630.1.1.1	A mapping of prefix to route entry.

2.1630.1.1.1 StrataL3RouteEntry

classId	*integer*	Class ID marking for packets in ingress pipeline.
ecmp	*boolean*	Flag indicating if route has ECMP nexthops.
[ecmpGroupId]	*integer*	ECMP nexthop ID.
[ecmpGroupSize]	*integer*	ECMP group size.
entryId	*integer*	Entry ID.
[hit]	*boolean*	Flag indicating if the traffic hit the route.
[nexthopId]	*integer*	Nexthop ID.
[nexthops]	*table(numeric string) = SimpleUcastNH* see 2.1629.4.3.1	A mapping of nexthop ID to nexthop.
[position]	*integer*	Position in the TCAM table.
[subBucket] **	*integer*	Indicate sub bucket pointer in shared SRAM. **Since: 4.22.1

2.1631 show platform trident l3 software routes-v6 [...]

see 2.1630

2.1632 show platform trident l3 software routing-vlan [...]

perVlanEntries	*list of PerVlanEntry* see 2.1632.1	List of per vlan routing entries.

2.1632.1 PerVlanEntry

entryId	*string*	Entry id.
macAddress	*MAC address*	Mac address.
macAddressMask	*MAC address*	Mac adress mask.
vlanId	*integer*	Vlan id.
vlanMask	*string*	Vlan mask.

2.1633 show platform trident l3 software urpf exception-list [...]

unsupportedRules	*list of UnsupportedAclRule* see 2.1633.1	ACL rules not supported by hardware.
urpfExceptions	*list of UrpfException* see 2.1633.2	uRPF exceptions.

2.1633.1 UnsupportedAclRule

aclName	*string*	ACL name.
aclType	*enum: IPv6 | IPv4*	ACL type.
unsupportedRuleId	*integer*	ACL rule id, not supported by hardware.

2.1633.2 UrpfException

aclName	*string*	ACL name.
aclType	*enum: IPv6 | IPv4*	ACL type.
[fapId] **	*integer*	Chip FAP ID. **Since: 4.24.2
hardwareStatus	*enum: Programmed | Not Programmed*	Programmed in hardware.
interface	*interface name*	Interface.
[memberInterface]	*interface name*	Member interface.
[modId]	*integer*	Chip module id (legacy attribute, use fapId instead).

2.1634 show platform trident l3 summary

revision 3

[alpm]	*AlpmTableState* see 2.1620.1	ALPM table.
[alpmMcastRoutesV4] **	*integer*	Number of IPv4 multicast ALPM routes. **Since: 4.32.0
configRsvdHostsV4	*integer*	Number of configured and reserved IPv4 hosts.
configRsvdHostsV6	*integer*	Number of configured and reserved IPv6 hosts.
configRsvdMcastRoutesV4	*integer*	Number of configured and reserved IPv4 multicast routes.
configRsvdMcastRoutesV6	*integer*	Number of configured and reserved IPv6 multicast routes.
defipWideTcamTableEntries **	*integer*	Number of Defip Multicast Tcam entries in use. **Since: 4.33.0
dlbEcmpFlowSetSize **	*integer*	DLB flowset size. **Since: 4.35.2
dlbEnabled **	*boolean*	Whether DLB(Dynamic Load Balancing) is enabled. **Since: 4.35.2
dlbSupported **	*boolean*	Whether DLB(Dynamic Load Balancing) is supported. **Since: 4.35.2
fapType	*string*	Front panel chip model.
fapTypesFabric	*list of string*	List of fabric chip models.
fastdropMcastRoutes	*integer*	Number of fastdrop multicast routes.
forwardingMode	*string*	Forwrading mode.
hostMcastRoutesV4	*integer*	Number of IPv4 multicast routes.
hostMcastRoutesV6	*integer*	Number of IPv6 multicast routes.
hostTableMode	*integer*	Host table mode.
hostsV4	*integer*	Number of IPv4 hosts.
hostsV6	*integer*	Number of IPv6 hosts.
ingDvpEntries	*integer*	Number of ingress DVP table entries in use.
ipTunnels	*integer*	Number of IP tunnels in use.
ipV4Routes	*integer*	Number of IPv4 routes (hosts+lpm).
ipV6Routes	*integer*	Number of IPv6 routes (hosts+lpm).
l2mcTablesizeL2	*integer*	L2MC table size L2.
l2mcTablesizeL3	*integer*	L2MC table size L3.
l3Intf	*integer*	Number of L3 interfaces.
lpmEntriesV4	*integer*	Number of LPM IPv4 entries in use.
lpmEntriesV6Full	*integer*	Number of LPM IPv6 full entries in use.
lpmEntriesV6Half	*integer*	Number of LPM IPv6 half entries in use.
lpmHalfFullEntries	*integer*	Number of LPM half full entries in use.
lpmMode	*integer*	LPM table mode.
[maxAlpmMcastRoutesV4] **	*integer*	Maximum possible number of IPv4 multicast ALPM routes. **Since: 4.32.2

maxDefipWideTcamTable-Entries **	*integer*	Maximum number of Defip Multicast Tcam entries. **Since: 4.33.0
maxDlbEcmpSetSize **	*integer*	Maximum DLB eligible ECMP group size. **Since: 4.35.2
maxEcmpRoutes	*integer*	Maximum possible number of ECMP paths/routes.
maxHosts	*integer*	Maximum possible number of IPv4 and IPv6 hosts.
maxIngDvpEntries	*integer*	Maximum possible number of ingress DVP table entries.
maxIpTunnels	*integer*	Maximum possible number of IP tunnels.
maxL3Intf	*integer*	Maximum possible number of L3 interfaces.
maxLpmEntries	*integer*	Maximum possible number of LPM IPv4 and IPv6 entries.
maxMcastGroups	*integer*	Maximum possible number of multicast replication groups.
maxMyStationTcamTable-Entries	*integer*	Maximum number of MyStationTcamTable entries.
[maxNextHopEcmpEntries]	*integer*	Maximum possible number of NextHop ECMP entries in Trident2.
[maxNextHopEcmpSets]	*integer*	Maximum possible number of NextHop ECMP groups in Trident2.
maxNextHopEntries	*integer*	Maximum possible number of NextHop unicast/multicast entries.
mcastGroups	*integer*	Number of multicast replication groups in use.
mcastModules	*list of McastModule* see 2.1634.1	Multicast modules.
mcastRoutesV4	*integer*	Number of IPv4 multicast routes.
mcastRoutesV6	*integer*	Number of IPv6 multicast routes.
mcastUnprogrammedRoutes	*table(string) = integer*	Multicast unprogrammed IPv4 routesstatistics. Key is VRF, value is the numberof unprogrammed multicast routes in thatVRF.
mcastUnprogrammedRoutesV6	*table(string) = integer*	Multicast unprogrammed IPv6 routesstatistics. Key is VRF, value is the numberof unprogrammed multicast routes in thatVRF.
mcastV4Enabled	*boolean*	Status of IPv4 multicast routing.
mcastV6Enabled	*boolean*	Status of IPv6 multicast routing.
mplsEnabled	*boolean*	Status of MPLS routing.
myStationTcamTableEntries	*integer*	Number of MyStationTcamTable entries in use.
[nextHopEcmpEntries]	*integer*	Number of NextHop ECMP entries in Trident2.
[nextHopEcmpSets]	*integer*	Number of NextHop ECMP groups in use in Trident2.
nextHopL3MCEntries	*integer*	Number of NextHop L3MC entries in use.
nextHopMcastEntries	*integer*	Number of NextHop multicast entries in use.

nextHopUcastEntries	*integer*	Number of NextHop unicast entries in use.
numDlbEnabledEcmpSets **	*integer*	Number of DLB enabled ECMP groups. **Since: 4.35.2
numUnprogrammedVrrp	*integer*	Unprogrammed VRRP group count.
[overlayInterfaceEntries]	*integer*	Number of interface entries in Overlay region.
[overlayInterfaceEntries-Reserved]	*integer*	Number of interface entries reserved for the Overlay region.
[overlayMaxNextHopEcmp-Entries]	*integer*	Maximum possible number of NextHop ECMP entries in Overlay region.
[overlayMaxNextHopEcmpSets]	*integer*	Maximum possible number of NextHop ECMP groups in Overlay region.
[overlayNextHopEcmpEntries]	*integer*	Number of NextHop ECMP entries in Overlay region.
[overlayNextHopEcmpEntries-MaxId]	*integer*	Maximum entry Id of ECMP Nexthops in Overlay region.
[overlayNextHopEcmpEntries-MinId]	*integer*	Minimum entry Id of ECMP Nexthops in Overlay region.
[overlayNextHopEcmpSets]	*integer*	Number of NextHop ECMP groups in usein Overlay region.
[overlayNextHopEcmpSetsMax-Id]	*integer*	Maximum group Id of NextHop ECMP groups in Overlay region.
[overlayNextHopEcmpSetsMin-Id]	*integer*	Minimum group Id of NextHop ECMP groups in Overlay region.
[overlayNexthopBanks]	*integer*	Number of banks allocated to overlay Nexthops.
[overlayNexthopEntries]	*integer*	Number of NextHop entries in overlay region.
[overlayNexthopEntries-Reserved]	*integer*	Number of NextHop entries reserved for the overlay region.
[perVlanRoutingEnabled]	*boolean*	Status of per vlan routing.
platformAdjSharing	*boolean*	Status of Platform Adjacency sharing.
reservedMcastGroups	*integer*	Number of reserved multicast replication groups in use.
routeDeletionDelay	*floating point number*	Route deletion delay.
rsvdHostsV4	*integer*	Number of reserved IPv4 hosts.
rsvdHostsV6	*integer*	Number of reserved IPv6 hosts.
rsvdMcastRoutesV4	*integer*	Number of reserved IPv4 multicast routes.
rsvdMcastRoutesV6	*integer*	Number of reserved IPv6 multicast routes.
[sdtagNexthopEntries]	*integer*	Number of SDTag Nexthop entries.
ucastV4Enabled	*boolean*	Status of IPv4 unicast routing.
ucastV6Enabled	*boolean*	Status of IPv6 unicast routing.
[underlayInterfaceEntries]	*integer*	Number of interface entries in Underlay region.
[underlayInterfaceEntries-Reserved]	*integer*	Number of interface entries reserved for the Underlay region.
[underlayMaxNextHopEcmp-Entries]	*integer*	Maximum possible number of NextHop ECMP entries in Underlay region.
[underlayMaxNextHopEcmp-Sets]	*integer*	Maximum possible number of NextHop ECMP groups in Underlay region.
[underlayNextHopEcmp-Entries]	*integer*	Number of NextHop ECMP entries in Underlay region.

[underlayNextHopEcmp-EntriesMaxId]	*integer*	Maximum entry Id of ECMP Nexthops in Underlay region.
[underlayNextHopEcmp-EntriesMinId]	*integer*	Minimum entry Id of ECMP Nexthops in Underlay region.
[underlayNextHopEcmpSets]	*integer*	Number of NextHop ECMP groups in use in Underlay region.
[underlayNextHopEcmpSets-MaxId]	*integer*	Maximum group Id of NextHop ECMP groups in Underlay region.
[underlayNextHopEcmpSets-MinId]	*integer*	Minimum group Id of NextHop ECMP groups in Underlay region.
[underlayNexthopBanks]	*integer*	Number of banks allocated to underlay Nexthops.
[underlayNexthopEntries]	*integer*	Number of NextHop entries in underlay region.
[underlayNexthopEntries-Reserved]	*integer*	Number of NextHop entries reserved for the underlay region.
unprogrammedV4Routes	*integer*	Number of unprogrammed IPv4 routes.
unprogrammedV6Routes	*integer*	Number of unprogrammed IPv6 routes.
urpfEnabled	*boolean*	Status of uRPF.

2.1634.1 McastModule

module	*integer*	Module ID.
[replHeadEntries]	*integer*	Number of replication head entries in use.
replHeadEntriesPerPipe	*table(string) = integer*	ReplHead entries in use per pipe.
replHeadMaxEntries	*integer*	Maximum number of replication head entries.
[replListEntries]	*integer*	Number of replication list entries in use.
replListEntriesPerPipe	*table(string) = integer*	ReplList entries in use per pipe.
replListMaxEntries	*integer*	Maximum number of replication list entries.

2.1635 show platform trident lag [...]

lags	*table(string) = LagDetailSingleEntry* see 2.1635.1	LAG details keyed by LAG ID.

2.1635.1 LagDetailSingleEntry

inHardware	*boolean*	Hardware or software data is stored in.
[interfaces]	*list of LagDetailSingle-InterfaceEntry* see 2.1635.1.1	Interfaces in the LAG.
ports	*integer*	Number of ports in LAG stored in software.
[portsHardware]	*integer*	Number of ports in LAG stored in hardware.
[trunkHardware]	*integer*	LAG ID in hardware.

2.1635.1.1 LagDetailSingleInterfaceEntry

[interface]	*string*	Front panel interface ID.
[modId]	*integer*	Switchcard module ID in software.
[modIdHardware]	*integer*	Switchcard module ID in hardware.
[portId]	*integer*	Switchcard port ID in software.
[portIdHardware]	*integer*	Switchcard port ID in hardware.

2.1636 show platform trident lag detail [...]

lags	*table(string) = LagDetailSingleEntry* see 2.1635.1	LAG details keyed by LAG ID.

2.1637 show platform trident lag nonucast-trunk-block-mask l3mc [...]

linecards	*table(string) = NonUcastTrunkBlockMaskTbl* see 2.1637.1	NonUcastTrunkBlockMask table grouped by linecards.

2.1637.1 NonUcastTrunkBlockMaskTbl

entries	*table(numeric string) = NonUcastTrunkBlockMaskEntry* see 2.1637.1.1	NonUcastTrunkBlockMask table entries.

2.1637.1.1 NonUcastTrunkBlockMaskEntry

interfaces	*list of string*	Interfaces in NonUcastTrunkBlockMask entry.

2.1638 show platform trident lag software

currentLagType	*enum: software | hardware*	Current LAG Type.
initialLagType	*enum: software | hardware*	Initial LAG Type.
transitionType	*enum: immediate | delayed*	Transition Type.

2.1639 show platform trident lanz coprocessor status

chips	*table(string) = CopStatusEntry* see 2.1639.1	Coprocessor status keyed by chip name.

2.1639.1 CopStatusEntry

chipInfoEntryList	*list of ChipInfoEntry* see 2.1639.1.1	List of Chip info entry.
configEntryList	*list of ConfigEntry* see 2.1639.1.2	List of Config entry.
csrEntryList	*list of CsrEntry* see 2.1639.1.3	List of CSR entry.
statusEntryList	*list of StatusEntry* see 2.1639.1.4	List of Status entry.
timeSyncEntryList	*list of TimeSyncEntry* see 2.1639.1.5	List of Time sync entry.

2.1639.1.1 ChipInfoEntry

cpuPort	*integer*	Cpu Port id.
portQueueInfo	*table(numeric string) = PortQueueInfoEntry* see 2.1639.1.1.1	Dict of Port Queue Info keyed by MMU port number.

2.1639.1.1.1 PortQueueInfoEntry

mCastQBase	*integer*	Start of Multicast queue.
mCastQCount	*integer*	Count of Multicast queue.
uCastQBase	*integer*	Start of Unicast queue.
uCastQCount	*integer*	Count of Unicast queue.

2.1639.1.2 ConfigEntry

cpuPortProfiles	*table(numeric string) = HighLowCellEntry* see 2.1639.1.2.1	CPU port profile dict keyed by port number.
dmaRecords	*integer*	Number of DMA records.
dmaSize	*integer*	Size of DMA buffer in bytes.
ethernetFabricPortProfiles	*table(numeric string) = HighLowCellEntry* see 2.1639.1.2.1	Port profile dict keyed by port number.
[fabricToSubportIdMap] **	*table(numeric string) = integer*	Subport id dict keyed by fabric port number. **Since: 4.34.1
genId **	*integer*	Identifier for a configuration update. **Since: 4.35.0
[invalidSubport] **	*integer*	Invalid subport id. **Since: 4.34.1
mirroringDisabled	*table(numeric string) = integer*	MMU port Entry dict keyed by port number.

mmuToLogicalPortMap **	*table(numeric string) = integer*	Logical port dict keyed by MMU port. **Since: 4.32.2
mtpAddress	*string*	EMIRROR_CONTROLX address for mirroring.
numUpdAgg	*integer*	Number of aggressive update messages.
portConfig	*table(numeric string) = integer*	Port config dict keyed by port number.
qlenUpdAggInterval	*integer*	Time between aggressiveupdate messages in microseconds.
qlenUpdInterval	*integer*	Time between update messages in microseconds.
[subportConfig] **	*table(numeric string) = integer*	Channelized port config dict keyed by subport id. **Since: 4.34.1

2.1639.1.2.1 HighLowCellEntry

highCells	*integer*	High cells.
lowCells	*integer*	Low cells.

2.1639.1.3 CsrEntry

crCfgChg	*boolean*	Config register: config needs to be updated.
crEnable	*boolean*	Config register: toggles LANZ.
crStatusUpdate	*integer*	Config register: Status was updated.
crTrace	*boolean*	Config register: toggles tracing.
dmaHeadPtr	*string*	DMA head pointer.
dmaReadPtr	*string*	Position of the DMA read pointer.
srCfgChg	*boolean*	Status Register: config was updated.
srInitialized	*boolean*	Status register: indicates run status.
srStatusUpdate	*integer*	Status Register: Status was updated.

2.1639.1.4 StatusEntry

bstStatCnt **	*integer*	Number of times bst_stat is latched. **Since: 4.35.0
dmaWritePtr	*string*	Position of last DMA msg written in bytes.
failedTransferCnt	*integer*	Number of failed transfers.
magicNumber	*string*	Should be 0x4c414e5a.
timestampH	*string*	High order bits of timestamp.
timestampL	*string*	Low order bits of timestamp.

2.1639.1.5 TimeSyncEntry

[hwTs]	*integer*	Current hardware timestamp.
[hwTsToUSec]	*string*	Current hardware timestamp in microseconds.
[noHwTsError]	*string*	Error String when unable to get Timestamp.

[now]	*string*	Current time in UTC.
[numTsUpdateErrors]	*integer*	Total number of errors encountered.
[numTsUpdates]	*integer*	Total number of timestamp updates.
[offset]	*integer*	Time offset in nanoseconds.
[state]	*enum: 3 | 0 | 1 | 2*	Current state of TimeSync: 0 : unknown1 : synchronizing2 : backOff3 : errorDetected.

2.1640 show platform trident lanz hardware status

chips	*table(string) = HwStatusEntry* see 2.1640.1	Hardware Status keyed by chip name.

2.1640.1 HwStatusEntry

freeBstProfiles	*integer*	Number of available new thresholds for Ethernet ports.
freeBstProfilesCpu	*integer*	Number of available new thresholds for Cpu port.
freeBstProfilesFabric	*integer*	Number of available new thresholds for Fabric ports.
interfaces	*table(Interface name) = SingleInterfaceEntry* see 2.1640.1.1	Interface profiles keyed by interface names.
thresholdToBstProfiles	*integer*	Number of thresholds in use for Ethernet ports.
thresholdToBstProfilesCpu	*integer*	Number of thresholds in use for Cpu port.
thresholdToBstProfiles-Fabric	*integer*	Number of thresholds in use for Fabric ports.

2.1640.1.1 SingleInterfaceEntry

highThreshold	*string*	High Threshold.
hwProfile	*string*	Hardware Profile, * Unavailable.

2.1641 show platform trident mac-address-table [...]

see 2.1581

2.1642 show platform trident mac-address-table diff [...]

see 2.1582

2.1643 show platform trident mac-address-table missing [...]

see 2.1583

2.1644 show platform trident mac-traffic-policy hardware-id summary

matchRules	*table(string) = MatchRuleHardwareSummary* see 2.1644.1	A mapping of rule name to hardware ID information.

2.1644.1 MatchRuleHardwareSummary

[aclName]	*string*	Access list name.
[hardwareId]	*integer*	Hardware ID for access list.

2.1645 show platform trident mac-traffic-policy rules status [...]

chips	*table(string) = MacTrafficPolicyRulesChipStatus* see 2.1645.1	A mapping of chip name to status of MAC traffic policy rules.

2.1645.1 MacTrafficPolicyRulesChipStatus

rules	*table(string) = MacTrafficPolicyRuleStatus* see 2.1645.1.1	A mapping of rule name to operational status information.

2.1645.1.1 MacTrafficPolicyRuleStatus

status	*enum: success | failed | notApplicable | inProgress*	Status type.

2.1646 show platform trident mirror index [...]

modules	*table(numeric string) = IndexTable* see 2.1646.1	Dictionary mapping a module ID to the index entries.

2.1646.1 IndexTable

free	*integer*	Free MTP indices.
indexes	*list of IndexRow* see 2.1646.1.1	Index usage information.
totalMtpIndices	*integer*	Total MTP indices.

2.1646.1.1 IndexRow

direction	*string*	Mirror direction.
index	*integer*	Index.
mirrorInterface	*interface name*	Mirror interface.
refs	*integer*	Reference count.

2.1647 show platform trident mirror session [...]

sessions	*table(string) = SessionInfo* see 2.1647.1	Dictionary mapping session name to details.

2.1647.1 SessionInfo

index	*list of SessionInfoRow* see 2.1647.1.1	List of port indices and module ID.
targetIntf	*interface name*	Target interface.

2.1647.1.1 SessionInfoRow

egressIndex	*integer*	Egress port index.
ingressIndex	*integer*	Ingress port index.
module	*integer*	Module ID.

2.1648 show platform trident mmu buffers status

moduleInfo	*table(string) = StrataMmuBufferModel* see 2.1648.1	A mapping between a linecard and MMU data.

2.1648.1 StrataMmuBufferModel

mmuData	*table(numeric string) = StrataMmuInfo* see 2.1648.1.1	A mapping between a MMU ID and MMU data.

2.1648.1.1 StrataMmuInfo

egressSharedCount	*integer*	Egress shared buffer cell usage count.
egressSharedTotal	*integer*	Egress shared buffer cell total count.
egressUsage	*integer*	Egress shared buffer cell usage percentage.
ingressHeadroomCount	*integer*	Ingress Headroom buffer cell usage count.
ingressHeadroomTotal	*integer*	Ingress Headroom buffer cell total count.
ingressHeadroomUsage	*integer*	Ingress Headroom buffer cell usage percentage.
ingressSharedCount	*integer*	Ingress shared buffer cell usage count.
ingressSharedTotal	*integer*	Ingress shared buffer cell total count.
ingressUsage	*integer*	Ingress shared buffer cell usage percentage.

2.1649 show platform trident mmu queue cpu-profile [...]

[availableProfiles]	*list of string*	Available CPU queue profiles.
profileName	*string*	Profile name.
queues	*table(string) = CpuQueueConfig* see 2.1649.1	Queue configs, keyed by their name.

2.1649.1 CpuQueueConfig

reserved	*Reserved* see 2.1649.1.1	The reserved value for this queue.
threshold	*Threshold* see 2.1649.1.2	The threshold value for this queue.

2.1649.1.1 Reserved

isDefault	*boolean*	The reserved value is the system default.
unit	*enum: cells | bytes*	Unit for the reserved value.
value	*integer*	The amount of memory to be reserved.

2.1649.1.2 Threshold

isDefault	*boolean*	The threshold value is the system default.
value	*floating point number*	Dynamic shared memory threshold.

2.1650 show platform trident mmu queue dcn

poolSizeCells	*table(string) = integer*	Mapping from slice name to allocated pool size.

2.1651 show platform trident mmu queue headroom

interfaces	*table(Interface name) = integer*	Available MMU headroom (Cells) for each priority group of an interface.
[poolLimit]	*integer*	Ingress headroom pool size (Cells) for each MMU.

2.1652 show platform trident mmu queue mirror-on-drop

slices	*table(string) = integer*	Allocated MMU mirror-on-drop pool (Cells) for each slice.

2.1653 show platform trident mmu queue mirror-on-drop counters [...]

slices	*table(string) = StrataMmu.Cli.StrataMmuPoolCountersModel* see 2.1653.1	Mapping from linecard to associated mirror-on-drop pool statistics.

2.1653.1 StrataMmu.Cli.StrataMmuPoolCountersModel

itmCounters	*table(string) = StrataMmu.Cli.ItmCountersModel* see 2.1653.1.1	Mapping from pool resource to pool statistics.
slice	*string*	Slice name.

2.1653.1.1 StrataMmu.Cli.ItmCountersModel

droppedPackets	*integer*	Packets not admitted due to pool being full.
sampledPackets	*integer*	Packets admitted to the pool.
xpe	*string*	MMU Ingress XPE key.

2.1654 show platform trident mmu queue mirror-on-drop status [...]

slices	*table(string) = StrataMmu.Cli.InterfaceListOccupancyModel* see 2.1654.1	Mapping from linecard to associated mirror-on-drop pool occupancy.

2.1654.1 StrataMmu.Cli.InterfaceListOccupancyModel

intfListOccupancy	*table(string) = StrataMmu.Cli.StrataMmuPoolOccupancyModel* see 2.1654.1.1	Mapping from interfaces to feature occupancy.
slice	*string*	Slice name.

2.1654.1.1 StrataMmu.Cli.StrataMmuPoolOccupancyModel

intfList	*string*	Interface list.
resourceOccupancy	*table(string) = integer*	Mapping from feature to pool occupancy.

2.1655 show platform trident mmu queue mirror-on-drop watermarks [...]

slices	*table(string) = StrataMmu.Cli.StrataMmuPoolWatermarksModel* see 2.1655.1	Mapping from linecard to associated mirror-on-drop pool watermarks.

2.1655.1 StrataMmu.Cli.StrataMmuPoolWatermarksModel

itmWatermarks	*table(string) = StrataMmu.Cli.ItmWatermarksModel* see 2.1655.1.1	Mapping from pool resource to pool watermarks.
slice	*string*	Slice name.

2.1655.1.1 StrataMmu.Cli.ItmWatermarksModel

highWaterMarks	*integer*	High watermarks of the pool.
xpe	*string*	MMU Ingress XPE key.

2.1656 show platform trident mmu queue status [...]

revision 2

interfaces	*table(Interface name) = PlatformInterfaceMmuStatusModel* see 2.1656.1	Mapping between interfaces and associated MMUs.

2.1656.1 PlatformInterfaceMmuStatusModel

egressMmuStatus	*table(numeric string) = PlatformInterfaceEgressMmuStatusModel* see 2.1656.1.1	Mapping between egress MMU IDs and egress queue status.
ingressMmuStatus	*table(numeric string) = PlatformInterfaceIngressMmuStatusModel* see 2.1656.1.2	Mapping between ingress MMU IDs and priority group status.
[numMmu] **	*integer*	Total number of MMUs in the chip. **Since: 4.21.3

2.1656.1.1 PlatformInterfaceEgressMmuStatusModel

mcastQueues	*table(numeric string) = PlatformMmuStatusModel* see 2.1656.1.1.1	Mapping between multicast queue IDs and MMU status.
ucastQueues	*table(numeric string) = PlatformMmuStatusModel* see 2.1656.1.1.1	Mapping between unicast queue IDs and MMU status.

2.1656.1.1.1 PlatformMmuStatusModel

[reserved]	*integer*	Queue minimum reserved bytes.
[staticLimit] **	*integer*	Queue static limit bytes. **Since: 4.35.2
[threshold]	*floating point number*	Queue threshold bytes.
used	*integer*	Queue used bytes.

2.1656.1.2 PlatformInterfaceIngressMmuStatusModel

priorityGroups	*table(numeric string) = PlatformMmuStatusModel* see 2.1656.1.1.1	Mapping between priority group IDs and MMU status.

2.1657 show platform trident mmu queue status cpu [...]

slices	*table(string) = PlatformCpuStatusModel* see 2.1657.1	Mapping from slice to associated CPU port status model.

2.1657.1 PlatformCpuStatusModel

egressMmus	*table(numeric string) = PlatformCpuEgressMmuStatusModel* see 2.1657.1.1	Mapping between egress MMU IDs and egress queue status.
ingressMmus	*table(numeric string) = PlatformInterfaceIngressMmuStatusModel* see 2.1656.1.2	Mapping between ingress MMU IDs and priority group status.
[numMmu]	*integer*	Total number of MMUs in the chip.

2.1657.1.1 PlatformCpuEgressMmuStatusModel

cpuQueues	*table(numeric string) = PlatformMmuStatusModel* see 2.1656.1.1.1	Mapping between CPU queue IDs and MMU status.

2.1658 show platform trident mmu queue watermark [...]

`[mmuIngressHeadroomPool-Watermark] **`	*StrataMmuIngress-HeadroomPoolWatermark-Model* see 2.1658.4	MMU Ingress Headroom Pool Watermarks (Cells) for all MMUs. **Since: 4.18.0
`mmuIngressHeadroomWatermark`	*StrataInterfaceMmuIngress-WatermarkModel* see 2.1658.1	MMU Ingress Headroom Watermarks (Cells) for all interfaces.
`mmuIngressSharedWatermark`	*StrataInterfaceMmuIngress-WatermarkModel* see 2.1658.1	MMU Ingress Shared Watermarks (Cells) for all interfaces.
`mmuMulticastSharedWatermark`	*StrataInterfaceMmu-MulticastSharedWatermark-Model* see 2.1658.2	MMU Multicast Shared Watermarks (Cells) for all interfaces.
`mmuUnicastSharedWatermark`	*StrataInterfaceMmu-UnicastSharedWatermark-Model* see 2.1658.3	MMU Unicast Shared Watermarks (Cells) for all interfaces.
`[numMmu] **`	*integer*	Total number of MMUs in the chip. **Since: 4.21.3

2.1658.1 StrataInterfaceMmuIngressWatermarkModel

`interfaces`	*table(Interface name) = StrataInterfaceMmuIngress-WatermarkMMUModel* see 2.1658.1.1	Mapping from interface to associated ingress MMUs for MMU Ingress Headroom/Shared Watermarks.

2.1658.1.1 StrataInterfaceMmuIngressWatermarkMMUModel

`mmus`	*table(numeric string) = StrataInterfaceMmuQueue-WatermarkPGModel* see 2.1658.1.1.1	Mapping from ingress MMU IDs to priority groups watermarks.

2.1658.1.1.1 StrataInterfaceMmuQueueWatermarkPGModel

`priorityGroups`	*table(numeric string) = integer*	Mapping from priority group number (0-7) to MMU Ingress (Headroom/Shared) Watermarks (Cells).

2.1658.2 StrataInterfaceMmuMulticastSharedWatermarkModel

`interfaces`	*table(Interface name) = StrataInterfaceMmu-MulticastSharedWatermark-MMUModel* see 2.1658.2.1	Mapping from interface to associated egress MMUs for MMU Multicast Shared Watermarks.

2.1658.2.1 StrataInterfaceMmuMulticastSharedWatermarkMMUModel

mmus	*table(numeric string) = StrataInterfaceMmuQueueWatermarkMCModel* see 2.1658.2.1.1	Mapping from egress MMU IDs to multicast queue watermarks.

2.1658.2.1.1 StrataInterfaceMmuQueueWatermarkMCModel

queues	*table(numeric string) = integer*	Mapping from multicast queue number (0-7) to MMU Multicast Shared Watermarks (Cells).

2.1658.3 StrataInterfaceMmuUnicastSharedWatermarkModel

interfaces	*table(Interface name) = StrataInterfaceMmuUnicastSharedWatermarkMMUModel* see 2.1658.3.1	Mapping from interface to associated egress MMUs for MMU Unicast Shared Watermarks.

2.1658.3.1 StrataInterfaceMmuUnicastSharedWatermarkMMUModel

mmus	*table(numeric string) = StrataInterfaceMmuQueueWatermarkUCModel* see 2.1658.3.1.1	Mapping from egress MMU IDs to unicast queue watermarks.

2.1658.3.1.1 StrataInterfaceMmuQueueWatermarkUCModel

queues	*table(numeric string) = integer*	Mapping from unicast queue number (0-7) to MMU Unicast Shared Watermarks (Cells).

2.1658.4 StrataMmuIngressHeadroomPoolWatermarkModel

units	*table(numeric string) = StrataUnitMmuIngressHeadroomPoolWatermarkModel* see 2.1658.4.1	Mapping from Switch units (chips) to associated ingress MMUs for MMU Ingress Headroom/Shared Watermarks.

2.1658.4.1 StrataUnitMmuIngressHeadroomPoolWatermarkModel

mmus	*table(numeric string) = integer*	Mapping from ingress MMU IDs to Headroom Pool Watermarks (Cells).

2.1659 show platform trident mmu queue watermark cpu [...]

slices	*table(string) = StrataCpuMmuQueueWatermarkModel* see 2.1659.1	Mapping from linecard to associated CPU port MMU Queue Watermarks.

2.1659.1 StrataCpuMmuQueueWatermarkModel

[cpuIngressSharedWatermark]	*StrataInterfaceMmuIngressWatermarkMMUModel* see 2.1658.1.1	MMU Ingress Shared Watermarks (Cells) for CPU port.
[cpuMulticastSharedWatermark]	*StrataInterfaceMmuMulticastSharedWatermarkMMUModel* see 2.1658.2.1	MMU Multicast Shared Watermarks (Cells) for CPU port.

2.1660 show platform trident mmu replication watermark [...]

units	*table(numeric string) = StrataUnitMmuRqeWatermarkModel* see 2.1660.1	Mapping from Switch units to associated MMUs for RQE Watermarks.

2.1660.1 StrataUnitMmuRqeWatermarkModel

mmus	*table(numeric string) = StrataBaseMmuRqeWatermarkModel* see 2.1660.1.1	Mapping from MMU IDs to associated RQE queues for RQE Watermarks.

2.1660.1.1 StrataBaseMmuRqeWatermarkModel

queues	*table(string) = integer*	Mapping from RQE queue to watermark value.

2.1661 show platform trident obm counters [...]

counterType	*enum: discards | usage*	OBM counters type, can be usage or discards.
units	*table(numeric string) = ObmIntfs* see 2.1661.1	Mapping from Switch units (chips) to associated interfaces for OBM counters.

2.1661.1 ObmIntfs

intfs	*table(Interface name) = ObmIntfCounters* see 2.1661.1.1	Mapping from interface to OBM counters.

2.1661.1.1 ObmIntfCounters

dropByte	*table(string) = integer*	OBM per-priority drop byte count.
dropPkt	*table(string) = integer*	OBM per-priority drop packet count.
usedByte	*table(string) = integer*	OBM per-priority usage byte count.

2.1662 show platform trident parity-event [...]

chipParityInformation	*table(string) = ChipParityInformation* see 2.1662.1	Parity information for a chip, keyed by chip name.
parityErrorCount	*integer*	Total parity error count.

2.1662.1 ChipParityInformation

fapId **	*integer*	Unique numerical chip identifier. **Since: 4.25.0
memParityErrors	*table(string) = MemParityInformation* see 2.1662.1.1	Parity information for a specific memory on the chip, keyed by memory name.
modId	*integer*	Chip module ID (legacy attribute, use fapId instead.
parityErrorCount	*integer*	Total parity error count on the chip.
sliceName	*string*	Name of the slice managing the chip.

2.1662.1.1 MemParityInformation

memId	*integer*	Unique numerical table identifier.
memType	*enum: reg | table | other*	The type of the memory, can be either a table or register.
offsetParityErrors	*table(numeric string) = OffsetParityInformation* see 2.1662.1.1.1	Parity information for a specific table offset, keyed by offset (int).
parityErrorCount	*integer*	Total number of parity errors reported on this memory.

2.1662.1.1.1 OffsetParityInformation

lastSeen	*floating point number*	Most recent parity event on this offset as seconds since epoc.
parityErrorCount	*integer*	Total number of parity errors reported at this offset.

2.1663 show platform trident priority-flow-control watchdog snapshot [...]

intfSnapshot	*table(Interface name) = IntfSnapshotModel* see 2.1663.1	A mapping of interface name to Snapshot.
snapshotSummary	*SnapshotSummaryModel* see 2.1663.2	Stage Snapshot Summary.

2.1663.1 IntfSnapshotModel

recoveryStageSnapshot	*StageSnapshotModel* see 2.1663.1.1	Recovery Stage Snapshot.
stuckStageSnapshot	*StageSnapshotModel* see 2.1663.1.1	Stuck Stage Snapshot.

2.1663.1.1 StageSnapshotModel

disableQ	*SnapshotModel* see 2.1663.1.1.1	Snapshot for Stage during disable queueing state.
pfcProfile	*SnapshotModel* see 2.1663.1.1.1	Snapshot for Stage during pfc profile state.
updateTcam	*SnapshotModel* see 2.1663.1.1.1	Snapshot for Stage during updating Tcam state.

2.1663.1.1.1 SnapshotModel

requestTime	*floating point number*	Time at which request was sent.
responseTime	*floating point number*	Time at which response was sent.

2.1663.2 SnapshotSummaryModel

recoveryStageSummary	*StageSummaryModel* see 2.1663.2.1	Recovery Stage Snapshot Summary.
stuckStageSummary	*StageSummaryModel* see 2.1663.2.1	Stuck Stage Snapshot Summary.

2.1663.2.1 StageSummaryModel

disableQ	*SummaryModel* see 2.1663.2.1.1	Summary for Stage during disable queueing state.
pfcProfile	*SummaryModel* see 2.1663.2.1.1	Summary for Stage during pfc profile state.
updateTcam	*SummaryModel* see 2.1663.2.1.1	Summary for Stage during updating Tcam state.

2.1663.2.1.1 SummaryModel

count	*integer*	Number of times the interfaces were in this particular stage and state.

`maxDuration`	*floating point number*	Maximum duration for which the interfaces were in this particular stage and state in milliseconds.
`minDuration`	*floating point number*	Minimum duration for which the interfaces were in this particular stage and state in milliseconds.
`movingAverage`	*floating point number*	Moving average of duration for which the interfaces were in this particular stage and state in milliseconds.

2.1664 show platform trident profile [...]

[activeScaleMode] **	*TileScale* see 2.1664.2	Active scale for current chip and profile. **Since: 4.31.0
chipProfiles	*table(string) = ChipProfileModel* see 2.1664.1	Dictionary of profile information per chip.
systemProfile	*default*	Current system profile.

2.1664.1 ChipProfileModel

activeProfile	*string*	Active profile configured on the chip.
chipName	*string*	Chip name.
supportedProfiles	*list of string*	Profiles supported by the chip.

2.1664.2 TileScale

[forwarding]	*ForwardingScale* see 2.1664.2.1	Forwarding Scale.

2.1664.2.1 ForwardingScale

[aoNat] **	*FeatureScale* see 2.1664.2.1.1	Address-Only NAT Scale. **Since: 4.34.0
[exactMatch] **	*FeatureScale* see 2.1664.2.1.1	Exact Match Scale. **Since: 4.33.0
[l2]	*FeatureScale* see 2.1664.2.1.1	Layer2 MAC Scale.
[l3Multicast]	*FeatureScale* see 2.1664.2.1.1	Layer3 IP Multicast Scale.
l3SourceLookup **	*boolean*	IP Source Lookup enabled. **Since: 4.33.1
[l3Unicast]	*FeatureScale* see 2.1664.2.1.1	Layer3 IP Unicast Scale.
[napt] **	*FeatureScale* see 2.1664.2.1.1	Network Address Port Translation Scale. **Since: 4.34.0
[num]	*integer*	Mode Number.
[pimSparseMode] **	*FeatureScale* see 2.1664.2.1.1	Vxlan Underlay Multicast PIM SM Scale. **Since: 4.33.2
[trafficPolicyDst] **	*FeatureScale* see 2.1664.2.1.1	Traffic Policy Destination Scale. **Since: 4.31.1
[trafficPolicySrc] **	*FeatureScale* see 2.1664.2.1.1	Traffic Policy Source Scale. **Since: 4.31.1
vxlanBridging	*boolean*	VxLAN Bridging enabled.
vxlanRouting	*boolean*	VxLAN Routing enabled.

2.1664.2.1.1 FeatureScale

maxScale	*integer*	Maximum Value.

minScale	*integer*	Minimum Value.

2.1665 show platform trident ptp hardware-sync [...]

see 2.1404

2.1666 show platform trident security

common	*CommonStatusModel* see 2.1666.1	Common MACsec information.
egress	*EgressStatusModel* see 2.1666.2	Egress MACsec information.
ingress	*IngressStatusModel* see 2.1666.3	Ingress MACsec information.

2.1666.1 CommonStatusModel

mode	*integer*	Security Association Mode.

2.1666.2 EgressStatusModel

errorStatus	*string*	Egress error status.

2.1666.3 IngressStatusModel

errorStatus	*string*	Ingress error status.
scTcamMiss	*integer*	Ingress SC TCAM miss.
spTcamMiss	*integer*	Ingress SP TCAM miss.

2.1667 show platform trident security interfaces [...]

interfaces	*table(Interface name) = ShowSecIntfStatusModel* see 2.1667.1	A mapping between an interface and ShowSecIntfStatusModel.

2.1667.1 ShowSecIntfStatusModel

interface	*interface name*	Interface name.
l2Feature	*L2Model* see 2.1667.1.1	L2 status information.
l3Feature	*L3Model* see 2.1667.1.2	L3 status information.
pktDrvFeature	*PktDrvModel* see 2.1667.1.3	PktDrv status information.
securityEngineFeature	*SecurityEngineModel* see 2.1667.1.4	Security Engine status information.
sliceFeature	*SliceModel* see 2.1667.1.5	Slice status information.
tcamFeature	*TcamModel* see 2.1667.1.6	TCAM status information.

2.1667.1.1 L2Model

[flexL2EntryIndex]	*integer*	Flex L2 Entry Index.
isConfigured	*boolean*	Configuration status.

2.1667.1.2 L3Model

isConfigured	*boolean*	Configuration status.
[mmuReplicationGroups]	*list of string*	MMU Replication Groups.

2.1667.1.3 PktDrvModel

isConfigured	*boolean*	Configuration status.

2.1667.1.4 SecurityEngineModel

[engineInstance] **	*integer*	Engine Instance. **Since: 4.32.0
[esecSaIndex]	*integer*	Encryption active SA index.
[esecScIndex]	*integer*	Encryption SC index.
isConfigured	*boolean*	Configuration status.
[isecSaIndexes]	*list of integer*	Decryption active SA indexes.
[isecScIndex]	*integer*	Decryption SC index.
[isecSpIndex]	*integer*	Decryption SP index.
[msSubportNum]	*integer*	Decryption MACsec subport number.
[secPortNum]	*integer*	Security port number.

2.1667.1.5 SliceModel

isConfigured	*boolean*	Configuration status.
[subportId]	*integer*	Subport ID.

2.1667.1.6 TcamModel

[decryptFirstPassEfpEntry]	*integer*	Decryption First pass EFP Entry.
[decryptFirstPassIfpEntry]	*integer*	Decryption First pass IFP Entry.
[decryptSecondPassIfpEntry]	*integer*	Decryption Second pass IFP Entry.
[encryptFirstPassEfpEntry]	*integer*	Encryption First pass EFP Entry.
[encryptSecondPassIfpEntry]	*integer*	Encryption Second pass IFP Entry.
isConfigured	*boolean*	Configuration status.

2.1668 show platform trident switch-extender counters queue egress

interfaces	*table(Interface name) = SwitchExtenderInterfaceModel* see 2.1668.1	Mapping between interface and queue information.

2.1668.1 SwitchExtenderInterfaceModel

[active]	*boolean*	Connected switchcard active. Only populated for ingress counters.
queues	*table(string) = SwitchExtenderQueueData* see 2.1668.1.1	Mapping between queue name and queue counter information.

2.1668.1.1 SwitchExtenderQueueData

droppedPkts	*integer*	Dropped packet count.

2.1669 show platform trident switch-extender counters queue ingress [...]

interfaces	*table(Interface name) = SwitchExtenderInterfaceBackplaneModel* see 2.1669.1	Mapping between interface and per-switchcard queue information.

2.1669.1 SwitchExtenderInterfaceBackplaneModel

connections	*table(string) = SwitchExtenderInterfaceModel* see 2.1668.1	Mapping between connected switchcard and backplane interface.

2.1670 show platform trident tcam [...]

chips	*table(string) = TcamChipInformation* see 2.1670.1	TCAM usage information keyed by switch name.

2.1670.1 TcamChipInformation

stages	*table(string) = TcamStageInformation* see 2.1670.1.1	Stage information keyed by stage name.

2.1670.1.1 TcamStageInformation

pipes	*table(string) = TcamPipeInformation* see 2.1670.1.1.1	Pipe information keyed by pipe ID.

2.1670.1.1.1 TcamPipeInformation

groups	*table(numeric string) = TcamGroupInformation* see 2.1670.1.1.1.1	Group information keyed by group ID.

2.1670.1.1.1.1 TcamGroupInformation

groupPerCopy	*table(numeric string) = TcamGroupPerCopy-Information* see 2.1670.1.1.1.2	Group per logical copy information keyed by copy ID.

2.1670.1.1.1.2 TcamGroupPerCopyInformation

availableEntries	*integer*	Total entries available for TCAM group.
[features]	*list of TcamFeatureInformation* see 2.1670.1.1.1.3	List of features.
[reservedEntries]	*integer*	Total entries reserved by the feature.
usedEntries	*integer*	Total entries used by TCAM group.

2.1670.1.1.1.3 TcamFeatureInformation

[entries]	*table(numeric string) = TcamEntryInformation* see 2.1670.1.1.1.4	Entry information keyed by entry ID.
featureName	*string*	Feature name.
[reservedEntries]	*integer*	Total entries reserved by the feature.
[usedEntries]	*integer*	Total entries used by the feature.

2.1670.1.1.1.4 TcamEntryInformation

description	*string*	Description of the entry.
hits	*integer*	Number of entry hits.

2.1671 show platform trident tcam counter object [...]

chips	*table(string) = TcamCounterObjectStageModel* see 2.1671.1	A mapping of chipname to its TCAM Flex-Counter Objects Info.

2.1671.1 TcamCounterObjectStageModel

stages	*table(string) = TcamCounterObjectPipeModel* see 2.1671.1.1	Stage information keyed by stage name.

2.1671.1.1 TcamCounterObjectPipeModel

pipes	*table(string) = TcamCounterObjectIdInfoModel* see 2.1671.1.1.1	Pipe information keyed by pipe ID.

2.1671.1.1.1 TcamCounterObjectIdInfoModel

objectIds	*table(numeric string) = TcamCounterObjectInfoModel* see 2.1671.1.1.1.1	A mapping from a counter objectID to counter object information.

2.1671.1.1.1.1 TcamCounterObjectInfoModel

colorAware	*boolean*	Counter object's color counting ability.
mode	*enum: shared | dedicated*	counter object mode.
objectId	*integer*	Counter object ID.
objectName	*string*	Counter object name.
reservedBy	*list of string*	List of features which reserve the object counter.
users	*list of string*	List of users for current counter object.

2.1672 show platform trident tcam cpu-bound [...]

chips	*table(string) = PoliciesModel* see 2.1672.1	Policies, keyed by chip name.

2.1672.1 PoliciesModel

[policies]	*list of PolicyMapModel* see 2.1672.1.1	Policies.

2.1672.1.1 PolicyMapModel

direction	*enum: output | input*	Direction in which policy map is applied.
policyMapName	*string*	Name of the policy map.
policyMapType	*enum: qos | controlPlane*	Type of policy map.
policyRequests	*table(string) = PolicyRequestDetails* see 2.1672.1.1.1	Policy requests, keyed by request name.

2.1672.1.1.1 PolicyRequestDetails

classMaps	*table(string) = ClassMapModel* see 2.1672.1.1.1.2	Class maps, keyed by class map name.
faps	*table(numeric string) = FapSet* see 2.1672.1.1.1.1	FAP set status, keyed by FAP ID.
featureGroupName	*string*	Feature group name.

`featureGroupType`	*enum: fgtEfpBreadthTest* | *fgtIfpTrafficConc* | *fgtIfpOpenflowFloodTable* | *fgtPolicyQosIp* | *fgtBreadthTest1* | *fgtIfpGroupMirrorAcl4* | *fgtIfpGroupMirrorIpAcl1* | *fgtL2CtrlArpInspection* | *fgtCompressionL4SrcPort* | *fgtIfpOpenflowRegularTable* | *fgtSecurityIngressIfpPAcl-Ip6Std* | *fgtL3CtrlTtlCheck* | *fgtAegisEgressRoutedIpv4* | *fgtUnicastEapol* | *fgtIfpAegisSegmentSecurity* | *fgtSecurityIngressVAclIp* | *fgtUnsupportedQualTestIfp* | *fgtIfpMacCollision-HandlingDst* | *fgtMirroringAcl3Mac-Ingress* | *fgtEgrPolicyQosIp* | *fgtEfpGroupMirrorPort-RateLimit* | *fgtIfpDirectflowL2Only* | *fgtSecurityIngressIfpPAcl-Ip6Vni* | *fgtIfpGroupMirrorIpAcl2* | *fgtEfpPTPBypass* | *fgtIfpTcpMssClamping* | *fgtVfpBreadthTest1* | *fgtIpv4v6EgressCounter* | *fgtL2CtrlDot1xMba* | *fgtMacsecInlineEgress* | *fgtIfpGroupMirrorIp6Acl4* | *fgtSecurityEgressPAclIp6-Std* | *fgtIntIfaTransitRules* | *fgtIfpGroupMirrorIpAcl4* | *fgtIntRules* | *fgtL2CtrlLlc-FrameValidation* | *fgtIfpOpenflowFull* | *fgtIfpOpenflowUdf* | *fgtIfpGroupMirrorMacAcl2* | *fgtInvalid* | *fgtVfpDirectflowP4RtVrf* | *fgtSviSharedPolicyQosIp* | *fgtDirectedBroadcastRules* | *fgtIfpChannelRedirection* | *fgtIfpOpenflowL2OnlyLow* | *fgtSecurityIngressPAclIp-Vni* | *fgtL3CtrlMlagCtrlTraffic* | *fgtIfpDirectflowP4Rt-PostcardIpv6* | *fgtMirroringAcl2Ip6Ingress* | *fgtMirroringAcl2IpIngress* | *fgtIfpL3ctrlExceptionTHx-Openflow* | *fgtVfpTripleBreadthTest* | *fgtIfpGroupMirrorAcl3* | *fgtSecurityIngressPAclIp6* | *fgtL2CtrlL3Routing* |	Feature group type.

interfaces	*list of Interface name*	Interfaces on which policy map is applied.
requestConfigType	*enum: deleteConfig* | *deleteConfigInRevOrder* | *testDrivenPartial-Exhaustion* | *invalid* | *updateInterfaceInRevOrder* | *updateInterface* | *revertConfig* | *updateAction* | *updateConfig* | *updateEntry* | *testDrivenExhaustion* | *newConfig*	Last request type.
requestStatusType	*enum: requestFailureOut-OfPolicerOrCounter* | *requestNone* | *requestFailureUnknown* | *requestFailureOutOf-SubportGroupId* | *requestFailureOutOfUDF* | *requestFailureOutOfSpace* | *requestFailureCounter-ObjectExhaustion* | *requestSuccess* | *request-FailureOutOfRangeChecker* | *requestFailureTimeout* | *requestFailureUDFGroup-Expansion* | *requestNotApplicable* | *requestPending* | *requestFailureConfigError* | *requestFailureIntfProfileId-NotFound*	Last known status of this request.
rulesIdsCount	*integer*	Number of rule IDs used by this request.

2.1672.1.1.1.1 FapSet

allPipes	*boolean*	Policy map is applied on all pipes.
pipes	*list of integer*	Pipes on which policy map is applied.

2.1672.1.1.1.2 ClassMapModel

aclName	*string*	Name of ACL matched to class map.
aclRuleIdsCount	*integer*	Number of rule IDs used by ACL.
aclType	*enum: ipv6* | *mac* | *ip*	Type of ACL.
classMapType	*enum: qos* | *controlPlane*	Type of class map.
[policerInfo]	*PolicerInfoModel* see 2.1672.1.1.1.3	Info of Policer attached to class map.
policerType	*enum: PolicerNone* | *PolicerUnshared* | *PolicerShared*	Type of policer.

[ruleIdsDetails]	*table(numeric string) = RuleIdModel* see 2.1672.1.1.1.4	Rule Details, keyed by sequence number.

2.1672.1.1.1.3 PolicerInfoModel

committedBurstSize	*integer*	Comitted burst size.
committedInformationRate	*integer*	Comitted information rate.
mode	*enum: policerModeCommitted | policerModeTrTcm | policerModeSrTcm*	Policer mode.
peakBurstSize	*integer*	Peak burst size.
peakInformationRate	*integer*	Peak information rate.
unit	*enum: policerUnitPackets | policerUnitBytes*	Policer unit.

2.1672.1.1.1.4 RuleIdModel

description	*string*	Description of rule.
hits	*integer*	Number of packets hit this rule.
[policerKey]	*string*	Policer Key.
[qualifiers]	*table(string) = Qualifier* see 2.1672.1.1.1.5	Qualifiers, keyed by qualifier type.
[rangeCheckers]	*table(string) = RangeChecker* see 2.1672.1.1.1.6	Range Checkers, keyed by range checker type.
ruleEnabled	*boolean*	Rule is enabled in hardware.

2.1672.1.1.1.5 Qualifier

data	*string*	Qualifier data.
mask	*string*	Qualifier mask.

2.1672.1.1.1.6 RangeChecker

high	*integer*	Highest range.
low	*integer*	Lowest range.

2.1673 show platform trident tcam directed-broadcast [...]

chips	*table(string) = TcamDirectedBroadcast-PipeModel* see 2.1673.1	A mapping of chipname to its Directed Broadcast TCAM Entries.

2.1673.1 TcamDirectedBroadcastPipeModel

pipes	*table(string) = TcamDirectedBroadcast-RulesModel* see 2.1673.1.1	A mapping of pipe number to rule set.

2.1673.1.1 TcamDirectedBroadcastRulesModel

rules	*table(string) = RuleInfoModel* see 2.1673.1.1.1	A mapping from a rule ID to information about the rule.

2.1673.1.1.1 RuleInfoModel

action	*enum: permit | drop*	Action for the rule.
dstIp	*IPv4 address*	Destination IP Address.
hits	*integer*	Number of packet hits against the rule.
[srcIp]	*IPv4 address*	Source IP Address; source IPs not in the permitted field set marked as '*'.

2.1674 show platform trident tcam group id [...]

slices	*table(string) = Trident-TcamGroupIdSliceFeatures* see 2.1674.1	A mapping from slice to its features.

2.1674.1 TridentTcamGroupIdSliceFeatures

[error]	*string*	Error message.
[features]	*list of TridentTcamGroupId-Feature* see 2.1674.1.1	List of features.

2.1674.1.1 TridentTcamGroupIdFeature

featureId	*integer*	Feature ID.
name	*string*	Feature name.
sdkId	*integer*	SDK ID.
stage	*enum: ifp | vfp | efp*	Stage.

2.1675 show platform trident tcam profile [...]

chips	*table(string) = TcamChipInfo* see 2.1675.1	A mapping from chip to it's groups.

2.1675.1 TcamChipInfo

groups	*table(numeric string) = ChipGroupInfo* see 2.1675.1.1	A mapping from group number to its qualifiers.

2.1675.1.1 ChipGroupInfo

currentQualifiers	*list of string*	Current Qualifiers.
dontCareQualifiers	*list of string*	Qualifier defaulting to Dont-Care (diff from config).
[dontCareQualifiersEntry]	*table(numeric string) = PerIdInfo* see 2.1675.1.1.1	Mapping from Entry ID to Qualifiers defaulting to Dont-Care.
feature **	*string*	Feature name. **Since: 4.31.0
groupName **	*string*	Group name. **Since: 4.31.0
programmedInHardware **	*boolean*	Programmed in hardware. **Since: 4.32.0
[reservedEntries] **	*integer*	Max number of entries for this reservation. **Since: 4.31.0
[reservedSlices] **	*list of integer*	The TCAM slices allocated to this group. **Since: 4.30.0
stage **	*enum: ifp | vfp | efp*	Stage. **Since: 4.31.0

2.1675.1.1.1 PerIdInfo

qualifiers	*list of string*	Qualifiers associated with this ID.

2.1676 show platform trident tcam qos [...]

see 2.1672

2.1677 show platform trident tcam summary [...]

switches **	*table(string) = StrataTcamSummaryChip* see 2.1677.1	Mapping from switches' name to their TCAM summary. **Since: 4.29.2

2.1677.1 StrataTcamSummaryChip

features	*table(string) = StrataTcamSummaryFeatureModel* see 2.1677.1.1	Mapping from features to slice groups they occupy.

2.1677.1.1 StrataTcamSummaryFeatureModel

bankType	*enum: ifp | flowtracker | vfp | efp*	Stage of TCAM slices.
banks	*list of integer*	Index of TCAM slices.

2.1678 show platform trident vfi mc-index

l3VfiMcIndexInfo	*table(numeric string) = L3VfiMcIndexInfo* see 2.1678.1	VFI MC Index table indexed by VLAN Id.

2.1678.1 L3VfiMcIndexInfo

[bcCore] **	*integer*	BC Index including core and edge ports. **Since: 4.33.1
[bcEdge] **	*integer*	BC Index including edge ports only. **Since: 4.33.1
[routedMc]	*integer*	Routed MC Index allocated for VFI.
[umcCore]	*integer*	UMC Index including core and edge ports.
[umcEdge]	*integer*	UMC Index including edge ports only.
uucCore	*integer*	UUC Index including core and edge ports.
uucEdge	*integer*	UUC Index including edge ports only.

2.1679 show platform trident vfi virtual-ports

revision 2

PhysicalInterfaceVps	*table(string) = L3VfiPhysicalInterfaceVp* see 2.1679.1	VFI virtual port table indexed by the physical port.
SystemInterfaceVps	*table(string) = L3VfiSystemInterfaceVp* see 2.1679.2	VFI virtual port table indexed by the system interface.

2.1679.1 L3VfiPhysicalInterfaceVp

vportAttributes	*list of L3VfiPhysicalInterfaceVpAttributes* see 2.1679.1.1	VFI attributes associated with the interface.

2.1679.1.1 L3VfiPhysicalInterfaceVpAttributes

dvp	*integer*	Destination virtual port associated with the interface.
egrVlanFilter **	*boolean*	Flag to indicate VLAN membership check on packets egressing the interface. **Since: 4.22.0
sdtagNextHopId	*integer*	SDTAG nexthop identifier for the interface.

tagged	*boolean*	Flag to indicate whether packets going out of the interface have to be tagged for this VLAN.
[vlanId]	*integer*	VLAN identifier.

2.1679.2 L3VfiSystemInterfaceVp

vportAttributes	*list of L3VfiSystemInterface-VpAttributes* see 2.1679.2.1	Attributes associated with the Virtual Port.

2.1679.2.1 L3VfiSystemInterfaceVpAttributes

dvp	*integer*	Virtual port identifier.

2.1680 show platform trident vfi vlan map

pendingVlans **	*list of integer*	Pending VLANs due to resource exhaustion. **Since: 4.26.2
vfis	*table(numeric string) = integer*	A mapping between VFI index and VLAN.

2.1681 show platform trident vlan membership egr-vp

vpVlanList	*list of VpVlanMembershipEntry* see 2.1681.1	VLAN membership table list.

2.1681.1 VpVlanMembershipEntry

[entryId]	*integer*	hardware entry ID.
interface	*interface name*	Front Panel Interface.
logicalPort	*integer*	Switchcard Logical Port number.
modId	*integer*	Switchcard ModId.
stpState	*string*	Spanning Tree state.
[untag]	*string*	untag egress packet.
vlanId	*integer*	VLAN ID.

2.1682 show platform trident vlan membership egr-vp unprogrammed

vpVlanList	*list of VpVlanMembershipEntry* see 2.1681.1	VLAN membership table list.

2.1683 show platform trident vlan membership ing-vp

vpVlanList	*list of VpVlanMembershipEntry* see 2.1681.1	VLAN membership table list.

2.1684 show platform trident vlan membership ing-vp unprogrammed

vpVlanList	*list of VpVlanMembershipEntry* see 2.1681.1	VLAN membership table list.

2.1685 show platform trident vlan profile

vlanProfiles	*table(numeric string) = VlanProfileEntry* see 2.1685.1	VLAN profiles keyed by VLAN profile ID.

2.1685.1 VlanProfileEntry

broadcastMask	*enum: b | a | none | ab*	BLOCK_MASK_A and BLOCK_MASK_B applied to broadcast packets.
knownMcastMask	*enum: b | a | none | ab*	BLOCK_MASK_A and BLOCK_MASK_B applied to known multicast packets.
l2Ipv4Pfm	*enum: all | none | unknown*	Mcast flood mode for L2.
l3Ipv4Pfm	*enum: all | none | unknown*	Mcast flood mode for IPv4.
l3Ipv6Pfm	*enum: all | none | unknown*	Mcast flood mode for IPv6.
unknownMcastMask	*enum: b | a | none | ab*	BLOCK_MASK_A and BLOCK_MASK_B applied to unknown multicast packets.
unknownUcastMask	*enum: b | a | none | ab*	BLOCK_MASK_A and BLOCK_MASK_B applied to unknown unicast packets.
vlanIP4McastL2Disabled	*boolean*	L2-only forwarding of IPMCv4 is disabled.
vlanIP6McastL2Disabled	*boolean*	L2-only forwarding of IPMCv6 is disabled.

2.1686 show platform trident vlan setting

vlans	*table(numeric string) = VlanSettingEntry* see 2.1686.1	VLAN settings keyed by VLAN ID.

2.1686.1 VlanSettingEntry

egressValid	*boolean*	Egress valid for VLAN.
forwardingVlan	*integer*	VLAN ID forwarding to.

ingressValid	*boolean*	Ingress valid for VLAN.
[profileId]	*integer*	VLAN's profile ID.
stg	*integer*	Spanning tree group ID.
vlanClassId	*integer*	ID of VLAN class.

2.1687 show platform trident vlan status

vlans	*table(numeric string) = VlanStatusEntry* see 2.1687.1	VLAN Statuses Keyed by VLAN ID.

2.1687.1 VlanStatusEntry

interfaces	*list of string*	List of interfaces of one VLAN ID.

2.1688 show platform trident vlan stg

topologies	*table(numeric string) = VlanStgEntry* see 2.1688.1	Spanning tree information of each topology keyed by topology ID.

2.1688.1 VlanStgEntry

[logicalFapIds]	*table(numeric string) = VlanStgLogicalFapEntry* see 2.1688.1.1	Interfaces for logical FAP keyed by logical FAP ID.
topoName	*string*	Name of topology.
vlans	*list of integer*	List of VLAN IDs in the spanning tree.

2.1688.1.1 VlanStgLogicalFapEntry

[interfaces]	*table(string) = VlanStgInterfaceEntry* see 2.1688.1.1.1	Interfaces in the spanning tree keyed by interface name.

2.1688.1.1.1 VlanStgInterfaceEntry

[modId]	*integer*	Switchcard module ID.
[portId]	*integer*	Switchcard port ID.
stpState	*enum: discarding | forwarding | learning | unknown*	Spanning tree state.

2.1689 show platform trident vxlan local-vtep

interfaces	*table(Interface name) = VxlanLocalVtepV4V6-InterfaceModel* see 2.1689.1	VXLAN interfaces.

2.1689.1 VxlanLocalVtepV4V6InterfaceModel

[vtepV4]	*VxlanLocalVtepInterface-InfoModel* see 2.1689.1.1	IPv4 VTEP.
[vtepV6]	*VxlanLocalVtepInterface-InfoModel* see 2.1689.1.1	IPv6 VTEP.

2.1689.1.1 VxlanLocalVtepInterfaceInfoModel

localVtep	*IP address*	Local VTEP address.
ttl	*integer*	Time to live (hops).
udpPort	*integer*	UDP port.

2.1690 show platform trident vxlan multicast route underlay [...]

underlayMroutes	*list of MrouteKeyToEM-EntryModel* see 2.1690.1	A List of Vxlan Underlay Mroutes.

2.1690.1 MrouteKeyToEMEntryModel

groupIp	*IP address*	Group IP address.
interfaceName	*interface name*	Interface name.
isActive	*boolean*	Underlay Mroute is active.
isProgrammed	*boolean*	Underlay Mroute is Programmed.
sourceIp	*IP address*	Source IP address.
vlanId	*integer*	VLAN Identifier.

2.1691 show platform trident vxlan multicast tunnel [...]

tunnels	*table(numeric string) = McastTunnelEntryModel* see 2.1691.1	A mapping of Encap Id to VXLAN Multicast Tunnels.

2.1691.1 McastTunnelEntryModel

dvpIndex	*integer*	Hardware destination index.
[groups]	*list of integer*	List of groups.
portNextHops	*list of PortNextHopModel* see 2.1691.1.1	List of Port-NextHops.
stale	*boolean*	Tunnel information is stale.

tunnelIp	*IP address*	VXLAN Multicast tunnel IP address.

2.1691.1.1 PortNextHopModel

nextHopId	*integer*	NextHop index.
port	*interface name*	Core interface.

2.1692 show platform trident vxlan multihoming groups non-peering

filteredGroups	*list of FilteredGroupRow* see 2.1692.1	Non-peering groups.

2.1692.1 FilteredGroupRow

coreGroup	*integer*	Core Group ID.
edgeGroup	*integer*	Edge Group ID.
filteredGroup	*integer*	Filtered Group ID.
vlan	*integer*	VLAN ID.

2.1693 show platform trident vxlan multihoming groups peering

peeringGroups	*list of PeeringGroupRow* see 2.1693.1	Peering groups.

2.1693.1 PeeringGroupRow

group	*integer*	Group ID.
tcamEntryId	*integer*	TCAM Entry ID.
vni	*integer*	VXLAN VNI.
vp	*integer*	Virtual Port.

2.1694 show platform trident vxlan next-hop

[herMlagVteps]	*table(string) = integer*	L3Mc Next-Hops, keyed by Remote MLAG HER VTEPs.
[herVteps]	*table(string) = HerVtepNextHopsModel* see 2.1694.1	L3Mc Next-Hops, keyed by HER VTEPs.
[localVtepNextHops]	*integer*	Total local remote VTEP Next-Hops.
[memberTunnelVteps]	*table(string) = integer*	L3Mc Next-Hops, keyed by Member tunnel VTEPs.
[mlagVtepNextHops]	*integer*	Total Mlag VTEP Next-Hops.
[remoteVteps]	*table(string) = integer*	Next-Hops, keyed by Remote VTEPs.
[vfis]	*table(string) = VfiNextHopsModel* see 2.1694.2	Next-Hops, keyed by VFI id.

2.1694.1 HerVtepNextHopsModel

[dropNextHop]	*boolean*	Next-Hops not part of L3MC Next-Hops collection.
[nextHopIds]	*list of integer*	Next-Hops in L3MC Next-Hops collection.

2.1694.2 VfiNextHopsModel

[mcIndex]	*integer*	Multicast index of VLAN.
[ports]	*table(Interface name) = PortVlanModel* see 2.1694.2.1	Next-Hops, keyed by L3 port.

2.1694.2.1 PortVlanModel

[multiVtepMlagNextHops]	*list of integer*	Next-hops for multiVTEP MLAG.
[sdtagNextHopId]	*integer*	Sdtag Next-Hop id.
[singleVtepMlagNextHops]	*list of integer*	Next-hops for singleVTEP MLAG.

2.1695 show platform trident vxlan port-to-next-hop

vxlanPortToNhTableColl	*table(Interface name) = VxlanPortToNhTable* see 2.1695.1	Port-To-Next-Hop Table for all Ports.

2.1695.1 VxlanPortToNhTable

installedNhId	*integer*	Next Hop ID Installed in Port-To-Next-Hop Table.
portToNextHops	*list of VxlanPortToNhEntryNhAttr* see 2.1695.1.1	Next Hop Entry Attributes.
tableOverflow	*boolean*	Flag indicating whether Port-To-Next-Hop Table is currently in Resource Overflow state.

2.1695.1.1 VxlanPortToNhEntryNhAttr

[installError]	*boolean*	Error installing this Entry in H/W?
nextHopId	*integer*	Port To Next Hop Table Index.
nextHopMac	*MAC address*	Next Hop MAC Address.

2.1696 show platform trident vxlan port-to-next-hop overflow

see 2.1695

2.1697 show platform trident vxlan routing-info

[recircChannel]	*interface name*	Recirculation Interface.
routerMac	*MAC address*	Router MAC Address.
[varpVtepIp]	*IP address*	VARP VTEP IP address.
[varpVtepIp6] **	*IP address*	VARP VTEP IPv6 address. **Since: 4.31.1
[varpVtepSvp]	*integer*	VARP VTEP SVP.
[virtualRouterMac]	*MAC address*	Virtual Router MAC Address.
vlans	*table(numeric string) = VlanToSvpEntry* see 2.1697.1	A mapping from VLAN to SVP info.

2.1697.1 VlanToSvpEntry

routerMacConfigured	*boolean*	Router MAC is configured.
[routerMacNotInShadow]	*boolean*	Router MAC not in MAC shadow.
[routerMacSetToDiscard]	*boolean*	Router MAC is set to discard.
svp	*integer*	SVP.
[virtualRouterMac-Configured]	*boolean*	Virtual Router MAC configured.
[virtualRouterMacNotIn-Shadow]	*boolean*	Virtual Router MAC present in shadow.
[virtualRouterMacSetTo-Discard]	*boolean*	Virtual Router MAC set to discard.
vlanXlateEntryPresent	*boolean*	VLAN XLATE Entry is present.

2.1698 show platform trident vxlan vlan [...]

vlans	*table(numeric string) = VxlanVlanEntry* see 2.1698.1	Mapping from VLAN to VXLAN VLAN mapping.

2.1698.1 VxlanVlanEntry

[mcastIndex]	*integer*	Mcast Index.
vfi	*integer*	VFI.
[virtualPorts]	*table(Interface name) = integer*	Mapping from Virtual Ports to SVP. Populated only for detail version of command.
[vlanSvp]	*integer*	VLAN SVP.
vni	*integer*	VNI.

2.1699 show platform trident vxlan vlan summary

[recircChannel]	*interface name*	Recirculation interface.
[varpSvp]	*integer*	Varp Vtep SVP allocated.
[varpVtepIp]	*IP address*	VARP VTEP IP address.
[varpVtepIp6] **	*IP address*	VARP VTEP IPv6 address. **Since: 4.31.1

[virtualRouterMac]	*MAC address*	Vxlan Virtual Router MAC Address.
[vxlanRouterMac]	*MAC address*	Vxlan Router MAC Address.
vxlanVlansWithVirtualPorts	*integer*	Vxlan VLANs with Virtual Ports.
vxlanVlansWithVniMapping	*integer*	Vxlan VLANs with VNI Mappings.

2.1700 show platform trident vxlan vp-usage

allConfigCount	*integer*	Virtual port usage presumed.
allStatusCount	*integer*	Virtual port usage actual.
edgeVpCount	*integer*	Edge virtual port count.
reservedCount	*integer*	Reserved virtual port count.
routableVlanCount	*integer*	Routable VLAN count.
totalUsedCount	*integer*	Total used virtual port count.
vpAllocFailures	*integer*	Virtual port allocation failures.
vpAllocRequests	*integer*	Virtual port allocation requests.
vpFreeRequests	*integer*	Virtual port free requests.
vpTableSize	*integer*	Virtual port table size.
vtepCount	*integer*	Virtual tunnel endpoint count.
vtepGroupCount	*integer*	Virtual tunnel endpoint group count.

2.1701 show platform trident vxlan vtep [...]

[herTunnelVteps]	*table(numeric string) = VxlanRemoteVtepInfoModel* see 2.1701.1	VXLAN HER tunnel VTEPs, keyed by remote ID.
[memberTunnelVteps]	*table(numeric string) = VxlanRemoteVtepInfoModel* see 2.1701.1	VXLAN member tunnel VTEPs, keyed remote ID.
[vxlanTunnelVteps]	*table(numeric string) = VxlanRemoteVtepInfoModel* see 2.1701.1	VXLAN tunnel VTEPs, keyed by remote ID.

2.1701.1 VxlanRemoteVtepInfoModel

[nhInfo]	*VxlanRemoteVtepNextHopInfoModel* see 2.1701.1.1	VXLAN remote VTEP next hop information.
remoteVtep	*IP address*	VXLAN tunnel IP address.

2.1701.1.1 VxlanRemoteVtepNextHopInfoModel

ecmp	*boolean*	VTEP has ECMP next hops.
nextHopId	*integer*	ECMP next hop ID.
rtNhUpdates	*integer*	Number of route next hop updates.

2.1702 show poe [...]

detail **	*boolean*	Show detailed status of each 2-pairs. **Since: 4.29.2
poePorts	*table(string) = PoePort* see 2.1702.1	PoE ports.

2.1702.1 PoePort

[alternative] **	*PoeChannel* see 2.1702.1.1	Details on alternative channel. **Since: 4.29.2
[current]	*floating point number*	Output current (milliamps).
[grantedPower] **	*floating point number*	PoE port granted power (watts). **Since: 4.22.0
[legacyDetectEnabled] **	*boolean*	Legacy detect enabled. **Since: 4.22.0
[lldpEnabled]	*boolean*	LLDP enabled.
[misconfigured] **	*boolean*	Legacy detect and port mode misconfiguraton. **Since: 4.24.2
[pdClass]	*string*	Powered device class.
[portCapacity] **	*floating point number*	PoE port capacity (watts). **Since: 4.23.1
portName	*string*	PoE port name.
[portPairset] **	*enum: fourPair | altB | altA*	Enabled pairset(s). **Since: 4.24.2
portPresent	*boolean*	PoE port present.
[portPriority] **	*enum: medium | high | low | critical*	PoE port priority. Available power is given to higher priority ports. A power supply failure can reduce the available power. **Since: 4.22.1
[portState]	*enum: adminShutdown | overloaded | unknown | invalid | fault | powered | detecting | linkDown | failed | classified | disabled | mismatch*	PoE port state.
[power]	*floating point number*	Output power (watts).
[powerLimit]	*floating point number*	PoE port power limit (watts).
[primary] **	*PoeChannel* see 2.1702.1.1	Details on primary channel. **Since: 4.29.2
[pseEnabled]	*boolean*	PSE functionalities enabled.
[temperature]	*floating point number*	Temperature (celsius).
[voltage]	*floating point number*	Output voltage (volts).

2.1702.1.1 PoeChannel

[current]	*floating point number*	Output current (milliamps).
[pairSet]	*string*	Pairset of the channel.
[pdClass]	*string*	Powered device class.

[portState]	*enum: adminShutdown | overloaded | unknown | invalid | fault | powered | detecting | linkDown | failed | classified | disabled | mismatch*	PoE channel state.
[power]	*floating point number*	Output power (watts).
[pseLimit]	*floating point number*	PoE port power limit (watts).
[voltage]	*floating point number*	Output voltage (volts).

2.1703 show poe histogram [...]

brief	*boolean*	Show brief histogram detail.
histogram	*boolean*	Show PoE port power histogram.
poePorts	*table(string) = PoePortHistory* see 2.1703.1	PoE ports power history.
statistics	*boolean*	Show PoE port power statistics.

2.1703.1 PoePortHistory

[currentPower]	*floating point number*	PoE port power (watts).
[maxPower]	*floating point number*	Max record power (watts).
[minPower]	*floating point number*	Min (non-zero) record power (watts).
[poePowerHistory]	*table(numeric string) = integer*	Rounded PoE power output history.
[portCapacity]	*floating point number*	PoE port capacity (watts).

2.1704 show poe neighbor [...]

poePorts	*table(Interface name) = PoePortNbrInfo* see 2.1704.1	A mapping of PoE port to its information.
powerBudget	*floating point number*	Total power budget in watts.
remainingPower	*floating point number*	Remaining power in watts.
usedPoePower	*floating point number*	Total used PoE output power in watts.

2.1704.1 PoePortNbrInfo

[lldpSystemDesc]	*list of string*	Neighbor system description.
[portState]	*enum: adminShutdown | overloaded | unknown | invalid | fault | powered | detecting | linkDown | failed | classified | disabled | mismatch*	PoE port state.
[power]	*floating point number*	Output power (watts).

2.1705 show poe statistics [...]

see 2.1703

2.1706 show policing [...]

revision 2

pktSizeAdjProfiles	*table(string) = PolicerPktSizeAdjProfileModel* see 2.1706.3	Policer packet size adjustment profiles index by their name.
policerInstances	*table(string) = PolicerInstanceModel* see 2.1706.2	Policer instances indexed by their name.
[priorityGroups] **	*PriorityGroupsInstanceModel* see 2.1706.4	Priority groups instances. **Since: 4.35.2
profiles	*table(string) = ProfileModel* see 2.1706.1	Profiles indexed by their name.

2.1706.1 ProfileModel

[configuredIngressIntfs]	*table(Interface name) = boolean*	A mapping of interface to whether it is configured on ingress.
police	*PoliceModel* see 2.1706.1.1	Policing configuration associated with profiles.
[policerAssociations]	*list of string*	Policers to which the profile is attached.
[priorityGroupAssociations] **	*priorityGroupAssociationModel* see 2.1706.1.2	Priority groups to which the profile is attached. **Since: 4.35.2
profileName	*string*	Profile name.

2.1706.1.1 PoliceModel

bc	*integer*	Committed Burst Rate.
bcUnit	*enum: packets | bytes | kbytes | mbytes*	burst unit.
be	*integer*	Excess Burst Size.
beUnit	*enum: packets | bytes | kbytes | mbytes*	burst unit.
cir	*integer*	Committed Information Rate.
[cirMax] **	*integer*	Maximum Committed Information Rate. **Since: 4.35.0
[cirMaxUnit] **	*enum: mbps | pps | kbps | bps*	CIRMAX unit. **Since: 4.35.0
cirUnit	*enum: mbps | pps | kbps | bps*	CIR unit.
[colorAware] **	*boolean*	Color Aware Flag. **Since: 4.34.2
[counters]	*table(string) = PoliceCounters* see 2.1706.1.1.1	A mapping from direction ('input' or 'output') to per interface police counters.
[couplingFlag] **	*boolean*	Coupling Flag. **Since: 4.34.2
[greenCounter]	*boolean*	Green counter is supported.

[perSviRedCounterWith-SharedPolicer]	*boolean*	Red counter per interface in shared policer mode is supported.
pir	*integer*	Peak Information Rate.
[pirMax] **	*integer*	Maximum Peak Information Rate. **Since: 4.35.0
[pirMaxUnit] **	*enum: mbps | pps | kbps | bps*	PIRMAX unit. **Since: 4.35.0
pirUnit	*enum: mbps | pps | kbps | bps*	PIR unit.
[policerName]	*string*	Policer name.
[redCounter]	*boolean*	Red counter is supported.
[yellowActions]	*PolicerActions* see 2.1706.1.1.2	Yellow Actions applicable only for trTCM Policer.

2.1706.1.1.1 PoliceCounters

[interfaces]	*table(string) = IntfPoliceCounters* see 2.1706.1.1.1.1	Police Counters.

2.1706.1.1.1.1 IntfPoliceCounters

[conformedBitsRate] **	*floating point number*	Conformed bits rate in bps. **Since: 4.29.2
conformedBytes	*integer*	Conformed number of bytes to policer.
conformedPackets	*integer*	Conformed number of packets to policer.
[droppedBitsRate] **	*floating point number*	Dropped bits rate in bps. **Since: 4.29.2
[exceededBitsRate] **	*floating point number*	Excess bits rate in bps. **Since: 4.29.2
exceededBytes	*integer*	Exceeded number of bytes to policer.
exceededPackets	*integer*	Exceeded number of packets to policer.
[updateInterval] **	*floating point number*	Stats update interval in seconds. **Since: 4.29.2
yellowBytes **	*integer*	Conformed number of bytes to PIR and not CIR. **Since: 4.20.5
yellowPackets **	*integer*	Conformed number of packets to PIR and not CIR. **Since: 4.20.5

2.1706.1.1.2 PolicerActions

[dropPrecedence]	*boolean*	Mark Drop-Prcedence.
[dscp]	*integer*	DSCP value.
[dscpConfiguredAsName]	*boolean*	The DSCP value was configured as a name.

2.1706.1.2 priorityGroupAssociationModel

priorityGroups	*table(string) = priorityListModel* see 2.1706.1.2.1	priorities in a priority group to which the profile is applied.

2.1706.1.2.1 priorityListModel

priorities	*list of integer*	priorites.

2.1706.2 PolicerInstanceModel

[configuredIngressIntfs]	*table(Interface name) = boolean*	A mapping of interface to whether it is configured on ingress.
policerName	*string*	Policer instance name.
profileName	*string*	Profile associated with Policer instance.

2.1706.3 PolicerPktSizeAdjProfileModel

[configuredIngressIntfs]	*table(Interface name) = HwProgrammingEnumModel* see 2.1706.3.1	A mapping of interface to whether it is configured on ingress.
pktSizeAdj	*integer*	Packet size adjustment configuration associated with profiles.
profileName	*string*	Profile name.

2.1706.3.1 HwProgrammingEnumModel

hwState	*enum: inactive | partial | active*	Hardware programming state.

2.1706.4 PriorityGroupsInstanceModel

priorityGroups	*table(string) = PriorityGroupModel* see 2.1706.4.1	Map of profiles applied to a priority group.

2.1706.4.1 PriorityGroupModel

priority	*table(numeric string) = string*	Profile associated with a priority level in a priority group.

2.1707 show policing interfaces [...]

intfCpuPolicerInfo **	*table(Interface name) = InterfacePolicerModel* see 2.1707.1	CPU interface-policer info keyed by interface. **Since: 4.29.0
intfEgrPolicerInfo **	*table(Interface name) = InterfacePolicerModel* see 2.1707.1	Egress interface-policer info keyed by interface. **Since: 4.29.0

intfPolicerInfo	*table(Interface name) = InterfacePolicerModel* see 2.1707.1	Ingress interface-policer info keyed by interface.

2.1707.1 InterfacePolicerModel

isConfigured	*HwProgrammingEnumModel* see 2.1706.3.1	Interface programming status.
[policerName]	*string*	Group policer.
[portChannelMembers]	*table(Interface name) = HwProgrammingEnumModel* see 2.1706.3.1	A mapping of member interface to whether it is configured.
[profileName]	*string*	Profile name.

2.1708 show policing interfaces counters [...]

cpuInterfaces **	*table(Interface name) = InterfacePolicingCounterModel* see 2.1708.1	Interface CPU policing counter info keyed by interface. **Since: 4.29.0
egrInterfaces **	*table(Interface name) = InterfacePolicingCounterModel* see 2.1708.1	Interface egress policing counter info keyed by interface. **Since: 4.29.0
interfaces	*table(Interface name) = InterfacePolicingCounterModel* see 2.1708.1	Interface ingress policing counter info keyed by interface.

2.1708.1 InterfacePolicingCounterModel

counters	*IntfPoliceCounters* see 2.1706.1.1.1.1	Policer Counters.
mode	*enum: trtcm | committed*	Policer mode.
[policerName]	*string*	Group policer.
[profileName]	*string*	Profile name.

2.1709 show policing policy-map type qos [...]

priorityGroups	*table(string) = Qos.Model.PriorityGroupPmapCmapAttachmentModel* see 2.1709.1	priority group policy-map attachment points.

2.1709.1 Qos.Model.PriorityGroupPmapCmapAttachmentModel

`priority`	*table(numeric string) = Qos.Model.PmapCmapAttachmentModel* see 2.1709.1.1	priority in a priority-group to policy-map class-map attachment point.

2.1709.1.1 Qos.Model.PmapCmapAttachmentModel

`policyMaps`	*table(string) = Qos.Model.CmapAttachmentModel* see 2.1709.1.1.1	policy-map to which a priority-group is attached.

2.1709.1.1.1 Qos.Model.CmapAttachmentModel

`classMaps`	*list of string*	class-maps to which a priority-group is attached.

2.1710 show policing priority-group [...]

see 2.1706.4

2.1711 show policy-map PMAP class CMAP [...]

revision 4

[classMap]	*ClassMap* see 2.1711.1	Wrapper around a class map.

2.1711.1 ClassMap

[bandwidth]	*BandwidthModel* see 2.1711.1.1	Bandwidth associated with the policy class, applicable only for CoPP policy maps.
[classMapStatistics]	*table(string) = ClassMapStatistics* see 2.1711.1.3	A mapping from direction ('input' or 'output') to class maps counter statistics.
classPrio	*integer*	Class priority - lower value has precedence.
[coppActionPoliceSupported]	*boolean*	Control plane policer supported.
[coppFlowBasedPolicer-Supported] **	*boolean*	Control plane flow based policer supported. **Since: 4.34.1
[count]	*boolean*	Count number of packets matching the policy class.
[intfPacketCounters]	*table(string) = IntfPacketCounters* see 2.1711.1.5	A mapping from direction ('input' or 'output') to per interface packet counters.
[isDisabled] **	*boolean*	disabled or not. **Since: 4.35.0
[mapType]	*enum: mapQos | mapPdp | mapControlPlane*	Determines if the class map is for CoPP or Qos or PDP policy map.
[match]	*table(string) = Match* see 2.1711.1.4	Matching access groups.
[matchCondition]	*enum: matchConditionAny | unspecified*	Match condition.
[matchedPackets]	*table(string) = ClassMapMatchPacket-CounterCollection* see 2.1711.1.2	A mapping from direction ('input' or 'output') to number of packets matched.
name	*string*	Name of class map.
[police]	*PoliceModel* see 2.1706.1.1	Ingress policing associated with the policy class.
[policerCounters] **	*table(string) = PoliceCounters* see 2.1706.1.1.1	A mapping from direction ('input' or 'output') to per interface police counters. **Since: 4.36.0
[policers] **	*PolicersModel* see 2.1711.1.6	Ingress policers associated with the policy class. **Since: 4.35.2
[qosParams]	*QosParams* see 2.1711.1.7	Value of Qos parameters, applicable only for Qos policy maps.
[shape]	*ShapeRateModel* see 2.584.1.1.1.2	Shape rate associated with the policy class, applicable only for CoPP policy maps.

2.1711.1.1 BandwidthModel

rate	*integer*	Bandwith supported.
unit	*enum: unspecified* | *pps* | *kbps* | *gbps*	Bandwidth unit.

2.1711.1.2 ClassMapMatchPacketCounterCollection

[interfaces]	*table(string) = ClassMapMatchPacketCounter* see 2.1711.1.2.1	Interface Matched Packets.

2.1711.1.2.1 ClassMapMatchPacketCounter

[packets]	*integer*	Number of packets matched.

2.1711.1.3 ClassMapStatistics

[conformedBitsRate]	*floating point number*	Conformed bits rate in bps.
[droppedBitsRate]	*floating point number*	Dropped bits rate in bps.
[exceededBitsRate]	*floating point number*	Excess bits rate in bps.
[updateInterval]	*floating point number*	Stats update interval in seconds.

2.1711.1.4 Match

[dscpValue]	*integer*	DSCP equivalent value in digits.
[l2ParamsValue]	*MatchL2Params* see 2.300.1.1.1	L2 Params values configured.
[matchDscpNameValid]	*boolean*	Flag to identify if string value of DSCP is used or numeric value.
[matchEcnValue]	*enum: dontCare* | *ect-ce* | *ect* | *non-ect* | *ce*	ECN value configured.
matchRule	*enum: matchMacAccessGroup* | *matchIpv6AccessGroup* | *matchDscpEcn* | *matchMplsTrafficClass* | *matchL2Params* | *matchIpAccessGroup*	Matching rule for the type.

2.1711.1.5 IntfPacketCounters

[dropPackets]	*integer*	Number of packets dropped.
[outPackets]	*integer*	Number of out packets.

2.1711.1.6 PolicersModel

[police]	*PoliceModel* see 2.1706.1.1	default policer associated with the policy class.
[priorityGroup]	*priorityGroupInstanceModel* see 2.1711.1.6.1	Priority-group associated with a policy class.

2.1711.1.6.1 priorityGroupInstanceModel

priority	*integer*	Priority associated with priority group instance.
priorityGroupName	*string*	Priority-group instance name.

2.1711.1.7 QosParams

[cos]	*integer*	COS value.
[drop]	*boolean*	Drop Packets.
[dropActionRestricted]	*boolean*	Is drop action restricted on the system.
[dropPrecedence]	*integer*	Drop Precedence value.
[dscp]	*integer*	DSCP value.
[dscpConfiguredAsName]	*boolean*	Flag to identify if the DSCP value was configured as a name.
[trafficClass]	*integer*	Traffic Class value.

2.1712 show policy-map PMAP counters [...]

revision 4

mapType	*enum: mapQos | mapPdp | mapCoppCli | mapControlPlane*	Determines if it is a CoPP or Qos or PDP policy map.
[maxCmapsPerPolicy]	*integer*	Maximum number of class maps supported per policy map.
policyMaps	*table(string) = PolicyMapModel* see 2.1712.1	List of all policy maps.

2.1712.1 PolicyMapModel

[activeIntfs]	*table(string) = InterfaceList* see 2.1712.1.2	Dictionary of list of interfaces with the policy active for the directions('input', 'output').
classMaps	*table(string) = ClassMap* see 2.1711.1	List of class maps for a given policy map.
[configuredIntfs]	*table(string) = InterfaceList* see 2.1712.1.2	Dictionary of list of interfaces with the policy configured for the directions('input', 'output').
hwStatus	*table(string) = HwStatus* see 2.1712.1.1	Hardware status for direction ('input', 'output').
[inactiveIntfs]	*table(string) = InterfaceList* see 2.1712.1.2	Dictionary of list of interfaces with the policy inactive for the directions('input', 'output').
mapType	*enum: mapQos | mapPdp | mapControlPlane*	Determines if it is a CoPP or Qos or PDP policy map.
name	*string*	Name of policy map.
[shared]	*boolean*	True if the policy map is shared.
spApplied	*table(string) = boolean*	True for the directions('input', 'output')having service policy.
summary	*boolean*	Print summary info.

2.1712.1.1 HwStatus

status	*enum: hwPrgmStatusSuccess | hwPrgmStatusFail | hwPrgmStatusInProgress*	Hardware programming status.
[unitsProgrammed]	*integer*	Number of units programmed.

2.1712.1.2 InterfaceList

[interfaces]	*list of Interface name*	List of interfaces.

2.1713 show policy-map [...]

revision 4

see 2.1712

2.1714 show policy-map copp PMAP

`intfIds`	*list of Interface name*	List of associated interfaces.

2.1715 show policy-map copp copp-system-policy

revision 4

see 2.1712

2.1716 show policy-map counters [...]

revision 4

see 2.1712

2.1717 show policy-map interface (INTF | SVI_INTF | VTI_INTF) [...]

revision 4

see 2.1712

2.1718 show policy-map interface INTF type control-plane

revision 4

see 2.1712

2.1719 show policy-map type copp (copp-system-policy | PMAP) class CMAP

revision 4

see 2.1711

2.1720 show policy-map type copp [...]

revision 4

see 2.1712

2.1721 show policy-map type copp counters [...]

revision 4

see 2.1712

2.1722 show policy-map type pbr [...]

revision 2

intf	*table(string) = string*	Policy map to intf map.
mapType	*enum: mapTrafficPolicy | mapTapAgg | mapSamplePolicy | mapQos | mapServerLoadBalancer | mapFlowspec | mapPbr*	Map type.
policyMaps	*table(string) = PolicyMapModel* see 2.1722.1	List of policy maps.

2.1722.1 PolicyMapModel

[appliedIngressIntfs]	*list of string*	List of interfaces with the policy applied on ingress.
[classMap]	*table(numeric string) = PolicyClassMapModel* see 2.1722.1.1	Mapping of priority to class map status.
[configuredIngressIntfs]	*list of string*	List of interfaces with the policy configured on ingress.
[configuredIngressIntfsAsFallback]	*list of string*	List of interfaces with the policy configured on ingress as fallback policy.
mapType	*enum: mapTrafficPolicy | mapTapAgg | mapSamplePolicy | mapQos | mapServerLoadBalancer | mapFlowspec | mapPbr*	Map type.
name	*string*	Name of policy map.
[rawClassMap]	*table(string) = ClassMapModel* see 2.302.1	Pseudo class maps for single match statements.

2.1722.1.1 PolicyClassMapModel

Could also be an instance of:
PbrPolicyClassMapModel 2.1722.1.2

[actionSetConfig] **	*ActionSetModel* see 2.1722.1.1.18	Action set configuration. **Since: 4.29.1
classMap	*ClassMapModel* see 2.302.1	Class map configuration.
[configuredAction]	*table(string) = ActionModel* see 2.1722.1.1.1	List of class actions.
name	*string*	Class map name.

2.1722.1.1.1 ActionModel

Could also be an instance of:
DropActionModel 2.1722.1.1.2
FwdActionModel 2.1722.1.1.3

NexthopGroupModel 2.1722.1.1.4
NexthopModel 2.1722.1.1.5
NoActionModel 2.1722.1.1.6
SetDscpModel 2.1722.1.1.7
SetTtlModel 2.1722.1.1.8
TapAggActionSetModel 2.1722.1.1.9
TapAggDropActionModel 2.1722.1.1.10
TapAggGroupModel 2.1722.1.1.11
TapAggHeaderRemoveActionModel 2.1722.1.1.12
TapAggIdTagModel 2.1722.1.1.13
TapAggMacAddressActionModel 2.1722.1.1.14
TapAggNexthopGroupModel 2.1722.1.1.15
TapAggStripHdrModel 2.1722.1.1.16
TapAggTimestampHeaderModel 2.1722.1.1.17

`actionType`	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.

2.1722.1.1.2 DropActionModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.

2.1722.1.1.3 FwdActionModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.

2.1722.1.1.4 NexthopGroupModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.
nexthopGroup	*string*	Next hop group name.

2.1722.1.1.5 NexthopModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.

[allowResolutionByDefault] **	*boolean*	Allow next hop resolution via default route. **Since: 4.35.0
nexthops	*table(numeric string) = IpGenericAddr* see 2.365.1.1.1.1	Set of next hops.
recursive	*boolean*	recursive or not.
vrfName	*string*	VRF name.

2.1722.1.1.6 NoActionModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.

2.1722.1.1.7 SetDscpModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.
dscpValue	*integer*	DSCP value.

2.1722.1.1.8 SetTtlModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.
ttlValue	*integer*	TTL value.

2.1722.1.1.9 TapAggActionSetModel

actionSet	*list of string*	List of action sets.
actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.

2.1722.1.1.10 TapAggDropActionModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.

2.1722.1.1.11 TapAggGroupModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.
[aggGroup]	*list of string*	List of TapAgg Groups to flow the traffic.
[aggIntf]	*list of Interface name*	List of Tool Interfaces to flow the traffic.

2.1722.1.1.12 TapAggHeaderRemoveActionModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.
preserveEth	*boolean*	Preserve the original Ethernet header, including VLAN tags if any.
size	*integer*	The number of bytes to remove after the Ethernet header, including any VLAN tags.

2.1722.1.1.13 TapAggIdTagModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.

idTag	*integer*	Id-tag value.
innerIdTag	*integer*	Inner id-tag value.

2.1722.1.1.14 TapAggMacAddressActionModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.
destMac	*MAC address*	Destination MAC address.
srcMac **	*MAC address*	Source MAC address. **Since: 4.27.2

2.1722.1.1.15 TapAggNexthopGroupModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.
[nexthopGroup]	*list of string*	List of nexthop-groups to flow the traffic.

2.1722.1.1.16 TapAggStripHdrModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.
dot1qRemoveVlans	*string*	VLAN indices to be removed.
hdrType	*enum: noStrip* | *dot1q*	Header type.

2.1722.1.1.17 TapAggTimestampHeaderModel

actionType	*enum: setNexthopGroup* | *deny* | *actionShaping* | *loadBalance* | *sample* | *actionSet* | *setIdentityTag* | *setHeaderRemove* | *setVrf* | *setVrfSecondary* | *redirectVxlan* | *permit* | *stripHeaderBytes* | *reportFlow* | *setTimestampHeader* | *mirror* | *maxActionEnum* | *setAggregationGroup* | *log* | *police* | *useVrfSecondary* | *setDecapVrf* | *sessionOffload* | *sampleAll* | *verifyFlowReturnFailure* | *sflow* | *setMacAddress* | *redirectVrfRouteTarget* | *accessList* | *redirectTunnel* | *flowTracking* | *actionTest1* | *actionTest3* | *actionTest2* | *setDscp* | *actionGoto* | *fwdAction* | *count* | *setNexthop* | *setTc* | *setTtl*	class action type.

2.1722.1.1.18 ActionSetModel

[actionSets]	*table(string) = NamedActionSetModel* see 2.1722.1.1.18.1	A mapping from action set name to actions.

2.1722.1.1.18.1 NamedActionSetModel

[actions]	*table(string) = ActionModel* see 2.1722.1.1.1	A mapping from action type to action value.
name	*string*	Action set name.

2.1722.1.2 PbrPolicyClassMapModel

[actionSetConfig] **	*ActionSetModel* see 2.1722.1.1.18	Action set configuration. **Since: 4.29.1
classMap	*ClassMapModel* see 2.302.1	Class map configuration.
[configuredAction]	*table(string) = ActionModel* see 2.1722.1.1.1	List of class actions.
name	*string*	Class map name.
[vrfs]	*table(string) = PbrPolicyClassMapVrfModel* see 2.1722.1.2.1	mapping of vrf name to policies.

2.1722.1.2.1 PbrPolicyClassMapVrfModel

action	*enum: nexthopGroupAction | nexthopAction | dropAction | noAction*	Type of routing action programmed for the vrf.
[actionVrf]	*string*	Name for egress vrf.
[nexthopGroup]	*string*	Nexthop group programmed for the vrf.
[nexthops]	*list of IpGenericAddr* see 2.365.1.1.1.1	Nexthops programmed for the vrf.
[ttl]	*integer*	TTL value.

2.1723 show policy-map type tapagg [...]

revision 2

see 2.1722

2.1724 show port numbering

numberingScheme	*enum: unknown | qsfpDense | default | OCTAL4 | qsfpExpanded | notAvailable | qsfpSparse*	Port numbering scheme.

2.1725 show port-channel [...]

see 2.134

2.1726 show port-channel dense

numberOfAggregators	*integer*	Number of aggregators.
numberOfChannelsInUse	*integer*	Number of channels in use.
portChannels	*table(Interface name) = PortChannelSummary* see 2.1726.1	Port-channels summary.

2.1726.1 PortChannelSummary

[fallback]	*FallbackConfigStatus* see 2.1726.1.1	Lag fallback status.
inactive **	*boolean*	Exceeds config limit. **Since: 4.25.0
[lacpMode]	*enum: passive | active | off*	LACP active or passive mode.
linkState	*enum: down | up*	state - port channels is up or down.
ports	*table(Interface name) = PortChannelMember-Summary* see 2.1726.1.2	Interfaces in port channel.
protocol	*enum: static | lacp | unconfigured*	Lag mode configuration.

2.1726.1.1 FallbackConfigStatus

[config]	*enum: fallbackStatic | fallbackIndividual*	Lag fallback type.
[status]	*enum: fallbackStatic | fallbackIndividual*	Lag fallback type.

2.1726.1.2 PortChannelMemberSummary

[exceedsMaxWeight] **	*boolean*	Exceeds maximum allowed weight. **Since: 4.26.2
intf	*interface name*	Interface name.
[lacpMisconfig]	*LacpMisconfig* see 2.1726.1.2.1	LACP misconfiguration state.
[lacpState]	*LacpPortState* see 2.971.1.2	LACP port state.
lagMember	*boolean*	Active member of the LAG.
linkDown	*boolean*	Is the interface down?
staticLag	*boolean*	Port is configured in a static LAG.
suspended	*boolean*	Interface is not active in the Port-Channel (wrong speed).
[txDisabled] **	*boolean*	Transmit disabled. **Since: 4.31.0

2.1726.1.2.1 LacpMisconfig

status	*enum: unknown | bundled | noAgg | idle | standby | negotiation | mismatchAgg*	LACP misconfiguration flags.

2.1727 show port-channel limits

portChannelLimits	*table(string) = LagGroupLimits* see 2.135.1	Map a LAG Group name to the ports it applies to, and the hardware lag limits applicable to them.

2.1728 show port-channel load-balance (jericho | jericho2 | jericho3 | jericho4) fields [...]

revision 4

see 2.1003

2.1729 show port-channel load-balance [...]

portChannels	*table(Interface name) = PortChannelTraffic* see 2.1729.1	Map the port-channel to interface traffic distribution.

2.1729.1 PortChannelTraffic

interfaceTraffic	*table(Interface name) = InterfaceTraffic* see 2.1729.1.1	Map from physical interface name to packet categories.

2.1729.1.1 InterfaceTraffic

inBroadcastPkts	*floating point number*	Broadcast packets received on this physical port, expressed as a percentage of total port-channel broadcast packets.
inMulticastPkts	*floating point number*	Multicast packets received on this physical port, expressed as a percentage of total port-channel multicast packets.
inUcastPkts	*floating point number*	Unicast packets received on this physical port, expressed as a percentage of total port-channel unicast packets.
outBroadcastPkts	*floating point number*	Broadcast packets sent on this physical port, expressed as a percentage of total port-channel broadcast packets.
outMulticastPkts	*floating point number*	Multicast packets sent on this physical port, expressed as a percentage of total port-channel multicast packets.
outUcastPkts	*floating point number*	Unicast packets sent on this physical port, expressed as a percentage of total port-channel unicast packets.

2.1730 show port-channel load-balance distribution

globalDlbLagEnabled	*boolean*	Dynamic load balancing on LAG is enabled globally.

2.1731 show port-channel load-balance trident fields

hashFunction	*enum: CRC32LO | CRC16CCITT | CRC32HI*	Hashing function implemented on this platform.
hashSeed	*integer*	hash seed.
lagHashFieldsCommon	*LagHashFieldsCommon* see 2.1731.1	Lag hashing on MISC fields.
lagHashFieldsGre	*LagHashFieldsGre* see 2.1731.2	Lag hashing on GRE fields.
lagHashFieldsGtp	*LagHashFieldsGtp* see 2.1731.3	Lag hashing on GTP fields.
lagHashFieldsIp	*LagHashFieldsIp* see 2.1731.4	Lag hashing on IP fields.
lagHashFieldsIpv6	*LagHashFieldsIpv6* see 2.1731.5	Lag hashing on IPV6 fields.
lagHashFieldsMac	*LagHashFieldsMac* see 2.1731.6	Lag hashing on MAC fields.
lagHashFieldsMim	*LagHashFieldsMim* see 2.1731.7	Lag hashing on MIM fields.
lagHashFieldsMpls	*LagHashFieldsMpls* see 2.1731.8	Lag hashing on MPLS fields.

2.1731.1 LagHashFieldsCommon

sysMacAddr	*boolean*	Lag hashing on the system MAC address.

2.1731.2 LagHashFieldsGre

ip6Ip6Outer	*boolean*	Lag hashing on GRE IPv6 over IPv6 outer IP address.
ip6IpOuter	*boolean*	Lag hashing on GRE IPv6 over IPv4 outer IP address.
ipIp6Outer	*boolean*	Lag hashing on GRE IPv4 over IPv6 outer IP address.
ipIpOuter	*boolean*	Lag hashing on GRE IPv4 over IPv4 outer IP address.
l2GreKey **	*boolean*	Lag hashing on L2 GRE Key. **Since: 4.33.0

2.1731.3 LagHashFieldsGtp

gtpVersion	*string*	Hash on either GTP version 1 or 2.
teid	*boolean*	Lag hashing on GTP teid.

2.1731.4 LagHashFieldsIp

Could also be an instance of:
LagHashFieldsIpv6 2.1731.5

dstIpHashable	*boolean*	Lag hashing on destination IP address.
dstIpPortHashable	*boolean*	Lag hashing on destination IP port.

ingressIntfHashable	*boolean*	Lag hashing on ingress interface.
ipProtocolHashable	*boolean*	Lag hashing on the IP Protocol.
l34HeaderHashable	*boolean*	Lag hashing on layer 3 an 4 headers.
macHeader	*boolean*	MAC header exists.
srcIpHashable	*boolean*	Lag hashing on source IP address.
srcIpPortHashable	*boolean*	Lag hashing on source IP port.
symmetricHash	*boolean*	Symmetric hashing in use.
ttlHashable	*boolean*	Lag hashing on TTL/next hop.
vlanHashable **	*boolean*	Lag hashing on VLAN. **Since: 4.32.1

2.1731.5 LagHashFieldsIpv6

dstIpHashable	*boolean*	Lag hashing on destination IP address.
dstIpPortHashable	*boolean*	Lag hashing on destination IP port.
flowLabel	*boolean*	Lag hashing on flow label.
ingressIntfHashable	*boolean*	Lag hashing on ingress interface.
ipProtocolHashable	*boolean*	Lag hashing on the IP Protocol.
l34HeaderHashable	*boolean*	Lag hashing on layer 3 an 4 headers.
macHeader	*boolean*	MAC header exists.
srcIpHashable	*boolean*	Lag hashing on source IP address.
srcIpPortHashable	*boolean*	Lag hashing on source IP port.
symmetricHash	*boolean*	Symmetric hashing in use.
ttlHashable	*boolean*	Lag hashing on TTL/next hop.
vlanHashable **	*boolean*	Lag hashing on VLAN. **Since: 4.32.1

2.1731.6 LagHashFieldsMac

ethTypeHashable	*boolean*	Lag hashing on ether type.
ingressIntfHashable	*boolean*	Lag hashing on ingress interface.
macDstHashable	*boolean*	Lag hashing on destination MAC address.
macSrcHashable	*boolean*	Lag hashing on source MAC address.
vlanHashable **	*boolean*	Lag hashing on VLAN. **Since: 4.32.1

2.1731.7 LagHashFieldsMim

isidHashable	*boolean*	Lag hashing on MIM ISID.
macDstHashable	*boolean*	Lag hashing on MIM destination MAC address.
macSrcHashable	*boolean*	Lag hashing on MIM source MAC address.
outerMac	*boolean*	Lag hashing on outer MAC.

2.1731.8 LagHashFieldsMpls

dstPortHashable **	*boolean*	Lag hashing on destination port. **Since: 4.31.0
ipDstHashable	*boolean*	Lag hashing on IP destination address.
ipSrcHashable	*boolean*	Lag hashing on IP source address.

labelHashable	*boolean*	Lag hashing on MPLS label.
outerMac	*boolean*	Lag hashing on outer MAC.
srcPortHashable **	*boolean*	Lag hashing on source port. **Since: 4.31.0
symmetricHash **	*boolean*	Lag MPLS Symmetric hashing in use. **Since: 4.31.0

2.1732 show port-channel load-balance trident udf

udfConfig	*list of StrataLagUdfHash-LoadBalanceModel* see 2.1732.1	list of user defined field hashes.

2.1732.1 StrataLagUdfHashLoadBalanceModel

etherType	*enum: IPv6 | IPv4*	Ethernet type.
headerStr	*string*	known header to start the offset.
ipProto	*string*	IP protocol.
mask	*integer*	mask for the offset.
offset	*integer*	packet offset in bytes from the known header.
status	*boolean*	HW status of the configuration.

2.1733 show port-security

persistence **	*boolean*	Port security protect mode is persistent. **Since: 4.25.0
portStatistics	*table(Interface name) = PortStatistic* see 2.1733.1	Port Security Statistics.
secureAddressAging **	*boolean*	A secured address can age out. **Since: 4.25.0
secureAddressMoves **	*boolean*	A secured address can move. **Since: 4.25.0
shutdownPersistence **	*boolean*	Port security shutdown mode is persistent. **Since: 4.34.2
totalAddresses	*integer*	Total number of addresses in the system.

2.1733.1 PortStatistic

currentAddr	*integer*	Current number of address learned.
intfStaticOnly **	*boolean*	Set the limit to number of static MACs on the port. **Since: 4.33.1
intfTotalMacLimitDisabled **	*boolean*	Interface total MAC limit disabled. **Since: 4.33.0
maxSecureAddr	*integer*	Maximum number of learned addresses.
numberOfViolations	*integer*	Number of security violations that have occurred.

`securityAction`	*enum: none* | *shutdown* | *protect*	Action to take to protect the ports security.

2.1734 show port-security interface [...]

interfaces	*table(Interface name)* = *Interface* see 2.1734.1	Per interface breakdown of port-security information.

2.1734.1 Interface

[addressChanges]	*integer*	Number of learn/move/age events on the interface.
agingTime	*integer*	Time before addresses age out (in minutes).
agingType	*inactivity*	Criteria for an address aging.
[allowedAddresses] **	*list of string*	Which Address:VlanId are allowed in protect mode. **Since: 4.15.3
[configuredMacAddresses]	*integer*	Number of configured MAC addresses on the interface.
[lastChangeDetails]	*InterestingAddress* see 2.1734.1.1	Last changed source address information.
[lastViolation]	*InterestingAddress* see 2.1734.1.1	Last violating address information.
logAddrsAfterLimit **	*enum: enabled* | *disabled*	Log new addresses seen past limit in protect mode. **Since: 4.15.3
maxMacAddresses	*integer*	Maximum MAC addresses allowed on the interface.
persistence **	*boolean*	Port security protect mode is persistent. **Since: 4.25.0
[portMaxEnabled] **	*boolean*	Port level limit is enabled. **Since: 4.25.1
portSecurityEnabled	*boolean*	Is port security enabled.
portStatus	*enum: secure-shutdown* | *secure-up* | *secure-protected* | *secure-down*	The status of the interface under port security.
secureAddressAging **	*boolean*	A secured address can age out. **Since: 4.25.0
secureAddressMoves **	*boolean*	A secured address can move. **Since: 4.25.0
secureStaticAddressAging	*disabled*	Are Secure Static addresses allowed to age (currently unused).
[securityViolationCount]	*integer*	Number of security violations on the interface.
shutdownPersistence **	*boolean*	Port security shutdown mode is persistent. **Since: 4.34.2
staticOnly **	*boolean*	Whether port-security is set to static-only mode. **Since: 4.33.1
[totalMacAddresses]	*integer*	Number of addresses learned on the interface.
violationMode	*enum: none* | *shutdown* | *protect*	Action port security will take to stop a violation.

2.1734.1.1 InterestingAddress

macAddress	*MAC address*	MAC Address.
time	*floating point number*	UTC representation of when the event occurred.
vlan	*integer*	VLAN the MAC address is in.

2.1735 show port-security mac-address

addresses	*list of Address* see 2.1735.1	Statistics for MAC addresses under port-security for this criteria.
totalAddresses	*integer*	Total number of MAC address under port-security for this criteria.

2.1735.1 Address

entryType	*enum: secureDynamic | secureConfigured*	Type of secured host.
interface	*interface name*	Interface that the address is learned on.
macAddress	*MAC address*	MAC address of host.
[remainingAge]	*integer*	Remaining minutes before interface ages out.
vlan	*integer*	VLAN host is learned in.

2.1736 show port-security vlan [...]

interfaces	*table(Interface name) = VlanDict* see 2.1736.1	Per interface breakdown of vlan based port-security information.
totalAddresses	*integer*	Total number of addresses in the system.

2.1736.1 VlanDict

vlans	*table(numeric string) = VlanStatistic* see 2.1736.1.1	Per vlan breakdown of vlan based port-security information.

2.1736.1.1 VlanStatistic

action	*enum: none | shutdown | protect*	Action to take to protect the ports security.
maxAddrs	*integer*	Maximum number of learned addresses.
numAddrs	*integer*	Current number of learned addresses.
numViolations	*integer*	Number of security violations that have occurred on the VLAN.

2.1737 show priority-flow-control [...]

revision 3

see 2.558

2.1738 show priority-flow-control buffer counters [...]

see 2.559

2.1739 show priority-flow-control buffer on-chip counters [...]

see 2.559.4

2.1740 show priority-flow-control counters [...]

revision 3

see 2.561

2.1741 show priority-flow-control counters detail [...]

revision 3

see 2.562

2.1742 show priority-flow-control counters history [...]

`interfaces`	*table(Interface name) = PfcIntfHistoryCounters-Model* see 2.1742.1	A mapping of interface name to priority flow control history counters.
`lastClearTimestamp`	*floating point number*	UTC timestamp when clear command was last issued.

2.1742.1 PfcIntfHistoryCountersModel

`priorities`	*table(numeric string) = PfcHistoryCountersModel* see 2.1742.1.1	A mapping of priority value to priority flow control history counters.

2.1742.1.1 PfcHistoryCountersModel

`[maxRxPfcOnTimeNs]`	*integer*	Max RX PFC on duration in ns.
`[maxRxPfcOnTimestamp]`	*floating point number*	UTC timestamp when max RX PFC on duration was recorded.

[totalRxPfcOnTimeNs]	*integer*	Total RX PFC on duration in ns.
[totalRxPfcOnTransitions]	*integer*	Total RX PFC on transitions.

2.1743 show priority-flow-control counters watchdog [...]

revision 2

see 2.563

2.1744 show priority-flow-control counters watchdog drop [...]

revision 3

see 2.564

2.1745 show priority-flow-control interfaces Fabric status

see 2.570

2.1746 show priority-flow-control interfaces packet-buffer profile [...]

interfaces	*table(Interface name) = PfcIntfPacketBufferProfile-Model* see 2.1746.1	A mapping of interface name to priorities mapped to packet-buffer profiles.

2.1746.1 PfcIntfPacketBufferProfileModel

priorities	*table(numeric string) = string*	A mapping of priority to packet-buffer profile.

2.1747 show priority-flow-control packet descriptor counters [...]

see 2.559.4

2.1748 show priority-flow-control packet-buffer profile [...]

headroomPercent	*integer*	Percent of global resources allocated to headroom pool.
losslessPriorities	*list of integer*	Priorities assigned to lossless profiles.
profiles	*table(string) = PfcPacket-BufferProfileModel* see 2.1748.1	A mapping of priority-flow-control packet-buffer profile name to profile model.

2.1748.1 PfcPacketBufferProfileModel

headroom	*integer*	Reserved bytes to buffer packets in-flight after PFC.
pauseAlpha	*integer*	Dynamic PFC pause burst-absorption-factor.
pauseMax	*integer*	Maximum buffered bytes before PFC pause.
pauseMin	*integer*	Minimum buffered bytes before PFC pause.
rejectAlpha	*integer*	Dynamic PFC drop threshold burst-absorption-factor.
rejectMax	*integer*	Maximum buffered bytes before packets dropped.
rejectMin	*integer*	Minimum buffered bytes before packets dropped.
resumeOffset	*integer*	Bytes offset from PFC pause threshold to unpause.
state	*enum: pending | modified | active | invalid*	Profile state after profile validation.

2.1749 show priority-flow-control status [...]

revision 2

see 2.566

2.1750 show privilege

privilegeLevel	*integer*	The current privilege level.

2.1751 show processes

processes	*table(numeric string) = ProcessInfo* see 2.1751.1	Mappping of a process pid to the detailed process information.
timeInfo	*SystemTimeInfo* see 2.1751.2	uptime and load averages info.

2.1751.1 ProcessInfo

cmd	*string*	the name of the command that launched the process.
cpuPct	*floating point number*	the percentage of CPU used by the process.
memPct	*floating point number*	the percentage of memory used by the process.
startTime	*floating point number*	the starting time of the process.
state	*string*	the process state code.
totalActiveTime	*integer*	the length of time the process has been active.

ttyName	*string*	the terminal associated with the process.

2.1751.2 SystemTimeInfo

currentTime	*floating point number*	the current timestamp.
loadAvg	*list of floating point number*	the average number of processes in the system that are in a runnable or uninterruptable state for the past 1, 5, and 15 minutes.
upTime	*floating point number*	the length of time the system has been running.
users	*integer*	the number of users that are currently logged on.

2.1752 show processes top once [...]

cpuInfo	*table(string) = CpuInfo* see 2.1752.1	Mapping of each CPU to its state percentages based on the interval since the last refresh.
memInfo	*SystemMemSum* see 2.1752.3	System physical and virtual memory usage.
processes	*table(numeric string) = ProcessActivityInfo* see 2.1752.2	Mapping of a process pid tothe detailed process activity.
threadsStateInfo	*ThreadsInfo* see 2.1752.4	the number of threads for each state.
timeInfo	*SystemTimeInfo* see 2.1751.2	uptime and load averages info.

2.1752.1 CpuInfo

hwIrq	*floating point number*	the percentage of time spent servicing hardware interrupts.
idle	*floating point number*	the percentage of idle time.
ioWait	*floating point number*	the percentage of time waiting for I/O completion.
nice	*floating point number*	the percentage of time running niced user processes.
stolen	*floating point number*	the percentage of time stolen from this vm by the hypervisor.
swIrq	*floating point number*	the percentage of time spent servicing software interrupts.
system	*floating point number*	the percentage of time running kernel processes.
user	*floating point number*	the percentage of time running un-niced user processes.

2.1752.2 ProcessActivityInfo

activeTime	*integer*	the length of time the process has been active in Centiseconds.
cmd	*string*	the command that launched the process.
cpuPct	*floating point number*	the percentage of CPU used by the process.
cpuPctType	*string*	CPU percentage display format.
memPct	*floating point number*	the percentage of memory used by the process.
niceValue	*integer*	the nice value of the process corresponding to a user-space concept.
priority	*string*	the process priority.
residentMem	*string*	the resident memory size.
sharedMem	*string*	the shared memory used by the process.
status	*string*	the process status.
userName	*string*	the effective user name of the owner of the processes.
virtMem	*string*	the amount of virtual memory used by the process.

2.1752.3 SystemMemSum

physicalMem	*MemInfo* see 2.1752.3.1	system physical memory info.
swapMem	*MemInfo* see 2.1752.3.1	system virtual memory info.

2.1752.3.1 MemInfo

memBuffer	*integer*	the amount of memory has been used in Kbytes.
memFree	*integer*	the amount of unused memory in Kbytes.
memTotal	*integer*	the amount of total memory in Kbytes.
memUsed	*integer*	the amount of memory currently being used in Kbytes.

2.1752.4 ThreadsInfo

run	*integer*	the total number of running tasks.
sleep	*integer*	the total number of sleeping tasks.
stop	*integer*	the total number of stopped tasks.
total	*integer*	the number of total tasks or threads.
zombie	*integer*	the total number of zombie tasks.

2.1753 show ptp

revision 2

see 2.469

2.1754 show ptp foreign-master-record

revision 2

intfForeignMasterRecords	*table(Interface name) = PtpIntfVlanForeignMaster-Records* see 2.1754.1	Collection of interface foreign master records.
[message]	*string*	Message to display in case of unexpected state.

2.1754.1 PtpIntfVlanForeignMasterRecords

interface	*interface name*	PTP interface name.
intfForeignMasterRecords	*list of PtpIntfForeign-MasterRecords* see 2.1754.1.1	List of foreign master records for this interface. They might be on different VLANs when ptp vlan is configured on a trunk interface.

2.1754.1.1 PtpIntfForeignMasterRecords

foreignMasterRecords	*list of PtpForeignMasterDS* see 2.1754.1.1.1	List of foreign master records for this interface.
maxForeignRecords	*integer*	Most foreign masters heard from on this port.
[vlanId]	*integer*	VLAN on which the PTP trunk interface have receive foreign master records.

2.1754.1.1.1 PtpForeignMasterDS

foreignMasterAnnounce-Messages	*integer*	Number of announce messages received from the foreign master.
[foreignMasterIp6Addr]	*IPv6 address*	IPv6 address of the foreign master.
[foreignMasterIpAddr]	*IPv4 address*	IPv4 address of the foreign master.
foreignMasterPortIdentity	*PtpPortIdentity* see 2.1754.1.1.1.1	PTP port identity on which the foreign master was seen.
timeAgo	*floating point number*	Last time this record was updated in monotonic seconds.

2.1754.1.1.1.1 PtpPortIdentity

clockIdentity	*string*	DefaultDS clock identity.
portNumber	*integer*	PTP port number.

2.1755 show ptp hardware-sync

see 2.1453

2.1756 show ptp hold-ptp-time

[holdPtpTimeExpiry] **	*floating point number*	Timestamp of when Ptp is expected to exit hold-over mode. **Since: 4.25.0
[holdPtpTimeInterval]	*integer*	hold-ptp-time interval in seconds.
[holdPtpTimeSinceEpoch] **	*floating point number*	Timestamp of when Ptp entered hold-over mode. **Since: 4.25.0
[holdPtpTimeState] **	*enum:* *holdoverTimerExpired* | *holdoverMasterDetected* | *holdoverInit* | *holdoverMode*	current Ptp hold-over mode. **Since: 4.25.0

[ptpMode]	*enum: ptpEndToEnd-TransparentClock | ptpPeerToPeerTransparent-Clock | ptpBoundaryClock | ptpGeneralized | ptpOneStepEndToEnd-TransparentClock | ptpOneStepBoundaryClock | ptpOneStepPeerToPeer-TransparentClock | ptpDisabled | ptpOrdinaryMasterClock*	PTP mode.

2.1757 show ptp interface INTFS vlan VLAN_ID

revision 3

interfaces	*table(Interface name) = PtpIntfVlans* see 2.1757.1	Collection of interfaces to display.

2.1757.1 PtpIntfVlans

interface	*interface name*	PTP interface name.
ptpInterfaceVlansStates	*list of PtpIntfWrapper* see 2.1757.1.1	List of PTP states on a same interface. There can be several of them when PTP is configured to run on multiple VLANs on a trunk interface.

2.1757.1.1 PtpIntfWrapper

[interface]	*PtpIntfBase* see 2.1757.1.1.1	PTP interface state.

2.1757.1.1.1 PtpIntfBase

Could also be an instance of:
PtpIntf 2.1757.1.1.2
PtpMpassIntf 2.1757.1.1.3

[mpassDisabledReason]	*enum: ptpDisabledPeerLink | notBoundaryMode | notConfigured | ucastNegEnabled | mlagIntfDisabled | delayMechanismNotE2e | ptpDisabledInterface | notMlagInterface*	MPASS Disabled Reason.
[mpassEnabled]	*boolean*	Interface is PTP MPASS enabled.
[mpassStatus]	*boolean*	Interface in MPASS active state.
[portState]	*enum: psFaulty | psListening | psPreMaster | psPassive | psMaster | psDisabled | psInitializing | psIsolatedSlave | psUncalibrated | psSlave*	PTP port state. See IEEE 1588-2008 for more information.
[syncTestRole]	*enum: syncTestMaster | syncTestDisabled | syncTestSlave*	PTP synctest state.
[vlanId]	*integer*	VLAN on which the PTP trunk interface is configured.

2.1757.1.1.2 PtpIntf

adminDisabled	*boolean*	Interface is PTP disabled.
[announceInterval]	*floating point number*	Announce interval in seconds. See IEEE 1588-2008 for more information.

[announceReceiptTimeout]	*integer*	Announce receipt timeout, measured in announce intervals. See IEEE 1588-2008 for more information.
[asCapable]	*boolean*	Interface is gptp capable.
[counters]	*PtpIntfCountersWrapper* see 2.1757.1.1.2.1	Interface PTP counters.
[delayMechanism]	*string*	PTP delay mechanism. See IEEE 1588-2008 for more information.
[delayReqInterval]	*floating point number*	Delay request interval. See IEEE 1588-2008 for more information.
[dscpEvent]	*integer*	Dscp value to set for Ptp Ipv4 event packets.
[dscpGeneral]	*integer*	Dscp value to set for Ptp Ipv4 general packets.
[lastGptpResidenceTime]	*integer*	Minimum measured gptp residence time.
[localPriority]	*integer*	Local Priority value. See ITU-T G8275 for more information.
managementMessageForwarding **	*enum: enabled* | *disabled* | *disabledForBcMcast*	management message forwarding. **Since: 4.33.2
[maxGptpResidenceTime]	*integer*	Last measured gptp residence time.
[maxStepsRemoved] **	*integer*	Steps removed threshold to drop announce messages. **Since: 4.35.2
[mcastTxAddr]	*MAC address*	Multicast destination address under PTP profile g8275.1.
[minGptpResidenceTime]	*integer*	Maximum measured gptp residence time.
[mpassDisabledReason]	*enum: ptpDisabledPeerLink* | *notBoundaryMode* | *notConfigured* | *ucastNegEnabled* | *mlagIntfDisabled* | *delayMechanismNotE2e* | *ptpDisabledInterface* | *notMlagInterface*	MPASS Disabled Reason.
[mpassEnabled]	*boolean*	Interface is PTP MPASS enabled.
[mpassStatus]	*boolean*	Interface in MPASS active state.
[peerDelayReqInterval]	*floating point number*	Peer delay request interval in seconds. See IEEE 1588-2008 for more information.
[peerPathDelay]	*integer*	Peer mean path delay in nanoseconds. See IEEE 1588-2008 for more information.
[portState]	*enum: psFaulty* | *psListening* | *psPreMaster* | *psPassive* | *psMaster* | *psDisabled* | *psInitializing* | *psIsolatedSlave* | *psUncalibrated* | *psSlave*	PTP port state. See IEEE 1588-2008 for more information.

ptpMode	*enum: ptpEndToEndTransparentClock | ptpPeerToPeerTransparentClock | ptpBoundaryClock | ptpGeneralized | ptpOneStepEndToEndTransparentClock | ptpOneStepBoundaryClock | ptpOneStepPeerToPeerTransparentClock | ptpDisabled | ptpOrdinaryMasterClock*	PTP mode.
[syncInterval]	*floating point number*	Sync interval in seconds. See IEEE 1588-2008 for more information.
[syncReceiptTimeout]	*integer*	Sync receipt timeout, measured in sync intervals. See IEEE 802.1AS for more information.
[syncTestRole]	*enum: syncTestMaster | syncTestDisabled | syncTestSlave*	PTP synctest state.
[timeSinceAsCapableLastChanged]	*string*	Time elasped since AS capable state of the port last changed.
[transportMode]	*enum: layer2 | ipv4 | ipv6*	Type of packet used to send PTP messages.
[txLagMember]	*interface name*	Member interface used for sending packets in a LAG.
[vlanId]	*integer*	VLAN on which the PTP trunk interface is configured.

2.1757.1.1.2.1 PtpIntfCountersWrapper

[interfaceCounters]	*PtpIntfCountersBase* see 2.1757.1.1.2.2	PTP counters state.
[vlanId]	*integer*	VLAN on which the PTP trunk interface is configured.

2.1757.1.1.2.2 PtpIntfCountersBase

Could also be an instance of:
PtpIntfCounters 2.1757.1.1.2.3
PtpIntfMpassCounters 2.1757.1.1.2.4

2.1757.1.1.2.3 PtpIntfCounters

[announceRx]	*integer*	Announce messages rx.
[announceTx]	*integer*	Announce messages tx.
delayReqRx	*integer*	Delay request rx.
delayReqTx	*integer*	Delay request tx.
delayRespRx	*integer*	Delay response rx.
delayRespTx	*integer*	Delay response tx.
followUpRx	*integer*	Follow up rx.
followUpTx	*integer*	Follow up tx.

[gptpFollowUpMessagesTx-Missed]	*integer*	Follow up gPTP messages tx missed.
[managementRx]	*integer*	Management rx.
[managementTx]	*integer*	Management tx.
pDelayReqRx	*integer*	Peer delay request rx.
pDelayReqTx	*integer*	Peer delay request tx.
pDelayRespFollowUpRx	*integer*	Peer delay response follow up rx.
pDelayRespFollowUpTx	*integer*	Peer delay response follow up tx.
pDelayRespRx	*integer*	Peer delay response rx.
pDelayRespTx	*integer*	Peer delay response tx.
[signalingRx]	*integer*	Signaling rx.
[signalingTx]	*integer*	Signaling tx.
syncRx	*integer*	Sync messages rx.
syncTx	*integer*	Sync messages tx.

2.1757.1.1.2.4 PtpIntfMpassCounters

announceLikeRx	*integer*	Forwarded Announce rx.
announceLikeTx	*integer*	Forwarded Announce tx.
delayReqLikeRx	*integer*	Forwarded Delay request rx.
delayReqLikeTx	*integer*	Forwarded Delay request tx.
delayRespLikeRx	*integer*	Forwarded Delay response rx.
delayRespLikeTx	*integer*	Forwarded Delay response tx.
followUpLikeRx	*integer*	Forwarded Follow up rx.
followUpLikeTx	*integer*	Forwarded Follow up tx.
syncLikeRx	*integer*	Forwarded Sync rx.
syncLikeTx	*integer*	Forwarded Sync tx.

2.1757.1.1.3 PtpMpassIntf

[counters]	*PtpIntfCountersWrapper* see 2.1757.1.1.2.1	Interface PTP MPASS counters.
delayReqExpiry	*floating point number*	Forwarded Delay request expiration timer.
[mpassDisabledReason]	*enum: ptpDisabledPeerLink* | *notBoundaryMode* | *notConfigured* | *ucastNegEnabled* | *mlagIntfDisabled* | *delayMechanismNotE2e* | *ptpDisabledInterface* | *notMlagInterface*	MPASS Disabled Reason.
[mpassEnabled]	*boolean*	Interface is PTP MPASS enabled.
[mpassStatus]	*boolean*	Interface in MPASS active state.
[portState]	*enum: psFaulty* | *psListening* | *psPreMaster* | *psPassive* | *psMaster* | *psDisabled* | *psInitializing* | *psIsolatedSlave* | *psUncalibrated* | *psSlave*	PTP port state. See IEEE 1588-2008 for more information.
syncExpiry	*floating point number*	Forwarded Sync expiration timer.

[syncTestRole]	*enum: syncTestMaster | syncTestDisabled | syncTestSlave*	PTP synctest state.
[vlanId]	*integer*	VLAN on which the PTP trunk interface is configured.

2.1758 show ptp interface [...]

revision 3

see 2.1757

2.1759 show ptp interface counters [...]

revision 3

interfaceCounters	*table(Interface name) = PtpIntfVlansCounters* see 2.1759.1	Interfaces to display counters.

2.1759.1 PtpIntfVlansCounters

interface	*interface name*	PTP interface name.
ptpInterfaceVlansCounters	*list of PtpIntfCountersWrapper* see 2.1757.1.1.2.1	List of PTP counters on a same interface. There can be several of them when PTP is configured to run on multiple VLANs on a trunk interface.

2.1760 show ptp interface counters drop [...]

counters	*table(Interface name) = PtpDebugIntfCounters* see 2.1760.1	PTP drop counters for all of the PTP interfaces.
disabled	*boolean*	PTP is disabled.

2.1760.1 PtpDebugIntfCounters

intfCounters	*list of PtpDebugCounter* see 2.1760.1.1	List of PTP drop counters on the interface.

2.1760.1.1 PtpDebugCounter

count	*integer*	Number of the PTP packets dropped.
direction	*enum: tx | rx*	Flow direction of the PTP packets dropped (Rx/Tx).
dropReason	*PtpDebugCounterDropReason* see 2.1760.1.1.1	Reason why the PTP packets are being dropped.
endpoint	*PtpEndpoint* see 2.1760.1.1.2	PTP endpoint where the packets are being dropped.

`lastSeen` **	*floating point number*	Last time a packet drop is seen, in seconds. **Since: 4.25.0

2.1760.1.1.1 PtpDebugCounterDropReason

debugReason	*enum: unexpectedFollowUp* | *sent* | *notAristaEthernetType* | *pDelayReqDropInNoFree-Running* | *recvMyOwnClockMsg* | *invalidUdp* | *maxReqWithoutDelayResp* | *missingIpHdr* | *lessForeign-MasterThreshold* | *invalidTlv* | *uCastGrantExpired* | *mpassMlagPeerNotPort-Channel* | *invalidMgmtId* | *waitForFollowUp* | *alreadySent* | *mpassNoPeerLinkPortDS* | *mpassInvalidMessageType* | *invalidDelayMsgType* | *badMaster* | *nonEthPktInGptp* | *pktQueueOverflow* | *vlan-NotInTrunkAllowedVlanList* | *noEventMsgEgress-Timestamp* | *mpassNoPeerLinkIntf* | *invalidUcastTlv* | *notBoundary* | *noPamForTxIntf* | *mpassAnnounceBeforeSync* | *lessBoundaryHops* | *invalidIpv4* | *noIngressSyncTimestamp* | *hwNotReadyForPacket* | *missingUdpHdr* | *staledPdelayReq* | *invalidDelayReq* | *unsupportedMsgTypeFor-Ucast* | *offsetFromMasterDrop-Threshold* | *missingIntf* | *invalidPdelayMsgType* | *badDomainNum* | *noUCastGrant* | *received* | *stpNotForwarding* | *noPendingToSend* | *portNotSlave* | *unexpectedGrant* | *alternateMasterFlag* | *truncatedDot1QTag* | *vlanNotConfOnIntf* | *ordinaryMaster* | *undersizedPkt* | *grandMasterNotAccepted* | *msgTxRxOnSameClk* | *mpassNoMlagIntfStatus* | *invalidMsgLen* | *roleMaster* | *mismatchLastReceivedSync* | *duplicateFollowUp* | *portIsDown* |	Reason of the PTP packet drop.

debugType	*enum:* *messageDelayRespLike* | *messagePDelayResp* | *messageDelayReqLike* | *messageFollowUpLike* | *messageSignaling* | *messageDelayReq* | *messageDelayResp* | *messageAnnounce* | *messagePDelayResp-Followup* | *messagePDelayReq* | *messageSyncLike* | *invalidPktFmt* | *messageFollowUp* | *messageManagement* | *messageSync* | *messageAnnounceLike*	Type of the PTP packet drop reason.

2.1760.1.1.2 PtpEndpoint

domain	*integer*	Domain number of the PTP endpoint.
intf	*interface name*	Interface of the PTP endpoint.
ip	*IP address*	IP address of the PTP endpoint (only for PTP unicast negotiation).
vlanId	*integer*	VLAN of the PTP endpoint.

2.1761 show ptp interface vlans [...]

interfaces	*table(Interface name) = PtpVlansExtendedWrapper* see 2.1761.1	A mapping of interfaces to ptp configured vlans on trunk port.
[message]	*string*	Message in case of unexpected state.

2.1761.1 PtpVlansExtendedWrapper

notAllowedVlans	*list of integer*	PTP configured vlans but not allowed on trunk port.
notCreatedVlans	*list of integer*	PTP configured vlans but not created.
vlans	*list of integer*	PTP configured vlans on trunk port.

2.1762 show ptp ip access-list

see 2.62

2.1763 show ptp local-clock

[ptpMode]	*enum: ptpEndToEndTransparentClock | ptpPeerToPeerTransparentClock | ptpBoundaryClock | ptpGeneralized | ptpOneStepEndToEndTransparentClock | ptpOneStepBoundaryClock | ptpOneStepPeerToPeerTransparentClock | ptpDisabled | ptpOrdinaryMasterClock*	PTP mode.
[ptpOrdinaryOrBoundaryClock]	*PtpOrdinaryOrBoundaryClock* see 2.1763.1	Information for ordinary or boundary clocks.

2.1763.1 PtpOrdinaryOrBoundaryClock

[boundaryClockProperties]	*PtpBoundaryClockProperties* see 2.1763.1.1	Boundary clock properties.
clockIdentity	*string*	DefaultDS clock identity.
clockQuality	*PtpClockQuality* see 2.1763.1.2	DefaultDS clock quality.
domainNumber	*integer*	DefaultDS domain number.
[localPriority] **	*integer*	DefaultDS local priority. See ITU-T G8275 for more information. **Since: 4.22.0
numberPorts	*integer*	DefaultDS number ports.
priority1	*integer*	DefaultDS priority1.
priority2	*integer*	DefaultDS priority2.

2.1763.1.1 PtpBoundaryClockProperties

[currentPtpSystemTime]	*integer*	Current sytem time measured with PTP.
[gptpCumulativeRateOffset]	*integer*	Estimated rate ratio expressed as an integer.
[gptpRateRatio]	*floating point number*	Estimated ratio of gPTP grandmaster to local clock frequency.
[lastSyncTime]	*integer*	Last time local clock synced from master.
meanPathDelay	*integer*	CurrentDS mean path delay to master in nanoseconds.
[neighborRateRatio]	*floating point number*	Estimated gPTP neighbor rate ratio.
offsetFromMaster	*integer*	CurrentDS offset from master in nanoseconds.
[skew]	*floating point number*	Ratio of master's seconds to local seconds.
stepsRemoved	*integer*	CurrentDS steps removed from GM.

2.1763.1.2 PtpClockQuality

accuracy	*integer*	Clock accuracy. See IEEE 1588-2008 for more information.
clockClass	*integer*	Clock class. See IEEE 1588-2008 for more information.
offsetScaledLogVariance	*integer*	Clock stability. See IEEE 1588-2008 for more information.

2.1764 show ptp local-clock time-properties

[message]	*string*	Message to display in case of unexpected state.
[timeProperty]	*PtpTimeProperty* see 2.1764.1	Time property data.

2.1764.1 PtpTimeProperty

currentUtcOffset	*integer*	Current offset between PTP time and UTC time. See IEEE 1588-2008 for more information.
currentUtcOffsetValid	*boolean*	Current offset between PTP time and UTC time is valid. See IEEE 1588-2008 for more information.
frequencyTraceable	*boolean*	timePropertiesDS.frequencyTraceable. See IEEE 1588-2008 for more information.
leap59	*boolean*	Last minute of today has 59 seconds. See IEEE 1588-2008 for more information.
leap61	*boolean*	Last minute of today has 61 seconds. See IEEE 1588-2008 for more information.
ptpTimescale	*boolean*	GM is using PTP timescale. See IEEE 1588-2008 for more information.
timeSource	*integer*	Time source GM is using. See IEEE 1588-2008 for more information.
timeTraceable	*boolean*	timePropertiesDS.timeTraceable. See IEEE 1588-2008 for more information.

2.1765 show ptp management-plane

revision 2

see 2.469

2.1766 show ptp masters

[message]	*string*	Message to display in case of unexpected state.
[parent]	*PtpParent* see 2.1766.1	PTP parent information.

2.1766.1 PtpParent

gmClockIdentity	*string*	Grandmaster clock identity. See IEEE 1588-2008 for more information.
gmClockQuality	*PtpClockQuality* see 2.1763.1.2	Grandmaster clock quality. See IEEE 1588-2008 for more information.
gmPriority1	*integer*	Grandmaster priority1. See IEEE 1588-2008 for more information.
gmPriority2	*integer*	Grandmaster priority2. See IEEE 1588-2008 for more information.
parentClockIdentity	*string*	Parent clock identity. See IEEE 1588-2008 for more information.
[parentIp6Addr] **	*IPv6 address*	IPv6 address of the parent. **Since: 4.21.3
[parentIpAddr]	*IPv4 address*	IPv4 address of the parent.
parentPortNumber	*integer*	Parent PTP port number. See IEEE 1588-2008 for more information.
parentTwoStepFlag **	*boolean*	Parent PTP Boundary Clock Two-Step Flag. **Since: 4.29.0

2.1767 show ptp monitor

[meanPathDelayThreshold]	*integer*	Mean path delay threshold.
monitorEnabled	*boolean*	PTP monitor enabled.
[offsetFromMasterThreshold]	*integer*	Offset from master threshold.
[ptpMode]	*enum: ptpEndToEndTransparentClock | ptpPeerToPeerTransparentClock | ptpBoundaryClock | ptpGeneralized | ptpOneStepEndToEndTransparentClock | ptpOneStepBoundaryClock | ptpOneStepPeerToPeerTransparentClock | ptpDisabled | ptpOrdinaryMasterClock*	PTP mode.
ptpMonitorData	*list of PtpMonitorDataEntry* see 2.1767.1	Collection of PTP data from all interfaces.
[skewThreshold]	*floating point number*	Skew threshold.

2.1767.1 PtpMonitorDataEntry

intf	*interface name*	Slave interface on which the PTP data has been recorded.
lastSyncSeqId **	*integer*	Last sequenceId of sync / followUp PTP message processed. **Since: 4.21.3
meanPathDelay	*integer*	Mean path delay value.
offsetFromMaster	*integer*	Offset from master value.

realLastSyncTime	*integer*	Epoch timestamp of when the PTP data has been detected.
skew	*floating point number*	Ratio of master's second to local second.

2.1768 show ptp mpass

[delayReqTimeout]	*integer*	Forwarded Delay request expiration timeout in seconds.
ptpIntfSummaries	*table(Interface name) = PtpIntfVlanSummary* see 2.469.2	A mapping of interface to a summary of its MPASS configuration.
[syncTimeout]	*integer*	Forwarded Sync expiration timeout in messages.

2.1769 show ptp mpass interface [...]

revision 3

see 2.1757

2.1770 show ptp mpass interface counters [...]

revision 3

see 2.1759

2.1771 show ptp region domain-number [...]

[clockDomain]	*integer*	PTP clock global domain number.
interfaces	*table(Interface name) = DomainNumbersVlans* see 2.1771.1	Active domains per interface per PTP VLAN.

2.1771.1 DomainNumbersVlans

domainNumbers	*list of integer*	PTP domains connected to this interface.
vlans	*table(numeric string) = DomainNumberList* see 2.1771.1.1	Active domains per PTP VLAN.

2.1771.1.1 DomainNumberList

domainNumbers	*list of integer*	Active domains.

2.1772 show ptp source

[sourceIp]	*IPv4 address*	Source IPv4 address to use when sending PTP messages.
[sourceIp6] **	*IPv6 address*	Source IPv6 address to use when sending PTP messages. **Since: 4.21.3

2.1773 show ptp source ip

see 2.1772

2.1774 show ptp unicast-negotiation candidate-grantor

candidateGrantors	*list of UcastNegCandidate-GrantorEntry* see 2.1774.1	List of candidate grantors.

2.1774.1 UcastNegCandidateGrantorEntry

grantorState	*enum: ucastNegCandidateMaster | ucastNegBlacklisted | ucastNegMaster*	State of the candidate grantor.
intf	*interface name*	Interface with which the candidate grantor is negotiating.
ipAddr	*IP address*	IP address of the candidate grantor.
profileName	*string*	Profile with which the candidate grantor is associated.

2.1775 show ptp unicast-negotiation granted

interfaces	*table(Interface name) = UcastNegMessages* see 2.1775.1	A mapping from the interface name to message infos.

2.1775.1 UcastNegMessages

messages	*list of UcastNegMessage* see 2.1775.1.1	Unicast Negotiation request sent from master/slave.

2.1775.1.1 UcastNegMessage

duration	*integer*	Duration of time, in seconds, agreed upon between the grantor and grantee.
expirationTime	*floating point number*	Time, in seconds, at which request was sent from grantor/grantee to Slave/Master.
ipAddr	*IP address*	Ip address of the Master/Slave from which we received a message.

logInterval	*integer*	log Interval of time, in seconds, agreed upon between the the and grantee.
messageType	*enum:* *messageDelayRespLike* | *messagePDelayResp* | *messageDelayReqLike* | *messageFollowUpLike* | *messageSignaling* | *messageDelayReq* | *messageDelayResp* | *none* | *messageAnnounce* | *messagePDelayResp-Followup* | *messagePDelayReq* | *messageSyncLike* | *messageFollowUp* | *messageManagement* | *messageSync* | *messageAnnounceLike*	Type of Message sent from potential Master/Slave to Slave/Master.

2.1776 show ptp unicast-negotiation profile [...]

profiles	*table(string) = UcastNegProfile* see 2.1776.1	Unicast Negotiation Profiles list.

2.1776.1 UcastNegProfile

announceDuration	*integer*	Announce duration of time of profile. See IEEE 1588-2008 for more information.
announceInterval	*integer*	Announce interval of time of profile. See IEEE 1588-2008 for more information.
delayResponseDuration	*integer*	Delay Response interval of profileSee IEEE 1588-2008 for more information.
delayResponseInterval	*integer*	Delay Response interval of profileSee IEEE 1588-2008 for more information.
syncDuration	*integer*	Sync duration of time of profile. See IEEE 1588-2008 for more information.
syncInterval	*integer*	Sync interval of time of profile. See IEEE 1588-2008 for more information.

2.1777 show ptp unicast-negotiation remote-grantee

remoteGrantees	*list of UcastNegRemote-GranteeEntry* see 2.1777.1	List of remote grantees.

2.1777.1 UcastNegRemoteGranteeEntry

intf	*interface name*	Interface with which the remote grantee can negotiate.
ipAddrAndMask	*IP address and mask length*	Allowed IP address range for the remote grantee.
profileName	*string*	Profile with which the remote grantee is associated.

2.1778 show ptp unicast-negotiation requested

see 2.1775

2.1779 show qos ecn [...]

delayEcnSupported	*boolean*	Global Delay based ECN supported.
[globalEcnDelayParameters]	*EcnDelayParametersModel* see 2.316.1.1.1	Global delay based ECN Parameters. Not applicable if Global delay based ECN is disabled.
[globalEcnParameters]	*EcnParametersModel* see 2.316.1.1.2	Global length based ECN Parameters. Not applicable if Global length based ECN is disabled.
globalEcnSupported	*boolean*	Global Buffer ECN supported.
globalEcnWeightSupported **	*boolean*	Global ECN Supported. **Since: 4.21.3

2.1780 show qos ecn counters

chipEcnCounter	*table(string) = integer*	A mapping between a chip name and ECN counter.

2.1781 show qos ecn delay [...]

[ecnDelayParameters]	*EcnDelayParametersModel* see 2.316.1.1.1	General delay ECN parameters.

2.1782 show qos interfaces [...]

intfAllQosAll	*table(Interface name)* = *IntfQosAllModel* see 2.1782.1	All the Interfaces with all Qos details for it.

2.1782.1 IntfQosAllModel

intfQosModel	*InterfaceQosModel* see 2.1782.1.1	Qos on Interface.
intfServicePolicyQosModel	*IntfServicePolicyQosModel* see 2.1782.1.2	Service Policy on Interface.

2.1782.1.1 InterfaceQosModel

burstSizeConfigSupported **	*boolean*	Burst-size config is supported. **Since: 4.24.0
[configuredBurstSize] **	*BurstSizeModel* see 2.1782.1.1.1	Configured burst-size. **Since: 4.24.0
[configuredPolicerPktSize-Adj] **	*PolicerPktSizeAdjModel* see 2.1782.1.1.4	Configured policer packet size adjustment. **Since: 4.27.0
[configuredPortGuaranteed-Bw] **	*GuaranteedBwModel* see 2.1782.1.1.2	Configured port guaranteed bandwidth. **Since: 4.25.2
[configuredPortShapeRate]	*ShapeRateModel* see 2.584.1.1.1.2	Configured port shape rate.
[configuredScheduler-Compensation] **	*SchedulerCompensation-Model* see 2.1782.1.1.5	Configured scheduler compensation. **Since: 4.26.2
cosToTcProfile **	*string*	COS-to-TC profile. **Since: 4.22.1
cpuTcToCosNamedMap **	*string*	CPU TC-to-COS map. **Since: 4.23.2
[defaultCos]	*integer*	Default COS value, if supported.
defaultCosSupported	*boolean*	Is default COS supported.
[defaultDscp]	*integer*	Default DSCP value, if supported.
defaultDscpSupported	*boolean*	Is default DSCP supported.
dscpPreserveIpMplsEncapMode **	*boolean*	DSCP Preserve for MPLS IP encap. **Since: 4.28.2
[dscpRewriteActive]	*boolean*	DSCP Rewrite Active, if hardware supports reporting.
dscpRewriteMap **	*string*	TC-to-DSCP map. **Since: 4.23.2
[dscpToCosRewriteActive]	*boolean*	DSCP To COS Rewrite active status, if hardware supports reporting.
dscpToTcMap **	*string*	DSCP-to-TC map. **Since: 4.27.0
[expRewriteActive] **	*boolean*	EXP Rewrite Active, if hardware supports reporting. **Since: 4.32.1
expToTcProfile **	*string*	EXP-to-TC profile. **Since: 4.30.1
interface	*string*	Qos on Interface.

interfaceGuaranteedBw-Supported **	*boolean*	Guaranteed bandwidth config is supported. **Since: 4.25.2
intfIsLag	*boolean*	Is a LAG Interface.
intfQosDetailedInfo-Available	*boolean*	Detailed Qos info of the interface is available.
intfQosInfoAvailable	*boolean*	Interface Qos info availability.
[operationalBurstSize] **	*BurstSizeModel* see 2.1782.1.1.1	Operational burst-size. **Since: 4.24.0
[operationalPolicerPktSize-Adj] **	*PolicerPktSizeAdjModel* see 2.1782.1.1.4	Operational policer packet size adjustment. **Since: 4.27.0
[operationalPortGuaranteed-Bw] **	*GuaranteedBwModel* see 2.1782.1.1.2	Operational port guaranteed bandwidth. **Since: 4.25.2
[operationalPortShapeRate]	*ShapeRateModel* see 2.584.1.1.1.2	Operational port shape rate.
[operationalScheduler-Compensation] **	*SchedulerCompensation-Model* see 2.1782.1.1.5	Operational scheduler compensation. **Since: 4.26.2
policerPktSizeAdjConfig-Supported **	*boolean*	Policer packet size config is supported. **Since: 4.27.0
schedulerCompensation-ConfigSupported **	*boolean*	Scheduler compensation config is supported. **Since: 4.26.2
[schedulingGroupModel] **	*IntfSchedulingGroupModel* see 2.1782.1.1.3	Scheduling Group Model. **Since: 4.25.0
[sliceName] **	*string*	Slice name corresponding to the Fabric interface. **Since: 4.17.0
tcDpToExpMap **	*string*	TC-to-EXP map. **Since: 4.32.1
tcToCosNamedMap **	*string*	TC-to-COS map. **Since: 4.23.2
trustMode	*enum: cosTrusted | unTrusted | dscpTrusted*	Qos Trustmode of interface.
[txQueueQosModel]	*TxQueueQosModel* see 2.1782.1.1.6	Transmit Queue Model.

2.1782.1.1.1 BurstSizeModel

unit	*enum: burstUnitMBytes | burstUnitBytes | burstUnitKBytes*	Burst-size unit.
value	*integer*	Burst-size value.

2.1782.1.1.2 GuaranteedBwModel

bandwidth	*integer*	Guaranteed bandwidth.
[percent] **	*integer*	Guaranteed bandwidth as percentage of reference. **Since: 4.25.0

[percentOf] **	*enum: unknown* | *parentInterfaceShapeRate* | *lineRate* | *schedulingGroupShapeRate* | *subinterfaceShapeRate*	Reference for guaranteed bandwidth percent. **Since: 4.25.2
unit	*enum: percent* | *unspecified* | *pps* | *kbps*	Guaranteed bandwidth unit.

2.1782.1.1.3 IntfSchedulingGroupModel

schedulingGroups	*table(string) = SchedulingElementModel* see 2.1782.1.1.3.1	Scheduling Groups configured for the interface, indexed by their name.

2.1782.1.1.3.1 SchedulingElementModel

Could also be an instance of:
HierarchyModel 2.1782.1.1.3.3
SchedulingGroupWithMembersModel 2.1782.1.1.3.4

[OperationalSubIntfBw] **	*SubInterfaceBwModel* see 2.1782.1.1.3.2	Subinterface operational bandwidth (float upto two decimals). **Since: 4.35.2
[configuredGuaranteedBw]	*GuaranteedBwModel* see 2.1782.1.1.2	Configured Guaranteed bandwidth.
[configuredShapeRate]	*ShapeRateModel* see 2.584.1.1.1.2	Configured Shape rate.
[operationalGuaranteedBw]	*GuaranteedBwModel* see 2.1782.1.1.2	Operational Guaranteed bandwidth.
[operationalShapeRate]	*ShapeRateModel* see 2.584.1.1.1.2	Operational Shape rate.

2.1782.1.1.3.2 SubInterfaceBwModel

[bandwidth]	*floating point number*	Subinterface operational bandwidth.
[unit]	*enum: percent* | *unspecified* | *pps* | *kbps*	Subinterface operational bandwidth unit.

2.1782.1.1.3.3 HierarchyModel

[OperationalSubIntfBw] **	*SubInterfaceBwModel* see 2.1782.1.1.3.2	Subinterface operational bandwidth (float upto two decimals). **Since: 4.35.2
[configuredGuaranteedBw]	*GuaranteedBwModel* see 2.1782.1.1.2	Configured Guaranteed bandwidth.
[configuredShapeRate]	*ShapeRateModel* see 2.584.1.1.1.2	Configured Shape rate.
[interfaceSpeed]	*integer*	linkSpeed (bps).
name	*string*	Name of the entity in the hierarchy.
[operationalGuaranteedBw]	*GuaranteedBwModel* see 2.1782.1.1.2	Operational Guaranteed bandwidth.

[operationalShapeRate]	*ShapeRateModel* see 2.584.1.1.1.2	Operational Shape rate.

2.1782.1.1.3.4 SchedulingGroupWithMembersModel

[OperationalSubIntfBw] **	*SubInterfaceBwModel* see 2.1782.1.1.3.2	Subinterface operational bandwidth (float upto two decimals). **Since: 4.35.2
[configuredGuaranteedBw]	*GuaranteedBwModel* see 2.1782.1.1.2	Configured Guaranteed bandwidth.
[configuredShapeRate]	*ShapeRateModel* see 2.584.1.1.1.2	Configured Shape rate.
[interfaces]	*table(Interface name) = SchedulingElementModel* see 2.1782.1.1.3.1	Member subinterfaces of the scheduling group.
[operationalGuaranteedBw]	*GuaranteedBwModel* see 2.1782.1.1.2	Operational Guaranteed bandwidth.
[operationalShapeRate]	*ShapeRateModel* see 2.584.1.1.1.2	Operational Shape rate.

2.1782.1.1.4 PolicerPktSizeAdjModel

profile	*string*	Packet size adjustment profile.
value	*integer*	Packet size adjustment configuration associated with the profile.

2.1782.1.1.5 SchedulerCompensationModel

unit	*burstUnitBytes*	Scheduler Compensation unit.
value	*integer*	Scheduler Compensation value.

2.1782.1.1.6 TxQueueQosModel

burstSizeConfigSupported **	*boolean*	Burst-size config is supported. **Since: 4.24.0
delayEcnSupported **	*boolean*	Delay based ECN supported. **Since: 4.17.0
ecnSupported	*boolean*	ECN supported.
guaranteedBwSupported	*boolean*	Guaranteed bandwidth supported.
multipleSchedGroups-Supported	*boolean*	Multiple scheduling groups supported.
nonEctSupported **	*boolean*	NON-ECT supported. **Since: 4.20.5
numTxQueue	*integer*	Number of Transmit Queues.
[numTxQueuePrint] **	*integer*	Number of Transmit Queues to print. **Since: 4.25.1
txQueueList	*list of TxQueue* see 2.1782.1.1.6.1	List of Transmit Queues.
wredSupported **	*boolean*	WRED supported. **Since: 4.17.0

wrrSupported	*boolean*	WRR Scheduling supported.

2.1782.1.1.6.1 TxQueue

[configuredBurstSize] **	*BurstSizeModel* see 2.1782.1.1.1	Configured burst-size. **Since: 4.24.0
[configuredGuaranteedBw]	*GuaranteedBwModel* see 2.1782.1.1.2	Configured Guaranteed bandwidth.
[configuredSchedMode]	*SchedulingModeModel* see 2.1782.1.1.6.2	Configured Scheduling mode.
[configuredShapeRate]	*ShapeRateModel* see 2.584.1.1.1.2	Configured Shape rate.
[configuredWrrBw]	*integer*	Configured WRR Bandwidth in percent.
[configuredWrrBwWeight] **	*integer*	Configured WRR Bandwidth weight. **Since: 4.31.1
dynamicEcnStatus **	*enum: enabled* | *disabled* | *not applicable*	Dynamic ECN Status on Transmit Queue. **Since: 4.33.0
ecnStatus	*enum: lengthAndDelayEnabled* | *delayEnabled* | *not applicable* | *enabled* | *disabled*	ECN Status on Transmit Queue.
nonEctStatus **	*enum: enabled* | *disabled* | *not applicable*	NON-ECT Status on Transmit Queue. **Since: 4.20.5
[operationalBurstSize] **	*BurstSizeModel* see 2.1782.1.1.1	Operational burst-size. **Since: 4.24.0
[operationalGuaranteedBw]	*GuaranteedBwModel* see 2.1782.1.1.2	Operational Guaranteed bandwidth.
[operationalSchedMode]	*SchedulingModeModel* see 2.1782.1.1.6.2	Operational Scheduling mode.
[operationalShapeRate]	*ShapeRateModel* see 2.584.1.1.1.2	Operational Shape rate.
[operationalWrrBw]	*integer*	Operational WRR Bandwidth in percent.
[operationalWrrBwWeight] **	*integer*	Operational WRR Bandwidth weight. **Since: 4.31.1
schedGroupId	*integer*	Scheduling Group Id.
txQueue	*string*	Transmit Queue.
txQueuePriority	*integer*	Transmit Queue Priority - higher txQueuePriority value has precedence.
wredStatus **	*enum: enabled* | *disabled* | *not applicable*	WRED Status on Transmit Queue. **Since: 4.17.0

2.1782.1.1.6.2 SchedulingModeModel

schedulingMode	*enum: unspecified* | *strictPriority* | *roundRobin* | *not applicable*	Scheduling mode.

2.1782.1.2 IntfServicePolicyQosModel

intfPolicyMaps	*table(string) = PolicyQosModel* see 2.1782.1.2.1	Policy maps list for an interface for different directions.

2.1782.1.2.1 PolicyQosModel

directionString	*enum: output | input*	Direction in which policy is applied.
name	*string*	Name of the policy map.
status	*enum: hwPrgmStatusSuccess | hwPrgmStatusFail | hwPrgmStatusInProgress*	Hardware programming status.

2.1783 show qos interfaces drop-thresholds [...]

dropThresholdsSupported	*boolean*	Drop Precedence thresholds supported.
intfDropThresholds-Collection	*table(Interface name) = IntfDropThresholdsModel* see 2.1783.1	A mapping of an interface to its drop thresholds.

2.1783.1 IntfDropThresholdsModel

txQueueDropThresholdsList	*list of TxQueueDrop-ThresholdsModel* see 2.1783.1.1	List of Transmit Queue Drop Threshold Settings.

2.1783.1.1 TxQueueDropThresholdsModel

[dropThreshold] **	*DropThresholdModel* see 2.1783.1.1.1	Drop threshold. **Since: 4.35.2
dropThresholds	*table(numeric string) = integer*	Drop Thresholds per drop precedence.
txQueue	*string*	Name of Egress Queue.

2.1783.1.1.1 DropThresholdModel

threshold	*integer*	Drop Threshold.
thresholdUnit	*string*	Unit for drop threshold.
[weighted]	*boolean*	Use WRR weight for drop threshold.

2.1784 show qos interfaces dscp mpls encapsulation disabled [...]

interfaces	*list of Interface name*	Interfaces with DSCP Preserve enabled.

2.1785 show qos interfaces ecn [...]

intfEcnCollection	*table(Interface name) = IntfEcnModel* see 2.316.1	Interface ECN.

2.1786 show qos interfaces ecn counters queue [...]

intfQueueCounters	*table(Interface name) = EcnQueueCounterModel* see 2.1786.1	Mapping from interface to tx-queue ecn counters.

2.1786.1 EcnQueueCounterModel

[locallyMarkedQueue-Counters] **	*table(numeric string) = integer*	Mapping from tx-queue to locally marked ecn counters. **Since: 4.33.2
queueCounters	*table(numeric string) = string*	Mapping from tx-queue to ecn counters.

2.1787 show qos interfaces ecn dynamic [...]

intfs	*table(Interface name) = IntfBufferBasedDecnModel* see 2.1787.1	Interface dynamic ECN.

2.1787.1 IntfBufferBasedDecnModel

txQueues	*table(string) = DecnParametersModel or NULL* see 2.1787.1.1	Transmit queue dynamic ECN settings.

2.1787.1.1 DecnParametersModel

floor	*integer*	Dynamic ECN floor value.
offset	*integer*	Dynamic ECN offset value.
unit	*enum: percent | mbytes | bytes | segments | kbytes | microseconds | milliseconds*	Dynamic ECN threshold unit.

2.1788 show qos interfaces fabric [...]

fabricAllQosAll	*table(string) = IntfQosAllModel* see 2.1782.1	A mapping between Fabric Interfaces to Qos details.

2.1789 show qos interfaces latency maximum [...]

interfaces	*table(Interface name) = IntfLatencyThresholdModel* see 2.1789.1	A mapping of interface to transmit queue latency threshold.

2.1789.1 IntfLatencyThresholdModel

txQueues	*list of TxQueueLatency-ThresholdModel* see 2.1789.1.1	List of transmit queue latency threshold settings.

2.1789.1.1 TxQueueLatencyThresholdModel

threshold	*integer*	Transmit queue latency threshold.
txQueue	*string*	Name of transmit queue.
unit	*string*	Latency threshold unit.

2.1790 show qos interfaces random-detect drop [...]

intfWredCollection	*table(Interface name) = IntfWredModel* see 2.1790.1	Interface WRED.

2.1790.1 IntfWredModel

txQueueWredList	*list of TxQueueWredModel* see 2.1790.1.1	List of Transmit Queue WRED Settings.

2.1790.1.1 TxQueueWredModel

dpWredSupported **	*boolean*	WRED per Drop-Precedence Supported. **Since: 4.27.2
txQueue	*string*	Name of Egress Queue.
[txQueueWredParameters]	*WredParametersModel* see 2.1790.1.1.1	Transmit Queue WRED Parameters. Not Applicable if Transmit Queue WRED is disabled.
wredWeightSupported **	*boolean*	WRED weight Supported. **Since: 4.21.3

2.1790.1.1.1 WredParametersModel

[dp] **	*integer*	Drop Precedence value. **Since: 4.27.2
maxDroprate	*integer*	Drop probability rate.
maxThreshold	*integer*	Maximum Threshold for WRED.
minThreshold	*integer*	Minimum Threshold for WRED.
[operationalMaxDroprate] **	*integer*	Operational Mark probability rate. **Since: 4.27.0
[segmentSizeInBytes]	*integer*	Size of segment unit in bytes.

unit	*enum: percent | mbytes | bytes | segments | kbytes | microseconds | milliseconds*	Threshold unit for WRED.
[weight] **	*integer*	Weight for averaging queue size. **Since: 4.21.3

2.1791 show qos interfaces random-detect ecn [...]

Could also be an instance of:
IntfAllEcnCollectionModel 2.1785

intfEcnCollection	*table(Interface name) = IntfEcnModel* see 2.316.1	Interface ECN.

see 2.1785

2.1792 show qos interfaces scheduler profile [...]

interfaces	*table(Interface name) = TxQueueSchedulerMapModel* see 2.1792.1	A mapping of interfaces to their tx queue to scheduler profile mapping.

2.1792.1 TxQueueSchedulerMapModel

[memberIntfs]	*table(Interface name) = boolean*	A mapping of member interfaces with their configuration status.
txQueues	*table(numeric string) = string*	A mapping of tx queue to its scheduler profile.

2.1793 show qos interfaces trust [...]

intfTrustModeCollection	*table(Interface name) = IntfTrustModeModel* see 2.1793.1	Interface trust mode.

2.1793.1 IntfTrustModeModel

[intfTrustModeParameters]	*IntfTrustModeParametersModel* see 2.1793.1.1	Trust Mode Parameters.

2.1793.1.1 IntfTrustModeParametersModel

configuredTrustMode	*enum: COS | UNTRUSTED | DEFAULT | DSCP*	Configured trust mode.
operationalTrustMode	*enum: COS | UNTRUSTED | DSCP*	Operational trust mode.

2.1794 show qos interfaces wred counters queue [...]

intfQueueCounters	*table(Interface name) = WredQueueCounterModel* see 2.1794.1	Mapping from interface to tx-q wred counters.

2.1794.1 WredQueueCounterModel

queueCounters	*table(numeric string) = MetaWredQueueCounterModel* see 2.1794.1.1	Mapping from tx-queue to wred counters.

2.1794.1.1 MetaWredQueueCounterModel

[ecnBytes]	*integer*	ECN marked bytes.
[ecnPkts]	*integer*	ECN marked packets.
[enqueueBytes]	*integer*	Total enqueued bytes.
[enqueuePkts]	*integer*	Total enqueued packets.
[tailDropBytes]	*integer*	Tail dropped bytes.
[tailDropPkts]	*integer*	Tail dropped packets.
[wredDropBytes]	*integer*	Bytes dropped due to WRED.
wredDropPkts	*integer*	Packets dropped due to WRED.

2.1795 show qos map cos to traffic-class [...]

cosToTcProfiles	*table(string) = CosToTcProfileModel* see 2.1795.1	CoS to Traffic-Class profiles, indexed by their name.

2.1795.1 CosToTcProfileModel

[cosDeiToDpMap] **	*table(string) = integer*	CoS DEI to Drop-Precedence mapping. **Since: 4.35.2
[cosDeiToTcMap] **	*table(string) = integer*	CoS DEI to Traffic-Class mapping. **Since: 4.35.2
[cosToDpMap] **	*table(numeric string) = integer*	CoS to Drop-Precedence mapping. **Since: 4.34.2
cosToTcMap	*table(numeric string) = integer*	CoS to Traffic-Class mapping.

2.1796 show qos map dscp to outDscp [...]

dscpToDscpNamedMaps	*table(string) = DscpToDscpMapModel* see 2.1796.1	DSCP To DSCP maps, indexed by their name.

2.1796.1 DscpToDscpMapModel

dscpToDscpNamedMap	*table(numeric string) = integer*	DSCP To DSCP mapping.

2.1797 show qos map dscp to traffic-class [...]

dscpToTcNamedMaps	*table(string) = DscpToTcMapModel* see 2.1797.1	DSCP To Traffic-Class maps, indexed by their name.

2.1797.1 DscpToTcMapModel

dscpToTcNamedMap	*table(numeric string) = integer*	DSCP To Traffic-Class mapping.

2.1798 show qos map exp to traffic-class [...]

expToTcProfiles	*table(string) = ExpToTcProfileModel* see 2.1798.1	EXP to Traffic-Class profiles, indexed by their name.

2.1798.1 ExpToTcProfileModel

[expToDpMap] **	*table(numeric string) = integer*	EXP to Drop-Precedence mapping. **Since: 4.35.2
expToTcMap	*table(numeric string) = integer*	EXP to Traffic-Class mapping.

2.1799 show qos map traffic-class to cos [...]

tcToCosNamedMaps	*table(string) = TcToCosMapModel* see 2.1799.1	Traffic-Class to CoS profiles, indexed by their name.

2.1799.1 TcToCosMapModel

[tcDpToCosNamedMap] **	*table(string) = integer*	Traffic-Class Drop-Precedence to CoS mapping. **Since: 4.35.2
[tcDpToDeiNamedMap] **	*table(string) = integer*	Traffic-Class Drop-Precedence to Dei mapping. **Since: 4.35.2
tcToCosNamedMap	*table(string) = integer*	Traffic-Class to CoS mapping.

2.1800 show qos map traffic-class to dscp [...]

dscpRewriteMaps	*table(string)* = *DscpRewriteMapModel* see 2.1800.1	A mapping between Dscp RewriteMap names and Dscp RewriteMap.

2.1800.1 DscpRewriteMapModel

tcDpToDscpMap **	*table(string)* = *integer*	Traffic-Class, Drop-Precedence to DSCP mapping. **Since: 4.27.1
tcToDscpMap	*table(numeric string)* = *integer*	Traffic-Class to DSCP mapping.

2.1801 show qos map traffic-class to exp [...]

tcDpToExpMaps	*table(string)* = *TcDpToExpMapModel* see 2.1801.1	A mapping between TcDpToExp Map names and TcDpToExp Maps.

2.1801.1 TcDpToExpMapModel

tcDpToExpMap	*table(string)* = *integer*	Traffic-Class, Drop-Precedence to EXP mapping.

2.1802 show qos maps [...]

cosRewriteDisableSupported	*boolean*	COS rewrite disable supported.
cosRewriteEnabled	*boolean*	COS rewrite enabled.
cosRewriteSupported	*boolean*	COS rewrite supported.
cosToDpMap **	*table(numeric string) = integer*	COS to Drop-Precedence mapping. **Since: 4.36.0
cosToDpMapSupported **	*boolean*	COS to Drop-Precedence mapping supported. **Since: 4.36.0
cosToTcMap	*table(numeric string) = integer*	COS to Traffic-Class mapping.
[cosToTcProfileAllModel] **	*CosToTcProfileAllModel* see 2.1795	User configured COS to Traffic-Class profiles. **Since: 4.22.1
cosToTcProfilePerInterface-Supported **	*boolean*	Configuration of CoS to Traffic-Class Map on interface supported. **Since: 4.22.1
deiToDpMap **	*table(numeric string) = integer*	DEI to Drop-Precedence mapping. **Since: 4.30.1
deiToDpMapSupported **	*boolean*	DEI to Drop-Precedence mapping supported. **Since: 4.30.1
dscpRewriteEnabled	*boolean*	DSCP rewrite enabled.
[dscpRewriteMapAllModel] **	*DscpRewriteMapAllModel* see 2.1800	User configured Traffic-Class and Drop-Precedence to DSCP profiles. **Since: 4.23.2
dscpRewritePerInterface-Supported **	*boolean*	Configuration of Traffic-Class to DSCP Map on interface supported. **Since: 4.23.2
dscpRewriteSupported	*boolean*	DSCP rewrite supported.
[dscpToDpMap] **	*table(numeric string) = integer*	DSCP to Drop-Precedence mapping. **Since: 4.22.0
dscpToDpMapSupported **	*boolean*	DSCP to Drop-Precedence mapping supported. **Since: 4.22.0
dscpToTcMap	*table(numeric string) = integer*	DSCP to Traffic-Class mapping.
[dscpToTcMapAllModel] **	*DscpToTcMapAllModel* see 2.1797	User configured Dscp to Traffic-Class maps. **Since: 4.25.1
dscpToTcMapPerInterface-Supported **	*boolean*	Configuration of DSCP To Traffic-Class Map on interface supported. **Since: 4.32.1
dscpToTcMapPerSubInterface-Supported **	*boolean*	Configuration of DSCP To Traffic-Class Map on subInterface supported. **Since: 4.28.0
dynamicExpMappingSupported **	*boolean*	Configuration of EXP to Traffic-Class and Traffic-Class to EXP mapping supported. **Since: 4.22.0
expRewriteEnabled **	*boolean*	EXP rewrite enabled. **Since: 4.33.2

expRewriteSupported **	*boolean*	Configuration of Traffic-Class to Exp Map on interface supported. **Since: 4.32.1
[expToTcMap] **	*table(numeric string) = integer*	EXP to Traffic-Class mapping when dynamic EXP mapping is supported. **Since: 4.22.0
[expToTcProfileAllModel] **	*ExpToTcProfileAllModel* see 2.1798	User configured EXP to Traffic-Class profiles. **Since: 4.30.1
expToTcProfilePerInterface-Supported **	*boolean*	Configuration of EXP to Traffic-Class Map on interface supported. **Since: 4.30.1
l2ControlReservedPg-Configurable **	*boolean*	L2 control priority group is supported and can be disabled. **Since: 4.35.2
l2ControlReservedPgEnabled **	*boolean*	L2 control priority group is enabled. **Since: 4.35.2
numMulticastQueueSupported	*integer*	Number of Multicast Queues supported.
numTcSupported	*integer*	Number of Traffic Classes supported.
numTxQueueSupported	*integer*	Number of Transmit Queues supported.
pwDecapDscpQosMapSupported **	*boolean*	Configuration of DSCP To Traffic-Class Map on pseudowire supported. **Since: 4.25.1
[tcDpToExpMap] **	*table(numeric string) = integer*	Traffic-Class and Drop-Prededence to EXP mapping when EXP rewrite is supported. **Since: 4.32.1
[tcDpToExpMapAllModel] **	*TcDpToExpMapAllModel* see 2.1801	User configured Traffic-Class and Drop-Precedence to EXP profiles. **Since: 4.32.1
[tcToCosMap]	*table(numeric string) = integer*	Traffic-Class to COS mapping when COS rewrite is supported.
[tcToCosMapAllModel] **	*TcToCosMapAllModel* see 2.1799	User configured Traffic-Class to CoS profiles. **Since: 4.23.2
tcToCosMapPerInterface-Supported **	*boolean*	Configuration of Traffic-Class to CoS Map on interface supported. **Since: 4.23.2
[tcToDscpMap]	*table(numeric string) = integer*	Traffic-Class to DSCP mapping when DSCP rewrite is supported.
tcToDscpMapSupported	*boolean*	Traffic-Class to DSCP mapping supported.
[tcToExpMap] **	*table(numeric string) = integer*	Traffic-Class to EXP mapping when dynamic EXP mapping is supported. **Since: 4.22.0
[tcToMcTxQueueMap]	*table(numeric string) = integer*	Traffic-Class to mc-tx-queue mapping when multicast queues are supported.
[tcToPriorityGroupMap] **	*table(numeric string) = integer*	Traffic-Class to PriorityGroup mapping. **Since: 4.21.0
tcToPriorityGroupMap-Supported **	*boolean*	Traffic-Class to Priority Group supported. **Since: 4.21.0
[tcToTxQueueMap]	*table(numeric string) = integer*	Traffic-Class to tx-queue mapping when unicast queues are supported.

2.1803 show qos profile [...]

qosProfiles	*table(string) = QosProfileModel* see 2.1803.1	A mapping between QoS profile name and QoS profiles.

2.1803.1 QosProfileModel

[configuredPortGuaranteed-Bw] **	*GuaranteedBwModel* see 2.1782.1.1.2	Configured port Guaranteed Bandwidth. **Since: 4.30.2
[configuredPortShapeRate] **	*ShapeRateModel* see 2.584.1.1.1.2	Configured port shape rate. **Since: 4.17.0
[configuredScheduler-Compensation] **	*SchedulerCompensation-Model* see 2.1782.1.1.5	Configured port scheduler compensation. **Since: 4.26.2
[configuredServicePolicy] **	*PolicyQosModel* see 2.1782.1.2.1	Configured Service Policy. **Since: 4.18.0
[cosToTcProfile] **	*string*	COS-to-TC profile. **Since: 4.35.0
[defaultCos] **	*integer*	Default COS value. **Since: 4.17.0
defaultCosSupported **	*boolean*	Default COS supported. **Since: 4.17.0
[defaultDscp] **	*integer*	Default DSCP value. **Since: 4.17.0
defaultDscpSupported **	*boolean*	Default DSCP supported. **Since: 4.17.0
dscpPreserveIpMplsEncapMode **	*boolean*	DSCP Preserve for MPLS IP encap. **Since: 4.28.2
[dscpToTcMap] **	*string*	DSCP-to-TC map. **Since: 4.35.0
numTxQueueSupported	*integer*	Number of Transmit Queues supported.
pfcEnabled	*boolean*	PFC enabled.
pfcPriorities	*table(numeric string) = PfcProfileModel* see 2.1803.1.1	A mapping between PFC priority and PFC configuration.
pfcWatchdogEnabled **	*boolean*	PFC Watchdog enabled. **Since: 4.17.0
[pfcWatchdogPortAction] **	*string*	Configured per-port action value for PFC Watchdog. **Since: 4.20.0
[pfcWatchdogPortTimer-Values] **	*PfcWatchdogPortTimer-Model* see 2.1803.1.2	Configured per-port timer values for PFC Watchdog. **Since: 4.20.0
schedulerCompensation-Supported **	*boolean*	Scheduler compensation supported. **Since: 4.26.2
[tcToCosNamedMap] **	*string*	TC-to-COS map. **Since: 4.35.0
trustMode **	*enum: cos | dscp | invalid | untrusted*	Qos Trustmode of interface. **Since: 4.17.0
txQueueProfiles	*table(numeric string) = TxQueueProfileModel* see 2.1803.1.3	A mapping between Transmit queue id and Transmit Queue configuration.

2.1803.1.1 PfcProfileModel

dynamicLoadBalancing	*boolean*	Dynamic load balancing.

2.1803.1.2 PfcWatchdogPortTimerModel

forcedRecovery	*boolean*	Force recover any stuck queue(s) after the recoveryTimer duration, irrespective of whether PFC frames are being received or not.
pollingInterval	*floating point number*	Configure the interval at which the watchdog should poll the queue(s).
recoveryTime	*floating point number*	Configure recovery-time after which stuck queue should recover and start forwarding.
timeout	*floating point number*	Configure timeout after which port should be errdisabled or should start dropping on congested priorities or just notify about the event.

2.1803.1.3 TxQueueProfileModel

txQueueModel	*TxQueue* see 2.1803.1.3.1	Transmit Queue model.

2.1803.1.3.1 TxQueue

[decn] **	*DecnParametersModel* see 2.1787.1.1	Transmit Queue Dynamic ECN Parameters. Not Applicable if Transmit Queue Dynamic ECN is disabled. **Since: 4.33.0
[dpThresholds] **	*table(numeric string) = DropPrecedenceThresholdsModel* see 2.1803.1.3.1.1	Tail drop thresholds per Drop Precedence. **Since: 4.22.0
[dpWred] **	*table(numeric string) = WredParametersModel* see 2.1790.1.1.1	Transmit Queue Dp WRED Parameters.Not Applicable if Transmit Queue Dp WRED is disable. **Since: 4.28.1
[dropThreshold] **	*DropThresholdModel* see 2.1783.1.1.1	Temporal tail drop threshold. **Since: 4.35.2
[ecn]	*EcnParametersModel* see 2.316.1.1.2	Transmit Queue ECN Parameters. Not Applicable if Transmit Queue ECN is disabled.
[ecnCounter] **	*boolean*	Count congested packets. **Since: 4.31.0
[ecnDelay] **	*EcnDelayConfigurationModel* see 2.1803.1.3.1.2	Transmit Queue Delay based ECN Parameters. Not Applicable if Transmit Queue delay ECN is disabled. **Since: 4.17.0

[ecnDelayConfig] **	*EcnDelayTxQParameters-Model* see 2.1803.1.3.1.3	Transmit Queue ECN Delay Parameters. Not Applicable if Transmit Queue ECN is disabled. **Since: 4.32.0
ecnMarkProbSupported **	*boolean*	ECN Mark Probability Supported,. **Since: 4.21.3
ecnWeightSupported **	*boolean*	ECN Weight Supported. **Since: 4.21.3
[guaranteedBw]	*GuaranteedBwModel* see 2.1782.1.1.2	Configured guaranteed bandwidth.
[latencyThreshold] **	*LatencyThresholdModel* see 2.1803.1.3.1.4	Configured latency threshold. **Since: 4.23.0
[noPriority] **	*boolean*	Transmit Queue priority. **Since: 4.30.2
[nonEct] **	*EcnParametersModel* see 2.316.1.1.2	Transmit Queue NON-ECT Parameters. Not Applicable if Transmit Queue NON-ECT is disabled. **Since: 4.20.5
nonEctWeightSupported **	*boolean*	NON-ECT Weight Supported. **Since: 4.21.3
[shapeRate]	*ShapeRateModel* see 2.584.1.1.1.2	Configured shape rate.
txQueue	*integer*	Transmit Queue id.
[txQueueType] **	*enum: mc-tx-queue | tx-queue | uc-tx-queue*	Type of Transmit Queue. It is tx-queue for platforms that don't support multicast and unicast queues. **Since: 4.17.0
[weightConfig] **	*integer*	Configured weight. **Since: 4.30.2
[wred] **	*WredParametersModel* see 2.1790.1.1.1	Transmit Queue WRED Parameters. Not Applicable if Transmit Queue WRED is disabled. **Since: 4.17.0
wredWeightSupported **	*boolean*	WRED Weight Supported. **Since: 4.21.3
[wrrBandwidthPercent]	*integer*	Configured WRR bandwidth in percent.

2.1803.1.3.1.1 DropPrecedenceThresholdsModel

percent	*integer*	Tail drop-thresholds in percent of corrrespondingDrop Precedence 0 threshold value.

2.1803.1.3.1.2 EcnDelayConfigurationModel

Could also be an instance of:
EcnDelayParametersModel 2.316.1.1.1

[configuredMarkProb] **	*floating point number*	Configured Mark Probability value in percentage. **Since: 4.35.0

[configuredMinThreshold] **	*floating point number*	Configured Minimum Threshold value in microseconds. **Since: 4.35.0
[configuredThreshold]	*floating point number*	Configured Threshold value in microseconds.
[source]	*enum: local | none | global*	Configuration source.

2.1803.1.3.1.3 EcnDelayTxQParametersModel

maxMarkProbability **	*integer*	Maximum marking probability. **Since: 4.35.0
maxThreshold	*integer*	Maximum Threshold for ECN.
minThreshold **	*integer*	Minimum Threshold for ECN. **Since: 4.35.0
unit	*enum: percent | mbytes | bytes | segments | kbytes | microseconds | milliseconds*	Threshold unit for ECN.

2.1803.1.3.1.4 LatencyThresholdModel

threshold	*integer*	Configured latency threshold.
unit	*string*	Latency threshold unit.

2.1804 show qos profile summary [...]

qosProfileApplication	*table(string) = QosProfileConfiguredIntfs* see 2.1804.1	A mapping between QoS Profile name and configured interfaces.

2.1804.1 QosProfileConfiguredIntfs

intfs	*list of string*	Interface name.

2.1805 show qos random-detect ecn [...]

Could also be an instance of:
GlobalAllEcnModel 2.1779

delayEcnSupported **	*boolean*	Global Delay based ECN supported. **Since: 4.17.0
[globalEcnDelayParameters] **	*EcnDelayParametersModel* see 2.316.1.1.1	Global delay based ECN Parameters. Not applicable if Global delay based ECN is disabled. **Since: 4.17.0
[globalEcnParameters]	*EcnParametersModel* see 2.316.1.1.2	Global length based ECN Parameters. Not applicable if Global length based ECN is disabled.
globalEcnSupported **	*boolean*	Global Buffer ECN supported. **Since: 4.17.0

`globalEcnWeightSupported` **	*boolean*	Global ECN Supported. **Since: 4.21.3

see 2.1779

2.1806 show qos scheduler profile [...]

profiles	*table(string) = QosSchedulerProfilePerSpeedAdjacencyModel* see 2.1806.1	A mapping of Qos scheduler profiles.

2.1806.1 QosSchedulerProfilePerSpeedAdjacencyModel

attributes	*table(string) = QosSchedulerProfileConfigModel* see 2.1806.1.1	A mapping of QoS scheduler profiles attributes and configurations.

2.1806.1.1 QosSchedulerProfileConfigModel

interfaces	*list of string*	Interface name.
parameters	*QosSchedulerProfileParametersModel* see 2.1806.1.1.1	Parameters of a QoS scheduler profile.

2.1806.1.1.1 QosSchedulerProfileParametersModel

creditRequestActiveForced	*boolean*	Credit request active forced.
creditRequestActiveThreshold	*integer*	Credit request active threshold.
creditRequestLatency	*integer*	Credit request latency.
creditRequestPreallocation	*integer*	Credit request preallocation.
creditRequestRateProgressionThreshold	*integer*	Credit request rate progression threshold.
creditRequestRateProgressionThresholds	*table(numeric string) = QosSchedulerProfileRateProgressionThresholds* see 2.1806.1.1.1.1	A mapping between rate progression levels and their thresholds.
creditRequestStatusIndicationThreshold	*integer*	Credit request status indication threshold.
emptyQueueBalanceExcessAllowed	*boolean*	Empty queue balance excess allowed.
emptyQueueBalanceMaximum	*integer*	Empty queue balance maximum.
emptyQueueBalanceMinimum	*integer*	Empty queue balance minimum.
excessCreditProtectionMaximumBalance	*integer*	Excess credit protection maximum balance.
excessCreditProtectionMaximumCredit	*integer*	Excess credit protection maximum credit.
excessCreditProtectionProgressive	*integer*	Excess credit protection progressive.

2.1806.1.1.1.1 QosSchedulerProfileRateProgressionThresholds

high	*integer*	Rate progression high threshold.
low	*integer*	Rate progression low threshold.

2.1807 show qos scheduler profile summary

profileName **	*string*	Scheduler profile. **Since: 4.35.0
profiles	*table(string) = QosSchedulerProfilePerSpeedAdjacencyModel* see 2.1806.1	A mapping of Qos scheduler profiles.

2.1808 show qos scheduling group [...]

interfaces	*table(Interface name) = IntfSchedulingGroupWithMembersModel* see 2.1808.1	A mapping of interface to its QoS scheduling groups.

2.1808.1 IntfSchedulingGroupWithMembersModel

schedulingGroups	*table(string) = SchedulingGroupWithMembersModel* see 2.1782.1.1.3.4	SchedulingGroups configured for the interface, indexed by their name.

2.1809 show qos scheduling hierarchy [...]

esspFlags **	*table(string) = integer*	A mapping of ESSPP flags. **Since: 4.35.2
interfaces	*table(Interface name) = QosSchedulingHierarchyModel* see 2.1809.1	A mapping of sub interface to its QoS scheduling hierarchy.

2.1809.1 QosSchedulingHierarchyModel

parentInterface	*HierarchyModel* see 2.1782.1.1.3.3	Scheduling information for the parent interface.
[schedulingGroup]	*HierarchyModel* see 2.1782.1.1.3.3	Scheduling group containing the subinterface.
subinterface	*HierarchyModel* see 2.1782.1.1.3.3	Scheduling information for the subinterface.
[txQueues]	*list of HierarchyModel* see 2.1782.1.1.3.3	List of transmit queues on the subinterface.

2.1810 show qos subinterface port-channel load-balancing

configuredLagSubIntfLoadBalancing	*boolean*	Configured Hardware based port-channel load balancing.
operationalLagSubIntfLoadBalancing	*boolean*	Operational Hardware based port-channel load balancing.

2.1811 show qos tx-queue

configuredMode	*boolean*	Configured txQueue percentage based allocation.
operationalMode	*boolean*	Operational txQueue percentage based allocation.

2.1812 show qos tx-queue shape rate precision

configured	*enum: psThreshold50Mbps | psThresholdNone*	Configured minimum precise rate.
operational	*enum: psThreshold50Mbps | psThresholdNone*	Operational minimum precise rate.

2.1813 show queue-monitor length (all | global-buffer | statistics)

bytesPerTxmpSegment	*integer*	Number of bytes per txmp segment.
entryList	*list of CongestionRecordModel* see 2.1813.1	List of the congestion records.
globalHitCount	*integer*	Number of times the global High threshold is hit.
lanzEnabled	*boolean*	Queue length monitoring enabled.
[platformName]	*enum: Xp | Sand | Strata | Barefoot | Mako*	Forwarding plane name.
reportTime	*floating point number*	UTC time at which the congestion report is generated.

2.1813.1 CongestionRecordModel

Could also be an instance of:
BarefootCongestionRecord 2.1813.2
BarefootStatisticsRecord 2.1813.3
MakoCongestionRecord 2.1813.4
MakoStatisticsRecord 2.1813.5
SandCongestionRecord 2.1813.6
SandLatencyRecord 2.1813.7
StrataCommonRecord 2.1813.8
StrataCongestionRecord 2.1813.9
StrataDropsRecord 2.1813.10
StrataLatencyRecord 2.1813.11
StrataStatisticsRecord 2.1813.12
XpCongestionRecord 2.1813.13
XpStatisticsRecord 2.1813.14

2.1813.2 BarefootCongestionRecord

duration	*integer*	Congestion duration in microseconds.
entryTime	*floating point number*	UTC time in seconds at which the congestion record occurred.
interface	*interface name*	Interface on which the congestion event occurred.
queueLength	*integer*	Queue length in segments.
txQueue	*integer*	TX-queue associated with the congestion.

2.1813.3 BarefootStatisticsRecord

interface	*interface name*	Interface on which the congestion events occurred.
numCongestionEvents	*integer*	Number of times congestion started on the interface per TX-Queue.
txQueue	*integer*	Traffic class associated with the congestion events.

2.1813.4 MakoCongestionRecord

bufferType	*enum: E | CM | I*	Congestion buffer type, I-Ingress, E-Egress, CM-Core memory.
durationUsecs	*integer*	congestion duration in microseconds.
entryTime	*floating point number*	UTC time in seconds at which the congestion record occurred.
entryType	*enum: S | E*	Congestion entry type, S-Start, E-End.
interface	*interface name*	Interface on which the congestion event occurred.

2.1813.5 MakoStatisticsRecord

bufferType	*integer*	Buffer associated with the congestion event.
interface	*interface name*	Interface on which the congestion events occurred.
numCongestionEvents	*integer*	Number of times congestion started on the interface per buffer type.

2.1813.6 SandCongestionRecord

duration	*integer*	congestion duration in seconds.
[durationUsecs]	*integer*	congestion duration in microseconds.
entryTime	*floating point number*	UTC time in seconds at which the congestion record occurred.
[entryTimeUsecs]	*integer*	UTC time in microseconds at which the congestion record occurred.
entryType	*enum: S | P | U | E*	Congestion entry type, S-Start, U-Update, E-End, P-Polling.
globalProtectionModeEnabled **	*boolean*	Global protection mode is enabled. **Since: 4.20.5
ingressPortSet	*list of Interface name*	Ingress port-set corresponding to the interfacewith the congestion.
interface	*string*	Interface on which the congestion event occurred. We monitor congestion for the front panel ports as well as the cpu port.
queueLength	*integer*	Queue length in bytes.
trafficClass	*integer*	Traffic-class associated with the congestion, if applicable. Number of traffic classes supported are 8(0 - 7).

2.1813.7 SandLatencyRecord

entryTime	*floating point number*	Time at which the TX latency is recorded.
globalProtectionModeEnabled	*boolean*	Global protection mode is enabled.
ingressPortSet	*list of Interface name*	Ingress port-set corresponding to the interface with the tx-latency.
interface	*interface name*	Destination interface.
trafficClass	*integer*	Traffic class associated with the tx delay. Number of traffic classes supported are 8(0 - 7).

txLatency	*floating point number*	Tx-delay information in usecs.

2.1813.8 StrataCommonRecord

[cardSlot]	*integer*	Card slot associated with the congestion event.Needed for distinguishing congestion records from CPU ports on multi-switch chips. Only valid for CPU congestion records.
[chipIndex]	*integer*	Chip index associated with the congestion event.Needed for distinguishing congestion records from CPU ports on multi-switch chips. Only valid for CPU congestion records.
interface	*interface name*	Interface on which the congestions events occurred.
trafficClass	*integer*	Traffic class associated with the congestion events. Number of traffic classes supported are 22 (0-11 for unicast, 12-21 for multicast).

2.1813.9 StrataCongestionRecord

[cardSlot] **	*integer*	Card slot associated with the congestion event.Needed for distinguishing congestion records from CPU ports on multi-switch chips. Only valid for CPU congestion records. **Since: 4.17.0
[chipIndex] **	*integer*	Chip index associated with the congestion event.Needed for distinguishing congestion records from CPU ports on multi-switch chips. Only valid for CPU congestion records. **Since: 4.17.0
congestionDuration	*integer*	Congestion duration associated with the congestion event (usecs). Only applicable with entries of type E. Value -1 represents an undeterministic value.
entryTime	*floating point number*	Time at which the congestion entry is generated.
entryType	*enum: S | U | E*	Congestion entry type, S-Start, U-Update, E-End.
[fabricPeerIntf] **	*string*	Peer interface for the congested fabric interface. **Since: 4.17.0
interface	*interface name*	Interface on which the congestions events occurred.
maxQueueLengthTime	*integer*	Time at which Max Queue length occurred relative to congestion start (usecs). Only applicable with entries of type E. Value of -1 represents an undeterministic value.

queueLength	*integer*	Queue length in segments, Segment size for S, U, and E type records varies per chip model.
trafficClass	*integer*	Traffic class associated with the congestion events. Number of traffic classes supported are 22 (0-11 for unicast, 12-21 for multicast).
txDrops	*integer*	Number of packet drops seen on the interface due to congestion.
txLatency	*floating point number*	Tx-delay information per interface (usecs).

2.1813.10 StrataDropsRecord

[cardSlot] **	*integer*	Card slot associated with the congestion event.Needed for distinguishing congestion records from CPU ports on multi-switch chips. Only valid for CPU congestion records. **Since: 4.17.0
[chipIndex] **	*integer*	Chip index associated with the congestion event.Needed for distinguishing congestion records from CPU ports on multi-switch chips. Only valid for CPU congestion records. **Since: 4.17.0
entryTime	*floating point number*	UTC time at which congestion drops are seen.
interface	*interface name*	Interface on which the congestions events occurred.
trafficClass	*integer*	Traffic class associated with the congestion events. Number of traffic classes supported are 22 (0-11 for unicast, 12-21 for multicast).
txDrops	*integer*	Number of packet drops seen on the interface due to congestion.

2.1813.11 StrataLatencyRecord

[cardSlot] **	*integer*	Card slot associated with the congestion event.Needed for distinguishing congestion records from CPU ports on multi-switch chips. Only valid for CPU congestion records. **Since: 4.17.0
[chipIndex] **	*integer*	Chip index associated with the congestion event.Needed for distinguishing congestion records from CPU ports on multi-switch chips. Only valid for CPU congestion records. **Since: 4.17.0
entryTime	*floating point number*	Time at which the tx latency is recorded.
interface	*interface name*	Interface on which the congestions events occurred.

trafficClass	*integer*	Traffic class associated with the congestion events. Number of traffic classes supported are 22 (0-11 for unicast, 12-21 for multicast).
txLatency	*floating point number*	Tx-delay information in usecs.

2.1813.12 StrataStatisticsRecord

[cardSlot] **	*integer*	Card slot associated with the congestion event.Needed for distinguishing congestion records from CPU ports on multi-switch chips. Only valid for CPU congestion records. **Since: 4.17.0
[chipIndex] **	*integer*	Chip index associated with the congestion event.Needed for distinguishing congestion records from CPU ports on multi-switch chips. Only valid for CPU congestion records. **Since: 4.17.0
interface	*interface name*	Interface on which the congestions events occurred.
numCongestionEvents	*integer*	Number of times congestion started on the interface per traffic-class.
trafficClass	*integer*	Traffic class associated with the congestion events. Number of traffic classes supported are 22 (0-11 for unicast, 12-21 for multicast).

2.1813.13 XpCongestionRecord

congestionDuration **	*integer*	congestion duration in microseconds. **Since: 4.20.0
entryTime	*floating point number*	UTC time in seconds at which the congestion record occurred.
entryType	*enum: S | U | E*	Congestion entry type, S-Start, U-Update, E-End.
interface	*interface name*	Interface on which the congestion event occurred.
maxQueueLengthTime	*integer*	Time at which Max Queue length occurred relative to congestion start (usecs). Only applicable with entries of type E. Value of -1 represents an undeterministic value.
queueLength	*integer*	Queue length in pages of 256 bytes.
trafficClass	*integer*	Traffic-class associated with the congestion.

2.1813.14 XpStatisticsRecord

interface	*string*	Interface on which the congestion events occurred.
numCongestionEvents	*integer*	Number of times congestion started on the interface per traffic-class.

`trafficClass`	*integer*	Traffic class associated with the congestion events. Number of traffic classes supported are 8(0 - 7).

2.1814 show queue-monitor length [...]

see 2.1813

2.1815 show queue-monitor length csv [...]

see 2.1813

2.1816 show queue-monitor length status

bytesPerRxmpSegment	*integer*	Rxmp segment size in bytes.
bytesPerTxmpSegment	*integer*	Txmp segment size in bytes.
globalBufferEnabled	*boolean*	Global buffer monitoring enabled.
globalBufferSupported	*boolean*	Global buffer monitoring supported.
globalHighThreshold	*integer*	High thresold on global buffer.
globalLogInterval	*floating point number*	Syslog interval for global buffer monitoring.
globalLowThreshold	*integer*	Low threshold on global buffer.
intfStatusAll	*table(string) = InterfaceStatusModel* see 2.1816.1	List of Interfaces.
lanzEnabled	*boolean*	Queue length monitoring enabled.
[lanzMode]	*enum: notifying | polling*	Configured queue length monitoring mode.
[lanzSliceModes] **	*table(string) = string*	Mapping of Slice name to Queue length monitoring status. **Since: 4.20.0
[latencyCapableLinecards] **	*table(string) = boolean*	Linecards capable of measuring ingresslatency. **Since: 4.22.1
logInterval	*floating point number*	Syslog interval in seconds.
lowThresholdSupported	*boolean*	lower threshold supported.
[makoShowQMonLenStatusModel] **	*MakoQueueMonitorLengthStatusModel* see 2.1816.2	Mako queue monitor length status. **Since: 4.29.0
maxQueueLength	*integer*	Maximum queue length.
mirrorDestIntf	*list of string*	Mirror destination interfaces.
mirroringSupported **	*boolean*	Mirroring supported. **Since: 4.15.2
numTotalSegments	*integer*	Total buffers in segments.
packetSamplingEnabled	*boolean*	Queue-Monitor Length Mirroring Enabled.
[platformName] **	*enum: Xp | Sand | Strata | Barefoot | Mako*	Forwarding plane name. **Since: 4.29.0
ptpSupported **	*boolean*	PTP is supported on current system. **Since: 4.22.1
qLenInterval	*integer*	Queue length interval.
queueLenUnit	*enum: bytes | segments*	Queue length specified in segments or bytes.
txLatencyEnabled **	*boolean*	Latency measurement enabled. **Since: 4.22.1
txLatencyEnablingSupported **	*boolean*	Latency measurement enabling supported. **Since: 4.28.1
txLatencyRequiresPtp **	*boolean*	Latency measurement requires PTP. **Since: 4.34.2
updateIntervalSupported	*boolean*	Update interval supported.
[updateIntervalSupportedCards] **	*table(string) = boolean*	List of cards types that support update interval. **Since: 4.23.0

2.1816.1 InterfaceStatusModel

highThreshold	*integer*	High threshold configured on the interface.
[inactiveWarning] **	*InactiveWarningModel* see 2.1816.1.1	Thresholds inactive if greater than the interface's maximum queue length. **Since: 4.20.0
lanzDisabled	*boolean*	Queue length monitoring disabled status on the interface.
lowThreshold	*integer*	Low threshold configured on the interface.
mirroringEnabled	*boolean*	Queue-monitor length mirroring enabled on the interface.

2.1816.1.1 InactiveWarningModel

maxQueueLength	*integer*	Maximum VOQ tail drop threshold.

2.1816.2 MakoQueueMonitorLengthStatusModel

[corememHighThreshold]	*integer*	High threshold on core memory buffer in bytes.
[corememLowThreshold]	*integer*	Low threshold on core memory buffer in bytes.
[corememMemorySize]	*integer*	Memory size of core memory buffer in bytes.
egressHighThreshold	*integer*	High threshold on egress buffer in bytes.
egressLowThreshold	*integer*	Low threshold on egress buffer in bytes.
egressMemorySize	*integer*	Memory size of egress buffer in bytes.
ingressHighThreshold	*integer*	High threshold on ingress buffer in bytes.
ingressLowThreshold	*integer*	Low threshold on ingress buffer in bytes.
ingressMemorySize	*integer*	Memory size of ingress buffer in bytes.
lanzEnabled	*boolean*	Queue length monitoring enabled.

2.1817 show queue-monitor streaming ((ip access-list) | (ipv6 access-list)) [...]

see 2.62

2.1818 show queue-monitor streaming clients [...]

revision 2

clientConnections	*integer*	Total number of clients connected to Lanz Streaming.
clientHostnames	*table(string) = ListOfHostnames* see 2.1818.1	A mapping of client hostname lists to VRF names.
lanzEnabled	*boolean*	Queue length monitoring enabled.
streamingEnabled	*boolean*	Queue length streaming enabled.

2.1818.1 ListOfHostnames

`hostnames`	*list of string*	List of hostnames.

2.1819 show radius

[groups]	*table(string) = ServerGroup* see 2.1819.2	Mapping of group name to group information.
lastCounterClearTime	*floating point number*	UTC time when the counters were last cleared.
radiusServers	*list of RadiusStats* see 2.1819.1	Mapping of server IP address or hostname to server information.
srcIntf	*table(string) = Interface name*	Configured source-interface name.

2.1819.1 RadiusStats

acctInterimUpdatesSent **	*integer*	Number of Accounting Interim Update messages sent to RADIUS server. **Since: 4.29.1
acctStartsSent **	*integer*	Number of Accounting Start messages sent to RADIUS server. **Since: 4.29.1
acctStopsSent **	*integer*	Number of Accounting Stop messages sent to RADIUS server. **Since: 4.29.1
badResponses	*integer*	Number of bad responses from the RADIUS server.
coaAckSent **	*integer*	Number of CoA Ack responses sent to RADIUS server. **Since: 4.22.1
coaNakSent **	*integer*	Number of CoA Nak responses sent to RADIUS server. **Since: 4.22.1
coaRequestsReceived **	*integer*	Number of CoA requests received from RADIUS server. **Since: 4.22.1
connectionErrors **	*integer*	Number of connection errors to the RADIUS server. **Since: 4.25.1
dmAckSent **	*integer*	Number of DM Ack responses sent to RADIUS server. **Since: 4.22.1
dmNakSent **	*integer*	Number of DM Nak responses sent to RADIUS server. **Since: 4.22.1
dmRequestsReceived **	*integer*	Number of DM requests received from RADIUS server. **Since: 4.22.1
dnsErrors	*integer*	Number of DNS errors by the RADIUS server.
lastAuthRequestTime **	*floating point number*	UTC timestamp of the last Authentication request sent to the RADIUS server. **Since: 4.35.2
messagesReceived	*integer*	Number of packets received from the RADIUS server.

messagesSent	*integer*	Number of packets sent to the RADIUS server.
numAuthRequestSent **	*integer*	Total number of Authentication request sent to RADIUS server. **Since: 4.35.2
requestsAccepted	*integer*	Number of requests accepted by the RADIUS server.
requestsChallenged **	*integer*	Number of challenge requests sent by the RADIUS server. **Since: 4.35.0
requestsRejected	*integer*	Number of requests rejected by the RADIUS server.
requestsRetransmitted	*integer*	Number of requests retransmitted by the RADIUS server.
requestsTimeout	*integer*	Number of requests to the RADIUS server timed out.
serverInfo	*ServerInfo* see 2.1819.1.1	Configured server information.

2.1819.1.1 ServerInfo

[acctport]	*integer*	Specifies server accounting port number.
authport	*integer*	Specifies server authorization port number.
[dot1xDynAuthEnabled] **	*boolean*	Specifies if dynamic authorization is enabled. **Since: 4.30.1
[dtlsport] **	*integer*	RADIUS server DTLS port number. **Since: 4.36.0
[dynAuthPort] **	*integer*	Specifies server dynamic authorization port number. **Since: 4.22.1
hostname	*string*	IP address or hostname of the RADIUS server.
[idleTimeout] **	*integer*	Idle timeout for RADIUS server. **Since: 4.36.0
[sslProfile] **	*string*	SSL profile for RADIUS server. **Since: 4.26.2
[tlsport] **	*integer*	RADIUS server TLS port number. **Since: 4.26.2
[vrf] **	*string*	The VRF over which this server is reachable. **Since: 4.25.1

2.1819.2 ServerGroup

members	*list of ServerInfo* see 2.1819.1.1	Mapping of server IP address or hostname to group information.
serverGroup	*string*	Configured server-group.

2.1820 show radius proxy client group [...]

groups	*table(string) = ClientGroupInfo* see 2.1820.1	Mapping of client group name to client group info.

2.1820.1 ClientGroupInfo

dynAuthDestPort **	*integer*	Dynamic authorization destination port. **Since: 4.34.1
dynAuthEnabled **	*boolean*	Enable dynamic authorization. **Since: 4.34.1
lastCounterClearTime	*floating point number*	UTC time when the counters were last cleared.
members	*list of ClientStats* see 2.1820.1.1	List of clients in a client group.

2.1820.1.1 ClientStats

acceptRespSent	*integer*	Number access-accept and password-ack messages sent to this client.
acctInterimUpdatesReceived	*integer*	Number of accounting interim update messages received from this client.
acctStartsReceived	*integer*	Number of accounting start messages received from this client.
acctStopsReceived	*integer*	Number of accounting stop messages received from this client.
badRequests	*integer*	Number of bad authentication and accounting requests received from this client.
badResponses	*integer*	Number of bad CaA and DM responses received from this client.
clientInfo	*ClientInfo* see 2.1820.1.1.1	Configured client information.
coaAcksReceived	*integer*	Number of CoA Ack responses received from this client.
coaNaksReceived	*integer*	Number of CoA Nak responses received from this client.
coaRequestsSent	*integer*	Number of CoA requests sent to this client.
connectionErrors	*integer*	Number of connection errors to the client.
dmAcksReceived	*integer*	Number of DM Ack responses received from this client.
dmNaksReceived	*integer*	Number of DM Nak responses received from this client.
dmRequestsSent	*integer*	Number of DM requests sent to this client.
messagesReceived	*integer*	Number of authentication and accounting request messages received from the client.
messagesSent	*integer*	Number of authentication and accounting response messages sent to the client.
rejectRespSent	*integer*	Number of access-reject and password-reject messages sent to this client.

2.1820.1.1.1 ClientInfo

acctPort	*integer*	Specifies accounting port number.
authPort	*integer*	Specifies authorization port number.
hostname	*string*	IP-address, subnet or hostname of the client.
[resolvedIpAddr]	*IP address and mask length*	Resolved IP-address of the client.
vrf	*string*	The VRF over which this client is reachable.

2.1821 show radius proxy server group [...]

groups	*table(string) = ServerGroupInfo* see 2.1821.1	Mapping of server group name to server group info.

2.1821.1 ServerGroupInfo

members	*list of ServerInfo* see 2.1821.1.1	List of servers in a server group.

2.1821.1.1 ServerInfo

[acctPort]	*integer*	Specifies accounting port number.
[authPort]	*integer*	Specifies authorization port number.
hostName	*string*	IP address or hostname of the RADIUS server.
[lastDeclaredDead]	*floating point number*	Switch time when the server was last declared dead.
[lastDeclaredDeadTime] **	*floating point number*	UTC time when the server was last declared dead. **Since: 4.36.0
[resolvedIpAddr]	*IP address*	Resolved IP-address of the RADIUS server.
serverId	*integer*	ID of the RADIUS server.
status	*string*	Status of the RADIUS server.
[tlsPort]	*integer*	RADIUS server TLS port number.
vrf	*string*	The VRF over which this server is reachable.

2.1822 show recirc-channel [...]

see 2.134

2.1823 show recirc-channel limits

recircChannelLimits	*table(string) = LagGroupLimits* see 2.135.1	Map a LAG Group name to the ports it applies to, and the hardware lag limits applicable to them.

2.1824 show recirc-channel traffic [...]

see 2.1729

2.1825 show redundancy file-replication

see 2.345.1.1

2.1826 show redundancy status

[agentsNotReady]	*list of string*	Agents not ready for SSO switchover.
allAgentSsoReady **	*boolean*	Agents not ready for SSO switchover. **Since: 4.26.0
[cardsSsoUnsupported] **	*list of string*	Cards SSO unsupported. **Since: 4.33.0
communicationDesc	*enum: Down | Up*	Description of communication link.
configuredProtocol	*enum: unknownProtocol | sso | simplex | rpr*	Configured redundancy protocol.
globalStageCompletion-Timeout **	*floating point number*	switchover completion timeout in seconds. **Since: 4.17.0
globalStageCompletion-TimeoutDefault **	*floating point number*	switchover completion timeout default in seconds. **Since: 4.17.0
lastRedundancyModeChange-Reason	*string*	Reason for last redundancy mode change.
[lastRedundancyModeChange-Time]	*floating point number*	Time of last redundancy mode change in UTC.
[lastSwitchoverReason] **	*string*	Reason for last switchover. **Since: 4.31.0
[lastSwitchoverTime] **	*floating point number*	Time of last switchover in UTC. **Since: 4.31.0
myMode	*enum: standby | disabled | active | unknown*	Redundancy mode of the supervisor.
operationalProtocol	*enum: unknownProtocol | sso | simplex | rpr*	Operational redundancy protocol.
[pcieModulesNotReady]	*list of string*	PCIE modules not ready for SSO switchover.
[pcieSsoReady]	*boolean*	Is PCIE switch ready for switchover.
peerMode	*enum: standby | disabled | active | unknown*	Redundancy mode of the peer supervisor.
peerState	*enum: inserted | notInserted | poweredOff | poweringOn | unknownPeerState*	Standby supervisor state.
slotId	*integer*	Slot id of the supervisor.
switchoverHotswapBum **	*boolean*	switchover hotswap early bum redirecton. **Since: 4.33.2
switchoverReady	*boolean*	Is switch ready for switchover.
switchoverReadyTimeElapsed **	*boolean*	Has the mandatory wait time after switchover elapsed. **Since: 4.26.2
unitDesc	*enum: Secondary | Primary*	Description of supervisor.

2.1827 show redundancy switchover sso

[lastSwitchoverStatus]	*enum: In Progress | Completed*	Status of last switchover.
[lastSwitchoverTime]	*floating point number*	Time of last switchover.
[logs]	*list of SwitchoverLog* see 2.1827.1	List of switchover logs.

switchoverCount	*integer*	Number of switchovers since reload.

2.1827.1 SwitchoverLog

msg	*string*	Log message.
time	*floating point number*	Time of the log relative to onset of switchover.

2.1828 show redundancy time-sync

currentMonoTimeDelta	*floating point number*	Time difference of current Monotonic time (seconds).
failCount	*integer*	Number of times that Monotonic time failed to update.
[lastErrorUpdating]	*string*	Reason for last error while updating Monotonic time.
lastMonoTimeUpdate	*floating point number*	Time of last update to Monotonic time sync.

2.1829 show reload

[allSupervisors]	*boolean*	All supervisors will be reloaded.
[reason]	*string*	Reason why a reload has been scheduled.
scheduled	*boolean*	A future reload is scheduled.
[scheduledTime]	*floating point number*	Time of the future reload (UTC).

2.1830 show reload cause [...]

[full]	*boolean*	Partial or full log.
[kernelCrashData] **	*list of string*	Kernel Panic EEPROM crash data. **Since: 4.24.2
resetCauses	*list of ReloadCause* see 2.1830.1	List of reload causes.

2.1830.1 ReloadCause

[debugInfo]	*list of string*	Information from debug file.
[debugInfoIsDir]	*boolean*	True if debug info is a directory.
description	*string*	Description of the reset cause.
[recommendedAction]	*string*	Action that is recommended.
[timestamp]	*floating point number*	Time of the reload.

2.1831 show reload cause history

resetHistory	*table(numeric string) = ReloadCauseList* see 2.1831.1	History of reload causes.

2.1831.1 ReloadCauseList

resetCauses	*list of ReloadCause* see 2.1831.1.1	List of reload causes.

2.1831.1.1 ReloadCause

[debugInfo]	*list of string*	Information from debug file.
[debugInfoIsDir]	*boolean*	True if debug info is a directory.
description	*string*	Description of the reset cause.
[recommendedAction]	*string*	Action that is recommended.
[timestamp]	*floating point number*	Time of the reload.

2.1832 show reload cause module (((MODNAME | (Supervisor MODNAME_SUPERVISOR) | (Linecard MODNAME_LINECARD) | (Fabric MODNAME_FABRIC) | (Switchcard MODNAME_SWITCHCARD))) | history) [...]

modules	*table(string) = Cli.Model.ModularReloadCauseModule* see 2.1832.1	List of modules with reload causes.

2.1832.1 Cli.Model.ModularReloadCauseModule

cards	*list of Cli.Model.ModularReloadCauseCard* see 2.1832.1.1	List of cards with reload causes.
module	*string*	Name of the module that reloads.

2.1832.1.1 Cli.Model.ModularReloadCauseCard

hwVersion	*string*	Hardware version of the card that reloads.
isInserted	*boolean*	If the card is still on the switch or not.
lastSeenTime	*floating point number*	The last time the card is seen on the switch.
model	*string*	Model name of the card that reloads.
reloadCauses	*list of Cli.Model.ModularReloadCause* see 2.1832.1.1.1	List of reload causes.
serialNum	*string*	Serial number of the card that reloads.

2.1832.1.1.1 Cli.Model.ModularReloadCause

debugInfo	*string*	Debugging information (fault logs) related to the reload.
description	*string*	Description of the reload cause.
[recommendedAction]	*string*	Action that is recommended.
recordType	*enum: ucd9012 | unknown | powerfuse*	Data type of the fault logs.

timestamp	*floating point number*	Time of the reload.

2.1833 show reload console logs [...]

consoleLog	*string*	Console log.

2.1834 show reload console status

blackboxEnabled	*boolean*	Console logging enabled.
blackboxManufacturer **	*string*	FRAM Manufacturer. **Since: 4.30.1
blackboxPowerOnRecording-Supported **	*boolean*	Console logging supported during power-on sequence. **Since: 4.33.1
blackboxProductId **	*integer*	FRAM Product ID. **Since: 4.30.1
blackboxSupported	*boolean*	Console logging supported.
consoleLogFiles	*table(numeric string) = ConsoleLogFile* see 2.1834.1	Available ConsoleLog files.

2.1834.1 ConsoleLogFile

dumpTime	*string*	ConsoleLog save time.
dumpTimestamp **	*integer*	ConsoleLog save timestamp. **Since: 4.34.2
fileName	*string*	ConsoleLog file name.
idVal	*integer*	ConsoleLog file id.

2.1835 show reload fast-boot

blockingList	*list of ReloadHitless-BlockingReason* see 2.1835.1	List blocking configuration for 'reload fast-boot'.
[inCmd] **	*string*	Command to schedule reload. **Since: 4.33.0
[scheduledReloadInfo] **	*string*	Scheduled reload info. **Since: 4.33.0
warningList	*list of ReloadHitless-WarningReason* see 2.1835.2	List of warnings for 'reload fast-boot'.

2.1835.1 ReloadHitlessBlockingReason

reason	*enum: IPv4uRPF* | *mstInstances* | *mlagStateUnstable* | *mlagNotEstablished* | *exceedSupportedTopology* | *portRole* | *stpNotReady* | *pbrConfigured* | *lacpRateFastLocalConfigured* | *tunnelIntfConfigured* | *lacpRateFastRemoteConfigured* | *stpBpduguard* | *directFlowEnabled* | *stpMode* | *transmitActive* | *maintenanceModeConfigured* | *vrrpEnabled* | *lagModeInconsistent* | *vxlanConfigured* | *openFlowEnabled* | *edgePort* | *IPv6uRPF*	IPv4uRPF : IPv4 uRPF is in ErrorDisabled state IPv6uRPF : IPv6 uRPF is in ErrorDisabled state directFlowEnabled : Directflow is enabled vrrpEnabled : VRRP is enabled lacpRateFastLocalConfigured : lacp fast rate configured locally lacpRateFastRemoteConfigured : lacp fast rate configured remotely openFlowEnabled : Openflow is enabled pbrConfigured : Pbr is configured stpMode : Spanning-tree mode is not supported edgePort : Spanning-tree portfast is not enabled for one or more ports portRole : One or more non-edge ports are in spanning-tree designated/backup role transmitActive : Transmit active is enabled for one or more ports mstInstances : Spanning-tree is enabled with more than one MST instance stpBpduguard : Spanning-tree BPDU guard is not enabled for one or more ports maintenanceModeConfigured : Maintenance Mode is configured lagModeInconsistent : Lag Modes differ between hardware and configuration mlagStateUnstable : Mlag state is neither primary nor secondary mlagNotEstablished : Mlag peer negotiation is not done yet vxlanConfigured : Vxlan is configured tunnelIntfConfigured : Tunnel Interface is configured exceedSupportedTopology : More spanning-tree topologies are configured than are supported on this platform stpNotReady : STP is not ready.

2.1835.2 ReloadHitlessWarningReason

reason	*enum: pimEnabled* | *bgpNoGrace* | *stpErrDisabled* | *mlagConfigured* | *mlagVersionCompatibility* | *insufficientUptime* | *ospf3NoGrace* | *macsec* | *ospfNoGrace* | *stpState* | *pfcWatchdogEnabled* | *igmpSnoopingQuerierVersion* | *runtimeErrdisabledIntfs* | *ptpEnabled* | *isisNoGrace* | *MACsecNonXPNCipherSuite* | *macSecFipsRestrictions* | *reloadDelayConfigured* | *igmpSnoopingEnabled* | *pimBidirEnabled* | *ripEnabled* | *pimHoldTime* | *mlagPortsActivePartial* | *varpEnabled*	bgpNoGrace : BGP is configured without graceful restart ospfNoGrace : OSPF is configured without graceful restart isisNoGrace : IS-IS is configured without graceful restart ospf3NoGrace : OSPF3 is configured without graceful restart pimEnabled : PIM is enabled ripEnabled : RIP is enabled varpEnabled : VARP is enabled igmpSnoopingEnabled : IGMP Snooping is enabled igmpSnoopingQuerierVersion : If you are performing an upgrade, the Igmp Snooping elected Querier version needs to be set to 3, else the upgrade will result in packet loss stpErrDisabled : One or more ports is errDisabled due to BPDU guard stpState : STP is not currently restartable mlagConfigured : Mlag is configured runtimeErrdisabledIntfs : Runtime errdisabled interface(s) found. Please note that they will be reenabled after hitless reload. If same conditions persist, interface(s) will be errdisabled again after the reload. ptpEnabled : PTP is enabled. PTP slaves will lose connection to the grandmaster and lose time sync. pfcWatchdogEnabled : PFC Watchdog is enabled. The current PFC Watchdog state may be lost on hitless reload. Monitoring will restart after the reload. mlagVersionCompatibility : If you are performing an upgrade, and the Release Notes for the new version of EOS indicate that MLAG is not backwards-compatible with the currently installed version (None), the upgrade will result in packet loss. mlagPortsActivePartial : reloadDelayConfigured : Mlag is configured with non-zero mlag/non-mlag reload-delay. This may result in packet loss pimBidirEnabled : PIM bidirectional is enabled pimHoldTime : Pim interface has join/prune holdtime that is less than two times default holdtime. This may result in packet loss macSecFipsRestrictions : MACsec FIPS restrictions are enabled. This may result in an extended traffic outage to perform FIPS POST during the reload. insufficientUptime : MACsecNonXPNCipherSuite : MACsec is enabled on the device with interfaces configured with aes128-gcm or aes256-gcm cipher suites. These interfaces may see extended traffic outage. macsec : MACsec is enabled.

2.1836 show reload hitless

blockingList	*list of ReloadHitlessBlockingReason* see 2.1835.1	List blocking configuration for 'reload hitless'.
warningList	*list of ReloadHitlessWarningReason* see 2.1835.2	List of warnings for 'reload hitless'.

2.1837 show rib loop (ip | ipv6) route [...]

loopedRoutes	*table(IPv4 or IPv6 address prefix) = LoopedRoute* see 2.1837.1	Map of routes involved in recursive route resolution loops.

2.1837.1 LoopedRoute

allNextHopsPartOfLoop	*boolean*	Set to true if all next-hops of this route are part of recursive route resolution loops.
protocol	*string*	The protocol for the looped route.

2.1838 show rib multicast route (ip | ipv6) [...]

revision 4

see 2.773

2.1839 show rib next-hop (ip | ipv6) [...]

revision 2

ribNextHopsByProtocol	*table(string) = RibNextHop* see 2.1839.1	Map of next-hop vias for each routing protocol.

2.1839.1 RibNextHop

[recursiveNextHops]	*list of RecursiveNextHop* see 2.773.1.1.1.1	List of next-hop routers through which routes in the RIB are reachable.
[resolvedNextHops]	*list of ResolvedNextHop* see 2.773.1.1.1.4	List of immediate next-hop routers through which routes in the RIB are reachable.
[ribNextHop]	*RibNextHopRibNextHop* see 2.1839.1.1	RIB nexthop.

2.1839.1.1 RibNextHopRibNextHop

[recursiveNextHops]	*list of RecursiveNextHop* see 2.773.1.1.1.1	Map of next-hop routers through which routes in the RIB are reachable.
[resolvedNextHops]	*list of ResolvedNextHop* see 2.773.1.1.1.4	List of immediate next-hop routers through which routes in the RIB are reachable.

2.1840 show rib next-hop (ip | ipv6) dependency

[ribNhDependencyByVrf]	*table(string) = RecursiveNhDependencyByProtocol* see 2.1840.1	Next-hop dependencies for all vrfs.

2.1840.1 RecursiveNhDependencyByProtocol

[ribNhDependencyByProtocol]	*table(string) = RecursiveNhDependencies* see 2.1840.1.1	Next-hop dependencies for all protocols in this vrf.

2.1840.1.1 RecursiveNhDependencies

[nextHops]	*list of RecursiveNhDependency* see 2.1840.1.1.1	List of next-hops and their dependencies.

2.1840.1.1.1 RecursiveNhDependency

[loopedNextHop]	*boolean*	Set to true if this next-hop is part of a recursive route resolution loop, false otherwise.
[nextHop]	*IP address*	Next hop router address.
[recursiveNextHops]	*list of RecursiveNhDependency* see 2.1840.1.1.1	The list of LPM next-hop routers through which this recursive next-hop is reachable.
[resolvedNextHops]	*list of ResolvedNextHop* see 2.773.1.1.1.4	The list of immediate next-hop routers through which this recursive next-hop is reachable.
[resolvingRoute]	*IP address prefix*	Covering route for this next-hop.
[routeType]	*enum: rip | connected | ospf3 | ospf | routingProtocols | staticConfig | vrfLeak | bgp | reserved | dynamicPolicy | routeInput | isis*	Protocol through which resolving route was learned.
[viaId]	*integer*	ID of Via.
[vrfName]	*string*	Name of VRF from which this next-hop was requested.

2.1841 show rib next-hop resolution route (ipv4 | ipv6) [...]

revision 2

[rcfExpr] **	*string*	RIB recursive resolution policy RCF expression. **Since: 4.35.2
[routeMap]	*string*	RIB recursive resolution policy route map.
[routes]	*table(IPv4 or IPv6 address prefix) = ResolutionRoute* see 2.1841.1	Map of routes to their recursive resolution status.

2.1841.1 ResolutionRoute

communityList **	*list of string*	BGP communities. **Since: 4.31.0
lastUpdateEpochTime **	*integer*	Timestamp in UTC time of the last time the route has been updated. **Since: 4.31.0
metric	*integer*	The routing protocol internal metric (cost) for this route.
metricType	*enum: AIGP | MED | metric*	The type of metric.
pendingAttributes **	*boolean*	Set to true if the tag or communityList is pending. **Since: 4.31.0
preference	*integer*	The administrative distance of this route.
protocol	*enum: routeInputRouteCacheConfig | rip | connected | ospf3 | ospf | routingProtocols | staticConfig | vrfLeak | bgp | staticRouteCacheConfig | gribi | reserved | dynamicPolicy | cbf | routeInput | isis*	The routing protocol for this route.
[recmpEligible] **	*boolean*	Set to true if this route is marked eligible for RECMP. **Since: 4.31.0
[recursiveNextHops]	*list of RecursiveNextHop* see 2.773.1.1.1.1	List of next-hop routers through which routes in the RIB are reachable.
resolvability	*enum: uninitialized | reject | accept*	The resolvability of this route.
[resolvedNextHops]	*list of ResolvedNextHop* see 2.773.1.1.1.4	List of immediate next-hop routers through which this route is reachable.
[tag] **	*integer*	The tag. **Since: 4.31.0

2.1842 show rib ready [...]

vrfs	*table(string) = RibReadyModel* see 2.1842.1	Per VRF Rib ready summary.

2.1842.1 RibReadyModel

[flags] **	*RibReadyFlags* see 2.1842.1.2	Various checkpoints along the path to declare Fib readyin ribd protocol model. **Since: 4.21.0
gracefullyRestarting	*boolean*	The vrf is gracefully restarting or not.
[protocols]	*table(string) = ProtoReadyModel* see 2.1842.1.1	Current state of the protocols taking part in the Rib ready process in multi-agent protocol model, key being protocol name.
[routes] **	*table(string) = RouteReady* see 2.1842.1.4	Current state of the route types considered part of the Rib ready process in ribd protocol model, key being route type. **Since: 4.21.0
startTime	*floating point number*	UTC time at which Rib ready verification was started.
[states]	*RibReadyStateModel* see 2.1842.1.3	Various states that occur during the Rib ready verification in the multi-agent protocol model.

2.1842.1.1 ProtoReadyModel

configPending	*boolean*	Whether processing of protocol configuration is pending or not.
configured	*boolean*	Whether the protocol is configured.
ready	*boolean*	Whether the protocol has converged.
[readyTime]	*floating point number*	UTC timestamp when this protocol became ready.
[timeTaken]	*floating point number*	Time elapsed from start until this protocol becomes ready.

2.1842.1.2 RibReadyFlags

fibReady	*boolean*	Whether the routes have been synced to FIB.
recursiveResolution	*boolean*	Whether the static routes have been recursively resolved.
ribReady	*boolean*	Whether all protocols have converged.
[timeTakenForFibReady]	*floating point number*	Time elapsed in seconds from start until FIB became ready.
[timeTakenForRecursive-Resolution]	*floating point number*	Time elapsed in seconds from start until static routes were recursively resolved.
[timeTakenForRibReady]	*floating point number*	Time elapsed in seconds from start until all protocols converged.
[timeTakenForV4RouteSync]	*floating point number*	Time elapsed in seconds from start until v4 routes were synced.
[timeTakenForV6RouteSync]	*floating point number*	Time elapsed in seconds from start until v4 routes were synced.

v4RouteSync	*boolean*	Whether v4Routes have been synced to Fib.
v6RouteSync	*boolean*	Whether v6 routes have been synced to Fib.

2.1842.1.3 RibReadyStateModel

fibReady	*boolean*	Whether the routes have been synced to FIB.
[fibReadyTime]	*floating point number*	UTC time at which all routes were synced to FIB.
igpReady	*boolean*	Whether IGPs have converged.
[igpReadyTime]	*floating point number*	UTC time at which IGPs converged.
recursiveResolution	*boolean*	Whether recursive resolution is complete.
[recursiveResolutionTime]	*floating point number*	UTC time at which recursive route resolution was complete.
ribReady	*boolean*	Whether all protocols have converged.
[ribReadyTime]	*floating point number*	UTC time at which all protocols converged.
[timeTakenForFibReady]	*floating point number*	Time elapsed in seconds from start until FIB became ready.
[timeTakenForIgpReady]	*floating point number*	Time elapsed in seconds from start until IGPs converged.
[timeTakenForRecursive-Resolution]	*floating point number*	Time elapsed in seconds from start until recursive resolution was complete.
[timeTakenForRibReady]	*floating point number*	Time elapsed in seconds from start until all protocols converged.

2.1842.1.4 RouteReady

configPending	*boolean*	Whether processing of route configuration is pending.
configured	*boolean*	Whether the route type is configured.
ready	*boolean*	Whether the route type has converged.
[timeTaken]	*floating point number*	Time elapsed from start until this route type became ready.

2.1843 show rib route (ip | ipv6) [...]

revision 4

see 2.773

2.1844 show rib route (ip | ipv6) internal [...]

revision 4

see 2.773

2.1845 show rib route (ip | ipv6) tag TAG [...]

revision 4

see 2.773

2.1846 show rib route summary [...]

ribRouteSummary	*table(string) = RibRouteSummaryForVrf* see 2.1846.1	Summary of routes in the RIB of each VRF.

2.1846.1 RibRouteSummaryForVrf

routeCountPerProtocol	*table(string) = integer*	Total number of routes for each routing protocol in the RIB.

2.1847 show rib route summary brief [...]

see 2.1846.1

2.1848 show rib system-tunneling-ldp-rib route ipv4 [...]

revision 2

see 2.807.1.1.3

2.1849 show route (ipv4 | ipv6) counters [...]

vrfs	*table(string) = RouteCounters* see 2.1849.1	A mapping of VRF name to per prefix counters.

2.1849.1 RouteCounters

counters	*list of RouteCounterEntry* see 2.1849.1.1	List of prefix counters.
[uniqueBackup] **	*boolean*	Dedicated backup enabled in VRF. **Since: 4.29.1

2.1849.1.1 RouteCounterEntry

[backupByteCount] **	*integer*	Backup path byte count. **Since: 4.29.1
[backupPacketCount] **	*integer*	Backup path packet count. **Since: 4.29.1
byteCount	*integer*	Byte count.
packetCount	*integer*	Packet count.

prefix	*IP address prefix*	Route prefix.
[programmed] **	*boolean*	Counter is programmed in hardware. **Since: 4.29.1

2.1850 show route cache (vrf (VRF | all)) [...]

[cmdErr]	*string*	Error message.
[vrfs]	*table(string) = Prefix* see 2.1850.1	Mapping of VRF name to IP routes.

2.1850.1 Prefix

[routes]	*table(IPv4 or IPv6 address prefix) = PrefixData* see 2.1850.1.1	Mapping of prefix to its corresponding data.

2.1850.1.1 PrefixData

[inHw]	*boolean*	Prefix in hardware.
[nextHopId]	*integer*	Next-hop index.
[nextHopInfo]	*table(numeric string) = NextHopInfo* see 2.1850.1.1.1	Mapping of next-hop id to next-hop info.

2.1850.1.1.1 NextHopInfo

macAddress	*MAC address*	Overlay MAC address.
remoteVtep	*IP address*	Remote VTEP IP address.
underlayFecId	*integer*	Underlay FEC ID.
vlanId	*integer*	VLAN ID.
vni **	*integer*	VNI. **Since: 4.25.2
vxlanId **	*interface name*	VXLAN Interface. **Since: 4.25.2

2.1851 show route cache (vrf (VRF | all)) ipv6 [...]

see 2.1850

2.1852 show route cache summary [...]

[cmdErr]	*string*	Error Message.
[summary]	*table(string) = RouteCacheSummary* see 2.1852.1	Route cache summary for IPv4.
[summaryIPv6] **	*table(string) = RouteCacheSummary* see 2.1852.1	Route cache summary for IPv6. **Since: 4.25.2

total **	*RouteCacheSummary* see 2.1852.1	Total across all VRFs and address families. **Since: 4.25.2

2.1852.1 RouteCacheSummary

configuredRoutes	*integer*	Number of routes configured.
routesInHw	*integer*	Number of routes programmed in Hardware.
routesInSfe	*integer*	Number of routes programmed in SFE.
unprogrammedRoutes	*integer*	Number of unprogrammed routes.

2.1853 show route cache threshold

thresholdParams	*table(string) = ThresholdParams* see 2.1853.1	Threshold params for different levels.

2.1853.1 ThresholdParams

hwUtil	*integer*	Hardware space utilization in percentage for this threhold level to kick in.
idleTime	*integer*	Idle time limit for prefixes at this threhold level in seconds.

2.1854 show route-map [...]

revision 5

see 2.1026.1.2

2.1855 show route-map config-sanity

revision 5

see 2.1026.1.3

2.1856 show route-map expanded [...]

revision 5

[mapName]	*string*	Name of specific route map to render.
pruned	*boolean*	Avoid rerendering common subtrees.
routeMaps	*table(string) = ExpandedRouteMap* see 2.1856.1	Route maps by name.

2.1856.1 ExpandedRouteMap

[entries]	*table(numeric string) = ExpandedRouteMapEntry* see 2.1856.1.1	Route map entries by sequence number.

2.1856.1.1 ExpandedRouteMapEntry

[continueClause]	*boolean*	Continue to next clause.
[continueSeqno]	*integer*	Sequence number of next clause.
description	*list of string*	Route map entry description.
filterType	*enum: deny | permit*	Filter type.
matchRules	*MatchRules* see 2.158.1.3.2.1	Match rules.
setRules	*SetRules* see 2.158.1.3.2.8	Set rules.
[statementName] **	*string*	Statement name for the YANG model. **Since: 4.33.0
[subRouteMap]	*SubRouteMap* see 2.1026.1.2.1.2	Sub route map.

2.1857 show router igp topology [...]

revision 2

`vrfs`	*table(string) = VrfModel* see 2.1857.1	IGP topology database per VRF.

2.1857.1 VrfModel

`[isis]`	*IgpInstanceInfoModel* see 2.1857.1.1	IGP topology information for IS-IS.
`[ospf]` **	*OspfInstanceInfoModel* see 2.1857.1.2	IGP topology information for Ospf. **Since: 4.31.1

2.1857.1.1 IgpInstanceInfoModel

`instances`	*table(numeric string) = IsisModel* see 2.1857.1.1.1	A mapping of the IGP instance ID to the IGP database.

2.1857.1.1.1 IsisModel

`[level1]`	*CommonProtocolModel* see 2.1857.1.1.1.1	IS-IS Level-1 topology information.
`[level2]`	*CommonProtocolModel* see 2.1857.1.1.1.1	IS-IS Level-2 topology information.

2.1857.1.1.1.1 CommonProtocolModel

`[ipv4]`	*table(string) = RouterModel* see 2.1857.1.1.1.2	IPv4 topology information per router ID.
`[ipv6]`	*table(string) = RouterModel* see 2.1857.1.1.1.2	IPv6 topology information per router ID.

2.1857.1.1.1.2 RouterModel

`[flexAlgo]` **	*list of integer*	List of all supported Flex Algos. **Since: 4.27.1
`[lanLinks]` **	*table(string) = NeighborListModel* see 2.1857.1.1.1.3	Neighbor information per LAN neighbor. **Since: 4.35.2
`[lans]`	*table(string) = NeighborModel* see 2.1857.1.1.1.4	Neighbor information per LAN neighbor for individually linked neighbors (deprecated - use lanLinks for the generalized case of multiply linked neighbors).
`[p2pLinks]` **	*table(string) = NeighborListModel* see 2.1857.1.1.1.3	Neighbor information per P2P neighbor. **Since: 4.35.2

[p2ps]	*table(string) = NeighborModel* see 2.1857.1.1.1.4	Neighbor information per P2P neighbor for individually linked neighbors (deprecated - use p2pLinks for the generalized case of multiply linked neighbors).
[reachability]	*table(IPv4 or IPv6 address prefix) = ReachabilityModel* see 2.1857.1.1.1.7	Reachability information per prefix.

2.1857.1.1.1.3 NeighborListModel

links	*list of NeighborModel* see 2.1857.1.1.1.4	List of all the links per neighbor.

2.1857.1.1.1.4 NeighborModel

[flexAlgoAttributes] **	*FlexAlgoAttributesModel* see 2.1857.1.1.1.5	flexAlgo related Attributes. **Since: 4.27.1
[interfaceAddresses]	*list of IP address*	Local interface IP addresses.
[localLinkId] **	*integer*	Local link ID. **Since: 4.36.0
metric	*integer*	Link cost.
[neighborAddresses]	*list of IP address prefix*	Remote interface IP addresses.
[remoteLinkId] **	*integer*	Remote link ID. **Since: 4.36.0

2.1857.1.1.1.5 FlexAlgoAttributesModel

[administrativeGroup]	*integer*	Administrative Group of the Link.
[administrativeGroups-Extended] **	*list of integer*	Extended Administrative Groups of the Link. **Since: 4.31.1
[defaultTeMetric] **	*integer*	TE default metric. **Since: 4.30.1
[minimumDelayMetric]	*integer*	Minimum Delay Metric in microseconds.
[sharedRiskLinkGroups]	*list of SharedRiskLinkGroup* see 2.1857.1.1.1.6	List of Shared Risk Link Group.

2.1857.1.1.1.6 SharedRiskLinkGroup

srlgId	*integer*	Shared Risk Link Group Identifier.
[srlgName]	*string*	Shared Risk Link Group Name.

2.1857.1.1.1.7 ReachabilityModel

[algo] **	*list of integer*	List of associated Flexible algorithms. **Since: 4.33.2
metric	*integer*	Link cost.

2.1857.1.2 OspfInstanceInfoModel

[instances]	*table(numeric string) = OspfModel* see 2.1857.1.2.1	A mapping of OSPF instance ID to OSPF database.

2.1857.1.2.1 OspfModel

[areas]	*table(string) = CommonProtocolModel* see 2.1857.1.1.1.1	OSPF topology information per area.

2.1858 show router rcf code [...]

rcfCodeUnits	*table(string) = string*	RCF code unit text keyed by code unit name.

2.1859 show router rcf errors [...]

active	*boolean*	Routing control functions are active.
compilationErrors	*list of string*	Routing control function running-config errors.

2.1860 show router rcf function FUNC_NAME

functionLocation	*FunctionLocationModel* see 2.1860.1	RCF function location information.
functionText	*string*	RCF function text.

2.1860.1 FunctionLocationModel

codeUnit	*string*	Code unit that the function is stored in.
lineNum	*integer*	Line number of the start of the function within the code unit.

2.1861 show router rcf function location [...]

functions	*table(string) = FunctionLocationModel* see 2.1860.1	RCF function location information keyed by function name.

2.1862 show router rcf pending

revision 2

pendingChanges	*boolean*	There are pending routing control function changes.
[rcfCode]	*RcfPendingCodeUnitModel* see 2.1862.1	Pending routing control function code.

rcfCodeUnits	*table(string) = RcfPendingCodeUnitModel* see 2.1862.1	Pending routing control function code units keyed by unit name.
rcfOpenConfigFunctions **	*table(string) = RcfPending-OpenConfigFunctionModel* see 2.1862.2	Pending OpenConfig functions keyed by function name. **Since: 4.35.2

2.1862.1 RcfPendingCodeUnitModel

[commandTag] **	*string*	Command tag associated with this code unit. **Since: 4.32.1
commandTagModified **	*boolean*	The command tag association for this code unithas been modified. **Since: 4.32.1
[rcfText]	*string*	Pending routing control function code unit text.
rcfTextModified	*boolean*	This pending code unit text has been modified.
[url]	*string*	Source file URL.

2.1862.2 RcfPendingOpenConfigFunctionModel

[text]	*string*	Pending OpenConfig function text.
textModified	*boolean*	This pending OpenConfig function text has been modified.

2.1863 show running-config [...]

see 2.324.1.1

2.1864 show running-config all [...]

see 2.324.1.1

2.1865 show running-config digest [...]

digest	*string*	Message digest for running-config or session-config.

2.1866 show schedule NAME | summary

jobs	*table(string) = ScheduleJobModels* see 2.1866.1	Maps job names to their respective details.
[maxJobs]	*integer*	Maximum number of jobs in progress at the same time.
[prependHostname]	*boolean*	Prepend host name to logfile.

2.1866.1 ScheduleJobModels

cliCommand	*string*	Scheduled Cli Command.
compressAlgo **	*string*	Compression algorithm. **Since: 4.33.0
interval	*integer*	Cli command execution interval (in mins).
[jobInProgress]	*boolean*	Job in progress.
[jobInProgressStartTime]	*floating point number*	Cli commmand in progress execution start time (in secs).
[lastRun]	*floating point number*	Time the job last executed (in secs).
[lastRunStatus]	*integer*	Cli command last execution status.
logfileDirectory	*string*	Logfile directory location.
maxLogFiles	*integer*	Maximum number of logfiles stored.
maxTotalSize **	*integer*	Maximum total size of log files in bytes. **Since: 4.26.2
nextRun	*floating point number*	Next execution start time (in secs).
timeout	*floating point number*	Cli command execution timeout (in secs).
verbose	*boolean*	Verbose logging state.

2.1867 show security first-instruction

[amd]	*AmdStatus* see 2.1867.1	AMD CPU specific attributes.
developmentConfiguration-Fused	*boolean*	Whether CPU is fused with development configuration.
firstInstructionTechnology	*enum: amdPlatformSecureBoot | intelBootGuard*	First instruction technology by CPU.
[intel]	*IntelStatus* see 2.1867.2	Intel CPU specific attributes.
productionConfiguration-Fused	*boolean*	Whether CPU is fused with production configuration.

2.1867.1 AmdStatus

modelId	*integer*	AMD PSB model ID.
revisionId	*integer*	AMD PSB revision ID.

2.1867.2 IntelStatus

oemKeyHash	*string*	Intel OEM key Hash.

2.1868 show security pki certificate rotation ROTATION_ID

[certificate]	*Certificate* see 2.1085.1	Certificate imported into this rotation.
certificateSigningRequest	*CertificateSigningRequest* see 2.1868.1	The certificate signing request for the rotation.
creationTime	*integer*	Time rotation was created.
importTimeout	*integer*	Number of mins after rotation creation time that a certificate must be imported by.
profileName	*string*	SSL profile name for this rotation.
rotationId	*string*	Rotation ID.
rotationState	*enum: importPending* | *commitPending* | *importExpired* | *commitExpired*	Rotation states. importPending: Pending import of certificate. importExpired: Certificate was not imported within importTimeout window. commitPending: Certificate has been imported, waiting on commit. commitExpired: Certificate expired before rotation was comitted.

2.1868.1 CertificateSigningRequest

pemValue	*string*	CSR in PEM format.
publicKey	*PublicKey* see 2.1085.1.3	Public key information.
subject	*DistinguishedName* see 2.1085.1.1	Entity associated with the certificate.
version	*integer*	X.509 version.

2.1869 show security pki certificate rotation [...]

rotations	*table(string) = CertificateRotation* see 2.1868	A mapping between Rotation ID and rotation information.

2.1870 show segment-security [...]

revision 2

segments	*table(string) = Segment* see 2.1870.1.1	A mapping of Segment name to segment information.
vrfs	*table(string) = Vrf* see 2.1870.1	A mapping from VRF to segment security.

2.1870.1 Vrf

enabled	*boolean*	Indicates whether segment-security is enabled.
ipv6PrefixSupported **	*boolean*	IPv6 prefix supoort is enabled. **Since: 4.24.0
segments	*table(string) = Segment* see 2.1870.1.1	A mapping of segment name to segment information.
vrfExist	*boolean*	Whether VRF exist.

2.1870.1.1 Segment

classMap	*string*	Class Map of type segment-security associated with this segment.
fromSegments	*table(string) = string*	A mapping from source segment name to policy.
[interfaceVlans] **	*list of InterfaceVlanRange* see 2.1870.1.1.1	Interface plus VLAN ranges which are part of this segment. **Since: 4.23.1
interfaces	*list of Interface name*	Interfaces which are part of this segment.
ipv4PrefixListName	*string*	Name of IPv4 prefix list.
ipv6PrefixListName **	*string*	Name of IPv6 prefix list. **Since: 4.24.0

2.1870.1.1.1 InterfaceVlanRange

interface	*interface name*	Interface.
vlanRanges	*list of VlanRangeModel* see 2.1870.1.1.1.1	List of VLAN ranges associated with this interface for this segment.

2.1870.1.1.1.1 VlanRangeModel

endVlanId	*integer*	End of VLAN range.
startVlanId	*integer*	Start of VLAN range.

2.1871 show segment-security application [...]

revision 3

services	*table(string) = Service* see 2.1871.1	Segment Security applications.

2.1871.1 Service

dstPrefix	*list of IP address prefix*	Destination IP Prefix.
serviceDef	*list of ServiceDef* see 2.1871.1.1	Application definition.
srcPrefix	*list of IP address prefix*	Source IP Prefix.

2.1871.1.1 ServiceDef

allProtocols	*boolean*	Definitions supports all IP protocols.
dstPort	*list of PortRange* see 2.1871.1.1.1	destination port.
[ipProtocol]	*integer*	IP protocol number.
srcPort	*list of PortRange* see 2.1871.1.1.1	source port.

2.1871.1.1.1 PortRange

end	*integer*	Port range end.
start	*integer*	Port range start.

2.1872 show segment-security counters [...]

revision 2

[bypassPackets]	*integer*	Packets not destined to any segment.
dstSegments	*table(string) = DestSegment* see 2.1872.1	A mapping of destination segment to source segment.
[flowsCreated]	*integer*	Number of flows created.
[invalidPackets]	*integer*	Invalid packets dropped counter.
policies	*table(string) = PolicyCounter* see 2.1872.2	A mapping of policy names to counters for that policy.
[vrf]	*string*	VRF in which segment security is defined.
vrfExist	*boolean*	Whether VRF is created.

2.1872.1 DestSegment

srcSegments	*table(string) = SourceSegment* see 2.1872.1.1	A mapping of source segment to counters.

2.1872.1.1 SourceSegment

[defaultDrops] **	*integer*	No matching rule in policy. **Since: 4.29.2
[drops] **	*integer*	Explicit drop action counter. **Since: 4.29.2
hits	*integer*	Number of packets evaluated.

[policyName]	*string*	Policy name.

2.1872.2 PolicyCounter

defaultDrops	*integer*	No matching rule in policy.
drops	*integer*	Explicit drop action counter.
hits	*integer*	Number of packets evaluated.

2.1873 show segment-security errors [...]

vrfs	*table(string) = Vrf* see 2.1873.1	A mapping from VRF to its errors.

2.1873.1 Vrf

[dstSegments]	*table(string) = DestSegment* see 2.1873.1.1	Destination segments keyed by their name.
[error]	*string*	Error causing policies for this VRF to fail to install.

2.1873.1.1 DestSegment

srcSegments	*table(string) = SourceSegment* see 2.1873.1.1.1	A mapping of source segment name to its error.

2.1873.1.1.1 SourceSegment

error	*string*	Error causing this segment to fail to install.

2.1874 show segment-security hardware counters [...]

vrfs	*table(string) = VrfHardwareCounters* see 2.1874.1	A mapping of VRF name to its counters.

2.1874.1 VrfHardwareCounters

destinationSegments	*table(string) = DestinationSegmentCounters* see 2.1874.1.1	A mapping of destination segment to its counters.
policies	*table(string) = PolicyCounters* see 2.1874.1.2	A mapping of policy name to its counters.

2.1874.1.1 DestinationSegmentCounters

sourceSegments	*table(string) = SourceSegmentCounters* see 2.1874.1.1.1	A mapping of source segment to policy counters.

2.1874.1.1.1 SourceSegmentCounters

drops	*integer*	Policy drop counter.
hits	*integer*	Policy match counter.
policyName	*string*	Policy name.

2.1874.1.2 PolicyCounters

drops	*integer*	Drop action counter.
hits	*integer*	Forward action counter.

2.1875 show segment-security hardware detail [...]

vrfs	*table(string) = VrfHardwareDetail* see 2.1875.1	A mapping of VRF name to its segments.

2.1875.1 VrfHardwareDetail

segments	*table(string) = SegmentHardwareDetail* see 2.1875.1.1	A mapping of segment name to its hardware detail.

2.1875.1.1 SegmentHardwareDetail

hardwareId	*integer*	Hardware ID of security segment.
prefixes	*table(IPv4 or IPv6 address prefix) = SegmentPrefixHardwareDetail* see 2.1875.1.1.1	A mapping for segment prefix to its hardware information.

2.1875.1.1.1 SegmentPrefixHardwareDetail

l2AdjIndex	*integer*	Layer 2 adjacency index.

2.1876 show segment-security hardware routes [...]

vrfs	*table(string) = VrfHardwareRoutes* see 2.1876.1	A mapping of VRF name to its segments.

2.1876.1 VrfHardwareRoutes

segments	*table(string) = SegmentHardwareRoutes* see 2.1876.1.1	A mapping of segment name to its routes in hardware.

2.1876.1.1 SegmentHardwareRoutes

hardwareId	*integer*	Hardware ID of security segment.
prefixes	*table(IPv4 or IPv6 address prefix) = SegmentRouteDetail* see 2.1876.1.1.1	A mapping of route its hardware information.

2.1876.1.1.1 SegmentRouteDetail

routeType	*enum: S | S,F | F*	Route type.

2.1877 show segment-security hardware summary [...]

vrfs	*table(string) = VrfHardwareSummary* see 2.1877.1	A mapping of VRF name to its segments.

2.1877.1 VrfHardwareSummary

segments	*table(string) = SegmentHardwareSummary* see 2.1877.1.1	A mapping of segment name to its hardware summary.

2.1877.1.1 SegmentHardwareSummary

hardwareId	*integer*	Hardware ID of segment.
prefixesConfigured	*integer*	Number of prefixes configured.
prefixesProgrammed	*integer*	Number of prefixes programmed in hardware.

2.1878 show segment-security policy [...]

policies	*table(string) = Policy* see 2.1878.1	Segment Security Policy.

2.1878.1 Policy

policyDefs	*table(numeric string) = PolicyDef* see 2.1878.1.1	A mapping of sequence no to policy rule.
readonly **	*boolean*	Whether policy is readonly. **Since: 4.24.0

2.1878.1.1 PolicyDef

action	*enum: deny* | *statelessRedirect* | *permit* | *statelessDeny* | *statelessPermit*	Action to be applied on application.
log	*boolean*	Whether logging enabled.
[nexthop] **	*IP address*	Nexthop IP address. **Since: 4.31.0
serviceName	*string*	Application name.

2.1879 show segment-security status [...]

ipv6PrefixSupported	*boolean*	IPv6 prefix supoort is enabled.
vrfs	*table(string) = Vrf* see 2.1879.1	A mapping of VRF name to its segments status.

2.1879.1 Vrf

dstSegments	*table(string) = DestSegment* see 2.1879.1.1	Destination segments keyed by their name.

2.1879.1.1 DestSegment

ipv4PrefixListName	*string*	Name of IPv4 prefix list.
ipv6PrefixListName	*string*	Name of IPv6 prefix list.
srcSegments	*table(string) = SourceSegment* see 2.1879.1.1.1	A mapping of source segment name to its status.

2.1879.1.1.1 SourceSegment

status	*enum: success* | *failed* | *waiting*	Segment status.

2.1880 show segment-security to (DST_IP | DST_IPV6) [...]

enabled	*boolean*	Segment-security is enabled.
segments	*table(string) = FwPolicyToInfoSourceSegments* see 2.1880.1	Policy mappings from destination segment(s) to source segment(s).
vrfExist	*boolean*	VRF exists.
[vrfName]	*string*	Relevant VRF name.

2.1880.1 FwPolicyToInfoSourceSegments

fromSegments	*table(string) = FwPolicyToInfoSourceSegment* see 2.1880.1.1	Mappings from source segment name to policy.

2.1880.1.1 FwPolicyToInfoSourceSegment

[policy]	*string*	Policy associated with segment.

2.1881 show service mss status

enabled	*boolean*	The Macro-Segmentation Service is enabled.
policyEnforcement	*MssPolicyEnforcementModel* see 2.1881.1	Policy enforcement properties.
running	*boolean*	The Macro-Segmentation Service is running.

2.1881.1 MssPolicyEnforcementModel

consistency	*enum: bestEffort | strict*	Policy enforcement mode.
rules	*MssPolicyEnforcementRulesModel* see 2.1881.1.1	Policy enforcement rules.

2.1881.1.1 MssPolicyEnforcementRulesModel

group	*boolean*	Group policy enforcement rule enabled.
verbatim	*boolean*	Verbtim policy enforcement rule enabled.

2.1882 show service vxlan address-table advertised [...]

revision 2

vniInDottedNotation	*boolean*	VNI display format.
vnis	*list of VxlanVniStatus* see 2.1882.1	list of Vxlan Vni Status, one per VNI.

2.1882.1 VxlanVniStatus

bumVtepListTable	*list of VxlanMacVtepListPair* see 2.1882.1.1	Flood table.
macAddress	*MAC address*	A MAC address.
unicastHostTable	*list of VxlanMacVtepPair* see 2.1882.1.2	Unicast address table.
[vlan]	*integer*	VLAN.
[vni]	*integer*	VNI.

2.1882.1.1 VxlanMacVtepListPair

macAddr	*MAC address*	Destination MAC address.
vtepIpList	*list of IPv4 address*	List of VTEPs.

vtepIpListType	*string*	BUM forwarding mode.

2.1882.1.2 VxlanMacVtepPair

macAddr	*MAC address*	Host Mac address.
[moveCount]	*integer*	Number of local and remote Mac moves.
vtepIp	*IPv4 address*	Vtep Ip address.

2.1883 show service vxlan address-table received [...]

revision 2

nonSwitchSources **	*table(string) = VxlanVniStatusList* see 2.1882	Mapping from non-switch source to VniStatus. **Since: 4.21.3
switches	*table(string) = VxlanVniStatusList* see 2.1882	Mapping from switch id to VniStatus.

2.1884 show service vxlan arp advertised [...]

vnis	*table(numeric string) = VxlanArpTable* see 2.1884.1	A mapping from VNI to ARP table.

2.1884.1 VxlanArpTable

addresses	*table(IPv4 or IPv6 address) = VxlanArpEntry* see 2.1884.1.1	A mapping from IP address to ARP entry.

2.1884.1.1 VxlanArpEntry

changes	*integer*	Number of times the ARP entry changed.
macAddress	*MAC address*	MAC address of an ARP entry.
preference	*integer*	ARP entry preference value.

2.1885 show service vxlan arp received [...]

switches	*table(string) = VxlanVtep* see 2.1885.1	A mapping from switch ID to vtep.

2.1885.1 VxlanVtep

vnis	*table(string) = VxlanArpTable* see 2.1884.1	A mapping from VNI to ARP table.

2.1886 show service vxlan nd advertised [...]

see 2.1884

2.1887 show service vxlan nd received [...]

see 2.1885

2.1888 show service vxlan status

`arpRelayVteps` **	*list of string*	List of VTEPs relaying ARP replies. **Since: 4.18.0
`[bgpEvpnRedistEnabled]` **	*boolean*	When set to True it means MAC-VTEP bindings generated by BGP EVPN are being redistributed in to Vxlan Control Service. **Since: 4.21.3
`[capability]` **	*VxlanControllerCapability* see 2.1888.1	Vxlan Controller capability. **Since: 4.15.3
`macLearning`	*enum: dataPlane* | *controlPlane*	MAC learning. Defaults to controlPlane.
`[multicastDistribution-Enabled]` **	*boolean*	When set to True it signifies multicast floodlist distribution happens on Vxlan Controller. **Since: 4.21.3
`[resyncInProgress]`	*boolean*	When set to True it signifies Vxlan Controller Service sync, after CVX restart, is in progress.
`resyncPeriod`	*integer*	Sync period in seconds for Vxlan Controller Service after CVX restart. Value of 0 means finish sync immediately after CVX reboot without waiting.
`[resyncStartedAt]`	*floating point number*	UTC Time at which sync of Vxlan Controller Service started after CVX restart. 0 signifies never.
`status`	*enum: stopped* | *running* | *shutting down*	Status of VxlanController agent.
`vniMapping` **	*enum: portDot1qTag* | *vlan*	VNI mapping. Defaults to vlan. **Since: 4.20.5

2.1888.1 VxlanControllerCapability

`indirectRouting` **	*boolean*	Indicates indirect routing support. **Since: 4.18.0
`routing`	*boolean*	Indicates routing support.

2.1889 show service vxlan vni advertised [...]

switchList	*table(string) = VniList* see 2.1889.1	List of VNIs advertised per switch.
vniDotted	*boolean*	VNI display format.

2.1889.1 VniList

converging	*boolean*	True if Vxlan Controller Service sync in progress.
vnis	*list of VniRange* see 2.1889.1.1	List of VNIs in dotted or plain notation.

2.1889.1.1 VniRange

maxVni	*integer*	Maximum value for VNI range.
minVni	*integer*	Minimum value for VNI range.

2.1890 show service vxlan vni received [...]

switchList	*table(string) = VniList* see 2.1889.1	List of switches and VNIs received from each.
vniDotted	*boolean*	VNI display format.
vniList	*table(string) = SwitchList* see 2.1890.1	List of VNIs and switches they were received from.

2.1890.1 SwitchList

switches	*list of string*	List of Switches, hostname, IP or default ID.

2.1891 show service-insertion connection [...]

connectionStatus	*list of SfeSiConnStatusModel* see 2.1891.1	All Connection Status.

2.1891.1 SfeSiConnStatusModel

connName	*string*	Connection name.
[connectivityMonitor]	*string*	Configured connectivity monitor hostname.
isActive	*boolean*	Connection is active or not.
[nextHop]	*string*	Nexthop of this exit.
[nhResolved]	*boolean*	Nexthop is resolved.
[primaryIntf]	*SfeSiConnIntfStatusModel* see 2.1891.1.1	Configured primary interface.
[secondaryIntf]	*SfeSiConnIntfStatusModel* see 2.1891.1.1	Configured secondary interface.

2.1891.1.1 SfeSiConnIntfStatusModel

intfEnabled	*boolean*	Interface is enabled.
intfId	*string*	Configured interface.
[monHostReachable]	*boolean*	Monitor host is reachable.
vrf	*string*	Configured VRF on this interface.

2.1892 show session-config [...]

see 2.324.1.1

2.1893 show session-config digest [...]

see 2.1865

2.1894 show sflow [...]

[accelEnabled] **	*boolean*	sFlow hardware acceleration running. **Since: 4.21.3
[accelSampleRate] **	*integer*	Sample rate for hardware acceleration, 1 sample per N packets. **Since: 4.21.3
[accelSupported] **	*boolean*	Is hardware acceleration supported. **Since: 4.21.3
[bgpExports]	*list of BgpExport* see 2.1894.1	List of BGP Exports.
datagrams	*integer*	Number of datagrams sent for regular sFlow samples.
[details]	*Details* see 2.1894.8	Detailed sFlow information.
[dropPacketExportRunning] **	*boolean*	sFlow export is running for drop samples. **Since: 4.30.1
[dropPacketSamplingEnabled] **	*boolean*	sFlow export enabled for dropped packets. **Since: 4.30.1
[dropSampleDatagrams] **	*integer*	Number of datagrams sent for drop samples. **Since: 4.30.1
[dropSamplesReceived] **	*integer*	Number of drop samples received at sFlow Agent. **Since: 4.30.1
[dropSamplesSent] **	*integer*	Number of drop samples sent to external collectors from sFlow Agent. **Since: 4.30.1
dscpValue **	*integer*	DSCP value in sFlow datagram. **Since: 4.24.1
[dynamicUdpSourcePort] **	*boolean*	Use dynamic UDP source port for sFlow entropy. **Since: 4.31.1
enabled	*boolean*	sFlow globally enabled.
gnpsiDestination **	*GnpsiDestination* see 2.1894.2	Gnpsi destination information. **Since: 4.34.1
[hardwareAccelSampleRate] **	*integer*	Hardware sample rate for hardware accelerated Sflow, 1 sample per N packets. **Since: 4.21.3
hardwareSampleRate	*integer*	Hardware sample rate for software Sflow, 1 sample per N packets.
hardwareSamples	*integer*	Number of hardware samples.
[hwSampleTruncateSize] **	*integer*	HW Sample truncate size limit in bytes for hardware acceleration. **Since: 4.24.2
[initializing] **	*boolean*	sFlow sampling is initializing. **Since: 4.35.2
ipv4Agents **	*list of Ipv4Source* see 2.1894.4	List of Agent IPv4 addresses. **Since: 4.33.0
ipv4Destinations	*list of Ipv4Destination* see 2.1894.3	List of IPv4 destinations.
[ipv4DestinationsForDropSamples] **	*list of Ipv4Destination* see 2.1894.3	List of IPv4 destinations for drop samples. **Since: 4.30.1

ipv4Sources	*list of Ipv4Source* see 2.1894.4	List of Source IPv4 addresses.
[ipv4SourcesForDropSamples] **	*list of Ipv4Source* see 2.1894.4	List of Source IPv4 addresses for drop samples. **Since: 4.30.1
ipv6Agents **	*list of Ipv6Source* see 2.1894.6	List of Agent IPv6 addresses. **Since: 4.33.0
ipv6Destinations	*list of Ipv6Destination* see 2.1894.5	List of IPv6 destinations.
[ipv6DestinationsForDrop-Samples] **	*list of Ipv6Destination* see 2.1894.5	List of IPv6 destinations for drop samples. **Since: 4.30.1
ipv6Sources	*list of Ipv6Source* see 2.1894.6	List of Source IPv6 addresses.
[ipv6SourcesForDropSamples] **	*list of Ipv6Source* see 2.1894.6	List of Source IPv6 addresses for drop samples. **Since: 4.30.1
maxDatagramSize **	*integer*	Max datagram size limit in bytes. **Since: 4.32.1
polling	*boolean*	sFlow polling.
pollingInterval	*floating point number*	Polling interval in seconds.
[rewriteDscp]	*boolean*	Rewrite DSCP value in sFlow samples.
running **	*boolean*	sFlow sampling is running. **Since: 4.30.1
samplePool	*integer*	Sample pool.
sampleRate	*integer*	Sample rate, 1 sample per N packets.
sampleTruncateSize **	*integer*	Sample truncate size limit in bytes. **Since: 4.23.2
samplingEnabled	*boolean*	sFlow sampling enabled.
sendingDatagrams	*list of SendingDatagram* see 2.1894.7	List of Sending datagrams.
[sendingDatagramsForDrop-Samples] **	*list of SendingDatagram* see 2.1894.7	List of sending datagrams for drop samples. **Since: 4.30.1
softwareSamples	*integer*	Number of samples.
totalPackets	*integer*	Total packets.

2.1894.1 BgpExport

export	*boolean*	Export BGP information.
vrfName	*string*	VRF name.

2.1894.2 GnpsiDestination

datagramsCount	*integer*	Number of datagrams sent to Gnpsi.
enabled	*boolean*	Gnpsi is configured to receive datagrams from Sflow.

2.1894.3 Ipv4Destination

datagramsCount **	*integer*	Number of datagrams sent to sFlow collector. **Since: 4.30.1
hostname	*string*	Hostname of sFlow collector.
ipv4Address	*IPv4 address*	IPv4 address of sFlow collector.
port	*integer*	Port of sFlow collector.
vrfName	*string*	Associated VRF for sFlow collector.

2.1894.4 Ipv4Source

ipv4Address	*IPv4 address*	Source IPv4 address.
[sourceInterface]	*interface name*	Source Interface.
vrfName	*string*	Associated VRF for sFlow source.

2.1894.5 Ipv6Destination

datagramsCount **	*integer*	Number of datagrams sent to sFlow collector. **Since: 4.30.1
hostname	*string*	Hostname of sFlow collector.
ipv6Address	*IPv6 address*	IPv6 address of sFlow collector.
port	*integer*	Port of sFlow collector.
vrfName	*string*	Associated VRF for sFlow collector.

2.1894.6 Ipv6Source

ipv6Address	*IPv6 address*	Source IPv6 address.
[sourceInterface]	*interface name*	Source Interface.
vrfName	*string*	Associated VRF for sFlow source.

2.1894.7 SendingDatagram

[gnpsiReceiver] **	*boolean*	Sending datagrams to Gnpsi. **Since: 4.34.1
reason	*enum: connectingToGnpsi* | *initializing* | *invalidDestination* | *noError* | *invalidSource* | *bindingInProgress* | *invalidVrf* | *gnpsiDisabled* | *invalidSourceDestination* | *smallDatagramSize* | *notRunning*	Reason for sendingDatagrams state.
sending	*boolean*	sFlow samples being sent.
vrfName	*string*	VRF name.

2.1894.8 Details

[accelUnsupported-Extensions] **	*list of string*	Extensions that are not supported for hardware acceleration. **Since: 4.21.3
hardwareSamplingEnabled	*boolean*	Hardware sampling enabled.
[portChannelOutputIfIndex] **	*enum: member | portchannel*	Output interface index for port channels. **Since: 4.22.0
[sampleEgressSubintf] **	*boolean*	Include output subinterface information in packet sample; sample sent in expanded format. **Since: 4.22.1
[sampleEncodingFormat] **	*enum: expanded | compact*	Encoding format for samples. **Since: 4.22.1
[sampleEvpnMplsExtension] **	*boolean*	Include MPLS VC extension header for EVPN packet sample. **Since: 4.33.1
[sampleIngressSubintf] **	*boolean*	Include input subinterface information in packet sample; sample sent in expanded format. **Since: 4.23.0
[sampleMplsExtension] **	*boolean*	Include MPLS extension header in packet sample. **Since: 4.22.0
sampleOutputInterface	*boolean*	Include output interface in packet sample.
[sampleReportForwarding-Vlan] **	*boolean*	Report forwarding VLAN ID. **Since: 4.34.2
[sampleReportForwarding-VlanMode] **	*enum: Untagged | All*	Report forwarding VLAN mode. **Since: 4.35.2
[sampleRouterExtension]	*boolean*	Include router extension header in packet sample.
[sampleSwitchExtension]	*boolean*	Include switch extension header in packet sample.
[sampleTunnelIpv4Egr-Extension] **	*boolean*	Include tunnel IPv4 egress extension header in packet sample. **Since: 4.22.0
[sampleUpdateSubIntfVlan] **	*boolean*	Report VLAN ID changes on L2 subinterfaces. **Since: 4.33.1
[sampleVplsExtension] **	*boolean*	Include MPLS VC extension header for VPLS packet sample. **Since: 4.32.0
[sampleVxlanExtension] **	*boolean*	Include VXLAN extension headers in packet sample. **Since: 4.32.1
[sampleVxlanHeaderStrip] **	*boolean*	Include VXLAN tunnel headers of VXLAN encapsulated packets in packet sample. **Since: 4.28.0
samplesDiscarded	*integer*	Number of discarded samples.
[sviIfindexInput] **	*boolean*	Input interface index of SVI reported in sample. **Since: 4.31.2

[sviIfindexOutput] **	*boolean*	Output interface index of SVI reported in sample. **Since: 4.31.2

2.1895 show sflow hardware accelerators

accelerators	*table(string) = SflowAcceleratorInfo* see 2.1895.1	Mapping of accelerator name to accelerator info.

2.1895.1 SflowAcceleratorInfo

accelRevision **	*integer*	Accelerator revision. **Since: 4.22.0
chips	*list of string*	List of chips directly connected to this accelerator.
pciAddress	*string*	PCI address of this accelerator.
sflowAccelFpgaType	*string*	Type of sFlow accelerator.
sliceName	*string*	Name of the slice on which this sFlow accelerator is located.

2.1896 show sflow hardware counters

counters	*table(string) = HardwareSflowCountersInfo* see 2.1896.1	sFlow accelerator counters.

2.1896.1 HardwareSflowCountersInfo

inPktCnt	*integer*	Incoming Packet Count.
inPktErrCnt	*integer*	Incoming Packet Error Count.
inProcPktCnt	*integer*	Incoming Processed Packet Count.
outFlowSampleCnt	*integer*	Outgoing Flow Sample Count.
outProcSflowDgramCnt	*integer*	Outgoing Processed Datagram Count.
outSflowDgramCnt	*integer*	Outgoing Sflow Datagram Count.
rcvPktDropCnt	*integer*	Receive Packet Drop Count.
rcvPktTrunCnt	*integer*	Packet Truncated Count.
samplePool	*integer*	Sample Pool.

2.1897 show sflow hardware mapping

chips	*table(string) = SflowAcceleratorMappingInfo* see 2.1897.1	Mapping of chip to sFlow accelerator.

2.1897.1 SflowAcceleratorMappingInfo

directConnection	*boolean*	Direct connection between the chip and the accelerator.
sflowAccelerator	*string*	sFlow accelerator name.

2.1898 show sflow hardware mapping lag

`lags`	*table(string)* = *SflowAcceleratorMapping-LagInfo* see 2.1898.1	Mapping of LAG to sFlow accelerator.

2.1898.1 SflowAcceleratorMappingLagInfo

`sflowAccelerator`	*string*	sFlow accelerator name.

2.1899 show sflow hardware status

accelPPSupported **	*boolean*	Whether sFlow hardware acceleration in pipeline mode is available on the system. **Since: 4.30.0
[agentIpAddress] **	*AgentIpAddress* see 2.1899.1	Selected agent ID address. **Since: 4.34.1
[inactiveFeatures]	*list of string*	List of sFlow features that are configured but not supported with hardware-accelerated sFlow, and will only take effect with software sFlow.
[modules]	*table(string) = SflowAccelModuleStatus* see 2.1899.3	Per-module status of hardware-accelerated sFlow.
[reasonsNotRunning]	*list of string*	List of reasons why sFlow hardware acceleration is not running.
running	*boolean*	Whether sFlow hardware acceleration is running.
sampleRate	*integer*	Sample rate, 1 sample per N packets.
vrfs **	*table(string) = Vrf* see 2.1899.2	A mapping from VRF's name to its collectors. **Since: 4.25.2

2.1899.1 AgentIpAddress

ipAddress	*IP address*	Agent ID address.
vrf	*string*	Associated VRF with the chosen agent ID address.

2.1899.2 Vrf

collectorIps	*table(IPv4 or IPv6 address) = Collector* see 2.1899.2.1	A mapping of collector IP address to its status.

2.1899.2.1 Collector

active	*boolean*	Whether this collector is active.
port	*integer*	Port of sFlow collector.
reason	*enum: noHardwareResource | missingConfig | noRouteToCollector | ip6CollectorInUse | enabled*	Reason why collector is disabled it's an empty string if collector is enabled.

2.1899.3 SflowAccelModuleStatus

hasAccelerators	*boolean*	Whether this module has sFlow accelerators.
sflowMode	*ModuleSflowMode* see 2.1899.3.1	Type of sFlow running for this module.

2.1899.3.1 ModuleSflowMode

active	*enum: hardware-accelerated | disabled | software*	Current sFlow status of this module.
configured	*enum: hardware-accelerated | software*	Whether this module is configured to use software or hardware-accelerated sFlow.

2.1900 show sflow interfaces [...]

revision 3

egressInterfacesEnabled-Default	*boolean*	Global egress sFlow configuration for interfaces.
enabled	*boolean*	sFlow globally enabled.
ingressInterfacesEnabled-Default	*boolean*	Global ingress sFlow configuration for interfaces.
interfaces	*table(Interface name) = SflowTypeStatusMap* see 2.1900.1.1	Mapping between an interface and its status.
lagInterfaces	*table(Interface name) = LagMemberSflowTypeStatus* see 2.1900.1	Mapping between a LAG member and its status.

2.1900.1 LagMemberSflowTypeStatus

lagInterface	*interface name*	LAG interface for LAG member.
lagSflowTypeStatus	*SflowTypeStatusMap* see 2.1900.1.1	sFlow type status map for LAG member.

2.1900.1.1 SflowTypeStatusMap

[intfOperStatusReason]	*string*	Operational status reason.
sFlows	*table(string) = SflowTypeStatus* see 2.1900.1.1.1	A mapping of sFlow type to its status.

2.1900.1.1.1 SflowTypeStatus

status	*enum: inactive | running | partial*	sFlow status for an interface.

2.1901 show sflow interfaces counters

enabled	*boolean*	sFlow globally enabled.
interfaces	*table(Interface name) = IntfSampleCounterMap* see 2.1901.1	Mapping between an interface and its sample counters.

2.1901.1 IntfSampleCounterMap

[egress]	*integer*	Interface egress sample count.
[ingress]	*integer*	Interface ingress sample count.

2.1902 show snapshot counters ecmp detail

agmIds	*table(numeric string) = integer*	Mapping from AGM ID to L2 Adjacency ID.
agmPool	*integer*	AGM pool.
endTime	*floating point number*	End time.
flexCtrPool	*integer*	Flex counter pool.
running	*boolean*	Running.
startTime	*floating point number*	Start time.

2.1903 show snapshot counters ecmp history

snapshots	*table(numeric string) = StrataEcmpSnapshotModel* see 2.1903.1	ECMP snapshots.

2.1903.1 StrataEcmpSnapshotModel

complete	*boolean*	Snapshot monitoring complete.
destinationDir	*string*	Path of the output directory.
endTime	*floating point number*	End time.
filenames	*table(numeric string) = string*	Mapping from L2 adjacency ID to output file name.
interval	*integer*	Polling interval in microseconds.
l2Adjacencies	*table(numeric string) = L2AdjacencyModel* see 2.1903.1.1	Mapping from L2 adjacency ID to member interfaces.
pollCount	*integer*	Total poll count.
requestId	*integer*	Request ID for this snapshot.
startTime	*floating point number*	Start time.

2.1903.1.1 L2AdjacencyModel

memberInterfaces	*list of string*	Member interfaces of this adjacency.

2.1904 show snapshot counters ecmp polling

pollInterval	*integer*	Poll interval in microseconds.
status	*table(numeric string) = EcmpMonitorPollingModel* see 2.1904.1	Polling information per FAP.

2.1904.1 EcmpMonitorPollingModel

avgProcessingTime	*floating point number*	Average processing time in microseconds.
avgSampleInterval	*integer*	Average sample interval in microseconds.
bufferFullCount	*integer*	Buffer full count.
maxBufferUsage	*floating point number*	Maximum Buffer Usage.
maxProcessingTime	*floating point number*	Maximum processing time in microseconds.
maxSampleInterval	*integer*	Maximum sample interval in microseconds.
sampleCount	*integer*	Total sample count.

2.1905 show snmp

chassis	*SnmpChassis* see 2.1905.2	Chassis ID.
contact	*Contact* see 2.1905.1	SNMP contact.
[counters]	*SnmpCounters* see 2.1905.3	SNMP counters.
enabled	*boolean*	Indicates whether SNMP is enabled.
location	*SnmpLocation* see 2.1905.5	SNMP location.
logging	*SnmpLogging* see 2.1905.6	SNMP logging.
misc	*SnmpMiscConfig* see 2.1905.7	SNMP miscellaneous configuration.
srcIntf	*SnmpInterface* see 2.1905.4	SNMP source interfaces.
vrfs	*SnmpVrfs* see 2.1905.8	SNMP VRFs.

2.1905.1 Contact

contact	*string*	SNMP Contact.

2.1905.2 SnmpChassis

chassisId	*string*	Chassis ID.

2.1905.3 SnmpCounters

groupLength	*integer*	Users in Group.
inBadCommunityNames	*integer*	Unknown community name.
inBadCommunityUses	*integer*	Illegal operation for community name.
inGetNextPdus	*integer*	Get-next PDUs.
inGetPdus	*integer*	Get-request PDUs.
inParseErrs	*integer*	Encoding errors.
inPkts	*integer*	SNMP packet input.
inRequestVars	*integer*	Requested variables.
inSetPdus	*integer*	Set-request PDUs.
inSetVars	*integer*	Altered variables.
inVersionErrs	*integer*	Bad SNMP version errors.
numberOfGroups	*integer*	Groups.
numberOfViews	*integer*	Views.
outBadValueErrs	*integer*	Bad value errors.
outGeneralErrs	*integer*	General errors.
outGetResponsePdus	*integer*	Response PDUs.
outNoSuchNameErrs	*integer*	No such name errors.
outPkts	*integer*	SNMP packets output.
outTooBigErrs	*integer*	Too big errors.

outTrapDrops **	*integer*	Trap drops. **Since: 4.31.0
outTrapPdus	*integer*	Trap PDUs.
serviceEnabled	*boolean*	status Snmp agent and snmpd.

2.1905.4 SnmpInterface

sourceInterfaces **	*table(string) = string*	A mapping between a VRF and the source interface. **Since: 4.17.0

2.1905.5 SnmpLocation

location	*string*	SNMP Location.

2.1905.6 SnmpLogging

hosts	*table(string) = SnmpLoggingHost* see 2.1905.6.1	Mapping between hostname and host information.
loggingEnabled	*boolean*	If logging is enabled.

2.1905.6.1 SnmpLoggingHost

port	*integer*	Port for SNMP logger.
[vrf]	*string*	VRF, if applicable, for SNMP logger.

2.1905.7 SnmpMiscConfig

transmitMsgMaxSize	*integer*	Maximum number of bytes in SNMP message (UDP/TCP payload).

2.1905.8 SnmpVrfs

snmpVrfs	*list of string*	List of VRFs the SNMP agent is enabled on.

2.1906 show snmp ((ipv4 access-list) | (ipv6 access-list)) [...]

see 2.62

2.1907 show snmp community

communities	*table(string) = SnmpCommunityDetailModel* see 2.1907.1	A mapping of SNMP community to detail community information.

2.1907.1 SnmpCommunityDetailModel

access	*enum: readOnly | readWrite*	Community access level.
defaultContext **	*string*	Context associated for this community. **Since: 4.29.1
ipV4AccessList	*string*	IPv4 access-list for this community.
[ipV4AccessListStatus]	*enum: nonExistent | ignoredNotAStandardAcl*	IPv4 access list status.
ipV6AccessList	*string*	IPv6 access-list for this community.
[ipV6AccessListStatus]	*enum: nonExistent | ignoredNotAStandardAcl*	IPv6 access list status.
view	*string*	Community MIB view name.
[viewStatus]	*notConfigured*	Snmp view status.

2.1908 show snmp debug counters table (TABLE | all) [...]

contexts	*table(string) = SnmpTableIteratorCounterModel* see 2.1908.1	Counters by context.

2.1908.1 SnmpTableIteratorCounterModel

tables	*table(string) = SnmpTableIteratorCounterType* see 2.1908.1.1	Counters by table.

2.1908.1.1 SnmpTableIteratorCounterType

counterTypes	*table(string) = SnmpTableIteratorCounter* see 2.1908.1.1.1	Table iterator counters by type.

2.1908.1.1.1 SnmpTableIteratorCounter

counters	*table(string) = integer*	Table iterator counters.

2.1909 show snmp debug identifier hashed

hashedIdentifiers	*table(string) = string*	A mapping of actual identifier to hashed identifier.

2.1910 show snmp engineID

localEngineId	*string*	Local SNMP EngineID.
remoteEngineIds	*SnmpRemoteEngineIdHostToPortModel* see 2.1910.1	Remote SNMP EngineIDs.

2.1910.1 SnmpRemoteEngineIdHostToPortModel

hosts	*table(string) = SnmpRemoteEngineIdPort-ToEngIdModel* see 2.1910.1.1	A mapping of hostname to a collection of UDP-ports.

2.1910.1.1 SnmpRemoteEngineIdPortToEngIdModel

ports	*table(numeric string) = string*	A mapping of UDP-port to engineID.

2.1911 show snmp group [...]

groups	*table(string) = SnmpGroup-VerToDetailModel* see 2.1911.1	A mapping of SNMP group name to SNMP versions.

2.1911.1 SnmpGroupVerToDetailModel

versions	*table(string) = SnmpGroupDetailModel* see 2.1911.1.1	A mapping of SNMP version to SNMP group details.

2.1911.1.1 SnmpGroupDetailModel

notifyView	*string*	Name of the SNMP notify view.
[notifyViewConfig]	*boolean*	True if the notify view exists and has been configured.
readView	*string*	Name of the SNMP read view.
[readViewConfig]	*boolean*	True if the read view exists and has been configured.
secModel	*enum: v2c | v3NoAuth | v3Priv | v1 | v3Auth*	Security model in effect for this group.
writeView	*string*	Name of the SNMP write view.
[writeViewConfig]	*boolean*	True if the write view exists and has been configured.

2.1912 show snmp local-interface

see 2.1905.4

2.1913 show snmp mib

contexts	*table(string) = SnmpOidsModel* see 2.1913.1	A mapping from a context (VRF) to its registered OIDs.

2.1913.1 SnmpOidsModel

oids	*list of string*	Registered OIDs.

2.1914 show snmp mib bridgemib portid [...]

portIDs	*table(string) = integer*	Map an interface name to a port ID.

2.1915 show snmp mib ifmib ifindex [...]

ifIndex	*table(Interface name) = integer*	Mapping between interface name and the corresponding SNMP interface index.
pending **	*list of Interface name*	Interfaces for which an ifIndex value has not yet been allocated. **Since: 4.24.0
reservedIfIndex **	*table(Interface name) = integer*	Mapping from interface name to the corresponding SNMP interface index reserved for use by an interface that has been deleted, if it is recreated in the future. **Since: 4.28.2

2.1916 show snmp mib notifications [...]

notifications	*list of SnmpSentNotification* see 2.1916.1	A list of notifications that were sent.

2.1916.1 SnmpSentNotification

oid	*string*	The notification that was sent.
variables	*list of SnmpSentNotificationVariable* see 2.1916.1.1	A list of variables for this notification.
when	*floating point number*	When the notification was sent (UTC Seconds).

2.1916.1.1 SnmpSentNotificationVariable

oid	*string*	The OID of the variable.
value	*string*	The value corresponding to the oid.

2.1917 show snmp mib qosmib counter-interval

enabled	*boolean*	QOS-MIB counters are enabled.
interval	*integer*	QOS-MIB counter update interval (seconds).

2.1918 show snmp mib translate OID

numeric	*string*	Numeric form of the OID.
symbolic	*string*	Symbolic (textual) form of the OID.

2.1919 show snmp net-snmp buffer

clientRecvBuf	*integer*	Client receive buffer size.
clientSendBuf	*integer*	Client send buffer size.
serverRecvBuf	*integer*	Server receive buffer size.
serverSendBuf	*integer*	Server send buffer size.

2.1920 show snmp notification

notifications	*list of SnmpNotification* see 2.1920.1	List of notifications that are configured.

2.1920.1 SnmpNotification

component	*string*	Component owning notification.
enabled	*boolean*	Notification is enabled.
name	*string*	Name of notification.
reason	*string*	Reason for notification state.

2.1921 show snmp notification host

hosts	*list of HostModel* see 2.1921.1	SNMP notification recipients.

2.1921.1 HostModel

hostname	*string*	Host name or IP address.
notificationType	*enum: inform | trap*	SNMP notification type.
port	*integer*	UDP port number.
protocolVersion	*enum: v1 | v3 | v2c*	SNMP version.
[refresh] **	*boolean*	Refresh hostname DNS resolution. **Since: 4.33.1
[v1v2cParams]	*SnmpV1V2cHostParams* see 2.1921.1.1	SNMPv1/v2c parameters.
[v3Params]	*SnmpV3HostParams* see 2.1921.1.2	SNMPv3 parameters.
[vrf]	*string*	Name of the VRF.

2.1921.1.1 SnmpV1V2cHostParams

communityString	*string*	Community string for SNMPv1/v2c.

2.1921.1.2 SnmpV3HostParams

securityLevel	*enum: authNoPriv | noAuthNoPriv | authPriv*	SNMPv3 security level.
user	*string*	SNMPv3 user.

2.1922 show snmp scheduler [...]

see 2.92

2.1923 show snmp user [...]

usersByVersion	*table(string) = UserCollectionModel* see 2.1923.1	SNMP users grouped by version v1, v2c or v3.

2.1923.1 UserCollectionModel

users	*table(string) = UserModel* see 2.1923.1.1	SNMP users.

2.1923.1.1 UserModel

groupConfigured	*boolean*	Indicates whether SNMP group is configured.
groupName	*string*	Group for the SNMP user.
[v3Params]	*SnmpV3UserParams* see 2.1923.1.1.1	SNMPv3 parameters for the user.

2.1923.1.1.1 SnmpV3UserParams

[authType]	*enum: MD5 | SHA-224 | SHA-384 | SHA-256 | SHA | SHA-512*	Authentication protocol for the user.
engineId	*string*	SNMPv3 engineID.
engineIdMatch **	*boolean*	The system engineID matches the user. **Since: 4.27.1
[privType]	*enum: DES | AES-256 | AES-128 | AES-192*	Privacy protocol for the user.

2.1924 show snmp v2-mib chassis

see 2.1905.2

2.1925 show snmp v2-mib contact

see 2.1905.1

2.1926 show snmp v2-mib location

see 2.1905.5

2.1927 show snmp view [...]

`views`	*list of SnmpView* see 2.1927.1	List of SNMP views.

2.1927.1 SnmpView

`name`	*string*	SNMP view name.
`viewType`	*table(string) = boolean*	Mapping from OID subtree to inclusion status.

2.1928 show spanning-tree [...]

spanningTreeInstances	*table(string) = SpanningTreeInstance* see 2.1928.1	Map STP instance names to their details.

2.1928.1 SpanningTreeInstance

bridge	*SpanningTreeBridge* see 2.1928.1.1	Spanning tree bridge details.
[detail]	*SpanningTreeInstance-Detail* see 2.1928.1.2	Spanning tree instance details.
[instanceName]	*string*	Name of spanning tree instance.
interfaces	*table(Interface name) = SpanningTreeInterface* see 2.1928.1.3	Map STP interface names to their details.
protocol	*enum: rstp | mstp | rapidPvst*	Spanning tree protocol configured.
[rootBridge]	*SpanningTreeBridge* see 2.1928.1.1	Spanning tree root bridge details.
[rootPort]	*SpanningTreeRootPort* see 2.1928.1.4	Root Port.

2.1928.1.1 SpanningTreeBridge

[detail]	*SpanningTreeBridgeDetail* see 2.1928.1.1.1	Spanning tree bridge details.
forwardDelay	*integer*	Forward delay for the bridge (seconds).
helloTime	*floating point number*	Hello time for the bridge (seconds).
macAddress	*MAC address*	MAC address of the bridge.
maxAge	*integer*	Max age for the bridge (seconds).
priority	*integer*	Priority of the bridge (0 to 61440 in increments of 4096).
systemIdExtension	*integer*	System Id extension.

2.1928.1.1.1 SpanningTreeBridgeDetail

transmitHoldCount	*integer*	Transmit Hold Count. This is the burstiness for transmitted BPDUs. TransmitHoldCount number of BPDUs are allowed to be transmitted every (2000/(Hello Time * TransmitHoldCount)) seconds, where Hello Time is in milliseconds.

2.1928.1.2 SpanningTreeInstanceDetail

[lastTopologyChangePort]	*interface name*	Port on which last topology change happened.
[lastTopologyChangeTime]	*integer*	Seconds since last topology change.
topologyChanges	*integer*	Number of topology changes occurred.

2.1928.1.3 SpanningTreeInterface

boundaryType	*enum: stp* | *mstpRegionPvst* | *none* | *mstpRegion*	Spanning tree boundary type.
cost	*integer*	Spanning tree path cost.
[detail]	*SpanningTreeInterface-Detail* see 2.1928.1.3.2	Spanning tree interface details.
edgePortType **	*enum: portfast* | *auto*	Edge port type. **Since: 4.31.2
inconsistentFeatures	*SpanningTreeInconsistent-Features* see 2.1928.1.3.1	Spanning tree inconsistent features.
[isEdgePort]	*boolean*	Interface is an edge port.
linkType	*enum: shared* | *p2p*	Spanning tree link type.
[mappedVlans]	*VlanList* see 2.1928.1.3.5	Vlans mapped to the MST instance interface.
portNumber	*integer*	Port number.
priority	*integer*	Spanning tree port priority.
role	*enum: backup* | *alternate* | *designated* | *root* | *master* | *disabled*	Spanning tree port role.
state	*enum: discarding* | *forwarding* | *learning*	Spanning tree port state.

2.1928.1.3.1 SpanningTreeInconsistentFeatures

bridgeAssurance	*boolean*	Bridge assurance is inconsistent.
loopGuard	*boolean*	Loop Guard is inconsistent.
[mstPvstBorder]	*boolean*	MST-PVST border is inconsistent.
rootGuard	*boolean*	Root Guard is inconsistent.

2.1928.1.3.2 SpanningTreeInterfaceDetail

Could also be an instance of:
SpanningTreeInterfaceAllDetail 2.1928.1.3.3
SpanningTreeInterfaceMstDetail 2.1928.1.3.4

designatedBridgeAddress	*MAC address*	Address of designated bridge.
designatedBridgePriority	*integer*	Priority of designated bridge.
designatedPathCost	*SpanningTreePathCost* see 2.1928.1.3.2.1	Designated path cost.
designatedPortNumber	*integer*	Port number of designated port.
designatedPortPriority	*integer*	Priority of designated port.
designatedRootAddress	*MAC address*	Address of designated root bridge.
designatedRootPriority	*integer*	Priority of designated root bridge.

2.1928.1.3.2.1 SpanningTreePathCost

Could also be an instance of:
SpanningTreePathCostCist 2.1928.1.3.2.2

SpanningTreePathCostDefault 2.1928.1.3.2.3

2.1928.1.3.2.2 SpanningTreePathCostCist

externalCost	*integer*	External Root Path Cost.
internalCost	*integer*	Internal Root Path Cost.

2.1928.1.3.2.3 SpanningTreePathCostDefault

cost	*integer*	Root Path Cost.

2.1928.1.3.3 SpanningTreeInterfaceAllDetail

counters	*SpanningTreeInterface-Counters* see 2.1928.1.3.3.2	Spanning Tree Interface Counters.
designatedBridgeAddress	*MAC address*	Address of designated bridge.
designatedBridgePriority	*integer*	Priority of designated bridge.
designatedPathCost	*SpanningTreePathCost* see 2.1928.1.3.2.1	Designated path cost.
designatedPortNumber	*integer*	Port number of designated port.
designatedPortPriority	*integer*	Priority of designated port.
designatedRootAddress	*MAC address*	Address of designated root bridge.
designatedRootPriority	*integer*	Priority of designated root bridge.
features	*table(string) = SpanningTreeFeatureStatus* see 2.1928.1.3.3.1	Spanning tree feature status.
forwardDelay	*integer*	Forwarding delay for port (seconds).
maxAge	*integer*	Max Age for port (seconds).
messageAge	*integer*	Message age for port (seconds).
rateLimitEnabled	*boolean*	BPDU rate limiter is enabled.
rateLimitInterval	*floating point number*	BPDU rate limiter window.
rateLimitMaxCount	*integer*	BPDU rate limiter maximum count.
[regionalRootAddress]	*MAC address*	Address of regional root bridge.
[regionalRootPriority]	*integer*	Priority of regional root bridge.
transitionsToForwarding	*integer*	Number of timer port transitioned to forwarding state.

2.1928.1.3.3.1 SpanningTreeFeatureStatus

default	*boolean*	The feature setting is at its default value.
value	*string*	The current feature setting.

2.1928.1.3.3.2 SpanningTreeInterfaceCounters

bpduOtherError	*integer*	BPDUs other error.
bpduRateLimitCount	*integer*	BPDU rate limiter count.

bpduReceived	*integer*	BPDUs received.
bpduSent	*integer*	BPDUs sent.
bpduTaggedError	*integer*	BPDUs tagged error.

2.1928.1.3.4 SpanningTreeInterfaceMstDetail

designatedBridgeAddress	*MAC address*	Address of designated bridge.
designatedBridgePriority	*integer*	Priority of designated bridge.
designatedPathCost	*SpanningTreePathCost* see 2.1928.1.3.2.1	Designated path cost.
designatedPortNumber	*integer*	Port number of designated port.
designatedPortPriority	*integer*	Priority of designated port.
designatedRootAddress	*MAC address*	Address of designated root bridge.
designatedRootPriority	*integer*	Priority of designated root bridge.
[regionalRootAddress]	*MAC address*	Address of regional root bridge.
[regionalRootPriority]	*integer*	Priority of regional root bridge.

2.1928.1.3.5 VlanList

vlans	*list of integer*	A list of vlans.

2.1928.1.4 SpanningTreeRootPort

cost	*SpanningTreePathCost* see 2.1928.1.3.2.1	Root Path Cost.
interface	*interface name*	Root Port Interface Name.
portNumber	*integer*	Port Number of Root Port.

2.1929 show spanning-tree blockedports

spanningTreeInstances	*table(string) = SpanningTreeBlockedPortsList* see 2.1929.1	Map STP instance names to blocked ports.

2.1929.1 SpanningTreeBlockedPortsList

spanningTreeBlockedPorts	*list of Interface name*	List of STP blocked ports.

2.1930 show spanning-tree counters

interfaces	*table(Interface name) = SpanningTreeInterfaceCounters* see 2.1928.1.3.3.2	Map interfaces to STP counters.

2.1931 show spanning-tree instance [...]

[detail]	*SpanningTreeBridgesDetail* see 2.1931.1	Spanning tree bridge details.
spanningTreeBridges	*table(string) = SpanningTreeBridge* see 2.1928.1.1	Map STP bridge names to their details.

2.1931.1 SpanningTreeBridgesDetail

[heartbeatTimeout] **	*floating point number*	Time (in seconds) of no received STP heartbeat before a timeout is declared. **Since: 4.18.0
[lastLocalHeartbeatTimeout] **	*floating point number*	Time of the last local STP heatbeat timeout. **Since: 4.18.0
[lastPeerHeartbeatTimeout] **	*floating point number*	Time of the last peer STP heartbeat timeout. **Since: 4.18.0
[localHeartbeatTimeouts-SinceReboot] **	*integer*	Number of local STP heartbeat timeouts that occured since the last reload. **Since: 4.18.0
mismatchedBpduMode **	*enum: accept | drop*	VLAN-mismatched BPDU handling mode in PVST. **Since: 4.30.2
[mstPvstBorderEffective]	*boolean*	MST-PVST interoperation is active.
[overriddenBy] **	*string*	By whom Stp is overridden. **Since: 4.18.0
[peerHeartbeatTimeouts-SinceReboot] **	*integer*	Number of peer STP heartbeat timeouts that occured since the last reload. **Since: 4.18.0
[peerHeartbeatWhileEnabled] **	*boolean*	Peer heartbeat check is enabled. **Since: 4.18.0
portChannelPortId-AllocationRange **	*PortChannelPortIdAlloc* see 2.1931.1.1	Allocation range for port-channel port ID. **Since: 4.29.2
[preserveOriginal2p5GAnd5G-Cost] **	*boolean*	Original 2.5G/5G cost (2000) is preserved. **Since: 4.30.1
restartable	*boolean*	STP is restartable.
[superRoot] **	*boolean*	This switch is network super root. **Since: 4.25.1

2.1931.1.1 PortChannelPortIdAlloc

reservedRangeMax	*integer*	Maximum value for reserved range.
reservedRangeMin	*integer*	Minimum value for reserved range.

2.1932 show spanning-tree interface ETHINTF [...]

interface	*interface name*	Name of interface.
spanningTreeInstances	*table(string) = SpanningTreeInterface* see 2.1928.1.3	Map STP instances to interfaces.

2.1933 show spanning-tree mst [...]

spanningTreeMstInstances	*table(string) = SpanningTreeMstInstance* see 2.1933.1	Map MST instance names to details.

2.1933.1 SpanningTreeMstInstance

bridge	*SpanningTreeBridgeBrief* see 2.1933.1.1	Spanning tree bridge details.
interfaces	*table(Interface name) = SpanningTreeInterface* see 2.1928.1.3	Map interface names to details.
mappedVlans	*VlanList* see 2.1928.1.3.5	Vlans mapped to the MST instance.
[regionalRootBridge]	*SpanningTreeBridgeBrief* see 2.1933.1.1	Spanning tree regional root bridge details.
[rootBridge]	*SpanningTreeBridgeBrief* see 2.1933.1.1	Spanning tree root bridge details.

2.1933.1.1 SpanningTreeBridgeBrief

Could also be an instance of:
SpanningTreeBridge 2.1928.1.1

macAddress	*MAC address*	MAC address of the bridge.
priority	*integer*	Priority of the bridge (0 to 61440 in increments of 4096).
systemIdExtension	*integer*	System Id extension.

2.1934 show spanning-tree mst configuration [...]

configuredMstInstances	*integer*	Number of MST instances configured.
[mstConfigurationDigest]	*string*	MST configuration digest.
mstConfigurationRevision	*integer*	MST configuration revision.
mstInstances	*table(numeric string) = VlanList* see 2.1928.1.3.5	Map MST instance numbers to corresponding Vlan list.
mstRegionName	*string*	MST region identifier.

2.1935 show spanning-tree mst interface ETHINTF [...]

[spanningTreeMstInterface]	*SpanningTreeMstInterface* see 2.1935.1	Spanning Tree MST interface details.

2.1935.1 SpanningTreeMstInterface

counters	*SpanningTreeInterface-Counters* see 2.1928.1.3.3.2	STP counters.
features	*table(string) = SpanningTreeFeatureStatus* see 2.1928.1.3.3.1	Spanning tree feature status.
interfaceName	*interface name*	Interface Name.
isEdgePort	*boolean*	Interface is an edge port.
mstInstances	*table(string) = SpanningTreeInterface* see 2.1928.1.3	Map MST instance names to interface details.

2.1936 show spanning-tree mst test information

bridgeAddr	*MAC address*	MAC address of bridge.
mstpRegionId	*string*	MSTP specific region Identifier.
name	*string*	Name of bridge.
stpInstances	*table(string) = BridgeStpiInfo* see 2.1936.1	A mapping of VLAN to spanning tree instances (rapid-pvst) OR the entire group of MSTP instances with key "Mst".
stpVersion	*enum: backup | rapid-pvst | stp | rapidPvstp | none | rstp | mstp*	Version of the protocol being run.

2.1936.1 BridgeStpiInfo

cistPathCost	*integer*	Common Internal Spanning Tree path cost.
cistRoot	*SpanningTreeBridgeBrief* see 2.1933.1.1	Common Internal Spanning Tree root identifier.
interfaces	*table(Interface name) = BridgeIntfInfo* see 2.1936.1.1	A mapping of interface name to its status info.
mstpInstances	*table(string) = BridgeMstiInfo* see 2.1936.1.2	A mapping of Multiple Spanning Tree Instance to its status info.

2.1936.1.1 BridgeIntfInfo

externalPathCost	*integer*	Operational value to use for the external path cost for the port. It is set based on the extPathCost and linkPathCost values in the PortConfig.

2.1936.1.2 BridgeMstiInfo

bridgeId	*SpanningTreeBridgeBrief* see 2.1933.1.1	Bridge identifier on this bridge.
designatedRoot	*SpanningTreeBridgeBrief* see 2.1933.1.1	Designated Root Bridge identifier.
interfaces	*table(Interface name) = BridgeMstiIntfInfo* see 2.1936.1.2.1	A mapping of interface name to its status info.

2.1936.1.2.1 BridgeMstiIntfInfo

fdbFlushes	*integer*	Incremented by one everytime fdb needs to be flushed.
internalPathCost	*integer*	Path cost used on this port, either derived from the link speed or specified via configuration.
portId	*SpanningTreePortId* see 2.1936.1.2.1.1	Port identifier for this MSTI. Each MSTI can have a different port priority resulting in a different port identifier.

role	*enum: backup | alternate | designated | root | master | disabled*	Current port role for this instance and port.

2.1936.1.2.1.1 SpanningTreePortId

number	*integer*	Port number.
priority	*integer*	Priority of port.

2.1937 show spanning-tree root [...]

instances	*table(string) = SpanningTreeRoot* see 2.1937.1	Map STP instance names to their root bridge.

2.1937.1 SpanningTreeRoot

rootBridge	*SpanningTreeBridge* see 2.1928.1.1	Spanning tree root bridge details.
[rootPort]	*SpanningTreeRootPort* see 2.1928.1.4	Root Port.

2.1938 show spanning-tree topology status [...]

topologies	*table(string) = Topology* see 2.1938.1	Maps a topology name to its topology information.
unmappedVlans	*list of integer*	VLAN numbers that are not mapped to any topology.

2.1938.1 Topology

interfaces	*table(string) = PortStatus* see 2.1938.1.1	Maps an interface name to its status.
vlans	*list of integer*	VLANs mapped in this topology.

2.1938.1.1 PortStatus

[lastChange]	*floating point number*	UNIX timestamp with millisecond precision of the last state change for this port.
[numChanges]	*integer*	Number of state changes for this port since the switch booted.
state	*enum: discarding | portStateUnknown | forwarding | learning*	State of the port.

2.1939 show spanning-tree transmit active [...]

bridgeAssuranceEnabled	*boolean*	Bridge Assurance is enabled in the configuration.
spanningTreeInstances	*table(string) = SpanningTreeBridgeAssuranceInterfaces* see 2.1939.1	Map STP instances to bridge assurance interfaces.

2.1939.1 SpanningTreeBridgeAssuranceInterfaces

interfaces	*table(Interface name) = SpanningTreeBridgeAssuranceValue* see 2.1939.1.1	Map STP interfaces to their Bridge Assurance values.

2.1939.1.1 SpanningTreeBridgeAssuranceValue

bridgeAssuranceValue	*enum: inconsistent | consistent | notNetworkPort*	Spanning Tree Bridge Assurance values.

2.1940 show spanning-tree vlan [...]

spanningTreeVlanInstances	*table(numeric string) = SpanningTreeVlanInstance* see 2.1940.1	Map vlans to their STP vlan instances. If a vlan exists, it will belong to this collection regardless of whether there is a spanning tree instance associated with it.

2.1940.1 SpanningTreeVlanInstance

[spanningTreeVlanInstance]	*SpanningTreeInstance* see 2.1928.1	Spanning tree vlan instance details. This field is None when a corresponding vlan exists, but has no spanning tree instance associated with it.

2.1941 show split-horizon group [...]

vlans	*table(string) = VlanWithGroups* see 2.1941.1	VLANs that use split horizon groups, keyed by VLAN.

2.1941.1 VlanWithGroups

groups	*table(string) = SplitHorizonGoup* see 2.1941.1.1	Split horizon groups keyed by group name.
vlanBundle **	*boolean*	This VLAN is part of a VLAN bundle. **Since: 4.32.0

2.1941.1.1 SplitHorizonGoup

`active`	*boolean*	This group is correctly configured and programmed.
`interfaces`	*list of string*	Interface within a split horizon group.
`[vplsInstName]` **	*string*	VPLS instance name. **Since: 4.32.0

2.1942 show srv6 adjacency-segments [...]

adjacencySegments	*AdjacencySegments* see 2.1942.1	SRv6 Adjacency Segments based on either locator or domain.

2.1942.1 AdjacencySegments

domains	*table(string) = Srv6DomainStatic-AdjacencySegments* see 2.1942.1.1	SRv6 static adjacency segments based on domains, keyed by domain name.
locators	*table(string) = Srv6LocatorStatic-AdjacencySegments* see 2.1942.1.2	SRv6 static adjacency segments based on locators, keyed by locator name.

2.1942.1.1 Srv6DomainStaticAdjacencySegments

usids	*table(numeric string) = Srv6StaticAdjacency-SegmentInstance* see 2.1942.1.1.1	SRv6 static adjacency segments of a domain, keyed by usid value.

2.1942.1.1.1 Srv6StaticAdjacencySegmentInstance

[flavors]	*Srv6SidFlavorFlags* see 2.20.1.1.2.36	SID flavors.
[inactiveReason]	*string*	legacy, prefer inactiveReasonCode.
[inactiveReasonCode] **	*enum: locatorNotActive | unknownState | domainNotActive | noValidVia | valueNotInLib*	Reason why adjacency segment is not active. **Since: 4.36.0
[prefix]	*IP address prefix*	Adjacency segment prefix.
state	*enum: inactive | active*	Adjacency segment state.
vias	*list of Srv6StaticAdjacency-SegmentVia* see 2.1942.1.1.1.1	List of all vias.

2.1942.1.1.1.1 Srv6StaticAdjacencySegmentVia

[inactiveReason]	*string*	legacy, prefer inactiveReasonCode.
[inactiveReasonCode] **	*enum: nexthopUnresolved | l3IntfNotOperationalIn-DefaultVrf | l3IntfDown | l3IntfDpRoutingDisabled*	Reason why adjacency segment via is not active. **Since: 4.36.0
l3Intf	*interface name*	Egress L3 interface.
nextHop	*IPv6 address*	Nexthop IPv6 address.
state	*enum: inactive | active*	Adjacency segment via state.

2.1942.1.2 Srv6LocatorStaticAdjacencySegments

usids	*table(numeric string) = Srv6StaticAdjacency-SegmentInstance* see 2.1942.1.1.1	SRv6 static adjacency segments of a locator, keyed by usid value.

2.1943 show srv6 capabilities

[otherCapabilities]	*OtherCapabilitiesModel* see 2.1943.1	Supported uSIDFormats.
[supportedEndBehavior-Flavors]	*Srv6EndFlavorsModel* see 2.1943.3	Supported end behavior flavors.
[supportedEndBehaviors]	*Srv6EndBehaviorsModel* see 2.1943.2	Supported end behaviors.
[supportedHeadendBehaviors]	*Srv6HeadendBehaviors-Model* see 2.1943.4	Supported headend behaviors.

2.1943.1 OtherCapabilitiesModel

uSIDFormats	*list of string*	uSID formats supported by the platform.

2.1943.2 Srv6EndBehaviorsModel

end	*boolean*	Supports End behavior.
endDt4	*boolean*	Supports End.DT4 behavior.
endDt46 **	*boolean*	Supports End.DT46 behavior. **Since: 4.36.0
endDt6	*boolean*	Supports End.DT6 behavior.
endDx4	*boolean*	Supports End.DX4 behavior.
endDx6	*boolean*	Supports End.DX6 behavior.
endX	*boolean*	Supports End.X behavior.

2.1943.3 Srv6EndFlavorsModel

nextCsid	*boolean*	Supports Next-CSID flavor.
psp	*boolean*	Supports Penultimate Segment Pop (PSP) of the SRH flavor.
usd	*boolean*	Supports Ultimate Segment Decapsulation (USD) flavor.
usp	*boolean*	Supports Ultimate Segment Pop (USP) of the SRH flavor.

2.1943.4 Srv6HeadendBehaviorsModel

hEncaps	*boolean*	Supports H.Encaps headend behavior.
hEncapsRed	*boolean*	Supports H.Encaps with Reduced Encapsulation.
hInsert	*boolean*	Supports H.Insert headend behavior.
hInsertRed	*boolean*	Supports H.Insert with Reduced Encapsulation headend behavior.

2.1944 show srv6 domain [...]

vrfs	*table(string) = Srv6DomainVrfModel* see 2.1944.1	Per VRF SRv6 configurations.

2.1944.1 Srv6DomainVrfModel

domains	*table(string) = Srv6DomainEntry* see 2.1944.1.1	Domain details.
numDomains	*integer*	Number of configured domains.

2.1944.1.1 Srv6DomainEntry

[block]	*IP address prefix*	Domain Block.
[gibRange]	*Srv6GibRange* see 2.1944.1.1.1	GIB Range.
[inactiveReason]	*string*	legacy, prefer inactiveReasonCode.
[inactiveReasonCode] **	*enum: invalidGibRange | vrfInoperational | blockNotConfigured | formatNotSupported | blockConflict*	Reason why domain is not active. **Since: 4.36.0
state	*enum: inactive | active*	Domain state.
usidLength	*integer*	uSID Length.

2.1944.1.1.1 Srv6GibRange

gibRangeMax	*integer*	max value of GIB Range.
gibRangeMin	*integer*	min value of GIB Range.

2.1945 show srv6 hardware ale adj [...]

sfibRoute	*list of Ale.Srv6FecRequestTableEntry* see 2.1945.1	Collection of SFIB Adj-SID routes.

2.1945.1 Ale.Srv6FecRequestTableEntry

adjacencyId	*integer*	Adjacency ID for programmed FEC request.
endpoint	*IPv6 prefix*	SRv6 Adj-SID endpoint.
fecId	*integer*	FEC ID generated for FEC request.
hwFecId	*integer*	HW FEC ID for programmed FEC request.
vias	*list of Ale.Srv6FecRequestVia* see 2.1945.1.1	Collection of vias to be programmed for the FEC request.

2.1945.1.1 Ale.Srv6FecRequestVia

`interface`	*interface name*	Interface for the SFIB via.
`nexthop`	*IPv6 address*	Nexthop for the SFIB via.

2.1946 show srv6 locator [...]

vrfs	*table(string) = Srv6ConfigVrfModel* see 2.1946.1	Per VRF SRv6 configurations.

2.1946.1 Srv6ConfigVrfModel

enabled	*boolean*	SRv6 enabled.
locators	*table(string) = Srv6LocatorEntry* see 2.1946.1.1	Locator details.
numLocators **	*integer*	Number of configured locators. **Since: 4.35.0
operational	*boolean*	SRv6 active.
[sourceAddress]	*IPv6 address*	Source encapsulation address for SRv6 Tunnels.

2.1946.1.1 Srv6LocatorEntry

[algorithm]	*integer*	IGP Algorithm.
algorithmName	*string*	IGP Algorithm.
blockLength	*integer*	Block length.
functionLength	*integer*	Function Length.
[inactiveReason]	*string*	legacy, prefer inactiveReasonCode.
[inactiveReasonCode] **	*enum: endUsidNotInRange | prefixConflict | flexAlgoUndefined | usidDomainNotConfigured | usidDomainInactive | prefixNotConfigured | endUsidConflict | prefixLengthExceeded | locatorVrfInoperational*	Reason why locator is not active. **Since: 4.36.0
locatorType	*string*	legacy, prefer locatorTypeCode.
locatorTypeCode **	*enum: classic | microSid*	Locator type. **Since: 4.36.0
[locatorUsidDomain]	*string*	Micro Segment Domain name.
[prefix]	*IP address prefix*	Prefix.
state	*enum: inactive | active*	Locator state.
usid	*integer*	uSID for this locator.

2.1947 show srv6 route [...]

routes	*table(string) = Srv6RouteEntry* see 2.1947.1	SRv6 Routes keyed by SID.

2.1947.1 Srv6RouteEntry

[domain] **	*string*	Domain for the SID. **Since: 4.35.2
locator	*string*	Locator for the SID.
[lookupVrf]	*string*	Lookup VRF name for SID behaviors.
sidInformation	*Srv6Sid* see 2.20.1.1.2.35	SID for the route.
source	*enum: sourceBgpL3Vpn | sourceStatic*	Source protocol.
[unprogrammed] **	*boolean*	Programming state for the SID. **Since: 4.35.0
vias **	*list of Srv6Via* see 2.1947.1.1	List of vias for the route. **Since: 4.35.2

2.1947.1.1 Srv6Via

interface	*string*	Interface Name.
nexthop	*string*	Next hop IP address.

2.1948 show srv6 route counters [...]

routes	*table(IPv4 or IPv6 address prefix) = Srv6.Cli.Srv6-RouteCountersEntry* see 2.1948.1	SRv6 Routes counters keyed by SID.

2.1948.1 Srv6.Cli.Srv6RouteCountersEntry

locator	*string*	Locator for the SID.
sidInformation	*Srv6.Cli.Srv6Sid* see 2.1948.1.1	SID for the route.
source	*enum: sourceBgpL3Vpn | sourceStatic*	Source protocol.
totalBytes	*integer*	Total number of bytes received for the SID.
totalPackets	*integer*	Total number of received packets for the SID.

2.1948.1.1 Srv6.Cli.Srv6Sid

behavior	*enum: endDt6 | unknown | endDt4 | endDx4 | end | endDx6 | endX | endDt46*	SID behavior.
[flavors]	*Srv6.Cli.Srv6SidFlavor-Flags* see 2.1948.1.1.1	SID flavors.
sid	*IP address prefix*	SID value (IPv6 prefix).

2.1948.1.1.1 Srv6.Cli.Srv6SidFlavorFlags

[nextCsid]	*boolean*	NEXT-CSID flavor.

[nextOnlyCsid]	*boolean*	NEXT-ONLY-CSID flavor.
[psp]	*boolean*	Penultimate Segment Pop (PSP) of the SRH flavor.
[usd]	*boolean*	Ultimate Segment Decapsulation (USD) flavor.
[usp]	*boolean*	Ultimate Segment Pop (USP) of the SRH flavor.

2.1949 show storm-control [...]

[aggregateTrafficClasses]	*table(numeric string) = StormControlType* see 2.1949.2.1	A mapping of Aggregate traffic class to storm control status.
[globalRules] **	*table(string) = GlobalStormControlType* see 2.1949.1	Global rules storm control status. **Since: 4.35.0
interfaces	*table(Interface name) = IntfStormControlStatus* see 2.1949.2	Per-interface storm control status.

2.1949.1 GlobalStormControlType

[active]	*boolean*	Whether storm control has been applied.
[dormant]	*boolean*	Rule is superseded by all traffic.
[drop]	*integer*	Packets dropped by storm control.
[dropOctets]	*integer*	Octets dropped by storm control.
[level]	*integer*	Storm control level.
[reason]	*string*	Reason for the status.
[thresholdType]	*enum: bitsPerSecond | packetsPerSecond | percentage*	Type of threshold applied.

2.1949.2 IntfStormControlStatus

active	*boolean*	Whether storm control has been applied.
errdisabled **	*boolean*	Whether the interface has been errdisabled. **Since: 4.30.2
reason	*string*	Reason for the status.
trafficTypes	*table(string) = StormControlType* see 2.1949.2.1	Applied storm control setting for a given traffic type.

2.1949.2.1 StormControlType

dormant	*boolean*	Rule is superseded by all traffic.
[drop]	*integer*	Packets dropped by storm control.
[dropOctets] **	*integer*	Octets dropped by storm control. **Since: 4.32.1
level	*integer*	Storm control level.
rate	*integer*	Effective allowed broadcast rate in bps.
thresholdType	*enum: bitsPerSecond | packetsPerSecond | percentage*	Type of threshold applied.

2.1950 show stun client counters [...]

cleanStarts	*integer*	No of times the agent started with proper cleanup done by the previous run.
nonCleanStarts	*integer*	No of times the agent started without proper cleanup done by the previous run.
stunServerProfileCounters	*list of StunServerProfileCountersModel* see 2.1950.1	Counters associated with a server profile.

2.1950.1 StunServerProfileCountersModel

invalidResponses	*integer*	No of invalid responses recevied.
name	*string*	Server profile name.
numRetries	*integer*	No of retries carried out for failed requests.
refreshRequests	*integer*	No of refresh requests sent.
responseProcessingFailures	*integer*	No of times an error was encountered during the processing of a received response.
retriesExhausted	*integer*	No of times the entire retry process failed.
sslTransportCounters	*StunTransportCountersModel* see 2.1950.1.1	SSL transport counters.
successfulResponses	*integer*	No of successful responses received.
tid	*string*	Transaction ID.
udpTransportCounters	*StunTransportCountersModel* see 2.1950.1.1	UDP transport counters.

2.1950.1.1 StunTransportCountersModel

connectionErrors	*integer*	Connection errors.
initializationFailures	*integer*	No of times the initialization failed.
readFailures	*integer*	No of read failures.
successfulInitializations	*integer*	No of successful initializations.
transport	*string*	SSL or UDP.
writeFailures	*integer*	No of write failures.

2.1951 show stun client translations [...]

bindings	*table(string) = StunClientBindingModel* see 2.1951.1	STUN bindings keyed by transaction ID.

2.1951.1 StunClientBindingModel

agentName	*string*	Agent Name.
[lastRefreshed]	*integer*	Seconds elapsed since last response.
[nextSslConnectionRefreshTimestamp] **	*integer*	Next SSL connection refresh time. **Since: 4.34.0
[publicAddress]	*IpAddrAndPort* see 2.723.1.1.1.1	Translated IP address and port.

[sourceAddress]	*IpAddrAndPort* see 2.723.1.1.1.1	Source IP address and port.
[sslConnectionLifetime] **	*integer*	SSL connection lifetime in seconds. **Since: 4.34.0
timeoutInterval	*integer*	STUN bindings timeout interval in seconds.
tlvs	*list of StunTlvModel* see 2.1951.1.1	STUN Attributes.

2.1951.1.1 StunTlvModel

tlvLen	*integer*	STUN TLV length.
tlvOrigin **	*string*	STUN TLV Origin. **Since: 4.33.2
tlvType	*string*	STUN TLV type.
tlvValue	*string*	STUN TLV value.

2.1952 show stun server bindings [...]

bindings	*table(string) = StunServerBindingModel* see 2.1952.1	STUN binding bindings keyed by transaction ID.

2.1952.1 StunServerBindingModel

numTlvs	*integer*	Number of STUN Attributes.
publicAddress	*IpAddrAndPort* see 2.723.1.1.1.1	Translated IP address and port.
[timeout]	*integer*	Seconds remaining until timeout.
timeoutInterval	*integer*	Bindings timeout interval in seconds.
tlvs	*list of StunTlvModel* see 2.1951.1.1	STUN Attributes.

2.1953 show stun server status

authMode	*enum: stunLongTermCredentials | ssl | none*	Authentication mode.
bindingTimeout	*integer*	Bindings timeout interval in seconds.
enabled	*boolean*	Service is enabled.
listeningIps	*table(IPv4 or IPv6 address) = Interface name*	Listening IP address and interface of the service.
listeningPort	*integer*	Listening port of the service.
[pid]	*integer*	Process ID of the service.
sslConnectionLifetime	*integer*	SSL connection lifetime in seconds.
timeOfLastRcvdBindingReq	*integer*	Seconds elapsed since the last binding response was received.

2.1954 show switch aggregation backplane floodset [...]

floodsetForIntfs	*list of SwagFloodsetForIntf* see 2.1954.1	Interfaces with the floodset information.

2.1954.1 SwagFloodsetForIntf

computedState	*enum: included | excluded*	Interface configuration for floodset participation.
hardwareState	*enum: pending | n/a | programmed | stale*	Programming status of floodset information.
interface	*interface name*	Name of the interface.

2.1955 show switch aggregation onboarding [...]

members	*table(MAC address) = SwagOnboardingMember* see 2.1955.1	Members that onboarded or are onboarding via ZTP.

2.1955.1 SwagOnboardingMember

clientId	*MAC address*	Switch MAC address.
dhcpIntfId	*list of Interface name*	Interfaces where switch was seen.
eosVersion	*string*	EOS version of the candidate switch.
hardwareRevision	*string*	Hardware revision of the candidate switch.
memberId	*integer*	Identifier for new member.
modelName	*string*	Model name of the candidate switch.
onboardingCount	*integer*	Number of times this switch has onboarded.
serialNumber	*string*	Serial number of the candidate switch.
state	*enum: swiDlStart | dhcpReplySent | error | swagConfigDlEnd | reload | bootConfigDlEnd | dhcpInformRecv | bootConfigDlStart | joinSwag | onboarded | startupConfigDlEnd | swagConfigDlStart | startupConfigDlStart | bootFileDlStart | bootFileDlEnd | swiDlEnd*	Current onboarding status.
stateChangeTime	*floating point number*	Time of last state change (UTC).
stateDetails **	*string*	Additional information for state. **Since: 4.35.2

2.1956 show switch aggregation onboarding configuration [...]

[memberConfigs]	*table(string) = SwagMemberConfig or NULL* see 2.1956.1	Switch aggregation onboarding configuration information.

2.1956.1 SwagMemberConfig

[backplaneChannels]	*table(Interface name) = BackplaneChannelConfig or NULL* see 2.1956.1.1	Backplane-Channel information.
[encryptedRootPasswd]	*string*	AAA root password.
[localMemberId]	*integer*	Identifier for local member.
[qsfpDefaultMode] **	*string*	Transceiver qsfp default-mode. **Since: 4.35.2
[timezone]	*string*	Clock timezone.
[vlan]	*integer*	Control network VLAN.

2.1956.1.1 BackplaneChannelConfig

[memberIntfs]	*table(Interface name) = BaMemberIntfConfig* see 2.1956.1.1.1	Member interface configuration command.
[peerMemberId]	*integer*	Identifier for peer member.

2.1956.1.1.1 BaMemberIntfConfig

[adminEnabled]	*string*	Interface administrative state.
[fecBypass]	*string*	Interface error-correction encoding bypass.
[fecEncoding]	*string*	Interface error-correction encoding.
[speedConfig]	*string*	Interface speed configuration.

2.1957 show switch aggregation reachability [...]

reachabilityStatus	*table(numeric string) = ReachabilityState* see 2.1957.1	Reachability for each SWAG member to every other SWAG member.

2.1957.1 ReachabilityState

reachability	*table(numeric string) = ReachabilityIntfAck* see 2.1957.1.1	Reachability to every SWAG member.

2.1957.1.1 ReachabilityIntfAck

[interface]	*interface name*	Name of the interface.
lastUpdated	*floating point number*	Time since the interface was last updated (UTC).
status	*enum: pending* | *unreachable* | *configured* | *stale* | *failed* | *reachable*	Installation status of reachability information.

2.1958 show switch aggregation summary

[activeSupervisorId]	*integer*	Identifier for the active supervisor in the SWAG.
[candidateId]	*integer*	Identifier for this member.
members	*table(numeric string) = MemberStatus* see 2.1958.1	SWAG member information.
[peerSupervisorId] **	*integer*	Identifier for the peer supervisor in the SWAG. **Since: 4.35.2
[vlan]	*integer*	Control network VLAN.

2.1958.1 MemberStatus

ipv4Address	*IPv4 address*	Member IP address.
[lastPingTimestamp]	*integer*	Epoch timestamp in seconds of the most recent agent ping event.
macAddress	*MAC address*	Member MAC address.
role	*enum: candidate* | *supervisorServer* | *worker* | *supervisorSwitch*	Role of member.

2.1959 show switch forwarding-mode

currentL3McastMode **	*enum: storeAndForward* | *defaultMode* | *cutThrough*	Current multicast forwarding mode. **Since: 4.21.3
currentMode	*enum: storeAndForward* | *defaultMode* | *cutThrough*	Current switching mode.
[cutThroughDropFcsError] **	*boolean*	Drop FCS error enabled in cut-through mode. **Since: 4.35.2
supportedL3McastModes **	*list of SupportedMode* see 2.1959.1	List of supported multicast modes. **Since: 4.21.3
supportedModes	*list of SupportedMode* see 2.1959.1	List of supported modes.

2.1959.1 SupportedMode

supportedMode	*enum: storeAndForward* | *defaultMode* | *cutThrough*	Supported switching modes.

2.1960 show switch scheduler

schedulerMode	*enum: oversubscribed* | *linerate*	Current scheduler mode.

2.1961 show sync-e esmc counters

clockSourceCounters	*table(Interface name) = SynceEsmcCountersInfo* see 2.1961.1	Clock source RX and TX ESMC counters.

2.1961.1 SynceEsmcCountersInfo

[rxInfo]	*SynceEsmcCountersRxInfo* see 2.1961.1.1	RX ESMC counters information.
[txInfo]	*SynceEsmcCountersTxInfo* see 2.1961.1.2	TX ESMC counters information.

2.1961.1.1 SynceEsmcCountersRxInfo

invalidCount	*integer*	Number of invalid ESMC messages received.
[lastCascadedEecCount] **	*integer*	Last received number of cascaded EECs. **Since: 4.29.1
[lastCascadedEeecCount] **	*integer*	Last received number of cascaded eEECs. **Since: 4.29.1
[lastEssm] **	*integer*	Last received ESSM code. **Since: 4.29.1
[lastQualityLevel]	*enum: QL-DNU | QL-EEEC | QL-FAILED | QL-EPRC | QL-ST2 | QL-TNC | QL-ST3E | QL-SSU-B | QL-DUS | QL-INV | QL-SSU-A | QL-NSUPP | QL-EEC1 | QL-PRC | QL-EPRTC | QL-SMC | QL-PRTC | QL-INVX | QL-EEC2 | QL-UNC | QL-PROV | QL-STU | QL-PRS*	Last received quality level.
[lastSsm]	*integer*	Last received SSM code.
validCount	*integer*	Number of valid ESMC messages received.

2.1961.1.2 SynceEsmcCountersTxInfo

[lastCascadedEecCount] **	*integer*	Last sent number of cascaded EECs. **Since: 4.29.1
[lastCascadedEeecCount] **	*integer*	Last sent number of cascaded eEECs. **Since: 4.29.1
[lastEssm] **	*integer*	Last sent ESSM code. **Since: 4.29.1

[lastQualityLevel]	*enum: QL-DNU* | *QL-EEEC* | *QL-FAILED* | *QL-EPRC* | *QL-ST2* | *QL-TNC* | *QL-ST3E* | *QL-SSU-B* | *QL-DUS* | *QL-INV* | *QL-SSU-A* | *QL-NSUPP* | *QL-EEC1* | *QL-PRC* | *QL-EPRTC* | *QL-SMC* | *QL-PRTC* | *QL-INVX* | *QL-EEC2* | *QL-UNC* | *QL-PROV* | *QL-STU* | *QL-PRS*	Last sent quality level.
[lastSsm]	*integer*	Last sent SSM code.
sentCount	*integer*	Number of ESMC messages sent.

2.1962 show sync-e esmc detail [...]

clockSourceDetail	*table(Interface name) = SynceEsmcDetailInfo* see 2.1962.1	Detailed Clock source RX and TX ESMC information.

2.1962.1 SynceEsmcDetailInfo

[rxInfo]	*SynceEsmcDetailRxInfo* see 2.1962.1.1	Detailed RX ESMC information.
[txInfo]	*SynceEsmcDetailTxInfo* see 2.1962.1.2	Detailed TX ESMC information.

2.1962.1.1 SynceEsmcDetailRxInfo

esmcTypeCount	*table(string) = integer*	ESMC messages received by type.
invalidCount	*integer*	Number of invalid ESMC messages received.
[lastCascadedEecCount] **	*integer*	Last received number of cascaded EECs. **Since: 4.29.1
[lastCascadedEeecCount] **	*integer*	Last received number of cascaded eEECs. **Since: 4.29.1
[lastClockIdentity] **	*string*	Last received Synce clockIdentity of the originator of the extended QlTlv. **Since: 4.29.1
[lastEsmcType]	*enum: information | event*	Last received ESMC message type.
[lastEssm] **	*integer*	Last received ESSM code. **Since: 4.29.1
[lastEtlvFlag] **	*integer*	Last received EEC/eEEC flag. **Since: 4.29.1
[lastInvalidTime]	*floating point number*	UTC timestamp of the last received invalid ESMC message.
[lastQualityLevel]	*enum: QL-DNU | QL-EEEC | QL-FAILED | QL-EPRC | QL-ST2 | QL-TNC | QL-ST3E | QL-SSU-B | QL-DUS | QL-INV | QL-SSU-A | QL-NSUPP | QL-EEC1 | QL-PRC | QL-EPRTC | QL-SMC | QL-PRTC | QL-INVX | QL-EEC2 | QL-UNC | QL-PROV | QL-STU | QL-PRS*	Last received quality level.
[lastSsm]	*integer*	Last received SSM code.
[lastValidTime]	*floating point number*	UTC timestamp of the last received valid ESMC message.
qualityLevelCount	*table(string) = QualityLevelCount* see 2.1962.1.1.1	ESMC messages received by quality level.
[sourceMac]	*MAC address*	Source MAC address of ethernet clock source.

validCount	*integer*	Number of valid ESMC messages received.

2.1962.1.1.1 QualityLevelCount

countBySsm	*table(string) = integer*	ESMC messages by SSM code.

2.1962.1.2 SynceEsmcDetailTxInfo

esmcTypeCount	*table(string) = integer*	ESMC messages sent by type.
[lastCascadedEecCount] **	*integer*	Last sent number of cascaded EECs. **Since: 4.29.1
[lastCascadedEeecCount] **	*integer*	Last sent number of cascaded eEECs. **Since: 4.29.1
[lastClockIdentity] **	*string*	Last sent Synce clockIdentity of the originator of the extended QlTlv. **Since: 4.29.1
[lastEsmcType]	*enum: information | event*	Last sent ESMC message type.
[lastEssm] **	*integer*	Last sent ESSM code. **Since: 4.29.1
[lastEtlvFlag] **	*integer*	Last sent EEC/eEEC flag. **Since: 4.29.1
[lastQualityLevel]	*enum: QL-DNU | QL-EEEC | QL-FAILED | QL-EPRC | QL-ST2 | QL-TNC | QL-ST3E | QL-SSU-B | QL-DUS | QL-INV | QL-SSU-A | QL-NSUPP | QL-EEC1 | QL-PRC | QL-EPRTC | QL-SMC | QL-PRTC | QL-INVX | QL-EEC2 | QL-UNC | QL-PROV | QL-STU | QL-PRS*	Last sent quality level.
[lastSentTime]	*floating point number*	UTC timestamp of the last sent ESMC message.
[lastSsm]	*integer*	Last sent SSM code.
qualityLevelCount	*table(string) = QualityLevelCount* see 2.1962.1.1.1	ESMC messages sent by quality level.
sentCount	*integer*	Number of ESMC messages sent.
[sourceMac]	*MAC address*	Source MAC address of ethernet clock source.

2.1963 show sync-e selection

clockSources	*list of SynceSelectionStatus* see 2.1963.1	List of candidate clock sources participating in the selection process.

2.1963.1 SynceSelectionStatus

clockSource	*ClockSource* see 2.68.1.1	Candidate clock source.
[holdoffTimeout]	*floating point number*	UTC timestamp for the hold-off timer expiry.
priority	*Priority* see 2.1963.1.1	Selection priority.
[qualityLevel]	*enum: QL-DNU* | *QL-EEEC* | *QL-FAILED* | *QL-EPRC* | *QL-ST2* | *QL-TNC* | *QL-ST3E* | *QL-SSU-B* | *QL-DUS* | *QL-INV* | *QL-SSU-A* | *QL-NSUPP* | *QL-EEC1* | *QL-PRC* | *QL-EPRTC* | *QL-SMC* | *QL-PRTC* | *QL-INVX* | *QL-EEC2* | *QL-UNC* | *QL-PROV* | *QL-STU* | *QL-PRS*	Quality level.
status	*string*	Eligibility of clock source.
[waitToRestoreTimeout]	*floating point number*	UTC timestamp for the wait-to-restore timer expiry.

2.1963.1.1 Priority

[disabled]	*boolean*	Clock source will not participate in selection process.
[value]	*integer*	Clock source selection priority.

2.1964 show system bmc status

bmcInReset	*boolean*	BMC is in reset.
[bmcUsb0PingResult]	*enum:* *bmcInterfaceUndetected* | *bmcHubInterface-* *Undetected* | *pingUnsuccessful* | *pingSuccessful*	BMC USB0 IPv6 ping test result.
[personalityOnReboot]	*enum: cpu* | *bmc*	The personality on reboot.

2.1965 show system coredump

coreFiles	*list of string*	List of core files on the device.
mode	*enum: disabled* | *compressed* | *compressedDeferred*	Core dump control mode.

2.1966 show system environment all

cooling	*SystemCooling* see 2.1966.1	Cooling information for the system.
extra	*list of SystemEnvAllExtra* see 2.1966.2	Extended environment information.
temperature	*SystemTemperature* see 2.1966.3	Temperature information for the system.
temperatureXcvr	*SystemXcvrTemperature* see 2.1966.4	Transceiver temperature information for the system.

2.1966.1 SystemCooling

airflowDirection	*enum: unknownAirflowDirection* | *backToFrontAirflow* | *frontToBackAirflow* | *mismatchedAirflow*	The direction of air flow in the system (front refers to port-side).
[ambientTemperature]	*floating point number*	Ambient temperature detected by the cooling system (in Celsius).
[configuredZones] **	*integer*	Configured number of card cooling zones. **Since: 4.27.1
coolingMode	*enum: debug* | *manual* | *automatic*	Mode of operation of the cooling system.
[currentZones] **	*integer*	Current number of cooling zones. **Since: 4.27.1
[defaultZones] **	*boolean*	Default number of card cooling zones is used. **Since: 4.27.1
fanTraySlots	*list of FanCollection* see 2.1966.1.1	Fan tray slots in the system.
fansStatus **	*enum: fanAlarmDebugMode* | *fanAlarmOk* | *fanAlarmCoolingNotOk* | *fanAlarmTempOverheating* | *fanAlarmIncorrectConfig* | *fanAlarmManualMode* | *fanAlarmUnknownAirflow* | *fanAlarmTempCritical* | *unknownFanAlarmLevel* | *fanAlarmForcedSpeed* | *fanAlarmTempSensorFailure*	Fans status. **Since: 4.31.1
[minFanSpeed] **	*integer*	User-set minimum fan speed (as %). **Since: 4.22.0
numCoolingZones **	*list of integer*	Supported number of card cooling zones. **Since: 4.27.1
[overrideFanSpeed]	*integer*	Fan speed at which manual override is configured (as %).
powerSupplySlots	*list of FanCollection* see 2.1966.1.1	Power supply slots in the system.
shutdownOnInsufficientFans	*boolean*	Shut the system down on insufficient fans if True.

systemStatus	*enum: unknownCooling-AlarmLevel* | *fanTrayFailedOrMissing* | *insufficientFabricCards* | *incompatibleFans* | *coolingOk* | *insufficientFans*	System cooling status.

2.1966.1.1 FanCollection

[fanTrayId] **	*integer*	The fan module ID. **Since: 4.35.2
fans	*list of Fan* see 2.1966.1.1.1	The fans in the fan collection.
label	*string*	Slot Label.
[speed]	*integer*	The aggregated speed of the fans in the fan collection (as %).
status	*enum: unsupported* | *notInserted* | *failed* | *ok* | *unknownHwStatus* | *powerLoss*	The status of the fan collection.

2.1966.1.1.1 Fan

[actualSpeed]	*integer*	Actual speed of the fan (as %).
[configuredSpeed]	*integer*	Configured speed for the fan (as %).
coolingDomain **	*string*	Cooling domain for the fan. **Since: 4.35.2
label	*string*	Label for the fan.
[lastSpeedStableChangeTime] **	*floating point number*	Timestamp in UTC (in seconds) when last time the fan's speed was stable. **Since: 4.20.0
[maxSpeed] **	*integer*	Maximum speed for the fan (in rpm). **Since: 4.20.0
[speedHwOverride] **	*boolean*	If the fan's speed is overridden by hardware. **Since: 4.21.3
[speedStable] **	*boolean*	If the fan's speed is stable. **Since: 4.20.0
status	*enum: unsupported* | *failed* | *ok* | *unknownHwStatus* | *powerLoss*	Status of the fan.
[uptime] **	*floating point number*	Timestamp in UTC (in seconds) when the last change in Fan's status occurred. **Since: 4.20.0
[vendorModel] **	*string*	Vendor and model identifier for the fan. **Since: 4.35.2

2.1966.2 SystemEnvAllExtra

Could also be an instance of:
PowerSupplies 2.395

2.1966.3 SystemTemperature

`actionOnOverheat` **	*enum: actionPowercycle* | *actionIgnore* | *actionUnknown* | *actionShutdown*	System action for an overheat event. **Since: 4.29.0
`ambientThreshold` **	*integer*	Ambient temperature (in Celsius) above which EOS will run in reduced capacity. **Since: 4.26.2
`cardSlots`	*list of FruSlot* see 2.1966.3.1	Card slots on a modular system.
`powerSupplySlots`	*list of FruSlot* see 2.1966.3.1	Power Supply Slots on the system.
`powercycleOnOverheat` **	*boolean*	Whether the system is configured to power-cycle on an overheat event. **Since: 4.26.0
`recoveryModeOnOverheat` **	*enum: recoveryModeRestricted* | *recoveryModeNA* | *recoveryModeNormal*	Specify recovery behavior after power-cycle. **Since: 4.26.2
`shutdownOnOverheat`	*boolean*	Whether the system is configured to shut-down on an overheat event.
`systemStatus`	*enum: temperatureSensorFailure* | *temperatureOk* | *temperatureOverheating* | *unknownTemperature-AlarmLevel* | *temperatureCritical*	Temperature status of the system.
`tempSensors`	*list of TempSensor* see 2.1966.3.1.1	Temperature sensors on a fixed system.

2.1966.3.1 FruSlot

`entPhysicalClass`	*string*	Physical entity class of the slot.
`relPos`	*string*	Slot relative position.
`tempSensors`	*list of TempSensor* see 2.1966.3.1.1	The temperatures sensors in the card slot.

2.1966.3.1.1 TempSensor

`alertCount`	*integer*	Number of times the alert has been triggered.
`[alertLastChange]`	*floating point number*	Last time the alert status changed in POSIX time.
`chipModel` **	*string*	Temperature sensor vendor model. **Since: 4.34.1
`[coolingDomains]` **	*list of string*	Array of strings representing the cooling domain(s) of the sensor. **Since: 4.34.0
`[criticalThreshold]`	*floating point number*	Configured critical temperature threshold to trigger a system shutdown (in Celsius).

[currentTemperature]	*floating point number*	Current temperature reported by the temperature sensor (in Celsius).
description	*string*	Temperature sensor description.
hwStatus	*enum: failed* | *ok* | *unknownHwStatus* | *disabled* | *invalidReading*	Hardware status reported by the temperature sensor.
inAlertState	*boolean*	Whether the system is in alert state.
isPidDriver **	*boolean*	Whether the sensor is currently the PID driver. **Since: 4.18.0
[lastPidDriverTime] **	*floating point number*	Last time the sensor was the PID driver. **Since: 4.18.0
[maxTemperature]	*floating point number*	Maximum temperature recorded by the temperature sensor (in Celsius).
[maxTemperatureLastChange]	*floating point number*	Last time the maximum temperature recorded by the temperature sensor changed in POSIX time.
name	*string*	Temperature sensor name.
[overheatThreshold]	*floating point number*	Configured temperature threshold to trigger an overheating event (inCelsius).
pidDriverCount **	*integer*	Number of times the sensor has been the PID driver. **Since: 4.18.0
[pidDriverStats] **	*list of floating point number*	Array of PID driver statistics for different time intervals. **Since: 4.34.0
position **	*enum: inlet* | *outlet* | *bidi* | *other*	Physical position of temperature sensor. **Since: 4.34.1
relPos	*string*	Temperature sensor relative position.
[setPointTemperature] **	*floating point number*	Current setpoint temperature used by the temperature sensor (in Celsius). **Since: 4.18.0
[targetTemperature] **	*floating point number*	Configured target temperature used for PID tuning (in Celsius). **Since: 4.18.0

2.1966.4 SystemXcvrTemperature

cardSlots	*list of FruSlot* see 2.1966.3.1	Card slots on a modular system.
tempSensors	*list of TempSensor* see 2.1966.3.1.1	Temperature sensors on a fixed system.

2.1967 show system environment cooling [...]

see 2.1966.1

2.1968 show system environment power

see 2.395

2.1969 show system environment power budget

consumedPower	*floating point number*	Total consumed power in watts.
powerBudget	*floating point number*	Budgeted power in watts.
powerConsumers	*table(string) = PowerConsumer* see 2.1969.1	Devices consuming power.
[powerDomains] **	*table(string) = PowerDomainStatus* see 2.1969.2	Power information per domain, keyed by domain name. **Since: 4.31.0
totalAvailablePower	*floating point number*	Total available power in watts.

2.1969.1 PowerConsumer

amount	*floating point number*	Amount of power the device is consuming in watts.

2.1969.2 PowerDomainStatus

consumedPower	*floating point number*	Consumed power in watts.
totalAvailablePower	*floating point number*	Total available power in watts.

2.1970 show system environment power current

cardSlots	*table(string) = FruSlot* see 2.397.1	A mapping of labels to card slots.
currentSensors	*table(string) = CurrentSensor* see 2.397.1.1	A mapping of labels to current sensors.

2.1971 show system environment power current detail

currentSensorDetails	*table(string) = CurrentSensorDetail* see 2.1971.1	A mapping of labels to current sensor detail.

2.1971.1 CurrentSensorDetail

[faultRecord] **	*table(numeric string) = FaultRecord* see 2.1971.1.1	A mapping of labels to fault records. **Since: 4.34.0
[maxCurrent]	*floating point number*	Measured maximum sensor current (amps).
[maxCurrentTimestamp]	*floating point number*	Timestamp of the maximum sensor current.

name	*string*	The current sensor's hardware label.

2.1971.1.1 FaultRecord

currentRecord	*table(numeric string) = CurrentRecord* see 2.1971.1.1.1	A mapping to current readings.
name	*string*	The sensor's hardware label.
recordId	*integer*	The Id of the fault record.

2.1971.1.1.1 CurrentRecord

timestamp	*floating point number*	Timestamp when the current is read.
value	*floating point number*	Measured current (amps).

2.1972 show system environment power detail

see 2.395

2.1973 show system environment power domain

[powerDomains]	*table(string) = PowerDomain* see 2.1973.1	Power domains, keyed by name.

2.1973.1 PowerDomain

interfaces	*list of Interface name*	List of interfaces in power domain.
powerSupply	*string*	Power supply name.

2.1974 show system environment power histogram

buckets	*table(numeric string) = integer*	Mapping of power ranges (in percent) to uptime (seconds) in the range.
sampleRate	*floating point number*	The rate (in samples per second) at which samples are collected.

2.1975 show system environment power histogram detail

buckets	*table(numeric string) = integer*	Mapping of power ranges (in percent) to uptime (seconds) in the range.
totalPower	*floating point number*	Total system power in watts.

2.1976 show system environment power pmbus

`cardSlots`	*table(string) = FruSlot* see 2.397.1	A mapping of labels to card slots.
`devices`	*table(string) = PmbusDevice* see 2.397.1.2	A mapping of lables to Pmbus devices.

2.1977 show system environment power voltage

revision 2

see 2.397

2.1978 show system environment temperature [...]

see 2.1966.3

2.1979 show system environment temperature pid-drivers

`cardSlots`	*list of FruSlot* see 2.1966.3.1	Card slots on a modular system.
`pollInterval`	*floating point number*	Environment temperature poll-interval.
`powerSupplySlots`	*list of FruSlot* see 2.1966.3.1	Power Supply Slots on the system.
`tempSensors`	*list of TempSensor* see 2.1966.3.1.1	Temperature sensors on a fixed system.

2.1980 show system environment temperature transceiver [...]

see 2.1966.4

2.1981 show system health storage

`devices`	*table(string) = StorageHealth* see 2.1981.1	Storage devices.

2.1981.1 StorageHealth

`[emmc]`	*EmmcLifetime* see 2.1981.1.1	eMMC lifetimes attributes.
`[smart]`	*SmartHealth* see 2.1981.1.2	S.M.A.R.T. health attributes.

2.1981.1.1 EmmcLifetime

[mlcWearLevel]	*floating point number*	MLC region fractional design wear remaining.
[reservesLevel]	*floating point number*	Reserve block fractional level remaining.
[slcWearLevel]	*floating point number*	SLC region fractional design wear remaining.

2.1981.1.2 SmartHealth

[health]	*string*	Overall device health.
[reallocationsRemaining]	*floating point number*	Fractional unused reallocations blocks.
[wearLevel]	*floating point number*	Percent design lifetime wear remaining.

2.1982 show system memory detail

memoryControllers	*table(string) = MemoryControllerDetailModel* see 2.1982.1	Maps a memory controller's name to its channels.

2.1982.1 MemoryControllerDetailModel

channels	*table(string) = ChannelDetailModel* see 2.1982.1.1	Maps a channel to its populated slots.

2.1982.1.1 ChannelDetailModel

slots	*table(string) = DimmDetailModel* see 2.1982.1.1.1	Maps a slot to its associated DIMM information.

2.1982.1.1.1 DimmDetailModel

memSize	*integer*	DIMM's memory size in gigabytes.
memType	*string*	DIMM's memory technology.
[model]	*string*	DIMM's model number.
[serial]	*string*	DIMM's serial number.
[vendor]	*string*	DIMM's manufacturer.

2.1983 show system memory errors

memoryControllers	*table(string) = MemoryControllerErrorsModel* see 2.1983.1	Maps a memory controller's name to its DIMMs.

2.1983.1 MemoryControllerErrorsModel

`dimms`	*table(string) = DimmErrorsModel* see 2.1983.1.1	Maps a DIMM's name to its error counters.

2.1983.1.1 DimmErrorsModel

`correctableErrorCount`	*integer*	Correctable error count for this DIMM.
`uncorrectableErrorCount`	*integer*	Uncorrectable error count for this DIMM.

2.1984 show system storage health

see 2.1981

2.1985 show system storage health smart

`devices`	*table(string) = DeviceSmartAttrs* see 2.1985.1	SMART attributes, keyed by device name.

2.1985.1 DeviceSmartAttrs

`attributes`	*list of SmartAttr* see 2.1985.1.1	SMART attribute list.

2.1985.1.1 SmartAttr

`name`	*string*	SMART attribute name.
`status`	*enum: failed | ok | n/a*	SMART attribute status.
`[unit]`	*string*	Units for value.
`[value]`	*integer*	SMART attribute value.

2.1986 show system storage health smart detail

revision 2

`devices`	*table(string) = DeviceSmartAttrDetails* see 2.1986.1	SMART attributes, keyed by device.

2.1986.1 DeviceSmartAttrDetails

`attributes`	*list of SmartAttrDetail* see 2.1986.1.1	SMART attribute list.

2.1986.1.1 SmartAttrDetail

[id]	*integer*	SMART attribute ID.
name	*string*	SMART attribute name.
[normalized]	*integer*	SMART normalized value.
raw	*integer*	SMART raw value.
[threshold]	*integer*	SMART threshold (lowest acceptable).
[timestamp] **	*floating point number*	time of SMART attribute collection in UTC seconds since epoch. **Since: 4.35.2
[worst]	*integer*	SMART worst normalized value.

2.1987 show system storage statistics

devices	*table(string) = IOStat* see 2.1987.1	Storage devices.

2.1987.1 IOStat

measurementTime **	*floating point number*	Switch time at which last measurement was done. **Since: 4.36.0
measurementTimestamp	*floating point number*	Switch time at which last measurement was done.
measurementType	*enum: total | dayAverage | lastDay | boot*	Type and length of measurement.
read	*integer*	Quantity of bytes read.
write	*integer*	Quantity of bytes written.

2.1988 show system storage statistics last day

see 2.1987

2.1989 show system storage statistics rates

see 2.1987

2.1990 show system systemd [...]

unitsStatus	*table(string) = SystemdUnitStatus* see 2.1990.1	Mapping of a systemd unit to its status.

2.1990.1 SystemdUnitStatus

unitDesc	*string*	Brief description of unit.
unitState	*enum: start-pre* | *unmounting-sigterm* | *stop-post* | *stop-pre-sigkill* | *dead* | *start* | *undefined* | *mounting-sigterm* | *stop* | *reload* | *running* | *auto-restart* | *mounted* | *remounting-sigkill* | *remounting* | *stop-sigabrt* | *stop-sigkill* | *final-sigterm* | *exited* | *unmounting* | *remounting-sigterm* | *stop-sigterm* | *mounting-sigkill* | *mounting-done* | *mounting* | *listening* | *start-chown* | *final-sigkill* | *unmounting-sigkill* | *stop-pre-sigterm* | *failed* | *start-post*	Active state of a systemd unit.

2.1991 show system systemd detail

systemdMounts	*SystemdMountpointsDetail* see 2.1991.1	Systemd aware mount points.
systemdServices	*SystemdServicesDetail* see 2.1991.2	Systemd managed services information.
systemdSockets	*SystemdSocketsDetail* see 2.1991.3	Systemd managed sockets information.

2.1991.1 SystemdMountpointsDetail

systemdMountpointsInfo	*table(string) = SystemdMountpointInfo* see 2.1991.1.1	Mapping of a systemd mount to detailed-description of its state.

2.1991.1.1 SystemdMountpointInfo

fsType	*string*	Filesystem type.
mountDesc	*string*	Mount point description.
mountPath	*string*	Where is the mountpoint.
mountState	*enum: start-pre* | *unmounting-sigterm* | *stop-post* | *stop-pre-sigkill* | *dead* | *start* | *undefined* | *mounting-sigterm* | *stop* | *reload* | *running* | *auto-restart* | *mounted* | *remounting-sigkill* | *remounting* | *stop-sigabrt* | *stop-sigkill* | *final-sigterm* | *exited* | *unmounting* | *remounting-sigterm* | *stop-sigterm* | *mounting-sigkill* | *mounting-done* | *mounting* | *listening* | *start-chown* | *final-sigkill* | *unmounting-sigkill* | *stop-pre-sigterm* | *failed* | *start-post*	Active state of a systemd unit.
[mountTime]	*floating point number*	Timestamp of when unit reached current state.

2.1991.2 SystemdServicesDetail

systemdServicesInfo	*table(string) = SystemdServiceData* see 2.1991.2.1	Mapping of a systemd service unit to de-tailed description of its state.

2.1991.2.1 SystemdServiceData

cgrpName	*string*	Name of with CGroup for system service unit.
cgrpTasks	*table(numeric string) = string*	Mapping of a cgroup process id to its command line.
svcActvState	*enum: start-pre | unmounting-sigterm | stop-post | stop-pre-sigkill | dead | start | undefined | mounting-sigterm | stop | reload | running | auto-restart | mounted | remounting-sigkill | remounting | stop-sigabrt | stop-sigkill | final-sigterm | exited | unmounting | remounting-sigterm | stop-sigterm | mounting-sigkill | mounting-done | mounting | listening | start-chown | final-sigkill | unmounting-sigkill | stop-pre-sigterm | failed | start-post*	Active state of a systemd unit.
svcDesc	*string*	Systemd service short description.
svcPid	*integer*	Process id. Not shown for reloaded SYS-V service.
svcState	*string*	Running/Exited status of service with status code.
[timestamp]	*floating point number*	Timestamp of when unit reached current state.

2.1991.3 SystemdSocketsDetail

systemdSocketsInfo	*table(string) = SystemdSocketInfo* see 2.1991.3.1	Mapping of a systemd socket to detailed-description of its state.

2.1991.3.1 SystemdSocketInfo

sockDesc	*string*	Description of socket.
sockState	*enum: start-pre* | *unmounting-sigterm* | *stop-post* | *stop-pre-sigkill* | *dead* | *start* | *undefined* | *mounting-sigterm* | *stop* | *reload* | *running* | *auto-restart* | *mounted* | *remounting-sigkill* | *remounting* | *stop-sigabrt* | *stop-sigkill* | *final-sigterm* | *exited* | *unmounting* | *remounting-sigterm* | *stop-sigterm* | *mounting-sigkill* | *mounting-done* | *mounting* | *listening* | *start-chown* | *final-sigkill* | *unmounting-sigkill* | *stop-pre-sigterm* | *failed* | *start-post*	Active state of a systemd unit.
sockType	*string*	Type of socket ie., stream/datagram etc.
[timestamp]	*floating point number*	Timestamp of when unit reached current state.

2.1992 show system systemd mountpoints detail

see 2.1991.1

2.1993 show system systemd services detail

see 2.1991.2

2.1994 show system systemd sockets detail

see 2.1991.3

2.1995 show tacacs

[groups]	*table(string) = ServerGroup* see 2.1995.1	Mapping of group name to group information.
lastCounterClearTime	*floating point number*	UTC time when the counters were last cleared.
srcIntf	*table(string) = Interface name*	Configured source-interface name.
tacacsServers	*list of TacacsStats* see 2.1995.2	Mapping of server IP address or hostname to server information.

2.1995.1 ServerGroup

members	*list of ServerInfo* see 2.1995.1.1	Mapping of server IP address or hostname to group information.
serverGroup	*string*	Configured server-group.

2.1995.1.1 ServerInfo

authport	*integer*	Specifies server authorization port number.
hostname	*string*	IP address or hostname of the TACACS+ server.
[sslProfile] **	*string*	SSL profile of the TACACS+ server. **Since: 4.35.2
[tlsEnabled] **	*boolean*	Specifies if TLS is enabled. **Since: 4.35.2
[vrf] **	*string*	The VRF over which this server is reachable. **Since: 4.25.1

2.1995.2 TacacsStats

[certErrors] **	*integer*	Number of connection failures due to certificate issues. **Since: 4.35.2
connectionCloses	*integer*	Number of TCP connection close requests sent to the TACACS+ server.
connectionDisconnects	*integer*	Number of disconnected TCP connections to the TACACS+ server.
connectionFailures	*integer*	Number of failed TCP connections to the TACACS+ server.
connectionOpens	*integer*	Number of new TCP connection requests sent to the TACACS+ server.
connectionTimeouts	*integer*	Number of timed out TCP connections to the TACACS+ server.
dnsErrors **	*integer*	Number of DNS errors by the TACACS+ server. **Since: 4.25.1
messagesReceived	*integer*	Number of packets received from the TACACS+ server.
messagesSent	*integer*	Number of packets sent to the TACACS+ server.

receiveErrors	*integer*	Number of errors received from the TACACS+ server.
receiveTimeouts	*integer*	Number of timeouts received from the TACACS+ server.
sendTimeouts	*integer*	Number of timeouts sent to the TACACS+ server.
serverInfo	*ServerInfo* see 2.1995.1.1	Configured server information.
unknownMandatoryAttr-Failures **	*integer*	Number of unknown mandatory attributes received from the TACACS+ server which failed the authorizations. **Since: 4.29.1
unknownMandatoryAttrIgnored **	*integer*	Number of unknown mandatory attributes received from the TACACS+ server which got ignored. **Since: 4.29.1

2.1996 show tap aggregation counters default-forwarding

interfaces	*table(Interface name) = CounterValue* see 2.1996.1	A mapping from interfaces to counter values.

2.1996.1 CounterValue

byteCount	*integer*	The number of bytes that have been counted.
packetCount	*integer*	The number of packets that have been counted.

2.1997 show tap aggregation counters tunnel termination gre

tunnels	*table(string) = CounterValue* see 2.1996.1	A mapping from TAP tunnels to counter values.

2.1998 show tap aggregation groups [...]

groups	*table(string) = TapAggGroup* see 2.1998.1	Tap-agg groups keyed by group name.

2.1998.1 TapAggGroup

tapPortStatuses	*table(Interface name) = PortStatus* see 2.1998.1.1	Mapping from interface name to a list of theirstatuses and configured policies.
toolPortStatuses	*table(Interface name) = PortStatus* see 2.1998.1.1	Mapping from interface name to a list of theirstatuses.

2.1998.1.1 PortStatus

policies **	*list of string*	List policies by whichthe port is added to the group. **Since: 4.18.1
statuses	*list of string*	List statuses of the interface. Active, Interface status not found, Link down, Link unknown, Lag member, Mirror destination.

2.1999 show tap aggregation groups map TAPPORT [...]

tapPortsMap	*table(Interface name) = MapPropertyList* see 2.1999.1	A mapping from tap to tool ports.

2.1999.1 MapPropertyList

mapPropertyList	*list of MapProperty* see 2.1999.1.1	List of tap/tool map properties.

2.1999.1.1 MapProperty

groupName	*string*	Group Name.
mappedIntfName	*interface name*	Tap/Tool Port Name.
policyName	*string*	PolicyMap/ClassMap Name.

2.2000 show tap aggregation groups map TOOLPORT [...]

toolPortsMap	*table(Interface name) = MapPropertyList* see 2.1999.1	A mapping from tool to tap ports.

2.2001 show tap aggregation nexthop-groups [...]

fecNexthopGroups	*table(string) = FecNexthopGroup* see 2.2001.1	Load balanced nexthop groups keyed by name.
mcgNexthopGroups	*list of McgNexthopGroup* see 2.2001.2	Multicast nexthop groups.

2.2001.1 FecNexthopGroup

members	*list of string*	Nexthop interfaces.
taps	*list of Source* see 2.2001.1.1	Tap interfaces.

2.2001.1.1 Source

policy	*string*	Policy by which traffic is sent, if available.
tap	*string*	Interface which sends traffic to the nexthop group.

2.2001.2 McgNexthopGroup

destinations	*list of Destination* see 2.2001.2.1	Destinations.
taps	*list of Source* see 2.2001.2.2	Tap interfaces.

2.2001.2.1 Destination

chosenIntf	*string*	Interface selected among its members.
nhg	*string*	Nexthop group member of the multicast.

2.2001.2.2 Source

policy	*string*	Policy by which traffic is sent, if available.
tap	*string*	Interface which sends traffic to the nexthop group.

2.2002 show tcpdump

revision 2

sessions	*table(string) = SessionModel* see 2.2002.1	A mapping between session name and session information.

2.2002.1 SessionModel

duration	*integer*	Capture duration (seconds).
enabled	*boolean*	Enabled.
errorMessage	*string*	Error message associated with the session.
interface	*string*	Capture source.
maxFileSize	*integer*	Max file size (millions of bytes).
maxPerPacketCaptureSize	*integer*	Per-packet capture size (bytes).
outputFile	*string*	Output file.
packetCount	*integer*	Packet count.
packetFilter	*string*	Packet filter.
running	*boolean*	Indicates if capture is running.
vrfName	*string*	VRF name.

2.2003 show terminal

length	*integer*	Length of the terminal in rows.
width	*integer*	Width of the terminal in columns.

2.2004 show trace AGENT

configTrace	*list of string*	Trace setting for agent when agent is not running.
[destination]	*string*	File name where trace output goes if not using the standard log file.
execTrace **	*list of string*	Active exec trace settings for agent. **Since: 4.29.2
execTraceStartTime **	*integer*	Time at which the exec trace was initialized. **Since: 4.29.2
execTraceTimeout **	*integer*	Time remaining in exec traces. **Since: 4.29.1
facilities	*table(string) = StateAndLevel* see 2.2004.1	A mapping of facility name to its trace settings.
[facilityNameWidth]	*integer*	Set the width of facility name in the trace output.
[filenameWidth]	*integer*	Set the width of file name in the trace output.
[functionNameWidth]	*integer*	Set the width of function name in the trace output.
showDate	*boolean*	Date in trace messages.
showFacilityName	*boolean*	Facility name in trace messages.
showFileName	*boolean*	File name in trace messages.
showFunctionName	*boolean*	Method name in trace messages.
showLineNumber	*boolean*	Line number in trace messages.
showPid	*boolean*	Pid in trace messages.
showTid	*boolean*	Tid in trace messages.
showTraceTimestamp	*boolean*	Timestamp in trace messages.
showTracelevel	*boolean*	Trace level in trace messages.

2.2004.1 StateAndLevel

levels	*list of string*	List of levels for which tracing has been enabled.

2.2005 show traffic generators status [...]

trafficGenerators	*table(string) = TrafficGenModel* see 2.2005.1	Traffic generators keyed by traffic generator ID.

2.2005.1 TrafficGenModel

active	*boolean*	Traffic Generator active.
destIntf	*list of Interface name*	Destination Interface(s).
enabled	*boolean*	Traffic Generator enabled.
error	*list of string*	Errors causing the generator to be inactive.
[interfaceRate]	*integer*	The destination(s) interface speed, in kbps.
[rate]	*floating point number*	Linerate Traffic Rate.

[recircGenId]	*integer*	Generation ID to determine when packets are to be sent.
[requestedRate]	*integer*	The requested rate, in kbps.
[sourceIntf]	*interface name*	Source Interface.
warning	*list of string*	Warnings for the generator.

2.2006 show traffic-engineering adaptive-virtual-topology area

routerIds	*list of IP address*	List of nodes managed for Adaptive Virtual Topology.

2.2007 show traffic-engineering adaptive-virtual-topology database

nodeRouterIds	*table(IPv4 or IPv6 address) = AvtNode* see 2.2007.1	Database node information keyed by node routerid.

2.2007.1 AvtNode

adjacentRouterIds	*table(IPv4 or IPv6 address) = AvtAdjacency* see 2.2007.1.1	Information about adjacent nodes keyed by routerid.
avtId	*list of integer*	List of AVT identifiers configured on this node.
[isUnderMaintenance] **	*boolean*	Is the node in maintenance mode. **Since: 4.34.1
regionId	*integer*	Region identifier.
role	*enum: region transit | unknown | edge | zone transit | pathfinder*	Role of the node.
siteId	*integer*	Site identifier.
zoneId	*integer*	Zone identifier.

2.2007.1.1 AvtAdjacency

labels	*table(numeric string) = AvtLink* see 2.2007.1.1.1	Information about link keyed by a label.

2.2007.1.1.1 AvtLink

[availableCapacity] **	*integer*	Available capacity in link in Mbps. **Since: 4.32.1
jitter	*floating point number*	Jitter of link in msecs.
latency	*floating point number*	Latency of link in msecs.
[load] **	*floating point number*	Load in link in percentage. **Since: 4.32.1
localWanId	*integer*	Local WAN Identifier.
loss	*floating point number*	Loss in link in percentage.
pathGroupId	*integer*	Path Group Identifier.
[pathMtu]	*integer*	Maximum transmission unit of link in bytes.
peerWanId	*integer*	Peer WAN Identifier.
[totalCapacity] **	*integer*	Total capacity in link in Mbps. **Since: 4.32.1

2.2008 show traffic-engineering adaptive-virtual-topology paths [...]

sourceRouterIds	*table(IPv4 or IPv6 address) = AvtPathsFromSource* see 2.2008.1	Adaptive Virtual Topology paths from source routerId.

2.2008.1 AvtPathsFromSource

avtIds	*table(numeric string) = AvtPathsForAvtId* see 2.2008.1.1	Paths for Application Virtual Topology identifier.

2.2008.1.1 AvtPathsForAvtId

[avt]	*string*	Adaptive Virtual Topology name.
avtId	*integer*	Adaptive Virtual Topology Identifier.
destinationRouterIds	*table(IPv4 or IPv6 address) = AvtPathsForDestination* see 2.2008.1.1.1	Adaptive Virtual Topology paths for destination.
vni	*integer*	VxLAN Network Identifier for VRF.
[vrf]	*string*	VRF name.

2.2008.1.1.1 AvtPathsForDestination

hopStacks	*list of AvtHopStack* see 2.2008.1.1.1.1	List of paths to a destination router.

2.2008.1.1.1.1 AvtHopStack

[availableCapacity] **	*integer*	Available capacity in link in Mbps. **Since: 4.32.1
hops	*list of AvtHop* see 2.2008.1.1.1.2	Represents hops in an Adaptive Virtual Topology path.
[isUnderMaintenance] **	*boolean*	Does the path go through a node under maintenance. **Since: 4.34.1
jitter	*floating point number*	Jitter of path in msecs.
latency	*floating point number*	Latency of path in msecs.
[load] **	*floating point number*	Load in link in percentage. **Since: 4.32.1
loss	*floating point number*	Loss in path in percentage.
[pathMtu]	*integer*	Maximum transmission unit of path in bytes.
[priority]	*integer*	Priority of path.
[state] **	*enum: pathDiscovered | pathAcceptedInAvt | pathAdvertisedToEdge*	State of the entry. **Since: 4.30.2
[totalCapacity] **	*integer*	Total capacity in link in Mbps. **Since: 4.32.1

2.2008.1.1.1.2 AvtHop

[isUnderMaintenance] **	*boolean*	Is the destination of the hop under maintenance. **Since: 4.34.1
label	*integer*	Label for this hop.
localWanId	*integer*	Local WAN Identifier.
node	*IP address*	Router Id of the nexthop node.
pathGroupId	*integer*	Path Group Identifier.
peerWanId	*integer*	Peer WAN Identifier.

2.2009 show traffic-engineering adaptive-virtual-topology paths history [...]

sourceRouterIds	*table(IPv4 or IPv6 address) = AvtPathEventsFromSource* see 2.2009.1	Adaptive Virtual Topology path selection events from source routerId.

2.2009.1 AvtPathEventsFromSource

avtIds	*table(numeric string) = AvtPathEventsForAvtId* see 2.2009.1.1	Path selection events for Application Virtual Topology identifier.

2.2009.1.1 AvtPathEventsForAvtId

[avt]	*string*	Adaptive Virtual Topology name.
avtId	*integer*	Adaptive Virtual Topology Identifier.
destinationRouterIds	*table(IPv4 or IPv6 address) = AvtPathEventsForDestination* see 2.2009.1.1.1	Adaptive Virtual Topology path selection events for destination.
vni	*integer*	VxLAN Network Identifier for VRF.
[vrf]	*string*	VRF name.

2.2009.1.1.1 AvtPathEventsForDestination

pathSelectionEvents	*list of AvtPathSelectionEvent* see 2.2009.1.1.1.1	Path selection events.

2.2009.1.1.1.1 AvtPathSelectionEvent

eventReason	*string*	Reason for this event occurrance.
eventTimestamp	*floating point number*	Event timestamp.
eventType	*enum: added | deleted*	Path selection event type.
generationId	*integer*	Path selection generation ID.
hopLabels	*list of integer*	List of labels that represent an Adaptive Virtual Topology path.

2.2010 show traffic-engineering cbf fec [...]

isCbfModeTc **	*boolean*	CBF mode (TC-based or DSCP-based). **Since: 4.34.2
vrfs	*table(string) = CbfFecModel* see 2.2010.1	Per VRF Traffic Engineering CBF override entries.

2.2010.1 CbfFecModel

isCbfModeTc **	*boolean*	CBF mode (TC-based or DSCP-based). **Since: 4.34.2
overrides	*list of CbfFecOverride* see 2.2010.1.1	CBF FEC override entry.

2.2010.1.1 CbfFecOverride

defaultFecId	*integer*	Default FEC ID.
[dscp]	*integer*	DSCP value.
ipVersion	*enum: ipv4 | ipv6*	IP version.
overrideFecId	*integer*	Overriding SR-TE Policy FEC ID.
[tc] **	*integer*	Traffic class value. **Since: 4.29.0
tunnelType	*enum: BGP LU Forwarding | maxTunnelType | IP-in-IP | MLDP P2MP | invalidTunnel | VXLAN VTEP Encap | IS-IS SRv6 | Nexthop | Static MPLS | SR-TE Policy | SR-TE | OSPF SR | IS-IS SRv6 TI-LFA | IS-IS FlexAlgo | Static MPLS Multicast | Nexthop Group | TI-LFA | LDP | RSVP LER SUB | SRv6 SR-TE SL | RSVP P2MP | RSVP LER | EosSdk sBFD | UDP | SRv6 Transport | EVPN VXLAN | VXLAN | RSVP FRR | IS-IS Remote TI-LFA | BGP LU | RSVP | IS-IS SR | Static Interface*	Tunnel Types.

2.2011 show traffic-engineering cbf mpls [...]

vrfs	*table(string) = Cbf.Cli.CbfMplsModel* see 2.2011.1	Per VRF Traffic Engineering MPLS CBF override LfibVsks entries.

2.2011.1 Cbf.Cli.CbfMplsModel

overrides	*list of Cbf.Cli.CbfMplsOverride* see 2.2011.1.1	MPLS CBF override LfibVsks.

2.2011.1.1 Cbf.Cli.CbfMplsOverride

defaultVias	*list of string*	Tunnel names of default mpls vias.
defaultVskIndex	*integer*	Index of Default LfibVsk.
defaultVskSource	*string*	Source of Default LfibVsk.
[indexId]	*boolean*	Set if specific Default LfibVsk's index is passed.
overrideVias	*list of string*	Tunnel names of override mpls vias.
overrideVskIndex	*integer*	Index of Override LfibVsk.
overrideVskSource	*string*	Source of Override LfibVsk.
status	*enum: labelActionNotSupported* | *hwNotReady* | *hwRequestPending* | *outOfResource* | *fecNotFound* | *programmed* | *unknownStatus*	MPLS CBF override status.
tc	*integer*	Traffic class value.

2.2012 show traffic-engineering cspf path IP_ADDR links

vrfs	*table(string) = CspfPathLinksVrfModel* see 2.2012.1	A mapping between VRF and information of all CSPF paths in that VRF.

2.2012.1 CspfPathLinksVrfModel

[v4Info]	*CspfPathLinksAfModel* see 2.2012.1.1	CSPF path information for IPv4 address family.
[v6Info]	*CspfPathLinksAfModel* see 2.2012.1.1	CSPF path information for IPv6 address family.

2.2012.1.1 CspfPathLinksAfModel

pathIps	*table(IPv4 or IPv6 address) = CspfPathLinksDestIpModel* see 2.2012.1.1.1	A mapping of a destination IP to all CSPF paths for that destination IP.

2.2012.1.1.1 CspfPathLinksDestIpModel

paths	*table(numeric string) = CspfPathLinksEntryModel* see 2.2012.1.1.1.1	A mapping of an id representing a constraint to the corresponding CSPF path.

2.2012.1.1.1.1 CspfPathLinksEntryModel

destinationOnSourceNode	*boolean*	Destination IP address is on the source node.
[links]	*table(numeric string) = CspfPathLinkAttrsModel* see 2.2012.1.1.1.2	TE information of each link in the CSPF path.
status	*enum: pathNotFound | pathNotComputed | cspfPending | explicitPathFailedValidation | pathFound*	Status of path computation.
tunnelName **	*string*	Tunnel Name. **Since: 4.34.1

2.2012.1.1.1.2 CspfPathLinkAttrsModel

found	*boolean*	Link found in topology.
[hopAddress]	*IP address*	Next hop address.
[linkAttributes]	*LinkAttributesModel* see 2.2012.1.1.1.3	Link attributes.

2.2012.1.1.1.3 LinkAttributesModel

[administrativeGroup]	*integer*	Administrative Group of the Link.

[administrativeGroups-Extended] **	*list of integer*	Extended Administrative Groups of the Link. **Since: 4.31.1
destinationIgpRouterId	*string*	Remote IGP Router ID.
destinationTeRouterId	*IP address*	Remote TE Router ID.
[igpMetric] **	*integer*	IGP metric. **Since: 4.35.2
interfaceAddresses	*list of InterfaceAddress* see 2.2012.1.1.1.4	List of local Interface Addresses forming the adjacency.
[maxLinkBw]	*integer*	Maximum bandwidth (bps) that can be used on Directed Link.
[maxReservableBw]	*integer*	Maximum bandwidth (bps) that can be reserved on Directed Link.
[metric]	*integer*	TE Link cost.
neighborAddresses	*list of InterfaceAddress* see 2.2012.1.1.1.4	List of remote Neighbor Addresses forming the adjacency.
networkType	*enum: lan | p2p*	Network type.
[sharedRiskLinkGroups]	*list of SharedRiskLink-GroupWithCost* see 2.2012.1.1.1.6	List of Shared Risk Link Groups.
sourceIgpRouterId	*string*	Local IGP Router ID.
sourceTeRouterId	*IP address*	Local TE Router ID.
topology	*TopologyModel* see 2.2012.1.1.1.7	Topology type information.
[unreservedBw]	*ReservablePriority-Bandwidth* see 2.2012.1.1.1.5	Maximum bandwidth reservable for a priority.

2.2012.1.1.1.4 InterfaceAddress

[ipv4Address]	*IPv4 address*	IPv4 address.
[ipv6Address]	*IPv6 address*	IPv6 address.

2.2012.1.1.1.5 ReservablePriorityBandwidth

priority0	*integer*	Reservable Bandwidth (bps) for priority level 0.
priority1	*integer*	Reservable Bandwidth (bps) for priority level 1.
priority2	*integer*	Reservable Bandwidth (bps) for priority level 2.
priority3	*integer*	Reservable Bandwidth (bps) for priority level 3.
priority4	*integer*	Reservable Bandwidth (bps) for priority level 4.
priority5	*integer*	Reservable Bandwidth (bps) for priority level 5.
priority6	*integer*	Reservable Bandwidth (bps) for priority level 6.
priority7	*integer*	Reservable Bandwidth (bps) for priority level 7.

2.2012.1.1.1.6 SharedRiskLinkGroupWithCost

cost	*integer*	Cost of SRLG Group.
groupId	*integer*	Shared Risk Link Group Identifier.
[groupName]	*string*	Shared Risk Link Group Name.

2.2012.1.1.1.7 TopologyModel

[isis]	*IsisTopologyInfoModel* see 2.2012.1.1.1.8	IS-IS topology information.
[ospf]	*OspfTopologyInfoModel* see 2.2012.1.1.1.9	OSPF topology information.

2.2012.1.1.1.8 IsisTopologyInfoModel

level	*integer*	IS-IS level.

2.2012.1.1.1.9 OspfTopologyInfoModel

areaId	*IPv4 address*	OSPF area ID.
instanceId	*integer*	OSPF instance ID.
version	*integer*	OSPF version.

2.2013 show traffic-engineering cspf path PATH_ID [...]

vrfs	*table(string) = CspfPathByIdVrfModel* see 2.2013.1	A mapping between Vrf and information of all CSPF paths in that vrf.

2.2013.1 CspfPathByIdVrfModel

[v4Info]	*CspfPathByIdEntryModel* see 2.2013.1.1	CSPF path information for IPv4 address family.
[v6Info]	*CspfPathByIdEntryModel* see 2.2013.1.1	CSPF path information for IPv6 address family.

2.2013.1.1 CspfPathByIdEntryModel

constraint	*CspfPathConstraintModel* see 2.2013.1.1.1	Path constraint.
[details]	*Details* see 2.2013.1.1.3	Detailed path information.
[dstAddr]	*IP address*	Address for destination.
hops	*list of CspfPathHopModel* see 2.2013.1.1.2	Hops specifying the path to the destination.
[pathId]	*integer*	Path ID.
[selfIncludeIps] **	*list of IP address*	Include IPs corresponding to self loops on the source node. **Since: 4.35.0
status	*enum: pathNotFound | pathNotComputed | cspfPending | explicitPathFailedValidation | pathFound*	Status of path computation.
tunnelName **	*string*	Tunnel Name. **Since: 4.34.1

2.2013.1.1.1 CspfPathConstraintModel

[bandwidth]	*integer*	Bandwidth reserved for this path in bits per second.
[bwSetupPriority]	*integer*	Priority of bandwidth reservation request.
[excludeAdminGroup]	*integer*	Admin Group excluded.
[excludeAdminGroups-Extended] **	*list of integer*	Extended Admin Groups excluded. **Since: 4.31.1
[excludeIntf]	*interface name*	Interface excluded from this path.
[excludeLinksWithAddress]	*list of IP address*	Addresses of links excluded.
[excludeNode]	*string*	Node excluded from this path.
[excludeSrlgOfIntf]	*IntfSrlg* see 2.776.1.1.1.7	SRLG excluded of interface.
[excludeSrlgOfPaths] **	*list of CspfPathHelperModel* see 2.2013.1.1.1.2	List of all paths whose SRLGs to be excluded. **Since: 4.25.1
[explicitPath]	*list of IP address*	Complete list of hops making up this path.
[includeAllAdminGroup]	*integer*	Admin Group included.

[includeAllAdminGroups-Extended] **	*list of integer*	Extended Admin Groups included. **Since: 4.31.1
[includeAnyAdminGroup]	*integer*	Any Admin Group included.
[includeAnyAdminGroups-Extended] **	*list of integer*	Any Extended Admin Groups included. **Since: 4.31.1
[includeHops]	*list of CspfIncludeHopModel* see 2.2013.1.1.1.1	Nodes or links included in this path.
[sharedBwGroupId]	*integer*	Shared bandwidth group ID.

2.2013.1.1.1.1 CspfIncludeHopModel

hop	*IP address*	Interface address or TE Router ID of the hop.
loose	*boolean*	The include hop constraint is loose.

2.2013.1.1.1.2 CspfPathHelperModel

destination	*IP address*	Destination address.
pathId	*integer*	Path index.
[srlgIds]	*list of integer*	List of SRLG IDs for the path.

2.2013.1.1.2 CspfPathHopModel

[includeIps]	*list of IP address*	Non-ingress IP addresses in includeHop constraint corresponding to teRouterId.
ipAddr	*IP address*	Interface IP address.
teRouterId	*IP address*	TE Router ID.

2.2013.1.1.3 Details

autoUpdate	*boolean*	Automatically re-optimize the path.
[bwLocallyAccounted]	*boolean*	Bandwidth is locally accounted as reserved.
[changeCount]	*integer*	Number of times path updated.
[lastUpdatedTime]	*floating point number*	UTC timestamp of the last path update.
refreshReqSeq	*integer*	Request sequence number.
[refreshRespSeq]	*integer*	Response sequence number.

2.2014 show traffic-engineering cspf path PATH_ID links

vrfs	*table(string) = CspfPathBy-IdLinksVrfModel* see 2.2014.1	A mapping between VRF and information of all CSPF paths in that VRF.

2.2014.1 CspfPathByIdLinksVrfModel

[v4Info]	*CspfPathByIdLinksAfModel* see 2.2014.1.1	CSPF path information for IPv4 address family.
[v6Info]	*CspfPathByIdLinksAfModel* see 2.2014.1.1	CSPF path information for IPv6 address family.

2.2014.1.1 CspfPathByIdLinksAfModel

destinationOnSourceNode	*boolean*	Destination IP address is on the source node.
dstAddr	*IP address*	Address for destination.
[links]	*table(numeric string) = CspfPathLinkAttrsModel* see 2.2012.1.1.1.2	TE information of each link in the CSPF path.
pathId	*integer*	Path ID.
status	*enum: pathNotFound | pathNotComputed | cspfPending | explicitPathFailedValidation | pathFound*	Status of path computation.
tunnelName **	*string*	Tunnel Name. **Since: 4.34.1

2.2015 show traffic-engineering cspf path [...]

revision 2

vrfs	*table(string) = CspfPathVrfModel* see 2.2015.1	A mapping between Vrf and information of all CSPF paths in that vrf.

2.2015.1 CspfPathVrfModel

[v4Info]	*CspfPathAfModel* see 2.2015.1.1	CSPF P2MP path information for IPv4 address family.
[v6Info]	*CspfPathAfModel* see 2.2015.1.1	CSPF P2MP path information for IPv6 address family.

2.2015.1.1 CspfPathAfModel

pathIps	*table(IPv4 or IPv6 address) = CspfPathDestIpModel* see 2.2015.1.1.1	A mapping of a destination IP to all CSPF paths for that destination IP.

2.2015.1.1.1 CspfPathDestIpModel

paths	*table(numeric string) = CspfPathEntryModel* see 2.2015.1.1.1.1	A mapping of an id representing a constraint to the corresponding CSPF path.

2.2015.1.1.1.1 CspfPathEntryModel

constraint	*CspfPathConstraintModel* see 2.2013.1.1.1	Path constraint.
[details]	*Details* see 2.2015.1.1.1.2	Detailed path information.
hops	*list of CspfPathHopModel* see 2.2013.1.1.2	Hops specifying the path to the destination.
[selfIncludeIps] **	*list of IP address*	Include IPs corresponding to self loops on the source node. **Since: 4.35.0
status	*enum: pathNotFound | pathNotComputed | cspfPending | explicitPathFailedValidation | pathFound*	Status of path computation.
tunnelName **	*string*	Tunnel Name. **Since: 4.34.1

2.2015.1.1.1.2 Details

autoUpdate	*boolean*	Automatically re-optimize the path.
[bwLocallyAccounted] **	*boolean*	Bandwidth is locally accounted as reserved. **Since: 4.28.1
[changeCount]	*integer*	Number of times path updated.

[lastUpdatedTime]	*floating point number*	UTC timestamp of the last path update.
refreshReqSeq	*integer*	Request sequence number.
[refreshRespSeq]	*integer*	Response sequence number.

2.2016 show traffic-engineering cspf path p2mp [...]

vrfs	*table(string) = CspfPathVrfP2mpModel* see 2.2016.1	A mapping between Vrf and information of all CSPF P2MP paths in that vrf.

2.2016.1 CspfPathVrfP2mpModel

[v4Info]	*CspfPathAfP2mpModel* see 2.2016.1.1	CSPF P2MP path information for IPv4 address family.
[v6Info]	*CspfPathAfP2mpModel* see 2.2016.1.1	CSPF P2MP path information for IPv6 address family.

2.2016.1.1 CspfPathAfP2mpModel

trees	*table(numeric string) = CspfPathTreeModel* see 2.2016.1.1.1	A mapping of a tree ID to all CSPF P2MP trees with that tree ID.

2.2016.1.1.1 CspfPathTreeModel

[details]	*Details* see 2.2016.1.1.1.6	Detailed path information.
leafPaths	*table(IPv4 or IPv6 address) = CspfLeafPathModel* see 2.2016.1.1.1.1	A mapping of a destination IP to all CSPF leaf paths for that destination IP.
tunnelName **	*string*	Tunnel Name. **Since: 4.34.1

2.2016.1.1.1.1 CspfLeafPathModel

[details]	*Details* see 2.2016.1.1.1.2	Detailed path information.
hops	*list of CspfPathHopModel* see 2.2013.1.1.2	Hops specifying the path to the destination.
[selfIncludeIps] **	*list of IP address*	Include IPs corresponding to self loops on the source node. **Since: 4.35.0
status	*enum: pathNotFound | pathNotComputed | cspfPending | explicitPathFailedValidation | pathFound*	Status of path computation.

2.2016.1.1.1.2 Details

constraint	*CspfLeafPathConstraintModel* see 2.2016.1.1.1.3	Path constraint.
lastUpdatedTime	*floating point number*	UTC timestamp of the last path update.
pathChangeCount	*integer*	Number of times path updated.

[pathNotFoundReason]	*PathNotFoundReasonModel* see 2.2016.1.1.1.5	Reason why path is not found.

2.2016.1.1.1.3 CspfLeafPathConstraintModel

[explictPath]	*list of CspfExplicitHopModel* see 2.2016.1.1.1.4	Nodes or links included in this path.

2.2016.1.1.1.4 CspfExplicitHopModel

hop	*IP address*	Interface address or TE Router ID of the hop.
node	*boolean*	The include hop constraint is a node.

2.2016.1.1.1.5 PathNotFoundReasonModel

[details]	*string*	Additional data on the reason why path is not found.
reason	*enum: includeHop-ConfiguredInDynamicTree* | *none* | *remerge*	The reason why path is not found.

2.2016.1.1.1.6 Details

constraint	*CspfPathTreeConstraint-Model* see 2.2016.1.1.1.7	Path constraint.
explicitRefreshReqSeq	*integer*	Reoptimization request sequence number.
pendingExplicitRespSeq	*boolean*	Reoptimization response sequence number is pending.
pendingRefreshRespSeq	*boolean*	Configuration response sequence number is pending.
refreshReqSeq	*integer*	Configuration request sequence number.
treePathChangeCount	*integer*	Number of times tree's hops updated.

2.2016.1.1.1.7 CspfPathTreeConstraintModel

[excludeAdminGroup]	*integer*	Admin Group excluded.
[excludeAdminGroups-Extended]	*list of integer*	Extended Admin Groups excluded.
explicitPath	*boolean*	Every hop in the tree must be specified.
[includeAllAdminGroup]	*integer*	Admin Group included.
[includeAllAdminGroups-Extended]	*list of integer*	Extended Admin Groups included.
[includeAnyAdminGroup]	*integer*	Any Admin Group included.
[includeAnyAdminGroups-Extended]	*list of integer*	Any Extended Admin Groups included.

2.2017 show traffic-engineering cspf path p2mp tunnel-name TUNNEL_NAME [...]

see 2.2016

2.2018 show traffic-engineering cspf path tunnel-name TUNNEL_NAME [...]

revision 2

see 2.2015

2.2019 show traffic-engineering cspf path tunnel-name TUNNEL_NAME links

see 2.2012

2.2020 show traffic-engineering database

revision 2

vrfs	*table(string)* = *TeVrfDbModel* see 2.2020.1	TE DB information per vrf.

2.2020.1 TeVrfDbModel

[ipv4]	*TeAfDbModel* see 2.2020.1.1	TE DB information for IPv4 address family.
[ipv6]	*TeAfDbModel* see 2.2020.1.1	TE DB information for IPv6 address family.

2.2020.1.1 TeAfDbModel

teRouterIds	*table(string)* = *TeRouterDbModel* see 2.2020.1.1.1	TE DB information per TE Router ID.

2.2020.1.1.1 TeRouterDbModel

igps	*table(string)* = *IgpInstanceInfoModel* see 2.2020.1.1.1.1	A mapping of the IGP name to the IGP information.

2.2020.1.1.1.1 IgpInstanceInfoModel

instances	*table(numeric string)* = *IgpModel* see 2.2020.1.1.1.2	A mapping of the IGP instance ID to the IGP database.

2.2020.1.1.1.2 IgpModel

areas	*table(IPv4 address)* = *TeSourceProtocolDbModel* see 2.2020.1.1.1.3	A mapping of the OSPF area ID to the area's TE database information.
levels	*table(numeric string)* = *TeSourceProtocolDbModel* see 2.2020.1.1.1.3	A mapping of the IS-IS level to the corresponding IS-IS TE database.

2.2020.1.1.1.3 TeSourceProtocolDbModel

routers	*table(string)* = *RouterInfoModel* see 2.2020.1.1.1.4	Protcol specific router information.

2.2020.1.1.1.4 RouterInfoModel

[lan]	*TeLinksModel* see 2.2020.1.1.1.5	TE DB information for LAN links.
numLinks	*integer*	Number of links.

[overload] **	*boolean*	IS-IS overload bit. **Since: 4.33.2
[p2p]	*TeLinksModel* see 2.2020.1.1.1.5	TE DB information for P2P links.
[reachabilities] **	*list of IP address prefix*	IP reachability prefixes. **Since: 4.35.0

2.2020.1.1.1.5 TeLinksModel

links	*list of NgbTeInfoModel* see 2.2020.1.1.1.6	TE information of each neighboring link.

2.2020.1.1.1.6 NgbTeInfoModel

[administrativeGroup]	*integer*	Administrative Group of the Link.
[administrativeGroups-Extended] **	*list of integer*	Extended Administrative Groups of the Link. **Since: 4.31.1
[igpMetric] **	*integer*	IGP metric. **Since: 4.35.2
interfaceAddresses	*list of InterfaceAddress* see 2.2012.1.1.1.4	List of local Interface Addresses forming the adjacency.
[localLinkId] **	*integer*	Local link ID. **Since: 4.36.0
[maxLinkBw]	*integer*	Maximum bandwidth (bps) that can be usedon Directed Link.
[maxReservableBw]	*integer*	Maximum bandwidth (bps) that can bereserved on Directed Link.
[metric]	*integer*	TE Link cost.
[neighborAddresses]	*list of InterfaceAddress* see 2.2012.1.1.1.4	List of remote Neighbor Addresses forming the adjacency.
neighborId	*string*	Neighbor Protocol ID.
[remoteLinkId] **	*integer*	Remote link ID. **Since: 4.36.0
[sharedRiskLinkGroups]	*list of SharedRiskLinkGroup* see 2.2020.1.1.1.7	List of Shared Risk Link Group.
[unreservedBw]	*ReservablePriority-Bandwidth* see 2.2012.1.1.1.5	Maximum bandwidth reservable for a priority.

2.2020.1.1.1.7 SharedRiskLinkGroup

Could also be an instance of:
SharedRiskLinkGroupWithCost 2.2012.1.1.1.6

groupId	*integer*	Shared Risk Link Group Identifier.
[groupName]	*string*	Shared Risk Link Group Name.

2.2021 show traffic-engineering database duplicate interface-address

intfIps	*table(IPv4 or IPv6 address) = InterfaceIpInfoModel* see 2.2021.1	TE information of each duplicate interface IP.

2.2021.1 InterfaceIpInfoModel

teRouterIds	*list of IP address*	TE RouterIds of the routers originating the IP address.

2.2022 show traffic-engineering database router-id IP

revision 2

see 2.2020

2.2023 show traffic-engineering gribi ipv4-aft [...]

vrfs	*table(string) = GribiIpAft* see 2.2023.1	IP AFT entries per VRF.

2.2023.1 GribiIpAft

prefixes	*table(IPv4 or IPv6 address prefix) = GribiIpAftEntry* see 2.2023.1.1	AFT entries keyed by prefix.

2.2023.1.1 GribiIpAftEntry

[fibAckAcknowledged] **	*AcknowledgementRouteVersionId* see 2.2023.1.1.1	Acknowledged FIB-ACK route version ID. **Since: 4.28.2
[fibAckRequested] **	*AcknowledgementRouteVersionId* see 2.2023.1.1.1	Requested FIB-ACK route version ID. **Since: 4.27.1
[metadata] **	*string*	Metadata. **Since: 4.27.1
nhgId	*integer*	Nexthop Group ID.
prefix	*IP address prefix*	Prefix.

2.2023.1.1.1 AcknowledgementRouteVersionId

failed **	*boolean*	Route failed installation in hardware. **Since: 4.28.2
requestedDelete	*boolean*	Route due to be deleted.
versionId	*integer*	Route version ID to be acknowledged.

2.2024 show traffic-engineering gribi ipv4-aft failed [...]

see 2.2023

2.2025 show traffic-engineering gribi ipv4-aft unacknowledged [...]

vrfs	*table(string) = GribiPendingIpAft* see 2.2025.1	Unacknowledged AFT entries per VRF.

2.2025.1 GribiPendingIpAft

unacknowledgedPrefixes	*table(string) = GribiIpAftVersionType* see 2.2025.1.1	Map of versioned Route AFT entries, keyed by Prefix.

2.2025.1.1 GribiIpAftVersionType

ipVersionAft	*table(numeric string) = GribiIpAftEntry* see 2.2023.1.1	Map of Route AFT entries, keyed by version ID.

2.2026 show traffic-engineering gribi ipv6-aft [...]

see 2.2023

2.2027 show traffic-engineering gribi ipv6-aft failed [...]

see 2.2023

2.2028 show traffic-engineering gribi ipv6-aft unacknowledged [...]

see 2.2025

2.2029 show traffic-engineering gribi mpls-aft [...]

mplsAft	*table(numeric string) = GribiMplsAftType* see 2.2029.1	Map of MPLS AFT entries, keyed by Label.

2.2029.1 GribiMplsAftType

label	*integer*	Label.
[mplsAftDetail]	*GribiMplsAftDetail* see 2.2029.1.1	gRIBI MPLS AFT detail.
nhgId	*integer*	Nexthop Group ID.

2.2029.1.1 GribiMplsAftDetail

[fecDetail]	*GribiFecDetail* see 2.2029.1.1.1	gRIBI FEC detail.

2.2029.1.1.1 GribiFecDetail

fecId	*integer*	FEC ID.
[fecVias]	*list of GribiFecVia* see 2.2029.1.1.1.1	List of FEC vias.

2.2029.1.1.1.1 GribiFecVia

[mplsVias]	*list of SrTeSegmentListVia* see 2.2029.1.1.1.2	Segment Routing Traffic Engineering policy information.
tunnelIdx	*integer*	Tunnel index.
[weight]	*integer*	Weight of the nexthop.

2.2029.1.1.1.2 SrTeSegmentListVia

interface	*interface name*	Egress L3 interface of the next hop.
[mplsLabels]	*list of integer*	MPLS label stack.
nexthop	*IP address*	Next hop IP address.

2.2030 show traffic-engineering gribi nexthop-aft [...]

revision 2

nhAft	*table(numeric string) = GribiNhAftType* see 2.2030.1	Map of Nexthop AFT entries, keyed by Nexthop ID.

2.2030.1 GribiNhAftType

[decapActionType]	*ipip*	Decapsulation type.
[encapActionType]	*ipip*	Encapsulation type.
[encapHeaderList] **	*list of GribiEncapHeader* see 2.2030.1.1	Encapsulation header list. **Since: 4.33.2
[interface]	*interface name*	Next hop interface.
[ipAddress]	*IP address*	Next hop address.
[ipInIpEncap]	*GribiIpInIpEncap* see 2.2030.1.2	IpInIp Encapsulation.
[macAddress]	*MAC address*	Next hop MAC address.
[nhAftDetail]	*GribiNhAftDetail* see 2.2030.1.3	gRIBI Nexthop AFT detail.
nhId	*integer*	Nexthop ID.
pushMplsLabels	*list of integer*	Push MPLS Label Stack Data for MPLS encap only.
[vrf]	*string*	VRF name.

2.2030.1.1 GribiEncapHeader

encapType	*enum: mpls | udp*	Encapsulation header type.
[mpls]	*GribiMplsEncap* see 2.2030.1.1.1	MPLS encap header.
[udp]	*GribiUdpEncap* see 2.2030.1.1.2	UDP encap header.

2.2030.1.1.1 GribiMplsEncap

[pushMplsLabels]	*list of integer*	Push MPLS Label Stack Data.

2.2030.1.1.2 GribiUdpEncap

[dscp]	*integer*	IP DSCP.
dstIp	*IP address*	Destination address.
[dstPort]	*integer*	Destination UDP port.
[ipTtl]	*integer*	IP TTL.
srcIp	*IP address*	Source address.
[srcPort]	*integer*	Source UDP port.

2.2030.1.2 GribiIpInIpEncap

dstIp	*IP address*	Destination address.
srcIp	*IP address*	Source address.

2.2030.1.3 GribiNhAftDetail

[tunnelDetail]	*GribiFecVia* see 2.2029.1.1.1.1	Tunnel detail.

2.2031 show traffic-engineering gribi nexthop-aft unacknowledged [...]

unacknowledgedNhs	*table(numeric string) = GribiNhAftVersionType* see 2.2031.1	Map of versioned Nexthop AFT entries, keyed by Nexthop ID.

2.2031.1 GribiNhAftVersionType

nhVersionAft	*table(numeric string) = GribiNhAftType* see 2.2030.1	Map of Nexthop AFT entries, keyed by versionId.

2.2032 show traffic-engineering gribi nexthop-group-aft [...]

details_	*boolean*	gRIBI Nexthop Group AFT Detail.
nhgAft	*table(numeric string) = GribiNhgAftType* see 2.2032.1	Map of Nexthop Group AFT entries, keyed by Nexthop Group ID.

2.2032.1 GribiNhgAftType

[backupNhgId] **	*integer*	Backup nexthop group ID. **Since: 4.28.1
[fecId]	*integer*	FEC ID.
[fibAckAcknowledged] **	*AcknowledgementFecVersionId* see 2.2032.1.1	Acknowledged FIB-ACK FEC version ID. **Since: 4.28.0
[fibAckRequested] **	*AcknowledgementFecVersionId* see 2.2032.1.1	Requested FIB-ACK FEC version ID. **Since: 4.27.2
nhgId	*integer*	Nexthop Group ID.
[nhgName] **	*string*	Nexthop Group name. **Since: 4.33.2
nhgNhs	*list of GribiNhgNhAftType* see 2.2032.1.2	List of nexthops in a Nexthop Group AFT entry.

2.2032.1.1 AcknowledgementFecVersionId

failed **	*boolean*	FEC install failed. **Since: 4.28.2
requestedDelete	*boolean*	FEC due to be deleted.
versionId	*integer*	FEC version ID to be acknowledged.

2.2032.1.2 GribiNhgNhAftType

[decapActionType] **	*ipip*	Decapsulation type. **Since: 4.28.1
[encapActionType] **	*ipip*	Encapsulation type. **Since: 4.28.1
[encapHeaderList] **	*list of GribiEncapHeader* see 2.2030.1.1	Encapsulation header list. **Since: 4.33.2
[fallbackVrf] **	*string*	Fallback VRF name. **Since: 4.28.1
[interface] **	*interface name*	Next hop interface. **Since: 4.26.2
[ipAddress] **	*IP address*	Next hop address. **Since: 4.26.2
[ipInIpEncap] **	*GribiIpInIpEncap* see 2.2030.1.2	IPv4 or IPv6 in IP encapsulation. **Since: 4.28.1
[macAddress] **	*MAC address*	Next hop MAC address. **Since: 4.28.1
[mplsVias]	*list of SrTeSegmentListVia* see 2.2029.1.1.1.2	Segment Routing Traffic Engineering policy information.
nhId	*integer*	Nexthop ID.

weight	*integer*	Weight of the nexthop.

2.2033 show traffic-engineering gribi nexthop-group-aft failed [...]

see 2.2032

2.2034 show traffic-engineering gribi nexthop-group-aft unacknowledged [...]

details_	*boolean*	gRIBI Nexthop Group AFT Detail.
unacknowledgedNhgs	*table(numeric string) = GribiNhgAftVersionType* see 2.2034.1	Map of versioned Nexthop Group AFT entries, keyed by Nexthop Group ID.

2.2034.1 GribiNhgAftVersionType

nhgVersionAft	*table(numeric string) = GribiNhgAftType* see 2.2032.1	Map of Nexthop Group AFT entries, keyed by version ID.

2.2035 show traffic-engineering interfaces [...]

interfaces	*list of TeIntfModel* see 2.2035.1	List of interfaces.

2.2035.1 TeIntfModel

adjSids	*list of AdjSid* see 2.2035.1.1	List of Adjacency SIDs.
adminGroup	*integer*	Administrative groups.
adminGroupNames **	*list of string*	List of Administrative group names. **Since: 4.27.1
adminGroupsExtended **	*list of integer*	Extended administrative groups. **Since: 4.31.1
delay	*TeDelay* see 2.2035.1.4	Delay parameters.
intf	*interface name*	Interface.
maxResvBw	*TeMaxResvBw* see 2.2035.1.5	Max reservable bandwidth.
metric	*integer*	Traffic engineering metric.
nodeSids	*list of NodeSid* see 2.2035.1.3	List of Node SIDs.
srlg	*list of IntfSrlg* see 2.2035.1.2	List of Shared Risk Link Groups.

2.2035.1.1 AdjSid

index	*integer*	Index of the Segment Identifier.
isIpV6	*boolean*	SID is IPv6.
isValue	*boolean*	Index is a value.

2.2035.1.2 IntfSrlg

gid	*integer*	Shared Risk Link Group identifier.
name	*string*	Shared Risk Link Group name.

2.2035.1.3 NodeSid

flexAlgoName	*string*	Algorithm Name.
index	*integer*	Index of the Segment Identifier.
isIpV6	*boolean*	SID is IPv6.

2.2035.1.4 TeDelay

[dynamicDelayType] **	*enum: measured | fallback*	Dynamic min delay value category. **Since: 4.32.1
style	*enum: static | twamp | dynamic*	Method for determining the delay.
units	*enum: microseconds | milliseconds*	Delay units.

value	*integer*	Interface delay.

2.2035.1.5 TeMaxResvBw

bwUnitType	*enum: percent | mbps | gbps*	Bandwidth units.
value	*integer*	Bandwidth.

2.2036 show traffic-engineering interfaces bandwidth [...]

interfaces	*table(Interface name) = TeInterfaceBwModel* see 2.2036.1	Dictionary of interface bandwidth statistics.
threshold	*integer*	IGP unreserved bandwidth update threshold in percentage.

2.2036.1 TeInterfaceBwModel

advertisedUnreserved-Bandwidths	*table(string) = BandwidthAdByIgp* see 2.2036.1.1	Dictionary of advertised unreserved bandwidth by IGP.
maxBandwidth	*integer*	Interface maximum bandwidth in bps.
maxReservableBandwidth	*integer*	Interface maximum reservable bandwidth in bps.
unreservedBandwidths	*table(numeric string) = integer*	Current unreserved bandwidth for each priority.

2.2036.1.1 BandwidthAdByIgp

bandwidthsInEachLevelOrArea	*table(numeric string) = AdvertisedBwOfPriority-Classes* see 2.2036.1.1.1	Dictionary of advertised unreserved bandwidth in each IGP level or area.
instanceName	*string*	IGP Instance name.

2.2036.1.1.1 AdvertisedBwOfPriorityClasses

bandwidths	*table(numeric string) = integer*	Advertised unreserved bandwidth for each priotiy in bps.

2.2037 show traffic-engineering rsvp

autoBwSupported **	*boolean*	Is auto bandwidth supported. **Since: 4.25.1
localIntf	*interface name*	Local interface.
localIntfConfigured **	*boolean*	Is the local interface configured. **Since: 4.30.2
localIntfIp	*IP address*	Local interface IP address.
lspCount	*integer*	Number of P2P LSPs.
lspUpCount	*integer*	Number of P2P LSPs that are up.
optimizationInterval **	*integer*	Optimization interval value in seconds. **Since: 4.25.1
p2mpLspCount **	*integer*	Number of P2MP LSPs. **Since: 4.32.1
p2mpLspUpCount **	*integer*	Number of P2MP LSPs that are up. **Since: 4.32.1
p2mpSubLspCount **	*integer*	Number of P2MP sub-LSPs. **Since: 4.33.0
p2mpSubLspUpCount **	*integer*	Number of P2MP sub-LSPs that are up. **Since: 4.33.0
p2mpTunnelCount **	*integer*	Number of P2MP tunnels. **Since: 4.32.1
p2mpTunnelUpCount **	*integer*	Number of P2MP tunnels that are up. **Since: 4.32.1
[splitBwTunnelCount] **	*integer*	Number of tunnels with split bandwidth configured. **Since: 4.26.2
[subTunnelCount] **	*integer*	Number of sub tunnels. **Since: 4.26.2
[subTunnelSecondaryInUse-Count] **	*integer*	Number of sub tunnels with secondary path in use. **Since: 4.26.2
[subTunnelUpCount] **	*integer*	Number of sub tunnels that are up. **Since: 4.26.2
tunnelCount	*integer*	Number of P2P tunnels.
tunnelSecondaryEnabledCount	*integer*	Number of tunnels with secondary path configured.
tunnelSecondaryInUseCount	*integer*	Number of tunnels with secondary path in use.
tunnelUpCount	*integer*	Number of P2P tunnels that are up.

2.2038 show traffic-engineering rsvp tunnel [...]

tunnels	*table(string) = RsvpLerTunnel* see 2.2038.1	Table of tunnel information keyed by tunnel name.

2.2038.1 RsvpLerTunnel

activePathType	*enum: split | unknown | secondary | primary*	Active path type.
[aliasTeps] **	*list of IP address*	Tunnel endpoint aliases. **Since: 4.26.0
autoBandwidth	*boolean*	Bandwidth is automatically determined.
[autoBandwidthParams]	*RsvpLerAutoBandwidthParams* see 2.2038.1.1	Parameters for tuning automagic bandwidth determination.
[color] **	*integer*	Tunnel color. **Since: 4.26.0
[configSource] **	*enum: unknown | frrBypass | default | mvpn | cli*	Tunnel configuration source. **Since: 4.30.2
currentBandwidth	*integer*	Currently reserved bandwidth in bps.
destination	*IP address*	Destination address.
[frrMode] **	*enum: linkProtection | nodeProtection | none*	Fast re-route mode. **Since: 4.35.2
[holdPriority]	*integer*	Hold priority.
[igpShortcut] **	*boolean*	Tunnel eligible to be used for IGP shortcuts. **Since: 4.25.1
[ldpTunneling] **	*boolean*	Tunnel eligible to be used for LDP tunneling. **Since: 4.25.1
[ldpTunnelingUcmp] **	*boolean*	UCMP enabled on tunnel for LDP tunneling. **Since: 4.26.2
lspCount	*integer*	Number of LSPs in this tunnel.
[lspIds] **	*list of integer*	LSP IDs in this tunnel. **Since: 4.31.2
[lsps]	*list of RsvpLerLsp* see 2.2038.1.3	P2P LSPs part of this tunnel.
mbb	*boolean*	Tunnel is getting re-established with make-before-break.
metric **	*integer*	Tunnel metric. **Since: 4.26.2
metricMode **	*enum: static | dynamic*	Tunnel metric mode. **Since: 4.30.0
[mtuSignalingEnabled]	*boolean*	MTU Signaling is enabled.
[optimizationInterval] **	*integer*	Optimization interval value in seconds. **Since: 4.25.1
[p2mpId] **	*integer*	P2MP ID in case of a P2MP tunnel. **Since: 4.32.1
[p2mpLsps] **	*list of RsvpLerP2mpLsp* see 2.2038.1.4	P2MP LSPs part of this tunnel. **Since: 4.33.2

[primaryPath]	*RsvpLerTunnelPath* see 2.2038.1.6.1	Primary path information (P2P).
[primaryTree] **	*RsvpLerTunnelTree* see 2.2038.1.7	Primary tree information (P2MP). **Since: 4.32.1
[profile] **	*string*	Tunnel profile name. **Since: 4.29.2
[profileState] **	*enum: applied | wrongType | notSpecified | notFound*	Tunnel profile state. **Since: 4.35.2
requestedBandwidth	*integer*	Requested bandwidth in bps.
[secondaryPaths]	*list of RsvpLerTunnelPath* see 2.2038.1.6.1	Secondary paths information (P2P).
[sessionId] **	*integer*	Session ID associated with this tunnel. **Since: 4.25.1
[setupPriority]	*integer*	Setup priority.
[signalBandwidth] **	*boolean*	Bandwidth is signaled. **Since: 4.26.2
source	*IP address*	Destination address.
splitTunnel **	*boolean*	Tunnel has split-tunnel enabled. **Since: 4.26.2
[splitTunnelParams] **	*RsvpLerSplitTunnelParams* see 2.2038.1.5	Parameters for split tunnel. **Since: 4.26.2
state	*enum: down | up | unknown*	Tunnel state.
[subTunnels] **	*table(numeric string) = RsvpLerSubTunnel* see 2.2038.1.6	Sub tunnels part of this tunnel keyed by sub tunnel ID. **Since: 4.26.2
[tunnelHistory]	*RsvpLerHistory* see 2.2038.1.2	Tunnel history events.
[tunnelIndex]	*integer*	Index of this tunnel in the tunnel FIB.

2.2038.1.1 RsvpLerAutoBandwidthParams

adjustmentPeriod	*floating point number*	Bandwidth adjustment period for auto bandwidth.
lastSampledBandwidth **	*integer*	Last sampled bandwidth for auto bandwidth in bps. **Since: 4.25.1
maxBandwidth	*integer*	Maximum bandwidth for auto bandwidth in bps.
minBandwidth	*integer*	Minimum bandwidth for auto bandwidth in bps.
[nextAdjustmentTime] **	*floating point number*	Bandwidth next adjustment timestamp for auto bandwidth. **Since: 4.35.2

2.2038.1.2 RsvpLerHistory

history	*list of RsvpLerHistoryEntry* see 2.2038.1.2.1	Recent history events.

2.2038.1.2.1 RsvpLerHistoryEntry

event	*string*	History event.

[hops] **	*list of IP address*	P2P path hops. **Since: 4.31.1
timestamp	*floating point number*	Timestamp of the event.
[tree] **	*table(IPv4 or IPv6 address) = RsvpLerPathWithChange* see 2.2038.1.2.1.1	Path and change type for each changed leaf of the P2MP tree. **Since: 4.32.2

2.2038.1.2.1.1 RsvpLerPathWithChange

changeType	*enum: changed | new | notFound | removed*	The type of change of a path.
[hops]	*list of IP address*	Path hops.

2.2038.1.3 RsvpLerLsp

bandwidth	*integer*	LSP requested bandwidth in bps.
[cspfPathKeyId]	*integer*	CSPF Path ID.
hops	*list of IP address*	Path hops.
inUse	*boolean*	LSP is in use.
lspErrors	*list of RsvpLerError* see 2.2038.1.3.1	Errors on this LSP.
lspId	*integer*	LSP ID.
pathSpecName	*string*	Path specification name.
pathSpecType	*enum: dynamic | unknown | explicit*	Path specification type.
pathType	*enum: unknown | secondary | primary*	Path type.
state	*enum: unknown | down | up | unverified | establishing*	LSP state.

2.2038.1.3.1 RsvpLerError

code	*integer*	RSVP error code.
node	*IP address*	Router on which the error occurred.
value	*integer*	RSVP error value.

2.2038.1.4 RsvpLerP2mpLsp

bandwidth	*integer*	LSP requested bandwidth in bps.
[cspfTreeId]	*integer*	CSPF Tree ID.
inUse	*boolean*	LSP is in use.
lspErrors	*list of RsvpLerError* see 2.2038.1.3.1	Errors on this LSP.
lspId	*integer*	LSP ID.
pathSpecName	*string*	Path specification name.
specType	*enum: dynamic | unknown | explicit*	Path specification type.
state	*enum: unknown | down | up | unverified | establishing*	LSP state.

[treeLeaves]	*table(IPv4 or IPv6 address) = RsvpLeaf* see 2.2038.1.4.1	Path and state for each leaf of the P2MP tree.

2.2038.1.4.1 RsvpLeaf

[hops]	*list of IP address*	Path hops.
state	*enum: down | up*	Leaf state.

2.2038.1.5 RsvpLerSplitTunnelParams

maxBandwidth **	*integer*	Maximum bandwidth for each sub-tunnel in bps. **Since: 4.27.0
minBandwidth **	*integer*	Minimum bandwidth for each sub-tunnel in bps. **Since: 4.27.0
quantum	*integer*	Quantum bandwidth for split-tunnel in bps.
reductionDelay **	*integer*	Sub-tunnel reduction delay interval value. **Since: 4.27.1
subTunnelInitial **	*integer*	Initial number of sub-tunnels for split-tunnel. **Since: 4.34.2
subTunnelLimit	*integer*	Upper limit on the number of sub-tunnels for split-tunnel.
subTunnelMinimum **	*integer*	Lower limit on the number of sub-tunnels for split-tunnel. **Since: 4.34.2

2.2038.1.6 RsvpLerSubTunnel

activePathType	*enum: unknown | secondary | primary*	Active path type.
currentBandwidth	*integer*	Sub tunnel bandwidth in bps.
[lastSampledBandwidth] **	*integer*	Last sampled bandwidth of this sub tunnel in bps. **Since: 4.27.1
lspCount	*integer*	Number of LSPs in this sub tunnel.
[lspIds] **	*list of integer*	LSP IDs in this sub tunnel. **Since: 4.31.2
[lsps]	*list of RsvpLerLsp* see 2.2038.1.3	LSPs part of this sub tunnel.
mbb	*boolean*	Sub tunnel is getting re-established with make-before-break.
[nextAdjustmentTime] **	*floating point number*	Bandwidth next adjustment timestamp for auto bandwidth. **Since: 4.35.2
[primaryPath]	*RsvpLerTunnelPath* see 2.2038.1.6.1	Primary path information.
[secondaryPaths]	*list of RsvpLerTunnelPath* see 2.2038.1.6.1	Secondary paths information.
[sessionId]	*integer*	Session ID associated with this sub tunnel.

state	*enum: down | up | unknown*	Sub tunnel state.
[subTunnelHistory]	*RsvpLerHistory* see 2.2038.1.2	Sub tunnel history events.
[tunnelIndex]	*integer*	Index of this sub tunnel in the tunnel FIB.

2.2038.1.6.1 RsvpLerTunnelPath

[cspfPathKeyId]	*integer*	CSPF Path ID.
hops	*list of IP address*	Path hops.
inUse	*boolean*	Path is in use.
[intfMtu]	*integer*	Interface MTU.
mbb	*boolean*	Path is being re-established with make-before-break.
pathErrors	*list of RsvpLerError* see 2.2038.1.3.1	Errors on this path.
[pathMtu]	*integer*	Path MTU.
[preSignaled]	*boolean*	Path is pre-signaled.
specName	*string*	Path specification name.
specType	*enum: dynamic | unknown | explicit*	Path specification type.
state	*enum: coldStandby | unknown | down | up | establishing*	Path state.

2.2038.1.7 RsvpLerTunnelTree

[cspfTreeId]	*integer*	CSPF Tree ID.
inUse	*boolean*	Tree is in use.
[intfMtus] **	*table(string) = integer*	Interface MTUs of a P2MP tunnel. **Since: 4.33.0
mbb	*boolean*	Tree is being re-established with make-before-break.
[pathMtu] **	*integer*	Path MTU. **Since: 4.33.0
specName	*string*	Tree specification name.
specType	*enum: dynamic | unknown | explicit*	Tree specification type.
state	*enum: coldStandby | unknown | down | up | establishing*	Tree state.
treeErrors	*list of RsvpLerError* see 2.2038.1.3.1	Errors on this tree.
treeLeaves	*table(IPv4 or IPv6 address) = RsvpLeaf* see 2.2038.1.4.1	Path and state for each leaf of this tree.

2.2039 show traffic-engineering segment-routing cbf fec [...]

`vrfs`	*table(string) = Cbf.Cli.SrTePolicyCbfFecModel* see 2.2039.1	Per VRF Segment Routing Traffic Engineering CBF overrideentries.

2.2039.1 Cbf.Cli.SrTePolicyCbfFecModel

`overrides`	*list of Cbf.Cli.SrTePolicyCbfFecOverride* see 2.2039.1.1	Policy FEC override entry.

2.2039.1.1 Cbf.Cli.SrTePolicyCbfFecOverride

`defaultFecId`	*integer*	Default FEC ID.
`dscp`	*integer*	DSCP value.
`ipVersion`	*enum: ipv6 | ipv4*	IP version.
`overrideFecId`	*integer*	Overriding SR-TE Policy FEC ID.

2.2040 show traffic-engineering segment-routing policy [...]

vrfs	*table(string) = SrTePolicyCandidatesModel* see 2.2040.1	Per VRF Segment Routing Traffic Engineering Policies.

2.2040.1 SrTePolicyCandidatesModel

enlpGlobal **	*enum: ipv4 | none | localPolicy | ipv4AndIpv6 | ipv6*	Global explicit null label policy. **Since: 4.25.2
policies	*list of SrTePolicyCandidates* see 2.2040.1.1	List of Segment Routing Traffic Engineering policies and its candidates.

2.2040.1.1 SrTePolicyCandidates

color	*integer*	Segment Routing Traffic Engineering Policy Color.
[description] **	*string*	Policy Description. **Since: 4.24.1
endpoint	*IP address*	Segment Routing Traffic Engineering Policy End point.
[epOverride] **	*IP address*	Endpoint override. **Since: 4.36.0
[name] **	*string*	Policy Name. **Since: 4.24.1
pathGroups	*list of SrTePolicyPathGroup* see 2.2040.1.1.1	Candidate paths for the Segment Routing Traffic Engineering policy.
[txBytes] **	*integer*	Aggregate number of transmitted bytes for the policy. **Since: 4.22.0
[txPackets] **	*integer*	Aggregate number of transmitted packets for the policy. **Since: 4.22.0

2.2040.1.1.1 SrTePolicyPathGroup

[activeTime]	*integer*	UTC seconds since epoch when the candidate path was selected as active.
[bindingSid]	*SrTePolicyBindingSid* see 2.2040.1.1.1.1	Binding Segment Identifier of the candidate path.
[discriminator]	*integer*	Protocol specific discriminator of the candidate path.
[endpointProvisioning] **	*enum: static | dynamic*	Policy Endpoint provisioning. **Since: 4.32.1
enlp **	*enum: ipv4 | none | localPolicy | ipv4AndIpv6 | ipv6*	Explicit null label policy of the candidate path. **Since: 4.23.1
[flexAlgoName] **	*string*	Flex Algorithm Definition Name. **Since: 4.31.2
[igpShortcutConfigured] **	*boolean*	IGP shortcut config for candidate path. **Since: 4.36.0

[igpShortcutEligible] **	*boolean*	IGP shortcut eligibility for candidate path. **Since: 4.36.0
inheritedGlobalEnlp **	*boolean*	Flag to indicate inheritance of Global explicit null label policy. **Since: 4.25.2
[lastChangeTime]	*integer*	UTC seconds since epoch when the candidate path was last updated.
[localConstraintName] **	*string*	Local Constraint Name. **Since: 4.33.2
[metric] **	*integer*	Metric of the candidate path. **Since: 4.28.1
[metricType] **	*enum: static* | *dynamicResolved* | *dynamicUnresolved*	Static or dynamic metric. **Since: 4.28.1
[notActiveReason]	*enum: higherDiscriminatorAvailable* | *bindingSidOutOfSrlbRange* | *higherPreferenceAvailable* | *segmentListsMissing* | *bindingSidConflict* | *bindingSidInUseByOtherApplication* | *bindingSidNotConfigured* | *samePriorityActive* | *betterProtocolAvailable* | *segmentListsUnresolved* | *lowerOriginAvailable*	Reason why this candidate path is not active.
originator	*SrTePolicyOriginator* see 2.2040.1.1.1.2	Originator of the candidate path.
[pathComputation] **	*enum: localConstraint* | *segmentRouting* | *configured* | *flexAlgo*	Path Computation Type. **Since: 4.32.1
preference	*integer*	Preference of the candidate path.
protocol	*enum: pcep* | *static* | *bgp*	Protocol source of the candidate path.
segmentLists	*list of SrTePolicyPathGroupSegmentList* see 2.2040.1.1.1.3	Segment lists that make up the candidate path.
state	*enum: valid* | *active* | *invalid*	State of the candidate path.

2.2040.1.1.1.1 SrTePolicyBindingSid

bindingSidType	*enum: mpls* | *ipv6*	Binding Segment Identifier Type.
dynamic **	*boolean*	Flag to indicate if BSID is assigned Dynamically. **Since: 4.32.2
[mplsLabelSid]	*integer*	Binding Segment Identifier in the form of an MPLS label.

2.2040.1.1.1.2 SrTePolicyOriginator

asn	*string*	Autonomous System Number.

nodeAddress	*IP address*	Node address of the originator.

2.2040.1.1.1.3 SrTePolicyPathGroupSegmentList

[backupVias] **	*list of SrTeSegmentListVia* see 2.2029.1.1.1.2	List of next hops for the backup path of the segment list, if the segment list is valid. **Since: 4.23.2
[counterInUse] **	*boolean*	Counter is in use for the segment list. **Since: 4.30.1
[invalidReason]	*enum: sbfdDown* | *resolvedLabelsExceedPlatformMsd* | *segmentListMissing* | *noResolvedLabels* | *unresolvedTopLabel*	Reason why this segment list is invalid.
[protectionState] **	*enum: protectionUnknown* | *unprotectedTilfaBackupExceedMSD* | *slProtected*	Segment list protection status and the reason why unprotected. **Since: 4.30.1
[sbfdHoldDownExpiryTime] **	*integer*	Time in seconds when the holddown timer expires. **Since: 4.33.0
[sbfdHoldDownStartTime] **	*integer*	UTC seconds since epoch when the holddown timer was started. **Since: 4.33.1
[sbfdHoldDownStopTime] **	*integer*	UTC seconds since epoch when the holddown timer was stopped. **Since: 4.33.1
[sbfdHoldDownTimeConfigured] **	*integer*	Configured SBFD Hold down time. **Since: 4.33.0
[sbfdReturnPathLabelStack] **	*list of SrTeSegment* see 2.2040.1.1.1.4	Segments that make up the SBFD return path. **Since: 4.29.2
[sbfdState] **	*enum: down* | *up* | *adminDown* | *init*	State of SBFD session. **Since: 4.23.2
[segmentListId]	*integer*	Internal Id of the segment list for valid candidate paths.
[segmentListValid]	*boolean*	Validity of the segment list for valid candidate paths.
segments	*list of SrTeSegment* see 2.2040.1.1.1.4	Segments that make up the segment list.
[txBytes]	*integer*	Total number of transmitted bytes.
[txPackets]	*integer*	Total number of transmitted packets.
[vias]	*list of SrTeSegmentListVia* see 2.2029.1.1.1.2	List of next hops for the primary path of the segment list, if the segment list is valid.
weight	*integer*	Weight of the segment list.

2.2040.1.1.1.4 SrTeSegment

[mplsLabelSid]	*integer*	Segment Identifier in the form of an MPLS label.

2.2041 show traffic-engineering segment-routing policy active [...]

vrfs	*table(string) = SrTePolicyActiveModel* see 2.2041.1	Per VRF Active Segment Routing Traffic Engineering Policies.

2.2041.1 SrTePolicyActiveModel

enlpGlobal **	*enum: ipv4 | none | localPolicy | ipv4AndIpv6 | ipv6*	Global explicit null label policy. **Since: 4.25.2
policies	*list of SrTePolicyActive* see 2.2041.1.1	List of Segment Routing Traffic Engineering policies installed in the forwarding plane.

2.2041.1.1 SrTePolicyActive

color	*integer*	Segment Routing Traffic Engineering Policy Color.
[description] **	*string*	Policy Description. **Since: 4.24.1
endpoint	*IP address*	Segment Routing Traffic Engineering Policy End point.
[epOverride] **	*IP address*	Endpoint override. **Since: 4.36.0
[name] **	*string*	Policy Name. **Since: 4.24.1
pathGroup	*SrTePolicyPathGroup* see 2.2040.1.1.1	Selected candidate path for the Segment Routing Traffic Engineering policy.
[txBytes] **	*integer*	Aggregate number of transmitted bytes for the policy. **Since: 4.22.0
[txPackets] **	*integer*	Aggregate number of transmitted packets for the policy. **Since: 4.22.0

2.2042 show traffic-engineering segment-routing policy fec [...]

[fecs]	*table(numeric string) = SrTePolicyFecInfo* see 2.2042.1	A mapping from policy FEC ID to policy information.

2.2042.1 SrTePolicyFecInfo

[policy]	*SrTePolicyBase* see 2.2042.1.1	Segment routing traffic engineering policy information.
[vias]	*list of SrTePolicyFecVia* see 2.2042.1.2	List storing the policy FEC vias.

2.2042.1.1 SrTePolicyBase

Could also be an instance of:
SrTePolicyActive 2.2041.1.1
SrTePolicyCandidates 2.2040.1.1

color	*integer*	Segment Routing Traffic Engineering Policy Color.
[description] **	*string*	Policy Description. **Since: 4.24.1
endpoint	*IP address*	Segment Routing Traffic Engineering Policy End point.
[epOverride] **	*IP address*	Endpoint override. **Since: 4.36.0
[name] **	*string*	Policy Name. **Since: 4.24.1
[txBytes] **	*integer*	Aggregate number of transmitted bytes for the policy. **Since: 4.22.0
[txPackets] **	*integer*	Aggregate number of transmitted packets for the policy. **Since: 4.22.0

2.2042.1.2 SrTePolicyFecVia

segmentListId	*integer*	Segment list identifier.
weight	*integer*	Segment list weight.

2.2043 show traffic-engineering segment-routing policy segment-list [...]

vrfs	*table(string) = SrTePolicySegmentLists* see 2.2043.1	A mapping from VRF to the segment lists it contains.

2.2043.1 SrTePolicySegmentLists

segmentLists	*table(numeric string) = SrTePolicySegmentList* see 2.2043.1.1	A mapping from segment list ID to the segment list.

2.2043.1.1 SrTePolicySegmentList

[backupVias] **	*list of SrTeSegmentListVia* see 2.2029.1.1.1.2	List of nexthops for the backup path of the segment list. **Since: 4.23.2
segments	*list of SrTeSegment* see 2.2040.1.1.1.4	List of segments composing the segment list.
valid	*boolean*	Validity of the segment list.
[vias]	*list of SrTeSegmentListVia* see 2.2029.1.1.1.2	List of next hops for the primary path of the segment list.

2.2044 show traffic-engineering segment-routing policy segment-list counters [...]

`vrfs`	*table(string) = SrTePolicySegmentListsCounters* see 2.2044.1	A mapping from VRF to the segment lists it contains.

2.2044.1 SrTePolicySegmentListsCounters

`segmentLists`	*table(numeric string) = SrTePolicySegmentListCounters* see 2.2044.1.1	A mapping from segment list ID to the segment list counters.

2.2044.1.1 SrTePolicySegmentListCounters

`[counterInUse]` **	*boolean*	Counter is in use for the segment list. **Since: 4.30.1
`[txBytes]`	*integer*	Total number of transmitted bytes.
`[txPackets]`	*integer*	Total number of transmitted packets.
`[vias]`	*list of SrTeSegmentListVia* see 2.2029.1.1.1.2	List of next hops for the segment list.

2.2045 show traffic-engineering segment-routing policy summary

revision 2

vrfs	*table(string) = SrTePolicySummaryModel* see 2.2045.1	Per VRF Segment Routing Traffic Engineering Policy summary.

2.2045.1 SrTePolicySummaryModel

bindingSidConflictInactive-PoliciesCount	*integer*	Number of inactive policies due to Binding SID conflict with other policies.
bindingSidConflictInvalid-PathGroupsCount	*integer*	Number of invalid candidate paths due to Binding SID conflict with other applications.
[dynamicBsidLabelRanges] **	*list of SrTePolicyDynBsid-LabelRangeModel* see 2.2045.1.1	Dynamic BSID label ranges information. **Since: 4.32.2
dynamicallyAssignBsid **	*boolean*	Assign BSIDs dynamically. **Since: 4.32.2
fecOptimizationsSupported	*boolean*	Indicates whether this device supports FEC optimizations or not.
maximumSidDepth **	*integer*	Maximum capacity of segment list label stack. **Since: 4.31.2
pathgroupStatistics	*SrTePolicyPathGroup-StatisticsModel* see 2.2045.1.2	Segment Routing Traffic Engineering Policy path group related Statistics.
perEndpointColorStatistics	*SrTePolicyStatisticsEntry-Model* see 2.2045.1.4	Per endpoint and color Segment Routing Traffic Engineering Policy statistics.
policyStatistics	*SrTePolicyStatisticsModel* see 2.2045.1.5	Per endpoint and color and source Segment Routing Traffic Engineering Policy statistics.
reserveServiceLabel **	*boolean*	Indicates whether there is one space reserved for a VPN service label in segment list label stack. **Since: 4.31.2
segmentListStatistics	*SrTePolicySegmentList-StatisticsModel* see 2.2045.1.3	Segment Routing Traffic Engineering Policy segment list related statistics.
specifiedBsidOnly **	*boolean*	BSIDs are optional. **Since: 4.32.1

2.2045.1.1 SrTePolicyDynBsidLabelRangeModel

base	*integer*	Range start of dynamic BSID label block.
inUse	*integer*	Number of dynamic BSIDs currently in use.
size	*integer*	Range size of dynamic BSID label block.

2.2045.1.2 SrTePolicyPathGroupStatisticsModel

sources	*table(string) = SrTePolicyPathGroupStatisticsEntryModel* see 2.2045.1.2.1	Per source Segment Routing Traffic Engineering Policy path group statistics.
total	*SrTePolicyPathGroupStatisticsEntryModel* see 2.2045.1.2.1	Total path group statistics for all Segment Routing Traffic Engineering Policy sources.

2.2045.1.2.1 SrTePolicyPathGroupStatisticsEntryModel

activePathGroups	*integer*	Number of candidate paths in active state.
[endpointProvisioning] **	*table(string) = SrTePolicyPathGroupEpProvisioningStatisticsModel* see 2.2045.1.2.1.1	Per Endpoint provisioning type Segment Routing Traffic Engineering Policy path group statistics. **Since: 4.32.1
invalidPathGroups	*integer*	Number of candidate paths in invalid state.
totalPathGroups	*integer*	All candidate paths in any state.
validPathGroups	*integer*	Number of candidate paths that are valid but not active.

2.2045.1.2.1.1 SrTePolicyPathGroupEpProvisioningStatisticsModel

pathComputation	*table(string) = SrTePolicyPathGroupComputationStatisticsEntryModel* see 2.2045.1.2.1.2	Per Path Computation type Segment Routing Traffic Engineering Policy path group statistics.

2.2045.1.2.1.2 SrTePolicyPathGroupComputationStatisticsEntryModel

activePathGroups	*integer*	Number of candidate paths per endpoint provisioning and path computation type in active state.
invalidPathGroups	*integer*	Number of candidate paths per endpoint provisioning and path computation type in invalid state.
totalPathGroups	*integer*	All candidate paths per endpoint provisioning and path computation type in any state.
validPathGroups	*integer*	Number of candidate paths per endpoint provisioning and path computation type that are valid but not active.

2.2045.1.3 SrTePolicySegmentListStatisticsModel

invalidSegmentLists	*integer*	Number of segment lists in invalid state.
validSegmentLists	*integer*	Number of segment lists in valid state.
validSegmentListsWithBackup **	*integer*	Number of valid segment lists with backup. **Since: 4.23.2

2.2045.1.4 SrTePolicyStatisticsEntryModel

activePolicies	*integer*	Number of policies in active state.
invalidPolicies	*integer*	Number of policies in invalid state.
totalPolicies	*integer*	All policies in any state.
validPolicies	*integer*	Number of policies that are valid but not active.

2.2045.1.5 SrTePolicyStatisticsModel

sources	*table(string) = SrTePolicyStatisticsEntryModel* see 2.2045.1.4	Per source Segment Routing Traffic Engineering Policy statistics.
total	*SrTePolicyStatisticsEntryModel* see 2.2045.1.4	Total Segment Routing Traffic Engineering policies with unique Endpoint, Color values irresepctive of source.

2.2046 show traffic-engineering segment-routing replication-segment [...]

vrfs	*table(string) = SrP2mpCandidatesModel* see 2.2046.1	A mapping of VRF name to its replication segments.

2.2046.1 SrP2mpCandidatesModel

replicationSegments	*table(numeric string) = SrP2mpCandidates* see 2.2046.1.1	Replication segments, keyed by their replication ID.

2.2046.1.1 SrP2mpCandidates

nodeAddress	*IP address*	Address of replication node.
pathInstance	*integer*	Path Instance number.
[replicationSid]	*SrP2mpReplicationSid* see 2.2046.1.1.2	Mpls label to identify replication segment.
root	*IP address*	Node address of root.
segmentLists	*list of SrP2mpRepSegSegmentList* see 2.2046.1.1.1	Replication segments information.
source	*enum: static | pcep*	Protocol source of replication segment.
state	*enum: valid | active | invalid*	State of the replication segment.
treeId	*integer*	Tree identifier.

2.2046.1.1.1 SrP2mpRepSegSegmentList

backupVias	*list of SrTeSegmentListVia* see 2.2029.1.1.1.2	List of next hops for the backup path of the segment list, if the segment list is valid.
[invalidReason]	*enum: sbfdDown | resolvedLabelsExceedPlatformMsd | segmentListMissing | noResolvedLabels | unresolvedTopLabel*	Reason why this segment list is invalid.
[segmentListId]	*integer*	Internal ID of the segment list for valid candidate paths.
[segmentListValid]	*boolean*	Validity of the segment list for valid candidate paths.
segments	*list of SrP2mpSegment* see 2.2046.1.1.1.1	Segments that make up the segment list.
vias	*list of SrTeSegmentListVia* see 2.2029.1.1.1.2	List of next hops for the primary path of the segment list, if the segment list is valid.

2.2046.1.1.1.1 SrP2mpSegment

[mplsLabelSid]	*integer*	Segment identifier in the form of an MPLS label.
[nexthopAddr]	*IP address*	Segment identifier in the form of next hop IP address.

2.2046.1.1.2 SrP2mpReplicationSid

[mplsLabelSid]	*integer*	Replication Segment Identifier in the form of an MPLS label.
replicationSidType	*enum: mpls* | *ipv6*	Replicaiton Segment Identifier Type.

2.2047 show traffic-engineering segment-routing replication-segment summary

vrfs	*table(string) = ReplicationSegmentSummaryModel* see 2.2047.1	Per VRF Segment Routing Replication Segments.

2.2047.1 ReplicationSegmentSummaryModel

nonSharedStatistics	*ReplicationSegmentRoot* see 2.2047.1.1	Segment Routing Traffic Engineering not shared Replication Segment related statistics.
protocolStats	*ReplicationSegmentStatisticsModel* see 2.2047.1.3	Per source protocol Routing Traffic Engineering Replication segment statistics.
replicationSegmentsRsidConflictCount	*integer*	Number of replication segment with RSID conflict.
sharedStatistics	*ReplicationSegmentSharedStatModel* see 2.2047.1.2	Segment Routing Traffic Engineering shared Replication Segment related statistics.

2.2047.1.1 ReplicationSegmentRoot

roots	*table(IPv4 or IPv6 address) = ReplicationSegmentTree* see 2.2047.1.1.1	Replication segments, keyed by their root address.

2.2047.1.1.1 ReplicationSegmentTree

trees	*table(numeric string) = ReplicationSegmentPath* see 2.2047.1.1.1.1	Replication segments, keyed by their tree ID.

2.2047.1.1.1.1 ReplicationSegmentPath

paths	*table(numeric string) = ReplicationSegmentStateModel* see 2.2047.1.1.1.2	Replication segments, keyed by their path instance number.

2.2047.1.1.1.2 ReplicationSegmentStateModel

active	*integer*	Number of replication segments in active state.
invalid	*integer*	Number of replication segments in invalid state.
valid	*integer*	Number of replication segments in valid state.

2.2047.1.2 ReplicationSegmentSharedStatModel

`replicationIds`	*table(numeric string) = ReplicationSegmentStateModel* see 2.2047.1.1.1.2	Replication segments, keyed by their replication id.

2.2047.1.3 ReplicationSegmentStatisticsModel

`sources`	*table(string) = ReplicationSegmentStateModel* see 2.2047.1.1.1.2	Replication segments, keyed by their source.
`totalStat`	*ReplicationSegmentStateModel* see 2.2047.1.1.1.2	Total replication segment statistics for all sources.

2.2048 show traffic-policy (cpu | vlan | interface) [...]

revision 2

[proportionalLagPolicer-Enabled] **	*boolean*	Proportional lag policer mode is enabled. **Since: 4.33.1
[trafficPolicies]	*table(string) = TrafficPolicy* see 2.2048.1	Traffic policy indexed by policy name.

2.2048.1 TrafficPolicy

[configuredIntfs]	*list of Interface name*	(Deprecated - refer to the "configuredIntfs" attribute in the "input" InterfaceCommon sub-model) List of interfaces the policy is configured on input.
[configuredVrfs]	*list of string*	Deprecated - refer to cpu.configuredVrfs attribute.
[cpu] **	*InterfaceCommon* see 2.2048.1.1	Information for CPU policy (enforced in hardware). **Since: 4.32.0
[cpuSoftware] **	*InterfaceCommon* see 2.2048.1.1	Information for CPU policy (enforced in software). **Since: 4.32.0
[description] **	*string*	Policy description. **Since: 4.33.1
[flowTracker] **	*string*	Sampled flow tracker for a traffic-policy flow tracking action. **Since: 4.36.0
[input] **	*InterfaceCommon* see 2.2048.1.1	Interface information for input policy. **Since: 4.26.0
[ipv4AppliedIntfs]	*list of Interface name*	(Deprecated - refer to the "ipv4AppliedIntfs" attribute in the "input" InterfaceCommon sub-model) Applied interfaces for IPv4 input traffic.
[ipv4AppliedVrfs]	*list of string*	Deprecated - refer to cpu.ipv4AppliedVrfs attribute.
[ipv4AppliedVrfsSoftware] **	*list of string*	Deprecated - refer to cpuSoftware.ipv4AppliedVrfs. **Since: 4.27.1
[ipv6AppliedIntfs]	*list of Interface name*	(Deprecated - refer to the "ipv6AppliedIntfs" attribute in the "input" InterfaceCommon sub-model) Applied interfaces for IPv6 input traffic.
[ipv6AppliedVrfs]	*list of string*	Deprecated - refer to cpu.ipv6AppliedVrfs attribute.
[ipv6AppliedVrfsSoftware] **	*list of string*	Deprecated - refer to cpuSoftware.ipv6AppliedVrfs. **Since: 4.27.1
[namedCounters]	*list of string*	Defined named counters for a traffic-policy.
[output] **	*InterfaceCommon* see 2.2048.1.1	Interface information for output policy. **Since: 4.26.0

rules	*list of Rule* see 2.1179.2.1	Detailed information of match rules.
[source] **	*enum: static | controller | other | sensor*	Contents source type. **Since: 4.34.2
[vacl] **	*VAclCommon* see 2.2048.1.2	Vlan information for VAcl policy. **Since: 4.27.2

2.2048.1.1 InterfaceCommon

[configuredIntfs]	*list of Interface name*	List of configured interfaces.
[configuredVni] **	*list of Vni* see 2.2048.1.1.1	List of configured VNIs. **Since: 4.32.2
[configuredVrfs] **	*list of string*	List of configured VRFs. **Since: 4.32.0
[ipv4AppliedIntfs]	*list of Interface name*	Applied interfaces for IPv4 traffic.
[ipv4AppliedVni] **	*list of Vni* see 2.2048.1.1.1	Applied VNIs for IPv4 traffic. **Since: 4.32.2
[ipv4AppliedVrfs] **	*list of string*	Applied VRFs for IPv4 traffic. **Since: 4.32.0
[ipv6AppliedIntfs]	*list of Interface name*	Applied interfaces for IPv6 traffic.
[ipv6AppliedVni] **	*list of Vni* see 2.2048.1.1.1	Applied VNIs for IPv6 traffic. **Since: 4.32.2
[ipv6AppliedVrfs] **	*list of string*	Applied VRFs for IPv6 traffic. **Since: 4.32.0
[macAppliedIntfs] **	*list of Interface name*	Applied interfaces for MAC traffic. **Since: 4.29.2
[macAppliedVni] **	*list of Vni* see 2.2048.1.1.1	Applied VNIs for MAC traffic. **Since: 4.32.2
[macAppliedVrfs] **	*list of string*	Applied VRFs for MAC traffic. **Since: 4.32.0

2.2048.1.1.1 Vni

[vlan]	*interface name*	dynamic vlan interface assigned for the vni.
[vni]	*integer*	vni.

2.2048.1.2 VAclCommon

[configuredVlans]	*list of string*	List of configured vlans.
[ipv4AppliedVlans]	*list of string*	Applied vlans for IPv4 traffic.
[ipv6AppliedVlans]	*list of string*	Applied vlans for IPv6 traffic.

2.2049 show traffic-policy (cpu | vlan | interface) counters [...]

[egressCounterGranularity] **	*enum: per-policy | per-interface*	Enabled counter granularity for traffic-policies applied on output of interfaces. **Since: 4.26.0
[egressTrafficPolicies] **	*table(string) = TrafficPolicyCounters* see 2.2049.1	Traffic policies applied on output of interfaces indexed by policy name. **Since: 4.26.0
[ingressCounterGranularity] **	*enum: per-policy | per-interface*	Enabled counter granularity for traffic-policies applied on input of interfaces. **Since: 4.25.0
[ingressCounterGranularity-VlanIntf] **	*enum: per-policy | per-interface*	Enabled counter granularity for traffic-policies applied on input of VLAN interfaces. **Since: 4.31.0
[trafficPolicies]	*table(string) = TrafficPolicyCounters* see 2.2049.1	Traffic policy indexed by policy name. Contains either policies applied on input of interfaces or CPU policies.

2.2049.1 TrafficPolicyCounters

[namedCounters]	*table(string) = CounterInfo* see 2.2049.1.1	Mapping of named counter to count data.
[unnamedCounters]	*table(string) = CounterInfo* see 2.2049.1.1	Mapping of rule name to count data.

2.2049.1.1 CounterInfo

[interfaces]	*table(string) = InterfaceInfo* see 2.2049.1.1.1	Count data per interface.
[policeCount] **	*PoliceCount* see 2.1179.2.1.1.4	Descriptive count for police. **Since: 4.31.1
[totals]	*TotalInfo* see 2.1179.2.1.1.6	Total hit counts.

2.2049.1.1.1 InterfaceInfo

[byteCount]	*integer*	Number of bytes matched.
[packetCount]	*integer*	Number of packets matched.

2.2050 show traffic-policy (cpu | vlan | interface) errors [...]

revision 2

[trafficPolicies]	*table(string) = TrafficPolicyErrors* see 2.2050.1	Traffic policy indexed by policy name.

2.2050.1 TrafficPolicyErrors

[cpu] **	*TrafficPolicyIntfErrorInfo* see 2.2050.1.1	Installation errors for policies applied to CPU (enforced in hardware). **Since: 4.32.1
[cpuSoftware] **	*TrafficPolicyIntfErrorInfo* see 2.2050.1.1	Installation errors for policies applied to CPU (enforced in software). **Since: 4.32.1
[input] **	*TrafficPolicyIntfErrorInfo* see 2.2050.1.1	Installation errors for policies applied on input of interfaces. **Since: 4.26.0
[ipv4FailedIntfs]	*list of Interface name*	(Deprecated - refer to "ipv4FailedIntfs" in the "input" TrafficPolicyIntfErrorInfo sub-model) Failed interfaces for IPv4 traffic.
[ipv4FailedVrfs]	*list of string*	Deprecated - refer to cpu.ipv4FailedVrfs.
[ipv4FailedVrfsSoftware] **	*list of string*	Deprecated - refer to cpuSoftware.ipv4FailedVrfs. **Since: 4.27.1
[ipv4InstallationErrors]	*list of string*	List of IPv4 installation errors. For traffic-policies applied on interfaces, refer to the "ipv4InstallationErrors" in the input/output TrafficPolicyIntfErrorInfo sub-models.
[ipv4InstallationErrors-Software] **	*list of string*	Deprecated - refer to cpuSoftware.ipv4VrfInstallationErrors. **Since: 4.27.1
[ipv6FailedIntfs]	*list of Interface name*	(Deprecated - refer to "ipv6FailedIntfs" in the "input" TrafficPolicyIntfErrorInfo sub-model) Failed interfaces for IPv6 traffic.
[ipv6FailedVrfs]	*list of string*	Deprecated - refer to cpu.ipv6FailedVrfs.
[ipv6FailedVrfsSoftware] **	*list of string*	Deprecated - refer to cpuSoftware.ipv6FailedVrfs. **Since: 4.27.1
[ipv6InstallationErrors]	*list of string*	List of IPv6 installation errors. For traffic-policies applied on interfaces, refer to the "ipv6InstallationErrors" in the input/output TrafficPolicyIntfErrorInfo sub-models.
[ipv6InstallationErrors-Software] **	*list of string*	Deprecated - refer to cpuSoftware.ipv6VrfInstallationErrors. **Since: 4.27.1
[macInstallationErrors] **	*list of string*	List of MAC installation errors. For traffic-policies applied on interfaces, refer to the "macInstallationErros" in the input/output TrafficPolicyIntfErrorInfo sub-models. **Since: 4.29.2

[output] **	*TrafficPolicyIntfErrorInfo* see 2.2050.1.1	Installation errors for policies applied on output of interfaces. **Since: 4.26.0
[source] **	*enum: static | controller | other | sensor*	Contents source type. **Since: 4.34.2
[vacl] **	*TrafficPolicyVAclErrorInfo* see 2.2050.1.2	Installation errors for policies applied on vlan. **Since: 4.27.2

2.2050.1.1 TrafficPolicyIntfErrorInfo

[ipv4FailedIntfs]	*list of Interface name*	Failed interfaces for IPv4 traffic.
[ipv4FailedVni] **	*list of Vni* see 2.2048.1.1.1	Failed VNIs for IPv4 traffic. **Since: 4.32.2
[ipv4FailedVrfs] **	*list of string*	Failed VRFs for IPv4 traffic. **Since: 4.32.0
[ipv4InstallationErrors]	*list of string*	List of IPv4 installation errors.
[ipv4VrfInstallationErrors] **	*list of string*	List of IPv4 VRF installation errors. **Since: 4.32.0
[ipv6FailedIntfs]	*list of Interface name*	Failed interfaces for IPv6 traffic.
[ipv6FailedVni] **	*list of Vni* see 2.2048.1.1.1	Failed VNIs for IPv6 traffic. **Since: 4.32.2
[ipv6FailedVrfs] **	*list of string*	Failed VRFs for IPv6 traffic. **Since: 4.32.0
[ipv6InstallationErrors]	*list of string*	List of IPv6 installation errors.
[ipv6VrfInstallationErrors] **	*list of string*	List of IPv6 VRF installation errors. **Since: 4.32.0
[macFailedIntfs] **	*list of Interface name*	Failed interfaces for MAC traffic. **Since: 4.29.2
[macFailedVni] **	*list of Vni* see 2.2048.1.1.1	Failed VNIs for MAC traffic. **Since: 4.32.2
[macFailedVrfs] **	*list of string*	Failed VRFs for MAC traffic. **Since: 4.32.0
[macInstallationErrors] **	*list of string*	List of MAC installation errors. **Since: 4.29.2
[macVrfInstallationErrors] **	*list of string*	List of MAC VRF installation errors. **Since: 4.32.0

2.2050.1.2 TrafficPolicyVAclErrorInfo

[ipv4FailedVlans]	*list of string*	Failed vlans for IPv4 traffic.
[ipv4InstallationErrors]	*list of string*	List of IPv4 installation errors.
[ipv6FailedVlans]	*list of string*	Failed vlans for IPv6 traffic.
[ipv6InstallationErrors]	*list of string*	List of IPv6 installation errors.

2.2051 show traffic-policy (cpu | vlan | interface) summary [...]

[trafficPolicies]	*table(string) = TrafficPolicySummary* see 2.2051.1	Traffic policy indexed by policy name.

2.2051.1 TrafficPolicySummary

[configuredIntfs]	*list of Interface name*	(Deprecated - refer to the "configuredIntfs" attribute in the "input" InterfaceCommon sub-model) List of interfaces the policy is configured on input.
[configuredVrfs]	*list of string*	Deprecated - refer to cpu.configuredVrfs attribute.
[cpu] **	*InterfaceCommon* see 2.2048.1.1	Information for CPU policy (enforced in hardware). **Since: 4.32.0
[cpuSoftware] **	*InterfaceCommon* see 2.2048.1.1	Information for CPU policy (enforced in software). **Since: 4.32.0
[description] **	*string*	Policy description. **Since: 4.33.1
[flowTracker] **	*string*	Sampled flow tracker for a traffic-policy flow tracking action. **Since: 4.36.0
[input] **	*InterfaceCommon* see 2.2048.1.1	Interface information for input policy. **Since: 4.26.0
[ipv4AppliedIntfs] **	*list of Interface name*	(Deprecated - refer to the "ipv4AppliedIntfs" attribute in the "input" InterfaceCommon sub-model) Applied interfaces for IPv4 input traffic. **Since: 4.23.0
[ipv4AppliedVrfs]	*list of string*	Deprecated - refer to cpu.ipv4AppliedVrfs attribute.
[ipv4AppliedVrfsSoftware] **	*list of string*	Deprecated - refer to cpuSoftware.ipv4AppliedVrfs. **Since: 4.27.1
[ipv6AppliedIntfs] **	*list of Interface name*	(Deprecated - refer to the "ipv6AppliedIntfs" attribute in the "input" InterfaceCommon sub-model) Applied interfaces for IPv6 input traffic. **Since: 4.23.0
[ipv6AppliedVrfs]	*list of string*	Deprecated - refer to cpu.ipv6AppliedVrfs attribute.
[ipv6AppliedVrfsSoftware] **	*list of string*	Deprecated - refer to cpuSoftware.ipv6AppliedVrfs. **Since: 4.27.1
[namedCounters] **	*list of string*	Defined named counters for a traffic-policy. **Since: 4.31.1
[output] **	*InterfaceCommon* see 2.2048.1.1	Interface information for output policy. **Since: 4.26.0

rules	*list of RuleSummary* see 2.2051.1.1	Summary of match rules configured.
[source] **	*enum: static | controller | other | sensor*	Contents source type. **Since: 4.34.2
[vacl] **	*VAclCommon* see 2.2048.1.2	Vlan information for VAcl policy. **Since: 4.27.2

2.2051.1.1 RuleSummary

Could also be an instance of:
Rule 2.1179.2.1

matchOption	*string*	Match on packet type.
ruleString	*string*	Match rule name.

2.2052 show traffic-policy field-set integer [...]

[integerFieldSets]	*table(string) = TrafficPolicyIntegerFieldSet* see 2.2052.1	Integer field sets by name.

2.2052.1 TrafficPolicyIntegerFieldSet

[integers]	*list of NumericalRange* see 2.1179.2.1.2.3	Integer ranges.
[policies] **	*PolicyUsage* see 2.2052.1.1	Policies applied with the field-set. **Since: 4.29.1
source	*enum: controller | url | bgp | static | andResults | sensor | other*	Contents source type.
[urlInfo]	*UrlInfo* see 2.2052.1.2	URL information.

2.2052.1.1 PolicyUsage

[policyNames]	*list of string*	policies applied with the field-set.

2.2052.1.2 UrlInfo

[urlPath]	*string*	Path to URL file.
[vrf]	*string*	Name of VRF for URL fetch.

2.2053 show traffic-policy field-set ipv4 prefix [...]

[prefixFieldSets]	*table(string) = IpPrefixFieldSet* see 2.2053.1	Prefix field sets by name.

2.2053.1 IpPrefixFieldSet

[andResultsFieldSetNames] **	*list of string*	Field sets for which and-results operation is done. **Since: 4.32.0
[appliedAndResultsFieldSet-Names] **	*list of string*	Field sets using this field set as the source of and-results. **Since: 4.34.1
[policies] **	*PolicyUsage* see 2.2052.1.1	Policies applied with the field-set. **Since: 4.29.1
[prefixes]	*list of IpPrefixWithExceptions* see 2.2053.1.1	Allowed prefixes with associated exception prefixes.
source	*enum: controller | url | bgp | static | andResults | sensor | other*	Contents source type.
[urlInfo] **	*UrlInfo* see 2.2052.1.2	URL information. **Since: 4.27.1

2.2053.1.1 IpPrefixWithExceptions

[exceptPrefixes]	*list of IP address prefix*	Exception prefixes.
[prefix]	*IP address prefix*	Allowed prefix.

2.2054 show traffic-policy field-set ipv6 prefix [...]

see 2.2053

2.2055 show traffic-policy field-set l4-port [...]

[l4PortFieldSets]	*table(string) = TrafficPolicyL4PortFieldSet* see 2.2055.1	Layer 4 port field sets by name.

2.2055.1 TrafficPolicyL4PortFieldSet

[policies] **	*PolicyUsage* see 2.2052.1.1	Policies applied with the field-set. **Since: 4.29.1
[ports]	*list of NumericalRange* see 2.1179.2.1.2.3	Port ranges.
source	*enum: controller | url | bgp | static | andResults | sensor | other*	Contents source type.
[urlInfo] **	*UrlInfo* see 2.2052.1.2	URL information. **Since: 4.27.1

2.2056 show traffic-policy field-set mac [...]

[macFieldSets]	*table(string) = TrafficPolicyMacFieldSet* see 2.2056.1	MAC address field sets by name.

2.2056.1 TrafficPolicyMacFieldSet

[macAddrs]	*list of MacAddressInfo* see 2.2056.1.1	MAC addresses with optional mask.
[policies]	*PolicyUsage* see 2.2052.1.1	Policies applied with the field-set.
source	*enum: controller | url | bgp | static | andResults | sensor | other*	Contents source type.
[urlInfo]	*UrlInfo* see 2.2052.1.2	URL information.

2.2056.1.1 MacAddressInfo

macAddr	*MAC address*	MAC address.

2.2057 show traffic-policy field-set service [...]

[serviceFieldSets]	*table(string) = TrafficPolicyServiceFieldSet* see 2.2057.1	service field sets by name.

2.2057.1 TrafficPolicyServiceFieldSet

[policies]	*PolicyUsage* see 2.2052.1.1	Policies applied with the field-set.
[protocols]	*list of ProtocolAndPort* see 2.2057.1.1	List of protocols.
source	*enum: controller | url | bgp | static | andResults | sensor | other*	Contents source type.
[urlInfo]	*UrlInfo* see 2.2052.1.2	URL information.

2.2057.1.1 ProtocolAndPort

Could also be an instance of:
Protocol 2.1179.2.1.2.15

[ports]	*list of Port* see 2.1179.2.1.2.17	List of L4 ports that can be ORed together.
[protocolRange]	*NumericalRange* see 2.1179.2.1.2.3	Protocol.

2.2058 show traffic-policy field-set vlan [...]

[vlanFieldSets]	*table(string) = TrafficPolicyVlanFieldSet* see 2.2058.1	VLAN field sets by name.

2.2058.1 TrafficPolicyVlanFieldSet

[policies] **	*PolicyUsage* see 2.2052.1.1	Policies applied with the field-set. **Since: 4.29.1
source	*enum: controller | url | bgp | static | andResults | sensor | other*	Contents source type.
[urlInfo] **	*UrlInfo* see 2.2052.1.2	URL information. **Since: 4.27.1
[vlans]	*list of NumericalRange* see 2.1179.2.1.2.3	VLAN ranges.

2.2059 show traffic-policy interface vrf detail [...]

[trafficPolicies]	*table(string) = VrfIntfOverrideInput* see 2.2059.1	Traffic policy indexed by policy name.

2.2059.1 VrfIntfOverrideInput

[input]	*OverriddenVrfInfo* see 2.2059.1.1	Interface information for input policy.

2.2059.1.1 OverriddenVrfInfo

[vrfs]	*list of ExcludedVrfIntfInfo* see 2.2059.1.1.1	List of overridden VRFs.

2.2059.1.1.1 ExcludedVrfIntfInfo

[excludedIntfs]	*list of Interface name*	List of excluded VRF interfaces.
[vrfName]	*string*	VRF Name.

2.2060 show traffic-policy protocol neighbors bgp

policies	*table(string) = ProtocolNeighbor* see 2.2060.1	Neighbors per policy.

2.2060.1 ProtocolNeighbor

vrfs	*table(string) = VrfRules* see 2.2060.1.1	Neighbors per VRF.

2.2060.1.1 VrfRules

rules	*list of NeighborRule* see 2.2060.1.1.1	Neighbor rules for IPV4/6.

2.2060.1.1.1 NeighborRule

[destinationPort]	*integer*	Destination port.
[maximumHops] **	*integer*	Maximum hop(s) allowed per GTSM for this speaker. **Since: 4.31.2
[sourcePort]	*integer*	Source port.
sourcePrefix	*IP address prefix*	Source prefix.

2.2061 show transceiver application [...]

ports	*table(string) = TransceiverApplications* see 2.2061.1	Mapping between port name and transceiver applications.

2.2061.1 TransceiverApplications

applications	*table(numeric string) = TransceiverApplicationStatus* see 2.2061.1.1	Mapping between application IDs and the information associated with each application.
mixedAppsCombinationRejected **	*boolean*	Combination of applications was accepted. **Since: 4.32.0

2.2061.1.1 TransceiverApplicationStatus

applicationCode	*integer*	Indicates the active application code.
hostInterface	*string*	Indicates the host interface of the active application.
hostLanes	*table(numeric string) = TransceiverApplicationHostLanes* see 2.2061.1.1.1	Mapping between application start lane and all the lanes under the given application.
mediaInterface	*string*	Indicates the media interface of the active application.
statusCodes	*table(string) = TransceiverApplicationHostLanes* see 2.2061.1.1.1	Mapping between configuration error code and list of lanes that report the given code.

2.2061.1.1.1 TransceiverApplicationHostLanes

lanes	*list of integer*	Host lanes (indexed starting at 1).

2.2062 show transceiver cdb capabilities [...]

revision 2

ports	*table(string) = TransceiverCdbCapabilitiesSlotDetail* see 2.2062.1	Mapping between the slot name and the CDB capabilities information of the inserted transceiver.

2.2062.1 TransceiverCdbCapabilitiesSlotDetail

[firmwareManagementCdbCapabilitiesAdvertised]	*TransceiverCdbCapabilitiesFirmwareManagement* see 2.2062.1.1	Firmware management CDB advertisements.
[firmwareManagementCdbCapabilitiesOverride]	*TransceiverCdbCapabilitiesFirmwareManagement* see 2.2062.1.1	Firmware management CDB overrides.
[moduleCdbCapabilitiesAdvertised]	*TransceiverCdbCapabilitiesModuleInfo* see 2.2062.1.2	Generic CDB capabilities advertisements.
[moduleCdbCapabilitiesOverride]	*TransceiverCdbCapabilitiesModuleInfo* see 2.2062.1.2	Generic CDB capabilities overrides.
serialNumber	*string*	Transceiver serial number.

2.2062.1.1 TransceiverCdbCapabilitiesFirmwareManagement

[firmwareAbortCommandMaxDuration]	*floating point number*	Maximum time in seconds the 'abort' firmware update command requires to execute and complete.
[firmwareAbortCommandSupport]	*boolean*	Firmware update abort command is supported.
[firmwareCompleteCommandMaxDuration]	*floating point number*	Maximum time in seconds the 'complete' firmware update command requires to execute and complete.
[firmwareCopyCommandMaxDuration]	*floating point number*	Maximum time in seconds the 'copy' firmware update command requires to execute and complete.
[firmwareCopyCommandSupport]	*boolean*	Firmware copy command is supported.
[firmwareErasedByteMarker]	*integer*	Byte value used to mark erased blocks.
[firmwareHitlessRestartSupported]	*boolean*	Indicates whether the transceiver can restart its firmware hitlessly.
[firmwareImageReadbackSupport]	*boolean*	Firmware image readback is supported.
[firmwareMaxEplTransactionSize]	*integer*	The maximum number of bytes that can be written to the EPL pages in a single SMBus transaction during a firmware CDB command.

[firmwareMaxLplTransaction-Size]	*integer*	The maximum number of bytes that can be written to the LPL page in a single SMBus transaction during a firmware CDB command.
[firmwarePasswordType]	*enum: vendorPassword* | *msaPassword* | *notApplicable* | *vendorPasswordSequence*	Password type required to unlock CDB firmware management commands.
[firmwareReadMethod]	*enum: epl* | *lpl* | *none* | *lplAndEpl*	Method used for reading a firmware binary from the transceiver.
[firmwareStartCommandMax-Duration]	*floating point number*	Maximum time in seconds the 'start' firmware update command requires to execute and complete.
[firmwareStartCommand-PayloadSize]	*integer*	Expected size in bytes of the firmware start payload.
[firmwareWriteCommandMax-Duration]	*floating point number*	Maximum time in seconds the 'download' firmware update command requires to execute and complete.
[firmwareWriteMethod]	*enum: epl* | *lpl* | *none* | *lplAndEpl*	Method used for writing a new firmware binary to the transceiver.
[skipFirmwareErasedBlock]	*boolean*	Skip firmware erased block.

2.2062.1.2 TransceiverCdbCapabilitiesModuleInfo

[autoPagingSupport]	*boolean*	Indicates whether EPL pages can be automatically selected.
[backgroundModeSupport]	*boolean*	Indicates whether CDB commands can be executed in the background.
[cdbCommandExecution-Trigger]	*enum: fullCommandWrite* | *commandIdWrite*	Action that triggers the start of a CDB command execution.
[cdbInstancesSupported]	*integer*	The number of CDB instances the inserted transceiver supports.
[cdbMaxBusyTime]	*floating point number*	Maximum time CDB commands require before reporting execution status.
[cdbModuleCommands-Supported]	*table(string) = boolean*	Mapping of supported general CDB commands.
[maxCompletionTime]	*floating point number*	Maximum time CDB commands require to complete.
[maxEplPagesSupported]	*integer*	The number of supported EPL pages.
[maxEplTransactionSize]	*integer*	The maximum number of bytes that can be written to the EPL pages in a single SMBus transaction.
[maxLplTransactionSize]	*integer*	The maximum number of bytes that can be written to the LPL page in a single SMBus transaction.

2.2063 show transceiver cdb operation [...]

ports	*table(string) = TransceiverCdbOperationSlotDetail* see 2.2063.1	Mapping between the slot name and the CDB operational parameters used for the inserted transceiver.

2.2063.1 TransceiverCdbOperationSlotDetail

[firmwareManagementCdbOperationDefault]	*TransceiverCdbOperationFirmwareManagement* see 2.2063.1.1	Firmware management CDB operational parameteres defaults.
[firmwareManagementCdbOperationOverride]	*TransceiverCdbOperationFirmwareManagement* see 2.2063.1.1	Firmware management CDB operational parameteres override.
[moduleCdbOperationDefault]	*TransceiverCdbOperationModuleInfo* see 2.2063.1.2	Generic CDB operational parameters defaults.
[moduleCdbOperationOverride]	*TransceiverCdbOperationModuleInfo* see 2.2063.1.2	Generic CDB operational parameters overrides.
serialNumber	*string*	Transceiver serial number.

2.2063.1.1 TransceiverCdbOperationFirmwareManagement

[fwActivateStandbyCliDisabled]	*boolean*	Indicates that the 'transceiver firmware activate-standby' CLI command is disabled by EOS.
[fwUpdateCliDisabled]	*boolean*	Indicates that the 'transceiver firmware update ...' CLI command is disabled by EOS.
[fwUpdateInactiveCliDisabled]	*boolean*	Indicates that the 'transceiver firmware update ... inactive' CLI command is disabled by EOS.
[postEplPageWriteDelay]	*floating point number*	Additional delay in seconds to be added after writing every EPL page with a firmware load.
[postRunCommandWaitDuration]	*floating point number*	Duration in seconds EOS waits after the completion of the CDB 'run' command, and prior to executing the CDB 'commit' command.
[preEplFirmwareWriteDelay]	*floating point number*	Additional delay in seconds to be added after all EPL pages have been populated with the firmware load, and before the CDB write command is triggered by writing the LPL page.

2.2063.1.2 TransceiverCdbOperationModuleInfo

[alwaysApplyMsaPassword]	*boolean*	Indicates whether EOS will always write the MSA password.
[failOnCdbCompleteTimeout]	*boolean*	Indicates whether EOS will treat CDB complete timeouts as failures.
[failOnCdbStatusTimeout]	*boolean*	Indicates whether EOS will treat CDB status timeouts as failures.

[postWriteDelay]	*floating point number*	Additional delay in seconds to be added after SMBus write transactions.
[skipCdbCompletePolling]	*boolean*	Indicates whether EOS will skip reading the CDB complete register.
[stopDomPolling]	*boolean*	Indicates whether vital DOM data should be interrupted during CDB command execution.

2.2064 show transceiver controller state [...]

slots	*table(string) = Xcvr.XcvrCliModels.ControllerState* see 2.2064.1	a collection mapping each slot to its xcvr controller state.

2.2064.1 Xcvr.XcvrCliModels.ControllerState

controllerState	*enum: unavailable | operational | diagnostic*	the state of an xcvr controller.

2.2065 show transceiver error [...]

ports	*table(string) = TransceiverErrorValues* see 2.2065.1	Mapping between port name and transceiver errors.

2.2065.1 TransceiverErrorValues

transceiverErrors	*table(string) = TransceiverErrorValueFormat* see 2.2065.1.1	A mapping of error to its details.

2.2065.1.1 TransceiverErrorValueFormat

count	*integer*	Number of failures since system boot.
lastError	*floating point number*	Last error update time in UTC.

[lastReason]	*enum: faultCauseUnsupportedPower | faultCauseInvalidChecksum | smbusErrMonitor | moduleFaultCauseProgramMemCorrupted | moduleNoFaultCause | smbusErrEepromRead | configAccepted | smbusErrNone | moduleFaultCauseUnknown | moduleFaultCauseCustom | smbusErrConfig | moduleFaultCauseReserved | smbusErrUnspecified | configRejected | smbusErrInitialization | faultCauseSmbusError | configNoStatus | faultCauseNone | smbusErrFaulty | mixedAppsAccepted | moduleFaultCauseDataMemCorrupted | moduleFaultCauseTecRunaway | mixedAppsRejected | smbusErrTestPattern | mixedAppsNone | faultCauseUnsupportedXcvr*	Last reason for error.

2.2066 show transceiver error-correction coherent degrade [...]

slots	*table(Interface name) = TransceiverCoherentFecDegradeSlot* see 2.2066.1	Mapping between slot name and coherent error-correction degrade info.

2.2066.1 TransceiverCoherentFecDegradeSlot

[detected]	*TransceiverCoherentFecDegradeParameter* see 2.2066.1.1	Detected degrade status.
[excessive]	*TransceiverCoherentFecDegradeParameter* see 2.2066.1.1	Excessive degrade status.

2.2066.1.1 TransceiverCoherentFecDegradeParameter

[configured]	*TransceiverCoherentFecDegradeThresholds* see 2.2066.1.1.1	Values of configured degrade thresholds.
[operational]	*TransceiverCoherentFecDegradeThresholds* see 2.2066.1.1.1	Values of operational degrade thresholds.
status	*enum: unsupported* | *unknown* | *alarm* | *notPresent* | *ok*	Error-correction degrade alarm status.

2.2066.1.1.1 TransceiverCoherentFecDegradeThresholds

tClear	*floating point number*	Value of error-correction degrade clear threshold.
tRaise	*floating point number*	Value of error-correction degrade raise threshold.

2.2067 show transceiver squelch [...]

slots	*table(string) = TransceiverSquelchTypes* see 2.2067.1	Mapping between slot name and transceiver squelch types.

2.2067.1 TransceiverSquelchTypes

rxAutoSquelch	*TransceiverSquelchType* see 2.2067.1.1	Transceiver RX auto squelch.

2.2067.1.1 TransceiverSquelchType

[configured]	*enum: enabled* | *moduleDefault* | *disabled*	The user-configured squelch setting.
lanes	*table(numeric string) = TransceiverLaneSquelchSetting* see 2.2067.1.1.1	Mapping from lane to transceiver squelch setting.
supported	*boolean*	Configuration supported on this module.

2.2067.1.1.1 TransceiverLaneSquelchSetting

[default]	*boolean*	Module default setting.
operational	*boolean*	Module operational setting.

2.2068 show transceiver status [...]

see 2.990

2.2069 show transceiver status electrical tuning file

[configured]	*string*	Path to file configured.
[lastChange]	*floating point number*	Last update time in UTC.
[loadSuccess]	*boolean*	Loaded configured file.
[synchronized]	*boolean*	Synced to all transceiver managers.
[version]	*string*	Version of configured file.
waitingFor	*list of string*	Unsynced transceiver managers.

2.2070 show transceiver status firmware update [...]

ports	*table(string) = TransceiverFirmwareUpdateSlotDetail* see 2.2070.1	Mapping between the slot name and the firmware update information of the inserted transceiver.

2.2070.1 TransceiverFirmwareUpdateSlotDetail

[firmwareUpdate]	*TransceiverFirmwareUpdateStatus* see 2.2070.1.2	Firmware update status.
[hardwareDependentCommand]	*TransceiverFirmwareHardwareStatus* see 2.2070.1.1	Hardware-level firmware update command status.
serialNumber	*string*	Transceiver serial number.
serialNumberLastChange	*floating point number*	UTC timestamp of the last change.

2.2070.1.1 TransceiverFirmwareHardwareStatus

cdbCommandAckTimeout	*TransceiverFirmwareCdbTimeout* see 2.2070.1.1.1	Number of CDB command timeouts.
commandType	*enum: download | abort | run | start | commit | complete*	Last CDB command issued.
commandTypeLastChange	*floating point number*	UTC timestamp of the last change.
status	*enum: success | in progress | fail | unknown*	Last CDB command status.
[statusDetail]	*TransceiverFirmwareHardwareStatusDetail* see 2.2070.1.1.2	Details for the last CDB result.
statusLastChange	*floating point number*	UTC timestamp of the last change.

2.2070.1.1.1 TransceiverFirmwareCdbTimeout

lastChange	*floating point number*	UTC timestamp of the last change.
timeoutCount	*integer*	Number of CDB command timeouts.

2.2070.1.1.2 TransceiverFirmwareHardwareStatusDetail

[decoded]	*string*	Result of the last CDB command.
lastChange	*floating point number*	UTC timestamp of the last change.
[rawValue]	*integer*	Raw status code of the last CDB commands.

2.2070.1.2 TransceiverFirmwareUpdateStatus

downloadPercentage	*integer*	Firmware update progress.
downloadPercentageLastChange	*floating point number*	UTC timestamp of the last change.

restartPercentage	*integer*	Firmware restart progress.
restartPercentageLastChange	*floating point number*	UTC timestamp of the last change.
status	*enum: success | timeout | terminated | idle | failed | running*	Firmware update status.
statusLastChange	*floating point number*	UTC timestamp of the last change.

2.2071 show transceiver status firmware version [...]

[ports]	*table(string) = TransceiverFirmwareCollection* see 2.2071.1	Mapping between the slot name and the firmware version information of the inserted transceiver.

2.2071.1 TransceiverFirmwareCollection

firmware	*TransceiverFirmwareVersionDetailDict* see 2.2071.1.1	images present on the transceiver.

2.2071.1.1 TransceiverFirmwareVersionDetailDict

active	*table(string) = TransceiverFirmwareVersionDetail* see 2.2071.1.1.1	Mapping from an active image to the image details.
inactive	*table(string) = TransceiverFirmwareVersionDetail* see 2.2071.1.1.1	Mapping from an inactive image to the image details.

2.2071.1.1.1 TransceiverFirmwareVersionDetail

buildNum	*integer*	Firmware build number.
committed	*boolean*	This firmware image will become active upon transceiver reinsertion.
majorVer	*integer*	Firmware major version.
minorVer	*integer*	Firmware minor version.

2.2072 show transceiver traffic-loopback capabilities [...]

loopbackCaps	*table(Interface name) = Capabilities* see 2.2072.1	Loopback capabilities of each transceiver that supports CMIS based loopback.

2.2072.1 Capabilities

capabilities	*list of Capability* see 2.2072.1.1	Loopback capability set.
simultaneousHostMedia	*boolean*	Module supports simultaneous loopback configuration on both the host and the media side.

2.2072.1.1 Capability

kind	*enum: system | network | perLane*	The type of loopback capability, either indicates traffic source or the per-lane capability.
side	*enum: host | media*	The side of the transceiver on which the loopback is considered on.
supported	*boolean*	Loopback capability is supported.

2.2073 show transceiver traffic-loopback status [...]

transceiverLoopback	*table(Interface name) = SlotInfo* see 2.2073.1	Loopback configuration and status of each transceiver that supports CMIS based loopback.

2.2073.1 SlotInfo

hostLanes	*table(numeric string) = LaneInfo* see 2.2073.1.1	Host side lane configuration and status information, keyed by lane ID.
mediaLanes	*table(numeric string) = LaneInfo* see 2.2073.1.1	Media side lane configuration and status information, keyed by lane ID.

2.2073.1.1 LaneInfo

configured	*enum: system | network | none*	The loopback source configuration.
operational	*enum: system | notSupported | none | network | notPresent*	The operational state of the loopback source configuration.

2.2074 show tunnel counters ip-in-ip [...]

entries	*list of TunnelCountersEntry* see 2.2074.1	tunnel hardware counters.

2.2074.1 TunnelCountersEntry

[endpoint]	*IP address prefix*	Endpoint of the tunnel.
[payloadType] **	*enum: mpls | ipv4 | unknown | ipv6*	The type of payload transported by the tunnel. **Since: 4.33.2
tunnelIndex	*integer*	Index of the tunnel entry in the source tunnel table.
[tunnelName]	*string*	Name for the tunnel entry.
[txBytes]	*integer*	Total number of transmitted bytes.
[txPackets]	*integer*	Total number of transmitted packets.

2.2075 show tunnel counters mpls rate [...]

entries	*list of MplsTunnelCounters-RateEntry* see 2.2075.1	MPLS tunnel hardware rates.

2.2075.1 MplsTunnelCountersRateEntry

[endpoint]	*IP address prefix*	Endpoint of the tunnel.
tunnelIndex	*integer*	Index of the tunnel entry in the source tunnel table.
[tunnelName]	*string*	Name for the tunnel entry.
tunnelType	*enum: BGP LU Forwarding | maxTunnelType | IP-in-IP | MLDP P2MP | IS-IS SR IPv6 | invalidTunnel | IS-IS SR IPv4 | VXLAN VTEP Encap | IS-IS SRv6 | Nexthop | Static MPLS | SR-TE Policy | SR-TE | OSPF SR | IS-IS SRv6 TI-LFA | IS-IS FlexAlgo | Static IPv6 | Static MPLS Multicast | Nexthop Group | TI-LFA | LDP | RSVP LER SUB | SRv6 SR-TE SL | RSVP P2MP | RSVP LER | EosSdk sBFD | UDP | SRv6 Transport | EVPN VXLAN | VXLAN | RSVP FRR | IS-IS Remote TI-LFA | BGP LU | RSVP | IS-IS SR | Static | Static Interface*	Tunnel type.
[txBps]	*floating point number*	Bits per second.
[txPps]	*floating point number*	Packets per second.

2.2076 show tunnel counters udp [...]

see 2.2074

2.2077 show tunnel fib [...]

revision 2

categories	*table(string) = TunnelFibCategory* see 2.2077.1	Collections of tunnels in the FIB, grouped by tunnel service type.

2.2077.1 TunnelFibCategory

entries	*table(numeric string) = TunnelFibEntry* see 2.2077.1.1	Tunnel FIB entries for a tunnel type.

2.2077.1.1 TunnelFibEntry

[algorithm] **	*string*	Algorithm associated with the endpoint. **Since: 4.26.0
[aliasEndpoints] **	*list of IP address prefix*	Additional prefixes used for underlay nexthop resolution. **Since: 4.26.0
backupVias	*list of TunnelFibVia* see 2.193.1.2.6.1	List of tunnel backup vias.
[endpoint]	*IP address prefix*	Route prefix used for underlay nexthop resolution.
[gueTunnelEntryFields] **	*GueTunnelEntryFields* see 2.2077.1.1.1	GUE common fields. **Since: 4.31.2
[interface]	*string*	Interface name for tunnel.
[seqNo] **	*integer*	Sequence number of tunnel entry. **Since: 4.24.1
[tunnelFecId]	*integer*	FEC identifier.
[tunnelId]	*integer*	Tunnel identifier.
tunnelIndex	*integer*	Tunnel index within tunnel type.
tunnelType	*enum: BGP LU Forwarding | maxTunnelType | IP-in-IP | MLDP P2MP | invalidTunnel | VXLAN VTEP Encap | IS-IS SRv6 | Nexthop | Static MPLS | SR-TE Policy | SR-TE | OSPF SR | IS-IS SRv6 TI-LFA | IS-IS FlexAlgo | Static MPLS Multicast | Nexthop Group | TI-LFA | LDP | RSVP LER SUB | SRv6 SR-TE SL | RSVP P2MP | RSVP LER | EosSdk sBFD | UDP | SRv6 Transport | EVPN VXLAN | VXLAN | RSVP FRR | IS-IS Remote TI-LFA | BGP LU | RSVP | IS-IS SR | Static Interface*	Tunnel type.

[tunnelViaStatus]	*enum: usingPrimaryVias | usingBackupVias | notProgrammed | unknown | unresolved*	Tunnel programming status.
vias	*list of TunnelFibVia* see 2.193.1.2.6.1	List of tunnel vias.

2.2077.1.1.1 GueTunnelEntryFields

payloadType	*string*	Payload type.
source	*IP address*	Source address of the tunnel.
[tos]	*integer*	Type of service.
[ttl]	*integer*	Time to live.

2.2078 show tunnel fib multicast [...]

revision 2

see 2.2077

2.2079 show tunnel rib (system-tunneling-ldp-tunnel-rib | system-igp-shortcut-tunnel-rib | system-tunnel-rib | (colored (system-colored-tunnel-rib | system-colored-tunneling-ldp-tunnel-rib | system-colored-igp-shortcut-tunnel-rib)) | TUNNEL_RIB_NAME) summary

name	*string*	Tunnel RIB name.
tunnels	*table(string) = integer*	Tunnel count keyed by tunnel type.

2.2080 show tunnel rib brief [...]

revision 3

entries	*table(IPv4 or IPv6 address prefix) = TunnelRibEntries-ByTunnelType* see 2.2080.1	Tunnel entries keyed by prefix.
name	*string*	Tunnel RIB name.

2.2080.1 TunnelRibEntriesByTunnelType

entries	*list of TunnelRibEntry* see 2.2080.1.1	List of tunnel entries of different tunnel types towards the same endpoint.

2.2080.1.1 TunnelRibEntry

metric	*integer*	IGP metric of tunnel endpoint entry.
metric2	*integer*	IGP metric 2 of tunnel endpoint entry.

[metricType] **	*enum: AIGP | MED | metric*	Metric type of tunnel endpoint entry. **Since: 4.26.0
pref	*integer*	Underlying IGP route's preference.
pref2	*integer*	Preference 2 of tunnel endpoint entry.
tunnelIndexes	*list of integer*	List of tunnel indexes ending at this tunnel endpoint.
tunnelPreference	*integer*	Tunnel preference used for tunnel RIB election.
tunnelType	*enum: BGP LU Forwarding | maxTunnelType | IP-in-IP | MLDP P2MP | IS-IS SR IPv6 | invalidTunnel | IS-IS SR IPv4 | VXLAN VTEP Encap | IS-IS SRv6 | Nexthop | Static MPLS | SR-TE Policy | SR-TE | OSPF SR | IS-IS SRv6 TI-LFA | IS-IS FlexAlgo | Static IPv6 | Static MPLS Multicast | Nexthop Group | TI-LFA | LDP | RSVP LER SUB | SRv6 SR-TE SL | RSVP P2MP | RSVP LER | EosSdk sBFD | UDP | SRv6 Transport | EVPN VXLAN | VXLAN | RSVP FRR | IS-IS Remote TI-LFA | BGP LU | RSVP | IS-IS SR | Static | Static Interface*	Tunnel type.

2.2081 show tunnel rib candidates [...]

endpoints	*table(IPv4 or IPv6 address prefix) = InternalTunnelRibCandidates* see 2.2081.1	Candidate tunnel entries, keyed by prefix.
name	*string*	Tunnel RIB name.

2.2081.1 InternalTunnelRibCandidates

candidates	*list of InternalTunnelRibCandidateEntry* see 2.2081.1.1	Candidate entries for tunnel RIB election, sorted by preference order.

2.2081.1.1 InternalTunnelRibCandidateEntry

tunnelIndexes	*list of integer*	Indexes of tunnels ending at this tunnel endpoint.
tunnelMetric	*integer*	Tunnel metric used for tunnel RIB election.
tunnelPreference	*integer*	Tunnel preference used for tunnel RIB election.

tunnelType	*enum: BGP LU Forwarding | maxTunnelType | IP-in-IP | MLDP P2MP | IS-IS SR IPv6 | invalidTunnel | IS-IS SR IPv4 | VXLAN VTEP Encap | IS-IS SRv6 | Nexthop | Static MPLS | SR-TE Policy | SR-TE | OSPF SR | IS-IS SRv6 TI-LFA | IS-IS FlexAlgo | Static IPv6 | Static MPLS Multicast | Nexthop Group | TI-LFA | LDP | RSVP LER SUB | SRv6 SR-TE SL | RSVP P2MP | RSVP LER | EosSdk sBFD | UDP | SRv6 Transport | EVPN VXLAN | VXLAN | RSVP FRR | IS-IS Remote TI-LFA | BGP LU | RSVP | IS-IS SR | Static | Static Interface*	Tunnel type.

2.2082 show tunnel rib colored brief [...]

endpoints	*table(IPv4 or IPv6 address prefix) = TunnelRibColors* see 2.2082.1	Colored tunnel entries keyed by endpoint.
name	*string*	System colored tunnel RIB name.

2.2082.1 TunnelRibColors

colors	*table(numeric string) = TunnelRibEntry* see 2.2080.1.1	Colored tunnel entries keyed by color.

2.2083 show tunnel rib multicast (mldp | rsvp | static)

name	*string*	Tunnel RIB name.
tunnels	*table(string) = MulticastTunnelRibEntry* see 2.2083.1	Tunnel entries keyed by FEC Element.

2.2083.1 MulticastTunnelRibEntry

tunnelIndexes	*list of integer*	List of tunnel indexes ending at this tunnel endpoint.
tunnelType	*enum: BGP LU Forwarding | maxTunnelType | IP-in-IP | MLDP P2MP | IS-IS SR IPv6 | invalidTunnel | IS-IS SR IPv4 | VXLAN VTEP Encap | IS-IS SRv6 | Nexthop | Static MPLS | SR-TE Policy | SR-TE | OSPF SR | IS-IS SRv6 TI-LFA | IS-IS FlexAlgo | Static IPv6 | Static MPLS Multicast | Nexthop Group | TI-LFA | LDP | RSVP LER SUB | SRv6 SR-TE SL | RSVP P2MP | RSVP LER | EosSdk sBFD | UDP | SRv6 Transport | EVPN VXLAN | VXLAN | RSVP FRR | IS-IS Remote TI-LFA | BGP LU | RSVP | IS-IS SR | Static | Static Interface*	Tunnel type.

2.2084 show tunnel rib summary

tunnels	*table(string) = integer*	Tunnel count keyed by tunnel RIB name.

2.2085 show twserver [...]

[listenPort]	*integer*	Server's listening port.
[localIpOrHost]	*string*	Local address.
[maxControlSessions]	*integer*	Maximum control sessions.
[maxTestPort]	*integer*	Maximum test port.
[minTestPort]	*integer*	Minimum test port.
[startTime]	*floating point number*	Twserver boot time in epoch.

2.2086 show twserver summary

activeVrfs	*list of string*	VRFs with servers running.
configuredVrfs	*list of string*	VRFs with servers configured.
serverStartAttempts	*integer*	Total number of server start attempts.
serverStartSuccesses	*integer*	Total number of server start successes.
serverStopAttempts	*integer*	Total number of server stop attempts.
serverStopSuccesses	*integer*	Total number of server stop successes.

2.2087 show uptime

see 2.1751.2

2.2088 show users

serials	*table(string) = Aaa.Cli.ShowAaaUserInfo* see 2.2088.1	Terminal information for serial connection.
vtys	*table(string) = Aaa.Cli.ShowAaaUserInfo* see 2.2088.1	Terminal information for ssh or telnet connections.

2.2088.1 Aaa.Cli.ShowAaaUserInfo

idleTime	*integer*	Duration of session's inactivity in seconds.
lineNumber	*integer*	Line number of the user session.
lineType	*enum: con | vty*	The line type of the user session.
[location]	*string*	Source IP address or hostname for vty sessions and absent for serial connections.
sessionTty	*boolean*	Indicates if this is the terminal used by the session that just ran this command.
user	*string*	Login name of the user of this session.

2.2089 show users accounts

users	*table(string) = Aaa.Cli.User* see 2.2089.1	Maps a username to details for this user.

2.2089.1 Aaa.Cli.User

privLevel	*integer*	The configured privilege level for this user (between 0 and 15 inclusive).
[role]	*string*	What role the account has been given (e.g. 'network-admin').
secondarySshKeys **	*list of string*	SSH secondary keys for this user. **Since: 4.28.2
[sshAuthorizedKey]	*string*	SSH public key for this user.
username	*string*	The username of this account.

2.2090 show users detail

nonInteractives	*table(numeric string) = Aaa.Cli.AaaSession* see 2.2090.1	Session information for nonInteractive connections.
serials	*table(numeric string) = Aaa.Cli.AaaSession* see 2.2090.1	Session information for serial connections.

vtys	*table(numeric string) = Aaa.Cli.AaaSession* see 2.2090.1	Session information for ssh or telnet connections.

2.2090.1 Aaa.Cli.AaaSession

authMethod	*string*	Authentication method of the session.
[remoteAddress]	*string*	Remote ip address.
[remoteHost]	*string*	Remote hostname.
role	*string*	Role assigned to the user.
[service]	*string*	Service.
sessionStartTime	*integer*	UTC time at which session was started.
state	*enum: pending | established*	State of the session either established or pending.
[terminal]	*string*	Maps to terminal type and terminal number.
username	*string*	Login name of the user of this session.

2.2091 show users roles [...]

defaultRole	*string*	Default role.
roles	*table(string) = Aaa.Cli.Rules* see 2.2091.1	Display the contents of built-in and user-defined roles.

2.2091.1 Aaa.Cli.Rules

rules	*list of Aaa.Cli.ShowRolesList* see 2.2091.1.1	A mapping of an authorization role name to its rules.

2.2091.1.1 Aaa.Cli.ShowRolesList

cmdPermission	*enum: deny | permit*	If match is found against a rule, decision is based on that rule and all other rules followed are ignored. If no match is found, the command is denied by default.
cmdRegex	*string*	Regular expression that corresponds to one or more CLI commands.
[mode]	*string*	The regex of a cli mode name for which this rule applies, if absent, rule is valid in all modes.
sequenceNumber	*integer*	Sequence number designates a rule's placement in the role, value ranges from 1 to 256.

2.2092 show version [...]

architecture	*string*	Control plane CPU architecture.
bootupTimestamp	*floating point number*	Bootup timestamp of the system.
[configMacAddress] **	*MAC address*	Configured MAC address of the system, change takes effect only after reboot. Available only on fixed systems. **Since: 4.24.0
[details]	*Details* see 2.2092.1	Detailed version information.
hardwareRevision	*string*	Name of the hardware revision of the switch.
[hwMacAddress] **	*MAC address*	Hardware MAC address of the system (might not be in use if there is a configured MAC). **Since: 4.24.0
imageFormatVersion **	*string*	EOS image format version number. **Since: 4.26.2
imageOptimization **	*string*	Optimization name of squash filesystem booted by the switch. **Since: 4.27.2
internalBuildId	*string*	Unique internal build ID.
internalVersion	*string*	Full internal EOS version number.
isIntlVersion **	*boolean*	Whether the running image is an international EOS image. **Since: 4.17.0
[kernelVersion] **	*string*	Kernel version. **Since: 4.25.0
memFree	*integer*	Available free memory in KB.
memTotal	*integer*	Size of the memory in KB.
mfgName **	*string*	Manufacturer name of the switch. **Since: 4.21.3
modelName	*string*	Model name of the switch.
serialNumber	*string*	Serial number of the switch.
systemMacAddress	*MAC address*	The operational MAC address of the system.
uptime **	*floating point number*	Uptime of the system. **Since: 4.21.0
version	*string*	EOS software image version.

2.2092.1 Details

components	*list of Component* see 2.2092.1.3	Hardware component versions.
deviations	*list of string*	List of hardware deviations.
[imageHistory] **	*list of ImageHistoryEntry* see 2.2092.1.1	History of changes to this image. **Since: 4.35.2
[onieVersion] **	*string*	Version of onie-installer used to provision EOS on the switch. **Since: 4.22.0
packages	*table(string) = Package* see 2.2092.1.2	RPM packages installed on the switch, keyed by package name.

switchType	*enum: fixedSystem* | *unknown* | *chassis*	The physical type of switch. Is 'unknown' if the system has not initialized.
systemEpoch **	*string*	Version of the system epoch. **Since: 4.17.0

2.2092.1.1 ImageHistoryEntry

description	*string*	Description of change.
[extra]	*string*	Additional details of change.
hostname	*string*	Hostname.
timestamp	*floating point number*	UTC timestamp of image modification.
username	*string*	Username.

2.2092.1.2 Package

release	*string*	Release string of the RPM package.
version	*string*	Version string of the package.

2.2092.1.3 Component

name	*string*	Name of the hardware component.
version	*string*	Version of the hardware component.

2.2093 show version compatibility SWI

errorList	*list of string*	List of compatibility blocking errors.
image	*string*	Software image URL.
warningList	*list of string*	List of compatibility warnings.

2.2094 show version firmware

Could also be an instance of:
Details 2.2092.1

components	*list of Component* see 2.2092.1.3	Hardware component versions.
switchType	*enum: fixedSystem* | *unknown* | *chassis*	The physical type of switch. Is 'unknown' if the system has not initialized.

see 2.2092.1

2.2095 show version license

licenses	*table(string) = string*	Licenses covering software present in EOS.

2.2096 show vlan [...]

[sourceDetail]	*string*	A description of the source of this configuration. When using MLAG, this field may indicate that the primary peer provided a config that overrides the secondary's local config.
vlans	*table(numeric string) = Status* see 2.2096.1	Configured VLANs, keyed by VLAN Id.

2.2096.1 Status

dynamic	*boolean*	Indicates whether or not this VLAN is dynamic.
interfaces	*table(string) = Interface* see 2.2096.1.1	List of interfaces that are a member of this VLAN, keyed by interface name.
name	*string*	VLAN name.
status	*enum: inactive | suspended | active*	VLAN administrative status.

2.2096.1.1 Interface

[annotation]	*string*	Annotation explaining any configuration specific to this interface, i.e. that the interface is in a port-channel.
blocked **	*boolean*	Traffic is being blocked on this interface. **Since: 4.26.0
egressOnly **	*boolean*	Tagged traffic can only egress on this interface. **Since: 4.35.2
[function] **	*string*	Use of this interface. **Since: 4.26.2
[functionDetail] **	*string*	Use of this interface. **Since: 4.26.2
privatePromoted	*boolean*	This is a private VLAN promoted port.

2.2097 show vlan brief [...]

see 2.2096

2.2098 show vlan brief count

[sourceDetail]	*string*	A description of the source of this configuration. When using MLAG, this field may indicate that the primary peer provided a config that overrides the secondary's local config.
totalVlans	*integer*	Number of existing VLANs.

2.2099 show vlan counters [...]

vlanCountersInfo	*table(numeric string) = VlanStats* see 2.2099.1	A mapping between VLAN ID and counter data.

2.2099.1 VlanStats

inBcastPkts	*integer*	Input broadcast packets.
inMcastPkts	*integer*	Input multicast packets.
inOctets	*integer*	Input octets.
inUcastPkts	*integer*	Input unicast packets.
outBcastPkts	*integer*	Output broadcast packets.
outMcastPkts	*integer*	Output multicast packets.
outOctets	*integer*	Output octets.
outUcastPkts	*integer*	Output unicast packets.

2.2100 show vlan dynamic

dynamicVlans	*table(string) = VlanIds* see 2.621.1.2	A Mapping between the Dynamic VLAN source and the VLANS.

2.2101 show vlan floodset expanded [...]

vlans	*table(numeric string) = FloodsetExpandedVlanModel* see 2.2101.1	Floodset expanded configurations, keyed by VLAN ID.

2.2101.1 FloodsetExpandedVlanModel

floodsetExpandedVlanId	*integer*	Target floodset expanded VLAN ID.
reason	*enum: valid | nonexistent | conflict*	Reason for the status of the expanded floodset configuration.

2.2102 show vlan interface dynamic

agents	*table(string) = VlanIntfs* see 2.2102.1	A Mapping between the Dynamic VLAN interface source and the VLANS.

2.2102.1 VlanIntfs

interfaces	*list of Interface name*	A list of the VLAN interfaces.

2.2103 show vlan internal allocation policy

endVlanId	*integer*	Ending VLAN Id.
policy	*enum: ascending | descending*	Internal VLAN allocation policy.
startVlanId	*integer*	Starting VLAN Id.

2.2104 show vlan internal usage

internalVlans	*table(numeric string) = string*	Mapping between the VLAN Id and the VLAN Name.

2.2105 show vlan internal usage reserved

internalVlans	*table(numeric string) = string*	Mapping between the VLAN Id and the corresponding Interface Name.

2.2106 show vlan private-vlan

privateVlans	*table(numeric string) = PrivateVlans* see 2.2106.1	A mapping between a primary VLAN Id and a list of private VLAN information.

2.2106.1 PrivateVlans

privateVlan	*list of PrivateVlan* see 2.2106.1.1	A list of the private VLAN information.

2.2106.1.1 PrivateVlan

interfaces	*list of Interface name*	List of interfaces in VLAN.
secondaryVlanId	*integer*	The secondary VLAN Id.
vlanType	*enum: community | normal | isolated*	The type of Private VLAN.

2.2107 show vlan trunk group [...]

[sourceDetail]	*string*	A description of the source of this configuration. When using MLAG, this field may indicate that the primary peer provided a config that overrides the secondary's local config.
trunkGroups	*table(numeric string) = GroupNames* see 2.2107.1	Trunk groups associated with each VLAN.

2.2107.1 GroupNames

names	*list of string*	Trunk group names.

2.2108 show vmtracer all [...]

revision 2

sessions	*table(string) = VmTracerSwitches* see 2.2108.1	A mapping of session names to vCenter switches.

2.2108.1 VmTracerSwitches

switches	*table(string) = SwitchInterfaces* see 2.2108.1.1	A mapping of switch names to switch interface sets.

2.2108.1.1 SwitchInterfaces

intfs	*table(string) = VmTracerInterface* see 2.2108.1.1.1	A mapping of interface names to interfaces.

2.2108.1.1.1 VmTracerInterface

hostName	*string*	Host name where this interface is attached.
switchName	*string*	Vswitch this interface is attached to.
uplinkName	*string*	Uplink port this interface is attached to.
vms	*table(MAC address) = VmTracerVm* see 2.2108.1.1.1.1	A mapping between VM mac and VM information.

2.2108.1.1.1.1 VmTracerVm

datacenter	*string*	Name of the Data Center where the VM resides.
[failoverToleranceState]	*enum: ftDisabled | ftStandby | ftActive*	Failover tolerance state.
host	*string*	Host name where VM resides.
[inVmotion]	*boolean*	Flag indicating if a VM is being Vmotioned.
interface	*string*	Interface on which the VM is connected.
[logicalSwitch]	*string*	Name of Vmware logical switch this vm is connected to.
macAddress	*MAC address*	MAC address of the VM.
[macStatus]	*enum: learnt | unlearnt*	VM Mac address learn status.
[nsxConnected]	*boolean*	Flag indicating if an NSX connection is active.
[physicalNic]	*string*	Name of the physical nic the VM is attached to.
portGroup	*string*	Name of the port group to which the VM belongs.
powerStatus	*enum: down | up*	Power status of the VM.
switch	*string*	Name of the vSwitch or DVS the VM is on.
[switchMtu]	*integer*	MTU of the vSwitch or DVS this VM is on.

[transportVlan]	*integer*	Transport VLAN for VXLAN VTEP.
[transportZone]	*string*	VXLAN Transport Zone of this VM.
[vCenterUrl]	*string*	Url of associated vCenter instance.
vNic	*string*	Name of the Vm Nic.
vlan	*string*	Portgroup vlan as 'native', 'trunk' or string representation of a vlan.
vmName	*string*	Name of the VM.
[vmType]	*enum: vmStandard | vmKernel*	Type of VM entry.
[vni]	*integer*	VNI of VXLAN that this VM is attached to.
[vtepIp]	*IPv4 address*	IP address of the VTEP used by this vm.

2.2109 show vmtracer interface INTFS vm VMNAME

intfs	*table(Interface name) = VmTracerGenericInterface* see 2.2109.1	A mapping of interface names to interfaces.

2.2109.1 VmTracerGenericInterface

Could also be an instance of:
VmTracerInterface 2.2108.1.1.1
VmTracerLagInterface 2.2109.2

vms	*table(MAC address) = VmTracerVm* see 2.2108.1.1.1.1	A mapping between VM mac and VM information.

2.2109.2 VmTracerLagInterface

members	*table(Interface name) = VmTracerInterface* see 2.2108.1.1.1	A mapping between interface names and LAG members.
vms	*table(MAC address) = VmTracerVm* see 2.2108.1.1.1.1	A mapping between VM mac and VM information.

2.2110 show vmtracer interface [...]

see 2.2109

2.2111 show vmtracer logical-switch [...]

scopes	*table(string) = NetworkScope* see 2.2111.1	A mapping of network scope display names to scopes.

2.2111.1 NetworkScope

[desc] **	*string*	Description of the network scope. **Since: 4.20.0
switches	*table(string) = LogicalSwitch* see 2.2111.1.1	A mapping of logical switch ids to switches.

2.2111.1.1 LogicalSwitch

controlPlane	*ControlPlane* see 2.2111.1.1.1	Mode of VMWare control plane.
displayName	*string*	Logical switch display name.
vni	*integer*	VXLAN VNI.

2.2111.1.1.1 ControlPlane

[mcastAddr]	*IPv4 address*	VXLAN ARP broadcast address.
mode	*enum: multicast | hybrid | unicast*	NSX mode.

2.2112 show vmtracer session SESSION (vcenter | vsm) [...]

sessionStatuses	*table(string) = VmTracerSessionStatus* see 2.2112.1	A mapping of session names to status information.

2.2112.1 VmTracerSessionStatus

[vCenterStatus]	*VCenterServiceStatus* see 2.2112.1.1	vCenter status.
[vShieldStatus]	*VShieldServiceStatus* see 2.2112.1.2	vShield manager status.

2.2112.1.1 VCenterServiceStatus

allowedVlans	*VlanIds* see 2.621.1.2	List of VLANs allowed in the vCenter session.
autoVlan	*boolean*	Whether auto VLAN provision is enabled.
serviceStatus	*WebServiceStatus* see 2.2112.1.1.1	vCenter appliance service status.

2.2112.1.1.1 WebServiceStatus

[details]	*StatusDetail* see 2.2112.1.1.1.1	Details of connection status associated with vShield/vCenterthat is only populated when requested by cli command.
sessionState	*enum: stateConnecting | stateUnknown | stateDisconnected | stateConnected*	Current vCenter/vShield session state.
sourceIntf **	*interface name*	Local interface for vCenter/vShield connections. **Since: 4.21.3
url	*string*	vCenter/vShield/NSX-V URL.
username	*string*	vCenter/vShield username.
vrf **	*string*	vCenter/vShield VRF. **Since: 4.21.3
vrfStatus **	*enum: vrfStatusError | vrfStatusUnknown | vrfStatusReady | vrfStatusWaiting*	VRF state of current session. **Since: 4.21.3

2.2112.1.1.1.1 StatusDetail

lastErrorCode	*string*	The last error code.
lastFailedMsg	*string*	The last failed message.
lastFailedMsgTime	*floating point number*	The time of the last failed message.
lastMsgSent	*string*	The last message sent.
lastStateChangeTime	*floating point number*	The time of last state change.
lastSuccessfulMsg	*string*	The last successful message.
lastSuccessfulMsgTime	*floating point number*	The time of the last successful message.
numFailedMsg	*integer*	The number of failed messages.

numSuccessfulMsg	*integer*	The number of successful messages.
responseTimeForLastMsg	*floating point number*	The time it took, in seconds, to send response for the last message.
timeOfLastMsg	*floating point number*	The time of the last message.

2.2112.1.2 VShieldServiceStatus

serviceStatus	*WebServiceStatus* see 2.2112.1.1.1	vShield appliance service status.

2.2113 show vmtracer session [...]

see 2.2112

2.2114 show vmtracer vm VM_NAME

revision 2

staleSessions	*table(string) = floating point number*	A mapping of stale session names to their sync time.
vms	*list of VmTracerVm* see 2.2108.1.1.1.1	List of VMs.

2.2115 show vmtracer vm [...]

revision 2

see 2.2114

2.2116 show vmtracer vxlan segment [...]

see 2.2111

2.2117 show vmtracer vxlan segment range

mcastRanges	*list of McastRange* see 2.2117.1	Multicast range.
vniRanges	*list of VniRange* see 2.2117.2	Vni range.

2.2117.1 McastRange

begin	*IPv4 address*	Start of Multicast Range.
end	*IPv4 address*	End of Multicast Range.

2.2117.2 VniRange

`begin`	*integer*	Start of VNI range.
`end`	*integer*	End of VNI range.

2.2118 show vpls [...]

revision 2

instances	*table(string) = VplsInstance* see 2.2118.1	VPLS instance information keyed by instance name.

2.2118.1 VplsInstance

macWithdrawalTrigger-Interface	*boolean*	Send MAC withdrawal messages on instance pseudowires when VPLS local interface goes down.
pseudowireGroups	*table(string) = VplsPseudowireGroup* see 2.2118.1.1	VPLS pseudowire group information keyed by group name.
vlans	*table(numeric string) = VplsVlan* see 2.2118.1.2	VPLS VLAN information keyed by VLAN ID.

2.2118.1.1 VplsPseudowireGroup

[forwardingPreferenceEvpn]	*boolean*	Prefer EVPN control plane for data forwarding as per RFC8560.
[macWithdrawalPropagation]	*enum: locallyTriggered | suppress | locallyTriggered-AndReceived*	Propagate locally triggered and received MAC withdrawal messages.
[macWithdrawalTriggerOn-PseudowireFailure]	*boolean*	Trigger MAC withdrawal transmission when a group pseudowire state transitions away from up.
neighbors	*table(IPv4 or IPv6 address) = VplsPseudowireGroup-Neighbor* see 2.2118.1.1.1	VPLS neighbor pseudowire information keyed by neighbor address.
[profile]	*string*	VPLS auto-discovery LDP pseudowire profile configuration.
signalingProtocol	*enum: ldp | bgp*	The signaling protocol used to negotiate the pseudowires in the group.
splitHorizon	*boolean*	VPLS split-horizon rule enforced across group pseudowires.

2.2118.1.1.1 VplsPseudowireGroupNeighbor

pseudowires	*table(string) = VplsPseudowire* see 2.2118.1.1.1.1	VPLS pseudowire information keyed by pseudowire ID.

2.2118.1.1.1.1 VplsPseudowire

[controlWord]	*boolean*	Control word used.
[flowLabelUsed]	*enum: disabled | both | receive | transmit*	Flow label used.
[interface]	*interface name*	Pseudowire interface.

[lastNegativeMacWithdrawal-ReceivedTime]	*floating point number*	Time when last negative MAC withdrawal all-from-me message was received.
[lastNegativeMacWithdrawal-SentTime]	*floating point number*	Time when last negative MAC withdrawal all-from-me message was sent.
[localConfig]	*LdpPseudowirePeerConfig* see 2.1330.1.1.2.3	Local pseudowire configuration.
[localStatus]	*enum: standby | up*	Local pseudowire status.
[negativeMacWithdrawal-Received]	*integer*	Number of negative MAC withdrawal all-from-me messages received.
[negativeMacWithdrawalSent]	*integer*	Number of negative MAC withdrawal all-from-me messages sent.
[neighborConfig]	*LdpPseudowirePeerConfig* see 2.1330.1.1.2.3	Neighbor pseudowire configuration.
[neighborStatus]	*enum: pwNotForwardingRemote | down | up | noRemoteEnd | mtuMismatch | standby | noLocalMapping | pwTypeMismatch | noPeerLabel | controlWordMismatch*	Neighbor pseudowire status.
[pseudowireType]	*enum: pwType5 | pwType4*	Pseudowire type.
status	*enum: pwNotForwardingRemote | noTunnelRib | unsupportedTunnelMode | neighborEvpn | down | up | noRemoteEnd | mtuMismatch | noTunnel | standby | noLocalMapping | pwTypeMismatch | noPeerLabel | cliConflict | controlWordMismatch | cliIncomplete*	Pseudowire status.
[tunnelIndexes]	*list of integer*	List of tunnel indexes ending at this tunnel endpoint.

[tunnelType]	*enum: BGP LU Forwarding | maxTunnelType | IP-in-IP | MLDP P2MP | IS-IS SR IPv6 | invalidTunnel | IS-IS SR IPv4 | VXLAN VTEP Encap | IS-IS SRv6 | Nexthop | Static MPLS | SR-TE Policy | SR-TE | OSPF SR | IS-IS SRv6 TI-LFA | IS-IS FlexAlgo | Static IPv6 | Static MPLS Multicast | Nexthop Group | TI-LFA | LDP | RSVP LER SUB | SRv6 SR-TE SL | RSVP P2MP | RSVP LER | EosSdk sBFD | UDP | SRv6 Transport | EVPN VXLAN | VXLAN | RSVP FRR | IS-IS Remote TI-LFA | BGP LU | RSVP | IS-IS SR | Static | Static Interface*	Tunnel type.
[vccvCcTypes]	*integer*	VCCV CC types used.
[vccvCvTypes]	*integer*	VCCV CV types used.

2.2118.1.2 VplsVlan

[normalizedTag]	*integer*	Pseudowire VPLS 802.1Q tag value.

2.2119 show vpls pseudowire brief (all | { (neighbor NEIGHBOR) | (pseudowire-type PW_TYPE) }) [...]

revision 2

see 2.2118

2.2120 show vrf [...]

vrfs	*table(string) = VrfEntry* see 2.2120.1	Mapping of Vrf name to Vrf information.

2.2120.1 VrfEntry

interfaces	*list of Interface name*	List of interfaces which are assigned to this vrf.
[interfacesV4] **	*list of Interface name*	List of IPv4 interfaces which are assigned to this vrf. **Since: 4.26.2
[interfacesV6] **	*list of Interface name*	List of IPv6 interfaces which are assigned to this vrf. **Since: 4.26.2

protocols	*IpProtocolDesc* see 2.2120.1.1	Information on ipv4 and ipv6 support for this vrf.
routeDistinguisher	*string*	Route Distinguisher associated with this vrf.
[vrfId] **	*integer*	Id associated with this vrf. **Since: 4.31.2
vrfState	*enum: deleting | up | creating*	Various states of vrf. 'creating' indicates vrf is being created, 'up' indicates vrf is created successfully and 'deleting' indicates vrf is being deleted.

2.2120.1.1 IpProtocolDesc

ipv4	*ProtocolInfo* see 2.2120.1.1.1	ipv4 protocol information for a vrf.
ipv6	*ProtocolInfo* see 2.2120.1.1.1	ipv6 protocol information for a vrf.

2.2120.1.1.1 ProtocolInfo

[multicastState]	*enum: up | initializing*	Indicates the state of the multicast routing after it is configured.
protocolState	*enum: down | up*	Protocol state is down when the vrf is being created, state is up otherwise.
routingState	*enum: down | up | initializingUp | initializingDown*	Indicates the various states of routing for the Vrf.'up' indicates routing is enabled for this vrf. 'down' indicates routing is disabled for this vrf. 'initializing up/down' indicates routing state is being configured.
supported	*boolean*	Indicates whether the protocol is supported.

2.2121 show vrf leak connected (ipv4 | ipv6)

destVrfs	*table(string) = LeakedConnectedRoutes* see 2.2121.1	A mapping of destination VRF to leaked connected routes.

2.2121.1 LeakedConnectedRoutes

routes	*table(IPv4 or IPv6 address prefix) = string*	A mapping of route prefix to the VRF that leaked it.

2.2122 show vrf leak id

vrfs	*table(string) = integer*	A mapping between VRF name and VRF ID.

2.2123 show vrf reserved-ports [...]

vrfs	*table(string) = VrfReservedPortsEntry* see 2.2123.1	Mapping of VRF name to its reserved ports.

2.2123.1 VrfReservedPortsEntry

config	*string*	Reserved Ports configuration associated with this VRF.
status	*string*	Reserved Ports status associated with this VRF.

2.2124 show vrf selection policy

[nexthopFeature] **	*enum: decapVrf | fallbackDecapVrf | none*	Next-hop feature status. **Since: 4.32.2
[vrfSelectionPolicies]	*table(string) = TrafficPolicy* see 2.2048.1	VRF selection policy indexed by policy name.

2.2125 show vrf selection policy errors

[vrfSelectionPolicies]	*table(string) = TrafficPolicyErrors* see 2.2050.1	VRF selection policy indexed by policy name.

2.2126 show vrf selection policy field-set ipv4 prefix [...]

see 2.2053

2.2127 show vrf selection policy field-set ipv6 prefix [...]

see 2.2053

2.2128 show vrf summary

vrfCount	*integer*	Number of VRFs.
vrfUpCount	*integer*	Number of up VRFs.
vrfV4RoutingCount	*integer*	Number of VRFs supporting IPv4 routing.
vrfV6RoutingCount	*integer*	Number of VRFs supporting IPv6 routing.

2.2129 show vrrp [...]

virtualRouters	*list of VrrpRouterDetailBase* see 2.2129.1	Virtual router status.

2.2129.1 VrrpRouterDetailBase

Could also be an instance of:
VrrpRouterDetailV4 2.2129.2
VrrpRouterDetailV6 2.2129.3

description	*string*	Vrrp description.
groupId	*integer*	VRRP group ID.
interface	*interface name*	Name of the interface.
macAddressInterval	*integer*	The time in seconds between sending neighbor discovery or arp of the virtual mac address.
masterDownInterval	*integer*	The master down interval of the virtual router in milliseconds.
masterInterval	*integer*	The master advertisement interval in seconds.
masterPriority	*integer*	Priority of the master virtual router.
preempt	*boolean*	Preemption status.
preemptDelay	*integer*	Preemption delay time in seconds.
preemptReload	*integer*	Preemption reload delay time in seconds.
priority	*integer*	Priority of the virtual router.
skewTime	*floating point number*	The skew of the master down interval in seconds.
state	*enum: backup | stopped | master*	stopped – the virtual router has been shutdown, backup – the virtual router is in backup mode, master – the virtual router is the master of the VRRP group.
stateTransitionTime **	*floating point number*	Timestamp in UTC of last VRRP state transition. **Since: 4.22.0
trackedObjects **	*list of TrackedObject* see 2.2129.1.1	Vrrp tracked objects. **Since: 4.21.3
version	*integer*	VRRP version.
virtualMac	*MAC address*	The virtual mac address of this vrrp group.
vrIdDisabled **	*boolean*	Virtual router id is disabled. **Since: 4.15.2
vrIdDisabledReason **	*string*	Virtual router id disabled description. **Since: 4.15.2
[vrfName]	*string*	Name of VRF.
vrrpAdvertInterval	*integer*	The time in seconds between sending Vrrp packets.

2.2129.1.1 TrackedObject

interface	*interface name*	Name of the interface.
priority	*integer*	Priority of the tracked object.
shutdown	*boolean*	Shutdown action.

trackedObject	*string*	Tracked object.

2.2129.2 VrrpRouterDetailV4

[authSringEncrytType] **	*enum: 7 | 8a*	The authentication password encryption algorithm. **Since: 4.31.0
[authString]	*string*	The authentication password encrypted text.
[authType]	*enum: md5 | text*	The type of authentication being used.
bfdPeerAddr **	*IPv4 address*	Bfd peer of the virtual router. **Since: 4.21.3
[bfdPeerState] **	*enum: shuttingDown | down | up*	Bfd peer state of the virtual router. **Since: 4.25.2
description	*string*	Vrrp description.
groupId	*integer*	VRRP group ID.
interface	*interface name*	Name of the interface.
macAddressInterval	*integer*	The time in seconds between sending neighbor discovery or arp of the virtual mac address.
masterAddr	*IPv4 address*	Current address of the master virtual router.
masterDownInterval	*integer*	The master down interval of the virtual router in milliseconds.
masterInterval	*integer*	The master advertisement interval in seconds.
masterPriority	*integer*	Priority of the master virtual router.
preempt	*boolean*	Preemption status.
preemptDelay	*integer*	Preemption delay time in seconds.
preemptReload	*integer*	Preemption reload delay time in seconds.
priority	*integer*	Priority of the virtual router.
skewTime	*floating point number*	The skew of the master down interval in seconds.
state	*enum: backup | stopped | master*	stopped – the virtual router has been shutdown, backup – the virtual router is in backup mode, master – the virtual router is the master of the VRRP group.
stateTransitionTime **	*floating point number*	Timestamp in UTC of last VRRP state transition. **Since: 4.22.0
trackedObjects **	*list of TrackedObject* see 2.2129.1.1	Vrrp tracked objects. **Since: 4.21.3
version	*integer*	VRRP version.
virtualIp	*IPv4 address*	Configured primary virtual Ipv4 address.
virtualIpSecondary	*list of IPv4 address*	Configured secondary virtual Ipv4 addresses.
virtualMac	*MAC address*	The virtual mac address of this vrrp group.
vrIdDisabled **	*boolean*	Virtual router id is disabled. **Since: 4.15.2
vrIdDisabledReason **	*string*	Virtual router id disabled description. **Since: 4.15.2

[vrfName]	*string*	Name of VRF.
vrrpAdvertInterval	*integer*	The time in seconds between sending Vrrp packets.

2.2129.3 VrrpRouterDetailV6

bfdPeerAddr **	*IPv6 address*	Bfd peer of the virtual router. **Since: 4.21.3
[bfdPeerState] **	*enum: shuttingDown | down | up*	Bfd peer state of the virtual router. **Since: 4.25.2
description	*string*	Vrrp description.
groupId	*integer*	VRRP group ID.
interface	*interface name*	Name of the interface.
linkLocalAddr **	*IPv6 address*	Derived link-local Ipv6 from the VRRP mac or the configured link-local Ipv6 address. **Since: 4.18.0
macAddressInterval	*integer*	The time in seconds between sending neighbor discovery or arp of the virtual mac address.
masterAddr	*IPv6 address*	Current address of the master virtual router.
masterDownInterval	*integer*	The master down interval of the virtual router in milliseconds.
masterInterval	*integer*	The master advertisement interval in seconds.
masterPriority	*integer*	Priority of the master virtual router.
preempt	*boolean*	Preemption status.
preemptDelay	*integer*	Preemption delay time in seconds.
preemptReload	*integer*	Preemption reload delay time in seconds.
priority	*integer*	Priority of the virtual router.
skewTime	*floating point number*	The skew of the master down interval in seconds.
state	*enum: backup | stopped | master*	stopped – the virtual router has been shutdown, backup – the virtual router is in backup mode, master – the virtual router is the master of the VRRP group.
stateTransitionTime **	*floating point number*	Timestamp in UTC of last VRRP state transition. **Since: 4.22.0
trackedObjects **	*list of TrackedObject* see 2.2129.1.1	Vrrp tracked objects. **Since: 4.21.3
version	*integer*	VRRP version.
virtualIpv6	*list of IPv6 address*	Configured secondary virtual Ipv6.
virtualMac	*MAC address*	The virtual mac address of this vrrp group.
vrIdDisabled **	*boolean*	Virtual router id is disabled. **Since: 4.15.2
vrIdDisabledReason **	*string*	Virtual router id disabled description. **Since: 4.15.2
[vrfName]	*string*	Name of VRF.
vrrpAdvertInterval	*integer*	The time in seconds between sending Vrrp packets.

2.2130 show vrrp brief [...]

virtualRouters	*list of VrrpRouterBriefBase* see 2.2130.1	Virtual router status.

2.2130.1 VrrpRouterBriefBase

Could also be an instance of:
VrrpRouterBriefV4 2.2130.2
VrrpRouterBriefV6 2.2130.3

groupId	*integer*	VRRP group ID.
interface	*interface name*	Name of the interface.
masterDownInterval	*integer*	The master down interval of the virtual router in milliseconds.
priority	*integer*	Priority of the virtual router.
state	*enum: backup | stopped | master*	stopped – the virtual router has been shutdown, backup – the virtual router is in backup mode, master – the virtual router is the master of the VRRP group.
stateTransitionTime **	*floating point number*	Timestamp in UTC of last VRRP state transition. **Since: 4.22.0
version	*integer*	VRRP version.
[vrfName]	*string*	Name of VRF.

2.2130.2 VrrpRouterBriefV4

groupId	*integer*	VRRP group ID.
interface	*interface name*	Name of the interface.
masterDownInterval	*integer*	The master down interval of the virtual router in milliseconds.
priority	*integer*	Priority of the virtual router.
state	*enum: backup | stopped | master*	stopped – the virtual router has been shutdown, backup – the virtual router is in backup mode, master – the virtual router is the master of the VRRP group.
stateTransitionTime **	*floating point number*	Timestamp in UTC of last VRRP state transition. **Since: 4.22.0
version	*integer*	VRRP version.
virtualIp	*IPv4 address*	The primary virtual Ipv4 address.
[vrfName]	*string*	Name of VRF.

2.2130.3 VrrpRouterBriefV6

groupId	*integer*	VRRP group ID.
interface	*interface name*	Name of the interface.
masterDownInterval	*integer*	The master down interval of the virtual router in milliseconds.
priority	*integer*	Priority of the virtual router.

state	*enum: backup | stopped | master*	stopped – the virtual router has been shutdown, backup – the virtual router is in backup mode, master – the virtual router is the master of the VRRP group.
stateTransitionTime **	*floating point number*	Timestamp in UTC of last VRRP state transition. **Since: 4.22.0
version	*integer*	VRRP version.
virtualIps	*list of IPv6 address*	Virtual Ipv6 addresses.
[vrfName]	*string*	Name of VRF.

2.2131 show vxlan address-table [...]

revision 2

addresses	*list of VxlanMacAddrListing* see 2.2131.1	List of VXLAN MAC addresses.

2.2131.1 VxlanMacAddrListing

addrType	*enum: dynamic | unknown | evpn | received | static*	Type of the MAC address.
interface	*string*	VXLAN interface for this address.
lastMove	*floating point number*	Time of the last move for this address. A value of 0 indicates the host has not moved.
[lastMoveTimestamp] **	*floating point number*	Absolute UTC Linux timestamp of last move. **Since: 4.33.2
macAddress	*MAC address*	MAC Address.
moves	*integer*	Number of times this address has moved.
vlanId	*integer*	VLAN Id of MAC address.
vteps	*list of IP address*	List of VTEPs corresponding to this address.

2.2132 show vxlan address-table count [...]

vtepCounts	*table(IPv4 or IPv6 address) = integer*	Count of MAC addresses per VTEP.

2.2133 show vxlan config-sanity [...]

categories	*table(string) = ConfigCheckCategory* see 2.2133.1	Map of category names to check categories.

2.2133.1 ConfigCheckCategory

allCheckPass	*boolean*	Category check passes when all items belonging to the category pass their checks.
description	*string*	Description of category.

detail **	*string*	Detail about this item. **Since: 4.26.2
hasWarning	*boolean*	Category contains warning.
items	*list of ConfigCheckItem* see 2.2133.1.1	List of items in this category.

2.2133.1.1 ConfigCheckItem

checkPass	*boolean*	Item check passed.
detail	*string*	Detail about this item.
hasWarning	*boolean*	Item contains warning.
name	*string*	Name of item.

2.2134 show vxlan control-plane [...]

vlans	*table(numeric string) = VlanControlPlaneConfigModel* see 2.2134.1	VLANs configured for VXLAN, keyed by VLAN.

2.2134.1 VlanControlPlaneConfigModel

controlPlanes	*table(string) = ControlPlaneConfigSourceModel* see 2.2134.1.1	Control planes active in a VLAN, keyed by control plane name.

2.2134.1.1 ControlPlaneConfigSourceModel

sources	*table(string) = ControlPlaneConfigDirectionModel* see 2.2134.1.1.1	Sources of control plane configuration, keyed by source name.

2.2134.1.1.1 ControlPlaneConfigDirectionModel

direction	*enum: export | import | both*	Direction of data sharing for a control plane.

2.2135 show vxlan controller address-table advertised [...]

revision 2

tableType	*string*	Advertised or Received.
vniStatus	*list of VxlanVniStatus* see 2.1882.1	Vxlan tables.

2.2136 show vxlan controller address-table received [...]

revision 2

see 2.2135

2.2137 show vxlan controller arp advertised [...]

protocol **	*enum: arp | nd*	Type of address protocol. **Since: 4.29.2
tableType	*enum: advertised | received*	Type of ARP or ND entries contained in this table.
vlanToArpTable	*table(numeric string) = VxlanArpTable* see 2.1884.1	A mapping from VLAN ID to ARP or ND table.

2.2138 show vxlan controller arp received [...]

see 2.2137

2.2139 show vxlan controller nd advertised [...]

see 2.2137

2.2140 show vxlan controller nd received [...]

see 2.2137

2.2141 show vxlan controller status

[purgeInProgress]	*boolean*	True if purging of HW MAC table entries received from CVX is in progress after CVX restart.
[resyncInProgress]	*boolean*	True if resync with CVX is in progress after CVX restart.
status	*enum: negotiating | disconnecting | established | connecting*	Connection status of Vxlan Control Service with CVX.

2.2142 show vxlan counters learn-restrict COUNTER [...]

counters	*enum: all | prefix | brief*	Select set of per-vlan counters.
learnCountersMap	*table(numeric string) = VxlanPrefixStatusModel* see 2.2142.1	Per VLAN learn list.

2.2142.1 VxlanPrefixStatusModel

learnFrom	*enum: learnFromDefault | learnFromList | learnFromFloodList | learnFromAny*	VTEP prefixes from which we learn.
numMatchAny	*integer*	Number of VTEPs that matched with learnFromAny.
numMatchFloodList	*integer*	Number of VTEPs that matched learnFromFloodList.
numMatchList	*integer*	Number of VTEPs that matched learnFromList.
numRejectFloodList	*integer*	Number of VTEPs dropped due to no match for learnFromFloodList.
numRejectList	*integer*	Number of VTEPs dropped due to no match for learnFromList.
prefixList	*table(IPv4 or IPv6 address prefix) = integer*	Per vlan learn list with number of VTEPs accepted.

2.2143 show vxlan counters software

revision 3

arpPkts	*integer*	Number of ARP packets sent to ARP resolver.
arpReplyL2RefreshNoHer **	*integer*	Number of ARP reply refresh pkts not headend replicated. **Since: 4.27.0
arpReplyRelayNoHer	*integer*	Number of ARP reply packets that were not headend replicated due to ARP relay.
arpReqNoHER	*integer*	Number of ARP request packets that were not headend replicated.
arpRxqRcvd	*integer*	Number of ARP request packets received.
arpRxqRcvdFromVarpMac	*integer*	Number of ARP request packets received from a virtual mac.
arpSendErr	*integer*	Number of send error for ARP packets.
arpSuppressCacheHitMacMiss **	*integer*	Number of ARP cache hits skipped during suppression due to target MAC being not installed. **Since: 4.27.2
arpSuppressSkipDynamicArp	*integer*	Number of dynamic ARP cache hits skipped during suppression due to sender virtual MAC.
arpSuppressSkipLocalIp	*integer*	Number of ARP cache hits skipped during suppression due to target IP address being local.
arpSuppressSkipLocalMac	*integer*	Number of ARP cache hits skipped during suppression due to target being local mac.
arpSuppressSkipMplsMac **	*integer*	Number of ARP cache hits skipped during suppression due to target being behind MPLS tunnel. **Since: 4.27.2
arpSuppressSkipProbe	*integer*	Number of ARP probes skipped ARP suppression.
arpSuppressSkipUnknownMac	*integer*	Number of ARP cache hits skipped during suppression due to sender address being unknown unicast.
arpSupressCache1Miss	*integer*	Number of Arp initial cache misses during Arp suppression.
arpSupressCacheMiss	*integer*	Number of Arp cache misses during Arp suppression.
arpSupressDeny	*integer*	Number of Arp supression packets denied due to ACL.
arpSupressTx	*integer*	Number of ARP cache hits during Arp suppression.
arpSupressTxBcast	*integer*	Number of ARP reply sent to bcast mac during Arp suppression.
arpSupressTxErr	*integer*	Number of ARP reply errors during Arp suppression.
dynamicMacEventSent **	*integer*	Number of dynamic MAC learned events sent to platform. **Since: 4.27.0

encapBytes	*integer*	Number of bytes sent to known remote vteps.
encapDiscardLocalMac	*integer*	Number of packets discarded due to destination being local.
encapDiscardMlagPeerLink	*integer*	Number of discard packets coming in on a MLAG peer link for encapsulation.
encapDiscardRunt	*integer*	Number of discard packets failing size check for encapsulation.
encapDiscardVlanMap	*integer*	Number of discard packets missing VLAN-2-VNI mapping for encapsulation.
encapDiscardVlanRange	*integer*	Number of discard packets failing VLAN range check for encapsulation.
encapDot1qTunnel	*integer*	Number of packets dot1Q received for encapsulation.
encapHwFwd	*integer*	Number of software packets forwarded to remote VTEPs via HW HER.
encapHwFwdErr	*integer*	Number of software packets failed in forwarding to remote VTEPs via HW HER.
encapNoRemoteVtep	*integer*	Number of discard packets destinated to empty flood list for encapsulation.
encapNoRemoteVtepBfd	*integer*	Number of discard packets destinated to empty BFD flood list for encapsulation.
encapPkts	*integer*	Number of packets sent to known remote vteps.
encapReadErr	*integer*	Number of read error packets received for encapsulation.
encapSchedHwHER **	*integer*	Number of software packets forwarded to remote VTEPs via scheduled hardware HER. **Since: 4.35.2
encapSchedHwHERErr **	*integer*	Number of software packets failed in forwarding to remote VTEPs via scheduled hardware HER. **Since: 4.35.2
encapSchedSwHER **	*integer*	Number of software packets forwarded to remote VTEPs via scheduled software HER. **Since: 4.32.2
encapSendDiscardHigh	*integer*	Number of high priority send error packets for encapsulation.
encapSendDiscardLow	*integer*	Number of low priority send error packets for encapsulation.
encapSendErr	*integer*	Number of send error packets for encapsulation.
encapSockDrop	*integer*	Number of pkts dropped by DMA driver socket.
encapTimeout	*integer*	Number of times the sender activity loop yield.
encapTxAnyRemoteVtep	*integer*	Number of BUM packets sent to first vtep on flood list.
encapTxTotalBytes	*integer*	Number of bytes sent after encapsulation.
encapTxTotalIpv6Bytes	*integer*	Total number of bytes encapped with IPv6 underlay.

encapTxTotalIpv6Pkts	*integer*	Total number of packets encapped with IPv6 underlay.
encapTxTotalPkts	*integer*	Number of packets sent after encapsulation.
encapVarpHwHER **	*integer*	Number of software packets forwarded from VARP MAC to remote VTEPs via HW HER. **Since: 4.35.2
encapVarpHwHERErr **	*integer*	Number of software packets from VARP MAC failed in forwarding to remote VTEPs via HW HER. **Since: 4.35.2
encapVarpSwHER **	*integer*	Number of software packets from VARP MAC for HER. **Since: 4.32.2
floodingSuppressCount	*integer*	Number of packets suppressed from getting flooded into Vxlan fabric.
garpPeerSyncMsgCount	*integer*	Number of GRAT ARP sync messages received.
garpPeerSyncMsgErrCount	*integer*	Number of GRAT ARP sync messages received in error.
garpPeerSyncMsgTxCount	*integer*	Number of GRAT ARP sync messges sent.
garpTgtSviSuppress	*integer*	Number of GRAT ARP pkts from SVI suppressed.
installedArpL2Count	*integer*	Number of bridged ARP entries installed.
installedArpL2EntryAgedOut	*integer*	Number of bridged ARP entries removed due to host mac aging.
installedArpL2Immediate-RefreshFail **	*integer*	Number of bridged ARP entries removed after immediate refresh timed out. **Since: 4.33.2
installedArpL2Immediate-RefreshPktsSent **	*integer*	Number of bridged ARP immediate refresh requests sent. **Since: 4.33.2
installedArpL2Immediate-RefreshPktsSentErr **	*integer*	Number of bridged ARP immediate refresh requests that failed to send. **Since: 4.33.2
installedArpL2RefreshSent	*integer*	Number of bridged ARP entry refresh pkts sent.
installedArpL2RefreshSent-Err	*integer*	Number of bridged ARP entry refresh failures.
installedArpL2ToL3Count	*integer*	Number of bridged ARP entries migrated from L2 to L3.
installedArpL2ToL3ErrCount	*integer*	Number of bridged ARP entries migrated from L2 to L3 in error.
installedGarpCount	*integer*	Number of GRAT ARP bindings added to ARP.
installedGarpErrCount	*integer*	Number of GRAT ARP bindings added to ARP in error.
installedNaCount	*integer*	Number of dynamic neighbor entries added to neighbor cache.
installedNaErrCount	*integer*	Number of dynamic neighbor entries added to neighbor cache with error.

installedNdL2Immediate-RefreshFail **	*integer*	Number of bridged ND entries removed after immediate refresh timed out. **Since: 4.33.2
installedNdL2Immediate-RefreshPktsSent **	*integer*	Number of bridged ND immediate refresh requests sent. **Since: 4.33.2
installedNdL2Immediate-RefreshPktsSentErr **	*integer*	Number of bridged ND immediate refresh requests that failed to send. **Since: 4.33.2
ipToMacMlagRecd	*integer*	Number of Ip to MAC bindings received from primary Mlag peer.
ipToMacMlagSent	*integer*	Number of Ip to MAC bindings sent to secondary Mlag peer.
naRx	*integer*	Number of Neighbor Advertisement pkts received.
naSuppressSkipInvalidOptPkt	*integer*	Number of Neighbor Advertisements found with invalid or absent options hdr.
naSuppressSkipInvalidPkt	*integer*	Number of Neighbor Advertisements found as invalid.
naSuppressTx	*integer*	Number of Neighbor Advertisement pkts suppressed.
naTgtSvi	*integer*	Number of Neighbor Advertisements not suppressed as target is SVI.
naTgtSviSuppress	*integer*	Number of Neighbor Advertisements suppressed as target is SVI.
noHERCount **	*integer*	Number of frames with no HER requested by dma-driver. **Since: 4.29.2
noIpv4LocalVtepAddr	*integer*	Number of times IPv4 local Vtep address not found while encapsulating the packets.
noIpv4RemoteVtepAddr	*integer*	Number of times IPv4 remote Vtep address not found while encapsulating the packets.
noIpv6LocalVtepAddr	*integer*	Number of times IPv6 local Vtep address not found while encapsulating the packets.
noIpv6RemoteVtepAddr	*integer*	Number of times IPv6 remote Vtep address not found while encapsulating the packets.
nsNASent	*integer*	Number of Neighbor Advertisement proxy pkts sent.
nsReqNoHER	*integer*	ND NS pkts skipped HER since target Ip matched SVI Ip.
nsRx	*integer*	Number of Neighbor Solicitation pkts received.
nsSuppressCache1Miss	*integer*	Number of Neighbor initial cache misses during ND NS proxy.
nsSuppressCacheMiss	*integer*	Number of Neighbor cache misses during ND NS proxy.
nsSuppressDad	*integer*	Number of Neighbor Solicitation DAD pkts suppressed.
nsSuppressDadVarpIp	*integer*	Number of Neighbor Solicitation DAD pkts from kernel to virtual IP suppressed.
nsSuppressDeny	*integer*	Number of ND NS proxy packets denied due to ACL.

nsSuppressNonUnicastSource	*integer*	Number of Neighbor Solicitation pkts from unspecified source.
nsSuppressSkipDynamicArp	*integer*	Number of dynamic Neighbor hits skipped during ND proxy due to source link address being router MAC.
nsSuppressSkipInvalidPkt	*integer*	Number of Neighbor Solicitation pkts found invalid.
nsSuppressSkipLocalIp	*integer*	Number of Neighbor hits skipped during ND NS proxy due to target address being local.
nsSuppressSkipLocalMac	*integer*	Number of Neighbor hits skipped during ND NS proxy due to target link layer being local.
nsSuppressSkipUnknownMac	*integer*	Number of Neighbor hits skipped during ND NS proxy due to sender MAC address being unknown unicast.
nsSuppressTx	*integer*	Number of Neighbor Solicitations suppressed.
nsSuppressTxErr	*integer*	Number of Neighbor Advertisement errors during ND NS proxy.
nsSuppressVirtualLinkLocal	*integer*	Number of Neighbor Solicitation pkts for virtual Link Local IP suppressed.
proxyDisabledBcastArpRx **	*integer*	Total number of broadcast ARPs received from local MAC when ARP proxy is disabled. **Since: 4.27.1
proxyDisabledBcastArp-SenderNotLearnedRx **	*integer*	Total number of broadcast ARPs received from unlearned MAC when ARP proxy is disabled. **Since: 4.27.1
proxyDisabledBcastArp-SenderRemoteRx **	*integer*	Total number of broadcast ARPs received from remote MAC when ARP proxy is disabled. **Since: 4.27.1
proxyDisabledBcastArp-SenderVmacRx **	*integer*	Total number of broadcast ARPs received from virtual MAC when ARP proxy is disabled. **Since: 4.27.1
proxyDisabledMcastNdRx **	*integer*	Total number of multicast NS or NA received from local MAC when ND proxy is disabled. **Since: 4.27.1
proxyDisabledMcastNdSender-NotLearnedRx **	*integer*	Total number of multicast NS/NA received from unlearned MAC when ND proxy is disabled. **Since: 4.27.1
proxyDisabledMcastNdSender-RemoteRx **	*integer*	Total number of multicast NS/NA received from remote MAC when ND proxy is disabled. **Since: 4.27.1

proxyDisabledMcastNdSender-VmacRx **	*integer*	Total number of multicast NS/NA received from virtual MAC when ND proxy is disabled. **Since: 4.27.1
rarpRxCount **	*integer*	Number of RARP pkts. **Since: 4.29.2
rarpRxInvalidCount **	*integer*	Number of RARP pkts that were invalid. **Since: 4.29.2
rsSuppressTx	*integer*	Number of Router Solicitation pkts suppressed.
rxForEncapBytes	*integer*	Number of bytes received for encapsulation.
rxForEncapBytesSockHiPrio	*integer*	Number of bytes received from high priority input queue for encapsulation.
rxForEncapBytesSockLoPrio	*integer*	Number of bytes received from low priority input queue for encapsulation.
rxForEncapPkts	*integer*	Number packets received for encapsulation.
rxForEncapPktsSockHiPrio	*integer*	Number of packets received from high priority input queue for encapsulation.
rxForEncapPktsSockLoPrio	*integer*	Number of packets received from low priority input queue for encapsulation.
vtepToVtepSourcePruned-Frames **	*integer*	Total number of bridged vtep-to-vtep pkts that were source pruned. **Since: 4.27.1

2.2144 show vxlan counters varp

revision 3

arpCacheEvpnConflictForce-Local **	*integer*	Number of solicited ARP replies triggering remote-to-local host move. **Since: 4.36.0
arpCacheInstallConflict	*integer*	Number of ARP cache installation conflicts.
arpCacheInstallErr	*integer*	Number of ARP cache installation failure.
arpCacheInstalled	*integer*	Number of ARP packets installed in ARP cache.
arpCacheSyncedInstall-Conflict	*integer*	Number of ARP packets sync install conflicts.
arpCacheSyncedInstallErr	*integer*	Number of ARP packets sync install failures.
arpCacheSyncedRx	*integer*	Number of ARP cache received from MLAG peer.
arpCacheSyncedTx	*integer*	Number of ARP cache sent to MLAG peer.
arpDynamicRemoteArpNotify-SyncedRx **	*integer*	Number of remote ARPs which have been received from MLAG peer. **Since: 4.27.0
arpDynamicRemoteArpNotify-SyncedTx **	*integer*	Number of Remote ARPs which have synced to MLAG peer. **Since: 4.27.0
arpLocalAddressTx	*integer*	Number of ARP request packets rewritten with local IP and bridged.
arpProbeDropForVarpIP **	*integer*	Number of inner ARP probes for VARP IP dropped. **Since: 4.28.0
arpPublishGarpInstall-Conflict **	*integer*	Number of ARP entries failed to install from Gratuitous ARPs due to conflict when ARP publish is enabled. **Since: 4.28.0
arpPublishGarpInstallErr **	*integer*	Number of ARP entries failed to install from Gratuitous ARPs when ARP publish is enabled. **Since: 4.28.0
arpPublishGarpInstalled **	*integer*	Number of ARP entries installed from Gratuitous ARPs when ARP publish is enabled. **Since: 4.28.0
arpPublishGarpRx **	*integer*	Number of Gratuitous ARPs received from a local MAC when ARP publish is enabled. **Since: 4.28.0
arpPublishGarpSenderRemote-Rx **	*integer*	Number of Gratuitous ARPs received from a remote MAC when ARP publish is enabled. **Since: 4.28.0
arpReplyBumListErr	*integer*	Number of received ARP reply packets failed to BUM processing error.

arpReplyHerHwFwd **	*integer*	Number of ARP or IPv6 NA reply pkts sent via H/WHER. **Since: 4.30.1
arpReplyHerHwFwdErr **	*integer*	Number of ARP or IPv6 NA reply pkts sent via H/W HER in error. **Since: 4.30.1
arpReplyHerToVespaGwTx **	*integer*	Number of VXLAN ARP reply packets headend replicated to VESPA GWs. **Since: 4.35.0
arpReplyHerTx	*integer*	Number of ARP reply packets received for HER encapsulation.
arpReplyMsgToArpMonErr	*integer*	Number of received ARP reply packets failed to ARP monitor processing error.
arpReplyPktSyncedRx	*integer*	Number of ARP reply packets synced over reception.
arpReplyPktSyncedTx	*integer*	Number of ARP reply packets synced over transmission.
arpReplyRcvd	*integer*	Number of ARP reply packets received.
arpReplyRelayTx	*integer*	Number of ARP reply relay packets sent.
arpReplyRewriteDiscard	*integer*	Number of ARP reply packets discard due to missing rewrite pending list match.
arpReplyRx	*integer*	Number of naked ARP reply packets received.
arpReplySrcIpErr	*integer*	Number of received ARP reply packets failed to source IP error check.
arpReplyToBridgeMac-Replicated	*integer*	Number of ARP reply packets rewritten and replicated.
arpReplyToVarpMacNoHer	*integer*	Number of ARP reply packets were not headend replicated.
arpReplyToVarpMacVarpVtepRx	*integer*	Number of ARP reply packets for VARP mac and VARP vtep.
arpReplyTx	*integer*	Number of ARP reply packets received for known VTEPencapsulation.
arpReplyUnmodSent	*integer*	Number of ARP reply packets sent with original source VARP MAC.
arpReqDecapAndTx	*integer*	Number of VXLAN ARP request decapsulated and sent.
arpReqDecapAndTxErr	*integer*	Number of VXLAN ARP request failure in decapsulated and sent.
arpReqDecapAndTxPortIdErr	*integer*	Number of VXLAN ARP request failure due to unknown CPU port id.
arpRxqRcvd	*integer*	Number of received ARP request packets.
arpRxqRcvdFromVarpMac	*integer*	Number of ARP request packets received from a virtual mac.
dropArpReqForNonSwitchIpTo-VarpVtep	*integer*	Number of ARP request packets for non-switch IP to VARP VTEP IP dropped.
dropArpReqForVarpIpToNon-VarpVtep	*integer*	Number of ARP request packets for virtual IP to local VTEP IP dropped.
dropNdNsReqForNonSwitchIp-ToVarpVtep **	*integer*	Number of IPv6 NS requests for non-switch IP to VARP VTEP IP dropped. **Since: 4.28.0

dropNdNsReqForVarpIpToNon-VarpVtep **	*integer*	Number of IPv6 NS requests for virtual IP to local VTEP IP dropped. **Since: 4.28.0
invalidArpRx	*integer*	Number of received ARP packets failure.
invalidIpChecksumRx	*integer*	Number of received packets failed due to invalid IP checksum.
invalidNaOptRx	*integer*	Number of naked neighbor advertisement packets received with invalid or no option hdr.
invalidNaRx	*integer*	Number of naked neighbor advertisement packets received that were invalid.
invalidNdRx **	*integer*	Number of invalid inner IPv6 NS or NA packets received. **Since: 4.28.0
invalidVxlanHdrRx	*integer*	Number of received packets failed due to invalid VXLAN Header check.
ipv4UnderlayPktsRx	*integer*	VXLAN encapped packets received with IPv4 underlay.
ipv6UnderlayPktsRx	*integer*	VXLAN encapped packets received with IPv6 underlay.
localAAInstalledWithout-ActiveRemote **	*integer*	Number of ActiveLocal hosts installed into ARP cache separately from remote binding. **Since: 4.27.1
naRx	*integer*	Number of naked neighbor advertisement packets received.
naToVarpMacNoHer	*integer*	Number of neighbor advertisement packets that were not headend replicated.
ndDadDropForVarpIP **	*integer*	Number of inner IPv6 DAD for VARP IP dropped. **Since: 4.28.0
ndNaReplyRcvd **	*integer*	Number of inner IPv6 NS replies received. **Since: 4.28.0
ndNaReplyToVarpMacVarpVtep-Rx **	*integer*	Number of IPv6 NA reply packets for VARP mac and VARP vtep received. **Since: 4.28.0
ndNaReplyTx **	*integer*	Number of IPv6 NA reply packets sent for known VTEP encapsulation. **Since: 4.28.0
ndNsDecapAndTx **	*integer*	Number of VXLAN NS decapsulated and sent. **Since: 4.30.0
ndNsDecapAndTxErr **	*integer*	Number of VXLAN NS failure in decapsulated and sent. **Since: 4.30.0
ndNsRxqRcvd **	*integer*	Number of inner IPv6 NS requests received. **Since: 4.28.0
ndNsRxqRcvdFromVarpMac **	*integer*	Number of inner IPv6 NS requests received from a virtual mac. **Since: 4.28.0

neighCacheEvpnConflict-ForceLocal **	*integer*	Number of solicited Neighbor Advertisements triggering remote-to-local host move. **Since: 4.36.0
neighCacheInstallConflict	*integer*	Number of IPv6 neighbor cache installation conflicts.
neighCacheInstallErr	*integer*	Number of IPv6 neighbor cache installation failures.
neighCacheInstalled	*integer*	Number of neighbor entries installed in IPv6 neighbor cache.
neighCacheSyncedInstall-Conflict	*integer*	Number of neighbor entries sync install conflicts.
neighCacheSyncedInstallErr	*integer*	Number of neighbor entries sync install failures.
neighCacheSyncedRx	*integer*	Number of neighbor entries received from MLAG peer.
neighCacheSyncedTx	*integer*	Number of neighbor entries sent to MLAG peer.
neighSyncMsgErrCount	*integer*	Number of neighbor sync messages received in error.
noVlanToVniMapErr	*integer*	Number of received packets failed due to missing VLAN-2-VNI map.
pktTooShortRx	*integer*	Number of received packets failed minimum frame size.
prependDecapForFabric	*integer*	Number of packets decapped and sent on fabric interface from the CPU.
prependDecapForTxFwd	*integer*	Number of packets decapped and sent on txfwd interface from the CPU.
prependDecapForTxRaw	*integer*	Number of packets decapped and sent on txraw interface from the CPU.
scheduledSyncMsgRxErrCount **	*integer*	Number of scheduled sync msg errors. **Since: 4.31.1
scheduledSyncMsgRxGapCount **	*integer*	Number of scheduled sync msg pkts dropped in transit. **Since: 4.31.1
scheduledSyncRxInstall-ConflictCount **	*integer*	Number of scheduled sync binding install conflicts. **Since: 4.31.1
scheduledSyncRxInstallCount **	*integer*	Number of scheduled sync bindings installed. **Since: 4.31.1
scheduledSyncRxInstallErr-Count **	*integer*	Number of scheduled sync binding install errors. **Since: 4.31.1
scheduledSyncRxPktCount **	*integer*	Number of scheduled sync msgs received. **Since: 4.31.1
scheduledSyncTxAsuShutdown-DropCount **	*integer*	Number of scheduled sync msgs dropped from being sent because VxlanSwFwd stage for ASU shutdown is complete. **Since: 4.34.1
scheduledSyncTxCount **	*integer*	Number of scheduled sync bindings sent. **Since: 4.31.1

scheduledSyncTxPktCount **	*integer*	Number of scheduled sync msgs sent. **Since: 4.31.1
sendLocalMacDropCount **	*integer*	Number of VXLAN ARP/ND pkts dropped from being sent to local ports. **Since: 4.34.2
unexpectedArpReplyRx	*integer*	Number of received ARP reply packets failure.
unexpectedEtherTypeRx	*integer*	Number of received packets failed due to unexpected ethertype.
unexpectedInnerNotArpRx	*integer*	Number of received packets failed due to inner ARP or IPv6 ND frames missing.
unexpectedIpProtoRx	*integer*	Number of received packets failed due to unexpected IP protocol value.
unexpectedNonIpRx	*integer*	Number of received packets failed due to non IP packet.
unexpectedUdpPortRx	*integer*	Number of received packets failed due to unexpected UDP destination port number.
unexpectedVlanIdRx **	*integer*	Number of received packets failed due to unexpected VLAN range. **Since: 4.27.0
vxlanArpReplyToMHLocalHost-Tx **	*integer*	Number of VXLAN ARP reply pkts sent to multhomed local host. **Since: 4.35.2
vxlanArpReplyToMHLocalHost-TxErr **	*integer*	Number of VXLAN ARP reply pkts sent to multhomed local host in error. **Since: 4.35.2
vxlanArpSockDropCount **	*integer*	Number of VXLAN ARP/ND pkts dropped in socket. **Since: 4.32.2
vxlanEncapArpRx	*integer*	Number of VXLAN ARP packets received.
vxlanEncapNdRx **	*integer*	Number of inner IPv6 NS or NA packets received. **Since: 4.28.0
vxlanEvpnPeerFilterDecapped **	*integer*	Number of VXLAN ARP packets filtered from multihoming peer and decapped. **Since: 4.27.1
vxlanSecArpReplyTx **	*integer*	Number of VxlanSec ARP replies sent. **Since: 4.27.1
vxlanSecArpReplyTxErr **	*integer*	Number of VxlanSec ARP replies sent in error. **Since: 4.27.1
vxlanSecArpReqForVarpIpDrop **	*integer*	Number of VxlanSec ARP requests to VARP IP dropped. **Since: 4.27.1
vxlanSecEncapArpRx **	*integer*	Number of VxlanSec ARP packets received. **Since: 4.27.1
vxlanSecEncapNdRx **	*integer*	Number of VxlanSec inner IPv6 NS or NA packets received. **Since: 4.28.0

vxlanSecNdNsForVarpIpDrop **	*integer*	Number of VxlanSec inner IPv6 NS requests to VARP IP dropped. **Since: 4.28.0
vxlanSecNdReplyTx **	*integer*	Number of VxlanSec inner IPv6 NA reply sent. **Since: 4.28.0
vxlanSecNdReplyTxErr **	*integer*	Number of VxlanSec inner IPv6 NA reply sent in error. **Since: 4.28.0

2.2145 show vxlan counters vni [...]

vniInDottedNotation	*boolean*	True if VNI string is in dotted notation.
vnis	*table(string) = VxlanVniCounters* see 2.2145.1	Mapping between VNI and its counters.

2.2145.1 VxlanVniCounters

[decapBUMPkts]	*integer*	Layer2 BUM (Broadcast, Unknown, and Multicast) packets decapped for a VNI.
[decapBytes]	*integer*	Bytes decapped for a VNI.
[decapDropExcptPkts]	*integer*	Dropped and Exception packets decapped for a VNI.
[decapKnownUcastPkts]	*integer*	Layer2 Known Unicast packets decapped for a VNI.
[decapPkts] **	*integer*	Packets decapped for a VNI. **Since: 4.33.0
[encapBUMPkts]	*integer*	Layer2 BUM (Broadcast, Unknown, and Multicast) packets for a VNI before replication for encap.
[encapBytes]	*integer*	Bytes encapped for a VNI.
[encapDropPkts]	*integer*	Dropped and Exception packets encapped for a VNI.
[encapPkts]	*integer*	Packets encapped for a VNI.

2.2146 show vxlan counters vtep [...]

[unlearntVteps]	*VxlanVtepCounters* see 2.2146.1	Decap Counters for unlearnt VTEPs.
vteps	*table(IPv4 or IPv6 address) = VxlanVtepCounters* see 2.2146.1	Mapping between IP address and VTEP counters.

2.2146.1 VxlanVtepCounters

[decapBUMPkts]	*integer*	Layer2 BUM (Broadcast, Unknown, and Multicast) packets decapped from VTEP.
[decapBytes]	*integer*	Bytes decapped from VTEP.
[decapDropExcptPkts]	*integer*	Dropped and Exception packets decapped from VTEP.

[decapKnownUcastPkts]	*integer*	Layer2 Known Unicast packets decapped from VTEP.
[decapPkts] **	*integer*	Packets decapped from VTEP. **Since: 4.22.1
[encapBumPkts] **	*integer*	BUM Packets encapped to VTEP. **Since: 4.22.1
[encapBytes]	*integer*	Bytes encapped to VTEP.
[encapDropExcptPkts]	*integer*	Dropped and Exception packets encapped to VTEP.
[encapPkts]	*integer*	Packets encapped to VTEP.

2.2147 show vxlan counters vtep vni [...]

vteps	*table(IPv4 or IPv6 address) = PerVtepVniCounters* see 2.2147.1	Mapping between remote VTEP IP address and VNI.

2.2147.1 PerVtepVniCounters

vnis	*table(string) = VniRemoteVtepCounters* see 2.2147.1.1	Mapping between VNI and its counters per VTEP.

2.2147.1.1 VniRemoteVtepCounters

encapPkts	*integer*	Packets encapped to VTEP-VNI pair.

2.2148 show vxlan flood traffic

[arpFlooding]	*boolean*	True if flooding of ARP traffic is enabled.
[defaultFlooding]	*boolean*	True if default flooding of all traffic is enabled.
[ndFlooding]	*boolean*	True if flooding of ND traffic is enabled.
[unknownMacFlooding]	*boolean*	True if flooding of unknown MAC traffic is enabled.

2.2149 show vxlan flood vtep [...]

floodMap	*table(string) = VxlanVtepListModel* see 2.2149.1	Per VLAN flood list.

2.2149.1 VxlanVtepListModel

vteps	*list of IP address*	VTEP IP address.

2.2150 show vxlan learn-restrict vtep [...]

learnMap	*table(numeric string) = VxlanPrefixListModel* see 2.2150.1	Per vlan learn list.

2.2150.1 VxlanPrefixListModel

learnFrom	*enum: learnFromDefault | learnFromList | learnFromFloodList | learnFromAny*	VTEP prefixes from which we learn.
prefixList	*list of IP address prefix*	VTEP IP address (prefix).

2.2151 show vxlan policers vni [...]

vxlanConfig	*table(string) = VxlanConfigModel* see 2.2151.1	A mapping of VXLAN interface to its configuration.

2.2151.1 VxlanConfigModel

vniQosInfo	*table(numeric string) = VxlanVniQosInfoModel* see 2.2151.1.1	A mapping of VNI to its policer information.

2.2151.1.1 VxlanVniQosInfoModel

[extVlan]	*integer*	VLAN-VNI-VRF mapping.
[iPolicerInfo] **	*VxlanVniPolicer* see 2.2151.1.1.1	Ingress policer information. **Since: 4.29.0
[oPolicerInfo] **	*VxlanVniPolicer* see 2.2151.1.1.1	Egress policer information. **Since: 4.29.0

2.2151.1.1.1 VxlanVniPolicer

mode	*VxlanVniPolicerModeEnum* see 2.2151.1.1.1.2	Policer mode configuration.
name	*string*	Policer name.
status	*VxlanVniPolicerHwStateEnum* see 2.2151.1.1.1.1	Policer hardware programming status.

2.2151.1.1.1.1 VxlanVniPolicerHwStateEnum

hwState	*enum: inactive | active*	Policer hardware state.

2.2151.1.1.1.2 VxlanVniPolicerModeEnum

value	*enum: profile | group*	Policer mode.

2.2152 show vxlan policers vni counters [...]

egrInterfaces	*table(Interface name) = VxlanVniPolicersAllCountersInfoModel* see 2.2152.1	Per VXLAN interface collection for egress policers.
ingInterfaces	*table(Interface name) = VxlanVniPolicersAllCountersInfoModel* see 2.2152.1	Per VXLAN interface collection for ingress policers.

2.2152.1 VxlanVniPolicersAllCountersInfoModel

vniPolicers	*table(numeric string) = VxlanVniPolicersCountersInfoModel* see 2.2152.1.1	Per VNI policer collection.

2.2152.1.1 VxlanVniPolicersCountersInfoModel

counters	*VniPolicingCounters* see 2.2152.1.1.1	VNI Policer Counters.
mode	*VxlanVniPolicerModeEnum* see 2.2151.1.1.1.2	Policer mode configuration.
[policerName]	*string*	Policer name.

2.2152.1.1.1 VniPolicingCounters

conformedBytes	*integer*	Conformed number of bytes to policer.
conformedPackets	*integer*	Conformed number of packets to policer.
exceededBytes	*integer*	Exceeded number of bytes to policer.
exceededPackets	*integer*	Exceeded number of packets to policer.

2.2153 show vxlan qos

revision 2

[decapDscpEcnPropagationDisabled]	*boolean*	VXLAN DSCP and ECN propagation is disabled for VXLAN decapsulated packets.
[dscpEcnRewriteBridgedEnabled] **	*boolean*	VXLAN DSCP and ECN rewrite is enabled for VXLAN bridged packets. **Since: 4.30.1
[ecnPropagation]	*boolean*	VXLAN ECN propagation is enabled.
outerDscpFromInnerDscp	*boolean*	Outer DSCP is derived from Inner DSCP.
routingDscpRewriteSupported	*boolean*	DSCP rewrite is supported on VXLAN routed packets.
trafficClassFromOuterDscp	*boolean*	Traffic Class is derived from Outer DSCP.

2.2154 show vxlan security profile

vteps	*table(IPv4 or IPv6 address) = string*	A mapping of VXLAN VTEP to its security profile.

2.2155 show vxlan vni [...]

vxlanIntfs	*table(Interface name) = VxlanVniVlanCollection* see 2.2155.1	A mapping of VXLAN interface to VNI collection.

2.2155.1 VxlanVniVlanCollection

vniBindings	*table(numeric string) = VxlanVniVlanMappingModel* see 2.2155.1.1	VNI to VLAN mapping.
vniBindingsToVrf **	*table(numeric string) = VxlanVniVrfMappingModel* see 2.2155.1.2	VNI to VRF mapping. **Since: 4.24.2

2.2155.1.1 VxlanVniVlanMappingModel

[dynamicVlan]	*boolean*	VLAN is dynamically configured.
interfaces	*table(Interface name) = VxlanIntfDot1qModel* see 2.2155.1.1.1	Ports associated with a VNI.
source	*string*	Source of VNI to VLAN mapping, (VCS, DYNVTEP, STATIC).
vlan	*integer*	VLAN ID.

2.2155.1.1.1 VxlanIntfDot1qModel

dot1q	*integer*	Dot1q tagged VLAN.
[dot1qTunnel] **	*boolean*	Dot1q-tunneled VLAN. **Since: 4.21.3
[error]	*string*	Error with VLAN translation.

2.2155.1.2 VxlanVniVrfMappingModel

source	*string*	Source of VNI to dynamic VLAN mapping.
vlan	*integer*	Dynamic VLAN ID.
[vrfName]	*string*	VRF which is associated with the VNI.

2.2156 show vxlan vni summary

vxlanVniSources	*table(string) = integer*	A mapping of VXLAN source to source count.

2.2157 show vxlan vtep [...]

interfaces	*table(Interface name) = VxlanInterface* see 2.2157.3	Mapping from VXLAN interface to list of VTEP addresses.
vtepTunnelTypes **	*table(IPv4 or IPv6 address) = TunnelTypeList* see 2.2157.2	Mapping of VTEP to list of tunnel types. **Since: 4.25.0
[vteps] **	*table(IPv4 or IPv6 address) = RemoteVtepConfig* see 2.2157.1	A mapping of remote VTEP to details. **Since: 4.24.2

2.2157.1 RemoteVtepConfig

[evpnDomain] **	*enum: remoteDomain | localDomain*	Domain in which VTEP is located. **Since: 4.27.0
learnedVia	*enum: dataPlane | controlPlane*	Source from which remote VTEP was learned.
macAddressLearning	*enum: controlPlane | datapath*	Source for MAC address learning for VTEP.

2.2157.2 TunnelTypeList

tunnelTypes	*list of TunnelType* see 2.2157.2.1	List of tunnel types.

2.2157.2.1 TunnelType

tunnelType	*enum: multicast | ecmp | flood | unicast*	VXLAN tunnel type.

2.2157.3 VxlanInterface

vteps	*list of IP address*	List of VTEPs.

2.2158 show vxlan vtep encapsulation [...]

[remoteVteps]	*table(IPv4 or IPv6 address) = VxlanEncapSourceIp-RewriteModelList* see 2.2158.1	Rewrite information per remote VTEP.

2.2158.1 VxlanEncapSourceIpRewriteModelList

rewriteInfo	*list of VxlanEncapSourceIp-RewriteModel* see 2.2158.1.1	List of Rewrite Info.

2.2158.1.1 VxlanEncapSourceIpRewriteModel

sourceIp	*IP address*	Source VTEP IP address.
vni	*integer*	VNI.

2.2159 show vxlan vtep summary

vxlanInterfaces	*table(Interface name) = integer*	Total VTEPs by interface.

2.2160 show world

[breakable]	*boolean*	Is that world breakable.
countries	*table(string) = Country* see 2.2160.1	Countries of the world.
population	*integer*	Population living in world.

2.2160.1 Country

capital	*string*	Name of country's capital.
[cities]	*table(string) = City* see 2.2160.1.1	Cities of the county.
[elections]	*string*	date of next election.
population	*integer*	Population of this country in millions.

2.2160.1.1 City

mayor	*string*	Name of the city's mayor.
[pools]	*integer*	Number of public pools in city.
population	*integer*	Population of this city in millions.

2.2161 show world bad

see 2.2160

2.2162 show world stream [...]

someInt	*integer*	some help.

2.2163 show zerotouch

mode	*enum: enabled | disabled | active*	ZeroTouch Mode.
[reloadOnCompletion] **	*enum: enabled | disabled*	Reload on completion of ZTP behavior. **Since: 4.35.0

`scriptTimeout`	*integer*	Script timeout in secs.
`[speedCycling]` **	*enum: active* | *paused*	ZTP speed-cycling behavior. **Since: 4.35.0

2.2164 traceroute adaptive-virtual-topology (vrf VRF) (avt AVT) (destination DEST) [...]

avt	*string*	AVT name in which the ping command is being executed.
destVtep	*string*	Destination VTEP IP.
[errorCode] **	*integer*	Error code if any while sending traceroue requests. **Since: 4.32.2
[errorMessage]	*string*	Error in sending traceroute requests.
[summary]	*table(string) = AvtPathTraceModel* see 2.2164.1	Path-wise traceroute summary.
vrf	*string*	VRF name in which the ping command is being executed.

2.2164.1 AvtPathTraceModel

[labelStack]	*list of integer*	LabelStack of the multihop path.
pathTrace	*list of AvtPathTraceInfoModel* see 2.2164.1.1	Traceroute details for a path.
reroutedPath	*boolean*	Flag to convey if there is rerouting along the path.

2.2164.1.1 AvtPathTraceInfoModel

[directPathId]	*integer*	Direct path ID corresponding to the current label.
[dstIp]	*string*	Destination IP of the path.
[egressInterface]	*string*	Egress interface from the source IP.
[errorCode]	*integer*	Error code if any error happens along the path.
[errorMessage]	*string*	Error message, if any error happens along the path.
[ingressInterface]	*string*	Ingress interface at the destination IP.
[labelSeq]	*integer*	label sequence number.
[onewayTime]	*floating point number*	Oneway time taken to traverse the current label.
[reroutedNode]	*boolean*	Flag to convey the node where reroute happens.
[srcIp]	*string*	Source IP of the path.

2.2165 traceroute mpls generic ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK)) [...]

revision 2

`traceroute`	*MplsTracerouteHdr* see 2.2165.1	Traceroute request.

2.2165.1 MplsTracerouteHdr

`dsInfoType`	*enum: dsmap | ddmap*	Downstream information type.
`errInfo`	*list of ErrInfo* see 2.5.1.2	Errors.
`[ldpModel]`	*GenericModel* see 2.5.1.3	MPLS LDP traceroute model.
`protocol`	*enum: raw | ldp | segment-routing | mldp | pwLdp | rsvp | vpn | bgpLu | generic | nexthop-group-tunnel | static | nexthop-group | SrTePolicy | segment-routing-ospf*	Protocol.
`[rsvpModel]` **	*RsvpModel* see 2.5.1.6	MPLS RSVP traceroute model. **Since: 4.30.0
`[srModel]` **	*SrModel* see 2.5.1.8	MPLS SR traceroute model. **Since: 4.28.2
`[statsModel]` **	*list of MplsVia* see 2.2165.1.1	Statistics summary per Via. **Since: 4.30.1
`viaModel`	*list of MplsVia* see 2.2165.1.1	Vias.

2.2165.1.1 MplsVia

`[interface]` **	*string*	Interface name. **Since: 4.30.1
`labelStack`	*list of integer*	LabelStack.
`nextHopIp`	*string*	NextHop IP.
`path`	*list of MplsPath* see 2.2165.1.1.1	Via paths.
`[stats]` **	*MplsTracerouteStatistics-Summary* see 2.2165.1.1.2	MPLS traceroute statistics summary. **Since: 4.30.1

2.2165.1.1.1 MplsPath

`hopPkt`	*list of HopPktInfo* see 2.2165.1.1.1.1	HopPktInfos.
`pathResult`	*enum: Error: Could not probe further... | Successfully explored path.*	Result of path exploration.

2.2165.1.1.1.1 HopPktInfo

dsInfo	*list of DownstreamInfo* see 2.2165.1.1.1.2	Downstream infos.
hopMtu	*integer*	Hop MTU.
[intfAndLabelStackInfo]	*IntfAndLabelStackInfo* see 2.2165.1.1.1.4	Intf and labelStack info.
oneWayDelay **	*integer*	One way delay (us). **Since: 4.29.1
replyHost	*string*	Reply address.
retCode	*enum: premTermination* | *usIntfUnknown* | *reservedRetCode* | *labelMappingMismatch* | *lblSwitchedFecChange* | *seeDdmTlv* | *labelSwitchedAtStackDep* | *noMappingForFec* | *dsMappingMismatch* | *noLabelEntryAtStackDep* | *labelSwitchedNoMplsFwd* | *protocolIntfMismatch* | *malFormEchoRequest* | *repRouterEgress* | *tlvNotUnderstood* | *noRetCode*	Return code.
roundTrip	*integer*	Roundtrip time (ms).
roundTripUs **	*integer*	RoundTrip time (us). **Since: 4.29.1
ttl	*integer*	Time to live.

2.2165.1.1.1.2 DownstreamInfo

addrType	*enum: ipv4Unnumbered* | *ipv4Numbered* | *ipv6Numbered* | *ipv6Unnumbered*	Address type.
dsIntfAddr	*string*	Downstream interface address.
dsIntfIndex	*integer*	Downstream interface index.
dsIpAddr	*string*	Downstream IP address.
dsType	*enum: downstreamDetailedMap* | *downstreamMap*	Downstream information type.
labelStack	*list of string*	Downstream label stack.
[popFecTypeList] **	*FecTypeList* see 2.2165.1.1.1.3	List of FEC types to pop. **Since: 4.30.1
[pushFecTypeList] **	*FecTypeList* see 2.2165.1.1.1.3	List of FEC types to push. **Since: 4.30.1

retCode	*enum: premTermination* | *usIntfUnknown* | *reservedRetCode* | *labelMappingMismatch* | *lblSwitchedFecChange* | *seeDdmTlv* | *labelSwitchedAtStackDep* | *noMappingForFec* | *dsMappingMismatch* | *noLabelEntryAtStackDep* | *labelSwitchedNoMplsFwd* | *protocolIntfMismatch* | *malFormEchoRequest* | *repRouterEgress* | *tlvNotUnderstood* | *noRetCode*	Return code.

2.2165.1.1.1.3 FecTypeList

fecTypeList	*list of string*	FEC TLV type list.

2.2165.1.1.1.4 IntfAndLabelStackInfo

addr	*string*	IP address.
addrType	*enum: ipv4Unnumbered* | *ipv4Numbered* | *ipv6Numbered* | *ipv6Unnumbered*	Address type.
intfAddr	*string*	Interface address.
intfIndex	*integer*	Interface index.
labelStack	*list of string*	Received label stack.

2.2165.1.1.2 MplsTracerouteStatisticsSummary

[mplsStatistics]	*list of MplsTracerouteStatistics* see 2.2165.1.1.2.1	MPLS traceroute statistics details.
packetLoss	*integer*	Percentage of packets lost.
packetsReceived	*integer*	Packets received.
packetsTransmitted	*integer*	Packets transmitted.
replyTime	*integer*	Reply timestamp time.

2.2165.1.1.2.1 MplsTracerouteStatistics

destination	*string*	Reply host address.
packetsReceived	*integer*	Packets received from destination.
roundTripTimeAvgUs	*integer*	Average round trip time in microseconds.
roundTripTimeMaxUs	*integer*	Maximum round trip time in microseconds.

roundTripTimeMinUs	*integer*	Minimum round trip time in microseconds.

2.2166 traceroute mpls ldp ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_M)) [...]

revision 2

see 2.2165

2.2167 traceroute mpls p2mp mldp ROOTADDR ((lsp-id OPQVAL) | (multicast ipv4 SOURCEADDR GROUPADDR)) [...]

revision 2

see 2.2165

2.2168 traceroute mpls rsvp session ((id SESSION_ID lsp LSP) | (name SESSION_NAME)) [...]

revision 2

see 2.2165

2.2169 traceroute mpls rsvp tunnel TUNNEL_NAME [...]

revision 2

see 2.2165

2.2170 traceroute mpls segment-routing ((((ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK))) | (ipv6 IPV6_ADDRESS) | (isis ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK))) | (isis ipv6 IPV6_ADDRESS)) | (ospf ip (IP_ADDRESS | (IP_ADDRESS_ADDR IP_ADDRESS_MASK)))) [...]

revision 2

see 2.2165

2.2171 who

see 2.2088