

FOXG20 pinout

J6 pinstrip pads

Pin #	IC Pin	Default	Alt	ID 2.6x	ID 3.1x	Note
J6.1		3.3V				Power line 3.3 Volt
J6.2		3.3V				Power line 3.3 Volt
J6.3	PB28	RTS1	GPIO	92	60	/dev/ttyS2 RTS
J6.4	PB7	RXD1	GPIO	71	39	/dev/ttyS2 RXD
J6.5	PB6	TXD1	GPIO	70	38	/dev/ttyS2 TXD
J6.6	PB29	CTS1	GPIO	93	61	/dev/ttyS2 CTS
J6.7	PB26	RTS0	GPIO	90	58	/dev/ttyS1 RTS
J6.8	PB5	RXD0	GPIO	69	37	/dev/ttyS1 RXD
J6.9	PB4	TXD0	GPIO	68	36	/dev/ttyS1 TXD
J6.10	PB27	CTS0	GPIO	91	59	/dev/ttyS1 CTS
J6.11						
J6.12		5V				Power line 5 Volt
J6.13	PB11	RXD3	GPIO	75	43	/dev/ttyS4 RXD
J6.14	PB10	TXD3	GPIO	74	42	/dev/ttyS4 TXD
J6.15	PB13	GPIO		77	45	
J6.16	PB12	GPIO		76	44	
J6.17	PB21	GPIO		85	53	
J6.18	PB20	GPIO		84	52	
J6.19	PB31	GPIO		95	63	
J6.20	PB30	GPIO		94	62	
J6.21	PA31	GPIO		63	31	
J6.22	PA30	GPIO		62	30	
J6.23						
J6.24	PA6	GPIO		38	6	
J6.25	PA7	GPIO		39	7	
J6.26	PA9	GPIO		41	9	
J6.27	PC3	AD3	NPCS3	99	67	Analog input 3 or SPI bus chip select 3
J6.28	PC2	AD2	GPIO	98	66	Analog input 2
J6.29	PC1	AD1	GPIO	97	65	Analog input 1
J6.30	PC0	AD0	GPIO	96	64	Analog input 0
J6.31	PA24	SCL	GPIO	56	24	I2C Clock

Pin #	IC Pin	Default	Alt	ID 2.6x	ID 3.1x	Note
J6.32	PA23	SCD	GPIO	55	23	I2C Data
J6.33	AVDD					Clean 3.3V out for A/D circuitry
J6.34	VREF					A/D voltage reference input
J6.35	AGND					Analog ground
J6.36	PA10	GPIO		42	10	
J6.37	PA22	GPIO		54	22	
J6.38	PA11	GPIO		43	11	
J6.39		GND				Power line GND
J6.40		GND				Power line GND

J7 pinstrip pads

Pin #	IC Pin	Default	Alt	ID 2.6x	ID 3.1x	Note
J7.1		GND				Power line GND
J7.2		GND				Power line GND
J7.3	PB18	GPIO		82	50	
J7.4	PB19	GPIO		83	51	
J7.5	PB16	GPIO		80	48	
J7.6	PB17	GPIO		81	49	
J7.7	PB2	CK	GPIO	66	34	SPI bus clock
J7.8	PB3	NPCS0	GPIO	67	35	SPI CS0
J7.9	PB0	MISO	GPIO	68	36	SPI MISO
J7.10	PB1	MOSI	GPIO	69	37	SPI MOSI
J7.11	PC14	GPIO		110	78	Signal level at 1.8V
J7.12	PC15	GPIO		111	79	Signal level at 1.8V
J7.13	PC12	GPIO		108	76	Signal level at 1.8V
J7.14	PC13	GPIO		109	77	Signal level at 1.8V
J7.15	PC9	GPIO		105	73	Signal level at 1.8V
J7.16	PC10	CTS3	GPIO	106	74	/dev/ttyS4 CTS at 1.8V.
J7.17	PC7	GPIO		103	71	Wired on PC7 red led. Signal level at 1.8V
J7.18	PC8	RTS3	GPIO	104	72	/dev/ttyS4 RTS. Signal level at 1.8V
J7.19	PC5	NPCS1	GPIO	101	69	SPI bus CS1
J7.20	PC6	GPIO		102	70	Reserved. Used to read if the client USB port is wired to a PC
J7.21	PB9	RXD2	GPIO	73	41	/dev/ttyS3 RXD

Pin #	IC Pin	Default	Alt	ID 2.6x	ID 3.1x	Note
J7.22	PB8	TXD2	GPIO	72	40	/dev/ttyS3 TXD
J7.23		BATT				RTC Battery input, Use this terminal to wire an external 3.3 volt RTC backup battery
J7.24		PGD				Wired to power good line on Netus PS1
J7.25		POK				Wired to power ok line on Netus PS1
J7.26		SHDNPS#				PS1 shutdown. Active low
J7.27	NRST					Active low CPU reset input line
J7.28	SHDN#					Wired to the SHDN Netus G20 line
J7.29		5V				5 volt power line
J7.30		WAKEUP				Wired to the WAKEUP Netus G20 line
J7.31	PB23	GPIO		87	55	
J7.32	PB22	GPIO		86	54	
J7.33	PB25	GPIO		89	57	
J7.34	PB24	GPIO		88	56	
J7.35	PA28	GPIO		60	28	
J7.36	PA27	GPIO		59	27	
J7.37	PA26	GPIO		58	26	
J7.38	PA25	GPIO		57	25	
J7.39		3.3V				Power line 3.3 Volt
J7.40		3.3V				Power line 3.3 Volt



(http://creativecommons.org/licenses/by-sa/4.0/deed.en_US)

This work is licensed under a Creative Commons Attribution-ShareAlike 4.0 International License (http://creativecommons.org/licenses/by-sa/4.0/deed.en_US). In case of sharing please indicate the origin: www.acmesystems.it (<http://www.acmesystems.it>).

Terms of use of this documentation



Acme Systems srl

Via Aldo Moro 53 - 00055 Ladispoli (RM) - Italy

Partita IVA / Codice Fiscale **IT 08114831004** - Iscritta al Registro delle Imprese di Roma al n. 08114831004 - REA: RM-1074631

Tel +39.06.99.12.187 - Fax +39.06.622.765.31

Email: info@acmesystems.it - pec: acmesystems@pec.it



(<http://www.microchip.com>)

[Privacy policy \(/privacy-policy\)](/privacy-policy) [Term & conditions \(/terms\)](/terms) [Tracking \(/tracking\)](/tracking) [Contact us \(/contact_us\)](/contact_us) [About us \(/about_us\)](/about_us) [Where we are \(/where_we_are\)](/where_we_are)
[TanzoLab \(http://www.tanzolab.it\)](http://www.tanzolab.it) [Follow us on Twitter \(https://twitter.com/acmesystemssrl\)](https://twitter.com/acmesystemssrl)

