

FR-011 Mission Control GUI — Field-Test Script

Scope: the educator GUI at `/portal/console` (Set up · Operate · Debrief) — the Launch Wizard, the ecosystem Board, the readiness cockpit, the live **Operate cards + room lifecycle**, the per-patient **encounter console** (PTT / handoff / roster), the QR sheet incl. the **patient avatar rig**, the shared station, resume-on-restart, Debrief, and accessibility. Run on the Mac (operator) + a tablet or two. Mark each step PASS/FAIL; paste failures back to Claude Code with the step #.

Updated 2026-06-21 — now covers the field-test polish wave (Operate live cards + pop-outs + room lifecycle, encounter-console PTT/handoff/roster, image picker, card-first launch) and the recent fixes: PTT selected-voice + mic-prompt + interim-transcript (b8620c8), and the patient avatar-rig QR on controls + printout (461111b).

Companion: the classic control room (`/portal/control`) stays the default fallback and is linked top-right on every screen.

Preflight (do first): run `scripts/preflight.sh` — confirms router / IP / cert / QR and reminds you to set **Private Wi-Fi Address OFF** on each tablet. Never burn time on network drift.

0. Setup

Launch the portal. Run this in a terminal — `run_cards.sh` changes into the project folder itself and sets card-first mode, so it works from any directory (`MEDSIM_HOST=0.0.0.0` makes it reachable from tablets):

```
MEDSIM_HOST=0.0.0.0 bash "/Users/petermarotta/Documents/Claude/Projects/Scenario structure to support character engagement/medsim_v8/scripts/run_cards.sh"
```

Or change into the project folder first, then launch:

```
cd "/Users/petermarotta/Documents/Claude/Projects/Scenario structure to support character engagement/medsim_v8"
MEDSIM_HOST=0.0.0.0 bash scripts/run_cards.sh
```

Stop it with **Ctrl+C** in that terminal (or `kill -TERM -f run_portal.py`). (Common slip: running the bare `.venv/bin/python run_portal.py` from a fresh terminal fails with "no such file" — that command only works from inside the project folder; the commands above don't.)

#	Step	Pass
0.1	Run a launch command above -> the portal boots (Uvicorn running on <code>https://0.0.0.0:8765</code>) and Chrome opens to the card UI.	
0.2	If a LAN device can't connect (operator fine but tablets fail / "Send failed" / no image): the LAN IP likely drifted out of the cert. Re-mint the leaf (NEVER the CA) with the BARE command <code>python scripts/dev_cert.py</code> (auto-detects the IP as an IP Address: SAN — do NOT pass the IP as a host arg), then restart the portal so it loads the new cert, and re-scan the tablet QR. Full runbook + verify command: <code>docs/CERTIFICATES-AND-NETWORK-CHANGES.md §2b</code> .	
0.3	Open <code>https://localhost:8765/</code> , log in -> you land on <code>/portal/console?mode=setup</code> (card-first, not the classic home). The top readiness bar paints.	
0.4	The active mode tab is a filled coloured box with white text (not an underline).	

1. Set up — Launch Wizard + Board (target: cold start < 90 s)

#	Step	Pass
1.1	Patients & rooms: one EHR dropdown (session-wide) + Number of beds (default 1). Set beds = 2.	
1.2	Scenario: one picker per bed; pick a scenario each -> the bed's patient is implied. Legacy v1 YAML (if any) shows ". legacy (no patient roster)".	

#	Step	Pass
1.3	Characters: Scenario characters per bed (patient locked; a recurring title across beds shows · V1 / · V2). Shared characters is a separate picker (common doctor, allied-health).	
1.4	Image picker: each character row has an image swatch strip — pick a face -> it is assigned (one image = the flat audio portrait AND the 3D-rig source photo).	
1.5	Devices: per-bed Basic + Advanced pickers; the Group -> Nursing station toggle appears (multi-bed).	
1.6	Review: EHR, beds + patients, shared-cast count, device count; readiness pill shown; Launch blocked only on a red check.	
1.7	Launch -> opens the room dashboard; devices minted (QRs ready). Time from 1.1 -> live: _____ s.	
1.8	Board: Set up -> Board layered cards (Scenario chars · Shared chars · Resources · Rooms/patients) match the Wizard; Launch works from the Board too.	

2. Operate — cockpit, live cards, room lifecycle

#	Step	Pass
2.1	Switch to Operate . The System status appears as a small button/bar (not a wall of tiles).	
2.2	Click System status -> a modal pops (tiles: traffic light + shape glyph + detail). Close via X / Esc / backdrop-click -> back to just the button; it never overlaps the cards below.	
2.3	A cold Speech tile -> tap Warm speech model -> green on the next poll. Test all re-runs every check; the restart-hint shows the command (does NOT restart the portal).	
2.4	Operations cards: one card per bed/patient (join + device + character counts), one per shared character (voice state + QR), the med cart(s) , and the Nursing station .	
2.5	Each card has Open (in place) and Pop out (new window). Pop a card onto a second monitor — it stays fully live off the existing polls.	
2.6	Pop-out targets are correct: patient -> encounter console; shared char -> shared station; med cart -> the device cart UI (/device/<join>/<cart>); nursing -> nursing station; medical records -> records page.	
2.7	Room lifecycle bar: Start · Pause · Resume · Inject scene (modal) · Print QR · End all (debrief) — Start arms a configured room, Pause/Resume gate student input, Inject scene posts a scene to every bed, End all builds the cohort debrief.	

3. Encounter console — patient drill-in (PTT / handoff / roster)

Open a patient's card in Operate (Open or Pop out) -> the encounter console.

#	Step	Pass
3.1	Back reads "<- Back to Mission Control" and returns to /portal/console?mode=operate (NOT the classic room).	
3.2	Every card collapses (caret / click the header) and Pops out to a solo window (one card, page chrome hidden, still live).	
3.3	Characters · voices: pick an ElevenLabs voice per character (Test previews it); Engage opens an in-console chat so you can play that character.	
3.4	PTT mic prompt: click a character chip (or focus the type box / hold the button) -> the browser microphone prompt appears ; Allow it. (If previously blocked: address-bar site icon -> Microphone -> Allow -> reload.)	

#	Step	Pass
3.5	PTT uses the selected voice: hold Hold to talk , say a line, release -> the reply is spoken in the character's assigned voice (e.g. Callum for Mr. Hayes), not the browser default.	
3.6	Quick release still sends: a fast hold-and-release (short utterance) still fires the turn (interim transcript captured) -> reply + TTS. Holding with no speech shows "Didn't catch that...".	
3.7	Type fallback: type a line + Enter -> reply in the selected voice (works where the mic / STT does not, e.g. Safari).	
3.8	Patient avatar-rig QR cell: a Avatar · <patient> · patient (animated rig) cell is present, with a Pair tablet link.	
3.9	Shift handoff card: Start (mode + counterpart) -> engage the counterpart via PTT -> it gives/receives report -> Score shows the SBAR coverage grid (check/cross) + self-vs-measured %.	
3.10	Connected stations card: live per-bed student roster (online / platform / turns); instructor Engage stations are filtered out.	

4. QR sheet + tablets

#	Step	Pass
4.1	Open the QR sheet (/portal/control/qr_print, or the link from a bed).	
4.2	Patient avatar rig: each patient page leads with a Patient avatar (animated rig) QR. Scan it on a bedside tablet -> the animated 3D rig loads (not a flat portrait), bound to that patient.	
4.3	Per-patient: chat / EHR / device stations + that bed's scenario-character avatar/voice QRs + bedside device QRs.	
4.4	Common page: shared characters (avatar vs voice) + common devices (Nursing Station + med cart); the Nursing Station is not repeated on each patient page.	
4.5	Shared char — one tablet, many patients (FR-007 v2): scan the one shared-character QR -> push-to-talk / type about Bed 1 -> AI reply (no echo) in its voice -> on the same tablet ask about Bed 2 -> it answers about the other patient (the doctor knows both).	
4.6	Shared-station PTT: on the shared character page, Hold to talk works (mic prompt -> STT -> AI reply spoken in the assigned voice); the type fallback works too.	

5. Resume on restart (G7)

#	Step	Pass
5.1	With the room live, gracefully restart (pkill -TERM). Boot log shows [resume] restored last session	
5.2	Re-login -> Operate shows the resumed room intact (scenario, beds, devices, shared cast). No echo on the resumed room — the Anthropic key self-heals on the first readiness poll.	
5.3	Launch a fresh scenario -> the resumed state clears (a fresh launch is not a resume).	
5.4	(Negative) corrupt / empty snapshot -> boot is clean, cockpit offers configure in Setup , never crashes.	

6. Debrief

#	Step	Pass
6.1	Switch to Debrief (tab = filled box). The panel links to Open debriefs (/portal/debrief).	

#	Step	Pass
6.2	From Operate's lifecycle bar, End all (debrief) -> confirm -> it builds the cohort debrief and opens it (/portal/debrief/cohort/<room>); connected students are disconnected.	
6.3	The cohort debrief lists each bed's session for review (per-patient debrief reachable).	

7. Fallback + accessibility (G8)

#	Step	Pass
7.1	"Switch to classic control room" (top-right) is present on every mode and lands on /portal/control/setup. The classic sidebar also has Mission Control (cards) back.	
7.2	Keyboard: Tab through the wizard / cockpit / encounter console — every control shows a visible focus ring ; tabs + buttons activate with Enter/Space; the System-status modal traps focus and Esc closes it.	
7.3	Shape-not-colour: readiness states read as glyphs (filled circle = green · triangle = amber · square = red), legible without colour.	
7.4	Touch: on a tablet, tabs / steppers / checkboxes / the PTT button are comfortably tappable (no fat-finger misses).	
7.5	Contrast: text is legible on the dark top bar + light panels in normal room light.	

Notes for paste-back

When a step fails, paste: the **step #**, what you saw vs expected, the browser + whether you **hard-refreshed** (Cmd+Shift+R drops a stale console.js), and any console //tmp/medsim_portal.log error. Claude fixes against the step.