

M46 — Hide ops-controls footer in modal + device QRs inline + on the print sheet

Phase: Phase 7 follow-on (post-M45, operator-feedback fix) **Status:** **DONE** **Blocked by:** M41 (QR print sheet), M42 (modal scaffold), M44 (modal-scope embed CSS), M45 (inline device cards) **Blocks:** none **Estimated effort:** 0.5 day

1. Purpose

Operator feedback after M45:

"On the device pop up page remove the control buttons in the footer of the page like run, pause, stop... etc. Also the QR code for the device created should populate in the encounter page to make it easier to use and be able to print out as part of the QR print out list."

Two distinct asks:

1. **Hide the .ops-controls footer** in the embed-mode modal. M44's CSS hid most of the v6 ops-view chrome, but it missed the `<div class="ops-controls">` footer at the bottom of `control_ops.html` (Pause / Resume / Preview debrief / End scenario / Kill switch buttons) PLUS its explanatory paragraph. The operator saw session-level controls that conflict with the M35 per-encounter Start/Pause/End in the parent console header.
2. **Surface device QRs in two places:** - **Inline** on each M45 device card in the encounter Devices area, so the operator can scan a phone at the cart right from the console. - **Printable** on the M41 QR sheet, so when the operator prints the encounter's QR sheet they get the device QRs to stick on the actual hardware.

2. Structure

Files touched:

- `portal/templates/control_ops.html`:

- Extended the embed-mode `<style>` block with a new rule:

```
``css .ops-controls, .ops-controls + p { display: none !important; } `
```

The `+p` adjacent-sibling selector kills the explanation paragraph below the buttons too. Conditional under `{% if embed_mode %}` so the v6 single-patient ops view (no `?embed=1`) keeps the controls.

- `portal/static/encounter_console.js`:

- `renderDeviceCard(s)` now appends a `.device-card-qr` block

immediately after the card header. The QR `<img>` hits `/api/qr.svg?data=...` with a server-style device-join URL (`${window.location.origin}/device/join?code=${joinCode}&station=${sid}`). Below the QR is the URL in monospace for typed fallback.

- `portal/static/encounter_console.css`:

- New `.device-card-qr` / `.device-card-qr-img` /

`.device-card-qr-url` styles. Compact strip (56px QR + URL), light-blue background to distinguish from the alarm block.

- `portal/server.py` (`portal_control_qr_print`):

The M41 print sheet was already showing 4 station QRs per encounter (Chat / EHR / Device / Nursing). M46 adds a new **■ Devices** (`{{N}}`) section under those four, with one block per bound device. The section only renders when there's at least one device (`{% if enc.devices %}`).

The operator can now print one sheet per encounter and:

- Hand the 4 station QRs to students
- Stick the per-device QRs on the actual hardware (cart, pump)

4. Functions (exported API surface)

Symbol	Where	Purpose
<code>.ops-controls</code> hide rule	<code>portal/templates/control_ops.html</code> <code>{% if embed_mode %} block</code>	Hides the v6 session control footer in modal-embed mode.
<code>renderDeviceCard(s)</code> (extended)	<code>portal/static/encounter_console.js</code>	Now renders a <code>.device-card-qr</code> strip with a server-style device-join URL.
Encounter devices view	<code>portal/server.py</code> <code>portal_control_qr_print</code>	New field on the print template's encounter dict carrying <code>station_id</code> / <code>device_kind</code> / <code>device_model</code> / <code>label</code> per bound device.
Per-device print block	<code>portal/templates/qr_print.html</code> <code>{% if enc.devices %}</code>	Renders <code>.device-qr-section</code> with per-device QR blocks.

5. Limitations

- **The inline device QR uses** `window.location.origin` as the

base URL. That's correct when the operator opens the encounter console on the LAN host the bedside phones are reaching, but wrong if the operator opens the console via a different host (e.g. an SSH tunnel). Mitigation: the URL is also visible in monospace under the QR — operator can verify it matches the base URL the device tablet will reach.

- **No device card on the v6 ops view's roster** is changed.

M46 only touches the encounter-console inline cards and the print sheet. The v6 ops view's device cards (visible in the modal iframe) still have their own QR popup via the device detail modal.

- **Print sheet layout** uses 3-column grid for device QRs. If a

bed has many devices (10+) the section grows tall; CSS `page-break-inside: avoid` keeps individual blocks atomic but the section as a whole may flow past the encounter's first page. Acceptable; the patient header is still readable on the device-only continuation page.

- **The** `.ops-controls + p` **selector** depends on the

explanation paragraph being the immediate sibling of `.ops-controls`. If a future v6 template edit inserts another element between them, the paragraph re-appears. Add to the hide list if that happens.

- **WS-pushed device additions** still trigger an inline card

re-render only on the next 3 s poll. The print sheet is fetched on demand — operator must re-open the sheet to see new devices.

6. Test status

Test file	Asserts	Status	Last run
tests/v7/test_device_qr_and_modal_footer.py::test_embed_mode_hide_s_ops_controls_footer	?embed=1 page CSS contains .ops-controls + .ops-controls + p hide rules	PASS	2026-05-27
...::test_embed_mode_hide_block_unchanged_without_embed_flag	Without ?embed=1 the hide rule isn't injected (v6 path unchanged)	PASS	2026-05-27
...::test_inline_device_card_includes_qr_strip	renderDeviceCard markup has .device-card-qr + .device-card-qr-img + /api/qr.svg?data= + /device/join?code= + &station=	PASS	2026-05-27
...::test_inline_device_card_qr_uses_encounter_join_code	QR URL is built from cfg.joinCode (the encounter's join code), not hard-coded	PASS	2026-05-27
...::test_qr_print_renders_device_qr_per_encounter	After registering a device, the print sheet renders the device's label + kind + model + QR URL	PASS	2026-05-27
...::test_qr_print_omits_device_section_when_no_devices	Encounter with no devices → no  Devices section	PASS	2026-05-27
...::test_qr_print_route_passes_devices_view_per_encounter	Two devices on one bed both render with their station ids + labels	PASS	2026-05-27
Full v7 suite	317 passed, 1 skipped (M20 Playwright skip — unchanged)	PASS	2026-05-27

7. Change list

Date	Author	Change	Files
2026-05-27	claude-code	Initial M46: embed-mode hides .ops-controls+sibling paragraph; inline device cards render a QR strip; print sheet carries per-device QR section; 7 new tests	portal/templates/control_ops.html, portal/static/encounter_console.{js,css}, portal/server.py, portal/templates/qr_print.html, tests/v7/test_device_qr_and_modal_footer.py (new)

8. Open questions / known issues

- **Base-URL detection** for the inline device QR uses

`window.location.origin`. If a future deployment puts the operator workstation behind a reverse proxy with a different external host, the QR encodes the proxy URL which may not be what the bedside phone reaches. The server-rendered QRs on the print sheet use `_base_url_for_qr(request)` which already handles this (it prefers the LAN IP over the request's Host header). A future fix could expose a JSON endpoint that the encounter console fetches once at boot for the canonical base URL.

- **Device QR refresh** on the inline card uses cache-busting via

the URL params (different `station_id` → different QR). If a device is deleted and re-added with the same id (unlikely — `station_ids` are tokens), the browser might cache the old QR. Acceptable; standard `<img>` cache behavior.

- **Print sheet section position**. Today devices are at the

bottom under the 4 station QRs. Some operators may want the device QRs above (closer to where the patient banner is). Defer to LAN-test feedback.

Render this guide to PDF with `python docs/module_guides/render_pdfs.py`.