CardDemo (Rust) — Manual Test Suite

Test cases derived from the Software Requirements Specification v1.2

Prepared with Claude Code

2026-11-06 — version 1.1

Contents

How to use this suite **2**

Sign-on **2**
TC-SGN-01 — Sign-on screen layout . . . 2
TC-SGN-02 — Mandatory user id / password . . . 3
TC-SGN-03 — Unknown user and wrong password . . . 3
TC-SGN-04 — Case-insensitive sign-on and role routing . . . 3
TC-SGN-05 — Exit and invalid key . . . 3

Main menu **4**
TC-MEN-01 — Main menu options . . . 4
TC-MEN-02 — Option validation . . . 4
TC-MEN-03 — Optional module not installed . . . 4
TC-MEN-04 — Navigation and return . . . 4

Admin menu **5**
TC-ADM-01 — Admin menu . . . 5

User administration **5**
TC-USR-01 — User list and paging . . . 5
TC-USR-02 — Search from a user id . . . 5
TC-USR-03 — Search beyond the last key abends (original defect) . . . 5
TC-USR-04 — Selection codes . . . 6
TC-USR-05 — Add user: validation and duplicates . . . 6
TC-USR-06 — Update user . . . 6
TC-USR-07 — Delete user . . . 6

Account view **7**
TC-ACV-01 — Account view: input checks . . . 7
TC-ACV-02 — Account view: display . . . 7

Account update **7**
TC-ACU-01 — Account update: fetch and no-change . . . 7
TC-ACU-02 — Account update: validation order . . . 7
TC-ACU-03 — Account update: commit . . . 8

Card list **8**
TC-CDL-01 — Card list and paging . . . 8
TC-CDL-02 — Card list filters and selection errors . . . 8

Card detail **9**
TC-CDV-01 — Card detail from the list . . . 9

TC-CDV-02 — Card detail by keys 9

Card update **9**
TC-CDU-01 — Card update cycle 9

Transaction list **10**
TC-TRL-01 — Transaction list 10

Transaction view **10**
TC-TRV-01 — Transaction view 10

Transaction add **10**
TC-TRA-01 — Transaction add: validations 10
TC-TRA-02 — Transaction add: copy last and add 11

Bill payment **11**
TC-BIL-01 — Bill payment 11

Reports **11**
TC-RPT-01 — Report submission 11

Batch **12**
TC-BAT-01 — Daily posting 12
TC-BAT-02 — Interest calculation 12
TC-BAT-03 — Combine and statements 12
TC-BAT-04 — Transaction report 12
TC-BAT-05 — File print utilities 13
TC-BAT-06 — Export / import round trip 13
TC-BAT-07 — Reload jobs and reset 13
TC-BAT-08 — Differential test against the original COBOL 13

Requirements coverage **13**

Execution log **14**

How to use this suite

Environment. Build `carddemo` (`cargo build --release` in `carddemo-rs`), set `CARDDEMO_HOME` to an empty directory and run `carddemo reset` before each test unless the precondition says otherwise. Online tests run in `carddemo online`. Keys: Enter, F1–F12 = PF1–PF12, Shift+F1–F12 = PF13–PF24, Esc = CLEAR, Tab between fields, Ctrl+E = ERASE EOF.

Users. `USER0001` / `PASSWORD` (regular user), `ADMIN001` / `PASSWORD` (administrator). Account and card numbers have no right-justification in the maps, so type all 11 / 16 digits.

Recording results. For each step, compare the screen or output with *Expected result* and mark the case Pass / Fail in the execution log at the end. Messages must match **exactly**, including spaces and punctuation.

Original behaviour. Some expected results reproduce known defects of the original COBOL application (marked KD-nn). They are expected results, not failures.

Sign-on

TC-SGN-01 — Sign-on screen layout

Requirements: FR-SGN-01, BR-ONL-001
Precondition: Data reset (`carddemo reset`)

#	Action	Expected result
1	Start `carddemo online`.	Sign-on screen: `Tran : CC00`, `Prog : COSGN00C`, titles, today's date `mm/dd/yy` and time, AppID `CARDDEMO`, SysID; the cursor is in User ID; the password field shows `________`.

TC-SGN-02 — Mandatory user id / password

Requirements: FR-SGN-02
Precondition: Data reset (`carddemo reset`)

#	Action	Expected result
1	Press Enter with all fields empty.	`Please enter User ID ...`, cursor in User ID.
2	Type `USER0001` in User ID, erase the password field (Ctrl+E), press Enter.	`Please enter Password ...`, cursor in Password.
3	Type User ID `USER0001`, leave the password field untouched (underscores), press Enter.	`Wrong Password. Try again ...` (the underscores are transmitted: FSET field).

TC-SGN-03 — Unknown user and wrong password

Requirements: FR-SGN-04, FR-SGN-05
Precondition: Data reset (`carddemo reset`)

#	Action	Expected result
1	User ID `NOBODY`, password `X`, Enter.	`User not found. Try again ...`
2	User ID `USER0001`, password `WRONG`, Enter.	`Wrong Password. Try again ...`, cursor in Password.

TC-SGN-04 — Case-insensitive sign-on and role routing

Requirements: FR-SGN-03, FR-SGN-06
Precondition: Data reset (`carddemo reset`)

#	Action	Expected result
1	User ID `user0001`, password `password`, Enter.	Main Menu (`CM00`, `COMEN01C`).
2	F3, then sign on as `admin001` / `password`.	Admin Menu (`CA00`, `COADM01C`).

TC-SGN-05 — Exit and invalid key

Requirements: FR-SGN-07, BR-ONL-005, BR-ONL-008
Precondition: Data reset (`carddemo reset`)

#	Action	Expected result
1	On the sign-on screen press F5.	`Invalid key pressed. Please see below...`
2	Press F3.	Screen cleared: `Thank you for using CardDemo application ...`; the session ends.

#	Action	Expected result
3	Press Enter.	A new sign-on screen is shown.

Main menu

TC-MEN-01 — Main menu options

Requirements: FR-MEN-01
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown)

#	Action	Expected result
1	Inspect the menu.	Options `01. Account View` … `11. Pending Authorization View` are listed.

TC-MEN-02 — Option validation

Requirements: FR-MEN-02, BR-ONL-005
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown)

#	Action	Expected result
1	Type `99`, Enter.	`Please enter a valid option number...`
2	Type `0`, Enter.	`Please enter a valid option number...`
3	Type `ab`, Enter.	`Please enter a valid option number...`
4	Press F7.	`Invalid key pressed. Please see below...`

TC-MEN-03 — Optional module not installed

Requirements: FR-MEN-04
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown)

#	Action	Expected result
1	Type `11`, Enter.	Red message `This option Pending is not installed...`

TC-MEN-04 — Navigation and return

Requirements: FR-MEN-06, FR-MEN-07
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown)

#	Action	Expected result
1	Type `1` (single digit), Enter.	Account View screen (`CAVW`). The option was right-justified to `01`.
2	Press F3.	Main menu.
3	Press F3.	Sign-on screen.

Admin menu

TC-ADM-01 — Admin menu

Requirements: FR-ADM-01..04
Precondition: Data reset (`carddemo reset`); signed on as ADMIN001 / PASSWORD (admin menu shown)

#	Action	Expected result
1	Inspect the menu.	Options 1-6 (User List/Add/Update/Delete (Security), Transaction Type ... (Db2)).
2	Type 5, Enter.	Green message `This option is not installed ...` (Db2 module out of scope).
3	Type 7, Enter.	`Please enter a valid option number...`
4	Press F3.	Sign-on screen.

User administration

TC-USR-01 — User list and paging

Requirements: FR-USR-LST-01, -02, -04, -05, -06
Precondition: Data reset (`carddemo reset`); signed on as ADMIN001 / PASSWORD (admin menu shown)

#	Action	Expected result
1	Option 1.	User list page `00000001`: ADMIN001 ... ADMIN005, USER0001 ... USER0005.
2	Press F7.	`You are already at the top of the page...`
3	Press F8.	Rows are blank and `You have reached the bottom of the page...` (KD-11).
4	Press F8 again.	`You are already at the bottom of the page...`
5	Press Enter.	The first page is listed again.

TC-USR-02 — Search from a user id

Requirements: FR-USR-LST-01
Precondition: Data reset (`carddemo reset`); signed on as ADMIN001 / PASSWORD (admin menu shown); user list shown

#	Action	Expected result
1	Type `USER0003` in Search User ID, Enter.	The list starts at USER0003.

TC-USR-03 — Search beyond the last key abends (original defect)

Requirements: KD-10
Precondition: Data reset (`carddemo reset`); signed on as ADMIN001 / PASSWORD (admin menu shown); user list shown

#	Action	Expected result
1	Type `ZZZZZZZZ` in Search User ID, Enter.	The screen shows `... Transaction CU00 failed with abend AEIP ...`. Enter returns to sign-on.

TC-USR-04 — Selection codes

Requirements: FR-USR-LST-03
Precondition: Data reset (`carddemo reset`); signed on as ADMIN001 / PASSWORD (admin menu shown); user list shown

#	Action	Expected result
1	Type `X` next to USER0001, Enter.	`You have reached the bottom of the page...`: with exactly 10 users the read-ahead hits end of file and its message replaces `Invalid selection. Valid values are U and D` (original behaviour).
2	Type `u` next to USER0001, Enter.	Update User screen with USER0001 pre-filled and `Press PF5 key to save your updates ...`

TC-USR-05 — Add user: validation and duplicates

Requirements: FR-USR-ADD-01..04
Precondition: Data reset (`carddemo reset`); signed on as ADMIN001 / PASSWORD (admin menu shown)

#	Action	Expected result
1	Option 2; press Enter.	`First Name can NOT be empty...`
2	Fill First `Ada`, Last `Lovelace`, User ID `USER0099`, Password `secret`, Type `U`; Enter.	Green `User USER0099 has been added ...`, fields cleared.
3	Repeat the same input.	`User ID already exist...`
4	Press F4.	Fields cleared.

TC-USR-06 — Update user

Requirements: FR-USR-UPD-01..04
Precondition: Data reset (`carddemo reset`); signed on as ADMIN001 / PASSWORD (admin menu shown)

#	Action	Expected result
1	Option 3, User ID `USER0002`, Enter.	Fields shown, `Press PF5 key to save your updates ...`
2	Press F5 without changes.	Red `Please modify to update ...`
3	Change First Name, press F5.	Green `User USER0002 has been updated ...`
4	User ID `NOBODY99`, Enter.	`User ID NOT found...`

TC-USR-07 — Delete user

Requirements: FR-USR-DEL-01..03
Precondition: Data reset (`carddemo reset`); signed on as ADMIN001 / PASSWORD (admin menu shown); USER0099 added (TC-USR-05)

#	Action	Expected result
1	Option 4, User ID `USER0099`, Enter.	Names and type are shown (no password), `Press PF5 key to delete this user ...`
2	Press F5.	Green `User USER0099 has been deleted ...`
3	Enter again with `USER0099`.	`User ID NOT found...`

Account view

TC-ACV-01 — Account view: input checks

Requirements: FR-ACV-01, -02, BR-AC-07
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown)

#	Action	Expected result
1	Option 1.	Info `Enter or update id of account to display`. Row 1 shows only `W` of the transaction id (map quirk FR-ACV-06).
2	Enter with an empty account.	`Account number not provided`, red `*` in the account field.
3	Account `abc`, Enter.	`Account Filter must be a non-zero 11 digit number`

TC-ACV-02 — Account view: display

Requirements: FR-ACV-03, -04
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown); account view

#	Action	Expected result
1	Account `00000000001`, Enter.	Status `Y`, balance and limits in `+ZZZ,ZZZ,ZZZ.99` form (current balance `+ 194.00`), dates, customer name, SSN as `999-99-9999`, address, phones.
2	Account `99999999999`, Enter.	`Account:99999999999 not found in Cross ref file. Resp:000000013 Reas:0000` (two spaces before `Resp:` and `Reas:`; the message is cut at 75 characters).
3	Press F3.	Main menu.

Account update

TC-ACU-01 — Account update: fetch and no-change

Requirements: FR-ACU-01..06
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown)

#	Action	Expected result
1	Option 2.	Info `Enter or update id of account to update`.
2	Account `0`, Enter.	`Account Number if supplied must be a 11 digit Non-Zero Number`
3	Account `00000000001`, Enter.	Details shown, info `Update account details presented above.`
4	Press Enter without changes.	`No change detected with respect to values fetched.`

TC-ACU-02 — Account update: validation order

Requirements: FR-ACU-07a..07i, FR-ACU-12
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown); account 00000000001 fetched

#	Action	Expected result
1	Set Primary Card Holder X, Enter.	FICO Score: should be between 300 and 850 (sample data FICO is invalid and is checked first).
2	Set FICO 750, State NY, Zip 10001, Phone 1 212/555/0100, Phone 2 212/555/0101, Primary X, Enter.	Primary Card Holder must be Y or N., the field is red.
3	Set Open Date month 13, Enter.	Open Date: Month must be a number between 1 and 12.
4	Set Date of Birth to a future year, Enter.	Date of Birth:cannot be in the future
5	Set SSN first part 666, Enter.	SSN: First 3 chars: should not be 000, 666, or between 900 and 999
6	Set Phone 1 area code 123, Enter.	Phone Number 1: Not valid North America general purpose area code
7	Set State NY, Zip 90210, Enter.	Invalid zip code for state

TC-ACU-03 — Account update: commit

Requirements: FR-ACU-08, -09, -10
Precondition: Data reset (carddemo reset); signed on as USER0001 / PASSWORD (main menu shown); account 00000000001 fetched

#	Action	Expected result
1	Fix FICO/State/Zip/Phones as in TC-ACU-02, Primary Y, Credit Limit 5000, Enter.	Info Changes validated.Press F5 to save; all fields protected.
2	Press F5.	Info Changes committed to database.
3	Press Enter; then view account 00000000001 (option 1).	The empty search screen is shown; account view shows credit limit + 5,000.00.

Card list

TC-CDL-01 — Card list and paging

Requirements: FR-CDL-01, -04, -05, -07
Precondition: Data reset (carddemo reset); signed on as USER0001 / PASSWORD (main menu shown)

#	Action	Expected result
1	Option 3.	7 cards in card-number order, page 1, info TYPE S FOR DETAIL, U TO UPDATE ANY RECORD.
2	Press F7.	NO PREVIOUS PAGES TO DISPLAY
3	Press F8, then F7.	Page 2 shown, then page 1 again with the same first card.

TC-CDL-02 — Card list filters and selection errors

Requirements: FR-CDL-02, -03, -06
Precondition: Data reset (carddemo reset); signed on as USER0001 / PASSWORD (main menu shown); card list

#	Action	Expected result
1	Account filter `abc`, Enter.	`ACCOUNT FILTER,IF SUPPLIED MUST BE A 11 DIGIT NUMBER`, field red.
2	Account filter `00000000002`, Enter.	Only cards of account 2 are listed.
3	Clear the filter; type `S` on row 1 and `U` on row 2, Enter.	`PLEASE SELECT ONLY ONE RECORD TO VIEW OR UPDATE`, both rows red.
4	Type `X` on a row, Enter.	`INVALID ACTION CODE`

Card detail

TC-CDV-01 — Card detail from the list

Requirements: FR-CDV-01, -05, -06
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown); card list

#	Action	Expected result
1	`S` on row 1, Enter.	Card detail: info `Displaying requested details`, embossed name, expiry month/year, status; search fields protected.
2	Press F3.	Card list.

TC-CDV-02 — Card detail by keys

Requirements: FR-CDV-02..04
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown)

#	Action	Expected result
1	Option `4`.	Info `Please enter Account and Card Number.`
2	Enter with both fields empty.	`Account number not provided`, both fields red `*`.
3	Account `00000000001`, card `1234`, Enter.	`CARD ID FILTER,IF SUPPLIED MUST BE A 16 DIGIT NUMBER`

Card update

TC-CDU-01 — Card update cycle

Requirements: FR-CDU-01..07, KD-07
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown); card list

#	Action	Expected result
1	`U` on row 1, Enter.	Info `Details of selected card shown above.`
2	Enter without changes.	`No change detected with respect to values fetched.`
3	Status `X`, Enter.	`Card Active Status must be Y or N`
4	Name `JOHN 2`, Enter.	`Card name can only contain alphabets and spaces`
5	Expiry month `13`, Enter.	`Card expiry month must be between 1 and 12`
6	Valid values (status `N`), Enter.	Info `Changes validated.Press F5 to save.`

#	Action	Expected result
7	Press F5.	Info `Changes committed to database`. The record's CVV is now `000` (KD-07).
8	Press Enter.	Back on the card list (called from the list).

Transaction list

TC-TRL-01 — Transaction list

Requirements: FR-TRL-01..05
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown); daily posting run (TC-BAT-01)

#	Action	Expected result
1	Option 6.	Page `00000001`. Row 1 is the initialisation record from DALYTRAN.PS.INIT (key X'00', shown blank). Ten rows per page.
2	Search Tran ID `abc`, Enter.	`Tran ID must be Numeric ...`
3	F8 / F7.	Next / previous page.
4	`S` on row 2, Enter.	Transaction View with that transaction.

Transaction view

TC-TRV-01 — Transaction view

Requirements: FR-TRV-01..04
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown)

#	Action	Expected result
1	Option 7, Enter with an empty id.	`Tran ID can NOT be empty...`
2	Id `9999999999999999`, Enter.	`Transaction ID NOT found...`
3	A valid id from the list, Enter.	All fields shown, amount `+99999999.99`.
4	F4 / F5.	Screen cleared / transaction list.

Transaction add

TC-TRA-01 — Transaction add: validations

Requirements: FR-TRA-01..07, BR-TRA-0
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown)

#	Action	Expected result
1	Option 8, Enter.	`Account or Card Number must be entered...`
2	Account `00000000001`, Enter.	Card number filled from XREF; `Type CD can NOT be empty...`
3	Fill all fields but amount `12.50`, Enter.	`Amount should be in format -99999999.99`
4	Amount `+00000012.50`, Orig Date `2022-02-30`, Enter.	`Orig Date - Not a valid date...`

#	Action	Expected result
5	Valid dates, Confirm empty, Enter.	`Confirm to add this transaction...`

TC-TRA-02 — Transaction add: copy last and add

Requirements: FR-TRA-08..10
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown)

#	Action	Expected result
1	Option `8`, account `00000000001`, press F5.	Fields copied from the last transaction; `Confirm to add this transaction...`
2	Confirm `Y`, Enter.	Green `Transaction added successfully.  Your Tran ID is <n>.`, where n = highest id + 1 as 16 digits.

Bill payment

TC-BIL-01 — Bill payment

Requirements: FR-BIL-01..08
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown)

#	Action	Expected result
1	Option `10`, Enter.	`Acct ID can NOT be empty...`
2	Account `00000000001`, Enter.	Balance `+0000000194.00`, `Confirm to make a bill payment...`
3	Confirm `Y`, Enter.	Green `Payment successful.  Your Transaction ID is <n>.`
4	Account `00000000001`, Enter.	`You have nothing to pay...`

Reports

TC-RPT-01 — Report submission

Requirements: FR-RPT-01..07, BR-RPT-0
Precondition: Data reset (`carddemo reset`); signed on as USER0001 / PASSWORD (main menu shown)

#	Action	Expected result
1	Option `9`, Enter.	`Select a report type to print report...`
2	`X` in Monthly, Enter.	`Please confirm to print the Monthly report...`
3	`X` in Monthly, Confirm `Y`, Enter.	Green `Monthly report submitted for printing ...`; the status line names the report data set (internal reader ran TRANREPT).
4	Custom with start month 13, Enter.	`Start Date - Not a valid Month...`
5	Custom 2022-01-01 .. 2022-12-31, Confirm `X`.	`"X" is not a valid value to confirm...`

Batch

TC-BAT-01 — Daily posting

Requirements: FR-BAT-POST-01..11
Precondition: Data reset (`carddemo reset`)

#	Action	Expected result
1	`carddemo job TRANBKP` then `carddemo job POSTTRAN`.	`TRANSACTIONS PROCESSED :000000300`, `TRANSACTIONS REJECTED :000000038`, POSTTRAN RC=0004.
2	Inspect `datasets/AWS.M2.CARDDEMO.DALYREJS.D0001W06`.	38 records of 430 bytes; the trailer holds reason 100-103 and its description.
3	Online: transaction list.	The posted transactions are listed; account balances changed accordingly.

TC-BAT-02 — Interest calculation

Requirements: FR-BAT-INT-01..07, KD-01
Precondition: TC-BAT-01 done

#	Action	Expected result
1	`carddemo job INTCALC --parm 2022071800`.	RC=0000; SYSTRAN generation written with ids `2022071800000001`..., type 01, category 0005, description `Int. for a/c <acct>`.
2	Check the last account in TCATBAL order (online account view).	Its cycle credit/debit are NOT reset (KD-01); other accounts are reset to 0.

TC-BAT-03 — Combine and statements

Requirements: FR-BAT-STMT-01..07
Precondition: TC-BAT-02 done

#	Action	Expected result
1	`carddemo job TRANBKP`, `carddemo job COMBTRAN`, `carddemo job CREASTMT`.	All RC=0000.
2	Open `STATEMNT.PS` and `STATEMNT.HTML`.	One statement per card/account with name, address, balance, FICO, transaction lines and `Total EXP:`; the HTML shows name/address, basic details and the transactions as a table (it has no total line).

TC-BAT-04 — Transaction report

Requirements: FR-BAT-REPT-01..08, KD-02, KD-03
Precondition: TC-BAT-01 done

#	Action	Expected result
1	`carddemo job TRANREPT --start 2022-01-01 --end 2099-12-31`.	Report with header, page totals every 20 lines, account totals and `Grand Total`.
2	Check the totals.	The last transaction's amount is counted twice in the final page total (KD-02); there is no final account total (KD-03).

TC-BAT-05 — File print utilities

Requirements: FR-BAT-RDR-01..03, FR-BAT-VER-01..02
Precondition: Data reset (`carddemo reset`)

#	Action	Expected result
1	`carddemo job READACCT` / `READCARD` / `READXREF` / `READCUST` / `DALYVRFY`.	Record dumps as described; READXREF and READCUST print each record twice; DALYVRFY shows card, account and customer for each of the 300 daily transactions, and once more for the last one after end of file (FR-BAT-VER-02); all cards verify with the sample data.

TC-BAT-06 — Export / import round trip

Requirements: FR-BAT-XPRT-01..05, KD-09
Precondition: Data reset (`carddemo reset`)

#	Action	Expected result
1	`carddemo job CBEXPORT`.	`CBEXPORT: Total Records Exported:` = customers + accounts + xrefs + transactions + cards.
2	`carddemo job CBIMPORT`.	`Errors Written: 000000000`, `Unknown Record Types: 000000000`; the *.IMPORT data sets equal the master files in every named field (FILLER bytes are X'00').

TC-BAT-07 — Reload jobs and reset

Requirements: FR-BAT-UTIL-03, NFR-08
Precondition: Data reset (`carddemo reset`)

#	Action	Expected result
1	`carddemo job ACCTFILE` (and the other reload jobs).	The cluster is reloaded from the sample data.
2	`time carddemo reset`.	Completes in well under a second.

TC-BAT-08 — Differential test against the original COBOL

Requirements: NFR-01, NFR-13, NFR-14, KD-12
Precondition: GnuCOBOL 3.x installed; `cargo build --release`

#	Action	Expected result
1	In `carddemo-rs`: `python3 difftest/run.py`.	Builds the original batch programs with GnuCOBOL, runs them and the Rust port on the same data, and prints the report (also in `difftest/out/report.md`).
2	Read the result table.	Every row is `identical` (one row marked with an accepted GnuCOBOL difference, explained under the table); `Overall: all outputs identical`; exit code 0.

Requirements coverage

Requirement group	Test cases
FR-ACU	TC-ACU-01, TC-ACU-02, TC-ACU-03
FR-ACV	TC-ACV-01, TC-ACV-02
FR-ADM	TC-ADM-01
FR-BAT-INT	TC-BAT-02
FR-BAT-POST	TC-BAT-01
FR-BAT-RDR	TC-BAT-05
FR-BAT-REPT	TC-BAT-04
FR-BAT-STMT	TC-BAT-03
FR-BAT-UTIL	TC-BAT-07
FR-BAT-VER	TC-BAT-05
FR-BAT-XPRT	TC-BAT-06
FR-BIL	TC-BIL-01
FR-CDL	TC-CDL-01, TC-CDL-02
FR-CDU	TC-CDU-01
FR-CDV	TC-CDV-01, TC-CDV-02
FR-MEN	TC-MEN-01, TC-MEN-02, TC-MEN-03, TC-MEN-04
FR-RPT	TC-RPT-01
FR-SGN	TC-SGN-01, TC-SGN-02, TC-SGN-03, TC-SGN-04, TC-SGN-05
FR-TRA	TC-TRA-01, TC-TRA-02
FR-TRL	TC-TRL-01
FR-TRV	TC-TRV-01
FR-USR-ADD	TC-USR-05
FR-USR-DEL	TC-USR-07
FR-USR-LST	TC-USR-01, TC-USR-02, TC-USR-04
FR-USR-UPD	TC-USR-06

41 test cases, 124 steps; 25 of 25 functional requirement groups covered.

Execution log

Executed 2026-11-06 by Claude Code (scripted): the online and batch cases run through the same 3270 screen model the terminal UI uses (`carddemo-rs/crates/online/tests/manual_suite.rs`, one test per case, every step asserted); TC-BAT-08 runs the GnuCOBOL differential test. Re-run with `python3 docs/tests/execute.py`. **41 of 41 passed.**

Test case	Date	Tester	Result	Notes
TC-SGN-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-SGN-02	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-SGN-03	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-SGN-04	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-SGN-05	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-MEN-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-MEN-02	2026-11-06	Claude Code (scripted)	Pass	scripted terminal

Test case	Date	Tester	Result	Notes
TC-MEN-03	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-MEN-04	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-ADM-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-USR-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-USR-02	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-USR-03	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-USR-04	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-USR-05	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-USR-06	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-USR-07	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-ACV-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-ACV-02	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-ACU-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-ACU-02	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-ACU-03	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-CDL-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-CDL-02	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-CDV-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-CDV-02	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-CDU-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-TRL-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-TRV-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-TRA-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-TRA-02	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-BIL-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-RPT-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-BAT-01	2026-11-06	Claude Code (scripted)	Pass	scripted terminal

Test case	Date	Tester	Result	Notes
TC-BAT-02	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-BAT-03	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-BAT-04	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-BAT-05	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-BAT-06	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-BAT-07	2026-11-06	Claude Code (scripted)	Pass	scripted terminal
TC-BAT-08	2026-11-06	Claude Code (scripted)	Pass	difftest/run.py: 40 comparisons, all identical