# plus legio

## _travelers guide
## _for adding stars to the sky

| 2 switches · 3 ways | 3 cv inputs | 6 hp |
|---|---|---|

[ pitch ] press  [ pitch ] hold  › then  noon = 12 o'clock  tags = the panel drawing

additive voice · simple adsr · envelope timbre mod and a chorus lfo

← back to the legio starsystem

= hold

### 01 what it is — p1_01

| | |
|---|---|
| additive | a stack of oscillators, level set by timbre |
| envelope | adsr from one time knob |
| movement | envelope timbre mod + chorus lfo |
| in L R | pm · audio in · L feeds R if alone |
| out L R | stereo out, up to 16 V peak to peak |
| platform | a legio firmware · other firmwares |

### 02 pitch — p1_02 · enc

| | |
|---|---|
| [ enc ] turn | fine tune |
| [ enc ] press + turn | coarse tune |
| enc jack | pitch jack · –2 to +5 V |

### 10 first flight — p1_10 · the manual's tutorial

1. a pitch sequence into enc
2. gates into trig
3. s1 + s2 off
4. set 1 and 2
5. mod + and try the lfo

### 03 time · timbre — p1_03 · knobs 1 + 2

| | |
|---|---|
| 1 [ time ] | relative adsr segment times · also lfo amount |
| 2 [ timbre ] | additive oscillator levels |

### 04 mod · lfo — p1_04 · s1 · s2 · top → bottom

| | |
|---|---|
| s1 + | envelope pushes timbre up · needs timbre below max |
| s1 off | no envelope mod |
| s1 – | envelope pulls timbre down · needs timbre above min |
| s2 lfo | env follows the adsr · on always · off |

### __fig.01 : signal path — in → out




as the manual describes it

### 05 jacks — p1_05 · trig · cv · audio

| | |
|---|---|
| trig hit | gate / trigger for the adsr · near +1.6 V |
| in pm L R | phase mod in · L feeds R |
| out L R | up to 16 V peak to peak |
| cv | pitch –2 to +5 V · time + timbre 0 – 5 V |

### __fig.02 : envelope — time knob scales every stage




### 08 patch ideas — p1_08 · the manual

**plain voice** — off · off
time and timbre to taste

**moving** — + · env
the envelope opens timbre, lfo follows

**more range** — any
another oscillator into pm

### __fig.03 : the panel — numbers match the legend




| | |
|---|---|
| enc | pitch · fine tune |
| 1 | time · relative adsr segment times |
| 2 | timbre · additive oscillator levels |
| s1 | mod · + · off · – |
| s2 | lfo · env · on · off |
| trig | hit · gate / trigger for the adsr |
| cv | pitch · 1 · 2 · pitch –2…+5 V · others … |
| in | pm L / R · L feeds R if alone |
| out | out L / R · stereo out |

### 09 specs — p1_09

| | |
|---|---|
| size | 6 hp · 1.5 in deep |
| power | 140 mA +12 V · 22 mA –12 V |
| cv in | 0 – 5 V · pitch –2 to +5 V |
| trig | rising edge near +1.6 V |
| boot LEDs | blue / blue |