

Lab 3: Installing VMware Workstation, Kali Linux and ALFA card

Melvin Viado

Durham College

INFT 1101: Wireless Network Security

Nargis Khan

October 2, 2025

Part Task 1: Changing Default Password of Your Virtual Machine

1. Boot the Kali VM system.
2. Hit one of the arrow keys to stop the system from booting.
3. Highlight the Kali GNU/Linux option and hit “E” to edit the GNU Grub entry.
4. Navigate to the line that says “linux”
5. On the same line that says “ro”, change to “rw” to make it read-write to allow us to interact with the file system and change the password.
6. Add “init=/bin/bash” on the same line to run the bash shell once the system is finished booting.
7. Press “Ctrl + X” to reboot the system with the changes.
8. Once in the bash shell, run the “passwd kali” command to change the password
9. Type the new password, hit enter, then retype the new password again, hit enter.
10. Run the “reboot -f” command to restart the system.
11. Login to the “kali” account with the new password
12. I changed my password to “SecurePassword”

Task 2: Scan Surrounding Wi-Fi Networks with ALFA Card

```

kali@kali:~$ sudo iwconfig
eth0    no wireless extensions.

kali@kali:~$ sudo iwconfig
lo      no wireless extensions.

kali@kali:~$ sudo iwconfig
lo      no wireless extensions.

kali@kali:~$ sudo iwconfig
eth0    no wireless extensions.

kali@kali:~$ sudo iwconfig
wlan0   unassociated ESSID:"" Nickname:"WIFIDEFAULT"
Mode:Managed Frequency:2.412 GHz Access Point: Not-Associated
Sensitivity:0dB
Retry:off RTS:0x0fff Fragment:0x0fff
Power Management:off
Link Quality:0 Signal level:0 Noise level:0
Rx packet error:0 Rx Invalid crypt:0 Rx Invalid frag:0
Tx successive retries:0 Invalid alics:0 Missed beacon:0

kali@kali:~$ sudo wifite
wifite 2.7.0
a wireless auditor by dervid2
maintained by kmccorder
https://github.com/kmccorder/wifite2

Interface PHY Driver Chipset
1: wlan0 phy1 802.11n Realtek Semiconductor Corp. RTL8812AU 802.11a/b/g/n/ac 2T2R DD WLAN Adapter

[+] Enabling monitor mode on wlan0... enabled

NUM ESSID CH ENCR FWH WPS CLIENT
1 (1E:94:1D:1D:58:47) 8 WPA 5500 no 3
2 DIRECT-83-4P 11 WPA-P 5500 no 3
3 DELL649 11 WPA-P 5500 yes 3
4 KVM_20_202 7 WPA-P 5500 no
5 30a 1 WPA-P 5700 yes 6
6 Realtek 1 WPA-P 5600 yes
7 Realtek 1 WPA-P 5600 yes
8 Realtek 11 WPA-P 5600 yes
9 (BA:A3:10:A2:83:9C) 6 WPA-P 5500 no
10 Realtek 11 WPA-P 5500 yes
11 (BA:A3:10:A2:83:9B) 6 WPA-P 5500 no
12 (88:AC:8A:71:57:08) 1 WPA-P 5600 no
13 (A2:74:80:10:78:15) 8 WPA-P 5600 no
14 Realtek 11 WPA-P 5600 yes
15 (22:48:8C:82:82:82) 6 WPA-P 5600 no
16 (A2:88:20:82:20:85) 1 WPA 5500 no
17 Realtek 8 WPA-P 5100 no
18 Realtek 11 WPA-P 5700 yes
19 (58:2C:1B:11:14:15) 9 WPA-P 5100 no
20 (06:74:10:AD:5E:FA) 11 WPA-P 5200 no
21 (C8:74:2B:AD:5E:FA) 11 WPA-P 5200 no
22 802.11n P2P 0x11 11 WPA-P 5100 yes
23 (C8:74:10:AD:5E:FA) 11 WPA-P 5100 yes
24 (38:A2:80:1F:1F:1F) 11 WPA-P 5600 no
25 Realtek 1 WPA-P 4500 yes 1
26 (38:A2:80:1F:1F:1F) 11 WPA-P 4500 no
27 5140e 8 WPA-P 4200 yes 2
28 Realtek 6 WPA-P 4100 yes
29 (42:75:C3:C0:80:80) 8 WPA-P 4100 no
30 (18:70:9C:10:11:11) 8 WPA-P 4000 no
31 (42:75:C3:C0:80:80) 8 WPA-P 4000 no
32 Realtek 8 WPA-P 4000 no
33 (3E:20:9C:72:72:72) 8 WPA-P 3800 no
34 (3E:20:9C:72:72:72) 8 WPA-P 3800 no

[+] Scanning. Found 31 target(s), 10 client(s). Ctrl-C when ready

```