Program NFC Business Cards

NexCort iQ digital cards · NTAG213 / NTAG215 / NTAG216 stickers

Field programming sheet · Rev 1.1
Keep with blank tags & Android phone

> **What you write to the tag:** `https://www.nexcortiq.us/c/{cardId}` — not the public profile URL `/card/{slug}`. Editing the card later does *not* require rewriting the tag.

BEFORE YOU START

- Blank NFC stickers: **NTAG213** **NTAG215** **NTAG216** (all OK)
- **Android phone** with NFC on, using **Chrome** (Web NFC). iPhone can *read* tags after programming but cannot write from Chrome/Safari.
- Or NexCort iQ Mobile (Android / iOS field app) if your agency uses the QR/NFC programmer
- Person's digital card created and **Activated / Published** in Business Cards
- Open NFC Card Management over **HTTPS** on the phone (not a desktop browser)

A. CONSOLE — CREATE & ASSIGN THE TAG

1. Sign in to NexCort iQ and open **NFC Card Management** (Business Cards → NFC).
2. Click **Add NTAG213** (creates the permanent tag record and URL).
3. Copy the URL shown for that card — form `https://www.nexcortiq.us/c/…`
4. Choose the person under **Assign to…** → click **Assign**.

B. WRITE THE PHYSICAL STICKER

Option 1 — Chrome on Android (recommended)

1. On the same NFC Card Management row, tap **Write to tag** (Web NFC).
2. Allow NFC when Chrome prompts, then hold the blank sticker flat against the **upper back** of the phone.
3. Keep still until the write succeeds.
4. Status should move to **programmed** automatically. If not, tap **Mark programmed**.

Option 2 — NexCort iQ Mobile

1. From the row, open **Open QR/NFC instructions** (or paste the `/c/…` URL into the field tool).
2. In the app, open the code / write screen and choose **Program NFC Tag**.
3. Hold the sticker to the phone until write completes.
4. Return to NFC Card Management → **Mark programmed**.

C. VERIFY BEFORE YOU HAND OUT THE CARD

1. With a second phone (or the same phone after leaving the write screen), tap the sticker.
2. The phone should open the person's public card (redirect from `/c/{cardId}`).
3. Confirm name, company, and "Add to Contacts" look correct.
4. In NFC Card Management, click **Mark verified**.

5. Affix the sticker to the business card / badge holder. Do not cover with metal laminate.

QUICK REFERENCE

Item	Value
Tag URL pattern	`https://www.nexcortiq.us/c/{cardId}`
Public profile (QR / share)	`https://www.nexcortiq.us/card/{slug}`
Supported tags	NTAG213, NTAG215, NTAG216
Android field app	NexCort iQ — Google Play `us.rapidcortex.app`
iOS field app	NexCort iQ Mobile — App Store (unlisted; use direct link)
Revoke a lost tag	NFC Card Management → enter reason → **Revoke** (profile stays up; tag goes to /c/revoked)

STATION CHECKLIST

	Step	Initials
☐	Card activated / published for this person	
☐	NTAG record created & assigned	
☐	URL written to sticker (Chrome or mobile app)	
☐	Status = programmed	
☐	Tap-test opens correct profile	
☐	Status = verified; sticker affixed	

> **Troubleshooting:** App missing Business Card NFC → need an RC admin build with the feature; sign into Venue or Campus, not Safe & Sound. No write prompt in Chrome → Android Chrome only, NFC enabled, HTTPS page (Safari / desktop cannot write). Tag not detected → remove phone case; hold center of tag to NFC antenna (usually upper back). Wrong page after tap → confirm you wrote the `/c/…` URL, not `/card/…`. Lost card → Revoke the NFC id; issue a new NTAG; do not reuse revoked ids.