


Streaming from the Mevo app

This guide walks through pointing a Mevo camera at the RTMP relay so the stream shows up on the site and is forwarded to YouTube + GameChanger.



What you need

- A Mevo camera + the **Mevo Multicam** app (iOS/Android), signed in with a **Mevo Plus / Pro** account — *Custom RTMP* is a paid-tier feature.
- The relay's public IP or hostname (the same server that runs `docker compose up` from this folder). Default RTMP port is **1935**.
- The site's `/relay` page open on a phone or laptop so you can confirm the stream is live.

One-time: set up a Custom RTMP destination in Mevo

1. Open the **Mevo Multicam** app and tap your camera to connect.
2. Tap the **broadcast / share** icon (top-right on the camera preview).
3. Choose **Custom RTMP** (under *More platforms* — not YouTube/Facebook).
4. Fill in:

Field	Value
Name	e.g. Field relay
RTMP URL	rtmp://SERVER_IP:1935/live
Stream Key	anything non-empty, e.g. mevo
Username	leave blank
Password	leave blank

The relay's application `live { ... }` block (see `nginx.conf.template`) accepts any stream key on the `/live` path, so the key value itself doesn't matter — pick something memorable.

5. Tap **Save**. The destination now appears in the broadcast sheet.

Recommended encoding settings

Set these from the broadcast sheet → **Settings** (gear icon) before going live. The relay just forwards bytes, so the bitrate Mevo sends is what YouTube and GameChanger will receive.

Setting	Recommended	Notes
Resolution	1080p	Drop to 720p if you're on weak LTE.
Frame rate	30 fps	60 fps doubles bitrate for little benefit.
Bitrate	4–6 Mbps	YouTube's 1080p30 sweet spot.
Keyframe	2 s	Required by YouTube; GameChanger is happy.
Audio	AAC, 128 kbps	Mevo default — leave alone.

If the **Source** bandwidth on `/relay` keeps dipping, the upload link is the bottleneck — drop to 720p / 3 Mbps.

Going live

1. In Mevo, make sure **Custom RTMP** → **Field relay** is toggled on in the broadcast destinations list. (Other destinations like YouTube/Facebook *direct* should normally be **off** — the relay is what fans out.)
2. Tap the big red **Go Live** button.
3. Open `https://<your-site>/relay` on a phone:
 - **Source** dot should turn green within ~5 seconds and show "Mevo".
 - **YouTube** and **GameChanger** dots should follow once the relay opens its push connections (usually 2–5 s later).
 - The big banner flips to **LIVE** with the incoming bitrate.
4. The home page (`/`) auto-detects the YouTube live broadcast and embeds it once YouTube reports the stream as active (typically 10–30 s after the relay starts pushing).

Stopping the stream

Tap **End broadcast** in the Mevo app. Within a few seconds:

- `/relay` flips back to **OFFLINE**.
- YouTube ends the live broadcast (and may auto-publish a VOD depending on your YouTube Studio settings).

Troubleshooting

Symptom on <code>/relay</code>	Likely cause / fix
Source: No input after Go Live	Wrong RTMP URL in Mevo, or port 1935 blocked. Check <code>SERVER_IP</code> and firewall.
Source green, YouTube red	YouTube stream key in <code>rtmp-relay/.env</code> (<code>DEST1</code>) is wrong/expired. Rotate it.
Source green, GameChanger red	Game not started in GameChanger, or <code>DEST2</code> URL/key stale. Re-grab from GC app.
Bitrate flapping / "Source" pulsing offline	Weak uplink. Lower Mevo bitrate, or move closer to the hotspot/router.
<code>/relay</code> shows "Relay server not configured"	Set the stats URL once: <code>http://SERVER_IP:8080/stat</code> in the Relay server URL panel.
Page shows OFFLINE but Mevo says live	The stats-pusher container probably crashed. <code>docker compose ps</code> on the relay host.

Rotating the YouTube key

YouTube keys can be regenerated from **YouTube Studio** → **Go Live** → **Stream settings**. After rotating, update `DEST1` in `rtmp-relay/.env` and restart the relay:

```
docker compose up -d --force-recreate rtmp-relay
```

GameChanger keys live in the GameChanger app under **Streaming** — same flow, update `DEST2` and recreate.