Vendor Escalation Playbook and SLA Levers

Model: VFIP-PL-ESCALATE-VENDOR — Category: Procedures

Description: Operational playbook for escalating firmware-related incidents with the inverter vendor. Includes SLA definitions, escalation matrix, evidence checklist, contractual remedies, rollback clauses, and templates for legal and procurement.

Table of Contents

1. Purpose and Scope
2. Executive Summary — XG-440 Firmware Incident
3. SLA Definitions and Levers
4. Escalation Matrix and Timelines
5. Evidence Checklist and Artifact Tracking
6. Vendor Release Notes (v3.14.2 → v3.15.0)
7. Change Ticket Summaries (Rollout and Hotfix)
8. O&M Incident Report & Postmortem
9. Dispatch Runbooks: SCADA → CMMS Mapping
10. Settlement & Imbalance Charge Guidance (ERCOT)
11. Quantifying Damages & Presentation
12. Contractual Remedies and Rollback Clauses
13. Templates: Emails, Briefs, and Legal Notices
14. Verification Steps and Audit Trail
15. Troubleshooting Matrix & Error Codes
16. Appendices: Field Names, Codes, and Artifact Examples

Purpose and Scope

This playbook prescribes the procedures, evidence collection, escalation timelines, contractual levers, and templates for managing and escalating firmware-related incidents with the inverter vendor for the XG-440 fleet. It is intended for operations, engineering, legal, and procurement stakeholders involved in incident response, claims, and remediation planning.

Scope includes:

- Firmware incidents specifically related to XG-440 inverters (versions v3.14.2 to v3.15.0).
- Rollout windows and hotfix events between 2025-11-20 and 2025-12-08.
- Evidence collection required to support financial claims (e.g., $1.42M production loss and $260K O&M spend).
- SLA enforcement steps and legal/procurement template messaging.

Executive Summary — XG-440 Firmware Incident

On rollout date 2025-11-20, vendor released firmware v3.14.2→v3.15.0 to the XG-440 fleet. The change introduced protective logic modifications and parameter adjustments that triggered protective trip codes and curtailment behavior across multiple plants during 2025-11-20 to 2025-12-10. A hotfix was issued on 2025-12-08. The measured financial impact is $1,420,000 in lost energy settlement, plus $260,000 in incremental O&M corrective spend. This document captures the technical,

contractual, and evidentiary path to escalate and, where justified, pursue contractual remedies.

> Immediate objective: preserve time-stamped evidence, escalate per SLA, obtain vendor remediation or rollback, and prepare quantified claim packet for contract remedies.

SLA Definitions and Levers

Define the key SLAs and levers available in the vendor contract. Use these codes when escalating and in legal correspondence.

Term	Definition	Measurement	Remedy/Levers
Priority Response Time (PRT)	Time from vendor ticket creation to first technical response acknowledging incident.	Hours — target: 2 hours for P1, 4 hours for P2.	Escalate to Tier 2 and Tier 3 contacts; trigger SLA credit if exceeded.
Resolution Time (RT)	Time from ticket creation to delivery of fix/rollback or acceptable workaround.	Hours/Days — P1: 24 hours; P2: 72 hours; P3: 10 business days.	Remedial action plan, hotfix delivery, or documented rollback within contract window.
Evidence Preservation Window (EPW)	Vendor obligation to preserve logs, telemetry, and signed ticket timestamps.	Minimum 90 days from incident start.	Legal hold; failure triggers contractual breach process.
Remediation Acceptance (RA)	Customer verification window to accept vendor test fix — default 72 hours.	Measured in business hours from delivery of fix build.	Partial acceptance may trigger additional test cycles and credits if unsuccessful.
Rollback Commitment (RB)	Vendor obligation to provide rollback instructions and signed binary for previous stable version.	Within 24 hours of agreed rollback decision.	Rollback support or compensation for extended remediation.

Contractual Levers (Priority)

1. Immediate remediation or rollback — operational priority.
2. SLA credits and financial offsets — applied per contract Appendix C.
3. Withhold of scheduled payments until remediation occurs — coordinate with procurement.
4. Formal breach notice and escalation to executive sponsor within vendor org.
5. Legal claim for damages with quantification packet (see Quantifying Damages section).

Escalation Matrix and Timelines

Use the matrix below to trigger the correct level of vendor engagement and internal notification chain. Times are measured from incident detection time (t0).

Severity	Criteria	Vendor Tier Contact	Target Response	Action Steps
P1 (Critical)	Fleet-wide curtailment > 15% of capacity, revenue impact > $100k/day, safety risk	Tier 1: Support Hotline (24/7), Tier 2: Engineering On-call, Tier 3: VP of Product	Initial ack: ≤ 2 hours; remediation plan: ≤ 8 hours	Open vendor ticket, notify internal Exec Sponsor, preserve SCADA snapshots, request hotfix/rollback.
P2 (High)	Single-plant curtailment > 10% or repeated protective trips across serial range	Tier 1 Support → Tier 2 Engineering	Ack: ≤ 4 hours; remediation plan: ≤ 24-48 hours	Collect telemetry, assign O&M crew for verification, request vendor patch and test schedule.
P3 (Medium)	Single inverter issues, isolated trips, or performance degradation	Tier 1 Support	Ack: ≤ 48 hours; remediation plan: ≤ 10 business days	Log ticket, schedule maintenance window, request RCA.

Vendor Tier Contact Template

(Use in subject line: `[VFIP-P1] XG-440 Incident — Plant CODE — t0=2025-11-20T14:03Z`)

```
To: support@vendor.example.com; oncall-engineering@vendor.example.com
Cc: vp-product@vendor.example.com; procurement@ourco.example.com
Subject: [VFIP-P1] XG-440 Incident — PLANT-ALPHA — t0=2025-11-20T14:03Z

Summary:
- Fleet: XG-440
- Affected serials: XG440-1001 → XG440-1250 (range)
- Symptom: Protective trip TRIP-31 and TRIP-44 triggered with curtailment
window 2025-11-20T13:58Z → 2025-11-20T18:12Z
- Impact estimate: $312,000 lost settlement (preliminary)
- Action requested: Immediate acknowledgement and remediation plan or rollback
package within 8 hours.
```

Evidence Checklist and Artifact Tracking

Collect and index every artifact to support a claim. Store copies in secured evidence repository (S3 or legal vault) with immutable timestamps where possible.

Artifact	Required Fields/Format	Retention	Owner
SCADA Event Extracts	CSV or Parquet: timestamp (ISO8601), device_id, status_code, power_mw, alarm_code	90+ days; snapshot on t0 and t0+24h	SCADA Engineer
Signed Vendor Ticket Timestamps	Ticket ID, created_at, vendor_ack_at, vendor_resolution_at, attachments	Contract EPW (90 days)	Operations / Procurement

Telemetry Snapshots — Pre/Post Upgrade	Binary logs and parsed metrics: voltage_v, cur_a, temp_c, freq_hz; snapshot at -24h, 0h, +24h	90 days	Controls Engineer
CMMS Work Orders & Invoices	WO ID, date, technician, labor_hours, parts_cost, invoice_pdf	7 years for accounting	O&M Manager
Change Ticket Summaries (Vendor Portal)	Release notes, serial ranges, deployment timeline	90 days	Engineering
Settlement Data	SCADA-to-Settlement reconciliation fields: interval_time, measured_mw, scheduled_mw, deviation_mw, imbalance_charge	7 years	Settlement Analyst

Evidence Index Example

```
EVIDENCE-INDEX-2025-11-20
- SCADA-PLANT-ALPHA-T0.csv  (t0=2025-11-20T13:58Z)
- TELEMETRY-PLANT-ALPHA-PRE-2025-11-19.parquet
- TICKET-#VND-55432.pdf (created=2025-11-20T14:11Z,
vendor_ack=2025-11-20T16:25Z)
- CMMS-WO-2025-11-21-994.pdf (invoice=2025-11-25, labor=48h)
- SETTLEMENT-ERCOT-2025-11-20.xlsx (interval reconciliation)
```

Vendor Release Notes (v3.14.2 → v3.15.0)

Below are the extracted, relevant sections from vendor release notes. Use exact fields when matching to logs.

v3.14.2 (Released 2025-11-18)

Summary: Minor protective logic tuning for frequency ride-through and anti-islanding detection.

Parameter Changes:

- `FRT_ENABLE`: true → true (no change)
- `FRT_TRIP_DELAY_MS`: 3000 → 2500
- `ANTISLIP_SENS`: 0.75 → 0.85

Protective Trip Codes Affected: TRIP-12 (FRT), TRIP-31 (Anti-Islanding)

Recommended Rollback Conditions: Increased incidence of TRIP-31 across multi-unit sites within first 24 hours — recommend rollback to v3.14.1.

v3.14.9 (Intermediate)

Summary: Additional changes to DC overcurrent thresholds and HVRT window adjustment.

Parameter Changes:

- `DC_OC_THRESH_A`: 120 → 115

- `HVRT_WINDOW_MS`: 2000 → 1800

Protective Trip Codes Affected: TRIP-44 (DC OC), TRIP-31 (anti-islanding)

Recommended Rollback Conditions: Repeated TRIP-44 occurrences, especially during system ramping, indicate revert to v3.14.5.

v3.15.0 (Released 2025-11-20)

Summary: Consolidated release including combined protective logic and a new adaptive curtailment feature.

Parameter Changes:

- `ADAPTIVE_CURTAILMENT_ENABLE`: false → true
- `CURTAIL_STEP_MW`: 0.5 → 1.0
- `TRIP_HYST_MS`: 1500 → 1000

Protective Trip Codes Introduced/Modified: TRIP-31 (modified), TRIP-44 (modified), TRIP-99 (new internal safety trip)

Recommended Rollback Conditions: If adaptive curtailment causes >10% unplanned curtailment during dispatch windows or repeated TRIP-99 occurrences, initiate rollback to v3.14.9.

Vendor Notes on Hotfix (v3.15.1) — Issued 2025-12-08

Summary: Hotfix targeted at TRIP-99 false-positive suppression and adaptive curtailment scaling.

Files Provided: v3.15.1 binary, rollback binary v3.14.9, test harness script `test-harness-3.15.1.sh`

Vendor Guidance: Apply to a single pilot inverter per plant and observe for 48 hours; collect pre/post snapshots.

Change Ticket Summaries (Rollout and Hotfix)

Extracts from vendor portal and internal change management. Use ticket IDs in all correspondence.

Ticket ID	Date	Scope	Serial Ranges	Notes
VND-CHG-2025-11020	2025-11-20	Fleet rollout v3.15.0	XG440-1001 → XG440-1500	Staggered deploy; initial window 2025-11-20T02:00Z → 2025-11-21T06:00Z. Vendor recommended pilot of 10 units per plant.
VND-CHG-2025-11021	2025-11-21	Continue rollout — remaining serials	XG440-1501 → XG440-2000	Rollback option documented as `RB-v3.14.9`. Deployment control plane indicated immediate status reports.

VND-HFX-2025-12008	2025-12-08	Hotfix v3.15.1	Pilot: XG440-1100, XG440-1333, XG440-1410 (per plant selection)	Hotfix marked urgent after TRIP-99 reports; vendor recommends pilot before global application.

Change Control Procedures

1. Validate rollback binary integrity via SHA256 against vendor-provided checksum before installation.
2. Create a rollback ticket immediately prior to deployment window and attach verification plan.
3. Record signed ticket acceptance and preservation acknowledgement to meet EPW.

O&M Incident Report & Postmortem (Day-by-Day)

Consolidated O&M timeline and root cause analysis. Use this as primary narrative for operational impact.

Timeline (Condensed)

1. 2025-11-20 02:00Z — Vendor rollout begins (v3.15.0). First pilot units in PLANT-ALPHA.
2. 2025-11-20 13:58Z — SCADA alarms: TRIP-31 and TRIP-44 observed across multiple inverters in PLANT-ALPHA. Automated curtailment engaged.
3. 2025-11-20 14:11Z — Ticket VND-CHG-2025-11020 updated with incident details. Vendor acknowledged at 2025-11-20 16:25Z.
4. 2025-11-20 18:12Z — Partial rollback executed on subset (20% of plant) reversing to v3.14.9; some units returned online; inconsistent behavior observed.
5. 2025-11-21 — Continued incidents at PLANT-BETA and PLANT-GAMMA; vendor performs analysis pointing to adaptive curtailment scaling.
6. 2025-12-08 — Vendor releases hotfix v3.15.1; pilot applied to selected serials; results mixed; rollback to v3.14.9 recommended by our Controls team.
7. 2025-12-10 — Final mitigation: full fleet rollback initiated and verified by 2025-12-12; vendor to provide RCA and remediation plan.

Curtailement Window Descriptions

Documented curtailment windows per plant (example extraction):

Plant	Start	End	Peak Deviation (MW)	Primary Trip Codes
PLANT-ALPHA	2025-11-20T13:58Z	2025-11-20T18:12Z	18.7	TRIP-31, TRIP-44

PLANT-BETA	2025-11-21T04:20Z	2025-11-21T10:40Z	12.3	TRIP-99, TRIP-44
PLANT-GAMMA	2025-11-22T07:10Z	2025-11-22T09:55Z	6.0	TRIP-31

Root Cause Hypothesis

Primary contributing factors identified:

- Adaptive curtailment scaling (ADAPTIVE_CURTAILMENT_ENABLE) set to true with increased CURTAIL_STEP_MW, causing stepwise curtailment during normal dispatch variability.
- Reduced TRIP_HYST_MS decreased hysteresis, increasing sensitivity and causing TRIP-31 / TRIP-44 activation during transient events.
- Deployment without sufficient pilot coverage across serial ranges and topologies.

Corrective Actions Taken

1. Immediate selective rollback to v3.14.9 across fleet between 2025-12-10 and 2025-12-12.
2. Comprehensive telemetry comparison and stitched SCADA snapshots for t-24h and t+24h for each plant.
3. Procured vendor commitment for extended EPW and delivery of incremental hotfix test plan.

Dispatch Runbooks: SCADA Alarms → CMMS Work Orders

Define deterministic mapping from SCADA alarm codes to CMMS corrective work orders. Use templates to speed crew dispatch and ensure consistent logging.

SCADA Alarm Code	Meaning	CMMS WO Template	Required Fields
TRIP-31	Anti-islanding protective trip	WO-TRIP-31-INSPECT	Device ID, serial, timestamp, pre/post telemetry snapshot refs, on-site technician initial findings
TRIP-44	DC overcurrent trip	WO-TRIP-44-DC-INV	Device ID, measured DC current, inverter DC temp, PV string isolation status
TRIP-99	Internal safety trip (new)	WO-TRIP-99-ROOT	Device ID, firmware version, binary hash, logged error stack, last command

CMMS Work Order Template — Example (WO-TRIP-31-INSPECT)

```
WO-ID: WO-TRIP-31-INSPECT-20251120-ALPHA-001
Plant: PLANT-ALPHA
Device: XG440-1105
Serial: XG440-1105
Reported At: 2025-11-20T14:01Z
Reported By: SCADA-AUTO
```

```
Priority: P1
Description:
- Protective Trip TRIP-31 engaged. Unit offline. Attach SCADA snapshot: SCADA-
PLANT-ALPHA-20251120-1401.csv
Tasks:
1) Verify inverter firmware version and binary hash.
2) Collect telemetry snapshot (t0 and t0+15m).
3) Perform local restart per vendor rollback/mitigation SOP.
4) Record test results in CMMS and attach to vendor ticket VND-CHG-2025-11020.
Cost Codes:
- Labor: 2 techs * 4 hours = [calculate]
- Parts: TBD
```

Settlement & Imbalance Charge Guidance (ERCOT)

Outline of how imbalance charges are calculated and which fields must be reconciled for claims. This section describes required reconciliation fields, example calculations, and evidence mapping.

Key Fields to Reconcile

- `interval_time` — Settlement interval timestamp (15-minute intervals in ERCOT).
- `measured_mw` — Metered (SCADA) output for the interval.
- `scheduled_mw` — ERCOT dispatch schedule for the resource.
- `deviation_mw` = scheduled_mw – measured_mw
- `imbalance_charge_usd` — Calculated penalty (deviation_mw * MRP or applicable price) per interval.

Example Imbalance Calculation (Simplified)

```
Interval: 2025-11-20 14:15Z - 14:30Z
scheduled_mw = 50.0
measured_mw  = 32.3
deviation_mw  = 50.0 - 32.3 = 17.7
market_price_per_mw = $45.00 (MRP for interval)
imbalance_charge = 17.7 * 45.00 = $796.50
```

Aggregate these calculations across all impacted intervals and plants to arrive at total settlement impact (documented $1,420,000). The settlement analyst must produce an interval-level reconciliation spreadsheet and attach SCADA extracts that match metered values.

Supporting Data Sources

- Vendor telemetry snapshots (to verify measured_mw values)
- ERCOT Market Data (MRP per interval)
- Internal dispatch schedules
- SCADA-to-meter reconciliation report signed by Settlement Analyst

Quantifying Damages & Presentation

Instructions for preparing the damages packet for legal and procurement review. Use the following steps and a standardized template to quantify and present the $1.42M production impact and $260K

O&M spend.

Required Calculation Steps

1. Interval-level reconciliation: For each 15-minute interval during incident windows, compute deviation_mw and per-interval imbalance charge (as above).
2. Apply applicable market price or penalty rate per contract clause (list clause reference: Contract Appendix D, imbalance pricing methodology).
3. Sum across intervals and plants to produce gross settlement loss.
4. List incremental O&M costs with CMMS invoices and labor logs to validate the $260,000 figure.
5. Subtract any mitigations or insurer recoveries to produce net claim amount.

Damage Presentation Template (Summary)

Summary of Losses

Description	Amount (USD)	Supporting Artifact
Lost energy settlement (aggregate)	$1,420,000.00	SETTLEMENT-2025-11-20-to-2025-12-10.xlsx (interval reconciliation)
Incremental O&M corrective spend	$260,000.00	CMMS-invoices-2025-11-20-to-2025-12-15.zip
Other demonstrable costs (travel, emergency staffing)	$12,500.00	Expense reports
Total Net Claim	**$1,692,500.00**	All artifacts referenced above

Articulation Tips for Legal Packet

- Include signed ticket timestamps showing vendor acknowledgement and remedies offered.
- Include telemetry pre/post snapshots with checksums and ingestion metadata.
- Attach CMMS invoices with labor breakdown and technician signatures.
- Provide settlement analyst affidavit certifying interval calculations.
- List mitigation steps attempted and vendor responses with timestamps.

Contractual Remedies and Rollback Clauses

Summarize the contract clauses most relevant to enforcement. Where possible, quote exact clause numbers when communicating with vendor and legal.

Commonly Used Clauses (Examples)

Clause	Purpose	Action

Appendix B — SLA Credits	Defines credit schedule for missed response and resolution SLAs	Calculate credits for each SLA miss and deduct from invoice or request direct refund.
Section 6.3 — Evidence Preservation	Vendor obligation to preserve logs and telemetry for EPW	Send formal preservation notice; use as basis for claim if vendor fails to preserve artifacts.
Section 8.1 — Rollback Support	Vendor to provide rollback package and support within 24 hours of request	Invoke and document rollback decision; if not met, pursue breach remedy.
Section 12 — Limitation of Liability	Caps vendor liability to X times fees, or excludes certain indirect damages	Assess exposure and prepare argument referencing vendor negligence in deviating from pilot guidance.

Procedural Steps to Invoke Remedies

1. Document all SLA misses with timestamps and ticket evidence.
2. Issue formal notice of breach per contract procedure (include clause references).
3. Request remediation plan and credits in writing; set 7-day response deadline.
4. If remediation unsatisfactory, instruct procurement to withhold payment and request executive escalation.
5. Prepare damages packet and serve notice of intent to claim if vendor does not agree to settlement terms.

Templates: Emails, Briefs, and Legal Notices

Ready-to-use templates for rapid communication. Replace bracketed fields before sending.

1) Executive Escalation Email (Operations → Vendor Exec)

```
To: vp-product@vendor.example.com
Cc: support@vendor.example.com; procurement@ourco.example.com;
legal@ourco.example.com
Subject: [VFIP-P1] Immediate Executive Escalation — XG-440 Fleet Incident
(t0=2025-11-20T13:58Z)

Dear [VP Product],

We are invoking executive escalation per Contract Section 8.1 due to a
production-impacting firmware deployment (v3.15.0) that has resulted in
cumulative settlement losses of $1,420,000 and $260,000 in incremental O&M
spend. Ticket: VND-CHG-2025-11020 (acknowledged 2025-11-20T16:25Z).

Requested actions:
1) Provide immediate rollback package and remote support by 2025-11-20T23:00Z.
2) Preserve all telemetry and ticket logs for EPW (90 days).
3) Provide remediation plan and timeline within 8 hours.

We expect a written response and plan of action.
```

```
Regards,
[Name]
Operations Director
```

2) Preservation Notice (Legal)

```
To: legal@vendor.example.com; cust-support@vendor.example.com
Subject: Formal Preservation Notice — XG-440 Incident 2025-11-20

This communication constitutes a formal preservation notice per Contract
Section 6.3. Preserve all logs, telemetry, firmware binaries, change control
records, and internal communications related to XG-440 and release versions
v3.14.2 through v3.15.1 (inclusive) for a minimum of 90 days.

Failure to preserve may be treated as spoliation and will be addressed in our
breach claim.

Regards,
[Name]
Senior Counsel, OurCo
```

3) Damage Claim Submission (Procurement → Vendor)

```
To: procurement@vendor.example.com; accounts@vendor.example.com
Subject: Damage Claim — XG-440 Deployment v3.15.0 — Claim ID: CLM-2025-11020-01

Attached: SETTLEMENT-RECON-2025-11-20-to-2025-12-10.xlsx, CMMS-
INVOICES-2025-11-20-to-2025-12-15.pdf, TICKET-ARCHIVE.zip

Claim Amount: $1,692,500.00
Basis: Settlement losses and incremental O&M spend resulting from firmware
deployment v3.15.0 (ticket VND-CHG-2025-11020). We request vendor remediation
or financial settlement within 30 days.

Regards,
[Name]
Head of Procurement
```

Verification Steps and Audit Trail

Post-remediation verification and audit steps to close the incident and prepare an audit-ready folder.

1. Confirm rollback binary application on all impacted serials and verify firmware versions via SCADA query: `SELECT serial, firmware_version FROM inverters WHERE updated_at > 2025-11-20`.
2. Collect and hash telemetry snapshots: compute SHA256 and store in evidence log.
3. Produce signed verification by Controls Engineer: include list of serials, timestamps, and test results.

4. Cross-validate CMMS work orders and invoices against on-site technician logs.
5. Generate final RCA document with vendor inputs and post the packet to Legal Vault with access control.

Verification Checklist

- All rollback binaries checksum-verified: yes/no
- SCADA pre/post snapshots collected and stored: yes/no
- Vendor ticket archive preserved: yes/no
- Settlement reconciliation signed by Analyst: yes/no
- CMMS invoices attached and verified: yes/no

Troubleshooting Matrix & Error Codes

Rapid troubleshooting flows for the most common trip codes observed during the incident.

TRIP-31 — Anti-Islanding Trip

Symptom	Likely Root Causes	Immediate Actions	Resolution
Unit trips offline during grid frequency fluctuation	Reduced TRIP_HYST_MS; ADAPTIVE_CURTAILMENT overreaction; firmware bug	1) Capture SCADA snapshot. 2) Check firmware version. 3) If v3.15.x, execute rollback pilot. 4) Create WO-TRIP-31-INSPECT.	Rollback to v3.14.9 or apply hotfix v3.15.1 per vendor guidance and monitor 48 hours.

TRIP-44 — DC Overcurrent Trip

Symptom	Likely Root Causes	Immediate Actions	Resolution
DC overcurrent alarms during ramp periods	Lowered DC_OC_THRESH_A; PV string transient; firmware mis-calculation	1) Verify DC current logs. 2) Inspect PV string isolation. 3) Apply vendor-provided mitigation or rollback.	Revert DC_OC_THRESH_A to previous value or rollback to stable firmware.

Appendices: Field Names, Codes, and Artifact Examples

Appendix A — SCADA/Telemetry Field Dictionary

Field	Type	Description
timestamp	ISO8601	Event timestamp in UTC
device_id	string	Internal device identifier
serial	string	Manufacturer serial number (e.g., XG440-1105)
firmware_version	string	Installed firmware (e.g., v3.15.0)

power_mw	float	Active power in MW
alarm_code	string	Protective trip code (e.g., TRIP-31)
binary_hash	SHA256	Binary hash of installed firmware

Appendix B — Example Artifact (Ticket Extract)

```
TICKET-VND-CHG-2025-11020
Created At: 2025-11-20T02:03Z
Vendor Ack At: 2025-11-20T16:25Z
Vendor Resolution At: 2025-12-12T20:11Z
Attachments:
- ReleaseNotes_v3.15.0.pdf
- Rollback_RB-v3.14.9.bin (sha256: 3b7f...9a1)
- TestResults_PLANT-ALPHA_pilot.pdf
```

Appendix C — Recommended Internal Tags for RAG Indexing

When storing artifacts for retrieval-augmented generation, tag using the following taxonomy:

- **incident_id**: XG440-20251120
- **firmware_version**: v3.15.0
- **trip_codes**: TRIP-31, TRIP-44, TRIP-99
- **plant**: PLANT-ALPHA / PLANT-BETA / PLANT-GAMMA
- **evidence_type**: SCADA, TELEMETRY, CMMS, TICKET, SETTLEMENT

Document Model: VFIP-PL-ESCALATE-VENDOR | Version: 1.0 | Generated: 2025-12-20

Distribution: Internal — Operations, Engineering, Legal, Procurement. Retain and store evidence in accordance with corporate retention policy.

Prepared by: Vendor Incident Response Team — OurCo