


Controlled by HTTP Get method

1. Overview

lotzone's device controlled by the HTTP get method in local network , which can be directly controlled by URL in the browser.

2. URL commands

- (1) <http://admin:12345678@192.168.1.166/relay.cgi?relayon1=on>
The relay 1 is on.
- (2) <http://admin:12345678@192.168.1.166/relay.cgi?relayoff1=off>
The relay 1 is off.
- (3) <http://admin:12345678@192.168.1.166/relay.cgi?pulse1=pulse>
The relay 1 is pulse.
- (4) <http://admin:12345678@192.168.1.166/state.cgi>
Get the state of the device.



```
{"cmd":"state","output":"00000000","input":"00000000","humidity":35.8,"centigrade":20.5,"fahrenheit":68.90,"sn":"v52471c418cbdffc"}
```

Return device status in JSON format

```
{
  "cmd": "state",           //The type of command
  "output": "10000000",    //state of relay
  "input": "00000000",     //state of input
  "humidity": 37.6,
  "centigrade": 35.7,
  "fahrenheit": 96.26,
  "sn": "v52471c468cbdffc" //Serial number code
}
```