

Toward Compact Multiqubit Gates on Trapped Ions: A Hardware-Aware Pulse Synthesis

Masoud Hakimi Heris
ECE Department
NC State University
Raleigh, NC, USA
mhakimi@ncsu.edu

Kevin J. Joven
ECE Department
NC State University
Raleigh, NC, USA
kjjovenn@ncsu.edu

Yuan Liu
ECE/CS/Physics Departments
NC State University
Raleigh, NC, USA
q_yuanliu@ncsu.edu

Frank Mueller
Computer Science Department
NC State University
Raleigh, NC, USA
fmuelle@ncsu.edu

Abstract—Multiqubit gates such as the Toffoli are essential building blocks for quantum algorithms, but their standard realization on trapped-ion hardware requires gate decomposition that adds significant circuit depth. This overhead is particularly relevant for advanced algorithmic frameworks such as quantum signal processing and quantum singular value transformation, which rely heavily on multi-controlled operations. As part of a broader investigation into native multiqubit gates on trapped ions, we examine the single-step Toffoli construction of Wang et al. [1], which has remained theoretical due to the controlled-rotation primitive it requires. Recent advances in effective-Hamiltonian engineering through Magnus expansions of bichromatic spin-dependent forces provide a route to that primitive. Using HyPulse [2], we apply optimal-control pulse design on realistic trapped-ion calibration parameters and synthesize a pulse that performs the Toffoli gate using the same physical resources as the construction of Wang et al. [1]. The result demonstrates that single-step Toffoli synthesis is feasible within this operator structure using only native trapped-ion primitives, providing a complementary route alongside existing proposals.

Index Terms—trapped ions, multiqubit gates, Toffoli, pulse synthesis, hybrid qubit-oscillator

I. INTRODUCTION

Multiqubit gates such as the Toffoli gate (CCNOT) are fundamental building blocks of quantum algorithms, used in error correction and the Grover diffusion operator [3]. Their standard realization on trapped-ion hardware decomposes into multiple two-qubit and single-qubit gates [4], [5], with each two-qubit gate implemented through a Mølmer-Sørensen (MS) interaction. The aggregate cost motivates the search for *single-step* multiqubit gates that bypass this decomposition overhead.

Beyond circuit depth, multiqubit gates are a key bottleneck for advanced quantum algorithms. Frameworks such as quantum signal processing (QSP) [6] and quantum singular value transformation (QSVT) [7], [8], which unify a broad class of quantum algorithms via block-encoded polynomial transformations, rely on multi-controlled rotations and ancilla-mediated controls. These operations are naturally expressed as multiqubit gates, so reducing their cost is not merely a depth-optimization concern but directly affects the feasibility of QSP/QSVT-based algorithms on near-term hardware.

Several proposals address this problem on trapped ions. Espinoza et al. [9] use adiabatic ramping of phonon-mediated Ising interactions. Katz et al. [10] use spin-dependent squeez-

ing at the second motional sideband. Earlier, Wang et al. [1] proposed a general framework in which any multiqubit gate can be realized through a shared motional bus, using controlled-displacement and controlled-rotation interactions. While the construction of Wang et al. [1] predates these later proposals, its specific realization on trapped-ion hardware has remained theoretical, since the controlled-rotation primitive ($\sigma_z \cdot a^\dagger a$) it requires has not been directly demonstrated.

This paper is a preliminary step toward filling that gap. As part of a broader effort on native multiqubit gates for trapped-ion platforms, we examine whether optimal-control pulse design [11] can synthesize a high-fidelity pulse using the same physical resources as the construction of Wang et al. [1] on realistic device parameters. Recent advances in effective-Hamiltonian engineering [12] provide a path: The second-order Magnus expansion of bichromatic spin-dependent forces produces the $\sigma_z \cdot a^\dagger a$ structure required for controlled rotation, where σ_z is the Pauli Z operator and $a^\dagger(a)$ is the creation (annihilation) operator. Combined with HyPulse [2], this lets us cast the Toffoli gate as a concrete pulse-design problem on realistic trapped-ion calibration parameters.

We contribute a synthesized pulse achieving process fidelity $F = 0.999998$ in $100 \mu\text{s}$ as a preliminary result, motivating further work on noise robustness, hardware-aware bandwidth, and extension to higher-order multiqubit gates.

II. METHOD

A. System Hamiltonian

Wang et al. [1] introduced a general framework for multi-qubit gates mediated by a shared harmonic bus, based on the time-dependent Hamiltonian

$$H(t) = v(t) \hat{A} x + w(t) \hat{B} p + r(t) \hat{C} n, \quad (1)$$

where $\hat{A}, \hat{B}, \hat{C}$ are commuting internal-state operators, x, p, n are the bus position, momentum, and number operators, and v, w, r are arbitrary time-dependent coefficients. They showed that this construction is sufficient to realize multi-qubit gates such as Toffoli and C^m -NOT, and to implement the Grover search algorithm directly.

For the 3-qubit Toffoli, Wang et al. [1] proposed a time-independent Hamiltonian of the form

$$H = \Omega \left[\frac{\sigma_z^{(1)} + \sigma_z^{(2)} + 1}{4\sqrt{K}} x - \sigma_x^{(3)} \left(n + \frac{1}{32K} \right) \right], \quad (2)$$

acting for duration $t = K \cdot 2\pi/\Omega$, where K is an integer, and $\sigma^{(j)}$ is applied to the j qubit position. Equation (2) combines a controlled-displacement (CD) on the two control qubits via the bus position x , a controlled-rotation (CR) on the target qubit via the bus number operator n , and a small carrier term on the target. The CR primitive can be realized through the second-order Magnus expansion of bichromatic spin-dependent forces [12].

We map the operator structure of Eq. (2) onto a five-channel control basis using native trapped-ion primitives. The collective CD on the two control ions uses two spin-dependent forces, one in each bus quadrature

$$H_1 = (\sigma_z^{(1)} + \sigma_z^{(2)}) \otimes X, \quad (3)$$

$$H_2 = (\sigma_z^{(1)} + \sigma_z^{(2)}) \otimes P, \quad (4)$$

where $X = (a + a^\dagger)/\sqrt{2}$ and $P = i(a^\dagger - a)/\sqrt{2}$. The CR on the target ion is built from a pair of spin-dependent forces whose second-order Magnus combination yields the $\sigma_z \cdot n$ interaction

$$H_3 = \sigma_x^{(3)} \otimes X, \quad (5)$$

$$H_4 = \sigma_y^{(3)} \otimes P. \quad (6)$$

A carrier drive on the target ion supplies the single-qubit term

$$H_5 = \sigma_x^{(3)} \otimes I_{\text{motion}}. \quad (7)$$

B. Pulse Synthesis

We implement the Toffoli plugin within HyPulse [2] and apply optimal-control pulse design [11] to optimize the five control amplitudes $\Omega_1(t), \dots, \Omega_5(t)$ over $N = 200$ piecewise-constant time slots covering total duration $T = 100 \mu\text{s}$. The optimization minimizes $1 - F_{\text{proc}}(U(T), U_{\text{Toffoli}})$, where F_{proc} is the process fidelity.

III. RESULTS

Using the five-channel control basis of Eq. (7) and the optimization setup described in Section II, we synthesize the Toffoli pulse with HyPulse [2]. The results below are obtained from closed-system simulation. Environmental noise sources such as motional heating, dephasing, and laser amplitude fluctuations are not included.

A. Pulse Waveform

Figure 1 shows the optimized waveforms across the five control channels.

B. Truth Table and Process Fidelity

Figure 2 summarizes the gate action on the 8-dimensional computational subspace. All eight inputs map to their correct Toffoli outputs with $F \geq 0.999998$. Average and worst-case truth-table fidelities are both 0.999998. Process fidelity is $F_{\text{proc}} = 0.999998$.




Fig. 1. Optimized pulse for the single-step Toffoli gate, five-channel waveform over $T = 100 \mu\text{s}$, $N = 200$ time slots. Channels $\Omega_1(t)$ – $\Omega_5(t)$ correspond to the operators H_1 – H_5 in Eq. (7).




Fig. 2. (a) Truth-table overlap matrix for all 8 computational basis inputs. The off-diagonal Toffoli structure $|110\rangle \leftrightarrow |111\rangle$ is correctly resolved. (b) Per-input fidelities; all 8 basis states reach $F = 1.0000$.

C. Process Unitary

Figure 3 shows the real and imaginary parts of the qubit-only reduced unitary. The Toffoli structure appears cleanly in the real part, with vanishing imaginary entries.

D. Phase-Space Trajectories

Figure 4 plots the bus-mode phase-space trajectories for each computational basis input. All eight trajectories return to the motional vacuum at the gate's end, confirming that the




Fig. 3. Real (a) and imaginary (b) parts of the reduced 8×8 unitary obtained by tracing out the motional mode and applying global-phase correction. The Toffoli structure is recovered exactly; residual imaginary entries are at the 10^{-3} level.




Fig. 4. Bus-mode phase-space trajectories ($\langle X \rangle$, $\langle P \rangle$) for each of the 8 computational basis inputs, with color encoding time (dark to light). The black circle marks the initial vacuum state; the red square marks the final state. All eight inputs return to the motional vacuum at gate end (final radius $\leq 1.1 \times 10^{-3}$), confirming the bus mode disentangles from the qubit subspace.

bus mode disentangles from the qubit subspace and that the resulting unitary acts purely on the qubit register.

E. Summary

The synthesized pulse implements the 3-qubit Toffoli with process fidelity $F = 0.999998$ in $T = 100 \mu s$ in closed-system simulation, with all eight computational basis states reaching the same fidelity and the bus mode fully disentangled from the qubit subspace at the gate's end. This places the construction of Wang et al. [1] on a concrete-pulse footing using only native trapped-ion primitives. Our approach differs from existing single-step proposals on the same platform: Rather than the adiabatic-Ising route of Espinoza et al. [9] or the second-sideband squeezing of Katz et al. [10], we operate at the first sideband through geometric-phase accumulation, providing a complementary data point in the multiqubit-gate landscape.

IV. DISCUSSION

Bus disentanglement. Across all eight computational basis inputs, the bus mode returns to motional vacuum at the gate's

end (Fig. 4). This confirms that the qubit-conditioned channels alone are sufficient to close the bus orbit and realize the Toffoli on the qubit subspace, without an explicit unconditional displacement.

Channel utilization. All five control channels in Eq. (7) are essential, i.e., removing any one of them collapses the gate fidelity. The collective CD on the control qubits and the bichromatic SDF pair on the target qubit each provide an independent degree of freedom that the optimizer exploits, and the carrier on the target qubit completes the basis required to map the geometric phase into the Toffoli structure.

Gate composition. The single-step pulse acts within the original qubit register, with no ancilla qubits or auxiliary modes required beyond the shared motional bus already present in trapped-ion hardware. This contrasts with decomposed realizations, where the same Toffoli action requires a sequence of multiple two-qubit and single-qubit gates with intermediate single-qubit phase corrections.

V. CONCLUSION AND FUTURE WORK

As the first step in our broader investigation of native multiqubit gates on trapped ions, we synthesize an optimal-control pulse using a five-channel control basis inspired by the construction of Wang et al. [1] on realistic trapped-ion calibration parameters, achieving process fidelity $F = 0.999998$ in $100 \mu s$ in closed-system simulation. The Toffoli plugin is integrated with HyPulse [2]. The result demonstrates that single-step Toffoli synthesis is feasible within the operator structure of Wang et al. using only native trapped-ion primitives. Our approach is grounded in first-sideband geometric-phase dynamics and is realized through direct optimal-control pulse synthesis, distinct from adiabatic ramping schemes [9] and from second-sideband squeezing-based constructions [10].

Future work follows two directions: open-system simulation including motional heating, dephasing, and laser amplitude noise; and extension to higher-order multiqubit gates (C^n -NOT), as well as generalization with $CCR_j(\theta)$, where $j \in \sigma_x, \sigma_y, \sigma_z$ and θ is a given angle, for direct comparison with adiabatic-Ising [9] and squeezing-based [10] approaches at matched ion counts.

DATA AND CODE AVAILABILITY

The computational code supporting the findings of this work is available from the corresponding author upon reasonable request.

ACKNOWLEDGMENTS

This work was supported in part by National Science Foundation grants OSI-2531350, PHY-2325080 and OMA-2120757. Yuan Liu and Frank Mueller were also supported in part by the U.S. Department of Energy, Office of Science, Advanced Scientific Computing Research, under contract number DE-SC0025384.

REFERENCES

- [1] X. Wang, A. Sørensen, and K. Mølmer, “Multibit gates for quantum computing,” *Physical Review Letters*, vol. 86, no. 17, pp. 3907–3910, 2001.
- [2] M. Hakimi Heris, Y. Liu, and F. Mueller, “HyPulse: A pulse synthesis framework for hybrid qubit-oscillator gates on trapped-ion platform,” *arXiv preprint arXiv:2604.26804*, 2026.
- [3] M. A. Nielsen and I. L. Chuang, *Quantum Computation and Quantum Information*, 10th ed. Cambridge University Press, 2010.
- [4] D. Maslov and G. W. Dueck, “Improved quantum cost for n -bit Toffoli gates,” *Electronics Letters*, vol. 39, no. 25, pp. 1790–1791, 2003.
- [5] V. V. Shende and I. L. Markov, “On the CNOT-cost of TOFFOLI gates,” *Quantum Information & Computation*, vol. 9, no. 5&6, pp. 461–486, 2009.
- [6] G. H. Low and I. L. Chuang, “Optimal Hamiltonian simulation by quantum signal processing,” *Physical Review Letters*, vol. 118, no. 1, p. 010501, 2017.
- [7] A. Gilyén, Y. Su, G. H. Low, and N. Wiebe, “Quantum singular value transformation and beyond: exponential improvements for quantum matrix arithmetics,” in *Proceedings of the 51st Annual ACM SIGACT Symposium on Theory of Computing (STOC)*, 2019, pp. 193–204.
- [8] K. J. Joven, E. R. Das, J. Bierman, A. Majumdar, M. Hakimi Heris, and Y. Liu, “Scalable quantum computational science: A perspective from block-encodings and polynomial transformations,” *APL Computational Physics*, vol. 2, no. 1, p. 010901, 2026.
- [9] J. D. A. Espinoza, K. Groenland, M. Mazzanti, K. Schoutens, and R. Gerritsma, “High-fidelity method for a single-step N -bit Toffoli gate in trapped ions,” *Physical Review A*, vol. 103, no. 5, p. 052437, 2021.
- [10] O. Katz, M. Cetina, and C. Monroe, “Programmable N -body interactions with trapped ions,” *PRX Quantum*, vol. 4, no. 3, p. 030311, 2023.
- [11] N. Khaneja, T. Reiss, C. Kehlet, T. Schulte-Herbrüggen, and S. J. Glaser, “Optimal control of coupled spin dynamics: design of NMR pulse sequences by gradient ascent algorithms,” *Journal of Magnetic Resonance*, vol. 172, no. 2, pp. 296–305, 2005.
- [12] R. T. Sutherland and R. Srinivas, “Universal hybrid quantum computing in trapped ions,” *Physical Review A*, vol. 104, no. 3, p. 032609, 2021.