

Date	
Manufacturer	FOX ESS
Trade mark	FOX ESS
Model (chargePointModel)	A022KS-T2S-B-WOGP
Manufacturer Vendor (chargePointVendor)	
Firmware version	1.01
Current (AC/DC)	AC
Internet connection for the test (and possibilities)	ETHERNET
Encryption (https/wss) : yes : precise / no : when is it planned ?	OUI
Ocpp version	1.6J
ChargeBox ID	TESTFOXSIMPLE
Classic Internal Port	
Specific URL (yes : precise / no)	YES
YES55 tester	FAHMI
Manufacturer tester	LOAN / FAHMI

works as expected	OK
works with non-blocking issue	OK+nb
not validated, blocking issue	NOK
could not be tested	No test
non applicable	n/a

Describe the test setup	
Web interface	OUI(FOXSWITCH)
Mobile application	
Electric connection	
Insert DHCP info	
Insert IP info	
Insert CBID info	
Insert URL info	
APN if necessary	

1- Start station				Description		Result
YES55	Mandatory	Charger				
A1	BootNotification	Check the receipt of the BootNotificationRequest and sending of the BootNotificationResponse. Note the presence of additional fields (in addition to Model, SerialNumber, Vendor & FirmwareVersion) & their uses.	yes	yes	Request Message [2,"4ee26ec3-593e-0a87-1170-4ee315b46d1c", BootNotification",{"chargePointVendor":"EV Charger", chargePointModel":"A022KS1","firmwareVersion": 0.43.1.01.0.40","chargePointSerialNumber": 60ALE73054XQ005"}] JSON Format { "chargePointVendor": "EV Charger", "chargePointModel": "A022KS1", "firmwareVersion": "0.43.1.01.0.40", "chargePointSerialNumber": "60ALE73054XQ005" } Response Result [3,"4ee26ec3-593e-0a87-1170-4ee315b46d1c", "currentTime":"2025-10-30T08:47:00.268Z","interval": 1800,"status":"Accepted"] JSON Format { "currentTime": "2025-10-30T08:47:00.268Z", "interval": 1800, "status": "Accepted" }]	OK
A2	Heartbeat	is there some heartbeat ? If yes, can we change the period ?	yes	yes	Request Message [2,"1983818381662261249","TriggerMessage", "requestedMessage":"Heartbeat"] JSON Format { "requestedMessage": "Heartbeat" } Response Result [3,"1983818381662261249",{"status":"Accepted"}] JSON Format { "status": "Accepted" } et : Request Message [2,"1983819283598041090","ChangeConfiguration",{"key": HeartbeatInterval",value":"9"}] JSON Format { "key": "HeartbeatInterval", "value": "9" } Response Result [3,"1983819283598041090",{"status":"Accepted"}] JSON Format { "status": "Accepted" }	OK
A3	Ping websocket	Is websocket ping supported? If so, at what interval? Test sending and receiving.	yes	yes	Request Message [2,"2006024810647613442","ChangeConfiguration",{"key": WebSocketPingInterval",value":"8"}] JSON Format { "key": "WebSocketPingInterval", "value": "8" } Response Result [3,"2006024810647613442",{"status":"Accepted"}] JSON Format { "status": "Accepted" }	OK
A4	StatusNotification	Check the receipt of the StatusNotificationRequest and sending of the StatusNotificationResponse. Check the presence or not of connectorID 0. If present, what is its use? Ask if they are sent systematically after reboot, or only if the Status has changed.	yes	yes		OK
A5	ChargeBox ID	Describe the naming / renaming	yes	yes	mobile app	OK

2- Charge with RFID tag						
B1	Reading RFID tag and which format is supported	What standards are supported (mifare / desfire)?	yes	yes		OK
B2	Authorize	Check receipt of the AuthorizeRequest and sending of the AuthorizeResponse. Describe indication (visual / audible) given to the user. Give the duration of the Timeout in factory configuration.	yes	yes	Request Message [2,"68d9900-0f13-e1c8-848f-701117024ee2","Authorize", {"idTag":"E672FD13"}] JSON Format { "idTag": "E672FD13" } Response Result [3,"68d9900-0f13-e1c8-848f-701117024ee2",{"idTagInfo": {"parentidTag":"1959977548254556162","status": Accepted"}] JSON Format { "idTagInfo": { "parentidTag": "1959977548254556162", "status": "Accepted" } }	OK
B3	StartTransaction	Check the reception of the StartTransactionRequest and sending of the StartTransactionResponse. MeterStart value: cumulative / 0?	yes	yes	equest Message [2,"a5a35574-c34e-442d-b5e5-2523d69a77a1", StartTransaction",{"connectorid":1,"idTag":"E672FD13", meterStart":0,"timestamp":"2026-02-09T09:30:47Z"}] JSON Format { "connectorid": 1, "idTag": "E672FD13", "meterStart": 0, "timestamp": "2026-02-09T09:30:47Z" } Response Result [3,"a5a35574-c34e-442d-b5e5-2523d69a77a1",{"idTagInfo": {"parentidTag":"1959977548254556162","status": Accepted"},"transactionid":2006973981}] JSON Format { "idTagInfo": { "parentidTag": "1959977548254556162", "status": "Accepted" }, "transactionid": 2006973981 }	OK

B4	MeterValues	Check the reception of the MeterValuesRequest and sending of the MeterValuesResponse. Describe whether the meter starts at 0 Wh or not. Indicate when the first MeterValues is sent. Describe what the MeterValueSampleInterval is and specify the values sent in factory configuration (MeterValuesSampleData) + those which must necessarily be kept.	yes	yes	Request Message [2,"0001a899-0b17-48f8-879e-e9000001a898", MeterValues,{"connectorId":1,"transactionId":2006973862, meterValue":{"timestamp":"2026-02-09T09:19:58Z", sampledValue":{"value":"0","context":"Sample.Periodic", measurand":"Energy.Active.Import.Register","unit":"Wh"}, value:"0.00","context":"Sample.Periodic","measurand": Power.Active.Import,"unit":"W"}}]]] JSON Format { "connectorId": 1, "transactionId": 2006973862, "meterValue": { "timestamp": "2026-02-09T09:19:58Z", "samplingValue": { "value": "0", "context": "Sample.Periodic", "measurand": "Energy.Active.Import.Register", "unit": "Wh" } { "value": "0.00", "context": "Sample.Periodic", "measurand": "Power.Active.Import", "unit": "W" } } }	OK
B5	StopTransaction	Check the reception of the StopTransactionRequest and sending of the StopTransactionResponse. Check that the TransactionID is correct (see StartTransactionResponse)	yes	yes	Request Message [2,"bca4fd0b-d5cd-43b5-40cd-4c948dfbbd4c", StopTransaction,{"idTag":"E672FD13","meterStop":0, timestamp:"2026-02-09T09:31:05Z","transactionId": 2006973981,"reason":"Local"}] JSON Format { "idTag": "E672FD13", "meterStop": 0, "timestamp": "2026-02-09T09:31:05Z", "transactionId": 2006973981, "reason": "Local" } Response Result [3,"bca4fd0b-d5cd-43b5-40cd-4c948dfbbd4c",{"idTagInfo": {"parentIdTag":"1959977548254556162","status": Accepted}}] JSON Format { "idTagInfo": { "parentIdTag": "1959977548254556162", "status": "Accepted" } }	OK
B6	Authorize denied	Check receipt of the AuthorizeRequest and sending of the AuthorizeResponse Blocked and absence of StartTransactionRequest. Describe indication (visual / audible) given to the user.	yes	yes	Request Message [2,"3dc0c15b4-c74a-dc84-deb4-3b708c5574ac","Authorize", {"idTag":"04BA2EF22E2090"}] JSON Format { "idTag": "04BA2EF22E2090" } Response Result [3,"3dc0c15b4-c74a-dc84-deb4-3b708c5574ac",{"idTagInfo": {"status":"Invalid"}}] JSON Format { "idTagInfo": { "status": "Invalid" } }	OK

C1	RemoteStartTransaction	Check receipt of RemoteStartTransactionRequest and sending of RemoteStartTransactionResponse, check receipt of StartTransactionRequest and send of StartTransactionResponse. Describe when a RemoteStartTransactionRequest can be Rejected. Expected behavior if the targeted connectorId is "0"?	yes	yes	Request Message [2,"1770629854234","RemoteStartTransaction", {"connectorId":1,"idTag":"177062985392946"}] JSON Format { "connectorId": 1, "idTag": "177062985392946" } Response Result [3,"1770629854234",{"status":"Accepted"}] JSON Format { "status": "Accepted" }	OK
C2	RemoteStopTransaction via Charge	Check the reception of the RemoteStopTransactionRequest and sending of the RemoteStopTransactionResponse, check the reception of the RemoteStartTransactionRequest and sending of the StopTransactionResponse. Describe in which case (s) a RemoteStopTransaction can be Rejected.	yes	yes	Request Message [2,"1770629970951","RemoteStopTransaction", {"transactionId":2006974038}] JSON Format { "transactionId": 2006974038 } Response Result [3,"1770629970951",{"status":"Accepted"}] JSON Format { "status": "Accepted" }	OK
C3	UnlockConnector via Charge	Check receipt of the UnlockConnectorRequest and sending of the UnlockConnectorResponse, and describe the expected behavior.	yes	yes	Request Message [2,"2020796438868570113","UnlockConnector", {"connectorId":1}] JSON Format { "connectorId": 1 } Response Result [3,"2020796438868570113",{"status":"Unlocked"}] JSON Format { "status": "Unlocked" }	OK

4- Technical remote actions						
D1	ResetSoft	Ask if implemented on the terminal side and test.	yes			OK
D2	ResetHard	Check the reception of the ResetRequest and sending of the ResetResponse, check the reception of the BootNotificationRequest and sending of the BootNotificationResponse. Specify whether the action unlocks the sockets.	yes	yes	Request Message [2,"1770630739369","Reset",{"type":"Hard"}] JSON Format { "type": "Hard" } Response Result [3,"1770630739369",{"status":"Accepted"}] JSON Format { "status": "Accepted" }	OK
D3	ClearCache	Verify receipt of the ClearCacheRequest and sending of the ClearCacheResponse, and describe the expected behavior. Indicate if the Cache is used, and how it is configured in factory configuration.	yes	yes	Request Message [2,"2020798639167164418","ClearCache",{}] JSON Format { "Response Result" }	OK

D4	ChangeConfiguration "MeterValueSampleInterval"	Check that the ChangeConfigurationResponse has been received, and that it is accepted. Specify whether to restart for the change to take effect. Check that the change has been taken into account in the current session (or start a new one).	yes	yes			OK
D5	GetDiagnostics	Ask if implemented on the terminal side + ask for supported protocols (SFTP / FTPS / HTTP / HTTPS /?) And describe what we are receiving.	yes	yes			OK
D6	UpdateFirmware	Ask if implemented on the terminal side + ask for supported protocols (SFTP / FTPS / HTTP / HTTPS /?) And describe what can be sent.	yes				OK

E1	Plug&Charge	Function available? With OCPP active? Yes: how to activate it? Test + description of the behavior	yes			Request Message [2,"2020803281561739266","ChangeConfiguration",{"key":"Cst_FreeVendActive","value":"true"}] JSON Format { "key": "Cst_FreeVendActive", "value": "true" } Response Result [3,"2020803281561739266",{"status":"Accepted"}] JSON Format { "status": "Accepted" }	OK
E2	Emergency Stop	Check the existence of an emergency stop button or equivalent system. Ask how we get back to the initial state.	yes				n/a
E3	Booking on station side	Ask if implemented on the charger side	yes				OK
E4	Power management on station or accessory side	Ask if implemented on the charger side. Request the expected behavior (charger side AND OCPP side). Check that it is standard. Ask if there are additional accessories (eg. LMS).	yes	yes			OK
E5	Contactless payment card reader	Check receipt of the DataTransferRequest and sending of the DataTransferResponse, check that the training of the DataTransfer is understood by the backend (payment works)	yes				n/a
E6	DataTransfer list	Give details of the existing DataTransfer with their function, confirmation of the VendorID and the content of the messageID.	yes				n/a
E7	Change URL supported	Check the receipt of the changeURL.	yes	yes		Request Message [2,"2020806342631411713","ChangeConfiguration",{"key":"Cst_BackendUrl","value":"wss://load-motion.com/OCPP16/66f527b0dc59adbee7f65f0166f53645dc59adbee7f66c00"}] JSON Format { "key": "Cst_BackendUrl", "value": "wss://load-motion.com/OCPP16/66f527b0dc59adbee7f65f0166f53645dc59adbee7f66c00" } Response Result [3,"2020806342631411713",{"status":"RebootRequired"}] JSON Format { "status": "RebootRequired" }	OK
E8	Change Chargebox ID supported	Check the receipt of the CBID.	yes	yes		Request Message [2,"2020808473702477825","ChangeConfiguration",{"key":"Cst_ChargeBoxId","value":"foxsimple3"}] JSON Format { "key": "Cst_ChargeBoxId", "value": "foxsimple3" } Response Result [3,"2020808473702477825",{"status":"RebootRequired"}] JSON Format { "status": "RebootRequired" }	OK
E9	Other accessory	/					n/a

6- Limit behaviors							
F1	Permanent authorize	Verify receipt of the AuthorizeRequest and send the AuthorizeResponse with a badge that has already been accepted. Ask in which case (s) an AuthorizeRequest is not sent, and what is the behavior in factory configuration.	yes	yes			OK
F2	Ongoing charge : communication loss, charge continues	Describe the behavior when resuming communication including reception of messages (exploit logs, in particular MeterValues)	yes	yes			OK
F3	Ongoing charge : communication loss, charge stopped, during the communication loss	Describe the behavior when resuming communication including reception of messages (exploit logs, in particular MeterValues & StopTransaction)	yes	yes			OK
F4	Communication loss : stop with the same tag used to start	Describe whether the load is stopped or not, then describe the behavior on return to communication	yes	yes			OK
F5	Station offline, swipe a known tag	Describe whether the load is started or not, then describe the behavior on return to communication including the reception of messages (log exploit) Specify whether there are different possible management options for the offline mode: all accepted / refuse all / Cache accepted, ...	yes	yes			OK
F6	Station offline, swipe an unknown tag	Describe whether the load is started or not, then describe the behavior on return to communication including the reception of messages (log exploit)	yes	yes			OK
F7	Ongoing charge, send a remote order to restart the station	Describe whether the load is stopped or not, then describe the behavior when it is back in communication. If the charge resumes, specify if it is on the same session, or a new one. In which case, specify the returned IDTag.	yes	yes			OK
F8	Ongoing charge, power failure to restart the station	Describe whether the load is stopped or not, then describe the behavior when it is back in communication. If the charge resumes, specify if it is on the same session, or a new one. In which case, specify the returned IDTag.	yes	yes			OK
F9	No door : plug and unplug E/F connector cable during charge	Describe whether the load is started and stopped or not	yes				n/a

7- Documentation							
G1	Technical documentation	Request existing technical documentation.	n/a				
G2	Commercial documentation	Request existing sales documentation.	n/a				
G3	Preventive maintenance	Request documentation relating to preventive maintenance.	n/a				
G4	Vendor error codes list	Request list.	n/a				
G5	ChangeConfiguration list	Request list.	n/a				
G6	Describe the process for the activation	Describe the configuration of the charger for activation.	n/a				
G7	Setup interface	Describe the type and access: remote (web), connected to the terminal: ...	n/a				
G8	Possible internet connections	Describe the possible connections.	n/a				
G9	ConnectorID / plug	Describe the numbering of the connectors of the test terminal by charging point, if the cables are attached, but also if there is other equipment with the same Firmware. In this case, describe the connectors / PDC in the same way.	n/a				
G10	Validation	Indicate if the compatibility test is 100% validated, or if there are elements to be confirmed. In which case, specify what, and YES55 / manufacturer side.	n/a				
Annotation			Pas de mid certifié encours de validation (Labo certifie le MID)				

Manufacturer signature	YES55 signature
------------------------	-----------------