Michael Huang
EN.625.740.81
Homework 9

1.

Show a perceptron that calculates $\bar{x}_1 x_2 \bar{x}_3$.

This is essentially NOT x_1 AND x_2 AND NOT x_3. We aim to have a target end state where we only get a positive value when x_2 is positive. An easy way to guarantee this is to have a positive coefficent for x_2 and negative for the other two. Summing this gives us something like $-x_1 + x_2 - x_3$ which we can easily see will be equal to or below 0 when any of x_1 or x_3 are true / 1. The only remaining cases are now when both are false / 0. When x_2 is also false or 0 in this case, then we indeed get 1 when x_2 is true / 1, and 0 otherwise. So in this case, with $s(a)$ being the function from the text where it gives 1 if $a \geq 0$, we therefore need to adjust this accordingly with to ensure that these are all below 0 in all other cases, so we can set our bias to -0.5 to ensure all outputs are below 0 except for the target case. Therefore:

$$\boxed{y = s(-x_1 + x_2 - x_3 - 0.5)}$$

2.

Show a perceptron that calculates $\bar{x}_2 x_3$.

This is essentially NOT x_2 AND x_3. We aim to have a target end state of 1 only when x_2 is false / 0 and x_3 is true / 1. Looking case by case, we can approach this similarly to the previous problem, with penalizing x_2 being true / 1 by setting it to a negative coefficient, and the opposite for x_3. This is $-x_2 + x_3$. The only case we need to account for now is that when the two are not the same value. When x_2 is 0 and x_3 is 1, we get 1, which is good, but when x_2 is 1 and x_3 is 0, we aim to get something below 0, but instead get 0. We therefore also add a bias of -0.5 here to ensure that our target case is above 0 and all other cases are below 0. Therefore:

$$\boxed{y = s(-x_2 + x_3 - 0.5)}$$

3.

Show a neural network that calculates $\bar{x}_1\bar{x}_2\bar{x}_3 + x_1x_2x_3$.

We basically aim to create a multi-layer perceptron that basically takes the ANDs of all NOT of the x values and all ANDs of all of the x values, and then takes the OR of these two values and gives value greater than 0 according to if either of these are 1. We can kind of reverse-engineer this – the only case in which OR gives a nonnegative value is if the hidden layers z_1 and z_2 both are 0, and above 0 otherwise. So we need to keep both coefficients positive. This gives us $z_1 + z_2$, which we see will give us 0 if both are 0. We can add the corresponding bias of -0.5 accordingly which also ensures that if either hidden layer value is 1, it will still be at least 0.5. Now looking at each layer:

$\bar{x_1}\bar{x_2}\bar{x_3}$, so we only get a value of above 0 when all are 0s, and negative otherwise. The easiest way to set this up is to set all coefficients to negative, which covers any of the values being 1 giving us a negative value, which ultimately outputs 0. Finally, handling all the 0s, we need to make sure this is above 0, so we add 0.5 as the bias. So we have

$$\boxed{z_1 = s(-x_1 - x_2 - x_3 + 0.5)}$$

$x_1x_2x_3$, so we only get a value above 0 when we have all 1s. An easier way to look at this is that if we have 2 or fewer trues, then we should have a negative result. So we can see that the bias should be -2.5, since this would guarantee a positive result for all 3 trues / 1s but negative for any other, giving us

$$\boxed{z_2 = s(x_1 + x_2 + x_3 - 2.5)}$$

Finally, we combine this accordingly:

$$\boxed{y = s(z_1 + z_2 - 0.5)}$$

4.

Show a neural network that calculates $\bar{p}_1 + x_1x_2x_3$.

p_1 represents the parity function of just x_1. The parity of n bits is 1 if an odd number of the inputs are 1, and 0 otherwise, so $\bar{p}_1$ simplifies directly to $\bar{x}_1$. This simplifies the problem down to a multi-layer perceptron that takes the NOT of x_1 and the AND of all of the x values, and then takes the OR of these two values. This OR is the same as the previous problem, so we have the same interaction with the the hidden layers z_1 and z_2; again this gives us $z_1 + z_2$, which we see will give us 0 if both are 0; again we add the corresponding bias of -0.5. Now looking at each layer:

$\bar{p}_1$ is just $\bar{x}_1$, so we only get a value of above 0 when x_1 is 0, and negative otherwise. The easiest way to set this up by setting the x_1 coefficient to a negative coefficient, which covers x_1 being 1 which gives us a negative value. Finally, to handle the 0, we need to make sure this is above 0, so we add 0.5 as the bias, which ensures that the $x_1 = 1$ case is still negative. So we have

$$\boxed{z_1 = s(-x_1 + 0.5)}$$

$x_1x_2x_3$, the same as we previously calculated:

$$\boxed{z_2 = s(x_1 + x_2 + x_3 - 2.5)}$$

Finally, we combine this accordingly:

$$\boxed{y = s(z_1 + z_2 - 0.5)}$$

5.

Show a neural network that calculates $p_2(x_1, x_2) \cdot p_3(x_1, x_2, x_3)$.

We can start by trying to simplify the parity functions. The total product of the

two parity functions must be 1, so they both must come out to 1. p_2 requires exactly one of x_1 or x_2 to be 1 for this to be 1. p_3 requires an odd number of total 1s across all three inputs (so either 1 or 3 1s). Taking this into account with the inputs, if exactly one of x_1 or x_2 is true / 1, then x_3 must be 0 to keep the total count of 1s odd (otherwise we'll have 2 1s). Therefore, the only two input states that satisfy both conditions simultaneously are $(0, 1, 0)$ and $(1, 0, 0)$. So we can reinterpret this expression as an OR statement now, since either of these will give us the target value of 1. So we can express this as $\bar{x}_1 x_2 \bar{x}_3 + x_1 \bar{x}_2 \bar{x}_3$.

As we did previously, we'll create a multi-layer perceptron that calculates the hidden layers; we do the same reverse-engineering as before, with the only case in which OR gives a nonnegative value is if the hidden layers z_1 and z_2 both are 0, and above 0 otherwise. We again keep both coefficients positive, giving us $z_1 + z_2$, which gives us 0 if both are 0; we can add the corresponding bias of -0.5 accordingly which also ensures that if either hidden layer value is 1, it will still be at least 0.5. Now looking at each layer:

$\bar{x}_1 x_2 \bar{x}_3$. We only get a value above 0 when x_2 is 1 and the others are 0, and negative otherwise. We do the same thing we did in Problem 1: we set the x_2 coefficient to positive (+1), and the x_1 and x_3 coefficients to negative (-1). Again, we want a positive result only for this exact combination, so we add -0.5 as the bias to ensure this is the case. So we have

$$\boxed{z_1 = s(-x_1 + x_2 - x_3 - 0.5)}$$

$x_1 \bar{x}_2 \bar{x}_3$. This is similar to the above, but we only get a value above 0 when x_1 is 1 and the others are 0. Similarly, we simply set the x_1 coefficient to positive (+1), and the x_2 and x_3 coefficients to negative (-1). Applying the same logic for the bias, we add -0.5, giving us

$$\boxed{z_2 = s(x_1 - x_2 - x_3 - 0.5)}$$

Finally, we combine this accordingly:

$$\boxed{y = s(z_1 + z_2 - 0.5)}$$

6.

Generate two-dimensional samples for each of two Gaussians, $p(\mathbf{x}|\omega_i) \sim N(\boldsymbol{\mu}_i, \Sigma_i)$ with

$$\boldsymbol{\mu}_1 = \begin{pmatrix} 1 \\ -1 \end{pmatrix}, \boldsymbol{\mu}_2 = \begin{pmatrix} 0 \\ 0 \end{pmatrix}, \Sigma_1 = \begin{pmatrix} 0.2 & 0 \\ 0 & 0.2 \end{pmatrix} = \Sigma_2.$$

Produce 100 samples from each distribution, but to guarantee linear separability, produce a replacement for a Class 1 vector whenever $x_1 - x_2 < 1$ and produce a replacement for a Class 2 vector whenever $x_1 - x_2 > 1$.

Use these vectors to design a linear classifier using the perceptron algorithm. After convergence, draw the decision boundary.