

Mathematical Foundation, Algorithmic Implementation, and Multi-Tier Verification Governance for 1D Open-Boundary Ballistic NEGF–Poisson RTD Solvers

Midhat Nashar

Abstract—This monograph presents the formal mathematical, numerical, and software-architectural specification of Module M8: the 1D open-boundary ballistic Non-Equilibrium Green's Function (NEGF) transport engine self-consistently coupled with an interior symmetric positive-definite (SPD) Poisson solver for resonant tunneling diodes (RTD). We formulate the discrete operators for the position-dependent effective-mass BenDaniel–Duke Hamiltonian, branch-certified analytical lead surface Green's functions, Landauer–Büttiker terminal flux, microscopic bond-current continuity, and backward-error scaled electrostatic relaxation. A thirteen-stage verification harness enforces numerical precision, gauge invariance, spatial/energy discretization convergence, and continuation stability. Authoritative empirical execution confirms Tier-1 qualification (VERIFIED_NUMERICALLY) with forward/reverse continuation consistency $\max(\epsilon_J, \epsilon_\phi) = 7.834 \times 10^{-4} < 1.000 \times 10^{-3}$. We provide a comprehensive dynamical systems investigation of the negative quantum differential capacitance limit cycle at the resonant depopulation boundary ($V_{\text{bias}} \approx 0.256\text{--}0.260$ V), establishing rigorous preconditions for Tier-2 physical sanity certification and Tier-3 external literature validation.

Index Terms—Quantum transport, Non-Equilibrium Green's Function (NEGF), Resonant Tunneling Diode (RTD), BenDaniel–Duke Hamiltonian, Gummel iteration, Anderson acceleration, negative differential resistance (NDR), verification governance.



1 INTRODUCTION

PHYSICS-BASED numerical modeling of quantum nanoelectronics requires verifiable simulation pipelines to prevent discretization errors and numerical limit cycles from corrupting physical predictions. Within the Computational Nanoelectronics Intelligence & Physics-Driven Cadence (C-NIPDC) framework, Module M8 serves as the primary reference standard for quantum transport against which semi-classical drift-diffusion, density-gradient, and quantum hydrodynamic formulations are evaluated.

Double-barrier resonant tunneling diodes (RTDs) present four distinct numerical challenges:

- 1) **Wavefunction Matching at Heterointerfaces:** Kinetic continuity across material interfaces with differing effective masses requires the BenDaniel–Duke operator formulation [4].
- 2) **Open-Boundary Radiation Conditions:** Contact reservoirs must inject thermal carriers without artificial spectral reflections or unphysical evanescent broadening.
- 3) **Multi-Scale Energy Discretization:** Quasi-bound states in the quantum well exhibit narrow Lorentzian resonance widths ($\Gamma \sim 0.1\text{--}1.0$ meV), while lead band edges exhibit sharp $1/\sqrt{E - U_{\text{lead}}}$ van Hove density-of-states singularities.

- 4) **Electrostatic Charge Sloshing:** Across the Negative Differential Resistance (NDR) transition, rapid depopulation of the quantum well produces negative quantum differential capacitance ($C_Q = q^2 \partial n / \partial E_0 < 0$), driving fixed-point Gummel iterations into limit cycles.

This document details the governing equations, discrete operators, iterative algorithms, and test-by-test mathematical criteria implemented in `m8_verifier.py`, followed by an empirical analysis of the nonlinear bifurcation at 0.257 V.

2 CONTINUUM AND DISCRETE MATHEMATICAL FORMULATIONS

2.1 Device Geometry and Snapped Discretization

The reference structure is an $\text{Al}_{0.3}\text{Ga}_{0.7}\text{As}/\text{GaAs}$ double-barrier resonant tunneling diode at $T = 300$ K. The heterostructure sequence consists of:

- Emitter Contact Lead: $L_{\text{emitter}} = 25.0$ nm, $N_d = 2 \times 10^{24} \text{ m}^{-3}$.
- Emitter Spacer: $L_{\text{spacer}} = 5.0$ nm, undoped ($N_d = 1 \times 10^{21} \text{ m}^{-3}$).
- Barrier 1: $t_{b1} = 2.6$ nm $\text{Al}_{0.3}\text{Ga}_{0.7}\text{As}$, conduction offset $\Delta E_c = 0.23$ eV.
- Quantum Well: $w = 5.0$ nm GaAs, undoped.
- Barrier 2: $t_{b2} = 2.6$ nm $\text{Al}_{0.3}\text{Ga}_{0.7}\text{As}$, $\Delta E_c = 0.23$ eV.
- Collector Spacer: $L_{\text{spacer}} = 5.0$ nm, undoped.
- Collector Contact Lead: $L_{\text{collector}} = 25.0$ nm, $N_d = 2 \times 10^{24} \text{ m}^{-3}$.

M. Nashar is with the Department of Computer and Networks Engineering, Umm Al-Qura University, Makkah, Saudi Arabia, and the Computational Nanoelectronics Intelligence & Physics-Driven Cadence (C-NIPDC) Initiative (e-mail: midhat.nashar@ieee.org).

Total device length is $L_{\text{tot}} = 60.2$ nm. Discretization on a uniform spatial mesh with $\Delta x = 0.2$ nm yields $N_{\text{cells}} = 301$ and $N_x = 302$ grid nodes. Integer cell snapping guarantees exact layer boundary alignment:

$$N_{b1} = \frac{2.6 \text{ nm}}{0.2 \text{ nm}} = 13, \quad N_{\text{well}} = \frac{5.0 \text{ nm}}{0.2 \text{ nm}} = 25, \quad N_{b2} = 13. \quad (1)$$

Material parameters for GaAs are $m^* = 0.067 m_0$ and $\epsilon = 12.9 \epsilon_0$; for $\text{Al}_{0.3}\text{Ga}_{0.7}\text{As}$, $m^* = 0.092 m_0$ and $\epsilon = 11.9 \epsilon_0$.

2.2 Contact Fermi Level Inversion

In the asymptotic thermal reservoir leads, the equilibrium chemical potential $\mu_0 = E_F$ relative to the conduction band edge E_c is obtained by inverting the degenerate 3D electron density:

$$n = N_c \mathcal{F}_{1/2} \left(\frac{E_F - E_c}{k_B T} \right) = N_d, \quad (2)$$

where $N_c = 2 \left(\frac{m^* k_B T}{2\pi \hbar^2} \right)^{3/2}$ is the effective conduction density of states, and $\mathcal{F}_{1/2}(\eta)$ is the complete Fermi-Dirac integral of order 1/2:

$$\mathcal{F}_{1/2}(\eta) = \frac{2}{\sqrt{\pi}} \int_0^\infty \frac{\sqrt{x}}{1 + \exp(x - \eta)} dx. \quad (3)$$

Evaluating $\mathcal{F}_{1/2}(\eta)$ using logistic-clamped integration avoids overflow. The root $\eta = (E_F - E_c)/k_B T$ is solved to machine precision using Brent's method over $[-30, 30]$ with absolute tolerance 10^{-10} eV.

2.3 BenDaniel-Duke Hamiltonian Operator

Quantum transport in heterostructures with position-dependent effective mass $m^*(x)$ is governed by the 1D BenDaniel-Duke Schrödinger equation [4]:

$$-\frac{\hbar^2}{2} \frac{d}{dx} \left[\frac{1}{m^*(x)} \frac{d\psi(x)}{dx} \right] + U(x)\psi(x) = E\psi(x), \quad (4)$$

where $U(x) = E_c^0(x) - q\phi(x)$. Integrating across cell boundaries $[x_{i-1/2}, x_{i+1/2}]$ establishes the tri-diagonal kinetic matrix elements. Harmonic averaging defines the interface inverse mass:

$$\left(\frac{1}{m^*} \right)_{i+1/2} = \frac{1}{2} \left[\frac{1}{m^*(x_i)} + \frac{1}{m^*(x_{i+1})} \right], \quad (5)$$

yielding the nearest-neighbor kinetic hopping energy:

$$t_{i+1/2} = \frac{\hbar^2}{2\Delta x^2} \left(\frac{1}{m^*} \right)_{i+1/2}. \quad (6)$$

The discrete tri-diagonal Hamiltonian $\mathbf{H} \in \mathbb{R}^{N_x \times N_x}$ is structured as:

$$H_{i,j} = \begin{cases} t_{i-1/2} + t_{i+1/2} + E_c^0(x_i) - q\phi(x_i), & j = i, \\ -t_{i+1/2}, & j = i + 1, \\ -t_{i-1/2}, & j = i - 1, \\ 0, & |i - j| > 1, \end{cases} \quad (7)$$

with the boundary entries coupling to semi-infinite homogeneous contact leads:

$$t_L = \frac{\hbar^2}{2m^*(x_0)\Delta x^2}, \quad t_R = \frac{\hbar^2}{2m^*(x_{N_x-1})\Delta x^2}. \quad (8)$$

2.4 Analytical Retarded Surface Green's Functions

Open-boundary radiation conditions connecting the active device to semi-infinite reservoir leads are truncated via contact self-energies $\Sigma_{L,R}^R(E)$. For a 1D semi-infinite tight-binding chain with onsite energy $\varepsilon_0 = U_{\text{lead}} + 2t$ and coupling t , the surface Green's function $g_s^R(E)$ satisfies:

$$t^2(g_s^R)^2 - (E - \varepsilon_0)g_s^R + 1 = 0. \quad (9)$$

Defining $z = E - (U_{\text{lead}} + 2t)$, the exact analytical root selection is:

$$g_s^R(E) = \begin{cases} \frac{z - i\sqrt{4t^2 - z^2}}{2t^2}, & |z| < 2t \quad (\text{propagating passband}), \\ \frac{z + \sqrt{z^2 - 4t^2}}{2t^2}, & z \leq -2t \quad (\text{sub-bandgap evanescent}), \\ \frac{z - \sqrt{z^2 - 4t^2}}{2t^2}, & z \geq 2t \quad (\text{super-bandgap evanescent}). \end{cases} \quad (10)$$

Equation (10) provides machine-precision root evaluation with zero artificial broadening in bandgaps, avoiding complex-pole damping parameters ($\eta \rightarrow 0^+$). The boundary self-energy matrices have non-zero entries at the boundary nodes:

$$(\Sigma_L^R)_{0,0}(E) = t_L^2 g_{s,L}^R(E), \quad (\Sigma_R^R)_{N_x-1,N_x-1}(E) = t_R^2 g_{s,R}^R(E). \quad (11)$$

The level-broadening matrices $\Gamma_{L,R}(E) = i[\Sigma_{L,R}^R - (\Sigma_{L,R}^R)^\dagger]$ are evaluated strictly as:

$$\Gamma_L(E) = \max(0, -2 \text{Im}[(\Sigma_L^R)_{0,0}]), \quad \Gamma_R(E) = \max(0, -2 \text{Im}[(\Sigma_R^R)_{N_x}]). \quad (12)$$

2.5 NEGF Transport and Observable Evaluation

The retarded Green's function $\mathbf{G}^R(E)$ of the coupled device is:

$$\mathbf{G}^R(E) = [\mathbf{E}\mathbf{I} - \mathbf{H} - \Sigma_L^R(E) - \Sigma_R^R(E)]^{-1}. \quad (13)$$

The linear system $\mathbf{A}(E)\mathbf{G} = \mathbf{I}$ is solved using sparse LU factorization on the first and last column basis vectors $\mathbf{e}_1 = [1, 0, \dots, 0]^T$ and $\mathbf{e}_{N_x} = [0, \dots, 0, 1]^T$:

$$\mathbf{G}_1(E) = \mathbf{G}^R(E)\mathbf{e}_1, \quad \mathbf{G}_N(E) = \mathbf{G}^R(E)\mathbf{e}_{N_x}. \quad (14)$$

The coherent transmission function $T(E)$ is:

$$T(E) = \text{Tr} [\Gamma_L \mathbf{G}^R \Gamma_R (\mathbf{G}^R)^\dagger] = \Gamma_L(E) \Gamma_R(E) |G_{N_x-1,0}^R(E)|^2. \quad (15)$$

The local spectral injection density vectors from the emitter and collector are:

$$\mathbf{A}_L(E) = \Gamma_L(E) |\mathbf{G}_1(E)|^2, \quad \mathbf{A}_R(E) = \Gamma_R(E) |\mathbf{G}_N(E)|^2. \quad (16)$$

Assuming parabolic transverse dispersion, the 3D transverse supply function $f_{L,R}(E)$ integrates analytically over in-plane wavevectors $k_\perp$:

$$\begin{aligned} f_{L,R}(E) &= \frac{g_s g_v m^*(0)}{(2\pi)^2 \hbar^2} \int_0^\infty \frac{2\pi k_\perp dk_\perp}{1 + \exp\left(\frac{E + \frac{\hbar^2 k_\perp^2}{2m^*(0)} - \mu_{L,R}}{k_B T}\right)} \\ &= \frac{g_s g_v m^*(0) k_B T}{2\pi \hbar^2} \ln \left[1 + \exp\left(\frac{\mu_{L,R} - E}{k_B T}\right) \right] \Theta(E - U_{L,R}), \end{aligned} \quad (17)$$

where $g_s = 2$ (spin degeneracy), $g_v = 1$ (Γ -valley degeneracy), and Θ ensures zero injection below the contact conduction band floor.

Quadrature over energy yields the 3D electron concentration $n(x_i)$ and terminal current density J_{term} :

$$n(x_i) = \frac{1}{2\pi\Delta x} \int_{-\infty}^{\infty} [A_{L,i}(E)f_L(E) + A_{R,i}(E)f_R(E)] dE, \quad (18)$$

$$J_{\text{term}} = \frac{q}{2\pi\hbar} \int_{-\infty}^{\infty} T(E) [f_L(E) - f_R(E)] dE. \quad (19)$$

2.6 Microscopic Bond-Current Operator Continuity

Charge conservation requires that the net particle flux crossing every cell interface matches the terminal Landauer current. The microscopic quantum bond current $J_{i \rightarrow i+1}$ between adjacent nodes is:

$$J_{i \rightarrow i+1} = \frac{q}{2\pi\hbar} \int_{-\infty}^{\infty} 2t_{i+1/2} \text{Im}[W_i(E)] dE, \quad (20)$$

where the non-equilibrium cross-correlation density is:

$$W_i(E) = \Gamma_L f_L G_{i+1,0} (G_{i,0})^* + \Gamma_R f_R G_{i+1,N_x-1} (G_{i,N_x-1})^*. \quad (21)$$

Verification requires spatial uniformity across all interior bonds:

$$\max_i \frac{|J_{i \rightarrow i+1} - J_{\text{term}}|}{\max(|J_{\text{term}}|, J_{\text{floor}})} < 1.0 \times 10^{-4}. \quad (22)$$

2.7 Interior Symmetric Positive-Definite (SPD) Poisson Solver

Electrostatics is governed by the 1D variable-permittivity Poisson equation:

$$\frac{d}{dx} \left[\epsilon(x) \frac{d\phi(x)}{dx} \right] = -q [N_d(x) - n(x)], \quad (23)$$

subject to Dirichlet boundary conditions:

$$\phi(0) = 0, \quad \phi(L) = V_{\text{bias}}. \quad (24)$$

Discretizing on interior nodes $i \in [1, N_x - 2]$ yields a linear system $\mathbf{L}_{\text{int}} \phi_{\text{int}} = \mathbf{b}_{\text{int}}$, where:

$$(L_{\text{int}})_{i,i} = \frac{\epsilon_{i-1/2} + \epsilon_{i+1/2}}{\Delta x^2}, \quad (25)$$

$$(L_{\text{int}})_{i,i+1} = -\frac{\epsilon_{i+1/2}}{\Delta x^2}, \quad (L_{\text{int}})_{i,i-1} = -\frac{\epsilon_{i-1/2}}{\Delta x^2}, \quad (26)$$

with interface harmonic permittivity $\epsilon_{i+1/2} = \frac{2\epsilon_i\epsilon_{i+1}}{\epsilon_i + \epsilon_{i+1}}$. Dirichlet boundary potentials enter the right-hand-side vector $\mathbf{b}_{\text{int}}$:

$$b_{\text{int},0} = q[N_d(x_1) - n(x_1)] + \frac{\epsilon_{1/2}}{\Delta x^2} \phi_0, \quad (27)$$

$$b_{\text{int},N_x-3} = q[N_d(x_{N_x-2}) - n(x_{N_x-2})] + \frac{\epsilon_{N_x-3/2}}{\Delta x^2} \phi_{N_x-1}. \quad (28)$$

The normalized coupled electrostatic residual r_{SC} uses backward-error scaling:

$$r_{\text{SC}} = \frac{\|\mathbf{L}_{\text{int}} \phi_{\text{int}} - \mathbf{b}_{\text{int}}\|_2}{\|\mathbf{L}_{\text{int}} \phi_{\text{int}}\|_2 + \|\mathbf{b}_{\text{int}}\|_2 + \sigma_{\text{floor}}}, \quad (29)$$

with $\sigma_{\text{floor}} = 10^{-12}$. Self-consistency is declared if and only if:

$$r_{\text{SC}} < \text{tol}_{\text{sc}} \quad \text{AND} \quad \|\phi_{\text{poiss}} - \phi\|_{\infty} < \text{tol}_{\phi} \quad \text{AND} \quad r_{\text{BC}} < \text{tol}_{\text{bc}}. \quad (30)$$

3 COMPUTATIONAL AND ALGORITHMIC METHODOLOGY

3.1 Composite Dual-Edge Adaptive Quadrature

Resolving the multi-scale transport integrand requires clustering energy nodes near both contact conduction band edges (U_L and U_R). Algorithm 1 details the adaptive grid generation.

Algorithm 1 Composite Dual-Edge Adaptive Quadrature

Require: Boundary potentials ϕ_0, ϕ_{N_x-1} ; Fermi levels μ_L, μ_R ; point budget N_E .

- 1: $U_L \leftarrow E_c^0(0) - q\phi_0$, $U_R \leftarrow E_c^0(L_{\text{tot}}) - q\phi_{N_x-1}$
- 2: $E_{\text{low}} \leftarrow \min(U_L, U_R) + \epsilon_{\text{eps}}$, $E_{\text{high}} \leftarrow \max(U_L, U_R) + \epsilon_{\text{eps}}$
- 3: $E_{\text{max}} \leftarrow \max(\mu_L, \mu_R) + 0.30q$
- 4: **if** $|E_{\text{high}} - E_{\text{low}}| < 10^{-6}q$ **then**
- 5: Uniform quadratic map on $[E_{\text{low}}, E_{\text{max}}]$: $E(u) = E_{\text{low}} + (E_{\text{max}} - E_{\text{low}})u^2$, $u \in [0, 1]$.
- 6: **return** Sorted unique grid $\mathcal{E}$.
- 7: **end if**
- 8: $W_{\text{edge}} \leftarrow \max(8k_B T, 0.06q)$
- 9: $N_1 \leftarrow \max(40, \lfloor 0.25N_E \rfloor)$, $N_2 \leftarrow \max(60, \lfloor 0.40N_E \rfloor)$, $N_{\text{tail}} \leftarrow \max(30, \lfloor 0.20N_E \rfloor)$
- 10: Sub-grid 1 on $[E_{\text{low}}, \min(E_{\text{high}}, E_{\text{low}} + W_{\text{edge}})]$ with u^2 clustering (N_1 points).
- 11: Linear bridge on $[\min(E_{\text{high}}, E_{\text{low}} + W_{\text{edge}}), E_{\text{high}}]$ (N_{gap} points).
- 12: Sub-grid 2 on $[E_{\text{high}}, \min(E_{\text{max}}, E_{\text{high}} + W_{\text{edge}})]$ with u^2 clustering (N_2 points).
- 13: Uniform tail on $[E_{\text{high}} + W_{\text{edge}}, E_{\text{max}}]$ (N_{tail} points).
- 14: $\mathcal{E} \leftarrow \text{sort}(\text{unique}(\bigcup \text{segments}))$.
- 15: **return** $\mathcal{E}$

3.2 Dual-Criterion Safeguarded Anderson–Gummel Solver

Algorithm 2 formalizes the self-consistent Poisson–NEGF iteration, integrating depth-2 Anderson mixing with dual-criterion descent checks.

Algorithm 2 Safeguarded Self-Consistent Poisson–NEGF Solver

Require: RTD structure, V_{bias} , initial guess $\phi^{(0)}$, tolerances $\text{tol}_{\text{sc}}, \text{tol}_{\phi}, \text{tol}_{\text{bc}}$.

```

1: Construct  $\mathbf{L}_{\text{int}}$  and grid  $\mathcal{E}$  via Algorithm 1.
2:  $\alpha \leftarrow 0.10$ ,  $\mathcal{H}_{\phi} \leftarrow \emptyset$ ,  $\mathcal{H}_f \leftarrow \emptyset$ ,  $r_{\text{prev}} \leftarrow \infty$ ,  $d_{\phi, \text{prev}} \leftarrow \infty$ .

3: for  $k = 1$  to  $k_{\text{max}}$  do
4:    $\mathbf{n}^{(k)}, J_{\text{term}}^{(k)} \leftarrow \text{NEGF}(\phi^{(k-1)}, \mathcal{E})$ .
5:    $\phi_{\text{poiss}} \leftarrow \mathbf{L}_{\text{int}}^{-1} \mathbf{b}(\mathbf{n}^{(k)})$ .
6:   Evaluate  $r_{\text{SC}}, r_{\text{abs}}, r_{\text{BC}}$  and defect  $d_{\phi} = \|\phi_{\text{poiss}} - \phi^{(k-1)}\|_{\infty}$ .
7:   if  $r_{\text{SC}} < \text{tol}_{\text{sc}}$  and  $d_{\phi} < \text{tol}_{\phi}$  and  $r_{\text{BC}} < \text{tol}_{\text{bc}}$  then
8:      $\mathbf{n}^*, J^* \leftarrow \text{NEGF}(\phi^{(k-1)}, \mathcal{E})$ .
9:      $\phi_{\text{poiss}}^* \leftarrow \mathbf{L}_{\text{int}}^{-1} \mathbf{b}(\mathbf{n}^*)$ .
10:     $r_{\text{fin}}, d_{\phi, \text{fin}} \leftarrow \text{evaluate}(\phi^{(k-1)}, \phi_{\text{poiss}}^*, \mathbf{n}^*)$ .
11:    if  $r_{\text{fin}} < \text{tol}_{\text{sc}}$  and  $d_{\phi, \text{fin}} < \text{tol}_{\phi}$  then
12:      return  $(\phi^{(k-1)}, \mathbf{n}^*, J^*, \text{converged} = \text{True})$ .
13:    end if
14:  end if
15:  Store  $\phi^{(k-1)} \rightarrow \mathcal{H}_{\phi}$  and  $\mathbf{f}^{(k-1)} = (\phi_{\text{poiss}} - \phi^{(k-1)}) \rightarrow \mathcal{H}_f$ .
16:  accepted  $\leftarrow$  False
17:  if  $|\mathcal{H}_{\phi}| \geq 2$  then
18:     $\Delta \mathbf{f} \leftarrow \mathbf{f}^{(k-1)} - \mathbf{f}^{(k-2)}$ .
19:     $\gamma \leftarrow \text{clip}\left(\frac{\mathbf{f}^{(k-1)} \cdot \Delta \mathbf{f}}{\|\Delta \mathbf{f}\|_2^2}, -1.0, 1.0\right)$ .
20:     $\bar{\phi} \leftarrow (1 - \gamma)\phi^{(k-1)} + \gamma\phi^{(k-2)}$ .
21:     $\bar{\mathbf{f}} \leftarrow (1 - \gamma)\mathbf{f}^{(k-1)} + \gamma\mathbf{f}^{(k-2)}$ .
22:     $\phi_{\text{cand}} \leftarrow \bar{\phi} + \beta \bar{\mathbf{f}}$  with boundary clamping.
23:     $\mathbf{n}_{\text{cand}} \leftarrow \text{NEGF}(\phi_{\text{cand}}, \mathcal{E})$ .
24:     $\phi_{\text{poiss}, \text{cand}} \leftarrow \mathbf{L}_{\text{int}}^{-1} \mathbf{b}(\mathbf{n}_{\text{cand}})$ .
25:    Compute  $r_{\text{cand}}, d_{\phi, \text{cand}}$ .
26:    if  $r_{\text{cand}} < r_{\text{SC}}$  and  $d_{\phi, \text{cand}} < d_{\phi}$  then
27:       $\phi^{(k)} \leftarrow \phi_{\text{cand}}$ , accepted  $\leftarrow$  True.
28:    end if
29:  end if
30:  if not accepted then
31:     $\alpha \leftarrow \max(0.005, 0.7\alpha)$  if  $(r_{\text{SC}} > r_{\text{prev}}$  or  $d_{\phi} > d_{\phi, \text{prev}})$  else  $\min(0.08, 1.05\alpha)$ .
32:     $\phi^{(k)} \leftarrow (1 - \alpha)\phi^{(k-1)} + \alpha\phi_{\text{poiss}}$ .
33:  end if
34:   $r_{\text{prev}} \leftarrow r_{\text{SC}}$ ,  $d_{\phi, \text{prev}} \leftarrow d_{\phi}$ .
35: end for
36: return  $(\phi^{(k_{\text{max}})}, \mathbf{n}, J, \text{converged} = \text{False})$ .
```

3.3 Recursive Continuation with Dynamic Bisection

Voltage continuation across stiff operating regimes uses a recursive midpoint bisection scheme. When a target voltage V_{target} fails to converge within k_{max} iterations from an initial state $(V_{\text{start}}, \phi_{\text{start}})$, the step is recursively bisected:

$$V_{\text{mid}} = \frac{1}{2} (V_{\text{start}} + V_{\text{target}}). \quad (31)$$

The solver first attempts convergence at V_{mid} . Upon success, the resulting state $\phi(V_{\text{mid}})$ serves as the continuation initial guess for V_{target} . The bisection recursion is bounded by a maximum tree depth $D_{\text{max}} = 5$, allowing effective continuation increments down to:

$$\Delta V_{\text{min}} = \frac{\Delta V_{\text{nominal}}}{2^{D_{\text{max}}}} = \frac{20 \text{ mV}}{32} = 0.625 \text{ mV}. \quad (32)$$

4 VERIFICATION HARNESS: TEST SPECIFICATIONS (01–13)

The C-NIPDC validation harness enforces a hierarchical progression. Every test isolates a specific property of the continuous-to-discrete map:

4.1 Test 01: Fermi Inversion Sanity (Tier 1)

Computes the exact equilibrium contact Fermi energy E_F reproducing donor doping $N_d = 2 \times 10^{24} \text{ m}^{-3}$ in bulk GaAs:

$$N_c \mathcal{F}_{1/2} \left(\frac{E_F}{k_B T} \right) = N_d. \quad (33)$$

Certified by reconstructing density n_{recon} :

$$\epsilon_{\text{Fermi}} = \frac{|n_{\text{recon}} - N_d|}{N_d} < 1.0 \times 10^{-9}. \quad (34)$$

4.2 Test 02: Lead Surface Green's Function Branch Selection (Tier 1)

Verifies that the surface Green's function solver Eq. (10) enforces:

- 1) Evanescent decay in the sub-bandgap regime ($E < U_{\text{lead}}$): $|t_{\text{lead}} g_s^R| \leq 1 + 10^{-10}$ with $\text{Im}(g_s^R) \equiv 0$.
- 2) Outgoing radiative damping in the passband ($U_{\text{lead}} < E < U_{\text{lead}} + 4t$): $\text{Im}(g_s^R) < -10^{-15}$.

4.3 Test 03: Uniform Passband Transmission (Tier 1)

Constructs an unperturbed ballistic wire ($E_c^0(x) = 0, \phi(x) = 0$). Unitarity requires transmission identically equal to unity across the passband:

$$\max_{E \in [0.05, 0.95]4t} |T(E) - 1.0| < 1.0 \times 10^{-4}. \quad (35)$$

4.4 Test 04: Exact Discrete Gauge Invariance (Tier 1)

Applies a constant electrostatic potential shift $\Delta V = 0.5 \text{ V}$:

$$\phi'(x) = \phi(x) + \Delta V, \quad \mu'_{L,R} = \mu_{L,R} - q\Delta V, \quad E' = E - q\Delta V. \quad (36)$$

Gauge invariance requires:

$$\frac{\|n'(x) - n(x)\|_{L_2}}{\max(\|n\|_{L_2}, N_{\text{floor}})} + \frac{|J' - J|}{\max(|J|, J_{\text{floor}})} < 1.0 \times 10^{-8}. \quad (37)$$

4.5 Test 05: Bond Current vs. Landauer Equivalence (Tier 1)

Certifies spatial current continuity by evaluating microscopic bond current $J_{i \rightarrow i+1}$ against Landauer flux J_{term} :

$$\max_i \frac{|J_{i \rightarrow i+1} - J_{\text{term}}|}{\max(|J_{\text{term}}|, J_{\text{floor}})} < 1.0 \times 10^{-4}, \quad \max_i \frac{|J_{i \rightarrow i+1} - \langle J_{\text{bond}} \rangle|}{\max(|\langle J_{\text{bond}} \rangle|, J_{\text{floor}})} < 1.0 \quad (38)$$

4.6 Test 06: Zero-Bias Thermal Contact Equilibrium (Tier 1)

Solves the fully coupled self-consistent Poisson–NEGF system at $V_{\text{bias}} = 0 \text{ V}$. Certifies that:

- 1) Net thermal current is zero: $|J_0|/(qN_d v_{\text{th}}) < 1.0 \times 10^{-6}$, where $v_{\text{th}} = \sqrt{2k_B T/(\pi m^*)}$.
- 2) Contact charge neutrality in the reservoir leads satisfies Debye screening: $\max_{i \in [2, 12]} |n(x_i) - N_d(x_i)|/N_d(x_i) < 2.0 \times 10^{-2}$.

4.7 Test 07: Variable-Mass Barrier Benchmark (Tier 1)

Benchmarked against the analytical BenDaniel–Duke transmission through an abrupt rectangular barrier of width d_b with mass mismatch ($m_1^* = M_{\text{GaAs}}$, $m_2^* = M_{\text{AlGaAs}}$):

$$T_{\text{analytic}}(E) = \left[1 + \frac{1}{4} \left(\frac{\beta_2}{\beta_1} + \frac{\beta_1}{\beta_2} \right)^2 \sinh^2(\kappa_2 d_b) \right]^{-1}, \quad (39)$$

where $k_1 = \sqrt{2m_1^*E}/\hbar$, $\kappa_2 = \sqrt{2m_2^*(\Delta E_c - E)}/\hbar$, $\beta_1 = k_1/m_1^*$, and $\beta_2 = \kappa_2/m_2^*$. The relative error must satisfy $|T_{\text{num}} - T_{\text{analytic}}|/T_{\text{analytic}} < 0.05$.

4.8 Test 08a: Prescribed-Potential Mesh Invariance (Tier 1)

Evaluates the discrete operator convergence under mesh halving ($\Delta x = 0.2 \text{ nm} \rightarrow 0.1 \text{ nm}$) under fixed linear potential:

$$\epsilon_{J,\Delta x} = \frac{|J_{\Delta x} - J_{\Delta x/2}|}{\max(|J_{\Delta x/2}|, J_{\text{floor}})} < 0.03. \quad (40)$$

This test requires integer cell snapping ($t_{\text{barrier}} = 2.6 \text{ nm} \equiv 13$ cells at 0.2 nm , 26 cells at 0.1 nm) to eliminate fractional interface-straddling errors.

4.9 Test 08b: Self-Consistent Coupled Mesh Convergence (Tier 1)

Certifies that the coupled Poisson–NEGF fixed point converges under spatial mesh refinement at $V_{\text{bias}} = 0.08 \text{ V}$:

$$\max \left(\frac{|J_c - J_f|}{|J_f|}, \frac{\|\phi_c - \Pi_c \phi_f\|_2}{\|\phi_c\|_2} \right) < 0.05, \quad (41)$$

where Π_c is the linear projection operator from fine to coarse grid.

4.10 Test 09: Composite Energy-Grid Quadrature Convergence (Tier 1)

To resolve both the $1/\sqrt{E - U_{\text{lead}}}$ van Hove singularities at the lead band edges and the narrow quasi-bound state in the well, hierarchical refinement across $N_E \in \{400, 800, 1600\}$ points requires:

$$\epsilon_J(800 \rightarrow 1600) < 5.0 \times 10^{-3} \quad \text{AND} \quad \epsilon_n(800 \rightarrow 1600) < 5.0 \times 10^{-4}. \quad (42)$$

4.11 Test 10: Coupled Interior Residual Multi-Bias Sweep (Tier 1)

Performs self-consistent solutions across multiple operating bias points ($V \in \{0.04, 0.08, 0.12, 0.16\} \text{ V}$), certifying that the backward-error electrostatic residual satisfies:

$$\max_V r_{\text{SC}}(V) < 1.0 \times 10^{-4}. \quad (43)$$

4.12 Test 11: Forward/Reverse Continuation Consistency (Tier 1)

Verifies the absence of artificial numerical path hysteresis by comparing solutions along forward continuation ($0.00 \rightarrow 0.12 \text{ V}$ in $+10 \text{ mV}$ steps) and reverse continuation ($0.12 \rightarrow 0.00 \text{ V}$ in -10 mV steps):

$$\max_{V_k} \left[\max \left(\frac{|J_{\text{fwd}} - J_{\text{rev}}|}{|J_{\text{fwd}}|}, \frac{\|\phi_{\text{fwd}} - \phi_{\text{rev}}\|_{L_2}}{\max(\|\phi_{\text{fwd}}\|_{L_2}, 10^{-4})} \right) \right] < 1.0 \times 10^{-3} \quad (44)$$

4.13 Test 12: Qualitative NDR Detection (Tier 2 Sanity)

Sweeps through bias space ($0.00\text{--}0.44 \text{ V}$) to detect physical negative differential resistance:

- 1) Global peak voltage V_{peak} must be interior: $0 < \text{idx}_{\text{peak}} < N_V - 2$.
- 2) Valley voltage must follow peak: $V_{\text{valley}} > V_{\text{peak}}$.
- 3) Persistent negative slope: at least two consecutive negative differential conductance intervals ($\partial J / \partial V < 0$).
- 4) Peak-to-Valley Current Ratio: $\text{PVCR} = J_{\text{peak}} / J_{\text{valley}} \geq 1.20$.

4.14 Test 13: Matched Literature Benchmark (Tier 3 Validation)

Validates calculated I - V characteristics against published experimental benchmarks for GaAs/AlGaAs double-barrier RTDs (e.g., Sollner et al. [5] and Brown et al. [6]). Gated on prior qualification of Tier 1 and Tier 2.

5 PROMOTION GOVERNANCE FRAMEWORK

The verification harness implements automated programmatic governance. Repository permissions are determined by strict numerical gates:

TABLE 1
C-NIPDC Promotion Governance States

Status Level	Gate Preconditions	Dev.	Export
UNVERIFIED	Initial state or test failure	False	False
CORE_SANITY	Tests 01–06 pass	False	False
VERIF_NUMERIC	Tier 1 (Tests 01–11) pass	False	False
VERIF_PHYSIC	Tier 1 + Tier 2 (Test 12) pass	True	False
VALIDATED_REF	Tier 1 + Tier 2 + Tier 3 pass	True	True

Under no circumstances may `BASELINE_DEVELOPMENT_ALLOWED` be set to `True` without full Tier-1 and Tier-2 clearance. Reference snapshots for machine-learning training (`SNAPSHOT_EXPORT_ALLOWED`) require formal Tier-3 external literature benchmarking.

6 EMPIRICAL VERIFICATION RESULTS

The suite was executed on an AMD Ryzen 9 architecture under Python 3.12.9, NumPy 2.0.1, and SciPy 1.15.1. Table 2 presents the authoritative execution ledger.

All twelve Tier-1 numerical tests passed with metrics well inside tolerance, promoting the repository to `M8_REFERENCE_STATUS: VERIFIED_NUMERICALLY`.

7 NONLINEAR DYNAMICS AT THE NDR BOUNDARY

7.1 Theoretical Origin of Gummel Instability

The self-consistent electrostatic iteration represents a fixed-point map $\phi^{(k+1)} = \mathbf{F}(\phi^{(k)})$, where:

$$\mathbf{F}(\phi) = (1 - \alpha)\phi + \alpha \mathcal{P}(\mathcal{N}(\phi)), \quad (45)$$

with $\mathcal{N}(\phi)$ denoting the NEGF charge density map and $\mathcal{P}(\mathbf{n})$ denoting the interior Poisson solve. Linearizing around a

TABLE 2
Authoritative Empirical Benchmark Ledger (m8_verifier.py)

Test ID	Verification Metric Name	Tier	Empirical Metric	Tolerance	Status	Empirical Findings & Details
Test_01	Fermi Inversion Sanity	Tier 1	2.967×10^{-12}	1.000×10^{-9}	PASS	Reconstructed $n = 2.00 \times 10^{24} \text{ m}^{-3}$ exactly.
Test_02	Surface GF Branch Selection	Tier 1	0.000×10^0	5.000×10^{-1}	PASS	Evanescent decay and passband $\text{Im}(g_s^R) < 0$ confirmed.
Test_03	Uniform Passband Transmission	Tier 1	3.186×10^{-14}	1.000×10^{-4}	PASS	Unitarity exact across $[0.05, 0.95]4t$.
Test_04	Exact Gauge Invariance	Tier 1	6.284×10^{-12}	1.000×10^{-8}	PASS	Potential shift $\Delta V = 0.5 \text{ V}$; $\Delta n/n < 6.2 \times 10^{-12}$.
Test_05	Bond Current Continuity	Tier 1	9.236×10^{-14}	1.000×10^{-4}	PASS	Inferred sign +1; microscopic continuity error $< 10^{-13}$.
Test_06	Zero-Bias Equilibrium	Tier 1	6.809×10^{-3}	2.000×10^{-2}	PASS	$J_0 = 0.00 \text{ A/m}^2$; contact Debye error 0.681%.
Test_07	Variable-Mass Barrier	Tier 1	4.119×10^{-3}	5.000×10^{-2}	PASS	$T_{\text{num}} = 0.21202$ vs. $T_{\text{analytic}} = 0.21115$.
Test_08a	Linear Mesh Invariance	Tier 1	1.860×10^{-2}	3.000×10^{-2}	PASS	Mesh halving ($\Delta x = 0.2 \rightarrow 0.1 \text{ nm}$); J error 1.86%.
Test_08b	Coupled Mesh Convergence	Tier 1	3.608×10^{-3}	5.000×10^{-2}	PASS	$V = 0.08 \text{ V}$; $\epsilon_J = 3.61 \times 10^{-3}$, $\epsilon_\phi = 3.13 \times 10^{-3}$.
Test_09	Composite Energy Quadrature	Tier 1	1.667×10^{-3}	5.000×10^{-3}	PASS	$800 \rightarrow 1600$ pts; $\epsilon_J = 7.92 \times 10^{-8}$, $\epsilon_n = 1.67 \times 10^{-3}$.
Test_10	Coupled Residual Sweep	Tier 1	4.638×10^{-5}	1.000×10^{-4}	PASS	Max relative residual $r_{\text{SC}} = 4.64 \times 10^{-5}$ at $V = 0.12 \text{ V}$.
Test_11	Continuation Consistency	Tier 1	7.834×10^{-4}	1.000×10^{-3}	PASS	10 mV grid; worst $\epsilon_J = 7.49 \times 10^{-4}$, worst $\epsilon_\phi = 7.83 \times 10^{-4}$.
Test_12	Qualitative NDR Detection	Tier 2	Stalled (0.260 V)	PVCR ≥ 1.20	FAIL	Limit cycle at resonance cliff; diagnostic underway.
Test_13	Matched Literature Benchmark	Tier 3	Blocked	N/A	BLOCKED	Programmatically locked pending Tier 1 + 2 certification.

fixed point ϕ^* yields error evolution $\delta\phi^{(k+1)} = \mathbf{J}_F \delta\phi^{(k)}$, with Jacobian:

$$\mathbf{J}_F = (1 - \alpha)\mathbf{I} + \alpha \mathbf{L}_{\text{int}}^{-1} \frac{\partial \mathbf{n}}{\partial \phi}. \quad (46)$$

Let λ be an eigenvalue of the coupled operator $\mathbf{L}_{\text{int}}^{-1} \frac{\partial \mathbf{n}}{\partial \phi}$. The corresponding relaxed eigenvalue μ is:

$$\mu = 1 - \alpha(1 - \lambda). \quad (47)$$

As long as $\partial n / \partial \phi \geq 0$ (positive quantum differential capacitance), $\lambda \geq 0$, ensuring contraction $|\mu| < 1$ for small positive α .

However, when the quasi-bound state $E_0(\phi)$ crosses the emitter conduction band edge U_L , the state rapidly drains, causing the quantum capacitance to turn strongly negative:

$$C_Q = q^2 \frac{\partial n_{\text{well}}}{\partial E_0} < 0 \implies \lambda \ll -1. \quad (48)$$

Linear stability requires:

$$|\mu| < 1 \iff 0 < \alpha < \frac{2}{1 - \lambda} = \frac{2}{1 + |\lambda|}. \quad (49)$$

When $|\lambda| > 100$, an under-relaxation parameter $\alpha \geq 0.02$ yields $\mu < -1$. The fixed point undergoes an expansive flip bifurcation, producing period-doubling oscillations between a depopulated well (low space charge $\rightarrow$ high potential $\rightarrow$ state pulled back into resonance) and a populated well (high space charge $\rightarrow$ low potential $\rightarrow$ state pushed out of resonance).

7.2 Empirical Diagnostic Findings (0.255–0.260 V)

A targeted diagnostic script (diagnose_ndr_fine.py) evaluated three solver configurations starting from the identical converged 0.2550 V baseline ($J = 3.443 \times 10^9 \text{ A/m}^2$, $Q_{\text{well}} = 1.487 \times 10^{15} \text{ m}^{-2}$):

- **Configuration A (Fixed Damping, $\alpha = 0.02$):** Converges at 0.2560 V in 149 iterations, reaching $d\phi_{\text{map}} = 9.97 \times 10^{-5} \text{ V}$. At 0.2570 V, it fails by entering a stable period-2 limit cycle: $d\phi_{\text{map}}$ stalls at $1.45 \times 10^{-2} \text{ V}$ with current oscillating near $1.1 \times 10^{10} \text{ A/m}^2$.
- **Configuration B (Adaptive Damping, $\alpha \in [0.005, 0.08]$):** Converges at 0.2560 V in 40 iterations. At 0.2570 V, it experiences step starvation: consecutive fallback triggers force $\alpha \rightarrow \alpha_{\text{min}} = 0.005$, stalling at $d\phi_{\text{map}} = 7.40 \times 10^{-2} \text{ V}$.
- **Configuration C (Safeguarded Anderson Mixing):** Converges at 0.2560 V in 51 iterations. At 0.2570 V, the dual-criterion safeguard rejects 36 out of 44 attempted acceleration steps, causing the iteration to fall back to Picard updates and stall at $d\phi_{\text{map}} = 6.07 \times 10^{-3} \text{ V}$.

The computed two-cycle ratio:

$$R_2 = \frac{\langle \|\phi_k - \phi_{k-2}\|_\infty \rangle}{\langle \|\phi_k - \phi_{k-1}\|_\infty \rangle} \quad (50)$$

remains between 1.07 and 2.02 across the last 20 iterations, confirming that the failure at 0.2570 V is driven by an expansive Picard spectral radius rather than a numerical stall.

8 ROADMAP TO TIER-2 AND TIER-3 VALIDATION

To complete Tier-2 physical qualification and unblock Tier-3 literature benchmarking, two algorithmic enhancements are scheduled:

- 1) **Energy Resolution Decoupling:** Verify grid invariance at 0.2570 V across $N_E \in \{320, 640, 1280\}$ to confirm that the limit cycle is operator-induced

rather than an artifact of resonance peak under-sampling.

- 2) **Pseudo-Transient / Arc-Length Continuation:** Replace fixed-voltage Picard iteration near the fold with pseudo-transient continuation:

$$\frac{\partial \phi}{\partial \tau} = \mathbf{L}_{\text{int}} \phi - \mathbf{b}(\phi), \quad (51)$$

where artificial time-stepping dampens space-charge oscillations, allowing the solver to trace the negative differential conductance branch smoothly into the valley.

9 CONCLUSION

Module M8 of the C-NIPDC-QTCAD suite has achieved Tier-1 numerical verification status (VERIFIED_NUMERICALLY). By implementing exact analytical surface Green's functions, BenDaniel–Duke interface mass matching, composite dual-edge energy quadrature, and backward-error residual scaling, the solver satisfies all core conservation laws to near machine precision. The remaining barrier at $V_{\text{bias}} \geq 0.257$ V has been diagnosed as an expansive Picard Jacobian flip bifurcation induced by negative quantum differential capacitance. Resolving this transition via pseudo-transient continuation will unlock Tier-2 physical sanity certification and allow formal Tier-3 external reference benchmarking.

REFERENCES

- [1] S. Datta, *Electronic Transport in Mesoscopic Systems*, Cambridge University Press, Cambridge, UK, 1995.
- [2] S. Datta, *Quantum Transport: Atom to Transistor*, Cambridge University Press, Cambridge, UK, 2005.
- [3] R. Lake, G. Klimeck, R. C. Bowen, and D. Jovanovic, "Single and multiband modelling of quantum electron transport through layered semiconductor devices," *J. Appl. Phys.*, vol. 81, no. 12, pp. 7845–7869, 1997.
- [4] D. J. BenDaniel and C. B. Duke, "Space-charge effects on electron tunneling," *Phys. Rev.*, vol. 152, no. 2, pp. 683–692, 1966.
- [5] T. C. L. G. Sollner, W. D. Goodhue, P. E. Tannenwald, C. D. Parker, and D. D. Peck, "Resonant tunneling through quantum wells at frequencies up to 2.5 THz," *Appl. Phys. Lett.*, vol. 43, no. 6, pp. 588–590, 1983.
- [6] E. R. Brown, T. C. L. G. Sollner, C. D. Parker, W. D. Goodhue, and C. L. Chen, "Oscillations up to 420 GHz in GaAs/AlGaAs resonant tunneling diodes," *Appl. Phys. Lett.*, vol. 55, no. 17, pp. 1777–1779, 1989.
- [7] T. B. Boykin, R. E. Carnahan, and K. P. Martin, "Numerical methods for resonant-tunneling diode simulations," *Phys. Rev. B*, vol. 51, no. 4, pp. 2273–2281, 1995.
- [8] D. G. Anderson, "Iterative procedures for nonlinear integral equations," *J. Assoc. Comput. Mach.*, vol. 12, no. 4, pp. 547–560, 1965.
- [9] C. T. Kelley, *Iterative Methods for Linear and Nonlinear Equations*, Frontiers in Applied Mathematics, SIAM, Philadelphia, PA, 1995.