

Annex 73A

(normative)

Next page message code field definitions

Change Table 73A–1 as follows:

Table 73A–1—Message code field values

Message code	M 10	M 9	M 8	M 7	M 6	M 5	M 4	M 3	M 2	M 1	M 0	Message code description
1	0	0	0	0	0	0	0	0	0	0	1	Null Message
2	0	0	0	0	0	0	0	0	0	1	0	Extended FEC and Technology Ability Message
5	0	0	0	0	0	0	0	0	1	0	1	Organizationally Unique Identifier Tagged Message
6	0	0	0	0	0	0	0	0	1	1	0	AN device Identifier Tag Code
10	0	0	0	0	0	0	0	1	0	1	0	EEE Technology Message Code. EEE capability is advertised using unformatted message code field in the Message Next Page (see 73A.4).

Insert 73A.1a after 73A.1 as follows:

73A.1a Message code 2—Extended FEC and Technology Ability Message code

The Extended FEC and Technology Ability Message code indicates additional abilities that are not accommodated in the Base Page link codeword (see 73.6.2). The Extended FEC and Technology Ability Message code consists of a message code Next Page (see Figure 73–7) with the message code field set to 000 0000 0010 and the unformatted code field used to indicate additional abilities.

Extended Technology Ability bits EA0:EA25 map to bits D16:D41 (U0:U25), CR host class bits EH0:EH1 bits map to bits D42:D43, and Extended FEC capability bits EF0:EF3 map to bits D44:D47 (U28:31). Reserved fields are sent as zero and ignored on receive.

See Table 73A–1a for more details of the Extended Technology Ability Field bit definitions.

Table 73A–1a—Extended Technology Ability^a

Bit	Technology
EA0	200GBASE-KR1 or 200GBASE-CR1
EA1	400GBASE-KR2 or 400GBASE-CR2
EA2	800GBASE-KR4 or 800GBASE-CR4
EA3	1.6TBASE-KR8 or 1.6TBASE-CR8
EA4 through EA25	Reserved
EH0 and EH1	CR host class for 200 Gb/s per lane PHYs
EF0 through EF3	Reserved for extended FEC ability

^a If the Extended Technology Ability Field is not received or not sent, then its effective value is all zeros.

Table 73A–1b defines how EH0 and EH1 indicate CR host class. When the host class of the PHY is set to a value other than ‘0 0’, the PMD shall be compliant to that host class. When indicating a specific host class, the recommended priority is HL, followed by HN, followed by HH. See 179.9 for host class compliance requirements.

Table 73A–1b—CR host class for 200Gb/s per lane PHYs^{ab}

EH0:EH1	Host class
0 0	Unspecified
0 1	Host-Nominal (HN)
1 0	Host-Low (HL)
1 1	Host-High (HH)

^a Setting EH0:EH1 to values other than “0 0” is optional.

^b Host class is only reported, no negotiation is required.

For message code 2 next pages, ACK2 is set to zero for transmitted next pages and ignored in received next pages.

The 32-bit unformatted code field of Message code 2 Next Page is saved in read only management registers 7.52 to 7.55 (see 45.2.7.13a and 45.2.7.13b).