



Copyright © 2003 by General Electric Company, Inc.

FMI Completion Certification Report

Mail To

GEMS - Americas

GEMS - Europe

G.E. Medical Systems
Attn: FMI Admin. W-523
P.O. Box 414
Milwaukee, WI 53201

GEMS - Europe
FMI Admin. 322
BP34
F78533 Buc Cedex, France

Send to your
Country FMI or Service
Administrator

FMI No.: 25325

FMI Title: 1GB Memory Upgrade for Octane1 Single Processors

Customer Full Name:

Number and Street Address:

City and Country:

Country Code

Site Number

System I.D.

Unit Tracked:

Model Number	Serial Number	Compl. Date DD/MM/YY	FMI Comp. Code	Service Hours	
				Labor	Travel

FMI Completion Code

1. Modification Complete or previously modified.
2. FMI not required per FMI instruction.
3. Not modified. Unit in storage. FMI kit returned to stock.
4. Modification refused or equipment altered. Customer signature and title required.
5. Unit location unknown or unit not in area. Product Locator notified.

Customer Refusal or Equipment Altered - Modification Pending.

Installer

Comments

Effectivity

Customers with an Octane 1 Single Processor that would like the LS2002 M4 SW FMI 25314. Console Model number 226683.

Purpose

The purpose of this FMI is to upgrade these Octane 1 Single Processors from ½ Gig of memory to 1.5 Gig of memory. The goal is to improve the performance of the customer's system so that the LS2002 SW FMI 25314 can be loaded onto the system. There have been customer complaints that loading the LS2002 SW FMI 25314 onto a customer's system that has and Octane 1 Single Processor with ½ Gig of memory. They have noted performance issues. The biggest issue is system slowdown.

Furnished Materials

Qty	Description	Part #
1	FMI Document	2375791-100
1	Directions to Install the memory	2373637-100
2	512 MB Memory	2169940-51

Tools Required

None.

People Power

Labor Estimates: 1 hour

Travel Estimates: 1 hour

Procedure

Before you Start

This FMI only applies to Octane Single Processor with 0.5MB of memory.

There are two ways to verify what type of Processor the Octane Computer has:

1. You can request a sweep as follows:

TO: autosc (MED) OR autosc@olc.med.ge.com

SUBJECT: sweep

Within the body of the mail, the following must be typed exactly as it appears below:

type = configuration

system id = xxx

system id = yyy

.

.

system id = zzz

where xxx, yyy, zzz are the various system IDs that you wish to have a sweep.

The reply from AUTOSC will be ...

.

.

HINV was run

.

.

1 360 MHZ IP30 Processors <- Number 1 = single processor; 2 = Double Processor
(Single Processor, you need to order FMI)

CPU: MIPS R12000 Processor Chip Revision: 2.3

FPU: MIPS R12010 Floating Point Chip Revision: 0.0

Main memory size: XXX Mbytes

Instruction cache size: 32 Kbytes

Data cache size: 32 Kbytes

2. If you are on site:

Open a shell and type: `hinv` **ENTER**

1 360 MHZ IP30 Processor <- Number 1 = single processor; 2 = Double Processor
(Single Processor you need to order FMI)

CPU: MIPS R12000 Processor Chip Revision: 3.5

FPU: MIPS R12010 Floating Point Chip Revision: 0.0

Main memory size: XXX Mbytes

Xbow ASIC: Revision 1.4

Instruction cache size: 32 Kbytes

Before shutting down, make a note of how much memory you are starting with.

Full and detailed procedure is in document 2373637-100, which is included in this FMI kit.

1. Shut down the System
2. Remove Console front cover
3. Unplug Octane Computer
4. Wait 5 minutes, and then remove system module
5. Remove cable attached to system module
6. Take appropriate precautions when handling ALL boards, Memory modules are sensitive to electrostatic discharge; please use your ESD kit.
7. Loosen screws that hold sliding handles on Octane
8. Pull both slide handles simultaneously
9. Remove all existing DIMMs
10. Insert the four new DIMMs from the kit into the first 2 banks closest to the CPU brick
11. Re-install removed DIMMs
12. Replace system module
13. Power up the Octane
14. Start System and Verify Memory is installed:

Open a shell

Type: `hinv` **ENTER**

Perform a tube warm up and test scan to confirm the system is functioning properly.

FMI Completion

Fill out and return the FMI Completion Certification Report paperwork (or electronically close your FMI dispatch) in accordance with your local procedure.