HD Stationary Thermal Interconnect

TGPU Power Supply

Stationary 48VDC Power Supply

Gnd

Chassis Ground

J7 3 1 2

NC, 24_Rtn, +24V, NC, 5_Rtn, +5V, -12V, 12_Rtn, +12V

J1 9 8 7 6 5 4 3 2 1

TGPU

UART

5V

J17 2 3 4 1

TxD, RxD, Gnd, +5V

J4B 1 2 3 4 5 6 7 8 9

Isolation

RS232 Chip

Isolator

Common Fan Control Board

LEDs:
Diag Fail- Amber
Heartbeat - Green (Blinks)
48VDC -Green
Default Mode - Amber

Processor

A/D

All Temp sensors Muxed into the same A/D

J4T 1 9 2 10

Send, Rtn

Gantry Heater/Blower

J4 (Heater) 1 2

Therm sensor

Stationary heater outlet temp

2kW Jumper

N.C. N.C. N.C. N.C.

Gantry Heater/Blower

Heate

J2 2 1

120VAC from PowerPan CB3

120VA C

Temp Switch

J1 3 4 1 2

SSR On (12Vdc)
SSR On (Gnd)
Current P1+
Current P1 -

J2 3 6 1 2

TR 3025-S Current Sensing

J5

J1

13 4 33 18 6 5 2 35 37 3 6 17 29 1 12 36 31 6 11 8 15 32 9 14 34 19 7 10 16 30

Blower

3 2 4 1 5 6

J3 6 5 4 2 1

48V
GND
Tacho
Speed Ctrl
Chassis Gnd

15 13 12 14 11 — 6 5 4 2 1 — Chassis Gnd, Speed Ctrl, Tacho, GND, 48V — Left Booster

5 8 7 9 6 — 6 5 4 2 1 — Chassis Gnd, Speed Ctrl, Tacho, GND, 48V — Left Rear

5 3 2 4 1 — 6 5 4 2 1 — Chassis Gnd, Speed Ctrl, Tacho, GND, 48V — Left Front

5 13 12 14 11 10 8 7 9 6 15 — 6 5 4 2 1 — Chassis Gnd, Speed Ctrl, Tacho, GND, 48V — Right Booster

6 5 4 2 1 — Chassis Gnd, Speed Ctrl, Tacho, GND, 48V — Right Rear

6 5 4 2 1 — Chassis Gnd, Speed Ctrl, Tacho, GND, 48V — Right Front

8.x Functional Interconnects and Block Diagrams	*Any copy made from the electronic version shall be considered an uncontrolled copy. Individuals with uncontrolled copies are responsible for ensuring the use of the current version.*	Proprietary to GE	**LAST UPDATED: SEPT 15, 2008**