TPPA PAYMENTS

Teller guide

Taking payments at a TPPA counter, from the start of the day to the day end.

For: Tellers

Version 1.0 · 2026-11-10

The screenshots come from a demonstration system: every name, account, amount and code in them is made up.

Contents

1 About this guide

- What the teller app is
- What you can and cannot do
- Words used in this guide

2 Getting started

- First start: registering this computer
- Signing in
- Signing in when the network is down
- The screen
- When "Payments cannot be taken right now"

3 Start of the day

- Choosing the receipt printer
- Loading the forms
- Calibrating: where the print lands on the form
- Recording the opening float

4 Taking a payment

- Step 1: the account
- Step 2: the amount due
- Several accounts for one customer
- Step 3: the payment
- Step 4: check and print
- Printed: give the change, next customer
- When printing stops
- One payment, start to finish

5 Today: reprints and voids

- Reprinting a receipt
- Voiding a receipt

6 Refunding a kiosk credit

When a refund is refused

7 Lock, help, theme and sign out

Locking the screen

Help and keyboard shortcuts

Theme

Signing out

8 Working offline

9 Day end

Opening the day end

Correcting the opening float

Counting the drawer

When the count is short or over

Day closed: the Z-reading

After the day is closed

A day that was not closed

10 Keyboard shortcuts

11 When something is not right

12 Quick reference

1. About this guide

This guide is for **tellers**: the counter staff who take utility bill payments at a TPPA branch. It follows a working day: signing in, getting the printer and the drawer ready, taking payments, fixing mistakes, refunding a kiosk credit, and closing the day.

The people in the screenshots are made up: **Ana Reyes** and **Ben Cruz** are tellers at Main Branch (0001), on Counter 1 and Counter 2. **Lea Garcia** is the branch manager.

What the teller app is

The teller app runs on the counter computer. With it you:

- take payments for the utilities your branch collects for (in the screenshots: **DLP**, Davao Light and Power Co., and **DCWD**, Davao City Water District), by cash, cheque or debit card;
- print the official receipt (OR) of each payment on the counter's receipt printer, the **Epson LX-310**;
- see today's receipts, reprint one, or void one with the branch manager;
- refund a kiosk credit slip, with the branch manager;
- count the drawer and close the day (the Z-reading).

The app keeps every payment on the counter computer first and sends it to head office. If the network is down, you keep working: the payments are sent when the network is back.

What you can and cannot do

You can	Only with the branch manager, on your screen	Only head office can
Take payments, print and reprint receipts	Void a receipt	Set the service fees
Choose the printer and calibrate it	Correct the opening float	Enable a utility at your branch
Record the opening float	Close the day with a cash difference	Open OR numbers for your terminal
Count the drawer and close the day when it balances	Refund a kiosk credit	Approve the receipt layout
Print the Z-reading		Register, reset or replace a terminal

How an approval works. The branch manager comes to your counter and types **their own username and password** into the approval fields on your screen. You stay signed in. The app checks that it is a different person from you, and that the person is a branch manager of your branch. A different person must approve: this is the four-eyes rule. Never type the manager's password for them, and never give anyone yours.

> **Note:** The branch manager can also sign in to the teller app and take payments. Everything in this guide works the same for them, except that they cannot approve their own void, float correction, cash difference or refund: another branch manager must.

Words used in this guide

Word	Meaning
OR	Official receipt. Each account paid gets its own OR number, for example 0001-01-00000001 (branch 0001, counter 01, then the number).
Opening float	The change fund in the cash drawer at the start of the day.
Service fee	TPPA's fee for each bill paid, set by head office. It is added to the bill.
Z-reading	The day's figures of your terminal, made when you close the day. Head office receives it.
Kiosk credit	A slip a payment kiosk prints when it kept a customer's cash but could not turn it into a payment.
Sync	The app sending your work to head office and receiving head office's settings (fees, utilities, staff).

2. Getting started


First start: registering this computer

A new counter computer is registered once, usually by IT or an administrator. You do not do this every day, but you should recognise the screens.

An administrator creates the terminal in the head office console and gets a **one-time code**: 12 letters and digits, valid for 24 hours, for one computer.


To register the computer:

1. Start the teller app. It shows **Set up this computer**.
2. Type the one-time code (1). Dashes are optional.
3. Leave **Server address** (2) as it is, unless IT tells you to change it.
4. Press **Register this computer** (3), or `Enter`.



1. Type the one-time code from the administrator
2. Server address: change only if IT says so
3. Register this computer (Enter)

A code that is wrong, already used or more than 24 hours old is refused: "This code is not valid or has expired. Ask the administrator for a new one."




1 The code as typed

2 Why it was refused

When the code is accepted, the app shows the terminal and its branch (1) and what it downloaded from head office (2): the utilities, the fee and receipt layout versions, the OR numbers of this terminal, and how many staff may sign in here.

5. Press **Continue to sign-in** (3), or `Enter`. **Download settings now** (4) fetches the settings again.



1. The terminal and its branch
2. What was downloaded from head office
3. Continue to sign-in (Enter)
4. Download the settings again


Tip: Each counter is its own terminal with its own code and its own OR numbers. Counter 2 was set up the same way: its screen read "Counter 2 is ready" and its receipts carry 02 in the OR number.

If the screen says "The settings have not been downloaded yet." and "Connect to the network and download the settings before taking payments.", connect the network and press **Download settings now**.

Signing in


Sign in at the start of your shift, with **your own** username and password.

1. Check the top line (1): it names this terminal and branch, and shows **Online** or **Offline**.
2. Type your username (2).
3. Type your password (3).
4. Press **Sign in** (4), or `Enter`.



1. This terminal and branch; Online or Offline
2. Your own username
3. Your password
4. Sign in (Enter)

A wrong username or password shows "Wrong username or password."



1. The message


Warning: Five wrong passwords in a row lock your account for 15 minutes: "This account is locked after too many wrong passwords. Wait 15 minutes, or ask an administrator to unlock it." Online, the count is the same everywhere: this counter, another counter and the web console. A right password starts it again from zero.

Other messages at sign-in:

Message	What it means and what to do
"Only tellers and the branch manager of this branch can sign in here."	Your account belongs to another branch, or to a role that does not work at counters. Ask the branch manager.
"This account is not active."	Your account is switched off. Ask the branch manager or head office.
"Enter your username and password."	One of the fields is empty.
"The settings have not been downloaded yet. Check the network, then sign in again."	The terminal has no settings yet. Check the network, then try again.

Signing in when the network is down

When the server cannot be reached, the sign-in screen shows **Offline** (1) and the note "Offline sign-in works for people who signed in online on this terminal in the last 36 hours." (2)



1 Offline

2 Who can sign in offline

You sign in the same way. The app checks your password on this computer. It refuses when:

Message	Why
"The server cannot be reached, and you have not signed in online on this terminal before. Connect to the network and sign in once, or ask a colleague who has."	You have never signed in online on this computer.
"Your last online sign-in on this terminal was more than 36 hours ago. Connect to the network and sign in online once."	Your last online sign-in here is too old.
"Your password was changed. Connect to the network and sign in online once."	Your password changed since your last online sign-in here.
"Your account is no longer allowed on this terminal. Ask the branch manager."	Head office removed you from this terminal's staff.
"Too many wrong passwords while offline. Connect to the network and sign in online."	Five wrong passwords while offline.

The screen

Once you are signed in, the screen has three parts.

Top bar. The TPPA name and this terminal ("Counter 1 · Main Branch 0001"); the four tabs, each with its key; and your name and role on the right (it opens the account menu).

Tab	Key	What it is for
Payment	`F2`	Taking a payment (the screen you use most).
Today	`F7`	This terminal's receipts today: reprint, void, refund a kiosk credit.
Day end	`F10`	Counting the drawer, closing the day, the Z-reading.
Printer	`F11`	Choosing the receipt printer and calibrating it.

The work area in the middle: the tab you are on.

The status bar at the bottom, always visible:


Item	What it tells you
Online, or **Offline: work is saved and sent later**	Whether the computer reaches head office. "Connecting…" shows briefly at start.
All synced, or **N waiting to sync**	How many records (payments, sign-ins, voids…) are still to be sent to head office.
Printer ready, or a printer problem	The receipt printer's state, for example "Printer: out of paper" or "Printer: none chosen (F11)". Point at it to see what to do.
OR numbers left: N	How many OR numbers this terminal still has. When it runs low it turns amber and adds ": tell head office".
A clock warning (only when needed)	"Clock N min off: ask IT to fix the time" when the computer clock is more than 5 minutes off; at more than 30 minutes, payments stop (see below).

Item	What it tells you
Date and time	Manila time, to the second. Receipts and the day end go by it.

The status bar of a ready counter reads, for example: "Online · All synced · Printer ready · OR numbers left: 99,999,999 · Tue, Nov 10 · 9:16:51 AM".

When "Payments cannot be taken right now"

If something stops payments, the Payment screen shows a red box "Payments cannot be taken right now." with the reason (1). You can still use Today, Day end and Printer.



1. Why payments cannot be taken
2. Check for new settings
3. Printer state (F11 to choose one)
4. Printer screen (F11)

In this example no printer is chosen yet: the status bar says "Printer: none chosen (F11)" (3). Press `F11` or the **Printer** tab (4) to choose it.

When head office has fixed something (a fee, a utility, OR numbers), press **Check for new settings** (2) to fetch the settings at once instead of waiting (the app also checks by itself every 15 seconds).

Reason on screen	What to do
"No receipt printer is chosen for this terminal. Open Printer (F11) and choose the LX-310."	Choose the printer (see Start of the day).
"The day is closed on this terminal (Z-reading done). Payments resume tomorrow; reprints still work."	Nothing: the day was closed. Customers go to another counter.
"Sync required. This terminal has not received settings for more than 36 hours, so it cannot know the current fees. Connect to the network; payments resume as soon as settings arrive."	Check the network cable or Wi-Fi; call IT if it stays.

Reason on screen	What to do
"The computer clock is N minutes off. Receipts carry the date and time, so fix the clock before taking payments."	Call IT to correct the computer's time.
"No fee is in force for any utility yet. Head office must approve one."	Call head office.
"No utility is enabled for this branch. Head office enables it in the console: Branches, choose this branch, then Utilities at this branch."	Call head office.
"No receipt layout is in force yet. Head office must approve one."	Call head office.
"This terminal has no official receipt numbers. Head office must open an OR series for it."	Call head office.
"All official receipt numbers of this terminal are used. Head office must open the next OR series."	Call head office.
"The OR number cannot be printed with the current pattern. Call head office."	Call head office.
"This terminal has no settings yet. Connect to the network and download them."	Check the network; call IT.
"The server does not recognise this computer, so payments could not reach head office. Ask IT."	Call IT (see When something is not right).
"Head office reset the registration of this terminal. Set this computer up again with the new code."	Call IT (see When something is not right).


3. Start of the day

Before the first customer: sign in, check the printer and its forms, and record the opening float.

Choosing the receipt printer

You choose the printer once on a new terminal, or again if the printer is replaced. The choice stays on this computer for every teller.

1. Press `F11` (**Printer**).
2. In **Printer** (1), choose **the Epson LX-310**, the counter's receipt printer.




1 Choose the receipt printer

2 Only the Epson LX-310 prints receipts

The hint (2) explains why: "Choose the Epson LX-310. Receipts are sent as raw ESC/P, so other printers cannot print them." (In the screenshots the list shows "TPPA folder printer", a stand-in used on the demonstration system.)

When the printer is chosen, the screen confirms "Receipts print on ..." and shows:

- the printer's state (1), for example **Printer ready**;
- the receipt layout in force (2): "Two copies: office and customer's, version 1 · 8.5" × 5.5" form, 15 characters per inch";
- the form (3), with what is pre-printed on it and where the app's print lands; **Test page** or **Sample receipt** (4) changes what the preview shows;
- the printer chosen (5), and below it the calibration steps.



1. Printer state: Printer ready
2. Receipt layout in force
3. Where the print lands on the form
4. Test page or sample receipt
5. The printer chosen

Loading the forms

Receipts print on the pre-printed official receipt forms (8.5" × 5.5", two copies: office and customer's). The logo, TPPA name and address, VAT REG. TIN and the receipt statement are already on the form; the app prints the account, name, payment, amounts and OR number into the boxes.


Load the forms in the LX-310 before the first payment. When you calibrate, load a blank or spoiled form instead.

Calibrating: where the print lands on the form

Calibrate when the print does not sit in the boxes of the form (after loading a new pack, or when the printer was moved). Each counter keeps its own offsets.


1. Load a blank or spoiled form (1).
2. Press **Print test page** (2). The test page prints boxes where the receipt text goes. The screen says "Test page sent. Compare the boxes with the boxes on the form."

3. Compare the printed boxes with the boxes on the form. Move the print with the arrow buttons (3), or the arrow keys; `Shift` + arrow moves more. The readout (4) shows how far, for example "1.3 mm right" and "1.1 mm down". The preview moves with it.
4. Print the test page again to check. (If you changed the offsets, they are saved first.)
5. Press **Save offsets** (5), or `Enter`. Until then the screen shows **Not saved**.



1. Load a blank or spoiled form
2. Print the test page
3. Move the print (or arrow keys)
4. How far it moved
5. Save the offsets (Enter)

After saving, the screen says "Saved offsets in use" (2), and the status bar shows **Printer ready** (3).




1 Test page sent

2 Offsets saved

3 Status bar: printer ready

To see how a real receipt sits on the form, press **Sample receipt**. It shows a made-up payment in the layout in force.




1 A sample receipt on the form

Every saved calibration is recorded with your name.

Recording the opening float

Before the first payment of the day, the Payment screen asks for the opening float: the change fund in the drawer.

1. Count the change fund in the drawer.
2. Type the amount (1). It is filled in with the last float recorded on this terminal; type over it if today's is different. Enter 0 if there is none.
3. Press **Record float** (2), or `Enter`.




1 The change fund counted in the drawer

2 Record float (Enter)

The screen explains why it matters: "At the day end the drawer should hold this plus the cash you take, less any kiosk credits refunded."

> **Important:** Count carefully. "A correction later needs the branch manager." To correct it, see Correcting the opening float in the Day end section.

The opening float is asked for once per day on each terminal. Counter 2, for example, recorded ₱1,000.00:



1. Opening float: 1,000.00
2. Record float (Enter)


4. Taking a payment

A payment has four steps, shown at the top of the Payment screen: **1. Account**, **2. Amount due**, **3. Payment**, **4. Print**. The keyboard does everything: `Enter` goes forward, `Esc` goes back one step and nothing you typed is lost.

On the right, **This customer** shows the running total all the time: each account with its bill and fee, then **Bills**, **Service fees**, **Total due**, and the change.


Step 1: the account

1. Check the utility (1). It shows the utility of the bill, for example **DCWD** Davao City Water District. If the bill is from another utility, press **Change** and choose it.
2. Type the **Account ID** (2) from the bill. Type the digits only: dashes are added for you.
3. Type the **Customer name** (3) as printed on the bill.
4. Press **Next: amount** (4), or `Enter`.




1. The utility of the bill: Change
2. Account ID from the bill
3. Customer name as on the bill
4. Next: amount (Enter)
5. This customer: the running total

Changing the utility. Change shows one tile per utility of your branch. Click one, or use the arrow keys. The cursor goes back to the Account ID.



1. Davao Light
2. Davao City Water

The hint under the Account ID gives the number of digits for the utility chosen: "11 digits from the bill. Dashes are added for you." for DLP (account IDs like 305-1234-5678), 9 digits for DCWD (like 123-456-789).




1. Utility: DLP
2. Dashes are added as you type
3. Name as printed on the bill
4. Next: amount (Enter)

If the number has the wrong length, the app says so, for example "Davao City Water District account IDs have 9 digits; this has 8." If you paste a number that is too long, it is refused, never cut short: "That has 12 digits; Davao City Water District account IDs have 9. Check the number on the bill."

A name filled in for you. When this account was paid on this terminal before, the app fills in the name from that payment (1) and the hint says "Filled from an earlier payment. Check it against the bill."

Already paid today. When the account was already paid today on this terminal, an amber warning shows (2), for example: "Already paid today for this account (9:16 AM, OR 0001-01-00000001). Ask the customer before taking a second payment." You can still go on if the customer wants to pay again.




1 Filled from the earlier payment

2 Already paid today: ask the customer

Step 2: the amount due

1. Type the **Bill amount** (1): the amount the customer is paying on this bill, for example 1500.00.
2. Check the fee and total (2): "Service fee set by head office; it cannot be changed here. This account: fee ₱2.00, total ₱1,502.00."
3. Press **Add and go to payment** (3), or `Enter`. To pay another bill for the same customer first, press **Add another account** (4), or `F3`. **Back** (5), or `Esc`, returns to the account.



1 The amount on the bill

2 Fee and total for this account

3 Add and go to payment (Enter)

4 Add another account (F3)


5 Back one step (Esc)

An empty or wrong amount shows "Enter the bill amount, for example 1500.00."

Several accounts for one customer

A customer can pay several bills, of the same or different utilities, in one go. They pay one total; each account still gets **its own OR**.

1. On the amount step, press **Add another account** (F3). The account step comes back as **Account 2** (1).
2. Choose the utility (2), type the account ID (3) and name, then the amount, as before.
3. The accounts already added show on the right (4), each with its bill and fee.
4. When all bills are in, press **Done adding: payment** (5), or F4 (or **Add and go to payment** on the amount step).



1. Account 2 of this customer
2. Utility: DCWD
3. Water account: 9 digits
4. The first account, with its fee
5. Done adding: payment (F4)


To take an account off before printing, press **Remove** under it in **This customer**. From the Payment step, **Add another account** (F3) adds one more.

Step 3: the payment

Choose how the customer pays (1): **Cash** F5, **Cheque** F6 or **Debit** F8. Cash is chosen first.

Cash

Amount received starts at the amount due (2): "Starts at the amount due: Enter if the customer pays it exactly." The right side shows the **Total due** (3) and the **Change** (4).




1. Cash F5, Cheque F6, Debit F8
2. Starts at the amount due
3. Total due: bills plus fees
4. Change

If the customer gives more:


- type the amount received over it, or
- use the bill buttons **+20**, **+50**, **+100**, **+200**, **+500**, **+1,000** (2): the first one replaces the amount, the next ones add to it. For example, three presses on **+1,000** make ₱3,000.00.
- **Exact** puts the amount due back.

The change to give shows on the right (3). Press **Check and print** (4), or `Enter`.



1. Amount received
2. Bill buttons: the first replaces, the next add
3. Change to give
4. Check and print (Enter)
5. Add another account (F3)


Not enough cash. If the amount received is less than the total due, the right side shows **SHORT BY** (2), the screen says "Short by 347.50. Collect more cash before printing." and **Check and print** stays disabled (3) until enough is received.



1. Amount received so far
2. Short by: not enough yet
3. Disabled until enough is received

Cheque


1. Press **Cheque** (1), or `F6`.
2. Type the **Cheque number** (2), digits only.
3. Enter the **Cheque date** (3) as written on the cheque.
4. Type the **Bank** (4).
5. Choose the **Type** (5): **Local**, **Regional**, **On-us** or **Manager's check**.
6. Check that the cheque is for exactly the total due (6): "The cheque must be for exactly ₱2,342.50. No change is given on cheques."
7. Press **Check and print**, or `Enter`.



1. Cheque (F6)
2. Cheque number
3. Date on the cheque
4. Bank
5. Type of cheque
6. Exact amount: no change on cheques

The app refuses a cheque it may not take, with the reason (2):


- "The cheque is older than 180 days (stale): not accepted." (the limit is head office's rule for the utility);
- "Post-dated cheques are not accepted.";
- "(utility) does not accept cheques." when head office does not allow cheques for that utility;
- "Enter the cheque number (digits only), date, bank and type." when something is missing.



1 Cheque date 2 Why it cannot be taken

Debit card

1. Press **Debit** (1), or `F8`. The screen says "The full amount ₱2,342.50 is charged on the card terminal."
2. Charge the total on the card terminal.
3. Type the **Card or approval reference** (2) from the card terminal (at least 4 characters). Without it: "Enter the card or approval reference from the card terminal."
4. Press **Check and print**, or `Enter`.




1 Debit (F8) 2 Card or approval reference

There is no change on a debit payment.

Step 4: check and print

The app shows each receipt as it will print: one per account, each with **its own OR number** (1), the account, name and utility, the bill (Collection), the fee's VAT lines and the total. The change is on the last one (2). Nothing is recorded yet.

1. Check the receipts with the customer: account, name and amounts.
2. Make sure the official receipt forms are loaded: "Load the official receipt forms first. Each account gets its own OR; the change is on the last one."
3. Press **Print receipt** (or **Print 2 receipts**...) (3), or `Enter`. To change something, press **Back** (4), or `Esc`.



1. Receipt 1: its own OR number
2. Receipt 2: with the change
3. Print (Enter)
4. Back (Esc)


When you press Print, the payment is recorded, the OR numbers are used, and the receipts print.

> **Note:** If the printer is not ready when you press Print (out of paper, offline...), the app stops before recording anything: for example "Printer is out of paper. Load forms, then press Enter to print. Nothing is recorded yet." Fix the printer, then press `Enter`.

Printed: give the change, next customer

The screen shows **Printed**, the OR numbers (1) and, for cash, **GIVE CHANGE** (2) in large figures.


1. Give the customer the change shown and their copies of the receipts.
2. Press **Next customer** (3), or `Enter`, for a clean Payment screen.



1. The OR numbers printed
2. Give change
3. Next customer (Enter)
4. Reprint (F9)
5. Saved and sent to head office

The line at the bottom (5) tells you where the payment is: "Saved on this computer and sent to head office." Offline it reads "Saved on this computer; it will be sent when the network is back." While it is on its way: "Saved on this computer; sending to head office." **Reprint** (4), or `F9`, prints this customer's receipts again, marked REPRINTED.

For a cheque or debit payment there is no change: "Paid by cheque. No change." (2).



1. The OR number
2. Paid by cheque. No change.
3. Next customer (Enter)

When printing stops

If the printer stops after the payment was recorded (paper out half-way, a jam), the screen shows **Printing stopped** with what to do, for example "Paper jam. Clear it and reload the forms, then press F9 to reprint OR 0001-01-00000001." and "The payment is saved; the number is not lost."


1. Fix the printer as the message says.
2. Press **Reprint** (`F9`), or `Enter`. The receipts print, marked REPRINTED.
3. Press **Next customer**.

Do not take the payment again: it is already recorded. If a receipt is really wrong, void it (see Today).

One payment, start to finish


Ben Cruz on Counter 2 takes a DLP bill of ₱980.00 from CRISTINA RAMOS, account 305-2222-3333.

1. Utility **DLP** (1), account ID (2), name (3), then **Next: amount** (`Enter`) (4).




1. Utility: DLP
2. Account 305-2222-3333
3. CRISTINA RAMOS
4. Next: amount (Enter)

2. Bill amount 980.00, `Enter`. The total due is ₱982.00, the bill plus the ₱2.00 fee (1). The customer gives ₱1,000.00 (2): one press on **+1,000**. Change ₱18.00 (3). **Check and print** (`Enter`) (4), then **Print receipt** (`Enter`).



1. Total due: bill plus fee
2. Amount received
3. Change to give
4. Check and print (Enter)

3. The OR number carries the counter, 02 (1). Give ₱18.00 change (2). The payment is saved and sent (3). **Next customer** (`Enter`) (4).




1. The OR number: counter 02
2. Give change
3. Saved and sent to head office
4. Next customer (Enter)

5. Today: reprints and voids

Press F7 (**Today**) to see the receipts of this terminal today, newest first.

At the top, the day's numbers (1): **PAYMENTS** (valid receipts), **COLLECTED** (their total), **VOIDED** and **REPRINTS**. Each row shows the OR number and time (2), the customer and account, how it was paid, the total and its status (**Valid** or **Voided**), with the number of reprints next to it. Each valid row has **Reprint** (3) and **Void** (4). **Refund a kiosk credit** (5) is at the top right.



1. The day's numbers
2. OR number and time
3. Reprint this receipt
4. Void (needs the branch manager)
5. Refund a kiosk credit

Today lists only payments taken on this terminal, on today's date.


Reprinting a receipt

Reprint when a receipt did not print well, or the customer needs another copy. A reprint is always marked **REPRINTED** on the receipt, and every reprint is counted and sent to head office.

To reprint a receipt:

1. Press F7 (**Today**).
2. Find the receipt by its OR number.
3. Press **Reprint** on its row.

The screen confirms "Reprinted 0001-01-00000002, marked REPRINTED." (1). The row shows how many times it was reprinted (2), and **REPRINTS** goes up (3).



1. Reprinted, marked REPRINTED
2. How many times reprinted
3. Reprints today


To reprint the last customer's receipts, press F9 on the Payment or Today screen. A voided receipt is never printed again ("This OR is voided; a voided OR is not printed again.").

Voiding a receipt

Void a receipt when it is wrong (for example, the wrong account was entered) and must not count. The branch manager approves the void on your screen. The OR number is kept and never used again.

To void a receipt:


1. Press F7 (**Today**) and find the receipt.
2. Press **Void** on its row. The dialog names the OR, the customer and the account.
3. Type the **Reason** (1), at least 3 characters, for example "Wrong account entered".
4. The branch manager types their **Manager username** (2) and **Manager password** (3).
5. Press **Void receipt** (4), or Enter. **Cancel** (5), or Esc, closes the dialog without voiding.



1. Why the receipt is voided
2. Branch manager: username
3. Branch manager: own password
4. Void receipt (Enter)
5. Cancel (Esc)


The void is refused when:

- you type your own username and password: "A different person must approve a void: the branch manager signs with their own password."



1. Refused: a different person must approve


- the person is not a branch manager, for example another teller: "Ben Cruz is not a branch manager. Only a branch manager can approve a void."



1 Refused: only a branch manager

- the reason is missing or too short: "Enter the reason, e.g. "Wrong account entered".";
- the username or password is empty: "Enter the branch manager's username and password.";
- the password is wrong: "Wrong username or password." (the password field is emptied; the manager's account locks after five wrong passwords, as at sign-in);
- the day is closed: "The day of OR 0001-01-00000004 is closed, so it can no longer be voided here. Call head office." (after the day end, the **Void** button is gone).

When the void is accepted, the screen says "OR 0001-01-00000004 voided. Approved by Lea Garcia." (1). The row is marked **Voided** with its reason (2), and **VOIDED** goes up (3). The voided receipt no longer counts in **PAYMENTS** and **COLLECTED**.



1 Voided, and who approved

2 Voided, with the reason

3 Voided today

After a void:

- If the customer still owes the bill, take the payment again with the right details. It gets a new OR number.
- The voided amount is left out of the day's cash: at the day end, **Cash expected** does not include it, and the Z-reading lists it under **Voided**.
- A void works offline too (see Working offline).


6. Refunding a kiosk credit

A payment kiosk prints a **kiosk credit slip** when it kept a customer's cash but could not turn it into a payment: "The customer left before the total was in", or "Payments stopped (power cut or fault) with cash in". The slip carries a code like KC-434U-VGR9. The customer brings it to a counter, and you pay the amount out of your drawer, with the branch manager's approval.

> **Important:** A refund needs the network: the code is checked with head office, so each slip is paid only once. It is not a payment: it gets no OR number and prints no receipt. Keep the slip with today's papers.

To refund a kiosk credit:


1. Take the slip from the customer.
2. Press `F7` (**Today**), then **Refund a kiosk credit**.
3. Type or scan the **Code on the slip** (1). Capitals and dashes are added for you.
4. Press **Check the code** (2), or `Enter`. **Cancel** (3), or `Esc`, closes it.



1. The code on the slip: KC-434U-VGR9
2. Check the code (Enter)
3. Cancel (Esc)


Head office answers with what the credit is (nothing changes yet): the amount (1), when the kiosk issued it (2), which kiosk and branch (3), and why the kiosk kept the cash (4).

5. Check that the code on the slip matches the title, and the amount.
6. The branch manager types their **Manager username** (5) and **Manager password** (6).
7. Press **Refund ₱100.00** (with the amount), or `Enter`.




1. What the credit is worth
2. When the kiosk issued it
3. Which kiosk, which branch
4. Why the kiosk kept the cash
5. Branch manager: username
6. Branch manager: own password

If you type your own username and password, the refund is refused: "A different person must approve a refund: the branch manager signs with their own password." The password field is emptied.



1. Refused: a different person must approve


The branch manager then types her own username (1) and password (2), and presses **Refund ₱100.00** (3). (In this picture the red message of the refused attempt is still showing; it clears when the manager's approval is sent.)



1 lea.garcia, the branch manager
2 She types her own password
3 Refund the amount (Enter)


Head office marks the credit refunded and the dialog closes. Today shows what to do (1): "Pay ₱100.00 to the customer from the drawer, and keep the slip KC-434U-VGR9 with today's papers. Approved by Lea Garcia."

8. Pay the amount to the customer from the drawer.
9. Keep the slip with today's papers.



1 Pay this from the drawer; keep the slip
2 Payments only: the refund is not one

The refund does not appear in Today's numbers or list (2): they show payments only. It is sent to head office (4: "All synced") and counted at the day end, where **Kiosk credits refunded** shows it and **Cash expected** is lowered by it.




1. Today's payments: 1, 982.00
2. The DLP payment
3. Refund a kiosk credit
4. The refund is sent to head office

When a refund is refused


Message	What to do
"Already refunded Nov 10, 10:09 AM at Main Branch 0001, counter 02, by Ben Cruz (approved by Lea Garcia). Do not pay it out again; keep the slip and call head office."	Do not pay. Keep the slip and call head office.
"Head office has no kiosk credit with this code. Check the code on the slip. If it is right, call head office: do not pay it out."	Check the code you typed. If it is right, do not pay; call head office.
"Enter the whole code, as on the slip: KC, then two groups of four letters and numbers."	Type the whole code.
"No network. A kiosk credit is checked with head office so it is paid only once. Connect to the network, or ask the customer to come back."	Wait for the network, or ask the customer to come back.
"The day is closed on this terminal: the drawer is counted. Refund it at another counter, or tomorrow."	Send the customer to a counter that is still open, or ask them to come back tomorrow.
"(name) is not a branch manager of this branch. Only a branch manager can approve a refund."	Ask a branch manager of your branch to approve.
"Wrong username or password."	The manager types the password again.

A slip already paid is refused at the first step, before any manager is asked:




1. The same code again
2. Refused: already refunded, when, where, by whom

An unknown code:



1. Head office has no such credit


After the day end on this terminal:



1 Refused: the day is closed here

7. Lock, help, theme and sign out

Your name, top right (1), opens the account menu: **Theme** (2), **Help and shortcuts** (3), **Lock screen** (4) and **Sign out** (5), with the time your shift started ("Shift since 9:17 AM").



1 Your name: open the menu
2 Theme: Auto, Light, Dark
3 Help and shortcuts (F1)
4 Lock screen (F12)
5 Sign out, with the shift start


Locking the screen

Lock the screen whenever you leave the counter. Press `F12`, or **Lock screen** in the menu. The app also locks by itself after 10 minutes without use.

Locking keeps your shift open. The screen shows who is signed in and since when (1): "Ana Reyes · shift open since 9:17 AM. Nothing was lost."


To unlock:

1. Type your password (2).
2. Press **Unlock** (3), or `Enter`.



1 Who is signed in, since when
2 Your password
3 Unlock (Enter)


Unlocking works offline too. Only the person signed in can unlock. A wrong password shows "Wrong password."; after five wrong passwords the app signs you out: "Too many wrong passwords: signed out. Sign in again."



1 Wrong password

Help and keyboard shortcuts

Press `F1`, or **Help and shortcuts** in the menu, to see the keys. Press `Esc` or **Close** (1) to close it.




1 Close (Esc)

Theme

Theme sets the colours: **Auto** follows the computer ("Follows this computer: light now."), **Light** or **Dark**. A Light or Dark choice is kept on this computer for every teller.

Signing out

Sign out at the end of your shift, or when another teller takes over the counter. Press **Sign out** in the account menu. The sign-in screen comes back (1).




1 Signed out: the sign-in screen

Closing the teller app also signs you out. Only one person is signed in on a terminal at a time.

8. Working offline

When the network or head office is unreachable, the status bar shows **Offline: work is saved and sent later** (1), and how many records are waiting (2).



1 Offline: work is saved and sent later

2 Records waiting to sync

What works offline:

- signing in (for people who signed in online here in the last 36 hours) and unlocking;
- taking payments by cash, cheque and debit, and printing them;
- reprints;
- voids, a float correction and closing the day, with the branch manager's approval: the manager's password is checked on this computer, so it works only if the manager signed in or approved online on this terminal in the last 36 hours;
- the day end and the Z-reading.

What does not work offline:

- refunding a kiosk credit (it is checked with head office);
- receiving new settings (fees, utilities, staff). After 36 hours without settings, payments stop ("Sync required...") until the network is back.

Everything you do offline is kept on this computer in order and sent when the network is back; **N waiting to sync** goes down to **All synced**. You do not need to do anything.

> **Warning:** Never reinstall or replace the counter computer while records are waiting to sync: they are only on this computer until they are sent. If the network is down for long, tell the branch manager and IT.


9. Day end

At the end of the day, you count the drawer, check the figures and close the day. Closing the day makes the **Z-reading** of your terminal, which head office receives. Each terminal closes its own day.

Opening the day end

Press `F10` (**Day end**). The screen has:

- the **Cash drawer** (1): one line per bill and coin;
- **THE DAY'S FIGURES** (2): ORs issued (how many, first to last), Cash, Cheques and Debit (total and count), Voided, Reprints and Kiosk credits refunded;
- whether everything was sent to head office (3): "Everything sent to head office", or "N waiting to sync: sent when the network is back";
- **CASH** (4): the **Opening float**, the **Cash expected**, the **Cash counted** and the **DIFFERENCE**.




1. Count the drawer: bills and coins
2. The day's figures
3. Sent to head office?
4. Cash expected

Cash expected is what the drawer should hold:

> Cash expected = Opening float + cash payments − kiosk credits refunded

Cheques and debit payments are not in the drawer cash; voided payments are left out. In this example: ₱2,000.00 float + ₱2,347.50 cash = ₱4,347.50.

On Counter 2, a kiosk credit was refunded. The day's figures (1) show **Kiosk credits refunded** ₱100.00 (1 refund) (2), and Cash expected is ₱1,000.00 + ₱982.00 − ₱100.00 = ₱1,882.00 (3). **Close day** (4) stays unavailable until you enter the count: "Enter the count to close the day."




1. The day's figures
2. Kiosk credits refunded: amount (count)
3. Cash expected: float + cash - refunds
4. Close day: only after the count

Correcting the opening float

If the opening float recorded in the morning was wrong, correct it before closing the day. The branch manager approves.

1. Press **Correct** next to **Opening float**.
2. Type the right float (1).
3. The branch manager types their **Manager username** and **Manager password**: "The branch manager approves the new float here with their own username and password."
4. Press **Save float**. **Cancel** closes it without a change.




1 The right float

Without the manager, the app refuses: "Today's opening float is already recorded (₱2,000.00). A branch manager approves a correction." Cash expected changes with the new float.

Counting the drawer

1. Count the cash in the drawer, by bill and by coin.
2. Type how many of each (1), from ₱1,000.00 down to ₱0.25. `Enter` moves to the next line. Each line shows its value, and **Counted** (2) the total.
3. Compare **Cash counted** with **Cash expected** (3).

When the two are equal, the screen shows **BALANCED** ₱0.00 (4). Press **Close day** (5).




1. How many of each bill
2. Counted
3. Cash counted against expected
4. Balanced
5. Close day

Before you close: "After closing, this terminal takes no more payments for this day. Reprints still work." Make sure the last customer is done.

When the count is short or over


When the count differs, the screen shows **SHORT** or **OVER** and the difference (1), for example "Short ₱20.00", and a box "The count is short by ₱20.00": "Count the drawer again, or a branch manager approves the difference here with their own username and password." (2)

1. Count the drawer again, and correct the numbers. Check the opening float too.
2. If the difference stays, call the branch manager.
3. The branch manager types their **Manager username** (3) and **Manager password** (4).
4. Press **Approve and close day**.



1 Short: the difference
2 Count again, or the manager approves
3 Branch manager: username
4 Branch manager: password

Refusals: your own password ("A different person must approve the cash difference: the branch manager signs with their own password."), someone who is not a branch manager, a wrong password, or empty fields ("Enter the branch manager's username and password.").




1 Refused: a different person must approve

Day closed: the Z-reading


The screen becomes **Day closed**, with when and by whom (1), for example "Closed 9:18 AM by Ana Reyes". It reads: "This terminal takes no more payments for this day; reprints still work. Head office has the Z-reading."

The **Z-reading** (2) shows the branch and terminal, the day's figures, the opening float, the cash expected and the cash counted. The **Cash** box (3) shows whether the drawer balanced, or the difference, and who approved a difference (4): "Difference approved by Lea Garcia."



1. Closed: when and by whom
2. The Z-reading
3. The cash difference
4. Who approved the difference
5. Print Z-reading


To print it, load a form and press **Print Z-reading** (5). "Print it when you need a paper copy, as often as needed." The screen confirms "Z-reading printed."



1. Z-reading printed

After the day is closed

- The Payment screen refuses new payments: "The day is closed on this terminal (Z-reading done). Payments resume tomorrow; reprints still work." (1) Send late customers to a counter that is still open.
- Reprints still work from Today; voids do not (the **Void** buttons are gone).
- Kiosk credits cannot be refunded on this terminal until tomorrow.
- Day end shows the Z-reading; you can print it again.
- Sign out when you leave the counter.



1 No more payments today

The next day, sign in as usual: the app asks for the new opening float before the first payment.

A day that was not closed

If a day with payments was not closed (for example the app was closed before the day end), Day end opens on that earlier day first, with "This is an earlier day that was not closed. Close it first; then close the next one." Count and close it the same way. Days are closed in order.

10. Keyboard shortcuts

Everything works without the mouse.

Key	What it does
`Enter`	Next step / confirm
`Esc`	Back one step; closes a dialog or the help
`F1`	Help and shortcuts

Key	What it does
`F2`	Payment (new payment)
`F3`	Add another account
`F4`	Done adding: go to payment
`F5` / `F6` / `F8`	Cash / Cheque / Debit
`F7`	Today's payments (reprint, void, kiosk credit refund)
`F9`	Reprint the last receipt (marked REPRINTED)
`F10`	Day end: cash count and Z-reading
`F11`	Printer and calibration
`F12`	Lock the screen
Arrow keys (Printer screen)	Move the print; `Shift` + arrow moves more
`Enter` (Day end count)	Next line of the count

11. When something is not right

Most problems show a message that says what to do. The common ones are below; the Troubleshooting guide has more.

What you see	What to do	Who to call
Status bar: "Printer: out of paper"	Load forms. Reprint with `F9` if a receipt was cut short.	-
"Printer: paper jam"	Clear the paper path and reload the forms, then `F9`.	-
"Printer: offline"	Check that the printer is switched on, online and connected.	IT if it stays
"Printer: paused"	Printing is paused in Windows: resume the printer in Printers & scanners.	IT
"Printer: not found", or "The chosen printer cannot print receipts..."	The LX-310 is missing or the wrong printer is chosen: choose the LX-310 in Printer (F11).	IT
The print is not in the boxes of the form	Calibrate (Printer, F11).	-
Printing stopped after a payment	Fix the printer, then **Reprint** (`F9`). Do not take the payment again.	-
"Payments cannot be taken right now."	Read the reason; see the table in Getting started.	Head office or IT
Offline, and many records waiting to sync	Keep working. Check the network cable or Wi-Fi.	IT if it lasts

What you see	What to do	Who to call
"Clock N min off: ask IT to fix the time"	Keep working, and report it.	IT
OR numbers left in amber ("tell head office")	Tell head office before the numbers run out.	Head office
"Only N OR numbers are left for M accounts. Take fewer accounts, and tell head office."	Take the accounts in smaller groups, and tell head office.	Head office
Your account is locked	Wait 15 minutes, or ask an administrator to unlock it.	Head office
You forgot your password	An administrator resets it. Then sign in online once.	Head office
A customer says they already paid	Look in Today (F7). An "Already paid today" warning shows it for this terminal.	-
A receipt is wrong	Void it with the branch manager, then take the payment again.	Branch manager
A receipt of a closed day is wrong	It cannot be voided at the counter.	Head office
A kiosk credit slip is refused	Do not pay it out; keep the slip.	Head office
"Sync stopped." in a red box	Keep the paper receipts; read the reason shown.	IT and head office
"The server does not recognise this computer"	Payments are stopped. Do not reinstall anything; keep the paper receipts.	IT
"This terminal was reset"	Everyone is signed out. IT sets the computer up again with a new code.	IT
"The app could not start" / "This computer cannot run the teller app"	Restart the computer once. If it happens again, call IT.	IT
"The payment could not be saved, and nothing was recorded."	Try again; if it happens again, call IT.	IT

Note: When the screen says "The server does not recognise this computer" or "This terminal was reset", it may list records that never reached head office, with their OR numbers. Keep the paper receipts and tell head office: IT is asked to confirm that before the computer is set up again.

12. Quick reference

Task	Where	Approval
Sign in	Sign-in screen, your own username and password	-
Choose the printer	Printer (F11), Printer	-
Calibrate the print	Printer (F11), Calibration, Save offsets (Enter)	-

Task	Where	Approval
Record the opening float	Payment (F2), before the first payment	-
Take a payment	Payment (F2): Account, Amount due, Payment, Print	-
Add another account	F3 (amount or payment step); F4 when done	-
Cash / cheque / debit	F5 / F6 / F8 on the payment step	-
Reprint the last receipt	F9	-
Reprint any receipt of today	Today (F7), Reprint	-
Void a receipt	Today (F7), Void, reason	Branch manager
Refund a kiosk credit	Today (F7), Refund a kiosk credit (network needed)	Branch manager
Correct the opening float	Day end (F10), Correct	Branch manager
Count the drawer and close the day	Day end (F10), count, Close day	-
Close the day with a difference	Day end (F10), Approve and close day	Branch manager
Print the Z-reading	Day end (F10) after closing, Print Z-reading	-
Lock the screen	F12, or your name, Lock screen	-
Help	F1, or your name, Help and shortcuts	-
Change the theme	Your name, Theme	-
Sign out	Your name, Sign out	-