Strona WWW | Przeglądarka i BLE OS | SoftDevice S112 | ble_sched.c (SWI2) | pętla główna, sched_store.c

Zapis rozkładu

16 writeValue WithResponse (113 B)

alt **[MTU ≥ 116]**

17 Write Request

18 RW_AUTHORIZE (WRITE_REQ)

19 validate

[MTU < 116]

20 Prepare Write ×n (bufor nrf_ble_qwr)

21 Execute Write

22 RW_AUTHORIZE (EXEC_WRITE)

23 qwr_cb: validate

24 authorize_reply (status)

validate = sched_decode;
OK → s_stage_ready
(długi: po odpowiedzi)

25 Write Response lub błąd ATT

26 table_replace, sched_store_save, limit 30 s

27 flash: kasowanie, zapis 0x7F000

28 readValue(), porównanie

Rozłączenie

29 limit lub alarm: disconnect

30 LL_TERMINATE

31 gattserver disconnected

32 GAP_EVT_ DISCONNECTED

bez połączenia: po 60 s
ADV_SET_TERMINATED

Strona WWW | Przeglądarka i BLE OS | SoftDevice S112 | ble_sched.c (SWI2) | pętla główna, sched_store.c