



M5 ACCESS SWITCH INPUT USER GUIDE (V1.0)

A wireless switch interface device

Milad Hajihassan

<https://github.com/milador/M5-Access-Switch-Input>

Contents

Usage requirements.....	2
Usage Components.....	2
Usage Process	2
How to Use?.....	2
How to Customize?	2
Sleep Mode	3

Usage requirements

Usage Components

1. Adaptive Switch x 2 (Example: [AJelly Bean](#))

Usage Process

How to Use?

1. Connect two Adaptive Switches to the Switch Input module through 3.5mm switch connectors.

1.1. Switch A

1.2. Switch B

2. Connect and pair to the host device (Example: Windows 10 PC)

On Windows 10:

2.1. Select **Start > Settings > Devices > Bluetooth & other devices** 2.2. Select **Add Bluetooth or other device > Bluetooth**. 2.3. Choose **Qwiic BLE Switch** and follow additional instructions if they appear. 2.4. Select **Done** once the device is paired.

3. Switch between modes by press and holding Switch A for 4 seconds or by pressing M5 button.

3.1. Switch Mode: Windows and Android, Switch A : a Key, Switch B : b Key

3.2. Switch Mac Mode: Mac, Switch A : F1 Key, Switch B : F2 Key

3.3. Morse Keyboard Mode: Morse code, Switch A : Dot, Switch B : Dash

3.4. Settings Mode: Change reaction time, Switch A : Decrease Reaction level, Switch B : Increase Reaction level

How to Customize?

1. Enter Settings Mode by press holding switch A 3 times for 4 seconds or by pressing M5 button. The screen will display a text in yellow to indicate it's in Settings Mode.
2. Press Switch A to Decrease Reaction level (Maximum is 1) : 500ms

3. Press Switch B to Increase Reaction level (Minimum is 10) : 50ms

Sleep Mode

The device goes to sleep mode if it's not used for more than one minute and automatically wakes up every 3 minutes. The device can be woken up if switch A or Switch B is pressed when the device is in sleep mode.