

scripts/run-helixqa-provider-qa.sh

Revision: 2 **Last modified:** 2026-06-30T00:00:00Z **Inheritance:** HelixConstitution §11.4.18 (script documentation mandate) + Lava §6.AD (HelixConstitution Inheritance). Constitutional bindings of the script itself: §6.AE (per-provider Challenge coverage), §6.AH (device in VM/container — no host-direct), §11.4.3 (topology SKIP, never a fake PASS), §11.4.27 (HelixQA full coverage), §11.4.87/§11.4.98 (autonomous, no manual intervention).

Overview

Thin Lava glue that runs **HelixQA** against the Lava Android app for a given provider (or all), feeding the matching Lava test bank, using the **claude CLI as the LLM/Vision model bridge** (HelixQA's BridgedCLIPProvider — no API key needed). It is the per-provider companion to scripts/run-genymotion-challenges.sh.

Prerequisites

- HelixQA buildable: submodules/helixqa + its own-org dep submodules (see docs/qa/helixqa-dependency-submodules.md, added 2026-06-08). go build ./cmd/helixqa.
- Lava banks present under lava-api-go/qa/banks/:
 - default mode resolves lava-<provider>-journey.yaml;
 - --matrix resolves lava-<provider>-matrix-journey.yaml instead.
- go (1.24+), adb, and the claude CLI on PATH.
- **A reachable device** — the Genymotion VM (default 127.0.0.1:6555) booted first, or a physical device with the Lava app (digital.vasic.lava.client.dev) installed. Per §6.AH the device **MUST** be a VM/container emulator, never a host-direct one.

Usage

```
# explicit per-provider bank run (default mode)
scripts/run-helixqa-provider-qa.sh --provider rutor --serial
127.0.0.1:6555

# matrix-journey bank for a provider (the broader matrix variant)
scripts/run-helixqa-provider-qa.sh --provider archiveorg --matrix

# every provider, sequentially
scripts/run-helixqa-provider-qa.sh --all

# doc-driven autonomous QA session instead of explicit banks
scripts/run-helixqa-provider-qa.sh --provider kinozal --autonomous
```

Inputs (flags)

Flag	Default	Description
--provider <id>	— (required unless --all)	One of the PROVIDERS set (below).
--all	—	Run every provider bank sequentially (non-zero exit if any fails).
--serial <s>	\$LAVA_REAL_DEVICE_SERIALS or 127.0.0.1:6555 (the Genymotion VM)	adb device serial to target.
--autonomous	off (helixqa run --banks)	Use helixqa autonomous (doc-driven session) instead of the explicit per-provider bank.
--matrix	off (journey)	Resolve banks as lava-<prov>-matrix-journey.yaml instead of the default lava-<prov>-journey.yaml.

PROVIDERS set

rutracker, rutor, iptorrents, kinozal, nmclub, archiveorg, gutenber
(the PROVIDERS array in the script; --all iterates exactly this list). A provider with no matching bank file is SKIPPed (honest, not a failure).

Environment overrides

- LAVA_QA_PACKAGE — app package id (default `digital.vasic.lava.client.dev`).
- LAVA_REAL_DEVICE_SERIALS — default adb serial when `--serial` is omitted.

Exit codes (anti-bluff)

- 0 — QA run completed.
- 1 — QA run reported failures (one or more banks failed).
- 2 — **honest BLOCKED**: no adb device in device state (or adb missing). NOT a pass (§6.AH/§11.4.3). Boot the Genymotion VM / attach a device, then re-run.
- 3 — helixqa build failed (check the dep submodules).
- 64 — usage error (unknown flag, or neither `--provider` nor `--all` given).

Internal behaviour

1. Parse flags; require `--provider <id>` or `--all`.
2. Honest device gate first — `adb connect <serial>` + check for a device-state entry; exit 2 if none.
3. Build the helixqa binary to a temp path (`GOMAXPROCS=2 go build ./cmd/helixqa`); print its version.
4. Confirm the claude bridge is on PATH (warn if absent — autonomous mode then lacks the LLM/Vision bridge).
5. Per provider, resolve the bank (`lava-<prov>-<journey|matrix-journey>.yaml`); SKIP if absent, else: `helixqa run --banks <bank> --platform android --device <serial> --package <pkg> --output .lava-ci-evidence/helixqa/<provider>/<run-id>/` (or `helixqa autonomous --project <root> --platforms android --env .env --output ... in --autonomous mode`).

Outputs

Per-run evidence under `.lava-ci-evidence/helixqa/<provider>/<run-id>/` (run id is a UTC timestamp suffixed with the provider).

Verified

- `bash -n` parse: clean (§11.4.67).
- No-device gate: exits 2 with the BLOCKED message when no VM is booted (honest BLOCKED, §6.AH/§11.4.3).

Related

- docs/qa/helixqa-wiring-plan.md — bridge-discovery facts + verbatim helixqa list proof.
- docs/qa/helixqa-dependency-submodules.md — the own-org deps that make the binary buildable.
- scripts/run-genymotion-challenges.sh — the Genymotion Compose-Challenge device path.
- scripts/autonomous-qa/run-matrix.sh — the backend×provider autonomous-QA matrix orchestrator.

Last verified: 2026-06-30 (revision 2 — documents --matrix, the full 7-provider PROVIDERS set incl. iptorrents/gutenberg, the --serial default, exit code 64, and the per-script constitutional bindings).