

Xinhmo

Start here

FOR STAFF

You need this Mac, the Canon camera, the SELPHY printer, and the Mac's login password. The very first time, also an internet connection.

What is in this folder

In the folder	What it is for
START-BOOTH	Double-click to run the booth
CHECK-BOOTH	Double-click to check the camera and printer only
START-HERE, OPERATORS-GUIDE	These guides
app	The booth itself. Staff never need to open it.

Every event

- 1 Plug in the camera and the printer, and switch both on.** Use the camera's power adapter, not just its battery.
- 2 Double-click** **START-B00TH** .
It checks the camera and the printer first. If something is wrong it says exactly what to do: follow the steps, press **Return**, and it checks again. When both say **OK**, the booth opens by itself.
Leave the black Terminal window open while the booth runs.
- 3 Open the staff page on your phone.** Use the address the booth shows and enter the staff code. The **Booth** tab shows the camera, the printer, the paper and the ink.

Just want to check the camera and printer? Double-click **CHECK-B00TH** . It runs the same check without opening the booth, and can print a test page.

The first time on a new Mac

- 1 **Moved this folder by zip, AirDrop or USB stick?** macOS may refuse to open it. Open Terminal, type the line below and a space, drag this folder onto the Terminal window, and press Return:

```
xattr -dr com.apple.quarantine
```

- 2 The **EDSDK** folder must be inside the **app** folder. It is Canon's camera software: licensed, never on GitHub, so it is copied across by hand.
- 3 **Double-click** **START-BOOTH** . The first time, macOS may say it *cannot be opened*: right-click it, choose **Open**, then **Open** again. Only once.

Setting up takes 5 to 15 minutes, by itself:

- It asks for this Mac's password. Nothing shows while you type; press Return.
- If a window asks to install Apple's *command line developer tools*, click **Install**, then double-click **START-BOOTH** again.

If something is off

Problem	Fix
The printer does nothing	System Settings > Printers & Scanners: add the printer. Its name must match <code>printerName</code> in <code>app/settings.json</code> .
Staff code	<code>staffPin</code> in <code>app/settings.json</code> . It starts as 1234. Change it.

Running an event: **OPERATORS-GUIDE.pdf**.