

Photon Voice

v2.52

Generated by Doxygen 1.8.17

1 Main Page	1
2 Namespace Documentation	3
2.1 Photon Namespace Reference	3
2.2 Photon.Voice Namespace Reference	3
2.2.1 Enumeration Type Documentation	6
2.2.1.1 AudioSampleType	6
2.2.1.2 Codec	6
2.3 Photon.Voice.FMOD Namespace Reference	6
2.4 Photon.Voice.Fusion Namespace Reference	6
2.5 Photon.Voice.IOS Namespace Reference	7
2.5.1 Enumeration Type Documentation	7
2.5.1.1 AudioSessionCategory	7
2.5.1.2 AudioSessionCategoryOption	8
2.5.1.3 AudioSessionMode	9
2.6 Photon.Voice.MacOS Namespace Reference	9
2.7 Photon.Voice.PUN Namespace Reference	9
2.8 Photon.Voice.PUN.UtilityScripts Namespace Reference	10
2.9 Photon.Voice.Unity Namespace Reference	10
2.10 Photon.Voice.Unity.FMOD Namespace Reference	11
2.11 Photon.Voice.Unity.UtilityScripts Namespace Reference	11
2.12 Photon.Voice.UWP Namespace Reference	11
2.13 Photon.Voice.Windows Namespace Reference	11
3 Class Documentation	13
3.1 AndroidAudioInAEC Class Reference	13
3.2 AndroidAudioInParameters Struct Reference	13
3.3 AudioChangesHandler Class Reference	14
3.3.1 Detailed Description	14
3.3.2 Member Data Documentation	14
3.3.2.1 HandleDeviceChange	14
3.3.2.2 HandleDeviceChangeAndroid	14
3.3.2.3 HandleDeviceChangeIOS	15
3.4 AudioClipWrapper Class Reference	15
3.5 AudioDesc Class Reference	15
3.6 AudioInChangeNotifier Class Reference	15
3.6.1 Member Function Documentation	16
3.6.1.1 Dispose()	16
3.6.2 Property Documentation	16
3.6.2.1 Error	16
3.7 AudioInChangeNotifier Class Reference	16
3.7.1 Member Function Documentation	17
3.7.1.1 Dispose()	17

3.7.2 Property Documentation	17
3.7.2.1 Error	17
3.8 AudioInChangeNotifierNotSupported Class Reference	17
3.9 AudioInEnumerator Class Reference	18
3.9.1 Detailed Description	18
3.9.2 Member Function Documentation	18
3.9.2.1 Dispose()	18
3.9.2.2 Refresh()	18
3.10 AudioInEnumerator Class Reference	19
3.11 AudioInEnumerator Class Reference	19
3.12 AudioInEnumerator Class Reference	19
3.13 AudioInEnumerator Class Reference	20
3.13.1 Detailed Description	20
3.13.2 Member Function Documentation	20
3.13.2.1 Dispose()	20
3.13.2.2 Refresh()	20
3.14 AudioInPusher Class Reference	21
3.15 AudioInPusher Class Reference	21
3.16 AudioInPusher Class Reference	21
3.16.1 Property Documentation	22
3.16.1.1 Channels	22
3.17 AudioInReader Class Reference	22
3.18 AudioInReader Class Reference	22
3.19 AudioInReader< T > Class Template Reference	23
3.19.1 Member Function Documentation	23
3.19.1.1 Read()	23
3.20 AudioOut< T > Class Template Reference	24
3.21 AudioOutCapture Class Reference	24
3.22 AudioOutDelayControl Class Reference	24
3.23 AudioOutDelayControl Class Reference	25
3.24 AudioOutDummy< T > Class Template Reference	25
3.25 AudioOutEvent< T > Class Template Reference	25
3.26 AudioSessionParameters Struct Reference	26
3.27 AudioSessionParametersPresets Class Reference	26
3.27.1 Member Data Documentation	26
3.27.1.1 Game	26
3.27.1.2 VoIP	27
3.28 AudioSyncBuffer< T > Class Template Reference	27
3.29 AudioUtil Class Reference	27
3.29.1 Detailed Description	29
3.29.2 Member Function Documentation	29
3.29.2.1 Convert() [1/2]	29

3.29.2.2 Convert() [2/2]	29
3.29.2.3 ForceToStereo< T >()	29
3.29.2.4 Resample< T >()	30
3.29.2.5 ResampleAndConvert() [1/2]	30
3.29.2.6 ResampleAndConvert() [2/2]	31
3.30 BufferReaderPushAdapterAsyncPool< T > Class Template Reference	31
3.30.1 Detailed Description	31
3.30.2 Constructor & Destructor Documentation	32
3.30.2.1 BufferReaderPushAdapterAsyncPool()	32
3.30.3 Member Function Documentation	32
3.30.3.1 Service()	32
3.31 BufferReaderPushAdapterAsyncPoolFloatToShort Class Reference	32
3.31.1 Detailed Description	33
3.31.2 Constructor & Destructor Documentation	33
3.31.2.1 BufferReaderPushAdapterAsyncPoolFloatToShort()	33
3.31.3 Member Function Documentation	33
3.31.3.1 Service()	33
3.32 BufferReaderPushAdapterAsyncPoolShortToFloat Class Reference	34
3.32.1 Detailed Description	34
3.32.2 Constructor & Destructor Documentation	34
3.32.2.1 BufferReaderPushAdapterAsyncPoolShortToFloat()	34
3.32.3 Member Function Documentation	34
3.32.3.1 Service()	35
3.33 BufferReaderPushAdapterBase< T > Class Template Reference	35
3.33.1 Detailed Description	35
3.33.2 Constructor & Destructor Documentation	35
3.33.2.1 BufferReaderPushAdapterBase()	35
3.33.3 Member Function Documentation	36
3.33.3.1 Dispose()	36
3.33.3.2 Service()	36
3.34 CaptureDevice Class Reference	36
3.34.1 Member Function Documentation	37
3.34.1.1 CleanUpAsync()	37
3.34.1.2 SelectPreferredCameraStreamSettingAsync()	37
3.34.1.3 StartRecordingAsync()	38
3.34.1.4 StopRecordingAsync()	38
3.34.2 Property Documentation	38
3.34.2.1 CaptureSource	38
3.35 ConnectAndJoin Class Reference	38
3.36 VoiceClient.CreateOptions Struct Reference	39
3.36.1 Member Data Documentation	39
3.36.1.1 Default	39

3.37 OpusCodec.Decoder< T > Class Template Reference	39
3.37.1 Member Function Documentation	40
3.37.1.1 Input()	40
3.37.1.2 Open()	40
3.38 RawCodec.Decoder< T > Class Template Reference	40
3.38.1 Member Function Documentation	41
3.38.1.1 Input()	41
3.38.1.2 Open()	41
3.39 DeviceEnumerator Class Reference	41
3.40 DeviceEnumeratorBase Class Reference	42
3.41 DeviceFeatures Class Reference	42
3.42 DeviceInfo Struct Reference	43
3.43 RecorderPreset.DSP Struct Reference	43
3.44 OpusCodec.Encoder< T > Class Template Reference	43
3.45 RawCodec.Encoder< T > Class Template Reference	44
3.46 OpusCodec.EncoderFloat Class Reference	44
3.47 OpusCodec.EncoderShort Class Reference	45
3.48 OpusCodec.Factory Class Reference	45
3.49 FactoryPrimitiveArrayPool< T > Class Template Reference	45
3.49.1 Detailed Description	45
3.50 FactoryReusableArray< T > Class Template Reference	46
3.50.1 Detailed Description	46
3.51 Flip Struct Reference	46
3.52 FMODRecorderSetup Class Reference	47
3.53 FrameBuffer Struct Reference	47
3.54 FrameOut< T > Class Template Reference	48
3.55 Framer< T > Class Template Reference	48
3.55.1 Detailed Description	48
3.55.2 Constructor & Destructor Documentation	49
3.55.2.1 Framer()	49
3.55.3 Member Function Documentation	49
3.55.3.1 Frame()	49
3.56 FramerResampler< T > Class Template Reference	49
3.56.1 Member Function Documentation	50
3.56.1.1 Frame()	50
3.57 FusionVoiceClient Class Reference	50
3.57.1 Member Data Documentation	51
3.57.1.1 UseFusionAppSettings	51
3.57.1.2 UseFusionAuthValues	51
3.58 AudioUtil.GeneratorPusher< T > Class Template Reference	51
3.58.1 Detailed Description	52
3.58.2 Member Function Documentation	52

3.58.2.1 SetCallback()	52
3.59 AudioUtil.GeneratorReader< T > Class Template Reference	52
3.59.1 Member Function Documentation	53
3.59.1.1 Read()	53
3.60 IAudioDesc Interface Reference	53
3.60.1 Detailed Description	54
3.60.2 Property Documentation	54
3.60.2.1 Channels	54
3.60.2.2 Error	54
3.60.2.3 SamplingRate	54
3.61 IAudioInChangeNotifier Interface Reference	54
3.62 IAudioOut< T > Interface Template Reference	55
3.63 IAudioPusher< T > Interface Template Reference	55
3.63.1 Detailed Description	55
3.63.2 Member Function Documentation	55
3.63.2.1 SetCallback()	55
3.64 IAudioReader< T > Interface Template Reference	56
3.64.1 Detailed Description	56
3.65 IDataReader< T > Interface Template Reference	56
3.65.1 Detailed Description	56
3.65.2 Member Function Documentation	56
3.65.2.1 Read()	56
3.66 IDecoder Interface Reference	57
3.66.1 Detailed Description	57
3.66.2 Member Function Documentation	57
3.66.2.1 Input()	57
3.66.2.2 Open()	57
3.66.3 Property Documentation	58
3.66.3.1 Error	58
3.67 IDecoderDirect< B > Interface Template Reference	58
3.67.1 Detailed Description	58
3.67.2 Property Documentation	58
3.67.2.1 Output	58
3.68 IDeviceEnumerator Interface Reference	59
3.69 IEncoder Interface Reference	59
3.69.1 Detailed Description	59
3.69.2 Member Function Documentation	60
3.69.2.1 DequeueOutput()	60
3.69.2.2 EndOfStream()	60
3.69.2.3 GetPlatformAPI< I >()	60
3.69.3 Property Documentation	60
3.69.3.1 Error	60

3.69.3.2 Output	60
3.70 IEncoderDirect< B > Interface Template Reference	61
3.70.1 Detailed Description	61
3.70.2 Member Function Documentation	61
3.70.2.1 Input()	61
3.71 IEncoderDirectImage Interface Reference	61
3.71.1 Detailed Description	62
3.71.2 Property Documentation	62
3.71.2.1 ImageFormat	62
3.72 AudioUtil.ILevelMeter Interface Reference	62
3.72.1 Detailed Description	62
3.72.2 Member Function Documentation	62
3.72.2.1 ResetAccumAvgPeakAmp()	63
3.72.3 Property Documentation	63
3.72.3.1 AccumAvgPeakAmp	63
3.72.3.2 CurrentAvgAmp	63
3.72.3.3 CurrentPeakAmp	63
3.73 ILocalVoiceAudio Interface Reference	63
3.73.1 Detailed Description	64
3.73.2 Member Function Documentation	64
3.73.2.1 VoiceDetectorCalibrate()	64
3.73.3 Property Documentation	64
3.73.3.1 LevelMeter	64
3.73.3.2 VoiceDetector	65
3.73.3.3 VoiceDetectorCalibrating	65
3.74 ILogger Interface Reference	65
3.75 ImageBufferInfo Struct Reference	65
3.76 ImageBufferNative Class Reference	66
3.77 ImageBufferNativeAlloc Class Reference	66
3.78 ImageBufferNativeGCHandleBytes Class Reference	66
3.79 ImageBufferNativeGCHandleSinglePlane Class Reference	67
3.80 ImageBufferNativePool< T > Class Template Reference	67
3.81 IProcessor< T > Interface Template Reference	67
3.81.1 Detailed Description	68
3.81.2 Member Function Documentation	68
3.81.2.1 Process()	68
3.82 IResettable Interface Reference	68
3.83 IServiceable Interface Reference	68
3.83.1 Detailed Description	69
3.83.2 Member Function Documentation	69
3.83.2.1 Service()	69
3.84 AudioUtil.IVoiceDetector Interface Reference	69

3.84.1 Detailed Description	70
3.84.2 Property Documentation	70
3.84.2.1 ActivityDelayMs	70
3.84.2.2 Detected	70
3.84.2.3 DetectedTime	70
3.84.2.4 On	70
3.84.2.5 Threshold	70
3.84.3 Event Documentation	71
3.84.3.1 OnDetected	71
3.85 IVoiceTransport Interface Reference	71
3.86 AudioUtil.LevelMeter< T > Class Template Reference	71
3.86.1 Detailed Description	72
3.86.2 Member Function Documentation	72
3.86.2.1 Process()	72
3.86.2.2 ResetAccumAvgPeakAmp()	72
3.87 AudioUtil.LevelMeterDummy Class Reference	72
3.87.1 Detailed Description	73
3.87.2 Member Function Documentation	73
3.87.2.1 ResetAccumAvgPeakAmp()	73
3.88 AudioUtil.LevelMeterFloat Class Reference	73
3.88.1 Detailed Description	73
3.88.2 Constructor & Destructor Documentation	74
3.88.2.1 LevelMeterFloat()	74
3.89 AudioUtil.LevelMeterShort Class Reference	75
3.89.1 Detailed Description	75
3.89.2 Constructor & Destructor Documentation	75
3.89.2.1 LevelMeterShort()	75
3.90 LoadBalancingTransport Class Reference	76
3.90.1 Detailed Description	77
3.90.2 Constructor & Destructor Documentation	77
3.90.2.1 LoadBalancingTransport()	77
3.90.3 Member Function Documentation	77
3.90.3.1 Dispose()	77
3.90.3.2 Service()	77
3.90.4 Property Documentation	78
3.90.4.1 VoiceClient	78
3.91 LoadBalancingTransport2 Class Reference	78
3.91.1 Detailed Description	78
3.92 LocalVoice Class Reference	78
3.92.1 Detailed Description	80
3.92.2 Member Function Documentation	80
3.92.2.1 RemoveSelf()	80

3.92.3 Property Documentation	80
3.92.3.1 DebugEchoMode	81
3.92.3.2 Encrypt	81
3.92.3.3 FEC	81
3.92.3.4 Fragment	81
3.92.3.5 FramesSent	81
3.92.3.6 FramesSentBytes	81
3.92.3.7 FramesSentFragmented	82
3.92.3.8 FramesSentFragments	82
3.92.3.9 Info	82
3.92.3.10 InterestGroup	82
3.92.3.11 IsCurrentlyTransmitting	82
3.92.3.12 LocalUserServiceable	82
3.92.3.13 Reliable	83
3.92.3.14 SendSpacingProfileMax	83
3.92.3.15 TargetPlayers	83
3.92.3.16 TransmitEnabled	83
3.93 LocalVoiceAudio< T > Class Template Reference	83
3.93.1 Detailed Description	84
3.93.2 Member Function Documentation	84
3.93.2.1 VoiceDetectorCalibrate()	84
3.93.3 Property Documentation	85
3.93.3.1 VoiceDetectorCalibrating	85
3.94 LocalVoiceAudioDummy Class Reference	85
3.94.1 Detailed Description	85
3.94.2 Member Function Documentation	85
3.94.2.1 VoiceDetectorCalibrate()	85
3.94.3 Member Data Documentation	86
3.94.3.1 Dummy	86
3.95 LocalVoiceAudioFloat Class Reference	86
3.95.1 Detailed Description	86
3.96 LocalVoiceAudioShort Class Reference	86
3.96.1 Detailed Description	86
3.97 LocalVoiceFramed< T > Class Template Reference	87
3.97.1 Detailed Description	87
3.97.2 Member Function Documentation	87
3.97.2.1 AddPostProcessor()	87
3.97.2.2 AddPreProcessor()	88
3.97.2.3 ClearProcessors()	88
3.97.2.4 Dispose()	88
3.97.2.5 PushData()	88
3.97.2.6 PushDataAsync()	89

3.97.2.7 RemoveProcessor()	89
3.97.3 Property Documentation	89
3.97.3.1 BufferFactory	89
3.97.3.2 PushDataAsyncReady	89
3.98 Logger Class Reference	89
3.99 MicAmplifier Class Reference	90
3.100 MicAmplifierFloat Class Reference	90
3.101 MicAmplifierShort Class Reference	90
3.102 MicrophonePermission Class Reference	91
3.102.1 Detailed Description	91
3.103 MicWrapper Class Reference	91
3.104 MicWrapperPusher Class Reference	92
3.105 MicWrapperPusherOnAudioFilterRead Class Reference	92
3.106 MonoPInvokeCallbackAttribute Class Reference	92
3.107 ObjectFactory< TType, TInfo > Interface Template Reference	92
3.107.1 Detailed Description	93
3.108 ObjectPool< TType, TInfo > Class Template Reference	93
3.108.1 Detailed Description	94
3.108.2 Constructor & Destructor Documentation	94
3.108.2.1 ObjectPool() [1/2]	94
3.108.2.2 ObjectPool() [2/2]	95
3.108.3 Member Function Documentation	95
3.108.3.1 AcquireOrCreate() [1/2]	95
3.108.3.2 AcquireOrCreate() [2/2]	95
3.108.3.3 Dispose()	95
3.108.3.4 Init()	96
3.108.3.5 Release() [1/2]	96
3.108.3.6 Release() [2/2]	96
3.108.4 Property Documentation	96
3.108.4.1 Info	97
3.109 OpusCodec Class Reference	97
3.110 PhotonAppSettings Class Reference	97
3.110.1 Detailed Description	98
3.110.2 Member Function Documentation	98
3.110.2.1 ToString()	98
3.110.2.2 UseCloud()	98
3.111 PhotonVoiceCreatedParams Class Reference	98
3.112 PhotonVoiceLagSimulationGui Class Reference	98
3.113 PhotonVoiceStatsGui Class Reference	99
3.113.1 Detailed Description	99
3.114 PhotonVoiceView Class Reference	99
3.114.1 Detailed Description	99

3.114.2 Property Documentation	100
3.114.2.1 IsRecording	100
3.114.2.2 IsSpeaking	100
3.114.2.3 RecorderInUse	100
3.114.2.4 SpeakerInUse	100
3.115 ImageBufferNative.PlaneSet Struct Reference	100
3.116 Platform Class Reference	101
3.117 AudioOutDelayControl.PlayDelayConfig Struct Reference	101
3.117.1 Member Data Documentation	101
3.117.1.1 Default	101
3.118 PrimitiveArrayPool< T > Class Template Reference	102
3.118.1 Detailed Description	102
3.119 PunVoiceClient Class Reference	102
3.119.1 Detailed Description	103
3.119.2 Member Function Documentation	103
3.119.2.1 ConnectAndJoinRoom()	104
3.119.2.2 Disconnect()	104
3.119.3 Member Data Documentation	104
3.119.3.1 AutoConnectAndJoin	104
3.119.3.2 AutoLeaveAndDisconnect	104
3.119.3.3 VoiceRoomNameSuffix	104
3.119.4 Property Documentation	104
3.119.4.1 Instance	105
3.119.4.2 UsePunAppSettings	105
3.119.4.3 UsePunAuthValues	105
3.120 RawCodec Class Reference	105
3.121 Recorder Class Reference	105
3.121.1 Detailed Description	107
3.121.2 Member Function Documentation	108
3.121.2.1 ResetLocalAudio()	108
3.121.2.2 RestartRecording()	108
3.121.2.3 SetAndroidNativeMicrophoneSettings()	108
3.121.2.4 SetlosAudioSessionParameters() [1/2]	109
3.121.2.5 SetlosAudioSessionParameters() [2/2]	109
3.121.2.6 VoiceDetectorCalibrate()	109
3.121.3 Property Documentation	110
3.121.3.1 AudioClip	110
3.121.3.2 Bitrate	110
3.121.3.3 DebugEchoMode	110
3.121.3.4 Encrypt	110
3.121.3.5 FrameDuration	110
3.121.3.6 InputFactory	111

3.121.3.7 InterestGroup	111
3.121.3.8 IsCurrentlyTransmitting	111
3.121.3.9 LevelMeter	111
3.121.3.10 LoopAudioClip	111
3.121.3.11 MicrophoneType	111
3.121.3.12 RecordingEnabled	112
3.121.3.13 RecordWhenJoined	112
3.121.3.14 ReliableMode	112
3.121.3.15 SamplingRate	112
3.121.3.16 SourceType	112
3.121.3.17 StopRecordingWhenPaused	112
3.121.3.18 TargetPlayers	113
3.121.3.19 TransmitEnabled	113
3.121.3.20 UseMicrophoneTypeFallback	113
3.121.3.21 UseOnAudioFilterRead	113
3.121.3.22 UserData	113
3.121.3.23 VoiceDetection	113
3.121.3.24 VoiceDetectionDelayMs	114
3.121.3.25 VoiceDetectionThreshold	114
3.121.3.26 VoiceDetector	114
3.121.3.27 VoiceDetectorCalibrating	114
3.122 RecorderPreset Class Reference	114
3.123 RemoteVoiceInfo Class Reference	115
3.123.1 Detailed Description	115
3.123.2 Property Documentation	115
3.123.2.1 ChannelId	115
3.123.2.2 Info	115
3.123.2.3 playerId	116
3.123.2.4 VoicId	116
3.124 RemoteVoiceLink Class Reference	116
3.125 RemoteVoiceOptions Struct Reference	116
3.125.1 Detailed Description	117
3.125.2 Member Function Documentation	117
3.125.2.1 SetOutput() [1/2]	117
3.125.2.2 SetOutput() [2/2]	117
3.125.3 Property Documentation	117
3.125.3.1 Decoder	117
3.125.3.2 OnRemoteVoiceRemoveAction	118
3.126 AudioUtil.Resampler< T > Class Template Reference	118
3.126.1 Detailed Description	118
3.126.2 Constructor & Destructor Documentation	118
3.126.2.1 Resampler()	118

3.126.3 Member Function Documentation	119
3.126.3.1 Process()	119
3.127 SaveIncomingStreamToFile Class Reference	119
3.128 SaveOutgoingStreamToFile Class Reference	119
3.129 SendFrameParams Struct Reference	119
3.130 RawCodec.ShortToFloat Class Reference	120
3.131 Speaker Class Reference	120
3.131.1 Member Function Documentation	121
3.131.1.1 RestartPlayback()	121
3.131.2 Property Documentation	121
3.131.2.1 IsLinked	121
3.131.2.2 IsPlaying	122
3.131.2.3 Lag	122
3.131.2.4 OnRemoteVoiceRemoveAction	122
3.131.2.5 PlayDelay	122
3.131.2.6 PlayDelayConfig	122
3.132 SpeakerAudioFilterRead Class Reference	122
3.133 SpeakerFMOD Class Reference	123
3.134 ImageBufferInfo.StrideSet Struct Reference	123
3.135 AudioUtil.TempoUp< T > Class Template Reference	123
3.136 TestTone Class Reference	123
3.137 AudioUtil.ToneAudioPusher< T > Class Template Reference	124
3.137.1 Detailed Description	124
3.137.2 Constructor & Destructor Documentation	124
3.137.2.1 ToneAudioPusher()	124
3.138 AudioUtil.ToneAudioReader< T > Class Template Reference	125
3.138.1 Detailed Description	125
3.138.2 Constructor & Destructor Documentation	125
3.138.2.1 ToneAudioReader()	125
3.139 UnityAudioOut Class Reference	126
3.140 UnityLogger Class Reference	126
3.141 UnityMicrophone Class Reference	126
3.141.1 Detailed Description	127
3.142 UnityVoiceClient Class Reference	127
3.142.1 Detailed Description	127
3.142.2 Member Function Documentation	127
3.142.2.1 ConnectUsingSettings()	127
3.142.3 Member Data Documentation	128
3.142.3.1 UseVoiceAppSettings	128
3.143 UnsupportedCodecException Class Reference	128
3.143.1 Detailed Description	128
3.143.2 Constructor & Destructor Documentation	128

3.143.2.1 UnsupportedCodecException()	128
3.144 UnsupportedPlatformException Class Reference	129
3.144.1 Detailed Description	129
3.144.2 Constructor & Destructor Documentation	129
3.144.2.1 UnsupportedPlatformException()	129
3.145 UnsupportedSampleTypeException Class Reference	130
3.145.1 Detailed Description	130
3.145.2 Constructor & Destructor Documentation	130
3.145.2.1 UnsupportedSampleTypeException()	130
3.146 OpusCodec.Util Class Reference	130
3.147 VideoInEnumerator Class Reference	130
3.148 VideoInEnumerator Class Reference	131
3.149 VoiceClient Class Reference	131
3.149.1 Detailed Description	133
3.149.2 Constructor & Destructor Documentation	133
3.149.2.1 VoiceClient()	133
3.149.3 Member Function Documentation	133
3.149.3.1 CreateLocalVoice()	133
3.149.3.2 CreateLocalVoiceAudioFromSource()	134
3.149.3.3 CreateLocalVoiceVideo()	134
3.149.3.4 LocalVoicesInChannel()	135
3.149.3.5 RemoteVoiceInfoDelegate()	135
3.149.3.6 RemoveLocalVoice()	135
3.149.3.7 Service()	136
3.149.4 Property Documentation	136
3.149.4.1 DebugLostPercent	136
3.149.4.2 EventsLost	136
3.149.4.3 FramesFragPart	136
3.149.4.4 FramesLate	136
3.149.4.5 FramesLateUsed	136
3.149.4.6 FramesLost	137
3.149.4.7 FramesMiss	137
3.149.4.8 FramesReceived	137
3.149.4.9 FramesReceivedFEC	137
3.149.4.10 FramesReceivedFragmented	137
3.149.4.11 FramesReceivedFragments	137
3.149.4.12 FramesRecovered	138
3.149.4.13 FramesSent	138
3.149.4.14 FramesSentBytes	138
3.149.4.15 FramesTryFEC	138
3.149.4.16 LocalVoices	138
3.149.4.17 OnRemoteVoiceInfoAction	138

3.149.4.18 RemoteVoiceInfos	139
3.149.4.19 RoundTripTime	139
3.149.4.20 RoundTripTimeVariance	139
3.149.4.21 SuppressInfoDuplicateWarning	139
3.150 VoiceComponent Class Reference	139
3.151 VoiceComponentImpl Class Reference	140
3.152 VoiceConnection Class Reference	140
3.152.1 Detailed Description	142
3.152.2 Member Function Documentation	142
3.152.2.1 AddSpeaker()	142
3.152.2.2 ConnectUsingSettings()	142
3.152.2.3 InstantiateSpeakerPrefab()	143
3.152.3 Member Data Documentation	143
3.152.3.1 ChannelAudio	143
3.152.3.2 ChannelVideo	143
3.152.3.3 Settings	144
3.152.3.4 UsePrimaryRecorder	144
3.152.4 Property Documentation	144
3.152.4.1 BestRegionSummaryInPreferences	144
3.152.4.2 ClientState	144
3.152.4.3 FramesLostPercent	144
3.152.4.4 FramesLostPerSecond	144
3.152.4.5 FramesReceivedPerSecond	145
3.152.4.6 PrimaryRecorder	145
3.152.4.7 SpeakerPrefab	145
3.152.4.8 VoiceClient	145
3.152.5 Event Documentation	145
3.152.5.1 RemoteVoiceAdded	145
3.152.5.2 SpeakerLinked	145
3.153 VoiceCreateOptions Struct Reference	146
3.153.1 Detailed Description	146
3.153.2 Member Data Documentation	146
3.153.2.1 DebugEchoMode	146
3.153.2.2 Encoder	146
3.153.2.3 Encrypt	147
3.153.2.4 FEC	147
3.153.2.5 Fragment	147
3.153.2.6 InterestGroup	147
3.153.2.7 Reliable	147
3.153.2.8 TargetPlayers	147
3.154 VoiceDebugScript Class Reference	148
3.154.1 Detailed Description	148

3.154.2 Member Data Documentation	148
3.154.2.1 DisableVad	148
3.154.2.2 ForceRecordingAndTransmission	149
3.154.2.3 IncreaseLogLevels	149
3.154.2.4 LocalDebug	149
3.154.2.5 TestAudioClip	149
3.154.2.6 TestUsingAudioClip	149
3.155 AudioUtil.VoiceDetector< T > Class Template Reference	149
3.155.1 Detailed Description	150
3.155.2 Member Function Documentation	150
3.155.2.1 Process()	150
3.155.3 Property Documentation	151
3.155.3.1 ActivityDelayMs	151
3.155.3.2 Detected	151
3.155.3.3 DetectedTime	151
3.155.3.4 On	151
3.155.3.5 Threshold	152
3.155.4 Event Documentation	152
3.155.4.1 OnDetected	152
3.156 AudioUtil.VoiceDetectorCalibration< T > Class Template Reference	152
3.156.1 Detailed Description	153
3.156.2 Constructor & Destructor Documentation	153
3.156.2.1 VoiceDetectorCalibration()	153
3.156.3 Member Function Documentation	153
3.156.3.1 Calibrate()	153
3.156.3.2 Process()	154
3.157 AudioUtil.VoiceDetectorDummy Class Reference	154
3.157.1 Detailed Description	154
3.158 AudioUtil.VoiceDetectorFloat Class Reference	154
3.158.1 Detailed Description	155
3.158.2 Constructor & Destructor Documentation	155
3.158.2.1 VoiceDetectorFloat()	155
3.159 AudioUtil.VoiceDetectorShort Class Reference	155
3.159.1 Detailed Description	155
3.159.2 Constructor & Destructor Documentation	156
3.159.2.1 VoiceDetectorShort()	156
3.160 VoiceEvent Class Reference	156
3.160.1 Member Data Documentation	156
3.160.1.1 Code	156
3.161 VoiceInfo Struct Reference	156
3.161.1 Detailed Description	157
3.161.2 Member Function Documentation	157

3.161.2.1 CreateAudio()	158
3.161.2.2 CreateAudioOpus()	158
3.161.2.3 CreateVideo()	159
3.161.3 Property Documentation	159
3.161.3.1 Bitrate	159
3.161.3.2 Channels	159
3.161.3.3 FPS	160
3.161.3.4 FrameDurationSamples	160
3.161.3.5 FrameDurationUs	160
3.161.3.6 FrameSize	160
3.161.3.7 Height	160
3.161.3.8 KeyFrameInt	160
3.161.3.9 SamplingRate	161
3.161.3.10 UserData	161
3.161.3.11 Width	161
3.162 AudioUtil.VoiceLevelDetectCalibrate< T > Class Template Reference	161
3.162.1 Detailed Description	162
3.162.2 Constructor & Destructor Documentation	162
3.162.2.1 VoiceLevelDetectCalibrate()	162
3.162.3 Member Function Documentation	162
3.162.3.1 Calibrate()	162
3.162.3.2 Process()	162
3.162.4 Property Documentation	163
3.162.4.1 LevelMeter	163
3.162.4.2 VoiceDetector	163
3.163 VoiceLogger Class Reference	163
3.164 VoiceNetworkObject Class Reference	164
3.164.1 Member Data Documentation	164
3.164.1.1 IsRecording	164
3.164.1.2 IsSpeaking	165
3.164.2 Property Documentation	165
3.164.2.1 RecorderInUse	165
3.164.2.2 SpeakerInUse	165
3.165 AudioUtil.WaveformAudioPusher< T > Class Template Reference	165
3.165.1 Detailed Description	166
3.166 AudioUtil.WaveformAudioReader< T > Class Template Reference	166
3.166.1 Detailed Description	166
3.167 WaveWriter Class Reference	166
3.168 WebRtcAudioDsp Class Reference	167
3.168.1 Member Data Documentation	167
3.168.1.1 IsSupported	167
3.169 WebRTCAudioLib Class Reference	168

3.170 WebRTCAudioProcessor Class Reference	168
3.171 WindowsAudioInPusher Class Reference	169
Index	171

Chapter 1

Main Page

Photon Voice 2 has three key classes:

- `Photon.Voice.Unity.VoiceConnection` (extends `Photon.Realtime.ConnectionHandler`)
- `Photon.Voice.Unity.Recorder`
- `Photon.Voice.Unity.Speaker`

If you also use the integration with PUN 2, we added two components for ease-of-use and more convenience:

- `Photon.Voice.PUN.PhotonVoiceNetwork`
- `Photon.Voice.PUN.PhotonVoiceView`

Photon Voice 2 also comes with a WebRTC based DSP (`Photon.Voice.Unity.WebRtcAudioDsp` using `Photon.Voice.WebRTCAudioProcessor`).

Read more in the official documentation [here](#).

You can download Photon Voice 2 [here](#).

Chapter 2

Namespace Documentation

2.1 Photon Namespace Reference

2.2 Photon.Voice Namespace Reference

Classes

- class [AudioDesc](#)
- class [AudioInChangeNotifierNotSupported](#)
- class **AudioInEnumeratorNotSupported**
- class [AudioOutDelayControl](#)
- class [AudioOutDummy](#)
- class [AudioSyncBuffer](#)
- class [AudioUtil](#)
Collection of Audio Utility functions and classes.
- class [BufferReaderPushAdapterAsyncPool](#)
BufferReaderPushAdapter<T> implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#).
- class [BufferReaderPushAdapterAsyncPoolFloatToShort](#)
BufferReaderPushAdapter<T> implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#), converting float samples to short.
- class [BufferReaderPushAdapterAsyncPoolShortToFloat](#)
BufferReaderPushAdapter<T> implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#), converting short samples to float.
- class [BufferReaderPushAdapterBase](#)
Adapter base reading data from [IDataReader<T>.Read](#) and pushing it to [LocalVoice](#).
- class [DeviceEnumeratorBase](#)
- class **DeviceEnumeratorNotSupported**
- class **DeviceEnumeratorSingleDevice**
- class [DeviceFeatures](#)
- struct [DeviceInfo](#)
- class [FactoryPrimitiveArrayPool](#)
PrimitiveArrayPool<T> as wrapped in object factory interface.
- class [FactoryReusableArray](#)
Array factory returnig the same array instance as long as it requested with the same array length. If length changes, new array instance created.
- struct [Flip](#)

- struct [FrameBuffer](#)
- class [FrameOut](#)
- class [Framer](#)
 - Utility class to re-frame packets.*
- class [FramerResampler](#)
- interface [IAudioDesc](#)
 - Audio Source interface.*
- interface [IAudioInChangeNotifier](#)
- interface [IAudioOut](#)
- interface [IAudioPusher](#)
 - Audio Pusher interface.*
- interface [IAudioReader](#)
 - Audio Reader interface.*
- interface [IDataReader](#)
 - Interface for pulling data, in case this is more appropriate than pushing it.*
- interface [IDecoder](#)
 - Generic decoder interface.*
- interface [IDecoderDirect](#)
 - Interface for an decoder which outputs data via explicit call.*
- interface [IDeviceEnumerator](#)
- interface [IEncoder](#)
 - Generic encoder interface.*
- interface [IEncoderDirect](#)
 - Interface for an encoder which consumes input data via explicit call.*
- interface [IEncoderDirectImage](#)
 - Interface for an encoder which consumes images via explicit call.*
- interface [ILocalVoiceAudio](#)
 - Interface for an outgoing audio stream.*
- interface [ILogger](#)
- struct [ImageBufferInfo](#)
- class [ImageBufferNative](#)
- class [ImageBufferNativeAlloc](#)
- class [ImageBufferNativeGCHandleBytes](#)
- class [ImageBufferNativeGCHandleSinglePlane](#)
- class [ImageBufferNativePool](#)
- interface [IProcessor](#)
 - Processor interface.*
- interface [IResettable](#)
- interface [IServiceable](#)
 - Interface for classes that want their [Service\(\)](#) function to be called regularly in the context of a [LocalVoice](#).*
- interface [IVoiceTransport](#)
- class [LoadBalancingTransport](#)
 - Extends [LoadBalancingClient](#) with media streaming functionality.*
- class [LoadBalancingTransport2](#)
 - Variant of [LoadBalancingTransport](#). Aims to be non-alloc at the cost of breaking compatibility with older clients.*
- class [LocalVoice](#)
 - Represents outgoing data stream.*
- class [LocalVoiceAudio](#)
 - Outgoing audio stream.*
- class [LocalVoiceAudioDummy](#)
 - Dummy [LocalVoiceAudio](#)*
- class [LocalVoiceAudioFloat](#)

- Specialization of LocalVoiceAudio<T> for float audio*
- class [LocalVoiceAudioShort](#)
 - Specialization of LocalVoiceAudio<T> for short audio*
- class [LocalVoiceFramed](#)
 - Typed re-framing [LocalVoice](#)*
- class [MonoPInvokeCallbackAttribute](#)
- interface [ObjectFactory](#)
 - Uniform interface to ObjectPool<TType, TInfo> and single reusable object.*
- class [ObjectPool](#)
 - Generic Pool to re-use objects of a certain type (TType) that optionally match a certain property or set of properties (TInfo).*
- class [OpusCodec](#)
- class [PhotonAppSettings](#)
 - Collection of connection-relevant settings, used internally by PhotonNetwork.ConnectUsingSettings.*
- class **PhotonTransportProtocol**
- class [Platform](#)
- class [PrimitiveArrayPool](#)
 - Pool of Arrays with components of type T, with [ObjectPool](#) info being the array's size.*
- class [RawCodec](#)
- class **RemoteVoice**
- class [RemoteVoiceInfo](#)
 - Information about a remote voice (incoming stream).*
- struct [RemoteVoiceOptions](#)
 - Event Actions and other options for a remote voice (incoming stream).*
- struct [SendFrameParams](#)
- class **SpacingProfile**
- class [UnsupportedCodecException](#)
 - Exception thrown if an unsupported codec is encountered.*
- class [UnsupportedPlatformException](#)
 - Exception thrown if an unsupported platform is encountered.*
- class [UnsupportedSampleTypeException](#)
 - Exception thrown if an unsupported audio sample type is encountered.*
- class **Util**
- class **VideoInEnumeratorNotSupported**
- class [VoiceClient](#)
 - Voice client interact with other clients on network via [IVoiceTransport](#).*
- struct [VoiceCreateOptions](#)
 - Used to initialize optional properties of the [LocalVoice](#) instance at creation time.*
- class [VoiceEvent](#)
- struct [VoiceInfo](#)
 - Describes stream properties.*
- class [WebRTCAudioLib](#)
- class [WebRTCAudioProcessor](#)

Enumerations

- enum **CameraFacing**
- enum [AudioSampleType](#)
 - The type of samples used for audio processing.*
- enum **FrameFlags** : byte
- enum [Codec](#)
 - Enum for Media Codecs supported by PhotonVoice.*
- enum **ImageFormat**
- enum **Rotation**

2.2.1 Enumeration Type Documentation

2.2.1.1 AudioSampleType

```
enum AudioSampleType [strong]
```

The type of samples used for audio processing.

2.2.1.2 Codec

```
enum Codec [strong]
```

Enum for Media Codecs supported by PhotonVoice.

Transmitted in [VoiceInfo](#). Do not change the values of this Enum!

Enumerator

AudioOpus	OPUS audio
-----------	------------

2.3 Photon.Voice.FMOD Namespace Reference

Classes

- class [AudioInEnumerator](#)
- class [AudioInReader](#)
- class [AudioOut](#)
- class [AudioOutEvent](#)

2.4 Photon.Voice.Fusion Namespace Reference

Classes

- class [FusionVoiceClient](#)
- class [VoiceNetworkObject](#)

Typedefs

- using **PhotonAppSettings** = global::Fusion.Photon.Realtime.PhotonAppSettings

2.5 Photon.Voice.IOS Namespace Reference

Classes

- class [AudioInChangeNotifier](#)
- class [AudioInPusher](#)
- class [AudioInReader](#)
- struct [AudioSessionParameters](#)
- class [AudioSessionParametersPresets](#)

Enumerations

- enum [AudioSessionCategory](#)
- enum [AudioSessionMode](#)
- enum [AudioSessionCategoryOption](#)

2.5.1 Enumeration Type Documentation

2.5.1.1 AudioSessionCategory

enum [AudioSessionCategory](#) [strong]

Enumerator

Ambient	Use this category for background sounds such as rain, car engine noise, etc. Mixes with other music. API_AVAILABLE(ios(3.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
SoloAmbient	Use this category for background sounds. Other music will stop playing. API_AVAILABLE(ios(3.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
Playback	Use this category for music tracks. API_AVAILABLE(ios(3.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
Record	Use this category when recording audio. API_AVAILABLE(ios(3.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
PlayAndRecord	Use this category when recording and playing back audio. API_AVAILABLE(ios(3.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
AudioProcessing	Use this category when using a hardware codec or signal processor while not playing or recording audio. API_DEPRECATED("No longer supported", ios(3.0, 10.0)) API_UNAVAILABLE(watchos, tvos) API_UNAVAILABLE(macos);
MultiRoute	Use this category to customize the usage of available audio accessories and built-in audio hardware. For example, this category provides an application with the ability to use an available USB output and headphone output simultaneously for separate, distinct streams of audio data. Use of this category by an application requires a more detailed knowledge of, and interaction with, the capabilities of the available audio routes. May be used for input, output, or both. Note that not all output types and output combinations are eligible for multi-route. Input is limited to the last-in input port. Eligible inputs consist of the following: AVAudioSessionPortUSBAudio, AVAudioSessionPortHeadsetMic, and AVAudioSessionPortBuiltInMic. Eligible outputs consist of the following: AVAudioSessionPortUSBAudio, AVAudioSessionPortLineOut, AVAudioSessionPortHeadphones, AVAudioSessionPortHDMI, and AVAudioSessionPortBuiltInSpeaker. Note that AVAudioSessionPortBuiltInSpeaker is only allowed to be used when there are no other eligible outputs connected. API_AVAILABLE(ios(6.0), watchos(2.0), tvos(9.0)) API_UNAVAILABLE(macos);
Generated by Doxygen	

2.5.1.2 AudioSessionCategoryOption

enum `AudioSessionCategoryOption` [strong]

Enumerator

MixWithOthers	This allows an application to set whether or not other active audio apps will be interrupted or mixed with when your app's audio session goes active. The typical cases are: (1) <code>AVAudioSessionCategoryPlayAndRecord</code> or <code>AVAudioSessionCategoryMultiRoute</code> this will default to false, but can be set to true. This would allow other applications to play in the background while an app had both audio input and output enabled (2) <code>AVAudioSessionCategoryPlayback</code> this will default to false, but can be set to true. This would allow other applications to play in the background, but an app will still be able to play regardless of the setting of the ringer switch (3) Other categories this defaults to false and cannot be changed (that is, the mix with others setting of these categories cannot be overridden. An application must be prepared for setting this property to fail as behaviour may change in future releases. If an application changes their category, they should reassert the option (it is not sticky across category changes). <code>MixWithOthers</code> is only valid with <code>AVAudioSessionCategoryPlayAndRecord</code> , <code>AVAudioSessionCategoryPlayback</code> , and <code>AVAudioSessionCategoryMultiRoute</code>
DuckOthers	This allows an application to set whether or not other active audio apps will be ducked when when your app's audio session goes active. An example of this is the Nike app, which provides periodic updates to its user (it reduces the volume of any music currently being played while it provides its status). This defaults to off. Note that the other audio will be ducked for as long as the current session is active. You will need to deactivate your audio session when you want full volume playback of the other audio. If your category is <code>AVAudioSessionCategoryPlayback</code> , <code>AVAudioSessionCategoryPlayAndRecord</code> , or <code>AVAudioSessionCategoryMultiRoute</code> , by default the audio session will be non-mixable and non-ducking. Setting this option will also make your category mixable with others (<code>AVAudioSessionCategoryOptionMixWithOthers</code> will be set). <code>DuckOthers</code> is only valid with <code>AVAudioSessionCategoryAmbient</code> , <code>AVAudioSessionCategoryPlayAndRecord</code> , <code>AVAudioSessionCategoryPlayback</code> , and <code>AVAudioSessionCategoryMultiRoute</code>
AllowBluetooth	This allows an application to change the default behaviour of some audio session categories with regards to showing bluetooth Hands-Free Profile (HFP) devices as available routes. The current category behavior is: (1) <code>AVAudioSessionCategoryPlayAndRecord</code> this will default to false, but can be set to true. This will allow a paired bluetooth HFP device to show up as an available route for input, while playing through the category-appropriate output (2) <code>AVAudioSessionCategoryRecord</code> this will default to false, but can be set to true. This will allow a paired bluetooth HFP device to show up as an available route for input (3) Other categories this defaults to false and cannot be changed (that is, enabling bluetooth for input in these categories is not allowed) An application must be prepared for setting this option to fail as behaviour may change in future releases. If an application changes their category or mode, they should reassert the override (it is not sticky across category and mode changes). <code>AllowBluetooth</code> is only valid with <code>AVAudioSessionCategoryRecord</code> and <code>AVAudioSessionCategoryPlayAndRecord</code>
DefaultToSpeaker	This allows an application to change the default behaviour of some audio session categories with regards to the audio route. The current category behavior is: (1) <code>AVAudioSessionCategoryPlayAndRecord</code> category this will default to false, but can be set to true. this will route to Speaker (instead of Receiver) when no other audio route is connected. (2) Other categories this defaults to false and cannot be changed (that is, the default to speaker setting of these categories cannot be overridden An application must be prepared for setting this property to fail as behaviour may change in future releases. If an application changes their category, they should reassert the override (it is not sticky across category and mode changes). <code>DefaultToSpeaker</code> is only valid with <code>AVAudioSessionCategoryPlayAndRecord</code>

2.5.1.3 AudioSessionMode

enum [AudioSessionMode](#) [strong]

Enumerator

Default	Modes modify the audio category in order to introduce behavior that is tailored to the specific use of audio within an application. Available in iOS 5.0 and greater. The default mode <code>API_AVAILABLE(ios(5.0), watchos(2.0), tvos(9.0))</code> <code>API_UNAVAILABLE(macos)</code> ;
VoiceChat	Only valid with <code>AVAudioSessionCategoryPlayAndRecord</code> . Appropriate for Voice over IP (VoIP) applications. Reduces the number of allowable audio routes to be only those that are appropriate for VoIP applications and may engage appropriate system-supplied signal processing. Has the side effect of setting <code>AVAudioSessionCategoryOptionAllowBluetooth</code> <code>API_AVAILABLE(ios(5.0), watchos(2.0), tvos(9.0))</code> <code>API_UNAVAILABLE(macos)</code> ;
VideoRecording	Only valid with <code>AVAudioSessionCategoryPlayAndRecord</code> or <code>AVAudioSessionCategoryRecord</code> . Modifies the audio routing options and may engage appropriate system-supplied signal processing. <code>API_AVAILABLE(ios(5.0), watchos(2.0), tvos(9.0))</code> <code>API_UNAVAILABLE(macos)</code> ;
Measurement	Appropriate for applications that wish to minimize the effect of system-supplied signal processing for input and/or output audio signals. <code>API_AVAILABLE(ios(5.0), watchos(2.0), tvos(9.0))</code> <code>API_UNAVAILABLE(macos)</code> ;
MoviePlayback	Engages appropriate output signal processing for movie playback scenarios. Currently only applied during playback over built-in speaker. <code>API_AVAILABLE(ios(6.0), watchos(2.0), tvos(9.0))</code> <code>API_UNAVAILABLE(macos)</code> ;
VideoChat	Only valid with <code>kAudioSessionCategory_PlayAndRecord</code> . Reduces the number of allowable audio routes to be only those that are appropriate for video chat applications. May engage appropriate system-supplied signal processing. Has the side effect of setting <code>AVAudioSessionCategoryOptionAllowBluetooth</code> and <code>AVAudioSessionCategoryOptionDefaultToSpeaker</code> . <code>API_AVAILABLE(ios(7.0), watchos(2.0), tvos(9.0))</code> <code>API_UNAVAILABLE(macos)</code> ;

2.6 Photon.Voice.MacOS Namespace Reference

Classes

- class [AudioInChangeNotifier](#)
- class [AudioInEnumerator](#)
Enumerates microphones available on device.
- class [AudioInPusher](#)
- class [AudioInReader](#)

2.7 Photon.Voice.PUN Namespace Reference

Classes

- class [PhotonVoiceView](#)

Component that should be attached to a networked [PUN](#) prefab that has [PhotonView](#). It will bind remote [Recorder](#) with local [Speaker](#) of the same networked prefab. This component makes automatic voice stream routing easy for players' characters/avatars.

- class [PunVoiceClient](#)

This class can be used to automatically sync client states between [PUN](#) and [Voice](#). It also finds the [Speaker](#) component for a character's voice. For this to work attach a [PhotonVoiceView](#) next to the [PhotonView](#) of your player's prefab.

2.8 Photon.Voice.PUN.UtilityScripts Namespace Reference

Classes

- class [VoiceDebugScript](#)

Utility script to be attached next to [PhotonVoiceView](#) & [PhotonView](#) on the player prefab to be network instantiated. Call `voiceDebugScript.CantHearYou()` on the networked object of the remote (or local) player if you can't hear the corresponding player.

2.9 Photon.Voice.Unity Namespace Reference

Classes

- class [AndroidAudioInAEC](#)
- struct [AndroidAudioInParameters](#)
- class [AudioChangesHandler](#)

This component is useful to handle audio device and config changes.

- class [AudioClipWrapper](#)
- class [AudioInEnumerator](#)
- class [AudioOutCapture](#)
- class [Logger](#)
- class [MicWrapper](#)
- class [MicWrapperPusher](#)
- class [MicWrapperPusherOnAudioFilterRead](#)
- class [PhotonVoiceCreatedParams](#)
- class [Recorder](#)

Component representing outgoing audio stream in scene.

- class [RecorderPreset](#)
- class [RemoteVoiceLink](#)
- class [Speaker](#)
- class [SpeakerAudioFilterRead](#)
- class [UnityAudioOut](#)
- class [UnityLogger](#)
- class [UnityMicrophone](#)

A wrapper around `UnityEngine.Microphone` to be able to safely use `Microphone` and compile for WebGL.

- class [UnityVoiceClient](#)

Component that represents a [Voice](#) client and manages a simple [Unity](#) integration: a single [Recorder](#) and multiple remote speakers.

- class [VideoInEnumerator](#)
- class [VoiceComponent](#)
- class [VoiceComponentImpl](#)
- class [VoiceConnection](#)

Component that represents a [Voice](#) client.

- class [VoiceLogger](#)
- class [WebRtcAudioDsp](#)

2.10 Photon.Voice.Unity.FMOD Namespace Reference

Classes

- class [FMODRecorderSetup](#)
- class [SpeakerFMOD](#)

2.11 Photon.Voice.Unity.UtilityScripts Namespace Reference

Classes

- class [ConnectAndJoin](#)
- class [MicAmplifier](#)
- class [MicAmplifierFloat](#)
- class [MicAmplifierShort](#)
- class [MicrophonePermission](#)
Helper to request Microphone permission on Android or iOS.
- class [PhotonVoiceLagSimulationGui](#)
- class [PhotonVoiceStatsGui](#)
Basic GUI to show traffic and health statistics of the connection to [Photon](#), toggled by shift+tab.
- class [SaveIncomingStreamToFile](#)
- class [SaveOutgoingStreamToFile](#)
- class [TestTone](#)
- class [WaveWriter](#)

2.12 Photon.Voice.UWP Namespace Reference

Classes

- class [AudioInEnumerator](#)
- class [AudioInPusher](#)
- class [CaptureDevice](#)
- class [DeviceEnumerator](#)
- class [VideoInEnumerator](#)

Functions

- delegate void **MediaCaptureInitCompleted** (MediaCapture mediaCpture, bool ok)

2.13 Photon.Voice.Windows Namespace Reference

Classes

- class [AudioInEnumerator](#)
Enumerates microphones available on device.
- class [WindowsAudioInPusher](#)

Chapter 3

Class Documentation

3.1 AndroidAudioInAEC Class Reference

Inherits [IAudioPusher< short >](#), and [IResettable](#).

Public Member Functions

- **AndroidAudioInAEC** ([Voice.ILogger](#) logger, bool enableAEC=false, bool enableAGC=false, bool enableNS=false)
- void **SetCallback** (Action< short[]> callback, [ObjectFactory](#)< short[], int > bufferFactory)
- void **Reset** ()
- void **Dispose** ()

Properties

- int **Channels** [get]
- int **SamplingRate** [get]
- string **Error** [get]

3.2 AndroidAudioInParameters Struct Reference

Public Attributes

- bool **EnableAEC**
- bool **EnableAGC**
- bool **EnableNS**

Static Public Attributes

- static [AndroidAudioInParameters](#) **Default** = new [AndroidAudioInParameters](#)() { EnableAEC = true, EnableAGC = true, EnableNS = true }

3.3 AudioChangesHandler Class Reference

This component is useful to handle audio device and config changes.

Inherits [VoiceComponent](#).

Public Attributes

- bool [HandleDeviceChange](#) = true
Try to react to device change notification when [Recorder](#) is started.
- bool [HandleDeviceChangeIOS](#)
iOS: Try to react to device change notification when [Recorder](#) is started.
- bool [HandleDeviceChangeAndroid](#)
Android: Try to react to device change notification when [Recorder](#) is started.

Protected Member Functions

- override void **Awake** ()

Additional Inherited Members

3.3.1 Detailed Description

This component is useful to handle audio device and config changes.

3.3.2 Member Data Documentation

3.3.2.1 HandleDeviceChange

```
bool HandleDeviceChange = true
```

Try to react to device change notification when [Recorder](#) is started.

3.3.2.2 HandleDeviceChangeAndroid

```
bool HandleDeviceChangeAndroid
```

Android: Try to react to device change notification when [Recorder](#) is started.

3.3.2.3 HandleDeviceChangeIOS

```
bool HandleDeviceChangeIOS
```

iOS: Try to react to device change notification when [Recorder](#) is started.

3.4 AudioClipWrapper Class Reference

Inherits [IAudioReader< float >](#).

Public Member Functions

- **AudioClipWrapper** (AudioClip audioClip)
- bool **Read** (float[] buffer)
- void **Dispose** ()

Properties

- bool **Loop** [get, set]
- int **SamplingRate** [get]
- int **Channels** [get]
- string **Error** [get]

3.5 AudioDesc Class Reference

Inherits [IAudioDesc](#).

Public Member Functions

- **AudioDesc** (int samplingRate, int channels, string error)
- void **Dispose** ()

Properties

- int **SamplingRate** [get]
- int **Channels** [get]
- string **Error** [get]

3.6 AudioInChangeNotifier Class Reference

Inherits [IAudioInChangeNotifier](#).

Public Member Functions

- **AudiolnChangeNotifier** (Action callback, [ILogger](#) logger)
- void [Dispose](#) ()

Disposes enumerator. Call it to free native resources.

Public Attributes

- bool **IsSupported** => true

Properties

- string [Error](#) [get]

If not null, the enumerator is in invalid state.

3.6.1 Member Function Documentation

3.6.1.1 Dispose()

```
void Dispose ( )
```

Disposes enumerator. Call it to free native resources.

3.6.2 Property Documentation

3.6.2.1 Error

```
string Error [get]
```

If not null, the enumerator is in invalid state.

3.7 AudiolnChangeNotifier Class Reference

Inherits [IAudiolnChangeNotifier](#).

Public Member Functions

- **AudiolnChangeNotifier** (Action callback, [ILogger](#) logger)
- void [Dispose](#) ()

Disposes enumerator. Call it to free native resources.

Public Attributes

- bool **IsSupported** => true

Properties

- string **Error** [get]
If not null, the enumerator is in invalid state.

3.7.1 Member Function Documentation

3.7.1.1 Dispose()

```
void Dispose ( )
```

Disposes enumerator. Call it to free native resources.

3.7.2 Property Documentation

3.7.2.1 Error

```
string Error [get]
```

If not null, the enumerator is in invalid state.

3.8 AudioInChangeNotifierNotSupported Class Reference

Inherits [IAudioInChangeNotifier](#).

Public Member Functions

- **AudioInChangeNotifierNotSupported** (Action callback, [ILogger](#) logger)
- void **Dispose** ()

Public Attributes

- bool **IsSupported** => false

Properties

- string **Error** [get]

3.9 AudioInEnumerator Class Reference

Enumerates microphones available on device.

Inherits [DeviceEnumeratorBase](#).

Public Member Functions

- **AudioInEnumerator** ([ILogger](#) logger)
- override void [Refresh](#) ()
Refreshes the microphones list.
- override void [Dispose](#) ()
Disposes enumerator. Call it to free native resources.

Additional Inherited Members

3.9.1 Detailed Description

Enumerates microphones available on device.

3.9.2 Member Function Documentation

3.9.2.1 Dispose()

```
override void Dispose ( ) [virtual]
```

Disposes enumerator. Call it to free native resources.

Implements [DeviceEnumeratorBase](#).

3.9.2.2 Refresh()

```
override void Refresh ( ) [virtual]
```

Refreshes the microphones list.

Implements [DeviceEnumeratorBase](#).

3.10 AudioInEnumerator Class Reference

Inherits [DeviceEnumeratorBase](#).

Public Member Functions

- **AudioInEnumerator** (FMODLib.System coreSystem, [ILogger](#) logger)
- override void **Refresh** ()
- override void **Dispose** ()

Additional Inherited Members

3.11 AudioInEnumerator Class Reference

Inherits [DeviceEnumeratorBase](#).

Public Member Functions

- **AudioInEnumerator** ([ILogger](#) logger)
- override void **Refresh** ()
- override void **Dispose** ()

Public Attributes

- override bool **IsSupported** => false

Properties

- override string **Error** [get]

Additional Inherited Members

3.12 AudioInEnumerator Class Reference

Inherits [DeviceEnumerator](#).

Public Member Functions

- **AudioInEnumerator** ([ILogger](#) logger)

Additional Inherited Members

3.13 AudiInEnumerator Class Reference

Enumerates microphones available on device.

Inherits [DeviceEnumeratorBase](#).

Public Member Functions

- **AudiInEnumerator** ([ILogger](#) logger)
- override void [Refresh](#) ()
Refreshes the microphones list.
- override void [Dispose](#) ()
Disposes enumerator. Call it to free native resources.

Additional Inherited Members

3.13.1 Detailed Description

Enumerates microphones available on device.

3.13.2 Member Function Documentation

3.13.2.1 Dispose()

```
override void Dispose ( ) [virtual]
```

Disposes enumerator. Call it to free native resources.

Implements [DeviceEnumeratorBase](#).

3.13.2.2 Refresh()

```
override void Refresh ( ) [virtual]
```

Refreshes the microphones list.

Implements [DeviceEnumeratorBase](#).

3.14 AudioInPusher Class Reference

Inherits [IAudioPusher< float >](#).

Public Member Functions

- **AudioInPusher** (int deviceId, [ILogger](#) logger)
- void **SetCallback** (Action< float[]> callback, [ObjectFactory](#)< float[], int > bufferFactory)
- void **Dispose** ()

Properties

- int **Channels** [get]
- int **SamplingRate** [get]
- string **Error** [get]

3.15 AudioInPusher Class Reference

Inherits [IAudioPusher< float >](#), and [IResettable](#).

Public Member Functions

- **AudioInPusher** ([AudioSessionParameters](#) sessParam, [ILogger](#) logger)
- void **SetCallback** (Action< float[]> callback, [ObjectFactory](#)< float[], int > bufferFactory)
- void **Reset** ()
- void **Dispose** ()

Properties

- int **Channels** [get]
- int **SamplingRate** [get]
- string **Error** [get]

3.16 AudioInPusher Class Reference

Inherits [IAudioPusher< short >](#).

Public Member Functions

- **AudioInPusher** ([ILogger](#) logger, int samplingRate, int channels, string deviceId)
- void **SetCallback** (Action< short[]> callback, [ObjectFactory](#)< short[], int > bufferFactory)
- ArraySegment< byte > **DequeueOutput** (out FrameFlags flags)
- void **EndOfStream** ()
- I **GetPlatformAPI**< I > ()
- void **Dispose** ()

Properties

- int **SamplingRate** [get]
- int **Channels** [get]
Number of channels in the audio signal.
- string **Error** [get]
- bool **ErrorAccess** [get]

3.16.1 Property Documentation

3.16.1.1 Channels

int Channels [get]

Number of channels in the audio signal.

3.17 AudiInReader Class Reference

Inherits [IAudioReader< float >](#), and [IResettable](#).

Public Member Functions

- **AudiInReader** ([AudioSessionParameters](#) sessParam, [ILogger](#) logger)
- void **Reset** ()
- void **Dispose** ()
- bool **Read** (float[] buf)

Properties

- int **Channels** [get]
- int **SamplingRate** [get]
- string **Error** [get]

3.18 AudiInReader Class Reference

Inherits [IAudioReader< float >](#).

Public Member Functions

- **AudiInReader** (int deviceId, [ILogger](#) logger)
- void **Dispose** ()
- bool **Read** (float[] buf)

Properties

- int **Channels** [get]
- int **SamplingRate** [get]
- string **Error** [get]

3.19 AudioInReader< T > Class Template Reference

Inherits [IAudioReader< T >](#).

Public Member Functions

- **AudioInReader** (FMODLib.System coreSystem, int device, int suggestedFrequency, [ILogger](#) logger)
- void **Dispose** ()
- bool **Read** (T[] readBuf)

Fill full given frame buffer with source uncompressed data or return false if not enough such data.

Public Attributes

- bool **isRecording**

Properties

- int? **SamplingRate** [get]
- int? **Channels** [get]
- string **Error** [get]

3.19.1 Member Function Documentation

3.19.1.1 Read()

```
bool Read (
    T[] buffer )
```

Fill full given frame buffer with source uncompressed data or return false if not enough such data.

Parameters

<i>buffer</i>	Buffer to fill.
---------------	-----------------

Returns

True if buffer was filled successfully, false otherwise.

Implements [IDataReader< T >](#).

3.20 AudioOut< T > Class Template Reference

Inherits [AudioOutDelayControl< T >](#).

Inherited by [AudioOutEvent< T >](#).

Public Member Functions

- **AudioOut** (FMODLib.System coreSystem, PlayDelayConfig playDelayConfig, [ILogger](#) logger, string logPrefix, bool debugInfo)
- override void **OutCreate** (int samplingRate, int channels, int bufferSamples)
- override void **OutStart** ()
- override void **OutWrite** (T[] frame, int offsetSamples)
- override void **Stop** ()

Protected Attributes

- int **channels**
- int **frequency**

Properties

- FMODLib.Sound **Sound** [get]
- FMODLib.Channel **Channel** [get]
- override long **OutPos** [get]
- string **Error** [get]

3.21 AudioOutCapture Class Reference

Inherits MonoBehaviour.

Events

- Action< float[], int > **OnAudioFrame**

3.22 AudioOutDelayControl Class Reference

Inherited by [AudioOutDelayControl< T >](#).

Classes

- struct [PlayDelayConfig](#)

3.23 AudioOutDelayControl Class Reference

Inherited by [AudioOutDelayControl< T >](#).

Classes

- struct [PlayDelayConfig](#)

3.24 AudioOutDummy< T > Class Template Reference

Inherits [IAudioOut< T >](#).

Public Member Functions

- void **Flush** ()
- void **Push** (T[] frame)
- void **Service** ()
- void **Start** (int frequency, int channels, int frameSamplesPerChannel)
- void **Stop** ()

Public Attributes

- bool **IsPlaying** => false
- int **Lag** => 0

Additional Inherited Members

3.25 AudioOutEvent< T > Class Template Reference

Inherits [AudioOut< T >](#).

Public Member Functions

- **AudioOutEvent** (FMODLib.System coreSystem, FMODLib.Studio.EventInstance fmodEvent, PlayDelayConfig playDelayConfig, [ILogger](#) logger, string logPrefix, bool debugInfo)
- override void **OutStart** ()
- override void **Stop** ()

Properties

- override long **OutPos** [get]

Additional Inherited Members

3.26 AudioSessionParameters Struct Reference

Public Member Functions

- int **CategoryOptionsToInt** ()
- override string **ToString** ()

Public Attributes

- [AudioSessionCategory](#) **Category**
- [AudioSessionMode](#) **Mode**
- [AudioSessionCategoryOption](#)[] **CategoryOptions**

3.27 AudioSessionParametersPresets Class Reference

Static Public Attributes

- static [AudioSessionParameters](#) **Game**
- static [AudioSessionParameters](#) **VoIP**

3.27.1 Member Data Documentation

3.27.1.1 Game

[AudioSessionParameters](#) **Game** [static]

Initial value:

```
= new AudioSessionParameters()
{
    Category = AudioSessionCategory.PlayAndRecord,
    Mode = AudioSessionMode.Default,
    CategoryOptions = new AudioSessionCategoryOption[] {
        AudioSessionCategoryOption.DefaultToSpeaker, AudioSessionCategoryOption.AllowBluetooth }
}
```

3.27.1.2 VoIP

```
AudioSessionParameters VoIP [static]
```

Initial value:

```
= new AudioSessionParameters()
{
    Category = AudioSessionCategory.PlayAndRecord,
    Mode = AudioSessionMode.VoiceChat,

    CategoryOptions = new AudioSessionCategoryOption[] { AudioSessionCategoryOption.AllowBluetooth }
}
```

3.28 AudioSyncBuffer< T > Class Template Reference

Inherits [AudioOutDelayControl< T >](#).

Public Member Functions

- **AudioSyncBuffer** (PlayDelayConfig playDelayConfig, [ILogger](#) logger, string logPrefix, bool debugInfo)
- override void **OutCreate** (int frequency, int channels, int bufferSamples)
- override void **OutStart** ()
- override void **OutWrite** (T[] data, int offsetSamples)
- override void **Stop** ()
- void **Read** (T[] outBuf, int outChannels, int outSampleRate)

Public Attributes

- override long **OutPos** => readPosSamples

3.29 AudioUtil Class Reference

Collection of Audio Utility functions and classes.

Classes

- class [GeneratorPusher](#)
IAudioPusher that provides a constant tone signal.
- class [GeneratorReader](#)
- interface [ILevelMeter](#)
Audio Level Metering interface.
- interface [IVoiceDetector](#)
Voice Activity Detector interface.
- class [LevelMeter](#)
Audio Level Meter.
- class [LevelMeterDummy](#)
Dummy Audio Level Meter that doesn't actually do anything.
- class [LevelMeterFloat](#)

- *LevelMeter* specialization for float audio.
- class [LevelMeterShort](#)
LevelMeter specialization for short audio.
- class [Resampler](#)
Sample-rate conversion Audio Processor.
- class [TempoUp](#)
- class [ToneAudioPusher](#)
IAudioPusher that provides a constant tone signal.
- class [ToneAudioReader](#)
IAudioReader that provides a constant tone signal.
- class [VoiceDetector](#)
Simple voice activity detector triggered by signal level.
- class [VoiceDetectorCalibration](#)
Calibration Utility for Voice Detector
- class [VoiceDetectorDummy](#)
Dummy VoiceDetector that doesn't actually do anything.
- class [VoiceDetectorFloat](#)
VoiceDetector specialization for float audio.
- class [VoiceDetectorShort](#)
VoiceDetector specialization for float audio.
- class [VoiceLevelDetectCalibrate](#)
Utility Audio Processor Voice Detection Calibration.
- class [WaveformAudioPusher](#)
IAudioPusher that provides the given waveform.
- class [WaveformAudioReader](#)
IAudioReader that provides the given waveform.

Static Public Member Functions

- static int **ToneToBuf**< T > (T[] buf, long timeSamples, int channels, double amp, double k, double phase↔ Mod=0)
- static int **ToneToBuf**< T > (T[] buf, int offset, int length, long timeSamples, int channels, double amp, double k, double phaseMod=0)
- static int **WaveformToBuf**< T > (T[] buf, T[] waveform, long timePos)
- static void **Resample**< T > (T[] src, T[] dst, int dstCount, int channels)
Resample audio data so that the complete src buffer fits into dstCount samples in the dst buffer.
- static void **Resample**< T > (T[] src, int srcOffset, int srcCount, T[] dst, int dstOffset, int dstCount, int channels)
- static void **Resample**< T > (T[] src, int srcOffset, int srcCount, int srcChannels, T[] dst, int dstOffset, int dstCount, int dstChannels)
- static void **ResampleAndConvert** (short[] src, float[] dst, int dstCount, int channels)
Resample audio data so that the complete src buffer fits into dstCount samples in the dst buffer, and convert short to float samples along the way.
- static void **ResampleAndConvert** (float[] src, short[] dst, int dstCount, int channels)
Resample audio data so that the complete src buffer fits into dstCount samples in the dst buffer, and convert float to short samples along the way.
- static void **Convert** (float[] src, short[] dst, int dstCount)
Convert audio buffer from float to short samples.
- static void **Convert** (short[] src, float[] dst, int dstCount)
Convert audio buffer from short to float samples.
- static void **ForceToStereo**< T > (T[] src, T[] dst, int srcChannels)
Convert audio buffer with arbitrary number of channels to stereo.

3.29.1 Detailed Description

Collection of Audio Utility functions and classes.

3.29.2 Member Function Documentation

3.29.2.1 Convert() [1/2]

```
static void Convert (
    float[] src,
    short[] dst,
    int dstCount ) [static]
```

Convert audio buffer from float to short samples.

Parameters

<i>src</i>	Source buffer.
<i>dst</i>	Destination buffer.
<i>dstCount</i>	Size of destination buffer (in total samples), source buffer must be of same length or longer.

3.29.2.2 Convert() [2/2]

```
static void Convert (
    short[] src,
    float[] dst,
    int dstCount ) [static]
```

Convert audio buffer from short to float samples.

Parameters

<i>src</i>	Source buffer.
<i>dst</i>	Destination buffer.
<i>dstCount</i>	Size of destination buffer (in total samples), source buffer must be of same length or longer.

3.29.2.3 ForceToStereo< T >()

```
static void ForceToStereo< T > (
    T[] src,
```

```
T[] dst,
int srcChannels ) [static]
```

Convert audio buffer with arbitrary number of channels to stereo.

For mono sources (`srcChannels==1`), the signal will be copied to both Left and Right stereo channels. For all others, the first two available channels will be used, any other channels will be discarded.

Parameters

<i>src</i>	Source buffer.
<i>dst</i>	Destination buffer.
<i>srcChannels</i>	Number of (interleaved) channels in src.

3.29.2.4 Resample< T >()

```
static void Resample< T > (
    T[] src,
    T[] dst,
    int dstCount,
    int channels ) [static]
```

Resample audio data so that the complete src buffer fits into dstCount samples in the dst buffer.

This implements a primitive nearest-neighbor resampling algorithm for an arbitrary number of channels.

Parameters

<i>src</i>	Source buffer.
<i>dst</i>	Destination buffer.
<i>dstCount</i>	Target size of destination buffer (in samples per channel).
<i>channels</i>	Number of channels in the signal (1=mono, 2=stereo). Must be > 0.

3.29.2.5 ResampleAndConvert() [1/2]

```
static void ResampleAndConvert (
    float[] src,
    short[] dst,
    int dstCount,
    int channels ) [static]
```

Resample audio data so that the complete src buffer fits into dstCount samples in the dst buffer, and convert float to short samples along the way.

This implements a primitive nearest-neighbor resampling algorithm for an arbitrary number of channels.

Parameters

<i>src</i>	Source buffer.
<i>dst</i>	Destination buffer.
<i>dstCount</i>	Target size of destination buffer (in samples per channel).
<i>channels</i>	Number of channels in the signal (1=mono, 2=stereo). Must be > 0.

3.29.2.6 ResampleAndConvert() [2/2]

```
static void ResampleAndConvert (
    short[] src,
    float[] dst,
    int dstCount,
    int channels ) [static]
```

Resample audio data so that the complete src buffer fits into dstCount samples in the dst buffer, and convert short to float samples along the way.

This implements a primitive nearest-neighbor resampling algorithm for an arbitrary number of channels.

Parameters

<i>src</i>	Source buffer.
<i>dst</i>	Destination buffer.
<i>dstCount</i>	Target size of destination buffer (in samples per channel).
<i>channels</i>	Number of channels in the signal (1=mono, 2=stereo). Must be > 0.

3.30 BufferReaderPushAdapterAsyncPool< T > Class Template Reference

BufferReaderPushAdapter<T> implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#).

Inherits [BufferReaderPushAdapterBase< T >](#).

Public Member Functions

- [BufferReaderPushAdapterAsyncPool](#) (IDataReader< T > reader)
Create a new BufferReaderPushAdapter instance
- override void [Service](#) ([LocalVoice](#) localVoice)
Do the actual data read/push.

Additional Inherited Members

3.30.1 Detailed Description

BufferReaderPushAdapter<T> implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#).

Acquires a buffer from pool before each Read, releases buffer after last Read (brings Acquire/Release overhead). Expects localVoice to be a LocalVoiceFramed<T> of same T.

3.30.2 Constructor & Destructor Documentation

3.30.2.1 `BufferReaderPushAdapterAsyncPool()`

```
BufferReaderPushAdapterAsyncPool (
    IDataReader< T > reader )
```

Create a new `BufferReaderPushAdapter` instance

Parameters

<code>reader</code>	DataReader to read from.
---------------------	--------------------------

3.30.3 Member Function Documentation

3.30.3.1 `Service()`

```
override void Service (
    LocalVoice localVoice ) [virtual]
```

Do the actual data read/push.

Parameters

<code>localVoice</code>	<code>LocalVoice</code> instance to push data to. Must be a <code>LocalVoiceFramed<T></code> of same T.
-------------------------	---

Implements `BufferReaderPushAdapterBase< T >`.

3.31 `BufferReaderPushAdapterAsyncPoolFloatToShort` Class Reference

`BufferReaderPushAdapter<T>` implementation using asynchronous `LocalVoiceFramed<T>.PushDataAsync`, converting float samples to short.

Inherits `BufferReaderPushAdapterBase< float >`.

Public Member Functions

- `BufferReaderPushAdapterAsyncPoolFloatToShort` (`IDataReader< float > reader`)
Create a new `BufferReaderPushAdapter` instance
- override void `Service` (`LocalVoice localVoice`)
Do the actual data read/push.

Additional Inherited Members

3.31.1 Detailed Description

BufferReaderPushAdapter<T> implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#), converting float samples to short.

This adapter works exactly like BufferReaderPushAdapterAsyncPool<T>, but it converts float samples to short. Acquires a buffer from pool before each Read, releases buffer after last Read.

Expects localVoice to be a LocalVoiceFramed<T> of same T.

3.31.2 Constructor & Destructor Documentation

3.31.2.1 BufferReaderPushAdapterAsyncPoolFloatToShort()

```
BufferReaderPushAdapterAsyncPoolFloatToShort (
    IDataReader< float > reader )
```

Create a new BufferReaderPushAdapter instance

Parameters

<i>reader</i>	DataReader to read from.
---------------	--------------------------

3.31.3 Member Function Documentation

3.31.3.1 Service()

```
override void Service (
    LocalVoice localVoice ) [virtual]
```

Do the actual data read/push.

Parameters

<i>localVoice</i>	LocalVoice instance to push data to. Must be a LocalVoiceFramed<T> of same T.
-------------------	---

Implements [BufferReaderPushAdapterBase< float >](#).

3.32 BufferReaderPushAdapterAsyncPoolShortToFloat Class Reference

BufferReaderPushAdapter<T> implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#), converting short samples to float.

Inherits [BufferReaderPushAdapterBase< short >](#).

Public Member Functions

- [BufferReaderPushAdapterAsyncPoolShortToFloat](#) ([IDataReader](#)< short > reader)
Create a new BufferReaderPushAdapter instance
- override void [Service](#) ([LocalVoice](#) localVoice)
Do the actual data read/push.

Additional Inherited Members

3.32.1 Detailed Description

BufferReaderPushAdapter<T> implementation using asynchronous [LocalVoiceFramed<T>.PushDataAsync](#), converting short samples to float.

This adapter works exactly like [BufferReaderPushAdapterAsyncPool<T>](#), but it converts short samples to float. Acquires a buffer from pool before each Read, releases buffer after last Read.

Expects localVoice to be a [LocalVoiceFramed<T>](#) of same T.

3.32.2 Constructor & Destructor Documentation

3.32.2.1 BufferReaderPushAdapterAsyncPoolShortToFloat()

```
BufferReaderPushAdapterAsyncPoolShortToFloat (
    IDataReader< short > reader )
```

Create a new BufferReaderPushAdapter instance

Parameters

<i>reader</i>	DataReader to read from.
---------------	--------------------------

3.32.3 Member Function Documentation

3.32.3.1 Service()

```
override void Service (
    LocalVoice localVoice ) [virtual]
```

Do the actual data read/push.

Parameters

<i>localVoice</i>	LocalVoice instance to push data to. Must be a LocalVoiceFramed<T> of same T.
-------------------	---

Implements [BufferReaderPushAdapterBase< short >](#).

3.33 BufferReaderPushAdapterBase< T > Class Template Reference

Adapter base reading data from [IDataReader<T>.Read](#) and pushing it to [LocalVoice](#).

Inherits [IServiceable](#).

Inherited by [BufferReaderPushAdapterAsyncPool< T >](#).

Public Member Functions

- abstract void [Service](#) ([LocalVoice](#) localVoice)
Do the actual data read/push.
- [BufferReaderPushAdapterBase](#) ([IDataReader< T >](#) reader)
Create a new [BufferReaderPushAdapterBase](#) instance
- void [Dispose](#) ()
Release resources associated with this instance.

Protected Attributes

- [IDataReader< T >](#) reader

3.33.1 Detailed Description

Adapter base reading data from [IDataReader<T>.Read](#) and pushing it to [LocalVoice](#).

Use this with a [LocalVoice](#) of same T type.

3.33.2 Constructor & Destructor Documentation

3.33.2.1 BufferReaderPushAdapterBase()

```
BufferReaderPushAdapterBase (
    IDataReader< T > reader )
```

Create a new [BufferReaderPushAdapterBase](#) instance

Parameters

<i>reader</i>	DataReader to read from.
---------------	--------------------------

3.33.3 Member Function Documentation

3.33.3.1 Dispose()

```
void Dispose ( )
```

Release resources associated with this instance.

3.33.3.2 Service()

```
abstract void Service (
    LocalVoice localVoice ) [pure virtual]
```

Do the actual data read/push.

Parameters

<i>localVoice</i>	LocalVoice instance to push data to.
-------------------	--

Implements [IServiceable](#).

Implemented in [BufferReaderPushAdapterAsyncPoolShortToFloat](#), [BufferReaderPushAdapterAsyncPoolFloatToShort](#), and [BufferReaderPushAdapterAsyncPool< T >](#).

3.34 CaptureDevice Class Reference

Public Types

- enum **Media**

Public Member Functions

- CaptureDevice** ([ILogger](#) logger, Media media, string deviceId)
- void **Initialize** ()
- void **InitializeAsync** ()
- async Task [CleanUpAsync](#) ()

Asynchronous method cleaning up resources and stopping recording if necessary.

- async Task< IMediaEncodingProperties > [SelectPreferredCameraStreamSettingAsync](#) (MediaStreamType mediaStreamType, Func< IMediaEncodingProperties, bool > filterSettings)
Allow selection of camera settings.
- async Task [StartRecordingAsync](#) (MediaEncodingProfile encodingProfile, Action< byte[], FrameFlags > encoderCallback)
Starts media recording asynchronously
- async Task [StopRecordingAsync](#) ()
Stops recording asynchronously

Static Public Member Functions

- static async Task< bool > **CheckForRecordingDeviceAsync** ()

Properties

- MediaCapture [CaptureSource](#) [get]
Creates url object from MediaCapture

Events

- EventHandler< MediaCaptureFailedEventArgs > **CaptureFailed**

3.34.1 Member Function Documentation

3.34.1.1 CleanUpAsync()

```
async Task CleanUpAsync ( )
```

Asynchronous method cleaning up resources and stopping recording if necessary.

3.34.1.2 SelectPreferredCameraStreamSettingAsync()

```
async Task<IMediaEncodingProperties> SelectPreferredCameraStreamSettingAsync (
    MediaStreamType mediaStreamType,
    Func< IMediaEncodingProperties, bool > filterSettings )
```

Allow selection of camera settings.

Parameters

<i>mediaStreamType</i>	Type of a the media stream.
<i>filterSettings</i>	A predicate function, which will be called to filter the correct settings.

3.34.1.3 StartRecordingAsync()

```
async Task StartRecordingAsync (
    MediaEncodingProfile encodingProfile,
    Action< byte[], FrameFlags > encoderCallback )
```

Starts media recording asynchronously

Parameters

<i>encodingProfile</i>	Encoding profile used for the recording session
------------------------	---

3.34.1.4 StopRecordingAsync()

```
async Task StopRecordingAsync ( )
```

Stops recording asynchronously

3.34.2 Property Documentation

3.34.2.1 CaptureSource

```
MediaCapture CaptureSource [get]
```

Creates url object from MediaCapture

3.35 ConnectAndJoin Class Reference

Inherits MonoBehaviour, IConnectionCallbacks, and IMatchmakingCallbacks.

Public Member Functions

- void **ConnectNow** ()
- void **OnCreatedRoom** ()
- void **OnCreateRoomFailed** (short returnCode, string message)
- void **OnFriendListUpdate** (List< FriendInfo > friendList)
- void **OnJoinedRoom** ()
- void **OnJoinRandomFailed** (short returnCode, string message)
- void **OnJoinRoomFailed** (short returnCode, string message)
- void **OnLeftRoom** ()
- void **OnConnected** ()
- void **OnConnectedToMaster** ()
- void **OnDisconnected** (DisconnectCause cause)
- void **OnRegionListReceived** (RegionHandler regionHandler)
- void **OnCustomAuthenticationResponse** (Dictionary< string, object > data)
- void **OnCustomAuthenticationFailed** (string debugMessage)

Public Attributes

- bool **RandomRoom** = true
- string **RoomName**

Properties

- bool **IsConnected** [get]

3.36 VoiceClient.CreateOptions Struct Reference

Public Attributes

- byte **VoiceIDMin**
- byte **VoiceIDMax**

Static Public Attributes

- static [CreateOptions](#) **Default**

3.36.1 Member Data Documentation

3.36.1.1 Default

[CreateOptions](#) **Default** [static]

Initial value:

```
= new CreateOptions()  
{  
    VoiceIDMin = 1,  
    VoiceIDMax = 15  
}
```

3.37 OpusCodec.Decoder< T > Class Template Reference

Inherits [IDecoder](#).

Public Member Functions

- **Decoder** (Action< [FrameOut](#)< T >> output, [ILogger](#) logger)
- void **Open** ([VoiceInfo](#) i)
Open (initialize) the decoder.
- void **Dispose** ()
- void **Input** (ref [FrameBuffer](#) buf)
Consumes the given encoded data.

Protected Attributes

- `OpusDecoder< T >` **decoder**

Properties

- string **Error** [get]

3.37.1 Member Function Documentation

3.37.1.1 Input()

```
void Input (
    ref FrameBuffer buf )
```

Consumes the given encoded data.

The callee can call `buf.Retain()` to prevent the caller from disposing the buffer. In this case, the callee should call `buf.Release()` when buffer is no longer needed.

Implements [IDecoder](#).

3.37.1.2 Open()

```
void Open (
    VoiceInfo info )
```

Open (initialize) the decoder.

Parameters

<i>info</i>	Properties of the data stream to decode.
-------------	--

Implements [IDecoder](#).

3.38 RawCodec.Decoder< T > Class Template Reference

Inherits [IDecoder](#).

Public Member Functions

- **Decoder** (`Action< FrameOut< T >>` output)

- void [Open](#) ([VoiceInfo](#) info)
Open (initialize) the decoder.
- void [Input](#) (ref [FrameBuffer](#) byteBuf)
Consumes the given encoded data.
- void **Dispose** ()

Properties

- string **Error** [get]

3.38.1 Member Function Documentation

3.38.1.1 Input()

```
void Input (
    ref FrameBuffer buf )
```

Consumes the given encoded data.

The callee can call buf.Retain() to prevent the caller from disposing the buffer. In this case, the callee should call buf.Release() when buffer is no longer needed.

Implements [IDecoder](#).

3.38.1.2 Open()

```
void Open (
    VoiceInfo info )
```

Open (initialize) the decoder.

Parameters

<i>info</i>	Properties of the data stream to decode.
-------------	--

Implements [IDecoder](#).

3.39 DeviceEnumerator Class Reference

Inherits [DeviceEnumeratorBase](#).

Inherited by [AudioInEnumerator](#), and [VideoInEnumerator](#).

Public Member Functions

- **DeviceEnumerator** ([ILogger](#) logger, Windows.Devices.Enumeration.DeviceClass deviceClass)
- override void **Refresh** ()
- override void **Dispose** ()

Additional Inherited Members

3.40 DeviceEnumeratorBase Class Reference

Inherits [IDeviceEnumerator](#).

Inherited by DeviceEnumeratorNotSupported, DeviceEnumeratorSingleDevice, [AudioInEnumerator](#), [AudioInEnumerator](#), [AudioInEnumerator](#), [VideoInEnumerator](#), [DeviceEnumerator](#), and [AudioInEnumerator](#).

Public Member Functions

- **DeviceEnumeratorBase** ([ILogger](#) logger)
- IEnumerable< [DeviceInfo](#) > **GetEnumerator** ()
- abstract void **Refresh** ()
- abstract void **Dispose** ()

Public Attributes

- virtual bool **IsSupported** => true

Protected Attributes

- List< [DeviceInfo](#) > **devices** = new List<[DeviceInfo](#)>()
- [ILogger](#) **logger**

Properties

- virtual string **Error** [get, protected set]

3.41 DeviceFeatures Class Reference

Public Member Functions

- **DeviceFeatures** (CameraFacing facing)

Properties

- CameraFacing **CameraFacing** [get]

3.42 DeviceInfo Struct Reference

Public Member Functions

- **DeviceInfo** (int id, string name, [DeviceFeatures](#) features=null)
- **DeviceInfo** (string id, string name, [DeviceFeatures](#) features=null)
- **DeviceInfo** (string name, [DeviceFeatures](#) features=null)
- override bool **Equals** (object obj)
- override int **GetHashCode** ()
- override string **ToString** ()

Static Public Member Functions

- static bool **operator==** ([DeviceInfo](#) d1, [DeviceInfo](#) d2)
- static bool **operator!=** ([DeviceInfo](#) d1, [DeviceInfo](#) d2)

Public Attributes

- [DeviceFeatures](#) **Features** => features == null ? DeviceFeatures.Default : features
- [DeviceFeatures](#) **features**

Static Public Attributes

- static readonly [DeviceInfo](#) **Default** = new [DeviceInfo](#)(true, -128, "", "[Default]")

Properties

- bool **IsDefault** [get]
- int **IDInt** [get]
- string **IDString** [get]
- string **Name** [get]

3.43 RecorderPreset.DSP Struct Reference

Public Attributes

- bool **AEC**
- bool **VAD**

3.44 OpusCodec.Encoder< T > Class Template Reference

Inherits [IEncoderDirect< T\[\]>](#).

Public Member Functions

- void **Input** (T[] buf)
- void **EndOfStream** ()
- ArraySegment< byte > **DequeueOutput** (out FrameFlags flags)
- I **GetPlatformAPI**< I > ()
- void **Dispose** ()

Protected Member Functions

- **Encoder** ([VoiceInfo](#) i, [ILogger](#) logger)
- abstract void **encodeTyped** (T[] buf)

Protected Attributes

- OpusEncoder **encoder**
- bool **disposed**

Properties

- string **Error** [get]
- Action< ArraySegment< byte >, FrameFlags > **Output** [get, set]

3.45 RawCodec.Encoder< T > Class Template Reference

Inherits [IEncoderDirect< T\[\]>](#).

Public Member Functions

- ArraySegment< byte > **DequeueOutput** (out FrameFlags flags)
- void **EndOfStream** ()
- I **GetPlatformAPI**< I > ()
- void **Dispose** ()
- void **Input** (T[] buf)

Properties

- string **Error** [get]
- Action< ArraySegment< byte >, FrameFlags > **Output** [get, set]

3.46 OpusCodec.EncoderFloat Class Reference

Inherits [OpusCodec.Encoder< float >](#).

Protected Member Functions

- override void **encodeTyped** (float[] buf)

Additional Inherited Members

3.47 OpusCodec.EncoderShort Class Reference

Inherits [OpusCodec.Encoder< short >](#).

Protected Member Functions

- override void **encodeTyped** (short[] buf)

Additional Inherited Members

3.48 OpusCodec.Factory Class Reference

Static Public Member Functions

- static [IEncoder](#) **CreateEncoder**< B > ([VoiceInfo](#) i, [ILogger](#) logger)

3.49 FactoryPrimitiveArrayPool< T > Class Template Reference

PrimitiveArrayPool<T> as wrapped in object factory interface.

Inherits [ObjectFactory< T\[\], int >](#).

Public Member Functions

- **FactoryPrimitiveArrayPool** (int capacity, string name)
- **FactoryPrimitiveArrayPool** (int capacity, string name, int info)
- **T[] New** ()
- **T[] New** (int size)
- void **Free** (T[] obj)
- void **Free** (T[] obj, int info)
- void **Dispose** ()

Properties

- int **Info** [get]

3.49.1 Detailed Description

PrimitiveArrayPool<T> as wrapped in object factory interface.

Template Parameters

<i>T</i>	Array element type.
----------	---------------------

3.50 FactoryReusableArray< T > Class Template Reference

Array factory returnig the same array instance as long as it requested with the same array length. If length changes, new array instance created.

Inherits [ObjectFactory< T\[\], int >](#).

Public Member Functions

- **FactoryReusableArray** (int size)
- **T[] New** ()
- **T[] New** (int size)
- void **Free** (T[] obj)
- void **Free** (T[] obj, int info)
- void **Dispose** ()

Properties

- int **Info** [get]

3.50.1 Detailed Description

Array factory returnig the same array instance as long as it requested with the same array length. If length changes, new array instance created.

Template Parameters

<i>T</i>	Array element type.
----------	---------------------

3.51 Flip Struct Reference

Public Member Functions

- override bool **Equals** (object obj)
- override int **GetHashCode** ()

Static Public Member Functions

- static bool **operator==** ([Flip](#) f1, [Flip](#) f2)
- static bool **operator!=** ([Flip](#) f1, [Flip](#) f2)
- static [Flip](#) **operator*** ([Flip](#) f1, [Flip](#) f2)

Static Public Attributes

- static [Flip](#) **None**
- static [Flip](#) **Vertical** = new [Flip](#)() { IsVertical = true }
- static [Flip](#) **Horizontal** = new [Flip](#)() { IsHorizontal = true }
- static [Flip](#) **Both** = Vertical * Horizontal

Properties

- bool **IsVertical** [get]
- bool **IsHorizontal** [get]

3.52 FMODRecorderSetup Class Reference

Inherits [VoiceComponent](#).

Protected Member Functions

- override void **Awake** ()

Additional Inherited Members

3.53 FrameBuffer Struct Reference

Public Member Functions

- **FrameBuffer** (byte[] array, int offset, int count, FrameFlags flags, byte frameNum, IDisposable disposer)
- **FrameBuffer** (byte[] array, FrameFlags flags, byte frameNum)
- **FrameBuffer** ([FrameBuffer](#) from, int offset, int count, FrameFlags flags, byte frameNum)
- void **Retain** ()
- void **Release** ()
- override string **ToString** ()

Public Attributes

- readonly byte[] **array**
- readonly int **offset**
- readonly int **count**
- readonly IDisposable **disposer**
- bool **disposed**
- int **refCnt**
- GCHandle **gcHandle**
- IntPtr **ptr**
- bool **pinned**
- bool **IsFEC** => (Flags & FrameFlags.FEC) != 0

Properties

- `IntPtr Ptr` [get]
- `byte[] Array` [get]
- `int Length` [get]
- `int Offset` [get]
- `FrameFlags Flags` [get]
- `byte FrameNum` [get]

3.54 `FrameOut< T >` Class Template Reference

Public Member Functions

- `FrameOut (T[] buf, bool endOfStream)`
- `FrameOut< T > Set (T[] buf, bool endOfStream)`

Properties

- `T[] Buf` [get]
- `bool EndOfStream` [get]

3.55 `Framer< T >` Class Template Reference

Utility class to re-frame packets.

Inherited by [FramerResampler< T >](#).

Public Member Functions

- `Framer (int frameSize)`
Create new [Framer](#) instance.
- `virtual IEnumerable< T[] > Frame (T[] buf)`
Append arbitrary-sized buffer and return available full frames.

Protected Attributes

- `T[] frame`
- `int sizeofT`
- `int framePos = 0`

3.55.1 Detailed Description

Utility class to re-frame packets.

3.55.2 Constructor & Destructor Documentation

3.55.2.1 Framer()

```
Framer (
    int frameSize )
```

Create new [Framer](#) instance.

3.55.3 Member Function Documentation

3.55.3.1 Frame()

```
virtual IEnumerable<T[]> Frame (
    T[] buf ) [virtual]
```

Append arbitrary-sized buffer and return available full frames.

Parameters

<i>buf</i>	Array of samples to add.
------------	--------------------------

Returns

Enumerator of full frames (might be none).

Reimplemented in [FramerResampler< T >](#).

3.56 FramerResampler< T > Class Template Reference

Inherits [Framer< T >](#).

Public Member Functions

- **FramerResampler** (int frameSize, int channels, int resampleNum, int resampleDen, bool interpolate)
- override IEnumerable< T[] > [Frame](#) (T[] bufT)
Append arbitrary-sized buffer and return available full frames.

Protected Attributes

- bool **TisFloat**
- bool **interpolate**
- int **channels**
- int **resampleNum**
- int **resampleDen**
- float **resampleRatioInv**
- int **delta**

3.56.1 Member Function Documentation

3.56.1.1 Frame()

```
override IEnumerable<T[]> Frame (
    T[] buf ) [virtual]
```

Append arbitrary-sized buffer and return available full frames.

Parameters

<i>buf</i>	Array of samples to add.
------------	--------------------------

Returns

Enumerator of full frames (might be none).

Reimplemented from [Framer< T >](#).

3.57 FusionVoiceClient Class Reference

Inherits [VoiceConnection](#), and [INetworkRunnerCallbacks](#).

Public Attributes

- bool [UseFusionAppSettings](#) = true
Whether or not to use the [Voice](#) Appld and all the other AppSettings from [Fusion](#)'s RealtimeAppSettings Scriptable↔ Object singleton in the [Voice](#) client/app.
- bool [UseFusionAuthValues](#) = true
Whether or not to use the same AuthenticationValues used in [Fusion](#) client/app in [Voice](#) client/app as well. This means that the same UserID will be used in both clients. If custom authentication is used and setup in [Fusion](#) Appld from dashboard, the same configuration should be done for the [Voice](#) Appld.

Protected Member Functions

- virtual void **Start** ()
- override void **Awake** ()
- override void **OnDestroy** ()
- override [Speaker](#) **InstantiateSpeakerForRemoteVoice** (int playerId, byte voiceId, object userData)

Additional Inherited Members

3.57.1 Member Data Documentation

3.57.1.1 UseFusionAppSettings

```
bool UseFusionAppSettings = true
```

Whether or not to use the [Voice](#) AppId and all the other AppSettings from [Fusion](#)'s RealtimeAppSettings Scriptable↔ Object singleton in the [Voice](#) client/app.

3.57.1.2 UseFusionAuthValues

```
bool UseFusionAuthValues = true
```

Whether or not to use the same AuthenticationValues used in [Fusion](#) client/app in [Voice](#) client/app as well. This means that the same UserID will be used in both clients. If custom authentication is used and setup in [Fusion](#) AppId from dashboard, the same configuration should be done for the [Voice](#) AppId.

3.58 AudioUtil.GeneratorPusher< T > Class Template Reference

[IAudioPusher](#) that provides a constant tone signal.

Inherits [IAudioPusher< T >](#).

Inherited by [AudioUtil.ToneAudioPusher< T >](#), and [AudioUtil.WaveformAudioPusher< T >](#).

Public Member Functions

- **GeneratorPusher** (int bufSizeMs=100, int samplingRate=48000, int channels=1)
- void **SetCallback** (Action< T[]> callback, [ObjectFactory](#)< T[], int > bufferFactory)
 - Set the callback function used for pushing data*
- void **Dispose** ()

Protected Member Functions

- abstract int **Gen** (T[] buf, long timeSamples)

Protected Attributes

- long **timeSamples**

Properties

- int **Channels** [get]
- int **SamplingRate** [get]
- string **Error** [get]

3.58.1 Detailed Description

[IAudioPusher](#) that provides a constant tone signal.

3.58.2 Member Function Documentation

3.58.2.1 SetCallback()

```
void SetCallback (
    Action< T[]> callback,
    ObjectFactory< T[], int > bufferFactory )
```

Set the callback function used for pushing data

Parameters

<i>callback</i>	Callback function to use
<i>bufferFactory</i>	Buffer factory used to create the buffer that is pushed to the callback

Implements [IAudioPusher< T >](#).

3.59 AudioUtil.GeneratorReader< T > Class Template Reference

Inherits [IAudioReader< T >](#).

Inherited by [AudioUtil.ToneAudioReader< T >](#), and [AudioUtil.WaveformAudioReader< T >](#).

Public Member Functions

- **GeneratorReader** (Func< double > clockSec=null, int samplingRate=48000, int channels=1)
- void **Dispose** ()
- bool **Read** (T[] buf)

Fill full given frame buffer with source uncompressed data or return false if not enough such data.

Protected Member Functions

- abstract int **Gen** (T[] buf, long timeSamples)

Properties

- int **Channels** [get]
- int **SamplingRate** [get]
- string **Error** [get]

3.59.1 Member Function Documentation

3.59.1.1 Read()

```
bool Read (
    T[] buffer )
```

Fill full given frame buffer with source uncompressed data or return false if not enough such data.

Parameters

<i>buffer</i>	Buffer to fill.
---------------	-----------------

Returns

True if buffer was filled successfully, false otherwise.

Implements [IDataReader< T >](#).

3.60 IAudioDesc Interface Reference

Audio Source interface.

Inherits [IDisposable](#).

Inherited by [AudioDesc](#), [IAudioPusher< T >](#), and [IAudioReader< T >](#).

Properties

- int [SamplingRate](#) [get]
Sampling rate of the audio signal (in Hz).
- int [Channels](#) [get]
Number of channels in the audio signal.
- string [Error](#) [get]
If not null, audio object is in invalid state.

3.60.1 Detailed Description

Audio Source interface.

3.60.2 Property Documentation

3.60.2.1 Channels

```
int Channels [get]
```

Number of channels in the audio signal.

3.60.2.2 Error

```
string Error [get]
```

If not null, audio object is in invalid state.

3.60.2.3 SamplingRate

```
int SamplingRate [get]
```

Sampling rate of the audio signal (in Hz).

3.61 [IAudioInChangeNotifier](#) Interface Reference

Inherits [IDisposable](#).

Inherited by [AudioInChangeNotifierNotSupported](#), [AudioInChangeNotifier](#), and [AudioInChangeNotifier](#).

Properties

- `bool` **IsSupported** [get]
- `string` **Error** [get]

3.62 `IAudioOut< T >` Interface Template Reference

Inherited by [AudioOutDelayControl< T >](#), and [AudioOutDummy< T >](#).

Public Member Functions

- `void` **Start** (int frequency, int channels, int frameSamplesPerChannel)
- `void` **Flush** ()
- `void` **Stop** ()
- `void` **Push** (T[] frame)
- `void` **Service** ()

Properties

- `bool` **IsPlaying** [get]
- `int` **Lag** [get]

3.63 `IAudioPusher< T >` Interface Template Reference

Audio Pusher interface.

Inherits [IAudioDesc](#).

Inherited by [AudioUtil.GeneratorPusher< T >](#).

Public Member Functions

- `void` [SetCallback](#) (Action< T[]> callback, [ObjectFactory](#)< T[], int > bufferFactory)
Set the callback function used for pushing data.

Additional Inherited Members

3.63.1 Detailed Description

Audio Pusher interface.

Opposed to an [IAudioReader](#) (which will deliver audio data when it is "pulled"), an [IAudioPusher](#) will push its audio data whenever it is ready,

3.63.2 Member Function Documentation

3.63.2.1 `SetCallback()`

```
void SetCallback (
    Action< T[]> callback,
    ObjectFactory< T[], int > bufferFactory )
```

Set the callback function used for pushing data.

Parameters

<i>callback</i>	Callback function to use.
<i>bufferFactory</i>	Buffer factory used to create the buffer that is pushed to the callback

Implemented in [AudioUtil.GeneratorPusher< T >](#).

3.64 IAudioReader< T > Interface Template Reference

Audio Reader interface.

Inherits [IDataReader< T >](#), and [IAudioDesc](#).

Inherited by [AudioUtil.GeneratorReader< T >](#), and [AudioInReader< T >](#).

Additional Inherited Members

3.64.1 Detailed Description

Audio Reader interface.

Opposed to an [IAudioPusher](#) (which will push its audio data whenever it is ready), an [IAudioReader](#) will deliver audio data when it is "pulled" (it's Read function is called).

3.65 IDataReader< T > Interface Template Reference

Interface for pulling data, in case this is more appropriate than pushing it.

Inherits [IDisposable](#).

Inherited by [IAudioReader< T >](#).

Public Member Functions

- bool [Read](#) (T[] buffer)

Fill full given frame buffer with source uncompressed data or return false if not enough such data.

3.65.1 Detailed Description

Interface for pulling data, in case this is more appropriate than pushing it.

3.65.2 Member Function Documentation

3.65.2.1 Read()

```
bool Read (
    T[] buffer )
```

Fill full given frame buffer with source uncompressed data or return false if not enough such data.

Parameters

<i>buffer</i>	Buffer to fill.
---------------	-----------------

Returns

True if buffer was filled successfully, false otherwise.

Implemented in [AudioInReader< T >](#), and [AudioUtil.GeneratorReader< T >](#).

3.66 IDecoder Interface Reference

Generic decoder interface.

Inherits [IDisposable](#).

Inherited by [IDecoderDirect< B >](#), [OpusCodec.Decoder< T >](#), and [RawCodec.Decoder< T >](#).

Public Member Functions

- void [Open](#) ([VoiceInfo](#) info)
Open (initialize) the decoder.
- void [Input](#) (ref [FrameBuffer](#) buf)
Consumes the given encoded data.

Properties

- string [Error](#) [get]
If not null, the object is in invalid state.

3.66.1 Detailed Description

Generic decoder interface.

3.66.2 Member Function Documentation

3.66.2.1 Input()

```
void Input (
    ref FrameBuffer buf )
```

Consumes the given encoded data.

The callee can call `buf.Retain()` to prevent the caller from disposing the buffer. In this case, the callee should call `buf.Release()` when buffer is no longer needed.

Implemented in [RawCodec.Decoder< T >](#), and [OpusCodec.Decoder< T >](#).

3.66.2.2 Open()

```
void Open (
    VoiceInfo info )
```

Open (initialize) the decoder.

Parameters

<i>info</i>	Properties of the data stream to decode.
-------------	--

Implemented in [RawCodec.Decoder< T >](#), and [OpusCodec.Decoder< T >](#).

3.66.3 Property Documentation

3.66.3.1 Error

`string Error [get]`

If not null, the object is in invalid state.

3.67 IDecoderDirect< B > Interface Template Reference

Interface for an decoder which outputs data via explicit call.

Inherits [IDecoder](#).

Properties

- `Action< B > Output [get, set]`
Callback to call when a new decoded data buffer is available.

Additional Inherited Members

3.67.1 Detailed Description

Interface for an decoder which outputs data via explicit call.

3.67.2 Property Documentation

3.67.2.1 Output

`Action Output [get], [set]`

Callback to call when a new decoded data buffer is available.

3.68 IDeviceEnumerator Interface Reference

Inherits IDisposable, and IEnumerable< DeviceInfo >.

Inherited by [DeviceEnumeratorBase](#).

Public Member Functions

- void **Refresh** ()

Properties

- bool **IsSupported** [get]
- string **Error** [get]

3.69 IEncoder Interface Reference

Generic encoder interface.

Inherits IDisposable.

Inherited by [IEncoderDirect< B >](#).

Public Member Functions

- ArraySegment< byte > [DequeueOutput](#) (out FrameFlags flags)
Returns next encoded data frame (if such output supported).
- void [EndOfStream](#) ()
Forces an encoder to flush and produce frame with EndOfStream flag (in output queue).
- I [GetPlatformAPI< I >](#) ()
Returns an platform-specific interface.

Properties

- string [Error](#) [get]
If not null, the object is in invalid state.
- Action< ArraySegment< byte >, FrameFlags > [Output](#) [set]
Set callback encoder calls on each encoded data frame (if such output supported).

3.69.1 Detailed Description

Generic encoder interface.

Depending on implementation, encoder should either call Output on each data frame or return next data frame in [DequeueOutput\(\)](#) call.

3.69.2 Member Function Documentation

3.69.2.1 DequeueOutput()

```
ArraySegment<byte> DequeueOutput (
    out FrameFlags flags )
```

Returns next encoded data frame (if such output supported).

3.69.2.2 EndOfStream()

```
void EndOfStream ( )
```

Forces an encoder to flush and produce frame with EndOfStream flag (in output queue).

3.69.2.3 GetPlatformAPI< I >()

```
I GetPlatformAPI< I > ( )
```

Returns an platform-specific interface.

Type Constraints

I : class

3.69.3 Property Documentation

3.69.3.1 Error

```
string Error [get]
```

If not null, the object is in invalid state.

3.69.3.2 Output

```
Action<ArraySegment<byte>, FrameFlags> Output [set]
```

Set callback encoder calls on each encoded data frame (if such output supported).

3.70 IEncoderDirect< B > Interface Template Reference

Interface for an encoder which consumes input data via explicit call.

Inherits [IEncoder](#).

Public Member Functions

- void [Input](#) (B buf)
Consumes the given raw data.

Additional Inherited Members

3.70.1 Detailed Description

Interface for an encoder which consumes input data via explicit call.

3.70.2 Member Function Documentation

3.70.2.1 Input()

```
void Input (
    B buf )
```

Consumes the given raw data.

Parameters

<i>buf</i>	Array containing raw data (e.g. audio samples).
------------	---

3.71 IEncoderDirectImage Interface Reference

Interface for an encoder which consumes images via explicit call.

Inherits [IEncoderDirect< ImageBufferNative >](#).

Properties

- ImageFormat [ImageFormat](#) [get]
Recommended encoder input image format. Encoder may support other formats.

Additional Inherited Members

3.71.1 Detailed Description

Interface for an encoder which consumes images via explicit call.

3.71.2 Property Documentation

3.71.2.1 ImageFormat

`ImageFormat ImageFormat [get]`

Recommended encoder input image format. Encoder may support other formats.

3.72 AudioUtil.ILevelMeter Interface Reference

Audio Level Metering interface.

Inherited by [AudioUtil.LevelMeter< T >](#), and [AudioUtil.LevelMeterDummy](#).

Public Member Functions

- void [ResetAccumAvgPeakAmp](#) ()
Reset [AccumAvgPeakAmp](#).

Properties

- float [CurrentAvgAmp](#) [get]
Average amplitude value over last half second.
- float [CurrentPeakAmp](#) [get]
Maximum amplitude value over last half second sec.
- float [AccumAvgPeakAmp](#) [get]
Average of CurrentPeakAmps since last reset.

3.72.1 Detailed Description

Audio Level Metering interface.

3.72.2 Member Function Documentation

3.72.2.1 ResetAccumAvgPeakAmp()

```
void ResetAccumAvgPeakAmp ( )
```

Reset [AccumAvgPeakAmp](#).

Implemented in [AudioUtil.LevelMeter< T >](#), and [AudioUtil.LevelMeterDummy](#).

3.72.3 Property Documentation

3.72.3.1 AccumAvgPeakAmp

```
float AccumAvgPeakAmp [get]
```

Average of CurrentPeakAmps since last reset.

3.72.3.2 CurrentAvgAmp

```
float CurrentAvgAmp [get]
```

Average amplitude value over last half second.

3.72.3.3 CurrentPeakAmp

```
float CurrentPeakAmp [get]
```

Maximum amplitude value over last half second sec.

3.73 ILocalVoiceAudio Interface Reference

Interface for an outgoing audio stream.

Inherited by [LocalVoiceAudio< T >](#), and [LocalVoiceAudioDummy](#).

Public Member Functions

- void [VoiceDetectorCalibrate](#) (int durationMs, Action< float > onCalibrated=null)
Trigger voice detector calibration process.

Properties

- [AudioUtil.IVoiceDetector](#) [VoiceDetector](#) [get]
The VoiceDetector in use.
- [AudioUtil.ILevelMeter](#) [LevelMeter](#) [get]
The LevelMeter utility in use.
- bool [VoiceDetectorCalibrating](#) [get]
If true, voice detector calibration is in progress.

3.73.1 Detailed Description

Interface for an outgoing audio stream.

A [LocalVoice](#) always brings a LevelMeter and a VoiceDetector, which you can access using this interface.

3.73.2 Member Function Documentation

3.73.2.1 VoiceDetectorCalibrate()

```
void VoiceDetectorCalibrate (
    int durationMs,
    Action< float > onCalibrated = null )
```

Trigger voice detector calibration process.

While calibrating, keep silence. [Voice](#) detector sets threshold based on measured background noise level.

Parameters

<i>durationMs</i>	Duration of calibration (in milliseconds).
<i>onCalibrated</i>	Called when calibration is complete. Parameter is new threshold value.

Implemented in [LocalVoiceAudioDummy](#), and [LocalVoiceAudio< T >](#).

3.73.3 Property Documentation

3.73.3.1 LevelMeter

[AudioUtil.ILevelMeter](#) [LevelMeter](#) [get]

The LevelMeter utility in use.

3.73.3.2 VoiceDetector

[AudioUtil.IVoiceDetector](#) VoiceDetector [get]

The VoiceDetector in use.

Use it to enable or disable voice detector and set its parameters.

3.73.3.3 VoiceDetectorCalibrating

bool VoiceDetectorCalibrating [get]

If true, voice detector calibration is in progress.

3.74 ILogger Interface Reference

Inherited by [LoadBalancingTransport](#), and [Logger](#).

Public Member Functions

- void **LogError** (string fmt, params object[] args)
- void **LogWarning** (string fmt, params object[] args)
- void **LogInfo** (string fmt, params object[] args)
- void **LogDebug** (string fmt, params object[] args)

3.75 ImageBufferInfo Struct Reference

Classes

- struct [StrideSet](#)

Public Member Functions

- **ImageBufferInfo** (int width, int height, [StrideSet](#) stride, ImageFormat format)

Properties

- int **Width** [get]
- int **Height** [get]
- [StrideSet](#) **Stride** [get]
- ImageFormat **Format** [get]
- Rotation **Rotation** [get, set]
- [Flip](#) **Flip** [get, set]

3.76 ImageBufferNative Class Reference

Inherited by [ImageBufferNativeAlloc](#), [ImageBufferNativeGCHandleBytes](#), and [ImageBufferNativeGCHandleSinglePlane](#).

Classes

- struct [PlaneSet](#)

Public Member Functions

- **ImageBufferNative** ([ImageBufferInfo](#) info)
- **ImageBufferNative** (IntPtr buf, int width, int height, int stride, ImageFormat imageFormat)
- virtual void **Release** ()
- virtual void **Dispose** ()

Public Attributes

- [ImageBufferInfo](#) Info
- [PlaneSet](#) Planes

3.77 ImageBufferNativeAlloc Class Reference

Inherits [ImageBufferNative](#), and [IDisposable](#).

Public Member Functions

- **ImageBufferNativeAlloc** ([ImageBufferNativePool](#)< [ImageBufferNativeAlloc](#) > pool, [ImageBufferInfo](#) info)
- override void **Release** ()
- override void **Dispose** ()

Additional Inherited Members

3.78 ImageBufferNativeGCHandleBytes Class Reference

Inherits [ImageBufferNative](#), and [IDisposable](#).

Public Member Functions

- **ImageBufferNativeGCHandleBytes** ([ImageBufferNativePool](#)< [ImageBufferNativeGCHandleBytes](#) > pool, [ImageBufferInfo](#) info)
- override void **Release** ()
- override void **Dispose** ()

Public Attributes

- `byte[][] PlaneBytes => planeBytes`

3.79 ImageBufferNativeGCHandleSinglePlane Class Reference

Inherits [ImageBufferNative](#), and [IDisposable](#).

Public Member Functions

- `ImageBufferNativeGCHandleSinglePlane (ImageBufferNativePool< ImageBufferNativeGCHandleSinglePlane > pool, ImageBufferInfo info)`
- `void PinPlane (byte[] plane)`
- `override void Release ()`
- `override void Dispose ()`

Additional Inherited Members

3.80 ImageBufferNativePool< T > Class Template Reference

Inherits [ObjectPool](#)< [T](#), [ImageBufferInfo](#) >.

Public Member Functions

- `delegate T Factory (ImageBufferNativePool< T > pool, ImageBufferInfo info)`
- `ImageBufferNativePool (int capacity, Factory factory, string name)`
- `ImageBufferNativePool (int capacity, Factory factory, string name, ImageBufferInfo info)`

Protected Member Functions

- `override T createObject (ImageBufferInfo info)`
- `override void destroyObject (T obj)`
- `override bool infosMatch (ImageBufferInfo i0, ImageBufferInfo i1)`

Additional Inherited Members

3.81 IProcessor< T > Interface Template Reference

Processor interface.

Inherits [IDisposable](#).

Inherited by [AudioUtil.LevelMeter](#)< [T](#) >, [AudioUtil.Resampler](#)< [T](#) >, [AudioUtil.VoiceDetector](#)< [T](#) >, [AudioUtil.VoiceDetectorCalibration](#) and [AudioUtil.VoiceLevelDetectCalibrate](#)< [T](#) >.

Public Member Functions

- `T[] Process (T[] buf)`
Process a frame of data.

3.81.1 Detailed Description

Processor interface.

3.81.2 Member Function Documentation

3.81.2.1 `Process()`

```
T [ ] Process (
    T [ ] buf )
```

Process a frame of data.

Parameters

<i>buf</i>	Buffer containing input data
------------	------------------------------

Returns

Buffer containing output data or null if frame has been discarded (VAD)

Implemented in [AudioUtil.VoiceLevelDetectCalibrate< T >](#), [AudioUtil.VoiceDetector< T >](#), [AudioUtil.VoiceDetectorCalibration< T >](#), [AudioUtil.LevelMeter< T >](#), and [AudioUtil.Resampler< T >](#).

3.82 IResettable Interface Reference

Inherited by [AudioInPusher](#), [AudioInReader](#), and [AndroidAudioInAEC](#).

Public Member Functions

- `void Reset ()`

3.83 IServiceable Interface Reference

Interface for classes that want their [Service\(\)](#) function to be called regularly in the context of a [LocalVoice](#).

Inherited by [BufferReaderPushAdapterBase< T >](#).

Public Member Functions

- void [Service](#) ([LocalVoice](#) localVoice)
Service function that should be called regularly.

3.83.1 Detailed Description

Interface for classes that want their [Service\(\)](#) function to be called regularly in the context of a [LocalVoice](#).

3.83.2 Member Function Documentation

3.83.2.1 Service()

```
void Service (  
    LocalVoice localVoice )
```

Service function that should be called regularly.

Implemented in [BufferReaderPushAdapterAsyncPool< T >](#), and [BufferReaderPushAdapterBase< T >](#).

3.84 AudioUtil.IVoiceDetector Interface Reference

[Voice](#) Activity Detector interface.

Inherited by [AudioUtil.VoiceDetector< T >](#), and [AudioUtil.VoiceDetectorDummy](#).

Properties

- bool [On](#) [get, set]
If true, voice detection enabled.
- float [Threshold](#) [get, set]
Voice detected as soon as signal level exceeds threshold.
- bool [Detected](#) [get]
If true, voice detected.
- DateTime [DetectedTime](#) [get]
Last time when switched to detected state.
- int [ActivityDelayMs](#) [get, set]
Keep detected state during this time after signal level dropped below threshold.

Events

- Action [OnDetected](#)
Called when switched to detected state.

3.84.1 Detailed Description

[Voice](#) Activity Detector interface.

3.84.2 Property Documentation

3.84.2.1 ActivityDelayMs

```
int ActivityDelayMs [get], [set]
```

Keep detected state during this time after signal level dropped below threshold.

3.84.2.2 Detected

```
bool Detected [get]
```

If true, voice detected.

3.84.2.3 DetectedTime

```
DateTime DetectedTime [get]
```

Last time when switched to detected state.

3.84.2.4 On

```
bool On [get], [set]
```

If true, voice detection enabled.

3.84.2.5 Threshold

```
float Threshold [get], [set]
```

[Voice](#) detected as soon as signal level exceeds threshold.

3.84.3 Event Documentation

3.84.3.1 OnDetected

Action OnDetected

Called when switched to detected state.

3.85 IVoiceTransport Interface Reference

Inherited by [LoadBalancingTransport](#).

Public Member Functions

- bool **IsChannelJoined** (int channelId)
- void **SendVoiceInfo** ([LocalVoice](#) voice, int channelId, bool targetMe, int[] targetPlayers)
- void **SendVoiceRemove** ([LocalVoice](#) voice, int channelId, bool targetMe, int[] targetPlayers)
- void **SendFrame** (ArraySegment< byte > data, FrameFlags flags, byte evNumber, byte frNumber, byte voiceld, int channelId, [SendFrameParams](#) par)
- string **ChannelIdStr** (int channelId)
- string **PlayerIdStr** (int playerId)
- int **GetPayloadFragmentSize** ([SendFrameParams](#) par)

3.86 AudioUtil.LevelMeter< T > Class Template Reference

Audio Level Meter.

Inherits [IProcessor< T >](#), and [AudioUtil.ILevelMeter](#).

Public Member Functions

- void [ResetAccumAvgPeakAmp](#) ()
Reset AccumAvgPeakAmp.
- abstract T[] [Process](#) (T[] buf)
Process a frame of data.
- void **Dispose** ()

Protected Attributes

- float **ampSum**
- float **ampPeak**
- int **bufferSize**
- float[] **prevValues**
- int **prevValuesHead**
- float **accumAvgPeakAmpSum**
- int **accumAvgPeakAmpCount**
- float **currentPeakAmp**
- float **norm**

Properties

- float **CurrentAvgAmp** [get]
- float **CurrentPeakAmp** [get, protected set]
- float? **AccumAvgPeakAmp** [get]

3.86.1 Detailed Description

Audio Level Meter.

3.86.2 Member Function Documentation

3.86.2.1 Process()

```
abstract T [ ] Process (
    T[] buf ) [pure virtual]
```

Process a frame of data.

Parameters

<i>buf</i>	Buffer containing input data
------------	------------------------------

Returns

Buffer containing output data or null if frame has been discarded (VAD)

Implements [IProcessor< T >](#).

3.86.2.2 ResetAccumAvgPeakAmp()

```
void ResetAccumAvgPeakAmp ( )
```

Reset AccumAvgPeakAmp.

Implements [AudioUtil.ILevelMeter](#).

3.87 AudioUtil.LevelMeterDummy Class Reference

Dummy Audio Level Meter that doesn't actually do anything.

Inherits [AudioUtil.ILevelMeter](#).

Public Member Functions

- void [ResetAccumAvgPeakAmp](#) ()
Reset AccumAvgPeakAmp.

Properties

- float **CurrentAvgAmp** [get]
- float **CurrentPeakAmp** [get]
- float **AccumAvgPeakAmp** [get]

3.87.1 Detailed Description

Dummy Audio Level Meter that doesn't actually do anything.

3.87.2 Member Function Documentation

3.87.2.1 ResetAccumAvgPeakAmp()

```
void ResetAccumAvgPeakAmp ( )
```

Reset AccumAvgPeakAmp.

Implements [AudioUtil.ILevelMeter](#).

3.88 AudioUtil.LevelMeterFloat Class Reference

[LevelMeter](#) specialization for float audio.

Inherits [AudioUtil.LevelMeter< float >](#).

Public Member Functions

- [LevelMeterFloat](#) (int samplingRate, int numChannels)
Create new [LevelMeterFloat](#) instance.
- override float[] **Process** (float[] buf)

Additional Inherited Members

3.88.1 Detailed Description

[LevelMeter](#) specialization for float audio.

3.88.2 Constructor & Destructor Documentation

3.88.2.1 LevelMeterFloat()

```
LevelMeterFloat (
    int samplingRate,
    int numChannels )
```

Create new [LevelMeterFloat](#) instance.

Parameters

<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>numChannels</i>	Number of channels in the audio signal.

3.89 AudioUtil.LevelMeterShort Class Reference

[LevelMeter](#) specialization for short audio.

Inherits [AudioUtil.LevelMeter< short >](#).

Public Member Functions

- [LevelMeterShort](#) (int *samplingRate*, int *numChannels*)
Create new [LevelMeterShort](#) instance.
- override short[] **Process** (short[] *buf*)

Additional Inherited Members

3.89.1 Detailed Description

[LevelMeter](#) specialization for short audio.

3.89.2 Constructor & Destructor Documentation

3.89.2.1 LevelMeterShort()

```
LevelMeterShort (  
    int samplingRate,  
    int numChannels )
```

Create new [LevelMeterShort](#) instance.

Parameters

<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>numChannels</i>	Number of channels in the audio signal.

3.90 LoadBalancingTransport Class Reference

Extends LoadBalancingClient with media streaming functionality.

Inherits LoadBalancingClient, [IVoiceTransport](#), [ILogger](#), and IDisposable.

Inherited by [LoadBalancingTransport2](#).

Public Member Functions

- virtual int **GetPayloadFragmentSize** ([SendFrameParams](#) par)
- void **LogError** (string fmt, params object[] args)
- void **LogWarning** (string fmt, params object[] args)
- void **LogInfo** (string fmt, params object[] args)
- void **LogDebug** (string fmt, params object[] args)
- bool **IsChannelJoined** (int channelId)
- [LoadBalancingTransport](#) ([ILogger](#) logger=null, [ConnectionProtocol](#) connectionProtocol=[ConnectionProtocol.Udp](#), bool cppCompatibilityMode=false)
Initializes a new [LoadBalancingTransport](#).
- new void [Service](#) ()
This method dispatches all available incoming commands and then sends this client's outgoing commands. Call this method regularly (2 to 20 times a second).
- virtual bool **ChangeAudioGroups** (byte[] groupsToRemove, byte[] groupsToAdd)
- void **SendVoiceInfo** ([LocalVoice](#) voice, int channelId, bool targetMe, int[] targetPlayers)
- void **SendVoiceRemove** ([LocalVoice](#) voice, int channelId, bool targetMe, int[] targetPlayers)
- void **SendFrame** (ArraySegment< byte > data, FrameFlags flags, byte evNumber, byte frNumber, byte voiceld, int channelId, [SendFrameParams](#) par)
- string **ChannelIdStr** (int channelId)
- string **PlayerIdStr** (int playerId)
- void [Dispose](#) ()
Releases all resources used by the [LoadBalancingTransport](#) instance.

Protected Member Functions

- virtual object **buildFrameMessage** (byte voiceld, byte evNumber, byte frNumber, ArraySegment< byte > data, FrameFlags flags)
- virtual void **onEventActionVoiceClient** (EventData ev)

Protected Attributes

- [VoiceClient](#) **voiceClient**
- readonly bool **cppCompatibilityMode**
- virtual byte **FrameCode** => [VoiceEvent.Code](#)

Properties

- [VoiceClient](#) **VoiceClient** [get]
The [VoiceClient](#) implementation associated with this [LoadBalancingTransport](#).

3.90.1 Detailed Description

Extends LoadBalancingClient with media streaming functionality.

Use your normal LoadBalancing workflow to join a [Voice](#) room. All standard LoadBalancing features are available. Use [VoiceClient](#) to work with media streams.

3.90.2 Constructor & Destructor Documentation

3.90.2.1 LoadBalancingTransport()

```
LoadBalancingTransport (
    ILogger logger = null,
    ConnectionProtocol connectionProtocol = ConnectionProtocol.Udp,
    bool cppCompatibilityMode = false )
```

Initializes a new [LoadBalancingTransport](#).

Parameters

<i>logger</i>	ILogger instance. If null, this instance LoadBalancingClient.DebugReturn implementation is used.
<i>connectionProtocol</i>	Connection protocol (UDP or TCP). ConnectionProtocol
<i>cppCompatibilityMode</i>	Use a protocol compatible with Voice C++ API.

3.90.3 Member Function Documentation

3.90.3.1 Dispose()

```
void Dispose ( )
```

Releases all resources used by the [LoadBalancingTransport](#) instance.

3.90.3.2 Service()

```
new void Service ( )
```

This method dispatches all available incoming commands and then sends this client's outgoing commands. Call this method regularly (2 to 20 times a second).

3.90.4 Property Documentation

3.90.4.1 VoiceClient

`VoiceClient VoiceClient [get]`

The [VoiceClient](#) implementation associated with this [LoadBalancingTransport](#).

3.91 LoadBalancingTransport2 Class Reference

Variant of [LoadBalancingTransport](#). Aims to be non-alloc at the cost of breaking compatibility with older clients.

Inherits [LoadBalancingTransport](#).

Public Member Functions

- **LoadBalancingTransport2** ([ILogger](#) logger=null, [ConnectionProtocol](#) connectionProtocol=[ConnectionProtocol.Udp](#), bool cppCompatibilityMode=false)
- override int **GetPayloadFragmentSize** ([SendFrameParams](#) par)

Protected Member Functions

- override object **buildFrameMessage** (byte voiceld, byte evNumber, byte frNumber, [ArraySegment< byte >](#) data, [FrameFlags](#) flags)
- override void **onEventActionVoiceClient** ([EventData](#) ev)

Protected Attributes

- override byte **FrameCode** => [VoiceEvent.FrameCode](#)

Additional Inherited Members

3.91.1 Detailed Description

Variant of [LoadBalancingTransport](#). Aims to be non-alloc at the cost of breaking compatibility with older clients.

3.92 LocalVoice Class Reference

Represents outgoing data stream.

Inherits [IDisposable](#).

Inherited by [LocalVoiceAudioDummy](#), and [LocalVoiceFramed< T >](#).

Public Member Functions

- void **SendSpacingProfileStart** ()
- void **RemoveSelf** ()
Remove this voice from it's [VoiceClient](#) (using [VoiceClient.RemoveLocalVoice](#))
- virtual void **Dispose** ()

Static Public Attributes

- const int **DATA_POOL_CAPACITY** = 50

Protected Member Functions

- bool **targetExits** (bool targetMe, int[] targetPlayers)
- void **sendVoiceInfoAndConfigFrame** (bool targetMe, int[] targetPlayers)
- void **sendVoiceRemove** (bool targetMe, int[] targetPlayers)

Protected Attributes

- int[] **targetPlayers_**
- [VoiceInfo](#) **info**
- [IEncoder](#) **encoder**
- [VoiceClient](#) **voiceClient**
- bool **threadingEnabled**
- [ArraySegment< byte >](#) **configFrame**
- volatile bool **disposed**
- object **disposeLock** = new object()
- bool **isJoined** => voiceClient != null && voiceClient.transport.IsChannelJoined(this.channelId)

Properties

- [VoiceInfo](#) **Info** [get]
Returns Info structure assigned on local voice cration.
- bool **TransmitEnabled** [get, set]
If true, stream data broadcasted.
- bool **IsCurrentlyTransmitting** [get]
Returns true if stream broadcasts.
- int **FramesSent** [get]
Sent frames counter.
- int **FramesSentFragmented** [get]
Sent fragmented frames counter.
- int **FramesSentFragments** [get]
Sent frames fragments counter.
- int **FramesSentBytes** [get]
Sent frames bytes counter.
- bool **Reliable** [get, set]
Send data reliable. See also [VoiceCreateOptions.Reliable](#).
- bool **Encrypt** [get, set]
Send data encrypted. See also [VoiceCreateOptions.Encrypt](#).

- bool **Fragment** [get, set]
Split frames into fragments according to the size provided by the Transport. See also [VoiceCreateOptions.Fragment](#).
- int **FEC** [get, set]
Forward Error Correction control. See also [VoiceCreateOptions.FEC](#).
- [IServiceable LocalUserServiceable](#) [get, set]
Optional user object attached to [LocalVoice](#). its `Service()` will be called at each [VoiceClient.Service\(\)](#) call.
- byte **Group** [get, set]
- byte **InterestGroup** [get, set]
If `InterestGroup != 0`, streaming only to the players subscribed to this group (if supported by the transport). See also [VoiceCreateOptions.InterestGroup](#).
- bool **DebugEchoMode** [get, set]
If true, outgoing stream routed back to client via server same way as for remote client's streams. See also [VoiceCreateOptions.DebugEchoMode](#).
- int[]?? **TargetPlayers** [get, set]
If `TargetPlayers` is not null, sending voice info and streaming only to clients having player numbers specified in the array (if supported by transport). See also [VoiceCreateOptions.TargetPlayers](#).
- string **SendSpacingProfileDump** [get]
- int **SendSpacingProfileMax** [get]
Logs input frames time spacing profiling results. Do not call frequently.
- byte **ID** [get]
- byte **EvNumber** [get]
- string **shortName** [get]
- string **Name** [get]
- string **LogPrefix** [get]

3.92.1 Detailed Description

Represents outgoing data stream.

3.92.2 Member Function Documentation

3.92.2.1 RemoveSelf()

```
void RemoveSelf ( )
```

Remove this voice from it's [VoiceClient](#) (using [VoiceClient.RemoveLocalVoice](#)

3.92.3 Property Documentation

3.92.3.1 DebugEchoMode

```
bool DebugEchoMode [get], [set]
```

If true, outgoing stream routed back to client via server same way as for remote client's streams. See also [VoiceCreateOptions.DebugEchoMode](#).

This functionality availability depends on transport.

3.92.3.2 Encrypt

```
bool Encrypt [get], [set]
```

Send data encrypted. See also [VoiceCreateOptions.Encrypt](#).

3.92.3.3 FEC

```
int FEC [get], [set]
```

Forward Error Correction control. See also [VoiceCreateOptions.FEC](#).

3.92.3.4 Fragment

```
bool Fragment [get], [set]
```

Split frames into fragments according to the size provided by the Transport. See also [VoiceCreateOptions.Fragment](#).

3.92.3.5 FramesSent

```
int FramesSent [get]
```

Sent frames counter.

3.92.3.6 FramesSentBytes

```
int FramesSentBytes [get]
```

Sent frames bytes counter.

3.92.3.7 FramesSentFragmented

```
int FramesSentFragmented [get]
```

Sent fragmented frames counter.

3.92.3.8 FramesSentFragments

```
int FramesSentFragments [get]
```

Sent frames fragments counter.

3.92.3.9 Info

```
VoiceInfo Info [get]
```

Returns Info structure assigned on local voice cration.

3.92.3.10 InterestGroup

```
byte InterestGroup [get], [set]
```

If InterestGroup != 0, streaming only to the players subscribed to this group (if supported by the transport). See also [VoiceCreateOptions.InterestGroup](#).

A remote voice is created even if the remote player is not subscribed to the InterestGroup. Use [VoiceCreateOptions.TargetPlayers](#) and [TargetPlayers](#) to completely hide the existence of [LocalVoice](#) from the remote player./>

3.92.3.11 IsCurrentlyTransmitting

```
bool IsCurrentlyTransmitting [get]
```

Returns true if stream broadcasts.

3.92.3.12 LocalUserServiceable

```
IServiceable LocalUserServiceable [get], [set]
```

Optional user object attached to [LocalVoice](#). its Service() will be called at each [VoiceClient.Service\(\)](#) call.

3.92.3.13 Reliable

```
bool Reliable [get], [set]
```

Send data reliable. See also [VoiceCreateOptions.Reliable](#).

3.92.3.14 SendSpacingProfileMax

```
int SendSpacingProfileMax [get]
```

Logs input frames time spacing profiling results. Do not call frequently.

3.92.3.15 TargetPlayers

```
int []?? TargetPlayers [get], [set]
```

If TargetPlayers is not null, sending voice info and streaming only to clients having player numbers specified in the array (if supported by transport). See also [VoiceCreateOptions.TargetPlayers](#).

TargetPlayers update triggers the sending of voice info to added players and voice remove to removed. Depending on the transport, TargetPlayers may disregard [InterestGroup](#): the remote player whos number is in TargetPlayers, receives the stream even if not subscribed to the interest group. If the local player number is in TargetPlayers, it works like [DebugEchoMode](#). Using both DebugEchoMode and TargetPlayers at the same time to route the stream back to the sender leads to an inconsistent state after one of the options is switched off: the voice is removed but the frames are still delivered.

3.92.3.16 TransmitEnabled

```
bool TransmitEnabled [get], [set]
```

If true, stream data broadcasted.

3.93 LocalVoiceAudio< T > Class Template Reference

Outgoing audio stream.

Inherits [LocalVoiceFramed< T >](#), and [ILocalVoiceAudio](#).

Public Member Functions

- void [VoiceDetectorCalibrate](#) (int durationMs, Action< float > onCalibrated=null)
Trigger voice detector calibration process.

Protected Member Functions

- void **initBuiltinProcessors** ()

Protected Attributes

- [AudioUtil.VoiceDetector](#)< T > **voiceDetector**
- [AudioUtil.VoiceDetectorCalibration](#)< T > **voiceDetectorCalibration**
- [AudioUtil.LevelMeter](#)< T > **levelMeter**
- int **channels**

Properties

- virtual [AudioUtil.IVoiceDetector](#) **VoiceDetector** [get]
- virtual [AudioUtil.ILevelMeter](#) **LevelMeter** [get]
- bool [VoiceDetectorCalibrating](#) [get]

True if the VoiceDetector is currently calibrating.

Additional Inherited Members

3.93.1 Detailed Description

Outgoing audio stream.

3.93.2 Member Function Documentation

3.93.2.1 VoiceDetectorCalibrate()

```
void VoiceDetectorCalibrate (
    int durationMs,
    Action< float > onCalibrated = null )
```

Trigger voice detector calibration process.

While calibrating, keep silence. [Voice](#) detector sets threshold basing on measured background noise level.

Parameters

<i>durationMs</i>	Duration of calibration in milliseconds.
<i>onCalibrated</i>	Called when calibration is complete. Parameter is new threshold value.

Implements [ILocalVoiceAudio](#).

3.93.3 Property Documentation

3.93.3.1 VoiceDetectorCalibrating

`bool VoiceDetectorCalibrating [get]`

True if the VoiceDetector is currently calibrating.

3.94 LocalVoiceAudioDummy Class Reference

Dummy [LocalVoiceAudio](#)

Inherits [LocalVoice](#), and [ILocalVoiceAudio](#).

Public Member Functions

- void [VoiceDetectorCalibrate](#) (int durationMs, Action< float > onCalibrated=null)
Trigger voice detector calibration process.

Static Public Attributes

- static [LocalVoiceAudioDummy Dummy](#) = new [LocalVoiceAudioDummy](#)()
A Dummy [LocalVoiceAudio](#) instance.

Properties

- [AudioUtil.IVoiceDetector VoiceDetector](#) [get]
- [AudioUtil.ILevelMeter LevelMeter](#) [get]
- bool [VoiceDetectorCalibrating](#) [get]

Additional Inherited Members

3.94.1 Detailed Description

Dummy [LocalVoiceAudio](#)

For testing, this [LocalVoiceAudio](#) implementation features a [AudioUtil.VoiceDetectorDummy](#) and a [AudioUtil.LevelMeterDummy](#)

3.94.2 Member Function Documentation

3.94.2.1 VoiceDetectorCalibrate()

```
void VoiceDetectorCalibrate (
    int durationMs,
    Action< float > onCalibrated = null )
```

Trigger voice detector calibration process.

While calibrating, keep silence. [Voice](#) detector sets threshold based on measured background noise level.

Parameters

<i>durationMs</i>	Duration of calibration (in milliseconds).
<i>onCalibrated</i>	Called when calibration is complete. Parameter is new threshold value.

Implements [ILocalVoiceAudio](#).

3.94.3 Member Data Documentation

3.94.3.1 Dummy

```
LocalVoiceAudioDummy Dummy = new LocalVoiceAudioDummy() [static]
```

A Dummy [LocalVoiceAudio](#) instance.

3.95 LocalVoiceAudioFloat Class Reference

Specialization of [LocalVoiceAudio<T>](#) for float audio

Inherits [LocalVoiceAudio< float >](#).

Additional Inherited Members

3.95.1 Detailed Description

Specialization of [LocalVoiceAudio<T>](#) for float audio

3.96 LocalVoiceAudioShort Class Reference

Specialization of [LocalVoiceAudio<T>](#) for short audio

Inherits [LocalVoiceAudio< short >](#).

Additional Inherited Members

3.96.1 Detailed Description

Specialization of [LocalVoiceAudio<T>](#) for short audio

3.97 LocalVoiceFramed< T > Class Template Reference

Typed re-framing [LocalVoice](#)

Inherits [LocalVoice](#).

Inherited by [LocalVoiceAudio< T >](#).

Public Member Functions

- void [AddPostProcessor](#) (params [IProcessor< T >\[\]](#) processors)
Adds processors after any built-in processors and everything added with AddPreProcessor.
- void [AddPreProcessor](#) (params [IProcessor< T >\[\]](#) processors)
Adds processors before built-in processors and everything added with AddPostProcessor.
- void [RemoveProcessor](#) (params [IProcessor< T >\[\]](#) processors)
Adds processors before built-in processors and everything added with AddPostProcessor.
- void [ClearProcessors](#) ()
Clears all processors in pipeline including built-in resampling. User should add at least resampler processor after call.
- void [PushDataAsync](#) (T[] buf)
Asynchronously push data into this stream.
- void [PushData](#) (T[] buf)
Synchronously push data into this stream.
- override void [Dispose](#) ()
Releases resources used by the LocalVoiceFramed<T> instance. Buffers used for asynchronous push will be disposed in encoder thread's 'finally'.

Protected Member Functions

- T[] [processFrame](#) (T[] buf, int p0, int p1)

Properties

- [FactoryPrimitiveArrayPool< T > BufferFactory](#) [get]
<see cref="PushData(T[])" and />.
- bool [PushDataAsyncReady](#) [get]
Whether this LocalVoiceFramed has capacity for more data buffers to be pushed asynchronously.

Additional Inherited Members

3.97.1 Detailed Description

Typed re-framing [LocalVoice](#)

Consumes data in array buffers of arbitrary length. Repacks them in frames of [VoiceInfo.FrameSize](#) length for further processing and encoding.

3.97.2 Member Function Documentation

3.97.2.1 AddPostProcessor()

```
void AddPostProcessor (
    params IProcessor< T >\[\] processors )
```

Adds processors after any built-in processors and everything added with AddPreProcessor.

Parameters

<i>processors</i>	
-------------------	--

3.97.2.2 AddPreProcessor()

```
void AddPreProcessor (
    params IProcessor< T >[] processors )
```

Adds processors before built-in processors and everything added with `AddPostProcessor`.

Parameters

<i>processors</i>	
-------------------	--

3.97.2.3 ClearProcessors()

```
void ClearProcessors ( )
```

Clears all processors in pipeline including built-in resampling. User should add at least resampler processor after call.

3.97.2.4 Dispose()

```
override void Dispose ( ) [virtual]
```

Releases resources used by the `LocalVoiceFramed<T>` instance. Buffers used for asynchronous push will be disposed in encoder thread's 'finally'.

Reimplemented from [LocalVoice](#).

3.97.2.5 PushData()

```
void PushData (
    T[] buf )
```

Synchronously push data into this stream.

3.97.2.6 PushDataAsync()

```
void PushDataAsync (
    T[] buf )
```

Asynchronously push data into this stream.

3.97.2.7 RemoveProcessor()

```
void RemoveProcessor (
    params IProcessor< T >[] processors )
```

Adds processors before built-in processors and everything added with AddPostProcessor.

Parameters

<i>processors</i>	
-------------------	--

3.97.3 Property Documentation

3.97.3.1 BufferFactory

```
FactoryPrimitiveArrayPool<T> BufferFactory [get]
```

<see cref="PushData(T[])" and />.

3.97.3.2 PushDataAsyncReady

```
bool PushDataAsyncReady [get]
```

Wether this [LocalVoiceFramed](#) has capacity for more data buffers to be pushed asynchronously.

3.98 Logger Class Reference

Inherits [ILogger](#).

Public Member Functions

- void **LogError** (string fmt, params object[] args)
- void **LogWarning** (string fmt, params object[] args)
- void **LogInfo** (string fmt, params object[] args)
- void **LogDebug** (string fmt, params object[] args)

3.99 MicAmplifier Class Reference

Inherits [VoiceComponent](#).

Properties

- float **AmplificationFactor** [get, set]

Additional Inherited Members

3.100 MicAmplifierFloat Class Reference

Inherits [IProcessor< float >](#).

Public Member Functions

- **MicAmplifierFloat** (float amplificationFactor)
- float[] **Process** (float[] buf)
- void **Dispose** ()

Properties

- float **AmplificationFactor** [get, set]
- bool **Disabled** [get, set]

3.101 MicAmplifierShort Class Reference

Inherits [IProcessor< short >](#).

Public Member Functions

- **MicAmplifierShort** (float amplificationFactor)
- short[] **Process** (short[] buf)
- void **Dispose** ()

Properties

- float **AmplificationFactor** [get, set]
- bool **Disabled** [get, set]

3.102 MicrophonePermission Class Reference

Helper to request Microphone permission on Android or iOS.

Inherits [VoiceComponent](#).

Public Member Functions

- void **InitVoice** ()

Protected Member Functions

- override void **Awake** ()

Properties

- bool? **HasPermission** [get]

Events

- static Action< bool > **MicrophonePermissionCallback**

Additional Inherited Members

3.102.1 Detailed Description

Helper to request Microphone permission on Android or iOS.

3.103 MicWrapper Class Reference

Inherits [IAudioReader< float >](#).

Public Member Functions

- **MicWrapper** (string device, int suggestedFrequency, [ILogger](#) logger)
- void **Dispose** ()
- bool **Read** (float[] buffer)

Properties

- int? **SamplingRate** [get]
- int? **Channels** [get]
- string **Error** [get]

3.104 MicWrapperPusher Class Reference

Inherits [IAudioPusher< float >](#).

Public Member Functions

- **MicWrapperPusher** (GameObject parent, string device, int suggestedFrequency, [ILogger](#) logger)
- void **SetCallback** (Action< float[]> callback, [ObjectFactory](#)< float[], int > bufferFactory)
- void **Dispose** ()

Properties

- int? **SamplingRate** [get]
- int? **Channels** [get]
- string **Error** [get]

3.105 MicWrapperPusherOnAudioFilterRead Class Reference

Inherits MonoBehaviour.

Events

- Action< float[], int > **OnAudioFrame**

3.106 MonoPInvokeCallbackAttribute Class Reference

Inherits Attribute.

Public Member Functions

- **MonoPInvokeCallbackAttribute** (Type t)

3.107 ObjectFactory< TType, TInfo > Interface Template Reference

Uniform interface to [ObjectPool<TType, TInfo>](#) and single reusable object.

Inherits [IDisposable](#).

Public Member Functions

- TType **New** ()
- TType **New** (TInfo info)
- void **Free** (TType obj)
- void **Free** (TType obj, TInfo info)

Properties

- TInfo **Info** [get]

3.107.1 Detailed Description

Uniform interface to ObjectPool<TType, TInfo> and single reusable object.

Template Parameters

<i>TType</i>	Object type.
<i>TInfo</i>	Type of property used to check 2 objects identity (like integral length of array).

3.108 ObjectPool< TType, TInfo > Class Template Reference

Generic Pool to re-use objects of a certain type (TType) that optionally match a certain property or set of properties (TInfo).

Inherits IDisposable.

Public Member Functions

- [ObjectPool](#) (int capacity, string name)
Create a new [ObjectPool](#) instance. Does not call [Init\(\)](#).
- [ObjectPool](#) (int capacity, string name, TInfo info)
Create a new [ObjectPool](#) instance with the given info structure. Calls [Init\(\)](#).
- void [Init](#) (TInfo info)
(Re-)Initializes this [ObjectPool](#).
- TType [AcquireOrCreate](#) ()
Acquire an existing object, or create a new one if none are available.
- TType [AcquireOrCreate](#) (TInfo info)
Acquire an existing object (if info matches), or create a new one from the passed info.
- virtual bool [Release](#) (TType obj, TInfo objInfo)
Returns object to pool.
- virtual bool [Release](#) (TType obj)
Returns object to pool, or destroys it if the pool is full.
- void [Dispose](#) ()
Free resources associated with this [ObjectPool](#)

Protected Member Functions

- abstract TType **createObject** (TInfo info)
- abstract void **destroyObject** (TType obj)
- abstract bool **infosMatch** (TInfo i0, TInfo i1)

Protected Attributes

- int **capacity**
- TInfo **info**
- int **pos**
- string **name**

Properties

- TInfo **Info** [get]
The property (info) that objects in this Pool must match.

3.108.1 Detailed Description

Generic Pool to re-use objects of a certain type (TType) that optionally match a certain property or set of properties (TInfo).

Template Parameters

<i>TType</i>	Object type.
<i>TInfo</i>	Type of parameter used to check 2 objects identity (like integral length of array).

3.108.2 Constructor & Destructor Documentation

3.108.2.1 ObjectPool() [1/2]

```
ObjectPool (
    int capacity,
    string name )
```

Create a new **ObjectPool** instance. Does not call **Init()**.

Parameters

<i>capacity</i>	Capacity (size) of the object pool.
<i>name</i>	Name of the object pool.

3.108.2.2 ObjectPool() [2/2]

```
ObjectPool (
    int capacity,
    string name,
    TInfo info )
```

Create a new [ObjectPool](#) instance with the given info structure. Calls [Init\(\)](#).

Parameters

<i>capacity</i>	Capacity (size) of the object pool.
<i>name</i>	Name of the object pool.
<i>info</i>	Info about this Pool's objects.

3.108.3 Member Function Documentation

3.108.3.1 AcquireOrCreate() [1/2]

```
TType AcquireOrCreate ( )
```

Acquire an existing object, or create a new one if none are available.

If it fails to get one from the pool, this will create from the info given in this pool's constructor.

3.108.3.2 AcquireOrCreate() [2/2]

```
TType AcquireOrCreate (
    TInfo info )
```

Acquire an existing object (if info matches), or create a new one from the passed info.

Parameters

<i>info</i>	Info structure to match, or create a new object with.
-------------	---

3.108.3.3 Dispose()

```
void Dispose ( )
```

Free resources associated with this [ObjectPool](#)

3.108.3.4 Init()

```
void Init (
    TInfo info )
```

(Re-)Initializes this [ObjectPool](#).

If there are objects available in this Pool, they will be destroyed. Allocates (Capacity) new Objects.

Parameters

<i>info</i>	Info about this Pool's objects.
-------------	---------------------------------

3.108.3.5 Release() [1/2]

```
virtual bool Release (
    TType obj ) [virtual]
```

Returns object to pool, or destroys it if the pool is full.

Parameters

<i>obj</i>	The object to return to the pool.
------------	-----------------------------------

3.108.3.6 Release() [2/2]

```
virtual bool Release (
    TType obj,
    TInfo objInfo ) [virtual]
```

Returns object to pool.

Parameters

<i>obj</i>	The object to return to the pool.
<i>objInfo</i>	The info structure about obj.

obj is returned to the pool only if objInfo matches this pool's info. Else, it is destroyed.

3.108.4 Property Documentation

3.108.4.1 Info

TInfo Info [get]

The property (info) that objects in this Pool must match.

3.109 OpusCodec Class Reference

Classes

- class [Decoder](#)
- class [Encoder](#)
- class [EncoderFloat](#)
- class [EncoderShort](#)
- class [Factory](#)
- class [Util](#)

Public Types

- enum **FrameDuration**

Properties

- static string **Version** [get]

3.110 PhotonAppSettings Class Reference

Collection of connection-relevant settings, used internally by PhotonNetwork.ConnectUsingSettings.

Inherits ScriptableObject.

Public Member Functions

- void [UseCloud](#) (string cloudAppid, string code="")
Sets appid and region code in the AppSettings. Used in Editor.
- override string [ToString](#) ()
String summary of the AppSettings.

Static Public Member Functions

- static void **LoadOrCreateSettings** ()

Public Attributes

- AppSettings **AppSettings**

Properties

- static [PhotonAppSettings](#) **Instance** [get]

3.110.1 Detailed Description

Collection of connection-relevant settings, used internally by PhotonNetwork.ConnectUsingSettings.

Includes the AppSettings class from the Realtime APIs plus some other, PUN-relevant, settings.

3.110.2 Member Function Documentation

3.110.2.1 ToString()

```
override string ToString ( )
```

String summary of the AppSettings.

3.110.2.2 UseCloud()

```
void UseCloud (
    string cloudAppid,
    string code = "" )
```

Sets appid and region code in the AppSettings. Used in Editor.

3.111 PhotonVoiceCreatedParams Class Reference

Properties

- [Voice.LocalVoice](#) **Voice** [get, set]
- [Voice.IAudioDesc](#) **AudioDesc** [get, set]

3.112 PhotonVoiceLagSimulationGui Class Reference

Inherits MonoBehaviour.

Public Member Functions

- void **Start** ()

3.113 PhotonVoiceStatsGui Class Reference

Basic GUI to show traffic and health statistics of the connection to [Photon](#), toggled by shift+tab.

Inherits [MonoBehaviour](#).

3.113.1 Detailed Description

Basic GUI to show traffic and health statistics of the connection to [Photon](#), toggled by shift+tab.

The shown health values can help identify problems with connection losses or performance. Example: If the time delta between two consecutive `SendOutgoingCommands` calls is a second or more, chances rise for a disconnect being caused by this (because acknowledgments to the server need to be sent in due time).

3.114 PhotonVoiceView Class Reference

Component that should be attached to a networked [PUN](#) prefab that has [PhotonView](#). It will bind remote [Recorder](#) with local [Speaker](#) of the same networked prefab. This component makes automatic voice stream routing easy for players' characters/avatars.

Inherits [VoiceComponent](#).

Protected Member Functions

- override void **Awake** ()

Properties

- [Recorder](#) [RecorderInUse](#) [get]
The Recorder component currently used by this [PhotonVoiceView](#)
- [Speaker](#) [SpeakerInUse](#) [get]
The Speaker component currently used by this [PhotonVoiceView](#)
- bool [IsSpeaking](#) [get]
If true, this [PhotonVoiceView](#) has a Speaker that is currently playing received audio frames from remote audio source
- bool [IsRecording](#) [get]
If true, this [PhotonVoiceView](#) has a Recorder that is currently transmitting audio stream from local audio source

Additional Inherited Members

3.114.1 Detailed Description

Component that should be attached to a networked [PUN](#) prefab that has [PhotonView](#). It will bind remote [Recorder](#) with local [Speaker](#) of the same networked prefab. This component makes automatic voice stream routing easy for players' characters/avatars.

3.114.2 Property Documentation

3.114.2.1 IsRecording

`bool IsRecording [get]`

If true, this [PhotonVoiceView](#) has a Recorder that is currently transmitting audio stream from local audio source

3.114.2.2 IsSpeaking

`bool IsSpeaking [get]`

If true, this [PhotonVoiceView](#) has a Speaker that is currently playing received audio frames from remote audio source

3.114.2.3 RecorderInUse

`Recorder RecorderInUse [get]`

The Recorder component currently used by this [PhotonVoiceView](#)

3.114.2.4 SpeakerInUse

`Speaker SpeakerInUse [get]`

The Speaker component currently used by this [PhotonVoiceView](#)

3.115 ImageBufferNative.PlaneSet Struct Reference

Public Member Functions

- **PlaneSet** (int length, IntPtr p0=default(IntPtr), IntPtr p1=default(IntPtr), IntPtr p2=default(IntPtr), IntPtr p3=default(IntPtr))

Properties

- IntPtr **this[int key]** [get, set]
- int **Length** [get]

3.116 Platform Class Reference

Static Public Member Functions

- static [IDeviceEnumerator](#) **CreateAudioInEnumerator** ([ILogger](#) logger)
- static [IAudioInChangeNotifier](#) **CreateAudioInChangeNotifier** (Action callback, [ILogger](#) logger)
- static [IEncoder](#) **CreateDefaultAudioEncoder**< T > ([ILogger](#) logger, [VoiceInfo](#) info)
- static [IAudioDesc](#) **CreateDefaultAudioSource** ([ILogger](#) logger, [DeviceInfo](#) dev, int samplingRate, int channels, object otherParams=null)
- static [IDeviceEnumerator](#) **CreateVideoInEnumerator** ([ILogger](#) logger)
- static [IEncoderDirectImage](#) **CreateDefaultVideoEncoder** ([ILogger](#) logger, [VoiceInfo](#) info)
- static [IDecoderDirect](#)< [ImageBufferNative](#) > **CreateDefaultVideoDecoder** ([ILogger](#) logger, [VoiceInfo](#) info)
- static [IVideoRecorder](#) **CreateDefaultVideoRecorder** ([ILogger](#) logger, [VoiceInfo](#) info, [DeviceInfo](#) camDevice, Action< [IVideoRecorder](#) > onReady)
- static [IVideoPlayer](#) **CreateDefaultVideoPlayer** ([ILogger](#) logger, [VoiceInfo](#) info, Action< [IVideoPlayer](#) > onReady)
- static [IPreviewManager](#) **CreateDefaultPreviewManager** ([ILogger](#) logger)
- static [IVideoRecorder](#) **CreateVideoRecorderUnityTexture** ([ILogger](#) logger, [VoiceInfo](#) info, [DeviceInfo](#) camDevice, Action< [IVideoRecorder](#) > onReady)
- static [IVideoPlayer](#) **CreateVideoPlayerUnityTexture** ([ILogger](#) logger, [VoiceInfo](#) info, Action< [IVideoPlayer](#) > onReady)
- static [IPreviewManager](#) **CreatePreviewManagerUnityTexture** ([ILogger](#) logger)

3.117 AudioOutDelayControl.PlayDelayConfig Struct Reference

Public Attributes

- int **Low**
- int **High**
- int **Max**
- int **SpeedUpPerc**

Static Public Attributes

- static [PlayDelayConfig](#) **Default**

3.117.1 Member Data Documentation

3.117.1.1 Default

[PlayDelayConfig](#) Default [static]

Initial value:

```
= new PlayDelayConfig()
{
    Low = 200,
    High = 200,
    Max = 1000,
    SpeedUpPerc = 5,
}
```

3.118 **PrimitiveArrayPool**< T > Class Template Reference

Pool of Arrays with components of type T, with [ObjectPool](#) info being the array's size.

Inherits [ObjectPool](#)< T[], int >.

Public Member Functions

- **PrimitiveArrayPool** (int capacity, string name)
- **PrimitiveArrayPool** (int capacity, string name, int info)

Protected Member Functions

- override T[] **createObject** (int info)
- override void **destroyObject** (T[] obj)
- override bool **infosMatch** (int i0, int i1)

Additional Inherited Members

3.118.1 Detailed Description

Pool of Arrays with components of type T, with [ObjectPool](#) info being the array's size.

Template Parameters

<i>T</i>	Array element type.
----------	---------------------

3.119 **PunVoiceClient** Class Reference

This class can be used to automatically sync client states between [PUN](#) and [Voice](#). It also finds the Speaker component for a character's voice. For this to work attach a [PhotonVoiceView](#) next to the PhotonView of your player's prefab.

Inherits [VoiceConnection](#).

Public Member Functions

- bool [ConnectAndJoinRoom](#) ()
Connect voice client to [Photon](#) servers and join a [Voice](#) room
- void [Disconnect](#) ()
Disconnect voice client from all [Photon](#) servers

Public Attributes

- bool [AutoConnectAndJoin](#) = true
Auto connect voice client and join a voice room when [PUN](#) client is joined to a [PUN](#) room
- bool [AutoLeaveAndDisconnect](#) = true
Auto disconnect voice client when [PUN](#) client is not joined to a [PUN](#) room

Static Public Attributes

- const string [VoiceRoomNameSuffix](#) = "_voice_"
Suffix for voice room names appended to [PUN](#) room names.

Protected Member Functions

- virtual void **Start** ()
- override void **OnDestroy** ()
- override void **OnVoiceStateChanged** ([ClientState](#) fromState, [ClientState](#) toState)
- override [Speaker](#) **InstantiateSpeakerForRemoteVoice** (int playerId, byte voiceld, object userData)

Properties

- static [PunVoiceClient Instance](#) [get]
Singleton instance for [PunVoiceClient](#)
- bool [UsePunAppSettings](#) [get, set]
Whether or not to use the [Voice](#) AppId and all the other AppSettings from [PUN](#)'s PhotonServerSettings Scriptable↔ Object singleton in the [Voice](#) client/app.
- bool [UsePunAuthValues](#) [get, set]
Whether or not to use the same PhotonNetwork.AuthValues in PunVoiceClient.Instance.Client.AuthValues. This means that the same UserID will be used in both clients. If custom authentication is used and setup in [PUN](#) app, the same configuration should be done for the [Voice](#) app.

Additional Inherited Members

3.119.1 Detailed Description

This class can be used to automatically sync client states between [PUN](#) and [Voice](#). It also finds the [Speaker](#) component for a character's voice. For this to work attach a [PhotonVoiceView](#) next to the PhotonView of your player's prefab.

3.119.2 Member Function Documentation

3.119.2.1 ConnectAndJoinRoom()

```
bool ConnectAndJoinRoom ( )
```

Connect voice client to [Photon](#) servers and join a [Voice](#) room

Returns

If true, connection command send from client

3.119.2.2 Disconnect()

```
void Disconnect ( )
```

Disconnect voice client from all [Photon](#) servers

3.119.3 Member Data Documentation

3.119.3.1 AutoConnectAndJoin

```
bool AutoConnectAndJoin = true
```

Auto connect voice client and join a voice room when [PUN](#) client is joined to a [PUN](#) room

3.119.3.2 AutoLeaveAndDisconnect

```
bool AutoLeaveAndDisconnect = true
```

Auto disconnect voice client when [PUN](#) client is not joined to a [PUN](#) room

3.119.3.3 VoiceRoomNameSuffix

```
const string VoiceRoomNameSuffix = "_voice_" [static]
```

Suffix for voice room names appended to [PUN](#) room names.

3.119.4 Property Documentation

3.119.4.1 Instance

`PunVoiceClient` Instance [static], [get]

Singleton instance for `PunVoiceClient`

3.119.4.2 UsePunAppSettings

`bool UsePunAppSettings` [get], [set]

Whether or not to use the `Voice` AppId and all the other AppSettings from `PUN`'s `PhotonServerSettings` Scriptable↔ Object singleton in the `Voice` client/app.

3.119.4.3 UsePunAuthValues

`bool UsePunAuthValues` [get], [set]

Whether or not to use the same `PhotonNetwork.AuthValues` in `PunVoiceClient.Instance.Client.AuthValues`. This means that the same `UserID` will be used in both clients. If custom authentication is used and setup in `PUN` app, the same configuration should be done for the `Voice` app.

3.120 RawCodec Class Reference

Classes

- class `Decoder`
- class `Encoder`
- class `ShortToFloat`

3.121 Recorder Class Reference

Component representing outgoing audio stream in scene.

Inherits `VoiceComponent`.

Public Types

- enum `InputSourceType`
- enum `MicType`

Public Member Functions

- bool [RestartRecording](#) ()
Restarts recording if Recorder.IsRecording is true
- void [VoiceDetectorCalibrate](#) (int durationMs, Action< float > detectionEndedCallback=null)
Trigger voice detector calibration process. While calibrating, keep silence. Voice detector sets threshold basing on measured background noise level.
- bool [SetIosAudioSessionParameters](#) (IOS.AudioSessionParameters asp)
Sets the AudioSessionParameters for iOS audio initialization when Photon MicrophoneType is used.
- bool [SetIosAudioSessionParameters](#) (IOS.AudioSessionCategory category, IOS.AudioSessionMode mode, IOS.AudioSessionCategoryOption[] options)
Sets the AudioSessionParameters for iOS audio initialization when Photon MicrophoneType is used.
- bool [SetAndroidNativeMicrophoneSettings](#) (bool aec=false, bool agc=false, bool ns=false)
Sets the native Android audio input settings when the Photon microphone type is used.
- bool [ResetLocalAudio](#) ()
Resets audio session and parameters locally to fix broken recording due to system configuration modifications or audio interruptions or audio routing changes.

Static Public Attributes

- const int **MIN_OPUS_BITRATE** = 6000
- const int **MAX_OPUS_BITRATE** = 510000

Protected Member Functions

- virtual void **SendPhotonVoiceCreatedMessage** ()
- void **Update** ()

Properties

- bool [TransmitEnabled](#) [get, set]
If true, audio transmission is enabled.
- bool [Encrypt](#) [get, set]
If true, voice stream is sent encrypted.
- bool [DebugEchoMode](#) [get, set]
If true, outgoing stream routed back to client via server same way as for remote client's streams.
- bool [ReliableMode](#) [get, set]
If true, stream data sent in reliable mode.
- bool [VoiceDetection](#) [get, set]
If true, voice detection enabled.
- float [VoiceDetectionThreshold](#) [get, set]
Voice detection threshold (0..1, where 1 is full amplitude).
- int [VoiceDetectionDelayMs](#) [get, set]
Keep detected state during this time after signal level dropped below threshold. Default is 500ms
- object [UserData](#) [get, set]
Custom user object to be sent in the voice stream info event.
- Func< [IAudioDesc](#) > [InputFactory](#) [get, set]
Set the method returning new Voice.IAudioDesc instance to be assigned to a new voice created with Source set to Factory
- [AudioUtil.IVoiceDetector?](#) [VoiceDetector](#) [get]

- Returns voice activity detector for recorder's audio stream.*
- byte [InterestGroup](#) [get, set]
Target interest group that will receive transmitted audio.
- int[] [TargetPlayers](#) [get, set]
Target players which will receive transmitted audio.
- bool [IsCurrentlyTransmitting](#) [get]
Returns true if audio stream broadcasts.
- [AudioUtil.ILevelMeter?](#) [LevelMeter](#) [get]
Level meter utility.
- bool [VoiceDetectorCalibrating](#) [get]
If true, voice detector calibration is in progress.
- [ILocalVoiceAudio](#) [voiceAudio](#) [get]
- InputSourceType [SourceType](#) [get, set]
Audio data source.
- MicType [MicrophoneType](#) [get, set]
Which microphone API to use when the Source is set to Microphone.
- AudioClip [AudioClip](#) [get, set]
Source audio clip.
- bool [LoopAudioClip](#) [get, set]
Loop playback for audio clip sources.
- SamplingRate [SamplingRate](#) [get, set]
Outgoing audio stream sampling rate.
- OpusCodec.FrameDuration [FrameDuration](#) [get, set]
Outgoing audio stream encoder delay.
- int [Bitrate](#) [get, set]
Outgoing audio stream bitrate.
- bool [RecordingEnabled](#) [get, set]
Gets or sets whether this [Recorder](#) is recording audio to be transmitted.
- bool [StopRecordingWhenPaused](#) [get, set]
If true, stop recording when paused resume/restart when un-paused.
- bool [UseOnAudioFilterRead](#) [get, set]
If true, recording will make use of [Unity](#)'s OnAudioFiltterRead callback from a muted local AudioSource.
- bool [UseMicrophoneTypeFallback](#) [get, set]
If true, if recording fails to start with [Unity](#) microphone type, [Photon](#) microphone type is used -if available- as a fallback and vice versa.
- bool [RecordWhenJoined](#) [get, set]
If true, recording starts when joining the room and stops when leaving the room.
- [DeviceInfo](#) [MicrophoneDevice](#) [get, set]
- bool [AndroidMicrophoneAGC](#) [get]
- bool [AndroidMicrophoneAEC](#) [get]
- bool [AndroidMicrophoneNS](#) [get]

Additional Inherited Members

3.121.1 Detailed Description

Component representing outgoing audio stream in scene.

3.121.2 Member Function Documentation

3.121.2.1 ResetLocalAudio()

```
bool ResetLocalAudio ( )
```

Resets audio session and parameters locally to fix broken recording due to system configuration modifications or audio interruptions or audio routing changes.

Returns

If reset is done.

3.121.2.2 RestartRecording()

```
bool RestartRecording ( )
```

Restarts recording if Recorder.IsRecording is true

3.121.2.3 SetAndroidNativeMicrophoneSettings()

```
bool SetAndroidNativeMicrophoneSettings (
    bool aec = false,
    bool agc = false,
    bool ns = false )
```

Sets the native Android audio input settings when the [Photon](#) microphone type is used.

Parameters

<i>aec</i>	Acoustic Echo Cancellation
<i>agc</i>	Automatic Gain Control
<i>ns</i>	Noise Suppression

Returns

If a change has been made.

3.121.2.4 SetIosAudioSessionParameters() [1/2]

```
bool SetIosAudioSessionParameters (
    IOS.AudioSessionCategory category,
    IOS.AudioSessionMode mode,
    IOS.AudioSessionCategoryOption[] options )
```

Sets the AudioSessionParameters for iOS audio initialization when [Photon](#) MicrophoneType is used.

Parameters

<i>category</i>	Audio session category to be used.
<i>mode</i>	Audio session mode to be used.
<i>options</i>	Audio session category options to be used

Returns

If a change has been made.

3.121.2.5 SetIosAudioSessionParameters() [2/2]

```
bool SetIosAudioSessionParameters (
    IOS.AudioSessionParameters asp )
```

Sets the AudioSessionParameters for iOS audio initialization when [Photon](#) MicrophoneType is used.

Parameters

<i>asp</i>	You can use custom value or one from presets, IOS.AudioSessionParametersPresets
------------	---

Returns

If a change has been made.

3.121.2.6 VoiceDetectorCalibrate()

```
void VoiceDetectorCalibrate (
    int durationMs,
    Action< float > detectionEndedCallback = null )
```

Trigger voice detector calibration process. While calibrating, keep silence. [Voice](#) detector sets threshold basing on measured background noise level.

Parameters

<i>durationMs</i>	Duration of calibration in milliseconds.
<i>detectionEndedCallback</i>	Callback when VAD calibration ends.

3.121.3 Property Documentation

3.121.3.1 AudioClip

`AudioClip AudioClip [get], [set]`

Source audio clip.

3.121.3.2 Bitrate

`int Bitrate [get], [set]`

Outgoing audio stream bitrate.

3.121.3.3 DebugEchoMode

`bool DebugEchoMode [get], [set]`

If true, outgoing stream routed back to client via server same way as for remote client's streams.

Initialized with serialized field and can be updated by Editor at runtime.

3.121.3.4 Encrypt

`bool Encrypt [get], [set]`

If true, voice stream is sent encrypted.

Initialized with serialized field and can be updated by Editor at runtime.

3.121.3.5 FrameDuration

`OpusCodec.FrameDuration FrameDuration [get], [set]`

Outgoing audio stream encoder delay.

3.121.3.6 InputFactory

```
Func<IAudioDesc> InputFactory [get], [set]
```

Set the method returning new [Voice.IAudioDesc](#) instance to be assigned to a new voice created with Source set to Factory

3.121.3.7 InterestGroup

```
byte InterestGroup [get], [set]
```

Target interest group that will receive transmitted audio.

If InterestGroup != 0, recorder's audio data is sent only to clients listening to this group. Initialized with serialized field and can be updated by Editor at runtime.

3.121.3.8 IsCurrentlyTransmitting

```
bool IsCurrentlyTransmitting [get]
```

Returns true if audio stream broadcasts.

3.121.3.9 LevelMeter

```
AudioUtil.ILevelMeter? LevelMeter [get]
```

Level meter utility.

3.121.3.10 LoopAudioClip

```
bool LoopAudioClip [get], [set]
```

Loop playback for audio clip sources.

3.121.3.11 MicrophoneType

```
MicType MicrophoneType [get], [set]
```

Which microphone API to use when the Source is set to Microphone.

3.121.3.12 RecordingEnabled

```
bool RecordingEnabled [get], [set]
```

Gets or sets whether this [Recorder](#) is recording audio to be transmitted.

3.121.3.13 RecordWhenJoined

```
bool RecordWhenJoined [get], [set]
```

If true, recording starts when joining the room and stops when leaving the room.

3.121.3.14 ReliableMode

```
bool ReliableMode [get], [set]
```

If true, stream data sent in reliable mode.

Initialized with serialized field and can be updated by Editor at runtime.

3.121.3.15 SamplingRate

```
SamplingRate SamplingRate [get], [set]
```

Outgoing audio stream sampling rate.

3.121.3.16 SourceType

```
InputSourceType SourceType [get], [set]
```

Audio data source.

3.121.3.17 StopRecordingWhenPaused

```
bool StopRecordingWhenPaused [get], [set]
```

If true, stop recording when paused resume/restart when un-paused.

3.121.3.18 TargetPlayers

```
int [] TargetPlayers [get], [set]
```

Target players which will receive transmitted audio.

Initialized with serialized field and can be updated by Editor at runtime

3.121.3.19 TransmitEnabled

```
bool TransmitEnabled [get], [set]
```

If true, audio transmission is enabled.

3.121.3.20 UseMicrophoneTypeFallback

```
bool UseMicrophoneTypeFallback [get], [set]
```

If true, if recording fails to start with [Unity](#) microphone type, [Photon](#) microphone type is used -if available- as a fallback and vice versa.

3.121.3.21 UseOnAudioFilterRead

```
bool UseOnAudioFilterRead [get], [set]
```

If true, recording will make use of [Unity](#)'s OnAudioFiltlerRead callback from a muted local AudioSource.

If enabled, 3D sounds and voice positioning can be lost.

3.121.3.22 UserData

```
object UserData [get], [set]
```

Custom user object to be sent in the voice stream info event.

3.121.3.23 VoiceDetection

```
bool VoiceDetection [get], [set]
```

If true, voice detection enabled.

3.121.3.24 VoiceDetectionDelayMs

```
int VoiceDetectionDelayMs [get], [set]
```

Keep detected state during this time after signal level dropped below threshold. Default is 500ms

3.121.3.25 VoiceDetectionThreshold

```
float VoiceDetectionThreshold [get], [set]
```

[Voice](#) detection threshold (0..1, where 1 is full amplitude).

3.121.3.26 VoiceDetector

```
AudioUtil.IVoiceDetector? VoiceDetector [get]
```

Returns voice activity detector for recorder's audio stream.

3.121.3.27 VoiceDetectorCalibrating

```
bool VoiceDetectorCalibrating [get]
```

If true, voice detector calibration is in progress.

3.122 RecorderPreset Class Reference

Inherits [VoiceComponent](#).

Classes

- struct [DSP](#)

Public Attributes

- RuntimePlatform **Platform**
- MicType **MicrophoneType**
- bool **DSPEnabled**
- [DSP](#) **DSPSettings**

Protected Member Functions

- override void **Awake** ()

Additional Inherited Members

3.123 RemoteVoiceInfo Class Reference

Information about a remote voice (incoming stream).

Properties

- [VoiceInfo Info](#) [get]
Remote voice info.
- int [ChannelId](#) [get]
ID of channel used for transmission.
- int [PlayerId](#) [get]
Player ID of voice owner.
- byte [VoiceId](#) [get]
Voice ID (unique in the room).

3.123.1 Detailed Description

Information about a remote voice (incoming stream).

3.123.2 Property Documentation

3.123.2.1 ChannelId

`int ChannelId [get]`

ID of channel used for transmission.

3.123.2.2 Info

`VoiceInfo Info [get]`

Remote voice info.

3.123.2.3 PlayerId

```
int PlayerId [get]
```

Player ID of voice owner.

3.123.2.4 Voiceld

```
byte VoiceId [get]
```

Voice ID (unique in the room).

3.124 RemoteVoiceLink Class Reference

Public Member Functions

- **RemoteVoiceLink** ([VoiceInfo](#) info, int playerId, byte voiceId, int channelId, ref [RemoteVoiceOptions](#) options)
- override string **ToString** ()

Public Attributes

- readonly [VoiceInfo](#) **VoiceInfo**
- readonly int **PlayerId**
- readonly byte **VoiceId**
- readonly int **ChannelId**

Events

- Action< [FrameOut](#)< float > > **FloatFrameDecoded**
- Action **RemoteVoiceRemoved**

3.125 RemoteVoiceOptions Struct Reference

Event Actions and other options for a remote voice (incoming stream).

Public Member Functions

- **RemoteVoiceOptions** ([ILogger](#) logger, string logPrefix, [VoiceInfo](#) voiceInfo)
- void **SetOutput** (Action< [FrameOut](#)< float > > output)
Create default audio decoder and register a method to be called when a data frame is decoded.
- void **SetOutput** (Action< [FrameOut](#)< short > > output)
Create default audio decoder and register a method to be called when a data frame is decoded.

Properties

- Action [OnRemoteVoiceRemoveAction](#) [get, set]
Register a method to be called when the remote voice is removed.
- [IDecoder Decoder](#) [get, set]
Remote voice data decoder. Use to set decoder options or override it with user decoder.

3.125.1 Detailed Description

Event Actions and other options for a remote voice (incoming stream).

3.125.2 Member Function Documentation

3.125.2.1 SetOutput() [1/2]

```
void SetOutput (
    Action< FrameOut< float >> output )
```

Create default audio decoder and register a method to be called when a data frame is decoded.

3.125.2.2 SetOutput() [2/2]

```
void SetOutput (
    Action< FrameOut< short >> output )
```

Create default audio decoder and register a method to be called when a data frame is decoded.

3.125.3 Property Documentation

3.125.3.1 Decoder

[IDecoder](#) Decoder [get], [set]

Remote voice data decoder. Use to set decoder options or override it with user decoder.

3.125.3.2 OnRemoteVoiceRemoveAction

Action OnRemoteVoiceRemoveAction [get], [set]

Register a method to be called when the remote voice is removed.

3.126 AudioUtil.Resampler< T > Class Template Reference

Sample-rate conversion Audio Processor.

Inherits [IProcessor< T >](#).

Public Member Functions

- [Resampler](#) (int dstSize, int channels)
Create a new [Resampler](#) instance.
- T[] [Process](#) (T[] buf)
Process a frame of data.
- void **Dispose** ()

Protected Attributes

- T[] **frameResampled**

3.126.1 Detailed Description

Sample-rate conversion Audio Processor.

This processor converts the sample-rate of the source stream. Internally, it uses [AudioUtil.Resample<T>\(T\[\], T\[\], int, int\)](#).

3.126.2 Constructor & Destructor Documentation

3.126.2.1 Resampler()

```
Resampler (
    int dstSize,
    int channels )
```

Create a new [Resampler](#) instance.

Parameters

<i>dstSize</i>	Frame size of a destination frame. Determines output rate.
<i>channels</i>	Number of audio channels expected in both in- and output.

3.126.3 Member Function Documentation

3.126.3.1 Process()

```
T [ ] Process (
    T [ ] buf )
```

Process a frame of data.

Parameters

<i>buf</i>	Buffer containing input data
------------	------------------------------

Returns

Buffer containing output data or null if frame has been discarded (VAD)

Implements [IProcessor< T >](#).

3.127 SaveIncomingStreamToFile Class Reference

Inherits [VoiceComponent](#).

Protected Member Functions

- override void **Awake** ()

Additional Inherited Members

3.128 SaveOutgoingStreamToFile Class Reference

Inherits [VoiceComponent](#).

Additional Inherited Members

3.129 SendFrameParams Struct Reference

Public Member Functions

- **SendFrameParams** (bool targetMe, int [] targetPlayers, byte interestGroup, bool reliable, bool encrypt)

Properties

- bool **TargetMe** [get]
- int[] **TargetPlayers** [get]
- byte **InterestGroup** [get]
- bool **Reliable** [get]
- bool **Encrypt** [get]

3.130 RawCodec.ShortToFloat Class Reference

Public Member Functions

- **ShortToFloat** (Action< [FrameOut](#)< float >> output)
- void **Output** ([FrameOut](#)< short > shortBuf)

3.131 Speaker Class Reference

Inherits [VoiceComponent](#).

Inherited by [SpeakerFMOD](#), and [SpeakerAudioFilterRead](#).

Public Member Functions

- void [RestartPlayback](#) ()
Restarts the audio playback of the linked incoming remote audio stream via AudioSource component.

Protected Member Functions

- override void **Awake** ()
- virtual [IAudioOut](#)< float > **CreateAudioOut** ()
- virtual void **OnDestroy** ()
- void **Update** ()

Protected Attributes

- [IAudioOut](#)< float > **audioOutput**
- [AudioOutDelayControl.PlayDelayConfig](#) **playDelayConfig** = [AudioOutDelayControl.PlayDelayConfig.Default](#)
- bool **restartOnDeviceChange** = true

Properties

- bool `IsPlaying` [get]
Is the speaker playing right now.
- int? `Lag` [get]
The current difference between positions in the buffer of (jittery) stream writer and (clock-driven) audio output reader in ms.
- Action< `Speaker` > `OnRemoteVoiceRemoveAction` [get, set]
Register a method to be called when remote voice removed.
- `RemoteVoiceLink RemoteVoice` [get]
- bool `IsLinked` [get]
Whether or not this `Speaker` has been linked to a remote voice stream.
- `AudioOutDelayControl.PlayDelayConfig PlayDelayConfig` [get, set]
Gets or sets jitter buffer config.
- int `PlayDelay` [get, set]
Gets or sets jitter buffer size in ms.
- bool `RestartOnDeviceChange` [get, set]

Additional Inherited Members

3.131.1 Member Function Documentation

3.131.1.1 RestartPlayback()

```
void RestartPlayback ( )
```

Restarts the audio playback of the linked incoming remote audio stream via AudioSource component.

Returns

True if playback is successfully restarted.

3.131.2 Property Documentation

3.131.2.1 IsLinked

```
bool IsLinked [get]
```

Whether or not this `Speaker` has been linked to a remote voice stream.

3.131.2.2 IsPlaying

```
bool IsPlaying [get]
```

Is the speaker playing right now.

3.131.2.3 Lag

```
int? Lag [get]
```

The current difference between positions in the buffer of (jittery) stream writer and (clock-driven) audio output reader in ms.

3.131.2.4 OnRemoteVoiceRemoveAction

```
Action<Speaker> OnRemoteVoiceRemoveAction [get], [set]
```

Register a method to be called when remote voice removed.

3.131.2.5 PlayDelay

```
int PlayDelay [get], [set]
```

Gets or sets jitter buffer size in ms.

The method updates PlayDelayConfig with reasonable values based on the single value provided. Use [PlayDelayConfig](#) for more precise control.

3.131.2.6 PlayDelayConfig

```
AudioOutDelayControl.PlayDelayConfig PlayDelayConfig [get], [set]
```

Gets or sets jitter buffer config.

Make sure that the new value is fully initialized or built from AudioOutDelayControl.PlayDelayConfig.Default.

3.132 SpeakerAudioFilterRead Class Reference

Inherits [Speaker](#).

Protected Member Functions

- override [IAudioOut](#)< float > **CreateAudioOut** ()

Additional Inherited Members

3.133 SpeakerFMOD Class Reference

Inherits [Speaker](#).

Protected Member Functions

- override [IAudioOut](#)< float > **CreateAudioOut** ()

Additional Inherited Members

3.134 ImageBufferInfo.StrideSet Struct Reference

Public Member Functions

- **StrideSet** (int length, int s0=0, int s1=0, int s2=0, int s3=0)

Properties

- int **this**[int key] [get, set]
- int **Length** [get]

3.135 AudioUtil.TempoUp< T > Class Template Reference

Public Member Functions

- void **Begin** (int channels, int changePerc, int skipGroup)
- int **Process** (T[] s, T[] d)
- int **End** (T[] s)
- int **endFloat** (float[] s)
- int **endShort** (short[] s)

3.136 TestTone Class Reference

Inherits MonoBehaviour.

3.137 AudioUtil.ToneAudioPusher< T > Class Template Reference

[IAudioPusher](#) that provides a constant tone signal.

Inherits [AudioUtil.GeneratorPusher< T >](#).

Public Member Functions

- [ToneAudioPusher](#) (int frequency=440, int bufSizeMs=100, int samplingRate=48000, int channels=1)
Create a new [ToneAudioReader](#) instance

Protected Member Functions

- override int **Gen** (T[] buf, long timeSamples)

Additional Inherited Members

3.137.1 Detailed Description

[IAudioPusher](#) that provides a constant tone signal.

3.137.2 Constructor & Destructor Documentation

3.137.2.1 ToneAudioPusher()

```
ToneAudioPusher (
    int frequency = 440,
    int bufSizeMs = 100,
    int samplingRate = 48000,
    int channels = 1 )
```

Create a new [ToneAudioReader](#) instance

Parameters

<i>frequency</i>	Frequency of the generated tone (in Hz).
<i>bufSizeMs</i>	Size of buffers to push (in milliseconds).
<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>channels</i>	Number of channels in the audio signal.

3.138 AudioUtil.ToneAudioReader< T > Class Template Reference

[IAudioReader](#) that provides a constant tone signal.

Inherits [AudioUtil.GeneratorReader< T >](#).

Public Member Functions

- [ToneAudioReader](#) (Func< double > clockSec=null, double frequency=440, int samplingRate=48000, int channels=1)

Create a new [ToneAudioReader](#) instance

Protected Member Functions

- override int **Gen** (T[] buf, long timeSamples)

Additional Inherited Members

3.138.1 Detailed Description

[IAudioReader](#) that provides a constant tone signal.

Because of current resampling algorithm, the tone is distorted if SamplingRate does not equal encoder sampling rate.

3.138.2 Constructor & Destructor Documentation

3.138.2.1 ToneAudioReader()

```
ToneAudioReader (
    Func< double > clockSec = null,
    double frequency = 440,
    int samplingRate = 48000,
    int channels = 1 )
```

Create a new [ToneAudioReader](#) instance

Parameters

<i>clockSec</i>	Function to get current time in seconds. In Unity , pass in '()' => AudioSettings.dspTime' for better results.
<i>frequency</i>	Frequency of the generated tone (in Hz).
<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>channels</i>	Number of channels in the audio signal.

3.139 UnityAudioOut Class Reference

Inherits [AudioOutDelayControl< float >](#).

Public Member Functions

- **UnityAudioOut** (AudioSource audioSource, PlayDelayConfig playDelayConfig, [ILogger](#) logger, string logPrefix, bool debugInfo)
- override void **OutCreate** (int frequency, int channels, int bufferSamples)
- override void **OutStart** ()
- override void **OutWrite** (float[] data, int offsetSamples)
- override void **Stop** ()

Protected Attributes

- readonly AudioSource **source**
- AudioClip **clip**

Properties

- override long **OutPos** [get]

3.140 UnityLogger Class Reference

Static Public Member Functions

- static void **Log** (DebugLevel level, Object obj, string tag, string objName, string fmt, params object[] args)

3.141 UnityMicrophone Class Reference

A wrapper around UnityEngine.Microphone to be able to safely use Microphone and compile for WebGL.

Static Public Member Functions

- static void **End** (string deviceName)
- static void **GetDeviceCaps** (string deviceName, out int minFreq, out int maxFreq)
- static int **GetPosition** (string deviceName)
- static bool **IsRecording** (string deviceName)
- static AudioClip **Start** (string deviceName, bool loop, int lengthSec, int frequency)
- static string **CheckDevice** ([Voice.ILogger](#) logger, string logPref, string device, int suggestedFrequency, out int frequency)

Properties

- static string[] **devices** [get]

3.141.1 Detailed Description

A wrapper around `UnityEngine.Microphone` to be able to safely use `Microphone` and compile for WebGL.

3.142 UnityVoiceClient Class Reference

Component that represents a [Voice](#) client and manages a simple [Unity](#) integration: a single [Recorder](#) and multiple remote speakers.

Inherits [VoiceConnection](#).

Public Member Functions

- override bool [ConnectUsingSettings](#) (`AppSettings overwriteSettings=null`)
Connect to [Photon](#) server using [Settings](#)

Public Attributes

- override bool **AlwaysUsePrimaryRecorder** => true
- bool [UseVoiceAppSettings](#) = false
Whether or not to use the [Voice](#) AppId and all the other AppSettings from [Fusion](#)'s `RealtimeAppSettings` Scriptable↔ Object singleton in the [Voice](#) client/app.

Protected Member Functions

- virtual void **Start** ()
- override [Speaker](#) **InstantiateSpeakerForRemoteVoice** (int playerId, byte voiceId, object userData)

Additional Inherited Members

3.142.1 Detailed Description

Component that represents a [Voice](#) client and manages a simple [Unity](#) integration: a single [Recorder](#) and multiple remote speakers.

3.142.2 Member Function Documentation

3.142.2.1 ConnectUsingSettings()

```
override bool ConnectUsingSettings (
    AppSettings overwriteSettings = null ) [virtual]
```

Connect to [Photon](#) server using [Settings](#)

Parameters

<code>overwriteSettings</code>	Overwrites Settings before connecting
--------------------------------	---

Returns

If true voice connection command was sent from client

Reimplemented from [VoiceConnection](#).

3.142.3 Member Data Documentation

3.142.3.1 UseVoiceAppSettings

```
bool UseVoiceAppSettings = false
```

Whether or not to use the [Voice](#) AppId and all the other AppSettings from [Fusion](#)'s RealtimeAppSettings Scriptable↔ Object singleton in the [Voice](#) client/app.

3.143 UnsupportedCodecException Class Reference

Exception thrown if an unsupported codec is encountered.

Inherits Exception.

Public Member Functions

- [UnsupportedCodecException](#) (string info, [Codec](#) codec)
Create a new [UnsupportedCodecException](#).

3.143.1 Detailed Description

Exception thrown if an unsupported codec is encountered.

3.143.2 Constructor & Destructor Documentation

3.143.2.1 UnsupportedCodecException()

```
UnsupportedCodecException (
    string info,
    Codec codec )
```

Create a new [UnsupportedCodecException](#).

Parameters

<i>info</i>	The info prepending standard message.
<i>codec</i>	The codec actually encountered.

3.144 UnsupportedPlatformException Class Reference

Exception thrown if an unsupported platform is encountered.

Inherits Exception.

Public Member Functions

- [UnsupportedPlatformException](#) (string subject, string platform=null)
Create a new [UnsupportedPlatformException](#).

3.144.1 Detailed Description

Exception thrown if an unsupported platform is encountered.

3.144.2 Constructor & Destructor Documentation

3.144.2.1 UnsupportedPlatformException()

```
UnsupportedPlatformException (
    string subject,
    string platform = null )
```

Create a new [UnsupportedPlatformException](#).

Parameters

<i>subject</i>	The info prepending standard message.
----------------	---------------------------------------

///

Parameters

<i>platform</i>	Optional platform name.
-----------------	-------------------------

3.145 UnsupportedSampleTypeException Class Reference

Exception thrown if an unsupported audio sample type is encountered.

Inherits [Exception](#).

Public Member Functions

- [UnsupportedSampleTypeException](#) (Type t)
Create a new [UnsupportedSampleTypeException](#).

3.145.1 Detailed Description

Exception thrown if an unsupported audio sample type is encountered.

PhotonVoice generally supports 32-bit floating point ("float") or 16-bit signed integer ("short") audio, but it usually won't be converted automatically due to the high CPU overhead (and potential loss of precision) involved.

3.145.2 Constructor & Destructor Documentation

3.145.2.1 UnsupportedSampleTypeException()

```
UnsupportedSampleTypeException (  
    Type t )
```

Create a new [UnsupportedSampleTypeException](#).

Parameters

<i>t</i>	The sample type actually encountered.
----------	---------------------------------------

3.146 OpusCodec.Util Class Reference

3.147 VideoInEnumerator Class Reference

Inherits [DeviceEnumerator](#).

Public Member Functions

- [VideoInEnumerator](#) ([ILogger](#) logger)

Additional Inherited Members

3.148 VideoInEnumerator Class Reference

Inherits [DeviceEnumeratorBase](#).

Public Member Functions

- **VideoInEnumerator** ([ILogger](#) logger)
- override void **Refresh** ()
- override void **Dispose** ()

Properties

- override string **Error** [get]

Additional Inherited Members

3.149 VoiceClient Class Reference

[Voice](#) client interact with other clients on network via [IVoiceTransport](#).

Inherits [IDisposable](#).

Classes

- struct [CreateOptions](#)

Public Member Functions

- delegate void [RemoteVoiceInfoDelegate](#) (int channelId, int playerId, byte voiceId, [VoiceInfo](#) voiceInfo, ref [RemoteVoiceOptions](#) options)
Remote voice info event delegate.
- IEnumerable< [LocalVoice](#) > [LocalVoicesInChannel](#) (int channelId)
Iterates through copy of all local voices list of given channel.
- void **LogSpacingProfiles** ()
- void **LogStats** ()
- void **SetRemoteVoiceDelayFrames** ([Codec](#) codec, int delayFrames)
- [VoiceClient](#) ([IVoiceTransport](#) transport, [ILogger](#) logger, [CreateOptions](#) opt=default([CreateOptions](#)))
Creates [VoiceClient](#) instance
- void [Service](#) ()
This method dispatches all available incoming commands and then sends this client's outgoing commands. Call this method regularly (2..20 times a second).
- [LocalVoice](#) [CreateLocalVoice](#) ([VoiceInfo](#) voiceInfo, int channelId, [VoiceCreateOptions](#) options=default([VoiceCreateOptions](#)))
Creates basic outgoing stream w/o data processing support. Provided encoder should generate output data stream.

- [LocalVoiceAudio](#)< T > **CreateLocalVoiceAudio**< T > ([VoiceInfo](#) voiceInfo, [IAudioDesc](#) audioSourceDesc, int channelId, [VoiceCreateOptions](#) options=default([VoiceCreateOptions](#)))
- [LocalVoice](#) **CreateLocalVoiceAudioFromSource** ([VoiceInfo](#) voiceInfo, [IAudioDesc](#) source, [AudioSampleType](#) sampleType, int channelId, [VoiceCreateOptions](#) options=default([VoiceCreateOptions](#)))
Creates outgoing audio stream of type automatically assigned and adds procedures (callback or serviceable) for consuming given audio source data. Adds audio specific features (e.g. resampling, level meter) to processing pipeline and to returning stream handler.
- [LocalVoiceVideo](#) **CreateLocalVoiceVideo** ([VoiceInfo](#) voiceInfo, [IVideoRecorder](#) recorder, int channelId, [VoiceCreateOptions](#) options=default([VoiceCreateOptions](#)))
Creates outgoing video stream consuming sequence of image buffers.
- void **RemoveLocalVoice** ([LocalVoice](#) voice)
Removes local voice (outgoing data stream).

Parameters

voice	Handler of outgoing stream to be removed.
-------	---

- void **onJoinChannel** (int channelId)
- void **onJoinAllChannels** ()
- void **onLeaveChannel** (int channel)
- void **onLeaveAllChannels** ()
- void **onPlayerJoin** (int channelId, int playerId)
- void **onPlayerJoin** (int playerId)
- void **onPlayerLeave** (int channelId, int playerId)
- void **onPlayerLeave** (int playerId)
- void **onVoiceInfo** (int channelId, int playerId, byte voiceId, byte eventNumber, [VoiceInfo](#) info)
- void **onVoiceRemove** (int playerId, byte[] voiceIds)
- void **onFrame** (int playerId, byte voiceId, byte evNumber, ref [FrameBuffer](#) receivedBytes, bool isLocalPlayer)
- void **Dispose** ()

Properties

- bool **ThreadingEnabled** = true [get, set]
- int [EventsLost](#) [get, set]
Lost events counter (the number of empty frames sent to the deocder).
- int [FramesLost](#) [get, set]
Lost frames counter (the number of empty frames sent to the deocder).
- int [FramesFragPart](#) [get, set]
The counter of assembled frames, fragments of which are partially missing.
- int [FramesRecovered](#) [get, set]
Recovered frames counter.
- int [FramesMiss](#) [get, set]
Counter of slots between correctly ordered frames.
- int [FramesLate](#) [get, set]
Counter of late (incorrectly ordered) frames.
- int [FramesLateUsed](#) [get]
Counter of late but still used frames.
- int [FramesReceived](#) [get]
Received frames counter.
- int [FramesReceivedFEC](#) [get, set]
Received FEC events counter.
- int [FramesTryFEC](#) [get, set]

- *FEC recovery attempts counter.*
• int [FramesReceivedFragments](#) [get, set]
- *Received events for fragmented frames counter.*
• int [FramesReceivedFragmented](#) [get, set]
- *Assembled fragmented frames counter.*
• int [FramesSent](#) [get]
- *Sent frames counter.*
• int [FramesSentBytes](#) [get]
- *Sent frames bytes counter.*
• int [RoundTripTime](#) [get]
- *Average time required voice packet to return to sender.*
• int [RoundTripTimeVariance](#) [get]
- *Average round trip time variation.*
• bool [SuppressInfoDuplicateWarning](#) [get, set]
- *Do not log warning when duplicate info received.*
• [RemoteVoiceInfoDelegate OnRemoteVoiceInfoAction](#) [get, set]
• *Register a method to be called when remote voice info arrived (after join or new new remote voice creation). Metod parameters: (int channelId, int playerId, byte voiceId, [VoiceInfo](#) voiceInfo, ref [RemoteVoiceOptions](#) options);*
- int [DebugLostPercent](#) [get, set]
• *Lost frames simulation ratio.*
- IEnumerable< [LocalVoice](#) > [LocalVoices](#) [get]
• *Iterates through copy of all local voices list.*
- IEnumerable< [RemoteVoiceInfo](#) > [RemoteVoiceInfos](#) [get]
• *Iterates through all remote voices infos.*

3.149.1 Detailed Description

[Voice](#) client interact with other clients on network via [IVoiceTransport](#).

3.149.2 Constructor & Destructor Documentation

3.149.2.1 VoiceClient()

```

VoiceClient (
    IVoiceTransport transport,
    ILogger logger,
    CreateOptions opt = default(CreateOptions) )

```

Creates [VoiceClient](#) instance

3.149.3 Member Function Documentation

3.149.3.1 CreateLocalVoice()

```

LocalVoice CreateLocalVoice (
    VoiceInfo voiceInfo,
    int channelId,
    VoiceCreateOptions options = default(VoiceCreateOptions) )

```

Creates basic outgoing stream w/o data processing support. Provided encoder should generate output data stream.

Parameters

<i>voiceInfo</i>	Outgoing stream parameters.
<i>channelId</i>	Transport channel specific to transport.
<i>options</i>	Voice creation options.

Returns

Outgoing stream handler.

3.149.3.2 CreateLocalVoiceAudioFromSource()

```
LocalVoice CreateLocalVoiceAudioFromSource (
    VoiceInfo voiceInfo,
    IAudioDesc source,
    AudioSampleType sampleType,
    int channelId,
    VoiceCreateOptions options = default(VoiceCreateOptions) )
```

Creates outgoing audio stream of type automatically assigned and adds procedures (callback or serviceable) for consuming given audio source data. Adds audio specific features (e.g. resampling, level meter) to processing pipeline and to returning stream handler.

Parameters

<i>voiceInfo</i>	Outgoing stream parameters.
<i>source</i>	Streaming audio source.
<i>sampleType</i>	Voice 's audio sample type. If does not match source audio sample type, conversion will occur.
<i>channelId</i>	Transport channel specific to transport.
<i>options</i>	Voice creation options.

Returns

Outgoing stream handler.

audioSourceDesc.SamplingRate and voiceInfo.SamplingRate may do not match. Automatic resampling will occur in this case.

3.149.3.3 CreateLocalVoiceVideo()

```
LocalVoiceVideo CreateLocalVoiceVideo (
    VoiceInfo voiceInfo,
    IVideoRecorder recorder,
    int channelId,
    VoiceCreateOptions options = default(VoiceCreateOptions) )
```

Creates outgoing video stream consuming sequence of image buffers.

Parameters

<i>voiceInfo</i>	Outgoing stream parameters.
<i>recorder</i>	Video recorder.
<i>channelId</i>	Transport channel specific to transport.
<i>options</i>	Voice creation options.

Returns

Outgoing stream handler.

3.149.3.4 LocalVoicesInChannel()

```
IEnumerable<LocalVoice> LocalVoicesInChannel (
    int channelId )
```

Iterates through copy of all local voices list of given channel.

3.149.3.5 RemoteVoiceInfoDelegate()

```
delegate void RemoteVoiceInfoDelegate (
    int channelId,
    int playerId,
    byte voiceId,
    VoiceInfo voiceInfo,
    ref RemoteVoiceOptions options )
```

Remote voice info event delegate.

3.149.3.6 RemoveLocalVoice()

```
void RemoveLocalVoice (
    LocalVoice voice )
```

Removes local voice (outgoing data stream).

Parameters

<i>voice</i>	Handler of outgoing stream to be removed.
--------------	---

3.149.3.7 Service()

```
void Service ( )
```

This method dispatches all available incoming commands and then sends this client's outgoing commands. Call this method regularly (2..20 times a second).

3.149.4 Property Documentation

3.149.4.1 DebugLostPercent

```
int DebugLostPercent [get], [set]
```

Lost frames simulation ratio.

3.149.4.2 EventsLost

```
int EventsLost [get], [set]
```

Lost events counter (the number of empty frames sent to the deocder).

3.149.4.3 FramesFragPart

```
int FramesFragPart [get], [set]
```

The counter of assembled frames, fragments of which are partially missing.

3.149.4.4 FramesLate

```
int FramesLate [get], [set]
```

Counter of late (incorrectly ordered) frames.

3.149.4.5 FramesLateUsed

```
int FramesLateUsed [get]
```

Counter of late but still used frames.

3.149.4.6 FramesLost

```
int FramesLost [get], [set]
```

Lost frames counter (the number of empty frames sent to the deocder).

3.149.4.7 FramesMiss

```
int FramesMiss [get], [set]
```

Counter of slots between correctly ordered frames.

3.149.4.8 FramesReceived

```
int FramesReceived [get]
```

Received frames counter.

3.149.4.9 FramesReceivedFEC

```
int FramesReceivedFEC [get], [set]
```

Received FEC events counter.

3.149.4.10 FramesReceivedFragmented

```
int FramesReceivedFragmented [get], [set]
```

Assembled fragmented frames counter.

3.149.4.11 FramesReceivedFragments

```
int FramesReceivedFragments [get], [set]
```

Received events for fragmented frames counter.

3.149.4.12 FramesRecovered

```
int FramesRecovered [get], [set]
```

Recovered frames counter.

3.149.4.13 FramesSent

```
int FramesSent [get]
```

Sent frames counter.

3.149.4.14 FramesSentBytes

```
int FramesSentBytes [get]
```

Sent frames bytes counter.

3.149.4.15 FramesTryFEC

```
int FramesTryFEC [get], [set]
```

FEC recorery attempts counter.

3.149.4.16 LocalVoices

```
IEnumerable<LocalVoice> LocalVoices [get]
```

Iterates through copy of all local voices list.

3.149.4.17 OnRemoteVoiceInfoAction

```
RemoteVoiceInfoDelegate OnRemoteVoiceInfoAction [get], [set]
```

Register a method to be called when remote voice info arrived (after join or new new remote voice creation). Metod parameters: (int channelId, int playerId, byte voiceld, [VoiceInfo](#) voiceInfo, ref [RemoteVoiceOptions](#) options);

3.149.4.18 RemoteVoiceInfos

```
IEnumerable<RemoteVoiceInfo> RemoteVoiceInfos [get]
```

Iterates through all remote voices infos.

3.149.4.19 RoundTripTime

```
int RoundTripTime [get]
```

Average time required voice packet to return to sender.

3.149.4.20 RoundTripTimeVariance

```
int RoundTripTimeVariance [get]
```

Average round trip time variation.

3.149.4.21 SuppressInfoDuplicateWarning

```
bool SuppressInfoDuplicateWarning [get], [set]
```

Do not log warning when duplicate info received.

3.150 VoiceComponent Class Reference

Inherits MonoBehaviour.

Inherited by [PhotonVoiceView](#), [AudioChangesHandler](#), [FMODRecorderSetup](#), [Recorder](#), [RecorderPreset](#), [Speaker](#), [MicAmplifier](#), [MicrophonePermission](#), [SaveIncomingStreamToFile](#), [SaveOutgoingStreamToFile](#), and [WebRtcAudioDsp](#).

Public Attributes

- [VoiceLogger](#) **VoiceLogger** => impl.VoiceLogger

Protected Member Functions

- virtual void **Awake** ()

Protected Attributes

- [Voice.ILogger](#) **Logger** => impl.Logger

Properties

- string **Name** [set]

3.151 VoiceComponentImpl Class Reference

Public Member Functions

- void **Awake** (MonoBehaviour mb)

Public Attributes

- [Voice.ILogger](#) **Logger** => logger
- [VoiceLogger](#) **VoiceLogger** => voiceLogger

Properties

- string **Name** [set]

3.152 VoiceConnection Class Reference

Component that represents a [Voice](#) client.

Inherits ConnectionHandler.

Inherited by [FusionVoiceClient](#), [PunVoiceClient](#), and [UnityVoiceClient](#).

Public Member Functions

- virtual bool [ConnectUsingSettings](#) (AppSettings overwriteSettings=null)
Connect to [Photon](#) server using [Settings](#)
- bool [AddSpeaker](#) ([Speaker](#) speaker, object userData)
Tries to link local [Speaker](#) with remote voice stream using UserData. Useful if [Speaker](#) created after stream is started.
- [Speaker](#) [InstantiateSpeakerPrefab](#) (GameObject parent, bool destroyOnRemove)
Instantiates [SpeakerPrefab](#), optionally attaches it to the provided parent.
- bool **AddRecorder** ([Recorder](#) rec)
- void **RemoveRecorder** ([Recorder](#) rec)

Public Attributes

- virtual bool **AlwaysUsePrimaryRecorder** => false
- AppSettings **Settings**
Settings to be used by this [Voice](#) Client
- [VoiceLogger](#) **VoiceLogger** => voiceComponentImpl.VoiceLogger
- bool **UsePrimaryRecorder** => this.usePrimaryRecorder
Use [VoiceConnection.PrimaryRecorder](#) directly.

Static Public Attributes

- const int **ChannelAudio** = 1
Recommended [Photon](#) Transport channel for audio. Chosen not to interfere with video and default channel.
- const int **ChannelVideo** = 2
Recommended [Photon](#) Transport channel for video. Chosen not to interfere with audio and default channel.

Protected Member Functions

- override void **Awake** ()
- virtual void **Update** ()
- virtual void **FixedUpdate** ()
- virtual void **OnDestroy** ()
- virtual [Speaker](#) **InstantiateSpeakerForRemoteVoice** (int playerId, byte voiceId, object userData)
- virtual void **OnVoiceStateChanged** ([ClientState](#) fromState, [ClientState](#) toState)
- void **CalcStatistics** ()
- virtual void **OnOperationResponseReceived** (OperationResponse operationResponse)

Protected Attributes

- [Voice.ILogger](#) **Logger** => voiceComponentImpl.Logger

Properties

- new [LoadBalancingTransport](#) **Client** [get]
- [VoiceClient](#) **VoiceClient** [get]
Returns underlying [Photon Voice](#) client.
- ClientState **ClientState** [get]
Returns [Photon Voice](#) client state.
- float **FramesReceivedPerSecond** [get]
Number of frames received per second.
- float **FramesLostPerSecond** [get]
Number of frames lost per second.
- float **FramesLostPercent** [get]
Percentage of lost frames.
- GameObject **SpeakerPrefab** [get, set]
Prefab that contains [Speaker](#) component to be instantiated when receiving a new remote audio source info
- [Recorder](#) **PrimaryRecorder** [get, set]
Primary [Recorder](#) to be used by [VoiceConnection](#) implementations directly or via integration objects.
- string **BestRegionSummaryInPreferences** [get, set]
Used to store and access the "Best Region Summary" in the Player Preferences.

Events

- Action< [Speaker](#) > [SpeakerLinked](#)
Fires when a speaker has been linked to a remote audio stream
- Action< [RemoteVoiceLink](#) > [RemoteVoiceAdded](#)
Fires when a remote voice stream is added

3.152.1 Detailed Description

Component that represents a [Voice](#) client.

3.152.2 Member Function Documentation

3.152.2.1 AddSpeaker()

```
bool AddSpeaker (
    Speaker speaker,
    object userData )
```

Tries to link local [Speaker](#) with remote voice stream using UserData. Useful if [Speaker](#) created after stream is started.

Parameters

<i>speaker</i>	Speaker ot try linking.
<i>userData</i>	UserData object used to bind local Speaker with remote voice stream.

Returns

3.152.2.2 ConnectUsingSettings()

```
virtual bool ConnectUsingSettings (
    AppSettings overwriteSettings = null ) [virtual]
```

Connect to [Photon](#) server using [Settings](#)

Parameters

<i>overwriteSettings</i>	Overwrites Settings before connecting
--------------------------	---

Returns

If true voice connection command was sent from client

Reimplemented in [UnityVoiceClient](#).

3.152.2.3 InstantiateSpeakerPrefab()

```
Speaker InstantiateSpeakerPrefab (
    GameObject parent,
    bool destroyOnRemove )
```

Instantiates [SpeakerPrefab](#), optionally attaches it to the provided parent.

[VoiceConnection](#) manages the instantiated object (destroys on [OnRemoteVoiceRemoveAction](#)).

Parameters

<i>parent</i>	The object to attach Steaker to.
<i>destroyOnRemove</i>	Automatically destroy instantiated prefab when remote voice is removed (the caller does not manages the instance).

Returns

Instantiated [Speaker](#) or null.

3.152.3 Member Data Documentation**3.152.3.1 ChannelAudio**

```
const int ChannelAudio = 1 [static]
```

Recommended [Photon](#) Transport channel for audio. Chosen not to interfere with video and default channel.

3.152.3.2 ChannelVideo

```
const int ChannelVideo = 2 [static]
```

Recommended [Photon](#) Transport channel for video. Chosen not to interfere with audio and default channel.

3.152.3.3 Settings

`AppSettings Settings`

Settings to be used by this [Voice](#) Client

3.152.3.4 UsePrimaryRecorder

`bool UsePrimaryRecorder => this.usePrimaryRecorder`

Use [VoiceConnection.PrimaryRecorder](#) directly.

3.152.4 Property Documentation

3.152.4.1 BestRegionSummaryInPreferences

`string BestRegionSummaryInPreferences [get], [set]`

Used to store and access the "Best Region Summary" in the Player Preferences.

3.152.4.2 ClientState

`ClientState ClientState [get]`

Returns [Photon Voice](#) client state.

3.152.4.3 FramesLostPercent

`float FramesLostPercent [get]`

Percentage of lost frames.

3.152.4.4 FramesLostPerSecond

`float FramesLostPerSecond [get]`

Number of frames lost per second.

3.152.4.5 FramesReceivedPerSecond

```
float FramesReceivedPerSecond [get]
```

Number of frames received per second.

3.152.4.6 PrimaryRecorder

```
Recorder PrimaryRecorder [get], [set]
```

Primary [Recorder](#) to be used by [VoiceConnection](#) implementations directly or via integration objects.

3.152.4.7 SpeakerPrefab

```
GameObject SpeakerPrefab [get], [set]
```

Prefab that contains [Speaker](#) component to be instantiated when receiving a new remote audio source info

3.152.4.8 VoiceClient

```
VoiceClient VoiceClient [get]
```

Returns underlying [Photon Voice](#) client.

3.152.5 Event Documentation

3.152.5.1 RemoteVoiceAdded

```
Action<RemoteVoiceLink> RemoteVoiceAdded
```

Fires when a remote voice stream is added

3.152.5.2 SpeakerLinked

```
Action<Speaker> SpeakerLinked
```

Fires when a speaker has been linked to a remote audio stream

3.153 VoiceCreateOptions Struct Reference

Used to initialize optional properties of the [LocalVoice](#) instance at creation time.

Public Attributes

- [IEncoder](#) `Encoder`
Encoder.
- `byte` [InterestGroup](#)
See [LocalVoice.InterestGroup](#).
- `int[]` [TargetPlayers](#)
See [LocalVoice.TargetPlayers](#)Set to [] to make sure that [LocalVoice](#) does not create Remote voices during creation
- `bool` [DebugEchoMode](#)
See [LocalVoice.DebugEchoMode](#).
- `bool` [Reliable](#)
See [LocalVoice.Reliable](#).
- `bool` [Encrypt](#)
See [LocalVoice.Encrypt](#).
- `bool` [Fragment](#)
See [LocalVoice.Fragment](#).
- `int` [FEC](#)
See [LocalVoice.FEC](#).

3.153.1 Detailed Description

Used to initialize optional properties of the [LocalVoice](#) instance at creation time.

3.153.2 Member Data Documentation

3.153.2.1 DebugEchoMode

`bool` `DebugEchoMode`

See [LocalVoice.DebugEchoMode](#).

3.153.2.2 Encoder

[IEncoder](#) `Encoder`

Encoder.

3.153.2.3 Encrypt

`bool Encrypt`

See [LocalVoice.Encrypt](#).

3.153.2.4 FEC

`int FEC`

See [LocalVoice.FEC](#).

3.153.2.5 Fragment

`bool Fragment`

See [LocalVoice.Fragment](#).

3.153.2.6 InterestGroup

`byte InterestGroup`

See [LocalVoice.InterestGroup](#).

3.153.2.7 Reliable

`bool Reliable`

See [LocalVoice.Reliable](#).

3.153.2.8 TargetPlayers

`int [] TargetPlayers`

See [LocalVoice.TargetPlayers](#) Set to [] to make sure that [LocalVoice](#) does not create Remote voices during creation

3.154 VoiceDebugScript Class Reference

Utility script to be attached next to [PhotonVoiceView](#) & PhotonView on the player prefab to be network instantiated. Call `voiceDebugScript.CantHearYou()` on the networked object of the remote (or local) player if you can't hear the corresponding player.

Inherits MonoBehaviourPun.

Public Member Functions

- void **CantHearYou** ()

Public Attributes

- bool [ForceRecordingAndTransmission](#)
Make sure recorder.TransmitEnabled and recorder.RecordingEnabled are true.
- AudioClip [TestAudioClip](#)
Audio file to be broadcast when TestUsingAudioClip is enabled.
- bool [TestUsingAudioClip](#)
Broadcast Audio file to make sure transmission over network works if microphone (audio input device/hardware) is not reliable. Requires setting AudioClip in TestAudioClip.
- bool [DisableVad](#)
Disable recorder.VoiceDetection for easier testing.
- bool [IncreaseLogLevels](#)
Set main voice component's log level to ALL (max).
- bool [LocalDebug](#)
Debug DebugEcho mode (Can't Hear My Self?!).

3.154.1 Detailed Description

Utility script to be attached next to [PhotonVoiceView](#) & PhotonView on the player prefab to be network instantiated. Call `voiceDebugScript.CantHearYou()` on the networked object of the remote (or local) player if you can't hear the corresponding player.

3.154.2 Member Data Documentation

3.154.2.1 DisableVad

`bool DisableVad`

Disable recorder.VoiceDetection for easier testing.

3.154.2.2 ForceRecordingAndTransmission

`bool ForceRecordingAndTransmission`

Make sure recorder.TransmitEnabled and recorder.RecordingEnabled are true.

3.154.2.3 IncreaseLogLevels

`bool IncreaseLogLevels`

Set main voice component's log level to ALL (max).

3.154.2.4 LocalDebug

`bool LocalDebug`

Debug DebugEcho mode (Can't Hear My Self?!).

3.154.2.5 TestAudioClip

`AudioClip TestAudioClip`

Audio file to be broadcast when TestUsingAudioClip is enabled.

3.154.2.6 TestUsingAudioClip

`bool TestUsingAudioClip`

Broadcast Audio file to make sure transmission over network works if microphone (audio input device/hardware) is not reliable. Requires setting AudioClip in TestAudioClip.

3.155 AudioUtil.VoiceDetector< T > Class Template Reference

Simple voice activity detector triggered by signal level.

Inherits [IProcessor< T >](#), and [AudioUtil.IVoiceDetector](#).

Public Member Functions

- abstract T[] [Process](#) (T[] buf)
Process a frame of data.
- void **Dispose** ()

Protected Attributes

- float **norm**
- float **threshold**
- int **activityDelay**
- int **autoSilenceCounter** = 0
- int **valuesCountPerSec**
- int **activityDelayValuesCount**

Properties

- bool [On](#) [get, set]
If true, voice detection enabled.
- float [Threshold](#) [get, set]
Voice detected as soon as signal level exceeds threshold.
- bool [Detected](#) [get, protected set]
If true, voice detected.
- DateTime [DetectedTime](#) [get]
Last time when switched to detected state.
- int [ActivityDelayMs](#) [get, set]
Keep detected state during this time after signal level dropped below threshold.

Events

- Action [OnDetected](#)
Called when switched to detected state.

3.155.1 Detailed Description

Simple voice activity detector triggered by signal level.

3.155.2 Member Function Documentation

3.155.2.1 Process()

```
abstract T [] Process (
    T[] buf ) [pure virtual]
```

Process a frame of data.

Parameters

<i>buf</i>	Buffer containing input data
------------	------------------------------

Returns

Buffer containing output data or null if frame has been discarded (VAD)

Implements [IProcessor< T >](#).

3.155.3 Property Documentation

3.155.3.1 ActivityDelayMs

```
int ActivityDelayMs [get], [set]
```

Keep detected state during this time after signal level dropped below threshold.

3.155.3.2 Detected

```
bool Detected [get], [protected set]
```

If true, voice detected.

3.155.3.3 DetectedTime

```
DateTime DetectedTime [get]
```

Last time when switched to detected state.

3.155.3.4 On

```
bool On [get], [set]
```

If true, voice detection enabled.

3.155.3.5 Threshold

`float Threshold [get], [set]`

[Voice](#) detected as soon as signal level exceeds threshold.

3.155.4 Event Documentation

3.155.4.1 OnDetected

`Action OnDetected`

Called when switched to detected state.

3.156 AudioUtil.VoiceDetectorCalibration< T > Class Template Reference

Calibration Utility for [Voice](#) Detector

Inherits [IProcessor< T >](#).

Public Member Functions

- [VoiceDetectorCalibration](#) ([IVoiceDetector](#) voiceDetector, [ILevelMeter](#) levelMeter, int samplingRate, int channels)
Create new [VoiceDetectorCalibration](#) instance.
- void [Calibrate](#) (int durationMs, Action< float > onCalibrated=null)
Start calibration.
- T[] [Process](#) (T[] buf)
Process a frame of data.
- void **Dispose** ()

Protected Attributes

- int **calibrateCount**

Properties

- bool **IsCalibrating** [get]

3.156.1 Detailed Description

Calibration Utility for [Voice](#) Detector

. Using this audio processor, you can calibrate the [IVoiceDetector.Threshold](#).

3.156.2 Constructor & Destructor Documentation

3.156.2.1 VoiceDetectorCalibration()

```
VoiceDetectorCalibration (
    IVoiceDetector voiceDetector,
    ILevelMeter levelMeter,
    int samplingRate,
    int channels )
```

Create new [VoiceDetectorCalibration](#) instance.

Parameters

<i>voiceDetector</i>	Voice Detector to calibrate.
<i>levelMeter</i>	Level Meter to look at for calibration.
<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>channels</i>	Number of channels in the audio signal.

3.156.3 Member Function Documentation

3.156.3.1 Calibrate()

```
void Calibrate (
    int durationMs,
    Action< float > onCalibrated = null )
```

Start calibration.

Parameters

<i>durationMs</i>	Duration of the calibration procedure (in milliseconds).
<i>onCalibrated</i>	Optional callback that is called after calibration is complete.

This activates the Calibration process. It will reset the given [LevelMeter](#)'s AccumAvgPeakAmp (accumulated average peak amplitude), and when the duration has passed, use it for the [VoiceDetector](#)'s detection threshold.

3.156.3.2 Process()

```
T [] Process (
    T[] buf )
```

Process a frame of data.

Parameters

<i>buf</i>	Buffer containing input data
------------	------------------------------

Returns

Buffer containing output data or null if frame has been discarded (VAD)

Implements [IProcessor< T >](#).

3.157 AudioUtil.VoiceDetectorDummy Class Reference

Dummy [VoiceDetector](#) that doesn't actually do anything.

Inherits [AudioUtil.IVoiceDetector](#).

Properties

- bool **On** [get, set]
- float **Threshold** [get, set]
- bool **Detected** [get]
- int **ActivityDelayMs** [get, set]
- DateTime **DetectedTime** [get]
- Action **OnDetected**

Additional Inherited Members

3.157.1 Detailed Description

Dummy [VoiceDetector](#) that doesn't actually do anything.

3.158 AudioUtil.VoiceDetectorFloat Class Reference

[VoiceDetector](#) specialization for float audio.

Inherits [AudioUtil.VoiceDetector< float >](#).

Public Member Functions

- [VoiceDetectorFloat](#) (int samplingRate, int numChannels)
Create a new [VoiceDetectorFloat](#) instance.
- override float[] **Process** (float[] buffer)

Additional Inherited Members

3.158.1 Detailed Description

[VoiceDetector](#) specialization for float audio.

3.158.2 Constructor & Destructor Documentation

3.158.2.1 VoiceDetectorFloat()

```
VoiceDetectorFloat (
    int samplingRate,
    int numChannels )
```

Create a new [VoiceDetectorFloat](#) instance.

Parameters

<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>numChannels</i>	Number of channels in the audio signal.

3.159 AudioUtil.VoiceDetectorShort Class Reference

[VoiceDetector](#) specialization for float audio.

Inherits [AudioUtil.VoiceDetector< short >](#).

Public Member Functions

- [VoiceDetectorShort](#) (int samplingRate, int numChannels)
Create a new [VoiceDetectorFloat](#) instance
- override short[] **Process** (short[] buffer)

Additional Inherited Members

3.159.1 Detailed Description

[VoiceDetector](#) specialization for float audio.

3.159.2 Constructor & Destructor Documentation

3.159.2.1 VoiceDetectorShort()

```
VoiceDetectorShort (
    int samplingRate,
    int numChannels )
```

Create a new [VoiceDetectorFloat](#) instance

Parameters

<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>numChannels</i>	Number of channels in the audio signal.

3.160 VoiceEvent Class Reference

Static Public Attributes

- const byte [Code](#) = 202
Single event used for voice communications.
- const byte **FrameCode** = 203

3.160.1 Member Data Documentation

3.160.1.1 Code

```
const byte Code = 202 [static]
```

Single event used for voice communications.

Change if it conflicts with other event codes used in the same [Photon](#) room.

3.161 VoiceInfo Struct Reference

Describes stream properties.

Public Member Functions

- override string **ToString** ()

Static Public Member Functions

- static [VoicelInfo CreateAudioOpus](#) (POpusCodec.Enums.SamplingRate samplingRate, int channels, OpusCodec.FrameDuration frameDurationUs, int bitrate, object userdata=null)
Create stream info for an Opus audio stream.
- static [VoicelInfo CreateAudio](#) (Codec codec, int samplingRate, int channels, int frameDurationUs, object userdata=null)
Create stream info for an audio stream.
- static [VoicelInfo CreateVideo](#) (Codec codec, int bitrate, int width, int height, int fps, int keyFrameInt, object userdata=null)
Create stream info for a video stream.

Properties

- [Codec](#) **Codec** [get, set]
- int [SamplingRate](#) [get, set]
Audio sampling rate (frequency, in Hz).
- int [Channels](#) [get, set]
Number of channels.
- int [FrameDurationUs](#) [get, set]
Uncompressed frame (audio packet) size in microseconds.
- int [Bitrate](#) [get, set]
Target bitrate (in bits/second).
- int [Width](#) [get, set]
Video width.
- int [Height](#) [get, set]
Video height
- int [FPS](#) [get, set]
Video frames per second
- int [KeyFrameInt](#) [get, set]
Video keyframe interval in frames
- object [UserData](#) [get, set]
Optional user data. Should be serializable by [Photon](#).
- int [FrameDurationSamples](#) [get]
Uncompressed frame (data packet) size in samples.
- int [FrameSize](#) [get]
Uncompressed frame (data packet) array size.

3.161.1 Detailed Description

Describes stream properties.

3.161.2 Member Function Documentation

3.161.2.1 CreateAudio()

```
static VoiceInfo CreateAudio (
    Codec codec,
    int samplingRate,
    int channels,
    int frameDurationUs,
    object userdata = null ) [static]
```

Create stream info for an audio stream.

Parameters

<i>codec</i>	Audio codec.
<i>samplingRate</i>	Audio sampling rate.
<i>channels</i>	Number of channels.
<i>frameDurationUs</i>	Uncompressed frame (audio packet) size in microseconds.
<i>userdata</i>	Optional user data. Should be serializable by Photon .

Returns

[VoiceInfo](#) instance.

3.161.2.2 CreateAudioOpus()

```
static VoiceInfo CreateAudioOpus (
    POpusCodec.Enums.SamplingRate samplingRate,
    int channels,
    OpusCodec.FrameDuration frameDurationUs,
    int bitrate,
    object userdata = null ) [static]
```

Create stream info for an Opus audio stream.

Parameters

<i>samplingRate</i>	Audio sampling rate.
<i>channels</i>	Number of channels.
<i>frameDurationUs</i>	Uncompressed frame (audio packet) size in microseconds.
<i>bitrate</i>	Stream bitrate (in bits/second).
<i>userdata</i>	Optional user data. Should be serializable by Photon .

Returns

[VoiceInfo](#) instance.

3.161.2.3 CreateVideo()

```
static VoiceInfo CreateVideo (
    Codec codec,
    int bitrate,
    int width,
    int height,
    int fps,
    int keyFrameInt,
    object userdata = null ) [static]
```

Create stream info for a video stream.

Parameters

<i>codec</i>	Video codec.
<i>bitrate</i>	Stream bitrate.
<i>width</i>	Streamed video width. If 0, width and height of video source used (no rescaling).
<i>height</i>	Streamed video height. If -1, aspect ratio preserved during rescaling.
<i>fps</i>	Streamed video frames per second.
<i>keyFrameInt</i>	Keyframes interval in frames.

///

Parameters

<i>userdata</i>	Optional user data. Should be serializable by Photon .
-----------------	--

Returns

[VoiceInfo](#) instance.

3.161.3 Property Documentation

3.161.3.1 Bitrate

```
int Bitrate [get], [set]
```

Target bitrate (in bits/second).

3.161.3.2 Channels

```
int Channels [get], [set]
```

Number of channels.

3.161.3.3 FPS

```
int FPS [get], [set]
```

Video frames per second

3.161.3.4 FrameDurationSamples

```
int FrameDurationSamples [get]
```

Uncompressed frame (data packet) size in samples.

3.161.3.5 FrameDurationUs

```
int FrameDurationUs [get], [set]
```

Uncompressed frame (audio packet) size in microseconds.

3.161.3.6 FrameSize

```
int FrameSize [get]
```

Uncompressed frame (data packet) array size.

3.161.3.7 Height

```
int Height [get], [set]
```

Video height

3.161.3.8 KeyFrameInt

```
int KeyFrameInt [get], [set]
```

Video keyframe interval in frames

3.161.3.9 SamplingRate

`int SamplingRate [get], [set]`

Audio sampling rate (frequency, in Hz).

3.161.3.10 UserData

`object UserData [get], [set]`

Optional user data. Should be serializable by [Photon](#).

3.161.3.11 Width

`int Width [get], [set]`

Video width.

3.162 AudioUtil.VoiceLevelDetectCalibrate< T > Class Template Reference

Utility Audio Processor [Voice](#) Detection Calibration.

Inherits [IProcessor< T >](#).

Public Member Functions

- [VoiceLevelDetectCalibrate](#) (int samplingRate, int channels)
Create new [VoiceLevelDetectCalibrate](#) instance
- void [Calibrate](#) (int durationMs, Action< float > onCalibrated=null)
Start calibration
- T[] [Process](#) (T[] buf)
Process a frame of data.
- void **Dispose** ()

Properties

- [ILevelMeter](#) [LevelMeter](#) [get]
The [LevelMeter](#) in use.
- [IVoiceDetector](#) [VoiceDetector](#) [get]
The [VoiceDetector](#) in use
- bool **IsCalibrating** [get]

3.162.1 Detailed Description

Utility Audio Processor [Voice](#) Detection Calibration.

Encapsulates level meter, voice detector and voice detector calibrator in single instance.

3.162.2 Constructor & Destructor Documentation

3.162.2.1 VoiceLevelDetectCalibrate()

```
VoiceLevelDetectCalibrate (
    int samplingRate,
    int channels )
```

Create new [VoiceLevelDetectCalibrate](#) instance

Parameters

<i>samplingRate</i>	Sampling rate of the audio signal (in Hz).
<i>channels</i>	Number of channels in the audio signal.

3.162.3 Member Function Documentation

3.162.3.1 Calibrate()

```
void Calibrate (
    int durationMs,
    Action< float > onCalibrated = null )
```

Start calibration

Parameters

<i>durationMs</i>	Duration of the calibration procedure (in milliseconds).
<i>onCalibrated</i>	Called when calibration is complete. Parameter is new threshold value.

This activates the Calibration process. It will reset the given [LevelMeter](#)'s AccumAvgPeakAmp (accumulated average peak amplitude), and when the duration has passed, use it for the [VoiceDetector](#)'s detection threshold.

3.162.3.2 Process()

```
T [ ] Process (
```

```
T[] buf )
```

Process a frame of data.

Parameters

<i>buf</i>	Buffer containing input data
------------	------------------------------

Returns

Buffer containing output data or null if frame has been discarded (VAD)

Implements [IProcessor< T >](#).

3.162.4 Property Documentation

3.162.4.1 LevelMeter

```
ILevelMeter LevelMeter [get]
```

The [LevelMeter](#) in use.

3.162.4.2 VoiceDetector

```
IVoiceDetector VoiceDetector [get]
```

The [VoiceDetector](#) in use

3.163 VoiceLogger Class Reference

Inherits [MonoBehaviour](#).

Static Public Member Functions

- static [VoiceLogger](#) **FindLogger** (GameObject gameObject)
- static [VoiceLogger](#) **CreateRootLogger** ()

Public Attributes

- DebugLevel **LogLevel** = DebugLevel.WARNING

3.164 VoiceNetworkObject Class Reference

Inherits NetworkBehaviour.

Public Member Functions

- override void **Spawned** ()
- override void **Despawned** (NetworkRunner runner, bool hasState)

Public Attributes

- [VoiceLogger](#) **VoiceLogger** => voiceComponentImpl.VoiceLogger
- bool [IsSpeaking](#) => this.SpeakerInUse != null && this.SpeakerInUse.IsPlaying
If true, this [VoiceNetworkObject](#) has a Speaker that is currently playing received audio frames from remote audio source
- bool [IsRecording](#) => this.RecorderInUse != null && this.RecorderInUse.IsCurrentlyTransmitting
If true, this [VoiceNetworkObject](#) has a Recorder that is currently transmitting audio stream from local audio source
- bool **IsLocal** => Runner.Topology == SimulationConfig.Topologies.Shared ? this.Object.HasStateAuthority : this.Object.HasInputAuthority

Protected Attributes

- [Voice.ILogger](#) **Logger** => voiceComponentImpl.Logger

Properties

- [Recorder](#) [RecorderInUse](#) [get]
The Recorder component currently used by this [VoiceNetworkObject](#)
- [Speaker](#) [SpeakerInUse](#) [get]
The Speaker component currently used by this [VoiceNetworkObject](#)

3.164.1 Member Data Documentation

3.164.1.1 IsRecording

```
bool IsRecording => this.RecorderInUse != null && this.RecorderInUse.IsCurrentlyTransmitting
```

If true, this [VoiceNetworkObject](#) has a Recorder that is currently transmitting audio stream from local audio source

3.164.1.2 IsSpeaking

```
bool IsSpeaking => this.SpeakerInUse != null && this.SpeakerInUse.IsPlaying
```

If true, this [VoiceNetworkObject](#) has a Speaker that is currently playing received audio frames from remote audio source

3.164.2 Property Documentation

3.164.2.1 RecorderInUse

```
Recorder RecorderInUse [get]
```

The Recorder component currently used by this [VoiceNetworkObject](#)

3.164.2.2 SpeakerInUse

```
Speaker SpeakerInUse [get]
```

The Speaker component currently used by this [VoiceNetworkObject](#)

3.165 AudioUtil.WaveformAudioPusher< T > Class Template Reference

[IAudioPusher](#) that provides the given waveform.

Inherits [AudioUtil.GeneratorPusher< T >](#).

Public Member Functions

- **WaveformAudioPusher** (int bufSizeMs=100, int samplingRate=48000, int channels=1)

Protected Member Functions

- override int **Gen** (T[] buf, long timeSamples)

Properties

- T[] **Waveform** [set]

Additional Inherited Members

3.165.1 Detailed Description

[IAudioPusher](#) that provides the given waveform.

3.166 AudioUtil.WaveformAudioReader< T > Class Template Reference

[IAudioReader](#) that provides the given waveform.

Inherits [AudioUtil.GeneratorReader< T >](#).

Public Member Functions

- **WaveformAudioReader** (Func< double > clockSec=null, int samplingRate=48000, int channels=1)

Protected Member Functions

- override int **Gen** (T[] buf, long timeSamples)

Properties

- T[] **Waveform** [set]

3.166.1 Detailed Description

[IAudioReader](#) that provides the given waveform.

3.167 WaveWriter Class Reference

Inherits `IDisposable`.

Public Member Functions

- **WaveWriter** (string fileName, int sampleRate, int bits, int channels)
- **WaveWriter** (Stream stream, int sampleRate, int bitsPerSample, int channels)
- void **Dispose** ()
- void **WriteSample** (float sample)
- void **WriteSamples** (float[] samples, int offset, int count)
- void **Write** (byte[] buffer, int offset, int count)
- void **Write** (byte value)
- void **Write** (short value)
- void **Write** (int value)
- void **Write** (float value)

Protected Member Functions

- virtual void **Dispose** (bool disposing)

3.168 WebRtcAudioDsp Class Reference

Inherits [VoiceComponent](#).

Public Member Functions

- void **AdjustVoiceInfo** (ref [VoiceInfo](#) voiceInfo, ref [AudioSampleType](#) st)

Public Attributes

- bool **IsSupported**

Protected Member Functions

- override void **Awake** ()

Properties

- bool **AEC** [get, set]
- bool **AecHighPass** [get, set]
- int **ReverseStreamDelayMs** [get, set]
- bool **NoiseSuppression** [get, set]
- bool **HighPass** [get, set]
- bool **Bypass** [get, set]
- bool **AGC** [get, set]
- int **AgcCompressionGain** [get, set]
- int **AgcTargetLevel** [get, set]
- bool **VAD** [get, set]

Additional Inherited Members

3.168.1 Member Data Documentation

3.168.1.1 IsSupported

bool IsSupported

Initial value:

=> `true`

3.169 WebRTCAudioLib Class Reference

Inherited by [WebRTCAudioProcessor](#).

Public Types

- enum **Error**
- enum **Param**

Public Member Functions

- static IntPtr **webrtc_audio_processor_create** (int samplingRate, int channels, int frameSize, int rev← SamplingRate, int revChannels)
- static int **webrtc_audio_processor_init** (IntPtr proc)
- static int **webrtc_audio_processor_set_param** (IntPtr proc, int param, int v)
- static int **webrtc_audio_processor_process** (IntPtr proc, short[] buffer, int offset, out bool voiceDetected)
- static int **webrtc_audio_processor_process_reverse** (IntPtr proc, short[] buffer, int bufferSize)
- static void **webrtc_audio_processor_destroy** (IntPtr proc)

3.170 WebRTCAudioProcessor Class Reference

Inherits [WebRTCAudioLib](#), and [IProcessor< short >](#).

Public Member Functions

- **WebRTCAudioProcessor** ([ILogger](#) logger, int frameSize, int samplingRate, int channels, int reverse← SamplingRate, int reverseChannels)
- short[] **Process** (short[] buf)
- void **OnAudioOutFrameFloat** (float[] data)
- void **Dispose** ()

Static Public Attributes

- static readonly int[] **SupportedSamplingRates** = { 8000, 16000, 32000, 48000 }

Properties

- int **AECStreamDelayMs** [set]
- bool?? **AEC** [set]
- bool? **AECHighPass** [set]
- bool?? **AECMobile** [set]
- bool? **HighPass** [set]
- bool? **NoiseSuppression** [set]
- bool? **AGC** [set]
- int **AGCCompressionGain** [set]
- int **AGCTargetLevel** [set]
- bool? **AGC2** [set]
- bool? **VAD** [set]
- bool **Bypass** [set]

Additional Inherited Members

3.171 WindowsAudioInPusher Class Reference

Inherits [IAudioPusher< short >](#).

Public Member Functions

- **WindowsAudioInPusher** (int deviceId, [ILogger](#) logger)
- void **SetCallback** (Action< short[]> callback, [ObjectFactory](#)< short[], int > bufferFactory)
- void **Dispose** ()

Properties

- int **Channels** [get]
- int **SamplingRate** [get]
- string **Error** [get]

Index

- AccumAvgPeakAmp
 - AudioUtil.ILevelMeter, [63](#)
- AcquireOrCreate
 - ObjectPool< TType, TInfo >, [95](#)
- ActivityDelayMs
 - AudioUtil.IVoiceDetector, [70](#)
 - AudioUtil.VoiceDetector< T >, [151](#)
- AddPostProcessor
 - LocalVoiceFramed< T >, [87](#)
- AddPreProcessor
 - LocalVoiceFramed< T >, [88](#)
- AddSpeaker
 - VoiceConnection, [142](#)
- AllowBluetooth
 - Photon.Voice.IOS, [8](#)
- Ambient
 - Photon.Voice.IOS, [7](#)
- AndroidAudioInAEC, [13](#)
- AndroidAudioInParameters, [13](#)
- AudioChangesHandler, [14](#)
 - HandleDeviceChange, [14](#)
 - HandleDeviceChangeAndroid, [14](#)
 - HandleDeviceChangeIOS, [14](#)
- AudioClip
 - Recorder, [110](#)
- AudioClipWrapper, [15](#)
- AudioDesc, [15](#)
- AudioInChangeNotifier, [15](#), [16](#)
 - Dispose, [16](#), [17](#)
 - Error, [16](#), [17](#)
- AudioInChangeNotifierNotSupported, [17](#)
- AudioInEnumerator, [18–20](#)
 - Dispose, [18](#), [20](#)
 - Refresh, [18](#), [20](#)
- AudioInPusher, [21](#)
 - Channels, [22](#)
- AudioInReader, [22](#)
- AudioInReader< T >, [23](#)
 - Read, [23](#)
- AudioOpus
 - Photon.Voice, [6](#)
- AudioOut< T >, [24](#)
- AudioOutCapture, [24](#)
- AudioOutDelayControl, [24](#), [25](#)
- AudioOutDelayControl.PlayDelayConfig, [101](#)
 - Default, [101](#)
- AudioOutDummy< T >, [25](#)
- AudioOutEvent< T >, [25](#)
- AudioProcessing
 - Photon.Voice.IOS, [7](#)
- AudioSampleType
 - Photon.Voice, [6](#)
- AudioSessionCategory
 - Photon.Voice.IOS, [7](#)
- AudioSessionCategoryOption
 - Photon.Voice.IOS, [8](#)
- AudioSessionMode
 - Photon.Voice.IOS, [9](#)
- AudioSessionParameters, [26](#)
- AudioSessionParametersPresets, [26](#)
 - Game, [26](#)
 - VoIP, [26](#)
- AudioSyncBuffer< T >, [27](#)
- AudioUtil, [27](#)
 - Convert, [29](#)
 - ForceToStereo< T >, [29](#)
 - Resample< T >, [30](#)
 - ResampleAndConvert, [30](#), [31](#)
- AudioUtil.GeneratorPusher< T >, [51](#)
 - SetCallback, [52](#)
- AudioUtil.GeneratorReader< T >, [52](#)
 - Read, [53](#)
- AudioUtil.ILevelMeter, [62](#)
 - AccumAvgPeakAmp, [63](#)
 - CurrentAvgAmp, [63](#)
 - CurrentPeakAmp, [63](#)
 - ResetAccumAvgPeakAmp, [62](#)
- AudioUtil.IVoiceDetector, [69](#)
 - ActivityDelayMs, [70](#)
 - Detected, [70](#)
 - DetectedTime, [70](#)
 - On, [70](#)
 - OnDetected, [71](#)
 - Threshold, [70](#)
- AudioUtil.LevelMeter< T >, [71](#)
 - Process, [72](#)
 - ResetAccumAvgPeakAmp, [72](#)
- AudioUtil.LevelMeterDummy, [72](#)
 - ResetAccumAvgPeakAmp, [73](#)
- AudioUtil.LevelMeterFloat, [73](#)
 - LevelMeterFloat, [74](#)
- AudioUtil.LevelMeterShort, [75](#)
 - LevelMeterShort, [75](#)
- AudioUtil.Resampler< T >, [118](#)
 - Process, [119](#)
 - Resampler, [118](#)
- AudioUtil.TempoUp< T >, [123](#)
- AudioUtil.ToneAudioPusher< T >, [124](#)

- ToneAudioPusher, 124
- AudioUtil.ToneAudioReader< T >, 125
 - ToneAudioReader, 125
- AudioUtil.VoiceDetector< T >, 149
 - ActivityDelayMs, 151
 - Detected, 151
 - DetectedTime, 151
 - On, 151
 - OnDetected, 152
 - Process, 150
 - Threshold, 151
- AudioUtil.VoiceDetectorCalibration< T >, 152
 - Calibrate, 153
 - Process, 153
 - VoiceDetectorCalibration, 153
- AudioUtil.VoiceDetectorDummy, 154
- AudioUtil.VoiceDetectorFloat, 154
 - VoiceDetectorFloat, 155
- AudioUtil.VoiceDetectorShort, 155
 - VoiceDetectorShort, 156
- AudioUtil.VoiceLevelDetectCalibrate< T >, 161
 - Calibrate, 162
 - LevelMeter, 163
 - Process, 162
 - VoiceDetector, 163
 - VoiceLevelDetectCalibrate, 162
- AudioUtil.WaveformAudioPusher< T >, 165
- AudioUtil.WaveformAudioReader< T >, 166
- AutoConnectAndJoin
 - PunVoiceClient, 104
- AutoLeaveAndDisconnect
 - PunVoiceClient, 104
- BestRegionSummaryInPreferences
 - VoiceConnection, 144
- Bitrate
 - Recorder, 110
 - VoiceInfo, 159
- BufferFactory
 - LocalVoiceFramed< T >, 89
- BufferReaderPushAdapterAsyncPool
 - BufferReaderPushAdapterAsyncPool< T >, 32
- BufferReaderPushAdapterAsyncPool< T >, 31
 - BufferReaderPushAdapterAsyncPool, 32
 - Service, 32
- BufferReaderPushAdapterAsyncPoolFloatToShort, 32
 - BufferReaderPushAdapterAsyncPoolFloatToShort, 33
 - Service, 33
- BufferReaderPushAdapterAsyncPoolShortToFloat, 34
 - BufferReaderPushAdapterAsyncPoolShortToFloat, 34
 - Service, 34
- BufferReaderPushAdapterBase
 - BufferReaderPushAdapterBase< T >, 35
- BufferReaderPushAdapterBase< T >, 35
 - BufferReaderPushAdapterBase, 35
 - Dispose, 36
 - Service, 36
- Calibrate
 - AudioUtil.VoiceDetectorCalibration< T >, 153
 - AudioUtil.VoiceLevelDetectCalibrate< T >, 162
- CaptureDevice, 36
 - CaptureSource, 38
 - CleanUpAsync, 37
 - SelectPreferredCameraStreamSettingAsync, 37
 - StartRecordingAsync, 38
 - StopRecordingAsync, 38
- CaptureSource
 - CaptureDevice, 38
- ChannelAudio
 - VoiceConnection, 143
- ChannelId
 - RemoteVoiceInfo, 115
- Channels
 - AudioInPusher, 22
 - IAudioDesc, 54
 - VoiceInfo, 159
- ChannelVideo
 - VoiceConnection, 143
- CleanUpAsync
 - CaptureDevice, 37
- ClearProcessors
 - LocalVoiceFramed< T >, 88
- ClientState
 - VoiceConnection, 144
- Code
 - VoiceEvent, 156
- Codec
 - Photon.Voice, 6
- ConnectAndJoin, 38
- ConnectAndJoinRoom
 - PunVoiceClient, 103
- ConnectUsingSettings
 - UnityVoiceClient, 127
 - VoiceConnection, 142
- Convert
 - AudioUtil, 29
- CreateAudio
 - VoiceInfo, 157
- CreateAudioOpus
 - VoiceInfo, 158
- CreateLocalVoice
 - VoiceClient, 133
- CreateLocalVoiceAudioFromSource
 - VoiceClient, 134
- CreateLocalVoiceVideo
 - VoiceClient, 134
- CreateVideo
 - VoiceInfo, 158
- CurrentAvgAmp
 - AudioUtil.ILevelMeter, 63
- CurrentPeakAmp
 - AudioUtil.ILevelMeter, 63
- DebugEchoMode
 - LocalVoice, 80
 - Recorder, 110

- VoiceCreateOptions, 146
- DebugLostPercent
 - VoiceClient, 136
- Decoder
 - RemoteVoiceOptions, 117
- Default
 - AudioOutDelayControl.PlayDelayConfig, 101
 - Photon.Voice.IOS, 9
 - VoiceClient.CreateOptions, 39
- DefaultToSpeaker
 - Photon.Voice.IOS, 8
- DequeueOutput
 - IEncoder, 60
- Detected
 - AudioUtil.IVoiceDetector, 70
 - AudioUtil.VoiceDetector< T >, 151
- DetectedTime
 - AudioUtil.IVoiceDetector, 70
 - AudioUtil.VoiceDetector< T >, 151
- DeviceEnumerator, 41
- DeviceEnumeratorBase, 42
- DeviceFeatures, 42
- DeviceInfo, 43
- DisableVad
 - VoiceDebugScript, 148
- Disconnect
 - PunVoiceClient, 104
- Dispose
 - AudioInChangeNotifier, 16, 17
 - AudioInEnumerator, 18, 20
 - BufferReaderPushAdapterBase< T >, 36
 - LoadBalancingTransport, 77
 - LocalVoiceFramed< T >, 88
 - ObjectPool< TType, TInfo >, 95
- DuckOthers
 - Photon.Voice.IOS, 8
- Dummy
 - LocalVoiceAudioDummy, 86
- Encoder
 - VoiceCreateOptions, 146
- Encrypt
 - LocalVoice, 81
 - Recorder, 110
 - VoiceCreateOptions, 146
- EndOfStream
 - IEncoder, 60
- Error
 - AudioInChangeNotifier, 16, 17
 - IAudioDesc, 54
 - IDecoder, 58
 - IEncoder, 60
- EventsLost
 - VoiceClient, 136
- FactoryPrimitiveArrayPool< T >, 45
- FactoryReusableArray< T >, 46
- FEC
 - LocalVoice, 81
- VoiceCreateOptions, 147
- Flip, 46
- FMODRecorderSetup, 47
- ForceRecordingAndTransmission
 - VoiceDebugScript, 148
- ForceToStereo< T >
 - AudioUtil, 29
- FPS
 - VoiceInfo, 159
- Fragment
 - LocalVoice, 81
 - VoiceCreateOptions, 147
- Frame
 - Framer< T >, 49
 - FramerResampler< T >, 50
- FrameBuffer, 47
- FrameDuration
 - Recorder, 110
- FrameDurationSamples
 - VoiceInfo, 160
- FrameDurationUs
 - VoiceInfo, 160
- FrameOut< T >, 48
- Framer
 - Framer< T >, 49
- Framer< T >, 48
 - Frame, 49
 - Framer, 49
- FramerResampler< T >, 49
 - Frame, 50
- FramesFragPart
 - VoiceClient, 136
- FrameSize
 - VoiceInfo, 160
- FramesLate
 - VoiceClient, 136
- FramesLateUsed
 - VoiceClient, 136
- FramesLost
 - VoiceClient, 136
- FramesLostPercent
 - VoiceConnection, 144
- FramesLostPerSecond
 - VoiceConnection, 144
- FramesMiss
 - VoiceClient, 137
- FramesReceived
 - VoiceClient, 137
- FramesReceivedFEC
 - VoiceClient, 137
- FramesReceivedFragmented
 - VoiceClient, 137
- FramesReceivedFragments
 - VoiceClient, 137
- FramesReceivedPerSecond
 - VoiceConnection, 144
- FramesRecovered
 - VoiceClient, 137

- FramesSent
 - LocalVoice, [81](#)
 - VoiceClient, [138](#)
- FramesSentBytes
 - LocalVoice, [81](#)
 - VoiceClient, [138](#)
- FramesSentFragmented
 - LocalVoice, [81](#)
- FramesSentFragments
 - LocalVoice, [82](#)
- FramesTryFEC
 - VoiceClient, [138](#)
- FusionVoiceClient, [50](#)
 - UseFusionAppSettings, [51](#)
 - UseFusionAuthValues, [51](#)
- Game
 - AudioSessionParametersPresets, [26](#)
- GetPlatformAPI< I >
 - LEncoder, [60](#)
- HandleDeviceChange
 - AudioChangesHandler, [14](#)
- HandleDeviceChangeAndroid
 - AudioChangesHandler, [14](#)
- HandleDeviceChangeIOS
 - AudioChangesHandler, [14](#)
- Height
 - VoiceInfo, [160](#)
- IAudioDesc, [53](#)
 - Channels, [54](#)
 - Error, [54](#)
 - SamplingRate, [54](#)
- IAudioInChangeNotifier, [54](#)
- IAudioOut< T >, [55](#)
- IAudioPusher< T >, [55](#)
 - SetCallback, [55](#)
- IAudioReader< T >, [56](#)
- IDataReader< T >, [56](#)
 - Read, [56](#)
- IDecoder, [57](#)
 - Error, [58](#)
 - Input, [57](#)
 - Open, [57](#)
- IDecoderDirect< B >, [58](#)
 - Output, [58](#)
- IDeviceEnumerator, [59](#)
- LEncoder, [59](#)
 - DequeueOutput, [60](#)
 - EndOfStream, [60](#)
 - Error, [60](#)
 - GetPlatformAPI< I >, [60](#)
 - Output, [60](#)
- LEncoderDirect< B >, [61](#)
 - Input, [61](#)
- LEncoderDirectImage, [61](#)
 - ImageFormat, [62](#)
- ILocalVoiceAudio, [63](#)
 - LevelMeter, [64](#)
 - VoiceDetector, [64](#)
 - VoiceDetectorCalibrate, [64](#)
 - VoiceDetectorCalibrating, [65](#)
- ILogger, [65](#)
- ImageBufferInfo, [65](#)
- ImageBufferInfo.StrideSet, [123](#)
- ImageBufferNative, [66](#)
- ImageBufferNative.PlaneSet, [100](#)
- ImageBufferNativeAlloc, [66](#)
- ImageBufferNativeGCHandleBytes, [66](#)
- ImageBufferNativeGCHandleSinglePlane, [67](#)
- ImageBufferNativePool< T >, [67](#)
- ImageFormat
 - LEncoderDirectImage, [62](#)
- IncreaseLogLevels
 - VoiceDebugScript, [149](#)
- Info
 - LocalVoice, [82](#)
 - ObjectPool< TType, TInfo >, [96](#)
 - RemoteVoiceInfo, [115](#)
- Init
 - ObjectPool< TType, TInfo >, [95](#)
- Input
 - IDecoder, [57](#)
 - LEncoderDirect< B >, [61](#)
 - OpusCodec.Decoder< T >, [40](#)
 - RawCodec.Decoder< T >, [41](#)
- InputFactory
 - Recorder, [110](#)
- Instance
 - PunVoiceClient, [104](#)
- InstantiateSpeakerPrefab
 - VoiceConnection, [143](#)
- InterestGroup
 - LocalVoice, [82](#)
 - Recorder, [111](#)
 - VoiceCreateOptions, [147](#)
- IProcessor< T >, [67](#)
 - Process, [68](#)
- IResettable, [68](#)
- IsCurrentlyTransmitting
 - LocalVoice, [82](#)
 - Recorder, [111](#)
- IServiceable, [68](#)
 - Service, [69](#)
- IsLinked
 - Speaker, [121](#)
- IsPlaying
 - Speaker, [121](#)
- IsRecording
 - PhotonVoiceView, [100](#)
 - VoiceNetworkObject, [164](#)
- IsSpeaking
 - PhotonVoiceView, [100](#)
 - VoiceNetworkObject, [164](#)
- IsSupported
 - WebRtcAudioDsp, [167](#)

- IVoiceTransport, 71
- KeyFrameInt
 - VoiceInfo, 160
- Lag
 - Speaker, 122
- LevelMeter
 - AudioUtil.VoiceLevelDetectCalibrate< T >, 163
 - ILocalVoiceAudio, 64
 - Recorder, 111
- LevelMeterFloat
 - AudioUtil.LevelMeterFloat, 74
- LevelMeterShort
 - AudioUtil.LevelMeterShort, 75
- LoadBalancingTransport, 76
 - Dispose, 77
 - LoadBalancingTransport, 77
 - Service, 77
 - VoiceClient, 78
- LoadBalancingTransport2, 78
- LocalDebug
 - VoiceDebugScript, 149
- LocalUserServiceable
 - LocalVoice, 82
- LocalVoice, 78
 - DebugEchoMode, 80
 - Encrypt, 81
 - FEC, 81
 - Fragment, 81
 - FramesSent, 81
 - FramesSentBytes, 81
 - FramesSentFragmented, 81
 - FramesSentFragments, 82
 - Info, 82
 - InterestGroup, 82
 - IsCurrentlyTransmitting, 82
 - LocalUserServiceable, 82
 - Reliable, 82
 - RemoveSelf, 80
 - SendSpacingProfileMax, 83
 - TargetPlayers, 83
 - TransmitEnabled, 83
- LocalVoiceAudio< T >, 83
 - VoiceDetectorCalibrate, 84
 - VoiceDetectorCalibrating, 85
- LocalVoiceAudioDummy, 85
 - Dummy, 86
 - VoiceDetectorCalibrate, 85
- LocalVoiceAudioFloat, 86
- LocalVoiceAudioShort, 86
- LocalVoiceFramed< T >, 87
 - AddPostProcessor, 87
 - AddPreProcessor, 88
 - BufferFactory, 89
 - ClearProcessors, 88
 - Dispose, 88
 - PushData, 88
 - PushDataAsync, 88
 - PushDataAsyncReady, 89
 - RemoveProcessor, 89
- LocalVoices
 - VoiceClient, 138
- LocalVoicesInChannel
 - VoiceClient, 135
- Logger, 89
- LoopAudioClip
 - Recorder, 111
- Measurement
 - Photon.Voice.IOS, 9
- MicAmplifier, 90
- MicAmplifierFloat, 90
- MicAmplifierShort, 90
- MicrophonePermission, 91
- MicrophoneType
 - Recorder, 111
- MicWrapper, 91
- MicWrapperPusher, 92
- MicWrapperPusherOnAudioFilterRead, 92
- MixWithOthers
 - Photon.Voice.IOS, 8
- MonoPInvokeCallbackAttribute, 92
- MoviePlayback
 - Photon.Voice.IOS, 9
- MultiRoute
 - Photon.Voice.IOS, 7
- ObjectFactory< TType, TInfo >, 92
- ObjectPool
 - ObjectPool< TType, TInfo >, 94
- ObjectPool< TType, TInfo >, 93
 - AcquireOrCreate, 95
 - Dispose, 95
 - Info, 96
 - Init, 95
 - ObjectPool, 94
 - Release, 96
- On
 - AudioUtil.IVoiceDetector, 70
 - AudioUtil.VoiceDetector< T >, 151
- OnDetected
 - AudioUtil.IVoiceDetector, 71
 - AudioUtil.VoiceDetector< T >, 152
- OnRemoteVoiceInfoAction
 - VoiceClient, 138
- OnRemoteVoiceRemoveAction
 - RemoteVoiceOptions, 117
 - Speaker, 122
- Open
 - IDecoder, 57
 - OpusCodec.Decoder< T >, 40
 - RawCodec.Decoder< T >, 41
- OpusCodec, 97
- OpusCodec.Decoder< T >, 39
 - Input, 40
 - Open, 40
- OpusCodec.Encoder< T >, 43

- OpusCodec.EncoderFloat, 44
- OpusCodec.EncoderShort, 45
- OpusCodec.Factory, 45
- OpusCodec.Util, 130
- Output
 - IDecoderDirect< B >, 58
 - IEncoder, 60
- Photon, 3
- Photon.Voice, 3
 - AudioOpus, 6
 - AudioSampleType, 6
 - Codec, 6
- Photon.Voice.FMOD, 6
- Photon.Voice.Fusion, 6
- Photon.Voice.IOS, 7
 - AllowBluetooth, 8
 - Ambient, 7
 - AudioProcessing, 7
 - AudioSessionCategory, 7
 - AudioSessionCategoryOption, 8
 - AudioSessionMode, 9
 - Default, 9
 - DefaultToSpeaker, 8
 - DuckOthers, 8
 - Measurement, 9
 - MixWithOthers, 8
 - MoviePlayback, 9
 - MultiRoute, 7
 - PlayAndRecord, 7
 - Playback, 7
 - Record, 7
 - SoloAmbient, 7
 - VideoChat, 9
 - VideoRecording, 9
 - VoiceChat, 9
- Photon.Voice.MacOS, 9
- Photon.Voice.PUN, 9
- Photon.Voice.PUN.UtilityScripts, 10
- Photon.Voice.Unity, 10
- Photon.Voice.Unity.FMOD, 11
- Photon.Voice.Unity.UtilityScripts, 11
- Photon.Voice.UWP, 11
- Photon.Voice.Windows, 11
- PhotonAppSettings, 97
 - ToString, 98
 - UseCloud, 98
- PhotonVoiceCreatedParams, 98
- PhotonVoiceLagSimulationGui, 98
- PhotonVoiceStatsGui, 99
- PhotonVoiceView, 99
 - IsRecording, 100
 - IsSpeaking, 100
 - RecorderInUse, 100
 - SpeakerInUse, 100
- Platform, 101
- PlayAndRecord
 - Photon.Voice.IOS, 7
- Playback
 - Photon.Voice.IOS, 7
- PlayDelay
 - Speaker, 122
- PlayDelayConfig
 - Speaker, 122
- PlayerId
 - RemoteVoiceInfo, 115
- PrimaryRecorder
 - VoiceConnection, 145
- PrimitiveArrayPool< T >, 102
- Process
 - AudioUtil.LevelMeter< T >, 72
 - AudioUtil.Resampler< T >, 119
 - AudioUtil.VoiceDetector< T >, 150
 - AudioUtil.VoiceDetectorCalibration< T >, 153
 - AudioUtil.VoiceLevelDetectCalibrate< T >, 162
 - IProcessor< T >, 68
- PunVoiceClient, 102
 - AutoConnectAndJoin, 104
 - AutoLeaveAndDisconnect, 104
 - ConnectAndJoinRoom, 103
 - Disconnect, 104
 - Instance, 104
 - UsePunAppSettings, 105
 - UsePunAuthValues, 105
 - VoiceRoomNameSuffix, 104
- PushData
 - LocalVoiceFramed< T >, 88
- PushDataAsync
 - LocalVoiceFramed< T >, 88
- PushDataAsyncReady
 - LocalVoiceFramed< T >, 89
- RawCodec, 105
- RawCodec.Decoder< T >, 40
 - Input, 41
 - Open, 41
- RawCodec.Encoder< T >, 44
- RawCodec.ShortToFloat, 120
- Read
 - AudioInReader< T >, 23
 - AudioUtil.GeneratorReader< T >, 53
 - IDataReader< T >, 56
- Record
 - Photon.Voice.IOS, 7
- Recorder, 105
 - AudioClip, 110
 - Bitrate, 110
 - DebugEchoMode, 110
 - Encrypt, 110
 - FrameDuration, 110
 - InputFactory, 110
 - InterestGroup, 111
 - IsCurrentlyTransmitting, 111
 - LevelMeter, 111
 - LoopAudioClip, 111
 - MicrophoneType, 111
 - RecordingEnabled, 111
 - RecordWhenJoined, 112

- ReliableMode, 112
- ResetLocalAudio, 108
- RestartRecording, 108
- SamplingRate, 112
- SetAndroidNativeMicrophoneSettings, 108
- SetIosAudioSessionParameters, 108, 109
- SourceType, 112
- StopRecordingWhenPaused, 112
- TargetPlayers, 112
- TransmitEnabled, 113
- UseMicrophoneTypeFallback, 113
- UseOnAudioFilterRead, 113
- UserData, 113
- VoiceDetection, 113
- VoiceDetectionDelayMs, 113
- VoiceDetectionThreshold, 114
- VoiceDetector, 114
- VoiceDetectorCalibrate, 109
- VoiceDetectorCalibrating, 114
- RecorderInUse
 - PhotonVoiceView, 100
 - VoiceNetworkObject, 165
- RecorderPreset, 114
- RecorderPreset.DSP, 43
- RecordingEnabled
 - Recorder, 111
- RecordWhenJoined
 - Recorder, 112
- Refresh
 - AudioInEnumerator, 18, 20
- Release
 - ObjectPool< TType, TInfo >, 96
- Reliable
 - LocalVoice, 82
 - VoiceCreateOptions, 147
- ReliableMode
 - Recorder, 112
- RemoteVoiceAdded
 - VoiceConnection, 145
- RemoteVoiceInfo, 115
 - ChannelId, 115
 - Info, 115
 - PlayerId, 115
 - VoiceId, 116
- RemoteVoiceInfoDelegate
 - VoiceClient, 135
- RemoteVoiceInfos
 - VoiceClient, 138
- RemoteVoiceLink, 116
- RemoteVoiceOptions, 116
 - Decoder, 117
 - OnRemoteVoiceRemoveAction, 117
 - SetOutput, 117
- RemoveLocalVoice
 - VoiceClient, 135
- RemoveProcessor
 - LocalVoiceFramed< T >, 89
- RemoveSelf
 - LocalVoice, 80
- Resample< T >
 - AudioUtil, 30
- ResampleAndConvert
 - AudioUtil, 30, 31
- Resampler
 - AudioUtil.Resampler< T >, 118
- ResetAccumAvgPeakAmp
 - AudioUtil.ILevelMeter, 62
 - AudioUtil.LevelMeter< T >, 72
 - AudioUtil.LevelMeterDummy, 73
- ResetLocalAudio
 - Recorder, 108
- RestartPlayback
 - Speaker, 121
- RestartRecording
 - Recorder, 108
- RoundTripTime
 - VoiceClient, 139
- RoundTripTimeVariance
 - VoiceClient, 139
- SamplingRate
 - IAudioDesc, 54
 - Recorder, 112
 - VoiceInfo, 160
- SaveIncomingStreamToFile, 119
- SaveOutgoingStreamToFile, 119
- SelectPreferredCameraStreamSettingAsync
 - CaptureDevice, 37
- SendFrameParams, 119
- SendSpacingProfileMax
 - LocalVoice, 83
- Service
 - BufferReaderPushAdapterAsyncPool< T >, 32
 - BufferReaderPushAdapterAsyncPoolFloatToShort, 33
 - BufferReaderPushAdapterAsyncPoolShortToFloat, 34
 - BufferReaderPushAdapterBase< T >, 36
 - IServiceable, 69
 - LoadBalancingTransport, 77
 - VoiceClient, 135
- SetAndroidNativeMicrophoneSettings
 - Recorder, 108
- SetCallback
 - AudioUtil.GeneratorPusher< T >, 52
 - IAudioPusher< T >, 55
- SetIosAudioSessionParameters
 - Recorder, 108, 109
- SetOutput
 - RemoteVoiceOptions, 117
- Settings
 - VoiceConnection, 143
- SoloAmbient
 - Photon.Voice.IOS, 7
- SourceType
 - Recorder, 112
- Speaker, 120

- IsLinked, [121](#)
- IsPlaying, [121](#)
- Lag, [122](#)
- OnRemoteVoiceRemoveAction, [122](#)
- PlayDelay, [122](#)
- PlayDelayConfig, [122](#)
- RestartPlayback, [121](#)
- SpeakerAudioFilterRead, [122](#)
- SpeakerFMOD, [123](#)
- SpeakerInUse
 - PhotonVoiceView, [100](#)
 - VoiceNetworkObject, [165](#)
- SpeakerLinked
 - VoiceConnection, [145](#)
- SpeakerPrefab
 - VoiceConnection, [145](#)
- StartRecordingAsync
 - CaptureDevice, [38](#)
- StopRecordingAsync
 - CaptureDevice, [38](#)
- StopRecordingWhenPaused
 - Recorder, [112](#)
- SuppressInfoDuplicateWarning
 - VoiceClient, [139](#)
- TargetPlayers
 - LocalVoice, [83](#)
 - Recorder, [112](#)
 - VoiceCreateOptions, [147](#)
- TestAudioClip
 - VoiceDebugScript, [149](#)
- TestTone, [123](#)
- TestUsingAudioClip
 - VoiceDebugScript, [149](#)
- Threshold
 - AudioUtil.IVoiceDetector, [70](#)
 - AudioUtil.VoiceDetector< T >, [151](#)
- ToneAudioPusher
 - AudioUtil.ToneAudioPusher< T >, [124](#)
- ToneAudioReader
 - AudioUtil.ToneAudioReader< T >, [125](#)
- ToString
 - PhotonAppSettings, [98](#)
- TransmitEnabled
 - LocalVoice, [83](#)
 - Recorder, [113](#)
- UnityAudioOut, [126](#)
- UnityLogger, [126](#)
- UnityMicrophone, [126](#)
- UnityVoiceClient, [127](#)
 - ConnectUsingSettings, [127](#)
 - UseVoiceAppSettings, [128](#)
- UnsupportedCodecException, [128](#)
 - UnsupportedCodecException, [128](#)
- UnsupportedPlatformException, [129](#)
 - UnsupportedPlatformException, [129](#)
- UnsupportedSampleTypeException, [130](#)
 - UnsupportedSampleTypeException, [130](#)
- UseCloud
 - PhotonAppSettings, [98](#)
- UseFusionAppSettings
 - FusionVoiceClient, [51](#)
- UseFusionAuthValues
 - FusionVoiceClient, [51](#)
- UseMicrophoneTypeFallback
 - Recorder, [113](#)
- UseOnAudioFilterRead
 - Recorder, [113](#)
- UsePrimaryRecorder
 - VoiceConnection, [144](#)
- UsePunAppSettings
 - PunVoiceClient, [105](#)
- UsePunAuthValues
 - PunVoiceClient, [105](#)
- UserData
 - Recorder, [113](#)
 - VoiceInfo, [161](#)
- UseVoiceAppSettings
 - UnityVoiceClient, [128](#)
- VideoChat
 - Photon.Voice.IOS, [9](#)
- VideoInEnumerator, [130](#), [131](#)
- VideoRecording
 - Photon.Voice.IOS, [9](#)
- VoiceChat
 - Photon.Voice.IOS, [9](#)
- VoiceClient, [131](#)
 - CreateLocalVoice, [133](#)
 - CreateLocalVoiceAudioFromSource, [134](#)
 - CreateLocalVoiceVideo, [134](#)
 - DebugLostPercent, [136](#)
 - EventsLost, [136](#)
 - FramesFragPart, [136](#)
 - FramesLate, [136](#)
 - FramesLateUsed, [136](#)
 - FramesLost, [136](#)
 - FramesMiss, [137](#)
 - FramesReceived, [137](#)
 - FramesReceivedFEC, [137](#)
 - FramesReceivedFragmented, [137](#)
 - FramesReceivedFragments, [137](#)
 - FramesRecovered, [137](#)
 - FramesSent, [138](#)
 - FramesSentBytes, [138](#)
 - FramesTryFEC, [138](#)
 - LoadBalancingTransport, [78](#)
 - LocalVoices, [138](#)
 - LocalVoicesInChannel, [135](#)
 - OnRemoteVoiceInfoAction, [138](#)
 - RemoteVoiceInfoDelegate, [135](#)
 - RemoteVoiceInfos, [138](#)
 - RemoveLocalVoice, [135](#)
 - RoundTripTime, [139](#)
 - RoundTripTimeVariance, [139](#)
 - Service, [135](#)
 - SuppressInfoDuplicateWarning, [139](#)

- VoiceClient, 133
- VoiceConnection, 145
- VoiceClient.CreateOptions, 39
 - Default, 39
- VoiceComponent, 139
- VoiceComponentImpl, 140
- VoiceConnection, 140
 - AddSpeaker, 142
 - BestRegionSummaryInPreferences, 144
 - ChannelAudio, 143
 - ChannelVideo, 143
 - ClientState, 144
 - ConnectUsingSettings, 142
 - FramesLostPercent, 144
 - FramesLostPerSecond, 144
 - FramesReceivedPerSecond, 144
 - InstantiateSpeakerPrefab, 143
 - PrimaryRecorder, 145
 - RemoteVoiceAdded, 145
 - Settings, 143
 - SpeakerLinked, 145
 - SpeakerPrefab, 145
 - UsePrimaryRecorder, 144
 - VoiceClient, 145
- VoiceCreateOptions, 146
 - DebugEchoMode, 146
 - Encoder, 146
 - Encrypt, 146
 - FEC, 147
 - Fragment, 147
 - InterestGroup, 147
 - Reliable, 147
 - TargetPlayers, 147
- VoiceDebugScript, 148
 - DisableVad, 148
 - ForceRecordingAndTransmission, 148
 - IncreaseLogLevels, 149
 - LocalDebug, 149
 - TestAudioClip, 149
 - TestUsingAudioClip, 149
- VoiceDetection
 - Recorder, 113
- VoiceDetectionDelayMs
 - Recorder, 113
- VoiceDetectionThreshold
 - Recorder, 114
- VoiceDetector
 - AudioUtil.VoiceLevelDetectCalibrate< T >, 163
 - ILocalVoiceAudio, 64
 - Recorder, 114
- VoiceDetectorCalibrate
 - ILocalVoiceAudio, 64
 - LocalVoiceAudio< T >, 84
 - LocalVoiceAudioDummy, 85
 - Recorder, 109
- VoiceDetectorCalibrating
 - ILocalVoiceAudio, 65
 - LocalVoiceAudio< T >, 85
- Recorder, 114
- VoiceDetectorCalibration
 - AudioUtil.VoiceDetectorCalibration< T >, 153
- VoiceDetectorFloat
 - AudioUtil.VoiceDetectorFloat, 155
- VoiceDetectorShort
 - AudioUtil.VoiceDetectorShort, 156
- VoiceEvent, 156
 - Code, 156
- VoiceId
 - RemoteVoiceInfo, 116
- VoiceInfo, 156
 - Bitrate, 159
 - Channels, 159
 - CreateAudio, 157
 - CreateAudioOpus, 158
 - CreateVideo, 158
 - FPS, 159
 - FrameDurationSamples, 160
 - FrameDurationUs, 160
 - FrameSize, 160
 - Height, 160
 - KeyFrameInt, 160
 - SamplingRate, 160
 - UserData, 161
 - Width, 161
- VoiceLevelDetectCalibrate
 - AudioUtil.VoiceLevelDetectCalibrate< T >, 162
- VoiceLogger, 163
- VoiceNetworkObject, 164
 - IsRecording, 164
 - IsSpeaking, 164
 - RecorderInUse, 165
 - SpeakerInUse, 165
- VoiceRoomNameSuffix
 - PunVoiceClient, 104
- VoIP
 - AudioSessionParametersPresets, 26
- WaveWriter, 166
- WebRtcAudioDsp, 167
 - IsSupported, 167
- WebRTCAudioLib, 168
- WebRTCAudioProcessor, 168
- Width
 - VoiceInfo, 161
- WindowsAudioInPusher, 169