

SiPass integrated

ADD5100 / DRI

Dual Reader Interface



The ADD5100 / DRI act as an interface between card readers and the advanced central controller (AC5102). Each of them can support up to two card readers.

- Interface module for up to two card readers
- Support for an entry reader and an exit reader to monitor and control a door from both sides
- Easy installation
- Four product variants in three different housings

Features

The ADD5100 / DRI dual reader controller (DRIs) secures doors or barriers by supporting one entry reader, one exit reader, a door strike to lock and unlock the door, and a door contact to detect the door's position (open or closed).

The on-board inputs of the DRI are individually supervised, which ensures that any wire tampering generates an alarm message in the system.

Each DRI has three programmable auxiliary input connections for the monitoring of system components such as cabinet doors, duress switches, or PIR motion sensors. The DRI also includes an auxiliary output which can be connected to a buzzer, strobe light or similar device and configured to trigger that device when security is breached.

The DRIs are fully updateable using the latest flash technology, and they are easily programmed via the host system to operate in the desired mode. This leading-edge technology allows the DRIs to be re-programmed or re-configured and used in conjunction with other Siemens security products, providing a complete and fully expandable security system.

The DRIs have been carefully engineered so that they can be easily mounted in a variety of environments. The DRI can be installed in common locations such as either near the door it controls or in the same cabinet as the advanced central controller.

- Supports all popular reader technologies
- Supports all readers with SiPass reader protocol
- Support for an entry reader and an exit reader
- Auxiliary 12VDC power source (min. voltage input 18VDC)
- Lock / door strike output (relay driven)
- Request-to-exit input
- Door contact input
- Three auxiliary inputs
- Auxiliary output (relay driven)
- Selectable supervision of input wires
- Communications status LED
- Activity Status LED
- Power Status LED
- Host system compatibility for configuration download via ACC

Type summary

Type	Part number	Designation
ADD5100 ¹	6FL7820-8CA10-1A	Dual reader interface including base plate

1 Replaces type designation RIM-010

ADD5100 / DRI	
Interface	FLN connection to controller: RS485 to readers: One RS485 bus for up to two RS485 readers (CerPass protocol) OR two Wiegand/Clock&Data ports
Operating Voltage	12...32 VDC ±20 %
Power Output	• Reader: 300 mA • Ancillary: 1 A
Power Consumption	25 W
Outputs	• Lock output relay (30 VDC, 2 A) • Auxiliary relay (30 VDC, 2 A)
Inputs	• REX button • Door contact • 3 Auxiliary All inputs unsupervised or supervised
Tamper Switch	Optional, auxiliary input
Firmware	Flash upgradeable
Indicators	Power, Activity, Communication
Operating Temperature	32...122 °F (0...50 °C)
Dimensions in inches (mm) (W x H x D)	4.92 x 4.92 x 1.34 (125 x 125 x 34)
Weight in lbs (kg)	0.66 (0.30)
Approval	CE, UL294, C-Tick

Issued by
Siemens Industry, Inc.
Smart Infrastructure
1000 Deerfield Pkwy
Buffalo Grove IL 60089
+1 847-215-1000

© Siemens Industry, Inc., 2022
Technical specifications and availability subject to change without notice.