

LAB MANUAL

CSE 324

Operating Systems Lab

Course Teacher

Nushrat Jahan Oyshi

Lecturer

Computer Science & Engineering

Daffodil International University

Lab 4

Functions:

Script: <i>hello.sh</i> <pre>#!/bin/bash function name () { commands } name () { commands }</pre>	Script: <i>hello.sh</i> <pre>#!/bin/bash function write () { echo "Hello World" } quit () { exit } write echo "done" quit</pre>
Script: <i>hello.sh</i> <pre>#!/bin/bash function write () { echo \$1 } quit () { exit } write Hello write World echo "done" quit</pre>	Script: <i>hello.sh</i> <pre>#!/bin/bash function write () { echo \$1 \$2 \$3 } quit () { exit } write Tom and Jerry echo "done" quit</pre>

Local Variables

Script: <i>hello.sh</i> <pre>#!/bin/bash function write () { name=\$1 echo "The first name is \$name" } name "Tom" echo "The second name is \$name" write Jerry echo "The third name is \$name : "</pre>	Script: <i>hello.sh</i> <pre>#!/bin/bash function write () { local name=\$1 echo "The first name is \$name" } name "Tom" echo "The second name is \$name : " write Jerry echo "The third name is \$name : "</pre>
---	--

Mini Project

Digital Clock

Script: *terminal*

date # shows the day date and time

date +%T # shows only time

sleep 1

<pre>clear date +%T sleep 1 clear date +%T sleep 1</pre>	Script: <i>clock.sh</i> <pre>#!/bin/bash Green="\e[1;36m" Cyan="\e[0;36m"</pre>
--	---

date +%T clear	# Cyan='\033[0;36m' while true # while ((1)) do clear echo \$ Cyan \$(date +%T) sleep 1 done
-------------------	---

Run C using GCC

Script: *terminal*

```
gcc --version
```

```
# latest versions of ubuntu have pre installed gcc if not then
```

```
sudo apt install build-essential  
# enter ubuntu password to install
```

```
touch hello.c  
# write a c program
```

```
# create output file using -o flag  
gcc hello.c -o oslab
```

```
# output file will be a binary file
```

```
./oslab
```