

Build Status — What Is Done and What Is Not

As of 19 September 2026. Counts in this document are generated from the repository, not maintained by hand: the block results come from `sim/run_sim.py`, the unknowns from the specification's own register.

At a glance

	Count
Circuit blocks simulated	22
Blocks passing their checks	21
Blocks failing deliberately	1 (<code>load_dump</code>)
Research memos	12
Unknowns closed	4
Unknowns partly answered	4
Unknowns still open	8
Phase	1.5 — block simulation, nearly complete

Nothing has been captured in KiCad, no PCB exists, and no firmware has been written. Everything below describes design work verified by simulation, which is the stage before schematic capture.

1. Circuit blocks — simulated and passing

Each block is a SPICE netlist plus a set of falsifiable checks. A block "passes" when every claim it makes about itself holds. These are design verification, not layout.

1.1 Power chain — 8 blocks

Block	What it covers	Status
<code>emi_filter</code>	Two-stage LC, CISPR 25 conducted, differential mode	Passing
<code>reverse_battery</code>	Ideal-diode P-FET vs series Schottky	Passing
<code>transient_clamp</code>	ISO 7637-2 pulse 2a, +112 V / 2 Ω / 50 μ s	Passing
<code>load_dump</code>	ISO 7637-2 pulse 5b, 40 V / 0.5 Ω / 400 ms	FAILS — deliberately
<code>buck_preregulator</code>	6–40 V to 5 V at 400 kHz	Passing
<code>sensor_rail</code>	5 V sensor distribution, one PTC per group	Passing
<code>mcu_pdn</code>	3V3 decoupling impedance, 100 m Ω target	Passing

Block	What it covers	Status
supervisor	Watchdog, brownout, fail-safe gate kill path	Passing

Why `load_dump` fails, and why that is correct. The TVS chosen against pulse 2a absorbs 46 J at 116 W under pulse 5b — roughly 100× both its single-pulse energy rating and its continuous dissipation rating. The failure is the deliverable: it says the part selection is wrong, not that the simulation is. The fix is a higher standoff voltage so the TVS stays off during a normal clamped load dump, rather than a larger part to absorb it. **Blocked on U16** — whether the alternator is suppressed at all decides which pulse applies.

1.2 Sensor front-ends — 6 blocks

Block	What it covers	Status
<code>sensor_ratiometric</code>	Pins 41/35/80/37, 0.5–4.5 V into a 3.3 V ADC	Passing
<code>sensor_differential</code>	Shared sensor ground on pin 34, single-ended vs differential	Passing
<code>ntc_frontend</code>	Pin 79 charge-air temperature, divider vs current source	Passing
<code>battery_sense</code>	Pins 04/06, 6–40 V rail into a 3.3 V ADC	Passing
<code>discrete_input</code>	Pins 20/24/71, active-high switched battery	Passing
<code>trip_module_sense</code>	Trip-module state, supervised three-state loop	Passing

`ntc_frontend` simulates **both** candidate topologies because **U2** is unresolved. One resistance measurement at the machine picks between them; the front-end is designed so that measurement selects a populate option rather than unblocking a redesign.

1.3 Speed and position — 1 block

Block	What it covers	Status
<code>vr_conditioner</code>	Crank VR sensor, pins 52/74/30	Passing

1.4 Injection — 3 blocks

Block	What it covers	Status
<code>injector_boost</code>	Why the boost stage exists, pins 03/05	Passing
<code>injector_turnoff</code>	Turn-off recirculation into the boost rail	Passing
<code>boost_converter</code>	Injector rail reservoir sizing	Passing

`boost_converter` passes but carries a recorded gap: it has **no bleed path**. Its charge source regulates the rail from below only. Harmless while current flowed outward; `injector_turnoff` now pushes energy back in, and a hold-current cutoff would climb the rail about 2 V per event with no way down.

1.5 Actuators — 3 blocks

Block	What it covers	Status
metering_unit_pwm	Pin 88, low-side PWM into the fuel metering solenoid	Passing
relay_driver	Pins 50/69, low-side FET with flyback	Passing
egr_hbridge	Pins 59/81, positional actuator, feedback on 37	Passing

1.6 Communications — 1 block

Block	What it covers	Status
can_termination	Split vs single termination, J1939 250 kbit/s	Passing

2. Circuits not yet built at all

These have no netlist, no schematic and no checks. They are the real gaps.

Missing circuit	Pins	Why it is not built
Cam sensor front-end	46 capture, 45 excitation	Found 19 Sep by the pin-map work. Spec §4 specified a pull-up to the 5 V sensor rail straight into a capture pin on a 3.3 V part — over the MCU's absolute maximum. It survived because no block simulated it: there is a <code>vr_conditioner</code> for crank and no cam equivalent
Intake throttle driver	6-pin connector	Blocked on U8. Reported battery-fed, which answers who supplies it, not who commands it. May be out of scope entirely
Pre/post-heat output	unknown	Blocked on U14. Same distinction — battery-fed is not the same as ECU-switched. The DSE4522 enables both at 50 °C and this design has no heater output

3. Verification not yet done

The blocks above are each simulated in isolation, at one temperature, against the stimuli named. These are the gaps in the *verification*, not in the circuits.

Gap	Consequence
No temperature corner anywhere	Every result is a 27 °C result. An engine bay is not 27 °C
ISO 7637-2 negative pulses unsimulated	And the TVS model is a single diode, so reusing it for reverse-polarity transients would give a confidently wrong answer rather than failing visibly. The model must be replaced before the test is meaningful
Common-mode EMI unmodelled	<code>emi_filter</code> covers differential mode only. Most real automotive failures are common mode, and modelling it honestly needs a layout to give the return path
Reverse-battery transient	The switch model turns off instantly, so it always looks perfect. The real number is a controller-datasheet question
Watchdog fault-detection time	<code>supervisor</code> bounds only what happens <i>after</i> reset asserts, not how long detection takes

4. Documents

Document	State
Reconciled Specification	Binding. Rewritten §3 on the fitted controller, §4 gained a hardware fail-safe requirement, register extended to U16
Field Handbook	Current
Sensor Reference	Current
Circuit Reference	Generated from the simulations at build time, so it cannot drift
Memos 01–12	Dated records. Superseded conclusions carry banners rather than being rewritten

Memo 01 and Memo 02 are substantially wrong and say so at the top.

Memo 01 misidentified the engine and advised discarding the correct search term. Memo 02 analysed a controller that is not fitted. They are kept because the reasoning that produced them is the record of how the error happened.

5. Unknowns

Closed — 4

#	Question	Answer
U11	Engine identity	3GK550ETA 4SR1 , app code 6K3.8703 , CPCB IV+ under certificate P25/2825/24
U1	ECU connector	Bosch 1 928 405 192 / 194 , code C keying
U13	Which controller is fitted	DSE4522 MKII AMF , not the KG640C the diagram shows
U12	Does the fuel relay remove power?	No — it only signals

Three of these four closed against what this project had reasoned. That is the single most useful thing to know about the desk work: it is productive, and it is not reliable without the machine.

Partly answered — 4

U4 CAN expectations (addresses 234 and 44 confirmed) · U5 injector drive profile (family envelope only, no part number) · U8 throttle (supply known, control not) · U14 pre/post-heat (supply known, control not)

Open — 8

U2 charge-air sensor topology · U6 pin 09 function · U7 pins 04/06 sense or feed · U9 catalyst sensor routing · U10 SENT signal identity · U15 what CRS-878 denotes · U16 alternator rectifier suppressed or not · plus U12's contact-type confirmation, which gates nothing

6. Decisions open, and blocking

Decision	Blocks	Why it cannot wait
Integrated driver IC vs discrete FETs	—	DECIDED 19 Sep 2026, memo 12. Discrete FETs, keeping the 100 V rail. MC33816 caps at 72 V, L9781 at a reported 80 V, and both are pre-drivers that need external FETs anyway
Passive pulldown vs active clamp	—	DECIDED 19 Sep 2026, memo 12. Active clamp, built discretely, at every gate. The integrated route relocates this problem rather than removing it
MC33816 last-time-buy 06/08/2027	Fallback path only	Needs a distributor conversation, not another search
L9781 datasheet unretrievable	Confirming the decision's runner-up	Five failed fetches across two sessions. Needs FAE or distributor access
Air-intake shutoff	Nothing electrical	Owners' decision. Nothing in this design can stop an oil-fuelled runaway
Trip-module pickup target	Module ordering	Whether it shares our flywheel target. Sharing is cheaper; separate preserves the independence that is the reason for fitting it

7. Phases

Phase	Output	State
0	Reconciled specification	Done
1	Research memos	Done — twelve
1.5	Block-level simulation	In progress — 22 blocks, 21 passing
2	KiCad hierarchical schematic capture	Not started
3	4-layer PCB layout, DRC, fab outputs	Not started
4	Firmware skeleton	Not started

What ends phase 1.5: the four missing circuits in §2, the verification gaps in §3, and the verification gaps in §3. The two driver decisions in §6 are now taken. What starts phase 2: assigning PTxx pins to the 94-way connector — which is also what unblocks the per-pin detail of the fail-safe requirement.

8. Work at the machine

Ordered by what it unblocks.

Task	Closes	Unblocks
Alternator rectifier part number, or a scope during a live disconnect under load	U16	The whole input-protection topology, and load_dump 's failure
Resistance across the charge-air element, cold	U2	The ntc_frontend populate choice
Follow the throttle's 6-pin cable to where it ends	U8	Whether a throttle driver exists at all

Task	Closes	Unblocks
Trace who switches the heater feed	U14	Whether a heater output is in scope
Injector part number from the body	U5	The boost rail's target voltage
Relay contact-type check	U12 confirmation	Nothing — recorded for completeness