

Foundations of Solar Microgrid Engineering

A Practical Reference for Small-Scale Renewable Power Systems

Test Knowledge Base Edition

2026

Contents

Chapter 1: Introduction to Solar Microgrids	3
1.1 A Brief History	3
1.2 Why Microgrids Matter	3
1.3 Scope of This Reference	3
Chapter 2: Core System Components	3
2.1 Photovoltaic Arrays	4
2.2 Charge Controllers	4
2.3 Battery Energy Storage Systems (BESS)	4
2.4 Inverters	4
2.5 Distribution and Protection	5
Chapter 3: Microgrid Architectures	5
3.1 DC-Coupled Architecture	5
3.2 AC-Coupled Architecture	5
3.3 Hybrid Architecture	5
3.4 Operating Modes	5
Chapter 4: Battery Chemistries Compared	6
4.1 Why Lithium Iron Phosphate Dominates New Installations	6
4.2 State of Charge and Depth of Discharge	6
4.3 Temperature Sensitivity	6
Chapter 5: Load Assessment and System Sizing	7
5.1 The Sizing Process	7
5.2 Step 1 — Load Tabulation	7
5.3 Step 2 — Battery Bank Sizing	7
5.4 Step 3 — PV Array Sizing	7
5.5 Step 4 — Inverter Sizing	8
Chapter 6: Protection, Safety, and Grounding	8
6.1 Overcurrent Protection	8
6.2 Ground-Fault Protection	8
6.3 Rapid Shutdown Requirements	8

6.4 Arc-Fault Detection	8
6.5 Battery Safety Enclosures	8
Chapter 7: Monitoring and Control Systems	9
7.1 Local Monitoring	9
7.2 SCADA and Remote Monitoring	9
7.3 Predictive Maintenance	9
7.4 Demand Response Integration	9
Chapter 8: Operations and Maintenance	9
8.1 Routine Panel Maintenance	9
8.2 Battery Bank Inspection	9
8.3 Common Fault Patterns	10
8.4 Recommended Spare Parts Inventory	10
Chapter 9: Case Studies	10
9.1 Case Study — Kestrel Ridge Relay Station	10
9.2 Case Study — Meridian Village Cooperative	10
9.3 Case Study — Thornbury Cold-Storage Facility	10
Chapter 10: Glossary of Key Terms	11
Chapter 11: Economics and Financing	11
11.1 Capital Cost Breakdown	11
11.2 Levelized Cost of Energy (LCOE)	11
11.3 Financing Models	12
11.4 Payback Period Considerations	12
Chapter 12: Environmental Impact and Lifecycle	12
12.1 Embodied Carbon	12
12.2 End-of-Life and Recycling	12
12.3 Land and Ecological Considerations	12
12.4 Comparative Emissions	13
Chapter 13: Standards, Codes, and Certification	13
13.1 Why Standards Matter	13
13.2 Common Standard Families	13
13.3 Interconnection Agreements	13
13.4 Commissioning and Testing	13
Appendix A: Quick Reference Sizing Formulas	13
Appendix B: Typical Panel Efficiency by Technology	14
Appendix C: Case Study Summary Table	14

Chapter 1: Introduction to Solar Microgrids

A solar microgrid is a self-contained electrical power system that generates, stores, and distributes electricity from photovoltaic (PV) sources to a defined group of loads, with the ability to operate either connected to a larger utility grid or fully independent of it. Microgrids are distinguished from simple rooftop solar installations by their ability to island — that is, to disconnect from the main utility grid during outages and continue serving local loads using stored energy.

The core purpose of a microgrid is resilience and energy independence. Rural communities, island nations, disaster-relief camps, and remote industrial sites all use microgrids where extending traditional transmission lines would be prohibitively expensive or physically impossible.

1.1 A Brief History

Early experimental solar microgrids date back to isolated telecom relay stations in the 1970s, which used small PV arrays paired with lead-acid batteries to power radio repeaters in locations with no road access. The technology remained a niche application for four decades because photovoltaic cells were expensive and battery storage was inefficient.

The turning point came with the steep decline in lithium-ion battery costs between 2015 and 2023, alongside a roughly ninety percent drop in the price of crystalline silicon PV modules over the same broader period. This made hybrid solar-battery microgrids economically competitive with diesel generators in many off-grid contexts for the first time.

1.2 Why Microgrids Matter

Three forces are driving global adoption:

1. **Rural electrification** — an estimated 570 million people worldwide still lack reliable grid access, and microgrids are frequently the fastest and cheapest way to reach them.
2. **Grid resilience** — utilities in wildfire- and hurricane-prone regions increasingly use microgrids to keep critical infrastructure (hospitals, water treatment plants) powered during planned outages.
3. **Decarbonization** — replacing diesel generator sets with solar-battery hybrids can cut site-level carbon emissions by more than eighty percent.

1.3 Scope of This Reference

This book covers the engineering fundamentals needed to design, size, install, and maintain a small-to-medium solar microgrid, generally defined here as systems ranging from 5 kW to 500 kW of installed PV capacity, serving anywhere from a single household cluster up to a small village or industrial campus.

Chapter 2: Core System Components

Every solar microgrid, regardless of scale, is built from five essential subsystems: the generation source, the power conversion equipment, the energy storage system, the protection and control layer, and the distribution network. This chapter introduces each in turn.

2.1 Photovoltaic Arrays

Photovoltaic panels convert sunlight directly into direct current (DC) electricity via the photovoltaic effect in semiconductor materials, most commonly crystalline silicon. Panels are rated by their power output under Standard Test Conditions (STC): an irradiance of 1000 W/m², a cell temperature of 25°C, and an air mass of 1.5.

Three panel technologies dominate the microgrid market:

- **Monocrystalline silicon** — highest efficiency (typically 20–23%), highest cost per watt, best for space-constrained installations.
- **Polycrystalline silicon** — moderate efficiency (15–18%), lower cost, slightly larger footprint for equivalent output.
- **Thin-film (CdTe or CIGS)** — lowest efficiency (10–13%), most tolerant of high temperatures and partial shading, favored in large ground-mount arrays where land is not constrained.

Panels degrade over time due to UV exposure, thermal cycling, and micro-cracking. Reputable manufacturers warranty no more than a 0.5% annual output decline, meaning a panel should retain roughly 87% of its original output after 25 years.

2.2 Charge Controllers

A charge controller regulates the flow of DC power from the PV array into the battery bank, preventing overcharging and, in some designs, deep discharge. Two technologies are in common use:

- **PWM (Pulse Width Modulation)** controllers are simple and inexpensive but require the panel array voltage to closely match the battery bank voltage, resulting in energy losses of 10–30% under mismatched conditions.
- **MPPT (Maximum Power Point Tracking)** controllers continuously adjust the electrical operating point of the array to extract the maximum available power regardless of temperature or irradiance changes, typically improving harvest by 20–30% over PWM in real-world conditions.

For any system above roughly 2 kW of PV capacity, MPPT controllers are considered the industry-standard choice.

2.3 Battery Energy Storage Systems (BESS)

The battery bank stores surplus daytime generation for use at night or during cloudy periods. Chapter 4 covers battery chemistries in depth, but at a system level, the storage subsystem also includes a Battery Management System (BMS), which monitors individual cell voltages, temperatures, and state of charge, and disconnects the bank if unsafe conditions are detected.

2.4 Inverters

Inverters convert DC electricity from the panels or batteries into alternating current (AC) suitable for standard household and industrial loads. Microgrid inverters fall into three categories:

- **Grid-following inverters** synchronize their output to an existing AC waveform (either from the utility or from another inverter) and cannot operate alone.
- **Grid-forming inverters** generate their own stable voltage and frequency reference, allowing a microgrid to operate independently (“island mode”) with no utility connection.

- **Hybrid inverters** combine PV input, battery charge/discharge control, and grid-forming or grid-following operation into a single unit, and are now the dominant choice for new microgrid installations under 100 kW.

2.5 Distribution and Protection

The final subsystem carries power from the inverter to individual loads, and includes circuit breakers, fuses, surge protection devices, and — in larger systems — a Supervisory Control and Data Acquisition (SCADA) layer for remote monitoring, discussed further in Chapter 7.

Chapter 3: Microgrid Architectures

3.1 DC-Coupled Architecture

In a DC-coupled system, the PV array, charge controller, and battery bank all operate on a shared DC bus, and a single inverter converts the combined DC power to AC for the loads. This architecture is simpler and typically more efficient for systems where most generation is intended to charge batteries, since power only passes through one conversion stage when going from panel to battery.

3.2 AC-Coupled Architecture

In an AC-coupled system, PV power is converted to AC immediately by a dedicated grid-following inverter, and a separate battery inverter (grid-forming) manages storage. AC coupling is preferred when retrofitting battery storage onto an existing solar installation, since the existing PV inverter does not need to be replaced.

3.3 Hybrid Architecture

Most modern microgrid installations use a hybrid architecture: a single hybrid inverter manages PV input, battery storage, and AC output simultaneously, reducing the number of discrete components, simplifying wiring, and lowering both installation cost and maintenance burden.

3.4 Operating Modes

A microgrid inverter typically supports four operating modes:

1. **Grid-tied mode** — the system operates connected to the utility grid, exporting surplus power or importing shortfall as needed.
 2. **Island mode** — the system disconnects entirely from the utility (automatically, during an outage, or manually) and the grid-forming inverter creates its own voltage reference.
 3. **Backup mode** — a subset of critical loads is automatically transferred to battery power within milliseconds of a utility outage being detected.
 4. **Peak-shaving mode** — the battery discharges during periods of high utility tariff pricing or high demand charges, even while grid-connected, to reduce the site's peak demand and overall electricity cost.
-

Chapter 4: Battery Chemistries Compared

Selecting the right battery chemistry is one of the highest-impact design decisions in a microgrid project, affecting upfront cost, lifespan, safety, and total cost of ownership.

Chemistry	Typical Cycle Life (to 80% capacity)	Round-Trip Efficiency	Usable Depth of Discharge	Relative Cost per kWh	Notes
Lead-acid (flooded)	300–500 cycles	70–80%	50%	Lowest	Requires regular watering and ventilation
Lead-acid (AGM/sealed)	500–800 cycles	75–85%	50%	Low	Maintenance-free, lower ventilation needs
Lithium Iron Phosphate (LFP)	3,000–6,000 cycles	92–96%	90–100%	Moderate	Industry standard for new microgrid projects
Nickel-Cobalt-Manganese (NCM)	1,000–2,000 cycles	90–95%	80–90%	Moderate-high	Higher energy density, more thermal sensitivity
Saltwater (sodium-ion)	3,000+ cycles	80–85%	100%	Low-moderate	Non-flammable, lower energy density

4.1 Why Lithium Iron Phosphate Dominates New Installations

LFP batteries have become the default choice for microgrid projects built after roughly 2020 for three reasons: they tolerate near-complete discharge without damage, they have a strong thermal stability profile that greatly reduces fire risk compared to other lithium chemistries, and their cycle life of 3,000 to 6,000 cycles typically translates to 10–15 years of daily use before capacity fades below 80% of nameplate rating.

4.2 State of Charge and Depth of Discharge

State of Charge (SOC) describes the current battery charge level as a percentage of full capacity. Depth of Discharge (DOD) describes how much of that capacity has been used, expressed as the inverse of SOC. Manufacturers specify a maximum recommended DOD to preserve battery lifespan; exceeding it repeatedly accelerates degradation.

4.3 Temperature Sensitivity

All battery chemistries lose usable capacity in cold conditions and degrade faster under sustained heat. As a rule of thumb, for every 10°C increase in average operating temperature above 25°C, a lithium-ion battery's

usable lifespan is reduced by approximately 30–50%, which is why battery enclosures in hot climates typically include active cooling or shading.

Chapter 5: Load Assessment and System Sizing

5.1 The Sizing Process

Correctly sizing a microgrid requires four sequential steps: (1) tabulating all loads and their daily energy consumption, (2) determining the required battery capacity to cover a target number of autonomy days, (3) calculating the PV array size needed to recharge the battery bank daily, and (4) selecting inverter capacity to handle peak simultaneous load.

5.2 Step 1 — Load Tabulation

Every appliance or load is characterized by its power draw (in watts) and its expected daily runtime (in hours), which together give daily energy consumption in watt-hours (Wh). For example, a household with the following loads:

Load	Power (W)	Hours/day	Energy (Wh/day)
LED lighting (6 bulbs)	60	5	300
Refrigerator	150	8 (effective compressor run-time)	1,200
Water pump	500	1	500
Television	100	4	400
Phone/laptop charging	40	3	120

Total daily energy demand: **2,520 Wh (2.52 kWh) per day.**

5.3 Step 2 — Battery Bank Sizing

Battery capacity must cover daily consumption plus a margin for days of poor sunlight, known as autonomy days. The formula is:

Required battery capacity (Wh) = Daily energy demand × Autonomy days ÷ Maximum depth of discharge

Using the example above with 2 autonomy days and an LFP battery rated for 95% usable DOD:

$2,520 \text{ Wh} \times 2 \div 0.95 = 5,305 \text{ Wh}$ (**approximately 5.3 kWh**) of nameplate battery capacity required.

5.4 Step 3 — PV Array Sizing

The PV array must generate enough energy in an average day to replace what was consumed, accounting for system losses (wiring, inverter conversion, dust soiling, and temperature derating), which are commonly estimated at a combined 20% for a well-designed system.

Required PV capacity (W) = Daily energy demand ÷ (Peak sun hours × System efficiency)

Using 5 peak sun hours per day (a typical value for many tropical and subtropical regions) and 80% system efficiency:

$2,520 \text{ Wh} \div (5 \times 0.80) = \mathbf{630 \text{ W}}$ of PV array capacity required, before adding any safety margin. Designers commonly add a further 15–20% margin to account for panel degradation over the system’s lifetime, bringing the practical target to roughly **740–760 W**.

5.5 Step 4 — Inverter Sizing

The inverter must be rated to handle the highest simultaneous power draw across all loads, not the average daily consumption. In the household example, if the water pump (500 W) and television (100 W) might run at the same moment as lighting (60 W), the inverter should be sized with headroom above this combined peak — commonly at least 25% above the calculated peak load to accommodate motor starting surges, which can briefly draw three to seven times a motor’s rated running current.

Chapter 6: Protection, Safety, and Grounding

6.1 Overcurrent Protection

Every conductor in a microgrid must be protected against overcurrent using fuses or circuit breakers rated appropriately for the wire’s ampacity. PV source circuits, battery circuits, and AC distribution circuits each require independent overcurrent protection, since a fault on one circuit should not be able to propagate into another.

6.2 Ground-Fault Protection

Ground-fault protection devices detect unintended current paths to earth, which can indicate insulation failure or equipment damage, and disconnect the affected circuit before it can cause a fire or shock hazard. In PV arrays, ground-fault detection is especially important because DC arc faults can sustain themselves and are harder to extinguish than AC faults.

6.3 Rapid Shutdown Requirements

Many jurisdictions require PV systems to include rapid shutdown functionality, which reduces conductor voltage to a safe level within 30 seconds of activation, protecting firefighters and emergency responders who may need to work near or on a structure with an active solar installation.

6.4 Arc-Fault Detection

DC arc-fault circuit interrupters (AFCIs) monitor the electrical signature of wiring for the characteristic high-frequency noise pattern produced by a loose connection or damaged conductor arcing, and disconnect the circuit before the arc can ignite surrounding material.

6.5 Battery Safety Enclosures

Battery banks, particularly lithium-based systems, are typically housed in enclosures with passive or active ventilation, thermal monitoring, and in larger installations, fire suppression systems tuned to lithium-battery

fires, which cannot be extinguished with standard water-based suppression due to the risk of thermal runaway reignition.

Chapter 7: Monitoring and Control Systems

7.1 Local Monitoring

Most modern inverters include a local display and companion mobile app showing real-time generation, consumption, battery state of charge, and historical energy flow data, typically logged at 1-minute to 15-minute intervals.

7.2 SCADA and Remote Monitoring

Larger microgrids (generally above 50 kW) commonly deploy a SCADA (Supervisory Control and Data Acquisition) system, which aggregates data from every major component — inverters, battery management systems, weather stations, and protective relays — into a central dashboard, allowing remote operators to monitor system health and issue control commands without visiting the site.

7.3 Predictive Maintenance

Advanced monitoring platforms increasingly apply anomaly detection to component performance data, flagging early indicators of failure such as gradually rising internal battery resistance or declining panel output relative to a cleaned reference panel, allowing maintenance teams to intervene before an outright failure occurs.

7.4 Demand Response Integration

Some microgrids integrate demand-response logic, automatically shedding non-critical loads (such as water heating or non-essential lighting) when battery state of charge falls below a configured threshold, extending the runtime of critical loads during extended low-sunlight periods.

Chapter 8: Operations and Maintenance

8.1 Routine Panel Maintenance

Dust, pollen, and bird droppings accumulate on panel surfaces and can reduce output by 5–25% depending on climate and cleaning frequency. In arid, dusty regions, a cleaning interval of every 4–6 weeks is common; in wetter climates with regular rainfall, natural cleaning may be sufficient for most of the year.

8.2 Battery Bank Inspection

Lithium battery systems require comparatively little manual maintenance beyond periodic inspection of the enclosure for ventilation blockages, verification that the BMS is reporting balanced cell voltages, and confirmation that thermal management systems are functioning. Lead-acid systems require more frequent attention, including periodic water top-ups for flooded designs and terminal corrosion checks.

8.3 Common Fault Patterns

Field data collected across many installations generally shows three failure categories in order of frequency: connector and wiring faults (often from thermal cycling and rodent damage), inverter failures (frequently caused by internal capacitor degradation after 8–12 years of service), and battery cell imbalance (usually a sign of an aging BMS or a manufacturing defect in one or more cells).

8.4 Recommended Spare Parts Inventory

A well-run microgrid maintenance program typically keeps on hand: spare fuses of each rating used in the system, at least one spare charge controller or inverter fan, surge protection modules (since these are considered sacrificial components), and basic torque tools for periodic connection re-tightening, since loose connections are a leading cause of localized overheating.

Chapter 9: Case Studies

9.1 Case Study — Kestrel Ridge Relay Station

Kestrel Ridge is a fictional composite case study representing a typical remote telecommunications relay installation. The site uses a 12 kW monocrystalline PV array paired with a 40 kWh Lithium Iron Phosphate battery bank, sized for 3 days of autonomy to keep the relay equipment powered through extended overcast periods. The system uses a DC-coupled architecture with a single 15 kW hybrid inverter, and has operated since commissioning with an average annual capacity factor of 21%.

9.2 Case Study — Meridian Village Cooperative

Meridian Village is a fictional composite case study representing a 40-household rural electrification project. The cooperative-owned system consists of a 85 kW polycrystalline ground-mount array, a 220 kWh mixed LFP battery bank split across four enclosures for redundancy, and three 30 kW grid-forming inverters operating in parallel for load-sharing and redundancy. The system includes a SCADA layer that allows the regional utility's operations center to monitor performance remotely, and supports a tariff structure in which households are billed per kWh consumed, with revenue funding ongoing maintenance.

9.3 Case Study — Thornbury Cold-Storage Facility

Thornbury is a fictional composite case study representing an industrial application: a small fish cold-storage warehouse that previously ran on diesel generators around the clock. The retrofit added a 60 kW thin-film PV array (chosen for its better high-temperature performance in the facility's hot coastal climate) and a 95 kWh sodium-ion battery bank, selected specifically for its non-flammable chemistry given the facility's food-storage safety requirements. The system operates in peak-shaving mode during grid-connected hours, discharging the battery during the utility's afternoon peak-tariff window, and switches to full island mode automatically during the region's frequent grid outages, maintaining cold-chain integrity for the stored inventory.

Chapter 10: Glossary of Key Terms

Autonomy days — the number of consecutive days a battery bank is designed to supply a site's full energy needs with no solar recharging, used as a design margin against extended cloudy weather.

Capacity factor — the ratio of actual energy produced by a generation source over a period to the maximum possible energy it could have produced if it operated at full rated output continuously.

Depth of Discharge (DOD) — the percentage of a battery's total capacity that has been discharged, expressed as the complement of state of charge.

Grid-forming inverter — an inverter capable of independently establishing voltage and frequency references, enabling a microgrid to operate without a connection to the utility grid.

Island mode — an operating condition in which a microgrid is electrically disconnected from the utility grid and self-sufficient.

MPPT (Maximum Power Point Tracking) — a charge controller technology that continuously adjusts the electrical operating point of a PV array to maximize power extraction.

Peak sun hours — a measure of solar resource expressed as the number of hours per day during which average irradiance would need to be 1000 W/m² to deliver the same total daily energy as the actual variable irradiance received.

SCADA (Supervisory Control and Data Acquisition) — a centralized system for monitoring and controlling distributed equipment across a facility or network of facilities.

State of Charge (SOC) — the current available capacity of a battery expressed as a percentage of its full capacity.

Thermal runaway — a self-reinforcing chain reaction inside a battery cell in which rising internal temperature accelerates chemical reactions that produce yet more heat, potentially leading to fire or explosion if not contained.

Chapter 11: Economics and Financing

11.1 Capital Cost Breakdown

For a typical hybrid microgrid installed in the 2025–2026 period, installed capital cost is generally distributed across the system as follows: PV modules account for roughly 25–30% of total cost, battery storage 30–35%, inverters and power electronics 15–20%, and the remainder split between structural mounting, wiring, protection equipment, permitting, and labor.

11.2 Levelized Cost of Energy (LCOE)

Levelized Cost of Energy expresses the total lifetime cost of a system (capital plus operations and maintenance, minus any salvage value) divided by the total lifetime energy it is expected to produce, yielding a cost figure in currency per kWh that allows fair comparison against grid electricity prices or diesel generation costs. Diesel generator sets in remote locations often produce power at an effective cost of 0.30 to 0.60 per kWh once fuel transport is included, whereas a well-designed solar-battery microgrid in a sunny climate can frequently achieve an LCOE of 0.08 to 0.18 per kWh over a 20-year system life.

11.3 Financing Models

Three financing structures are common for community and commercial microgrid projects:

1. **Direct ownership** — the site owner purchases the system outright and retains all savings, but bears full upfront capital risk.
2. **Power Purchase Agreements (PPAs)** — a third-party developer owns and maintains the system, selling electricity to the site at a fixed or escalating per-kWh rate, removing upfront cost for the site owner.
3. **Cooperative or utility ownership** — as illustrated in the Meridian Village case study, a community-owned entity finances the system collectively and recovers costs through metered billing to member households.

11.4 Payback Period Considerations

Simple payback period is calculated by dividing total installed cost by annual savings versus the prior energy source (typically diesel fuel and generator maintenance costs). Projects replacing diesel generation commonly see payback periods of 3 to 7 years, while projects that are the first electrification a site has ever had are better evaluated on LCOE and social impact rather than payback against a prior cost, since there was no prior electricity expense to offset.

Chapter 12: Environmental Impact and Lifecycle

12.1 Embodied Carbon

Manufacturing PV panels and batteries has an embodied carbon cost, primarily from silicon refining, cell manufacturing, and battery material processing. Despite this, a typical crystalline silicon panel installed in a moderate-to-high sunlight region achieves energy payback — the point at which it has generated as much energy as was consumed to produce it — within 1 to 2.5 years, out of a 25-to-30-year operating life.

12.2 End-of-Life and Recycling

Photovoltaic panels reaching end of life can have roughly 85–95% of their material mass recovered through dedicated recycling processes, primarily glass and aluminum framing, though silicon wafer and silver contact recovery remains less mature and more costly at present. Lithium battery recycling recovers a high percentage of cobalt, nickel, and copper, but lithium recovery rates have historically been lower, motivating ongoing research into more efficient extraction processes as battery volumes scale globally.

12.3 Land and Ecological Considerations

Ground-mount arrays raise land-use questions distinct from rooftop installations. Many newer projects address this through “agrivoltaics” — raising panel height and spacing to allow continued grazing or shade-tolerant crop cultivation beneath the array — or by prioritizing degraded or marginal land unsuitable for agriculture.

12.4 Comparative Emissions

Displacing one kWh of diesel-generated electricity with one kWh of solar-battery microgrid electricity avoids on the order of 0.6 to 0.9 kilograms of carbon dioxide equivalent emissions, depending on the efficiency and load factor of the displaced generator, making generator replacement one of the highest-impact single interventions available to an off-grid site seeking to lower its emissions footprint.

Chapter 13: Standards, Codes, and Certification

13.1 Why Standards Matter

Consistent technical standards ensure that components from different manufacturers can be safely combined, that installations are inspectable against a known benchmark, and that insurers and financiers can assess project risk consistently across regions.

13.2 Common Standard Families

Microgrid components and installations are typically certified against several overlapping standard families covering electrical safety, performance testing, and grid interconnection behavior. Inverters intended for grid-interactive operation must demonstrate correct anti-islanding behavior — automatically ceasing to energize the grid-side connection when utility power is lost, to protect utility line workers performing repairs.

13.3 Interconnection Agreements

Any microgrid capable of exporting power to a utility grid, even occasionally, generally requires a formal interconnection agreement with the local utility, specifying protection settings, metering arrangements, and liability terms before the system is permitted to operate in grid-tied mode.

13.4 Commissioning and Testing

Before a microgrid is handed over to its operator, a commissioning process verifies as-built wiring against design drawings, confirms protective device settings, tests automatic transfer between grid-tied and island modes, and validates that monitoring data being reported matches independently measured values, catching integration errors before they can cause field failures.

Appendix A: Quick Reference Sizing Formulas

- Required battery capacity (Wh) = Daily energy demand × Autonomy days ÷ Maximum depth of discharge
- Required PV capacity (W) = Daily energy demand ÷ (Peak sun hours × System efficiency)
- Recommended inverter headroom = Peak simultaneous load × 1.25 (minimum), higher if motor loads are present

Appendix B: Typical Panel Efficiency by Technology

Technology	Efficiency Range
Monocrystalline silicon	20–23%
Polycrystalline silicon	15–18%
Thin-film (CdTe/CIGS)	10–13%

Appendix C: Case Study Summary Table

Site	PV Capacity	Battery Capacity	Battery Chemistry	Architecture	Special Feature
Kestrel Ridge Relay Station	12 kW	40 kWh	LFP	DC-coupled	3-day autonomy for remote telecom
Meridian Village Cooperative	85 kW	220 kWh	LFP	Hybrid, parallel inverters	SCADA + per-kWh billing
Thornbury Cold-Storage Facility	60 kW	95 kWh	Sodium-ion	Hybrid	Peak-shaving + island backup