CS327: Compilers

Lab Assignment #4

Intermediate Code Generation

Three-Address Code in Quadruple Format

Submitted by

Bhavya Parmar

Mohit

Surriya Gokul

Tanishq Bhushan Chaudhari

Instructor

Shouvick Mondal

Semester: January–May 2026

Indian Institute of Technology Gandhinagar

Contents

1 Overview **1**

2 Language Design: "Simple" **1**
2.1 Supported Types . . . 1
2.2 Supported Constructs . . . 2
2.3 Relation to Previous Assignment (Cyrix) . . . 2

3 Part 1: Intermediate Code Generation **2**
3.1 Quadruple Representation . . . 2
3.2 Temporary Variable Generation . . . 2
3.3 SDT Actions for Expressions . . . 3
3.4 Type Checking and Implicit Casting . . . 3
3.5 Declaration IR . . . 3
3.6 The Assignment PDF Example . . . 3

4 Part 2: Extended IR Support — Control Flow **4**
4.1 if Statement . . . 4
4.2 if-else Statement . . . 4
4.3 while Loop . . . 4
4.4 for Loop . . . 5
4.5 Implementation Detail: the `for_gbody` Global . . . 5

5 Part 3: Code Output Format **6**
5.1 Output Structure . . . 6
5.2 Quadruple Table Format . . . 6
5.3 Symbol Table Format . . . 6
5.4 Note on Expression Statements . . . 6

6 Part 4: Error Handling **7**
6.1 Design: Error Buffering with IR Suppression . . . 7
6.2 Detected Error Categories . . . 8
6.3 Parser Error Verbosity . . . 8

7 Symbol Table Design **8**
7.1 Structure . . . 8
7.2 Scoping Rules . . . 9

8 Test Cases **9**
8.1 Tests 01–10: Standard Programs . . . 9
8.1.1 Test 01 — Basic Arithmetic + Casting (Excerpt) . . . 9
8.1.2 Test 05 — while Loop (Excerpt) . . . 10
8.1.3 Test 07 — Nested if-else (Excerpt) . . . 10
8.1.4 Test 08 — Scoping (Excerpt) . . . 11
8.1.5 Test 09 — break and continue . . . 11
8.2 Tests 11–15: Error Handling . . . 11
8.3 Test 16 — Assignment PDF Example . . . 12

9 Implementation Pipeline **12**
9.1 File Structure 12
9.2 Build and Run 13
9.3 Data Flow 13

10 Team Contributions **13**

11 Design Decisions and Justifications **13**

12 Conclusion **14**

1 Overview

This report documents the design and implementation of an **Intermediate Code Generator** for a C-like language called **Simple**, built as the fourth assignment of CS327 Compilers. The compiler translates source programs into **Three-Address Code (TAC)** represented in **Quadruple format**, following the Dragon Book (Aho, Lam, Sethi, Ullman) approach of Syntax-Directed Translation (SDT) with back-patching.

The compiler is implemented using **Flex** (lexer) and **Bison** (parser), and produces:

- A statement-by-statement IR trace with the source line echoed alongside generated quads and a live symbol table snapshot.
- A complete quadruple table at the end of compilation.
- A complete symbol table showing scope, lifetime, initialization status, and last known value for every declared variable.
- Meaningful error diagnostics for semantic errors, with IR suppression on failure.

The pipeline is fully end-to-end: source text → lexer → parser → SDT actions → quad table → formatted output.

2 Language Design: "Simple"

For this assignment the team designed a focused, C-like language called **Simple**. The language was deliberately kept small so that every construct maps cleanly to well-defined TAC patterns, while still being expressive enough to write non-trivial programs.

2.1 Supported Types

`int`, `float`, `void`.
`void` variables can be declared but cannot be assigned or used in expressions or conditions.

2.2 Supported Constructs

Category	Constructs
Declarations	`int x;` `int x = expr;`
Arithmetic	`+`, `-`, `*`, `/`, `%` with correct precedence
Unary	Unary minus (`-`), logical NOT (`!`), bitwise NOT (`~`)
Relational	`<`, `>`, `<=`, `>=`, `==`, `!=`
Logical	`&&`, `||`
Assignment	`=`, `+=`, `-=`, `*=`, `/=`
Increment/Decrement	Prefix `++x`, `--x`; Postfix `x++`, `x--`
Selection	`if`, `if-else`, nested `if-else` chains
Iteration	`while`, `for` (with optional init/cond/update)
Jump	`break`, `continue`, `return`, `return expr`
Blocks	Nested { } with full lexical scoping and variable shadowing
Comments	`// ...` and `/* ... */`

2.3 Relation to Previous Assignment (Cyrix)

In Assignment 3, the team implemented a much richer grammar (Cyrix) with lambdas, `foreach`, `match`, `fn`, `var`, power operator (`**`), and more. For A4, the instructor confirmed that only the constructs explicitly listed in the assignment specification need IR generation. Therefore Simple is a clean, focused subset—all constructs in Simple have correct and complete IR generation, whereas the exotic Cyrix constructs (lambdas, generics, etc.) are not required and not present.

3 Part 1: Intermediate Code Generation

3.1 Quadruple Representation

Each IR instruction is stored as a **quadruple**:

$$(\underbrace{\texttt{op}}_{\text{operator}}, \underbrace{\texttt{arg1}}_{\text{first operand}}, \underbrace{\texttt{arg2}}_{\text{second operand}}, \underbrace{\texttt{result}}_{\text{destination}})$$

Unused fields are printed as `-`. The table also carries an `expr` column that renders a human-readable form of each instruction (e.g. `t1=a+b`, `ifFalse t1 goto L2`) for quick reading.

3.2 Temporary Variable Generation

A global counter `tc` generates temporaries `t1`, `t2`, ... in sequential order. Similarly, a counter `lc` generates labels `L1`, `L2`, ...

```
static char *nt(void) { char *b=malloc(16); snprintf(b,16,"t%d",++tc);
    return b; }
static char *nl(void) { char *b=malloc(16); snprintf(b,16,"L%d",++lc);
    return b; }
```

3.3 SDT Actions for Expressions

Every expression non-terminal returns a **place** — either a temporary name or the variable itself — as its semantic value (`$$`). Quads are emitted bottom-up as the parser reduces rules.

Expression	Quads Emitted	Result Place
`A + B`	`(+, A, B, t)`	`t`
`A - B`	`(-, A, B, t)`	`t`
`A * B`	`(*, A, B, t)`	`t`
`A / B`	`(/, A, B, t)`	`t`
`A % B`	`(%, A, B, t)`	`t`
`-E`	`(minus, E, -, t)`	`t`
`!E`	`(!, E, -, t)`	`t`
`x = E`	`(=, E, -, x)`	`x`
`x += E`	`(+, x, E, t)  (=, t, -, x)`	`x`

3.4 Type Checking and Implicit Casting

The compiler performs static type checking and inserts explicit cast quads when needed. Arithmetic and relational operators promote operands to a common numeric type (`float` dominates `int`). Assignments cast the RHS to the LHS type. The cast operations are emitted as quads and shown in the `expr` column as function-like calls.

Cast	Quad Emitted	Expr Column
`int` → `float`	`(itof, x, -, t)`	`t= itof(x)`
`float` → `int`	`(ftoi, x, -, t)`	`t= ftoi(x)`

3.5 Declaration IR

- `int x;` → symbol table entry only; **no quad emitted**. The variable appears in the symbol table with `Init? = no`.
- `int x = E;` → symbol table entry **plus** `(=, E, -, x)` (with implicit cast if needed).
- `void x;` is allowed, but any initialization or assignment to `x` is a semantic error.

This follows the Dragon Book convention: uninitialised declarations simply reserve a name in the symbol table without generating code.

3.6 The Assignment PDF Example

The assignment specification includes the expression `a = b*-c + b*-c` as a reference. Our compiler (test16.c) produces exactly the expected quadruples:

```
| t1= minus c        | minus  | c      | -      | t1     |
| t2=b*t1            | *      | b      | t1     | t2     |
| t3= minus c        | minus  | c      | -      | t3     |
| t4=b*t3            | *      | b      | t3     | t4     |
| t5=t2+t4           | +      | t2     | t4     | t5     |
| a=t5               | =      | t5     | -      | a      |
```

This matches the format shown in the assignment PDF exactly.

4 Part 2: Extended IR Support — Control Flow

Control flow is handled using **back-patching**, following Dragon Book §6.7. Labels and conditional jumps are emitted with placeholder targets (`??`) and later filled in once the target address is known.

4.1 if Statement

`if (C) S`

Quad	Description
`(ifFalse, C, goto, ??)`	Jump if condition false; target back-patched to L_f
[S quads]	Body
`(label,` L_f`, -, -)`	False label

4.2 if-else Statement

`if (C) S else S1`

Quad	Description
`(ifFalse, C, goto, ??)`	Jump to L_f if false
[S quads]	True body
`(goto, ??, -, -)`	Jump to L_{end}
`(label,` L_f`, -, -)`	False label
[S1 quads]	False body
`(label,` L_{end}`, -, -)`	End label

Nested `if-else` chains (e.g. `else if`) are handled naturally because `else if` is just an `if-else` where the else-body is itself another `if-else`. A dedicated LIFO **if-goto stack** (`if_goto_stack`) ensures that the `goto Lend` quad index for each level is stored independently and never overwritten by inner levels.

4.3 while Loop

`while (C) S`

Quad	Description
`(label,` L_s`, -, -)`	Loop start
[C evaluation]	Condition
`(ifFalse, C, goto, ??)`	Exit if false; patched to L_{end}
[S quads]	Body
`(goto,` L_s`, -, -)`	Back-edge
`(label,` L_{end}`, -, -)`	Exit label

4.4 for Loop

```
for (init; cond; update) S
```

The for loop is the most complex construct. Our IR follows the standard Dragon Book layout where the **update code is placed before the body** (using a forward jump), ensuring correct execution order while keeping the condition check at the top of each iteration:

Quad	Description
[init quads]	Initialiser
`(label,` L_{test}`, -, -)`	Condition check point
`(ifFalse, cond, goto, ??)`	Exit if false; patched to L_{end}
`(goto, ??, -, -)`	Forward jump to L_{body}; patched at emit time
`(label,` L_{update}`, -, -)`	Update section
[update quads]	Increment/decrement
`(goto,` L_{test}`, -, -)`	Loop back to condition
`(label,` L_{body}`, -, -)`	Body entry
[S quads]	Body
`(goto,` L_{update}`, -, -)`	Jump to update
`(label,` L_{end}`, -, -)`	Exit label

The `continue` statement jumps to L_{update} (not L_{test}), correctly re-running the update before re-testing the condition. The `break` statement's goto quad index is collected into a per-loop **break buffer** and back-patched to L_{end} when the loop closes.

4.5 Implementation Detail: the `for_gbody` Global

Yacc mid-rule actions occupy exactly one union slot (`$$`). The for-loop's update mid-rule action needs to pass both a label string (`Lupdate`) and an integer (the `goto Lbody` quad index) to the closing action — but a single slot can only hold one. We store the quad index in a **static global** `for_gbody` and the label string in the slot. This is safe because for-loops do not recursively re-enter their own mid-rule actions.

5 Part 3: Code Output Format

5.1 Output Structure

The compiler produces a rich, multi-section output for every source file:

1. **Banner** — compiler name, assignment, and source file name.
2. **Source program** — echoed with line numbers.
3. **Statement-by-statement trace** — for each statement:
   a. Source line (with line number)
   b. Newly generated IR quads in tabular format
   c. Current symbol table state
4. **Final complete quadruple table** — all quads with source line annotation.
5. **Final complete symbol table** — all variables with full lifetime and scope information.

5.2 Quadruple Table Format

Each row has six columns: `No` (sequence number), `expr` (human-readable form), `op`, `arg1`, `arg2`, `result`. The `expr` column is generated by the printer by inspecting the `op` field and formatting accordingly — for example, a binary op becomes `result=arg1 op arg2`; an `ifFalse` quad becomes `ifFalse arg1 goto result`; a cast quad prints as `t= itof(x)` or `t= ftoi(x)`.

```
+======+=====================+===============+===============+===============+===============+=============+
|  No  |        expr         |      op       |     arg1      |     arg2      |    result     |  Src Line   |
+======+=====================+===============+===============+===============+===============+=============+
|    3 | t1=a+b              | +             | a             | b             | t1            | line 4      |
|    4 | c=t1                | =             | t1            | -             | c             | line 4      |
```

5.3 Symbol Table Format

The symbol table is printed after every statement, showing scope depth, declaration line, live-until (either "active" or the closing line number), initialisation status, and the last known value. The value `?` means "unknown" (used when a value is control-flow dependent or not yet assigned).

```
+------------------+---------+-------+-------------+--------------+---------+--------------+
|      Name        |  Type   | Scope | Decl Line   |  Live Until  |  Init?  |    Value     |
+------------------+---------+-------+-------------+--------------+---------+--------------+
|>x                | int     |   0   | line 2      | active       | yes     | 1            |
| x                | int     |   1   | line 5      | line 11      | yes     | 100          |
+------------------+---------+-------+-------------+--------------+---------+--------------+
(> = currently in scope)
```

The `>` marker identifies variables currently in scope. Out-of-scope ("gone") variables from closed blocks are also retained in the table for historical completeness.

5.4 Note on Expression Statements

For bare expression statements (e.g. `z += 4;`) the IR quads are emitted during expression evaluation (before the semicolon reduces), so by the time the `expression_statement` action fires, the quads already exist in the table. The statement-level display therefore shows only the updated symbol table for these statements, rather than repeating the quads. This is a minor display quirk — the quads themselves are always present in the final quadruple table in the correct position.

6 Part 4: Error Handling

6.1 Design: Error Buffering with IR Suppression

Rather than printing errors to `stderr` interleaved with normal output, the compiler uses an **error buffer** design:

```
typedef struct { char msg[256]; } ErrEntry;
static ErrEntry ERR[MAX_ERRORS];
static int      err_cnt = 0;
static int      suppress_ir = 0;

void add_error(const char *fmt, ...) {
    /* collect error; set suppress_ir = 1 */
}
```

All errors (lex, parse, and semantic) call `add_error()`, which buffers them. The `suppress_ir` flag prevents any IR output from being printed. At the end of compilation, `main()` makes one decision:

- **No errors:** Print full IR output, final quad table, final symbol table, and `[OK]`.
- **Errors:** Print all buffered error messages together in a dedicated **ERRORS DETECTED** section, and `[FAIL]`. IR is suppressed entirely.

This produces clean, unambiguous output: a user either gets full IR or a clean error report — never a mix.

6.2 Detected Error Categories

Error Type	Detection Point	Message Format
Redeclaration in same scope	`sym_decl()`	`[Semantic Error] Line N: 'x' already declared (first at line M)`
Use of undeclared variable	`primary_expression`	`[Semantic Error] Line N: use of undeclared variable 'x'`
Assignment to undeclared variable	`assignment_expression`	`[Semantic Error] Line N: assignment to undeclared variable 'x'`
Void variable initialisation / assignment	`declaration_statement`, `assignment_expression`	`[Semantic Error] Line N: void variable 'x' cannot be initialized`
Void value used in expression or condition	`primary_expression`, condition rules	`[Semantic Error] Line N: void value used in expression`
`break` outside loop	`jump_statement`	`[Semantic Error] Line N: 'break' outside a loop`
`continue` outside loop	`jump_statement`	`[Semantic Error] Line N: 'continue' outside a loop`
Unknown character	`simple.l` rule	`[Lex Error] Line N: unknown character 'X'`
Syntax error	`yyerror()`	`[Parse Error] Line N near 'tok': ...`

6.3 Parser Error Verbosity

The parser uses `%define parse.error verbose` so Bison generates error messages that name the unexpected token and list the tokens that were expected, making syntax errors highly informative.

7 Symbol Table Design

7.1 Structure

```c
typedef struct {
    char name[64], type[16], value[64];
    int  scope;     /* nesting depth at declaration */
    int  init;      /* 0 = declared only, 1 = assigned at least once */
    int  decl;      /* source line of declaration */
    int  end;       /* line where scope closed (-1 = still live) */
    int  active;    /* 1 = currently visible */
} Sym;
```

7.2 Scoping Rules

- Every { block increments the scope depth; every } decrements it and marks all variables at that depth as inactive (setting `end` to the current line).
- **Lookup is innermost-scope-first**: the table is scanned from newest to oldest, so inner declarations shadow outer ones of the same name.
- **Redeclaration** within the *same* scope at the *same* depth is an error. Redeclaration in an *inner* scope (shadowing) is legal and correctly handled.
- **Value tracking**: after a constant assignment (`x = 5`), the value `5` is recorded in the symbol table. After an expression assignment (`x = t3`), the temp name is recorded. This gives the evaluator visibility into what each variable currently holds.
- **Conservative unknowns inside control flow**: assignments inside `if/else` blocks or loops mark the value as `?` because the assignment may or may not execute along all paths. This keeps the symbol table consistent without changing the IR.

8 Test Cases

The compiler was tested with **16 programs**: 10 standard programs (tests 01–10), 5 error-handling programs (tests 11–15), and 1 program replicating the assignment PDF example (test 16).

8.1 Tests 01–10: Standard Programs

Test	Description	Key Constructs Exercised
01	Basic arithmetic and assignment	`+`, `-`, `*`, `/`, declarations, `=`
02	Unary operators and compound assignments	`-x`, `+=`, `-=`, `*=`, `/=`
03	Simple `if` (no else)	Conditional jump, back-patching
04	`if-else`	Two-branch selection
05	`while` loop	Loop labels, back-edge, condition
06	`for` loop	All 4 labels, update before body
07	Nested `if-else` (grade classifier)	3-level nesting, if-goto stack
08	Block scoping and variable shadowing	Two `x` variables, scope table
09	`for` loop with `break` and `continue`	Break buffer, continue target
10	Nested loops + `&&` + `+=`	Full integration, 30 quads

8.1.1 Test 01 — Basic Arithmetic + Casting (Excerpt)

Source:

```
int a = 5;
int b = 10;
float c = a + b;
int d = a * b - c;
int e;
```

```
e = d / 2;
```

Final Quadruple Table:

```
|     1 | a=5          | =      | 5     | -     | a     | line 2  |
|     2 | b=10         | =      | 10    | -     | b     | line 3  |
|     3 | t1=a+b       | +      | a     | b     | t1    | line 4  |
|     4 | t2= itof(t1)| itof   | t1    | -     | t2    | line 4  |
|     5 | c=t2         | =      | t2    | -     | c     | line 4  |
|     6 | t3=a*b       | *      | a     | b     | t3    | line 5  |
|     7 | t4= itof(t3)| itof   | t3    | -     | t4    | line 5  |
|     8 | t5=t4-c      | -      | t4    | c     | t5    | line 5  |
|     9 | t6= ftoi(t5)| ftoi   | t5    | -     | t6    | line 5  |
|    10 | d=t6         | =      | t6    | -     | d     | line 5  |
|    11 | t7=d/2       | /      | d     | 2     | t7    | line 7  |
|    12 | e=t7         | =      | t7    | -     | e     | line 7  |
```

8.1.2 Test 05 — while Loop (Excerpt)

Source:

```
int i = 0;
int sum = 0;
while (i < 5) {
    sum = sum + i;
    i = i + 1;
}
```

Final Quadruple Table:

```
|     3 | label L1           | label    | L1    | -     | -     | line 4  |
|     4 | t1=i<5             | <        | i     | 5     | t1    | line 4  |
|     5 | ifFalse t1 goto L2| ifFalse  | t1    | goto  | L2    | line 4  |
|     6 | t2=sum+i           | +        | sum   | i     | t2    | line 5  |
|     7 | sum=t2             | =        | t2    | -     | sum   | line 5  |
|     8 | t3=i+1             | +        | i     | 1     | t3    | line 6  |
|     9 | i=t3               | =        | t3    | -     | i     | line 6  |
|    10 | goto L1            | goto     | L1    | -     | -     | line 7  |
|    11 | label L2           | label    | L2    | -     | -     | line 7  |
```

8.1.3 Test 07 — Nested if-else (Excerpt)

Source:

```
int marks = 82;
int grade;
if (marks >= 90)        grade = 10;
else if (marks >= 80)   grade = 9;
else if (marks >= 70)   grade = 8;
else                    grade = 7;
```

Final Quadruple Table (control-flow quads only):

```
|     2 | t1=marks>=90        | >=       | marks| 90    | t1    |
|     3 | ifFalse t1 goto L1 | ifFalse  | t1   | goto  | L1    |
|     4 | grade=10            | =        | 10   | -     | grade|
|     5 | goto L6             | goto     | L6   | -     | -     |  <- patched
```

```
|     6 | label L1            | label    | L1    | -     | -     |
|     7 | t2=marks>=80        | >=       | marks| 80    | t2    |
|     8 | ifFalse t2 goto L2 | ifFalse | t2    | goto | L2    |
|     9 | grade=9             | =        | 9     | -     | grade|
|    10 | goto L5             | goto     | L5    | -     | -     |  <- patched
|    11 | label L2            | label    | L2    | -     | -     |
    ... (continues to L3, L4, L5, L6)
|    18 | label L4            | label    | L4    | -     | -     |
|    19 | label L5            | label    | L5    | -     | -     |
|    20 | label L6            | label    | L6    | -     | -     |
```

Each `goto` is correctly back-patched to its matching end-label via the LIFO `if_goto_stack`.

8.1.4 Test 08 — Scoping (Excerpt)

Source:

```
int x = 1;
int y = 2;
{
    int x = 100;    /* shadows outer x */
    y = x + y;     /* uses inner x=100 */
    { int z = x * 2; y = y + z; }
}
int result = x + y;  /* uses outer x=1 */
```

The symbol table snapshot after the outer block closes correctly shows the inner `x` (scope 1) as `gone` and the outer `x` (scope 0) as `active`. The quad `(+, x, y, t4)` for `result` uses the outer `x=1`.

8.1.5 Test 09 — break and continue

Source:

```
for (i = 0; i < 10; i = i + 1) {
    if (i == 5) break;
    if (i == 2) continue;
    sum = sum + i;
}
```

Key quads:

```
|    14 | goto L6    |  <- break:    jumps to Lend (L6), back-patched
|    18 | goto L2    |  <- continue: jumps to Lupdate (L2)
```

8.2 Tests 11–15: Error Handling

Test	Error Scenario	Errors Detected	Outcome
11	Redeclaration of `x` in same scope + void init	2 semantic errors	`[FAIL]`, IR suppressed
12	Use of undeclared `c` and `e`	2 semantic errors	`[FAIL]`, IR suppressed
13	`break`/`continue` outside loop	2 semantic errors	`[FAIL]`, IR suppressed
14	Unknown characters `@` and `#`	1 lex + 1 parse error	`[FAIL]`, IR suppressed
15	Mixed: scope redeclaration + undeclared var	2 semantic errors	`[FAIL]`, IR suppressed

Example error output (test 11):

```
=== ERRORS DETECTED (2) ====================================
    [Semantic Error] Line 4: 'x' already declared in this scope
                                                    (first declared at line 2)
    [Semantic Error] Line 5: void variable 'z' cannot be initialized
=====================================================================
[FAIL] 2 error(s) found. IR output suppressed.
```

8.3 Test 16 — Assignment PDF Example

Source:

```
int a = 1;
int b = 2;
int c = 3;
a = b * -c + b * -c;
```

Final Quadruple Table:

```
|    4 | t1= minus c    | minus | c    | -    | t1   | line 4  |
|    5 | t2=b*t1        | *     | b    | t1   | t2   | line 4  |
|    6 | t3= minus c    | minus | c    | -    | t3   | line 4  |
|    7 | t4=b*t3        | *     | b    | t3   | t4   | line 4  |
|    8 | t5=t2+t4       | +     | t2   | t4   | t5   | line 4  |
|    9 | a=t5           | =     | t5   | -    | a    | line 4  |
```

This is an exact match of the quadruple table shown in the assignment specification.

9 Implementation Pipeline

9.1 File Structure

File	Role	Lines
`simple.l`	Flex lexer	≈100
`simple.y`	Bison parser + SDT + all IR logic	≈1000
`Makefile`	Build automation	40
`tests/test01--10.c`	Standard test programs	10 files
`tests/test11--15.c`	Error-handling test programs	5 files
`tests/test16.c`	Assignment PDF example	1 file
`outputs/output01--16.txt`	Outputs	16 files

9.2 Build and Run

```
sudo apt install bison flex   # one-time install
make                          # build the compiler
make tests                    # run all 16 tests, save outputs
make run FILE=tests/test01.c  # run a single test
make clean                    # remove build artifacts
```

9.3 Data Flow

$$\texttt{source.c} \xrightarrow{\text{flex (simple.l)}} \text{token stream} \xrightarrow{\text{bison (simple.y)}} \text{LALR(1) parse + SDT} \xrightarrow{\text{emit_q()}} \text{quad table} \xrightarrow{\text{print_summary()}} \text{formatted output}$$

10 Team Contributions

Team Member	Contribution
Bhavya Parmar	*Rewrote the previous Cyrix grammar for this assignment (removed extra constructs).*
Mohit	*SDT for basic constructs; type checking and implicit casting logic; IR output formatting and output verification.*
Surriya Gokul	*Control-flow SDT (if/else/loops) and back-patching logic checks.*
Tanishq Bhushan Chaudhari	*Test suite creation (tests 01–16), output verification, and report write-up polishing.*

11 Design Decisions and Justifications

1. **Named non-terminal `if_prefix` for if/if-else.** Writing two separate rules both starting with `IF '(' expression ')'` caused 22 reduce/reduce conflicts in Bison (the parser cannot tell which rule to start reducing until it sees `ELSE` or not). Factoring the shared prefix into `if_prefix` reduces this to the single expected dangling-else shift/reduce conflict, which Bison resolves correctly by default (shift = attach else to nearest if).

2. **LIFO `if_goto_stack` for nested if-else.** The `goto Lend` quad index from the outer if-else must survive while the inner if-else runs. A single global is overwritten; a stack preserves each level independently.

3. `for_gbody` **global for the for-loop.** A single mid-rule action slot cannot carry both a `char*` (Lupdate label) and an `int` (goto Lbody index). The static global `for_gbody` carries the integer, while the slot carries the string. This is safe because for-loop mid-rule actions do not re-enter each other recursively.

4. **Error buffering and IR suppression.** Rather than printing errors to stderr mid-output, all errors are buffered. If any error occurred, the final output is a clean error report with no partial IR. This prevents the evaluator from seeing corrupted or misleading intermediate code.

5. **Dragon Book quadruple convention, no optimisation.** All IR is emitted exactly as the Dragon Book prescribes, with no constant folding, dead-code elimination, or any other optimisation. This ensures the output is predictable and matches lecture slide conventions.

6. `%option yylineno` **in Flex.** Rather than manually maintaining a line counter in the lexer, `%option yylineno` asks Flex to track line numbers automatically. This eliminates the `yylineno` redefinition error that occurs when the lexer and the Flex-generated `lex.yy.c` both try to define the same variable.

12 Conclusion

The Simple compiler correctly implements all four parts of Assignment 4:

- **Part 1** — IR generation for arithmetic, assignment, unary operators, and temporary variable generation, verified against the assignment PDF example.
- **Part 2** — Extended IR for `if`, `if-else`, `while`, `for`, `break`, and `continue`, using Dragon Book back-patching.
- **Part 3** — Clean tabular output with an `expr` column, a live symbol table after each statement, and a final complete quad table.
- **Part 4** — Nine distinct error categories detected and reported clearly, with IR suppressed on any error.

The compiler has been tested with 16 programs (10 standard + 5 erroneous + 1 PDF example) and all outputs have been verified correct. The system is ready for evaluation.