

Installation Guide

1. End-User Installation (Windows)

Prerequisites

- **Operating System:** Windows 10 (64-bit) or newer.
- **Hardware:** 64-bit Processor, 4GB RAM.
- **Network:** Connection to the same Local Area Network (LAN) as your Monnit Gateways.

Important Limitation

Sensor Configuration: This utility acts as a read-only monitor for Monnit sensors. It **cannot** be used to configure sensor settings (Heartbeats, Aware Thresholds, etc.) on the hardware itself. All sensor hardware configuration must be performed using the iMonnit software suite before or during deployment.

Steps

1. Download the latest installer: Monnit ALTA MODBUS TCP Utility Setup v.2.0.0.exe.
2. Run the installer.
 - **User Selection:** You can choose to install for "Just Me" (does not require Admin) or "All Users" (requires Admin).
 - **Shortcuts:** Keep "Create Desktop Shortcut" checked for easy access.
3. Launch the application from the Desktop shortcut or Start Menu.

Data Location & Backups

The application stores all data locally on your machine.

- **Database Location:** C:\Users\[USERNAME]\AppData\Roaming\monnit-modbus-tcp-utility\
 - **Files to Backup:**
 - sensor_data.db: Contains all sensor history, gateway configurations, and alerts.



Monnit MODBUS TCP Utility

Windows Application Updates

The utility includes a built-in update engine designed to keep your system secure and up-to-date with minimal downtime.

Automatic Updates

By default, the application checks for updates weekly if the "Update Automatically" setting is enabled in the Portal Settings.

1. The app checks GitHub in the background.
2. If an update is found, it downloads automatically.
3. A notification will appear in the Portal Settings tab allowing you to "Restart & Install".

Manual Updates

You can manually check for updates at any time:

1. Navigate to the **Portal Settings** tab.
2. Locate the **Application Updates** section.
3. Click **Check for Updates**.
4. If an update is available, wait for the download to complete, then click **Restart & Install**.

Storage Requirements for Updates

Please ensure your system has at least **500 MB** of free space available. This accounts for the download of the new installer (approx. 100-150 MB) and the temporary unpacking process required to replace the application files safely.

2. Mac & Linux Installation

The application codebase is cross-platform compatible, but the pre-built installer provided is typically for Windows. To run on macOS or Linux, you may need to build from source or obtain a platform-specific package.

macOS

- **Supported Versions:** macOS 10.15 (Catalina) or newer.

Monnit MODBUS TCP Utility

- **Installation:** If a .dmg is provided, drag the application to your Applications folder. If running from source, follow standard Node.js/Electron build procedures.
- **Data Location:** ~/Library/Application Support/monnit-modbus-tcp-utility/

Linux

- **Supported Distributions:** Ubuntu 20.04+, Debian 10+, Fedora 32+.
- **Installation:** .ApplImage or .deb files may be provided. Make the ApplImage executable (chmod +x) and run it.
- **Data Location:** ~/.config/monnit-modbus-tcp-utility/ or
\$XDG_CONFIG_HOME/monnit-modbus-tcp-utility/