

Brief comments on the newly added feature to `getLocalSpace()` to split up channel symmetry into groups: $NC \rightarrow [n_{c1}, n_{c2}, \dots]$

The setup function `getLocalSpace()` now allows to group multiple spinful channels into separate symmetries. The tweak is based on the parameter `NC`, which now accepts a set of numbers, rather than just a single one. For example (#1),

```
>> [FF,Z,SS,IS]=getLocalSpace('FermionS',...
    'SU2spin,Acharge,SUNchannel','NC',[2 1],'-v');

getLo'>getLocal':555 17:48:46 <i> fermionic (2+1)-level system
getLo'>getLocal':555 17:48:46 ==> SU2spin,Acharge,SUNchannel [SU2,A,A,SU2]
```

This splits up both, `Acharge` and `SUNchannel` into groups:

- if a group in `NC=[..., nc, ...]` consists of `nc>1` flavors, this will result into a `U(1)` charge label plus an `SU(nc)` channel symmetry for this subset of flavors.
- for `nc=1`, only a `U(1)` charge label is generated.
- all `Acharge` labels are grouped together, and also all `SUNchannel` labels; the order of whether the `Acharge` labels are the `SUNchannel` labels come first, is given by their order in the call to `getLocalSpace` (see above).
- more information on the symmetry labels (and in particular their order, and more verbose info strings) can be obtained by looking into the `IS.SOP` structure

```
>> {IS.SOP.info}'
'total spin SU(2)'
'U(1) charge group #1 (1,2)'
'U(1) charge group #2 (3)'
'SU(2) channel group #1'
```

Example #2 (same as above, but reversed grouping; note altered order of symmetries)

```
>> [FF,Z,SS,IS]=getLocalSpace('FermionS',...
    'SU2spin,Acharge,SUNchannel','NC',[1 2],'-v');

getLo'>getLocal':555 17:58:58 <i> fermionic (1+2)-level system
getLo'>getLocal':555 17:58:58 ==> SU2spin,Acharge,SUNchannel [SU2,A,A,SU2]

>> {IS.SOP.info}'
'total spin SU(2)'
'U(1) charge group #1 (1)'
'U(1) charge group #2 (2,3)'
'SU(2) channel group #2'
```

Example #3 (4 spinful flavors, likely already too large for actual NRG runs)

```
>> [FF,Z,SS,IS]=getLocalSpace('FermionS',...
    'SU2spin,Acharge,SUNchannel','NC',[2 2],'-v');

getLo'>getLocal':555 18:01:36 <i> fermionic (2+2)-level system
getLo'>getLocal':555 18:01:36 ==> SU2spin,Acharge,SUNchannel [SU2,A,A,SU2,SU2]

>> {IS.SOP.info}'
'total spin SU(2)'
'U(1) charge group #1 (1,2)'
'U(1) charge group #2 (3,4)'
'SU(2) channel group #1'
'SU(2) channel group #2'
```