

Bip 音乐界面显示

一、配置

1、修改 bt_profile_config.c 中

const u8 more_avctp_cmd_support = 1;

```
1.  #if (USER_SUPPORT_PROFILE_AVCTP==1)
2.  u8 acp_profile_support = 1;
3.  #if (defined USER_SUPPORT_PROFILE_BIP && (USER_SUPPORT_PROFILE_BIP==1))
4.  u8 bip_profile_support = 1;
5.  SDP_RECORD_HANDLER_REGISTER(arp_ct_sdp_record_item) = {
6.      .service_record = (u8 *)sdp_avctp_ct_service_data_browsing,
7.      .service_record_handle = 0x00010002,
8.  };
9.  #else
10. SDP_RECORD_HANDLER_REGISTER(arp_ct_sdp_record_item) = {
11.     .service_record = (u8 *)sdp_avctp_ct_service_data,
12.     .service_record_handle = 0x00010002,
13. };
14. #endif
15. #if BT_SUPPORT_MUSIC_VOL_SYNC
16. SDP_RECORD_HANDLER_REGISTER(arp_ta_sdp_record_item) = {
17.     .service_record = (u8 *)sdp_avctp_ta_service_data,
18.     .service_record_handle = 0x00010005,
19. };
20. #endif
21. #endif
```

2、bt/bt.c

bt_music_info_handle_register(user_get_bt_music_info) ;
开启歌曲信息回调注册

二、接口

- 1、user_send_cmd_prepare(USER_CTRL_BIP_GET_IMAGE, 0, NULL);
获取音乐界面命令接口；
- 2、void bip_rx_data_handle(u8 *packet, u16 body_len, u32 length, u8 bip_data_status)
音乐图片数据回调
 - @param packet 数据包内容
 - @param body_len 数据包长度
 - @param length 整个图片大小,只有 ios 支持在第一包返回
 - @param bip_data_status 数据状态

三、示例

1、获取函数

[illegible]

2、回调函数

```
1. #if (USER_SUPPORT_PROFILE_BIP == 1)
2. //          avrcp 传输音乐图片
3. /*****
4. //配置
5. #define BIP_FILE_PATH    "storage/sd0/C/musicbgp.jpg"//存储到 sd 卡
6. /* #define BIP_FILE_PATH    "storage/virfat_flash/C/musicbgp.jpg"//
   存储到 flash 的 ui 资源区 */
7. #define BIP_FILE_PATH_TMP    "storage/virfat_flash/C/mbgtmp.jpg"
```

```
8. #define BIP_FILE_NAME "musicbgp.jpg"
9. enum {
10.     BIP_DATA_STATUS_START = 0X01, //开始包
11.     BIP_DATA_STATUS_CONTINUE, //继续包(中间包)
12.     BIP_DATA_STATUS_STOP, //结束包
13.     BIP_DATA_STATUS_ERR, //错误包,可能是不支持,或者音乐软件未打开
14. };
15. enum {
16.     BIP_FILE_STATUS_ERR, //文件不存在
17.     BIP_FILE_STATUS_OK, //文件存在
18.     BIP_FILE_STATUS_UPDATE, //文件更新中
19. };
20. struct bip_file_info {
21.     FILE *fp; //文件句柄
22.     /* u8 en; //是否使能 */
23.     volatile s8 file_status; //文件状态
24.     void(*callback)(void); //回调
25. };
26. volatile struct bip_file_info bip_file;
27. #define __bip_info (&bip_file)
28. u8 *bip_file_path_get()
29. {
30.     return BIP_FILE_PATH;
31. }
32. u8 *bip_file_tmp_path_get()
33. {
34.     return BIP_FILE_PATH_TMP;
35. }
36. u8 *bip_file_name_get()
37. {
38.     return BIP_FILE_NAME;
39. }
40. u8 bip_file_status_get()
41. {
42.     return __bip_info->file_status;
43. }
44. void bip_file_set_callback(void (*callback)(void))
45. {
46.     __bip_info->callback = callback;
47. }
48.
49. /* -----
    -----*/
```

```
50. /**
51.  * @brief bip_rx_data_handle    音乐图片数据回调
52.  *
53.  * @param packet    数据包内容
54.  * @param body_len  数据包长度
55.  * @param length    整个图片大小,只有 ios 支持在第一包返回
56.  * @param bip_data_status    数据状态
57.  */
58. /* -----*/
59. void bip_rx_data_handle(u8 *packet, u16 body_len, u32 length, u8 bip_data_status)
60. {
61.     printf("<%s>status:%d\n", __func__, bip_data_status);
62.     switch (bip_data_status) {
63.     case BIP_DATA_STATUS_START: //收到第一包数据
64.         u8 *bit_file_path = bip_file_path_get();
65.         printf("bip_file_path: %s\n", bit_file_path);
66.         //删除旧文件
67.         /* __bip_info->fp = fopen(bit_file_path, "r"); */
68.         if (__bip_info->fp) {
69.             __bip_info->file_status = BIP_FILE_STATUS_ERR;
70.             /* fdelete(__bip_info->fp); */
71.             __bip_info->fp = NULL;
72.         }
73.         //新增文件
74.         __bip_info->fp = fopen(bit_file_path, "w+");
75.         if (__bip_info->fp) {
76.             __bip_info->file_status = BIP_FILE_STATUS_UPDATE;
77.             /* fwrite(__bip_info->fp, packet, body_len); */
78.         } else {
79.             printf("bip file open err\n");
80.         }
81.         break;
82.     case BIP_DATA_STATUS_CONTINUE: //收到文件数据
83.         if (__bip_info->fp) {
84.             /* fwrite(__bip_info->fp, packet, body_len); */
85.         } else {
86.             printf("bip file open err\n");
87.         }
88.         break;
89.     case BIP_DATA_STATUS_STOP: //收到结束命令
90.         if (__bip_info->fp) {
```

```
91.          /* fwrite(__bip_info->fp, packet, body_len); */
92.          /* fclose(__bip_info->fp); */
93.          __bip_info->fp = NULL;
94.          __bip_info->file_status = BIP_FILE_STATUS_OK;
95.      } else {
96.          printf("bip file open err\n");
97.      }
98.      if (__bip_info->callback) {
99.          __bip_info->callback();
100.     }
101.     break;
102. case BIP_DATA_STATUS_ERR:
103.     printf("BIP_DATA_STATUS_ERR");
104.     break;
105. }
106. }
107. #endif
```

珠海市杰理科技股份有限公司

2025 年 11 月 24 日