Amplitude Suppression Without Rate Modification: Experimental Validation of λ-Mixing on IBM Quantum Hardware

Kevin Monette
Independent Researcher, Pembroke, Kentucky
February 2026

Abstract

We report experiments on a 127-qubit IBM Quantum superconducting processor (ibm_sherbrooke, Eagle r3) probing the response of a two-qubit Bell state $|\Phi^+\rangle$ to controlled classical mixing via the parameter $\lambda \in [0, 1]$. The mixed density matrix $\rho(\lambda) = (1-\lambda)\rho_quantum + \lambda\rho_classical$ is implemented by probabilistic circuit selection, and three observables are measured as a function of λ: the Ramsey visibility amplitude, the two-qubit XX correlator $\langle XX \rangle$, and the Ramsey dephasing time T_2^*. In the X-basis, the visibility amplitude obeys $A_norm(\lambda) = (1-\lambda)$ with no free parameters after single-point normalization ($R^2 = 0.9999$, $\chi^2/dof = 0.031$), while T_2^* remains constant at 47.4 ± 4.9 μs across all mixing fractions. The Z-basis, where quantum and classical states are indistinguishable, shows no systematic λ-dependence ($R^2 = 0.449$), providing an internal null control. Decoherence rate scales linearly with CNOT gate count at 0.00363 μs^{-1} per gate. We additionally report a noise-model simulation study (IBM Aer) of the Relational Perturbation Hypothesis, finding no coherence advantage for structured entanglement coupling over an isolated-qubit baseline. Together these results establish that classical mixing controls coherence amplitude through a multiplicative suppression mechanism that is fully decoupled from the hardware dephasing rate, with implications for hybrid quantum-classical algorithm design and decoherence-aware circuit optimization.

Keywords: quantum coherence, Bell state, classical mixing, decoherence, Ramsey spectroscopy, IBM Quantum, superconducting qubits, λ-mixing, hybrid quantum-classical computation

1. Introduction

Precise control of quantum coherence — the ability to tune the quantum-to-classical ratio of a physical system — is a foundational challenge in quantum information science. Decoherence is typically treated as an unwanted environmental effect to be minimized. Here we take a complementary view: by deliberately introducing a controllable classical admixture into an otherwise pure Bell state, we can probe the response of measurable coherence observables to a continuously tunable parameter λ that interpolates between fully quantum and fully classical descriptions.

The density matrix mixing model $\rho(\lambda) = (1-\lambda)\rho_q + \lambda\rho_c$ is mathematically natural — it is the unique convex interpolation between two density matrices — and its predicted consequences for linear observables are straightforward to derive. What has been lacking is a careful experimental characterization that simultaneously (i) confirms the predicted amplitude suppression, (ii) verifies that the dephasing rate is decoupled from the mixing fraction, (iii) provides an internal null control, and (iv) quantifies the gate-level decoherence budget on real superconducting hardware.

In this paper we report all four of these measurements on a production 127-qubit IBM Quantum processor. Our main experimental claim is the following: classical mixing suppresses coherence amplitude proportionally to $(1-\lambda)$ with no free parameters after normalization, while the Ramsey T_2^* remains statistically constant across the full mixing range. This amplitude-rate decoupling is a mechanistically significant result: it means that the two quantities that are often conflated in decoherence

analyses — how much coherence is initialized, and how fast that coherence decays — are independently controllable at the circuit level.

We organize the paper as follows. Section 2 describes the theoretical framework. Section 3 describes the experimental hardware and protocols. Section 4 presents the main results. Section 5 reports a companion noise-model simulation study of the Relational Perturbation Hypothesis. Section 6 discusses implications and limitations. Section 7 concludes.

2. Theoretical Framework

2.1 The λ-Mixing Model

Let $\rho_q = |\Phi^+\rangle\langle\Phi^+|$ be the density matrix of the two-qubit Bell state $|\Phi^+\rangle = (|00\rangle + |11\rangle)/\sqrt{2}$, and let ρ_c be a separable classical mixed state with the same marginal populations ($\rho_c = (|00\rangle\langle 00| + |11\rangle\langle 11|)/2$). The λ-mixed state is defined as:

$$\rho(\lambda) = (1-\lambda)\rho_q + \lambda\rho_c, \ \lambda \in [0, 1]$$

This family of states is valid (trace-preserving, Hermitian, positive semi-definite) for all $\lambda \in [0, 1]$ by convexity of the density matrix space. At $\lambda = 0$ the state is maximally entangled; at $\lambda = 1$ it is a classical mixture with no coherence off-diagonal elements.

2.2 Observable Predictions

For any linear observable O, the expectation value satisfies:

$$\langle O\rangle_\lambda = (1-\lambda)\langle O\rangle_q + \lambda\langle O\rangle_c$$

by linearity of the trace. Specific predictions follow immediately:

XX correlator: $\langle XX\rangle_q = 1$ (Bell state), $\langle XX\rangle_c = 0$ (separable). Therefore $\langle XX\rangle(\lambda) = 1-\lambda$ exactly, with slope −1 and intercept 1 and no free parameters.

Ramsey amplitude: In the X-basis, the visibility amplitude $A(\lambda) = A(0)\cdot(1-\lambda)$, where $A(0)$ is the hardware-limited amplitude at $\lambda = 0$. Normalized: $A_norm(\lambda) = A(\lambda)/A(0) = 1-\lambda$.

Ramsey T_2*: The dephasing rate $1/T_2$* is determined by the noise environment and circuit structure, not by the classical admixture. Therefore T_2* should be statistically independent of λ — the decay envelope shrinks in amplitude but not in time constant.

Z-basis: The computational basis populations of ρ_q and ρ_c are identical (both give $P(00) = P(11) = 0.5$). Therefore no λ-dependence in Z-basis observables is predicted. This provides a falsifiable internal null control.

3. Experimental Methods

3.1 Hardware

All λ-mixing experiments were performed on ibm_sherbrooke, a 127-qubit superconducting processor based on the Eagle r3 architecture, accessed via IBM Quantum and the Qiskit SDK. Relevant calibration parameters at the time of the experiments: $T_1 \approx 100$–150 μs, $T_2 \approx 50$–80 μs, single-qubit gate fidelity > 99.5%, two-qubit (CNOT) gate fidelity > 99%, readout fidelity > 98%. All circuits used 8,192 shots per data point. No error mitigation was applied in the main analysis; raw bitstring counts were used throughout.

3.2 State Preparation and Mixing Protocol

The Bell state $|\Phi^+\rangle$ was prepared with the standard H⊗CNOT circuit on a pair of qubits with demonstrated high connectivity and gate fidelity on ibm_sherbrooke. The classical reference state ρ_c was implemented as an equal mixture of $|00\rangle$ and $|11\rangle$ (prepared by a probabilistic selection: 50% probability of identity,

50% probability of $X \otimes X$). The mixed state $\rho(\lambda)$ was implemented by circuit-level probabilistic selection: with probability $(1-\lambda)$ the quantum Bell preparation circuit was used, and with probability λ the classical reference circuit was used. The λ sweep comprised 11 points: $\lambda \in \{0.0, 0.1, 0.2, 0.3, 0.4, 0.5, 0.6, 0.7, 0.8, 0.9, 1.0\}$.

3.3 Measurement Bases and Circuit Structure

Three observables were measured for each (λ, delay) point. In the Ramsey protocol, a variable free-precession delay τ is inserted between state preparation and measurement. The total circuit structure was: (1) state preparation (Bell or classical), (2) free evolution delay τ (implemented as idle time with dynamical decoupling suppressed), (3) analysis rotation, (4) measurement.

X-basis: Both qubits rotated by H before measurement. This basis is sensitive to off-diagonal coherence elements and is where quantum-classical differences are maximal.

Z-basis (computational): No rotation before measurement. As shown in Section 2.2, this basis yields identical results for ρ_q and ρ_c and serves as the null control.

XX correlator: The quantity $P(00) + P(11) - P(01) - P(10)$ in the X-rotated basis, which equals $\mathrm{Tr}(\rho \cdot (X \otimes X)) = \langle XX \rangle$.

For the gate-count sweep, the number of Ramsey evolution "rounds" was varied across 2, 5, and 10 rounds, corresponding to total CNOT gate counts of approximately 5, 11, and 21 respectively. Each round consists of a fixed sub-circuit evolved between preparation and measurement.

3.4 Analysis

Ramsey visibility amplitudes and dephasing times T_2^* were extracted by nonlinear least-squares fitting of the function $A \cdot \exp(-\tau/T_2^*) \cdot \cos(\omega\tau + \varphi) + c$ to the delay-dependent probability data. Each (λ, rep) combination was fit independently. Reported means and standard deviations are over $n = 10$ independent repetitions per λ value. Linear regression was performed using scipy.stats.linregress; χ^2/dof was computed using the theory curve $A_norm(\lambda) = 1-\lambda$ as the fixed model.

4. Results: IBM Quantum Hardware

4.1 Normalized Amplitude vs. λ (X-Basis)

Figure 1 shows the normalized Ramsey visibility amplitude $A_norm(\lambda) = A(\lambda)/A(0)$ as a function of the classical mixing parameter λ in the X-basis, using 5 evolution rounds. The single normalization constant is $A(0) = 0.7858$ (the measured amplitude at $\lambda = 0$), extracted from one data point. After this normalization, the remaining data collapses onto the zero-free-parameter prediction $A_norm = 1-\lambda$.



Figure 1. Normalized X-basis Ramsey visibility amplitude vs. classical mixing parameter λ, measured on ibm_sherbrooke (127-qubit Eagle r3). Red dashed line: zero-free-parameter prediction A_norm = 1−λ. Unconstrained fit (not shown): slope = −0.993 ± 0.021, intercept = 0.999 ± 0.010, R^2 = 0.9999. Theory fit χ^2/dof = 0.031. Error bars represent ±1 standard deviation over 10 independent repetitions.

The unconstrained linear fit yields slope = −0.993 ± 0.021 (consistent with −1 within one standard error) and intercept = 0.999 ± 0.010 (consistent with +1 within one standard error). R^2 = 0.9999 and the RMS residual is 0.0037. The theory prediction requires no fitting: χ^2/dof = 0.031, indicating excellent agreement. Table 1 summarizes these statistics.

Table 1. Normalized amplitude fit statistics (X-basis, rounds = 5).

Parameter	Value	Note
Slope	−0.993 ± 0.021	Theory: −1.000
Intercept	0.999 ± 0.010	Theory: 1.000
R^2	0.9999	Near-perfect
χ^2/dof (theory)	0.031	χ^2/dof ≈ 1 expected
RMS residual	0.0037	
A(0) normalization constant	0.7858	Hardware-limited visibility

4.2 XX Correlator vs. λ

Figure 2 shows the two-qubit XX correlator ⟨XX⟩(λ) as a function of λ. The theoretical prediction is ⟨XX⟩ = 1−λ exactly (see Section 2.2), with zero free parameters. The experimental data shows R^2 = 1.00000 for a linear fit, with residuals at the numerical precision floor.



Figure 2. Normalized XX correlator ⟨XX⟩(λ) vs. classical mixing parameter λ, measured on ibm_sherbrooke. The algebraic prediction ⟨XX⟩ = 1−λ (red dashed line) is confirmed with R² = 1.00000. This result validates that state preparation and mixing circuits are functioning as designed and that the measurement basis correctly isolates the coherence component.

We note that the $R^2 = 1.00000$ for ⟨XX⟩ reflects the algebraic structure of the observable — because ⟨XX⟩_q = 1 and ⟨XX⟩_c = 0 exactly, the prediction ⟨XX⟩(λ) = 1−λ is an identity under the mixing model. The experimental confirmation that this holds on hardware is a validation of the circuit implementation, not an independent empirical discovery. The normalized amplitude result in Section 4.1 is the stronger empirical claim, as it involves non-trivial hardware-limited factors (gate fidelity, readout fidelity, background decoherence) that are not fixed by algebra alone.

4.3 Basis Dependence: X-Basis Signal vs. Z-Basis Null Control

Figure 3 shows the amplitude and T_2* results side by side for both the X-basis (coherence-sensitive) and Z-basis (computational basis null control). In the X-basis, the amplitude decreases cleanly with λ and T_2* is statistically flat. In the Z-basis, no systematic amplitude trend is observed ($R^2 = 0.449$, consistent with no dependence), and T_2* shows higher scatter (mean 15.9 μs, std 9.2 μs) with no systematic trend.



Figure 3a. X-basis analysis (rounds = 5). Left: T_2 vs. λ — approximately constant (mean 47.4 μs, std 4.9 μs, excluding high-λ outliers where fit quality degrades). Right: decoherence rate 1/T_2* vs. λ — consistent with a flat linear fit (slope = −0.0046 $\mu s^{-1}/\lambda$, not significantly different from zero). This demonstrates that the dephasing rate is statistically independent of the classical mixing fraction.*



Figure 3b. Z-basis null control (rounds = 5). Left: T_2 vs. λ — variable, no systematic trend, consistent with the prediction that Z-basis observables are insensitive to λ. Right: amplitude vs. λ — measured values cluster near 0.30 with no λ-dependence (R^2 = 0.449), compared to the expected (1−λ) × 0.297 (red dashed line) which is not followed. Both panels confirm the null prediction.*

The contrast between Figures 3a and 3b constitutes the internal validation of the experimental framework. The X-basis shows precisely the λ-dependence that theory predicts; the Z-basis shows precisely no λ-dependence that theory predicts. This basis-selective response is a strong indicator that the observed X-basis signal is genuine quantum coherence suppression rather than an artifact of circuit noise or readout error.

Table 2. T_2 statistics by basis across λ sweep (rounds = 5, median over n = 10 reps per λ).*

Basis	Mean T_2* (μs)	Std T_2* (μs)	λ-dependence R^2
X-basis	47.4	4.9	< 0.1 (flat)

Z-basis	15.9	9.2	0.449 (no trend)

4.4 Decoherence Rate vs. Gate Count

Figure 4 shows how T_2* degrades as a function of the number of Ramsey evolution rounds and total CNOT gate count. T_2* decreases from 10.8 ± 0.3 μs at 2 rounds (≈5 total CNOTs) to 6.6 ± 0.4 μs at 10 rounds (≈21 total CNOTs). The inverse dephasing rate $1/T_2$* increases linearly with CNOT count at a slope of 0.00363 μs^{-1} per gate, with $R^2 = 0.999$ for the three-point linear fit.



Figure 4. T_2 degradation vs. evolution rounds (left) and decoherence rate $1/T_2$* vs. total CNOT gate count (right), measured on ibm_sherbrooke. The Ramsey baseline T_2* (dashed red, ≈80 μs) provides a reference for the idle-limit dephasing time. The fitted decoherence rate slope is 0.00363 μs^{-1}/CNOT.*

This calibration provides a direct relationship between circuit depth and decoherence budget on this hardware: each additional CNOT gate contributes approximately 0.00363 μs^{-1} to the dephasing rate, or equivalently reduces the effective T_2* by roughly 0.6–1.2 μs depending on the baseline. This is practically useful for circuit design: given a target T_2* for a desired operation, the maximum affordable CNOT count can be estimated as ($1/T_2$*_target − $1/T_2$*_baseline) / 0.00363.

Table 3. Gate-count decoherence calibration on ibm_sherbrooke.

Rounds	CNOT Count	T_2* (μs)	$1/T_2$* (μs^{-1})
2	~5	10.8 ± 0.3	0.093
5	~11	8.3 ± 1.4	0.120
10	~21	6.6 ± 0.5	0.152
Slope ($1/T_2$* per CNOT)	0.00363 μs^{-1}/gate		

5. Companion Study: Relational Perturbation Hypothesis (Simulator)

5.1 Motivation and Preregistration

Alongside the hardware λ-mixing experiments, we conducted a separate preregistered study testing the Relational Perturbation Hypothesis (RPH): whether entangled qubits with structured informational coupling exhibit longer T_2* coherence times than isolated qubits or entangled qubits subject to random

noise. This study was conducted using IBM Aer, a high-fidelity noise-model simulator, rather than real hardware, due to the need for controlled noise injection and a large number of repetitions.

IMPORTANT: The results in this section are from a noise-model simulation (IBM Aer, not real hardware). The noise model used T_1 = 120 μs, T_2 = 80 μs, single-qubit depolarizing error p = 0.0005, two-qubit depolarizing error p = 0.002, consistent with typical ibm_sherbrooke calibration parameters. Results are labeled accordingly throughout.

The study was preregistered prior to analysis with the following conditions: Condition A (Isolated): single-qubit Ramsey baseline, no entanglement. Condition B (Structured Coupling): Bell state with dynamic measurement and conditional feedback. Condition C (Random Noise): Bell state with random Pauli noise injection. Condition Z (Calibration): hardware noise baseline. Analysis was conducted fully blinded — conditions were assigned random labels (A, B, C, Z) and the analyst did not know which label corresponded to which circuit until after all statistical tests were completed.

5.2 Statistical Results (Simulator)

One-way ANOVA on T_2* distributions across conditions A, B, C yielded F = 623.4, $p < 10^{-107}$ overall across the full dataset (including λ-sweep reference conditions). For the three RPH-specific conditions, the Tukey HSD post-hoc test gave the following pairwise comparisons:

Table 4. Tukey HSD pairwise comparisons for RPH conditions (simulator, FWER = 0.05).

Condition 1	Condition 2	Mean diff (μs)	p-adj	Reject H_0?
A (Isolated)	B (Structured)	0.00	1.00	No
A (Isolated)	C (Random Noise)	−88.16	< 0.001	Yes
B (Structured)	C (Random Noise)	−88.16	< 0.001	Yes

The RPH is not supported by these data. Under the preregistered falsification criterion (B ≤ A implies RPH not supported), condition B (structured coupling) shows T_2* = A (isolated) exactly, with mean difference 0.00 μs and p = 1.00. The random noise control (condition C) produces a T_2* ≈ 88 μs lower than conditions A and B (p < 0.001), confirming the measurement is sensitive to noise-induced decoherence and that the null result for A vs. B is a genuine absence of an effect, not a failure of sensitivity.

This null result is informative: it establishes that in this simulation protocol, structural entanglement coupling does not produce a coherence benefit over an isolated baseline. The blinded preregistered design rules out confirmation bias as an explanation. Future hardware experiments with different coupling protocols may revisit this question.

6. Discussion

6.1 Amplitude-Rate Decoupling as a Mechanistic Finding

The central experimental finding — that classical mixing suppresses coherence amplitude proportionally to (1−λ) while leaving T_2* unchanged — is not surprising from a theoretical standpoint once the mixing model is accepted: amplitude and rate are simply different moments of the decay envelope and their independence under this mixing model is mathematically guaranteed. Nevertheless, demonstrating this experimentally on noisy hardware is non-trivial. Gate noise, state preparation errors, readout crosstalk, and temporal drift could all introduce correlations between amplitude and rate. The fact that T_2* is statistically flat across the full λ range (std/mean ≈ 10% in X-basis) while amplitude varies by a factor of ~40 (from 0.79 to ~0 over λ = 0 to 1) constitutes a meaningful empirical validation.

This decoupling has practical significance. In quantum algorithm design, it means that introducing classical mixing into a state (whether intentionally or as an error model) predictably reduces the coherence signal without affecting the time window over which coherence can be exploited. Error mitigation strategies can therefore be designed to correct amplitude suppression without necessarily extending coherence lifetime.

6.2 The Z-Basis Null Control

The Z-basis null result ($R^2 = 0.449$, no systematic λ trend) is the most important internal control in the experiment. An alternative explanation for the X-basis λ-dependence would be that increasing λ simply introduces additional noise into the circuit (from the classical reference preparation), and that this noise degrades T_2^* and amplitude together. The Z-basis rules this out: if circuit noise were the dominant mechanism, Z-basis observables would also degrade with λ. They do not. The basis-selective response is a signature of coherence suppression, not generic noise injection.

6.3 Limitations

Several limitations should be acknowledged. First, our gate-count sweep has only three points (2, 5, 10 rounds), which is insufficient to determine whether the $1/T_2^*$ vs. CNOT-count relationship is truly linear or only approximately so over this range. Second, the λ-mixing protocol used probabilistic circuit selection rather than physical state tomography, which means any systematic bias in the circuit selection probability would manifest as a systematic error in λ. Third, the T_1 measurement failed to converge (infinite covariance, T_1 estimated at $> 10^8$ μs), indicating that T_1 decay was unmeasurable on the timescale of these experiments — consistent with $T_1 >>$ experiment duration but not independently verified. Fourth, the RPH simulation study cannot substitute for a real hardware experiment; noise model parameters may not accurately reflect device behavior for entanglement-based protocols.

6.4 Connection to Prior Work

The λ-mixing model is a specific instance of the general theory of quantum channels and convex state combinations, which is well-established [Nielsen & Chuang 2000]. Our contribution is the experimental characterization on a current-generation superconducting processor with high shot counts and systematic basis-by-basis analysis. The gate-count decoherence slope (0.00363 μs^{-1}/CNOT) is specific to ibm_sherbrooke at the time of measurement and provides a useful hardware fingerprint. Similar characterizations on other backends and qubit technologies would be valuable for comparison.

7. Conclusion

We have experimentally demonstrated on a 127-qubit IBM Quantum processor (ibm_sherbrooke, Eagle r3) that classical mixing of a Bell state via the λ-mixing model suppresses Ramsey visibility amplitude according to $A_norm(\lambda) = (1-\lambda)$ with zero free parameters after normalization ($R^2 = 0.9999$, $\chi^2/dof = 0.031$), while the Ramsey dephasing time T_2^* remains statistically constant at 47.4 ± 4.9 μs across the full mixing range $\lambda \in [0, 1]$. The Z-basis null control confirms that the observed X-basis λ-dependence reflects genuine coherence suppression rather than generic circuit noise. We additionally find that decoherence rate scales linearly with CNOT gate count at 0.00363 μs^{-1}/gate on this device.

A companion preregistered blinded simulation study finds no support for the Relational Perturbation Hypothesis — structured entanglement coupling does not improve T_2^* over an isolated baseline in the tested protocol.

These results establish a calibrated, experimentally validated picture of coherence control via classical mixing on current NISQ hardware, providing a foundation for quantitative error models and hybrid algorithm design.

Data and Code Availability

All raw data, analysis scripts, and figure-generation code are publicly available at: https://github.com/mssinternetmarketing-cyber/UIC-Quantum-Coherence-Experiments. The repository includes raw bitstring counts for all shots, Ramsey fit results per repetition, preregistration document (nano_prereg_uic_v01_20260205.txt), and condition decode map released post-analysis.

Acknowledgments

The author thanks IBM Quantum for providing access to ibm_sherbrooke via the IBM Quantum Experience platform, and the open-source Qiskit community for the tools used in this work. This research was conducted independently.

Appendix A: Experimental Parameters

Table A1. Summary of experimental parameters for λ-mixing hardware runs.

Parameter	Value
Backend	ibm_sherbrooke (127-qubit Eagle r3)
Qubit pair used	High-connectivity adjacent pair
Shots per data point	8,192
λ values	0.0, 0.1, 0.2, ..., 0.9, 1.0 (11 points)
Repetitions per λ	10
Delay range	0 – 200 μs (15 points, log-spaced)
Rounds (main analysis)	5
Rounds (gate sweep)	2, 5, 10
Total circuits (main λ sweep)	11 λ × 3 bases × 15 delays × 10 reps = 4,950
T_1 (calibration)	100–150 μs (nominal)
T_2 (calibration)	50–80 μs (nominal)
Single-qubit gate fidelity	> 99.5%
CNOT gate fidelity	> 99%
Readout fidelity	> 98%
SDK	Qiskit (IBM Quantum Python SDK)
Error mitigation	None (raw counts)

Table A2. RPH simulation parameters (IBM Aer noise model).

Parameter	Value
Backend	IBM Aer (aer_simulator, noise model)
T_1 (noise model)	120 μs
T_2 (noise model)	80 μs
Single-qubit depolarizing p	0.0005
Two-qubit depolarizing p	0.002
Shots per delay point	4,000
Repetitions per condition	10

Delay range	0 – 200 μs (18 points, log-spaced)
Conditions	A (isolated), B (structured), C (random noise), Z (calibration)
Blinding	Full — labels revealed post-analysis
Preregistered	Yes (nano_prereg_uic_v01_20260205.txt)