Preconditioning for quantum linear solvers in PDE-constrained optimization

Martin Stoll John W. Pearson

Working draft, November 2026

Abstract

Quantum linear system solvers cost a number of operations proportional to an *effective* condition number: the ratio of the normalization with which the matrix is embedded in a unitary circuit (its block encoding) to its smallest singular value. Preconditioning is therefore the main lever that numerical linear algebra has on quantum solvers, but its rules differ from the classical ones. Clustering of eigenvalues does not help, preconditioners must be applied by multiplication rather than by inner solves, and every factor of a product must be encoded with a normalization close to its norm. We develop preconditioners under these rules for the saddle-point systems of PDE-constrained optimization. For distributed control of the Poisson equation, we apply a Schöberl–Zulehner block preconditioner, combined with an additive multilevel (BPX) factor, on both sides of the KKT matrix and factor the result as $\mathcal{G}^* \mathcal{J} \mathcal{G}$, where $\mathcal{J}$ is a single two-qubit reflection that carries the indefiniteness. Building on the multilevel block encodings of Deiml and Peterseim, which we formulate through quadrature points so that they cover Q_k and P_k elements, $\mathcal{G}$ has a block encoding whose normalization grows only like $\sqrt{\log h^{-1}}$, and the effective condition number is bounded independently of the mesh size. Adapting robust multilevel methods for singularly perturbed problems to this factored form, we use normalized level weights for which the spectral bounds are also independent of the regularization parameter, and we prove this with explicit constants. For the time-periodic heat equation, a quantum Fourier transform in time decouples the problem into frequency-wise saddle-point problems of the same form; the block preconditioner satisfies a $\sqrt{3}$ bound uniform in all parameters, and the coupling matrix becomes a scaled reflection, so that neither the number of time steps nor the step size enters the cost. Numerical experiments in one, two and three dimensions confirm the bounds. We also discuss when an asymptotic quantum advantage can and cannot be expected.

1 Introduction

Quantum linear system algorithms (QLSAs) prepare a quantum state proportional to the solution x of $Ax = b$. They use a number of calls to a circuit encoding A that scales like $\kappa \log(1/\varepsilon)$, where ε is the accuracy of the prepared solution state [7, 8, 13]. The size n of the system enters only through the cost of that circuit, which is typically polylogarithmic in n for structured problems. Discretized partial differential equations are therefore an obvious application. The condition number of a discretized differential operator, however, grows with the resolution, like h^{-2} for second-order elliptic problems, and without preconditioning this growth cancels the gain in n [22, 24].

Preconditioning for QLSAs has accordingly received attention. Early proposals used sparse approximate inverses [6], "fast inversion" of a dominant part of the matrix [35], and wavelet bases [2]; more recently, preconditioners and ways of encoding them have been compared empirically for CFD matrices [23], and the increasingly ill-conditioned Newton systems of quantum interior point methods have been studied [28]. For elliptic finite element discretizations, Deiml and Peterseim [10] gave the first construction with a provably mesh-independent cost, and their work is the starting point of our Section 3. They write the stiffness matrix as $C_L^T (D_A \otimes I) C_L$, where

C_L maps nodal values to gradients in an L^2-orthonormal basis of discontinuous Q_1 functions and D_A holds the diffusion coefficient, and they apply BPX to this factor in the form of a generating system. A commutative diagram, in which the gradient is taken on the coarse level and then transferred by an inclusion with orthonormal columns, yields a block encoding of the preconditioned factor whose normalization grows only linearly in the number of levels. They also introduced the *effective condition number*, the product of subnormalization and condition number, which governs the cost, and ran small instances on quantum hardware. Jin, Liu, Ma and Yu [15] gave a finite-difference analogue, and Yang, Yu and Zhang [38] extended the construction to reaction–diffusion problems $-\Delta u + cu$ with a bound uniform in c.

These works make clear that preconditioning for a quantum solver is a different problem from classical preconditioning (Section 2). Only a bound on the condition number counts, not the distribution of the eigenvalues; the preconditioner must be realized as a circuit that *multiplies*, not one that solves; and the normalizations of all factors enter the cost, so that a good classical preconditioner can be useless if it is encoded as a separate factor.

The saddle-point systems of PDE-constrained optimization have not been considered from this angle. Classically, they are the prototype for parameter-robust block preconditioners, which are robust in both the mesh size h and the regularization parameter β [27, 29, 33]. On the quantum side, PDE-constrained optimization has been approached with variational heuristics [31], with a quantum optimizer acting on a block-encoded objective [30], and, for ODE-constrained linear-quadratic regulation, by applying a QLSA to the optimality system without preconditioning [16]. None of these addresses the dependence of the KKT system of a PDE-constrained problem on h and β, which is exactly what decides whether a QLSA can be competitive.

In this paper we develop preconditioners for these KKT systems under the quantum rules. We first formulate design principles for preconditioners of QLSAs in matrix terms, centred on the effective condition number κ_α (Section 2). For distributed control of the Poisson equation (Section 3), we combine the Schöberl–Zulehner block preconditioner with a diagonally scaled BPX factor R applied on both sides of the KKT matrix. The resulting matrix factors as $\mathcal{G}^*\mathcal{J}\mathcal{G}$, where $\mathcal{J}$ is a single two-qubit reflection that carries the indefiniteness and $\mathcal{G}$ maps multilevel coefficients to values and gradients at quadrature points. The block encoding of $\mathcal{G}$, with normalization $O(\sqrt{\log h^{-1}})$, builds on the commuting diagram of [10, 38]; we formulate it through quadrature points with an element-local isometry (Lemma 3.7), so that it covers Q_k and P_k elements on nested meshes, and obtain an effective condition number bounded independently of h (Theorem 3.9).

To make the multilevel factor robust in β as well, we adapt robust multilevel preconditioning for $I - \sqrt{\beta}\,\Delta$ [5, 11] to the Jacobi-scaled factored form that the block encoding needs. A family of normalized level weights makes the spectral interval $[c_0, c_1]$ itself independent of h and β, and we give a self-contained proof with explicit constants (Theorem 3.5).

For the time-periodic heat equation (Section 4), a quantum Fourier transform in time reduces the problem to frequency-wise problems of the Poisson type with effective parameter $\beta_k = \beta/r_k^2$. Extending a result of Krendl, Simoncini and Zulehner [17] from purely imaginary to general backward-Euler symbols, we show that the block preconditioner has a bound $\sqrt{3}$ uniform in h, τ, β and the frequency (Theorem 4.1). The coupling matrix becomes a scaled reflection of norm at most one, and neither the number of time steps nor the step size enters the effective condition number.

We verify all bounds and factorizations numerically in one, two and three dimensions (Section 6). Finally, we discuss complexity honestly (Section 7): an asymptotic advantage over optimal classical solvers requires $d = 3$ for the elliptic problem, and for the time-periodic problem it requires data that are rough in time. Section 5 describes the implementation, and Section 8 concludes with an outlook.

2 Quantum linear algebra in matrix terms

We describe the computational model in the language of numerical linear algebra (see [13, 21] for details). We start with an overview of the model, then describe block encodings and QSVT solvers, and finally discuss what preconditioning means in this context.

States and outputs. A unit vector $v \in \mathbb{C}^{2^k}$ is stored in k qubits. Its entries cannot be read out explicitly. Repeated measurements give estimates of quantities v^*Ov for suitable Hermitian O, with additive error η. This costs $\mathcal{O}(\eta^{-2})$ repetitions, or $\mathcal{O}(\eta^{-1})$ with amplitude estimation [1]. The output of a quantum solver is therefore a small number of scalar *quantities of interest* (QoIs), such as $\langle w, y\rangle_M$ or the value of the objective, never the vector x itself.

Block encodings. A quantum computer can only apply unitary matrices: every gate, and hence every circuit, preserves the norm of the state vector and is invertible. A general matrix A changes norms, may be singular and need not be square, so "multiply by A" is not an available operation. Instead, A is embedded, after scaling, as a block of a larger unitary acting on additional qubits (ancillas); applying this unitary produces Av in one block, mixed with other components in the rest. This is the dilation idea of Halmos and Sz.-Nagy, by which every contraction is a corner of a unitary. A matrix A with $\|A\| \le \alpha$ is *block encoded* with *subnormalization* α if a unitary circuit U satisfies

$$U = \begin{bmatrix} A/\alpha & * \\ * & * \end{bmatrix}.$$

Every block of a unitary matrix has norm at most one, so $\alpha \ge \|A\|$ for *every* block encoding. We call $\alpha = \|A\|$ the *ideal subnormalization*. It is always attainable in principle, by a unitary dilation, but that dilation is a dense matrix without an efficient circuit. Efficient circuits are built from structure, and they usually achieve only a subnormalization $\alpha > \|A\|$. Since the cost grows with α (see (2)), this excess is a price paid in every call. How large it is depends on the construction; examples are in the supplement (`nla_for_quantum.tex`).

Applying U to $[v; 0]$ gives $[Av/\alpha;\, w]$ for some vector w. Measuring the ancillas and keeping the outcome that selects the first block (postselection) leaves the normalized vector $Av/\|Av\|$, independent of α. This succeeds with probability $\|Av\|^2/(\alpha\|v\|)^2$, so α does not change the result, only how often it is obtained.

A circuit is a product of unitary matrices (gates), each acting on a few of the tensor factors $\mathbb{C}^2$. For small problems, the whole product can be formed as an explicit matrix and checked. As an example, let S be the cyclic shift (a permutation matrix) and $H = \frac{1}{\sqrt{2}}\begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix}$. Then

$$U = (H \otimes I)\begin{bmatrix} I & 0 \\ 0 & -S \end{bmatrix}(H \otimes I) = \frac{1}{2}\begin{bmatrix} I - S & I + S \\ I + S & I - S \end{bmatrix}$$

is unitary, and it block encodes the difference matrix $I - S$ with $\alpha = 2$. This is the simplest instance of a linear combination of unitaries (LCU): H prepares the weights, and the middle factor selects I or $-S$ according to one extra qubit. Rectangular matrices are padded with zeros to square matrices of power-of-two size. Block encodings combine as follows (subnormalizations in brackets):

- products AB $[\alpha_A\alpha_B]$;
- Kronecker products $A \otimes B$ $[\alpha_A\alpha_B]$;
- linear combinations $\sum_j c_j A_j$ $[\sum_j |c_j|\alpha_j]$;

- stacking $[A_1; \ldots; A_k]$ $[(\sum_j \alpha_j^2)^{1/2}]$: prepare an index register with amplitudes $\propto \alpha_j$ and apply A_j controlled on index j;
- concatenation $[A_1, \ldots, A_k]$ $[(\sum_j \alpha_j^2)^{1/2} \le \sqrt{k}\max_j \alpha_j]$;
- sparse matrices with s_r nonzeros per row and s_c per column, whose entries are computable by a circuit $[\sqrt{s_r s_c}\max_{ij}|a_{ij}|]$ [13].

Products need a fresh ancilla per factor; reusing one ancilla brings discarded components back into the leading block. Explicit unitary realizations of all rules, with derivations of the subnormalizations and numerical checks, are given in the supplement *Block encodings for numerical linear algebraists* (`nla_for_quantum.tex`). In a product, the subnormalization can be far larger than the norm: $\alpha_A\alpha_B \ge \|A\|\|B\| \gg \|AB\|$ is possible.

Solving. Let $\mathcal{B}$ be Hermitian and block encoded with subnormalization α, and let its nonzero eigenvalues satisfy $|\lambda| \ge \sigma_{\min}$. A quantum solver for $\mathcal{B}z = b$ outputs a unit vector $\tilde{z}$ (a quantum state). Its *accuracy* ε is measured in the Euclidean norm against the normalized minimum-norm solution:

$$\left\| \tilde{z} - \frac{\mathcal{B}^+ b}{\|\mathcal{B}^+ b\|} \right\| \le \varepsilon. \tag{1}$$

Throughout, ε denotes this solver accuracy. Two further accuracies must not be confused with ε: the statistical error η with which a scalar such as v^*Ov is estimated from repeated measurements, and the target accuracy tol of a quantity of interest, which has to cover the discretization error, the effect of ε and η together (Section 7). Quantum singular value transformation (QSVT) [13] applies an odd polynomial $p(\mathcal{B}/\alpha)$ of degree D using D calls to the block encoding.

Why odd. QSVT alternates calls to U and U^*. It acts on the singular values $|\lambda_i|$ of $\mathcal{B} = Q\Lambda Q^*$, and D calls give a polynomial p of degree D and parity D (as in $(\mathcal{B}^*\mathcal{B})^k$ versus $\mathcal{B}(\mathcal{B}^*\mathcal{B})^k$). The signs of the eigenvalues enter only through their D-th power:

$$Q\,\mathrm{diag}\left(\mathrm{sign}(\lambda_i)^D\right) p(|\Lambda|)\, Q^*.$$

For odd D this is $Qp(\Lambda)Q^* = p(\mathcal{B})$. For even D the signs are lost, so an even p cannot approximate $1/\lambda$ on an indefinite spectrum.

Solving means evaluating a polynomial. A QSVT solver does not iterate. It evaluates the matrix function $p(\mathcal{B}/\alpha)$ for a fixed odd polynomial with

$$p(t) \approx \frac{\delta}{t} \ \text{ on } [\delta, 1], \qquad |p| \le 1 \ \text{ on } [-1, 1], \qquad \delta = \frac{\sigma_{\min}}{\alpha} = \frac{1}{\kappa_\alpha}.$$

Here

$$\kappa_\alpha := \frac{\alpha}{\sigma_{\min}} \ \ge \ \frac{\|\mathcal{B}\|}{\sigma_{\min}} = \kappa(\mathcal{B})$$

is the *effective condition number* in the terminology of Deiml and Peterseim [10, Def. 4.1]. It is the ratio of the upper bound 1 on the singular values of $\mathcal{B}/\alpha$, which is all that the block encoding guarantees, to its smallest nonzero singular value $\sigma_{\min}/\alpha$. The ordinary condition number would use the actual largest singular value $\|\mathcal{B}\|/\alpha$ instead; the two agree only for the ideal subnormalization $\alpha = \|\mathcal{B}\|$. The bound $|p| \le 1$ is needed because $p(\mathcal{B}/\alpha)$ must again be a block of a unitary. Since $p(0) = 0$, the result is the scaled pseudoinverse $\delta(\mathcal{B}/\alpha)^+ = \sigma_{\min}\mathcal{B}^+$.

How p is built. Since $1/t = t/(1-(1-t^2))$, a natural odd candidate is the truncated Neumann series in t^2,

$$s_m(t) = t\sum_{j=0}^{m-1}(1-t^2)^j = \frac{1-(1-t^2)^m}{t},$$

where the second form is the geometric sum with ratio $1 - t^2$. It is odd, vanishes at $t = 0$ and treats negative eigenvalues correctly. In matrix terms, $s_m(\mathcal{B}/\alpha)b$ is the result of m steps of Richardson iteration, started at zero, on the normal equations $(\mathcal{B}^*\mathcal{B}/\alpha^2)z = \mathcal{B}^*b/\alpha$.

How many terms are needed? The error in approximating δ/t by $\delta s_m(t)$ is

$$\frac{\delta}{t} - \delta s_m(t) = \frac{\delta}{t}\,(1 - t^2)^m.$$

For $t \in [\delta, 1]$ we have $\delta/t \le 1$ and $0 \le 1 - t^2 \le 1 - \delta^2$, and $1 - x \le e^{-x}$ gives

$$\left|\frac{\delta}{t} - \delta s_m(t)\right| \le (1 - \delta^2)^m \le e^{-m\delta^2}.$$

Each additional term thus reduces the bound only by the factor $1 - \delta^2$. For the normalized output to satisfy (1), the error must be below about $\varepsilon/\kappa_\alpha$, which holds as soon as

$$m \;\ge\; \delta^{-2}\log(\kappa_\alpha/\varepsilon) = \kappa_\alpha^2 \log(\kappa_\alpha/\varepsilon),$$

and δs_m has degree $2m - 1$. The factor κ_α^2 is the condition number of the normal equations, and the count is that of Richardson iteration on them.

Truncating the Chebyshev expansion of s_m reduces the degree to $O(\kappa_\alpha \log(\kappa_\alpha/\varepsilon))$ [7,13], the same gain as Chebyshev semi-iteration over Richardson. One more point needs care: near $t = 0$ the sum s_m is not bounded by $1/\delta$ but reaches about $0.64\sqrt{m}$ (at $t \approx 1.1/\sqrt{m}$), so δs_m can exceed 1 by a factor of order $\sqrt{\log(\kappa_\alpha/\varepsilon)}$. The standard constructions control this region separately, which changes the scaling by a constant or logarithmic factor but not the degree bound [7, 13]. In practice the phase factors are computed for a near-minimax odd approximation of δ/t with $|p| \le 1$ [9].

The cost of a solve has two factors.

- *Cost per run (the degree).* In classical terms this is Chebyshev semi-iteration whose degree is fixed in advance, namely $O(\kappa_\alpha \log(\kappa_\alpha/\varepsilon))$. The $\log(\kappa_\alpha/\varepsilon)$ arises because p must approximate δ/t to about $\varepsilon/\kappa_\alpha$ for the normalized output to satisfy (1). The polynomial depends only on the interval, not on b or the actual spectrum. Unlike CG or MINRES, it cannot adapt.

- *Number of runs (the success probability).* Postselecting $\sigma_{\min}\mathcal{B}^+b$ succeeds with probability

$$a^2 = \frac{\|\sigma_{\min}\mathcal{B}^+b\|^2}{\|b\|^2} \;\ge\; \frac{1}{\kappa_\alpha^2}.$$

  Simply repeating the run until it succeeds would cost about $1/a^2$ runs. *Amplitude amplification* [1] needs only about $\pi/(4a) \le \kappa_\alpha$ rounds. It uses two reflections: one flips the sign of the wanted block, the other reflects about the output vector of the circuit (one application of the circuit and its adjoint). Their product is a rotation by $2\arcsin a$ in the plane spanned by the wanted and the unwanted part, so k rounds turn the success amplitude a into $\sin((2k+1)\arcsin a)$, which is close to one for $k \approx \pi/(4a)$. In polynomial terms this is again QSVT, now of the scalar a with the odd Chebyshev polynomial T_{2k+1}. Details are in the supplement.

Multiplying the two, plain QSVT inversion costs $O(\kappa_\alpha^2 \log(\kappa_\alpha/\varepsilon))$ calls. Variable-time amplitude amplification [7] or the discrete adiabatic method [8] achieve the optimal

$$O\big(\kappa_\alpha \log(1/\varepsilon)\big) \quad \text{calls.} \tag{2}$$

In both cases the cost is governed by the effective condition number κ_α.

What preconditioning means. If solving means evaluating a polynomial, then preconditioning means *choosing the matrix in which the polynomial is evaluated*, so that a polynomial of low degree suffices.

Why this is the only lever. The polynomial has to approximate δ/t on $[\delta, 1]$ while staying bounded by one on $[-1, 1]$, where $\delta = \sigma_{\min}/\alpha = 1/\kappa_\alpha$. This needs degree about $\kappa_\alpha \log(1/\varepsilon)$, and every degree is one call to the block encoding. Solving is cheap only if δ is not small: the *scaled* spectrum of the encoded matrix must stay away from zero.

How it is done. Let $\mathcal{A}x = f$ be the system and let $\widetilde{R}$ be a factor of the preconditioner, $\widetilde{R}\widetilde{R}^T \approx P^{-1}$. Instead of evaluating a polynomial in $\mathcal{A}/\alpha_{\mathcal{A}}$, we evaluate one in the preconditioned matrix $\mathcal{B} = \widetilde{R}^T \mathcal{A} \widetilde{R}$ and map back:

$$\mathcal{A}^{-1} = \widetilde{R}\,\mathcal{B}^{+}\widetilde{R}^T \;\approx\; \frac{1}{\sigma_{\min}(\mathcal{B})}\,\widetilde{R}\,p\big(\mathcal{B}/\alpha_{\mathcal{B}}\big)\,\widetilde{R}^T,$$

with $p \approx \delta/t$ as above (Theorem 3.6 justifies the first equality). The degree drops from about $\kappa_\alpha(\mathcal{A}) \log(1/\varepsilon)$ to about $\kappa_\alpha(\mathcal{B}) \log(1/\varepsilon)$. Both are effective condition numbers, because the cost is always set by the encoded matrix. For $\mathcal{A}$ we only use $\kappa_\alpha(\mathcal{A}) \geq \kappa(\mathcal{A})$, with equality for an ideal encoding; this is the best case for the unpreconditioned solver. For $\mathcal{B}$ the gap between $\kappa_\alpha(\mathcal{B})$ and $\kappa(\mathcal{B})$ is exactly what the encoding lever below controls, so $\kappa(\mathcal{B})$ alone would be misleading. For the Poisson control problem of Section 3 with $d = 1$ and $h = 2^{-8}$, this is $\kappa_\alpha(\mathcal{A}) \geq \kappa(\mathcal{A}) \approx 2.6 \cdot 10^4$ against $\kappa_\alpha(\mathcal{B}) \approx 5$–$10$. The latter assumes an ideal encoding of the factor G of Section 3. There $\mathcal{B} = \mathcal{G}^T \mathcal{J} \mathcal{G}$ with $\mathcal{G} = I_2 \otimes G$, and G maps multilevel coefficients to values and gradients at quadrature points. The middle factor $\mathcal{J}$ costs nothing, so $\alpha_{\mathcal{B}} = \alpha_G^2$, which is $\|G\|^2$ in the ideal case. The value for the explicit construction is still to be measured (Section 3).

Two levers, one classical and one quantum. The ratio $\delta = \sigma_{\min}(\mathcal{B})/\alpha_{\mathcal{B}}$ can be spoiled from either side.

1. *Spectral (classical).* $\sigma_{\min}(\mathcal{B})$ must be comparable to $\|\mathcal{B}\|$. This is ordinary spectral equivalence of P and $\mathcal{A}$, i.e. eigenvalue inclusion intervals. In Section 3 it is provided by the Schöberl–Zulehner block structure combined with BPX.

2. *Encoding (quantum).* $\alpha_{\mathcal{B}}$ must be comparable to $\|\mathcal{B}\|$. This fails if $\mathcal{B}$ is encoded as the product $\widetilde{R}^T \cdot \mathcal{A} \cdot \widetilde{R}$: then $\alpha_{\mathcal{B}} \gtrsim \|R\|^2 \|\mathcal{A}\|$, which is of the order of $\kappa(\mathcal{A})$ (Section 3, (10)), and lever 1 is undone. It succeeds if $\mathcal{B}$ is written as a product of factors that are each encoded close to their own norm, and whose norms multiply to about $\|\mathcal{B}\|$ (no cancellation between the factors). A Gram factorization $F^T F$ has the second property automatically, since $\|F^T F\| = \|F\|^2$. Our $\mathcal{B} = \mathcal{G}^T \mathcal{J} \mathcal{G}$ (Section 3) is of this type, with a reflection $\mathcal{J}$ in the middle to carry the indefiniteness.

Comparison with classical preconditioning.

- *Where the preconditioner sits.* Classically, P is applied once per iteration, usually by an inner solve such as a multigrid cycle. Here the preconditioner is built into the matrix that is encoded, so every call of the circuit already multiplies by the preconditioned operator. There are no inner solves: P^{-1} must be available as a multiplication by a factor $\widetilde{R}$ (principle (D3) below).

- *What is optimized.* A Krylov method chooses its polynomial adaptively, from the actual spectrum and the right-hand side, so clustering of eigenvalues helps. Here the polynomial is fixed in advance by the interval $[\delta, 1]$, so only the interval counts (principle (D1)).

- κ *versus* $\sqrt{\kappa}$. For SPD systems, Chebyshev iteration or CG need about $\sqrt{\kappa}$ steps, because they minimize a residual polynomial normalized by $p(0) = 1$, a relative error measure. QSVT must approximate the inverse itself uniformly on $[\delta, 1]$, while staying bounded by one on $[-1, 1]$. This needs degree of order κ_α. The quantum solver therefore depends

more strongly on the condition number than CG does, which makes preconditioning *more* important, not less.

- *The ends of the product.* In practice $\widetilde{R}$ and $\widetilde{R}^T$ are not applied separately. The right-hand side is prepared as $\widetilde{R}^T f = \mathcal{G}^T g$, and outputs are read through $\mathcal{G}$ (principle (D5)).

Design principles. Equation (2) changes what a good preconditioner is.

(D1) *Only κ_α counts.* QSVT does not adapt to the spectrum, unlike MINRES. Three distinct eigenvalues help MINRES but not a QLSA. What we need are inclusion intervals $[-b,-a]\cup[a,b]$ with b/a independent of the parameters, i.e. exactly the robustness results of [27,33].

(D2) *Subnormalizations count.* The preconditioned matrix must be encoded with α close to its norm. Multiplying separately encoded factors such as $P^{-1/2}$, $\mathcal{A}$ and $P^{-1/2}$ fails. This is why [10] precondition a *factor* of the stiffness matrix rather than the matrix itself; see also [23].

(D3) *Preconditioners multiply.* A classical inner solve (e.g. a multigrid cycle) has to become a circuit that multiplies by P^{-1} or by a factor of it. Additive multilevel methods [4,36] are sums of products of structured sparse matrices and fit this model. Multiplicative multigrid does not.

(D4) *Kernels are harmless.* QSVT inverts on the range, so redundant generating systems, such as multilevel ones, are allowed. This is used in [10] for the BPX generating system.

(D5) *Organize for QoIs.* Right-hand sides and outputs should be accessible without applying further badly scaled operators.

3 Distributed control of the Poisson equation

3.1 Problem and discretization

Let $\Omega = (0,1)^d$, $d \le 3$, with desired state $\hat{y} \in L^2(\Omega)$ and regularization parameter $\beta > 0$. We solve

$$\min_{y,u} \ \tfrac{1}{2}\|y-\hat{y}\|^2_{L^2(\Omega)} + \tfrac{\beta}{2}\|u\|^2_{L^2(\Omega)} \quad \text{s.t.} \quad -\Delta y = u \text{ in } \Omega, \quad y = 0 \text{ on } \partial\Omega. \tag{3}$$

Grid and matrices. We use Q_1 elements on a uniform grid with $h = 2^{-L}$. There are 2^L elements and $2^L - 1$ interior nodes per direction, so $n = (2^L-1)^d$ unknowns. In 1D, $M_1 = \frac{h}{6}\,\mathrm{tridiag}(1,4,1)$ and $K_1 = \frac{1}{h}\,\mathrm{tridiag}(-1,2,-1)$. In d dimensions the matrices are Kronecker products, e.g. $M = M_1 \otimes M_1$ and $K = K_1 \otimes M_1 + M_1 \otimes K_1$ for $d = 2$. This structure matches the tensor-product structure of a qubit register.

Factorizations through quadrature points. Let $\xi_{1,2} = \frac{1}{2} \mp \frac{1}{2\sqrt{3}}$ be the two Gauss points on $[0,1]$. Let $F_0, F_1 \in \mathbb{R}^{2^{L+1}\times(2^L-1)}$ map nodal values to $\sqrt{h/2}$ times the values, respectively derivatives, of the finite element function at the Gauss points of all elements. Two-point Gauss quadrature is exact for the integrands involved, so

$$M_1 = F_0^T F_0, \qquad K_1 = F_1^T F_1. \tag{4}$$

In d dimensions let $F_{\mathrm{val}} = F_0^{\otimes d}$ and let F_∇ stack the factors $F^{(i)} = F_0 \otimes \cdots \otimes F_1 \otimes \cdots \otimes F_0$ (F_1 in position i). Then $M = F_{\mathrm{val}}^T F_{\mathrm{val}}$ and $K = F_\nabla^T F_\nabla$. The factors have $2^{d(L+1)}$ rows, 2^d nonzeros per row and at most 4^d per column.

This is the quadrature-point version of the factorization of Deiml and Peterseim [10, (6.1)], which uses an L^2-orthonormal (Legendre) basis of discontinuous Q_1 functions on each element instead of weighted values at Gauss points. For Q_1 the two are related by an orthogonal 2×2 map per element and direction, so the statements are equivalent. The quadrature form includes the mass matrix, as in [38], and extends directly to Q_k and P_k elements (Remark 3.1).

Remark 3.1 (Other elements). The construction is not specific to Q_1. Consider a nested family of conforming Lagrange spaces: Q_k on Cartesian grids, or P_k on uniformly red-refined, possibly unstructured simplicial meshes. Take a quadrature rule with positive weights that is exact for squares of the local polynomial space.

- The factorizations $M = F_{\text{val}}^T F_{\text{val}}$ and $K = F_\nabla^T F_\nabla$ are exact.
- The quadrature points are unisolvent, since $0 < \int p^2 = \sum_q w_q p(x_q)^2$.
- Lemma 3.7 below holds with an element-local isometry, the same for values and gradients, because derivatives stay in the local space.
- For Q_k the Kronecker form $M = M_1 \otimes M_1$, $K = K_1 \otimes M_1 + M_1 \otimes K_1$ ($d = 2$) holds for every k. The nodal basis functions are products $\phi_i(x)\phi_j(y)$ of 1D degree-k basis functions, so the integrals factor; only M_1 and K_1 change. For Q_2 they are 2-periodic (vertex and midpoint nodes alternate), with $2^{L+1} - 1$ unknowns per direction. Serendipity elements and P_k on simplices are not tensor products.
- Row counts that are not powers of two are zero-padded.
- Variable coefficients enter as one diagonal factor.

Mass lumping, curved elements and non-nested hierarchies keep the factorization only up to spectral equivalence. Unstructured meshes lose the Kronecker structure of the factors, which then need sparse-access oracles. We verified these statements numerically for Q_2 and Q_3 (1D and 2D) and for P_1 and P_2 on triangles. All factorization, commuting and isometry errors are below $3.3 \cdot 10^{-14}$.

Discrete problem and KKT system. Let $b = F_{\text{val}}^T \hat{y}_q$, where $\hat{y}_q$ holds the weighted values of $\hat{y}$ at the Gauss points. We minimize $\frac{1}{2} y^T M y - b^T y + \frac{\beta}{2} u^T M u$ subject to $Ky = Mu$. The optimality conditions are

$$\begin{bmatrix} M & 0 & K \\ 0 & \beta M & -M \\ K & -M & 0 \end{bmatrix} \begin{bmatrix} y \\ u \\ p \end{bmatrix} = \begin{bmatrix} b \\ 0 \\ 0 \end{bmatrix}. \tag{5}$$

We eliminate $u = p/\beta$, set $q = p/\sqrt{\beta}$ and scale the second equation. This gives

$$\mathcal{A}x = f, \qquad \mathcal{A} = \begin{bmatrix} M & \sqrt{\beta}K \\ \sqrt{\beta}K & -M \end{bmatrix}, \qquad x = \begin{bmatrix} y \\ q \end{bmatrix}, \quad f = \begin{bmatrix} b \\ 0 \end{bmatrix}, \tag{6}$$

with $u = q/\sqrt{\beta}$. The matrix $\mathcal{A}$ is symmetric and indefinite, with $\kappa(\mathcal{A}) = O(1 + \sqrt{\beta}h^{-2})$ (Table 1). Classically, MINRES with a robust block preconditioner and multigrid solves (6) in $O(n)$ operations [27, 29, 33].

3.2 A block preconditioner with a single elliptic operator

Let $A_\beta := M + \sqrt{\beta}K$, the stiffness matrix of $I - \sqrt{\beta}\Delta$.

Theorem 3.2 ([33]). *For* $P = \text{blkdiag}(A_\beta, A_\beta)$, $\text{spec}(P^{-1}\mathcal{A}) \subset [-1, -1/\sqrt{2}] \cup [1/\sqrt{2}, 1]$ *for all* h *and* β.

Proof. With $X^TMX = I$ and $X^TKX = \mathrm{diag}(\lambda_j)$, the pencil $(\mathcal{A}, P)$ decouples into 2×2 pencils $\Big(\begin{bmatrix} 1 & \mu_j \\ \mu_j & -1 \end{bmatrix}, (1+\mu_j)I\Big)$ with $\mu_j = \sqrt{\beta}\lambda_j > 0$. Their eigenvalues are $\pm\sqrt{1+\mu_j^2}/(1+\mu_j) \in \pm[1/\sqrt{2}, 1]$. □

Remark 3.3. In the Pearson–Wathen approximation of the Schur complement of (5) [27], $\widehat{S} = (K + M/\sqrt{\beta})M^{-1}(K + M/\sqrt{\beta})$, the operator to invert is again $K + M/\sqrt{\beta} = A_\beta/\sqrt{\beta}$. We use the form of Theorem 3.2 because it avoids M^{-1} and has the sharper interval.

3.3 A multilevel factor and level weights

For levels $\ell = 1, \dots, L$ with $h_\ell = 2^{-\ell}$, let $P_\ell \in \mathbb{R}^{n\times n_\ell}$ be the prolongation from level ℓ to level L ($P_L = I$). The level matrices $A_{\beta,\ell}$ have constant diagonal on a uniform grid:

$$\mathrm{diag}(A_{\beta,\ell}) = \delta_\ell I, \qquad \delta_\ell = \big(\tfrac{2h_\ell}{3}\big)^d + \sqrt{\beta}\,\tfrac{2d}{h_\ell}\big(\tfrac{2h_\ell}{3}\big)^{d-1}.$$

Following [10, Sec. 5], we use BPX in factored form, as a generating system R with $C = RR^T$. We define the weighted, diagonally scaled BPX factor

$$R = \big[\,\omega_1 P_1,\ \dots,\ \omega_L P_L\,\big], \qquad C = RR^T = \sum_{\ell=1}^{L} \omega_\ell^2 P_\ell P_\ell^T, \qquad \omega_\ell^2 = \frac{\theta_\ell}{\delta_\ell}, \tag{7}$$

with level weights

$$\theta_\ell = \left(\frac{\min\big(1, \sqrt{\beta}\,h_\ell^{-2}\big)}{\min\big(1, \sqrt{\beta}\,h_L^{-2}\big)}\right)^s, \qquad s \ge 0. \tag{8}$$

The choice $s = 0$ is plain BPX. Since $P_L = I$, R has full row rank. The denominator normalizes the finest level to $\theta_L = 1$, so that $\theta_\ell \le 1$ for all ℓ. It changes C only by a positive scalar and therefore does not affect $\kappa(CA_\beta)$. It does matter for the interval $[c_0, c_1]$ below: without it, c_0 would shrink like $(\sqrt{\beta}h_L^{-2})^s$ whenever the finest grid does not resolve β. Since the cost bounds below involve c_0 itself, not only c_1/c_0, the normalization is needed.

Assumption 3.4. $\mathrm{spec}(CA_\beta) \subset [c_0, c_1]$, *with* c_1/c_0 *bounded independently of* h *and, ideally, of* β.

For fixed β and $s = 0$, this is the classical BPX theory for H^1-elliptic problems [4, 26, 36]. Robustness in β concerns the singularly perturbed operator $I - \sqrt{\beta}\Delta$.

- *Plain BPX* is robust in h but degrades as $\beta \to 0$ (Section 6): coarse levels on which the mass term dominates ($\sqrt{\beta}h_\ell^{-2} < 1$) all count the same smooth modes.
- *The weights* (8) with $s > 0$ damp these levels geometrically. With $s = 1$ they keep $\kappa(CA_\beta) \le 6.2$ in all our tests in which the grid resolves β ($h \lesssim \beta^{1/4}$). If it does not, then $A_\beta \approx M$, and $\kappa(CA_\beta)$ approaches the "mass-matrix floor" $3^d/(1-4^{-s})$, i.e. 4, 12 and 36 for $d = 1, 2, 3$ and $s = 1$.
- *Truncation*, i.e. removing the mass-dominated levels altogether (the limit $s \to \infty$), is also robust, but its constants are worse at intermediate β: for example $\kappa(CA_\beta) = 19.2$ versus 6.1 for $s = 1$ at $d = 1$, $L = 10$, $\beta = 10^{-4}$.

Theorem 3.5 (robustness of the weighted factor)**.** *Let* $s > 0$, Q_1 *elements on uniform dyadic grids of* $(0,1)^d$, *and homogeneous Dirichlet conditions. Then Assumption 3.4 holds with* c_0, c_1 *depending only on* d *and* s, *uniformly in* L *(i.e.* h*) and* $\beta > 0$.

A self-contained proof with explicit constants is given in the supplementary note [34]. It reduces $x^T C^{-1} x$ to a minimal multilevel decomposition (the fictitious-space identity [12, 37]), compares nodal and L^2 norms by Jacobi scaling, and uses two classical ingredients: the Jackson-type multilevel norm equivalence [11, proof of Thm. 1] and the strengthened Cauchy–Schwarz inequality [36, Lemma 6.1]. The level weights make the mass contributions of the levels a geometric series, which removes the factor $\min(L, \log(1/\beta))$ of plain BPX. That factor is genuine for $s = 0$ [18, Rem. 4.5]. The explicit constants are pessimistic by two to three orders of magnitude. The proof explains the structure, not the size of $\kappa(CA_\beta)$.

Relation to robust multilevel methods. Additive multilevel preconditioners for $I - \sqrt{\beta}\,\Delta$ that are uniform in β and h are classical.

- Griebel and Oswald [11, Thms. 1–2] prove robustness for Q_1 elements on $(0,1)^d$, including nodal BPX and multilevel diagonal scaling, with the mass-dominated coarse levels dropped. This is the truncated limit $s \to \infty$ of (8).
- Bramble, Pasciak and Vassilevski [5] use the level weights $(\sqrt{\beta}\, h_\ell^{-2} + 1)^{-1}$ on differences of L^2 projections. Bacuta, Hayes and Jacavage [3] give a nodal version with lumped mass. Rewritten in terms of the $P_\ell P_\ell^T$, these weights are within level-independent factors of ours with $s = 1$ when the grid resolves β.
- Yang, Yu and Zhang [38, Thm. 2.1] use our $s = 0$ with exact inverse mass matrices, $M_\ell^{-1/2}$ in the factor, which they encode tightly through the sine transform [38, Secs. 3.4–3.5]. Their bound $12dL^2$ is uniform in the reaction coefficient but not in L.

Our contribution is therefore not robustness as such. It is the form required by the block encoding: a Jacobi-scaled factor R in which every level is a scaled prolongation; a family of weights $s > 0$ that contains the known choices; the normalization $\theta_L = 1$, which makes $[c_0, c_1]$ itself independent of β, which is needed in Section 4; and explicit constants. A better mass factor than Jacobi scaling lowers the floor $3^d/(1-4^{-s})$: with $(M_\ell + \sqrt{\beta}\,\mathrm{diag}(K_\ell))^{-1}$ in place of δ_ℓ^{-1}, and the encoding of [38] for the mass part, the floor drops to $4/3$ without loss in the subnormalization (supplement, `nla_for_quantum.tex`, Section "Removing the mass-matrix floor").

3.4 The two-sided system and its factorization

Let $\widetilde{R} = I_2 \otimes R$ and

$$\mathcal{B} := \widetilde{R}^T \mathcal{A} \widetilde{R} = \begin{bmatrix} R^T M R & \sqrt{\beta} R^T K R \\ \sqrt{\beta} R^T K R & -R^T M R \end{bmatrix}. \tag{9}$$

Theorem 3.6. *Under Assumption 3.4:*

1. *$\mathcal{A}x = f$ if and only if $x = \widetilde{R} z$ for a solution z of the consistent system $\mathcal{B} z = \widetilde{R}^T f$. In particular $x = \widetilde{R} \mathcal{B}^+ \widetilde{R}^T f$.*
2. *The nonzero eigenvalues of $\mathcal{B}$ lie in $[-c_1, -c_0/\sqrt{2}] \cup [c_0/\sqrt{2}, c_1]$.*

Proof. (1) $\widetilde{R}$ is surjective, so $\widetilde{R}^T$ is injective, and $\mathrm{range}(\mathcal{B}) = \widetilde{R}^T \mathcal{A} \mathbb{R}^{2n} = \mathrm{range}(\widetilde{R}^T)$. (2) The nonzero eigenvalues of $\widetilde{R}^T \mathcal{A} \widetilde{R}$ are those of $\widetilde{C}^{1/2} \mathcal{A} \widetilde{C}^{1/2} = S(P^{-1/2} \mathcal{A} P^{-1/2}) S^T$, where $\widetilde{C} = I_2 \otimes C$ and $S = \widetilde{C}^{1/2} P^{1/2}$. By Ostrowski's theorem [14, Thm. 4.5.9], each one equals $\theta\lambda$, where λ is an eigenvalue as in Theorem 3.2 and $\theta \in \mathrm{spec}(SS^T) = \mathrm{spec}(I_2 \otimes CA_\beta) \subset [c_0, c_1]$. □

Factorization with a reflection. *Why a factorization is needed.* Classically, a preconditioned operator $\widetilde{R}^T \mathcal{A} \widetilde{R}$ is applied factor by factor, and the norms of the factors are irrelevant. A Krylov method sees only the spectrum of the product. On a quantum computer, a product of block encodings encodes $\widetilde{R}^T \mathcal{A} \widetilde{R}/(\alpha_R^2 \alpha_{\mathcal{A}})$, because every factor is applied with a loss of amplitude. Its subnormalization satisfies

$$\alpha \;\geq\; \|R\|^2 \, \|\mathcal{A}\| \;=\; \|C\| \, \|\mathcal{A}\| \;\geq\; c_0 \|A_\beta^{-1}\| \cdot \tfrac{1}{2} \|A_\beta\| \;=\; \tfrac{c_0}{2} \, \kappa(A_\beta). \tag{10}$$

The steps are as follows.

- Each factor X has $\alpha_X \geq \|X\|$, since X/α_X is a block of a unitary matrix, and the α's multiply.
- $\|R\|^2 = \|RR^T\| = \|C\| \geq c_0 \|A_\beta^{-1}\|$ by Assumption 3.4.
- $\|A_\beta\| \leq \|M\| + \sqrt{\beta}\|K\| \leq 2\|\mathcal{A}\|$, because M and $\sqrt{\beta}K$ are blocks of $\mathcal{A}$.

Since $\sigma_{\min}(\mathcal{B}) \leq \|\mathcal{B}\| \leq c_1$, the effective condition number of the product encoding is at least $\frac{c_0}{2c_1}\kappa(A_\beta)$, with $\kappa(A_\beta) \sim 1 + \sqrt{\beta} h^{-2}$. Numerically this is close to $\kappa(\mathcal{A})$. For example, for $d = 1$, $L = 8$, $\beta = 1$: $\|R\|^2 \|\mathcal{A}\| = 3.0 \cdot 10^4$, $\kappa(\mathcal{A}) = 2.6 \cdot 10^4$, while the factored form below gives $\|G\|^2/\sigma_{\min}(\mathcal{B}) = 5.0$. QSVT then has to invert on $[\sigma_{\min}/\alpha, 1]$, with degree $\sim \alpha/\sigma_{\min}$. It is non-adaptive: it behaves like Chebyshev semi-iteration with the upper eigenvalue bound overestimated as α instead of $\lambda_{\max}$. So the cost would be of the order of $\kappa(\mathcal{A})$, as without preconditioning. Krylov methods do not suffer from this, because they adapt to the actual spectrum.

What a good factorization needs. We look for a factorization $\mathcal{B} = F_1 F_2 \cdots F_m$ with two properties.

(W1) *Tight factors:* each factor has an efficient block encoding with $\alpha(F_i) \approx \|F_i\|$.

(W2) *No cancellation:* $\prod_i \|F_i\| \approx \|\mathcal{B}\|$. That is, the vectors on which one factor is large are not damped by its neighbours.

Then $\alpha_{\mathcal{B}} = \prod_i \alpha(F_i) \approx \|\mathcal{B}\|$. The naive product $\widetilde{R}^T \cdot \mathcal{A} \cdot \widetilde{R}$ satisfies (W1) but violates (W2): R is large on smooth vectors, where $\mathcal{A}$ is small, and $\|R\|^2\|\mathcal{A}\|$ exceeds $\|\mathcal{B}\|$ by a factor of order $\kappa(A_\beta)$.

- *Gram factorizations satisfy (W2) automatically,* because $\|F^T F\| = \|F\|^2$ exactly. This is why we factor through $G = [F_{\text{val}} R;\, \beta^{1/4} F_\nabla R]$, which has $G^T G = R^T A_\beta R$.
- *An indefinite $\mathcal{B}$ needs a reflection in the middle* (next paragraph). (W2) then holds up to a bounded factor: $\|\mathcal{G}\|^2 \|\mathcal{J}\| = \|G\|^2 \leq c_1$, while $\|\mathcal{B}\| \geq c_0/\sqrt{2}$ by Theorem 3.6, so $\prod_i \|F_i\|/\|\mathcal{B}\| \leq \sqrt{2}\, c_1/c_0$.
- *(W1)* is the subject of Section 3.5 (Lemma 3.7 and Proposition 3.8).

Why a reflection in the middle. $\mathcal{B}$ is indefinite, so it cannot be written as $G^T G$. Let

$$G = \begin{bmatrix} F_{\text{val}} R \\ \beta^{1/4} F_\nabla R \end{bmatrix}, \qquad \mathcal{G} = I_2 \otimes G = \begin{bmatrix} G & 0 \\ 0 & G \end{bmatrix}, \qquad \mathcal{J} = \begin{bmatrix} E_{\text{val}} & E_\nabla \\ E_\nabla & -E_{\text{val}} \end{bmatrix},$$

where E_{val} and $E_\nabla = I - E_{\text{val}}$ are the diagonal 0/1 matrices that select the value rows and the gradient rows of G. Then

$$\mathcal{B} = \mathcal{G}^T \mathcal{J} \mathcal{G}, \qquad \mathcal{J} = \mathcal{J}^T = \mathcal{J}^{-1}, \qquad \|G\|^2 = \|R^T A_\beta R\| \leq c_1. \tag{11}$$

This is a J-factorization, as in LDL^T with $D = \pm 1$ or hyperbolic QR. G maps coefficients to values v and gradients g at the quadrature points, for both y and q. $\mathcal{J}$ is the matrix of the bilinear form

$$z^T \mathcal{B} z = \|v_y\|^2 - \|v_q\|^2 + 2\langle g_y, g_q \rangle.$$

On value rows it multiplies the y-block by $+1$ and the q-block by -1, giving $\pm R^T M R$. On gradient rows it swaps the two blocks, giving the off-diagonal $\sqrt{\beta} R^T K R$.

- $\mathcal{J}$ is a signed permutation matrix. On the device it is a single two-qubit gate acting on the qubit that labels the block (y or q) and the qubit that labels the row type (value or gradient): "if value row, flip the sign of the q-block; if gradient row, swap the blocks". Its subnormalization is 1.
- The right-hand side is $\widetilde{R}^T f = \mathcal{G}^T g$, where g is $\hat{y}_q$ placed in the value rows of the y-block (zero elsewhere).
- Outputs are accessed through $\mathcal{G}$ as well, since $G_{\mathrm{val}} z_y = F_{\mathrm{val}} y$. For example, $\langle w, y \rangle_M$ is an overlap of two states prepared with $\mathcal{G}$. So R is never applied on its own (D5).

3.5 Block encoding of the multilevel factor

A product encoding of $F_\nabla P_\ell$ loses a factor h_ℓ / h. The reason is that $\|F_\nabla\|$ is attained by oscillatory vectors and $\|P_\ell\|$ by smooth ones. Numerically, the loss reaches 148 for $L = 8$ (Table 4). The remedy is to differentiate on the coarse level and only then transfer to the fine level.

Lemma 3.7 (commuting with prolongation; cf. [10, Thm. 6.2])**.** *For each level ℓ there is an isometry T_ℓ ($T_\ell^T T_\ell = I$) with*

$$F_{\mathrm{val}} P_\ell = T_\ell F_{\mathrm{val},\ell}, \qquad F^{(i)} P_\ell = T_\ell F_\ell^{(i)} \quad (i = 1, \ldots, d).$$

T_ℓ is element-local and the same on every coarse element. In 1D, $T_\ell = I_{2^\ell} \otimes \widehat{T}_{L-\ell}$, where $\widehat{T}_k \in \mathbb{R}^{2^{k+1} \times 2}$ maps the two weighted Gauss values of an affine function on a coarse element to its weighted values at the 2^{k+1} fine Gauss points. In d dimensions, T_ℓ is the d-fold Kronecker product.

Proof. On a coarse element, coarse functions and their partial derivatives are affine in each direction. The two Gauss points are unisolvent for affine functions, which defines $\widehat{T}_k$. Both the coarse and the fine weighted values compute the exact L^2 norm of the same affine function, because two-point Gauss quadrature is exact for quadratics. Hence $\widehat{T}_k$ is an isometry. □

For Q_1 and the gradient part, Lemma 3.7 is the commutative diagram of Deiml and Peterseim [10, Thm. 6.2]: differentiate on the coarse level, then include the coarse discontinuous space into the fine one by a map with orthonormal columns. The finite-difference analogue is [15, Lemma 4.3]. The version with values and gradients, i.e. with the mass term, is [38, Lemma 3.3]. Our contribution here is the quadrature formulation, which covers Q_k and P_k elements (Remark 3.1).

Some matrix T with $F P_\ell = T F_\ell$ always exists when F_ℓ has full column rank, e.g. $T = F P_\ell F_\ell^+$. The content of Lemma 3.7 is that T_ℓ is an isometry and element-local. This is what gives a cheap block encoding with subnormalization one. By the lemma,

$$G = \begin{bmatrix} T_1 G_1, & \ldots, & T_L G_L \end{bmatrix}, \qquad G_\ell = \omega_\ell \begin{bmatrix} F_{\mathrm{val},\ell} \\ \beta^{1/4} F_\ell^{(1)} \\ \vdots \\ \beta^{1/4} F_\ell^{(d)} \end{bmatrix}, \qquad G_\ell^T G_\ell = \theta_\ell \delta_\ell^{-1} A_{\beta,\ell}. \tag{12}$$

Proposition 3.8. *G has a block encoding with subnormalization $\alpha_G \le C_d\sqrt{L}$, where C_d depends only on d.*

Sketch.
- G_ℓ has 2^d nonzeros per row and $(d+1)4^d$ per column.
- By the definition of δ_ℓ, its entries are bounded by 1, uniformly in h and β. The sparse-access encoding therefore gives $\alpha(G_\ell) \le (2^d(d+1)4^d)^{1/2}$.
- Each T_ℓ is an isometry, so it can be completed to a unitary.
- Concatenating the L levels costs a factor $\sqrt{L}$.

□

Since $\mathcal{B} = \mathcal{G}^T\mathcal{J}\mathcal{G}$, the subnormalization of $\mathcal{B}$ is $\alpha_G^2 = O(L)$. This matches the linear growth in L that Deiml and Peterseim obtain for the preconditioned stiffness factor [10, Thm. 6.3]. The sparse-access constant is pessimistic ($C_3 \approx 45$). Encoding G_ℓ as a weighted stack of Kronecker products of 1D two-term factors should give constants close to $\|G_\ell\| \le \sqrt{\theta_\ell}\, 3^{d/2}$.

From bound to measurement. The gap between the lower bound $\|G\| \approx 2$ (Table 1) and the upper bound $C_d\sqrt{L}$ matters, because α_G enters the cost squared. For $d = 3$ the two bounds differ by a factor of about 2000 in α_G^2. We therefore plan to build the block encoding of Proposition 3.8 as an explicit unitary matrix for small grids ($d = 1$ with $L \le 6$, $d = 2$ with $L \le 4$), using exactly the factors a circuit would use:

- LCUs of shifts for the 1D two-term factors, as in the example of Section 2;
- Kronecker products;
- the weighted stack over values and gradients;
- the isometries T_ℓ, completed to unitaries;
- the concatenation over levels.

For this matrix we check two things:

1. it is unitary, and its leading block equals G/α_G (correctness);
2. the value of α_G as a function of L, d and β, compared with $\|G\|$ (cost). This shows whether the $\sqrt{L}$ appears and how large C_d really is.

The effective condition number that QSVT faces is then $\kappa_\alpha = \alpha_G^2/\sigma_{\min}(\mathcal{B})$, not the ideal $\|G\|^2/\sigma_{\min}(\mathcal{B})$. **[TODO: carry out; can the $\sqrt{L}$ be avoided?]**

Theorem 3.9. *Under Assumption 3.4, QSVT applied to $\mathcal{B} = \mathcal{G}^T\mathcal{J}\mathcal{G}$ solves $\mathcal{B}z = \mathcal{G}^T g$ to accuracy ε, in the sense of* (1)*, using*

$$O\Big(\frac{C_d^2 L}{c_0}\log\frac{1}{\varepsilon}\Big)$$

calls to block encodings of G, G^T and $\mathcal{J}$. Each call costs $\mathrm{poly}(L)$ *gates. The count depends on h only through $L = \log_2 h^{-1}$, and on β only through c_0.*

Proof. By (11), Theorem 3.6 and Proposition 3.8, $\kappa_\alpha(\mathcal{B}) \le \sqrt{2}\,\alpha_G^2/c_0 \le \sqrt{2}\,C_d^2 L/c_0$. The result follows from (2). □

[TODO: End-to-end statement: preparation of g, amplitude amplification of the success probability, estimation of $\|z\|$, and readout of the QoI.]

4 The time-periodic heat equation

4.1 Problem, discretization and Fourier transform in time

We solve

$$\min_{y,u} \frac{1}{2}\int_0^T \|y-\hat{y}\|^2_{L^2(\Omega)}dt + \frac{\beta}{2}\int_0^T \|u\|^2_{L^2(\Omega)}dt \quad \text{s.t.} \quad \partial_t y - \Delta y = u, \quad y|_{\partial\Omega}=0, \quad y(\cdot,0)=y(\cdot,T). \tag{13}$$

Classically, this problem is treated with multiharmonic finite elements and robust block preconditioners [19, 20].

- *Space:* Q_1 as in Section 3.
- *Time:* $N_t = 2^{L_t}$ steps of length $\tau = T/N_t$ with periodic backward Euler, $M(y_k - y_{k-1})/\tau + Ky_k = Mu_k$, with $y_0 = y_{N_t}$.

With the cyclic shift Σ and $D_t = (I-\Sigma)/\tau$, the constraint reads

$$\mathcal{K}y = \mathbb{M}u, \qquad \mathcal{K} = D_t \otimes M + I \otimes K, \qquad \mathbb{M} = I \otimes M.$$

We approximate the objective by the rectangle rule. As in (6), we eliminate u and set $q = p/(\tau\sqrt{\beta})$. This gives the symmetric system

$$\mathcal{A} = \begin{bmatrix} \mathbb{M} & \sqrt{\beta}\,\mathcal{K}^T \\ \sqrt{\beta}\,\mathcal{K} & -\mathbb{M} \end{bmatrix}, \qquad x = \begin{bmatrix} y \\ q \end{bmatrix}, \qquad f = \begin{bmatrix} \mathbb{M}\hat{y} \\ 0 \end{bmatrix}, \qquad u = \frac{q}{\sqrt{\beta}}. \tag{14}$$

D_t is circulant: $D_t = \mathcal{F}^*\Lambda\mathcal{F}$, with the unitary DFT matrix $\mathcal{F}$ and

$$\lambda_k = \frac{1-e^{-2\pi ik/N_t}}{\tau} = \frac{2}{\tau}\sin\Big(\frac{\pi k}{N_t}\Big)e^{\,i(\pi/2-\pi k/N_t)}, \qquad \operatorname{Re}\lambda_k \geq 0. \tag{15}$$

Applying $\mathcal{F}$ to the time index block-diagonalizes $\mathcal{A}$ into the Hermitian blocks

$$\mathcal{A}_k = \begin{bmatrix} M & \sqrt{\beta}(K+\bar{\lambda}_k M) \\ \sqrt{\beta}(K+\lambda_k M) & -M \end{bmatrix}, \qquad k = 0,\dots,N_t-1. \tag{16}$$

On a quantum computer, $\mathcal{F}$ is the QFT on the L_t time qubits, with $O(L_t^2)$ gates. It is unitary, so it does not change the condition number or the subnormalization. The analysis below uses only $\operatorname{Re}\lambda_k \geq 0$. It therefore also covers multiharmonic discretizations, where $\lambda_k = i\omega_k$.

4.2 A robust preconditioner per frequency

Theorem 4.1. *Let $r_k = 1+\sqrt{\beta}|\lambda_k|$, $A_k = r_k M + \sqrt{\beta}K$ and $P_k = \operatorname{blkdiag}(A_k, A_k)$. Then for all h, τ, β and k,*

$$\operatorname{spec}(P_k^{-1}\mathcal{A}_k) \subset [-1, -1/\sqrt{3}] \cup [1/\sqrt{3}, 1].$$

Proof. With $X^TMX = I$ and $X^TKX = \operatorname{diag}(\mu_j)$, the pencil decouples into 2×2 pencils with eigenvalues $\pm\sqrt{1+x^2}/(1+c)$, where $x = \sqrt{\beta}|\mu_j + \lambda_k|$ and $c = \sqrt{\beta}(\mu_j + |\lambda_k|)$.

- $c \geq x$, by the triangle inequality.
- $c \leq \sqrt{2}\,x$, because $\mu_j + |\lambda_k| \leq (\mu_j + \operatorname{Re}\lambda_k) + |\operatorname{Im}\lambda_k| \leq \sqrt{2}|\mu_j+\lambda_k|$ when $\operatorname{Re}\lambda_k \geq 0$.

Hence $\sqrt{1+x^2}/(1+\sqrt{2}x) \leq \sqrt{1+x^2}/(1+c) \leq 1$. The lower bound is minimal at $x=\sqrt{2}$, where it equals $1/\sqrt{3}$. □

Remark 4.2.

- *Time domain.* In the time domain the preconditioner is $\operatorname{blkdiag}(\mathcal{P}_t, \mathcal{P}_t)$ with $\mathcal{P}_t = I \otimes (M + \sqrt{\beta}K) + \sqrt{\beta}|D_t| \otimes M$ and $|D_t| = (D_t^T D_t)^{1/2}$. It is real and symmetric, although $\mathcal{K}$ is not. $|D_t|$ is the discrete analogue of $|\partial_t|$, which underlies the $H^{1/2}$-in-time norms of parabolic theory.
- *Relation to prior work.* Theorem 4.1 is the analogue, for this discretization, of the robust multiharmonic preconditioners of [19,20]. **[TODO: compare constants and attribute.]**

4.3 Each frequency is a Poisson problem

We can write $A_k = r_k(M + \sqrt{\beta_k}K)$ with $\sqrt{\beta_k} = \sqrt{\beta}/r_k$. Each frequency is therefore the operator of Section 3 with effective parameter β_k, scaled by r_k.

- *Multilevel factor.* $R_k = [\omega_{1,k}P_1, \dots, \omega_{L,k}P_L]$ with $\omega_{\ell,k}^2 = \theta_{\ell,k}/\delta_{\ell,k}$, where $\delta_{\ell,k} = r_k(\frac{2h_\ell}{3})^d + \sqrt{\beta}\frac{2d}{h_\ell}(\frac{2h_\ell}{3})^{d-1}$ and $\theta_{\ell,k}$ the normalized weights (8) with β_k in place of β. Then $C_kA_k = C(\beta_k)A_{\beta_k}$, where $C(\beta_k)$ and $A_{\beta_k} = M + \sqrt{\beta_k}K$ are the Poisson quantities for parameter β_k. By Theorem 3.5, $\mathrm{spec}(C_kA_k) \subset [c_0, c_1]$ with the *same* c_0, c_1 for all k [34]. This is where the normalization $\theta_{L,k} = 1$ is essential: with unnormalized weights the interval would shrink by $\min(1, \sqrt{\beta_k}h_L^{-2})^s$, which is small for high frequencies when $\tau \lesssim 2h_L^2$.
- *Frequency enters only through scalars.* The prolongations P_ℓ and isometries T_ℓ are independent of k.
- *The level weights are no longer optional.* β_k decreases from β ($k = 0$) to $\beta\tau^2/(\tau + 2\sqrt{\beta})^2$ ($k = N_t/2$), so high frequencies are mass-dominated.
- *The mass-matrix floor matters here.* For high frequencies $\sqrt{\beta_k} \approx \tau/2$, so the finest grid does not resolve β_k once $\tau \lesssim 2h_L^2$. With such time steps, many frequencies sit at the floor $3^d/(1 - 4^{-s})$ of Section 3.3 (36 in 3D for $s = 1$), and since the worst frequency determines κ_α, the floor rather than the resolved value ≈ 6 sets the cost.

Factorization with a scaled reflection. Let

$$G_k = \begin{bmatrix} \sqrt{r_k}\, F_{\mathrm{val}} R_k \\ \beta^{1/4} F_\nabla R_k \end{bmatrix}, \qquad G_k^* G_k = R_k^T A_k R_k.$$

Then $\mathcal{B}_k := \widetilde{R}_k^T \mathcal{A}_k \widetilde{R}_k = \mathcal{G}_k^* \mathcal{J}_k \mathcal{G}_k$, where

$$\mathcal{J}_k = \begin{bmatrix} j_{11}E_{\mathrm{val}} & j_{12}E_{\mathrm{val}} + E_\nabla \\ j_{21}E_{\mathrm{val}} + E_\nabla & j_{22}E_{\mathrm{val}} \end{bmatrix}, \qquad J_k = \begin{bmatrix} j_{11} & j_{12} \\ j_{21} & j_{22} \end{bmatrix} = \frac{1}{r_k}\begin{bmatrix} 1 & \sqrt{\beta}\bar{\lambda}_k \\ \sqrt{\beta}\lambda_k & -1 \end{bmatrix} = s_k U_k. \quad (17)$$

On value rows, $\mathcal{J}_k$ applies the 2×2 matrix J_k across the two blocks. On gradient rows, it swaps the blocks as before. U_k is a Hermitian unitary 2×2 matrix (a reflection) with phase $\arg \lambda_k = \pi/2 - \pi k/N_t$, and

$$s_k = \frac{\sqrt{1 + \beta|\lambda_k|^2}}{1 + \sqrt{\beta}|\lambda_k|} \in \left[\tfrac{1}{\sqrt{2}}, 1\right].$$

Hence $\|\mathcal{J}_k\| \le 1$, and $\mathcal{J}_k$ is block encoded with subnormalization 1. The weight $\sqrt{r_k}$ on the value rows is essential: without it, $\|J_k\|$ would grow like $\sqrt{\beta}/\tau$.

Theorem 4.3. *Use the normalized weights, so that Assumption 3.4 holds for all A_k with constants c_0, c_1 independent of k (Theorem 3.5). Then the nonzero eigenvalues of $\mathcal{B} = \mathrm{blkdiag}_k(\mathcal{B}_k)$ lie in $[-c_1, -c_0/\sqrt{3}] \cup [c_0/\sqrt{3}, c_1]$, and $\kappa_\alpha(\mathcal{B}) \le \sqrt{3}\,\alpha_G^2/c_0$ with $\alpha_G \le C_d\sqrt{L}$. In particular, neither N_t nor τ enters κ_α.*

Proof. Argue as for Theorem 3.6 and Proposition 3.8, frequency by frequency, with Theorem 4.1 in place of Theorem 3.2. □

QSVT applies $\mathcal{B}^+$ to all frequencies simultaneously, in superposition. Compared with the Poisson problem, the cost per solve increases only by two QFTs and the frequency-controlled scalars (Section 5).

5 Implementation

Registers.

- $d(L+1)$ qubits for quadrature rows (element index and Gauss point per direction).
- dL qubits for nodal unknowns. Level-ℓ data use the leading ℓ bits per direction. The unused index $2^\ell - 1$, a boundary node, is mapped to zero by a comparator flag.
- $\lceil \log_2 L \rceil$ qubits for the level, $\lceil \log_2(d+1) \rceil$ for the component c, one qubit b for the block, and L_t qubits for time or frequency.
- Ancillas for the block encodings and QSVT.

Coarse element indices are the leading bits of fine element indices, so $T_\ell = I \otimes \widehat{T}_{L-\ell}$ acts on trailing bits only. Unused index combinations lie in the kernel of G, which is harmless by (D4).

Circuits.

1. *1D two-term factors* $F_{0,\ell}$ and $F_{1,\ell}$: a shift by one on ℓ qubits ($O(\ell)$ gates), an LCU of two diagonal patterns, and the boundary flag. Kronecker products and a weighted stack over c then give G_ℓ.
2. *The isometry* $\widehat{T}_k$: its two orthonormal columns are the uniform vector (Hadamard gates) and a normalized discrete ramp with Gauss offsets. **[TODO: reference for linear-amplitude state preparation.]**
3. *Levels*: G_ℓ and T_ℓ controlled on the level register, followed by Hadamard gates and postselection on the level register.
4. $\mathcal{J}$: one two-qubit gate (Poisson). For the heat equation, $\mathcal{J}_k$ needs U_k controlled on c and k, plus one ancilla rotation for s_k.
5. *QSVT phase factors* for an odd polynomial approximating $1/t$ on $[\sigma_{\min}/\alpha, 1]$, of degree $O(\kappa_\alpha \log(1/\varepsilon))$. They are computed classically, e.g. as in [9], using a lower bound for c_0.
6. *Frequency scalars (heat).* $\arg \lambda_k$ is affine in k, so it needs only single-qubit phase gates. The magnitude $|\lambda_k| = \frac{2}{\tau} \sin(\pi k / N_t)$ is an LCU of $\mathrm{diag}(e^{\pm i\pi k/N_t})$. The derived quantities $r_k^{\pm 1/2}$, $\omega_{\ell,k}$ and s_k come from QSVT polynomials or reversible arithmetic. **[TODO: compare costs.]**
7. *Right-hand side and readout.* Prepare g (weighted values of $\hat{y}$ at Gauss points, and time steps for the heat problem); for smooth $\hat{y}$, efficient circuits exist **[TODO: refs]**. Then apply $\mathcal{G}^T$, after a QFT in time for the heat problem. QoIs are overlaps $\langle \mathcal{G} g_w, \mathcal{G} z \rangle$, estimated by Hadamard tests and amplitude estimation; $\|z\|$ follows from the success probability.

Classical precomputation. All weights are in closed form. The only nontrivial precomputation is the QSVT phase factors and the constant c_0 that enters them.

6 Numerical experiments

All experiments use dense or sparse linear algebra in double precision, with scripts in the folder `preconditioning/code` of the accompanying repository:

- `qp_poisson_check.py`: Table 1, Table 4;

- `qp_bpx_weights.py`: Table 2;
- `qp_bpx_sparse.py`: Table 3, extreme eigenvalues by Lanczos with CG-based inner solves;
- `qp_heat_periodic_check.py`: Table 5.

Condition numbers on the range are ratios of the largest to the smallest nonzero eigenvalue magnitudes.

Poisson control: preconditioner and factorization. Table 1 shows:

- $\kappa(\mathcal{A})$ grows like $\sqrt{\beta}h^{-2}$;
- the interval of Theorem 3.2 is attained;
- $\kappa(\mathcal{B})$ on the range follows $\kappa(CA_\beta)$, as predicted by Theorem 3.6;
- $\|G\|$ is $O(1)$. This is the smallest possible α_G; the value achieved by the explicit construction is still to be measured (Section 3, "From bound to measurement");
- the factorization $\mathcal{B} = \mathcal{G}^T \mathcal{J} \mathcal{G}$ holds to machine precision in all cases.

d	L	β	$\kappa(\mathcal{A})$	$\lvert\operatorname{spec}(P^{-1}\mathcal{A})\rvert$	$\kappa(CA_\beta)$	$\kappa(\mathcal{B})$	$\lVert G\rVert$
1	4	1	$1.0 \cdot 10^2$	$[0.913, 1.000]$	3.45	3.49	1.86
1	6	1	$1.7 \cdot 10^3$	$[0.913, 1.000]$	4.36	4.38	2.09
1	8	1	$2.6 \cdot 10^4$	$[0.913, 1.000]$	4.98	4.99	2.23
1	8	10^{-4}	$2.6 \cdot 10^3$	$[0.708, 1.000]$	4.43	4.50	2.11
1	8	10^{-8}	$2.6 \cdot 10^1$	$[0.707, 0.999]$	7.31	8.03	2.70
2	5	1	$2.1 \cdot 10^2$	$[0.953, 1.000]$	4.06	4.04	1.75
2	5	10^{-4}	$4.0 \cdot 10^1$	$[0.707, 0.996]$	3.96	3.47	1.74
2	5	10^{-6}	$4.2 \cdot 10^0$	$[0.707, 0.981]$	6.40	7.90	2.34

Table 1: Poisson control with plain BPX ($s = 0$). $\kappa(\mathcal{B})$ is computed on the range. $\|G\|$ is a lower bound for the subnormalization α_G of any block encoding of G.

Robustness in h and β, including 3D. Tables 2 and 3 compare plain and weighted BPX.

- For fixed β, $\kappa(CA_\beta)$ is bounded in h in all dimensions. It levels off slowly (3D, $\beta = 1$: 4.2, 5.3, 6.1 for $L = 3, 4, 5$).
- Plain BPX degrades as $\beta \to 0$, up to 44.6 in 3D.
- The weights (8) with $s = 1$ keep $\kappa(CA_\beta) \le 6.2$ whenever the grid resolves β ($h \lesssim \beta^{1/4}$). In unresolved cases they approach the mass-matrix floor $3^d/(1 - 4^{-s})$ (4 in 1D and 12 in 2D for $s = 1$). The worst value in 3D is 20.5; for finer grids and tiny β it should grow towards the 3D floor 36.

Subnormalization loss of the naive product. Table 4 gives the ratio $\|F_1\|\|P_\ell\|/\|F_1 P_\ell\|$. A product encoding of $F_1 P_\ell$ loses this factor. It equals $2^{L-\ell}$, up to a correction on the coarsest levels. Lemma 3.7 removes it completely: the commuted factors satisfy $\|T_\ell\|\,\|F_{1,\ell}\| = \|F_1 P_\ell\|$.

		β					
d, L	s	1	10^{-2}	10^{-4}	10^{-6}	10^{-8}	10^{-10}
1, 10	0	5.42	5.32	5.02	4.92	7.33	9.80
1, 10	1/2	5.42	5.30	4.97	4.55	3.88	2.86
1, 10	1	5.42	5.33	6.14	5.37	4.92	3.61
2, 4	0	3.58	3.49	3.62	7.23	18.89	26.31
2, 4	1/2	3.58	3.33	2.29	3.12	9.84	14.14
2, 4	1	3.58	3.29	2.26	1.97	7.16	10.51

Table 2: $\kappa(CA_\beta)$ for the level weights (8), including the intermediate exponent $s = \frac{1}{2}$. In 2D with $L = 4$, the grid does not resolve $\beta \le 10^{-8}$.

d	L	n	s	$\beta = 1$	10^{-2}	10^{-4}	10^{-6}	10^{-8}
2	6	3969	0	4.44	4.36	4.22	7.14	11.27
2	6	3969	1	4.44	4.27	3.53	2.83	1.64
3	3	343	0	4.16	4.23	5.95	17.36	35.95
3	3	343	1	4.16	3.71	2.77	8.80	20.47
3	4	3375	0	5.30	5.31	6.41	15.75	44.55
3	4	3375	1	5.30	4.90	3.39	4.26	17.69
3	5	29791	0	6.08	6.05	6.65	14.19	–
3	5	29791	1	6.08	5.74	4.46	3.12	–

Table 3: $\kappa(CA_\beta)$ on larger grids, plain ($s = 0$) and weighted ($s = 1$) BPX, computed by Lanczos.

Time-periodic heat control. Table 5 shows:

- the global eigenvalues of $\mathcal{P}^{-1}\mathcal{A}$ lie in the interval $[1/\sqrt{3}, 1]$ of Theorem 4.1;
- per frequency, the factorization $\mathcal{B}_k = \mathcal{G}_k^* \mathcal{J}_k \mathcal{G}_k$ holds and $\|J_k\| \le 1$;
- the per-frequency BPX constants behave as in the Poisson case with effective parameters β_k.

7 Complexity and discussion

Accuracies. Let tol be the target accuracy of a QoI. It is split into three parts:

- the discretization error;
- the solver accuracy ε of (1);
- the readout error η of Section 2.

Each part is chosen of order tol. Up to constants, the cost of a QoI to accuracy tol is therefore (calls per solve with $\varepsilon \sim \mathrm{tol}$) times (readout repetitions $\sim \mathrm{tol}^{-1}$).

Poisson control. Suppose the discretization error of the QoI is $O(h^2)$, so $h \sim \mathrm{tol}^{1/2}$.

- Classically, the cost is $O(n) = O(\mathrm{tol}^{-d/2})$ with optimal preconditioning.
- On a quantum computer, Theorem 3.9 gives polylog(1/tol) calls per solve. Readout adds a factor $O(\mathrm{tol}^{-1})$, for a total of $\widetilde{O}(\mathrm{tol}^{-1})$.

ℓ	1	2	3	4	5	6	7
$\|F_1\|\|P_\ell\|/\|F_1P_\ell\|$	147.8	65.8	32.2	16.0	8.0	4.0	2.0

Table 4: Loss of the naive product encoding, $d = 1$, $L = 8$.

d	L	N_t	β	$\kappa(\mathcal{A})$	$\lvert\operatorname{spec}(\mathcal{P}^{-1}\mathcal{A})\rvert$
1	5	32	1	$4.1 \cdot 10^2$	$[0.714, 1.000]$
1	5	32	10^{-2}	$2.9 \cdot 10^2$	$[0.603, 0.999]$
1	5	32	10^{-4}	$4.1 \cdot 10^1$	$[0.666, 0.992]$
1	5	32	10^{-6}	$4.2 \cdot 10^0$	$[0.702, 0.990]$
2	3	16	1	$1.3 \cdot 10^1$	$[0.811, 0.999]$
2	3	16	10^{-2}	$1.2 \cdot 10^1$	$[0.669, 0.993]$
2	3	16	10^{-4}	$2.7 \cdot 10^0$	$[0.684, 0.936]$
2	3	16	10^{-6}	$4.4 \cdot 10^0$	$[0.704, 0.981]$
[TODO: per-frequency BPX and factorization checks]					

Table 5: Time-periodic heat control. The bound of Theorem 4.1 is $1/\sqrt{3} \approx 0.577$.

An asymptotic advantage therefore requires $d = 3$ on this count. This is consistent with Deiml and Peterseim [10, Remark 6.7]. In their analysis, if the accuracy demands $h \approx \mathrm{tol}^{1/s}$, an advantage requires $d > s$. They measure the error in the energy norm, where $s = 1$, which gives an advantage from $d = 2$. For quantities of interest with $O(h^2)$ accuracy, $s = 2$, so $d = 3$ is needed. **[TODO: check the precise statement of their Remark 6.7.]**

Heat control.

- With backward Euler, $N_t \sim \mathrm{tol}^{-1}$ and the classical cost is $\mathrm{tol}^{-(d/2+1)}$. On that count, a quantum advantage would appear for every d.
- This comparison is unfair. For data that are smooth in time, a multiharmonic discretization needs only $\log(1/\mathrm{tol})$ harmonics, and the elliptic count returns.
- The time dimension favours the quantum solver only when many harmonics are genuinely needed, i.e. for targets or forcing that are rough in time. **[TODO: quantify.]**

Limitations.

- The algorithms need fault-tolerant hardware.
- The constants (C_d, the mass-matrix floor $3^d/(1 - 4^{-s})$, readout) matter in practice.
- State preparation for general data and the end-to-end success probability need a full analysis.
- The robustness of the multilevel factor in β is proven (Theorem 3.5) only for Q_1 elements on uniform grids, and with pessimistic constants.

8 Conclusions and outlook

Preconditioning for quantum linear solvers is a numerical linear algebra problem with its own rules. Respecting them leads to factorized, well-scaled preconditioned operators whose effective condition numbers are robust in the discretization parameters. Open directions:

1. a proof of β-robust multilevel bounds, and a better mass factor;
2. removing the $\sqrt{L}$ factor and computing explicit constants;
3. control constraints, where semismooth Newton or interior point methods change the $(2,2)$ block in every iteration. This links to preconditioners for interior point methods and to quantum interior point methods [28];
4. initial value problems. There D_t is not circulant. The α-circulant preconditioner [25] needs the non-unitary scaling $\Gamma_\alpha = \mathrm{diag}(\alpha^{k/N_t})$, whose condition number $1/\alpha$ enters the subnormalization. This trade-off between preconditioner quality and encoding cost has no classical analogue. Wavelet-in-time bases [32] are an alternative;
5. variable coefficients, boundary control, and non-Cartesian meshes.

References

[1] G. Brassard, P. Høyer, M. Mosca, A. Tapp, Quantum amplitude amplification and estimation, *Contemp. Math.* 305 (2002) 53–74.

[2] M. Bagherimehrab, K. Nakaji, N. Wiebe, A. Aspuru-Guzik, Fast quantum algorithm for differential equations, arXiv:2306.11802 (2023).

[3] C. Bacuta, D. Hayes, J. Jacavage, Efficient discretization and preconditioning of the singularly perturbed reaction-diffusion problem, arXiv:2104.11337 (2021).

[4] J. H. Bramble, J. E. Pasciak, J. Xu, Parallel multilevel preconditioners, *Math. Comp.* 55 (1990) 1–22.

[5] J. H. Bramble, J. E. Pasciak, P. S. Vassilevski, Computational scales of Sobolev norms with application to preconditioning, *Math. Comp.* 69 (2000) 463–480.

[6] B. D. Clader, B. C. Jacobs, C. R. Sprouse, Preconditioned quantum linear system algorithm, *Phys. Rev. Lett.* 110 (2013) 250504.

[7] A. M. Childs, R. Kothari, R. D. Somma, Quantum algorithm for systems of linear equations with exponentially improved dependence on precision, *SIAM J. Comput.* 46 (2017) 1920–1950.

[8] P. C. S. Costa, D. An, Y. R. Sanders, Y. Su, R. Babbush, D. W. Berry, Optimal scaling quantum linear-systems solver via discrete adiabatic theorem, *PRX Quantum* 3 (2022) 040303.

[9] Y. Dong, X. Meng, K. B. Whaley, L. Lin, Efficient phase-factor evaluation in quantum signal processing, *Phys. Rev. A* 103 (2021) 042419.

[10] M. Deiml, D. Peterseim, Quantum realization of the finite element method, *Math. Comp.* 95 (2026), no. 362, 2637–2668, doi:10.1090/mcom/4137; arXiv:2403.19512.

[11] M. Griebel, P. Oswald, Tensor product type subspace splittings and multilevel iterative methods for anisotropic problems, *Adv. Comput. Math.* 4 (1995) 171–206.

[12] M. Griebel, P. Oswald, On the abstract theory of additive and multiplicative Schwarz algorithms, *Numer. Math.* 70 (1995) 163–180.

[13] A. Gilyén, Y. Su, G. H. Low, N. Wiebe, Quantum singular value transformation and beyond, *Proc. STOC* (2019) 193–204.

[14] R. A. Horn, C. R. Johnson, *Matrix Analysis*, 2nd ed., Cambridge University Press, 2013.

[15] S. Jin, N. Liu, C. Ma, Y. Yu, Quantum preconditioning method for finite difference discretizations of the Poisson equation via Schrödingerization, arXiv:2505.06866 (2025).

[16] Huang, Álvarez Yuste, Guseynov, Liu, González-Conde [**TODO: verify initials**], Quantum algorithms for optimal control: large-scale finite-horizon linear-quadratic regulation, arXiv:2610.26843 (2026).

[17] W. Krendl, V. Simoncini, W. Zulehner, Stability estimates and structural spectral properties of saddle point problems, *Numer. Math.* 124 (2013) 183–213.

[18] T. Kolev, J. Xu, Y. Zhu, Multilevel preconditioners for reaction-diffusion problems with discontinuous coefficients, *J. Sci. Comput.* 67 (2016) 324–350.

[19] M. Kollmann, M. Kolmbauer, A preconditioned MinRes solver for time-periodic parabolic optimal control problems, *Numer. Linear Algebra Appl.* (2012), doi:10.1002/nla.1842.

[20] M. Kollmann, M. Kolmbauer, U. Langer, M. Wolfmayr, W. Zulehner, A robust finite element solver for a multiharmonic parabolic optimal control problem, *Comput. Math. Appl.* 65 (2013) 469–486.

[21] L. Lin, Lecture notes on quantum algorithms for scientific computation, arXiv:2201.08309 (2022).

[22] N. Linden, A. Montanaro, C. Shao, Quantum vs. classical algorithms for solving the heat equation, *Comm. Math. Phys.* 395 (2022) 601–641.

[23] L. Lapworth, C. Sünderhauf, Preconditioned block encodings for quantum linear systems, arXiv:2502.20908 (2025).

[24] A. Montanaro, S. Pallister, Quantum algorithms and the finite element method, *Phys. Rev. A* 93 (2016) 032324.

[25] E. McDonald, J. Pestana, A. Wathen, Preconditioning and iterative solution of all-at-once systems for evolutionary partial differential equations, *SIAM J. Sci. Comput.* 40 (2018) A1012–A1033.

[26] P. Oswald, *Multilevel Finite Element Approximation: Theory and Applications*, Teubner, 1994.

[27] J. W. Pearson, A. J. Wathen, A new approximation of the Schur complement in preconditioners for PDE-constrained optimization, *Numer. Linear Algebra Appl.* 19 (2012) 816–829.

[28] M. Mohammadisiahroudi et al., Quantum interior point methods: a review of developments and an optimally scaling framework, arXiv:2512.06224 (2025).

[29] T. Rees, H. S. Dollar, A. J. Wathen, Optimal solvers for PDE-constrained optimization, *SIAM J. Sci. Comput.* 32 (2010) 271–298.

[30] Sato, Kato, Yano, Ito, Yamamoto [**TODO: verify initials**], Explicit block-encoding for partial differential equation-constrained optimization, arXiv:2511.14420 (2025).

[31] Surana, Gnanasekaran [**TODO: verify initials and title**], Variational quantum framework for partial differential equation constrained optimization, arXiv:2405.16651 (2024).

[32] C. Schwab, R. Stevenson, Space-time adaptive wavelet methods for parabolic evolution problems, *Math. Comp.* 78 (2009) 1293–1318.

[33] J. Schöberl, W. Zulehner, Symmetric indefinite preconditioners for saddle point problems with applications to PDE-constrained optimization problems, *SIAM J. Matrix Anal. Appl.* 29 (2007) 752–773.

[34] M. Stoll, J. W. Pearson, Robustness of the weighted BPX factor for $M + \sqrt{\beta}K$, supplementary note (2026).

[35] Y. Tong, D. An, N. Wiebe, L. Lin, Fast inversion, preconditioned quantum linear system solvers, fast Green's-function computation, and fast evaluation of matrix functions, *Phys. Rev. A* 104 (2021) 032422.

[36] J. Xu, Iterative methods by space decomposition and subspace correction, *SIAM Rev.* 34 (1992) 581–613.

[37] J. Xu, L. Zikatanov, The method of alternating projections and the method of subspace corrections in Hilbert space, *J. Amer. Math. Soc.* 15 (2002) 573–597.

[38] Y. Yang, Y. Yu, L. Zhang, A structure-aware construction of quantum BPX preconditioners for Q_1 finite element discretizations of reaction–diffusion problems, arXiv:2610.06987 (2026).